



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)

**cPCI-3534 cPCI-3544 cPCI-3538**  
**4/8 Ports Serial**  
**Communication Modules**  
**User's Guide**



Recycled Paper



© Copyright 1996~2001 ADLINK Technology Inc.

All Rights Reserved.

Manual Rev 1.20: April 4, 2001

Part No : 50-11200-201

The information in this document is subject to change without prior notice in order to improve reliability, design and function and does not represent a commitment on the part of the manufacturer.

In no event will the manufacturer be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use the product or documentation, even if advised of the possibility of such damages.

This document contains proprietary information protected by copyright. All rights are reserved. No part of this manual may be reproduced by any mechanical, electronic, or other means in any form without prior written permission of the manufacturer.

### **Trademarks**

cPCI-3534, cPCI-3544 and cPCI-3538 are registered trademarks of ADLINK TECHNOLOGY INC., MS-DOS, Windows 95, Windows NT are registered trademark of Microsoft Corporation. Intel is a registered trademark of Intel Corporation. Other product names mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective companies.

# Getting service from ADLINK

- ◆ Customer Satisfaction is always the most important thing for ADLINK TECHNOLOGY INC. If you need any help or service, please contact us and get it.

| <b>ADLINK TECHNOLOGY INC.</b> |   |                     |                 |
|-------------------------------|---|---------------------|-----------------|
| Web Site                      | http://www.adlink.com.tw  |                     |                 |
| Sales and Service             | service@adlink.com.tw   |                     |                 |
| Technical Support             | NuDAQ   | nudaq@adlink.com.tw |                 |
|                               | NuDAM   | nudam@adlink.com.tw |                 |
|                               | NuIPC   | nuipc@adlink.com.tw |                 |
|                               | NuPRO   | nupro@adlink.com.tw |                 |
|                               | Software  | sw@adlink.com.tw    |                 |
|                               | AMB   | amb@adlink.com.tw   |                 |
| TEL                           | +886-2-82265877   | FAX                 | +886-2-82265717 |
| Address                       | 9F, No. 166, Jian Yi Road, Chungho City, Taipei 235, Taiwan, R.O.C. |                     |                 |

- ◆ Please inform us of your detailed information for a prompt, satisfactory and constant service.

| <b>Detailed Company Information</b> |  |     |  |
|-------------------------------------|--|-----|--|
| Company/Organization                |  |     |  |
| Contact Person                      |  |     |  |
| E-mail Address                      |  |     |  |
| Address                             |  |     |  |
| Country                             |  |     |  |
| TEL                                 |  | FAX |  |
| Web Sit                             |  |     |  |
| <b>Questions</b>                    |  |     |  |
| Product Model                       |  |     |  |
| Environment to Use                  | ? OS _____<br>? Computer Brand _____<br>? M/B :                      ? CPU :<br>? Chipset :                      ? BIOS :<br>? Video Card :<br>? Network Interface Card :<br>? Other : |     |  |
| Challenge Description               |  |     |  |
| Suggestions for ADLINK              |  |     |  |

## ADLINK cPCI Multi-port Communication Module Comparison Chart

|  | <b>3534</b>  | <b>3544</b>  | <b>3538</b>   |
|--|--|--|---|
| <b>Serial port per system</b>          | 4~8  | 4~32   | 8~16  |
| <b>RS-232 port per module</b>          | 3  | -  | 8   |
| <b>RS-422/485 per module</b>           | 1  | 4  | -   |
| <b>CPU</b>                             | -  | -  | -   |
| <b>Serial communication controller</b> | 16C554   | 16C554   | 16C554  |
| <b>MAX System throughput</b>           | 115.2K*4   | 115.2K*4   | 115.2K*8  |
| <b>Hardware compatibility</b>          | cPCI bus   | cPCI bus   | cPCI bus  |
| <b>Software compatibility</b>          | DOS Windows (3.1/95/98/NT)<br>LINUX SCO<br>Open Server | Windows (95/98/NT) QNX                               | DOS Windows (3.1/95/98/NT)<br>LINUX SCO<br>Open Server            |
| <b>External connector</b>              | Four DB25 male cable connector or DB9 male connector   | Four DB25 male cable connector or DB9 male connector | Eight DB25 male cable connector or DB9 connector                  |
| <b>Rear IO Connector</b>               | R3534  | R3544  | R3538   |
| <b>Surge protection</b>                | Y  | Y  | Y   |
| <b>Accessory</b>                       | C425M<br>C409M   | C425M<br>C409M                                       | C825M<br>C809M  |
| <b>Isolation protection</b>            | Port D:<br>embedded isolated RS422 or RS 485           | Embedded isolated RS422 or RS 485                    | Y (C888XB)<br>option external isolated RS-232 or RS-422 or RS-485 |
| <b>Dimension</b>                       | 160mm (length)<br>100mm (width)                        | 160mm (length)<br>100mm (width)                      | 160mm (length)<br>100mm (width)                                   |



# Table of Contents

|   |           |
|---|-----------|
| <b>Chapter 1 Introduction</b> .....                               | <b>1</b>  |
| 1.1 About the Serial Communication Modules .....                  | 1         |
| 1.2 Overview of cPCI-3534 .....                                   | 2         |
| 1.2.1 <i>What is cPCI-3534?</i> .....                             | 2         |
| 1.2.2 <i>Feature of cPCI-3534</i> .....                           | 2         |
| 1.2.3 <i>Specification of cPCI-3534</i> .....                     | 3         |
| 1.2.4 <i>Connector Pin Assignment of cPCI-3534</i> .....          | 4         |
| 1.3 Overview of cPCI-3544 .....                                   | 8         |
| 1.3.1 <i>What is cPCI-3544?</i> .....                             | 8         |
| 1.3.2 <i>Feature of cPCI-3544</i> .....                           | 8         |
| 1.3.3 <i>Specification of cPCI-3544</i> .....                     | 9         |
| 1.3.4 <i>Connector Pin Assignment of cPCI-3544</i> .....          | 11        |
| 1.4 Overview of cPCI-3538 .....                                   | 14        |
| 1.4.1 <i>What is cPCI-3538?</i> .....                             | 14        |
| 1.4.2 <i>Feature of cPCI-3538</i> .....                           | 14        |
| 1.4.3 <i>Specification of cPCI-3538</i> .....                     | 15        |
| 1.4.4 <i>Connector Pin Assignment of cPCI-3538</i> .....          | 17        |
| <b>Chapter 2 Installation</b> .....                               | <b>20</b> |
| 2.1 What You Have .....   | 20        |
| 2.2 Unpacking.....  | 21        |
| 2.3 Installation Procedure .....                                  | 22        |
| 2.4 Hardware Configuration .....                                  | 23        |
| 2.4.1 <i>Wiring Example</i> .....                                 | 23        |
| 2.5 Software Installation .....                                   | 24        |
| 2.5.1 <i>Windows NT Installation</i> .....                        | 24        |
| 2.5.2 <i>Windows 95/98 Installation</i> .....                     | 26        |
| 2.5.3 <i>For UNIX, LINUX and QNX user</i> .....                   | 27        |
| 2.5.4 <i>Windows 95/98/NT Utility Diagram for cPCI-3544</i> ..... | 28        |
| 2.6 AP Examples .....   | 30        |
| 2.6.1 <i>Dos Environment</i> .....                                | 30        |
| 2.6.2 <i>Windows(Windows 95/98/NT) Environment</i> .....          | 30        |
| 2.6.3 <i>Linux Environment</i> .....                              | 30        |
| <b>Product Warranty/Service</b> .....                             | <b>31</b> |





# 1

## Introduction

---

### 1.1 About the Serial Communication Modules

- ◆ The serial communication modules are intelligent serial input/output multi-port controller modules, which go with the new generation of PC platform CompactPCI. The modules can reduce the frequency for serial communication controller to interrupt main CPU on the mainboard to improve the whole system performance.
- ◆ Traditionally, the serial communication controller will interrupt the MPU character by character. This action will waste MPU processing time and drop the system computing power. If the MPU is processing some non-interrupted task, then the serial controller will overrun and data lost.
- ◆ The serial communication interface series can support buffer capability or local processor and dual port RAM in each port's transmit and receive channel simultaneously. This capability will reduce the frequency of interrupt and increase the non-interrupt task's interval.
- ◆ The serial communication interface series use ASIC PCI controller to interface the module to cPCI bus. The ASIC fully implement the PCI local bus specification Rev. 2.1. All related bus configurations, such as base memory address and interrupt assignment, are automatically controlled by BIOS software. It does not need any user interaction and pre-study for the configurations. This removes the burden of searching for a conflict-free configuration.

---

## 1.2 Overview of cPCI-3534

### 1.2.1 What is cPCI-3534?

The cPCI-3534 is an enhanced four ports serial communication module used for Compact-PCI platform. It includes a PGA(Programmable Gate Array) to support the serial communication controller and a 37-pin connector to connect external I/O port from the front panel or using the rear IO.

The expansion cable has four standard DB25 or DB9 connectors and one DB37 connector to connect with cPCI-3534 interface card.

The R-3534 transition board can support rear IO connection by using one DB37 connector.

### 1.2.2 Feature of cPCI-3534

- 32-bit CompactPCI 3U form factor
- PCI Rev.2.1 Plug and Play
- IRQ and IO address automatically assigned by PCI plug-n-play
- 4 communication ports intelligent buffer
- One isolated industry communication port
- High Speed Communication (max. 115200 bps)
- Suitable for modems, data display, data collection, telecommunication
- Supports up to 2 cards/8 ports per system
- Supports DOS, Windows 3.1, Windows 95/98, and Windows NT operation system

### 1.2.3 Specification of cPCI-3534

- ◆ Compliant with PCI Spec.2.1
- ◆ Serial communication controller:
  - 16C550A compatible
  - 1.8432 ~ 7.3728 MHz
- ◆ System IO mapping:
  - Assigned by PCI BIOS
  - Shared IRQ
- ◆ Flow control
  - Xon/Xoff control
  - RTS/CTS control
- ◆ Port Capability:
  - 3 independent RS-232C compatible ports
  - 1 isolated RS-422/485 port (DIP switch select)
  - Max. port per system: 8 (2 card)
- ◆ Isolation voltage: 2500VDC
- ◆ Baud rate: Each port can be configured to 50~115,200 bps
- ◆ Operation System Compatibility: DOS, Windows 3.1, and Windows 95/98/NT
- ◆ Connector: DB37 female connector
- ◆ Cable: External cable with 4 standard DB25 male connector
- ◆ Operating temperature: 0 ~ 55 °C

- ◆ Storage temperature: -20 ~ 65 °C
- ◆ Humidity: 10% ~ 95%, non-condensing
- ◆ Dimension: 160 x 100 mm<sup>2</sup> (6.3 x 3.9 in.<sup>2</sup>) 3U
  - Power consumption: +5V @ 1400mA typical

### 1.2.4 Connector Pin Assignment of cPCI-3534

DB37 female connector pin assignment for cPCI-3534.

| DB37 Pin No. | Signal Name    | DB37 Pin No. | Signal Name    |
|--------------|----------------|--------------|----------------|
| 1            | RXD1(IN)       | 20           | TXD1(OUT)      |
| 2            | CTS1(IN)       | 21           | RTS1(OUT)      |
| 3            | DSR1(IN)       | 22           | DTR1(OUT)      |
| 4            | DCD1(IN)       | 23           | RI1(IN)        |
| 5            | GND            | 24           | RXD2(IN)       |
| 6            | TXD2(OUT)      | 25           | CTS2(IN)       |
| 7            | RTS2(OUT)      | 26           | DSR2(IN)       |
| 8            | DTR2(OUT)      | 27           | DCD2(IN)       |
| 9            | GND            | 28           | RI2(IN)        |
| 10           | --             | 29           | RI3(IN)        |
| 11           | GND            | 30           | DCD3(IN)       |
| 12           | DTR3(OUT)      | 31           | DSR3(IN)       |
| 13           | RTS3(OUT)      | 32           | CTS3(IN)       |
| 14           | TXD3(OUT)      | 33           | RXD3(IN)       |
| 15           | GND4           | 34           | --             |
| 16           | --             | 35           | 422TXD4-(I/O)  |
| 17           | 422RXD4-(IN)   | 36           | 485TRXD4+(I/O) |
| 18           | 485TRXD4-(I/O) | 37           | 422TXD4+(OUT)  |
| 19           | 422RXD4+(IN)   | --           | --             |

DB25 male connector pin assignment in cPCI-3534 module for RS-232 interface (port A, B and C).

| DB25 Pin No. | Signal Name |
|--------------|-------------|
| 2            | TXD(OUT)    |
| 3            | RXD(IN)     |
| 4            | RTS(OUT)    |
| 5            | CTS(IN)     |
| 6            | DSR(IN)     |
| 7            | GND         |
| 8            | DCD(IN)     |
| 20           | DTR(OUT)    |

DB25 male connector pin assignment in cPCI-3534 module for RS-422/485 interface (port D).

| DB25 Pin No. | Signal Name   |
|--------------|---------------|
| 2            | 422TXD+(OUT)  |
| 3            | 422RXD+(IN)   |
| 4            | 485TRXD+(I/O) |
| 5            | 485TRXD-(I/O) |
| 6            | 422RXD-(IN)   |
| 7            | GND           |
| 20           | 422TXD-(OUT)  |

DB9 male connector pin assignment in cPCI-3534 module for RS-232 interface (port A, B and C).

| DB9 Pin No. | Signal Name |
|-------------|-------------|
| 2           | TXD(OUT)    |
| 3           | RXD(IN)     |
| 4           | RTS(OUT)    |
| 5           | CTS(IN)     |
| 6           | DSR(IN)     |
| 7           | GND         |
| 8           | DCD(IN)     |
| 9           | DTR(OUT)    |

DB9 male connector pin assignment in cPCI-3534 module for RS-422/485 interface (port D).

| DB25 Pin No. | Signal Name   |
|--------------|---------------|
| 2            | 422TXD+(OUT)  |
| 3            | 422RXD+(IN)   |
| 4            | 485TRXD+(I/O) |
| 5            | 485TRXD-(I/O) |
| 6            | 422RXD-(IN)   |
| 7            | GND           |
| 20           | 422TXD-(OUT)  |

J2 connector pin assignment in cPCI-3534 module for RS-232/422/485 interface.

|     |     |                  |                 |                  |                  |                  |     |                   |
|-----|-----|------------------|-----------------|------------------|------------------|------------------|-----|-------------------|
| 22  | GND | GA4              | GA3             | GA2              | GA1              | GA0              | GND | P2 / J2 CONNECTOR |
| 21  | GND |                  |                 |                  |                  |                  | GND |                   |
| 20  | GND |                  |                 |                  |                  |                  | GND |                   |
| 19  | GND | FG               | N+              | N-               | SG               |                  | GND |                   |
| 18  | GND |                  |                 |                  |                  |                  | GND |                   |
| 17  | GND |                  |                 |                  |                  |                  | GND |                   |
| 16  | GND |                  |                 | TXD+             | TXD-             | SG               | GND |                   |
| 15  | GND | FG               | RXD+            | RXD-             |                  |                  | GND |                   |
| 14  | GND |                  |                 |                  |                  |                  | GND |                   |
| 13  | GND |                  |                 |                  |                  |                  | GND |                   |
| 12  | GND | DSR <sup>③</sup> | SG <sup>③</sup> | DCD <sup>③</sup> | DTR <sup>③</sup> |                  | GND |                   |
| 11  | GND | FG <sup>③</sup>  | TX <sup>③</sup> | RX <sup>③</sup>  | RTS <sup>③</sup> | CTS <sup>③</sup> | GND |                   |
| 10  | GND |                  |                 |                  |                  |                  | GND |                   |
| 9   | GND |                  |                 |                  |                  |                  | GND |                   |
| 8   | GND | DSR <sup>②</sup> | SG <sup>②</sup> | DCD <sup>②</sup> | DTR <sup>②</sup> |                  | GND |                   |
| 7   | GND | FG <sup>②</sup>  | TX <sup>②</sup> | RX <sup>②</sup>  | RTS <sup>②</sup> | CTS <sup>②</sup> | GND |                   |
| 6   | GND |                  |                 |                  |                  |                  | GND |                   |
| 5   | GND |                  |                 |                  |                  |                  | GND |                   |
| 4   | GND | DSR <sup>①</sup> | SG <sup>①</sup> | DCD <sup>①</sup> | DTR <sup>①</sup> |                  | GND |                   |
| 3   | GND | FG <sup>①</sup>  | TX <sup>①</sup> | RX <sup>①</sup>  | RTS <sup>①</sup> | CTS <sup>①</sup> | GND |                   |
| 2   | GND |                  |                 |                  |                  |                  | GND |                   |
| 1   | GND |                  |                 |                  |                  |                  | GND |                   |
| Pin | Z   | A                | B               | C                | D                | E                | F   |                   |

①Port A ②Port B ③Port C

### RS-232

FG : Frame Ground TX : Transmit Data  
 RX : Receive Data  
 RTS : Request to Send CTS : Clear to Send  
 DSR : Data Set Ready  
 SG : Signal Ground DCD : Data Carrier Detect  
 DTR : Data Terminal Ready

### RS-422

TXD+ : Transmit Data Positive  
 TXD- : Transmit Data Negative

RXD+ : Receive Data Positive  
RXD- : Receive Data Negative

### **RS-485**

D+ : Data Signal Positive  
D- : Data Signal Negative

### **R-3534 Rear IO Daughter Board**

The R-3534 rear I/O daughter board provides a rear I/O connection transition, the connector and cable used in the rear is the same as the front.

#### ***DIP Switch and Jumper Setting***

|       |        |        |
|-------|--------|--------|
| SW1   | ON     | OFF    |
| SW1-1 | Card1  | Card2  |
| SW1-4 | RS-422 | RS-485 |

The JP1 is for the RS422 terminator and the JP2 is for the RS-485 terminator. The terminator is ON while the jumper is ON



---

## 1.3 Overview of cPCI-3544

### 1.3.1 What is cPCI-3544?

The cPCI-3544 is an enhanced four ports serial communication module for industry communication interface RS-422/485 by Compact-PCI platform. It includes a PGA(Programmable Gate Array) to support the serial communication controller and a 37-pin connector to connect external I/O port from the front panel or using the rear IO.

The expansion cable has four standard DB25 or DB9 connectors and one DB37 connector to connect with cPCI-3544 interface card.

The R-3544 transition board can support rear IO connection by using one DB37 connector.

### 1.3.2 Feature of cPCI-3544

- ◆ 32-bit CompactPCI 3U form factor
- ◆ PCI Rev.2.1 Plug and Play
- ◆ IRQ and IO address automatically assigned by PCI plug-n-play
- ◆ 4 communication ports intelligent buffer
- ◆ RS-422/485 hardware/software selectable
- ◆ RS-485 with auto direction flow control
- ◆ Channel to channel isolated industry communication port
- ◆ High speed communications concurrently (max. 115200 bps)
- ◆ Supports up to 8 cards/32 ports per system
- ◆ Supports DOS, Windows 95/98, and Windows NT operation system

### 1.3.3 Specification of cPCI-3544

- ◆ Compliant with PCI Spec.2.1
- ◆ Serial communication controller:
  - ◆ 16C550A compatible
  - ◆ 1.8432 ~ 7.3728 MHz
  - ◆ System IO mapping:
    - Assigned by PCI BIOS
    - Shared IRQ
  - ◆ Flow control
    - RS-485 auto direction
  - ◆ Port Capability:
    - 4 isolated RS-422/485 port (DIP switch/software select)
    - Max. port per system: 32 (8 card)
  - ◆ Isolation voltage: 500VDC
  - ◆ Baud rate: Each port can be configured to 50~115,200 bps
  - ◆ Operation System Compatibility: Windows 95/98/NT/QNX
  - ◆ Connector: DB37 female connector
  - ◆ Cable: External cable with 4 standard DB25(C425M) or DB9(C409M) male connector
  - ◆ Operating temperature: 0 ~ 55 °C

- ◆ Storage temperature: -20 ~ 65 °C
- ◆ Humidity: 10% ~ 95%, non-condensing
- ◆ Dimension: 160 x 100 mm<sup>2</sup> (6.3 x 3.9 in.<sup>2</sup>) 3U
- ◆ Power consumption: +5V @ 1400mA typical

### 1.3.4 Connector Pin Assignment of cPCI-3544

DB37 female connector pin assignment for cPCI-3544.

| DB37 Pin No. | Signal Name    | DB37 Pin No. | Signal Name    |
|--------------|----------------|--------------|----------------|
| 1            | 422_RXD1+(IN)  | 20           | 422_TXD1+(OUT) |
| 2            | 485_D1+(I/O)   | 21           | --             |
| 3            | 422_RXD1-(IN)  | 22           | 422_TXD1-(OUT) |
| 4            | 485_D1-(I/O)   | 23           | --             |
| 5            | GND1           | 24           | 422_RXD2+(IN)  |
| 6            | 422_TXD2+(OUT) | 25           | 485_D2+(I/O)   |
| 7            | --             | 26           | 422_RXD2-(IN)  |
| 8            | 422_TXD2-(OUT) | 27           | 485_D2-(I/O)   |
| 9            | GND2           | 28           | --             |
| 10           | --             | 29           | --             |
| 11           | GND3           | 30           | 485_D3-(I/O)   |
| 12           | 422_TXD3-(OUT) | 31           | 422_RXDC-(IN)  |
| 13           | --             | 32           | 485_D3+(I/O)   |
| 14           | 422_TXD3+(OUT) | 33           | 422_RXD3+(IN)  |
| 15           | GND4           | 34           | --             |
| 16           | 485_D4-(I/O)   | 35           | 422_TXD4-(OUT) |
| 17           | 422_RXD4-(IN)  | 36           | --             |
| 18           | 485_D4+(I/O)   | 37           | 422_TXD4+(OUT) |
| 19           | 422RXD4+(IN)   | --           | --             |

DB25 male connector pin assignment in cPCI-3544 module for RS-422/485 interface.

| DB25 Pin No. | Signal Name |
|--------------|-------------|
| 2            | 422_TXD+    |
| 3            | 422_RXD+    |
| 5            | 485_D+      |
| 6            | 422_RXD-    |
| 7            | GND         |
| 8            | 485_D-      |
| 20           | 422_TXD-    |

DB9 male connector pin assignment in cPCI-3544 module for RS-422/485 interface.

| DB9 Pin No. | Signal Name |
|-------------|-------------|
| 1           | 485_D-      |
| 2           | 422_RXD+    |
| 3           | 422_TXD+    |
| 4           | 422_TXD-    |
| 5           | GND         |
| 6           | 422_RXD-    |
| 8           | 485_D+      |

J2 connector pin assignment in cPCI-3544 module for RS-422/485 interface.

|     |     |              |               |               |               |               |     |
|-----|-----|--------------|---------------|---------------|---------------|---------------|-----|
| 22  | GND | GA4          | GA3           | GA2           | GA1           | GA0           | GND |
| 21  | GND |              |               |               |               |               | GND |
| 20  | GND |              |               |               |               |               | GND |
| 19  | GND |              | TXD- <b>4</b> |               | TXD+ <b>4</b> |               | GND |
| 18  | GND | GND <b>4</b> | D- <b>4</b>   | RXD- <b>4</b> | D+ <b>4</b>   | RXD+ <b>4</b> | GND |
| 17  | GND |              |               |               |               |               | GND |
| 16  | GND |              |               |               |               |               | GND |
| 15  | GND |              |               |               |               |               | GND |
| 14  | GND |              | TXD- <b>3</b> |               | TXD+ <b>3</b> |               | GND |
| 13  | GND | GND <b>3</b> | D- <b>3</b>   | RXD- <b>3</b> | D+ <b>3</b>   | RXD+ <b>3</b> | GND |
| 12  | GND |              |               |               |               |               | GND |
| 11  | GND |              |               |               |               |               | GND |
| 10  | GND |              |               |               |               |               | GND |
| 9   | GND |              | TXD- <b>2</b> |               | TXD+ <b>2</b> |               | GND |
| 8   | GND | GND <b>2</b> | D- <b>2</b>   | RXD- <b>2</b> | D+ <b>2</b>   | RXD+ <b>2</b> | GND |
| 7   | GND |              |               |               |               |               | GND |
| 6   | GND |              |               |               |               |               | GND |
| 5   | GND |              |               |               |               |               | GND |
| 4   | GND |              | TXD- <b>1</b> |               | TXD+ <b>1</b> |               | GND |
| 3   | GND | GND <b>1</b> | D- <b>1</b>   | RXD- <b>1</b> | D+ <b>1</b>   | RXD+ <b>1</b> | GND |
| 2   | GND |              |               |               |               |               | GND |
| 1   | GND |              |               |               |               |               | GND |
| Pin | Z   | A            | B             | C             | D             | E             | F   |

P2 / J2 CONNECTOR

❶ Port A ❷ Port B ❸ Port C ❹ Port D

### RS-422

TXD+ : Transmit Data Positive

TXD- : Transmit Data Negative

RXD+ : Receive Data Positive

RXD- : Receive Data Negative

### RS-485

D+ : Data Signal Positive

D- : Data Signal Negative

## R-3544 Rear IO Daughter Board

The R-3544 rear I/O daughter board provides a rear I/O connection transition, the connector and cable used in the rear is the same as the front.

### *DIP Switch and Jumper Setting*

| CARD NO. |   | Port Select |       |     |       |     |       |     |       |     |
|----------|---|-------------|-------|-----|-------|-----|-------|-----|-------|-----|
| SW1-3    | # |             | PortA |     | PortB |     | PortC |     | PortD |     |
| 000      | 0 | SW          | On    | Off | On    | Off | On    | Off | On    | Off |
| 100      | 1 | 4           | 485   | 422 |       |     |       |     |       |     |
| 010      | 2 | 5           |       |     | 485   | 422 |       |     |       |     |
| 110      | 3 | 6           |       |     |       |     | 485   | 422 |       |     |
| 001      | 4 | 7           |       |     |       |     |       |     | 485   | 422 |
| 101      | 5 |             |       |     |       |     |       |     |       |     |
| 011      | 6 |             |       |     |       |     |       |     |       |     |
| 111      | 7 |             |       |     |       |     |       |     |       |     |

The JP1, JP3, JP5, JP7 is for the RS422 terminator and the JP2, JP4, JP6, JP8 is for the RS-485 terminator. The terminator is ON while the jumper is ON

---

## 1.4 Overview of cPCI-3538

### 1.4.1 What is cPCI-3538?

The cPCI-3538 is an enhanced eight ports serial communication card used for cPCI platform. It includes a PGA(Programmable Gate Array), which supports the serial communication controller, and a 62-pin connector which connects external I/O port on the front panel or the rear IO.

The expansion cable has eight standard DB25 connectors and one DB62 connector to connect to cPCI-3538 interface card. User may also use one DB62 to DB62 cable to connect between one cPCI-3538 and C588XB for providing 8 channel isolated RS-232/422/485 interface.

The R-3538 transition board can support rear IO connection by using one DB62 connector.

### 1.4.2 Feature of cPCI-3538

- ◆ 32-bit CompactPCI 3U form factor
- ◆ PCI Rev.2.1 Plug and Play
- ◆ IRQ and IO address automatically assigned by PCI plug-and-play
- ◆ 8 communication ports intelligent buffer
- ◆ High Speed Communication (max. 115200 bps)
- ◆ Suitable for modems, data display, data collection, telecommunication
- ◆ Supports up to 2 cards/8 ports per system
- ◆ Supports DOS, Windows 3.1, Windows 95/98, and Window NT operation system
- ◆ Optional isolated RS-232/422/485 interface for each port independently by C888XB

### 1.4.3 Specification of cPCI-3538

- ◆ Compliant with PCI Spec.2.1
- ◆ Serial communication controller:
  - 16C550A compatible
  - 1.8432 ~ 7.3728 MHz
- ◆ System IO mapping:
  - Assigned by PCI BIOS
  - Shared IRQ
- ◆ Flow control
  - Xon/Xoff control
  - RTS/CTS control
- ◆ Port Capability:
  - 8 independent RS-232C compatible ports
  - Optional external C588XB box for extending to 8 isolated RS-232/422/485 port
  - Max. port per system: 16 (2 card)
- ◆ Baud rate: Each port can be configured to 50~115,200 bps
- ◆ Operation System Compatibility: DOS, Windows 3.1, and Windows 95/98/NT
- ◆ Connector: DB62 female connector
- ◆ Cable: External cable with 8 standard DB25 male connector
- ◆ Operating temperature: 0 ~ 55 °C



- ◆ Storage temperature: -20 ~ 65 °C
- ◆ Humidity: 10% ~ 95%, non-condensing
- ◆ Dimension: 160 x 100 mm<sup>2</sup> (6.3 x 3.9 in.<sup>2</sup>) 3U
- ◆ Power consumption: +5V @ 1400mA typical

### 1.4.4 Connector Pin Assignment of cPCI-3538

DB62 female connector pin assignment for cPCI-3538.

| DB62 Pin No. | Signal Name | DB62 Pin No. | Signal Name | DB62 Pin No. | Signal Name |
|--------------|-------------|--------------|-------------|--------------|-------------|
| 1            | TXD1(OUT)   | 22           | TXD2(OUT)   | 43           | GND         |
| 2            | RXD1(IN)    | 23           | RXD2(IN)    | 44           | GND         |
| 3            | RTS1(OUT)   | 24           | RTS2(OUT)   | 45           | GND         |
| 4            | CTS1(IN)    | 25           | CTS2(IN)    | 46           | TXD4(OUT)   |
| 5            | DSR1(IN)    | 26           | DSR2(IN)    | 47           | RXD4(IN)    |
| 6            | DTR1(OUT)   | 27           | DTR2(OUT)   | 48           | RTS4(OUT)   |
| 7            | DCD1(IN)    | 28           | DCD2(IN)    | 49           | CTS4(IN)    |
| 8            | TXD3(OUT)   | 29           | TXD7(OUT)   | 50           | DSR4(IN)    |
| 9            | RXD3(IN)    | 30           | RXD7(IN)    | 51           | DTR4(OUT)   |
| 10           | RTS3(OUT)   | 31           | RTS7(OUT)   | 52           | DCD4(IN)    |
| 11           | CTS3(IN)    | 32           | CTS7(IN)    | 53           | TXD8(OUT)   |
| 12           | DSR3(IN)    | 33           | DSR7(IN)    | 54           | RXD8(IN)    |
| 13           | DTR3(OUT)   | 34           | DTR7(OUT)   | 55           | RTS8(OUT)   |
| 14           | DCD3(IN)    | 35           | DCD7(IN)    | 56           | CTS8(IN)    |
| 15           | TXD5(OUT)   | 36           | TXD6(OUT)   | 57           | DSR8(IN)    |
| 16           | RXD5(IN)    | 37           | RXD6(IN)    | 58           | DTR8(OUT)   |
| 17           | RTS5(OUT)   | 38           | RTS6(OUT)   | 59           | DCD8(IN)    |
| 18           | CTS(IN)     | 39           | CTS6(IN)    | 60           | GND         |
| 19           | DSR5(IN)    | 40           | DSR6(IN)    | 61           | GND         |
| 20           | DTR5(OUT)   | 41           | DTR6(OUT)   | 62           | GND         |
| 21           | DCD5(IN)    | 42           | DCD6(IN)    | --           | --          |

DB25 male connector pin assignment in cPCI-3538 module for RS-232 interface (port A-H).

| DB25 Pin No. | Signal Name |
|--------------|-------------|
| 2            | TXD(OUT)    |
| 3            | RXD(IN)     |
| 4            | RTS(OUT)    |
| 5            | CTS(IN)     |
| 6            | DSR(IN)     |
| 7            | GND         |
| 8            | DCD(IN)     |
| 20           | DTR(OUT)    |

DB9 male connector pin assignment in cPCI-3538 module for RS-232 interface (port A-H).

| DB25 Pin No. | Signal Name |
|--------------|-------------|
| 2            | TXD(OUT)    |
| 3            | RXD(IN)     |
| 4            | RTS(OUT)    |
| 5            | CTS(IN)     |
| 6            | DSR(IN)     |
| 7            | GND         |
| 8            | DCD(IN)     |
| 20           | DTR(OUT)    |

J2 connector pin assignment in cPCI-3538 module for RS-232 interface.

|     |     |                  |                  |                  |                  |                  |     |                   |
|-----|-----|------------------|------------------|------------------|------------------|------------------|-----|-------------------|
| 22  | GND | GA4              | GA3              | GA2              | GA1              | GA0              | GND | P2 / J2 CONNECTOR |
| 21  | GND |                  |                  |                  |                  |                  | GND |                   |
| 20  | GND | DSR <sup>8</sup> | DCD <sup>8</sup> | DTR <sup>8</sup> | RTS <sup>8</sup> | CTS <sup>8</sup> | GND |                   |
| 19  | GND | FG <sup>8</sup>  | TX <sup>8</sup>  | RX <sup>8</sup>  | SG <sup>8</sup>  |                  | GND |                   |
| 18  | GND | FG <sup>7</sup>  | TX <sup>7</sup>  | RX <sup>7</sup>  | SG <sup>7</sup>  |                  | GND |                   |
| 17  | GND | DSR <sup>7</sup> | DCD <sup>7</sup> | DTR <sup>7</sup> | RTS <sup>7</sup> | CTS <sup>7</sup> | GND |                   |
| 16  | GND |                  |                  |                  |                  |                  | GND |                   |
| 15  | GND | DSR <sup>6</sup> | DCD <sup>6</sup> | DTR <sup>6</sup> | RTS <sup>6</sup> | CTS <sup>6</sup> | GND |                   |
| 14  | GND | FG <sup>6</sup>  | TX <sup>6</sup>  | RX <sup>6</sup>  | SG <sup>6</sup>  |                  | GND |                   |
| 13  | GND | FG <sup>5</sup>  | TX <sup>5</sup>  | RX <sup>5</sup>  | SG <sup>5</sup>  |                  | GND |                   |
| 12  | GND | DSR <sup>5</sup> | DCD <sup>5</sup> | DTR <sup>5</sup> | RTS <sup>5</sup> | CTS <sup>5</sup> | GND |                   |
| 11  | GND |                  |                  |                  |                  |                  | GND |                   |
| 10  | GND | DSR <sup>4</sup> | DCD <sup>4</sup> | DTR <sup>4</sup> | RTS <sup>4</sup> | CTS <sup>4</sup> | GND |                   |
| 9   | GND | FG <sup>4</sup>  | TX <sup>4</sup>  | RX <sup>4</sup>  | SG <sup>4</sup>  |                  | GND |                   |
| 8   | GND | FG <sup>3</sup>  | TX <sup>3</sup>  | RX <sup>3</sup>  | SG <sup>3</sup>  |                  | GND |                   |
| 7   | GND | DSR <sup>3</sup> | DCD <sup>3</sup> | DTR <sup>3</sup> | RTS <sup>3</sup> | CTS <sup>3</sup> | GND |                   |
| 6   | GND |                  |                  |                  |                  |                  | GND |                   |
| 5   | GND | DSR <sup>2</sup> | DCD <sup>2</sup> | DTR <sup>2</sup> | RTS <sup>2</sup> | CTS <sup>2</sup> | GND |                   |
| 4   | GND | FG <sup>2</sup>  | TX <sup>2</sup>  | RX <sup>2</sup>  | SG <sup>2</sup>  |                  | GND |                   |
| 3   | GND | FG <sup>1</sup>  | TX <sup>1</sup>  | RX <sup>1</sup>  | SG <sup>1</sup>  |                  | GND |                   |
| 2   | GND | DSR <sup>1</sup> | DCD <sup>1</sup> | DTR <sup>1</sup> | RTS <sup>1</sup> | CTS <sup>1</sup> | GND |                   |
| 1   | GND |                  |                  |                  |                  |                  | GND |                   |
| Pin | Z   | A                | B                | C                | D                | E                | F   |                   |

## **RS-232**

|     |   |                     |     |   |                     |
|-----|---|---------------------|-----|---|---------------------|
| FG  | : | Frame Ground        | TX  | : | Transmit Data       |
| RX  | : | Receive Data        |     |   |                     |
| RTS | : | Request to Send     | CTS | : | Clear to Send       |
| DSR | : | Data Set Ready      |     |   |                     |
| SG  | : | Signal Ground       | DCD | : | Data Carrier Detect |
| DTR | : | Data Terminal Ready |     |   |                     |

## **R-3538 Rear IO Daughter Board**

The R-3538 rear I/O daughter board provides a rear I/O connection transition, the connector and cable used in the rear are the same as the front.

# 2

## Installation

This chapter describes the configurations of the serial communication module. At first, the contents in the package and unpacking information that you should care about are described. The serial communication modules are plug-and-play and very easy to install into cPCI system.

---

### 2.1 What You Have

In addition to this *User's Manual*, the package includes the following items:

- ◆ cPCI-3534/3544/3538 Serial Communication Interface Module
- ◆ Expansion Cable (C425M, C409M or C825M, C809M)
- ◆ R-3534/3538 Rear IO Daughter Board (For the rear I/O version)
- ◆ “ADLink All-in-One Compact Disc” or Disks

If any of these items is missing or damaged, contact the dealer from whom you purchased the product. Save the shipping materials and carton in case you want to ship or store the product in the future.

---

## 2.2 Unpacking

Your serial communication module contains sensitive electronic components that can be easily damaged by static electricity.

The module should be done on a grounded anti-static mat. The operator should be wearing an anti-static wristband, grounded at the same point as the anti-static mat.

Inspect the module carton for obvious damage. Shipping and handling may cause damage to your module. Be sure there are no shipping and handling damages on the module before processing.

After opening the module carton, extract the system module and place it only on a grounded anti-static surface component side up.

Again inspect the module for damage. Press down on all the socket IC's to make sure that they are properly seated. Do this only with the module place on a firm flat surface.

---

Note: DO NOT APPLY POWER TO THE MODULE IF IT HAS BEEN DAMAGED.

---

***You are now ready to install your cPCI Module.***

---

## 2.3 Installation Procedure

1. Turn off your cPCI computer system.
2. Turn off all accessories (printer, modem, monitor, etc.) connected to computer.
3. Select a cPCI slot.
4. Before handling the serial communication module, discharge any static buildup on your body by touching the metal case of the computer. Hold the edge and do not touch the components.
5. Position the module into the cPCI slot you selected.
6. Secure the module in place of the system.

---

## 2.4 Hardware Configuration

The serial communication module has plug and play component, the card can requests memory usage (I/O port locations) of the card which is assigned by system BIOS. The address assignment is done on a board-by-board basis for all serial communication cards in the system.

The jumper SW1-1 for cPCI-3534 and the JP1 for cPCI-3538 is used for the system to recognize the first or second card of the same model in the system if there are two cards of the same on board.

The SW1-3 for cPCI-3544 is used for the system to recognize the card number of the same model in the system if there are more than two cards of the same on board.

### 2.4.1 Wiring Example

You can use the C425M and C409M for wiring. Please refer to Chapter 1 for pin assignment.



---

## 2.5 Software Installation

### 2.5.1 Windows NT Installation

Once Windows NT system has been started, login using an account with administrative right.

1. Start the [Control Panel] applet by double clicking the icon in the [Program Managers] main group.
2. In the [Control Panel] applet, double click [Network] icon to bring up the Network Control Panel Applet (NCPA).
3. Within the NCPA, select the [Add Adaptor] button, a list of possible adaptors should be displayed. Go to the end of this list and select <Other> requires disk from manufacturer.
4. When prompted for the path, specify the drive and directory where the NCPA can find the new driver for the card you install.

For cPCI-3534, we may specify as follow:

X:\NuCOMCPCI3534\NT4

For cPCI-3544, we may specify as follow:

X:\NuCOMCPCI3544\NT4

For cPCI-3538, we may specify as follow:

X:\NuCOMCPCI3538\NT4

( Where X indicates CD-ROM drive )

1. Now, you can follow the configuration dialog boxes to install the driver.
2. In the default condition, the TTY port is given name from "COM3". User can specify the start "COM" port number in installation procedure.
3. We can install up to two same type serial communication cards in one NT system.

4. When you need to install two same type serial communication cards in one NT system, you must confirm to let one card's SW1-1 is ON while the other card's SW1-1 is OFF for cPCI-3534 and JP1 is ON while the other card's JP1 is OFF for cPCI-3538. The same manner can be apply to cPCI-3544 with SW1-3 adjusting to different number.
5. The card with switch ON will have low COM port number. The card with switch OFF will have higher COM port number follow the card with switch ON.
6. If you install two the same type serial communication modules with switch ON or OFF simultaneously, we can not confirm that both cards will active properly.
7. If you install multiple cards in one NT system simultaneously, please confirm that the COM port number assigned do not overlap for different card. Or you may have improperly operation in your system.
8. For easy to maintain NT system's COM port number, we suggest that you must set the switch ON for the first card to be installed in NT system.
9. After you install the driver, you need to reboot your PC, then you can have more COM port available.
10. If you had installed our NT driver in your system before, you might remove this driver firstly, then you can install our new version driver. Or you might have some problem in your system.

## 2.5.2 Windows 95/98 Installation

Once Windows 95/98 system has been started, the plug & play function in 95/98 system will find the new serial communication card. If this is the first time to install serial communication card in your Windows 95/98 system, you will be informed to install the driver. Please follow the instruction message to input the COM port number starting value for the first and second cards.

Because the resource will be assigned by PCI BIOS, it is not easy to check which card is first or second from resource. So the switch will play the role for system to fix the COM port number for each card.

After you had installed the driver, you might be informed to have new hardware found. You do not have to install the driver again, Windows 95/98 will add the COM port automatically.

1. You can install up to two cPCI-3534/3538 cards in one 95/98 system.
2. When you need to install two same type cards in one 95/98 system, you must confirm to let one card's switch is ON, and the other card's switch is OFF.
3. The card with switch ON will have COM port number assigned for first card. The card with switch OFF will have COM port number assigned for second card.
4. If you install two the same type serial communication cards with switch ON or OFF simultaneously, we can not confirm that both cards will active properly.
5. If you install multiple cards in one 95/98 system simultaneously, please confirm that the COM port number assigned does not overlap for different card. Or you may have improperly operation in your system.
6. For easy to maintain 95/98 system's COM port number, we suggest that you must set the switch ON for the first card to be installed in 95/98 system.
7. The serial communication card can be used in interrupt shared mode. PCI BIOS will assign IRQ for each serial communication card. For multi-card application, we can just share one IRQ in each card, but you must confirm that one system may have minimum one IRQ left for P&P function. If there are no IRQ left to be

assigned to serial communication card, you might have wrong operation.


### **2.5.3 For UNIX, LINUX and QNX user**


You can download the .tar driver from ADLINK website or contact the dealer near you for service and support.

## 2.5.4 Windows 95/98/NT Utility Diagram for cPCI-3544

The cPCI-3534/3538 doesn't need any configuration utility. It just likes the system COM ports.

The cPCI-3544 is a 4-Port RS-422/485 serial communication module. It supports the software configuration for RS-422/485. When choosing the RS-422 mode, the RS-485 port would be disabled automatically. You can run the AdlComSet.exe for configuration.





---

## 2.6 AP Examples

Please follow the installation guide above first.

### **2.6.1 Dos Environment**

For cPCI-3534/3538, please refer to the README file includes in the driver.

The cPCI-3544 doesn't provide the DOS library, if you want to program by yourself. Contact the dealer from whom you purchase the product, or the service mailbox in ADLink.

### **2.6.2 Windows(Windows 95/98/NT) Environment**

You can find the extra ports in the system control panel after installing the driver. And you can program just the same as usual COM port. There are sample program in the driver. Please refer to that.

### **2.6.3 Linux Environment**

You can find the sample program in the driver.

## Product Warranty/Service

ADLINK warrants that equipment furnished will be free from defects in material and workmanship for a period of one year from the date of shipment. During the warranty period, we shall, at our option, either repair or replace any product that proves to be defective under normal operation.

This warranty shall not apply to equipment that has been previously repaired or altered outside our plant in any way as to, in the judgment of the manufacturer, affect its reliability. Nor will it apply if the equipment has been used in a manner exceeding its specifications or if the serial number has been removed.

ADLINK does not assume any liability for consequential damages as a result from our product uses, and in any event our liability shall not exceed the original selling price of the equipment. The remedies provided herein are the customer's sole and exclusive remedies. In no event shall ADLINK be liable for direct, indirect, special or consequential damages whether based on contract of any other legal theory.

The equipment must be returned postage-prepaid. Package it securely and insure it. You will be charged for parts and labor if the warranty period is expired or the product is proves to be misuse, abuse or unauthorized repair or modification.





## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)