

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.


Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Visit our website - *Click HERE*



PNOZ 1

PILZ
THE SPIRIT OF SAFETY

- Safety relays

Operating Manual-21114-EN-04

This document is the original document.

All rights to this documentation are reserved by Pilz GmbH & Co. KG. Copies may be made for the user's internal purposes. Suggestions and comments for improving this documentation will be gratefully received.

Source code from third-party manufacturers or open source software has been used for some components. The relevant licence information is available on the Internet on the Pilz homepage.

Pilz®, PIT®, PMI®, PNOZ®, Primo®, PSEN®, PSS®, PVIS®, SafetyBUS p®, SafetyEYE®, SafetyNET p®, the spirit of safety® are registered and protected trademarks of Pilz GmbH & Co. KG in some countries.


SD means Secure Digital

Introduction **4**
Validity of documentation 4
Using the documentation 4
Definition of symbols 4

Safety **5**
Intended use 5
Safety regulations 5
Safety assessment 5
Use of qualified personnel 6
Warranty and liability 6
Disposal 6
For your safety 6

Unit features **7**

Safety features **7**

Block diagram/terminal configuration **7**
Types: AC 7
Type: DC 8

Function Description **8**
Operating modes 8
Timing diagram 9

Installation **9**

Wiring **9**

Preparing for operation **10**

Operation **12**
Status indicators 12

Faults – Interference **12**

Dimensions in mm **13**

Technical details **14**
Safety characteristic data 23

Supplementary data **24**
Service life graph 24

Order reference **25**

EC declaration of conformity **25**

Introduction

Validity of documentation

This documentation is valid for the product PNOZ 1. It is valid until new documentation is published.

This operating manual explains the function and operation, describes the installation and provides guidelines on how to connect the product.

Using the documentation

This document is intended for instruction. Only install and commission the product if you have read and understood this document. The document should be retained for future reference.

Definition of symbols

Information that is particularly important is identified as follows:



DANGER!

This warning must be heeded! It warns of a hazardous situation that poses an immediate threat of serious injury and death and indicates preventive measures that can be taken.



WARNING!

This warning must be heeded! It warns of a hazardous situation that could lead to serious injury and death and indicates preventive measures that can be taken.



CAUTION!

This refers to a hazard that can lead to a less serious or minor injury plus material damage, and also provides information on preventive measures that can be taken.



NOTICE

This describes a situation in which the product or devices could be damaged and also provides information on preventive measures that can be taken. It also highlights areas within the text that are of particular importance.



INFORMATION

This gives advice on applications and provides information on special features.

Safety

Intended use

The safety relay PNOZ 1 provides a safety-related interruption of a safety circuit.

The safety relay meets the requirements of EN 60947-5-1 and EN 60204-1 and may be used in applications with:

- E-STOP pushbuttons
- Safety gates

The following is deemed improper use in particular

- Any component, technical or electrical modification to the product,
- Use of the product outside the areas described in this manual,
- Use of the product outside the technical details (see Technical details [📖 14]).



NOTICE

EMC-compliant electrical installation

The product is designed for use in an industrial environment. The product may cause interference if installed in other environments. If installed in other environments, measures should be taken to comply with the applicable standards and directives for the respective installation site with regard to interference.

Safety regulations

Safety assessment

Before using a device, a safety assessment in accordance with the Machinery Directive is required.

The product as an individual component fulfils the functional safety requirements in accordance with EN ISO 13849 and EN 62061. However, this does not guarantee the functional safety of the overall plant/machine. To achieve the relevant safety level of the overall plant/machine's required safety functions, each safety function needs to be considered separately.

Use of qualified personnel

The products may only be assembled, installed, programmed, commissioned, operated, maintained and decommissioned by persons who are competent to do so.

A competent person is a qualified and knowledgeable person who, because of their training, experience and current professional activity, has the specialist knowledge required. To be able to inspect, assess and operate devices, systems and machines, the person has to be informed of the state of the art and the applicable national, European and international laws, directives and standards.

It is the company's responsibility only to employ personnel who

- Are familiar with the basic regulations concerning health and safety / accident prevention,
- Have read and understood the information provided in the section entitled Safety
- Have a good knowledge of the generic and specialist standards applicable to the specific application.

Warranty and liability

All claims to warranty and liability will be rendered invalid if

- The product was used contrary to the purpose for which it is intended,
- Damage can be attributed to not having followed the guidelines in the manual,
- Operating personnel are not suitably qualified,
- Any type of modification has been made (e.g. exchanging components on the PCB boards, soldering work etc.).

Disposal

- In safety-related applications, please comply with the mission time T_M in the safety-related characteristic data.
- When decommissioning, please comply with local regulations regarding the disposal of electronic devices (e.g. Electrical and Electronic Equipment Act).

For your safety

The unit meets all the necessary conditions for safe operation. However, please note the following:

- Note for overvoltage category III: If voltages higher than low voltage (>50 VAC or >120 VDC) are present on the unit, connected control elements and sensors must have a rated insulation voltage of at least 250 V.

Unit features

- Positive-guided relay outputs:
  - 3 safety contacts (N/O), instantaneous
  - 1 auxiliary contact (N/C), instantaneous
- Connection options for:
  - E-STOP pushbutton
  - Safety gate limit switch
  - Start button
- LED display for:
  - Supply voltage
  - Switch status of the safety contacts
- See order reference for unit types

Safety features


The safety relay meets the following safety requirements:

- The circuit is redundant with built-in self-monitoring.
- The safety function remains effective in the case of a component failure.
- The correct opening and closing of the safety function relays is tested automatically in each on-off cycle.

Block diagram/terminal configuration

Types: AC


- U_B: 24 VAC; Order no. 775600
- U_B: 48 VAC; Order no. 775620
- U_B: 110 - 120 VAC; Order no. 775630
- U_B: 230 - 240 VAC; Order no. 775650



*Insulation between the non-marked area and the relay contacts: Basic insulation (overvoltage category III), Protective separation (overvoltage category II)

Type: DC

- U_B: 24 VDC; Order no. 775695



*Insulation between the non-marked area and the relay contacts: Basic insulation (over-voltage category III), Protective separation (overvoltage category II)

Function Description

The safety relay PNOZ 1 provides a safety-oriented interruption of a safety circuit. When supply voltage is supplied the "POWER" LED is lit. The unit is ready for operation when the feedback loop X1-X2 and the start circuit T33-T34 are closed.

- Input circuit is closed (e.g. E-STOP pushbutton not operated):
  - The LEDs "CH.1" and "CH.2" are lit.
  - Safety contacts 13-14, 23-24 and 33-34 are closed, auxiliary contact 41-42 is open. The unit is active.
- Input circuit is opened (e.g. E-STOP pushbutton operated):
  - The LEDs "CH.1" and "CH.2" go out.
  - Safety contacts 13-14, 23-24 and 33-34 are opened redundantly, auxiliary contact 41-42 is closed.

NOTICE


If the safety requirement (e.g. E-STOP pushbutton operated) is triggered < 6 s after starting, the delay-on de-energisation of the instantaneous safety contacts may be increased (see Technical details [14]).

Operating modes

- Single-channel operation: No redundancy in the input circuit, earth faults in the start and input circuit are detected.
- Dual-channel operation without detection of shorts across contacts: Redundant input circuit, detects PNOZ 1
  - earth faults in the start and input circuit,
  - short circuits in the input circuit.
- Automatic start: Unit is active once the input circuit has been closed.

- Manual start: Unit is active once the input circuit and the start circuit are closed.
- Increase in the number of available contacts by connecting contact expandsion modules or external contactors/relays.

Timing diagram



Legend

- Power: Supply voltage
- Start: Start circuit
- Input: Input circuit
- Output safe: Safety contacts
- Output aux: Auxiliary contact
- [1]: Automatic start
- [2]: Manual start
- a: Input circuit closes before start circuit
- b: Start circuit closes before input circuit
- t_1: Switch-on delay
- t_2: Delay-on de-energisation
- t_3: Recovery time

Installation

- The unit should be installed in a control cabinet with a protection type of at least IP54.
- Use the notch on the rear of the unit to attach it to a DIN rail (35 mm).
- When installed vertically: Secure the unit by using a fixing element (e.g. retaining bracket or end angle).

Wiring

Please note:

- Information given in the "Technical details [14]" must be followed.
- Outputs 13-14, 23-24, 33-34 are safety contacts; output 41-42 is an auxiliary contact (e.g. for display).
- Auxiliary contact 41-42 should **not** be used for safety circuits!



- Do not connect undesignated terminals.
- To prevent contact welding, a fuse should be connected before the output contacts (see Technical details [📖 14]).
- Calculation of the max. cable length I_{max} in the input circuit:





$$I_{max} = \frac{R_{lmax}}{R_l / km}$$

R_{lmax} = max. overall cable resistance (see Technical details [📖 14])
R_l / km = cable resistance/km

- Use copper wiring with a temperature stability of 60/75 °C.
- To prevent EMC interferences (particularly common-mode interferences) the measures described in EN 60204-1 must be executed. This includes the separate routing of cables of the control circuits (input, start and feedback loop) from other cables for energy transmission or the shielding of cables, for example.
- Do not switch low currents using contacts that have been used previously with high currents.
- Adequate protection must be provided on all output contacts with capacitive and inductive loads.
- On 24 VDC devices:
  The power supply must comply with the regulations for extra low voltages with protective electrical separation (SELV, PELV) in accordance with VDE 0100, Part 410.






Preparing for operation

Supply voltage	AC	DC
		

Input circuit	Single-channel	Dual-channel
E-STOP **without** detection of shorts across contacts		
Safety gate **without** detection of shorts across contacts		

NOTICE


With single-channel wiring the safety level of your machine/plant may be lower than the safety level of the unit (see Safety characteristic data [23]).

Start circuit	E-STOP wiring (single-channel, dual-channel) Safety gate (single-channel)	Safety gate (dual-channel)
Automatic start		
Automatic start with start-up test		
Manual start		

NOTICE

In the event of an automatic start or manual start with bridged start contact (fault):

The unit starts up automatically when the safeguard is reset, e.g. when the E-STOP pushbutton is released. Use external circuit measures to prevent an unexpected restart.

Feedback loop	without feedback loop monitoring	With feedback loop monitoring
Link or contacts from external contactors		

Legend

- S1/S2: E-STOP/safety gate switch
- S3: Reset button
- : Switch operated
- : Gate open
- : Gate closed

Operation

When the relay outputs are switched on, the mechanical contact on the relay cannot be tested automatically. Depending on the operational environment, measures to detect the non-opening of switching elements may be required under some circumstances.

When the product is used in accordance with the European Machinery Directive, a check must be carried out to ensure that the safety contacts on the relay outputs open correctly. Open the safety contacts (switch off output) and start the device again, so that the internal diagnostics can check that the safety contacts open correctly

- for SIL CL 3/PL e at least 1x per month
- for SIL CL 2/PL d at least 1x per year



NOTICE

The safety function should be checked after initial commissioning and each time the plant/machine is changed. The safety functions may only be checked by qualified personnel.

Status indicators

LEDs indicate the status and errors during operation:

LED on

POWER

Supply voltage is present.


CH.1
Safety contacts of channel 1 are closed.

CH.2
Safety contacts of channel 2 are closed.

Faults – Interference

- Earth fault: The supply voltage fails and the safety contacts open. Once the cause of the respective fault has been rectified and the supply voltage is switched off for approx. 1 minute, the unit is ready for operation again.
- Contact malfunctions: If the contacts have welded, reactivation will not be possible after the input circuit has opened.
- LED "POWER" does not light: Short circuit or no supply voltage.

Dimensions in mm



Technical details

Order no. 775600 – 775620

See below for more order numbers

General	775600	775620
Certifications	CCC, CE, EAC (Eurasian), TÜV, cULus Listed	CCC, CE, EAC (Eurasian), TÜV, cULus Listed
Electrical data	**775600**	**775620**
Supply voltage		
Voltage	24 V	48 V
Kind	AC	AC
Voltage tolerance	-15 %/+10 %	-15 %/+10 %
Output of external power supply (AC)	5,5 VA	5,5 VA
Frequency range AC	50 - 60 Hz	50 - 60 Hz
Duty cycle	100 %	100 %
Inputs	**775600**	**775620**
Number	2	2
Voltage at		
Input circuit DC	24 V	24 V
Start circuit DC	24 V	24 V
Feedback loop DC	24 V	24 V
Current at		
Input circuit DC	30 mA	30 mA
Start circuit DC	50 mA	50 mA
Feedback loop DC	50 mA	50 mA
Max. overall cable resistance Rl-max		
Single-channel at UB AC	200 Ohm	200 Ohm
Dual-channel without detection of shorts across contacts at UB AC	350 Ohm	350 Ohm
Relay outputs	**775600**	**775620**
Number of output contacts		
Safety contacts (N/O), instantaneous	3	3
Auxiliary contacts (N/C)	1	1
Max. short circuit current IK	1 kA	1 kA
Utilisation category		
In accordance with the standard	EN 60947-4-1	EN 60947-4-1

Relay outputs	775600	775620
Utilisation category of safety contacts		
AC1 at	**400 V**	**400 V**
Min. current	**0,01 A**	**0,01 A**
Max. current	**5 A**	**5 A**
Max. power	**2000 VA**	**2000 VA**
AC1 at	**240 V**	**240 V**
Min. current	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**
Max. power	**2000 VA**	**2000 VA**
DC1 at	**24 V**	**24 V**
Min. current	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**
Max. power	**200 W**	**200 W**
Utilisation category of auxiliary contacts		
AC1 at	**240 V**	**240 V**
Min. current	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**
Max. power	**2000 VA**	**2000 VA**
DC1 at	**24 V**	**24 V**
Min. current	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**
Max. power	**200 W**	**200 W**
Utilisation category		
In accordance with the standard	**EN 60947-5-1**	**EN 60947-5-1**
Utilisation category of safety contacts		
AC15 at	**230 V**	**230 V**
Max. current	**5 A**	**5 A**
DC13 (6 cycles/min) at	**24 V**	**24 V**
Max. current	**7 A**	**7 A**
Utilisation category of auxiliary contacts		
AC15 at	**230 V**	**230 V**
Max. current	**5 A**	**5 A**
DC13 (6 cycles/min) at	**24 V**	**24 V**
Max. current	**7 A**	**7 A**
Utilisation category in accordance with UL		
Voltage	**240 V AC G. P.**	**240 V AC G. P.**
With current	**8 A**	**8 A**
Voltage	**24 V DC Resistive**	**24 V DC Resistive**
With current	**5 A**	**5 A**
Pilot Duty	**B300, R300**	**B300, R300**

Relay outputs	775600	775620
External contact fuse protection, safety contacts		
In accordance with the standard	**EN 60947-5-1**	**EN 60947-5-1**
Max. melting integral	**240 A²s**	**240 A²s**
Blow-out fuse, quick	**10 A**	**10 A**
Blow-out fuse, slow	**6 A**	**6 A**
Blow-out fuse, gG	**10 A**	**10 A**
Circuit breaker 24V AC/DC, characteristic B/C	**6 A**	**6 A**
External contact fuse protection, auxiliary contacts		
Max. melting integral	**240 A²s**	**240 A²s**
Blow-out fuse, quick	**10 A**	**10 A**
Blow-out fuse, slow	**6 A**	**6 A**
Blow-out fuse, gG	**10 A**	**10 A**
Circuit breaker 24 V AC/DC, characteristic B/C	**6 A**	**6 A**
Conventional thermal current	**8 A**	**8 A**
Contact material	**AgSnO2 + 0,2 µm Au**	**AgSnO2 + 0,2 µm Au**
Times	**775600**	**775620**
Switch-on delay		
With automatic start typ.	**190 ms**	**190 ms**
With automatic start max.	**270 ms**	**270 ms**
With automatic start after power on typ.	**215 ms**	**215 ms**
With automatic start after power on max.	**320 ms**	**320 ms**
With manual start typ.	**190 ms**	**190 ms**
With manual start max.	**270 ms**	**270 ms**
Delay-on de-energisation		
With E-STOP typ.	**15 ms**	**15 ms**
With E-STOP, duty cycle < 6 s, max.	**400 ms**	**400 ms**
With E-STOP, duty cycle ≥ 6 s, max.	**30 ms**	**30 ms**
With power failure typ.	**60 ms**	**60 ms**
With power failure max.	**400 ms**	**400 ms**
Recovery time at max. switching frequency 1/s		
After E-STOP	**300 ms**	**300 ms**
After power failure	**350 ms**	**350 ms**
Supply interruption before de-energisation	**35 ms**	**35 ms**
Simultaneity, channel 1 and 2 max.	**140 ms**	**140 ms**
Environmental data	**775600**	**775620**
Climatic suitability	**EN 60068-2-78**	**EN 60068-2-78**

Environmental data	775600	775620
Ambient temperature		
Temperature range	**-10 - 55 °C**	**-10 - 55 °C**
Storage temperature		
Temperature range	**-40 - 85 °C**	**-40 - 85 °C**
Climatic suitability		
Humidity	**93 % r. h. at 40 °C**	**93 % r. h. at 40 °C**
Condensation during operation	**Not permitted**	**Not permitted**
EMC	**EN 60947-5-1, EN 61000-6-2, EN 61326-3-1**	**EN 60947-5-1, EN 61000-6-2, EN 61326-3-1**
Vibration		
In accordance with the standard	**EN 60068-2-6**	**EN 60068-2-6**
Frequency	**10 - 55 Hz**	**10 - 55 Hz**
Amplitude	**0,35 mm**	**0,35 mm**
Airgap creepage		
In accordance with the standard	**EN 60947-1**	**EN 60947-1**
Overvoltage category	**III / II**	**III / II**
Pollution degree	**2**	**2**
Rated insulation voltage	**400 V**	**400 V**
Rated impulse withstand voltage	**4 kV**	**4 kV**
Protection type		
Housing	**IP40**	**IP40**
Terminals	**IP20**	**IP20**
Mounting area (e.g. control cabinet)	**IP54**	**IP54**
Mechanical data	**775600**	**775620**
Mounting position	**Any**	**Any**
Mechanical life	**10,000,000 cycles**	**10,000,000 cycles**
Material		
Bottom	**PPO UL 94 V0**	**PPO UL 94 V0**
Front	**ABS UL 94 V0**	**ABS UL 94 V0**
Top	**PPO UL 94 V0**	**PPO UL 94 V0**
Connection type	**Screw terminal**	**Screw terminal**
Mounting type	**Fixed**	**Fixed**
Conductor cross section with screw terminals		
1 core flexible	**0,2 - 4 mm², 24 - 10 AWG**	**0,2 - 4 mm², 24 - 10 AWG**
2 core with the same cross section, flexible with crimp connectors, no plastic sleeve	**0,2 - 2,5 mm², 24 - 14 AWG**	**0,2 - 2,5 mm², 24 - 14 AWG**
2 core with the same cross section, flexible without crimp connectors or with TWIN crimp connectors	**0,2 - 2,5 mm², 24 - 14 AWG**	**0,2 - 2,5 mm², 24 - 14 AWG**
Torque setting with screw terminals	**0,6 Nm**	**0,6 Nm**
Stripping length with screw terminals	**8 mm**	**8 mm**

Mechanical data	775600	775620
Dimensions		
Height	**87 mm**	**87 mm**
Width	**90 mm**	**90 mm**
Depth	**121 mm**	**121 mm**
Weight	**500 g**	**500 g**

Where standards are undated, the 2020-07 latest editions shall apply.

Order no. 775630 -775695

General	775630	775650	775695
Certifications	**CCC, CE, EAC (Euras-ian), TÜV, cULus Listed**	**CCC, CE, EAC (Euras-ian), TÜV, cULus Listed**	**CCC, CE, EAC (Euras-ian), TÜV, cULus Listed**
Electrical data	**775630**	**775650**	**775695**
Supply voltage			
Voltage	**110 - 120 V**	**230 - 240 V**	**24 V**
Kind	**AC**	**AC**	**DC**
Voltage tolerance	**-15 %/+10 %**	**-15 %/+10 %**	**-15 %/+10 %**
Output of external power supply (AC)	**5,5 VA**	**5,5 VA**	–
Output of external power supply (DC)	–	–	**2,5 W**
Frequency range AC	**50 - 60 Hz**	**50 - 60 Hz**	–
Residual ripple DC	–	–	**160 %**
Duty cycle	**100 %**	**100 %**	**100 %**
Max. inrush current im-pulse			
Current pulse, A1	–	–	**10 A**
Pulse duration, A1	–	–	**0,25 ms**
Inputs	**775630**	**775650**	**775695**
Number	**2**	**2**	**2**
Voltage at			
Input circuit DC	**24 V**	**24 V**	**24 V**
Start circuit DC	**24 V**	**24 V**	**24 V**
Feedback loop DC	**24 V**	**24 V**	**24 V**
Current at			
Input circuit DC	**30 mA**	**30 mA**	**40 mA**
Start circuit DC	**50 mA**	**50 mA**	**50 mA**
Feedback loop DC	**50 mA**	**50 mA**	**50 mA**

Inputs	775630	775650	775695
Max. overall cable resistance RImax			
Single-channel at UB DC	–	–	**150 Ohm**
Single-channel at UB AC	**200 Ohm**	**200 Ohm**	–
Dual-channel without detection of shorts across contacts at UB DC	–	–	**250 Ohm**
Dual-channel without detection of shorts across contacts at UB AC	**350 Ohm**	**350 Ohm**	–
Relay outputs	**775630**	**775650**	**775695**
Number of output contacts			
Safety contacts (N/O), instantaneous	**3**	**3**	**3**
Auxiliary contacts (N/C)	**1**	**1**	**1**
Max. short circuit current IK	**1 kA**	**1 kA**	**1 kA**
Utilisation category			
In accordance with the standard	**EN 60947-4-1**	**EN 60947-4-1**	**EN 60947-4-1**
Utilisation category of safety contacts			
AC1 at	**400 V**	**400 V**	**400 V**
Min. current	**0,01 A**	**0,01 A**	**0,01 A**
Max. current	**5 A**	**5 A**	**5 A**
Max. power	**2000 VA**	**2000 VA**	**2000 VA**
AC1 at	**240 V**	**240 V**	**240 V**
Min. current	**0,01 A**	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**	**8 A**
Max. power	**2000 VA**	**2000 VA**	**2000 VA**
DC1 at	**24 V**	**24 V**	**24 V**
Min. current	**0,01 A**	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**	**8 A**
Max. power	**200 W**	**200 W**	**200 W**

Relay outputs	775630	775650	775695
Utilisation category of auxiliary contacts			
AC1 at	**240 V**	**240 V**	**240 V**
Min. current	**0,01 A**	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**	**8 A**
Max. power	**2000 VA**	**2000 VA**	**2000 VA**
DC1 at	**24 V**	**24 V**	**24 V**
Min. current	**0,01 A**	**0,01 A**	**0,01 A**
Max. current	**8 A**	**8 A**	**8 A**
Max. power	**200 W**	**200 W**	**200 W**
Utilisation category			
In accordance with the standard	**EN 60947-5-1**	**EN 60947-5-1**	**EN 60947-5-1**
Utilisation category of safety contacts			
AC15 at	**230 V**	**230 V**	**230 V**
Max. current	**5 A**	**5 A**	**5 A**
DC13 (6 cycles/min) at	**24 V**	**24 V**	**24 V**
Max. current	**7 A**	**7 A**	**7 A**
Utilisation category of auxiliary contacts			
AC15 at	**230 V**	**230 V**	**230 V**
Max. current	**5 A**	**5 A**	**5 A**
DC13 (6 cycles/min) at	**24 V**	**24 V**	**24 V**
Max. current	**7 A**	**7 A**	**7 A**
Utilisation category in accordance with UL			
Voltage	**240 V AC G. P.**	**240 V AC G. P.**	**240 V AC G. P.**
With current	**8 A**	**8 A**	**8 A**
Voltage	**24 V DC Resistive**	**24 V DC Resistive**	**24 V DC Resistive**
With current	**5 A**	**5 A**	**5 A**
Pilot Duty	**B300, R300**	**B300, R300**	**B300, R300**
External contact fuse protection, safety contacts			
In accordance with the standard	**EN 60947-5-1**	**EN 60947-5-1**	**EN 60947-5-1**
Max. melting integral	**240 A²s**	**240 A²s**	**240 A²s**
Blow-out fuse, quick	**10 A**	**10 A**	**10 A**
Blow-out fuse, slow	**6 A**	**6 A**	**6 A**
Blow-out fuse, gG	**10 A**	**10 A**	**10 A**
Circuit breaker 24V AC/DC, characteristic B/C	**6 A**	**6 A**	**6 A**

Relay outputs	775630	775650	775695
External contact fuse protection, auxiliary contacts			
Max. melting integral	240 A²s	240 A²s	240 A²s
Blow-out fuse, quick	10 A	10 A	10 A
Blow-out fuse, slow	6 A	6 A	6 A
Blow-out fuse, gG	10 A	10 A	10 A
Circuit breaker 24 V AC/DC, characteristic B/C	6 A	6 A	6 A
Conventional thermal current	8 A	8 A	8 A
Contact material	AgSnO2 + 0,2 µm Au	AgSnO2 + 0,2 µm Au	AgSnO2 + 0,2 µm Au
Times	**775630**	**775650**	**775695**
Switch-on delay			
With automatic start typ.	190 ms	190 ms	190 ms
With automatic start max.	270 ms	270 ms	250 ms
With automatic start after power on typ.	215 ms	215 ms	190 ms
With automatic start after power on max.	320 ms	320 ms	250 ms
With manual start typ.	190 ms	190 ms	190 ms
With manual start max.	270 ms	270 ms	250 ms
Delay-on de-energisation			
With E-STOP typ.	15 ms	15 ms	15 ms
With E-STOP, duty cycle < 6 s, max.	400 ms	400 ms	400 ms
With E-STOP, duty cycle ≥ 6 s, max.	30 ms	30 ms	30 ms
With power failure typ.	60 ms	60 ms	60 ms
With power failure max.	400 ms	400 ms	400 ms
Recovery time at max. switching frequency 1/s			
After E-STOP	300 ms	300 ms	300 ms
After power failure	350 ms	350 ms	350 ms
Supply interruption before de-energisation	35 ms	35 ms	35 ms
Simultaneity, channel 1 and 2 max.	140 ms	140 ms	140 ms
Environmental data	**775630**	**775650**	**775695**
Climatic suitability	EN 60068-2-78	EN 60068-2-78	EN 60068-2-78
Ambient temperature			
Temperature range	-10 - 55 °C	-10 - 55 °C	-10 - 55 °C
Storage temperature			
Temperature range	-40 - 85 °C	-40 - 85 °C	-40 - 85 °C

Environmental data	775630	775650	775695
Climatic suitability			
Humidity	93 % r. h. at 40 °C	93 % r. h. at 40 °C	93 % r. h. at 40 °C
Condensation during operation	Not permitted	Not permitted	Not permitted
EMC	EN 60947-5-1, EN 61000-6-2, EN 61326-3-1	EN 60947-5-1, EN 61000-6-2, EN 61326-3-1	EN 60947-5-1, EN 61000-6-2, EN 61326-3-1
Vibration			
In accordance with the standard	EN 60068-2-6	EN 60068-2-6	EN 60068-2-6
Frequency	10 - 55 Hz	10 - 55 Hz	10 - 55 Hz
Amplitude	0,35 mm	0,35 mm	0,35 mm
Airgap creepage			
In accordance with the standard	EN 60947-1	EN 60947-1	EN 60947-1
Overvoltage category	III / II	III / II	III / II
Pollution degree	2	2	2
Rated insulation voltage	400 V	400 V	400 V
Rated impulse withstand voltage	4 kV	4 kV	4 kV
Protection type			
Housing	IP40	IP40	IP40
Terminals	IP20	IP20	IP20
Mounting area (e.g. control cabinet)	IP54	IP54	IP54
Mechanical data	**775630**	**775650**	**775695**
Mounting position	Any	Any	Any
Mechanical life	10,000,000 cycles	10,000,000 cycles	10,000,000 cycles
Material			
Bottom	PPO UL 94 V0	PPO UL 94 V0	PPO UL 94 V0
Front	ABS UL 94 V0	ABS UL 94 V0	ABS UL 94 V0
Top	PPO UL 94 V0	PPO UL 94 V0	PPO UL 94 V0
Connection type	Screw terminal	Screw terminal	Screw terminal
Mounting type	Fixed	Fixed	Fixed
Conductor cross section with screw terminals			
1 core flexible	0,2 - 4 mm², 24 - 10 AWG	0,2 - 4 mm², 24 - 10 AWG	0,2 - 4 mm², 24 - 10 AWG
2 core with the same cross section, flexible with crimp connectors, no plastic sleeve	0,2 - 2,5 mm², 24 - 14 AWG	0,2 - 2,5 mm², 24 - 14 AWG	0,2 - 2,5 mm², 24 - 14 AWG
2 core with the same cross section, flexible without crimp connectors or with TWIN crimp connectors	0,2 - 2,5 mm², 24 - 14 AWG	0,2 - 2,5 mm², 24 - 14 AWG	0,2 - 2,5 mm², 24 - 14 AWG
Torque setting with screw terminals	0,6 Nm	0,6 Nm	0,6 Nm

Mechanical data	775630	775650	775695
Stripping length with screw terminals	**8 mm**	**8 mm**	**8 mm**
Dimensions			
Height	**87 mm**	**87 mm**	**87 mm**
Width	**90 mm**	**90 mm**	**90 mm**
Depth	**121 mm**	**121 mm**	**121 mm**
Weight	**500 g**	**500 g**	**400 g**

Where standards are undated, the 2020-07 latest editions shall apply.

Safety characteristic data



NOTICE

You must comply with the safety characteristic data in order to achieve the required safety level for your plant/machine.

Operating mode	EN ISO 13849-1: 2015 PL	EN ISO 13849-1: 2015 Category	EN 62061 SIL CL	EN 62061 PFH_D [1/h]	IEC 61511 SIL	IEC 61511 PFD	EN ISO 13849-1: 2015 T_M [year]
–	**PL e**	**Cat. 4**	**SIL CL 3**	**2,31E-09**	**SIL 3**	**2,03E-06**	**20**

Explanatory notes for the safety-related characteristic data:

- The SIL CL value in accordance with EN 62061 corresponds to the SIL value in accordance with EN 61508.
- T_M is the maximum mission time in accordance with EN ISO 13849-1. The value also applies as the retest interval in accordance with EN 61508-6 and IEC 61511 and as the proof test interval and mission time in accordance with EN 62061.

All the units used within a safety function must be considered when calculating the safety characteristic data.



INFORMATION

A safety function's SIL/PL values are **not** identical to the SIL/PL values of the units that are used and may be different. We recommend that you use the PAScal software tool to calculate the safety function's SIL/PL values.

Supplementary data


CAUTION!

It is essential to consider the relay's service life graphs. The relay outputs' safety-related characteristic data is only valid if the values in the service life graphs are met.

The PFH value depends on the switch frequency and the load of the relay output.
If the service life graphs are not accessible, the stated PFH value can be used irrespective of the switch frequency and the load, as the PFH value already considers the relay's B10d value as well as the failure rates of the other components.

Service life graph

The service life graphs indicate the number of cycles from which failures due to wear must be expected. The wear is mainly caused by the electrical load; the mechanical load is negligible.



Example

- Inductive load: 0.2 A
- Utilisation category: AC15
- Contact service life: 4 000 000 cycles

Provided the application to be implemented requires fewer than 4 000 000 cycles, the PFH value (see Technical details) can be used in the calculation.

To increase the service life, sufficient spark suppression must be provided on all output contacts. With capacitive loads, any power surges that occur must be noted. With DC contactors, use flywheel diodes for spark suppression.

Order reference

Product type	Features	Connection type	Order no.
PNOZ 1	24 V AC	Screw terminals	775600
PNOZ 1	48 V AC	Screw terminals	775620
PNOZ 1	110 – 120 VAC	Screw terminals	775630
PNOZ 1	230 – 240 VAC	Screw terminals	775650
PNOZ 1	24 V DC	Screw terminals	775695

EC declaration of conformity

This product/these products meet the requirements of the directive 2006/42/EC for machinery of the European Parliament and of the Council. The complete EC Declaration of Conformity is available on the Internet at www.pilz.com/support/downloads.
Representative: Norbert Fröhlich, Pilz GmbH & Co. KG, Felix-Wankel-Str. 2, 73760 Ostfildern, Germany

Support

Technical support is available from Pilz round the clock.

Americas
Brazil
+55 11 97569-2804
Canada
+1 888 315 7459
Mexico
+52 55 5572 1300
USA (toll-free)
+1 877-PILZUSA (745-9872)

Asia
China
+86 21 60880878-216
Japan
+81 45 471-2281
South Korea
+82 31 778 3300

Australia
+61 3 95600621

Europe
Austria
+43 1 7986263-0
Belgium, Luxembourg
+32 9 3217570
France
+33 3 88104003
Germany
+49 711 3409-444
Ireland
+353 21 4804983
Italy, Malta
+39 0362 1826711
Scandinavia
+45 74436332
Spain
+34 938497433
Switzerland
+41 62 88979-32
The Netherlands
+31 347 320477
Turkey
+90 216 5775552
United Kingdom
+44 1536 462203

You can reach our international hotline on:
+49 711 3409-444
support@pilz.com

Pilz develops environmentally-friendly products using ecological materials and energy-saving technologies. Offices and production facilities are ecologically designed, environmentally-aware and energy-saving. So Pilz offers sustainability, plus the security of using energy-efficient products and environmentally-friendly solutions.

Energy saving by Pilz

BLUECOMPETENCE Alliance Member
Partner of the Engineering Industry Sustainability Initiative

pilz
Partner of:
The Best of German Engineering

21114-EN-04, 2020-10 Printed in Germany
© Pilz GmbH & Co. KG, 2019

CECE®, CHRE®, CMSE®, InduraNET p®, Leansafe®, Master of Safety®, Master of Security®, PAS4000®, PAScal®, PASconfig®, Pilz®, PIT®, PLID®, PMCprimo®, PMCprotego®, PMCtendo®, PMD®, PMI®, PNOZ®, PRBT®, PRCM®, Primo®, PRTM®, PSEN®, PSS®, PVIS®, SafetyBUS p®, SafetyEYE®, SafetyNET p®, THE SPIRIT OF SAFETY® are registered and protected trademark of Pilz GmbH & Co. KG in some countries. We would point out that product features may vary from the details stated in this document, depending on the status at the time of publication and the scope of the equipment. We accept no responsibility for the validity, accuracy and entirety of the text and graphics presented in this information. Please contact our Technical Sup if you have any questions.

We are represented internationally. Please refer to our homepage www.pilz.com for further details or contact our headquarters.

Headquarters: Pilz GmbH & Co. KG, Felix-Wankel-Straße 2, 73760 Ostfildern, Germany
Telephone: +49 711 3409-0, Telefax: +49 711 3409-133, E-Mail: info@pilz.com, Internet: www.pilz.com

PILZ
THE SPIRIT OF SAFETY

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP