

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Visit our website - *Click HERE*

IP-OptoAD12

Opto-Isolated 12-bit A/D Conversion IndustryPack®

User's Manual

©SBS GreenSpring Modular I/O
Subject to change without notice.
Manual Revision: 2 7/27/99 Hardware Revision: A

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

IP-OptoAD12

Opto-Isolated 12-bit A/D Conversion IndustryPack®

SBS GreenSpring Modular I/O
181 Constitution Drive
Menlo Park, CA 94025
(415) 327-1200
(415) 327-3808 FAX

©1994-1998 SBS GreenSpring Modular I/O. IndustryPack is a registered trademark of SBS GreenSpring. QuickPack, Unilin and LineSafe are trademarks of SBS GreenSpring.

SBS GreenSpring acknowledges the trademarks of other organizations for their respective products mentioned in this document.

All rights are reserved: No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without the express consent of SBS GreenSpring. This document is meant solely for the purpose in which it was delivered.

SBS GreenSpring reserves the right to make any changes in the devices or device specifications contained herein at any time and without notice. Customers are advised to verify all information contained in this document.

The electronic equipment described herein generates, uses and may radiate radio frequency energy, which can cause radio interference. SBS GreenSpring assumes no liability for any damages caused by such interference.

SBS GreenSpring products are **not** authorized for use as critical components in medical applications such as life support equipment, without the express consent of the president of SBS GreenSpring.

This product has been designed to operate with IndustryPack carriers and compatible user-provided equipment. Connection of incompatible hardware is likely to cause serious damage. SBS GreenSpring assumes no liability for any damages caused by such incompatibility.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Table of Contents

PRODUCT DESCRIPTION **1**

FUNCTIONAL DESCRIPTION **2**

ANALOG INPUT 2
DATA CORRECTION 2
ADC CORRECTION FORMULA 2

ID PROM CONTENTS **4**

IP ADDRESSING **7**

ADC REGISTER SET 7
ADC Control Register Address $00 ..... *7*
ADC Channel Selection 7
ADC Gain Selection 8
ADC Automatic Settling Time Control 8
ADC Pipeline Mode Control 9
ADC Interrupt Enable 9
ADC Data Register Address $02 ..... *9*
ADC Status Register Address $05 ..... *10*
ADC Convert Start Register Address $07 ..... *10*
Interrupt Vector Register Address $09 ..... *11*
ID Write Enable Register Address $0B *11*

OPERATING MODES **12**

MODE OVERVIEW 12
AUTOMATIC MODE 12
State Diagram Automatic Mode *13*
Automatic Mode with Data Pipeline *13*
Automatic Mode without Data Pipeline *14*
NORMAL MODE 15
State Diagram Normal Mode *16*
Normal Mode with Data Pipeline *16*
Normal Mode without Data Pipeline *17*

IP I/O CONNECTOR **19**

ANALOG INPUT CONNECTIONS 19
POWER INPUT CONNECTIONS 19

SPECIFICATIONS **20**

WARRANTY AND REPAIR **21**

SERVICE POLICY 21
OUT OF WARRANTY REPAIRS 21

ORDER INFORMATION ..... ERROR! BOOKMARK NOT DEFINED.

SCHEMATICS ..... ERROR! BOOKMARK NOT DEFINED.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

List of Figures

Figure 1 IP-OptoAD12 Block Diagram 1
Figure 2 ID PROM Contents IP-OptoAD12-BPV-1 4
Figure 3 ID PROM Contents IP-OptoAD12-BPV-2 5
Figure 4 ID PROM Contents IP-OptoAD12-UPV-1 5
Figure 5 ID PROM Contents IP-OptoAD12-UPV-2 6
Figure 6 ADC Control Register Address 7
Figure 7 CONTREG Input Channel Selection and Mode 8
Figure 8 CONTREG Input Gain Selection 8
Figure 9 CONTREG Automatic Settling Time Control 9
Figure 10 CONTREG Pipeline Mode Control 9
Figure 11 CONTREG Interrupt Enable 9
Figure 12 ADC Data Register 10
Figure 13 Data Register Description 10
Figure 14 ADC Status Register 10
Figure 15 INTVEC Interrupt Vector Register 11
Figure 16 Operating Modes 12
Figure 17 State Diagram Automatic Mode 13
Figure 18 Flowchart Automatic Mode with Data Pipeline 14
Figure 19 Flowchart Automatic Mode without Data Pipeline 15
Figure 20 State Diagram Normal Mode 16
Figure 21 Flowchart Normal Mode with Data Pipeline 17
Figure 22 Flowchart Normal Mode without Data Pipeline 18
Figure 23 IP-OptoAD12 Analog Input Connections 19
Figure 24 IP-OptoAD12 Power Input Connections 19

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Product Description

The IP-OptoAD12 is an IndustryPack^{R} compatible module providing a galvanically isolated 16 channel multiplexed 12 bit ADC with on board DC/DC converter.

Data acquisition and conversion time is mode dependent: up to 10 ms without channel / gain change and up to 12.5 ms with channel / gain change.

The 16 input channels of the multiplexer can be configured by software to operate either in single ended mode or in differential mode with eight inputs. The multiplexer of the ADC circuit is over voltage protected up to 70 $V_{p-p.}$ A programmable gain amplifier allows gains of 1, 2, 5, 10 (IP-OptoAD12-BPV-1 and IP-OptoAD12-UPV-1) or 1, 2, 4, 8 (IP-OptoAD12-UPV-2 and IP-OptoAD12-BPV-2) . The full scale input range is ±10V for the IP-OptoAD12-BPV-1 and IP-OptoAD12-BPV-2 and 0V to 10V for the IP-OptoAD12-UPV-1 and IP-OptoAD12-UPV-2 (for a gain of 1).

Each IP-OptoAD12 is calibrated at the factory. Calibration information is stored in the Identification PROM unique to each IP.




Figure 1 IP-OptoAD12 Block Diagram

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Functional Description

Analog Input

The IP-OptoAD12 provides 16 single ended or 8 differential multiplexed analog inputs. The desired input and the mode (single ended or differential) is selected by programming the input multiplexer.

A software programmable gain amplifier with gain settings of 1, 2, 5 and 10 for the IP-OptoAD12-BPV-1/UPV-1 and 1, 2, 4 and 8 for the IP-OptoAD12-BPV-2/UPV-2 allows a direct connection of a wide range of sensors and instrumentation. The maximum analog input voltage range is ±10V at a gain of 1 for the IP-OptoAD12-BPV-1 and IP-OptoAD12-BPV-2. For the IP-OptoAD12-UPV-1/UPV-2 the maximum analog input voltage range is 0V to 10V at a gain of 1.

The ADC is a 12 bit ADS7808 with a maximum sample and conversion time of 10ms . The 12 bit data are alined in the bits 15-4 of a 16 bit data word, bits 3-0 are always zero.

In multiplexed analog input systems a settling time must expire before the data can be converted after the change of the input channel. This settling time is depended on the programmed gain. At the most analog input solutions it is the responsibility of the user to observe the settling time. The IP-OptoAD12 module has an Automatic Settling Time Control mode. If this mode is enabled, a write to the ADC Control Register, which is necessary to select a new input channel by the multiplexer, initiates a data conversion automatically after the settling time has expired.

The absolute accuracy of the module is increased by using the possibility to correct the data by software with factory calibration factors, which are stored in the individual ID PROM of the module.

Data Correction

There are two errors which affect the DC accuracy of the ADC. The first is the zero error (offset). This is the data value when converting with the input connected with its own ground in single ended mode, or with shorted inputs in differential mode. This error is corrected by subtracting the known error from all readings.

The second error is the gain error. Gain error is the difference between the ideal gain and the actual gain of the programmable gain amplifier and the ADC. It is corrected by multiplying the data value by a correction factor.

The data correction values are obtained during factory calibration and are stored in the modules individual version of the ID PROM. The ADC has a pair of offset and gain correction values for each of the programmable gains.

The correction values are stored in the ID PROM as two's complement byte wide values in the range -128 to 127. For higher accuracy they are scaled to 1/4 LSB.

ADC Correction Formula

The basic formula for correcting any ADC reading for the IP-OptoAD12-BPV-1/BPV-2 (input voltage range +/- 10V) is :

$$\mathbf{Value = Reading * (1 - Gain_{corr} / 8192) - Offset_{corr} \div 4}$$

The basic formula for correcting any ADC reading for the IP-OptoAD12-UPV-1/UPV-2 (input voltage range 0V-10V) is:

$$\mathbf{Value = Reading * (1 - Gain_{corr} / 16384) - Offset_{corr} \div 4}$$

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Value is the corrected result, Reading is the data read from the ADC, $Gain_{corr}$ and $Offset_{corr}$ are the correction factors from the ID PROM.

$Gain_{corr}$ and $Offset_{corr}$ correction factors are stored for each for the possible gain settings.

Note: Floating point arithmetics or scaled integer arithmetics is necessary to avoid rounding error while computing above formula.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

ID PROM Contents

ADDRESS	FUNCTION	
$01	ASCII 'I'	$49
$03	ASCII 'P'	$50
$05	ASCII 'A'	$41
$07	ASCII 'C'	$43
$09	Manufacturer ID	$B3
$0B	Model Number	$18
$0D	Revision	$10
$0F	RESERVED	$00
$11	Driver-ID low-byte	$00
$13	Driver-ID high-byte	$00
$15	number of bytes used	$15
$17	C R C	$ variable
$19	Version -10	$0A
$1B	Offset Error at Gain = 1	$ board dependent
$1D	Offset Error at Gain = 2	$ board dependent
$1F	Offset Error at Gain = 5	$ board dependent
$21	Offset Error at Gain = 10	$ boar dependent
$23	Gain Error at Gain = 1	$ board dependent
$25	Gain Error at Gain = 2	$ board dependent
$27	Gain Error at Gain = 5	$ board dependent
$29	Gain Error at Gain = 10	$ board dependent
$2B	Not used	$00
$ 3F	$ 00	

Figure 2 ID PROM Contents IP-OptoAD12-BPV-1

ADDRESS	FUNCTION	
$01	ASCII 'I'	$49
$03	ASCII 'P'	$50
$05	ASCII 'A'	$41
$07	ASCII 'C'	$43
$09	Manufacturer ID	$B3
$0B	Model Number	$18
$0D	Revision	$10
$0F	RESERVED	$00
$11	Driver-ID low-byte	$00
$13	Driver-ID high-byte	$00
$15	number of bytes used	$15
$17	C R C	$ variable
$19	Version -11	$0B
$ 1B	Offset Error at Gain = 1	$ board dependent

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

$ 1D	Offset Error at Gain = 2	$ board dependent
$ 1F	Offset Error at Gain = 4	$ board dependent
$ 21	Offset Error at Gain = 8	$ board dependent
$ 23	Gain Error at Gain = 1	$ board dependent
$ 25	Gain Error at Gain = 2	$ board dependent
$ 27	Gain Error at Gain = 4	$ board dependent
$ 29	Gain Error at Gain = 8	$ board dependent
$ 2B	Not used	$00
$ 3F	$ 00	

Figure 3 ID PROM Contents IP-OptoAD12-BPV-2

ADDRESS	FUNCTION	
$01	ASCII 'I'	$49
$03	ASCII 'P'	$50
$05	ASCII 'A'	$41
$07	ASCII 'C'	$43
$09	Manufacturer ID	$B3
$0B	Model Number	$18
$0D	Revision	$10
$0F	RESERVED	$00
$11	Driver-ID low-byte	$00
$13	Driver-ID high-byte	$00
$15	number of bytes used	$15
$17	C R C	$ variable
$19	Version -20	$14
$1B	Offset Error at Gain = 1	$ board dependent
$1D	Offset Error at Gain = 2	$ board dependent
$1F	Offset Error at Gain = 5	$ board dependent
$21	Offset Error at Gain = 10	$ board dependent
$23	Gain Error at Gain = 1	$ board dependent
$25	Gain Error at Gain = 2	$ board dependent
$27	Gain Error at Gain = 5	$ board dependent
$29	Gain Error at Gain = 10	$ board dependent
$2B	Not used	$00
.....	.....	
$3F	$00	

Figure 4 ID PROM Contents IP-OptoAD12-UPV-1

ADDRESS	FUNCTION	
$01	ASCII 'I'	$49
$03	ASCII 'P'	$50
$05	ASCII 'A'	$41
$07	ASCII 'C'	$43
$09	Manufacturer ID	$B3
$0B	Model Number	$18
$0D	Revision	$10
$0F	RESERVED	$00
$11	Driver-ID low-byte	$00

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

$13	Driver-ID high-byte	$00
$15	number of bytes used	$15
$17	C R C	$ variable
$19	Version -21	$15
$1B	Offset Error at Gain = 1	$ board dependent
$1D	Offset Error at Gain = 2	$ board dependent
$1F	Offset Error at Gain = 4	$ board dependent
$21	Offset Error at Gain = 8	$ board dependent
$23	Gain Error at Gain = 1	$ board dependent
$25	Gain Error at Gain = 2	$ board dependent
$27	Gain Error at Gain = 4	$ board dependent
$29	Gain Error at Gain = 8	$ board dependent
$2B	Not used	$00
.....	.....	
$3F	$00	

Figure 5 ID PROM Contents IP-OptoAD12-UPV-2

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

IP Addressing

The IP-OptoAD12 is controlled by a set of registers, which are directly accessible in the IO address space of the IP.

ADDRESS	NAME	FUNCTION	SIZE	ACCESS
$ 00	CONTREG	ADC Control Register	word	R/W
$ 02	DATAREG	ADC Data Register	word	R/W
$ 05	STATREG	ADC Status Register	byte	RO
$ 07	CONVERT	ADC Convert Start Register	byte	WO
$ 09	INTVEC	Interrupt Vector Register	byte	R/W
$ 0B	IDWRENA	ID-PROM write enable	byte	WO

Note: IDWRENA is for factory use only, do **not** write to this register.

ADC Register Set

The ADC of the IP-OptoAD12 is controlled by a set of 4 registers. All registers are cleared by IP_RESET.

ADC Control Register
ADC Data Register
ADC Status Register
ADC Convert Start Register

ADC Control Register Address $00

The ADC Control Register CONTREG is used to select an input channel, the gain and the mode for the next data conversion. This is done by writing the corresponding bit pattern into bit 0 to bit 9.




Figure 6 ADC Control Register Address

ADC Channel Selection

Bit 0 to bit 3 of the ADC Control Register CONTREG are used to select an input channel for the data conversion.

Bit 4 of the ADC Control Register CONTREG is used to control if the module operates in differential or in single ended mode. If this bit is set to '1' differential mode is selected.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com




Figure 7 CONTREG Input Channel Selection and Mode

Note: In differential mode only channels 1 to 8 may be selected. In this mode channels 9 to 16 are used as - input for channels 1 to 8.

ADC Gain Selection

Bit 5 and bit 6 of the ADC Control Register CONTREG are used to program the gain of the input amplifier.




Figure 8 CONTREG Input Gain Selection

ADC Automatic Settling Time Control

If bit 7 of the ADC Control Register CONTREG is set to '1', the Automatic Mode for the settling time is enabled. In this mode a data conversion is initiated by writing to the ADC Control Register CONTREG, but however is automatically delayed by hardware until the gain depended settling time has expired.
If bit 7 of the ADC Control Register CONTREG is set to '0', the Normal Mode for the settling time is enabled. In this mode a data conversion is initiated by writing to the ADC Convert Start Register CONVERT after selecting the desired channel and gain by writing to the ADC Control Register CONTREG.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com




Figure 9 CONTREG Automatic Settling Time Control

Note: The settling time for all IP-OptoAD12 Modules is 10ms for all gains.

ADC Pipeline Mode Control

If bit 8 is set to '1' the pipeline mode is selected. In pipeline mode the result from the conversion (N-1) is shifted into the ADC Data Register DATAREG during the conversion N.




Figure 10 CONTREG Pipeline Mode Control

ADC Interrupt Enable

Bit 8 of the ADC Control Register CONTREG is used to enable interrupt generation of the module. If this bit is set to '1' interrupts are always initiated, whenever the settling time is over (on IP_INTREQ1) and data conversion has been completed (on IP_INTREQ0). If the module is in the automatic mode (bit7 set to '1') only one interrupt at the end of data conversion (on IP_INTREQ0) is being generated.




Figure 11 CONTREG Interrupt Enable

ADC Data Register Address $02

The ADC Data Register DATAREG contains the converted data value. The 12 bit ADC value is shifted in the higher bit's of the data register by hardware . This allows direct processing of the data as a 16 bit two's complement integer value for the IP-OptoAD12-BPV-1/BPV-2 and 16 bit straight binary for IP-OptoAD12-UPV-1/UPV-2.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com




Figure 12 ADC Data Register

DESCRIPTION	DIGITAL OUTPUT	
	binary complement IP-OptoAD12-BPV-1/BPV-2	straight binary IP-OptoAD12-BPV-1/BPV-2
+ Full Scale (FS - 1LSB)	$7FF0	$FFF0
Midscale	$0000	$8000
One LSB Below Midscale	$FFF0	$7FF0
- Full Scale	$8000	$0000

Figure 13 Data Register Description

Note: The contents of ADC Data Register DATAREG is not valid as long as the ADC Busy Flag is read as '1'.

ADC Status Register Address $05

Bit 0 and bit 1 of the ADC Status Register STATREG reflect the status of the ADC converter. As long as bit 0 is read as '1', the settling time did not expire after writing to the ADC Control Register CONTREG. Bit 1 indicates the busy status of the ADC converter itself ('1' = ADC busy). If Automatic Mode is active bit 1 indicates a '1' during the settling time and the conversion time.




Figure 14 ADC Status Register

Note: Bit 2 - 7 of the ADC Status Register are undefined.

ADC Convert Start Register Address $07

If the IP-OptoAD12 is configured in Normal Mode writing any value into the ADC Convert Register CONVERT starts a data conversion immediately.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Note: In normal mode it is in the responsibility of the user to observe the settling time busy flag and the ADC busy flag of the ADC Status Register. Writes to the ADC Convert Start Register CONVERT during ADC busy = '1' are ignored.

Interrupt Vector Register Address $09

The Interrupt Vector Register INTVEC is a byte wide read/write register. The Interrupt Vector Register is shared between both interrupt sources, but both, the settling time ready and the ADC data ready will create an individual interrupt. A read cycle to the INTVEC Register acknowledges and clears the interrupt.




Figure 15 INTVEC Interrupt Vector Register

For an interrupt from settling time ready bit 0 of the interrupt vector will read as '1'. For an interrupt from the ADC data ready bit 0 will read as '0'. If the vector register is for example loaded with '$60', settling time ready will create an interrupt at vector '$61' and ADC data ready will create an interrupt at vector '$60'.

Note: The interrupt settling time ready is created by the falling edge of settling time busy status and uses the INTREQ1, the interrupt ADC ready is created by the falling edge of ADC busy status and uses the INTREQ0 interrupt line of the IP bus.

ID Write Enable Register Address $0B

This register is for factory use only. Do not write to this register. If bit 0 is set '1' a write access to the ID-PROM is enabled.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Operating Modes

The IP-OptoAD12 supports four operating modes which are selected with bit 7 (Normal/Automatic Mode) and bit 8 (Pipeline/no Pipeline Mode) of the ADC Control Register CONTREG.

Mode Overview

- Normal Mode / No Pipeline Mode
- Automatic Mode / No Pipeline Mode
- Normal Mode / Pipeline Mode
- Automatic Mode / Pipeline Mode

	CONTREG Bit 7 = 1 Automatic Mode	CONTREG Bit 7 = 0 Normal Mode
CONTREG Bit 8 = 1 Pipline Mode	After the settling time has expired conversion N is started and the result of conversion N-1 is shifted into the ADC Data Register.	A write access to the CONVERT register starts conversion N and shifts the result of conversion N-1 into the ADC Data Register.
CONTREG Bit 8 = 0 No Pipline Mode	After the settling time has expired conversion N is started and the result of conversion N is shifted into the ADC Data Register.	A write access to the CONVERT register starts conversion N and shifts the result of conversion N into the ADC Data Register.

Figure 16 Operating Modes

Note: In Normal Mode the user should observe the settling time by the settle busy flag in the ADC Status Register.

Automatic Mode

The Automatic Mode is enabled by setting bit 7 of the ADC Control Register CONTREG to '1'. A write access to the ADC Control Register CONTREG with bit 7 set to '1' start a conversion for the programmed channel and gain after the settling time has expired. In Pipeline Mode (bit 8 of the ADC Control Register CONTREG set to '1') the result of the previous conversion is shifted into the ADC

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Data Register DATAREG during the actual conversion. If the Pipeline Mode is switched off the result of the actual conversion is shifted into the ADC Data Register DATAREG.

State Diagram Automatic Mode





Figure 17 State Diagram Automatic Mode

In Automatic Mode the ADC busy flag is active during the whole cycle of channel/gain select, settling time and data conversion. When the ADC busy flag becomes inactive (= '0') the conversion result is accessible in the ADC Data Register DATAREG and an interrupt will be generated if interrupts are enabled.

Automatic Mode with Data Pipeline

If Automatic Mode with Pipeline is selected during conversion N the result of conversion N-1 is shifted into the ADC Data Register DATAREG. The acquisition and conversion time in this mode is 20ms.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com



Write access to the ADC Control Register starts automatically the conversion N after the settling time has expired and shifts the result of conversion N-1 into the ADC Data Register.

Bit1 of the ADC Status Register indicates ADC busy during the whole cycle.


Read data of the conversion N-1 from ADC Data Register

Figure 18 Flowchart Automatic Mode with Data Pipeline

Automatic Mode without Data Pipeline

If Automatic Mode without Pipeline is selected the result of the actual conversion is shifted into the ADC Data Register DATAREG. The acquisition and conversion time in this mode is 30ms.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com



Write access to the ADC Control Register starts automatically the conversion after the settling time has expired and shifts the result into the ADC Data Register.

Bit1 of the ADC Status Register indicates ADC busy during the whole cycle.

Read data of the actual conversion from the ADC Data Register

Figure 19 Flowchart Automatic Mode without Data Pipeline

Normal Mode

The Normal Mode is enabled by setting bit 7 of the ADC Control Register CONTREG to `0`. A write access to the ADC Control Register CONTREG with bit 7 set to '0' (Normal Mode enabled) selects a new channel and gain for the next conversion. As long as the settling time expires bit 0 of the ADC Status Register STATREG (settle busy flag) reads as `1`. After the settling time has expired a conversion can be started by writing to the ADC Convert Start Register CONVERT. To achieve higher conversion rates it is possible to select a new channel and gain for the next conversion after the previous conversion has been started. In this mode the settling time for the new channel and the conversion time of the actual channel proceed simultaneously. As long as bit 1 of the ADC Status Register STATREG (ADC busy flag) reads as `1` conversion is in progress. Reading bit 1 of the ADC Status Register as `0`indicates that the conversion result is accessible in the ADC Data Register DATAREG.

If interrupts are enabled two interrupts will be generated: the first interrupt at the end of the settling time, the second interrupt at the end of conversion.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

State Diagram Normal Mode





Figure 20 State Diagram Normal Mode

Normal Mode with Data Pipeline

If Normal Mode with Pipeline is selected during conversion N the result of conversion N-1 is shifted into the ADC Data Register DATAREG. In this mode it is possible that the settling time and conversion time simultaneous proceed. The acquisition and conversion time in this mode is 10ms with no change of channel / gain and 12.5ms with change of channel / gain.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com



Write access to ADC Control Register.

Read bit 0 of ADC Status Register to check for end of settling time.

Write access to ADC Start Convert Register starts conversion N and shifts result of conversion N-1 into the ADC Data Register.

Select a new channel and a new gain during conversion proceeds by a write access to the ADC Control Register.

Read bit1 of the ADC Status Register to check for end of conversion.

Read result of the conversion N-1 from ADC Data Register.


Figure 21 Flowchart Normal Mode with Data Pipeline

Note: For conversions without channel and gain change it is not necessary to observe the settle busy flag of the ADC Status Register.

Normal Mode without Data Pipeline

If Normal Mode without Pipeline is selected the result of the actual conversion is shifted into the ADC Data Register DATAREG. In this mode it is possible that the settling time and conversion time simultaneous proceed. The acquisition and conversion time in this mode is 20ms.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com



Write access to ADC Control Register

Read bit 0 of ADC Status Register to check for end of settling time.

Write access to ADC Start Convert Register starts conversion and shifts result of conversion into the ADC Data Register.

Select a new channel and a new gain during conversion proceeds by a write access to the ADC Control Register.

Read bit1 of the ADC Status Register to check for end of conversion.

Read result of the conversion from ADC Data Register.

Figure 22 Flowchart Normal Mode without Data Pipeline

Note: For conversions without channel and gain change it is not necessary to observe the settle busy flag of the ADC Status Register.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

IP I/O connector

Analog Input Connections

Pin-Number	Single Ended	Differential
01	ADC Input 1	ADC Input 1 +
02	ADC Input 9	ADC Input 1 -
03	AGND	AGND
04	ADC Input 10	ADC Input 2 -
05	ADC Input 2	ADC Input 2 +
06	AGND	AGND
07	ADC Input 3	ADC Input 3 +
08	ADC Input 11	ADC Input 3 -
09	AGND	AGND
10	ADC Input 12	ADC Input 4 -
11	ADC Input 4	ADC Input 4 +
12	AGND	AGND
13	ADC Input 5	ADC Input 5 +
14	ADC Input 13	ADC Input 5 -
15	AGND	AGND
16	ADC Input 14	ADC Input 6 -
17	ADC Input 6	ADC Input 6 +
18	AGND	AGND

Figure 23 IP-OptoAD12 Analog Input Connections

Power Input Connections

Pin-Number	Function
44	AGND
45	-15V
46	AGND
47	+15V
48	AGND
49	+5V
50	AGND

Figure 24 IP-OptoAD12 Power Input Connections

Note: The power input connections are reserved for special versions of the IP-OptoAD12 without on board DC/DC converter.

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Specifications

Logic Interface	IndustryPack Logic Interface
Size	Single-wide IP
I/O Interface	50-conductor flat cable
Analog Inputs	16 single ended channels or 8 differential channels
Input Isolation	All channels galvanically isolated from IP Interface DC/DC converter on board
Input Gain Amplifier	IP-OptoAD12-BPV-1/IP-OptoAD12-UPV-1: Programmable for gain 1, 2, 5, 10 IP-OptoAD12-BPV-2/IP-OptoAD12-UPV-2: Programmable for gain 1, 2, 4, 8
Input Voltage Range	IP-OptoAD12-BPV-1: IP-OptoAD12-UPV-1: ±10V, 0V to 10V (gain = 1) ±5V , 0V to 5V (gain = 2) ±2V , 0V to 2V (gain = 5) ±1V , 0V to 1V (gain = 10) IP-OptoAD12-BPV-2: IP-OptoAD12-UPV-2: ±10V, 0V to 10V (gain = 1) ±5V, 0V to 5V (gain = 2) ±2.5V, 0V to 2.5V (gain = 4) ±1.25V, 0V to 1.25V (gain = 8)
Input Over Voltage	Input over voltage protection up to 70V p-p
Input ADC	12 bit ADC; data acquisition and conversion time up to 10ms without channel/gain change and up to 12.5ms with channel/gain change (mode dependent).
Calibration Data	Calibration data for gain and offset correction in ID PROM
Accuracy	± 1LSB, after calibration for all IP-OptoAD12 Modules.
Linearity	± 1LSB for all IP-OptoAD12 Modules
Wait States	IDSEL 1 wait state IOSEL 0 wait state INTSEL 0 wait state
Power Requirements	typ. 310 mA @ 5V
Environmental	Operating -40? C to 85? C Storage -45? C to 125? C Humidity 5 - 95% non-condensing

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Warranty and Repair

SBS GreenSpring warrants this product to be free from defects in workmanship and materials under normal use and service and in its original, unmodified condition, for a period of one year from the time of purchase. If the product is found to be defective within the terms of this warranty, SBS GreenSpring's sole responsibility shall be to repair, or at SBS GreenSpring's sole option to replace, the defective product. The product must be returned by the original customer, insured, and shipped prepaid to SBS GreenSpring. All replaced products become the sole property of SBS GreenSpring.

SBS GreenSpring's warranty of and liability for defective products is limited to that set forth herein. SBS GreenSpring disclaims and excludes all other product warranties and product liability, expressed or implied, including but not limited to any implied warranties of merchantability or fitness for a particular purpose or use, liability for negligence in manufacture or shipment of product, liability for injury to persons or property, or for any incidental or consequential damages.

SBS GreenSpring's products are not authorized for use as critical components in life support devices or systems without the express written approval of the president of SBS GreenSpring.

Service Policy

Before returning a product for repair, verify as well as possible that the suspected unit is at fault. Then call the Customer Service Department for a RETURN MATERIAL AUTHORIZATION (RMA) number. Carefully package the unit, in the original shipping carton if this is available, and ship prepaid and insured with the RMA number clearly written on the outside of the package. Include a return address and the telephone number of a technical contact. For out-of-warranty repairs, a purchase order for repair charges must accompany the return. SBS GreenSpring will not be responsible for damages due to improper packaging of returned items. For service on SBS GreenSpring products not purchased directly from SBSGreenSpring, contact your reseller. Products returned to SBS GreenSpring for repair by other than the original customer will be treated as out-of-warranty.

Out of Warranty Repairs

Out of warranty repairs will be billed on a material and labor basis. The current minimum repair charge is $100. Customer approval will be obtained before repairing any item if the repair charges will exceed one half of the quantity one list price for that unit. Return transportation and insurance will be billed as part of the repair and is in addition to the minimum charge.

For Service Contact:

Customer Service Department
SBS GreenSpring Modular I/O
181 Constitution Drive
Menlo Park, CA 94025
(415) 327-1200
FAX: (415) 327-3808
email: support@greenspring.com

Artisan Scientific - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisan-scientific.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP