



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

SIMATIC S7-200

Quick Reference Card

Interrupts			
Event Number	Interrupt Description	Priority Group	Priority in Group
8	Port 0: Receive character	Communications (highest)	0
9	Port 0: Transmit complete		0
23	Port 0: Receive message complete		0
24	Port 1: Receive message complete		1
25	Port 1: Receive character		1
26	Port 1: Transmit complete		1
19	PT0 0 complete interrupt	Discrete (middle)	0
20	PT0 1 complete interrupt		1
0	Rising edge, I0.0		2
2	Rising edge, I0.1		3
4	Rising edge, I0.2		4
6	Rising edge, I0.3		5
1	Falling edge, I0.0		6
3	Falling edge, I0.1		7
5	Falling edge, I0.2		8
7	Falling edge, I0.3		9
12	HSC0 CV=PV (current value = preset value)		10
27	HSC0 direction changed		11
28	HSC0 external reset		12
13	HSC1 CV=PV (current value=preset value)		13
14	HSC1 direction input changed		14
15	HSC1 external reset		15
16	HSC2 CV= PV		16
17	HSC2 direction changed		17
18	HSC2 external reset		18
32	HSC3 CV=PV (current value=preset value)		19
29	HSC4 CV=PV (current value=preset value)		20
30	HSC4 direction changed		21
31	HSC4 external reset		22
33	HSC5 CV=PV (current value = preset value)	23	
10	Timed interrupt 0	Timed (lowest)	0
11	Timed interrupt 1		1
21	Timer T32 CT= PT interrupt		2
22	Timer T96 CT=PT interrupt		3

Special Memory Bits			
SM0.0	Always On	SM1.0	Result of operation = 0
SM0.1	First Scan	SM1.1	Overflow or illegal value
SM0.2	Retentive data lost	SM1.2	Negative result
SM0.3	Power up	SM1.3	Division by 0
SM0.4	30 s off / 30 s on	SM1.4	Table full
SM0.5	0.5 s off / 0.5 s on	SM1.5	Table empty
SM0.6	Off 1 scan / on 1 scan	SM1.6	BCD to binary conversion error
SM0.7	Switch in RUN position	SM1.7	ASCII to HEX conversion error

High-Speed Counter Modes								
Mode	HSC0			HSC3	HSC4			HSC5
	I0.0	I0.1	I0.2	I0.1	I0.3	I0.4	I0.5	I0.4
0	Clk			Clk	Clk			Clk
1	Clk		Reset		Clk		Reset	
3	Clk	Direction			Clk	Direction		
4	Clk	Direction	Reset		Clk	Direction	Reset	
6	Clk Up	Clk Dwn			Clk Up	Clk Dwn		
7	Clk Up	Clk Dwn	Reset		Clk Up	Clk Dwn	Reset	
9	Phase A	PhaseB			PhaseA	Phase B		
10	Phase A	PhaseB	Reset		PhaseA	Phase B	Reset	
Mode	HSC1				HSC2			
	I0.6	I0.7	I1.0	I1.1	I1.2	I1.3	I1.4	I1.5
0	Clk				Clk			
1	Clk		Reset		Clk		Reset	
2	Clk		Reset	Start	Clk		Reset	Start
3	Clk	Direction			Clk	Direction		
4	Clk	Direction	Reset		Clk	Direction	Reset	
5	Clk	Direction	Reset	Start	Clk	Direction	Reset	Start
6	Clk Up	Clk Dwn			Clk Up	Clk Dwn		
7	Clk Up	Clk Dwn	Reset		Clk Up	Clk Dwn	Reset	
8	Clk Up	Clk Dwn	Reset	Start	Clk Up	Clk Dwn	Reset	Start
9	Phase A	Phase B			Phase A	Phase B		
10	Phase A	Phase B	Reset		Phase A	Phase B	Reset	
11	Phase A	Phase B	Reset	Start	Phase A	Phase B	Reset	Start

Description	Range Limit				Accessible as...			
	CPU 221	CPU 222	CPU 224	CPU 226	Bit	Byte	Word	DWord
User program size	2 Kwords	2 Kwords	4 Kwords	4 Kwords				
User data size	1 Kwords	1 Kwords	2.5 Kwords	2.5 Kwords				
Process-image input register	I0.0 to I15.7	I0.0 to I15.7	I0.0 to I15.7	I0.0 to I15.7	Ix.y	IBx	IWx	IDx
Process-image output register	Q0.0 to Q15.7	Q0.0 to Q15.7	Q0.0 to Q15.7	Q0.0 to Q15.7	Qx.y	QBx	QWx	QDx
Analog inputs (read only)	—	AIW0 to AIW30	AIW0 to AIW62	AIW0 to AIW62			AIWx	
Analog outputs (write only)	—	AQW0 to AQW30	AQW0 to AQW62	AQW0 to AQW62			AQWx	
Variable memory (V) ¹	V0.0 to V2047.7	V0.0 to V2047.7	V0.0 to V5119.7	V0.0 to V5119.7	Vx.y	VBx	VWx	VDx
Local Memory (L) ²	L0.0 to L63.7	L0.0 to L63.7	L0.0 to L63.7	L0.0 to L63.7	Lx.y	LBx	LWx	LDx
Bit Memory (M)	M0.0 to M31.7	M0.0 to M31.7	M0.0 to M31.7	M0.0 to M31.7	Mx.y	MBx	MWx	MDx
Special Memory (SM) Read only	SM0.0 to SM179.7 SM0.0 to SM29.7	SM0.0 to SM299.7 SM0.0 to SM29.7	SM0.0 to SM299.7 SM0.0 to SM29.7	SM0.0 to SM299.7 SM0.0 to SM29.7	SMx.y	SMBx	SMWx	SMDx
Timers	256 (T0 to T255)	256 (T0 to T255)	256 (T0 to T255)	256 (T0 to T255)	Tx		Tx	
Retentive on-delay 1 ms	T0, T64	T0, T64	T0, T64	T0, T64				
Retentive on-delay 10 ms	T1 to T4, T65 to T68	T1 to T4, T65 to T68	T1 to T4, T65 to T68	T1 to T4, T65 to T68				
Retentive on-delay 100 ms	T5 to T31, T69 to T95	T5 to T31, T69 to T95	T5 to T31, T69 to T95	T5 to T31, T69 to T95				
On/Off delay 1 ms	T32, T96	T32, T96	T32, T96	T32, T96				
On/Off delay 10 ms	T33 to T36, T97 to T100	T33 to T36, T97 to T100	T33 to T36, T97 to T100	T33 to T36, T97 to T100				
On/Off delay 100 ms	T37 to T63, T101 to T255	T37 to T63, T101 to T255	T37 to T63, T101 to T255	T37 to T63, T101 to T255				
Counters	C0 to C255	C0 to C255	C0 to C255	C0 to C255	Cx		Cx	
High-speed counter	HC0, HC3, HC4, HC5	HC0, HC3, HC4, HC5	HC0 to HC5	HC0 to HC5				HCx
Sequential control relays (S)	S0.0 to S31.7	S0.0 to S31.7	S0.0 to S31.7	S0.0 to S31.7	Sx.y	SBx	SWx	SDx
Accumulator registers	AC0 to AC3	AC0 to AC3	AC0 to AC3	AC0 to AC3		ACx	ACx	ACx
Jumps/Labels	0 to 255	0 to 255	0 to 255	0 to 255				
Calls/Subroutines	0 to 63	0 to 63	0 to 63	0 to 63				
Interrupt routines	0 to 127	0 to 127	0 to 127	0 to 127				
PID loops	0 to 7	0 to 7	0 to 7	0 to 7				
Port	Port 0	Port 0	Port 0	Port 0, Port 1				

¹ All V memory can be saved to permanent memory. ² LB60 to LB63 are reserved by STEP 7-Micro/WIN 32, version 3.0 or later.

Boolean Instructions			
LD	N	Load	9-2
LDI	N	Load Immediate	9-3
LDN	N	Load Not	9-2
LDNI	N	Load Not Immediate	9-3
A	N	AND	9-2
AI	N	AND Immediate	9-3
AN	N	AND Not	9-2
ANI	N	AND Not Immediate	9-3
O	N	OR	9-2
OI	N	OR Immediate	9-3
ON	N	OR Not	9-2
ONI	N	OR Not Immediate	9-3
LDBx	N1, N2	Load result of Byte Compare N1(x: <, <=, =, >, >=, or <>)	9-10
ABx	N1, N2	AND result of Byte Compare N1(x: <, <=, =, >, >=, or <>) N2	9-10
OBx	N1, N2	OR result of Byte Compare N1(x: <, <=, =, >, >=, or <>) N2	9-10
LDWx	N1, N2	Load result of Word Compare N1(x: <, <=, =, >, >=, or <>) N2	9-11
AWx	N1, N2	AND result of Word Compare N1(x: <, <=, =, >, >=, or <>) N2	9-11
OWx	N1, N2	OR result of Word Compare N1(x: <, <=, =, >, >=, or <>) N2	9-11
LDDx	N1, N2	Load result of DWord Compare N1(x: <, <=, =, >, >=, or <>) N2	9-12
ADx	N1, N2	AND result of DWord Compare N1(x: <, <=, =, >, >=, or <>) N2	9-12
ODx	N1, N2	OR result of DWord Compare N1(x: <, <=, =, >, >=, or <>) N2	9-12
LDRx	N1, N2	Load result of Real Compare N1(x: <, <=, =, >, >=, or <>) N2	9-13
ARx	N1, N2	AND result of Real Compare N1(x: <, <=, =, >, >=, or <>) N2	9-13
ORx	N1, N2	OR result of Real Compare N1(x: <, <=, =, >, >=, or <>) N2	9-13
NOT		Stack Negation	9-4
EU		Detection of Rising Edge	9-4
ED		Detection of Falling Edge	9-4
=	N	Assign Value	9-6
=I	N	Assign Value Immediate	9-6
S	S_BIT, N	Set bit Range	9-7
R	S_BIT, N	Reset bit Range	9-7
SI	S_BIT, N	Set bit Range Immediate	9-8
RI	S_BIT, N	Reset bit Range Immediate	9-8
Math, Increment, and Decrement Instructions			
+I	IN1, OUT	Add Integer, DWord or Real	9-73
+D	IN1, OUT		9-74
+R	IN1, OUT	IN1+OUT=OUT	9-82
-I	IN1, OUT	Subtract Integer, DWord, or Real	9-73
-D	IN1, OUT		9-74
-R	IN1, OUT	OUT-IN1=OUT	9-82
MUL	IN1, OUT	Multiply Integer (16*16->32) Multiply Integer or Double Integer or Real	9-77
*R	IN1, OUT		9-83
*D	IN1, OUT		9-76
*I	IN1, OUT	IN1 * OUT = OUT	9-75
DIV	IN1, OUT	Divide Integer or Real	9-77
/R	IN1, OUT	OUT / IN1 = OUT	9-83
/D	IN1, OUT		9-76
/I	IN1, OUT		9-75
SQRT	IN, OUT	Square Root	9-85
LN	IN, OUT	Natural Logarithm	9-85
INCB	OUT	Increment Byte, Word or DWord	9-79
INCW	OUT		9-79
INCD	OUT		9-80

DECB	OUT	Decrement Byte, Word, or DWord	9-79
DECW	OUT		9-79
DECD	OUT		9-80
PID	Table, Loop	PID Loop	9-87
COS	Table, Loop	Sine, Cosine, Tangent, or Natural Exponential	9-86
SIN	Table, Loop		9-86
TAN	Table, Loop		9-86
EXP	In, Out		9-86
Timer and Counter Instructions			
TON	Txxx, PT	On Delay Timer	9-15
TOF	Txxx, PT	Off Delay Timer	9-15
TONR	Txxx, PT	Retentive On Delay Timer	9-15
CTU	Cxxx, PV	Count Up	9-23
CTUD	Cxxx, PV	Count Up/Down	9-23
CTD	Cxxx, PV	Count Down	9-23
Real Time Clock Instructions			
TODR	T	Read Time of Day clock	9-71
TODW	T	Write Time of Day clock	9-71
Program Control Instructions			
END		Conditional End of Program	9-145
STOP		Transition to STOP Mode	9-145
WDR		WatchDog Reset (300 ms)	9-146
JMP	N	Jump to defined Label	9-148
LBL	N	Define a Label to Jump to	9-148
CALL	N	Call a Subroutine	9-149
CRET		Conditional Return from SBR	9-149
FOR	INDX, INIT, FINAL	For/Next Loop	9-154
NEXT			9-154
LSCR	N	Load, Transition, and End Sequence Control Relay Segment	9-157
SCRT	N		9-157
SCRE			9-157
AENO		And ENO	9-168
Move, Shift, Rotate and Fill Instructions			
MOVB	IN, OUT	Move Byte, Word, DWord, Real	9-102
MOVW	IN, OUT		9-102
MOVD	IN, OUT		9-102
MOVR	IN, OUT		9-102
BMB	IN, OUT, N	Block Move Byte, Word, DWord	9-103
BMW	IN, OUT, N		9-103
BMD	IN, OUT, N		9-103
BIR	IN, OUT,	Move Byte Immediate Read	9-106
BIW	IN, OUT,	Move Byte Immediate Write	9-106
SWAP	IN	Swap Bytes	9-105
SHRB	Data, S_bit, N	Shift Register Bit	9-127
SRB	OUT, N	Shift Right Byte, Word, DWord	9-120
SRW	OUT, N		9-121
SRD	OUT, N		9-122
SLB	OUT, N	Shift Left Byte, Word, DWord	9-120
SLW	OUT, N		9-121
SLD	OUT, N		9-122
RRB	OUT, N	Rotate Right Byte, Word, DWord	9-123
RRW	OUT, N		9-124
RRD	OUT, N		9-125
RLB	OUT, N	Rotate Left Byte, Word, DWord	9-123
RLW	OUT, N		9-124
RLD	OUT, N		9-125
FILL	IN, OUT, N	Fill memory space with pattern	9-113
Logic Operations			
ALD		And for combinations	9-197
OLD		Or for combinations	9-197
LPS		Logic Push (stack control)	9-197
LRD		Logic Read (stack control)	9-197
LPP		Logic Pop (stack control)	9-198
LDS		Load Stack(stack control)	9-198
ANDB	IN1, OUT	Logical And of Byte, Word, and DWord	9-114
ANDW	IN1, OUT		9-115
ANDD	IN1, OUT		9-116

ORB	IN1, OUT	Logical Or of Byte, Word, and DWord	9-114
ORW	IN1, OUT		9-115
ORD	IN1, OUT		9-116
XORB	IN1, OUT	Logical XOR of Byte, Word, and DWord	9-114
XORW	IN1, OUT		9-115
XORD	IN1, OUT		9-116
INVB	OUT	Invert Byte, Word and DWord	9-118
IN VW	OUT		9-118
INVD	OUT	(1's complement)	9-118
Table, Find, and Conversion Instructions			
ATT	Data, Table	Add data to table	9-107
LIFO	Table, Data	Get data from table	9-112
FIFO	Table, Data		9-111
FND=Src, Patrn, Indx		Find data value in table that matches comparison	9-109
FND<>Src, Patrn, Indx			9-109
FND< Src, Patrn, Indx			9-109
FND> Src, Patrn, Indx			9-109
BCDI	OUT	Convert BCD to Integer	9-130
IBCD	OUT	Convert Integer to BCD	9-130
DTR	IN, OUT	Convert DWord to Real	9-130
TRUNC	IN, OUT	Convert Real to DWord	9-131
ROUND	IN, OUT	Convert Real to DWord	9-131
DTI	IN, OUT	Convert DWord to Word	9-132
ITD	IN, OUT	Convert Word to Dword	9-132
BTI	IN, OUT	Convert Byte to Word	9-133
ITB	IN, OUT	Convert Word to Byte	9-133
ATH	IN, OUT, LEN	Convert ASCII to HEX	9-139
HTA	IN, OUT, LEN	Convert HEX to ASCII	9-139
ITA	IN, OUT, FMT	Convert Integer to ASCII	9-140
DTA	IN, OUT, FMT	Convert Double Integer to ASCII	9-142
RTA	IN, OUT, FMT	Convert Real to ASCII	9-143
DECO	IN, OUT	Decode	9-135
ENCO	IN, OUT	Encode	9-135
SEG	IN, OUT	Generate 7-segment pattern	9-137
Interrupt			
CRETI		Conditional Return form Interrupt	9-171
ENI		Enable Interrupts	9-173
DISI		Disable Interrupts	9-173
ATCH	INT, EVENT	Attach Interrupt routine to event	9-169
DTCH	EVENT	Detach event	9-169
Communication			
XMT	TABLE, PORT	Freeport transmission	9-186
RCV	TABLE, PORT	Freeport receive message	9-186
NETR	TABLE, PORT	Network Read	9-180
NETW	TABLE, PORT	Network Write	9-180
GPA	ADDR, PORT	Get Port Address	9-196
SPA	ADDR, PORT	Set Port Address	9-196
High-Speed Instructions			
HDEF	HSC, Mode	Define High Speed Counter mode	9-27
HSC	N	Activate High Speed Counter	9-27
PLS	X	Pulse Output	9-49



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com