



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com



MIL-240TX 100BASE-TX Port Selector Transceiver
MIL-240FXC 100M SC Redundant Port Selector Transceiver
MIL-240FXT 100M ST Redundant Port Selector Transceiver



- Provides fault-tolerant redundant connections between critical nodes
- Easy to install and use
- Uses standards-based technology

The 240 Redundant Port Selectors make up a family of Fast Ethernet fault-tolerant transceivers. They significantly reduce network downtime, adding a new level of redundancy to Fast Ethernet connections. They also provide a redundant path for critical fast devices.

In a Fast Ethernet network, a critical device such as a file server may be connected to the rest of the network through a hub or a switch. A common problem in this configuration is that the server is often connected to the network through a single cable. If the cable fails, then the server is disconnected from the rest of the network. Similarly, if a port of a hub or switch to which the server is connected fails, the server is disconnected from the network.

The 240TX, 240FXC and 240FXT Redundant Transceivers have three ports: one for the critical (main) device, one for the default (primary) path for the critical device, and another (backup) for the backup path. They are smart devices that will not send any signal on a path that is not active. If the primary path loses its link, then the 240TX, 240FXC and 240FXT will immediately (in less than one microsecond) switch to the backup path.

When the primary path re-establishes its link, the 240 Redundant Port Selector family will automatically switch back to the primary path.



MILAN Technology
 1329 Moffett Park drive
 Sunnyvale, CA 94089
 1-800-466-4626
www.milan.com

Fast Ethernet Redundant Transceivers

MIL-240TX / MIL-240FXC / MIL-240FXT

Features

Unique Features on the 240TX

- Three shielded RJ45 connectors
- Fault-tolerant support for UTP Category 5 cable

Unique Features on the 240FXC/240FXT

- Three ST fiber connectors (240FXT)
- Three SC fiber connectors (240FXC)
- Fault-tolerant for multi-mode fiber
- 100BASE-FX compliant

Common Features of the 240TX, 240FXC and 240FXT

- Supports half- and full-duplex transmission
- Supports 100 m UTP or 2 km fiber transmission distance (full-duplex)
- IEEE 802.3u compliant
- Supports "back-to-back" installation configuration
- Four diagnostic LEDs
- Power supply adapter for international versions

RJ45 Connectors

Type: 8-position, RJ45 receptacle

1: TX+ 5: NC

2: TX- 6: RX-

3: RX+ 7: NC

4: NC 8: NC

(NC= No connection)

Fiber Specifications

Launch power (dBm): Max: 7.0 Min: 15.1

Receiver sensitivity (dBm): Min: 34.4

Maximum cable length: Approximately 2 km (full-duplex)

Latency: 9 nanoseconds

Wavelength: 1300 nm

LED's

PWR: Indicates the presence of POWER

MPSD: Indicates the presence of a LINK signal from the user device connected to the MAIN Port

PPSD: Indicates the presence of a LINK signal from the user device connected to the PRIMARY Port

BPSD: Indicates the presence of a LINK signal from the user device connected to the BACKUP Port

Environmental

Operating temperature: 0° - 40°C (32°F - 105°F)

Storage temperature: 20°C - 70°C (-4°F - 158°F)

Relative humidity: 10% - 90% (non-condensing)

Altitude: 0 - 3,660 m (0 - 12,000 feet)

Power Requirements

Domestic

- Input: 110 VAC @ 60 Hz

- Output: 5 volts DC, 1.5 Amp

International (with IEC receptacle connector)

- Input: 220 VAC @ 50 Hz

- Output: 5 volts DC, 1.5 Amp

Regulatory Approvals

FCC Class A

CE Mark

EN55022 Class B

EN50082

UL 1950

CSA 22 No. 950

EN60950

Ordering Information

MIL-240TX 100BASE-TX Port Selector Transceiver

MIL-240FXC 100M SC Redundant Port Selector Transceiver

MIL-240FXT 100M ST Redundant Port Selector Transceiver

Warranty

Comprehensive 5 years

Milan Technology reserves the right to change specifications or other product information without notice. This publication could include technical inaccuracies or typographical errors. Milan Technology provides this publication "as is" without warranty of any kind, either expressed or implied, including implied warranties of merchantability or fitness for a particular purpose. If your jurisdiction does not allow disclaimer of expressed or implied warranties in certain transactions, this disclaimer may not be applicable.

Milan Technology, the Milan Technology logo are trademarks of MiLAN Technology. All other trademarks are the property of their respective holders.

© Copyright 2003 MiLAN Technology



MiLAN Technology
1329 Moffett Park Drive
Sunnyvale, CA 94089
1-800-466-4526
www.milan.com



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com