



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)

# PXI-3800 Series

3U PXI Intel® Pentium® M System Controllers with VGA/GbE/CF



## Introduction

The ADLINK PXI-3800 series system controller complies with PXI specifications Rev. 2.2 and features up to 1.8 GHz Pentium® M CPU support, hot swappable CompactFlash card, USB 2.0 ports, and Gigabit Ethernet. By using an Intel® Embedded Pentium® M CPU and Intel® 855GME chipset, the PXI-3800 provides both long life and excellent driver support to meet the majority of industrial applications. In addition to its rugged, industrial package, the PXI-3800's extraordinary reliability, high computing performance, and low power consumption make it ideal for test and measurement applications in harsh environments.

### Notice:

These PXI™ controllers implement rear I/O. PXI™ controllers with rear I/O are designed to operate with a matching rear transition module which provides internal or external chassis I/O.

### Warning:

If these PXI™ controllers are used with a chassis that contains a rear transition module that does not match the controller, the rear I/O functionality may not operate and may cause damage to the PXI™ controller or the rear transition module.

## Features

- PXI specifications Rev. 2.2 compliant
- Intel® Pentium® M processor, FSB 400 MHz, CPU frequency up to 1.8 GHz
- Two 200-pin DDR SO-DIMM sockets supporting up to 2 GB RAM
- One 44-pin EIDE (primary IDE) with build-in 2.5 low-profile HDD (40 GB, min.)
- Two CompactFlash interfaces for HDD and FDD replacement; CF2 supports hot swappable CF card functionality

- I/O interface
  - One 10/100/1000 Mb Ethernet port
  - Two USB 2.0 Ports
  - Two RS-232/422/485 ports
  - One parallel port
  - VGA output supporting 1280 x 1024 resolution
  - One AC97 stereo audio output
  - Trigger I/O for advanced PXI trigger functions
- Programmable watchdog timer

## Ordering Information

- **PXI-3800/PM18+**  
3U PXI Pentium® M 1.8 GHz System Controller with 2 GB Memory & 80 GB HDD
- **PXI-3800/PM18**  
3U PXI Pentium® M 1.8 GHz System Controller with 512 MB Memory & 40 GB HDD
- **PXI-3800**  
3U PXI Pentium® M 1.6 GHz System Controller with 512 MB Memory & 40 GB HDD
- **PXI-3800/CM13**  
3U PXI Celeron® M 1.3 GHz System Controller with 512 MB Memory & 40 GB HDD

## Specifications

Model Name	PXI-3800/CM13	PXI-3800	PXI-3800/PM18	PXI-3800/PM18+
<b>Core Features</b>				
CPU	Intel® Celeron® M 320 1.3 GHz	Intel® Pentium® M 747 1.6 GHz	Intel® Pentium® M 745 1.8 GHz	Intel® Pentium® M 745 1.8 GHz
FSB	400 MHz			
Chipset	Intel® 855 GME Graphic Memory Control HUB Intel® 6300ESB I/O Controller Hub			
Memory	512 MB DDR RAM (Two 200-pin SO-DIMM sockets support up to 2 GB memory)			2GB DDR RAM
<b>Display</b>				
CRT	Analog CRT route to VGA connector on the faceplate up to 1280 x 1024 resolution			
LVDS (For rear I/O only)	Single channel LVDS via DVO to LVDS controller up to 1280x1024 resolution			
Interface	One analog VGA DB-15 connector on the faceplate			
<b>I/O Connectivity</b>				
Hard Drive	40 GB IDE hard drive, 5400 RPM			80 GB IDE hard drive, 5400 RPM
IDE port	One 44-pin ATA-33 EIDE interface for external IDE device			
Ethernet	On board Intel® 82545EM Gigabit Ethernet controller One RJ-45 connector with speed/link/active LED on the faceplate			
USB	Two USB 2.0 ports on the faceplate			
Serial Port	Two 16C550 UART compatible COM ports on the faceplate COM1 is RS-232/422/485 jumper selectable			
LPT port	One high-speed bi-directional SPP/EPP/ECP parallel port			
PS2 Keyboard/Mouse	One PS2 KB/MS connector on the faceplate			
Audio	AC97 audio output on faceplate			
Trigger I/O	SMB connector on the faceplate to route an external trigger signal to/from PXI™ trigger bus			
CompactFlash Socket	Two CompactFlash type II sockets. CF1 is based on internal primary IDE interface. CF2 is hot-swappable interface on the faceplate			
<b>Mechanical and Environmental</b>				
Dimensions	3U PXI™ module 60.5 mm x 128.7 mm x 213.2 mm			
Slot Requirements	1 system slot plus 2 controller expansion slots			
Weight	0.9 kg			
Operating Temp.	0 to 55°C			
Storage Temp.	-20 to 80°C			
Relative Humidity	5 to 95%, non-condensing			
Shock	30 G, half-sine, 11 ms pulse duration			
Vibration	Operating: 5 to 500 Hz, 0.5 Grms, 3 axes Non-operating: 5 to 500 Hz, 2.46 Grms, 3 axes			
Emissions Compliance	EN 55022 FCC Class A			
CE Compliance	Immunity: EN 55024			



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)