



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

Model PCI-SG

Synchronized Generator for Computer Clock Synchronization



- PCI local bus operation
- Zero latency
- IRIG A or B input
- IRIG B output
- 1 PPS output
- Programmable pulse rate output/interrupt
- External event occurrence interrupt
- Time compare input/interrupt
- Optional software development kit and drivers

The PCI-SG provides precise time, with zero latency, to computers that have PCI expansion slots. The time is derived from an IRIG A or B time code input or the internal oscillator in the stand-alone generator mode. The frequency of the internal oscillator is precisely disciplined to that of the external synchronization input. Synchronization to an external 1 PPS is also possible.

Time, microseconds through years, and status information are supplied on demand over the 32-bit PCI bus. In addition to time and status, the PCI-SG provides a 1 PPS pulse rate, a programmable time-compare register, a programmable frequency pulse rate, an external event time capture, and an IRIG B serial time code output.

Rear panel BNC connectors are used for the IRIG code input/output. A rear panel mounted multipin connector contains the 1 PPS pulse rate output, the programmable pulse rate output, the external event input signal and the input/output connections for the RS-422 versions of the input/output IRIG time code. You can also configure the analog input code to be single-ended with various input impedance choices. A transformer coupling option is also available. The output code is single ended in its standard configuration or you can specify the balanced transformer coupling option.

Information provided over the PCI bus includes time, status, and the time of occurrence of the external event. Interrupts generated by the programmable rate generator, the occurrence of an external event input, and the time compare occurrence are also provided. Depending upon the operating mode, you can program the hours offset from UTC, leap second, year and daylight savings time.

A TrueTime software development kit, SDK for PCI/CPCI, is optionally available for Windows 95/98 and Windows NT. The SDK includes a Windows NT kernel mode device driver, a Windows 95/98 VxD device driver, a DLL for accessing either of the drivers, a sample program, and code examples. This TrueTime SDK is a tremendous time saving tool for quickly integrating all of the features of the PCI-SG into an application program. Complete access to timing information, status, and control is easily available using the SDK. See the TrueTime SDK for PCI/CPCI data sheet for complete specifications.

SPECIFICATIONS PCI-SG

SYNCHRONIZED GENERATOR MODE

Analog Input Code:	IRIG A or B Ratio: 2:1 to 5:1 Amplitude: 0.5-10 Vpp Impedance: 50-600-10k ohms, internal (single-ended) switch selectable Connector: BNC Timing 5 microseconds Accuracy:
RS-422 Input Code:	IRIG A or B Timing 5 microseconds Accuracy: Connector: DE9

External 1 PPS Input*:	1 microsecond timing accuracy (uses external event input port)
Error Bypass:	Factory set to three frames

STAND-ALONE GENERATOR MODE

Allows the user to preset, start and stop the PCI-SG over the PCI bus.

GENERAL SPECIFICATIONS

IRIG B Serial Code Output (Analog):	Amplitude: Adjustable, 0.5 to 10 Vpp into 600 ohms Ratio: Fixed, 3:1 Connector: BNC
IRIG B Serial Code Output (RS-422):	Amplitude: RS-422 levels Connector: DE9
Oscillator:	Accuracy: 5×10^{-8} (when disciplined to IRIG Code or optional GPS input) Stability: 2.5 PPM, 0°C to +50°C, unlocked
1 PPS Pulse Rate Output:	Level: 0-5 Vdc** Timing: Positive edge on time Duty Cycle: 50% Connector: DE9
Programmable Pulse Rate Output:	Rates: 1 PPS, 10 PPS, 100 PPS, 1 kPPS, 10 kPPS Outputs: Interrupt and pulse Amplitude: 0-5 Vdc** Connector: DE9
External Event Occurrence Input:	Resolution: Microseconds-years Output: Interrupt Event Input: Positive edge of 2-5 Vdc pulse Impedance: Approximately 2k ohms Connector: DE9
Time Compare Output:	Resolution: Microseconds-years Outputs: Interrupt and pulse at compare time Amplitude: +5 Vdc** on compare Connector: DE9

MECHANICAL/ENVIRONMENTAL

Power:	<5 watts
Size:	PCI short card
Operating Temperature:	0°C to +50°C
Storage Temperature:	-17°C to +85°C
Humidity:	To 95%, noncondensing
Certification:	CE pending, Year 2000

SOFTWARE

The PCI-SG includes the TrueTime TimeServer 32 application program for Windows 95/98/NT, which provides control over time-related settings and runs as a background task keeping the computer clock synchronized to the PCI-SG card. TimeServer 32 is a 32-bit Windows application that can provide a Dynamic Data Exchange (DDE) linkage between your installed TrueTime hardware product and DDE-aware Windows applications, such as Microsoft® Excel.

OPTIONS

- TrueTime Software Development Kit (SDK) PCI/CPCI for Windows

95/98 and Windows NT

- For GPS synchronization, see the GPS-PCI data sheet
- Transformer Coupled Input Code (single ended or balanced)
- Transformer Coupled Output Code (balanced)



* When external 1 PPS is used as sync input, the external event is not available.

** 5 Vdc outputs have standard HCMOS levels.

Specifications subject to change without notice.



[Home](#) 

Copyright © 1998 TrueTime, Inc.



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com