



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)

# Analog Input Module for Compact FieldPoint

## NI cFP-AI-118

- 8 analog voltage differential input channels
- 8 voltage input ranges  $-\pm 1$ ,  $\pm 5$ ,  $\pm 10$ ,  $\pm 15$ , 0 to 1, 0 to 5, 0 to 10, and 0 to 15 V
- 16-bit resolution
- Simultaneous sampling on all channels
- 10 Hz digital sync filter configurable per channel
- 100 V<sub>rms</sub> Category I continuous channel-to-channel isolation, verified by 750 V<sub>rms</sub>, 5 s dielectric withstand test
- 250 V<sub>rms</sub> Category II continuous channel-to-ground isolation, verified by a 2,300 V<sub>rms</sub>, 5 s dielectric withstand test
- Hot-swappable
- -40 to 70 °C operation



## Overview

The National Instruments cFP-AI-118 Compact FieldPoint module can measure eight analog inputs at 16-bit resolution at a 10 kS/s per-channel sampling rate with multiple voltage ranges. In addition to high resolution and simultaneous sampling, the NI cFP-AI-118 features 750 V<sub>rms</sub> channel-to-channel isolation and 2,300 V<sub>rms</sub> channel-to-backplane isolation, verified by a 5 s dielectric withstand test. This module also was designed using a new architecture in which the controller obtains access to the module memory immediately, significantly reducing jitter. This feature makes this module ideal for industrial environments where sensors and actuators work at different voltage levels, and ground loops are common.

## Ordering Information

NI cFP-AI-118 .....777318-118

### Recommended Compact FieldPoint System Products

NI cFP-2120 .....777317-2120

NI cFP-BP-4 .....778617-04

NI cFP-CB-1 .....778618-01

NI PS-5 power supply .....778805-90

NI Developer Suite Professional Control Edition .....777906-03

## BUY NOW!

For complete product specifications, pricing, and accessory information, call 800 813 3693 (U.S.) or go to [ni.com/compactfieldpoint](http://ni.com/compactfieldpoint).



# Analog Input Module for Compact FieldPoint

## Specifications

Typical for -40 to 70 °C temperature range and for operation with the 10 Hz filter enabled unless otherwise noted.

### Input Characteristics

Number of channels.....	8 differential
Maximum signal input range.....	±15 V (±15.75 V with overranging)
Maximum voltage (V+ or V- to earth) .....	250 V <sub>rms</sub> , Measurement Category II
ADC resolution.....	16 bits (refer to table)
Type of ADC .....	Delta-sigma

### Effective Resolution by Input Range and Filter Setting

Nominal Input Range (V)	With Overranging (V)	Effective Resolution <sup>1</sup> (No Filtering) (µV)	Effective Resolution <sup>1</sup> with 10 Hz Filter (µV)
±1	±1.05	100	32
±5	±5.25	160	160
±10	±10.5	320	320
±15	±15.75	480	480
0 to 1	0 to 1.05	100	16
0 to 5	0 to 5.25	100	80
0 to 10	0 to 10.5	160	160
0 to 15	0 to 15.75	240	240

<sup>1</sup>Includes quantization errors and typical RMS noise.

All-channel sample rate	
With 10 Hz filter .....	3.45 kHz <sup>1</sup>
Without filtering .....	10.42 kHz <sup>1</sup>
Input bandwidth (-3 dB) .....	3 kHz minimum
Common-mode rejection at 60 Hz, with 50 Ω source impedance and no filtering	
Channel to channel.....	110 db
Channel to ground .....	110 db
Crosstalk attenuation.....	>100 dB
RMS noise.....	100 µV
Peak-to-peak noise .....	700 µV
Settling time to 1 LSB	
Full-scale step (-15 to 15 V) .....	2.1 ms
1% step.....	1.6 ms
Semaphore acquisition jitter .....	None
Monotonicity .....	Warranted over the operating temperature range
Input resistance .....	1 MΩ
Input capacitance.....	<50 pF
Overvoltage protection .....	±250 V

<sup>1</sup>The all-channel update rate refers to the time the module takes to sample all channels. The overall system update rate is affected by other factors, such as the aggregate module update rate and software loop rate. To calculate the system update rate, visit [ni.com/info](http://ni.com/info) and enter "systemrate."

### Accuracy by Input Range and Temperature Range

Nominal Input Range (V)	Typical Accuracy at 15 to 35 °C (% of Reading; % of Full Scale)	Warranted Accuracy at 15 to 35 °C (% of Reading; % of Full Scale)
±1	±0.037; ±0.006	±0.086; ±0.036
±5	±0.037; ±0.003	±0.066; ±0.009
±10	±0.037; ±0.003	±0.064; ±0.005
±15	±0.037; ±0.003	±0.063; ±0.004
0 to 1	±0.037; ±0.006	±0.111; ±0.036
0 to 5	±0.037; ±0.003	±0.071; ±0.009
0 to 10	±0.037; ±0.003	±0.066; ±0.005
0 to 15	±0.037; ±0.003	±0.065; ±0.004

Gain error drift .....	7.4 ppm/°C
Offset error drift.....	3 µV/°C

### Isolation Voltage

Isolation voltage is verified by a dielectric withstand test.

Channel-to-channel isolation	
Continuous .....	100 V <sub>rms</sub>
Withstand .....	750 V <sub>rms</sub> , 5 s max
Channel-to-backplane isolation	
Continuous .....	250 V <sub>rms</sub>
Withstand .....	2,300 V <sub>rms</sub> , 5 s max
Channel-to-ground isolation	
Continuous .....	250 V <sub>rms</sub>
Withstand .....	2,300 V <sub>rms</sub> , 5 s max

### Physical Characteristics

LED indicators	
Power (green)	
Ready (green)	
Dimensions.....	127.1 by 73.3 by 23.9 mm (5.00 by 2.89 by 0.94 in.)
Weight.....	117 g (4.1 oz)
Warm-up time .....	30 minutes

### Power Requirements

Power from network module .....	1.125 W
---------------------------------	---------

### Environment

Operating temperature .....	-40 to 70 °C
Storage temperature.....	-40 to 85 °C
Relative humidity .....	10 to 90%, noncondensing
Maximum altitude.....	2,000 m; at higher altitudes the isolation voltage ratings must be lowered
Pollution degree .....	2

### Shock and Vibration

Operating vibration, random (IEC 60068-2-64) .....	10 to 500 Hz, 5 g <sub>rms</sub>
Operating vibration, sinusoidal (IEC 60068-2-6) .....	10 to 500 Hz, 5 g
Operating shock (IEC 60068-2-27) .....	50 g, 3 ms half sine, 18 shocks at 6 orientations; 30 g, 11 ms half sine, 18 shocks at 6 orientations

BUY ONLINE at [ni.com](http://ni.com) or CALL 800 813 3693 (U.S.)

## Analog Input Module for Compact FieldPoint

---

### Safety and Compliance

#### Safety

This product is designed to meet the requirements of the following standards of safety for electrical equipment for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA 61010-1

**Note:** For UL and other safety certifications, refer to the product label or visit [ni.com/certification](https://ni.com/certification), search by model number or product line, and click the appropriate link in the Certification column.

#### Electromagnetic Compatibility

This product is designed to meet the requirements of the following standards of EMC for electrical equipment for measurement, control, and laboratory use:

- EN 61326 EMC requirements; Minimum Immunity
- EN 55011 Emissions; Group 1, Class A
- CE, C-Tick, ICES, and FCC Part 15 Emissions; Class A

**Note:** For EMC compliance, operate this device according to product documentation.

#### CE Compliance

This product meets the essential requirements of applicable European Directives, as amended for CE marking, as follows:

- 2006/95/EC; Low-Voltage Directive (safety)
- 2004/108/EC; Electromagnetic Compatibility Directive (EMC)

**Note:** Refer to the Declaration of Conformity (DoC) for this product for any additional regulatory compliance information. To obtain the DoC for this product, visit [ni.com/certification](https://ni.com/certification), search by model number or product line, and click the appropriate link in the Certification column.

#### Waste Electrical and Electronic Equipment (WEEE)

**EU Customers:** At the end of their life cycle, all products must be sent to a WEEE recycling center. For more information about WEEE recycling centers and National Instruments WEEE initiatives, visit [ni.com/environment/weee.htm](https://ni.com/environment/weee.htm).

# NI Services and Support



NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing. Visit [ni.com/services](http://ni.com/services).

## Training and Certification

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit [ni.com/training](http://ni.com/training).

## Professional Services

Our NI Professional Services team is composed of NI applications and systems engineers and a worldwide National Instruments Alliance Partner program of more than 600 independent consultants and

integrators. Services range from start-up assistance to turnkey system integration. Visit [ni.com/alliance](http://ni.com/alliance).



## OEM Support

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit [ni.com/oem](http://ni.com/oem).

## Local Sales and Technical Support

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at [ni.com/support](http://ni.com/support).

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit [ni.com/ssp](http://ni.com/ssp).

## Hardware Services

### NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with [ni.com/pxiadvisor](http://ni.com/pxiadvisor).

### Calibration Services

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit [ni.com/calibration](http://ni.com/calibration).

### Repair and Extended Warranty

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit [ni.com/services](http://ni.com/services).



[ni.com](http://ni.com) • 800 813 3693

National Instruments • [info@ni.com](mailto:info@ni.com)



©2008 National Instruments Corporation. All rights reserved. FieldPoint, National Instruments, National Instruments Alliance Partner, NI, ni.com, NI Developer Suite, and SCXI are trademarks of National Instruments. Other product and company names listed are trademarks or trade names of their respective companies. A National Instruments Alliance Partner is a business entity independent from NI and has no agency, partnership, or joint-venture relationship with NI.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | [www.artisanTG.com](http://www.artisanTG.com)



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)