



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

- High speed—as fast as 15μs
- Current suppression
- Low noise

The Keithley Model 427 amplifier provides high speed combined with low noise and selectable gain, current suppression, and rise time. It is the fastest Keithley picoammeter, with rise times as fast as 15μs at 10⁸V/A gain. Rise times as fast as 1.5ms at the maximum gain of 10¹¹V/A may be selected.

By selecting slower rise times, wider dynamic range and lower noise are obtained: at 10¹¹V/A gain, noise of 3 × 10⁻¹⁵A rms is achieved, with a dynamic range of 13,000:1.

The built-in current suppression with 10-turn resolution permits compensation of large steady-state currents to observe small changes on a more sensitive range. Eight decade ranges of current suppression are provided, from 10⁻¹⁰ to 10⁻³A.

Transient overloads up to 1000V are absorbed without damage, and to prevent unrecognized distortion, the 427



gives visible indication of all overloads.

These features, plus the 427's combination of speed, dynamic range, and sensitivity, make it extremely useful with scanning electron microscopes, sensitive spectrum analyzers, mass

spectrometers, and photomultiplier systems. It is also widely used for measurement of photo effects in biological systems and membrane transport studies, as well as measurement of beam currents and semiconductor properties.

RANGE: 10⁴ to 10¹¹V/A in eight decade ranges. (10⁻¹³A resolution to 10⁻³A full output.)

OUTPUT: ±10V at up to 3mA.

OUTPUT RESISTANCE: <10Ω dc to 30kHz.

OUTPUT ACCURACY: ±2% reading up to 10⁸V/A range, ±4% of reading on the 10¹⁰ and 10¹¹V/A ranges exclusive of noise, drift, and current offset.

RISE TIME (10% to 90%): Adjustable in 1× and 3.3× steps from "Fast Rise Time" listed below to 330ms.

NOISE vs. RISE TIME*:

GAIN V/A	FAST RISE TIME			WIDE DYNAMIC RANGE		
	RISE TIME (10%-90%)	DYNAMIC RANGE	NOISE (A RMS)	DYNAMIC RANGE	NOISE (A RMS)	RISE TIME (10%-90%)
10 ¹¹	1.5 ms	100	4 × 10 ⁻¹³	1.3 × 10 ⁴	3 × 10 ⁻¹⁵	330 ms
10 ¹⁰	400 μs	200	2 × 10 ⁻¹²	2 × 10 ⁴	2 × 10 ⁻¹⁴	100 ms
10 ⁹	200 μs	400	1 × 10 ⁻¹¹	2 × 10 ⁴	2 × 10 ⁻¹³	10 ms
10 ⁸	60 μs	800	5 × 10 ⁻¹¹	2 × 10 ⁴	2 × 10 ⁻¹²	1 ms
10 ⁷	40 μs	2000	2 × 10 ⁻¹⁰	2 × 10 ⁴	2 × 10 ⁻¹¹	100 μs
10 ⁶ -10 ⁴	15 μs	2000	—	2 × 10 ⁴	—	100 μs

*With ≤100pF input shunt capacitance. Noise and/or rise time increase as input shunt capacitance increases (1000pF maximum).

OFFSET CURRENT: <10⁻¹²A at 25°C and up to 70% relative humidity.

STABILITY: Current offset doubles per 10°C above 25°C. Voltage drift is <0.005%/°C and <0.005% per day of full output after 1-hour warmup.

CURRENT SUPPRESSION: 10⁻¹⁰A to 10⁻³A in eight decade ranges with 0.1% resolution (10-turn potentiometer). Stability is ±0.2% of suppressed value per °C, ±0.2% per day.

INPUT VOLTAGE DROP: <400μV for full-scale output on 10⁶ to 10¹¹V/A ranges when properly zeroed.

EFFECTIVE INPUT RESISTANCE: <15Ω on 10⁴ and 10⁵ V/A ranges, increasing to <4MΩ on 10¹¹V/A range.

MAXIMUM INPUT OVERLOAD: **Transient:** 1000V on any range for up to 3 seconds using a Keithley (or other 10mA-limited) high voltage supply. **Continuous:** 500V on 10¹¹ to 10⁷V/A ranges, decreasing to 200 on 10⁶, 70 on 10⁵, and 20V on 10⁴V/A ranges.

OVERLOAD INDICATION: Lamp indicates pre-filter or post-filter overload.

DYNAMIC RESERVE: 10 (20dB).

CONNECTORS: Input (front): BNC. Output (front and rear): BNC.

POWER: 90-125V or 180-250V (switch selected), 50-60Hz, 5W.

DIMENSIONS, WEIGHT: 100mm high × 220mm wide × 315mm deep (4 in. × 8¾ in. × 12½ in.). Net weight 3kg (7 lbs.).

ACCESSORIES AVAILABLE: See Selector Guide on page 49.



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com