

NEOS FOAOM

Two Port Coupled Acousto-Optical Modulator



Limited Availability
Used and in Excellent Condition

Open Web Page

<https://www.artisanng.com/46135-11>

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.



Your **definitive** source
for quality pre-owned
equipment.

Artisan Technology Group

(217) 352-9330 | sales@artisanng.com | artisanng.com

- Critical and expedited services
- In stock / Ready-to-ship

- We buy your excess, underutilized, and idle equipment
- Full-service, independent repair center

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

Agilent Optical Amplifier Test System

E2156A



Agilent Technologies' Customizable Optical Amplifier Test System.

The Agilent E2156A provides a fully integrated test system for optical amplifier (OA) manufacturers. The E2156A provides highly accurate measurements on an open, extensible platform that can be customized to meet user-specific needs.

Just Enough Test

OA manufacturers can configure the E2156A with just the right amount of test capabilities for budget-sensitive applications, and protect their investment by easily upgrading the system to meet new OA test requirements.

Users can work within a familiar software environment to easily change device test sequences, allowing manufacturers to remain cost-competitive

while responding quickly to new technological and market requirements.

Manufacturers can stay cost competitive in the metro market by using our new solution for low-cost test of metro optical amplifiers. This is achieved through low system cost, test throughput optimization and support of low-cost OA technologies, including SOA, EDWA.

Key Benefits

The Agilent E2156A optical amplifier test system offers several benefits:

- reduced cost of test with one system that tests all OA technology devices
- versatility with Agilent's large variety of upgrades
- scalability and investment protection allowing users to purchase a minimum amount of test equipment and upgrade as necessary

- flexibility that lets users easily customize their system within an open software environment

The E2156A uses Agilent's industry leading optical measurement instrumentation. Our standard configuration measures Gain (G), Noise figure (NF) and other derived parameters. The system uses the interpolation with source subtraction (ISS) test method. The time domain extinction (TDE) is available as an option.

Manufacturing and R&D Environments

The Agilent E2156A is a fully automated, integrated turn-key solutions that provide flexibility, accuracy, and repeatability. The Optical Amplifier test system can be used in design verification, production test, or quality assurance and offers unbeatable performance capabilities.



Typical Characteristics

www.agilent.com

System Characteristics

- Wavelength Range (w/C-TLS & L-TLS)	- 1525-1620 nm
- Wavelength Accuracy (measurement)	- 0.025 nm
- Maximum DUT Output Power	- 25 dBm (standard)
- DUT Output Power Measurement Accuracy	- +/- 0.16 dB

Gain and PDG Measurements

- Gain Measurement Accuracy	- +/- 0.12 dB
- Gain Measurement Repeatability	- <0.02 dB typ. Standard deviation
- System Residual PDG (PDG accuracy)	- +/- 0.1 dB typ.
	- +/- 0.02 dB typ. enhanced (opt)

Noise Figure Measurements

- NF Accuracy (ISS)	- +/- 0.3 dB
- NF Accuracy (TDE)	- +/- 0.19 dB
- NF Measurement Repeatability	- <0.02 dB typ. Standard deviation

Source Characteristics

- Maximum WDM DUT Input Power (ISS)	- +11.8 dBm typ. 12 channel WDM
	- +14.8 dBm typ. 20 channel WDM
- DUT Input Power Set Accuracy	- +/- 0.1 dB
- DUT Input Power Set Repeatability	- <0.02 dB typ. Standard deviation
- Minimum WDM Source Channel Spacing	- 100 GHz (ISS), 50 GHz (TDE)
- Loss from Source Input to DUT Input	- 6.5 dB nom ¹

List of Measurements

- Gain, Gain Flatness	- Total Output Power
- Noise Figure	- ASE Power
- PDG (optional)	- Signal Input Power
- Transients (optional)	- Signal Output Power

Environmental Conditions

- Operating Temperature	- 10 to 35 C ⁰
- Storage Temperature	- -40 to 70 C ⁰
- Humidity	- 80% RH

Specifications exclude DUT connector effects

1. Base system without Polarization Controller and Multi-DUT switch

By internet, phone, or fax, get assistance with all of your test & measurement needs.

Online assistance:

www.agilent.com/find/assist

Phone or Fax

United States

(tel) 800 452 4844

Canada

(tel) 877 894 4414

(fax) 905 282 6495

China

(tel) 800 810 0189

(fax) 800 820 2816

Europe

(tel) (31 20) 547 2323

(fax) (31 20) 547 2390

Japan

(tel) 426 56 7832

(fax) 426 56 7840

Korea

(tel) (82 2) 2004 5004

(fax) (82 2) 2004 5115

Latin America

(tel) (305) 269 7500

(fax) (305) 269 7599

Taiwan

(tel) 0800 047 866

(fax) 0800 286 331

Other Asia Pacific Countries

(tel) (65) 6375 8100

(fax) (65) 6836 0252

Email: tm_asia@agilent.com

Product specifications and descriptions in this document are subject to change without notice.

Microsoft, Windows, and Windows NT are U.S. registered trademarks of Microsoft Corp.

Agilent Email Updates

www.agilent.com/find/email_updates

Get the latest information on the products and applications you select.

© Agilent Technologies, Inc. 2002

Printed in USA, September 15, 2002

Part number #5988-7760EN



Agilent Technologies

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisanng.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisanng.com | artisanng.com

