

Keithley 616
Autoranging Digital Electrometer



© Artisan Technology Group

**Limited Availability
Used and in Excellent Condition**

Open Web Page

<https://www.artisanng.com/94014-1>

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.



Your **definitive** source
for quality pre-owned
equipment.

Artisan Technology Group

(217) 352-9330 | sales@artisanng.com | artisanng.com

- Critical and expedited services
- In stock / Ready-to-ship

- We buy your excess, underutilized, and idle equipment
- Full-service, independent repair center

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

616/Digital Electrometer

Autoranging

- Measures V, I, R and Q, and is a current source
- $2 \times 10^{14}\Omega$ input resistance
- $2 \times 10^{-15}\text{A}$ current noise



The 616 is an autoranging digital electrometer with sensitivity to $10\mu\text{V}/\text{digit}$ and 0.2% voltage accuracy. The easy-to-read $3\frac{1}{2}$ -digit LED display includes the convenience of automatic polarity and decimal point. The 616 is essentially a digital multimeter optimized for measurements from high source impedance.

The input amplifier provides high input resistance ($2 \times 10^{14}\Omega$), low offset current (less than $5 \times 10^{-15}\text{A}$) and low noise. The double-shielded input section permits floating operations up to $\pm 1000\text{V}$ above chassis. The Model 616's box-within-a-box construction keeps unshielded capacitance from input HI to chassis ground below 0.1pF , so that CMRR is greater than 140dB with up to $10^{11}\Omega$ source resistance.

When combined with the optional Model 6162 Isolated Output/Control, the 616 can be used in measurement systems with control of sensitivity as well as digital output data.

Voltage measurements

As a high input resistance voltmeter, the 616 provides fully automatic ranges from $\pm 10\text{mV}$ ($10\mu\text{V}$ sensitivity) to $\pm 200\text{V}$ DC. Voltage sensitivity can be selected over a range of five decades - automatically, manually or remotely with the optional Model 6162 Isolated Output/Control. With an input resistance greater than $2 \times 10^{14}\Omega$, the 616 accurately measures over a wide range of source resistances with negligible loading error. The 616 also provides quick recovery from overloads. Voltage stability is better than $50\mu\text{V}/^\circ\text{C}$.

Current measurements

As a picoammeter, the 616 has ranges from 10^{-13}A (10^{-16}A digital sensitivity) to 10^{-1}A with 100% overranging. Measurements can be made in either the shunt (normal) mode or the feedback (fast) mode, thus permitting an optimum speed/noise/input voltage tradeoff.

Resistance measurements

As an ohmmeter, the 616 employs a two terminal, constant current method of resistance measurement to read $10^3\Omega$ to $10^{14}\Omega$ full range with 100% overranging. The constant current source may also be used to test semiconductors for breakdown voltage and other I-V characteristics.

Charge measurements

As a coulombmeter, the 616 measures from 10^{-5}C to 10^{-12}C full range with 100% overranging. The instrument can be used for current integration with voltages from $10\mu\text{V}$ to 200V developed on the integrating capacitor.

Optional output/control

With the Model 6162 Isolated Output/Control, remote control lines allow selection of measurement sensitivity over five decades, by means of controlling the voltage gain of the amplifier. Individual strobe lines permit data transfer using a minimum of four control lines (bit-parallel, character serial output). The 6162 outputs are fully isolated, providing complete data, timing outputs and multiple strobe lines. The open-collector BCD outputs are compatible with most TTL and DTL logic.

AS AN AUTORANGING VOLTMETER

RANGE: $\pm 10\mu\text{V}$ per digit (10mV full range) to $\pm 100\text{V}$ full range in five decade ranges. 100% overranging to 1999 on all ranges.

ACCURACY (18°C to 28°C): $\pm(0.2\%$ of reading + 0.1% of range).

READING TIME: Less than 4 seconds to within 0.1% of final reading, except where limited by source characteristics.

ZERO DRIFT: Less than $(50\mu\text{V} + 0.01\%$ of range) per °C, and less than 100 μV per 24-hour period after two hours warmup.

NOISE: $\pm 10\mu\text{V}$ with input shorted.

INPUT IMPEDANCE: Greater than $2 \times 10^{11}\Omega$ shunted by 20pF. Input resistance may be selected in decade steps from 10 to $10^{11}\Omega$.

NORMAL MODE REJECTION RATIO

RANGE	NMRR	MAXIMUM AC
10mV	94dB	2V p-p
100mV	80dB	2V p-p
1 V	80dB	20V p-p
10 V	60dB	20V p-p
100 V	60dB	200V p-p

For voltage of line frequency and at least 10% of full range DC reading. Maximum total input 200V peak AC & DC.

COMMON MODE REJECTION RATIO: Greater than 140dB at line frequency with 300V peak-to-peak from LO to ground, up to $10^{11}\Omega$ source resistance, and at least 10% of full range DC reading.

AS AN AMMETER

RANGE: $\pm 10^{-10}\text{A}$ per digit (10^{-12}A full range) to $\pm 0.1\text{A}$ full range in 13 decade ranges. 100% overranging to 1999 on all ranges.

ACCURACY (18°C to 28°C):

RANGE SWITCH SETTING	ACCURACY
10^{-1} to 10^{-7}A	$\pm(0.5\%$ of reading + 0.1% of range)
10^{-8}A	$\pm(2\%$ of reading + 0.1% of range)
10^{-9} to 10^{-11}A	$\pm(5\%$ of reading + 0.1% of range)

NOISE: $2 \times 10^{-15}\text{A}$ peak-to-peak on the most sensitive range, exclusive of alpha particle disturbance.

OFFSET CURRENT: Less than $5 \times 10^{-15}\text{A}$.

COMMON MODE REJECTION: 300V peak-to-peak at line frequency from circuit LO to chassis ground on any range and with at least 10% of full range DC reading will not degrade accuracy more than 0.3% of range. (Equivalent to 140dB CMRR.)

AS AN OHMMETER

RANGE: 1Ω per digit (1000 Ω full range) to $10^{14}\Omega$ full range in 12 decade ranges. 100% overranging to 1999 on all ranges.

ACCURACY (18°C to 28°C):

RANGE SWITCH SETTING	ACCURACY
10^5 to 10^7	$\pm(0.5\%$ of reading + 0.1% of range)
$10^8\Omega$	$\pm(2\%$ of reading + 0.1% of range)
10^9 to $10^{14}\Omega$	$\pm(5\%$ of reading + 0.1% of range)

METHOD: Two-terminal constant-current. Current equals reciprocal of Ohms range.

AS A COULOMB METER

RANGE: $\pm 10^{-15}\text{C}$ per digit (10^{-12}C full range) to $\pm 10^{-5}\text{C}$ full range in 8 decade ranges. 100% overranging to 1999 on all ranges.

ACCURACY (18°C to 28°C): $\pm(5\%$ of reading + 0.1% of range).

AS A CONSTANT CURRENT SOURCE

RANGE: 8 currents in decade steps from 10^{-9} to 10^{-12}A using Ohms ranges. HI terminal is positive.

COMPLIANCE: Up to 200V.

ACCURACY (18°C to 28°C): $\pm 0.5\%$ from 10^{-5} to 10^{-7}A . $\pm 2\%$ at 10^{-8}A . $\pm 5\%$ from 10^{-9} to 10^{-12}A .

LOAD REGULATION: Better than 0.1% for loads up to $10^{11}\Omega$.

GENERAL

DISPLAY: 3 digits plus 1 overrange digit; decimal position, polarity and overload indication; 5 readings per second. Depending on sensitivity setting, 3 least-significant digits blink or blank when overload condition exists.

POLARITY SELECTION: Automatic.

SENSITIVITY SELECTION: Automatic: Voltage sensitivity selection is fully automatic. Sensitivity selection is automatic two decades above and below range switch setting for resistance, charge and most current measurements. Manual: Front panel switch. Remote: Programmable with the Model 6162 Output/Control (optional).

ISOLATION: Circuit LO to chassis ground greater than $10^9\Omega$ shunted by 500pF (decreasing to $10^8\Omega$ at 30°C and 70% relative humidity). Circuit LO may be floated up to $\pm 1000\text{V}$ with respect to chassis ground.

ANALOG OUTPUTS: Unity Gain: For DC inputs, output is equal to input within 20ppm for output currents of 1mA or less. In the fast mode, output polarity is opposite input polarity. 1V: $\pm 1\text{V}$ at up to 1mA with respect to circuit LO for full range input; 100% overrange capability. In the normal mode, the output polarity is opposite input polarity.

OPERATING ENVIRONMENT: 18°C to 28°C, 0% to 70% relative humidity. 10°C to 50°C with derated specifications. Storage: 0°C to 70°C.

CONNECTORS: Input: Teflon-insulated triaxial. Analog Outputs: Unity gain, 1V, chassis, LO and guard; binding posts. BCD Output: Internal connectors for interfacing the Model 6162 Isolated Output/Control.

DIMENSIONS, WEIGHT: Style M, 90mm (3½") half-rack, overall bench size 100mm high \times 220mm wide \times 400mm deep (4" \times 8¾" \times 15¾"). Net weight, 4.8kg (11 lbs.).

POWER: Line operation: 90-125 or 180-250V (switch selected), 50-60 Hz, 9W.

ACCESSORY SUPPLIED: Model 6011 Input Cable: 1m (3 ft.) triaxial cable with triaxial connector and 3 alligator clips.

SPECIFICATIONS/6162

DIGITAL OUTPUT: BCD (8421) open collector logic represents each of 3 digits (0 = "0000"), overrange digit, uprange ("0"), polarity (+ = "1"), decimal position (5 lines), exponent (5 line, BCD), exponent polarity (+ = "1"), downrange ("0"), zero check ("1"), and function (2 bit code).

ACCURACY: ± 1 digit with respect to 616 display.

FLAG (FLAG): Logic "1" ("0") from 50ms to 7 seconds depending on Print Rate setting. No change in digital output is made during this interval.

OUTPUT LOGIC LEVELS: Output Logic "1" \equiv open collector to output LO. Output Logic "0" \equiv closure to output LO. Output Device MC858P or equivalent (greater than 6V breakdown, 0.5V at +35mA sink).

REMOTE CONTROLS:

Zero Check: Logic "0" actuates 616 Zero Check.

Sensitivity: 4-line code for remote sensitivity setting of 616.

Display Hold: Logic "0" retains last reading on display (except polarity).

Output Hold: Logic "0" retains data from last reading.

Strobe: 8 lines for serializing in multiples of 4 bits. Logic "1" inhibits controlled output lines.

CONTROL LOGIC LEVELS: Logic "1" \equiv either an open circuit or a voltage between +2 and +12V referenced to output LO. Logic "0" \equiv closure to output LO within 0.5V while sinking 2.5mA.

PRINT RATE: Variable via front panel control from ½ second per reading to 7 seconds per reading in ½ second increments.

ISOLATION: Input LO to output LO: sufficient to maintain 616 isolation specifications except adds 200pF capacitance. Output LO to ground: greater than $10^9\Omega$ shunted by 0.1 μF . Output LO may be floated up to $\pm 100\text{V}$ with respect to ground.

CONNECTORS: Input: Attached cable connects to 616. Output: 50-pin AMP type 205211-1. Mating connector supplied.

ENVIRONMENT: Operating: 10°C to 50°C, 0% to 70% relative humidity. Storage: 0°C to 70°C.

POWER: 90-125 or 180-250V (switch selected), 50-60Hz, 9W.

DIMENSIONS, WEIGHT: Style M, 90mm (3½") half-rack, overall bench size 100mm high \times 220mm wide \times 400mm deep (4" \times 8¾" \times 15¾"). Net weight, 3.2kg (7 lbs.).

ACCESSORY SUPPLIED: Model 1007 Dual Rack Mounting Kit.

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisanng.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisanng.com | artisanng.com

