Multiple Output Linear DC Power Supply



\$3595.00

In Stock
Qty Available: 2
Used and in Excellent Condition

Open Web Page

https://www.artisantg.com/72541-2

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.

- Critical and expedited services
- In stock / Ready-to-ship

- We buy your excess, underutilized, and idle equipment
- · Full-service, independent repair center



Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group

(217) 352-9330 | sales@artisantg.com | artisantg.com

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.





6625A, 6626A, 6628A, 6629A

Precision Multiple-Output 25 W-50 W GPIB

Up to four fully isolated power supplies in a 3 U package Fast, low-noise outputs

Dual-range, precision low current measurement

Built-in measurements and advanced programmable features

Protection features to ensure DUT safety

Two or four isolated outputs
are integrated into one package,
conserving rack space and GPIB
addresses. Dual ranges allow for
more current at lower voltage levels
The outputs can be connected in
parallel or series to further increase
the flexibility that these products
offer the system designer. Program-
ming is done using industry
standard SCPI commands and
test system integration can be
further simplified be using the
VXI <i>Plug&Play</i> drivers. These
power supplies help reduce test
time with fast up and down pro-
gramming, which is enhanced by
the active down-programmer
which can sink the full rated
current.

These power supplies are very useful on the R&D bench. The accuracy of both the programming and the measurement systems allow precise control and monitoring of prototype bias power. The extensive protection features protect valuable prototypes, including very fast CV/CC crossover. The power supply can be controlled from either the front panel keypad or, for automated testing, from the GPIB.

Specifications (at 0° to 55°C unless otherwise specified)		25 W output	50 W output
Output power	Low-range volts, amps	0 to 7 V, 0 to 15 mA	0 to 16 V, 0 to 200 mA
	High range volts, amps	0 to 50 V, 0 to 500 mA	0 to 50 V, 0 to 1 A or 0 to 16 V, 0 to 2 A
Output combinations			
for each model	GG2EA (2) Draginian	1	1
(total number of outputs)	6625A (2) Precision	2	2
	6626A (4) Precision	_	2
	6628A (2) Precision	_	4
<u> </u>	6629A (4) Precision		•
Programming accuracy (at 25°C ±5°C)	Voltage	1.5 mV + 0.016% (low) 10 mV + 0.016% (high)	3 mV + 0.016% (low) 10 mV + 0.016% (high)
	Current	15 μA + 0.04% (low) 100 μA + 0.04% (high)	185 μA + 0.04% (low) 500 μA + 0.04% (high)
Readback accuracy (at 25°C ±5°C)	Voltage	0.016% + 2 mV (low) 0.016% + 10 mV (high)	0.016% + 3.5 mV (low) 0.016% + 10 mV (high)
	+/-Current	0.03% + 15 μA (low) 0.03% + 130 μA (high)	0.04% + 250 μA (low) 0.04% + 550 μA (high)
Ripple and noise	Constant voltage rms	500 μV	500 μV
(peak-to-peak, 20 Hz to 20 MHz; rms, 20 Hz to 10 MHz)	peak-to-peak	3 mV	3 mV
	Constant current rms	0.1 mA	0.1 mA
Load regulation	Voltage	0.5 mV	0.5 mV
	Current	0.005 mA	0.01 mA
Load cross regulation	Voltage	0.25 mV	0.25 mV
	Current	0.005 mA	0.01 mA
Line regulation	Voltage	0.5 mV	0.5 mV
	Current	0.005 mA	0.01 mA
Transient response time change within specfications		Less than 75 µs for the output to recover to within 75 mV of nominal value following a load	
Supplemental Characteristics		(Non-warranted characteristics determined by design and useful in applying the product)	
		25-watt output 50-watt output	
Average programming resolution	Voltage	460 μV (low)	1 mV (low)
		3.2 mV (high)	3.2 mV (high)
	Current	1 μA (low)	13 μA (low)
	23.70110	33 μA (high)	131 μA (high)
	OVP	230 mV	230 mV
Output programming response time	011	6 ms	6 ms
(time to settle within 0.1% of full sc			o

More detailed specifications at www.agilent.com/find/6620

Precision Multiple-Output: 25 W-50 W GPIB (Continued)

Application Notes:

10 Practical Tips You Need to Know About Your Power Products 5965-8239E

10 Hints for Using Your Power Supply to Decrease Test Time 5968-6359E

Understanding Linear Power Supply Operation (AN1554) 5989-2291EN

Modern Connectivity -Using USB and LAN I/O Converters (AN 1475-1) 5989-0123EN

Supplemental Characteristics for all model numbers

DC Floating Voltage: All outputs can be floated up to $\pm 240~\rm Vdc$ from chassis ground

Remote Sensing: Up to 10 V drop per load lead. The drop in the load leads is subtracted from the voltage available for the load.

Command Processing Time: 7 ms typical with front-panel display disabled

Input Power: 550 W max., 720 VA max.

GPIB Interface Capabilities: SH1, AH1, T6, L4, SR1, RL1, PP1, DC1, DT0, C0, E1.

Software Driver: VXIPlug&Play

Regulatory Compliance: Listed to UL 1244; conforms to IEC 61010-1.

Size: 425.5 mm W x 132.6 mm H x 497.8 mm D (16.75 in x 5.22 in x 19.6 in)

Weight: 6626A, 6629A: Net, 17.4 kg (38 lb); shipping, 22.7 kg (50 lb) 6625A, 6628A: Net, 15.5 kg (34 lb); shipping, 20.8 kg (46 lb)

Warranty Period: One year

Ordering Information

Opt 100 87 to $106 \, \mathrm{Vac}$, $47 \, \mathrm{to} \, 66 \, \mathrm{Hz}$ Input, $6.3 \, \mathrm{A}$ (Japan only)

 $\textbf{0pt 120} \ \ 104 \ to \ 127 \ Vac, \ 47 \ to \ 63 \ Hz$

 $\textbf{Opt\,220}\ \ 191\ to\ 233\ Vac,\ 47\ to\ 66\ Hz,\ 3.0\ A$

 $\textbf{0pt 240}\ 209\ to\ 250\ Vac,\ 47\ to\ 66\ Hz,\ 3.0\ A$

 $\textbf{Opt 750} \ \operatorname{Relay Control} \ and \ \operatorname{DFI/RI}$

Opt \$50 Similar to option 750, however the remote inhibit does not latch

- * **Opt 908** Rack-mount Kit (p/n 5062-3977)
- * **Opt 909** Rack-mount Kit w/Handles (p/n 5063-9221)

Opt OL1 Full documentation on CD-ROM, and printed standard documentation package

Opt 0L2 Extra copy of standard printed documentation package **Opt 0B0** Full documentation on CD-ROM only

Opt OB3 Service Manual

* Support rails required

Accessories

p/n 1494-0059 Rack Slide Kit E3663AC Support rails for Agilent rack cabinets

Agilent Models: 6625A, 6626A, 6628A, 6629A


Terminal Strip Detail


Output 2 & 3



Output 1 & 4

+S +V -V +S +0V -0V





More detailed specifications at www.agilent.com/find/6620

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisantg.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today? (217) 352-9330 | sales@artisantg.com | artisantg.com

