Simons 6ES7 307-1KA01-0AA0 SITOP Simatic S7-300 Power Supply



Limited Availability
Used and in Excellent Condition

Open Web Page

https://www.artisantg.com/97862-2

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.

- Critical and expedited services
- In stock / Ready-to-ship

- · We buy your excess, underutilized, and idle equipment
- · Full-service, independent repair center

ARTISAN'
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group

(217) 352-9330 | sales@artisantg.com | artisantg.com

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

Data sheet

SIMATIC S7-300, Digital output SM 322, Isolated 16 DO, relay contacts, 1x 20-pole



Figure similar

Supply voltage	
Load voltage L+	
Rated value (DC)	120 V
Load voltage L1	
Rated value (AC)	230 V
Input current	
from supply voltage L+, max.	250 mA
from backplane bus 5 V DC, max.	100 mA
Power loss	
Power loss, typ.	4.5 W
Digital outputs	
Number of digital outputs	16; Relays
Switching capacity of the outputs	
• on lamp load, max.	50 W; 230 V AC
Output current	
	2 A

• for signal "1" minimum load current	10 mA
Switching frequency	
• with resistive load, max.	1 Hz
• with inductive load, max.	0.5 Hz
• on lamp load, max.	1 Hz
• mechanical, max.	10 Hz
Total current of the outputs (per group)	
horizontal installation	
— up to 60 °C, max.	8 A
vertical installation	
— up to 40 °C, max.	8 A
Relay outputs	
Rated supply voltage of relay coil L+ (DC)	24 V
 Number of operating cycles, max. 	100 000; 50 000 (24 V DC, at 2 A); 700 000 (120 V AC, at 2 A); 100 000 (230 V AC, at 2 A)
Switching capacity of contacts	
— with inductive load, max.	2 A; 2 A (230 V AC), 2 A (24 V DC)
— with resistive load, max.	2 A; 2 A (230 V AC), 2 A (24 V DC)
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Interrupts/diagnostics/status information	
Interrupts/diagnostics/status information Diagnostic functions	No
Interrupts/diagnostics/status information Diagnostic functions Alarms	
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm	No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages	No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break	No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit	No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown	No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage	No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED	No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED • Rated load voltage PWR (green)	No No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms Diagnostic alarm Diagnostic messages Wire-break Short-circuit Fuse blown missing load voltage Diagnostics indication LED Rated load voltage PWR (green) Fuse OK FSG (green)	No No No No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED • Rated load voltage PWR (green)	No No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED • Rated load voltage PWR (green) • Fuse OK FSG (green) • Status indicator digital output (green)	No No No No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms Diagnostic alarm Diagnostic messages Wire-break Short-circuit Fuse blown missing load voltage Diagnostics indication LED Rated load voltage PWR (green) Fuse OK FSG (green) Status indicator digital output (green) Potential separation Potential separation digital outputs	No No No No No No Vo Yes
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED • Rated load voltage PWR (green) • Fuse OK FSG (green) • Status indicator digital output (green)	No No No No No No No No
Interrupts/diagnostics/status information Diagnostic functions Alarms Diagnostic alarm Diagnostic messages Wire-break Short-circuit Fuse blown missing load voltage Diagnostics indication LED Rated load voltage PWR (green) Fuse OK FSG (green) Status indicator digital output (green) Potential separation Potential separation digital outputs	No No No No No No Vo Yes
Interrupts/diagnostics/status information Diagnostic functions Alarms Diagnostic alarm Diagnostic messages Wire-break Short-circuit Fuse blown missing load voltage Diagnostics indication LED Rated load voltage PWR (green) Fuse OK FSG (green) Status indicator digital output (green) Potential separation Potential separation digital outputs between the channels	No No No No No No No Yes
Interrupts/diagnostics/status information Diagnostic functions Alarms • Diagnostic alarm Diagnostic messages • Wire-break • Short-circuit • Fuse blown • missing load voltage Diagnostics indication LED • Rated load voltage PWR (green) • Fuse OK FSG (green) • Status indicator digital output (green) Potential separation Potential separation digital outputs • between the channels • between the channels, in groups of	No No No No No No Yes 8

Connection method		
required front connector	20-pin	
Dimensions		
Width	40 mm	
Height	125 mm	
Depth	120 mm	
Weights		
Weight, approx.	250 g	
last modified:	07/27/2018	

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisantg.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today? (217) 352-9330 | sales@artisantg.com | artisantg.com

