

Sorensen XDC 60-100

6000 Watt Series Digital DC Power Supply



In Stock

Used and in Excellent Condition

Open Web Page

<https://www.artisanng.com/65096-28>

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.



Your **definitive** source
for quality pre-owned
equipment.

Artisan Technology Group

(217) 352-9330 | sales@artisanng.com | artisanng.com

- Critical and expedited services
- In stock / Ready-to-ship

- We buy your excess, underutilized, and idle equipment
- Full-service, independent repair center

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

Smart choice for power

xantrex

[Home](#)[Products](#)[Support](#)[Buy](#)[Company](#)[Contacts](#)[\[Enlarge Image\]](#)[Product Info](#) | [Specifications](#) | [Compare](#)**Specifications Available**

- ▶ 6 kW 10-600
- ▶ 6 kW 20-300
- ▶ 6 kW 30-200
- ▶ 6 kW 40-150
- ▶ 6 kW 60-100
- ▶ 6 kW 80-75
- ▶ 6 kW 100-60
- ▶ 6 kW 150-40
- ▶ 6 kW 300-20
- ▶ 6 kW 600-10
- ▶ 12 kW 10-1200
- ▶ 12 kW 20-600
- ▶ 12 kW 30-400
- ▶ 12 kW 40-300
- ▶ 12 kW 60-200
- ▶ 12 kW 80-150
- ▶ 12 kW 100-120
- ▶ 12 kW 150-80
- ▶ 12 kW 300-40
- ▶ 12 kW 600-20

6 kW 10-600

Electrical Specifications	
Output ratings:	
Output Voltage ¹	0-10 V
Output Current ²	0-600 A
Output Power	6000 W
Line Regulation: ³	
Voltage (0.01% of Vmax)	1 mV
Current (0.05% of Imax)	150 mA
Load regulation: ⁴	
Voltage (0.05% of Vmax + 5 mV)	10 mV
Current (0.1% of Imax + 20 mA)	150 mA
Meter accuracy:	
Voltage (0.15% of Vmax)	15 mV
Current (0.5% of Imax)	3 A
Output noise (0-20 MHz):	
Voltage (p-p)	85 mV
Output ripple (rms):	
Voltage	10 mV
Current ⁵	500 mA
Drift (30 minutes): ⁶	
Voltage (0.04% of Vmax)	4 mV
Current (0.6% of Imax)	3600 mA
Drift (8 hours): ⁷	
Voltage (0.02% of Vmax)	2 mV
Current (0.04% of Imax)	240 mA
Temperature coefficient: ⁸	
Voltage (0.04% of Vmax/° C)	4 mV
Current (0.06% of Imax/° C)	360 mA
OVP adjustment range: (0 to 103% of Vmax)	0-10.3 V
Efficiency: ⁹	85%
 1. Minimum output voltage is <0.3% of rated voltage at zero output setting. 2. Minimum output current is <0.2% of rated current at zero output setting when measured with rated load resistance. 3. For input voltage variation over the AC input voltage range, with constant rated load. 4. For 0-100% load variation, with constant nominal line voltage. 5. Current mode noise is measured from 10% to 100% of rated output voltage, full current, unit in CC mode. 6. Maximum drift over 30 minutes with constant line, load, and temperature, after power on. 7. Maximum drift over 8 hours with constant line, load and temperature, after 30 minutes warm-up. 8. Change in output per ° C change in ambient temperature, with constant line and load. 9. Typical efficiency at nominal input voltage and full output power.	
General Specifications	
Operational AC input voltage	3-phase 190-242 VAC (47-63 Hz) (standard); 3-phase 342-500 VAC, 47-63 Hz, 3 wire and safety ground, (optional)
Input Power Factor Correction	0.95 (nominal 208 Vrms), 0.9 (nominal 400 Vrms HV input option)
Remote analog programming	Voltage and current programming inputs 0-5 V, 0-10 V (default) voltage sources. Galvanically isolated from supply output.
Remote analog monitoring	Voltage and current monitor outputs 0-5 V, 0-10 V (default) ranges for 0-100% of output. Galvanically isolated from supply output.
Dimensions (H x W x D)	5.2 x 19.0 x 21.0" (133.5 x 483 x 533 mm)
Weight	Approximately 75 lb (34 kg)
Warranty	Five years
Regulatory Approvals	
CE-marked units meet: EN61010-1, EN61000-6-2 and EN61000-6-4; CSA C/US certified to UL3111-1 and CSA C22.2 No 1010.1 Meets USA EMC standard: FCC, part 15B, class A; Meets Canadian EMC standard:	

[Web Site Terms & Conditions](#)

©2000 - 2009 Xantrex Technology Inc.

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisanng.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisanng.com | artisanng.com

