

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction


All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Curtiss-Wright / ACRA Control KAD/ADC/109/S1/00* at our website: *Click HERE*

KAD/ADC/109/S1

Full-bridge ADC (voltage excitation, programmable analog gain, 6kHz b/w) – 8ch at 24ksps

Description



The KAD/ADC/109/S1 provides independent excitation for up to eight channels. Each channel has a separate programmable amplifier, programmable filter and A/D converter.

At the heart of the KAD/ADC/109/S1 is a hard-wired state-machine that over-samples all channels at a rate between 96ksps and 192ksps and digitally filters any noise above the user programmable cutoff frequency. This is achieved using cascaded, half-band, decimate by two, fifteen tap, finite-impulse-response (FIR) filters with 32-bit coefficients followed by an 8th order Butterworth IIR filter with a default cutoff point set a quarter of the sampling frequency.


All signals are sampled simultaneously. Thus, when several channels are sampled at different sampling rates, at the start of an acquisition cycle all channels will be aligned.

Features

- Eight full or ½-bridge, potentiometer or differential ended (D/E) input channels
- 16-bit simultaneous sampling on all channels
- High accuracy
- Programmable excitation, balance current and range per channel
- 8th order Butterworth filter with programmable cutoff frequency per channel
- Short to ground on any channel does not affect others
- Bipolar excitation and balancing before instrumentation amplifier
- Up to 24,000 samples per second per channel
- Up to 6kHz bandwidth
- Enhanced mechanical strength between motherboard and daughterboard
- High impedance per channel when powered off

Applications

- Bridge sensors
- Differential voltage measurement
- Strain gage measurement



First of eight channels on the KAD/ADC/109/S1

Contact Us

USA (626) 851-3100
United Kingdom +44-1202-481-771
Ireland +353-1-295-1264

Contact Support

Penny + Giles Support
Acra Support
City of Industry Support

Applications

Air Data Computing
Cockpit Voice Recording
Data Concentration
Fire Protection
Flight Test
Health and Usage Monitoring
Ice Protection & Detection
Space Vehicle Data Acquisition

Resources

Avionics Tech Notes
Brochures
Conference Papers
Flight Test Tech Notes
Manuals
Technical Publications
User Stories
Videos

Engage With Us

Login
Our Blog
Flight Test Community
Tech Horizons Events

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP