

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *OMRON / Delta Tau PMAC PCI-Lite* at our website: ***Click HERE***

Turbo PMAC-Lite PCI, 4-axis with ±10V Servo Outputs PCI Board

Recommended for applications with three or four ±10V channel requirements in either a PCI-PC based or stand alone environment. The term "*Lite*" stands for the limitation of only one DSPGATE Gate-Array IC on board. In comparison with the non-Turbo version, this board provides better velocity and acceleration control algorithms (lookahead) and an overall improved firmware. The number of channels can always be expanded, from 4 to 12, through the use of an ACC-24P.



Part Number

400-603657-TRx

Number of Channels

The Turbo PMAC-Lite PCI can have only one on-board DSPGATE that provides four channels axis interface circuitry, each including:

- 16-bit ±10V differential analog output
- Differential/single-ended encoder input with 'A', 'B' quadrature channels and 'C' index channel
- Four input flags, two output flags
- Interface to external 16-bit serial ADC

CPU and Memory

The Turbo PMAC-Lite PCI is provided with an 80 MHz DSP56303 CPU (120 MHz PMAC equivalent) and flash memory. Any variable change in a flash type memory needs to be saved manually in Turbo PMAC for it to be retained on a power-up\reset cycle. Therefore, if machine parameters like parts counters or state variables are required, the Option-16A battery-backed parameter RAM is suggested.

- Option-5C0: this is the standard CPU and memory configuration. It is provided automatically if no Option-5xx is specified. It provides an 80 MHz DSP56303 CPU (120 MHz PMAC equivalent), 128k x24 of compiled/assembled program memory, 128k x 24 of user data memory, and a 1M x 8 flash memory.
- Option-5C3: it provides an 80 MHz DSP56303 CPU (120 MHz PMAC equivalent) with 8k x 24 of internal memory, an expanded 512k x 24 of compiled/assembled program memory, an expanded 512k x 24 of user data memory, and a 4M x 8 flash memory.
- Option-5D0: it provides a 100 MHz DSP56309 CPU (150 MHz PMAC equivalent) with 34k x 24 of internal memory, 128k x 24 of compiled/assembled program memory, 128k x 24 of user data memory; and a 1M x 8 flash memory.
- Option-5D3: it provides a 100 MHz DSP56309 CPU (150 MHz PMAC equivalent) with 34k x 24 of internal memory, an expanded 512k x 24 of compiled/assembled program memory, an expanded 512k x 24 of user data memory, and a 4M x 8 flash memory.
- Option-5E0: it provides a 160 MHz DSP56311 CPU (240 MHz PMAC equivalent) with 128k x 24 of internal memory, 128k x 24 of compiled/assembled program memory, 128k x 24 of user data memory; and a 1M x 8 flash memory.
- Option-5E3: it provides a 160 MHz DSP56311 CPU (240 MHz PMAC equivalent) with 128k x 24 of internal memory, 512k x 24 of compiled/assembled program memory, 512k x 24 of user data memory; and a 4M x 8 flash memory.
- Option-16A: 32Kx24 SRAM battery-backed parameter memory





Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Communications

The Turbo PMAC-Lite PCI can communicate either through the PCI bus or through the RS-422 serial interface using the optional ACC-3D flat cable. All communication ports in a Turbo PMAC are independent of each other allowing multiple devices communicating with it at any given time.

- Option-2: The 8Kx16 Dual Ported RAM provides a method of sharing memory between PMAC and the host computer for very fast interchange of data. The Option-2 is installed on-board of the PMAC.
- Option-9T: Auxiliary RS-232 serial port. This option is installed in the CPU piggyback board and connects to the computer through the optional ACC-3L flat cable.

Firmware Version

PMAC is provided with the latest firmware revision with the regular servo algorithm.

- Option-10: Through this option an older than the latest firmware released version could be ordered on-board. When possible, use the same firmware revision for similar machines, and this is important in cases where the new PMAC is a replacement in an already existing machine or a new machine using same existing programs is developed.

Miscellaneous

The following ports are provided standard in any PMAC:

- Display port for the connection to a vacuum fluorescent or liquid crystal display
- JOPTO Port: this port provides eight general-purpose digital inputs and eight general-purpose digital outputs at 5 to 24 VDC levels and a maximum of 100 mA per output. This 34-pin connector was designed for easy interface to OPTO-22 or equivalent optically isolated I/O modules when different voltage levels or opto-isolation to the PMAC board is necessary.
- Multiplexer Port providing eight input lines and eight output lines at TTL levels. When using the PMAC ACC-34x type boards these lines allow multiplexing up to 1024 I/O lines on the port.
- Control panel port with dedicated control inputs, dedicated indicator outputs, a quadrature encoder input, and an analog input (requires PMAC OPT-15).

Most options to the PMAC board are only possible to install in factory whereas most accessories for PMAC can be ordered and installed at a later stage. Therefore, it is important to order all the necessary options at the time when PMAC is ordered.

- Option-7: Plate mounting for standalone applications. PMAC is mounted in an aluminum plate allowing its installation as a stand-alone controller.
- Option-8A: The standard clock crystal in PMAC has ±100 ppm accuracy. Through this option a high-accuracy clock crystal (±15 ppm) is installed instead. This option is required only for an accurate synchronization and velocity accuracy for long-term applications. Generally, this will be noticeable only if a continuous move sequence lasts more than 10 minutes.
- Option-12: 8-channel on-board 12-bit A/D converter. With this option extra components are added on the PMAC board for eight analog-to-digital converters with 12-bits resolution and 0-5 or ±2.5V range. Typically this option is used for analog sensors reading but not used regularly for analog sensors feedback devices.
- Option-12A: Extra 8-channel on-board 12-bit A/D converter. This option requires Option-12 and provides a total of 16 analog-to-digital converters with 12-bits resolution and 0-5 or ±2.5V range.
- Option-15: Voltage to frequency (V-to-F) converter to use control panel port analog input. This feature uses one of the encoder channels in PMAC to provide a low-resolution method of a single analog input interface.
- Option-18A: Electronic board identification number module. This option could be used to let a host computer program identify the Turbo PMAC board connected to the machine.





Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP