ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *GE Fanuc IC600YB904* at our website: *Click HERE*

SERIES SIX

PROGRAMMABLE CONTROLLERS

AC OUTPUT MODULES

GEK-83514C

8 outputs @
115 Vac
230 Vac

GENERAL DESCRIPTION

The AC output modules function as discrete switching devices between user AC power sources and user loads. The modules are available in two versions: 11 S Vac and 230 Vac. The features and benefits of these modules are summarized in Table 1.

A module contains eight outputs, divided into two groups, each group capable of connecting a common power source. Each output circuit utilizes a TRIAC as a switching device that connects the associated output terminal to the high side of the user power source when the output is in the ON state.

Provision is made in the Series Six Programmable Controller (PC) to automatically disable the outputs of the AC Output modules in the event of an Input/Output I/O chain failure or a Central Processor Unit (CPU) failure.

Visible through a lens on the faceplate are pairs of neon lamps associated with each output. One lamp indicates that the output is in the ON state; the other indicates the status of a fuse also included in each of the eight output circuits.

TABLE 1. FEATURES AND BENEFITS

FEATURES	BENEFITS
Two modules available: - 115Vac - 230Vac	Useful in a variety of applications
Indicator lights for each output: - ON/OFF light - Blown Fuse light	Simplifies troubleshooting.
Eight inputs per module.	Efficient use of I/O rack space.
Optically-coupled inputs.	Provides electrical isolation between power sources and Series Six PC.

APPLICATIONS

* Solenoids
* Indicator lights
* Motors
* Motor starters

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

- Power Requirements: 5V DC, 535 mA maximum
  Supplied by I/O power supply.

Module	User-Supplied Voltage	Leakage (OFF)
115V AC	90-130V AC	1.7mA @ 115V
230V AC	180-260V AC	1.0mA @ 230V

- ON-State Current:

  Maximum: 2 A @ 40°C (Derate to 50% duty cycle @ 60°C).

  Minimum: 5 mA

- ON-State Voltage Drop: 1.5V typical 2.5V max.
- Humidity: 5-95% (non-condensing)
- Storage Temperature: -20° to +80°C
- Dimensions:

  Circuit Board: 8.15 x 11.0 x 1.20 (inches)
  208 x 280 x 31 (mm)

  Faceplate: 12.46 x 1.175 (inches)
  317 x 30 (mm)

- Inrush Current: 12 A for 33 ms (max.)
- ON Delay: less than 1 ms
- OFF Delay: Less than 1/2 cycle
- Number of Outputs:

  Eight (8), in two groups of 4 outputs with common high and neutral connections.

- Operating Temperature: 0-60°C
  (at the outside of the rack)

FIGURE 1. SPECIFICATIONS




FIGURE 2. USER ITEMS

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

① Terminal Cover

② User Terminal Block:
Accepts connections from user output devices and the AC power source(s). See the "Installation" section of this Data Sheet.

③ Circuit-Board Terminal Block:
Mates with the user termina1 block.

④ Output Lights: 1 through 8

Off: Corresponding output is in the ON state.

Off: Corresponding output is in the OFF state.

⑤ BF (Blown Fuse) Lights

On: The fuse for corresponding output is open (blown).

Off: The fuse for corresponding output is OK.

⑥ Output-Circuit Fuses (3 A normal blow).

FIGURE 2. USER ITEMS (Part 2 of 2)

INSTALLATION

The AC Output modules can be installed in an I/O rack *or* the I/O rack section of the Model 60 Central Processor Unit (CPU). Follow these steps:

1. Set the Dual-In-Line Package (DIP) switches directly behind the card slot on the rack backplane to establish the correct correspondence between the input terminals on this module and a group of eight consecutive input numbers in the user program. For further information on I/O DIP switch settings. refer to the lnstallation section of the Series Six Installation and Maintenance Manual (GEK-25361).

2. Use the extraction/insertion tool furnished with the Series Six CPU to insert (or remove> this module in the card slot.

3. Guide the faceplate over the circuit board so that the terminals near the bottom of each are mated; secure the faceplate to the rack using the thumb-screws at the top and bottom.

4. Refer to Figure 3. Connect one side of the user circuit to the appropriate input terminal (1 through 8). Circuits connected to inputs 1 through 4 must have their opposite sides connected to either of the N1 terminals. Likewise, circuit connected to inputs 5 through 8 must have their opposite sides connected to either of the N2 terminals.

   In reference to Figure 3, note that wires connected to the N1 terminals are at the same potential, as are wires connected to the N2 terminals.

   Each input terminal can accommodate one No. 12 AWG wire or two No. 14 AWG wires.

5. Guide the terminal cover onto the top of the terminal block, then slide it downward over the terminals.

A markable area is provided on the plastic lens beside each Light-Emitting Diode (LED) for noting the function or source of each input. The faceplates are color coded:

Yellow:	115 Vac
Red:	230 Vac

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

WARNING

Voltages from user field devices may be present on the faceplate terminals, even if the power supply in the I/O rack is off. Care should be taken when handing the faceplate of this module or any wires connected to it.




FIGURE 3. TYPICAL USER OUTPUT CONNECTIONS

ORDERING INFORMATION

Module	Circuit Board and Faceplate	Circuit Board	Faceplate
115 Vac	IC600BF904B	IC600YB904B	IC600FP904B
230 Vac	IC600BF905B	IC600YB905B	IC600FP905B

CATALOG NUMBER REVISION SUFFIX

The equipment listed above having the catalog numbers shown and the same equipment having a higher alpha suffix is designed for listing by UL for use as auxiliary control devices. The equipment is a direct replacement for equipment having the same catalog number but a lower alpha suffix.

This symbol on the nameplate means the product is listed by Underwriters Laboratories Inc. (UL Standard No. 508, Industrial Control Equipment, subsection Electronic Power Conversion Equipment.)

For further information, contact your local GE Fanuc sales office.

GE Fanuc Automation North America, Inc., Charlottesville, Virginia

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP