ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Abaco Systems / SBS / Bit 3 400-201* at our website: ***Click HERE***

INTERNET ARCHIVE Wayback Machine
http://www.bit3.com/dualport.html Go
7 captures 30 Oct 96 - 6 Jun 02
OCT FEB JUL
14
1996 1997 2001
Close Help

BIT 3 COMPUTER CORPORATION

DATA SHEET

MODEL 400-201/202/203/204/205/206

DUAL PORT RAM OPTIONS

Dual Port RAM cards are optional memory cards for computer systems that are interconnected by Bit 3 Adaptors*. Optional Dual Port RAM provides a memory buffer; saves the cost of additional memory cards; and for some systems, such as VMEbus systems, requires no additional card slots.

* Bit 3 Adaptors connect two computer systems via a memory mapped interface. A fully functional Adaptor interface consists of two printed circuit cards and a cable that connects the two cards.

The Dual Port RAM card installs on an Adaptor card and is accessible to either system. As shared memory, either system can address Dual Port RAM via random access reads and writes. Access to the memory card uses only the bandwidth of the accessing bus. Consequently, transfer speed is increased and data can be exchanged with minimal impact on the performance of the other system's bus. Both systems can access Dual Port RAM simultaneously with the Adaptor arbitrating accesses.

Bit 3 Adaptors provide access to Dual Port RAM by a chassis at either end of the Adaptor cable. Dual Port RAM is treated as global memory and access to it is accomplished identically to bus memory access. Direct Mode, a method of communication used by all Bit 3 Adaptors, allows Dual Port RAM addresses to be mapped one-for-one to address space on each system's bus. The target addresses need not be the same for both buses.

Most Bit 3 Adaptors also support Page Mode Dual Port RAM access. Page Mode addressing allows a relatively small range of addresses on a bus to be used as a "window" for access to all Dual Port RAM. Window size is variable, from 64K to 1M byte. When a system accesses an address within the window, the Adaptor decodes only the lower 16 - 20 address bits. The upper address bits for the Dual Port RAM destination address are provided by a programmable Adaptor register. The number of upper address bits used can be changed by an I/O write instruction.

FEATURES

* Supports 32-bit data access when used on most systems except PC/AT, MULTIBUS and Q22-bus systems.

* 3" x 5" printed circuit card.

* Low profile.

* Installs component side down on the Adaptor card.

* Standoff holds the installed card securely in place.

* Requires no additional slots in a VMEbus chassis.

* Specially designed Grant Continuity cards are available for Q22-bus installations**.

* Static RAM and dynamic RAM Dual Port RAM cards are available. See specifications below.

** Q22-bus inter-card spacing is .5 inches. A Bit 3 Adaptor card for the Q22-bus with a Dual Port RAM card installed extends into the adjacent slot's space. A half-height Q22-bus card, however, can be installed in the remaining space within the slot. The half-height card plugs into the slot's C and D connectors; a Grant Continuity card, available from Bit 3, plugs into the A and B connectors behind the Dual Port RAM card. Consequently, two slots accommodate the Bit 3 Adaptor card, Q22-bus card, Dual Port RAM card and Grant Continuity card.

SPECIFICATIONS

* Model# 400-201 --
Size: 32K byte
Type: Static
Speed From Local Bus**: .39 microsecond (usec)
Speed From Remote Bus**: 2.0 usec

* Model# 400-202 --
Size: 128K byte
Type: Static
Speed From Local Bus**: .39 usec
Speed From Remote Bus**: 2.0 usec

* Model# 400-203 --
Size: 1M byte
Type: Dynamic

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

INTERNET ARCHIVE Wayback Machine Go 7 captures 30 Oct 96 - 6 Jun 02 OCT FEB JUL 14 1996 1997 2001 Close Help

* Model# 400-204 --
Size: 2M byte
Type: Dynamic
Speed From Local Bus**: .45 usec
Speed From Remote Bus**: 2.0 usec

* Model# 400-205 --
Size: 4M byte
Type: Dynamic
Speed From Local Bus**: .45 usec
Speed From Remote Bus**: 2.0 usec

* Model# 400-206 --
Size: 8M byte
Type: Dynamic
Speed From Local Bus**: .45 usec
Speed From Remote Bus**: 2.0 usec

** Speeds vary somewhat depending on the type of bus and Adaptor card the Dual Port RAM is installed on.

DISCLAIMER

All trademarks are the property of their respective companies.

Specifications subject to change without notice.
Pub. No. 100,198 2/94

Cable Configuration Guide Warranties
Repair Service Products List
How To Contact Bit 3 Home Page

Revised: December 18, 1996

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP