



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)

## Multichannel Backreflection Meter



### Key Features

- No deadzone
- SM and MM models available
- Measurements at 850, 1310, 1490, 1550 or 1625 nm
- Integrated switch included in the calibration
- Multidisplay mode
- Industry leading backreflection range

### Applications

- SM fiber connector and component testing
- Ribbon fiber measurements
- MM fiber connector testing
- Complies with IEC 61300-3-6, IEC 61300-3-4

### Safety Information

- Complies to CE requirements plus UL3101-1 and CAN/CSA-C22.2 No. 1010.1. Meets the requirements of Class 1 in standard IEC 60825-1(2002) and complies with 21CFR1040.10 except deviations per Laser Notice No. 50, July 2001.

CLASS 1 LASER PRODUCT  
(IEC 60825-1, 2002)

The JDSU Multichannel Backreflection Meter performs a wide range of single-mode (SM) or multimode (MM) backreflection and loss measurement functions, ranging from single component testing to automated multifiber testing. The primary functions of high sensitivity backreflection measurements and power measurements can be augmented by adding multiple output ports and multiple internal light sources.

The meter is available with 1, 4, 12 or 24 output ports. A multidisplay mode lets the viewer see multiple test results at a glance.

The meter is used for single fiber and ribbon fiber connector measurements. The use of hybrid jumpers allow a quick change of the connector type without limiting the backreflection range. The meter is also available with 2 or 3 internal sources for measurements at 850, 1310, 1490, 1550 or 1625 nm.

The 3-mm InGaAs detector is particularly useful for high sensitivity single fiber applications. The 5-mm Ge detector is an economical solution for measurements of ribbon fiber connectors and can accurately measure connectors with up to 8 MM and 12 SM fibers. The large surface 10-mm InGaAs detector is ideal for measurements of larger fiber count ribbon connectors, and can be used with wavelengths extending in the L-band. One FC detector adapter is supplied with the unit, and other adapters, such as MTP/MPO or MU for ribbon fiber connector types, are also available.

The meter is supplied with one calibrated hybrid jumper for calibration purposes and one hybrid test jumper for measurement purposes. Both jumpers are equipped with an FC/APC connector on one end (for the output port of the meter) and an FC/PC connector on the other end. Uncalibrated hybrid jumpers for measurements with other connector types are also available.

## 2

## Specifications

Parameter	Single-mode (SM)			Multimode (MM)		
Operating wavelengths	1310, 1490, 1550, 1625 ± 10 nm			850, 1310, 1550 ± 20 nm		
Outputs	1, 4, 12 or 24					
Detector type	3 mm InGaAs	5 mm Ge <sup>8</sup>	10 mm InGaAs	3 mm InGaAs	5 mm Ge <sup>8</sup>	10 mm InGaAs
Power range <sup>1</sup>	0 to -80 dBm	0 to -40 dBm	-5 to -40 dBm	0 to -60 dBm	0 to -40 dBm	0 to -40 dBm
Relative power accuracy <sup>5,9</sup>	± 0.15 dB <sup>6</sup>	± 0.15 dB <sup>6</sup>	± 0.15 dB <sup>6</sup>	± 0.15 dB <sup>7</sup>	± 0.15 dB <sup>7</sup>	± 0.15 dB <sup>7</sup>
Relative power accuracy (5 dB range) <sup>5,9</sup>	± 0.05 dB <sup>6</sup>	± 0.05 dB <sup>6</sup>	± 0.05 dB <sup>6</sup>	± 0.15 dB <sup>7</sup>	± 0.15 dB <sup>7</sup>	± 0.15 dB <sup>7</sup>
Backreflection range <sup>1,2,9</sup>	0 to -75 dB	0 to -75 dB	0 to -75 dB	0 to -40 dB	0 to -40 dB	0 to -40 dB
Relative backreflection accuracy <sup>3,9</sup>	± 0.4 dB <sup>3</sup>	± 0.4 dB <sup>4</sup>	± 0.4 dB <sup>3</sup>	± 0.7 dB	± 0.7 dB	± 0.7 dB
Relative backreflection accuracy (5 dB range) <sup>3,9</sup>	± 0.3 dB <sup>3</sup>	± 0.3 dB <sup>4</sup>	± 0.3 dB <sup>3</sup>	± 0.7 dB	± 0.7 dB	± 0.7 dB
Absolute power accuracy	± 0.25 dB typical at -10 dBm					
Backreflection resolution	0.1 dB					
Power resolution	0.01 dB					
Input voltage	100 to 240 V AC, 50 to 60 Hz					
Power consumption	80 V A maximum					
Chassis size						
1-output	3 U x 364 mm x 147.1 mm					
4/12/24-output	3 U x 471 mm x 147.1 mm					
Remote interface	RS-232					

1. Depending on the measurement setup, measurements with lower levels are possible at reduced accuracy.
2. Reduced backreflection accuracy in the last 10 dB of range based on termination effectiveness. Depending on the measurement setup, measurements with lower levels are possible at reduced accuracy.
3. Following the user-calibration procedure at the recommended interval.
4. For a typical application, add ± 0.4 dB for readings between -60 and -67 dB. Add ± 0.8 dB for readings between -67 and -72 dB. Add ± 1.5 dB for readings between -72 and -75 dB.
5. Immediately after performing a dark measurement.
6. Add ± 0.1 dB in the last 10 dB of the range.
7. Add ± 0.1 dB in the last 5 dB of the range.
8. 5 mm Ge detector can accurately measure ribbon fiber connectors with up to 8 MM or 12 SM fibers at wavelengths up to 1600 nm.
9. Measured at ambient temperature ± 3 °C.

**Ordering Information**

For more information on this or other products and their availability, please contact your local JDSU account manager or JDSU directly at 1-800-498-JDSU (5378) in North America and +800-5378-JDSU worldwide or via email at sales@jdsu.com.

**Sample Part Number: RX3070+1122FA7**

1310/1550nm, 12 output channels, 5mm Ge detector, 9/125um fiber

**RX30n0+1xxyFAz**
**Wavelength**

**Code n**      **Source Wavelength (nm)**

1	850
3	1310
5	1550
9	850/1310
7	1310/1550
E	1310/1550/1625
G	850/1310/1550
K	1310/1490/1550
L	1490/1550/1625

**Channels**

**Code xx**      **Number of Output Channels**

01	1 output channel
04	4 output channels (Only available with SM models)
12	12 output channels
24	24 output channels

**Detector Type**

**Code y**

1	3 mm InGaAs
2	5 mm Ge (Only available with 12 and 24 output channels)
3	10 mm InGaAs (Only available with 12 and 24 output channels)

**Connector Type**

**Code**

FA	FC/APC
----	--------

**Fiber Type (µm)**

**Code z**

7	9/125
1	50/125
2	62.5/125

**Optional Accessories**

For additional accessories refer to SWS, MAP, and RX Accessories datasheet.

UL is a registered trademark of Underwriters Laboratories Inc.

All statements, technical information and recommendations related to the products herein are based upon information believed to be reliable or accurate. However, the accuracy or completeness thereof is not guaranteed, and no responsibility is assumed for any inaccuracies. The user assumes all risks and liability whatsoever in connection with the use of a product or its application. JDSU reserves the right to change at any time without notice the design, specifications, function, fit or form of its products described herein, including withdrawal at any time of a product offered for sale herein. JDSU makes no representations that the products herein are free from any intellectual property claims of others. Please contact JDSU for more information. JDSU and the JDSU logo are trademarks of JDS Uniphase Corporation. Other trademarks are the property of their respective holders. ©2007 JDS Uniphase Corporation. All rights reserved. 10109641 010 0507 MBM.DS.TM.AE

**Test & Measurement Regional Sales**

<b>NORTH AMERICA</b> TEL: 1 866 228 3762 FAX: +1 301 353 9216	<b>LATIN AMERICA</b> TEL: +55 11 5503 3800 FAX: +55 11 5505 1598	<b>ASIA PACIFIC</b> TEL: +852 2892 0990 FAX: +852 2892 0770	<b>EMEA</b> TEL: +49 7121 86 2222 FAX: +49 7121 86 1222	<b>WEBSITE: <a href="http://www.jdsu.com">www.jdsu.com</a></b>
---	--	---	---	--



## Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

### SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

### *InstraView*<sup>SM</sup> REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at [www.instraview.com](http://www.instraview.com) ↗

### WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. [www.artisanng.com/WeBuyEquipment](http://www.artisanng.com/WeBuyEquipment) ↗

### LOOKING FOR MORE INFORMATION?

Visit us on the web at [www.artisanng.com](http://www.artisanng.com) ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

**Contact us:** (888) 88-SOURCE | [sales@artisanng.com](mailto:sales@artisanng.com) | [www.artisanng.com](http://www.artisanng.com)