

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *National Instruments PXIe-5820* at our website: ***Click HERE***

SPECIFICATIONS

PXIe-5820

1.25 GS/s Baseband I/Q Vector Signal Transceiver

Contents

Definitions....2
Conditions....2
Differential Operation....3
Frequency....4
    Internal Frequency Reference....4
I/Q Input....5
    I/Q Input Common-Mode Accuracy....5
    I/Q Input DC Offset....5
    I/Q Input Absolute AC Gain Accuracy....5
    I/Q Input Frequency Response....6
    I/Q Input Settling Time....7
    I/Q Input Average Noise Density....8
    I/Q Input Spectral Characteristics....9
I/Q Output....11
    I/Q Output Common-Mode Accuracy....11
    I/Q Output DC Offset....12
    I/Q Output Absolute AC Gain Accuracy....12
    I/Q Output Frequency Response....12
    I/Q Output Settling Time....14
    I/Q Output Average Noise Density....14
    I/Q Output Spectral Characteristics....14
Additional Performance Information....16
    Image Suppression....16
    SINAD and ENOB....16
    I/Q Loopback Third-Order Intermodulation (IMD3)....17
    I/Q Loopback Second-Order Intermodulation (IMD2)....19
Application-Specific Modulation Quality....21
    WLAN 802.11ax....21
    WLAN 802.11ac....21
    LTE....22
Baseband Characteristics....23
    Onboard FPGA....23
    Onboard DRAM....24
    Onboard SRAM....24

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Front Panel I/O....24
I/Q IN 0....24
I/Q OUT 0....25
REF IN....27
REF OUT....27
PFI 0....28
DIGITAL I/O....28
Power Requirements....30
Calibration....30
Physical Characteristics....31
Environment....31
Operating Environment....31
Storage Environment....31
Shock and Vibration....31
Compliance and Certifications....32
Safety....32
Electromagnetic Compatibility....32
CE Compliance....33
Online Product Certification....33
Environmental Management....33

Definitions

Warranted specifications describe the performance of a model under stated operating conditions and are covered by the model warranty.

The following characteristic specifications describe values that are relevant to the use of the model under stated operating conditions but are not covered by the model warranty.

- *Typical* specifications describe the performance met by a majority of models.
- *Typical-95* specifications describe the performance met by 95% (≈2σ) of models with a 95% confidence.
- *Nominal* specifications describe an attribute that is based on design, conformance testing, or supplemental testing.

Specifications are *Warranted* unless otherwise noted.

Conditions

Warranted specifications are valid under the following conditions unless otherwise noted.

- Over ambient temperature range of 0 °C to 45 °C.
- 30 minutes warm-up time.
- Calibration cycle is maintained.
- Chassis fan speed is set to High. In addition, NI recommends using slot blockers and EMC filler panels in empty module slots to minimize temperature drift.
- Calibration IP is used properly during the creation of custom FPGA bitfiles.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Typical specifications do not include measurement uncertainty and are measured immediately after a device self-calibration is performed.

Unless otherwise noted, specifications assume the PXIe-5820 is configured in the following default mode of operation:

- I/Q IN voltage range: 2.0 V_{pk-pk} differential
- I/Q IN common-mode voltage: 0 V
- I/Q OUT voltage range: 1.0 V_{pk-pk} differential
- I/Q OUT common-mode voltage: 0 V
- I/Q OUT load impedance: 100 Ω differential

Note Within the specifications, *self-calibration °C* refers to the recorded device temperature of the last successful self-calibration. You can read the self-calibration temperature from the device using the appropriate software functions.


Differential Operation

The I/Q inputs and outputs of the PXIe-5820 support differential operation. This section explains some of the fundamental analog signal processing that occurs in the first stages of the I/Q receiver.

A differential signal system has a positive component (V_{INPUT}(CH+)) and a negative component (V_{INPUT}(CH-)). The differential signal can have a common-mode offset (V_{IN_COM}) shared by both V_{INPUT}(CH+) and V_{INPUT}(CH-). The differential input signal is superimposed on the common-mode offset. The input circuitry rejects the input common-mode offset signal.

In a differential system, any noise present on both V_{INPUT}(CH+) and V_{INPUT}(CH-) gets rejected. Differential systems also double the dynamic range compared to a single-ended system with the same voltage swing. The following figure illustrates the key concepts of differential offset and common-mode offset associated with a differential system.

Figure 1. Definition of Common-Mode Offset and Differential Offset



Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

where

V_{IN_PP+} represents the peak-to-peak amplitude of the positive AC input signal

V_{IN_PP-} represents the peak-to-peak amplitude of the negative AC input signal

V_{DO} represents the differential offset voltage

V_{IN_COM} represents the common-mode offset voltage

V_{OUT_PP} represents the peak-to-peak amplitude of the output signal

In the previous figure, the input common-mode voltage is not present after the first stage of the receiver system. The signal remaining at the output of the receiver circuitry is the signal of interest.

Note The differential signal can have an offset between V_{INPUT}(CH+) and V_{INPUT}(CH-). This is known as the *differential offset* and is retained by the receiver circuitry.

In an I/Q analyzer, a differential offset can occur because of LO leakage or harmonics. In the case of I/Q generation, a differential offset can cause spurs and magnitude error.

In a phase-balanced differential system, the peak-to-peak amplitude of the positive AC input signal (V_{IN_PP+}) is equal to the peak-to-peak amplitude of the negative AC input signal (V_{IN_PP-}). The AC peak-to-peak amplitude of the output signal is the sum of V_{IN_PP+} and V_{IN_PP-}. A more general definition for the output voltage regardless of phase is the difference between V_{IN_PP+} and V_{IN_PP-} described by the following equation:

$V_{OUT} = (V_{INPUT}(CH+)) - (V_{INPUT}(CH-))$

The common-mode offset, which represents the rejected component common to both signals, is described by the following equation:

$V_{IN_COM} = [(V_{INPUT}(CH+)) + (V_{INPUT}(CH-))]/2$

Frequency

Complex I/Q equalized bandwidth[1]	1 GHz
Frequency Range	DC-500 MHz

Note To operate the device in complex baseband mode, configure each channel with identical ranges and termination. Complex baseband mode requires two input signals that are 90° out of phase.

Internal Frequency Reference

Initial adjustment accuracy	$\pm 200 \times 10^{-9}$
Temperature stability	$\pm 1 \times 10^{-6}$, maximum

[1] Complex equalized bandwidth is the combined bandwidth of I and Q channels. Valid only when using identical gain and termination settings for each I/Q channel.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Aging	±1 × 10^{-6} per year, maximum
Accuracy	*Initial adjustment accuracy* ± *Aging* ± *Temperature stability*

I/Q Input

I/Q Input Common-Mode Accuracy

Table 1. I/Q Input Common-Mode Accuracy, Typical

Common-Mode (V)	Accuracy (mV) at 23 °C
-0.25 to 1.50	±2.5
Conditions: Measured with a DMM. Common-mode offset is not adjusted during self-calibration. Valid for vertical ranges between 0.1 V_{pp} and 2.0 V_{pp}, differential. Measured with both input terminals terminated to ground through a high impedance >1 MΩ.	

I/Q Input DC Offset

Table 2. I/Q Input Differential DC Offset Error, Typical

Reference Location	DC Offset at 23 °C ± 5 °C
At ADC	<-57 dBFS
At connector	<10 mV
Conditions: Terminated with 100 Ω differential impedance.	

I/Q Input Absolute AC Gain Accuracy

Table 3. I/Q Input Absolute AC Gain Accuracy (dB)

Input Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
0.5 to 4.0	±0.57	±0.71
	±0.15, typical	±0.28, typical

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 3. I/Q Input Absolute AC Gain Accuracy (dB) (Continued)

Input Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
1.0 to 4.0	±0.44	±0.57

Conditions: Valid for all common-mode voltages. Measured with 10 MHz CW tone from a 100 Ω differential source.

This specification is valid only when the module is operating within the specified ambient temperature range and within ±5 °C from the last self-calibration temperature, as indicated by the **niRFSA Device Temperature** property or `NIRFSA_ATTR_DEVICE_TEMPERATURE` attribute.

I/Q Input Frequency Response

Table 4. I/Q Input Frequency Response[2] (dB)

Frequency	Input Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
100 kHz to 100 MHz	0.5 to 4.0	±0.31, typical	±0.36, typical
		±0.82	±0.92
	1.0 to 4.0	±0.67	±0.77
100 kHz to 250 MHz	0.5 to 4.0	±0.31, typical	±0.36, typical
		±0.82	±0.97
	1.0 to 4.0	±0.67	±0.83
100 kHz to 500 MHz	0.5 to 4.0	±0.31, typical	±0.62, typical
		±0.82	±1.22
	1.0 to 4.0	±0.68	±1.10

[2] Referenced to 10 MHz. Digital equalization enabled. Valid only when using identical gain and termination settings for each I/Q channel.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com


Table 4. I/Q Input Frequency Response[2] (dB) (Continued)

Frequency	Input Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
10 MHz to 250 MHz	0.5 to 4.0	±0.10, typical	±0.28, typical
10 MHz to 500 MHz		±0.25, typical	±0.62, typical

Conditions: Valid for all common-mode voltages. Referenced to 10 MHz.

This specification is the individual I or Q channel flatness and is valid only when the module is operating within the specified ambient temperature range and within ±5 °C from the last self-calibration temperature, as indicated by the **niRFSA Device Temperature** property or the `NIRFSA_ATTR_DEVICE_TEMPERATURE` attribute.

Figure 2. I/Q Input Frequency Response, Nominal[3]



I/Q Input Settling Time

Table 5. I/Q Input Amplitude Settling Times, Nominal

Proximity to Final Settled Value (dB)	Settling Time (µs)
0.5	9
0.1	100

[2] Referenced to 10 MHz. Digital equalization enabled. Valid only when using identical gain and termination settings for each I/Q channel.

[3] Measured at 23 °C with 0 V common-mode and 1 V_{pp} vertical range, differential.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 5. I/Q Input Amplitude Settling Times, Nominal (Continued)

Proximity to Final Settled Value (dB)	Settling Time (µs)
0.05	100
0.01	100


Nominal common-mode voltage settling time (0.01 dB)[4] 1.2 ms

I/Q Input Average Noise Density

Table 6. I/Q Average Input Noise Density, Typical

Input Vertical Range (V_{pp}, Differential)	dBm/Hz	dBFs/Hz
0.5	-152	-149
1	-143	-146
2	-141	-149
3	-140	-150
Conditions: Terminated with a 100 Ω differential impedance.		


Figure 3. Input Average Noise Density vs. Linear Frequency (dBFS/Hz), Nominal [5]



[4] Nominal settling time is for max common-mode change.
[5] Terminated with a 100 Ω differential impedance. Linear scale used for frequency axis.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 4. Input Average Noise Density vs. Log Frequency (dBFS/Hz), Nominal [6]



I/Q Input Spectral Characteristics

Harmonics[7]

Table 7. I/Q Input I Channel Highest Harmonic Spur Level (dBc)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-74	-78	-76	-80
1	-75	-80	-76	-83
2	-76	-81	-73	-80
3	-78	-80	-73	-79

Table 8. I/Q Input Q Channel Highest Harmonic Spur Level (dBc)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-78	-81	-78	-81
1	-80	-85	-82	-86

[6] Terminated with a 100 Ω differential impedance. Log scale used for frequency axis.
[7] Conditions: Measured with a -2 dBFS CW tone.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 8. I/Q Input Q Channel Highest Harmonic Spur Level (dBc) (Continued)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
2	-79	-82	-80	-85
3	-77	-80	-79	-84

Table 9. I/Q Input I Channel THD (dBc)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-74	-77	-75	-79
1	-75	-80	-75	-82
2	-76	-80	-73	-79
3	-77	-79	-73	-79

Table 10. I/Q Input Q Channel THD (dBc)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-76	-79	-77	-81
1	-80	-84	-81	-85
2	-79	-81	-79	-84
3	-76	-79	-78	-83

Table 11. I/Q Input Second Harmonic (dBc), Nominal

Input Vertical Range (V_{pp}, Differential)	10 MHz	100 MHz
0.5	-89	-89
1	-89	-88
2	-89	-89
3	-89	-88

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 12. I/Q Input Third Harmonic (dBc), Nominal

Input Vertical Range (V_{pp}, Differential)	10 MHz	100 MHz
0.5	-88	-91
1	-89	-89
2	-86	-85
3	-86	-84

Non-Harmonics[8]

Table 13. I/Q Input Non-Harmonics (dBc)

Input Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-80	-82	-79	-81
1	-79	-81	-79	-81
2	-80	-81	-79	-81
3	-80	-81	-80	-82

I/Q Output

I/Q Output Common-Mode Accuracy

Table 14. I/Q Output Common-Mode Accuracy, Typical

Common-Mode (V)	Accuracy (mV) at 23 °C
-0.25 to 1.50	±2
Conditions: Measured with a DMM. Common-mode offset is not adjusted during self-calibration. Valid for vertical ranges between 0.1 V_{pp} and 2.0 V_{pp}, differential. Measured with both output terminals terminated to ground through a high impedance >1 MΩ.	

[8] Conditions: Measured with a -2 dBFS CW tone.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

I/Q Output DC Offset

Table 15. I/Q Output Differential DC Offset Error[9] (dBr), Typical

Temperature Range	I/Q Output DC Offset Error
23 °C ± 5 °C	-60
dBr is dB relative to the peak to peak output voltage setting (V_{pp}, differential).	

I/Q Output Absolute AC Gain Accuracy

Table 16. I/Q Output Absolute AC Gain Accuracy (dB)

Output Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C ± 45 °C
0.25 to 2.0	±0.43	±0.68
	±0.10, typical	±0.35, typical
Conditions: Valid for all common-mode voltages. 10 MHz CW tone into a 100 Ω differential load. This specification is valid only when the module is operating within the specified ambient temperature range and within ±5 °C from the last self-calibration temperature, as indicated by the **niRFSG Device Temperature** property or the `NIRFSA_ATTR_DEVICE_TEMPERATURE` attribute.		

I/Q Output Frequency Response

Table 17. I/Q Output Frequency Response (dB)

Frequency Range	Output Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
100 kHz to 100 MHz	0.25 to 2.0	±0.17, typical	±0.24, typical
		±0.51	±0.61
	0.50 to 2.0	±0.44	±0.54

[9] Conditions: 100 Ω differential load.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com


Table 17. I/Q Output Frequency Response (dB) (Continued)

Frequency Range	Output Vertical Range (V_{pp}, Differential)	23 °C ± 5 °C	0 °C to 45 °C
100 kHz to 250 MHz	0.25 to 2.0	±0.17, typical	±0.25, typical
		±0.57	±0.69
	0.50 to 2.0	±0.55	±0.68
100 kHz to 500 MHz	0.25 to 2.0	±0.18, typical	±0.36, typical
		±0.65	±0.83
	0.50 to 2.0	±0.59	±0.80

Conditions: Valid for all common-mode voltages. Referenced to 10 MHz.

This specification is the individual I or Q channel flatness and is valid only when the module is operating within the specified ambient temperature range and within ±5 °C from the last self-calibration temperature, as indicated by the **niRFSG Device Temperature** property or the `NIRFSA_ATTR_DEVICE_TEMPERATURE` attribute.

Figure 5. I/Q Output Frequency Response, Nominal[10]



[10] Measured at 23 °C with 0 V common-mode and 1 V_{pp} vertical range, differential.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

I/Q Output Settling Time

Table 18. I/Q Output Nominal Amplitude Settling Times

Proximity to Final Settled Value (dB)	Settling Time (us)
0.5	9
0.1	100
0.05	100
0.01	100

Nominal common-mode settling time (0.01 dB)[11] 1.2 ms

I/Q Output Average Noise Density

Table 19. I/Q Average Output Noise Density, Typical

Output Vertical Range (V_{pp}, Differential)	dBm/Hz	dBFS/Hz
0.5	-152	-147
1	-154	-155
2	-156	-162
Conditions: Terminated with a 100 Ω differential impedance.		

I/Q Output Spectral Characteristics

Harmonics[12]

Table 20. I/Q Output I or Q Channel Highest Harmonic Spur Level (dBc)

Output Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-77	-80	-70	-74
1	-78	-80	-69	-74
2	-69	-71	-66	-68

[11] Nominal settling time is for max common-mode voltage change.
[12] Conditions: Measured with a -1 dBFS CW tone.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 21. I/Q Output I or Q Channel THD (dBc)

Output Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-75	-78	-69	-73
1	-77	-78	-69	-73
2	-69	-70	-65	-67

Table 22. I/Q Output I or Q Channel Second Harmonic (dBc)

Output Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-72	-82	-67	-77
1	-73	-81	-68	-77
2	-74	-82	-66	-76

Table 23. I/Q Output I or Q Channel Third Harmonic (dBc)

Output Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-73	-81	-69	-78
1	-79	-85	-73	-80
2	-72	-75	-65	-71

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Non-Harmonics[13]

Table 24. I/Q Loopback Non-Harmonics

Output Vertical Range (V_{pp}, Differential)	10 MHz		100 MHz	
	Typical	Nominal	Typical	Nominal
0.5	-76	-77	-75	-77
1	-79	-81	-79	-81
2	-80	-82	-79	-81

Additional Performance Information

Image Suppression

Table 25. I/Q Loopback Image Suppression[14] (dBc), Nominal

Complex Bandwidth	Image Suppression
200 MHz	-69
1 GHz	-61
Image suppression is equivalent to or better than the specification at all frequency offsets within the specified bandwidth.	

SINAD and ENOB

Table 26. Input SINAD and ENOB

Real Bandwidth (MHz)	Real SINAD	Real ENOB	Complex SINAD	Complex ENOB
0.5	80.1	13.0	80.5	13.1
1	79.9	13.0	80.4	13.1
2.5	79.7	13.0	80.3	13.1

[13] Conditions: Measured in loopback with a -1 dBFS CW tone. The I/Q input vertical range is set to twice the I/Q output vertical range.

[14] Measured at 23 °C. Digital equalization enabled. Valid only when using identical gain and termination settings for each I/Q channel. Measured using short phase matched loopback cables <1 ps.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 26. Input SINAD and ENOB (Continued)

Real Bandwidth (MHz)	Real SINAD	Real ENOB	Complex SINAD	Complex ENOB
5	78.8	12.8	79.4	12.9
10	77.9	12.6	78.4	12.7
20	77.7	12.6	78.3	12.7
100	76.3	12.4	77.4	12.6
500	69.5	11.3	70.6	11.4
Complex equalized bandwidth is the combined bandwidth of I and Q channels.				

Table 27. Output SINAD and ENOB

Real Bandwidth (MHz)	Real SINAD	Real ENOB	Complex SINAD	Complex ENOB
0.5	79.3	12.9	80.5	13.1
1	78.7	12.8	80.1	13.0
2.5	75.8	12.3	77.9	12.6
5	76.8	12.5	78.7	12.8
10	75.8	12.3	77.9	12.6
20	74.3	12.0	76.8	12.5
100	69.7	11.3	72.5	11.8
500	63.6	10.3	66.6	10.8
Complex equalized bandwidth is the combined bandwidth of I and Q channels.				

I/Q Loopback Third-Order Intermodulation (IMD3)

Table 28. I/Q Loopback IMD3 (dBc), Typical


Vertical Range (V_{pp}, Differential)	0 °C to 45 °C	
	Center Frequency (MHz)	
	10 MHz	100 MHz
0.25	-80	-78
0.50	-80	-78

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table 28. I/Q Loopback IMD3 (dBc), Typical (Continued)

Vertical Range (V_{pp}, Differential)	0 °C to 45 °C	
	Center Frequency (MHz)	
	10 MHz	100 MHz
1.00	-78	-76
2.00	-75	-73
Conditions: Measured in loopback with two-tone stimulus, each tone is -8 dBFS with a 700 kHz spacing between the tones (equally spaced from the center frequency). IQ In and IQ Out ports are configured with the same Vertical Range and with 0 V common-mode.		


Figure 6. 10 MHz IMD3, Nominal[15]



[15] Measured at 23 °C with both I/Q In and I/Q Out common-mode voltage set to 0 V and with I/Q In vertical range set to 2.0 V_{pp}, differential.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 7. 100 MHz IMD3, Nominal[16]



I/Q Loopback Second-Order Intermodulation (IMD2)

Table 29. I/Q Loopback IMD2 (dBc), Typical

Vertical Range (V_{pp}, Differential)	0 °C to 45 °C	
	Center Frequency (MHz)	
	10 MHz	100 MHz
0.25	-74	-68
0.50	-73	-67
1.00	-73	-68
2.00	-73	-67
Conditions: Measured in loopback with two-tone stimulus, each tone is -8 dBFS with a 700 kHz spacing between the tones (equally spaced from the center frequency). IQ In and IQ Out ports are configured with the same Vertical Range and with 0 V common-mode.		

[16] Measured at 23 °C with both I/Q In and I/Q Out common-mode voltage set to 0 V and with I/Q In vertical range set to 2.0 V_{pp}, differential.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 8. 10 MHz IMD2, Nominal[17]





Figure 9. 100 MHz IMD2, Nominal[18]



[17] Measured at 23 °C with both I/Q In and I/Q Out common-mode voltage set to 0 V and with I/Q In vertical range set to 2.0 V_{pp}, differential.

[18] Measured at 23 °C with both I/Q In and I/Q Out common-mode voltage set to 0 V and with I/Q In vertical range set to 2.0 V_{pp}, differential.


Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Application-Specific Modulation Quality

WLAN 802.11ax

EVM (Bandwidth: 80 MHz)[19]	-50 dB, typical

Figure 10. 802.11ax Measured EVM (80 MHz)



WLAN 802.11ac

EVM (Bandwidth: 80 MHz)[20]	-50 dB, typical
EVM (Bandwidth: 160 MHz)[21]	-50 dB, typical

[19] Loopback with phase matched cables <1 ps; transmit power auto-leveled based on real-time average power measurements; MCS=11.

[20] Loopback with phase matched cables <1 ps; transmit power auto-leveled based on real-time average power measurements; MCS=11.

[21] Loopback with phase matched cables <1 ps; transmit power auto-leveled based on real-time average power measurements; MCS=11.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 11. 802.11ac Measured EVM (80 MHz)





Figure 12. 802.11ac Measured EVM (160 MHz)




LTE

EVM (Bandwidth: 20 MHz) [22]	-60 dB, typical

[22] Loopback with phase matched cables <1 ps; transmit power auto-leveled based on real-time average power measurements.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 13. LTE Measured EVM (20 MHz)



Baseband Characteristics

Analog-to-digital converters (ADCs)	
Resolution	14 bits
Sample rate	1.25 GS/s
I/Q data rate[23]	19 kS/s to 1.25 GS/s
Digital-to-analog converters (DACs)	
Resolution	16 bits
Sample rate[24]	1.25 GS/s
I/Q data rate[25]	19 kS/s to 1.25 GS/s

Onboard FPGA

FPGA	Xilinx Virtex-7 X690T
LUTs	433,200
Flip-flops	866,400
DSP48 slices	3,600
Embedded block RAM	52.9 Mbits
Data transfers	DMA, interrupts, programmed I/O
Number of DMA channels	56

[23] I/Q data rates lower than 1.25 GS/s are achieved using fractional decimation.
[24] DAC sample rate is internally interpolated to 2.5 GS/s, automatically configured.
[25] I/Q data rates lower than 1.25 GS/s are achieved using fractional interpolation.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Onboard DRAM

Memory size	2 banks, 2 GB per bank
Theoretical maximum data rate	12 GB/s per bank

Onboard SRAM

Memory size	2 MB
Maximum data rate (read)	31 MB/s
Maximum data rate (write)	29 MB/s

Front Panel I/O

I/Q IN 0

Connectors	MMPX (female)
Input coupling, per terminal	DC
Input type	Differential
Number of channels	2

Vertical Range

Input voltage range per I/Q input pin[26] (no damage)	-3 V to 5 V
Common-mode range[27]	-0.25 V to 1.5 V
Maximum vertical range	4 V_{pp}, differential

Impedance

DC differential input impedance	100 ± 10 Ω, typical

[26] Common-mode voltage plus peak AC voltage.
[27] Valid for all Vpp differential levels with a 100 Ω differential source.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 14. I/Q Input Impedance, Nominal





Figure 15. I/Q Input Differential Return Loss, Nominal



I/Q OUT 0

Connectors	MMPX (female)
Output coupling, per terminal	DC
Output type	differential
Number of channels	2

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Vertical Range

Maximum voltage range per I/Q output pin (no damage)	V_{com} ±3.5 V
Common-mode range[28]	-0.25 V to 1.5 V


Table 30. I/Q Output Vertical Range (V_{pp}, Differential)

NI RFSG Signal Bandwidth Setting (Complex)	Maximum Vertical Range
≤ 160 MHz	3.4, nominal
≤ 1 GHz	2, typical
Conditions: Into a 100 Ω differential load.	

Impedance

DC differential output impedance 100 ± 10 Ω, typical


Figure 16. I/Q Output Impedance, Nominal



[28] Valid for all V_{pp}, differential levels.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 17. I/Q Output Differential Return Loss, Nominal



REF IN

Connector	MMPX (female)
Frequency	10 MHz
Tolerance[29]	$\pm 10 \times 10^{-6}$
Amplitude[30]	0.7 $V_{pk\text{-}pk}$ to 3.3 $V_{pk\text{-}pk}$ into 50 Ω, typical
Input impedance	50 Ω, nominal
Coupling	AC

REF OUT

Connector	MMPX (female)
Frequency	10 MHz, nominal
Amplitude	1.65 $V_{pk\text{-}pk}$ into 50 Ω, nominal
Output impedance	50 Ω, nominal
Coupling	AC

[29] *Frequency Accuracy = Tolerance × Reference Frequency*
[30] Jitter performance improves with increased slew rate of input signal.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

PFI 0

Connector	MMPX (female)
Voltage levels[31]	
Absolute maximum input range	-0.5 V to 5.5 V
V_{IL}, maximum	0.8 V
V_{IH}, minimum	2.0 V
V_{OL}, maximum	0.2 V with 100 µA load
V_{OH}, minimum	2.9 V with 100 µA load
Input impedance	10 kΩ, nominal
Output impedance	50 Ω, nominal
Maximum DC drive strength	24 mA

DIGITAL I/O

Connector	Molex Nano-Pitch I/O
5.0 V Power	±5%, 50mA maximum, nominal

Table 31. DIGITAL I/O Signal Characteristics

Signal	Type	Direction
MGT Tx± <3..0>	Xilinx Virtex-7 GTH	Output
MGT Rx± <3..0>	Xilinx Virtex-7 GTH	Input
MGT REF±	Differential	Input
DIO <1..0>[32]	Single-ended	Bidirectional
DIO <7..2>	Single-ended	Bidirectional
5.0 V	DC	Output
GND	Ground	—

Digital I/O High Speed Serial MGT[33]

Data rate	500 Mbps to 12 Gbps, nominal
Number of Tx channels	4

[31] Voltage levels are guaranteed by design through the digital buffer specifications.
[32] Pins are multiplexed with MGT REF±.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Number of Rx channels	4
I/O AC coupling capacitor	100 nF

MGT Tx± <3..0> Channels

Minimum differential output voltage[34]	800 mV_{pk-pk} into 100 Ω, nominal

MGT Rx± <3..0> Channels

Differential input voltage range	
≤ 6.6 GB/s	150 mV_{pk-pk} to 2000 mV_{pk-pk}, nominal
> 6.6 GB/s	150 mV_{pk-pk} to 1250 mV_{pk-pk}, nominal
Differential input resistance	100 Ω, nominal

MGT Reference Clock

Clocking Resources	
Internal MGT reference[35]	78.125 MHz to 625 MHz
Data Clock	156.25 MHz
MGT REF± Input	60 MHz to 820 MHz, nominal


MGT REF± Input

AC coupling capacitors	100 nF
Differential input resistance	100 Ω, nominal
Differential input V_{pk-pk} range	350 mV to 2000 mV, nominal
Absolute maximum input range	-1.25 V to 4.5 V[36]

[33] For detailed FPGA and High Speed Serial Link specifications, refer to Xilinx documentation.
[34] When transmitter output swing is set to the maximum setting.
[35] Internal MGT Reference is derived from the Sample Clock PLL. Available frequencies are 2.5 GHz / *N*, where 4 ≤ N ≤ 32. Set via MGT component level IP (CLIP).
[36] Absolute maximum levels at input, prior to AC coupling capacitors.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Figure 18. DIGITAL I/O Nano-Pitch Connector



Power Requirements

Table 32. Power Requirements

Voltage (V_{DC})	Typical Current (A)
+3.3	3.3
+12	6.0
Power is 83 W, typical. Consumption is from both PXI Express backplane power connectors. Conditions: Simultaneous generation and acquisition using NI-RFSG and NI-RFSA at 1.25 GS/s I/Q rate, 45 °C ambient temperature. Power consumption depends on FPGA image being used.	

Calibration

Interval	1 year

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Physical Characteristics

PXIe-5820 module	3U, two slot, PXI Express module 4.1 cm × 13.0 cm × 21.6 cm 1.6 in × 5.1 in × 8.5 in
Weight	795 g (28.0 oz)

Environment

Maximum altitude	2,000 m (800 mbar) (at 25 °C ambient temperature)
Pollution Degree	2

Indoor use only.

Operating Environment

Ambient temperature range	0 °C to 45 °C (Tested in accordance with IEC 60068-2-1 and IEC 60068-2-2.Meets MIL-PRF-28800F Class 3 low temperature limit and MIL-PRF-28800F Class 4 high temperature limit.)
Relative humidity range	10% to 90%, noncondensing (Tested in accordance with IEC 60068-2-56.)

Storage Environment

Ambient temperature range	-40 °C to 71 °C (Tested in accordance with IEC 60068-2-1 and IEC 60068-2-2. Meets MIL-PRF-28800F Class 3 limits.)
Relative humidity range	5% to 95%, noncondensing (Tested in accordance with IEC 60068-2-56.)

Shock and Vibration

Operating shock	30 g peak, half-sine, 11 ms pulse (Tested in accordance with IEC 60068-2-27. Meets MIL-PRF-28800F Class 2 limits.)

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Random vibration	
Operating	5 Hz to 500 Hz, 0.3 g_{rms} (Tested in accordance with IEC 60068-2-64.)
Nonoperating	5 Hz to 500 Hz, 2.4 g_{rms} (Tested in accordance with IEC 60068-2-64. Test profile exceeds the requirements of MIL-PRF-28800F, Class 3.)

Compliance and Certifications

Safety

This product is designed to meet the requirements of the following electrical equipment safety standards for measurement, control, and laboratory use:

- IEC 61010-1, EN 61010-1
- UL 61010-1, CSA C22.2 No. 61010-1

Note For UL and other safety certifications, refer to the product label or the *Online Product Certification* section.

Electromagnetic Compatibility

This product meets the requirements of the following EMC standards for electrical equipment for measurement, control, and laboratory use:

- EN 61326-1 (IEC 61326-1): Class A emissions; Basic immunity
- EN 55011 (CISPR 11): Group 1, Class A emissions
- EN 55022 (CISPR 22): Class A emissions
- EN 55024 (CISPR 24): Immunity
- AS/NZS CISPR 11: Group 1, Class A emissions
- AS/NZS CISPR 22: Class A emissions
- FCC 47 CFR Part 15B: Class A emissions
- ICES-001: Class A emissions

Note In the United States (per FCC 47 CFR), Class A equipment is intended for use in commercial, light-industrial, and heavy-industrial locations. In Europe, Canada, Australia, and New Zealand (per CISPR 11), Class A equipment is intended for use only in heavy-industrial locations.

Note Group 1 equipment (per CISPR 11) is any industrial, scientific, or medical equipment that does not intentionally generate radio frequency energy for the treatment of material or inspection/analysis purposes.

Note For EMC declarations, certifications, and additional information, refer to the *Online Product Certification* section.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CE Compliance CE

This product meets the essential requirements of applicable European Directives, as follows:

- 2014/35/EU; Low-Voltage Directive (safety)
- 2014/30/EU; Electromagnetic Compatibility Directive (EMC)

Online Product Certification

Refer to the product Declaration of Conformity (DoC) for additional regulatory compliance information. To obtain product certifications and the DoC for this product, visit *ni.com/certification*, search by model number or product line, and click the appropriate link in the Certification column.

Environmental Management

NI is committed to designing and manufacturing products in an environmentally responsible manner. NI recognizes that eliminating certain hazardous substances from our products is beneficial to the environment and to NI customers.

For additional environmental information, refer to the *Minimize Our Environmental Impact* web page at *ni.com/environment*. This page contains the environmental regulations and directives with which NI complies, as well as other environmental information not included in this document.

Waste Electrical and Electronic Equipment (WEEE)

EU Customers At the end of the product life cycle, all NI products must be disposed of according to local laws and regulations. For more information about how to recycle NI products in your region, visit *ni.com/environment/weee*.

电子信息产品污染控制管理办法（中国 RoHS）

中国客户 National Instruments 符合中国电子信息产品中限制使用某些有害物质指令(RoHS)。关于 National Instruments 中国 RoHS 合规性信息，请登录 `ni.com/environment/rohs_china`。(For information about China RoHS compliance, go to `ni.com/environment/rohs_china`.)

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Information is subject to change without notice. Refer to the *NI Trademarks and Logo Guidelines* at ni.com/trademarks for information on NI trademarks. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering NI products/technology, refer to the appropriate location: **Help**»**Patents** in your software, the patents.txt file on your media, or the *National Instruments Patent Notice* at ni.com/patents. You can find information about end-user license agreements (EULAs) and third-party legal notices in the readme file for your NI product. Refer to the *Export Compliance Information* at ni.com/legal/export-compliance for the NI global trade compliance policy and how to obtain relevant HTS codes, ECCNs, and other import/export data. NI MAKES NO EXPRESS OR IMPLIED WARRANTIES AS TO THE ACCURACY OF THE INFORMATION CONTAINED HEREIN AND SHALL NOT BE LIABLE FOR ANY ERRORS. U.S. Government Customers: The data contained in this manual was developed at private expense and is subject to the applicable limited rights and restricted data rights as set forth in FAR 52.227-14, DFAR 252.227-7014, and DFAR 252.227-7015.

© 2017—2018 National Instruments. All rights reserved.

377089B-01 March 16, 2018

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP