



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

Compax3 S0XX V2 Specifications

Specifications

Drive Input Power
 Voltage
 Phase
 Frequency
 24 VDC Logic Power (Required)
 Drive Output Power
 PWM
 Continuous Current (RMS)
 Peak Current (RMS)
 Commutation

S025 V2

S063 V2

S100 V2

S150 V2

80-253 VAC	80-253 VAC	80-253 VAC	80-253 VAC
1Ø	1Ø	3Ø	3Ø
50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
24 VDC ±15%	24 VDC ±15%	24 VDC ±15%	24 VDC ±15%
16/32 kHz (selectable)	16/32 kHz (selectable)	16/32 kHz (selectable)	8/16/32 kHz (selectable)
2.5 Amps	6.3 Amps	10 Amps	15 Amps
5 Amps	12.6 Amps	20 Amps	30 Amps
Sinusoidal	Sinusoidal	Sinusoidal	Sinusoidal

Performance
 Torque Loop
 Velocity Loop
 Position Loop

62.5 micro seconds
 125 micro seconds
 125 micro seconds

Command Inputs (T10 only)
 Velocity and Torque Mode
 Position Mode

14 bit, ±10 VDC Analog
 Step & Direction; 5V or 24 V level (300 kHz input frequency); differential signal

Onboard Digital Inputs
 Type

Sinking type, 24 V nom. @ 10 mA, high = 9-32 V, low <8 V

Functions
 1xx T10 (4 dedicated)
 1xx T11 (8 dedicated)
 1xx T30 (8 programmable*)
 1xx T40 (8 programmable*)

Drive stage enable, control input enable, reset, motor brake open/close
 Motion interrupt, Start, Drive Stage enable + 5 motion profile select inputs (or 4 inputs with a home input)
 User definable via IEC61131-3 programming environment
 User definable via IEC61131-3 programming environment

Analog Inputs (T11, T30, T40)

Two (dedicated); 14 bit

Onboard Digital Outputs

Type
 Functions
 1xx T10 (4 dedicated)
 1xx T11 (4 dedicated)
 1xx T30 (4 programmable*)
 1xx T40 (4 programmable*)

Sourcing type, rated for 24 V @ 100 mA, short-circuit protected

Encoder
 Relay

Programmable up to 16,384 ppr (pre-quadrature)
 Normally closed, dry contact (switching current: 10-300 mA, switching voltage [AC/DC]: 100 mV-60 V)

Analog Outputs (T11, T30, T40)

Two (dedicated); 8 bit; software configurable as monitor outputs

Communications

Type
 Baud Rate
 Multi-drop (RS485)
 Profibus**
 CANopen**

RS232 (3-wire) on RS485 (2- or 4-wire); 8-bit word length, 1 stop bit, no parity
 Fixed at 115.8 Kbaud for RS232; adjustable for RS485
 Up to 255 nodes
 DPV0 supported; selectable Baud rate, 12 Mbd maximum transmission speed
 DCiA, DS102 supported; selectable Baud rate, 1 Mbd maximum transmission speed

Environmental

Temperature
 Humidity
 IP Class

Still air: 33-113°F (0-45°C); moving air: 33-122°F (0-50°C)
 0-75%, non-condensing
 IP 20; IP 54 option available

Protection

Short Circuit
 Brownout
 Over Voltage
 Over Temperature
 I_{2t}
 Safety Isolation

Phase-to-phase, phase-to-ground
 Below 70 VDC
 Will shut down when power dissipation capacity is exceeded
 Motor 330°F (170°C), Drive 221°F (105°C)
 Error generated if peak current > 3 seconds
 VDE0160

Standards

UL, cUL, CE (EMC), CE (LVD)

Internal Regeneration
 Capacities/Storable Energy

Compax3 S025 V2: 560 µF / 15Ws
 Compax3 S063 V2: 1120 µF / 30Ws
 Compax3 S100 V2: 780 µF / 21Ws
 Compax3 S150 V2: 1,170 µF / 31Ws

* 12 additional I/O points available as an option
 ** Applicable only to models supporting this option

Compax3 SXXX V4 Specifications

Specifications	S038 V4	S075 V4	S150 V4	S300 V4
Drive Input Power				
Voltage	80-525 VAC	80-525 VAC	80-525 VAC	80-525 VAC
Phase	3Ø	3Ø	3Ø	3Ø
Frequency	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
24 VDC Logic Power (Required)	24 VDC ±15%	24 VDC ±15%	24 VDC ±15%	24 VDC ±15%
Drive Output Power				
PWM	16/32 kHz (selectable)	16/32 kHz (selectable)	8/16/32 kHz (selectable)	8/16/32 kHz (selectable)
Continuous Current (RMS)	3.8 Amps	7.5 Amps	15 Amps	30 Amps
Peak Current (RMS)	7.5 Amps	15 Amps	30 Amps	60 Amps
Commutation	Sinusoidal	Sinusoidal	Sinusoidal	Sinusoidal

Performance	62.5 micro seconds
Torque Loop	125 micro seconds
Velocity Loop	125 micro seconds
Position Loop	
Command Inputs (T10 only)	
Velocity and Torque Mode	14 bit, ±10 VDC Analog
Position Mode	Step & Direction; 5V or 24 V level (300 kHz input frequency); differential signal
Onboard Digital Inputs	
Type	Sinking type, 24 V nom. @ 10 mA, high = 9-32 V, low <8 V
Functions	
1xx T10 (4 dedicated)	Drive stage enable, control input enable, reset, motor brake open/close
1xx T11 (8 dedicated)	Motion interrupt, Start, Drive Stage enable + 5 motion profile select inputs (or 4 inputs with a home input)
1xx T30 (8 programmable*)	User definable via IEC61131-3 programming environment
1xx T40 (8 programmable*)	User definable via IEC61131-3 programming environment
Analog Inputs (T11, T30, T40)	Two (dedicated); 14 bit
Onboard Digital Outputs	
Type	Sourcing type, rated for 24 V @ 100 mA, short-circuit protected
Functions	
1xx T10 (4 dedicated)	No fault, drive enabled, in position window, at zero point
1xx T11 (4 dedicated)	No fault, position reached, power stage active, at zero point
1xx T30 (4 programmable*)	User definable via IEC61131-3 programming environment
1xx T40 (4 programmable*)	User definable via IEC61131-3 programming environment
Encoder	Programmable up to 16,384 ppr (pre-quadrature)
Relay	Normally closed, dry contact (switching current: 10-300 mA, switching voltage [AC/DC]: 100 mV-60 V)
Analog Outputs (T11, T30, T40)	Two (dedicated); 8 bit; software configurable as monitor outputs
Communications	
Type	RS232 (3-wire) on RS485 (2- or 4-wire); 8-bit word length, 1 stop bit, no parity
Baud Rate	Fixed at 115.8 Kbaud for RS232; adjustable for RS485
Multi-drop (RS485)	Up to 255 nodes
Profibus**	DPV0 supported; selectable Baud rate, 12 Mbd maximum transmission speed
CANopen**	DCiA, DS102 supported; selectable Baud rate, 1 Mbd maximum transmission speed
Environmental	
Temperature	Still air: 33-113°F (0-45°C); moving air: 33-122°F (0-50°C)
Humidity	0-75%, non-condensing
IP Class	IP 20; IP 54 option available
Protection	
Short Circuit	Phase-to-phase, phase-to-ground
Brownout	Below 70 VDC
Over Voltage	Will shut down when power dissipation capacity is exceeded
Over Temperature	Motor 330°F (170°C), Drive 221°F (105°C)
I ² t	Error generated if peak current > 3 seconds
Safety Isolation	VDE0160
Standards	UL, cUL, CE (EMC), CE (LVD)
Internal Regeneration Capacities/Storable Energy	Compax3 S038 V4: 235 µF / 37Ws Compax3 S075 V4: 470 µF / 75Ws Compax3 S150 V4: 690 µF / 110Ws Compax3 S300 V4: 1,100 µF / 176Ws

* 12 additional I/O points available as an option
** Applicable only to models supporting this option



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com