



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

SIEMENS

Product data sheet

6ES7231-7PD22-0XA0


SIMATIC S7-200, T/C INPUT MOD. EM 231,
FOR S7-22X CPU ONLY, 4 AI,
+/-80 MV AND THERMOCOUPLE TYPE
J,K,S,T,R,E,N;
15BIT+VORZ.

Input current	
from load voltage L+ (without load), max.	60 mA
from backplane bus 5 V DC, max.	87 mA
Power losses	
Power loss, typ.	1.8 W
Analog inputs	
Number of analog inputs	4
permissible input voltage for voltage input (destruction limit), max.	30 V
Loop resistance cable	100 Ω
Updating time (all channels)	405 ms
Input ranges	
Voltage	Yes
Current	No
Thermocouple	Yes
Resistance thermometer	No

Resistance	No
Input ranges (rated values), voltages	
-80 mV to +80 mV	Yes
Input resistance (-80 mV to +80 mV)	1 M Ω
Input ranges (rated values), thermoelements	
Type E	Yes
Type J	Yes
Input resistance (type J)	1 M Ω
Type K	Yes
Input resistance (Type K)	1 M Ω
Type N	Yes
Input resistance (Type N)	1 M Ω
Type R	Yes
Input resistance (Type R)	1 M Ω
Type S	Yes
Input resistance (Type S)	1 M Ω
Type T	Yes
Input resistance (Type T)	1 M Ω
Cable length	
Cable length, shielded, max.	100 m ; to the sensor
Analog value creation	
Measurement principle	Sigma Delta
Integrations and conversion time/ resolution per channel	
Resolution with overrange (bit including sign), max.	16 bit ; Temperature 0.1 °C / 0.1 °F
Interference voltage suppression for interference frequency f1 in Hz	85 dB at 50 / 60 / 400 Hz
Displayable conversion value range	
bipolar signals	-27.648 to +27.648
Errors/accuracies	
cold connection point	+/-1.5 °C
Repeat accuracy in settled status at 25 °C (relative to input area)	+/- 0,05 %
Operational limit in overall temperature range	

Voltage, relative to output area	+/- 0,1 %
Interference voltage suppression for $f = n \times (f_l \pm 1\%)$, f_l = interference frequency	
common mode voltage, max.	120 V ; AC
Common mode interference, min.	120 dB ; At 120 V DC
Interrupts/diagnostics/status information	
Diagnostics indication LED	
External fault EXTF (red)	Yes
Group error SF (red)	Yes
Galvanic isolation	
Galvanic isolation analog inputs	
Galvanic isolation analog inputs	Yes
Permissible potential difference	
between inputs and MANA (UCM)	500 V AC
between M internally and the inputs	500 V AC
Connection method	
Plug-in I/O terminals	No
Dimensions	
Width	71.2 mm
Height	80 mm
Depth	62 mm
Weight	
Weight, approx.	210 g
Status	Dec 19, 2011



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com