

ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Visit our website - *Click HERE*

HIGH-SPEED SILICON DETECTOR - DET2-SI

DESCRIPTION


Thorlab's DET2-SI is a ready-to-use high-speed photo detector. The unit comes complete with a photo diode and internal 22.5V bias battery enclosed in a ruggedized aluminum housing. The DET2 uses a quartz window to extend the detector response into the UV. An 8-32 tapped hole is provided on the base of the housing to mount the detector directly to a Thorlabs positioning device (1/2" post holder, mounting plates, etc.). The DET series of detectors covers a spectral range of 190 to 1800nm with rise times below 1ns.


SPECIFICATIONS:

Detector: Silicon PIN
Spectral Response: 185-1100nm
Peak Wavelength: 920nm ± 50nm
Rise/Fall Time[1]: ≤1ns
Diode Capacitance: 1.8pF
NEP: 5×10^{-14} W / √Hz
Dark Current: 2.5 nA
Active Area: 1.0mm^2(round)
Linearity Limit: 1mW

Housing: Black Anodized Aluminum
Size: 0.75" x 1.3" x 2"
Output: BNC, DC-Coupled
Bias: 22.5V Battery
Mounting: 8-32 Tapped Hole
Diode Socket: TO-5, Anode Marked
Damage Threshold: 100mW CW
0.5 J / cm^2 (10 ns pulse)

Notes:
1. 50Ω Terminating Resistor





Thorlab's DET series are ideal for measuring both pulsed and CW light sources. Each DET includes a reverse-biased PIN photo diode, bias battery, and an ON/OFF switch packaged in a ruggedized housing. The BNC output signal is the direct photocurrent out of the photo diode anode and is a function of the incident light power and wavelength. The responsivity, $\Re(\lambda)$, can be read from Figure 1 to estimate the amount of the photocurrent to expect. Most users will wish to convert this photocurrent to a voltage for viewing on an oscilloscope or DVM. This is accomplished by adding an external load resistance, R_{LOAD}. The output voltage is derived as:

$$V_O = P * \Re(\lambda) * R_{LOAD.}$$

The bandwidth, f_{BW}, and the rise-time response, T_R, are determined from the diode capacitance, C_J, and the load resistance, R_{LOAD}:

$$f_{BW} = 1 / (2\pi * R_{LOAD} * C_J), \; T_R = 0.35 / f_{BW}$$

For maximum bandwidth, we recommend using a 50Ω coax cable with a 50Ω terminating resistor at the end of the coax. This will also minimize ringing by matching the coax with its characteristic impedance. If bandwidth is not important, you can increase the amount of voltage for a given input light by increasing the R_{LOAD}.

Also Available: Large Area Silicon detectors, Germanium Detectors (800 - 1800nm), and amplified detectors.

SALES: (201) 579-7227
FAX: (201) 383-8406
75 MILL ST. • P.O. BOX 366 • NEWTON, NJ 07860-1453
THORLABS INC

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP