

Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

 FAST SHIPPING AND DELIVERY TENS OF THOUSANDS OF **IN-STOCK ITEMS** EQUIPMENT DEMOS HUNDREDS OF **SUPPORTED** LEASING/MONTHLY

SECURE ASSET SOLUTIONS

at our full-service, in-house repair center Instra View REMOTE INSPECTION

Experienced engineers and technicians on staff

SERVICE CENTER REPAIRS

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com

WE BUY USED EQUIPMENT Sell your excess, underutilized, and idle used equipment

We also offer credit for buy-backs and trade-ins

www.artisantg.com/WeBuyEquipment >

LOOKING FOR MORE INFORMATION?

Visit us on the web at **www.artisantg.com** [→] for more

information on price quotations, drivers, technical

specifications, manuals, and documentation

199999/120000 Counts Dual Display Digital Multimeter





GW Instek GDM-8255A/8251A portable precision multimeters engage with 5 1/2 digits, dual-display, 0.012% high DC voltage accuracy and various advanced measuring function to make electrical relative signal measurement faster and easier. In addition, the standard RS-232 and USB device make the GDM-8255A/8251A an ideal tool and inexpensive solution for field service, development/maintenance, education and ATE system applications.

Various Measuring Functions

GDM-8255A/ 8251A provide 9 major measuring functions such as DCV/ACV, DCI/ACI, 2w/4w Resistance, Diode, Frequency, Continuity test and Temperature. The 0.012% DC voltage accuracy provides user the best measuring precision at the DC voltage applications.

In addition, there are several advanced measuring functions such as Max, Min, dB, dBm, REL/REL#, Hold, Compare and Math functions to enhance the serviceability of measuring results.

Combinational Dual Display

The GDM-8255A/ 8251A offer varieties of dual display combinations with main measurement function which allows the GDM-8255A/8251A to measure two properties of input signal. The dual display function can save customers measuring time when dealing with applications require multiple parameters simultaneously.

Standard Multiple Interfaces

GDM-8255A/ 8251A provide the standard multiple interfaces for PC connection: RS232C and USB device port. Unlike the common RS232 transfer speed, the GDM-8255A/8251A even raises the baud rate up to 115200 which is 12 times faster.

It makes the command or data flow faster and smoother.

In addition, the digital I/O terminal outputs the result of comparison measurements to control external devices for ATE applications. By providing an independent VCC for the terminal, the digital I/O outputs can also be used as power source for TTL or CMOS logics.

Convenient Remote Control & Data

For a convenient remote control and a long data capture, the GDM-8255A/8251A accompanies free software, DMM-Viewer. This software allows users to remotely control the GDM-8255A/8251A without entering extra commands. Besides, the software interface and even the measurement method resemble those of GDM-8255A/GDM-8251A front panel, thus guaranteeing safe operation and shortened training and program development time.

For data capturing through a PC, the software allows users to observe measuring result before saving it as a file for further study. In addition, the saved data can be reloaded for converting into a graph. With the DMM-Viewer PC software, the user operation of GDM-8255A/8251A can be much more effective.

Good Training tool for Education

The PC software, DMM-Viewer, is designed using a graphical user interface. With this kind design, users can easily operate as they work with unit. Besides, the DMM-Viewer could be operated as a training tool while it dose not communicate with GDM-8251A/8255A. It is beneficial for a class teaching of digital multimeter.

GDM-8255A (199999 Counts) GDM-8251A (120000 Counts)

FEATURES

- GDM-8255A: 199999 Counts Display
 GDM-8251A: 120000 Counts Display
- VFD , Two Colors Display
- Auto/Manual Ranging
- 2/4 Wire Resistance Measurement
- Temperature Measurement
- True RMS (AC, AC+DC)
- Selectable Measurement Rate
- Frequency Measurement
- Max./Min., REL, dBm, Compare, Math, Store, Recall, dB

APPLICATIONS

- Products maintenance & development
- Circuit repair & debug
- Auto test equipment
- Education experiment & training

GW INSTEK

Made to Measure

GDM-8255A/8251A

SPECIFICATIONS			
		GDM-8255A	GDM-8251A
FULL SCALE		199999 Counts	120000 Counts
SAMPLE RATE		Slow: 5 1/2 digits, 10 readings/second Medium: 4 1/2 digits, 30 readings/second Fast: 3 1/2 digits, 60 readings/second	
DC VOLTAGE	Range Accuracy Input Impedance	100mV, 1V, 10V, 100V, 1000V 5 ranges \pm (0.012% rdg + 5 digits) 10M Ω	
AC VOLTAGE True RMS	Range Accuracy Input Impedance	100mV, 1V, 10V, 100V, 750V 5 ranges 20Hz~45Hz :± (1% rdg + 100 digits) 45Hz ~ 10kHz :± (0.2% rdg + 100 digits) 10kHz ~ 30kHz :± (1% rdg + 100 digits) 30kHz~100kHz :± (3% rdg + 200 digits) 1.1MΩ in parallel with approx. 100pF	
DC CURRENT	Range Accuracy	10mA, 100mA, 1A, 10A 4 ranges 10mA , 100mA :± (0.05% rdg + 15 digits) 1A, 10A range :± (0.2% rdg + 5 digits)	
AC CURRENT True RMS	Range Accuracy	10mA, 100mA, 1A, 10A 4 ranges 10mA, 100mA range: 20Hz ~ 50Hz:± (1.5% rdg + 100 digits) 50Hz ~ 10kHz:± (0.5% rdg + 100 digits) 10kHz~20kHz:± (2% rdg + 200 digits) 1A, 10A range: 50Hz~10kHz:± (1% rdg + 100 digits)	
RESISTANCE	Range 2W Accuracy 4W Accuracy	$100\Omega\ , 1\mbox{$\mathbb{N}$}\Omega\ , 10\mbox{$\mathbb{N}$}\Omega\ , 10\mbox{$\mathbb{N}$}\Omega\$	
DIODE TEST	Open Circuit Voltage Approx.2.0V, Test Current 0.5mA		
FREQUENCY	10Hz~800kHz		
CONTINUITY BEEPER	$1\sim 1000\Omega$ Define by user		
TEMPERATURE	0° C ~ 300° C : J , K , T Type		
OTHER FUNCTIONS	Auto range / Manual, Math : MX + B/ % / 1/X Max, Min, dBm, dB, REL, Hold, Compare, Store, Recall		
DISPLAY	VFD, Two Colors Display		
INTERFACE	Digital I/O, USB Device, RS-232C		
DIMENSIONS & WEIGHT	265(W) x 107(H) x 350(D) mm, Approx. 2.6 kg		

Note : (*)USE "REL" Mode

Specifications subject to change without notice. DM-8255AGD2DH

ORDERING INFORMATION

GDM-8255A 199999 Counts Dual Display Digital Multimeter GDM-8251A 120000 Counts Dual Display Digital Multimeter

Quick start user manual x 1, Power cord x 1, Test lead GTL-117 x 1, CD x 1 (including complete user manual and PC software DMMViewer) Calibration key GDM-01 x 1 (Compatible with Fluke 5720A/5725A calibrators only)

OPTIONAL ACCESSORIES

USB Cable

GTL-108A 4W Type test lead

GTL-245

GTL-232 RS232C Cable, 9-pin Female to 9-pin, null Modem for Computer

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No. 7-1, Jhongsing Road, Tucheng City, Taipei County 236, Taiwan T +886-2-2268-0389 F +886-2-2268-0639 E-mail: marketing@goodwill.com.tw

China Subsidiary INSTEK ELECTRONIC (SHANGHAI) CO., LTD.

8F, of NO.2 Building, No.889 Yishan Road, Shanghai China T+86-21-6485-3399 F+86-21-5450-0789 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

GOOD WILL INSTRUMENT (M) SDN. BHD.
27, Persiaran Mahsuri 1/1, Sunway Tunas,
11900 Bayan Lepas, Penang, Malaysia.
T +604-6309988 F +604-6309989
E-mail: sales@goodwill.com.my

U.S.A. Subsidiary

INSTEK AMÉRICA CORP. 3661 Walnut Avenue Chino, CA 91710, U.S.A. T+1-909-5918358 F+1-909-5912280 E-mail: sales@instek.com Japan Subsidiary

INSTEK JAPAN CORPORATION

INSTEK JAPAN CORPORATION
4F, Prosper Bldg, 1-3-3 Iwamoto-Cho Chiyoda-Ku,
Tolyo 101-0032 Japan
T +81-3-5823-5656 F +81-3-5823-5655
E-mail: info@instek.co.jp Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.
Room No.805, Ace Hightech-City B/D 1Dong,
Mullae-Dong 3Ga 54-66, Yeongduengpo-Gu, Seoul, Korea
T +82-2-3439-2205 F +82-2-3439-2207
E-mail: sales@gwinstek.co.kr





Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

 FAST SHIPPING AND DELIVERY TENS OF THOUSANDS OF **IN-STOCK ITEMS** EQUIPMENT DEMOS HUNDREDS OF **SUPPORTED** LEASING/MONTHLY

SECURE ASSET SOLUTIONS

at our full-service, in-house repair center Instra View REMOTE INSPECTION

Experienced engineers and technicians on staff

SERVICE CENTER REPAIRS

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com

WE BUY USED EQUIPMENT Sell your excess, underutilized, and idle used equipment

We also offer credit for buy-backs and trade-ins

www.artisantg.com/WeBuyEquipment >

LOOKING FOR MORE INFORMATION?

Visit us on the web at **www.artisantg.com** [→] for more

information on price quotations, drivers, technical

specifications, manuals, and documentation