



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

Capacity: 8M, 16M, 32M, 64M, 128M, 256MB
Cycle/Access Time Random Read: 200/175 nsec Random Write: 175/50 nsec Block Transfer Read: 125/100 nsec Block Transfer Write: 100/45 nsec.
VME bus compatible per Rev. D A32/A24, D64/D32/D16/D8 (UAT)
Module selection on 1 megabyte boundaries with switch-selectable lower and upper limits
Block Transfer (BLT) within 256 bytes in the D32 mode, and 2KB in the D64 mode
Parity generation and checking on each byte
Lifetime Warranty on parts and labor

Providing up to 256MB of DRAM, the MM-6290D memory module also operates with a 64-bit word per VMEbus specification Rev. D.

The MM-6290D supports A32/A24, D64/D32/D16/D8. Besides the D64 block mode read and write accesses, the MM-6290D responds to A32 and A24 address modifiers for long word, word and byte transfers. Address modifier codes are programmed into a socketed IFL, which allows A32 or A24 masters to access memory when residing on the same bus. The memory module also supports long word, word, unaligned and byte read, write and read-modify-write accesses. Module selection is on 1MB boundaries, with switch-selectable upper and lower limits.

Each 8-bit byte has an associated bit for parity error detection. Parity status is stored and transmitted via BERR*; asserting BERR* inhibits the DTACK* signal during memory read operations.

Ensuring module reliability, complete inspection and testing is performed while running memory diagnostics. In addition, all units undergo 48 hours of burn-in while running diagnostics. Furthermore, Micro Memory backs up board reliability with a **Lifetime Warranty**.

MM-6290D Specifications

- Capacity** : 8M, 16M, 32M, 64M; 128M, 256MB
- Cycle/Access Time (nsec.)** :
Random Read: 200/175
Write: 175/50
Block Transfer Read: 125/100
Write: 100/45
- Address** : A32/A24 address bits
- Data In/Data Out** : D64/D32/D16/D8
- Sequential Access** : Block transfer (BLT) within 256 bytes in the D32 mode, and 2KB in the D64 mode
- Address Modifiers** : 6-bit, decoded by socketed IFL with the following codes:
A24: 39, 3A, 3D and 3E
A32: 09, 0A, 0D and 0E
A24 with BLT: 38, 3F
A32 with BLT: 0B, 0F
A24/D64 with BLT: 38, 3C
A32/D64 with BLT: 08, 0C
- Parity** : Byte-wide parity generation and checking. Parity output stored and transmitted via BERR*
- Interface** : VMEbus-compatible per Rev. D
Modes of Operation : Read, write, read-modify-write, long word, word, unaligned, block transfer
Refresh



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com