



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com



SERVOSTAR™ CD SynqNet™

Description

The **CD SynqNet** is a SynqNet™ servo drive based on the field-proven range of SERVOSTAR™ CD drives. The power stage is the same as that of the CD, while the control stage is a dedicated SynqNet™ design. The **CD SynqNet** is designed as a Torque drive, with torque command being provided at high servo update rates from the SynqNet™ controller. Extensive I/O support is provided, with both function-specific inputs, such as Limit Switches, Home and Brake, and numerous general purpose I/Os. The **CD SynqNet** provides divide-by-N capability, enabling it to be programmed to generate an output pulse every N counts of the drive's encoder counter register.

SynqNet™

SynqNet™ (<http://www.synqnet.org>) is a high performance, all-digital synchronous network designed for multi-axis motion control applications. The physical layer of SynqNet™ is based on IEEE 802.3 standards for 100BASE-TX, the physical layer of Ethernet, while the data link and application layers of SynqNet™ are specifically designed for motion control applications. The 100BASE-TX media system is based on specifications published in the ANSI TP-PMD physical media standard. The 100BASE-TX system operates over two pairs of wires, one pair for 'receive' data signals and the other pair for 'transmit' data signals.



Power Ratings

| Identification | Output Continuous Current (RMS per phase) | Output Peak Current (RMS per phase) | AC Line Input Voltage (VAC L-L nominal) | DC Bus Voltage (nominal) |
|----------------|---|-------------------------------------|---|--------------------------|
| Lx 03 5x5 | 3 Amps | 9 Amps (0.5 Sec) | 115 - 1phase | 160VDC |
| | | | 230 - 1phase | 320VDC |
| | | | 3 phase, 110V per phase | 160VDC |
| Lx 06 5x5 | 6 Amps | 18 Amps (0.5 Sec) | 115 - 1phase | 160VDC |
| | | | 230 - 1 phase | 320VDC |
| | | | 3 phase, 110V per phase | 160VDC |
| Lx 10 5x5 | 10 Amps | 20 Amps (2 sec) | 3 phase, 110V per phase | 160VDC |
| Lx 06 6x5 | 6 Amps | 12 Amps (2 sec) | 3 phase, 380V | 540VDC |
| | | | 3 phase, 480V | 680VDC |
| Lx 10 6x5 | 10 Amps | 18 Amp. (0.5 sec) | 3 phase, 380V | 540VDC |
| | | | 3 phase, 480V | 680VDC |





SERVOSTAR™ CD SynqNet™

Features

Feedback

- Incremental Encoder and Heidenhain EnDat® Sine Encoder. Other options include support for Resolver and Stegmann Hiperface®.
- Auxiliary encoder feedback, used for Dual Loop or Master / Slave operation.
- Commutation initialization with minimal motion.

SynqNet™

- Network bandwidth for torque updates up to 16kHz
- Remote diagnostics of motor drive performance
- Remote drive configuration and setup
- Real-time diagnostic programming/ data collection over SynqNet
- Support for multiple feedback and dual-loop servo control
- Automatic network configuration and integrity check
- Cabling over 100 Meters between each node
- Electrical isolation for robust noise immunity

Servo Control

- Fully digital current loop
- Advanced patented sinewave commutation technology provides smooth, precise low-speed control as well as high-speed performance
- Accurate torque control due to precision balanced current loops with closed loop sensors
- Patented torque angle control enhances motor performance

I/O

- 5V through 24V operation
- Dedicated Hardware enable, Positive and Negative Limit and Home inputs
- Brake Output via dry contact relay
- Eight general purpose opto-isolated inputs
- Four general purpose opto-isolated outputs
- Two bi-directional RS422 I/Os
- Fast Divide-by-N pulse output
- Two analog inputs

Robust Power Stage Options

- Self-protecting power modules
- Full protection against short circuit, over-voltage, under-voltage, motor and drive over-temperature, over-current and feedback loss
- Flexible current foldback protection

Ordering Information

Please note: Some models are not standard, but are available upon request

300V Option:

Feedback Options
 E - Encoder
 R - Resolver
 B - Sine Encoder

LE 06 565

Logic Power Source
 5 - Internal logic power
 6 - External logic power

Current Rating
 03 - 3Amp continous; 9Amp peak
 06 - 6Amp continous; 18Amp peak
 10 - 10Amp continous; 20Amp peak

600V Option:

LE 06 665

Current Rating
 06 - 6Amp continous; 12Amp peak
 10 - 10Amp continous; 18Amp peak





Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com