



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

MPV990 - 4 Channel Anti-Aliasing Filter

The MPV990 is a four-channel anti-aliasing (low-pass) filter board mechanically compatible with the VMEbus. Anti-aliasing filters are frequently required in high accuracy data systems in order to reduce the distortion effect of out of band frequencies mixing with the sampling frequency to produce in-band frequency components. The MPV990 incorporates 4 independent anti-aliasing filter circuits. The inputs are connected via 4 BNC connectors and the outputs via a 37 way 'D' type connector. The analog input section features a programmable gain instrumentation amplifier, the gain of which can be set to any value between 0.1 and 10,000. The filter section features a low pass filter with a definable cut-off frequency in the range 2Hz to 20kHz. The roll-off is 100dB/octave with a minimum stop band attenuation of 60dB. The output section is compatible with Pentland Systems' existing range of VMEbus analog input boards, such as the MPV908 series. For applications in which increased output drive capability from the filter is required, a user selected amplifier may be added.

Features

- Four channels with independent 3-stage low pass filter circuits
- Selectable cut-off frequencies
- Incorporates precision input instrumentation amplifiers
- Double Eurocard format suitable for use in VMEbus systems
- +5V supply from VMEbus P1 connector
- Short circuit protection on outputs
- Provision for customer specific output amplifiers

Specification (at 25°C)

Input Amplifier

- Input channels: 4
- Gain ranges: 0.1 to 10,000 (resistor programmable)
- Input voltage: \pm V (max) single-ended or differential
- Input impedance: >1M Ohm
- Filter:-
 - Frequency cut-off range 2Hz to 20kHz
 - Cut-off frequency (Fc) \pm of chosen value
 - Stopband frequency (Fs) 1.75Fc
 - Gain Error 0 \pm 25dB
 - Passband ripple:-
 - 2Hz<10kHz. <0.15dB
 - 10kHz<20kHz <0.5dB
 - Stopband attenuation: \geq 60dB
 - Roll-off 100dB/octave
- Output (no amplifier):-
 - Output current +4mA (max with resistive load)
 - Output impedance <5 Ohms
- Signal/noise ratio: >75dB
- Total Harmonic Distortion: <0.01%
- Operating temperature: 0°C to +60°C
- Power Requirement: \pm \pm @ 1.5A (supplied from P1 connector)
- Input connectors: 4 x BNC sockets
- Output connector: 37 pin 'D' type

Ordering Information

MPV990: Anti-Aliasing Board

Navigation: to [Product Summary](#) or [Pentland Homepage](#)



E-mail requests for further information to: ja@pentland.co.uk
Copyright © 1995 Pentland Systems Ltd.



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com