Motorola TM-PIMC-0101 Transition Module



In Stock

New From Surplus Stock

Open Web Page

https://www.artisantg.com/62906-1

All trademarks, brandnames, and brands appearing herein are the property of their respective owners.

- Critical and expedited services
- In stock / Ready-to-ship

- We buy your excess, underutilized, and idle equipment
- · Full-service, independent repair center

ARTISAN'
TECHNOLOGY CROUP

Your **definitive** source for quality pre-owned equipment.


Artisan Technology Group

(217) 352-9330 | sales@artisantg.com | artisantg.com

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

Board Level Products

TM-PIMC-0001 TRANSITION MODULE/PIM CARRIER




Advantages

The TM-PIMC-0001 transition module provides rear I/O for the MCPN750 series of CompactPCI single-board computers, supplying four COM ports and one 10/100BaseTx Ethernet port. It is also equipped with a CompactFlash™ socket for user-supplied IDE flash modules.

This transition module also functions as a PMC Interface Module (PIM) carrier, supporting the flexible PIM scheme for PMC rear I/O. Two PIM sites are provided that interface with each of the PMC sites on the MCPN750. The TM-PIMC-0001 module is 6U high, 80mm deep, and IEEE 1101.11 compliant. It is also hot-swappable when used with the MCPN750.

Visit our website for additional details about PIM.





CompactPCI Backplane

Specifications

TM-PIMC Transition Module/PIM Carrier

Dimensions

Height: 233.4 mm (9.2 in.) Depth: 80.0 mm (3.1 in.) Front Panel Height: 261.8 mm (10.3 in.) Width: 19.8 mm (0.8 in.)

PIM Card Slot

+3.3V, +5V, +12V, -12V

Module Types: Two single-wide or one double-wide

I/O Connectors

Asynchronous Serial Ports: Two RJ-45 labeled as COM1 and COM2;

Two 10-pin headers as COM3 and COM4

Ethernet:

IDE Flash: One standard 50-pin CompactFlash socket

Note: Jn0 PIM connectors incorporate other MCPN750 I/O for future host interface modules.

Hot Swap

Can be removed from active system after MCPN750 is removed.

Power LED on front panel indicates power status on MCPN750 and transition module.

Power Requirements

Not including CompactFlash or PIMs

+5V: 200 mA typical, 400 mA maximum

+3.3V, +12V and -12V are not used by the transition module, but may be used by

PIMs

Year 2000 Readiness

This product is year 2000 ready as defined by Motorola Computer Group. For additional information, reference http://www.mcg.mot.com/year2000.

Warranty

Five-year return-to-factory warranty

Environmental

(verification pending)

Storage/Transit Operating Temperature: 0° C to $+55^{\circ}$ C -40° C to +65° C forced air cooling Humidity (NC): 10% to 80% 10% to 90% Altitude: 5,000 m 15,000 m 8 G RMS, 2 GRMS. Vibration: 20-2000 Hz random 20-2000 Hz random

Safety

Canada:

All printed wiring boards (PWBs) are manufactured with a flammability rating of 94V-0 by UL recognized manufacturers.

Electromagnetic Compatibility (EMC)

Intended for use in systems meeting the following regulations:

ILS. FCC Part 15, Subpart B, Class A (non-residential) ICES-003, Class A (non-residential)

Motorola products are tested in a representative system to the following standards

(verification pending):

CE Mark per European EMC Directive 89/336/EEC with Amendments; Emissions: EN55022 Class B; Immunity: EN50082-1

Demonstrated MTBF

(based on sample testing in accelerated stress environment)

Mean/95% Confidence: Target 100,000 hours, verification pending

Ordering Information

Part Number Description

MCPN750 transition module/PIM carrier: RJ-45 Ethernet TM-PIMC-0001

connector, two RJ-45 async serial port connectors, two headers for async serial ports, one CompactFlash socket, two

PIM slots

Related Product

MCPN750-xxxx CompactPCI non-system slot CPU module PIM-0100 PIM E1 interface card for MPMC860

For more information, visit our World Wide Web site at http://www.mcg.mot.com To call us dial 1-800-759-1107 in the U.S. and 512-434-1526 outside the U.S. Corporate headquarters address: Motorola Computer Group, 2900 S. Diablo Way, Tempe, AZ 85282

Copyright 1999 Motorola, Inc. Data Sheet: TMPIM-D1 8/99



Motorola and the Motorola logo are registered trademarks of Motorola, Inc. All other names, products, and services mentioned may be trademarks or registered trademarks of their respective holders.

This data sheet identifies products, their specifications, and their characteristics, which may be suitable for certain applications. It does not constitute an offer to sell or a commitment of present or future availability, and should not be relied upon to state the terms and conditions, including warranties and disclaimers thereof, on which Motorola may sell products. A prospective buyer should exercise its own independent judgement to confirm the suitability of the products for particular applications. Motorola reserves the right to make changes, without notice, to any products or information herein which will, in its sole discretion, improve reliability, function, or design. Motorola does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under its patent or other intellectual property rights or under others. This disclaimer extends to any prospective buyer, and it includes Motorola's licensee, licensee's transferees, and licensee's customers and users. Availability of some of the products and services described herein may be restricted in some locations

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at artisantg.com for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today? (217) 352-9330 | sales@artisantg.com | artisantg.com

