



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

Search: [United States Home](#) > ... > [3499 Switch Family](#) > [Multiplexer Relays](#) >[Talk with an Expert](#)[Feedback](#)

N2260A 2-Wire, 40-Channel Multiplexer Module

General Specifications

Relays : Armature latching relay

Thermal Offset: <math> < 3 \mu V </math>

Relay Life (mechanical): 10^8

Maximum Scan Rate: 80 Chan./ sec

Input Characteristics

Maximum Current: 1A

Maximum Voltage: 200V

Maximum Power: 60W or 62.5VA

Initial Closed Channel Resistance: <math> < 1 \text{ Ohm} </math>

DC Isolation (<math> < 40^\circ \text{C}</math>, 60% RH)

Open Channel, Channel-Channel: $> 10^{10} \text{ Ohm}$ HI-LO: $> 10^{10} \text{ Ohm}$ Channel-Chassis: $> 10^{10} \text{ Ohm}$

AC Isolation

Capacitance (with 1 channel closed):

Open Channel, Channel-Channel: <math> < 7 \text{ pF} </math>

HI-LO: <math> < 75 \text{ pF} </math>

Channel-Chassis: <math> < 150 \text{ pF} </math>

Insertion Loss (with 50 Ohm termination):

100kHz: <math> < 0.10 \text{ dB} </math>

1MHz: <math> < 0.20 \text{ dB} </math>

10MHz: <math> < 1.50 \text{ dB} </math>

Crosstalk (with 50 Ohm termination):

100kHz: <math> < -70 \text{ dB} </math>

1MHz: <math> < -50 \text{ dB} </math>

10MHz: <math> < -30 \text{ dB} </math>

Accessories

N2290A Screw Terminal block

N2296A Crimp & insert terminal block

N2297A DIN96 -to-Twin-D50 cable

N2299A DIN96 -to-Quad-D25 cable

Note: All voltage and current is in DC or AC RMS if not specified



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com