Artisan Technology Group

Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS
Experienced engineers and technicians on staff at our full-service, in-house repair center

InstraView℠ REMOTE INSPECTION
Remotely inspect equipment before purchasing with our interactive website at ***www.instraview.com*** ↗

WE BUY USED EQUIPMENT
Sell your excess, underutilized, and idle used equipment
We also offer credit for buy-backs and trade-ins
www.artisantg.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?
Visit us on the web at ***www.artisantg.com*** ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com

TRIPLE OUTPUT DIGITAL PWR SPLY

Model 1760 **(The 1760 has been discontinued.)**

Discontinued Instrument Trade-in Program

The 1760 was DISCONTINUED on August 1st, 2002 and was replaced by the 1760A

Model 1760A

Two 0-30 VDC, 2 A sections capable of independent, series or parallel operation One 4-6.5 VDC, 5 A section Switchable series/parallel operation

- 30 V sections Adjustable current limit controls
- 30 V sections Two 3 digit LED displays
- one reads volts or amps of "B" supply
- one reads volts or amps of "A" supply or 4V-6.5V supply Unique variable tracking, B track A at 5% to 100%

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Specifications	**Model 1760**
Output Voltage	0-30V (A&B)
	4-6.5 V (C)
Output Current	0-2A (A&B)
	0-5A (C)
Constant Voltage Operation	
Voltage Regulation	
Line (120 VAC +- 10%)	<= 10mV
Load	<= 10mV
Recovery Time	100ms
Ripple & Noise	<= 1mVrms
Weight	21 lbs. (9.5 kg)

Two Year Warranty

Accessories

SUPPLIED: Instruction Manual, Spare Fuse

OPTIONAL (for all models): TL-SA Hook up cables.

Model: TLPS

Power Supply Test Leads Set

New accessory kit combines safety and functionality. The highly flexible silicone jacked test leads feature a retractile sheathed banana plug to connect to the Power Supply and a fixed sheath banana plug to protect the user. A complete selection of accessories are included -

- large alligator clips, standard alligator clips, spade lug and banana plug adapters -
- to make your connects easier. For Power Supplies with remote sensing capability, a ready-made lead set also included.

Temperature Coefficient	<= 300 ppm^0 C
Constant Current Operation	
Adjustable Current Range	5% to 100% (A&B)
Current Regulation	
Line (120 VAC +- 10%)	<= 0.2% + 3mA
Load	<= 0.2% + 3mA
Current Ripple	<= 3 mA
Metering	
Display	2 three digit LEDs
Voltmeter Range	0-99.9 V
Voltmeter Accuracy	+-(0.5% rdg + 2 digits)
Ampmeter Range	0-9.99 A
Ampmeter Accuracy	+-(0.5% rdg + 2 digits)
Overload Protection	Current limiting, Reverse polarity, overvoltage, Short circuit
Power Requirements	108 - 132 VAC 60 Hz, 120/220/230/240/VAC, +- 10%, 50/60 Hz version available
Power Consumption	350W
Operating Temperature	-15 ^{0} to 70 ^{0} C <= 85% R.H.
Storage Temperature	-15 ^{0} to 70 ^{0} C <= 85% R.H.
Dimensions (HxWxD)	5.7''x10.5''x15'' (145x267x381 mm)

Artisan Technology Group

Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS
Experienced engineers and technicians on staff at our full-service, in-house repair center

InstraView℠ REMOTE INSPECTION
Remotely inspect equipment before purchasing with our interactive website at ***www.instraview.com*** ↗

WE BUY USED EQUIPMENT
Sell your excess, underutilized, and idle used equipment
We also offer credit for buy-backs and trade-ins
www.artisantg.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?
Visit us on the web at ***www.artisantg.com*** ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com