ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *OMRON / Delta Tau ACC-E1* at our website: ***Click HERE***

Backplane Boards

Part	Core Part Number	Description[1]	Minimum Rack Size (slots)[2]	Backplane Data Slots *Provided*	+5V Current Required[3]	Notes
ACC-U4	603462	4+1-slot backplane	7	4	1.00A	
ACC-U6	603403	6+1-slot backplane	9	6	1.00A	
ACC-U8	603463	8+1-slot backplane	11	8	1.00A	Cannot fit in ACC-P1 rack with 3-slot power supply
ACC-U10	603464	10+1-slot backplane	13	10	1.00A	Cannot fit in ACC-P1 rack with 3-slot power supply
ACC-U12	603465	12+1-slot backplane	15	12	1.00A	Cannot fit in ACC-P1 rack with 3-slot power supply
ACC-U14	603466	14+1-slot backplane	17	14	1.00A	Cannot fit in ACC-P1 or P2 rack with 3-slot power supply
ACC-U16	603471	16+1-slot backplane	19	16	1.00A	Cannot fit in ACC-P1 or P2 rack with 3-slot power supply
ACC-U18	603491	18+1-slot backplane	21	18	1.00A	Cannot fit in ACC-P1 or P2 rack with 3-slot power supply

Notes:

1. "n+1-slot" means "n" data slots for inter-board communications, and 1 power slot for direct installation of a power supply
2. Assumes a 3-slot power supply is installed in the power slot (rightmost connector), extending 2 slots past right end of backplane
3. Current draw of backplane boards is due to bus termination resistors

Power Supplies

Part	Core Part Number	Description	Rack Slots Required	+5V Current *Provided*	+15V Current *Provided*[2]	-15V Current *Provided*[3]	AC Power (MAX)
ACC-E1	603269	AC-input power supply	3	14.0A	1.5A	1.5A	3.3A rms
ACC-F1	603909	DC-input power supply	3	14.0A	1.5A	1.5A	-

Notes:

1. Must be installed in the single power slot in the ACC-U*n* backplane board
2. Power may be provided in the range of +12V to +15V nominal (+11.5V to +16.5V actual)
3. Power may be provided in the range of -12V to -15V nominal (-11.5V to -16.5V actual). 0.12A of this quantity is required for the power supply's own cooling fan and is not available for other boards.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP