ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Instek GDM-8135* at our website: ***Click HERE***



FEATURES

* 7 Functions AC/ DC Voltage, AC/DC Current, Resistance, Diode Test and Continuity Beeper
* Large 0.5" Red LED Display
* High Voltage 1200V and 20A Current Range
* All Range with Protection Circuit
* 0.1% DCV Accuracy
* Auto Zero Circuit

GDM-8135 (3 1/2 Digits)

SPECIFICATIONS

DC VOLTAGE

Range	200mV, 2V, 20V, 200V, 1200V 5 ranges
Accuracy	±(0.1% rdg + 1 digit)
Input Impedance	10MΩ

AC VOLTAGE

Range	200mV, 2V, 20V, 200V, 1000V 5 ranges
Accuracy	200mV ~ 20V 3 ranges : 40Hz ~ 1kHz±(0.5% rdg + 1 digit) 1kHz ~ 10kHz±(1% rdg + 1 digit) 10kHz ~ 20kHz±(2% rdg + 1 digit) 20kHz ~ 40kHz±(5% rdg + 1 digit) 200V range : 40Hz ~ 1kHz±(0.5% rdg + 1 digit) 1kHz ~ 10kHz ±(1% rdg + 1 digit) 1000V range : 40Hz ~ 1kHz±(0.5% rdg + 1 digit)
Input Impedance	10MΩ

DC CURRENT

Range	200μA, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	200μA ~ 200mA 4 ranges : ±(0.2% rdg + 1 digit) 2A ~ 20A 2 ranges : ±(0.5% rdg + 1 digit)

AC CURRENT

Range	200μA, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	200μA ~ 200mA 4 ranges 40Hz ~ 1kHz±(0.5% rdg + 1 digit) 1kHz ~ 10kHz±(1% rdg + 1 digit) 10kHz ~ 20kHz±(2% rdg + 1 digit) 2A ~ 20A 2 ranges, 40Hz ~ 2kHz±(1% rdg + 2 digits)

RESISTANCE

Range	200Ω, 2k, 20k, 200kΩ, 2MΩ, 20MΩ 6 ranges.
Accuracy	200Ω ~ 2MΩ 5ranges : ±(0.2% rdg + 1 digit) 20MΩ range :±(0.5% rdg + 1 digit)

DIODE TEST

Test Current	Max. 1 mA
Open Voltage	Max. 13V

CONTINUITY BEEPER

Description	Buzzer sounds if conductance less than 10Ω
Test Current	Max. 1 mA
Open Voltage	Max. 13V

DISPLAY
0.5" LED display

POWER SOURCE
AC 100V/120V/220V/230V±10%, 50/60Hz

ACCESSORIES
Instruction manual x 1, Power cord x 1, Test lead GTL-107A x 1

DIMENSIONS & WEIGHT
245(W) x 95(H) x 280(D) mm, Approx. 2kg

ORDERING INFORMATION

GDM-8135 3 1/2 Digits Digital Multimeter

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP