ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Mini-Circuits SHP-200* at our website: ***Click HERE***

Coaxial

High Pass Filter

SHP-200+

50Ω 185 to 3000 MHz



CASE STYLE: FF99

Connectors	Model
SMA	SHP-200+

+RoHS Compliant

The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

Maximum Ratings

Operating Temperature	-55°C to 100°C
Storage Temperature	-55°C to 100°C
RF Power Input	0.5W max.

Permanent damage may occur if any of these limits are exceeded.

Features

- rugged shielded case
- other standard and custom SHP models available with wide selection of fco


Applications

- lab use
- transmitters/receivers
- radio communications

High Pass Filter Electrical Specifications

STOPBAND (MHz)		fco (MHz) Nom.	PASSBAND (MHz)	VSWR (:1)	
(loss > 40 dB)	(loss > 20 dB)	(loss 3 dB)	(loss <1 dB)	Stopband Typ.	Passband Typ.
DC-90	90-116	164	185-3000	17	1.6


Outline Drawing




Outline Dimensions (inch / mm)

B	D	E	wt
.67	1.98	.312	grams
17.02	50.29	7.92	42.0

typical frequency response




electrical schematic




Typical Performance Data

Frequency (MHz)	Insertion Loss (dB) x̄	σ	Return Loss (dB)	Frequency (MHz)	Group Delay (nsec)
10.00	71.62	2.72	0.06	75.00	2.93
50.00	87.09	4.73	0.13	90.00	2.71
70.00	73.00	0.87	0.10	95.00	2.71
75.00	68.35	1.20	0.09	100.00	3.03
90.00	55.00	0.48	0.11	104.00	3.20
95.00	50.91	0.53	0.13	108.00	3.21
100.00	47.05	0.54	0.14	112.00	3.36
108.00	41.12	0.52	0.19	116.00	3.60
116.00	35.41	0.54	0.25	120.00	3.87
120.00	32.62	0.56	0.28	140.00	6.03
140.00	18.90	0.65	0.52	150.00	8.41
160.00	5.88	0.58	2.57	160.00	11.87
170.00	1.99	0.26	7.68	170.00	12.82
180.00	0.82	0.06	18.19	180.00	10.02
185.00	0.68	0.03	22.90	185.00	8.64
200.00	0.55	0.03	21.35	200.00	6.12
300.00	0.28	0.02	30.67	300.00	2.20
400.00	0.31	0.01	17.13	400.00	1.28
500.00	0.35	0.01	14.65	500.00	0.90
600.00	0.34	0.01	14.54	600.00	0.70
700.00	0.32	0.01	15.30	700.00	0.59
800.00	0.29	0.01	16.38	800.00	0.52
900.00	0.27	0.01	17.76	900.00	0.47
1000.00	0.25	0.01	19.27	1000.00	0.44
1100.00	0.25	0.01	20.89	1100.00	0.41
1200.00	0.25	0.01	22.44	1200.00	0.39
1300.00	0.26	0.01	24.09	1300.00	0.38
1400.00	0.25	0.01	25.43	1400.00	0.36
2000.00	0.31	0.01	27.03	2000.00	0.33
3000.00	0.51	0.02	17.33	3000.00	0.32


INSERTION LOSS



RETURN LOSS



GROUP DELAY



Notes

A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP