ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Nallatech BenADDA-Pro* at our website: ***Click HERE***

Product Brief (Preliminary)

The BenADDA-PRO is an addition to the popular BenADDA product range, providing high-speed analogue data processing combined with the impressive of features the DIME-II product family module with support for PCI, cPCI, VME, & PC/104+ form factors

NALLATECH

DIME-II™

BenADDA-PRO

Processing Module



Key Features

- Single width DIME-II module
- Xilinx® Virtex-II Pro® User FPGA (P50)
- Up to 53k logic cells of programmable logic per module
- Up to 4X Block RAM and embedded multipliers compared to equivalent Virtex®-II FPGAs
- 400+ Module-to-Motherboard DIME-II User I/O
- Multiple clocking options – 4 internal clocks, external clock input
- 8Mbytes ZBT® SRAM – arranged in 2 independent banks
- On-board PowerPC processor support
- Supported in Nallatech DIMEtalk™ and FUSE™
- Includes Nallatech ZBT SRAM interface IP core

User Benefits

- ✓ Virtex-II PRO FPGA
- ✓ 2 x 14-bit ADC channels supporting maximum sample rate of 105MSPS
- ✓ 2 x 14-bit DAC channels supporting maximum sample rate of 160MSPS
- ✓ Provides scalability – deploy multiple modules on a single DIME-II motherboard
- ✓ Based on the proven DIME-II standard
- ✓ Supported by FUSE™ & DIMEtalk™ for easy FPGA design implementation

Overview

The BenADDA-PRO DIME-II module is an addition to the BenADDA product family providing high-speed analogue data processing capabilities with a Xilinx® Virtex-II Pro® FPGA.

Dual ADC Channels

The BenADDA-PRO is equipped with two AD6645 ADC devices from Analog Devices. The sampled data can be processed directly by the on-board FPGA.

Dual DAC Channels


The BenADDA-PRO offers flexible high-speed, high-resolution data conversion for both baseband and direct IF applications using two AD9772 devices from Analog Devices, which directly controlled by the on-board FPGA.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Product Brief

Do you require ordering information or have product questions? Our worldwide sales teams and technical specialists are ready to assist you. Please contact us via one of the methods detailed below…

Functional Diagram



Bus Support

Bus	2VP50 FPGA
Adjacent In	64-bits
Adjacent Out	64-bits
Local Bus	64-bits
GPIO	21-bits
CommLink 0	12-bits
CommLink 1	12-bits
CommLink 2	12-bits
CommLink 3	12-bits
CommLink 4	12-bits
CommLink 5	12-bits
CommLink 6	12-bits
CommLink 7	12-bits

NOTES

All DIME-II buses are bi-directional. Where a bus uses a naming convention which indicates it is an in or out bus, this is a conceptual name. Functionally, the bus can be used for either input to the module, output from the module, or a combination of both.

This information should be used in conjunction with the equivalent on other DIME-II products to establish the I/O compatibility between multiple products being used together.

The symbol 'x' indicates that a bus is not supported by an FPGA version.

Specifications

- XC2VP50 FF1152 FPGA
- 2 x 14-bit ADC channels up to 105MSPS sampling
- 2 x 14-bit 160MSPS DAC channels
- 8MB ZBT SRAM (2 independent banks of 4MB)
- Status LEDs
- Secondary XC2V80 FPGA for clocking control
- Up to 6 different methods for clocking ADCs/DACs
  - 105MHz on-board crystal oscillator
  - External clock input via front panel connector
  - 3 program oscillators
- Various analogue / output build configurations
  - contact Nallatech for full list of supported build configurations
- 3rd order input filter – f_C, cut-off around Nyquist at 57.9MHz

Deliverables

- BenADDA PRO Module
- Software and Documentation CD
- 90 days Product Maintenance (software updates, technical support, support lounge access)

Order Codes

Main order code - BenADDA-PRO-XX-Y

Option Codes

XX: Analogue I/O build options
01 - Op_Amp (DC) Coupled Outputs + Single-ended Analogue Inputs
02 - Op_Amp (DC) Coupled Outputs + Differential Analogue Inputs
03 - Directly Coupled Outputs + Single-ended ADC Inputs
04 - Directly Coupled Outputs + Differential Analogue Inputs
Y: FPGA speed grade options: -5; -6;

Contact Details

Europe & Asia Pacific
Nallatech Ltd
Boolean House
One Napier Park
Cumbernauld
Glasgow G68 0BH
UK

Phone: +44 (0)1236 789500
Fax: +44 (0)1236 789599
Email: contact@nallatech.com

North America
Nallatech Inc
1010 Liberty Road
Suite 103
Eldersburg
MD. 21784
USA

Phone: (407) 384 9255
Fax: (407) 384 8555
Email: contact@nallatech.com

Nallatech Inc
Suite 470
226 Airport Parkway
San Jose
CA 95110
USA

Phone : (408) 467 5075
Fax : (408) 436 5402
Email: contact@nallatech.com

NALLATECH

Copyright © 2004, Nallatech, All rights reserved. BenDATA 2, Nallatech, the Nallatech logo, "The High Performance FPGA Systems Company", DIMEtalk, DIMEscript, DIME, DIME-II and FUSE are trademarks of Nallatech Ltd. Windows is a registered trademark of Microsoft Corporation in the United States and other countries. All other product names, trademarks and registered trademarks are property of their respective holders. Nallatech believes the information contained in this document to be correct at the time of publication and cannot accept responsibility for any loss or damage resulting from the use of this information. All information is subject to change at any time, without notice.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP