Artisan Technology Group

Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS
Experienced engineers and technicians on staff at our full-service, in-house repair center

InstraView℠ REMOTE INSPECTION
Remotely inspect equipment before purchasing with our interactive website at ***www.instraview.com*** ↗

WE BUY USED EQUIPMENT
Sell your excess, underutilized, and idle used equipment
We also offer credit for buy-backs and trade-ins
www.artisantg.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?
Visit us on the web at ***www.artisantg.com*** ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com

Serial Installation Guide

Contents

Supported Operating Systems 1
PCI/PCI Express/PXI Serial Installation 2
USB Serial Installation 2
ENET Serial Installation 3
ExpressCard Serial Installation 3
PCMCIA Serial Installation 4

Supported Operating Systems

The following table lists the operating systems each hardware interface supports.

Interface Type	Windows 7 32	Windows 7 64	Windows Vista 32	Windows Vista 64	Windows 2000/XP
PCI-843*x*	✓	✓	✓	✓	✓
PCI-232/485	✓	✓	✓	✓	✓
NI PCIe-843*x*	✓	✓	✓	✓	✓
PXI-843*x*	✓	✓	✓	✓	✓
PXI-842*x*	✓	✓	✓	✓	✓
USB	✓	✓	✓	✓	✓
ENET	✓	✓[1]	✓	✓[1]	✓
ExpressCard	✓	✓	✓	✓	✓
PCMCIA			✓[2]		✓[2]

[1] NI-VISA support only.
[2] Supported by NI-Serial versions 3.5.0 and earlier.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

PCI/PCI Express/PXI Serial Installation

Refer to the *Serial Hardware and Software Help* (available on the CD) for more information about troubleshooting problems, configuring the hardware and software, programming requirements, and more.

1. Log on as Administrator or as a user with administrator privileges.
2. Insert the *NI-Serial Software for Windows* CD.
3. Click **Install Software** and follow the onscreen instructions.
4. Power down the computer, install your serial PCI, PCI Express, or PXI hardware, and power on the computer.
5. After Windows detects your hardware, select **Start»Programs» National Instruments»NI-Serial»Troubleshooting Wizard**.
6. The Troubleshooting Wizard window appears. This application verifies the software and hardware installation and sequentially tests each NI serial port.
7. Connect the cables.

USB Serial Installation

Caution Electrostatic Discharge (ESD) of 2000 V or greater during operation can disrupt the USB-485 device. Build up of static charges on the human body or nearby equipment can easily meet or exceed this level of voltage, so you must use standard ESD precautions when operating this hardware.

Refer to the *Serial Hardware and Software Help* (available on the CD) for more information about troubleshooting problems, configuring the hardware and software, programming requirements, and more.

1. Log on as Administrator or as a user with administrator privileges.
2. Insert the *NI-Serial Software for Windows* CD.
3. Click **Install Software** and follow the onscreen instructions.
4. Restart the computer.
5. If you are installing a USB-485/4, connect the external power supply.
6. Connect the USB cable from the USB hardware to an available USB port on your computer or USB hub.
7. Select **Start»Programs»National Instruments»NI-Serial» Troubleshooting Wizard**.
8. The Troubleshooting Wizard window appears. This application verifies the software and hardware installation and sequentially tests each NI serial port.
9. Connect the cables.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

ENET Serial Installation

Refer to the *Serial Hardware and Software Help* (available on the CD) for more information about troubleshooting problems, configuring the hardware and software, programming requirements, and more.

1. Log on as Administrator or as a user with administrator privileges.
2. Insert the *NI-Serial Software for Windows* CD.
3. Click **Install Software** and follow the onscreen instructions.
4. Restart the computer.
5. Install your Serial ENET hardware.
   a. Select **Start»Programs»National Instruments»NI-Serial» Add Serial ENET** to launch the Add Serial ENET wizard.
   b. Follow the prompts to add your serial ENET interface(s). If you see the Hardware Installation dialog box, click **Continue Anyway**. You may see two Hardware Installation dialog boxes per port being installed.
   c. When finished adding your serial ENET interface(s), restart your computer.
6. Select **Start»Programs»National Instruments»NI-Serial» Troubleshooting Wizard**.
7. The Troubleshooting Wizard window appears. This application verifies the software and hardware installation and sequentially tests each NI serial port.
8. Connect the cables.

ExpressCard Serial Installation

Refer to the *Serial Hardware and Software Help* (available on the CD) for more information about troubleshooting problems, configuring the hardware and software, programming requirements, and more.

1. Log on as Administrator or as a user with administrator privileges.
2. Insert the *NI-Serial Software for Windows* CD.
3. Click **Install Software** and follow the onscreen instructions.
4. Restart the computer.
5. Insert your serial ExpressCard hardware.
6. Select **Start»Programs»National Instruments»NI-Serial» Troubleshooting Wizard**.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

7. The Troubleshooting Wizard window appears. This application verifies the software and hardware installation and sequentially tests each NI serial port.
8. Connect the cables.

PCMCIA Serial Installation

Refer to the *Serial Hardware and Software Help* (available on the CD) for more information about troubleshooting problems, configuring the hardware and software, programming requirements, and more.

1. Log on as Administrator or as a user with administrator privileges.
2. Insert the *NI-Serial Software for Windows* CD.
3. Click **Install Software** and follow the onscreen instructions.
4. Restart the computer.
5. Insert your serial PCMCIA hardware.
6. Select **Start»Programs»National Instruments»NI-Serial» Troubleshooting Wizard**.
7. The Troubleshooting Wizard window appears. This application verifies the software and hardware installation and sequentially tests each NI serial port.
8. Connect the cables.

National Instruments, NI, ni.com, and LabVIEW are trademarks of National Instruments Corporation. Refer to the *Terms of Use* section on `ni.com/legal` for more information about National Instruments trademarks. The ExpressCard™ word mark and logos are owned by PCMCIA and any use of such marks by National Instruments is under license. Other product and company names mentioned herein are trademarks or trade names of their respective companies. For patents covering National Instruments products/technology, refer to the appropriate location: **Help»Patents** in your software, the `patents.txt` file on your media, or the *National Instruments Patent Notice* at `ni.com/patents`.

© 2005–2009 National Instruments Corporation. All rights reserved.

371583H-01 Oct09

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group

Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS
Experienced engineers and technicians on staff at our full-service, in-house repair center

InstraView℠ REMOTE INSPECTION
Remotely inspect equipment before purchasing with our interactive website at ***www.instraview.com*** ↗

WE BUY USED EQUIPMENT
Sell your excess, underutilized, and idle used equipment
We also offer credit for buy-backs and trade-ins
www.artisantg.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?
Visit us on the web at ***www.artisantg.com*** ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisantg.com | www.artisantg.com