ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Nortel NTDK23BA* at our website: ***Click HERE***

NORTEL NETWORKS

Enterprise Solutions

Meridian 1 Options 11 - 81C Product Catalog

Effective
July 17, 2000

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NORTEL NETWORKS

CO Commercial Operations

Date: July 17, 2000

U.S. Meridian 1 Product Catalog

Changes Since Publication

Please refer to the following website for current product delivery information: (http://www.nortelnetworks.com/partnercenter) or (http://www.nortelnetworks.com/partnercentre). Once there, partners should be able to access the site using their NIC login/password. Nortel Networks has provided a link in the page for any difficulties encountered or click on "feedback".

Please note the following changes to the U.S. Meridian 1 product catalog that occurred after the distribution of the April 17, 2000, product catalog.

- **Please note the following announcement:**
  - NTHU21AC - Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package AC, and HTHU21DC - Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC, have been removed as a recommended upgrade path. NTHU29 package is recommended.

- **Vintage change:**

Old Vintage	New Vintage	Description	Discount Category	Price
NTLH01AA	NTLH01AB	CD-ROM, X11 Release 25	No change	No change

Paper Copy Distribution Eliminated

The CSP will be sent by email only, providing product catalog information that has changed since publication of the last CSP or catalog. The Product Offer Communications group looks forward to providing you an enhanced level of service through the email CSP notification.

Please keep us informed of any changes in your email address to ensure our ability to provide you with timely updates of the CSP bulletins. Send your email address, along with your name, company name, and street address to **mbsgprs@nortelnetworks.com** or notify your District Sales Manager of the email address.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Table of Contents

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Changes Since Publication (July 17, 2000)

Summary of Changes - July 17, 2000

Manufacture discontinued 25
Status changes 28
New product introductions 29
Price changes 38
Description changes 47
Package content adjustments 49
Volume Discount Indicator Changes 55

Price by Chapter

Meridian 1 Option 11C Compact 58

System Packages 58
Meridian 1 Internet Enabled 58
Optional Component Packages 58
Upgrade Packages 59
Optional Components 59
Documentation 60
Miscellaneous 61

Option 11/11E/11C Hardware and Software 62

Meridian 1 Option 11C New System Packages 62
Basic System Hardware Package 62
System Software Packages - New Systems 62
Meridian 1 Internet Enabled 62
Meridian 1 Option 11C Mini Software Packages 62
Optional Features 63
Meridian 1 Option 11C Documentation 63
English Coil 63
English Binder 64
CD-ROM 64
Meridian 1 Option 11C Cabinet Expansion Packages 64
Expansion Cabinets 64
Meridian 1 Option 11/11E/11C Merchandise Hardware 64
Peripheral Equipment (PE) 64
DTI/PRI/BRI Hardware 65
Line-side T1 66
Mini Carrier Remote 66
Power Equipment 66
Meridian 1 Option 11/11E/11C Miscellaneous Hardware 66
Option 11C Software Feature Set Upgrade 69
Release 22 (or later) Software Up-issue to "Latest" Issue 69
Meridian 1 Option 11/11E Cabinet Expansion Packages 70
Meridian 1 Option 11/11E Documentation 70

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

English - Binder 70
English - Coil 70
Meridian 1 Option 11/11E to 11C Cabinet Upgrade Packages 70
Hardware Upgrades 70
Software Upgrade Packages - Used With Option 11/11E to 11C Upgrades 71
Meridian 1 System Software 72
Options 51C-81C 72
System/Software Compatibility 72
Capacity Requirements 72
Option 11C Software 73
Software Updates/Replacements 73
Capacity Expansion 73
Option 11C Software 74
Option 11 Release 24 Software 74
System Software 74
Base Features 74
Software Updates 74
Miscellaneous 75
Option 11 Release 24 Software Order Code/Option Matrix 76
Option 11 Release 21 Software 81
Option 11 Release 21 Software Order Code/Option Matrix 81
System Software 84
Software Updates 92
X11 Software for Large Systems 92
Base Features 92
Optional Features 93
X11 Release 25 Software 93
Base/Option Features 93
Broadcast Features 99
RAN Broadcast 99
Music Broadcast 100
ISDN/BRI Features 100
ACD/Message Processing Features 100
Meridian Link Associated Station (AST) Features 101
X11 Release 24 Software 102
X11 Release 25 Software Order Code/Option Matrix 102
Base/Option Features 104
Broadcast Features 109
RAN Broadcast 109
Music Broadcast 110
ISDN/BRI Features 110
ACD/Message Processing Features 111
Meridian Link Associated Station (AST) Features 113
X11 Release 24 Software Order Code/Option Matrix 114
X11 Release 23 Software 116
Base/Option Features 116

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Broadcast Features 121
RAN Broadcast 121
Music Broadcast 122
ISDN/BRI Features 122
ACD/Message Processing Features 123
Meridian Link Associated Station (AST) Features 125
X11 Release 23 Software Order Code/Option Matrix 126
X11 Release 22 Software 128
Base/Option Features 128
ISDN/BRI Features 132
ACD/Message Processing Features 132
Meridian Link Associated Station (AST) Features 133
X11 Release 22 Software Order Code/Option Matrix 134
X11 Release 21 Software 136
Base/Option Features 136
ISDN/BRI Features 139
ACD/Message Processing Features 140
Meridian Link Associated Station (AST) Features 141
X11 Release 21 Software Order Code/Option Matrix 142
X11 Release 19 Software 144
Base/Optional Features 144
ISDN/BRI Features 147
ACD/Message Processing Features 147
Meridian Link Associated Station (AST) Features 148
X11 Release 19 Software Order Code/Option Matrix 149
X11 Release 15-17 Software 150
Base/Optional Features 151
ISDN Features 153
ACD/Message Processing Features 154
X11 Release 15-17 Software Order Code/Option Matrix 155
Software Administrative Fees 156
Meridian 1 Internet Enabled 157

Meridian 1 Core System Hardware 158

System Packages 158
Meridian 1 Internet Enabled 158
Component Packages 158
X11 Release 23 hardware upgrade paths 162
Determining Appropriate Cable Lengths for Multi-Group Systems (Option 81 and 81C) . 164
Upgrade Packages 164
Migration Policies 166
Telephone Migration Credits 166
Telephone Upgrades 166
Order Codes / Pricing 166
Equipment Returns 167
EPE to IPE Migration Credits 168
Peripheral Equipment Upgrades 169

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Codes/Pricing . . . 169
Equipment Returns . . . 170
Ordering . . . 171
Equipment Returns . . . 172
Equipment Return Procedure Migration Policy . . . 173
Meridian Integrated Applications . . . 176
Meridian Integrated Personal Call Director . . . 176
Meridian Integrated Applications Miscellaneous . . . 176
Components . . . 176
Cards . . . 176
Column/Module/Card Cages Products . . . 183
Cooling Units . . . 184
Data Products . . . 185
Disk/Tape Drives . . . 185
Power/Rectifier Products . . . 185
Shelves/Tiers . . . 187
Cables . . . 187
Miscellaneous . . . 196

Meridian 1 Telephones and Attendant Products . . . 200

M3900 Series . . . 200
Optional/Value Added Components . . . 200
Meridian Modular Telephones . . . 201
Optional/Value Added Components . . . 202
Meridian Digital Telephones . . . 203
Optional/Value Added Components . . . 204
Consoles . . . 204
Accessories/Replacement Parts . . . 205
Headset Products . . . 205
Cords . . . 205
Handsets . . . 206
Designation Material . . . 206
Miscellaneous . . . 209
Documentation . . . 210

Meridian 1 Message Processing - Applications . . . 212

Message Processing - Applications . . . 212
Message Services Module (MSM) . . . 212
System Compatibility . . . 212
System Capacity . . . 213
Contact . . . 213
Meridian Mail Release 13 . . . 213
Summary of Features . . . 213
Core MM13 Features are: . . . 213
Web-PC Features are: . . . 213
Meridian Mail Upgrades/Expansions . . . 214
Charges for Release Updates and Feature Additions . . . 214

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Service Transaction Fees 214
Examples of Meridian Mail Upgrades 214
Adding a New Feature 214
Updating Release and Adding a New Feature 215
Expanding Ports 215
Updating Release and Adding a New Feature 215
Meridian Mail Factory Upgrade Service 216
Meridian Mail Upgrade Service 216
System Port Charge for Meridian Mail Upgrades 216
Meridian Mail Factory Upgrade Service 217
Example of Meridian Mail Factory Upgrade Service 217
Configuration Rules for the MC Upgrades Tool 218
Meridian Mail Platform Migration 218
CallPilot 218
CallPilot Release 1.06 218
CallPilot Systems 219
Meridian 1 Systems Software 220
Meridian 1 Option 11C Systems 220
Meridian 1 Option 51C/61C/81/81C Systems 220
CallPilot Hardware 220
Expansion Hardware 220
LAN Connection Hardware 220
Miscellaneous Hardware 220
Cables 223
Raid Kits 224
CallPilot Software 224
Expansion Software 224
Channels 224
Storage Expansions 224
Per Seat Clients 224
Software Options 225
Networking 225
Network Message Service 226
Miscellaneous Software Options 226
CallPilot Documentation 227
Meridian Mail Hardware - Option 11C Mini 230
Base Platform Packages - Meridian Mail Mini 230
Meridian Mail-Option 11 230
Language Tapes 230
Meridian Mail Hardware-Option 11 235
Base Platform Packages-Card Option 235
Base System Software 235
Optional Features 235
Networking Software 236
Enhanced Reporting Software - Meridian Mail Reporter 236
Software Administration Fees 236

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System Expansions . . . 237
Ports/Storage . . . 237
Ports . . . 237
Expanded Storage Software . . . 238
System Upgrades . . . 238
Software Release Updates . . . 238
Components . . . 239
Component Packages . . . 239
Component Cards . . . 239
Disk Drives . . . 239
Tape Drives/Accessories . . . 239
Cables . . . 239
Miscellaneous . . . 240
Meridian Mail - Option 11 (EC11) . . . 240
Language Tapes . . . 240
Meridian Mail Hardware - Option 11 - EC11 . . . 245
Base Platform Packages - EC11 . . . 245
Base System Software . . . 245
Optional Features . . . 245
Networking Software . . . 246
Enhanced Reporting Software - Meridian Mail Reporter . . . 246
Software Administrative Fees . . . 246
Optional Hardware . . . 246
Disk Shadowing . . . 246
System Expansions . . . 247
Ports/Nodes/Storage . . . 247
Ports . . . 247
Node Expansions . . . 247
Storage Expansion . . . 248
System Upgrades . . . 248
Software Release Update . . . 248
Components . . . 248
Component Packages . . . 248
Cards . . . 249
Disk Drives . . . 249
Tape Drive/Accessories . . . 249
Cables . . . 249
Miscellaneous . . . 250
Meridian Mail-Option 21-81 (Modular Option EC/Modular Option GP/Modular Option) 250
Stand Alone . . . 250
Language Tapes . . . 250
Meridian Mail Hardware . . . 255
Base Platform Packages . . . 255
Modular EC . . . 255
Modular GP . . . 256
Non Northern PBX/Modular Option GP Connectivity . . . 256

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Connections 256
Meridian Mail Software 256
Base System Software 256
Optional Features 256
Networking Software 257
Enhanced Reporting Software - Meridian Mail Reporter 257
Software Administration Fees 257
Optional Hardware 258
Disk Shadowing 258
Modular Option EC 258
Modular Option GP 258
Modular Option 258
System Expansions 258
Ports/Nodes/Storage 258
Ports 258
Node Expansions 259
Storage Expansion 262
System Upgrades 263
Hardware - Disk/Tape Drive and Processors 263
Modular Option EC 263
Modular Option GP/Modular Option 263
Processor Upgrades 263
Software Upgrades 263
Modular Option EC 263
Modular Option GP 263
Modular Option 264
Platform Migration 264
Migration to a Modular Option 264
Migration Hardware 264
Processor Upgrade 264
Disk Drive Upgrade (only required if existing disk drive is 155MB) 264
Migration to a Modular Option GP 265
Migration Hardware 265
Processor Upgrade 265
Disk Drive Upgrade (only required if existing disk drive is 155MB) 265
Migration Software 265
Modular Option EC 265
Modular Option GP 265
Modular Option 266
Components 266
Component Packages 266
Cards 266
Disk Drives 267
Tape Drive/Accessories 267
Cables 267
Miscellaneous 269

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Text Telephony System 269
System Packages 269
Hardware Upgrades 269
Additional Software Clients 269
Documentation 269
Symposium Messenger 270
Software Packages 270
Symposium Assistant 270
Software Packages 270
Messenger Software Upgrades 270
Hardware Packages 270
Servers 270
Meridian Application Server Spares 270
Messenger Services and Documentation 271
Messenger and Assistant Documentation 271
Meridian IVR Release 2 Integrated 272
Components 272
Open IVR 272
Optional System Packages 272
Components 272
Spares 273
Documentation 275
SYMPOSIUM Professional Services - IVR Services 275
SYMPOSIUM 276
SYMPOSIUM OPEN IVR 4.0 276
Common Options 276
AP and AP - Unique Options 276
MRS Tower - Unique Options 277
MRS/Rack and MRS/Rack - Unique Options 277
MRS/AP and MRS/AP - Unique Options 277
AP and MRS/AP Options 277
MRS Tower, MRS/Rack and MRS/AP Options 278
PEB-Based MRS or MRS/AP Expansions 280
Site Options 280
Application, Upgrade and Bundled Packages 281
Spares Packages 281
PEB-Based Spares 283
Documentation Spares Packages 285
SYMPOSIUM Integrated IVR Release 2.2 286
Integrated IVR Release 2.2 System Information 286
Meridian 1 and Meridian Mail Considerations for Integrated IVR Release 2.2 287
Meridian 1 X11 Hardware and Software 287
Meridian Mail Hardware and Software 287
General Ordering Considerations for Integrated IVR Release 2.2 289
SYMPOSIUM Integrated IVR Release 2.2 Packages 290
Options Upgrade 290

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Options 290
Voice Prompt/Database Editor. 290
Voice Ports. 290
Host Communications 291
VT100 291
SNA 292
RDBMS Connectivity 293
Fax 293
UPS 293
Audio Line Interface 294
LAN Interface 294
Memory Expansion 294
Meridian ACCESS Cable Kit 294
Enhancements CD 294
Hardware 294
Software 295
Cables. 295
Documentation. 295
SYMPOSIUM Call Center 295
SYMPOSIUM Express Call Center Software 295
SYMPOSIUM Express Call Center Merchandise 296
SYMPOSIUM Express Call Center Documentation 296
SYMPOSIUM Call Center Server. 297
Server Base Software. 297
System Software 297
CCS 100 Software. 297
CCS 200 Software. 297
CCS 300 Software. 298
CCS 350 New System Software 298
Upgrade Software 298
Symposium Call Center Server. 298
MAX 7 or MAX 8 Upgrade to CCS 100 298
MAX 6 Upgrade to CCS 100 299
MAX 5 Upgrade to CCS 100 299
MAX Pre-Release 5 or PEP Upgrade to CCS 100 299
MAX with CCR Upgrade to CCS 200 300
MAX Virtual Upgrade to CCS 200 300
CCR Upgrade to CCS 100 301
CCR Upgrade to CCS 200 301
NACD and NAC to CCS 300 301
NACD Upgrade to CCS 300. 302
SYMPOSIUM Service Products. 302
Server Hardware 302
Complete Systems 302
Components Common to all Systems. 303
701t / 702t Merchandise. 303

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1001t Merchandise . . . 304
1000t Merchandise . . . 305
1003t Merchandise . . . 305
Common Merchandise . . . 306
SYMPOSIUM Call Center Server Documentation . . . 307
Release 1 . . . 307
SYMPOSIUM WebResponse Server . . . 308
Desktop . . . 308
SYMPOSIUM Agent . . . 308
SYMPOSIUM FastView . . . 310
Packages . . . 310
Installation . . . 311

Meridian 1 Call Center and CTI Products . . . 312

Call Center Software Service Transaction Fees . . . 312
Meridian MAX . . . 312
Meridian MAX Release 9 Software Upgrade Matrix . . . 312
Hardware for Meridian MAX Release 9 Systems . . . 316
Meridian MAX-SNNE System Hardware . . . 316
Upgrades to MAX-SNNE System Hardware . . . 316
Hardware Expansion Packages for Meridian MAX-SNN and Meridian MAX-SNNE Systems . . . 316
Meridian MAX-IPEE System Hardware . . . 316
Meridian MAX-IPE to MAX-IPEE Upgrade/Repair Hardware . . . 316
Chassis Conversion Kits for Meridian MAX-IPE and MAX-IPEE Modules . . . 316
Hardware for Pre-Meridian MAX Release 9 Systems . . . 316
Expansion Packages for Existing Meridian MAX-SEE, Option MAX, and MAX-SNN Systems . . . 316
Meridian MAX Hardware Spares Packages . . . 317
Meridian MAX Release 9 Software . . . 317
Meridian MAX-SNNE Release 9 System Software . . . 317
Options for Meridian MAX-SNN and MAX-SNNE Release 9 Software . . . 317
Upgrades to Meridian MAX-SNN and MAX-SNNE Release 9 System Software . . . 317
Migrating Release 9 System Software from Meridian MAX-SNN/IPE/IPEE to Meridian MAX-SNNE . . . 318
Meridian MAX-IPEE Release 9 System Software . . . 318
Options for Meridian MAX-IPE and MAX-IPEE Release 9 Software . . . 318
Upgrades to Meridian MAX-IPE or MAX-IPEE Release 9 System Software . . . 318
Media Replacement/Upissues for Meridian MAX Release 9 Software . . . 319
Software for Pre-Meridian MAX Release 9 Systems . . . 319
Options for Pre-Meridian MAX Release 9 Software . . . 319
Media Replacement/Upissues for Pre-Meridian MAX Release 9 Software . . . 319
Expansion for Pre-Meridian MAX Release 9 Software . . . 320
Release Upgrades for Pre-Meridian MAX Release 9 Software . . . 320
Meridian MAX Software Administration Fees . . . 320
Meridian MAX Software Tools . . . 321
Meridian MAX Documentation . . . 321

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian MAX Release 9 Documentation. . . . 321
Meridian MAX Release 8 Documentation. . . . 321
Meridian MAX Release 7 Documentation. . . . 321
Meridian MAX Release 6 Documentation. . . . 321
Meridian Terminal Emulator (MTE) 322
MTE Software. . . . 322
MTE Release 9 Software 322
Upgrades to MTE Release 9 Software 322
MTE Release 5 Software 322
MTE Documentation 322
MTE Release 9 Documentation 322
MTE Release 8 Documentation 322
MTE Release 7 Documentation 322
MTE Release 6 Documentation 323
Meridian MAXcaster 323
ACD-MAX 323
Software Administrative Fees. . . . 323
ACD-D Auxiliary Processor 323
Meridian Network Administration Center (NAC). . . . 323
Base Software 323
Media Replacement/Upissue for NAC 2.5 323
Hardware Packages. . . . 324
NAC Software Services Transaction Fee 324
NAC Documentation 324
Meridian Link and CCR Co-Residency. . . . 324
Software 324
Base Software 324
Software Release Updates/Migration. . . . 325
Software Administrative Fees. . . . 325
Support Services 325
SYMPOSIUM TAPI Service Provider 325
Services Available 326
Call Center and CTI Products-Merchandise 326
Components 326
Modules, Shelves and Power Supplies 326
Disk Drives, Tape Drives and Media. . . . 326
Application Module Cards 327
Miscellaneous. . . . 327
Cables and Related Merchandise 327
eCommerce Solutions 330
WebShare Products 330
View Manager. . . . 330
Security and Policy Management 330
Access Policy Manager. . . . 330

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Other Application Products 332
Meridian Private-switch Emergency Response 332
Meridian Private-switch Emergency Response Unit 332
Meridian Private-switch Emergency Notification PC Software 332
Meridian Private-switch Monitor Software 332
Meridian Private-switch Emergency Documentation 332
Meridian 1 Remote Solutions 333
Remote Office 9150 - Solutions for the Small Branch Office 333
Remote Office 9110 and 9115 - Solutions for the Teleworker 333
Remote Office Components 333
Remote Office Documentation and Training 334
Meridian HomeOffice II Remote Equipment 334
Meridian HomeOffice II Host Equipment 334
Meridian HomeOffice II Documentation and Training 334
Meridian HomeOffice II Additional Items 335
Meridian 1 System Administration Products 336
Optivity Telephony Manager (OTM) 336
New Installation 336
MAT Upgrades to OTM 336
OTM Upgrades 337
OTM Billing 1.0 Codes - New Installation 337
OTM Application Additions 337
MAT to Billing Upgrades 338
Additional OTM Clients 338
User Guides 338
Services and Support 338
Meridian Administration Tool Release 6 338
End-User Base Packages 338
Application Packages 339
Upgrades From MAT 5 or MAT 6 339
Upgrades From MAT 4 340
Hardware 340
Meridian Administration Tool Release 4 341
Upgrades 341
Hardware 341
Spares Packages 342
Hardware 342
Meridian Mail 342
Call Center 342
Open IVR 342
Symposium Messenger/Assistant 343
Meridian Integrated Conference Bridge 343
Meridian Integrated RAN 343

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Documentation 344
NTPs 344
Information/User Guides 350
Collateral Listing 356
Ordering Procedures 357
Sales Collateral Order Form 357
MERIDIAN 1 - Meridian Call Center 359
Brochures 359
Customer Testimonials 360
Demos 362
Sales Training 362
Videos 362
MERIDIAN 1 - Options 11C through 81C. 363
Business Cases 363
Brochures/Flyers 363
Systems 364
Remote Services 364
System Management 365
Guides/Handbooks 365
Demo Disks 365
Meridian Digital Telephones/Attendant Consoles 365
Brochures/Flyers 365
ISDN and Data Services 367
Brochures 367
Videos 367
Controlling Access Privileges. 368
SYMPOSIUM. 368
Brochures 368
Customer Testimonials 370
Demo Disks/Audio. 371
Videos 371
Training 371
MERIDIAN 1 - Meridian Multimedia Messaging 372
Brochures 372
Guides/Handbooks 374
Demo Disks 374
Videos 374
CD-ROM 375
Miscellaneous. 375

Reference

Price List

Manufacture discontinued

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

General Section

General Policy. 1720
About this product catalog. 1720
Catalog distribution policy 1720
Products supported by this catalog. 1720
Definition of business day 1720
Holidays 1720
Time zone abbreviations. 1721
Pricing information 1721
Pricing policies 1721
Distributor discounts 1721
Gross Distributor Price/Net Distributor Price calculation 1722
Non-discountable items 1722
Standard price item definition 1722
Software licenses and right to use fees 1723
Meridian Software License Transfer Agreement 1723
Warranties 1727
Hardware warranty period 1727
Software warranty period 1727
Ordering Process, Policies, and Procedures 1728
Order placement. 1728
Order placement methods. 1728
Order transaction types. 1728
Order contacts. 1729
Training 1729
Required order information 1730
Order restrictions 1730
Order forms 1731
Order acknowledgment 1731
Minimum POs 1731
Order changes 1731
Product order change requests 1731
Stock product. 1731
Custom product 1731
Order rescheduling 1732
Carrying charges. 1732
Order cancellation 1732
Product delivery. 1733
Standard shipment leadtime 1733
Partial shipments 1733
Nortel Networks products 1733
Products manufactured by third parties. 1733
Shipping methods 1734
Shipment/Order discrepancies 1734
Proof-of-delivery 1734

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Product availability limitations 1734
Product availability status. 1734
Controlled release products 1735
Shipment leadtimes for controlled release products. 1735
Return Policies and Procedures 1736
Software return policy 1736
Equipment return options 1736
Return contacts 1736
Restocking policies 1738
Restocking charges. 1738
Restocking process 1738
Repair policies and procedures 1739
Repair and service responsibilities 1739
Distributor responsibility. 1739
Repair warranty 1739
Products manufactured by third parties. 1739
Non-repairable parts 1739
Repair pricing 1740
In-warranty 1740
Out-of-warranty. 1740
Repair agents 1740
Repair contacts and schedules 1740
Repair procedures. 1741
Emergency repair 1742
After Hours Emergency Advance Replacement Policy 1742
Repair advance replacement 1743
Repair advance replacement policies 1743
Repair advance replacement procedures 1743
Defective on arrival (DOA). 1744
DOA policies 1744
Meridian 1 DOA procedures 1745
Standard Price Items 1747
Warranties and disclaimers of warranties 1747
Technical support. 1747
Meridian 1 Customer Owned and Maintained System (COAMS) 1747
Objective. 1747
Definitions 1747
Customer in Good Standing 1747
Customer Owned and Maintained Systems (COAMS). 1747
Customer Service Report (CSR) 1748
Customer Technical Services (CTS). 1748
Maintenance Qualification Program 1748
Nortel Networks 1748
Nortel Networks Practices (NTPs) 1748
Quality Audits 1748
Quality Audited Systems. 1748

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Quality Certified Authorized Distribution Channel 1748
COAMS responsibilities. 1749
COAMS policy. 1750
COAMS training 1752
Minimum course requirement for COAMS participation. 1752
Training courses available (Meridian 1) 1752
COAMS technical support fees 1753
Telephone support. 1753
On-site support 1754
Meridian Administration Tools 1756
Meridian 1 Security Services Offerings 1757
Meridian 1 Security Audit 1757
Meridian 1 Security Consulting 1758
Meridian 1 Security Seminars 1758
Meridian Mail Factory Upgrade Services 1759
Product Catalog 1759
Support/Installation and Maintenance 1761
Meridian 1 CTS technical support. 1761
Technical support fees 1761
Meridian 1 Customer Quality Engineering Support 1763
Field Service Installation and Maintenance. 1764
Installation and Maintenance quotes 1764
Technical Support services. 1765
Service locations. 1765
On-site installation 1765
Pre-Installation services 1765
Installation services. 1766
Union labor 1766
On-site Maintenance definition 1766
Maintenance service levels. 1766
Maintenance activities 1767
Scheduled maintenance. 1767
Technical/Telephone software support 1767
Remote diagnosis 1767
Corrective maintenance. 1767
Repair 1767
Response time targets. 1768
Emergency response time 1768
Non-emergency response time 1768
On-site service response time 1768
Non-contracted emergency service. 1768
DEPOT - Maintenance Services 1769
Moves, additions, and changes 1769
Time and Material Labor Schedule for Core M1, Norstar and Companion. 1769
Time and Material Labor Schedule for Applications. 1770

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System/Software Orders and Upgrades 1771
New system orders 1771
Meridian 1 Options 11C-81C 1771
General requirements 1771
System and application software orders 1772
System/software upgrades 1772
Software updates 1772
Software update orders 1772
Software update charges 1773
In-house conversion charge 1773
Factory Service Program 1773
Enhanced In-house conversions 1774
What is included at this price? 1774
What needs to be provided by the Distributor? 1774
Engineered Upgrades - Quote basis 1775
Applicable systems 1775
Conversion ordering information 1775
Generic/release updates 1778
Generic update 1778
Release update 1778
Generic/release software issues 1778
Software service transaction matrix 1779
Feature addition or deletion 1780
Capacity change 1781
System software capacity 1781
Terminal Number (TN) 1781
ACD Agent 1781
DSL 1781
Capacity expansion/reduction charges 1781
Software media replacement 1782
Upgrades 1782
Meridian 1 Option 11 upgrades 1782
Ordering software update 1783
Replacing damaged cartridges (Options 11 and 11E only) 1783
Replacing damaged Option 11C daughterboards 1783
Updating Meridian Mail Card option 1783
Meridian 1 Options 21 - 81C upgrades 1784
Applicable RTU fees 1784
Pre-X11 Rel. 23 upgrades to Rel. 23 on CD-ROM media - Special Policy 1784
Pre-X11 Release 22 to X11 Release 22 updates 1784
Pre-X11 Release 15 1784
X11 Release 15 or 16 to X11 Release 17 - special policy 1784
Selecting TN and ACD levels for software updates 1784
Exceeding TN/ACD limits on original system 1785
Updating Release 15/16 to Release 17/18 1786
TN count for X11 Rel 15.55 and later through Rel 16 (all issues) 1787

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

TN count for X11 Release 15 (pre Release 15.55) 1787
Placing software update order 1787
Software update order form. 1787
Web Based Services 1789
Meridian Applications - Special Policies 1790
SYMPOSIUM Agent. 1790
SYMPOSIUM Agent Software Support (SV000149) 1790
SYMPOSIUM Agent INSTALL - PREP (SV000147) 1791
SYMPOSIUM Agent INSTALL - PRO (SV000148) 1791
SYMPOSIUM Professional Services Order Process 1792
SYMPOSIUM TAPI Server 1792
TAPI Server Software Support Services (SV000091) 1792
TAPI Server INSTALL-PREP (SV000088) 1793
TAPI Server INSTALL-PRO (SV000089) 1794
Installation Support Limitations 1794
SYMPOSIUM WebResponse Server 1794
Open IVR. 1796
Enterprise Solutions Field Service support 1796
Ordering policy 1796
Support services 1796
INSTALL-PREP 1797
INSTALL-PRO 1797
Yearly maintenance services. 1797
Post-sales IVR applications development support 1797
Support services 1798
Ordering process 1798
Meridian Mail Reporter (MMR) Service Plan. 1798
Defect resolution 1798
Limited installation support 1798
Navigation support 1799
Interpretation 1799
Support service availability 1799
SYMPOSIUM Messenger 1799
Ordering process and procedures 1799
Transaction order types 1799
Order contacts 1800
Warranty-period repair and replacement service 1800
Software returns contact 1800
Installation and service 1800
Meridian Application Server Support and Service Overview 1801
Installation Only Options 1803
Installation and Training Options 1804
Training Only Options 1806
Warranty Service Options 1806
Post Warranty Service Options 1807
Software support and basic maintenance 1809

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Support services 1809
Telephone support schedule 1810
On-site support 1810
Technical Assistance Service fees 1810
Hardware and Software Packaging 1811
Meridian Mail requirements 1811
Messenger PC Requirements (Clients) 1812
Client Operating Systems Supported 1812
LAN requirements 1812
Packaging 1812
Package content 1812
System configuration 1813
Policies 1813
New system orders (hardware and software) 1814
Meet site environment prerequisites 1814
Select the appropriate service offering 1814
Select the appropriate LAN connectivity option 1814
Order the appropriate site license 1814
New system software 1815
System upgrades, expansions, and merchandise orders 1815
Client expansion 1815
Combination client expansion and system upgrade 1815
Upgrade to Visual Voice and Fax Messaging Service 1815
Upgrade software 1815
Optional software 1816
Meridian Passport Software Policy 1816
Software Upgrades 1816
Hardware Upgrades 1816
Software Release Numbering 1816
Meridian Passport 1816
Meridian Passport Manager 1816
Software Ratings 1817
Active 1817
Sustained 1817
Retired 1817
CTS Support Pricing 1817
Authorized Support Personnel 1817
Meridian 1 Hardware/Software Status 1818
Software status 1818
Software support based on status 1818
Software status 1819
Applications software status 1820
Hardware status 1821
System status 1821
Applications hardware status 1822
Meridian 1 system/software compatibility matrix 1823

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Index

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Summary of Changes - July 17, 2000

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

I. Manufacture discontinued

Order Code	Description	Replaced By
A0617012	600MB Tape Drive Unit	
A0633651	40MB PCMCIA Card - Blank	
A0730856	600MB Tape Drive Repair Kit	
AS1053A	Peripheral Equipment Module Package AC	
AS1053D	Peripheral Equipment Module Package DC	
NT2F75AA	Meridian Communications Adapter User Guide (M3900 Series, Package of 15 P0903781)	
NT4N65AA	cPCI Core Network Interface Card (2 Ports)	
NT4N66AA	cPCI Core Network Interface Transition Card	NT4N66AB
NT5D12AF	Dual Port DTI/PRI (DDP) Card	
NT5D83AA	Nortel SYMPOSIUM Messenger Demo CD-ROM	
NT5F37AA	Fiber Network Reference Guide	NT5F36AA
NT5G53AA	MIPCD Kit	NT5G53AB
NT5P41TC	MAS - Model 500 Serial Card Kit	
NT6R47AA	Meridian Mail Master Tape, North American 1 - Release 13	NT6R47AD
NT6R47BA	Meridian Mail Master Tape, North American 2 - Release 13	NT6R47BD
NT6R47CA	Meridian Mail Master Tape, European 1 - Release 13	NT6R47CD
NT6R47DA	Meridian Mail Master Tape, European 2 - Release 13	NT6R47DD
NT6R47EA	Meridian Mail Master Tape, European 3 - Release 13	NT6R47ED
NT6R47FA	Meridian Mail Master Tape, European 4 - Release 13	NT6R47FD
NT6R47GA	Meridian Mail Master Tape, European 5 - Release 13	NT6R47GD
NT6R47HA	Meridian Mail Master Tape, Asia/Pacific 1 - Release 13	NT6R47HD
NT6R47JA	Meridian Mail Master Tape, Asia/Pacific 2 - Release 13	NT6R47JD
NT8R70AA	Meridian IP Telecommuter NTP CD ROM	NTLH16AA
NT9F30AA	SYMPOSIUM Call Center Server 1001t	
NT9F30AD	SYMPOSIUM Call Center Server 1001t	
NT9F31AA	SYMPOSIUM Call Center Server 1001t with RAID	
NT9F31AD	SYMPOSIUM Call Center Server 1001t with RAID	
NT9F46AA	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly	
NT9F51AB	SYMPOSIUM Call Center Server Release 1.1 Replacement Software	
NTAG26AA	MF Receiver Card - IPE	NTAG26AB

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTJH93EA	MAX-IPE to IPEE Upgrade Kit #1	
NTKG80CE	Option 11C Mini English Documentation Suite - Release 25 - Coil	
NTLH15AA	CP PII with IGS Reference Library	NT5F36AA
NTLT82AA	MIRAN to MIRAN Release 2 PCMCIA Upgrade Kit	
NTMN66AA66	Meridian Key-Based Expansion Module, Platinum (M3900 Series)	
NTMN66AA70	Meridian Key-Based Expansion Module, Charcoal (M3900 Series)	
NTMN69AA66	Meridian Communications Adapter (MCA), Platinum (M3900 Series)	
NTMN69AA70	Meridian Communications Adapter (MCA), Charcoal (M3900 Series)	
NTRH9056	VTG VB2001	
NTTK30AA	Option 11C Release 25 English Documentation Package, Binder	
NTTK31AA	Option 11C Release 25 English Documentation Package, Coil	
NTVM0002	Messenger 1.1 Windows Client Package, 100 Users	
NTVM0054	Messenger 3.0 Windows Client Package - 200 Users	
NTVM0062	Messenger 4.0 Windows Client Package - 50	
NTVM0063	Messenger 4.0 Windows Client Package - 100	
NTVM0064	Messenger 4.0 Windows Client Package - 200	
NTVM0065	Messenger 4.0 Windows Client Package - 500	
NTVM0066	Messenger 4.0 Windows Client Package - 1000	
NTVM0067	Messenger 4.0 Windows Client Package - 2000	
NTVM00JA	Messenger 1.1 Fax on Demand	
NTVM00SF	Pentium Platform Based Messenger 1.1 to 4.0 Upgrade	
NTVM0200	1.0 Administration Guide	
NTVM12DA	MAS Model 501 Server	
NTVM16AA	Messenger 1.1 Server Software Kit	
NTZD11AA	SYMPOSIUM Call Center Server French Release 1.0 Base Software	
P0885697	MIPCD NTP Guide (English)	P0914163
P0886005	MIPCD NTP Guide (French)	P0914553
P0886006	MIPCD User Guide (French)	P0914554
P0891259	MIPCD User Guide (English)	P0914505
P0902865	Meridian IP Telecommuter NTP	P0912864
QPC578D	Integrated Service Digital Line Card (ISDLC)	
QSD65A	Dual Loop PE Shelf	
SV000019	MAS Server Installation and Setup	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SV000021	Messenger 4.0: Installation and Administration and User Training, On-site	
SV000022	Assistant 1.0 Administration and User Training	
SV000113	Assistant Post Warranty Phone 8-5	
SV000114	Assistant Post Warranty Phone 7x24	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

II. Status changes

Order Code	Description	Old status	New status
A0656287	OIVR 2 x Hardware UPS for AP and MRS/AP	MR	RO
A0741574	702t OEM System With no Processor and no Memory	RO	CUR
NTDK57AA	Dongle	RO	CUR
NTSK11CL	Release 25A US General Business Feature Set	RO	CUR
NTSK11CN	Option 11C General Business Feature Set - Release 25	RO	CUR
NTSK11DN	Option 11C Enhanced Business Feature Set - Release 25	RO	CUR
NTSK11EN	Option 11C Enterprise Business Feature Set - Release 25	RO	CUR
NTSK11FL	Release 25A US NAS/VNS Feature Set	RO	CUR
NTSK11FN	Option 11C NAS/VNS Feature Set - Release 25	RO	CUR
P0886140	CallPilot Multimedia Users Guide	CUR	RO

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

III. New product introductions

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
A0620530	Santa Clara	Modem for SMDI Link in T1 Application	Y	2,450.00	D	N/A	N/A
A0744727	Santa Clara	128MB SDRAM	Y	1,240.00	H	N/A	N/A
A0788107	Santa Clara	T1 2 Pair Cable with RJ48 Connector	Y	80.00	D	N/A	N/A
A0788198	Santa Clara	VTG Adapter Cable	Y	170.00	D	N/A	N/A
A0797692	Santa Clara	SYMPOSIUM Call Center Server 1003t System Board PCA	Y	3,050.00	H	2,156.50	H
A0797705	Santa Clara	SYMPOSIUM Call Center Server 1003t Input/Output PCA	Y	1,650.00	H	1,305.25	H
A0797722	Santa Clara	SYMPOSIUM Call Center Server 1003t Voltage Regulator Module	Y	118.00	H	N/A	N/A
A0797724	Santa Clara	SYMPOSIUM Call Center Server 1003t Memory PCA	Y	165.00	H	N/A	N/A
A0797727	Santa Clara	SYMPOSIUM Call Center Server 1003t NetServer Hot-Swap Ultra2 Internal Stor-age Cage	Y	690.00	H	N/A	N/A
A0797938	Santa Clara	SYMPOSIUM Call Center Server 1003t 256MB 50ns EDO DIMM Kit (4x64MB)	Y	1,650.00	H	N/A	N/A
A0797948	Santa Clara	SYMPOSIUM Call Center Server 1003t Fan Assembly for Input/Output, Retainer	Y	76.00	H	N/A	N/A
A0797950	Santa Clara	SYMPOSIUM Call Center Server 1003t Fan Assembly for System Board	Y	52.00	H	N/A	N/A
A0797971	Santa Clara	Pentium III Xeon 500 MHz, 512KB ECC L2 Cache	Y	3,300.00	H	N/A	N/A
A0797984	Santa Clara	9GB Hot-Swap Ultra2 SCSI LP Hard Disk Drive	Y	3,200.00	H	2,099.75	H
A0798087	Santa Clara	SYMPOSIUM Call Center Server 1003t PCI Ethernet Adapter	Y	135.00	H	N/A	N/A
A0798092	Santa Clara	SYMPOSIUM Call Center Server 1003t Wide SCSI Host Adapter Board	Y	165.00	H	N/A	N/A
A0798117	Santa Clara	Non-Hot-Swap Tray	Y	85.00	H	N/A	N/A
A0798129	Santa Clara	SYMPOSIUM Call Center Server Power Supply Module, 300W	Y	400.00	H	N/A	N/A
A0798155	Santa Clara	SYMPOSIUM Call Center Server 1003t Internal SCSI Input/Output Cable	Y	121.00	H	N/A	N/A
A0798177	Santa Clara	SYMPOSIUM Call Center Server 1003t Fan Assembly for CPU	Y	52.00	H	N/A	N/A
A0798258	Santa Clara	SYMPOSIUM Call Center Server 1003t NetServer Keyboard	Y	205.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
A0798259	Santa Clara	SYMPOSIUM Call Center Server 1003t 1.44MB Floppy Disk Drive	Y	78.00	H	N/A	N/A
A0798260	Santa Clara	SYMPOSIUM Call Center Server 1003t Mini-DIN Mouse	Y	65.00	H	N/A	N/A
A0800927	Santa Clara	SYMPOSIUM Call Center Server 1003t 32x MAX EIDE CD-ROM Drive	Y	203.00	H	N/A	N/A
A0801312	Santa Clara	SYMPOSIUM Call Center Server 1003t Processor Terminator	Y	52.00	H	N/A	N/A
A0813446	Santa Clara	256 MB SDRAM	Y	2,050.00	D	N/A	N/A
NT2F82AB	Santa Clara	Meridian M3905 Quick Reference Guide (Package of 15 P0907179)	N	28.00	H	N/A	N/A
NT4N65AB	Santa Clara	cPCI Core Network Interface Card (2 Ports)	Y	2,200.00	I	425.00	H
NT4N66AB	Santa Clara	cPCI Core Network Interface Transition Card	Y	500.00	I	N/A	N/A
NT5D12AG	Nashville & Santa Clara	Dual Port DTI/PRI (DDP) Card	Y	11,500.00	I	1,000.00	H
NT5G95AA	Santa Clara	PCMCIA Flash Card Upgrade, MIPCD	Y	400.00	H	N/A	N/A
NT6R16AB	Santa Clara	PC Pack, Entopia MMP40, Card Option (Any Slot)	Y	10,000.00	D	N/A	N/A
NT6R47AD	Santa Clara	MM13.13 Master Tape NA 1	Y	100.00	D	N/A	N/A
NT6R47BD	Santa Clara	MM Release 13.13 Master Tape NA 2	Y	100.00	D	N/A	N/A
NT6R47CD	Santa Clara	MM Release 13.13 Master Tape Europe 1	Y	100.00	D	N/A	N/A
NT6R47DD	Santa Clara	MM Release 13.13 Master Tape Europe 2	Y	100.00	D	N/A	N/A
NT6R47ED	Santa Clara	MM Release 13.13 Master Tape Europe 3	Y	100.00	D	N/A	N/A
NT6R47FD	Santa Clara	MM Release 13.13 Master Tape Europe 4	Y	100.00	D	N/A	N/A
NT6R47GD	Santa Clara	MM Release 13.13 Master Tape Europe 5	Y	100.00	D	N/A	N/A
NT6R47HD	Santa Clara	MM Release 13.13 Master Tape Asia/ Pacific 1	Y	100.00	D	N/A	N/A
NT6R47JD	Santa Clara	MM Release 13.13 Master Tape Asia/ Pacific 2	Y	100.00	D	N/A	N/A
NT8D64BH	Santa Clara	Floor Module Anchor Hole Template	N	150.00	H	N/A	N/A
NT9F27AC	Santa Clara	SYMPOSIUM Call Center Server 1003t Peripherals Package	Y	535.00	H	N/A	N/A
NT9F43AD	Santa Clara	DMS SCCS Release 3.0 CD-ROM Client CD (Merchandise)	Y	25.00	D	N/A	N/A
NT9F90AA	Santa Clara	SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51	Y	20,370.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NT9F90BA	Santa Clara	SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0	Y	20,370.00	H	N/A	N/A
NTDR85AA	Santa Clara	Remote Office 911x User Guide	N	30.00	H	N/A	N/A
NTDR88AA	Santa Clara	Remote Office 911x North American Power Supply	Y	95.00	D	N/A	N/A
NTDW80AA	Santa Clara	Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	Y	80.00	D	N/A	N/A
NTDW81AA	Santa Clara	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (CD-ROM)	N	20.00	H	N/A	N/A
NTJR27AA	Santa Clara	CallPilot 1.07 Telset User Guide Package - Canadian French	Y	100.00	H	N/A	N/A
NTJR48AA	Santa Clara	CallPilot Telset Guide Package (Quantity 10), English	N	90.00	H	N/A	N/A
NTLH16AA	Santa Clara	Meridian IP Telecommuter NTP CD ROM	N	10.00	H	N/A	N/A
NTMN35FA-66	Santa Clara	Meridian M3905 Call Center, Release 2, Platinum	Y	550.00	D	120.00	H
NTMN35FA-70	Santa Clara	Meridian M3905 Call Center, Release 2, Charcoal	Y	550.00	D	120.00	H
NTQR11AA	Santa Clara	Remote Office 9115 4-User Starter Package - 16 RLC	Y	7,295.00	D	N/A	N/A
NTQR12AA	Santa Clara	Remote Office 9115 4-User Expansion Package - 16 RLC	Y	4,485.00	D	N/A	N/A
NTQR14AA	Santa Clara	Remote Office 9110 4-User Starter Package - 16 RLC	Y	7,295.00	D	N/A	N/A
NTQR15AA	Santa Clara	Remote Office 9110 4-User Expansion Package - 16 RLC	Y	4,485.00	D	N/A	N/A
NTQR16AA	Santa Clara	Remote Office 9110 Unit with North American Power Supply	Y	845.00	D	150.00	H
NTQR17AA	Santa Clara	Remote Office 9115 Unit with North American Power Supply	Y	895.00	D	150.00	H
NTRG08AD	Santa Clara	CallPilot 1.07 IPE (200i) Base Documentation Package	N	380.00	H	N/A	N/A
NTRG09AD	Santa Clara	702t Base Documentation Package, English	Y	380.00	H	N/A	N/A
NTRG10AD	Santa Clara	CallPilot 1.07 1001rp Base Documentation Package, English	Y	380.00	H	N/A	N/A
NTRG15AC	Santa Clara	CallPilot 1.07 Installation and Configuration Guide Package	N	110.00	H	N/A	N/A
NTRG16AC	Santa Clara	CallPilot 1.07 702t Installation and Configuration Guide Package	N	110.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NTRG17AC	Santa Clara	CallPilot 1.07 1001rp Installation and Configuration Guide	N	110.00	H	N/A	N/A
NTRG19AC	Santa Clara	CallPilot 1.07 Documentation CD-ROM	N	25.00	H	N/A	N/A
NTRG22AC	Santa Clara	CallPilot 1.07 Desktop Messaging Quick Reference Guide, Quantity 10	N	50.00	H	N/A	N/A
NTRG22EC	Santa Clara	CallPilot 1.07 Desktop Quick Reference Guide Package, French	N	50.00	H	N/A	N/A
NTRH0914	Santa Clara	Analog Loop Start Cable	Y	170.00	D	N/A	N/A
NTRH0915	Santa Clara	CT to CT Bus Cable	Y	90.00	D	N/A	N/A
NTRH21CA	Santa Clara	MPB 16-2T Carrier Card	Y	1,410.00	D	N/A	N/A
NTRH8101	Santa Clara	Application Server Master Driver CD Bootable	Y	10.00	H	N/A	N/A
NTRH9060	Santa Clara	VTG VB2009	Y	5,000.00	D	N/A	N/A
NTRH9065	Santa Clara	Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card	Y	3,550.00	D	N/A	N/A
NTRH9100	Santa Clara	SYMPOSIUM Call Center Server 1003t Base System	Y	15,590.00	H	N/A	N/A
NTRK26AA	Santa Clara	Software Assembly, CCS 100 - New System Software (1 Agent)	Y	720.00	D	N/A	N/A
NTRK26BA	Santa Clara	Software Assembly, CCS 100 - New System Software (10 Agents)	Y	6,528.00	D	N/A	N/A
NTRK26CA	Santa Clara	Software Assembly, CCS 100 - New System Software (50 Agents)	Y	29,292.00	D	N/A	N/A
NTRK26DA	Santa Clara	Software Assembly, CCS 100 - New System Software (100 Agents)	Y	51,888.00	D	N/A	N/A
NTRK26EA	Santa Clara	Software Assembly, CCS 100 - New System Software (500 Agents)	Y	225,900.00	D	N/A	N/A
NTRK26GA	Santa Clara	Software Assembly, CCS 100 - New System Software (5 Agents)	Y	3,450.00	D	N/A	N/A
NTRK26HA	Santa Clara	Software Assembly, CCS 100 - New System Software (20 Agents)	Y	12,720.00	D	N/A	N/A
NTRK26JA	Santa Clara	Software Assembly, CCS 100 - New System Software (200 Agents)	Y	100,800.00	D	N/A	N/A
NTRK27AA	Santa Clara	Software Assembly, CCS 200 - New System Software (1 Agent)	Y	300.00	D	N/A	N/A
NTRK27BA	Santa Clara	Software Assembly, CCS 200 - New System Software (10 Agents)	Y	2,724.00	D	N/A	N/A
NTRK27CA	Santa Clara	Software Assembly, CCS 200 - New System Software (50 Agents)	Y	12,204.00	D	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NTRK27DA	Santa Clara	Software Assembly, CCS 200 - New System Software (100 Agents)	Y	21,624.00	D	N/A	N/A
NTRK27EA	Santa Clara	Software Assembly, CCS 200 - New System Software (500 Agents)	Y	94,128.00	D	N/A	N/A
NTRK27GA	Santa Clara	Software Assembly, CCS 200 - New System Software (5 Agents)	Y	1,440.00	D	N/A	N/A
NTRK27HA	Santa Clara	Software Assembly, CCS 200 - New System Software (20 Agents)	Y	5,400.00	D	N/A	N/A
NTRK27JA	Santa Clara	Software Assembly, CCS 200 - New System Software (200 Agents)	Y	42,600.00	D	N/A	N/A
NTSF8519	Santa Clara	Enable Package 381, 382 for M3900 Sets Phase II	N	No charge		N/A	N/A
NTSF8722	Nashville & Santa Clara	Option 11C Software Rls 24C Upissue Keycode	Y	500.00	H	N/A	N/A
NTSK11AP	Nashville & Santa Clara	Option 11C Software Daughterboard - Release 25 Combo	Y	1,400.00	I	400.00	H
NTSW31AA	Santa Clara	Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08)	N	650.00	H	N/A	N/A
NTTK44AA	Santa Clara	RSM Cable	Y	120.00	D	N/A	N/A
NTTK45AA	Santa Clara	Option 11C 48MB Blank PCMCIA Memory Card Assembly	Y	650.00	H	N/A	N/A
NTTS50AA	Santa Clara	Meridian Mail Mini Networking Package	Y	1,100.00	D	N/A	N/A
NTUB20AD	Santa Clara	CallPilot 1.07 IPE Base Server Software Assembly	Y	70.00	D	N/A	N/A
NTUB22AD	Santa Clara	CallPilot 1.07 Base Software Assembly	Y	85.00	H	N/A	N/A
NTUB40AC	Santa Clara	CallPilot 1.07 Server Software CD	Y	10.00	D	N/A	N/A
NTUB41AC	Santa Clara	CallPilot 1.07 Administration Client CD	Y	10.00	D	N/A	N/A
NTUB42AC	Santa Clara	CallPilot 1.07 Desktop Messaging CD	Y	10.00	D	N/A	N/A
NTUB43AC	Santa Clara	CallPilot 1.07 PEP Software CD	Y	10.00	D	N/A	N/A
NTUB44AC	Santa Clara	CallPilot 1.07 Language Prompts CD	Y	15.00	D	N/A	N/A
NTUB44BC	Santa Clara	CallPilot 1.07 Language Prompts CD Sets (3)	Y	30.00	D	N/A	N/A
NTUB45AC	Santa Clara	CallPilot 1.07 Web Messaging CD	Y	10.00	D	N/A	N/A
NTUB71AA	Santa Clara	CallPilot 1.07 GB, 200i Token Ring LAN Option	N	No charge		N/A	N/A
NTUB72AA	Santa Clara	CallPilot 1.07 GB, 200i Ethernet LAN Option	N	No charge		N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NTUB73AA	Santa Clara	CallPilot 1.07 GB, 700/1000 Series Token Ring LAN Option	N	No charge		N/A	N/A
NTUB74AA	Santa Clara	CallPilot 1.07 GB, 700/1000 Series Ethernet LAN Option	N	No charge		N/A	N/A
NTUB80AA	Santa Clara	CallPilot 1.07 GB, MPC-8 - Expand Option (No Charge)	N	No charge		N/A	N/A
NTUB81AA	Santa Clara	DSP Connectivity Package - Digitel	N	No charge		N/A	N/A
NTUB83AA	Santa Clara	DSP Connectivity Option - MSL-100	N	No charge		N/A	N/A
NTUF24AA	Santa Clara	DMS SCCS Release 3 CD-ROM Document CD (Merchandise)	Y	25.00	D	N/A	N/A
NTZC80AA	Santa Clara	Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	Y	6,000.00	D	N/A	N/A
NTZC81AA	Santa Clara	Meridian IP Telephony Gateway Line 2.0 Systems Package	Y	6,200.00	D	N/A	N/A
NTZC82AA	Santa Clara	Internet Telephone Software Parameter (Large System)	N	90.00	D	N/A	N/A
NTZC84AA	Santa Clara	Internet Telephone Software Parameter (Small System)	N	90.00	D	N/A	N/A
NTZD0005	Santa Clara	Marketing Package DMS SYMPOSIUM Call Center Server, New System	N	No charge		N/A	N/A
NTZD0006	Santa Clara	Marketing Package DMS SYMPOSIUM Call Center Server, Upgrade System	N	No charge		N/A	N/A
NTZD0007	Santa Clara	Marketing Package DMS SYMPOSIUM Call Center Server, Spare System	N	No charge		N/A	N/A
NTZD02AD	Santa Clara	SYMPOSIUM Call Center Server, 702t Advanced	Y	8,100.00	H	N/A	N/A
NTZD02BD	Santa Clara	SYMPOSIUM Call Center Server, 702t Advanced with RAID	Y	12,500.00	H	N/A	N/A
NTZD21AA	Santa Clara	DMS SCCS Release 3.0 Peripherals Package	Y	1,000.00	D	N/A	N/A
NTZD24AA	Santa Clara	Software Assembly, SCCS Release 3 Base Software (DMS/MSL)	Y	3,980.00	D	N/A	N/A
NTZD26AA	Santa Clara	702t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	Y	12,500.00	D	N/A	N/A
NTZD27AA	Santa Clara	1003t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	Y	24,600.00	D	N/A	N/A
NTZE07EA	Santa Clara	CallPilot 2 Voice Channels	Y	4,000.00	D	N/A	N/A
NTZE10HA	Santa Clara	CallPilot Fax Capability - 20 Users	N	1,000.00	D	N/A	N/A
NTZE10JA	Santa Clara	CallPilot 5000 Fax Users	Y	50,000.00	D	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NTZE10KA	Santa Clara	CallPilot Fax Capability - 200 Users	N	4,500.00	D	N/A	N/A
NTZE11HA	Santa Clara	CallPilot Desktop Messaging Capability - 20 Users	N	2,000.00	D	N/A	N/A
NTZE11JA	Santa Clara	CallPilot Desktop Messaging Capability - 5000 Users	Y	125,000.00	D	N/A	N/A
NTZE11KA	Santa Clara	CallPilot Desktop Messaging Capability - 200 Users	N	11,000.00	D	N/A	N/A
NTZE12HA	Santa Clara	CallPilot Speech Activated Messaging Capability - 20 Users	N	3,000.00	D	N/A	N/A
NTZE12JA	Santa Clara	CallPilot Speech Activated Messaging Capability - 5000 Users	Y	130,000.00	D	N/A	N/A
NTZE12KA	Santa Clara	CallPilot Speech Activated Messaging Capability - 200 Users	N	14,000.00	D	N/A	N/A
NTZE13DA	Santa Clara	CallPilot Networking (EN, AMIS, VPIM) 1 to 96 Channels	Y	8,000.00	D	N/A	N/A
NTZE14DA	Santa Clara	CallPilot NMS Networking, 1 to 96 Channels	Y	5,000.00	D	N/A	N/A
NTZE19AA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 20 Users	Y	1,000.00	D	N/A	N/A
NTZE19BA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 50 Users	Y	2,000.00	D	N/A	N/A
NTZE19CA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 100 Users	Y	3,500.00	D	N/A	N/A
NTZE19DA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 200 Users	Y	6,000.00	D	N/A	N/A
NTZE19EA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 500 Users	Y	12,500.00	D	N/A	N/A
NTZE19FA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 1000 Users	Y	22,000.00	D	N/A	N/A
NTZE19GA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 5000 Users	Y	100,000.00	D	N/A	N/A
NTZE19HA	Santa Clara	CallPilot Multimedia Mailboxes with Voice - 10,000 Users	Y	165,000.00	D	N/A	N/A
NTZE25CA	Santa Clara	CallPilot Conversion 4 Voice Channels to 2 Fax Channels	Y	500.00	D	N/A	N/A
NTZE25DA	Santa Clara	CallPilot Conversion 4 Voice Channels to 1 Speech Channel	Y	500.00	D	N/A	N/A
NTZE26CA	Santa Clara	CallPilot Conversion 2 Fax Channels to 4 Voice Channels	Y	500.00	D	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
NTZE27CA	Santa Clara	CallPilot Conversion 1 Speech Channel to 4 Voice Channels	Y	500.00	D	N/A	N/A
NTZE29BA	Santa Clara	CallPilot to Lucent (2 Wire) Integration	N	5,000.00	D	N/A	N/A
NTZE29CA	Santa Clara	CallPilot to Siemens/Rolm Integration	N	4,000.00	D	N/A	N/A
NTZE29DA	Santa Clara	CallPilot to Mitel Integration	N	4,000.00	D	N/A	N/A
NTZE29EA	Santa Clara	CallPilot to Nortel SL-100 Integration	N	5,000.00	D	N/A	N/A
NTZE31AA	Santa Clara	IPE CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	Y	80.00	D	N/A	N/A
NTZE31BA	Santa Clara	Tower/Rack CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	Y	85.00	D	N/A	N/A
NTZE39BA	Santa Clara	CallPilot 1.07 to Lucent (2 Wire) Integration Software	Y	No charge		N/A	N/A
NTZE39CA	Santa Clara	CallPilot 1.07 to Siemens/Rolm Integration Software	Y	No charge		N/A	N/A
NTZE39DA	Santa Clara	CallPilot 1.07 to Mitel Integration Software	Y	No charge		N/A	N/A
NTZE39EA	Santa Clara	CallPilot 1.07 to SL-100 Integration Software	Y	No charge		N/A	N/A
NTZE4001	Santa Clara	CallPilot 1.07 New System Ordering Code	N	No charge		N/A	N/A
NTZE4002	Santa Clara	CallPilot 1.07 Upgrade Ordering Code	N	No charge		N/A	N/A
NTZE4003	Santa Clara	CallPilot Platform Migration Order Code	N	No charge		N/A	N/A
NTZE4004	Santa Clara	CallPilot Bulk - System Order Code	N	No charge		N/A	N/A
NTZE80AA	Santa Clara	CallPilot 1.07 IPE Base Package	Y	9,000.00	D	N/A	N/A
NTZE81AA	Santa Clara	CallPilot 1.07 702t Base Package	Y	21,000.00	D	N/A	N/A
NTZE82AA	Santa Clara	CallPilot 1.07 1001rp DC Base Package	Y	51,000.00	D	N/A	N/A
NTZE83AA	Santa Clara	CallPilot 1.07 1001rp AC Base Package	Y	51,000.00	D	N/A	N/A
NTZE99BA	Santa Clara	CallPilot 1.07 GB, DSE Connectivity Option - Lucent 2 Wire	N	No charge		N/A	N/A
NTZE99CA	Santa Clara	CallPilot 1.07 GB, DSE Connectivity Option - Siemens/ROLM	N	No charge		N/A	N/A
NTZE99DA	Santa Clara	CallPilot 1.07 GB, DSE Connectivity Option - Mitel	N	No charge		N/A	N/A
NTZE99EA	Santa Clara	CallPilot 1.07 GB, T1 (SL-100) Connectivity Option - SL-100	N	No charge		N/A	N/A
P0905783	Santa Clara	CallPilot 1.07 Installation and configuration Switch Set Up	N	10.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Order Loc	Description	Vol Dsct Ind	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
P0905786	Santa Clara	CallPilot 1.07 200i Installation and Configuration Server Hardware Guide	N	30.00	H	N/A	N/A
P0905787	Santa Clara	CallPilot 702t Installation and Configuration Server Hardware - Part 2	N	30.00	H	N/A	N/A
P0905789	Santa Clara	CallPilot 1.07 Planning and Engineering Guide	N	15.00	H	N/A	N/A
P0905790	Santa Clara	CallPilot 1.07 Getting Started Guide	N	10.00	H	N/A	N/A
P0905791	Santa Clara	CallPilot 1.07 Monitoring and Security for Administrators	N	22.00	H	N/A	N/A
P0905796	Santa Clara	CallPilot 1.07 Administrators Guide	N	60.00	H	N/A	N/A
P0905797	Santa Clara	CallPilot 1.07 Client Software Installation	N	35.00	H	N/A	N/A
P0905798	Santa Clara	CallPilot 1.07 Reporter Guide	N	15.00	H	N/A	N/A
P0905799	Santa Clara	CallPilot 1.07 Applications Builder Guide	N	50.00	H	N/A	N/A
P0905800	Santa Clara	CallPilot 1.07 Meridian Mail to CallPilot Migration Guide	N	15.00	H	N/A	N/A
P0905810	Santa Clara	CallPilot 1.07 Desktop Messaging Software Installation and Maintenance Guide	N	15.00	H	N/A	N/A
P0910806	Santa Clara	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (Paper)	N	20.00	H	N/A	N/A
P0911675	Santa Clara	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	Y	50.00	H	N/A	N/A
P0912864	Santa Clara	Meridian IP Telecommuter NTP	N	15.00	H	N/A	N/A
P0913184	Santa Clara	CallPilot 1.07 Feature Operations Video	Y	115.00	H	N/A	N/A
P0914300	Santa Clara	Installation Flowchart and Worksheets - Part 1 (English)	N	20.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

IV. Price changes

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
A0601464	Modem Cable, 10 Ft. DB9 Female to DB25 Male	25.00	D	40.00	H
A0627875	Cleaning Cartridge	115.00	D	80.00	H
A0648372	4 Ft. Ethernet Cable, Category 5	10.00	D	25.00	H
A0648374	2 Ft. Ethernet Cable, Category 5	10.00	D	25.00	H
A0648375	7 Ft. Ethernet Cable, Category 5	10.00	D	25.00	H
A0648377	10 Ft. Ethernet Cable, Category 5	10.00	D	25.00	H
A0648378	15 Ft. Ethernet Cable, Category 5	10.00	D	25.00	H
A0648379	25 Ft. Ethernet Cable, Category 5	15.00	D	25.00	H
A0676108	DC Power Supply for Rack Cabinet	1,025.00	D	1,600.00	D
A0677506	Dry Clean Cartridge	150.00	D	50.00	H
A0677508	13GB Data Cartridge	170.00	D	110.00	H
A0681164	Alarm Status Module	1,180.00	D	600.00	D
A0681326	Hot-Swap Fan Assembly	580.00	D	720.00	D
A0683743	Video Card Adapter	310.00	D	430.00	D
A0684822	F/F Wide to Narrow SCSI Cable Adapter	140.00	D	200.00	D
A0685305	Floppy Cable	35.00	D	85.00	D
A0723663	48V DC 400W Load Sharing Hot Swap Power Supply	3,580.00	D	5,000.00	D
A0725949	DC Power Cable for PS400-48 Power Supply	160.00	D	190.00	D
A0729069	M/M Wide-Nar SCSI Adapter	150.00	D	125.00	H
A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems	80.00	D	110.00	D
A0738130	128MB DIMM	800.00	D	600.00	D
A0741561	300W Power Supply	155.00	H	500.00	H
A0741572	Floppy Cable	35.00	D	80.00	D
A0741574	702t OEM System With no Processor and no Memory	2,500.00	H	N/A	N/A
A0741576	Fan Assembly	10.00	H	27.00	H
A0744456	CallPilot 128 MB DIMM	1,090.00	D	3,700.00	D
A0761148	702t CPU 450 MHz Pentium II	1,390.00	H	900.00	H
A0766163	CallPilot DSE Extender Cable - 100 Ft.	200.00	D	170.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
A0766997	Wide SCSI Terminator	55.00	D	80.00	D
A0769310	14 Foot, Shielded Ethernet Cable	25.00	D	30.00	D
A0769312	SCSI Adapter	50.00	D	70.00	D
A0780247	Data Cartridge	85.00	D	80.00	D
A0788129	Shielded 9-Drop Wide SCSI Cable	320.00	D	550.00	D
A0788131	9 Drop SC Bus Cable	30.00	D	65.00	D
A0797692	SYMPOSIUM Call Center Server 1003t System Board PCA	3,050.00	H	N/A	N/A
A0797705	SYMPOSIUM Call Center Server 1003t Input/Output PCA	1,650.00	H	N/A	N/A
A0797722	SYMPOSIUM Call Center Server 1003t Voltage Regulator Module	118.00	H	N/A	N/A
A0797724	SYMPOSIUM Call Center Server 1003t Memory PCA	165.00	H	N/A	N/A
A0797727	SYMPOSIUM Call Center Server 1003t NetServer Hot-Swap Ultra2 Internal Storage Cage	690.00	H	N/A	N/A
A0797938	SYMPOSIUM Call Center Server 1003t 256MB 50ns EDO DIMM Kit (4x64MB)	1,650.00	H	N/A	N/A
A0797941	Rack Rails	340.00	D	230.00	D
A0797948	SYMPOSIUM Call Center Server 1003t Fan Assembly for Input/Output, Retainer	76.00	H	N/A	N/A
A0797950	SYMPOSIUM Call Center Server 1003t Fan Assembly for System Board	52.00	H	N/A	N/A
A0798087	SYMPOSIUM Call Center Server 1003t PCI Ethernet Adapter	135.00	H	N/A	N/A
A0798092	SYMPOSIUM Call Center Server 1003t Wide SCSI Host Adapter Board	165.00	H	N/A	N/A
A0798155	SYMPOSIUM Call Center Server 1003t Internal SCSI Input/Output Cable	121.00	H	N/A	N/A
A0798177	SYMPOSIUM Call Center Server 1003t Fan Assembly for CPU	52.00	H	N/A	N/A
A0798258	SYMPOSIUM Call Center Server 1003t NetServer Keyboard	205.00	H	N/A	N/A
A0798259	SYMPOSIUM Call Center Server 1003t 1.44MB Floppy Disk Drive	78.00	H	N/A	N/A
A0798260	SYMPOSIUM Call Center Server 1003t Mini-DIN Mouse	65.00	H	N/A	N/A
A0800927	SYMPOSIUM Call Center Server 1003t 32x MAX EIDE CD-ROM Drive	203.00	H	N/A	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
A0801312	SYMPOSIUM Call Center Server 1003t Processor Terminator	52.00	H	N/A	N/A
A0805092	Pentium III SBC 500MHz CPU	2,600.00	D	6,000.00	D
A0805434	Power Supply AC - 500 Watts	1,750.00	D	3,800.00	D
A0806019	IDE Cable to CD ROM	180.00	D	250.00	D
AS1074	DTI/PRI Package	4,160.00	H	4,160.00	I
NT2F78AA	Feature Card Label Sheet (M3901, Package of 25 P0906396)	35.00	D	15.00	D
NT2F79AA	Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627)	50.00	H	41.00	H
NT2F80AA	Meridian M3905 User Guide, Release 1 (Package of 15 P0903629)	40.00	H	30.00	H
NT2F83AA	Telephone Number Sheet (M3900 Series, Package of 15 P0888695)	50.00	D	25.00	D
NT4N65AB	cPCI Core Network Interface Card (2 Ports)	2,200.00	I	N/A	N/A
NT4N66AB	cPCI Core Network Interface Transition Card	500.00	I	N/A	N/A
NT5D12AG	Dual Port DTI/PRI (DDP) Card	11,500.00	I	N/A	N/A
NT5G95AA	PCMCIA Flash Card Upgrade, MIPCD	400.00	H	N/A	N/A
NT8D14BB	Universal Trunk Card	3,950.00	I	4,300.00	I
NT8D15AK	E&M Trunk Card	2,933.00	I	5,200.00	I
NT9F27AC	SYMPOSIUM Call Center Server 1003t Peripherals Package	535.00	H	N/A	N/A
NT9F90AA	SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51	20,370.00	H	N/A	N/A
NT9F90BA	SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0	20,370.00	H	N/A	N/A
NTAK09DA	DTI/PRI Card	4,000.00	H	4,000.00	I
NTAK1305	SCSI Cable (6 Ft.)	115.00	D	140.00	D
NTDK57AA	Dongle	10.00	D	N/A	N/A
NTDK92BA	Mini Chassis Expander	2,500.00	I	1,500.00	I
NTLH16AA	Meridian IP Telecommuter NTP CD ROM	10.00	H	N/A	N/A
NTMN16AA66	Brandline Insert, Platinum (Package of 250 P0904456, M3900 Series)	180.00	H	40.00	H
NTMN16AA70	Brandline Insert, Charcoal (Package of 250 P0904455, M3900 Series)	180.00	H	40.00	H
NTMN17AA66	Handset, Platinum (M3900 Series)	40.00	D	20.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTMN17AA70	Handset, Charcoal (M3900 Series)	40.00	D	20.00	D
NTMN18AA66	Handset Kit, Platinum (M3905)	42.00	D	25.00	D
NTMN18AA70	Handset Kit, Charcoal (M3905)	42.00	D	25.00	D
NTMN71AA66	Meridian Accessory Connection Module (ACM), Platinum (M3900 Series)	35.00	D	25.00	D
NTMN71AA70	Meridian Accessory Connection Module (ACM), Charcoal (M3900 Series)	35.00	D	25.00	D
NTRG14AC	CallPilot 1.07 Networking Package	100.00	H	200.00	H
NTRH01AA	CallPilot MPC-8	500.00	D	600.00	D
NTRH0910	Break Interconnect Cable (6 Ft.)	150.00	D	215.00	D
NTRH0911	Cable Assembly, Breakout Box Interconnect-Cable, 15 Ft.	150.00	D	200.00	D
NTRH09AA	Breakout Panel Assembly	370.00	D	750.00	D
NTRH1405	CallPilot Internal Ethernet Cabling (IPE System)	30.00	D	42.00	D
NTRH1406	CallPilot Token Ring Cabling (IPE System)	125.00	D	165.00	D
NTRH1407	CallPilot Intermediate SCSI Cable	180.00	D	250.00	D
NTRH1408	CallPilot Intermediate SCSI Cable	110.00	D	150.00	D
NTRH1409	CallPilot Intermediate SCSI Cable	110.00	D	160.00	D
NTRH14AA	200 Series Base System Assembly	3,620.00	D	15,000.00	D
NTRH16BA	Hard Drive Data Cable	35.00	D	45.00	D
NTRH20AB	CallPilot MPB-16	2,300.00	D	N/A	N/A
NTRH20BA	MPB 16-4	2,300.00	D	7,000.00	D
NTRH8027	Windows NT 4.0 OS Recovery CD	10.00	D	15.00	D
NTRH8033	Windows NT 4.0 Install Diskette	10.00	D	15.00	D
NTRH9004	3.5" EIDE Floppy Drive	70.00	H	120.00	H
NTRH9007	SCSI RAID Controller	2,180.00	H	3,260.00	H
NTRH9010	PCI Token Ring Network Card	520.00	D	520.00	H
NTRH9011	14" SVGA Color Monitor	380.00	D	380.00	H
NTRH9013	OIVR 2 x Hardware - Keyboard	60.00	D	60.00	H
NTRH9014	Three Button Mouse	90.00	D	90.00	H
NTRH9016	External Modem 33.6	280.00	D	450.00	H
NTRH9032	700 Series DC Power Converter	3,000.00	D	6,500.00	D
NTRH9034	Backup Tape Drive	3,000.00	D	3,400.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTRH9035	IDE CD-ROM Drive	275.00	H	350.00	H
NTRH9036	CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack	250.00	D	425.00	D
NTRH9038	CallPilot External SCSI Tape Drive, 4GB (IPE System)	1,900.00	D	4,000.00	D
NTRH9039	CallPilot Ethernet Adaptor PCMCIA (IPE System)	390.00	D	600.00	D
NTRH9040	Callpilot Token Ring Adapter PCMCIA (IPE System)	750.00	D	1,000.00	D
NTRH9049	4 GB IDE Drive for the 200i System	370.00	D	600.00	D
NTRH9053	9 GB Disk Hot Swap	1,100.00	D	2,400.00	D
NTRH9054	9 GB SCSI Disk	1,120.00	D	2,250.00	D
NTRH9057	VTG VB2002	5,000.00	D	500.00	D
NTRH9059	VTG VB2007	5,000.00	D	500.00	D
NTRH9068	Dual Pentium III SBC	6,950.00	D	19,000.00	D
NTRH9069	Transceiver (MAU to 10 Base T)	95.00	D	200.00	D
NTRH9100	SYMPOSIUM Call Center Server 1003t Base System	15,590.00	H	N/A	N/A
NTSF8519	Enable Package 381, 382 for M3900 Sets Phase II	No charge		N/A	N/A
NTSF8722	Option 11C Software Rls 24C Upissue Key-code	500.00	H	N/A	N/A
NTSK11BC	Option 11C Release 22.46 Programmed PCM-CIA Card	1,500.00	I	1,050.00	I
NTSW31AA	Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08)	650.00	H	N/A	N/A
NTUB16AA	CallPilot External Modem Kit	300.00	D	700.00	D
NTUB51AA	CallPilot Token Ring LAN Kit - IPE Systems	870.00	D	1,500.00	D
NTUB52AA	CallPilot Ethernet LAN Connection Kit - IPE Systems	415.00	D	800.00	D
NTUB53AA	CallPilot External Tape Drive - IPE Systems	2,240.00	D	4,500.00	D
NTUB54AA	CallPilot Recovery Kit - IPE	1,060.00	D	2,000.00	D
NTUB55AA	CallPilot Tower/Rack Internal Tape Drive Kit	5,200.00	D	5,000.00	D
NTUB56AA	CallPilot 14" Monitor Kit	600.00	D	950.00	D
NTUB58AA	CallPilot 700 Series RAID Kit	5,000.00	D	9,000.00	D
NTUB59AA	CallPilot CD ROM Drive	700.00	D	800.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTV412RA	AP Redundancy - 1 Voice Port RTU for 1 AP	170.00	H	95.00	H
NTV450CA	Custom Cell Builder RTU - 1 AP (or MRS/ AP)	2,670.00	D	2,185.00	D
NTV450MA	Development License Upgrade - 1 to 4 Users	22,810.00	D	15,700.00	D
NTV450PA	Prompt Manager and Loading Tool - 1 AP (or MRS/AP)	2,560.00	D	1,900.00	D
NTV450SA	Development License - 1 User	20,810.00	D	10,980.00	D
NTV454VA	Host Connectivity Software - VT100 - 16 Session Base RTU	7,550.00	D	6,275.00	D
NTV454WA	Host Connectivity Software - VT100 - 16 Session RTU Expansion	7,550.00	D	6,275.00	D
NTV457PA	PureSpeech Recite Development Kit - 1 AP RTU	16,370.00	H	13,700.00	H
NTV460SA	Software-Based Disk Mirroring License RTU - OIVR 4.0 AP, MRS, or MRS/AP	3,490.00	H	2,300.00	H
NTV461NA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America	23,520.00	H	15,400.00	H
NTV461PA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America - Pulse Detection	26,360.00	H	18,150.00	H
NTV462NA	Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America	33,620.00	H	21,780.00	H
NTV464NA	Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA	6,250.00	H	4,070.00	H
NTV467LA	Fax - Gammalink - 12 Port Card and 12 Port RTU	34,170.00	D	22,500.00	D
NTV467MA	Fax - Gammalink - 6 Port Card and 6 Port RTU	17,610.00	D	11,700.00	D
NTV467SA	Fax - Gammalink - 4 Port Card and 4 Port RTU	12,810.00	D	8,800.00	D
NTV468CA	Text to Speech - TrueVoice - Base Card and 2 Port RTU	14,200.00	D	12,400.00	D
NTV468LA	Text to Speech - L and H - Base Card and 6 Port RTU	22,520.00	D	17,800.00	D
NTV468PA	Speech Recognition - PureSpeech Recite - Continuous Digits - Base Card and 2 Port RTU	15,000.00	D	13,100.00	D
NTV468QA	Speech Recognition - PureSpeech Recite - Lite - Base Card and 2 Port RTU	18,790.00	D	16,450.00	D
NTV468RA	Speech Recognition - PureSpeech Recite - Pro - Base Card and 2 Port RTU	21,600.00	D	18,900.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTV468SA	Speech Recognition - PureSpeech Recite - IQ - Base Card and 2 Port RTU	24,250.00	D	21,000.00	D
NTV468TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - Base Card and 2 Port RTU	15,610.00	D	13,400.00	D
NTV468UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - Base Card and 2 Port RTU	20,160.00	D	17,200.00	D
NTV468VA	Speech Recognition - VCS for Antares - Discrete - Base Card and 4 Port RTU	18,670.00	D	16,100.00	D
NTV468WA	Speech Recognition - VCS for Antares - Continuous - Base Card and 2 Port RTU	14,960.00	D	13,000.00	D
NTV468YA	Speech Recognition - PureSpeech Recite - LA Spanish - Pro - Base Card and 2 Port RTU	23,540.00	D	20,000.00	D
NTV468ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - Base Card and 2 Port RTU	26,710.00	D	22,600.00	D
NTV469CA	Text to Speech - TruVoice - 2 Port RTU Expansion	5,420.00	D	4,550.00	D
NTV469LA	Text to Speech - L and H - 6 Port RTU Expansion	13,010.00	D	9,900.00	D
NTV469PA	Speech Recognition - PureSpeech - Continuous Digits - 2 Port RTU Expansion	6,220.00	D	5,375.00	D
NTV469QA	Speech Recognition - PureSpeech Recite - Lite - 2 Port RTU Expansion	10,010.00	D	8,750.00	D
NTV469RA	Speech Recognition - PureSpeech Recite - Pro - 2 Port RTU Expansion	12,830.00	D	11,200.00	D
NTV469SA	Speech Recognition - PureSpeech Recite - IQ - 2 Port RTU Expansion	15,470.00	D	13,600.00	D
NTV469TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	6,840.00	D	5,700.00	D
NTV469UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - 2 Port RTU Expansion	11,380.00	D	9,500.00	D
NTV469VA	Speech Recognition - VCS for Antares - Discrete - 4 Port RTU Expansion	9,890.00	D	8,200.00	D
NTV469WA	Speech Recognition - VCS for Antares - Continuous - 2 Port RTU Expansion	6,180.00	D	5,150.00	D
NTV469YA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	14,770.00	D	12,300.00	D
NTV469ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - 2 Port RTU Expansion	17,940.00	D	14,900.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTZC35AA	Meridian 1 Attendant Hospitality Services 1 Console Bundle	9,000.00	D	13,700.00	D
NTZC35CA	Meridian 1 Attendant Hospitality Services 3 Console Bundle	28,500.00	D	31,000.00	D
NTZC35DA	Meridian 1 Attendant Hospitality Services Large (4) Console Bundle	37,000.00	D	55,000.00	D
NTZC35EA	Meridian 1 Attendant Hospitality Services Large Expansion Bundle	7,000.00	D	8,000.00	D
NTZC36AA	Meridian 1 Attendant Hospitality Services 1 Console Software Bundle	6,000.00	D	9,200.00	D
NTZC36CA	Meridian 1 Attendant Hospitality Services 3 Console Software Bundle	15,000.00	D	15,780.00	D
NTZC36DA	Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle	25,000.00	D	35,280.00	D
NTZC37BA	Meridian 1 Attendant Hospitality Services Software for Expansion from 2 to 3 Console Bundle	7,000.00	D	10,000.00	D
NTZC37CA	Meridian 1 Attendant Hospitality Services Software for Expansion from 3 to 4 Console Bundle	10,000.00	D	20,000.00	D
NTZD27AA	1003t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	24,600.00	D	N/A	N/A
NTZE07AA	CallPilot 4 Voice Channels	8,000.00	D	14,000.00	D
NTZE07BA	CallPilot 2 FAX Channels	8,000.00	D	7,000.00	D
NTZE07CA	CallPilot 1 Speech Activated Messaging Channel	8,000.00	D	7,000.00	D
NTZE10AA	CallPilot FAX Capability -20 Users	1,000.00	D	250.00	D
NTZE10BA	CallPilot FAX Capability - 50 Users	1,500.00	D	1,000.00	D
NTZE10CA	CallPilot FAX Capability - 100 Users	2,500.00	D	1,500.00	D
NTZE10DA	CallPilot FAX Capability - 200 Users	4,500.00	D	2,000.00	D
NTZE10EA	CallPilot FAX Capability - 500 Users	8,000.00	D	7,500.00	D
NTZE10FA	CallPilot FAX Capability - 1000 Users	14,000.00	D	10,000.00	D
NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	2,000.00	D	500.00	D
NTZE11BA	CallPilot Desktop Messaging Capability - 50 Users	3,500.00	D	2,000.00	D
NTZE11CA	CallPilot Desktop Messaging Capability - 100 Users	6,000.00	D	3,500.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	New CLP	Distr. Disc.	Old CLP	Distr. Disc.
NTZE11DA	CallPilot Desktop Messaging Capability - 200 Users	11,000.00	D	6,000.00	D
NTZE12AA	CallPilot Speech Activated Messaging Capability - 20 Users	3,000.00	D	500.00	D
NTZE12BA	CallPilot Speech Activated Messaging Capability - 50 Users	4,500.00	D	2,250.00	D
NTZE12CA	CallPilot Speech Activated Messaging Capability - 100 Users	7,500.00	D	4,000.00	D
NTZE12DA	CallPilot Speech Activated Messaging Capability - 200 Users	14,000.00	D	7,000.00	D
NTZE12EA	CallPilot Speech Activated Messaging Capability - 500 Users	32,000.00	D	30,000.00	D
NTZE12FA	CallPilot Speech Activated Messaging Capability - 1000 Users	53,000.00	D	50,000.00	D
NTZE26BA	CallPilot Conversion 2 Fax Channels to 1 Speech Channel	500.00	D	.00	H
NTZE27AA	CallPilot Conversion 1 Speech Channel to 2 Fax Channels	500.00	D	.00	H
P0684414	Hard Drive Power Cable	17.00	D	25.00	D
P0886144	CallPilot Network Planning Guide	20.00	H	30.00	H
P0886145	CallPilot NMS Installation and Administration Guide	20.00	H	30.00	H
P0886146	CallPilot AMIS Installation and Administration Guide	20.00	H	30.00	H
P0886147	CallPilot Enterprise Networking Installation and Administration Guide	20.00	H	30.00	H
P0886148	CallPilot Integrated AMIS Installation and Administration Guide	20.00	H	30.00	H
P0886149	CallPilot VPIM Networking Package	20.00	H	30.00	H
P0911675	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	50.00	H	N/A	N/A
P0912864	Meridian IP Telecommuter NTP	15.00	H	N/A	N/A
SVC0001	Meridian 1 Security Audit Per Hour	200.00	H	175.00	H
SVC0007	Meridian 1 Security Consulting per day plus travel and expense	1,600.00	H	1,500.00	H
SVC0010	Meridian 1 Security Seminar (per day) Plus Travel and Expense for One Consultant	1,750.00	H	1,275.00	H
SW0229D	Meridian 911	50,000.00	I	4,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

V. Description changes

Order Code	Old description	New description
NTDR69AA	iRemote 9150 Unit	Remote Office 9150 Unit
NTDR81AA	iRemote Product CD-ROM Package	Remote Office Product CD-ROM Package
NTDR83AA	iRemote Technical Training CD-ROM Package	Remote Office Technical Training CD-ROM Package
NTDR84AA	iRemote 9150 Installation and Administration Guide	Remote Office 9150 Installation and Administration Guide
NTDR87AA	iRemote 9150 Universal Power Supply	Remote Office 9150 Universal Power Supply
NTQR05AA	iRemote 9150 8-User VoIP Package - 16 RLC	Remote Office 9150 8-User VoIP Package - 16 RLC
NTQR06AA	iRemote 9150 8-User Starter Package - 16 RLC	Remote Office 9150 8-User Starter Package - 16 RLC
NTQR07AA	iRemote 9150 8-User Starter Package - 32 RLC Option 51-81	Remote Office 9150 8-User Starter Package - 32 RLC Option 51-81
NTQR08AA	iRemote 9150 8-User Starter Package - 32 RLC Option 11	Remote Office 9150 8-User Starter Package - 32 RLC Option 11
NTQR09AA	iRemote 9150 Branch Expansion Package	Remote Office 9150 Branch Expansion Package
NTQR10AA	iRemote 9150 8-User Expansion Package	Remote Office 9150 8-User Expansion Package
NTRH9057	Rolm/Siemens 8 Channel Card	VTG VB2002
NTRH9059	Mitel 8 Channel Card	VTG VB2007
NTSK11BA	Option 11C Release 22.08 Programmed 40 MB PCMCIA Card	Option 11C Release 22.08 Programmed PCMCIA Card
NTSK11BB	Option 11C Release 22.16 Programmed 40 MB PCMCIA Card	Option 11C Release 22.16 Programmed PCMCIA Card
NTSK11BC	Option 11C Release 22.46 Programmed 40 MB PCMCIA Card	Option 11C Release 22.46 Programmed PCMCIA Card
NTSK11BF	Option 11C Release 23.18 Programmed 40 MB PCMCIA Card	Option 11C Release 23.18 Programmed PCMCIA Card
NTSK11BG	Option 11C Release 23.35 Programmed 40 MB PCMCIA Card	Option 11C Release 23.35 Programmed PCMCIA Card
NTSK11BH	Option 11C Release 23.55 Programmed 40MB PCMCIA Card	Option 11C Release 23.55 Programmed PCMCIA Card
NTSK11BK	Option 11C Release 24.24 Programmed 40MB PCMCIA Card	Option 11C Release 24.24 Programmed PCMCIA Card
NTSK11BN	Option 11C Release 25 Programmed 40MB PCMCIA Card	Option 11C Release 25 Programmed PCMCIA Card
NTZD02AA	SYMPOSIUM Server, 702t Advanced	SYMPOSIUM Call Center Server, 702t Advanced with Windows NT 3.51

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Old description	New description
NTZD02BA	SYMPOSIUM Call Center Server, 702t Advanced with RAID	SYMPOSIUM Call Center Server, 702t Advanced with RAID with Windows NT 3.51
NTZE10AA	CallPilot FAX Capability - 5 Users	CallPilot FAX Capability -20 Users
NTZE10BA	CallPilot FAX Capability - 25 Users	CallPilot FAX Capability - 50 Users
NTZE10CA	CallPilot FAX Capability - 50 Users	CallPilot FAX Capability - 100 Users
NTZE10DA	CallPilot FAX Capability - 100 Users	CallPilot FAX Capability - 200 Users
NTZE11AA	CallPilot Desktop Messaging Capability - 5 Users	CallPilot Desktop Messaging Capability - 20 Users
NTZE11BA	CallPilot Desktop Messaging Capability - 25 Users	CallPilot Desktop Messaging Capability - 50 Users
NTZE11CA	CallPilot Desktop Messaging Capability - 50 Users	CallPilot Desktop Messaging Capability - 100 Users
NTZE11DA	CallPilot Desktop Messaging Capability - 100 Users	CallPilot Desktop Messaging Capability - 200 Users
NTZE12AA	CallPilot Speech Activated Messaging Capability - 5 Users	CallPilot Speech Activated Messaging Capability - 20 Users
NTZE12BA	CallPilot Speech Activated Messaging Capability - 25 Users	CallPilot Speech Activated Messaging Capability - 50 Users
NTZE12CA	CallPilot Speech Activated Messaging Capability - 50 Users	CallPilot Speech Activated Messaging Capability - 100 Users
NTZE12DA	CallPilot Speech Activated Messaging Capability - 100 Users	CallPilot Speech Activated Messaging Capability - 200 Users
P0886145	CallPilot Installation and Administration Guide	CallPilot NMS Installation and Administration Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

VI. Package content adjustments

Order Code	Description	Act	Qty	Item Order Code
A0741574	702t OEM System With no Processor and no Memory	Delete	1	A0741561
		Delete	1	A0741572
		Delete	1	A0741576
		Delete	1	A0806019
		Delete	1	NTRH9004
		Delete	1	NTRH9035
NTHF35AA	SYMPOSIUM Express Call Center LAN Package Option 11C	Delete	1	A0383333
		Add	1	NTRH9069
NTHF36AA	SYMPOSIUM Express Call Center LAN Package, Options 61C-81C	Delete	2	A0383333
		Add	2	NTRH9069
NTHF69AA	Symposium Express Call Center LAN Package, 51C	Delete	1	A0383333
		Add	1	NTRH9069
NTHU24AC	Option 81C from Option 61C (NT5D21) Upgrade AC	Add	1	NT5F36AA
		Delete	1	NT5F37AA
NTHU24DC	Option 81C from Option 61C (NT5D21) Upgrade DC	Add	1	NT5F36AA
		Delete	1	NT5F37AA
NTHY01AA	Option 81C (CP PII) Systems Spares Package	Delete	1	NT4N65AA
		Add	1	NT4N65AB
NTMW18BA	Meridian Mail Compact Option Releaes 13 Software Package	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTSF6501	Option 11C Compact to Option 11C Migration Package	Delete	1	NTTK31AA
NTSF8011	Option 11C Mini General Business Software Package	Delete	1	NTSK11CN
		Add	1	NTSK11CP
NTSF8012	Option 11C Mini Enhanced Business Software Package	Delete	1	NTSK11DN
		Add	1	NTSK11DP
NTSF8013	Option 11C Mini Enterprise Business Software Package	Delete	1	NTSK11EN
		Add	1	NTSK11EP
NTSF8014	Option 11C Mini NAS/VNS Software Package	Delete	1	NTSK11FN
		Add	1	NTSK11FP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Act	Qty	Item Order Code
NTSF8020	Option 11C General Business Software Package	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11CN
		Add	1	NTSK11CP
NTSF8021	Option 11C Enhanced Business Software Package	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11DN
		Add	1	NTSK11DP
NTSF8022	Option 11C Enterprise Software Package	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11EN
		Add	1	NTSK11EP
NTSF8023	Option 11C NAS/VNS Software Package	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11FN
		Add	1	NTSK11FP
NTSF8028	Option 11/11E to Option 11C General Business Software Upgrade	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11CN
		Add	1	NTSK11CP
NTSF8029	Option 11/11E to Option 11C Enhanced Business Software Upgrade	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11DN
		Add	1	NTSK11DP
NTSF8030	Option 11/11E to Option 11C Enterprise Software Upgrade	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11EN
		Add	1	NTSK11EP
NTSF8031	Option 11/11E to Option 11C NAS/VNS Software Upgrade	Delete	1	NTSK11AN
		Add	1	NTSK11AP
		Delete	1	NTSK11FN

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Act	Qty	Item Order Code
		Add	1	NTSK11FP
NTSF8048	Option 11C General Business Software Feature Upgrade	Delete	1	NTSK11CN
		Add	1	NTSK11CP
NTSF8049	Option 11C Enhanced Business Software Feature Upgrade	Delete	1	NTSK11DN
		Add	1	NTSK11DP
NTSF8050	Option 11C Enterprise Software Feature Upgrade	Delete	1	NTSK11EN
		Add	1	NTSK11EP
NTSF8051	Option 11C NAS/VNS Software Feature Upgrade	Delete	1	NTSK11FN
		Add	1	NTSK11FP
NTSZ00AC	Option 81C 68060 Enhanced Call Process New System Pkg AC (IGS Network Included)	Add	1	NT5F36AA
NTSZ00DC	Option 81C New System Package DC	Add	1	NT5F36AA
		Delete	1	NT5F37AA
NTSZ25AC	Option 81C Call Processor PII New System Package AC (Fiber Network Fabric Included)	Add	2	NT8D80BZ
NTSZ26AC	Option 81C Call Processor PII New System Package AC (IGS Network Included)	Add	2	NT8D80BZ
NTSZ26DC	Option 81C Call Processor PII New System DC (IGS Network Included)	Add	2	NT8D80BZ
NTTS36AA	External RSM Breakout Assembly (4 RS-232 Ports)	Delete	1	NTMW51AA
		Add	1	NTTK44AA
NTUB02AC	CallPilot 1.07 702t Base Hardware Package	Delete	1	A0648379
		Delete	1	A0731666
		Delete	1	A0767488
		Delete	1	NTUB06AC
		Delete	1	P0841936
		Delete	1	P0887450
		Delete	1	P0887451
NTUB03AC	CallPilot 1.07 1001rp AC Base Hardware - 500 Wat	Delete	1	A0648379
		Delete	1	A0767488
		Delete	1	NTUB10AB
		Delete	1	P0841936
		Delete	1	P0887450
		Delete	1	P0887451

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Act	Qty	Item Order Code
NTUB04AC	CallPilot 1.07 1001rp DC Base Hardware Package	Delete	1	A0648379
		Delete	1	A0676108
		Delete	1	A0767488
		Delete	1	NTUB11AB
		Delete	1	P0841936
		Delete	1	P0887450
		Delete	1	P0887451
NTUB06AB	CallPilot 702t Configuration Assembly	Delete	3	NTRH9030
NTUB58AA	CallPilot 700 Series RAID Kit	Delete	1	NTRH8003
NTV201AU	IIVR 2.2 UPS Package	Add	1	A0656287
NTV202AD	1000VA UPS Hardware Spare	Add	1	A0656287
NTZB77AA	Meridian Integrated Personal Call Director, 8 ports 50 users	Add	1	NT5G53AB
		Add	1	P0914163
		Add	1	P0914505
NTZB78AA	Meridian Integrated Personal Call Director, 16 ports 100 users	Add	1	NT5G53AB
		Add	1	P0886008
		Add	1	P0914163
		Add	1	P0914505
NTZB79AA	Meridian Integrated Personal Call Director, 24 ports 150 users	Add	1	NT5G53AB
		Add	1	P0886009
		Add	1	P0914163
		Add	1	P0914505
NTZB80AA	Meridian Integrated Personal Call Director, 32 ports 200 users	Add	1	NT5G53AB
		Add	1	P0886010
		Add	1	P0914163
		Add	1	P0914505
NTZC57AA	Meridian Mail Release 13 Base Software	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZC57BA	Meridian Mail EC11 Base Software, Release 13	Delete	1	NT6R47AA
NTZC58AA	Meridian Mail Mini Option, 2 Ports, 2 Hours Package	Delete	1	NT6R16AA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Act	Qty	Item Order Code
		Add	1	NT6R16AB
NTZC58BA	Meridian Mail Mini Option, 4 Ports, 5 Hours Package	Delete	1	NT6R16AA
		Add	1	NT6R16AB
NTZC58CA	Meridian Mail Mini Option, 8 Ports, 5 Hours Package	Delete	1	NT6R16AA
		Add	1	NT6R16AB
NTZD63AA	Meridian Mail Card Option Release 6 to Release 13 Upgrade	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD63BA	Meridian Mail Card Option Release 8/9/10/11/12 to Release 13 Upgrade	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD65AA	Meridian Mail EC11 Release 10, 11, or 12 to Release 13 Upgrade	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD67AA	Meridian Mail Release 8, 9, 10, 11, or 12 to Release 13 Migration, Options, Modular Option to Modular EC	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD68AA	Meridian Mail EC Release 8, 9.19 to Release 13 Upgrade	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD68BA	Meridian Mail EC Release 9.58 and Later/Release 10/11/12 to Release 13 Upgrade	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD69AA	Meridian Mail Release 4 to Release 13 Software Migration, GP to Modular GP	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD69BA	Meridian Mail Modular GP Release 5 to Release 13 Upgrade or Migration from GP to Modular GP	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD69CA	Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD69DA	Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD69EA	Meridian Mail Modular GP Release 9/10/11/12 to Release 13 Upgrade or Migration from GP to Modular GP	Delete	1	NT6R47AA
		Add	1	NT6R47AD

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Act	Qty	Item Order Code
NTZD70AA	Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD70BA	Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD70CA	Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD70DA	Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD70EA	Meridian Mail Release 3 to Release 13 Software Migration, from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZD70FA	Meridian Mail Release 4 to Release 13 Software Migration, from Options to Modular Option	Delete	1	NT6R47AA
		Add	1	NT6R47AD
NTZR57CA	Meridian Mail Release 13 Base Software	Delete	1	NT6R47AA
		Add	1	NT6R47AD

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

VII. Volume Discount Indicator Changes

Order Code	Description	Old Volume Discount Ind	New Volume Discount Ind
SW0229D	Meridian 911	N	Y

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Price by Chapter

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Option 11C Compact
System Packages

S § ➤	NTKS1002	Option 11C Compact InterOffice Communications Package	2,150.00	I
S ➤	NTKS1011	Option 11C Compact Advanced Hospitality Communications Package	6,000.00	I
S § ➤	NTKS3001	Meridian Mail Release 12 Compact Option 4 Ports 24 Hours Package	10,000.00	D

Meridian 1 Internet Enabled

S ★ ➤	NTDW80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	80.00	D
S ★ ➤	NTZC80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	6,000.00	D
S ★ ➤	NTZC81AA	Meridian IP Telephony Gateway Line 2.0 Systems Package	6,200.00	D
S ★ ➤ Δ	NTZC82AA	Internet Telephone Software Parameter (Large System)	90.00	D
S ★ ➤ Δ	NTZC84AA	Internet Telephone Software Parameter (Small System)	90.00	D

Optional Component Packages

S ➤	NTKS2001	Option 11C Compact Office Communications Package - Additional 8 TN’s	1,470.00	I
S § ➤	NTKS2002	Option 11C Compact InterOffice Communications Package - Additional 8 TN’s	1,870.00	I
S ➤	NTKS2010	Option 11C Compact Hospitality Communications Expansion TN’s	1,050.00	I
S ➤	NTKS2011	Option 11C Compact Advanced Hospitality Package - Additional 8 TN’s	2,100.00	I
S ➤ Δ	NTKS2020	Option 11C Compact Network Message Communications Expansion TN’s (8). This marketing package provides a keycode which allows 8 additional TN’s for the Network Message Communications Package.	2,057.00	I
S § ➤	NTMW14AA	Option 11C Compact Expansion Cabinet Package	8,000.00	I
S ➤	NTMW14BA	Option 11C Compact Hospitality 10-slot Expansion Cabinet Package	8,000.00	I
S § ➤	NTMW38AA	Mini IPE 1.5MB DTI/PRI Package	2,400.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Upgrade Packages				
S § ➤	NTKS2052	Meridian Mail Release 11 or Release 12 to Release 13 Compact Option Software Upgrade Package. 4 Full Service Ports, 24 hours storage, 2 languages, Voice Menus, Announcements, Auto Attendant, Thru Dial, Integrated Voice Mailbox Admin and Outcalling	1,000.00	D
S ➤	NTKS2500	X27 Software Up-issue (within the same Release)	1,050.00	I
S ➤	NTKS2501	X27 Software Release Upgrade	1,300.00	I
S ➤ Δ	NTSF6501	Option 11C Compact to Option 11C Migration Package	17,355.00	H
Optional Components				
S § ➤	NT5R36AC	Meridian Mail Release 11.19 Software Tape	100.00	D
S § ➤	NTKS9050	DISA Option 11C Compact	No charge	
S ➤	NTKS9051	This code allows the addition software packages to be enabled for Inter-Office Feature Set.	2,000.00	I
S ➤	NTMW01AA	Option 11C Compact System Core Card	4,000.00	I
S § ➤	NTMW02AB	Meridian Mail Compact Option 68K Memory Card	3,600.00	D
S § ➤	NTMW03AA	4-Port DSP Daughter Card	4,500.00	D
S ➤	NTMW04AA	Mini IPE 1.5MB DTI/PRI Card	2,400.00	I
S ➤	NTMW05AA	Mini IPE 24 Port Digital Line Card	2,400.00	I
S ➤	NTMW06AA	Mini IPE 16 Port Analog Line Card	2,400.00	I
S ➤	NTMW07AA	Mini IPE 4 Port Trunk/4 Port Line Card	2,150.00	I
S § ➤	NTMW11AB	Option 11C Compact AC Power Supply	1,460.00	I
S § ➤	NTMW16AA	Meridian Mail Release 11 Compact Option Port Expansion (Ports 5 & 6)	2,700.00	I
S § ➤	NTMW16AB	Meridian Mail Release 12 Compact Option Port Expansion (Ports 5 & 6)	2,700.00	I
S § ➤	NTMW16BA	Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 5 & 6)	2,700.00	I
S § ➤	NTMW17AA	Meridian Mail Release 11 Compact Option Port Expansion (Ports 7&8)	2,700.00	I
S § ➤	NTMW17AB	Meridian Mail Release 12 Compact Option Port Expansion (Ports 7 & 8)	2,700.00	I
S § ➤	NTMW17BA	Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 7 & 8)	2,700.00	I
S ➤	NTMW30AD	Option 11C Compact Release 2.0 Programmed Software Daughterboard	1,420.00	I
S ➤	NTMW30BA	Option 11C Compact Software Delivery Card (PCMCIA) Release 1.00	1,500.00	I
S	NTMW30BB	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.01	1,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NTMW30BC	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.10	1,500.00	I
S	NTMW30BD	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 2.0	1,500.00	I

Documentation

S Δ	NT1F94AA	Meridian Mail Release 12 Voice Messaging Package	15.00	H
S Δ	NTMW42CA	Option 11C Compact Documentation Library (CDROM)	55.00	H
S ➤ Δ	NTMW43BA	Option 11C Compact Customer Documentation Package	160.00	H
S ➤ Δ	P0839941	Meridian Mail 11 Maintenance Messages (SEERS)	25.00	H
S ➤ Δ	P0872785	Option 11C Compact Set Based Administration	20.00	H
S § ➤ Δ	P0872788	Mini IPE 1.5 MB DTI/PRI Guide	40.00	H
S ➤ Δ	P0873717	Meridian Mail Compact Option System Administration Guide	40.00	H
S § ➤ Δ	P0873719	Meridian Mail Compact Option Enterprise Networking Installation and Administration Guide Release 11	10.00	H
S Δ	P0875905	Meridian Mail Release 12 Maintenance Messages (SEERs)	25.00	H
S ✓ Δ	P0875913	Meridian Mail Enterprise Networking Installation and Administration Guide Release 12	10.00	H
S Δ	P0884766	Option 11C Compact NMS Mail Reference Guide	16.00	H
S Δ	P0885216	Option 11C Compact Technical Reference Guide	30.00	H
S Δ	P0885220	Registrar User Guide	20.00	H
S ➤ Δ	P0885221	Compact Hospitality Meridian Mail Guest Cards (15)	15.00	H
S Δ	P0890121	Option 11C Compact Software Input-Output Guide	60.00	H
S Δ	P0890122	Option 11C Compact Features and Services Guide	40.00	H
S Δ	P0890123	Option 11C Compact Planning and Installation Guide	30.00	H
S Δ	P0890124	MAT 6 Option 11C Compact Introduction Guide	15.00	H
S Δ	P0890125	Multi-Line CAP User Guide	15.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Miscellaneous				
S ➤	NTKS1005	Option 11C Compact Spares Package	10,500.00	I
S † ➤	NTKS1012	Journal Call Accounting Software with Billing	8,400.00	I
S ➤	NTKS1013	Registrar Front Desk Software with Billing	8,400.00	I
S ➤	NTKS1015	Journal/Registrar Software CDROM Up-Issue	50.00	H
S ➤	NTKS2050	Compact Option Dual Language Prompting	No charge	
S ➤	NTKS2051	Compact Option Additional Language	600.00	D
S † ➤	NTMW0802	Option 11C Compact Cabinet Fan Assembly	180.00	I
S Δ	NTMW35AA	Option 11C Compact Hospitality 10-slot cabinet		
S § ➤	NTMW37AA	Mini IPE 1.5MB DTI/PRI Cable	300.00	D
S ➤	NTMW44AA	Mini IPE 4 Port Trunk Card	1,700.00	I
S	NTMW55AA	Compact Hospitality Guest Administration Console RS232 Cable (40 ft.)	75.00	D
S ➤ Δ	P0885044	Journal Rate Table (Update)	215.00	H
S Δ	P0885219	Journal Administration and User Guide	32.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Option 11/11E/11C Hardware and Software

Meridian 1 Option 11C New System Packages

Meridian Option 11C system hardware, software and documentation are ordered individually on the same purchase order and will be delivered as one order. These items are not packaged together with the Basic System Packages and do not include any line/trunk cards or PFTU.

Basic System Hardware Package

S § ➤	NTSF1030	Option 11C Mini Chassis Package	4,000.00	I
S § ➤	NTSF1031	Option 11C Mini Chassis Package with SSC	7,500.00	I
S ➤	NTSF1101	Option 11C Single Cabinet AC	2,600.00	I
S ➤	NTSF1102	Option 11C Single Cabinet DC	2,600.00	I

System Software Packages - New Systems

S ✓ ➤	NTSF8020	Option 11C General Business Software Package	2,000.00	I
S ✓ ➤	NTSF8021	Option 11C Enhanced Business Software Package	3,500.00	I
S ✓ ➤	NTSF8022	Option 11C Enterprise Software Package	6,500.00	I
S ✓ ➤	NTSF8023	Option 11C NAS/VNS Software Package	7,500.00	I

Meridian 1 Internet Enabled

S ★ ➤	NTDW80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	80.00	D
S ★ ➤	NTZC80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	6,000.00	D
S ★ ➤	NTZC81AA	Meridian IP Telephony Gateway Line 2.0 Systems Package	6,200.00	D
S ★ ➤ Δ	NTZC82AA	Internet Telephone Software Parameter (Large System)	90.00	D
S ★ ➤ Δ	NTZC84AA	Internet Telephone Software Parameter (Small System)	90.00	D

Meridian 1 Option 11C Mini Software Packages

S ✓ ➤	NTSF8011	Option 11C Mini General Business Software Package	1,500.00	I
S ✓ ➤	NTSF8012	Option 11C Mini Enhanced Business Software Package	2,400.00	I
S ✓ ➤	NTSF8013	Option 11C Mini Enterprise Business Software Package. 11C Mini Enterprise Business Software Package	4,000.00	I
S ✓ ➤	NTSF8014	Option 11C Mini NAS/VNS Software Package. 11C Mini NAS/VNS Software Package	4,675.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	NTSF8101	Option 11C 100 Additional TNs - General Business		2,500.00	I
S ➤	NTSF8102	Option 11C 100 Additional TNs - Enhanced Business		4,250.00	I
S ➤	NTSF8103	Option 11C 100 Additional TNs - Enterprise		7,500.00	I
S ➤	NTSF8104	Option 11C 100 Additional TNs - NAS/VNS		8,500.00	I

Optional Features

S † ➤	NTKS1012	Journal Call Accounting Software with Billing		8,400.00	I
S ➤	NTKS1013	Registrar Front Desk Software with Billing		8,400.00	I
S ➤	NTSF8501	Option 11C Package #22 - DISA		No charge	
S ➤ Δ	NTSF8508	AST (100 Increment)		No charge	
S ➤ Δ	NTSF8509	Call Identification (CALL-ID Package 247)		No charge	
S ➤	NTSF8512	Option 11C Electronic Brandlining - Display Customization		250.00	I
S ➤ Δ	NTSF8513	Option 11C RAN Connections for Release 23.18		No charge	
S ➤	NTSF8514	Increment the Option 11C RAN Connections ISM parameter by 1		400.00	I
S ➤	NTSF8516	Option 11C Release 23 for CallPilot (Keycode only)		No charge	
B ➤	NTSF8730	Option 11C TMDI D-Channels Keycode	∞	655.00	I

Meridian 1 Option 11C Documentation

English Coil

B ➤ Δ	NT6R78AD	Option 11C R24 English Documentation Package - Coil		90.00	H
S Δ	NTLH08AA	X11 Software Features Guide		50.00	H
B ➤ Δ	NTTK31AB	Option 11C Release 25 English Documentation Package, Coil		90.00	H
N ➤ Δ	NTTK33AB	Option 11C Distributor Technical Library Package, Release 25		70.00	H
S Δ	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package		50.00	H
S	P0735211	Background Terminal User Guide (15/PK)		42.00	H
B Δ	P0835273	Customer Configuration Backup and Restore (Coil)		10.00	H
S Δ	P0889191	X11 Software Features Guide, Release 24 and Earlier		50.00	H
B Δ	P0907449	Customer Configuration Backup and Restore (Coil)		10.00	H
B Δ	P0907452	Option 11C Release 25 Technical Reference Guide - English		10.00	H
S Δ	P0907454	2.0 MB DTI/PRI Administration/Maintenance Guide		26.00	H
S Δ	P0907455	Option 11C BRI Guide (Release 18 to 24) - English		40.00	H
S Δ	P0910790	Technical Reference Guide, Release 25		50.00	H
B Δ	P0910793	2.0 MB DTI/PRI Administration and Maintenance Guide		50.00	H
B Δ	P0910795	BRI Guide, Release 25		50.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
English Binder				
B ➤ Δ	NTTK30AB	Option 11C Release 25 English Documentation Package, Binder	90.00	H
B Δ	P0837621	Option 11E - 1.5MB DTI/PRI Administration and Maintenance (Binder)	10.00	H
B Δ	P0837640	Option 11E - BRI Administration and Maintenance (Binder)	40.00	H
B Δ	P0837647	Option 11E - Technical Reference Guide (Binder)	40.00	H
B Δ	P0907453	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	35.00	H
B Δ	P0910791	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	50.00	H
CD-ROM				
S ➤ Δ	NTTK32CB	Option 11C Customer Documentation Library on CD-ROM, Release 25	75.00	H

Meridian 1 Option 11C Cabinet Expansion Packages

Expansion Cabinets

S ➤	NTSF1032	Option 11C Mini Chassis Expander Package	2,500.00	I
S ➤	NTSF1033	Option 11C Mini Chassis CPU Upgrade Package	2,400.00	I
S ➤	NTSF2101	Option 11C - 30 Ft. Expansion Cabinet AC	2,300.00	I
S ➤	NTSF2102	Option 11C - 30 Ft. Expansion Cabinet DC	2,300.00	I
S ➤	NTSF2103	Option 11C - 2 Mile Expansion Cabinet AC	7,300.00	I
S ➤	NTSF2104	Option 11C - 2 Mile Expansion Cabinet DC	7,300.00	I
S ➤	NTSF2105	Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber)	7,300.00	I
S ➤	NTSF2106	Option 11C - 2 Mile Expansion Cabinet Single Mode DC	7,300.00	I
S ➤	NTSF2200	Chassis Fiber Expansion Package (30 Ft.)	7,500.00	I
S ➤	NTSF2201	Chassis Fiber Expansion Package (2mi. Multi-Mode)	10,000.00	I
S ➤	NTSF2202	Chassis Fiber Expansion Package (2mi. Single-Mode)	10,000.00	I

Meridian 1 Option 11/11E/11C Merchandise Hardware

Peripheral Equipment (PE)

S ➤	NT1R20AB	Intelligent OPS Line Card	3,000.00	I
S ➤	NT5D60AA	CLASS Modem card	4,000.00	D
S ➤	NT6D70AA	S/T Interface Line Card (SILC)	3,500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT6D71AA	U-Interface Line Card (UILC)	3,800.00	I
S ➤	NT7D16BA	Data Access Card	2,000.00	I
S ✓ ➤	NT8D02GA	Digital Line Card (DLC)	3,500.00	I
S ✓ ➤	NT8D09BA	Analog Message Waiting Line Card	3,500.00	I
S ✓ ➤	NT8D14BB	Universal Trunk Card	3,950.00	I
S ✓ ➤	NT8D15AK	E&M Trunk Card	2,933.00	I
S ➤	NTBK22AA	Option 11E MISP Circuit Card	3,500.00	I
S ➤	NTCW80CA	Meridian IP Telephony Gateway (ITG) Base Card	3,500.00	D
S ➤	NTZC12CA	Meridian IP Telephony Gateway (ITG) Small and Large Systems Package	3,290.00	D
S ➤	NTZC13BA	Meridian IP Telephony Gateway (ITG) Card. The Meridian ITG is a single IPE card that includes the hardware and software to support 8 simultaneous voice over IP trunk calls.	3,160.00	D
S ➤	NTZC14AA	Meridian Integrated IP Telephony Gateway (ITG) PCMCIA Card	800.00	H
S Δ	P0905051	Meridian IP Telephony Gateway (ITG) NTPs. The NTPs are documents used to describe and configure the ITG card and the network environment where it operates.	15.00	H

DTI/PRI/BRI Hardware

S ➤	AS1073	SDI/DCH Package	3,100.00	I
S ✓ † ➤	AS1074	DTI/PRI Package	4,160.00	H
S ✓ † ➤	NTAK09DA	DTI/PRI Card	4,000.00	H
S	NTAK10DC	2.0 MB DTI Card with Clock Controller	4,000.00	I
S ➤	NTAK93AB	DCHI Card	1,000.00	I
S ➤	NTBK04AA	1.544 MByte Carrier Cable	300.00	D
S	NTBK05CA	Cable 20 Ft. Coax - 2.0MB DTI/PRI to MDF	180.00	D
S	NTBK05DA	2.0MB DTI/PRI Twisted Pair Cable	180.00	D
S ➤	NTBK22AA	Option 11E MISP Circuit Card	3,500.00	I
S ➤	NTBK50AA	2.0MB Primary Rate Interface Card	3,750.00	I
S	NTBK51BA	Option 11 Downloadable DCHI	1,150.00	I
B ➤	NTRB21AA	T1 Multipurpose Digital Interface (TMDI)	3,200.00	I
S ➤	NTSF3100	2.0MB DTI Package Option 11C	4,200.00	I
S ➤	NTSF3101	2.0MB PRI Package Option 11C	3,950.00	I
B ➤	NTSF6800	Option 11C TMDI Package (1.5MB DTI/PRI)	3,400.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Line-side T1				
S ➤	NT5D14AD	Line-Side T1 Interface Card (Option 11/11E/11C)	5,000.00	I
S Δ	P0815404	Line-Side T1 Interface Card Description, Installation and Maintenance	12.00	H
Mini Carrier Remote				
S	NT5D67CA	Remote Mini Carrier Interface Card	7,000.00	I
S	NT5D68CA	Local Mini Carrier Interface Card (Option 11)	5,800.00	I
S ➤	NT5D69CA	Local Mini Carrier Extender Card (Option 11)	1,750.00	D
S	NT5D85AA	Local Mini Carrier Interface Cable	400.00	D
S ➤	NT5D86AA	Local Mini Carrier Extender Cable	400.00	D
S	NT5D87AA	Remote Mini Carrier Interface Cable	400.00	D
S	NT7R87BA	T1 Link Cable Kit (32 Ft.)	220.00	D
S ➤	NTZB07AB	Mini Local Package (Option 11)	6,000.00	I
S ➤	NTZB08AA	Mini Remote Package AC	8,000.00	I
S ➤	NTZB09AA	Mini Remote Package DC	8,000.00	I
S	P0878469	Mini Carrier Remote NTP	20.00	H
Power Equipment				
B ➤	A0620100	Replacement Battery (For NTAK75AA/AB)	260.00	H
S	NTAK0420	Power Cable	60.00	D
S ➤	NTAK28AB	Battery Junction Box	170.00	H
S ➤	NTAK75AB	2-4 Hour Battery Back-Up Unit	2,225.00	H
S ➤	NTAK76AB	15-30 Minute Battery Back-up Unit	550.00	H
S	NTDK72AA	DC/DC Power Supply	1,500.00	I
B ➤	NTDK78AA	AC/DC Power Supply	1,460.00	I
S ✓	NTTK14AA	Option 11C Mini Power Cord Kit	20.00	I
Meridian 1 Option 11/11E/11C Miscellaneous Hardware				
S ➤	A0378652	Null Modem Connector, Female/Male	35.00	D
S ➤	A0379431	OPS Protector Device	100.00	I
S ➤	A0381016	Null Modem Connector, (Female/Female)	35.00	D
S ➤	A0632902	33 Ft. Plastic Fiber Cable (11E/11C)	160.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTAK02BC	SDI/DCH Card	3,000.00	I
S ➤	NTAK03DA	TDS/DTR Card	1,700.00	I
S ➤	NTAK1104	PFTU/Console Power Cable	60.00	D
S ➤	NTAK1108	SDI Cable	40.00	D
B ➤	NTAK11BD	Main/Expansion Cabinet	2,500.00	I
S ➤	NTAK1204	Expansion Cable - Copper (7 Ft.)	160.00	D
B	NTAK19EC	2 Port SDI Cable (6 Ft.)	160.00	D
S ➤	NTAK19FB	4 Port SDI Cable	200.00	D
S ➤	NTAK21BA	Expansion Cartridge	300.00	I
S ➤	NTAK27AA	Option 11 Cabinet Pedestal	440.00	I
S ➤	NTAK80AA	Option 11 System Back-Up Cartridge	550.00	I
S ➤	NTAK9204	OPS Cable	40.00	D
S ➤	NTAK92BA	OPS Protection Module	1,675.00	I
S ➤	NTAK98AA	Power Supply Cable	40.00	D
S ➤	NTBK45AC	System Core Pack	3,200.00	I
S ➤	NTBK47AB	Expansion Daughterboard	600.00	I
S ➤	NTBK48AA	3-port SDI Cable (1.5m or 5 Ft.)	180.00	D
S	NTBK51BA	Option 11 Downloadable DCHI	1,150.00	I
S ➤	NTBK54AB	Main Fiber Interface (MFI) Kit	590.00	D
S ➤	NTBK55AB	Expansion Fiber Interface (EFI) Kit	550.00	D
S ➤	NTBK80AA	Ground Bar	75.00	D
S ➤	NTBK81AA	Fiber Management Kit	50.00	D
S ➤	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	4,575.00	I
S ➤	NTDK20EA	Option 11C System Core Card	4,000.00	I
S ➤	NTDK21AA	Option 11C- Blank Software Daughterboard	1,300.00	I
S ➤	NTDK22AA	30 Ft. Fiber Daughterboard - Multi Mode	1,000.00	I
S ➤	NTDK23AA	30 Ft. Fiber Receiver Card	1,000.00	I
S ✓ ➤	NTDK23BA	30 Ft. Fiber Receiver Card	1,000.00	I
S ➤	NTDK24AB	2 Mile Fiber Daughterboard - Multi-Mode	4,000.00	I
S	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	4,000.00	I
S ➤	NTDK26AA	Backwards Compatible Daughterboard	600.00	I
S ➤	NTDK27AA	Ethernet Adapter Cable	75.00	D
S ➤	NTDK30AA	Database Upgrade Tool	200.00	I
S ➤	NTDK48AA	Main Cabinet Cable Kit	200.00	D
S ➤	NTDK49AA	Expansion Cabinet Cable Kit	100.00	D
S ➤	NTDK68AA	16MB SIMM	850.00	H
S ✓ ➤	NTDK79AA	2 Mile Fiber Daughterboard Single Mode	4,000.00	I
S ✓ ➤	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	4,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
N ➤	NTDK81AA	Option 11C Blank Software Daughterboard	1,300.00	I
S ➤	NTDK84AA	30 Ft. DUAL Port Fiber Daughterboard	1,600.00	I
S ➤	NTDK85AA	2 Mile Multi Mode DUAL Port Fiber Daughterboard	6,000.00	I
S	NTDK88AA	Option 11C Mini Main Chassis Cable Kit	130.00	I
S	NTDK89AA	Option 11C Mini Chassis Expander Cable Kit	130.00	I
S	NTDK91BA	Option 11C Mini Main Chassis	2,500.00	I
S ✓	NTDK92BA	Mini Chassis Expander	2,500.00	I
S ➤	NTDK97AB	Option 11C Mini System Controller Card (Blank)	4,000.00	I
S † ➤	NTSK11AA	Option 11C Software Daughterboard - Release 22.08D	1,400.00	I
S † ➤	NTSK11AB	Option 11C Software Daughterboard - Release 22.16	1,400.00	I
S † ➤	NTSK11AC	Option 11C Software Daughterboard - Release 22.46	1,400.00	I
S † ➤	NTSK11AF	Option 11C Software Daughterboard - Release 23.18	1,400.00	I
S † ➤	NTSK11AG	Option 11C Software Daughterboard - Release 23.35	1,400.00	I
S † ➤	NTSK11AH	Option 11C Software Daughterboard - Release 23.55	1,400.00	I
B † ➤	NTSK11AK	Option 11C Software Daughterboard - Release 24.24	1,400.00	I
B ✓ ➤	NTSK11AN	Option 11C Software Daughterboard - Release 25	1,400.00	I
B ★ ➤	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo	1,400.00	I
S ✓	NTSK11BA	Option 11C Release 22.08 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BB	Option 11C Release 22.16 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BC	Option 11C Release 22.46 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BF	Option 11C Release 23.18 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BG	Option 11C Release 23.35 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BH	Option 11C Release 23.55 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BK	Option 11C Release 24.24 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BN	Option 11C Release 25 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11ZN	Release 25 Programmed Mini System Controller Pack	1,910.00	I
S ✓	NTTK08AA	Option 11C Mini Vertical Wall Mount Kit	60.00	I
S ✓	NTTK09AA	Option 11C Mini 19 Inch Rack Mount Kit	80.00	I
S	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	13.00	I
S ✓	NTTK11AA	Option 11C Mini Horizontal Wall Mount Kit	80.00	I
S ✓	NTTK13AA	Option 11C 48MB Software Daughterboard (Blank)	1,380.00	I
S ✓	NTTK24AA	Option 11C Mini Fiber Cable Management Kit	50.00	I
S ★ ➤	NTTK45AA	Option 11C 48MB Blank PCMCIA Memory Card Assembly. 48MB Blank PCMCIA Memory Card Assembly	650.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
B	P0714224	MDF Locking Bar Restraint Bracket. MDF Locking Bar Restraint Bracket is used to secure MDF cables in the Option 11 cabinet.	34.00	I
S	P0714236	Mounting Bracket	50.00	I
S Δ	P0816832	Fiber Routing Guide	20.00	H
S ➤ Δ	P0850716	Option 11C Programming Fee for PCMCIA Card	500.00	H

Option 11C Software Feature Set Upgrade

(Adding additional software features by exchanging Feature Set for higher level)

The Option 11C software delivery mechanism enables software feature packages to be activated via keycodes. This capability allows for much quicker and less expensive addition of optional software features since no cartridge will be required, a site specific keycode will activate the desired feature sets. The keycodes will be controlled via a security device which is system specific.

The following codes are used to change software features set on an existing Option 11C system. Additional features are added by purchasing a higher level feature code set. Refer to Appendix for detailed information on feature complements in each feature set. No credit is allowed for moving to a lower level.

Documentation is not included and must be ordered separately. Serial Number must be included with order.

Order one of these packages to upgrade to a new feature package within Option 11C.

S ✓ ➤	NTSF8048	Option 11C General Business Software Feature Upgrade	3,000.00	I
S ✓ ➤	NTSF8049	Option 11C Enhanced Business Software Feature Upgrade	4,500.00	I
S ✓ ➤	NTSF8050	Option 11C Enterprise Software Feature Upgrade	7,500.00	I
S ✓ ➤	NTSF8051	Option 11C NAS/VNS Software Feature Upgrade	8,500.00	I

Release 22 (or later) Software Up-issue to "Latest" Issue

S ➤	NTSF8702	Option 11C Software Upissue Keycode	500.00	H
S ➤	NTSF8712	Option 11C Software Upgrade Fee to Current	1,000.00	I
B ✓ ➤	NTSF8722	Option 11C Software Rls 24C Upissue Keycode. This code can be used to upissue Option 11C Rls 24 systems to Rls 24C (25.08) only.	500.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Option 11/11E Cabinet Expansion Packages

S ➤	AS1171	Option 11E 1st Expansion Cabinet Package AC	4,000.00	I
S ➤	AS1172	Option 11E 1st Expansion Cabinet Package DC	4,000.00	I
S ➤	AS1173	Option 11E 2nd Expansion Cabinet Package AC	5,335.00	I
S ➤	AS1174	Option 11E 2nd Expansion Cabinet Package DC	5,335.00	I
S ➤	AS1175	Fiber Interface Kit	2,200.00	I

Meridian 1 Option 11/11E Documentation

English - Binder

B Δ	P0837621	Option 11E - 1.5MB DTI/PRI Administration and Maintenance (Binder)	10.00	H
B Δ	P0837640	Option 11E - BRI Administration and Maintenance (Binder)	40.00	H
B Δ	P0837647	Option 11E - Technical Reference Guide (Binder)	40.00	H
B Δ	P0907453	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	35.00	H
B Δ	P0910791	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	50.00	H

English - Coil

N ➤ Δ	NTTK33AB	Option 11C Distributor Technical Library Package, Release 25	70.00	H
S	P0735211	Background Terminal User Guide (15/PK)	42.00	H
B Δ	P0835273	Customer Configuration Backup and Restore (Coil)	10.00	H
B Δ	P0907452	Option 11C Release 25 Technical Reference Guide - English	10.00	H
S Δ	P0910790	Technical Reference Guide, Release 25	50.00	H

Meridian 1 Option 11/11E to 11C Cabinet Upgrade Packages

Hardware Upgrades

S ➤	NTDK18AA	Cabinet Upgrade Kit	850.00	I
S ➤	NTDK19AA	SSC Upgrade Kit	800.00	I
S ➤	NTSF6001	Option 11/11E to 11C Single Cabinet Upgrade	3,465.00	I
S ➤	NTSF6002	Option 11/11E to 11C Two Cabinet Copper Upgrade	3,945.00	I
S ➤	NTSF6003	Option 11/11E to 11C Two Cabinet Fiber Upgrade (30 Ft.)	5,500.00	I
S ➤	NTSF6004	Option 11/11E to 11C Two Cabinet Fiber Upgrade (2 mile)	12,300.00	I
S ➤	NTSF6005	Option 11/11E to 11C Three Cabinet Fiber Upgrade (30 Ft.)	8,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTSF6006	Option 11/11E to 11C Three Cabinet Fiber Upgrade (2 mile)	17,100.00	I
S ➤	NTSF6007	Option 11/11E to 11C - Two Cabinet Ethernet Upgrade (2 Mile - Single Mode Fiber)	12,300.00	I
S ➤	NTSF6008	Option 11/11E to 11C Three Cabinet Single Mode Fiber Upgrade (2 Mile)	17,100.00	I

Software Upgrade Packages - Used With Option 11/11E to 11C Upgrades

S ✓ ➤	NTSF8022	Option 11C Enterprise Software Package	6,500.00	I
S ✓ ➤	NTSF8023	Option 11C NAS/VNS Software Package	7,500.00	I
S ✓ ➤	NTSF8028	Option 11/11E to Option 11C General Business Software Upgrade	3,000.00	I
S ✓ ➤	NTSF8029	Option 11/11E to Option 11C Enhanced Business Software Upgrade	4,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 System Software
Options 51C-81C

The Meridian 1/SL-1 software pricing structure varies depending on system type and software generic and release. The following groups of Meridian 1/SL-1 software exist:

- X11 Release 22, 23, and 24 software (for use with Options 51C/61C/81/81C)
- X11 Release 21 software (for use with STE, RT, NT, XT and Option 81C)
- X11 Release 19-21 software (for use with STE, RT, NT, XT and Options 21E-81)
- X11 Release 15-17 software (for use with STE, RT, NT, XT and Options 21-71)

System/Software Compatibility

Because these software groups typically include multiple generics and releases, be sure to check the compatibility of a feature to ensure it can be added to your particular system. In some cases, only software updates are required to add a feature. In other cases, a system upgrade may be required. To assist you in making the right selections for your system, refer to the following:

- For system compatibility, see Reference Section (Book 2)
- For software release information, see "Meridian 1 Hardware/Software Status" in the General Section (Book 1)
- For further assistance, contact your Nortel Santa Clara Customer Response Center Representative

Capacity Requirements

The usage capacity of your system is determined by the Terminal Numbers (TNs) purchased. (TN is the software designation of a logical termination point, either physical or virtual, defined in Meridian 1 software.) Usually a single physical connection, such as a single basic telephone line, corresponds to one TN. However, some physical connections require more than one termination point. Lines designated as Consoles and Digital Voice/Data lines each use two TNs. DTI/PRI lines require 24 TNs. Although not physical terminations, the software requires one TN each for Meridian Mail and Digitone Receiver ports.

Base software pricing, as well as pricing for Base optional features, new releases, upgrades, and capacity changes for Meridian 1 system users is based on system port (TN) levels. Therefore, you should understand your TN

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

requirements well if you wish to optimize your cost. Ordering policies and procedures are found in the General Section.

Usage levels, based on the number of users in each case, serve as multipliers to determine the total price for adding features or expanding software capacity on the system. Optional system TN-based software features have maximum charge levels of 1000 TNs. For systems with more than 1000 ports, you need only purchase Meridian 1 Base software when expanding your system.

Charges for ACD, Meridian Link, ISDN BRI, RAN Broadcast, and Music Broadcast features are independently based on their unique usage.

Option 11C Software

Option 11C system software uses high-level software packaging and a graduated pricing structure based on usage capacity. Maximum charge levels do not apply to Option 11C software. There are four software packages available to Option 11C customers.

Software Updates/Replacements

When purchasing additional features and releases, issue updates, or replacing a damaged cartridge a new software cartridge will be sent to replace the current software. If additional feature packages are added to the same release of software, a new keycode is issued rather than new software media. Appropriate credits are issued when the replaced/damaged software cartridges are returned.

With the introduction of keycodes on the Option 11C, software package codes remain the same from release to release. For customers who want to upgrade to the current release, a new Software Upgrade code has been added. For example, an Option 11C customer who currently uses Release 22 General Business Package can order the Software Upgrade code (NTSF8712) to upgrade to Release 23 General Business Package.

Capacity Expansion

Each software cartridge is equipped with 200 system ports or TNs. For increased system port capacity, additional software can be purchased in increments of 100 TNs. Add-on cost is quoted in the price list per hundred TNs. Please refer to the Option 11C Reference and Pricing Reference sections for detailed information regarding purchasing additional system port capacity.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

Option 11C Software

Option 11 Release 24 Software

System Software

S ✓ ➤	NTSF8020	Option 11C General Business Software Package		2,000.00	I
S ✓ ➤	NTSF8021	Option 11C Enhanced Business Software Package		3,500.00	I
S ✓ ➤	NTSF8022	Option 11C Enterprise Software Package		6,500.00	I
S ✓ ➤	NTSF8023	Option 11C NAS/VNS Software Package		7,500.00	I

Base Features

S ➤	NTSF8501	Option 11C Package #22 - DISA		No charge	
S ➤ Δ	NTSF8508	AST (100 Increment)		No charge	

Software Updates

S ✓ ➤	NTSF8028	Option 11/11E to Option 11C General Business Software Upgrade		3,000.00	I
S ✓ ➤	NTSF8029	Option 11/11E to Option 11C Enhanced Business Software Upgrade		4,500.00	I
S ✓ ➤	NTSF8030	Option 11/11E to Option 11C Enterprise Software Upgrade		7,500.00	I
S ✓ ➤	NTSF8031	Option 11/11E to Option 11C NAS/VNS Software Upgrade		8,500.00	I
S ✓ ➤	NTSF8048	Option 11C General Business Software Feature Upgrade		3,000.00	I
S ✓ ➤	NTSF8049	Option 11C Enhanced Business Software Feature Upgrade		4,500.00	I
S ✓ ➤	NTSF8050	Option 11C Enterprise Software Feature Upgrade		7,500.00	I
S ✓ ➤	NTSF8051	Option 11C NAS/VNS Software Feature Upgrade		8,500.00	I
S ➤	NTSF8101	Option 11C 100 Additional TNs - General Business		2,500.00	I
S ➤	NTSF8102	Option 11C 100 Additional TNs - Enhanced Business		4,250.00	I
S ➤	NTSF8103	Option 11C 100 Additional TNs - Enterprise		7,500.00	I
S ➤	NTSF8104	Option 11C 100 Additional TNs - NAS/VNS		8,500.00	I
S ➤	NTSF8514	Increment the Option 11C RAN Connections ISM parameter by 1		400.00	I
S ➤	NTSF8712	Option 11C Software Upgrade Fee to Current		1,000.00	I
B ➤	NTSF8730	Option 11C TMDI D-Channels Keycode	∞	655.00	I

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted	
★ New product introduction	†	Additions & maintenance	➤	See reference book	
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only	
S Santa Clara	N	Nashville	B	Both order locations	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Miscellaneous				
S ➤	NTKS1013	Registrar Front Desk Software with Billing	8,400.00	I
S ➤	NTSF8512	Option 11C Electronic Brandlining - Display Customization	250.00	I
S ➤ Δ	NTSF8513	Option 11C RAN Connections for Release 23.18	No charge	
S † ➤	NTSK11AA	Option 11C Software Daughterboard - Release 22.08D	1,400.00	I
S † ➤	NTSK11AB	Option 11C Software Daughterboard - Release 22.16	1,400.00	I
S † ➤	NTSK11AC	Option 11C Software Daughterboard - Release 22.46	1,400.00	I
S † ➤	NTSK11AF	Option 11C Software Daughterboard - Release 23.18	1,400.00	I
S † ➤	NTSK11AG	Option 11C Software Daughterboard - Release 23.35	1,400.00	I
S † ➤	NTSK11AH	Option 11C Software Daughterboard - Release 23.55	1,400.00	I
B † ➤	NTSK11AK	Option 11C Software Daughterboard - Release 24.24	1,400.00	I
B ✓ ➤	NTSK11AN	Option 11C Software Daughterboard - Release 25	1,400.00	I
B ★ ➤	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo	1,400.00	I
B ✓ ➤	NTSK11BK	Option 11C Release 24.24 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BN	Option 11C Release 25 Programmed PCMCIA Card	1,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Option 11 Release 24 Software Order Code/Option Matrix

Order Code	Description	Options
NTSF8020	**Option 11C General Business Software Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 44, 45, 46, 47, 48, 49, 51, 52, 53, 54, 55, 56, 57, 58, 59, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 115, 116, 119, 121, 125, 127, 132, 133, 139, 140, 141, 157, 160, 162, 164, 167, 170, 173, 174, 179, 180, 181, 185, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 223, 229, 234, 240, 242, 243, 246, 247, 251, 254, 256, 258, 296, 301, 310, 315, 324, 327, 328, 329, 350, 362, 364
NTSF8021	**Option 11C Enhanced Business Software Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 149, 154, 155, 157, 160, 162, 164, 167, 170, 172, 173, 174, 178, 179, 180, 181, 185, 186, 191, 200, 202, 203, 204, 205, 206, 208, 210, 212, 216, 222, 223, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 254, 256, 258, 291, 296, 297, 301, 310, 315, 324, 327, 328, 329, 334, 350, 351, 362, 364, 380
NTSF8022	**Option 11C Enterprise Software Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 26, 27, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTSF8023	**Option 11C NAS/VNS Software Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 159, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382
NTSF8028	**Option 11/11E to Option 11C General Business Software Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 44, 45, 46, 47, 48, 49, 51, 52, 53, 54, 55, 56, 57, 58, 59, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 115, 116, 119, 121, 125, 127, 132, 133, 139, 140, 141, 157, 160, 162, 164, 167, 170, 173, 174, 179, 180, 181, 185, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 223, 229, 234, 240, 242, 243, 246, 247, 251, 254, 256, 258, 296, 301, 310, 315, 324, 327, 328, 329, 350, 362, 364, 380
NTSF8029	**Option 11/11E to Option 11C Enhanced Business Software Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 149, 154, 155, 157, 160, 162, 164, 167, 170, 172, 173, 174, 178, 179, 180, 181, 185, 186, 191, 200, 202, 203, 204, 205, 206, 208, 210, 212, 216, 222, 223, 229, 233, 234, 235, 240, 242, 243, 246, 247, 251, 254, 256, 258, 291, 296, 297, 301, 310, 315, 324, 327, 328, 329, 334, 350, 351, 362, 364, 380, 381, 382

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTSF8030	**Option 11/11E to Option 11C Enterprise Software Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 26, 27, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382
NTSF8031	**Option 11/11E to Option 11C NAS/ VNS Software Upgrade**	0, 1, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 159, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTSF8048	**Option 11C General Business Software Feature Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 44, 45, 46, 47, 48, 49, 51, 52, 53, 54, 55, 56, 57, 58, 59, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 115, 116, 119, 121, 125, 127, 132, 133, 139, 140, 141, 157, 160, 162, 164, 167, 170, 173, 174, 179, 180, 181, 185, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 223, 229, 234, 240, 242, 243, 246, 247, 251, 254, 256, 258, 296, 301, 310, 315, 324, 327, 328, 329, 350, 362, 364
NTSF8049	**Option 11C Enhanced Business Software Feature Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 149, 154, 155, 157, 160, 162, 164, 167, 170, 172, 173, 174, 178, 179, 180, 181, 185, 186, 191, 200, 202, 203, 204, 205, 206, 208, 210, 212, 216, 222, 223, 229, 233, 234, 235, 240, 242, 243, 246, 247, 251, 254, 256, 258, 291, 296, 297, 301, 310, 315, 324, 327, 328, 329, 334, 350, 351, 362, 364, 380, 381, 382
NTSF8050	**Option 11C Enterprise Software Feature Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 26, 27, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTSF8051	**Option 11C NAS/VNS Software Feature Upgrade**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 129, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 154, 155, 157, 158, 159, 160, 161, 162, 164, 167, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 184, 185, 186, 191, 192, 200, 202, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 242, 243, 246, 247, 249, 251, 253, 254, 256, 258, 263, 291, 296, 297, 301, 305, 306, 307, 310, 311, 312, 315, 316, 321, 324, 327, 328, 329, 330, 331, 332, 333, 334, 348, 350, 351, 362, 364, 380, 381, 382
NTSF8501	**Option 11C Package #22 - DISA**	22

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Option 11 Release 21 Software

Option 11 Release 21 Software Order Code/Option Matrix

Order Code	Description	Options
NTBK83AG	**Release 21 Software Cartridge - General Business Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 44, 45, 46, 47, 48, 49, 51, 52, 53, 54, 55, 56, 57, 58, 59, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 115, 116, 119, 121, 125, 127, 132, 133, 139, 140, 141, 157, 160, 162, 164, 170, 173, 174, 179, 180, 181, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 223, 229, 234, 243, 246, 250, 251, 254, 256, 258, 301
NTBK83BG	**Release 21 Software Cartridge - Enhanced Business Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 132, 133, 139, 140, 141, 145, 146, 149, 155, 157, 160, 162, 164, 170, 172, 173, 174, 178, 179, 180, 181, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 216, 222, 223, 229, 234, 235, 240, 243, 246, 250, 251, 253, 256, 258, 291, 301
NTBK83CG	**Release 21 Software Cartridge - Enterprise Business Package**	0, 1, 2, 3, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 155, 157, 158, 160, 161, 162, 164, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 186, 191, 192, 200, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 233, 234, 235, 240, 243, 246, 247, 250, 251, 253, 254, 256, 258, 291, 301, 312
NTBK83DG	**Release 21 Software Cartridge - General (No DISA)**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 44, 45, 46, 47, 48, 49, 51, 52, 53, 54, 55, 56, 57, 58, 59, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 115, 116, 119, 121, 125, 127, 132, 133, 139, 140, 141, 157, 160, 162, 164, 170, 173, 174, 179, 180, 181, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 223, 229, 234, 243, 246, 251, 254, 256, 258, 301

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTBK83EG	**Release 21 Software Cartridge - Enhanced (No DISA)**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 63, 64, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 131, 132, 133, 139, 140, 141, 145, 146, 149, 155, 157, 160, 162, 164, 170, 172, 173, 174, 178, 179, 180, 181, 186, 191, 200, 203, 204, 205, 206, 208, 210, 212, 216, 222, 223, 229, 233, 234, 235, 240, 243, 246, 251, 253, 256, 258, 291, 301
NTBK83FG	**Release 21 Software Cartridge - Enterprise Business (No DISA)**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 56, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 131, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 155, 157, 158, 160, 161, 162, 164, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 186, 191, 192, 200, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 234, 235, 240, 243, 246, 247, 251, 253, 254, 256, 258, 291, 301, 312
NTBK83GG	**Release 21 Software Cartridge - Network Attendant Service (NAS)/ Virtual Network Services (VNS) Package**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 22, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 155, 157, 158, 159, 160, 161, 162, 164, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 186, 191, 192, 200, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 234, 235, 240, 243, 246, 247, 250, 251, 254, 256, 258, 291, 301, 312

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
NTBK83HG	**Release 21 Software Cartridge - Network Attendant Service (NAS)/ Virtual Network Services (VNS) Package (No DISA)**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 45, 46, 47, 48, 49, 50, 51, 52, 53, 54, 55, 57, 58, 59, 60, 61, 62, 63, 64, 67, 70, 71, 72, 73, 74, 75, 76, 77, 79, 80, 81, 83, 86, 87, 88, 89, 90, 91, 92, 93, 95, 98, 99, 100, 101, 102, 103, 105, 107, 108, 109, 110, 111, 113, 114, 115, 116, 117, 118, 119, 121, 125, 127, 132, 133, 139, 140, 141, 145, 146, 147, 148, 149, 150, 151, 153, 155, 157, 158, 159, 160, 161, 162, 164, 170, 172, 173, 174, 175, 178, 179, 180, 181, 183, 186, 191, 192, 200, 203, 204, 205, 206, 207, 208, 209, 210, 212, 214, 215, 216, 218, 219, 222, 223, 224, 225, 229, 234, 235, 240, 243, 246, 247, 251, 254, 256, 258, 291, 301, 312

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
System Software				
S ➤	NTBK83AG	Release 21 Software Cartridge - General Business Package. Includes: - 500/2500 Line Disconnect - 500/2500 Set Features - 500/2500 Single-Line ACD Set - Access Restrictions - ACD 500/2500 Single Line Sets - ACD Alternate Call Answer - ACD CDR Queue Record - ACD Display Queue Enhancement - ACD Flexible Call Force - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Advanced Features - Alarm Filters for Fault Management - Attendant Administration - Attendant Alternative Answering - Attendant Barge-In - Attendant Break-In - Attendant Busy Lamp Field Display - Attendant Busy Verification - Attendant Call Selection - Attendant Calls Waiting Indication - Attendant Camp-On - Attendant End-to-End Signaling - Attendant Forward No Answer - Attendant Incoming Call Indicators - Attendant Interpositional Transfer - Attendant Lockout - Attendant Overflow Position - Attendant Position Busy - Attendant Recall - Attendant Secrecy - Attendant Splitting - Attendant Trunk Group Busy Verification - Audible Reminder of Held Calls - Auto Handsfree Answerback - Auto Line Selection - Autodial - Autodial Tandem Transfer (ATX) - Automatic Answer Back	2,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- Automatic Line Selection		
		- Automatic Set Based Installation		
		- Automatic Set Relocation		
		- Automatic Wake-Up		
		- Auxillary Processor Link		
		- B8ZS and ESF for DTI Loops		
		- Background Terminal Facility		
		- Basic ACD		
		- Basic Alternate Route Selection (BARS)		
		- Basic Authorization Code		
		- Basic Call Processing		
		- Basic Queuing		
		- Basic Routing		
		- Boss Secretarial Filtering		
		- Bridging 500/2500 Sets		
		- Call Detail Recording		
		- Call Forward - All Calls/Busy		
		- Call Forward - External Deny/Hunt by Call Type		
		- Call Forward - Hunt Override via FCC		
		- Call Forward - No Answer/Flexible/Second Level		
		- Call Forward - Reminder Tone		
		- Call Forward - Remote		
		- Call Forward - Save on Data Dump/Sysload		
		- Call Forward Busy Status		
		- Call Hold/Deluxe/Permanent		
		- Call Join		
		- Call Park		
		- Call Park on Non-Supervised CO Trunks		
		- Call Party Name Display		
		- Call Transfer		
		- Call Waiting/Internal		
		- Calling Party Privacy		
		- CCSA Access		
		- CDR Forced Charge Account		
		- CDR on TTY (CDR List)		
		- Centralized Answering Position		
		- Centrex Switch Hook Flash		
		- Charge Account for CDR		
		- Charge Account/Authorization Code		
		- Command Status Line		
		- Compliance for DID Answer Supervision		
		- Conference Warning Tone		
		- Conference/TDS		
		- Controlled Class of Service		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

- Coordinated Dialing Plan (CDP)
- Data Port Hunting
- Deluxe Hold
- Departmental Listed Directory Number
- Dial Access to Group Call
- Dial Intercom
- Dialed Number Identification Service (DNIS)
- Dialed Number Identification Services (DNIS) Length Flexibility
- DID Answer Supervision
- Digit Display
- Digit Key Signaling
- Digital Telephone Set
- Direct Inward System Access (DISA)
- Direct Private Network Access
- Directed Call Pickup
- Distinctive Ringing
- DNIS Enhancements
- Do Not Disturb, Group
- Do Not Disturb, Individual
- End-to-End Signaling
- Enhanced Conference, TDS, and MFS Card
- Enhanced Controlled Class of Service
- Enhanced Malicious Call Trace
- Enhanced Music
- Enhanced Night Service
- Extended PBX Features
- Extended Peripheral Equipment
- Fast Tone & Digit Switch (TDS)
- FCC - Equal Access Carrier Access Code (CAC) for NANP
- FCC - Interchangeable Number Plan Area (NANP)
- Flexible Call Back Queuing
- Flexible Call Force
- Flexible Code Restriction
- Flexible Feature Code Enhancements
- Flexible Feature Codes (Electronic Lock/Remote Call Forward)
- Flexible Numbering Plan
- Flexible Orbiting Prevention Timer
- Flexible Tones and Cadences
- Forced Charge Account
- Global CDR Record
- Group Call
- Handsfree Voice Call
- History File
- Hospitality Screen

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- Hospitality Voice Services		
		- HOT Line Services/Enhanced HOT Line (Flexible Hot Line)		
		- Hunting		
		- Improved End-to-End Signaling		
		- Incoming DID Digit Conversion		
		- Integrated Messaging System Link		
		- Integrated Voice & Data		
		- Intercept Treatment		
		- Internal Call Forward		
		- Internal CDR		
		- IVMS Link		
		- Last Number Redial		
		- Limited Access to Overlays		
		- M2250 TCM Console		
		- M2317 Digital Display Telephone Set		
		- M3000 Touchphone		
		- Maid ID for Room Status		
		- Make Set Busy		
		- Make Set busy - Voice Call Override Enhancement		
		- Malicious Call Trace		
		- Malicious Call Trace-DN/TN Prime		
		- Manual Line Selection		
		- Manual Signaling		
		- Manual Trunk Service		
		- Meridian 1 Fault Management		
		- Meridian 1 OA&M Feature Improvement		
		- Meridian 1 Overlay Restructuring		
		- Meridian Administration Tool (MAT)		
		- Meridian Communications Adaptor (MCA)		
		- Meridian Communications Unit (MCU)		
		- Meridian Digital Telephones		
		- Meridian Hospitality Voice Services		
		- Meridian Mail Link		
		- Meridian Modular Telephone Sets		
		- Meridian Modular Telephone Sets - Automatic Gain Control/ Handset Volume Reset		
		- Meridian Modular Telephone Sets - Handsfree Download		
		- Message Center		
		- Message Registration		
		- MIS Operation Recovery		
		- MSDL/MISP Interface Handler		
		- Multi-Attendant Console Operation		
		- Multi-Customer		
		- Multi-Language Wake-Up		
		- Multi-Party Operations		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- Multiple Appearance DN Redirection Prime (MARP)		
		- Multiple Tenant Service		
		- Music Package/Enhanced Music		
		- Network 500/2500 Line Disconnect		
		- Network Alternate Route Selection (NARS)		
		- Network Authorization Code		
		- Network Class of Service		
		- Network Queuing & Routing		
		- Network Traffic Measurement		
		- New Flexible Code Restriction		
		- Night Service		
		- No Hold Conference		
		- Off-Hook Alarm Security		
		- Off-Premise Extension (OPX)		
		- Office Data Administration System (ODAS)		
		- On-Hook Dialing		
		- Optional Outpulsing		
		- Paging Interface		
		- PBX Interface for DTI/CPI		
		- Phantom TN		
		- PMSI Standardization		
		- Pretranslation		
		- Priority Override		
		- Privacy/Override/Release		
		- Private Line Service		
		- Property Management System Interface (PMSI)		
		- RAN for Calls Diverted to External Trunks		
		- Recall after Parking		
		- Recall to Same Attendant		
		- Recorded Announcement (RAN)		
		- Recorded Overflow Announcement		
		- Recorded Telephone Dictation		
		- Recovery on Misoperation Attendant Console		
		- Remote Backup		
		- Restricted Call Transfer		
		- Ring Again		
		- Ring Again on No Answer		
		- Room Status		
		- Scheduled Access Restriction		
		- Secretarial Filtering		
		- Set Relocation		
		- Short Buzz for Digital Sets		
		- Speed Call on Private Lines		
		- Station Activity Record		

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- Station Clamp-On - Station Category Indication - Station Specific Authorization Codes - Station-to-Station Dialing - Stored Number Redial - Superloop Administration - Supervisor Control of Queue Size - Supervisory Attendant Console - System Speed Call - Time and Date - Transparent Data Networking - Trunk Barring - Trunk Improvement Program - Trunk Verification from a Station - Uninterrupted Line Connections - Used New CDR Format - User Selectable Call Direction - VIP Automatic Wake-Up - XOPX - Expanded Off-Premise Station Line Card for IPE		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTBK83BG	Release 21 Software Cartridge - Enhanced Business Package. Includes everything in the General Package, PLUS the following: - ACD Activity Code - ACD Auxillary Processor/Pkg D - ACD Auxillary Processor/Pkg D - Link Processor - ACD Auxillary Processor/Pkg D - Security - ACD Display Enhancement - ACD Link (MAX) - ACD Report Control - ANI Route Selection - Automatic ID of Outgoing Calls - Automatic Number Identification (ANI) - Backup D-Channel (Meridian 1, DMS, AT&T) - Call Pickup Network Wide - Call-by-Call Service Selection - Calling Line ID in CDR - Console Digit Key Signaling - Console Presentation Group Level Services - DTI/PRI Timeslot Re-Use - Electronic Lock, Network Wide - Enhanced ACD Overflow - Inter-Exchange Carrier (In-Band ANI) - ISDN Basic Rate Interface - ISDN BRI Line Application - ISDN BRI Supplementary Services - ISDN BRI/PRI Interworking - ISDN Primary Rate Interface (PRI) - ISDN Signaling - Meridian ACD Basic Reports/Pkg C1 - Meridian ACD Load Mgmt/Pkg C2 - Meridian COMPANION - Meridian MAX Reports + Enhancements - Meridian MAX-IPE - Name Display for DNIS - National ISDN (NI-2) TR 1268 - Network Call Redirection - Network Name Display (SL-100, DMS-100/250) - Network Wide Listed Directory Number (NWLDN) - PRI - Priority Queuing - Trunk Hook-Flash Enhancement	3,500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTBK83CG	Release 21 Software Cartridge - Enterprise Business Package. Includes everything in the Enhanced Business Package PLUS the following: - Attendant & Network Wide-Remote Call Forward - Call Pickup, Network Wide - CDR Expansion - Customer Controlled Routing (CCR) - DN Expansion - Enhanced ACD Routing - Feature Group D - Hold in Queue for IVR - Hotline Type "!" - ISDN Application Processor Third Party - ISDN Call Connection Limitations - ISDN Signaling Link - Line Load Control - Meridian Link - M911 Abandoned Call - Meridian Mail Link Module - Network ACD (NACD) - Network Call ID - Network Call Transfer - Network Message Services - Network Message Waiting Indication (NMWI) interworking w/DMS - Network Queuing - Main - Network Ring Again - Network Signaling - Network Speed Call - Off-Hook Queuing - Originator Routing Control/Remote Virtual Queuing - Predictive Dialing - Fast Transfer - Trunk Optimization - Unique Call ID	6,500.00	I
S ➤	NTBK83DG	Release 21 Software Cartridge - General (No DISA). Includes everything in the General Package except - DISA (Option 22) - Direct Private Network Access (Option 250).	2,000.00	I
S ➤	NTBK83EG	Release 21 Software Cartridge - Enhanced (No DISA). Includes everything in the Enhanced Business Package except - DISA (Option 22).	3,500.00	I
S ➤	NTBK83FG	Release 21 Software Cartridge - Enterprise Business (No DISA). Includes everything in the Enterprise Business Package except - DISA (Option 22).	6,500.00	I
S ➤	NTBK83GG	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package. Includes everything in the Enterprise Package, PLUS the following: - Network Attendant Service (NAS) - Virtual Network Service	7,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTBK83HG	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package (No DISA). Includes everything in the NAS Package except - DISA (Option 22) - Direct Private Network Access (Option 250).	7,500.00	I

Software Updates

S ➤	NTSF8702	Option 11C Software Upissue Keycode	500.00	H
B ✓ ➤	NTSF8722	Option 11C Software Rls 24C Upissue Keycode. This code can be used to upissue Option 11C Rls 24 systems to Rls 24C (25.08) only.	500.00	H
S ➤	SW1121E	General Business Software (Add. 100 TNs)	2,000.00	I
S ➤	SW1122E	Enhanced Business Software (Add. 100 TNs)	3,500.00	I
S ➤	SW1126D	Enterprise Business Software (Add. 100 TNs)	6,500.00	I
S ➤	SW1127D	NAS Software (Add. 100 TNs)	7,500.00	I
S ➤	SW1131E	General Business Software Update	3,000.00	I
S ➤	SW1132E	Enhanced Business Software Update	4,500.00	I
S ➤	SW1141D	Enterprise Business Software Update	7,500.00	I
S ➤	SW1142D	NAS Software Update	8,500.00	I

X11 Software for Large Systems

X11 Large System Software uses a graduated pricing structure based on feature usage. Base software pricing, as well as pricing for optional Base features, new releases, upgrades, and capacity changes for Meridian 1 system users are based on system port (TN) levels.

ISDN BRI feature prices are based on the number of Digital Subscriber Loops (DSLs) needed for ISDN Base Rate Interface (BRI) features.

All ACD/Call Center and Message Processing features prices are based on the number of ACD Agents in the systems.

Meridian Link Module Software prices are based on the number of telephone sets that are to be controlled or monitored by a computer application connected to Meridian 1 via Meridian Link.

Base Features

Base software is priced in increments of 100 up to 1000, and in increments of 500 thereafter, as shown below:

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 base software: TN pricing tables

Number of TNs	TN Level
1-100	1
101-200	2
201-300	3
301-400	4
401-500	5
501-600	6
601-700	7
701-800	8
801-900	9
901-1000	10
1001-1500	11
1501-2000	12
2001-2500	13
2500+	Note
Note: Increments of 500 TNs thereafter: Level + (TNs -1000)/500 +10	

Optional Features

The maximum charge level for optional features with TN-based pricing is Level 10 (1000 TNs). Minimum purchase requirement for new systems are specified as follows:

Options	Minimum TNs
21E	200
51	200
61	200
81	1000
Note: Minimum purchase requirements waived for upgrades.	

X11 Release 25 Software

Base/Option Features

S ➤ Δ	NTS101AA	Call Processor II	1	No charge	
S ➤ ⊗	NTS102AA	Corporate Directory, Virtual Office	1	500.00	I
S ➤ Δ	NTS103AA	Fiber Network	1	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0000L	Meridian 1 Base System Software: Release 25. Includes: - 500/250 Line Disconnect Incoming & Outgoing Calls - 500/2500 Set Features - Alarm Management - ANI Route Selection - Attendant Administration - Attendant Alternative Answering - Attendant and Network Wide Remote Call Forward - Attendant Autoline Key - Attendant Blocking of DN - Attendant Break-In - Attendant Emergency Codes - Attendant End-to-End Signaling - Attendant Forward No Answer - Authorization Codes/Authorization Code Security - Automatic Handsfree Answerback - Automatic Line Selection - Automatic Number Identification (ANI) - Automatic Set Display - Automatic Set Relocation - BARS - Basic Message Center - Call Forward & Busy Status - Call Forward / Hunt Override via FFC - For Network, Require s NAS - Call Forward Reminder Tone - Call Forward Save on Dump/Sysload - Call Page Networkwide - Call Park / Call Park on Non-Supervised CO Trunks - Call Park & Page, Network Wide, Requires NAS for internode operation - Call Park Networkwide - Call Party Name Display - Call Pick-up - Call Redirection by Time of Day - Called Party Control FFC - Calling Party Privacy Enhancement - Call Trace Enhancement - Call Waiting Redirection - CDR 100 Hour Call - CDR Charge Account Code - CDR Forced Charge Account - CDR on Busy Tone	∞	6,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- CENTREX Switch Hook Flash - Conference - Deluxe Hold - Departmental LDN - Dial Access to Group Call - Dial Intercom - DID Answer Supervision - Digital Display - Direct Private Network Access - Directory Number Delayed Ringing - Distinctive Ringing - Do-Not-Disturb - E.164 ESN Numbering Plan Expansion (Time-T) - Electronic Lock - Network Wide - Emergency Services Access - Basic - End-To-End Signaling Enhancements - Enhanced Controlled Class of Service - Enhanced Malicious Call Trace - Enhanced Music - Enhanced Night Service - Ethernet Connectivity - Flexible Feature Code Enhancements - Flexible Hotline - Global CDR Record - History File - Incoming DID Conversion - Individual Attendant DN/DID - Individual Call Hold Enhancement - Intercept - Internal Call Forward - Internal CDR - Last Number Redial/Stored Number Redial - Limited Access to Overlays - Make Set Busy - Malicious Call Trace DN/TN Print - Meridian Mail Trunk Access Restrictions - Meridian Mail Voice Mailbox Integration - MSDL/MISP Interface Handler - Multi-Party Operations - Multi-User Login - NARS - Network Wide Listed Directory Numbers (LDN) - Requires SW0055 (NAS) to operate over the network		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- New Flexible Code Restriction		
		- North American Numbering Plan (NANP)		
		- ODAS		
		- Off-Hook Alarm Security		
		- Phantom TN Operation		
		- Pretranslation/System Speed Call Enhancement		
		- Priority Override		
		- Recall After Parking		
		- Recall To Same Attendant		
		- Recorded Announcements		
		- Diverted Calls/Overflow		
		- Recovery of Misoperation of the Attendant Console		
		- Remote Call Forward		
		- Restricted Call Transfer		
		- Ring Again on No Answer		
		- Scheduled Access Restrictions		
		- SDI Support on MSDL		
		- Selectable Conferee Display and Disconnect		
		- Semi-Automatic Camp-On		
		- Series Call		
		- Set Based Administration		
		- Set-to-Set Messaging		
		- Single Terminal Access		
		- Speed Call on Private Lines		
		- Station Activity Record		
		- Station Camp-On		
		- Station Category Indicator		
		- Superloop Administration		
		- Supervised CO Trunk Simplification		
		- Supervisory Console		
		- System Speed Call		
		- Transparent Data Networking		
		- Trunk Barring		
		- Trunk Traffic Enhancements		
		- Trunk Verification		
		- User Selectable Call Redirection		
		- 510 Truck Route Member Expansion		
		- Automatic Hold		
		- Call Capacity Report Enhancements		
		- Call Redirection by Day		
		- Call Party Privacy Override		
		- Make Set Busy Improvement		
		- Message Waiting Indicator by DN		
		- Bearer Capability in CDR		

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- Meridian Companion - Meridian Companion Enhanced Capacity - MSDL/DDP Status Message Enquiry Throttle - Off Hook Alarm Enhancements - Meridian 1 Inventory Query - Semi-permanent connection enhancement			
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0011A	Option 81 - Required for Option 81	∞	No charge	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	∞	No charge	
S ➤	SW0015A	SNMP Open Alarms	1	500.00	I
S ➤	SW0016A	MAT Data Buffering and Access	1	1,500.00	I
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030B	Flexible Tones and Cadences. - Distinctive Ringing by DN	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0040A	CLASS Software. Custom Local Area Signaling Service (CLASS) Includes: - Calling Name - Calling Number	∞	1,750.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	1	No charge	
S ➤	SW0049A	Remote Software Option	10	250.00	I
S ➤	SW0050B	Networking	10	1,250.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0051B	ISDN Networking. Includes: - B-Channel Overload Control - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - NPI and TON in CDR Records - Primary Rate Interface - National ISDN 2 PRI (TR-1268) - MSDL Idle Code Selection - Display of Access Prefix on CLID - MCDN Alternate Routing	10	2,250.00	I
S ➤	SW0052D	Private ISDN Networking. Includes: - Call Pickup, Network Wide - Trunk Anti-Tromboning	10	500.00	I
S ➤	SW0053B	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call - NI-2 Call by Call Service Selection	10	800.00	I
S ➤	SW0055A	Network Attendant Services. Includes: - ISDN Supplementary Package	10	2,500.00	I
S ➤	SW0057A	Virtual Network Service	10	800.00	I
S ➤	SW0059B	Network Message Services	10	1,100.00	I
S ➤	SW0060A	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up	10	250.00	I
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I
S ➤	SW0104B	Q.Sig ISDN Networking Software. - MCDN End-to-End Transparency	10	2,500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0105A	ISDN Q.Sig Supplementary Services. Includes: - Q.Sig Path Replacement - Q.Sig Call Diversion Notification - Q.Sig Alternate Routing	10	500.00	I
S ➤	SW0110A	2.0 MB DTI/PRI Networking	10	250.00	I
S ➤	SW0165A	Emergency Services Access (ESA) Enhanced Services. Includes: - Basic on-site notification - ISDN trunk to CAMA tandem ESA calls - non-DID to DID mapping	10	2,500.00	I
S ➤	SW0170A	Call Pilot Connectivity	1	No charge	
S ➤	SW0234A	Electronic Brandlining - Display Customization	∞	250.00	I

Broadcast Features

S ➤	SW0150A	Recorded Announcement Broadcast. Provides one software connection from a RAN source to incoming callers. Up to 48 callers can be connected to a single RAN source through 1 trunk port.		400.00	I
S ➤	SW0155A	Music Broadcast. Provides a software connection from a music source to incoming callers. Up to 64 callers can be connected to a single music source through 1 trunk port.		140.00	I

RAN Broadcast

RAN Broadcast Connections allow multiple callers to simultaneously listen to recorded announcements through a single trunk port via software. Each unit of SW0150A provides one RAN connection. Multiple RAN Connections are purchased by ordering multiple units of SW0150A. One RAN "connection" provides RAN services to one caller/listener.

RAN Broadcast pricing table

Number of Recorded Announcement Listeners	Number of RAN connection purchased
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Music Broadcast

Music Broadcast Connections allow multiple callers to simultaneously listen to music on-hold through a single trunk port via software. Each unit of SW0155A provides one music connection. Multiple music connections are purchased by ordering multiple units of SW0155A. One music "connection" provides music on-hold services to one caller/listener.

Broadcast features pricing table

Number of RAN connections	Number of Music connections
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)

ISDN/BRI Features

S ➤	SW0101C	Basic Rate Interface. Includes: - BRI Supplementary Services - ISDN BRI Capacity Enhancements - National ISDN	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I

ACD/Message Processing Features

S ➤	NT1R29AA	Next Generation Connectivity	1	No charge
S ✓ ➤	NT1R59AA	Symposium Call Center Server - Next Generation	1	No charge

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0221C	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - 7 Digit DNIS for MAX - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Called ID - Dialed Number ID Service (DNIS) - DNIS Length Flexibility - Dual VAS ID - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control of Queue Size - N Digit DNIS	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	
S ➤	SW0228A	CCR-NACD Interworking	1	5,000.00	D
S ✓ ➤	SW0229D	Meridian 911. Includes: - Call Waiting Notification - 10/20 Digit on ANI	1	4,000.00	I
S ➤	SW0230A	Multiple Queue Assignment	∞	1,500.00	I

Meridian Link Associated Station (AST) Features

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 24 Software

X11 Release 25 Software Order Code/Option Matrix

Order Code	Description	Options
NT1R29AA	**Next Generation Connectivity**	324
NT1R59AA	**Symposium Call Center Server - Next Generation**	311
NTS101AA	**Call Processor II**	368
NTS102AA	**Corporate Directory, Virtual Office**	381, 382
NTS103AA	**Fiber Network**	365
SW0000L	**Meridian 1 Base System Software: Release 25**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 121, 127, 132, 133, 139, 140, 141, 157, 162, 164, 167, 170, 173, 174, 181, 186, 191, 203, 204, 205, 222, 223, 227, 228, 229, 234, 240, 242, 243, 245, 246, 250, 251, 253, 254, 256, 258, 296, 301, 306, 307, 310, 329, 350, 380
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0011A	**Option 81 - Required for Option 81**	298
SW0013A	**Option 81C - Required for Option 81C**	299
SW0015A	**SNMP Open Alarms**	315
SW0016A	**MAT Data Buffering and Access**	351
SW0028A	**Fast TDS**	87
SW0030B	**Flexible Tones and Cadences**	125, 185
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0040A	**CLASS Software**	332, 333
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0048A	**Meridian COMPANION CLID/CPND/ Privacy**	240
SW0049A	**Remote Software Option**	286
SW0050B	**Networking**	37, 38, 39, 59, 62, 63, 67, 160
SW0051B	**ISDN Networking**	118, 145, 146, 147, 291
SW0052D	**Private ISDN Networking**	148, 192, 312
SW0053B	**Public ISDN Access**	117, 149, 334
SW0055A	**Network Attendant Services**	159, 161
SW0057A	**Virtual Network Service**	183
SW0059B	**Network Message Services**	175, 219
SW0060A	**Basic Hospitality**	99, 100, 101, 102, 206, 212
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101C	**Basic Rate Interface**	216, 235
SW0102A	**Meridian 1 Packet Handler**	248
SW0104B	**Q.Sig ISDN Networking Software**	263, 305, 348
SW0105A	**ISDN Q.Sig Supplementary Services**	316
SW0110A	**2.0 MB DTI/PRI Networking**	129, 154, 202
SW0150A	**Recorded Announcement Broadcast**	327
SW0155A	**Music Broadcast**	328
SW0165A	**Emergency Services Access (ESA) Enhanced Services**	330, 331
SW0170A	**Call Pilot Connectivity**	153, 324, 364
SW0221C	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0228A	**CCR-NACD Interworking**	321
SW0229D	**Meridian 911**	224, 225, 249
SW0230A	**Multiple Queue Assignment**	297
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

Base/Option Features

S ➤	SW0000K	Meridian 1 Base System Software: Release 24. Includes: - 500/250 Line Disconnect Incoming & Outgoing Calls - 500/2500 Set Features - Alarm Management - ANI Route Selection - Attendant Administration - Attendant Alternative Answering - Attendant and Network Wide Remote Call Forward - Attendant Autoline Key - Attendant Blocking of DN - Attendant Break-In - Attendant Emergency Codes - Attendant End-to-End Signaling - Attendant Forward No Answer - Authorization Codes/Authorization Code Security - Automatic Handsfree Answerback - Automatic Line Selection - Automatic Number Identification (ANI) - Automatic Set Display - Automatic Set Relocation - BARS - Basic Message Center - Call Forward & Busy Status - Call Forward / Hunt Override via FFC - For Network, Require s NAS - Call Forward Reminder Tone - Call Forward Save on Dump/Sysload - Call Page Networkwide - Call Park / Call Park on Non-Supervised CO Trunks - Call Park & Page, Network Wide, Requires NAS for internode operation - Call Park Networkwide - Call Party Name Display - Call Pick-up - Call Redirection by Time of Day - Called Party Control FFC - Calling Party Privacy Enhancement - Call Trace Enhancement - Call Waiting Redirection - CDR 100 Hour Call - CDR Charge Account Code - CDR Forced Charge Account - CDR on Busy Tone	∞	6,000.00	I

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- CENTREX Switch Hook Flash - Conference - Deluxe Hold - Departmental LDN - Dial Access to Group Call - Dial Intercom - DID Answer Supervision - Digital Display - Direct Private Network Access - Directory Number Delayed Ringing - Distinctive Ringing - Do-Not-Disturb - E.164 ESN Numbering Plan Expansion (Time-T) - Electronic Lock - Network Wide - Emergency Services Access - Basic - End-To-End Signaling Enhancements - Enhanced Controlled Class of Service - Enhanced Malicious Call Trace - Enhanced Music - Enhanced Night Service - Ethernet Connectivity - Flexible Feature Code Enhancements - Flexible Hotline - Global CDR Record - History File - Incoming DID Conversion - Individual Attendant DN/DID - Individual Call Hold Enhancement - Intercept - Internal Call Forward - Internal CDR - Last Number Redial/Stored Number Redial - Limited Access to Overlays - Make Set Busy - Malicious Call Trace DN/TN Print - Meridian Mail Trunk Access Restrictions - Meridian Mail Voice Mailbox Integration - MSDL/MISP Interface Handler - Multi-Party Operations - Multi-User Login - NARS - Network Wide Listed Directory Numbers (LDN) - Requires SW0055 (NAS) to operate over the network		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- New Flexible Code Restriction - North American Numbering Plan (NANP) - ODAS - Off-Hook Alarm Security - Phantom TN Operation - Pretranslation/System Speed Call Enhancement - Priority Override - Recall After Parking - Recall To Same Attendant - Recorded Announcements - Diverted Calls/Overflow - Recovery of Misoperation of the Attendant Console - Remote Call Forward - Restricted Call Transfer - Ring Again on No Answer - Scheduled Access Restrictions - SDI Support on MSDL - Selectable Conferee Display and Disconnect - Semi-Automatic Camp-On - Series Call - Set Based Administration - Single Terminal Access - Speed Call on Private Lines - Station Activity Record - Station Camp-On - Station Category Indicator - Superloop Administration - Supervised CO Trunk Simplification - Supervisory Console - System Speed Call - Transparent Data Networking - Trunk Barring - Trunk Traffic Enhancements - Trunk Verification - User Selectable Call Redirection - 510 Truck Route Member Expansion - Automatic Hold - Call Capacity Report Enhancements - Call Redirection by Day - Call Party Privacy Override - Make Set Busy Improvement - Message Waiting Indicator by DN - Bearer Capability in CDR - Meridian Companion - Meridian Companion Enhanced Capacity - MSDL/DDP Status Message Enquiry Throttle - Off Hook Alarm Enhancements - Meridian 1 Inventory Query - Semi-permanent connection enhancement		

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0011A	Option 81 - Required for Option 81	∞	No charge	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	∞	No charge	
S ➤	SW0015A	SNMP Open Alarms	1	500.00	I
S ➤	SW0016A	MAT Data Buffering and Access	1	1,500.00	I
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030B	Flexible Tones and Cadences. - Distinctive Ringing by DN	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0040A	CLASS Software. Custom Local Area Signaling Service (CLASS) Includes: - Calling Name - Calling Number	∞	1,750.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	1	No charge	
S ➤	SW0049A	Remote Software Option	10	250.00	I
S ➤	SW0050B	Networking	10	1,250.00	I
S ➤	SW0051B	ISDN Networking. Includes: - B-Channel Overload Control - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - NPI and TON in CDR Records - Primary Rate Interface - National ISDN 2 PRI (TR-1268) - MSDL Idle Code Selection - Display of Access Prefix on CLID - MCDN Alternate Routing	10	2,250.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0052D	Private ISDN Networking. Includes: - Call Pickup, Network Wide - Trunk Anti-Tromboning	10	500.00	I
S ➤	SW0053B	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call - NI-2 Call by Call Service Selection	10	800.00	I
S ➤	SW0055A	Network Attendant Services. Includes: - ISDN Supplementary Package	10	2,500.00	I
S ➤	SW0057A	Virtual Network Service	10	800.00	I
S ➤	SW0059B	Network Message Services	10	1,100.00	I
S ➤	SW0060B	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up - Flexible DID	10	250.00	I
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I
S ➤	SW0104B	Q.Sig ISDN Networking Software. - MCDN End-to-End Transparency	10	2,500.00	I
S ➤	SW0105A	ISDN Q.Sig Supplementary Services. Includes: - Q.Sig Path Replacement - Q.Sig Call Diversion Notification - Q.Sig Alternate Routing	10	500.00	I
S ➤	SW0110A	2.0 MB DTI/PRI Networking	10	250.00	I
S ➤	SW0165A	Emergency Services Access (ESA) Enhanced Services. Includes: - Basic on-site notification - ISDN trunk to CAMA tandem ESA calls - non-DID to DID mapping	10	2,500.00	I
S ➤	SW0170A	Call Pilot Connectivity	1	No charge	
S ➤	SW0234A	Electronic Brandlining - Display Customization	∞	250.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Broadcast Features

The following features are introduced as of Release 23.

- Recorded Announcement Broadcast
- Music Broadcast

These features are priced independently of the overall system TN count and in increments of one connection with a system maximum of 9,999 connections. When provisioning Recorded Announcement Broadcast (RAN Broadcast) or Music Broadcast, the number of software "connections" ordered should be equal to the maximum number of people who can listen to the recorded announcement/music at any one time.

S ➤	SW0150A	Recorded Announcement Broadcast. Provides one software connection from a RAN source to incoming callers. Up to 48 callers can be connected to a single RAN source through 1 trunk port.	400.00	I
S ➤	SW0155A	Music Broadcast. Provides a software connection from a music source to incoming callers. Up to 64 callers can be connected to a single music source through 1 trunk port.	140.00	I

RAN Broadcast

RAN Broadcast Connections allow multiple callers to simultaneously listen to recorded announcements through a single trunk port via software. Each unit of SW0150A provides one RAN connection. Multiple RAN Connections are purchased by ordering multiple units of SW0150A. One RAN "connection" provides RAN services to one caller/listener.

RAN Broadcast pricing table

Number of Recorded Announcement Listeners	Number of RAN connection purchased
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)
Note: Continues in increments of one, up to 9,999	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Music Broadcast

Music Broadcast Connections allow multiple callers to simultaneously listen to music on-hold through a single trunk port via software. Each unit of SW0155A provides one music connection. Multiple music connections are purchased by ordering multiple units of SW0155A. One music "connection" provides music on-hold services to one caller/listener.

Broadcast features pricing table

Number of RAN connections	Number of Music connections
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)
Note: Continues in increments of one, up to 9,999.	

ISDN/BRI Features

ISDN BRI features prices are based on the number of Digital Subscriber Loops (DSLs) used in the system. A DSL is the software designation of a BRI physical connection that accommodates two B-channels.

BRI features are priced in increments of 50 DSLs, as the following table shows:

X11 ISDN BRI software: DSL pricing table

Number of DSLs	DSL Level
1-50	1
51-100	2
101-150	3
151-200	4
201-250	5
251-300	6
301-350	7
351-400	8
401-450	9

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 ISDN BRI software: DSL pricing table

Number of DSLs	DSL Level
451-500	10
501-550	11
551-600	12
601-650	13
651+	Note
Note: Increments of 50 DSLs thereafter: Level + DSLs/50	

S ➤	SW0101C	Basic Rate Interface. Includes: - BRI Supplementary Services - ISDN BRI Capacity Enhancements - National ISDN	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I

ACD/Message Processing Features

All ACD/Call Center and Message Processing feature prices are based on the number of ACD Agents in the system. An ACD Agent is any TN with a Directory Number (DN) designated as an ACD DN in Meridian 1 software. Meridian Mail ports also count as ACD Agents.

ACD/Call Center and Message Processing feature prices are in increments of 20 from 1 to 200 agents and increments of 100 above 200 agents, as follows:

X11 ACD/Message Processing software: ACD agent pricing table

Number of ACD Agents	Agent Level
1-20	1
21-40	2
41-60	3
61-80	4
81-100	5
101-120	6
121-140	7
141-160	8
161-180	9
181-200	10
201-300	11
301-400	12
401-500	13

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 ACD/Message Processing software: ACD agent pricing table

Number of ACD Agents	Agent Level
501+	Note
Note: Increments of 100 Agents thereafter: Level = (Agents - 200)/100+10	

S ➤	NT1R29AA	Next Generation Connectivity	1	No charge	
S ✓ ➤	NT1R59AA	Symposium Call Center Server - Next Generation	1	No charge	
S ➤	SW0221C	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - 7 Digit DNIS for MAX - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Called ID - Dialed Number ID Service (DNIS) - DNIS Length Flexibility - Dual VAS ID - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control of Queue Size - N Digit DNIS	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0228A	CCR-NACD Interworking	1	5,000.00	D
S ➤	SW0229C	Meridian 911. Includes: - Call Waiting Notification	1	4,000.00	I
S ➤	SW0230A	Multiple Queue Assignment	∞	1,500.00	I

Meridian Link Associated Station (AST) Features

Pricing for the Meridian Link Module Software (SW0251A) is based on the number of telephone sets that are to be controlled or monitored by a computer application connected to Meridian 1 via Meridian Link. Each such set must be configured with the "AST" feature. A set with this feature is known as an "Associated Station" or AST set.

Each increment of Meridian Link Module Software increases the number of ASTs that can be controlled or monitored by Meridian Link.

Note: When the maximum level of 18 increments is ordered, the AST limit is set equal to the system TN limit.

X11 software AST set pricing table

Number of SW0251 increments	Number of AST sets configurable
1	1-20
2	21-40
3	41-60
4	61-80
5	81-100
6	101-120
7	121-140
8	141-160
9	161-180
10	181-200
11	201-300
12	301-400
13	401-500
14	501-600
15	601-700
16	701-800
17	801-900
	901-up to system TN limit

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 24 Software Order Code/Option Matrix

Order Code	Description	Options
NT1R29AA	**Next Generation Connectivity**	324
NT1R59AA	**Symposium Call Center Server - Next Generation**	311
SW0000K	**Meridian 1 Base System Software: Release 24**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 121, 127, 132, 133, 139, 140, 141, 157, 162, 164, 167, 170, 173, 174, 181, 186, 191, 203, 204, 205, 222, 223, 227, 228, 229, 234, 240, 242, 243, 245, 246, 250, 251, 253, 254, 256, 258, 296, 301, 306, 307, 310, 329, 350
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0011A	**Option 81 - Required for Option 81**	298
SW0013A	**Option 81C - Required for Option 81C**	299
SW0015A	**SNMP Open Alarms**	315
SW0016A	**MAT Data Buffering and Access**	351
SW0028A	**Fast TDS**	87
SW0030B	**Flexible Tones and Cadences**	125, 185
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0040A	**CLASS Software**	332, 333
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0048A	**Meridian COMPANION CLID/CPND/ Privacy**	240
SW0049A	**Remote Software Option**	286
SW0050B	**Networking**	37, 38, 39, 59, 62, 63, 67, 160
SW0051B	**ISDN Networking**	118, 145, 146, 147, 291

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0052D	**Private ISDN Networking**	148, 192, 312
SW0053B	**Public ISDN Access**	117, 149, 334
SW0055A	**Network Attendant Services**	159, 161
SW0057A	**Virtual Network Service**	183
SW0059B	**Network Message Services**	175, 219
SW0060B	**Basic Hospitality**	99, 100, 101, 102, 206, 212, 362
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101C	**Basic Rate Interface**	216, 235
SW0102A	**Meridian 1 Packet Handler**	248
SW0104B	**Q.Sig ISDN Networking Software**	263, 305, 348
SW0105A	**ISDN Q.Sig Supplementary Services**	316
SW0110A	**2.0 MB DTI/PRI Networking**	129, 154, 202
SW0150A	**Recorded Announcement Broadcast**	327
SW0155A	**Music Broadcast**	328
SW0165A	**Emergency Services Access (ESA) Enhanced Services**	330, 331
SW0170A	**Call Pilot Connectivity**	153, 324, 364
SW0221C	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0228A	**CCR-NACD Interworking**	321
SW0229C	**Meridian 911**	224, 225
SW0230A	**Multiple Queue Assignment**	297
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 Release 23 Software

Base/Option Features

S ➤	SW0000J	Meridian 1 Base System Software: Release 23. Includes: - 500/250 Line Disconnect Incoming & Outgoing Calls - 500/2500 Set Features - Alarm Management - ANI Route Selection - Attendant Administration - Attendant Alternative Answering - Attendant and Network Wide Remote Call Forward - Attendant Autoline Key - Attendant Blocking of DN - Attendant Break-In - Attendant Emergency Codes - Attendant End-to-End Signaling - Attendant Forward No Answer - Authorization Codes/Authorization Code Security - Automatic Handsfree Answerback - Automatic Line Selection - Automatic Number Identification (ANI) - Automatic Set Display - Automatic Set Relocation - BARS - Basic Message Center - Call Forward & Busy Status - Call Forward / Hunt Override via FFC - For Network, Require s NAS - Call Forward Reminder Tone - Call Forward Save on Dump/Sysload - Call Page Networkwide - Call Park / Call Park on Non-Supervised CO Trunks - Call Park & Page, Network Wide, Requires NAS for internode operation - Call Park Networkwide - Call Party Name Display - Call Pick-up - Call Redirection by Time of Day - Called Party Control FFC - Calling Party Privacy Enhancement - Call Trace Enhancement - Call Waiting Redirection - CDR 100 Hour Call - CDR Charge Account Code - CDR Forced Charge Account - CDR on Busy Tone	∞	6,000.00	I

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- CENTREX Switch Hook Flash - Conference - Deluxe Hold - Departmental LDN - Dial Access to Group Call - Dial Intercom - DID Answer Supervision - Digital Display - Direct Private Network Access - Directory Number Delayed Ringing - Distinctive Ringing - Do-Not-Disturb - E.164 ESN Numbering Plan Expansion (Time-T) - Electronic Lock - Network Wide - Emergency Services Access - Basic - End-To-End Signaling Enhancements - Enhanced Controlled Class of Service - Enhanced Malicious Call Trace - Enhanced Music - Enhanced Night Service - Ethernet Connectivity - Flexible Feature Code Enhancements - Flexible Hotline - Global CDR Record - History File - Incoming DID Conversion - Individual Attendant DN/DID - Individual Call Hold Enhancement - Intercept - Internal Call Forward - Internal CDR - Last Number Redial/Stored Number Redial - Limited Access to Overlays - Make Set Busy - Malicious Call Trace DN/TN Print - Meridian Mail Trunk Access Restrictions - Meridian Mail Voice Mailbox Integration - MSDL/MISP Interface Handler - Multi-Party Operations - Multi-User Login - NARS - Network Wide Listed Directory Numbers (LDN) - Requires SW0055 (NAS) to operate over the network		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- New Flexible Code Restriction - North American Numbering Plan (NANP) - ODAS - Off-Hook Alarm Security - Phantom TN Operation - Pretranslation/System Speed Call Enhancement - Priority Override - Recall After Parking - Recall To Same Attendant - Recorded Announcements - Diverted Calls/Overflow - Recovery of Misoperation of the Attendant Console - Remote Call Forward - Restricted Call Transfer - Ring Again on No Answer - Scheduled Access Restrictions - SDI Support on MSDL - Selectable Conferee Display and Disconnect - Semi-Automatic Camp-On - Series Call - Set Based Administration - Single Terminal Access - Speed Call on Private Lines - Station Activity Record - Station Camp-On - Station Category Indicator - Superloop Administration - Supervised CO Trunk Simplification - Supervisory Console - System Speed Call - Transparent Data Networking - Trunk Barring - Trunk Traffic Enhancements - Trunk Verification - User Selectable Call Redirection			
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0011A	Option 81 - Required for Option 81	∞	No charge	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	∞	No charge	
S ➤	SW0015A	SNMP Open Alarms	1	500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030A	Flexible Tones and Cadences	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0040A	CLASS Software. Custom Local Area Signaling Service (CLASS) Includes: - Calling Name - Calling Number	∞	1,750.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	1	No charge	
S ➤	SW0049A	Remote Software Option	10	250.00	I
S ➤	SW0050B	Networking	10	1,250.00	I
S ➤	SW0051B	ISDN Networking. Includes: - B-Channel Overload Control - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - NPI and TON in CDR Records - Primary Rate Interface - National ISDN 2 PRI (TR-1268) - MSDL Idle Code Selection - Display of Access Prefix on CLID - MCDN Alternate Routing	10	2,250.00	I
S ➤	SW0052D	Private ISDN Networking. Includes: - Call Pickup, Network Wide - Trunk Anti-Tromboning	10	500.00	I
S ➤	SW0053B	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call - NI-2 Call by Call Service Selection	10	800.00	I
S ➤	SW0055A	Network Attendant Services. Includes: - ISDN Supplementary Package	10	2,500.00	I
S ➤	SW0057A	Virtual Network Service	10	800.00	I
S ➤	SW0059B	Network Message Services	10	1,100.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0060A	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up	10	250.00	I
S ➤	SW0060B	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up - Flexible DID	10	250.00	I
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I
S ➤	SW0104A	Q.Sig ISDN Networking Software	10	2,500.00	I
S ➤	SW0105A	ISDN Q.Sig Supplementary Services. Includes: - Q.Sig Path Replacement - Q.Sig Call Diversion Notification - Q.Sig Alternate Routing	10	500.00	I
S ➤	SW0165A	Emergency Services Access (ESA) Enhanced Services. Includes: - Basic on-site notification - ISDN trunk to CAMA tandem ESA calls - non-DID to DID mapping	10	2,500.00	I
S ➤	SW0234A	Electronic Brandlining - Display Customization	∞	250.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Broadcast Features

The following features are introduced as of Release 23.

- Recorded Announcement Broadcast
- Music Broadcast

These features are priced independently of the overall system TN count and in increments of one connection with a system maximum of 9,999 connections. When provisioning Recorded Announcement Broadcast (RAN Broadcast) or Music Broadcast, the number of software "connections" ordered should be equal to the maximum number of people who can listen to the recorded announcement/music at any one time.

S ➤	SW0150A	Recorded Announcement Broadcast. Provides one software connection from a RAN source to incoming callers. Up to 48 callers can be connected to a single RAN source through 1 trunk port.	400.00	I
S ➤	SW0155A	Music Broadcast. Provides a software connection from a music source to incoming callers. Up to 64 callers can be connected to a single music source through 1 trunk port.	140.00	I

RAN Broadcast

RAN Broadcast Connections allow multiple callers to simultaneously listen to recorded announcements through a single trunk port via software. Each unit of SW0150A provides one RAN connection. Multiple RAN Connections are purchased by ordering multiple units of SW0150A. One RAN "connection" provides RAN services to one caller/listener.

RAN Broadcast pricing table

Number of Recorded Announcement Listeners	Number of RAN connection purchased
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)
Note: Continues in increments of one, up to 9,999	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Music Broadcast

Music Broadcast Connections allow multiple callers to simultaneously listen to music on-hold through a single trunk port via software. Each unit of SW0155A provides one music connection. Multiple music connections are purchased by ordering multiple units of SW0155A. One music "connection" provides music on-hold services to one caller/listener.

Broadcast features pricing table

Number of RAN connections	Number of Music connections
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
10+ (Note)	10+ (Note)
Note: Continues in increments of one, up to 9,999.	

ISDN/BRI Features

ISDN BRI features prices are based on the number of Digital Subscriber Loops (DSLs) used in the system. A DSL is the software designation of a BRI physical connection that accommodates two B-channels.

BRI features are priced in increments of 50 DSLs, as the following table shows:

X11 ISDN BRI software: DSL pricing table

Number of DSLs	DSL Level
1-50	1
51-100	2
101-150	3
151-200	4
201-250	5
251-300	6
301-350	7
351-400	8
401-450	9

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 ISDN BRI software: DSL pricing table

Number of DSLs	DSL Level
451-500	10
501-550	11
551-600	12
601-650	13
651+	Note

S ➤	SW0101C	Basic Rate Interface. Includes: - BRI Supplementary Services - ISDN BRI Capacity Enhancements - National ISDN	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I

ACD/Message Processing Features

All ACD/Call Center and Message Processing feature prices are based on the number of ACD Agents in the system. An ACD Agent is any TN with a Directory Number (DN) designated as an ACD DN in Meridian 1 software. Meridian Mail ports also count as ACD Agents.

ACD/Call Center and Message Processing feature prices are in increments of 20 from 1 to 200 agents and increments of 100 above 200 agents, as follows:

X11 ACD/Message Processing software: ACD agent pricing table

Number of ACD Agents	Agent Level
1-20	1
21-40	2
41-60	3
61-80	4
81-100	5
101-120	6
121-140	7
141-160	8
161-180	9
181-200	10
201-300	11
301-400	12
401-500	13
501+	Note
Note: Increments of 100 Agents thereafter: Level = (Agents - 200)/100+10	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0221C	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - 7 Digit DNIS for MAX - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Called ID - Dialed Number ID Service (DNIS) - DNIS Length Flexibility - Dual VAS ID - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control of Queue Size - N Digit DNIS	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	
S ➤	SW0228A	CCR-NACD Interworking	1	5,000.00	D
S ➤	SW0229C	Meridian 911. Includes: - Call Waiting Notification	1	4,000.00	I
S ➤	SW0230A	Multiple Queue Assignment	∞	1,500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Link Associated Station (AST) Features

Pricing for the Meridian Link Module Software (SW0251A) is based on the number of telephone sets that are to be controlled or monitored by a computer application connected to Meridian 1 via Meridian Link. Each such set must be configured with the "AST" feature. A set with this feature is known as an "Associated Station" or AST set.

Each increment of Meridian Link Module Software increases the number of ASTs that can be controlled or monitored by Meridian Link.

Note: When the maximum level of 18 increments is ordered, the AST limit is set equal to the system TN limit.

X11 software AST set pricing table

Number of SW0251 increments	Number of AST sets configurable
1	1-20
2	21-40
3	41-60
4	61-80
5	81-100
6	101-120
7	121-140
8	141-160
9	161-180
10	181-200
11	201-300
12	301-400
13	401-500
14	501-600
15	601-400
16	701-800
17	801-900
	901-up to system TN limit

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 23 Software Order Code/Option Matrix

Order Code	Description	Options
SW0000J	**Meridian 1 Base System Software: Release 23**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 54, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 121, 127, 132, 133, 139, 140, 141, 157, 162, 164, 170, 173, 174, 181, 186, 191, 203, 204, 205, 222, 223, 227, 228, 229, 234, 242, 243, 245, 246, 250, 251, 253, 254, 256, 258, 296, 301, 306, 307, 310, 329
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0011A	**Option 81 - Required for Option 81**	298
SW0013A	**Option 81C - Required for Option 81C**	299
SW0015A	**SNMP Open Alarms**	315
SW0028A	**Fast TDS**	87
SW0030A	**Flexible Tones and Cadences**	125
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0040A	**CLASS Software**	332, 333
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0048A	**Meridian COMPANION CLID/CPND/ Privacy**	240
SW0049A	**Remote Software Option**	286
SW0050B	**Networking**	37, 38, 39, 59, 62, 63, 67, 160
SW0051B	**ISDN Networking**	118, 145, 146, 147, 291
SW0052D	**Private ISDN Networking**	148, 192, 312
SW0053B	**Public ISDN Access**	117, 149, 334
SW0055A	**Network Attendant Services**	159, 161
SW0057A	**Virtual Network Service**	183

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0059B	**Network Message Services**	175, 219
SW0060A	**Basic Hospitality**	99, 100, 101, 102, 206, 212
SW0060B	**Basic Hospitality**	99, 100, 101, 102, 206, 212, 362
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101C	**Basic Rate Interface**	216, 235
SW0102A	**Meridian 1 Packet Handler**	248
SW0104A	**Q.Sig ISDN Networking Software**	263, 305
SW0105A	**ISDN Q.Sig Supplementary Services**	316
SW0150A	**Recorded Announcement Broadcast**	327
SW0155A	**Music Broadcast**	328
SW0165A	**Emergency Services Access (ESA) Enhanced Services**	330, 331
SW0221C	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0228A	**CCR-NACD Interworking**	321
SW0229C	**Meridian 911**	224, 225
SW0230A	**Multiple Queue Assignment**	297
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 Release 22 Software

Base/Option Features

S ➤	SW0000H	Meridian 1 Release 22 Base Software. Includes: - 500/2500 Line Disconnect Incoming & Outgoing Calls - 500/2500 Set Features - Alarm Management - ANI Route Selection - Attendant Administration - Attendant Alternative Answering - Attendant and Network Wide Remote Call Forward - Attendant Blocking of DN - Attendant Break-In - Attendant End-to-End Signaling - Attendant Forward No Answer - Authorization Codes/Authorization Code Security - Automatic Handsfree Answerback - Automatic Line Selection - Automatic Number Identification (ANI) - Automatic Set Relocation - BARS - Basic Message Center - Call Forward & Busy Status - Call Forward / Hunt Override via FFC - For Network, Requires NAS - Call Forward Reminder Tone - Call Forward Save on Dump/Sysload - Call Page Networkwide - Call Park / Call Park on Non-Supervised CO Trunks - Call Park & Page, Network Wide, Requires NAS for internode operation - Call Park Networkwide - Call Party Name Display - Call Pick-up - Call Redirection by Time of Day - Called Party Control FFC - Call Trace Enhancement - Call Waiting Redirection - CDR 100 Hour Call - CDR Charge Account Code - CDR Forced Charge Account - CENTREX Switch Hook Flash - Conference - Deluxe Hold - Departmental LDN - Dial Access to Group Call - Dial Intercom	∞	6,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- DID Answer Supervision		
		- Digital Display		
		- Direct Private Network Access		
		- Directory Number Delayed Ringing		
		- Distinctive Ringing		
		- Do-Not-Disturb		
		- E.164 ESN Numbering Plan Expansion (Time-T)		
		- Electronic Lock - Network Wide		
		- End-To-End Signaling Enhancements		
		- Enhanced Controlled Class of Service		
		- Enhanced Malicious Call Trace		
		- Enhanced Music		
		- Enhanced Night Service		
		- Ethernet Connectivity		
		- Flexible Feature Code Enhancements		
		- Flexible Hotline		
		- Global CDR Record		
		- History File		
		- Incoming DID Conversion		
		- Intercept		
		- Internal Call Forward		
		- Internal CDR		
		- Last Number Redial/Stored Number Redial		
		- Limited Access to Overlays		
		- Make Set Busy		
		- Malicious Call Trace DN/TN Print		
		- Meridian Mail Trunk Access Restrictions		
		- Meridian Mail Voice Mailbox Integration		
		- MSDL/MISP Interface Handler		
		- Multi-Party Operations		
		- Multi-User Login		
		- NARS		
		- Network Wide Listed Directory Numbers (LDN) - Requires SW0055 (NAS) to operate over the network		
		- New Flexible Code Restriction		
		- North American Numbering Plan (NANP)		
		- ODAS		
		- Off-Hook Amarm Security		
		- Phantom TN Operation		
		- Priority Override		
		- Recall After Parking		
		- Recall To Same Attendant		
		- Recorded Announcements - Diverted Calls/Overflow		
		- Recovery of Misoperation of the Attendant Console		
		- Remote Call Forward		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- Restricted Call Transfer - Ring Again on No Answer - Scheduled Access Restrictions - SDI Support on MSDL - Semi-Automatic Camp-On - Series Call - Set Based Administration - Single Terminal Access - Speed Call on Private Lines - Station Activity Record - Station Camp-On - Station Category Indicator - Superloop Administration - Supervised CO Trunk Simplification - Supervisory Console - System Speed Call - Transparent Data Networking - Trunk Barring - Trunk Traffic Enhancements - Trunk Verification - User Selectable Call Redirection			
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0011A	Option 81 - Required for Option 81	∞	No charge	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	∞	No charge	
S ➤	SW0015A	SNMP Open Alarms	1	500.00	I
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030A	Flexible Tones and Cadences	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	1	No charge	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0049A	Remote Software Option	10	250.00	I
S ➤	SW0050B	Networking	10	1,250.00	I
S ➤	SW0051B	ISDN Networking. Includes: - B-Channel Overload Control - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - NPI and TON in CDR Records - Primary Rate Interface - National ISDN 2 PRI (TR-1268) - MSDL Idle Code Selection - Display of Access Prefix on CLID - MCDN Alternate Routing	10	2,250.00	I
S ➤	SW0052D	Private ISDN Networking. Includes: - Call Pickup, Network Wide - Trunk Anti-Tromboning	10	500.00	I
S ➤	SW0053A	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call Service	10	800.00	I
S ➤	SW0055A	Network Attendant Services. Includes: - ISDN Supplementary Package	10	2,500.00	I
S ➤	SW0057A	Virtual Network Service	10	800.00	I
S ➤	SW0059B	Network Message Services	10	1,100.00	I
S ➤	SW0060A	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up	10	250.00	I
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I
S ➤	SW0104A	Q.Sig ISDN Networking Software	10	2,500.00	I
S ➤	SW0105A	ISDN Q.Sig Supplementary Services. Includes: - Q.Sig Path Replacement - Q.Sig Call Diversion Notification - Q.Sig Alternate Routing	10	500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
ISDN/BRI Features					
S ➤	SW0101C	Basic Rate Interface. Includes: - BRI Supplementary Services - ISDN BRI Capacity Enhancements - National ISDN	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I
ACD/Message Processing Features					
S ➤	SW0221C	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - 7 Digit DNIS for MAX - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Called ID - Dialed Number ID Service (DNIS) - DNIS Length Flexibility - Dual VAS ID - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control of Queue Size - N Digit DNIS	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	
S ➤	SW0228A	CCR-NACD Interworking	1	5,000.00	D
S ➤	SW0229C	Meridian 911. Includes: - Call Waiting Notification	1	4,000.00	I
S ➤	SW0230A	Multiple Queue Assignment	∞	1,500.00	I

Meridian Link Associated Station (AST) Features

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 22 Software Order Code/Option Matrix

Order Code	Description	Options
SW0000H	**Meridian 1 Release 22 Base Software**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 121, 127, 132, 133, 139, 140, 141, 157, 162, 164, 170, 173, 174, 181, 186, 191, 203, 204, 205, 222, 223, 227, 228, 229, 234, 242, 243, 245, 246, 250, 251, 253, 254, 256, 258, 296, 301, 306, 307, 310
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0011A	**Option 81 - Required for Option 81**	298
SW0013A	**Option 81C - Required for Option 81C**	299
SW0015A	**SNMP Open Alarms**	315
SW0028A	**Fast TDS**	87
SW0030A	**Flexible Tones and Cadences**	125
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0048A	**Meridian COMPANION CLID/CPND/ Privacy**	240
SW0049A	**Remote Software Option**	286
SW0050B	**Networking**	37, 38, 39, 59, 62, 63, 67, 160
SW0051B	**ISDN Networking**	118, 145, 146, 147, 291
SW0052D	**Private ISDN Networking**	148, 192, 312
SW0053A	**Public ISDN Access**	117, 149
SW0055A	**Network Attendant Services**	159, 161
SW0057A	**Virtual Network Service**	183
SW0059B	**Network Message Services**	175, 219

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0060A	**Basic Hospitality**	99, 100, 101, 102, 206, 212
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101C	**Basic Rate Interface**	216, 235
SW0102A	**Meridian 1 Packet Handler**	248
SW0104A	**Q.Sig ISDN Networking Software**	263, 305
SW0105A	**ISDN Q.Sig Supplementary Services**	316
SW0221C	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0228A	**CCR-NACD Interworking**	321
SW0229C	**Meridian 911**	224, 225
SW0230A	**Multiple Queue Assignment**	297
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 Release 21 Software

Base/Option Features

S ➤	SW0000G	Meridian 1 Release 21 Base Software. Includes: - 500/2500 Line Disconnect Incoming & Outgoing Calls - 500/2500 Set Features - ANI Route Selection - Attendant Alternative Answer - Attendant and Network Wide Remote Call Forward - Attendant Blocking of DN - Attendant Break-In - Attendant End-to-End Signaling - Attendant Forward No Answer - Authorization Codes / Authorization Code Security - Automatic Handsfree Answerback - Auto Line Selection - Automatic Number Identification (ANI) - Automatic Set Relocation - BARS - Basic Message Center - Call Forward & Busy Status - Call Forward / Hunt Override via FFC - For Network, Requires NAS - Call Forward Reminder Tone - Call Forward Save on Dump / Sysload - Call Park / Call Park on Non-Supervised CO Trunks - Call Party Name Display - Call Pick-up - Call Trace Enhancement - Call Waiting Redirection - Calling Party Privacy - CDR Charge Account Code - CDR Forced Charge Account - CENTREX Switch Hook Flash - Conference - Deluxe Hold - Departmental LDN - Dial Access to Group Call - Dial Intercom - DID Answer Supervision - Digital Display - Direct Private Network Access - Directory Number Delayed Ringing - Distinctive Ringing - Do-Not-Disturb	∞	6,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		- Electronic Lock - Network Wide - End-to-End Signaling Enhancements - Enhanced Controlled Class of Service - Enhanced Malicious Call Trace - Enhanced Music - Enhanced Night Service - Flexible Feature Code Enhancements - Flexible Hotline - Global CDR Record - History File - Incoming DID Conversion - Intercept - Internal Call Forward - Internal CDR - Last Number Redial / Stored Number Redial - Limited Access to Overlays - Make Set Busy - Malicious Call Trace DN/TN Print - Meridian Mail Voice Mailbox Integration - MSDL/MISP Interface Handler - Multi-Party Operation - Multi-user Login - NARS - Network Wide Listed Directory Numbers- Requires SW0055A (NAS) to operate over the network - New Flexible Code Restriction - North American Numbering Plan (NANP) - ODAS - Off-Hook Alarm Security - Phantom TN Operation - Priority Override - Recall After Parking - Recall to Same Attendant - Recorded Announcement - Diverted Calls / Overflow - Recovery of Misoperation of the Attendant Console - Remote Call Forward - Restricted Call Transfer - Ring Again No Answer - Scheduled Access Restrictions - SDI Support on MSDL - Semi-Automatic Camp-On - Series Call - Set Based Administration - Single Terminal Access		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- Speed Call on Private Lines - Station Activity Record - Station Camp-on - Station Category Indicator - Superloop Administration - Supervised CO Trunk Simplification - Supervisory Console - System Speed Call - Transparent Data Networking - Trunk Barring - Trunk Traffic Enhancements - Trunk Verification - User Selectable Call Redirection			
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0011A	Option 81 - Required for Option 81	∞	No charge	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	∞	No charge	
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030A	Flexible Tones and Cadences	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	1	No charge	
S ➤	SW0049A	Remote Software Option	10	250.00	I
S ➤	SW0050B	Networking	10	1,250.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0051B	ISDN Networking. Includes: - B-Channel Overload Control - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - NPI and TON in CDR Records - Primary Rate Interface - National ISDN 2 PRI (TR-1268) - MSDL Idle Code Selection - Display of Access Prefix on CLID - MCDN Alternate Routing	10	2,250.00	I
S ➤	SW0052D	Private ISDN Networking. Includes: - Call Pickup, Network Wide - Trunk Anti-Tromboning	10	500.00	I
S ➤	SW0053A	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call Service	10	800.00	I
S ➤	SW0055A	Network Attendant Services. Includes: - ISDN Supplementary Package	10	2,500.00	I
S ➤	SW0057A	Virtual Network Service	10	800.00	I
S ➤	SW0059B	Network Message Services	10	1,100.00	I
S ➤	SW0060A	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up	10	250.00	I
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I

ISDN/BRI Features

S ➤	SW0101C	Basic Rate Interface. Includes: - BRI Supplementary Services - ISDN BRI Capacity Enhancements - National ISDN	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

ACD/Message Processing Features

S ➤	SW0221C	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - 7 Digit DNIS for MAX - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Called ID - Dialed Number ID Service (DNIS) - DNIS Length Flexibility - Dual VAS ID - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control of Queue Size - N Digit DNIS	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	
S ➤	SW0229C	Meridian 911. Includes: - Call Waiting Notification	1	4,000.00	I
S ➤	SW0230A	Multiple Queue Assignment	∞	1,500.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

Meridian Link Associated Station (AST) Features

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 21 Software Order Code/Option Matrix

Order Code	Description	Options
SW0000G	**Meridian 1 Release 21 Base Software**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 54, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 121, 127, 132, 133, 139, 140, 141, 157, 162, 164, 170, 173, 174, 181, 186, 191, 203, 204, 205, 222, 223, 227, 228, 229, 234, 242, 243, 245, 246, 250, 251, 253, 254, 256, 258, 301
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0011A	**Option 81 - Required for Option 81**	298
SW0013A	**Option 81C - Required for Option 81C**	299
SW0028A	**Fast TDS**	87
SW0030A	**Flexible Tones and Cadences**	125
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0048A	**Meridian COMPANION CLID/CPND/ Privacy**	240
SW0049A	**Remote Software Option**	286
SW0050B	**Networking**	37, 38, 39, 59, 62, 63, 67, 160
SW0051B	**ISDN Networking**	118, 145, 146, 147, 291
SW0052D	**Private ISDN Networking**	148, 192, 312
SW0053A	**Public ISDN Access**	117, 149
SW0055A	**Network Attendant Services**	159, 161
SW0057A	**Virtual Network Service**	183
SW0059B	**Network Message Services**	175, 219
SW0060A	**Basic Hospitality**	99, 100, 101, 102, 206, 212

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101C	**Basic Rate Interface**	216, 235
SW0102A	**Meridian 1 Packet Handler**	248
SW0221C	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0229C	**Meridian 911**	224, 225
SW0230A	**Multiple Queue Assignment**	297
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

X11 Release 19 Software

Base/Optional Features

S ➤	SW0000E	Meridian 1 Release 19 Base Software. Includes: - 500 Set Features - 500/2500 Line Disconnect - 2500 Set Features - Advanced Features - ANI - ANI Route Selection - ARS Traffic/Queuing - Attendant Alternative Answer - Attendant End-to-End Signaling - Authorization Code - Automatic Set Relocation - Auto Handsfree Answerback - Auto Line Selection - BARS - Basic - Basic Message Center - Call Forward Reminder Tone - Call Park - Call Party Name Display - Call Trace Enhancement - CDR Charge Account Code - CDR Forced Charge Account - CDR List - Centrex Switch Hook Flash - Conference/TDS - Controlled Class of Service - DID Answer Supervision - Deluxe Hold - Departmental LDN - Dial Intercom - Digital Display - Directed Call Pickup - Distinctive Ringing - Do-Not-Disturb - End-to-End Signaling - Enhanced Controlled Class of Service - Enhanced Music - Flexible Hotline - Group Call - Handsfree Voice Call - History File	∞	5,750.00	I

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- Incoming DID Digit Conversion - Intercept - Internal Call Forward - Internal CDR - Last Number Redial - Limited Access to Overlays - M2250 Console - Make Set Busy - Malicious Call Trace - Meridian Digital Telephone - Meridian M2317 Telephone - Meridian M3000 Telephone - Meridian Mail Voice Mailbox Integration - Modular Meridian Terminals - MSDL/MISP Interface Handler - Multi-Customer - Multi-user Login - Music Package - NARS - NANP - Interchange NPA - New Flexible Code Restriction - OA&M Feature Enhancements - ODAS - Off-Hook Alarm Security - PBX Interface - Recorded Announcement - Recorded Overflow Announcer - Remote Call Forward/Flexible Feature Codes - RPE - SDI Support on MSDL - Single Terminal Access - Station Category Indicator - Station Specific Authorization Codes - Stored Number Redial - Superloop - Superloop Administration - Supervisory Console - System Speed Call - Time & Date - Transparent Data Networking - Trunk Verification - User Selectable Call Redirection			
S ➤	SW0003A	NARS/CDR Format		No charge	
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S ➤	SW0006A	Automatic Trunk Maintenance	10	1,250.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S ➤	SW0028A	Fast TDS	1	No charge	
S ➤	SW0030A	Flexible Tones and Cadences	10	800.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S ➤	SW0032A	CAS - Main/Remote	10	500.00	I
S ➤	SW0033A	Attendant Overflow Position	10	300.00	I
S ➤	SW0034A	Line Load Control	10	500.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	
S ➤	SW0050A	Networking. Includes: - Coordinated Dialing Plan - Network Authorization Code - Network Signaling - Network Call Transfer - Network Queuing - Network Speed Call - Off-Hook Queuing	10	1,250.00	I
S ➤	SW0051A	ISDN Networking. Includes: - Back Up D-Channel (Meridian 1, DMS, AT&T 4ESS) - Calling Line ID in CDR - ISDN Signaling - ISDN Signaling Link - Network Call Redirection - Network Name Display (SL-100, DMS 100/250) - Primary Rate Interface	10	2,250.00	I
S ➤	SW0052A	Private ISDN Networking. Includes: - Network Ring Again - Trunk Optimization (Before Answer) - Remote Virtual Queuing	10	500.00	I
S ➤	SW0053A	Public ISDN Access. Includes: - Inter-Exchange Carrier/In-Band ANI - Call by Call Service	10	800.00	I
S ➤	SW0060A	Basic Hospitality. Includes: - Automatic Wake-Up - Background Terminal - Message Registration - Multi-Language Wake-Up - Room Status - VIP Automatic Wake-Up	10	250.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤	SW0061B	Advanced Hospitality/PMSI. Includes: - Maid ID - PMSI Enhancements	10	800.00	I
S ➤	SW0062A	Hospitality Voice Services. Includes: - Console Digit Key Signaling	10	1,500.00	I

ISDN/BRI Features

S ➤	SW0101B	Basic Rate Interface. Includes: - ISDN BRI Capacity Enhancements - BRI Supplementary Services	∞	500.00	I
S ➤	SW0102A	Meridian 1 Packet Handler	∞	2,000.00	I

ACD/Message Processing Features

S ➤	SW0221B	ACD/Message Processing. Includes: - 500/2500 Single-Line ACD Set - ACD-CDR Queue Record - ACD Display Queue Enhancement - ACD Package A - ACD Package B - ACD Priority Agent - ACD Timed Overflow - Auxiliary Processor Link - Dialed Number ID Service (DNIS) - DNIS Enhancement - Flexible Call Force - IVMS Link - Meridian Mail Link - Name Display for DNIS - Supervisory Control	∞	2,000.00	I
S ➤	SW0222A	Enhanced ACD Overflow	∞	No charge	
S ➤	SW0223A	Enhanced ACD Routing	∞	800.00	I
S ➤	SW0224A	Enhanced Call Center Management. Includes: - ACD Link (MAX) - ACD Load Management (C2) - ACD Report Control - ACD Reports (C1) - Meridian MAX Report Enhancements - Activity Codes for Not Ready	∞	2,250.00	I
S ➤	SW0225B	Enhanced Call Center Routing. Includes: - Enhanced Call Treatment	∞	1,700.00	I
S ➤	SW0226A	Call Center Networking	∞	5,000.00	I
S ➤	SW0227A	Hold in Queue for IVR	∞	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ➤ ⊗	SW0229A	Meridian 911. Includes: - Call Waiting Notification	1	4,000.00	I
S ➤	SW7464	Meridian Link & CCR Co-Resident AST/Agent Software Level	18	4,500.00	I

Meridian Link Associated Station (AST) Features

S ➤	SW0251A	Meridian Link Module Software. Includes: - Predictive Dialing-Fast Transfer Support	18	2,000.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 19 Software Order Code/Option Matrix

Order Code	Description	Options
SW0000E	**Meridian 1 Release 19 Base Software**	0, 1, 2, 4, 5, 7, 8, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 55, 57, 58, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 92, 93, 95, 107, 108, 110, 113, 115, 119, 139, 140, 157, 164, 170, 173, 174, 203, 204, 205, 222, 223, 227, 228, 229, 242, 243, 245, 246
SW0005A	**DN Expansion**	150, 151
SW0006A	**Automatic Trunk Maintenance**	65, 84
SW0009A	**Multi-Tenant**	86, 172
SW0028A	**Fast TDS**	87
SW0030A	**Flexible Tones and Cadences**	125
SW0031A	**Hospitality Screen Enhancements**	208
SW0032A	**CAS - Main/Remote**	26, 27
SW0033A	**Attendant Overflow Position**	56
SW0034A	**Line Load Control**	105
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0050A	**Networking**	37, 38, 39, 59, 62, 63, 67
SW0051A	**ISDN Networking**	118, 145, 146, 147
SW0052A	**Private ISDN Networking**	148, 192
SW0053A	**Public ISDN Access**	117, 149
SW0060A	**Basic Hospitality**	99, 100, 101, 102, 206, 212
SW0061B	**Advanced Hospitality/PMSI**	103, 210
SW0062A	**Hospitality Voice Services**	179, 180
SW0101B	**Basic Rate Interface**	216
SW0102A	**Meridian 1 Packet Handler**	248
SW0221B	**ACD/Message Processing**	35, 40, 41, 45, 77, 83, 85, 98, 109, 111, 116, 247
SW0222A	**Enhanced ACD Overflow**	178
SW0223A	**Enhanced ACD Routing**	214
SW0224A	**Enhanced Call Center Management**	42, 43, 50, 51, 114, 155
SW0225B	**Enhanced Call Center Routing**	215
SW0226A	**Call Center Networking**	207
SW0227A	**Hold in Queue for IVR**	218
SW0229A	**Meridian 911**	224, 225
SW0251A	**Meridian Link Module Software**	153, 209

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 15-17 Software

X11 Releases 15 -17 software use a graduated pricing structure based on usage capacity. The base software package includes many standard features. Additional optional features are also available.

All base software pricing, as well as pricing for optional features, new releases, upgrades and capacity changes for X11 Release 15-17 users is based on system port (TN) levels. The base software package includes many standard features. Additional optional features are also available.

Features are priced in increments of 100 from 1 to 1000 TNs and increments of 500 above 1000 TNs, as the following table shows:

X11 Release 15-17 software: TN pricing table

Number of TNs	TN Level
1-100	1
101-200	2
201-300	3
301-400	4
401-500	5
501-600	6
601-700	7
701-800	8
801-900	9
901-1000	10
1001-1500	11
1501-2000	12
2001-2500	13
2500+	Note
Note: Increments of 500 TNs thereafter: Level + (TNs - 1000)/500 + 10	

Maximum charge levels do not apply to Meridian 1 Base Software. Features with a maximum charge level of one are one time charge additions, regardless of system size.

As Releases 15 and 16 are retired, feature additions and TN expansions will require updates to Release 17 or later. There is a special policy in force to assist Release 15 and 16 users in upgrading systems. Specifics on this policy and other information on upgrading a Release 15 or 16 system can be found in the General Section under "System/Software Orders and Upgrades."

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.

Base/Optional Features

S ➤	SW0000C	Meridian 1 Release 17 Base Software. Includes: - 500 Set Features - 500/2500 Line Disconnect - 2500 Set Features - Advanced Features - ARS Traffic/Queuing - Attendant End-to-End Signaling - Authorization Code - Automatic Set Relocation - Auto Handsfree Answerback - Auto Line Selection - BARS - Basic - Basic Message Center - Call Park - Call Party Name Display - CDR Charge Account Code - CDR Forced Charge Account - CDR List - Centrex Switch Hook Flash - Conference/TDS - Controlled Class of Service - DID Answer Supervision - Deluxe Hold - Departmental LDN - Dial Intercom - Digital Display - Directed Call Pickup - Distinctive Ringing - Do-Not-Disturb - End-to-End Signaling - Enhanced Controlled Class of Service - Enhanced Music - Flexible Hotline - Group Call - History File - Intercept - Internal CDR - Last Number Redial - Limited Access to Overlays - M2250 Console - Make Set Busy	∞	5,750.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
		- Malicious Call Trace - Meridian Digital Telephone - Meridian M2317 Telephone - Meridian M3000 Telephone - Modular Meridian Terminals - Music Package - NANP - Interchangeable NPA and Expanded CAC - New Flexible Code Restrictions - ODAS - PBX Interface - Recorded Announcement - Recorded Overflow Announcer - Remote Call Forward / Flexible Feature Codes - Station Category Indicator - Stored Number Redial - Superloop - Superloop Administration - System Speed Call - Time & Date			
S † ➤	SW0001A	Special Application Features. Includes: - Incoming DID Digit Conversion - Trunk Verification	10	800.00	I
S ➤	SW0005A	DN Expansion. Includes: - CDR Expansion	10	400.00	I
S † ➤	SW0008A	Multi-Customer	10	550.00	I
S ➤	SW0009A	Multi-Tenant. Includes: - Console Presentation Group	10	1,750.00	I
S † ➤	SW0010A	Automatic Number Identification (ANI). Includes: - ANI Route Selection	10	1,650.00	I
S † ➤	SW0017A	Hospitality/Healthcare Features. Includes: - Automatic Wake-Up - Background Terminal - Pretranslation - Room Status - Message Registration	10	400.00	I
S † ➤	SW0018A	Property Management Systems Interface	10	900.00	I
S † ➤	SW0019A	Attendant Overflow Position	1	550.00	I
S † ➤	SW0020A	Supervisory Console	1	900.00	I
S † ➤	SW0021A	Attendant Alternative Answer	1	900.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S † ➤	SW0022A	RPE	1	900.00	I
S † ➤	SW0024A	Line Load Control	1	2,750.00	I
S † ➤	SW0025A	CAS - Main	1	2,750.00	I
S † ➤	SW0026A	CAS - Remote	1	1,650.00	I
S ➤	SW0028A	Fast TDS	1	No charge	
S † ➤	SW0029B	Advanced Hospitality Features. Includes: - Multi-Language Wake-Up - VIP Automatic Wake-Up - Maid ID	10	400.00	I
S ➤	SW0030A	Flexible Tones and Cadences	10	800.00	I
S ➤	SW0031A	Hospitality Screen Enhancements	1	No charge	
S † ➤	SW0041A	NARS	10	900.00	I
S † ➤	SW0042A	Coordinated Dialing Plan	10	900.00	I
S † ➤	SW0043A	Network Authorization Code	10	550.00	I
S † ➤	SW0044A	Basic ESN Features. Includes: - Network Call Transfer - Network Queuing - Network Signaling	10	900.00	I
S † ➤	SW0045A	Advanced ESN Features. Includes: - Off-Hook Queuing - Network Speed Call	10	1,100.00	I
S ➤	SW0046A	Feature Group D. Includes: - CDR Expansion	10	3,000.00	I
S ➤	SW0047A	Direct Inward System Access (DISA)	1	No charge	

ISDN Features

S † ➤	SW0300C	Basic ISDN Features. Includes: - ISDN Signaling - Calling Line ID in CDR - Network Call Redirection - Network Name Display (SL-100 DMS 100/250) - Back Up D-Channel for Meridian 1 - Back Up D-Channel for AT&T and DMS	1	550.00	I
S † ➤	SW0301A	Primary Rate Access	10	2,500.00	I
S † ➤	SW0302A	ISDN Signaling Link	10	1,925.00	I
S † ➤	SW0303B	Advanced ISDN Features. Includes: - Network Ring Again - Trunk Optimization	10	550.00	I
S † ➤	SW0304B	Inter-Exchange Carrier/In-Band ANI	10	900.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S † ➤	SW0305A	Call by Call Service	10	900.00	I
S † ➤	SW0306A	Network Message Services	10	1,400.00	I

ACD/Message Processing Features

S † ➤	SW0201B	Basic ACD Features. Includes: - ACD Package A - ACD-CDR Queue Record - 500/2500 Single-line ACD Set	1	300.00	I
S † ➤	SW0202C	Advanced ACD Features. Includes: - ACD Package B - Dialed Number ID Service - Name Display for DNIS - ACD Priority Agent - Supervisor Control of Queue Size - Flexible Call Force	10	900.00	I
S † ➤	SW0203B	ACD Reports Feature. Includes: - ACD Package C1 - ACD Report Control	10	1,925.00	I
S † ➤	SW0204A	ACD Load Management (ACD-C2)	10	700.00	I
S † ➤	SW0205A	ACD Link (MAX/ACD-D)	10	300.00	I
S † ➤	SW0206A	ACD D/MAX Report Enhancements	1	300.00	I
S † ➤	SW0207A	Enhanced ACD Overflow	10	900.00	I
S † ➤	SW0208A	ACD Timed Overflow	10	300.00	I
S † ➤	SW0209A	Network ACD	10	6,250.00	I
S † ➤	SW0210A	Enhanced ACD Routing	10	900.00	I
S † ➤	SW0211A	Enhanced Call Treatment	10	3,850.00	I
S † ➤	SW0401A	Auxiliary Processor Link	10	300.00	I
S † ➤	SW0402A	IVMS Link	10	1,100.00	I
S † ➤	SW0403A	Meridian Mail Link	10	300.00	I
S † ➤	SW0406C	Meridian Link Module Software	10	3,300.00	I
S † ➤	SW0407A	Meridian Hospitality Voice Services Features. Includes: - Hospitality Voice Services - Console Digit Key Signaling	10	1,650.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 15-17 Software Order Code/Option Matrix

Order Code	Description	Options
SW0000C	**Meridian 1 Release 17 Base Software**	0, 1, 4, 5, 7, 8, 9, 10, 11, 14, 16, 17, 18, 19, 20, 21, 23, 24, 25, 28, 29, 32, 33, 34, 36, 44, 46, 47, 48, 49, 52, 53, 55, 57, 60, 61, 64, 70, 71, 72, 73, 74, 75, 76, 80, 81, 88, 89, 90, 91, 95, 107, 108, 115, 119, 139, 140, 157, 164, 170, 173, 203, 204, 205, 222, 223
SW0001A	**Special Application Features**	110, 113
SW0005A	**DN Expansion**	150, 151
SW0008A	**Multi-Customer**	2
SW0009A	**Multi-Tenant**	86, 172
SW0010A	**Automatic Number Identification (ANI)**	12, 13
SW0017A	**Hospitality/Healthcare Features**	92, 99, 100, 101, 102
SW0018A	**Property Management Systems Interface**	103
SW0019A	**Attendant Overflow Position**	56
SW0020A	**Supervisory Console**	93
SW0021A	**Attendant Alternative Answer**	174
SW0022A	**RPE**	15
SW0024A	**Line Load Control**	105
SW0025A	**CAS - Main**	26
SW0026A	**CAS - Remote**	27
SW0028A	**Fast TDS**	87
SW0029B	**Advanced Hospitality Features**	206, 210, 212
SW0030A	**Flexible Tones and Cadences**	125
SW0031A	**Hospitality Screen Enhancements**	208
SW0041A	**NARS**	58
SW0042A	**Coordinated Dialing Plan**	59
SW0043A	**Network Authorization Code**	63
SW0044A	**Basic ESN Features**	37, 38, 67
SW0045A	**Advanced ESN Features**	39, 62
SW0046A	**Feature Group D**	151, 158
SW0047A	**Direct Inward System Access (DISA)**	22
SW0201B	**Basic ACD Features**	40, 45, 83
SW0202C	**Advanced ACD Features**	41, 98, 116
SW0203B	**ACD Reports Feature**	42
SW0204A	**ACD Load Management (ACD-C2)**	43

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Order Code	Description	Options
SW0205A	**ACD Link (MAX/ACD-D)**	50, 51
SW0206A	**ACD D/MAX Report Enhancements**	114, 155
SW0207A	**Enhanced ACD Overflow**	178
SW0208A	**ACD Timed Overflow**	111
SW0209A	**Network ACD**	207
SW0210A	**Enhanced ACD Routing**	214
SW0211A	**Enhanced Call Treatment**	77, 215
SW0300C	**Basic ISDN Features**	118, 145
SW0301A	**Primary Rate Access**	146
SW0302A	**ISDN Signaling Link**	147
SW0303B	**Advanced ISDN Features**	148
SW0304B	**Inter-Exchange Carrier/In-Band ANI**	149
SW0305A	**Call by Call Service**	117
SW0306A	**Network Message Services**	175
SW0401A	**Auxiliary Processor Link**	109
SW0402A	**IVMS Link**	35
SW0403A	**Meridian Mail Link**	77, 85
SW0406C	**Meridian Link Module Software**	153, 209
SW0407A	**Meridian Hospitality Voice Services Features**	179, 180

Software Administrative Fees

S ➤ Δ	599SL1-1	Software Service Transaction Fee	650.00	H
S ✓ ➤ Δ	NTSW31AA	Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08). This code to be used when upgrading Opt 51C - 81C machines from Rls 24 to Rls 24C (25.08)	650.00	H
S ➤ Δ	SERV0002	Spare set of blank 3.5 inch 4MB floppy diskettes. For customer backup	500.00	H
S ➤ Δ	SERV0003	Spare set of blank 5.25 in diskettes. Used to back-up customer database	500.00	H
S ➤ Δ	SERV0031	In-House Software Conversion Fee	100.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Internet Enabled

Status	Order Code	Description	CLP	Distr. Disc.
S ★ ➤	NTDW80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	80.00	D
S ★ ➤ Δ	NTZC82AA	Internet Telephone Software Parameter (Large System)	90.00	D
S ★ ➤ Δ	NTZC84AA	Internet Telephone Software Parameter (Small System)	90.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Core System Hardware

System Packages

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTSF1032	Option 11C Mini Chassis Expander Package	2,500.00	I
S ➤	NTSF1033	Option 11C Mini Chassis CPU Upgrade Package	2,400.00	I
S ✓ ➤	NTSZ00AC	Option 81C 68060 Enhanced Call Process New System Pkg AC (IGS Network Included)	86,500.00	I
S ✓ ➤	NTSZ00DC	Option 81C New System Package DC	86,500.00	I
S ✓ ➤ ⊗	NTSZ25AC	Option 81C Call Processor PII New System Package AC (Fiber Network Fabric Included)	86,500.00	I
S ➤ ⊗	NTSZ25DC	Option 81C Call Processor PII New System Package DC (Fiber Network Fabric Included)	86,500.00	I
S ✓ ➤ ⊗	NTSZ26AC	Option 81C Call Processor PII New System Package AC (IGS Network Included)	86,500.00	I
S ✓ ➤ ⊗	NTSZ26DC	Option 81C Call Processor PII New System DC (IGS Network Included)	86,500.00	I
S ➤	SY1009A	Meridian 1 Option 51C System Package AC	16,000.00	I
S ➤	SY1009D	Meridian 1 Option 51C System Package DC	16,000.00	I
S ➤	SY1016A	Option 61C System Package AC	24,000.00	I
S ➤	SY1016D	Option 61C System Package DC	24,000.00	I
S ➤	SY1025A	Meridian 1 Option 81C System Package AC	60,500.00	I
S ➤	SY1025D	Meridian 1 Option 81C System Package DC	60,500.00	I

Meridian 1 Internet Enabled

S ★ ➤	NTZC80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	6,000.00	D
S ★ ➤	NTZC81AA	Meridian IP Telephony Gateway Line 2.0 Systems Package	6,200.00	D

Component Packages

S † ➤	228SL1-1	Connector Housing Box Assembly	140.00	I
S † ➤	AS1006A	Network Group Package AC	20,000.00	I
S † ➤	AS1006D	Network Group Package DC	20,000.00	I
S ➤	AS1007A	Network Module Package AC	6,000.00	I
S ➤	AS1007D	Network Module Package DC	6,000.00	I
S § ➤	AS1013	Special Console/Line Card Package	5,000.00	I
S ➤	AS1017D	Customer Provided DC Power Assembly	2,750.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	AS1019	Network Cable Package - 2nd Group	290.00	D
S ➤	AS1020	Network Cable Package - 3rd Group	325.00	D
S ➤	AS1021	Network Cable Package - 4th Group	340.00	D
S ➤	AS1022	Network Cable Package - 5th Group	350.00	D
S ➤	AS1039A	Option 81/81C Network Group Assembly AC	20,000.00	I
S ➤	AS1039D	Option 81/81C Network Group Assembly DC	20,000.00	I
S † ➤	AS1040	Option 81 Network Cable Package, 2nd Group	700.00	I
S † ➤	AS1041	Option 81 Network Cable Package, 3rd Group	750.00	I
S † ➤	AS1042	Option 81 Network Cable Package, 4th Group	780.00	I
S † ➤	AS1043	Option 81 Network Cable Package, 5th Group	800.00	I
S ➤	AS1051	4 Port SDI Assembly	3,100.00	I
S ➤	AS1052	4 Port SDI Paddle Board Assembly	3,400.00	I
S ➤	AS1054A	Intelligent Peripheral Equipment Module Package AC	12,000.00	I
S ➤	AS1054D	Intelligent Peripheral Equipment Module Package DC	12,000.00	I
S ➤	AS1061	PRI Package	4,700.00	I
S † ➤	AS1062	PRI Package (2nd Tier)	4,875.00	I
S † ➤	AS1063	PRI Package (Cabinet)	4,875.00	I
S ➤	AS1073	SDI/DCH Package	3,100.00	I
S ✓ † ➤	AS1074	DTI/PRI Package	4,160.00	H
S ➤	AS1078	Network Group Expansion Interface Package	2,650.00	D
S ➤	AS1081A	Pedestal/Top Cap Package AC	7,000.00	I
S ➤	AS1081D	Pedestal/Top Cap Package DC	7,000.00	I
S ➤	AS1087D	Rectifier Rack Assembly	2,150.00	H
S ➤	AS1088D	Rectifier Rack Assembly	4,500.00	H
S ➤	AS1089	Fiber Remote Local Package	8,750.00	I
S ➤	AS1090A	Fiber Remote Main Wall Mount Remote Package AC	11,250.00	I
S ➤	AS1090D	Fiber Remote Main Wall Mount Remote Package DC	11,250.00	I
S ➤	AS1091A	Expansion Wall Mount Remote Package AC	2,800.00	I
S ➤	AS1091D	Expansion Wall Mount Remote Package DC	2,800.00	I
S ➤	AS1092A	Fiber Remote Floor Standing Remote Package AC	15,250.00	I
S ➤	AS1092D	Fiber Remote Floor Standing Remote Package DC	15,250.00	I
S ➤	AS1093	Carrier Remote Local Package	8,750.00	I
S ➤	AS1094A	Carrier Remote Main Wall Mount Remote Package AC	11,250.00	I
S ➤	AS1094D	Carrier Remote Main Wall Mount Remote Package DC	11,250.00	I
S ➤	AS1095A	Carrier Remote Floor Standing Remote Package AC	15,250.00	I
S ➤	AS1095D	Carrier Remote Floor Standing Remote Package DC	15,250.00	I
S ➤	AS1130	Option 51C/61C/81 CE Spares Package	18,000.00	I
S ➤	AS1132	Option 51C/61C/81C System Spares Package	36,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	AS1140	Local fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	13,500.00	I
S ➤	AS1141	Remote Fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	10,500.00	I
S ➤	AS1142	Local Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	13,500.00	I
S ➤	AS1143	Remote Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	10,500.00	I
S ➤	AS1144	Local Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	22,500.00	I
S ➤	AS1145	Remote Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	15,500.00	I
S ➤	AS1146	Local Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	22,500.00	I
S ➤	AS1147	Remote Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	15,500.00	I
S ➤	AS1171	Option 11E 1st Expansion Cabinet Package AC	4,000.00	I
S ➤	AS1172	Option 11E 1st Expansion Cabinet Package DC	4,000.00	I
S ➤	AS1173	Option 11E 2nd Expansion Cabinet Package AC	5,335.00	I
S ➤	AS1174	Option 11E 2nd Expansion Cabinet Package DC	5,335.00	I
S ➤	AS1200D	MFA150 Modular Power Assembly - Single Shelf	3,200.00	H
S ➤	AS1201D	MFA150 Modular Power Assembly - Dual Shelf	7,400.00	H
S ➤	AS1204D	50 Amp Rectifier Expansion Package	5,000.00	H
S ➤	AS1208A	Power Supply Spares Package AC	6,000.00	I
S ➤	AS1208D	Power Supply Spares Package DC	6,000.00	I
S ➤	AS1209D	System 600/48 Modular Power Package - Main Cabinet	12,000.00	H
S ➤	AS1210D	System 600/48 Modular Power Package - Supplemental Cabinet	8,000.00	H
S ➤	AS1240	Option 81C Network Cable Package, 2nd Group	700.00	I
S ➤	AS1241	Option 81C Network Cable Package, 3rd Group	750.00	I
S ➤	AS1242	Option 81C Network Cable Package, 4th Group	780.00	I
S ➤	AS1243	Option 81C Network Cable Package, 5th Group	800.00	I
S ➤	AS1250	Option 81C Core/Network Group Kit	8,500.00	I
S ➤	AS7200	Dual Port DTI/PRI Package	12,000.00	I
S ➤	AS7201	Dual Port DTI/PRI Package (Cabinet)	12,400.00	I
S ➤	AS7202	Dual Port DTI/PRI Package (ST, STE, RT)	12,100.00	I
S ➤	E1201A	Column Expansion Package AC	7,000.00	I
S ➤	E1201D	Column Expansion Package DC	7,000.00	I
S ➤	NT7R67BA	Local Carrier/Monitor Cable Assembly	300.00	D
S ➤	NT7R67CA	Local Maintenance/Clock Cable Assembly	200.00	D
S ➤	NT7R67DA	Local External Maintenance Cable Assembly	200.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT7R68AA	Remote Carrier/Alarm Cable Assembly	300.00	D
S ➤	NT7R68BA	Remote Maintenance Cable Assembly	200.00	D
S ➤	NT7R69AA	Extension Local Carrier Cable Assembly	150.00	D
S ➤	NT7R69BA	Extension Local Maintenance Cable Assembly	150.00	D
S ✓ ➤ ⊗	NTHY01AA	Option 81C (CP PII) Systems Spares Package	45,000.00	I
S ✓ ➤ ⊗	NTHY01AC	Option 81C (CP PII) Power Supply Spares Package AC	7,000.00	I
S ✓ ➤ ⊗	NTHY01DC	Option 81C (CP PII) Power Supply Spares Package DC	7,000.00	I
S ✓ ➤	NTHY20AC	Fiber Network Group Assembly Package AC	20,000.00	I
S ✓ ➤	NTHY20DC	Fiber Network Group Assembly Package DC	20,000.00	I
S ✓ ➤	NTHY21AA	Option 81C Fiber Core Network Group 0 Kit	8,500.00	I
S ✓ ➤	NTHY23AA	FIJI Group Conversion Kit	7,250.00	I
S ✓ ➤	NTHY24AC	Fiber Network Group Column Package AC	37,000.00	I
S ✓ ➤	NTHY24DC	Fiber Network Group Column Package DC	37,000.00	I
S ➤	NTSF2101	Option 11C - 30 Ft. Expansion Cabinet AC	2,300.00	I
S ➤	NTSF2102	Option 11C - 30 Ft. Expansion Cabinet DC	2,300.00	I
S ➤	NTSF2103	Option 11C - 2 Mile Expansion Cabinet AC	7,300.00	I
S ➤	NTSF2104	Option 11C - 2 Mile Expansion Cabinet DC	7,300.00	I
S ➤	NTSF2105	Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber)	7,300.00	I
S ➤	NTSF2106	Option 11C - 2 Mile Expansion Cabinet Single Mode DC	7,300.00	I
S ➤	NTSF2200	Chassis Fiber Expansion Package (30 Ft.)	7,500.00	I
S ➤	NTSF2201	Chassis Fiber Expansion Package (2mi. Multi-Mode)	10,000.00	I
S ➤	NTSF2202	Chassis Fiber Expansion Package (2mi. Single-Mode)	10,000.00	I
S ➤	NTSF3100	2.0MB DTI Package Option 11C	4,200.00	I
S ➤	NTSF3101	2.0MB PRI Package Option 11C	3,950.00	I
B ➤	NTSF6800	Option 11C TMDI Package (1.5MB DTI/PRI)	3,400.00	I
S ➤	NTZB06AB	Mini Local Package (Options 21-81)	6,000.00	I
S ➤	NTZB07AB	Mini Local Package (Option 11)	6,000.00	I
S ➤	NTZB08AA	Mini Remote Package AC	8,000.00	I
S ➤	NTZB09AA	Mini Remote Package DC	8,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

X11 Release 23 hardware upgrade paths

The chart that follows illustrates the Release 19 and 21 hardware upgrade paths for all SL-1 and Meridian 1 systems. Although the Release 19 and 21 upgrade paths have been simplified, there are still three paths available for Release 19 and 21 upgrades, the paths are as follows:

- Card
- Card Cage
- Module

Locate the type of system to be upgraded on the left side of the chart. The arrows show the upgrade paths available with the appropriate upgrade package order code(s).

For example, for a system type of SL-1 M, the upgrade paths point to the following:

- Option 51C (U9643A/D)
- Option 61C (U9639A/D)


Additional information can be found in the Reference Section in Book Three.

Note: This package includes hardware items commonly needed to perform the system upgrade. Some configurations may require additional items which are not included in these packages. Therefore, an engineering analysis of the existing system must be completed to ensure all hardware upgrade items have been identified and are available at the time of the upgrade installations.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com



Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Determining Appropriate Cable Lengths for Multi-Group Systems (Option 81 and 81C)

Cable length = (rounded to nearest foot)

(# of UEM's spanned left/right) x 36" +

(# of UEM's spanned up/down) x 18" +

(18" if within same column)

Upgrade Packages

S ✓ ➤ ⊗	NTHU21DC	Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC	64,000.00	I
S ✓ ➤ ⊗	NTHU22AC	Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Cage Upgrade Package AC	54,000.00	I
S ✓ ➤ ⊗	NTHU22DC	Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Upgrade Package DC	54,000.00	I
S ✓ ➤	NTHU24AC	Option 81C from Option 61C (NT5D21) Upgrade AC	34,000.00	I
S ✓ ➤	NTHU24DC	Option 81C from Option 61C (NT5D21) Upgrade DC	34,000.00	I
S ➤ ⊗	NTHU28AC	Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/ 51C or 61C (NT9D11, NT5D21) Upgrade Package AC	77,500.00	I
S ➤ ⊗	NTHU28DC	Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/ 51C or 61C (NT9D11, NT5D21) Upgrade Package DC	77,500.00	I
S ➤ ⊗	NTHU29AC	Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package AC	86,500.00	I
S ➤ ⊗	NTHU29DC	Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package DC	86,500.00	I
S ➤	NTSF6001	Option 11/11E to 11C Single Cabinet Upgrade	3,465.00	I
S ➤	NTSF6002	Option 11/11E to 11C Two Cabinet Copper Upgrade	3,945.00	I
S ➤	NTSF6003	Option 11/11E to 11C Two Cabinet Fiber Upgrade (30 Ft.)	5,500.00	I
S ➤	NTSF6004	Option 11/11E to 11C Two Cabinet Fiber Upgrade (2 mile)	12,300.00	I
S ➤	NTSF6005	Option 11/11E to 11C Three Cabinet Fiber Upgrade (30 Ft.)	8,000.00	I
S ➤	NTSF6006	Option 11/11E to 11C Three Cabinet Fiber Upgrade (2 mile)	17,100.00	I
S ➤	NTSF6007	Option 11/11E to 11C - Two Cabinet Ethernet Upgrade (2 Mile - Single Mode Fiber)	12,300.00	I
S ➤	NTSF6008	Option 11/11E to 11C Three Cabinet Single Mode Fiber Upgrade (2 Mile)	17,100.00	I
S ✓ ➤	NTZB93FA	MICA Upgrade Add 27 Ports	23,800.00	D
S ✓ ➤	NTZB93GA	MICA Upgrade Add 12 Ports	11,600.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	U9620	Connector Mounting Kit	160.00	I
S ➤	U9639A	Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/ 21A/21/21E Upgrade Package AC	24,000.00	I
S ➤	U9639D	Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/ 21A/21/21E Upgrade Package DC	24,000.00	I
S ➤	U9640	Option 61C from Option 61 Cardcage Upgrade Package AC/DC	16,500.00	I
S ➤	U9641A	Option 61C from Option 51 Upgrade Package AC	18,000.00	I
S ➤	U9641D	Option 61C from Option 51 Upgrade Package DC	18,000.00	I
S ➤	U9643A	Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package AC	16,000.00	I
S ➤	U9643D	Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package DC	16,000.00	I
S ➤	U9644A	Option 51C from Option 21/21E Cardcage Upgrade Package AC	16,000.00	I
S ➤	U9644D	Option 51C from Option 21/21E Cardcage Upgrade Package DC	16,000.00	I
S ➤	U9645	Option 51C from Option 51 Cardcage Upgrade Package AC/DC	8,500.00	I
S ➤	U9646A	Option 61C from Option 51C Upgrade Package AC	10,500.00	I
S ➤	U9646D	Option 61C from Option 51C Upgrade Package DC	10,500.00	I
S ➤	U9650A	Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/ XT/71 Core and Network Upgrade Package AC	60,500.00	I
S ➤	U9650D	Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/ XT/71 Core and Network Upgrade Package DC	60,500.00	I
S ➤	U9651A	Option 81C from XN/XT/71 Core Upgrade Package AC (Dual Column)	38,000.00	I
S ➤	U9651D	Option 81C from XN/XT/71 Core Upgrade Package DC (Dual Column)	38,000.00	I
S ➤	U9652	Option 81C from Option 71 Card Cage Upgrade Package AC/DC	25,000.00	I
S ➤	U9653A	Option 81C from XN/XT/71 Core Upgrade Package AC (Single Column)	38,000.00	I
S ➤	U9653D	Option 81C from XN/XT/71 Core Upgrade Package DC (Single Column)	38,000.00	I
S ➤	U9654A	Option 81C from Option 61C Upgrade (Package #1) AC	34,000.00	I
S ➤	U9654D	Option 81C from Option 61C Upgrade (Package #1) DC	34,000.00	I
S ➤	U9655A	Option 81C from Option 61C Upgrade (Package #2) AC	39,500.00	I
S ➤	U9655D	Option 81C from Option 61C Upgrade (Package #2) DC	39,500.00	I
S ➤	U9656A	Option 81C from Option 61C Upgrade (Package #3) AC	44,000.00	I
S ➤	U9656D	Option 81C from Option 61C Upgrade (Package #3) DC	44,000.00	I
S ➤	U9657	Option 81C from Option 81 Card Cage Upgrade Package AC/DC	25,000.00	I
S ➤	U9658A	Option 81C from Option 61 (Modular) Upgrade Package AC	48,500.00	I
S ➤	U9658D	Option 81C from Option 61 (modular) Upgrade Package DC	48,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Migration Policies

Telephone Migration Credits

Under the terms of the Telephone Migration Policy, Nortel Networks offers incentives to migrate existing telephones sets by providing a 15% credit for M2000 telephones, M3000 telephones, or consoles. Please refer to the Qualifying Migrations Credit Table to identify which sets are eligible.

All replaced telephones must be returned to Nortel Networks to receive the credits. Telephone set credits are provided on a one-for-one basis with the number of sets returned, no supporting line card returns are required.

The telephone migration policy may be used only when the existing system is running current or active software. If the system is running retired software, it must be updated to a current or active software release to qualify for this telephone migration discount. Refer to the "Ordering Procedures" section of the Product Catalog for a listing of current software.

Telephone Upgrades

Order Codes / Pricing

To receive these credits, include both the Standard Order Code(s) and the Migration Order Code(s) o nthe purchase order.

Standard Order Code	Migration Order Code	Description	Mig Disc	Disc Cat	Std CLP	Mig CLP	CLP Credit
NT9K05AA	MIG03385	M2006	15%	D	$135	$115	($20)
NT9K08AA	MIG03386	M2008	15%	D	$175	$149	($26)
NT9K08AB	MIG03387	M2008HF	15%	D	$240	$204	($36)
NT9K08AC	MIG03388	M2008 w/Display	15%	D	$350	$298	($52)
NT9K08AD	MIG03389	M2008HF w/Display	15%	D	$390	$332	($58)
NTZK20AA	MIG03390	M2016S	15%	D	$830	$706	($124)
NT9K18AC	MIG93391	M2216 ACD-1	15%	D	$525	$446	($79)
NT9K16AA	MIG03392	M2616	15%	D	$400	$340	($60)
NT9K16AC	MIG03393	M2616 w/Display	15%	D	$525	$446	($79)
NT2K36AA	MIG03394	M2616CT	15%	D	$1100	$935	($165)
NT6G00AF	MIG03409	M2250 Attendant Console	15%	D	$3400	$2890	($510)
AS1066	MIG03410	Attendant PC Console	15%	D	$6600	$5610	($990)
NTMN31BA	MIG03395	M3901	15%	D	$80	$68	($12)
NTMN32BA	MIG03396	M3902	15%	D	$165	$140	($25)
NTMN33BA	MIG03397	M3903	15%	D	$335	$285	($50)
NTMN34BA	MIG03398	M3904	15%	D	$550	$468	($82)
NTMN35BA	MIG03399	M3905	15%	D	$550	$468	($82)
NT2K68AA	MIG03400	Analog Terminal Adapter (ATA)	15%	D	$190	$162	($28)
NT2K69AA	MIG03401	Meridian Communications Adapter (MCA)	15%	D	$300	$255	($45)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Equipment Returns

The following table lists the telephones that may be returned for new telephones.

Qualifying Migration Credits

Telephone Returns	New Telephone Credits	
SL-1 (QSU1, QSU3, QSU8,	MIG03385	M2006
QSU60, QSU61)	MIG03386	M2008
M1109 (QSU71)	MIG03388	M2008 w/Display
M2006	MIG03387	M2008HF
M2008	MIG03389	M2008HF w/Display
M2008 w/Display	MIG03390	M2016S
M2008HF	MIG03391	M2216ACD-1
M2008HF w/Display	MIG03392	M2616
M2009 (NT1F05)	MIG03393	M2616 w/Display
M2016S	MIG03394	M2616CT
M2018	MIG03395	M3901
M2112 (NT1F06)	MIG03396	M3902
M2018 (NT1F07)	MIG03397	M3903
M2616	MIG03398	M3904
M2616CT	MIG03399	M3905
	MIG03400	Analog Terminal Adapter (ATA)
	MIG03401	Meridian Communications Adapter (MCA)
Consoles:		
QCW4		
718SL1-1 (M1250)	MIG03409	M2250 Console
M2250 Console	MIG03410	Attendant PC Console

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

EPE to IPE Migration Credits

Under the terms of the EPE to IPE Migration Policy, Nortel Networks offers incentives to replace Enhanced Peripheral Equipment (EPE) with Intelligent Peripheral Equipment (IPE) by providing a 15% migration credit on all IPE purchases. All replaced EPE must be returned to Nortel to receive any discounts.

The EPE to IPE migration policy may be used only when the existing system is running current or active software. If the system is running retired software, it must be updated to a current or active software release to qualify for this EPE migration discount. Refer to the "Ordering Procedures" section of the Product Catalog for listing of current software.

> Note: Release 14 does not support IPE; therefore, does not qualify for these EPE to IPE migration credits.

For each EPE item returned, a credit will be provided towards a comparable quantity of IPE equipment. Due to the different capacities, the quantity of equipment discountable is approximately equal to the quantity returned, but not necessarily exact. Network card credits are provided on a one-for-one basis with the number of EPE loops returned. Line/trunk card credits are provided on a one-for-one basis with number of EPE ports returned. IPE module purchases require PE shelf/tier/module and appropriate buffer card returns on a one-for-one basis.

A worksheet provided at the end of this section can assist you in calculating the amount of allowable migration credits.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Peripheral Equipment Upgrades

Order Codes/Pricing

To receive these credits, include both standard order code(s) and Migration Order Code(s) on purchase order.

STD Order Code	Mig Order Code	Description	Disc		STD CLP	Mig CLP*	Credit @CLP
AS1054A	MIG03411	INTELL PERIPH EQUIP MOD PKG AC	15%	I	$12,000.00	$10,200.00	($1,800.00)
AS1054D	MIG03412	INTELL PERIPH EQUIP MOD PKG DC	15%	I	$12,000.00	$10,200.00	($1,800.00)
NT7D16BA	MIG03418	DATA ACCESS CARD	15%	I	$2,000.00	$1,700.00	($300.00)
NT8D02GA	MIG03419	DIGITAL LINE CARD (DLC)	15%	I	$3,500.00	$2,975.00	($525.00)
NT8D04BA	MIG03413	SUPERLOOP NETWORK CARD	15%	I	$3,500.00	$2,975.00	($525.00)
NT8D09BA	MIG03420	ANALOG MESSAGE WAITING LINE CARD	15%	I	$3,500.00	$2,975.00	($525.00)
NT8D14BB	MIG03414	UNIVERSAL TRUNK CARD	15%	I	$3,950.00	$3,357.50	($592.50)
NT8D15AK	MIG03415	E&M TRUNK CARD	15%	I	$2,933.00	$2,493.05	($439.95)
NT8D16AB	MIG03416	DIGITONE RECEIVER CARD	15%	I	$2,500.00	$2,125.00	($375.00)
NT8D17FA	MIG03417	CONFERENCE/TDS CARD	15%	I	$5,000.00	$4,250.00	($750.00)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Equipment Returns

The following table lists the EPE that may be returned for credit toward IPE.

EPE Returns	IPE Credits	
PE Cards:		
QPC60, QPC61, QPC70, QPC71,	MIG03418	Data Access Card
QPC74, QPC192, QPC218,	MIG03419	Digital Line Card
QPC219, QPC237, QPC250,	MIG03420	Analog MW Line Card
QPC267, QPC297, QPC311,	MIG03414	Universal Trunk Card
QPC353, QPC422, QPC430,	MIG03415	E&M Trunk Card
QPC432, QPC449, QPC450,	MIG03416	Digitone Receiver Card
QPC451, QPC452, QPC494,		
QPC574, QPC578, QPC594,		
QPC710, QPC72, QPC723,		
QPC789, QPC79, QPC930		
PE Shelves/Cabinets/Modules:		
AS1053A/D (NT8D13), QSD3,	MIG03411	IPE Module Package AC
QSD31, QSD32, QSD34, QSD35,	MIG03412	IPE Module Package DC
QSD64, QSD65, QSD66,		
QSD7, QSD73, QSD80, QSP35,		
QSP36, QCA109, QCA136, QCA137,		
QCA147, QCA7, QCA74, QCA8		
Network Cards:		
QPC362, QPC376, QPC414,	MIG03413	Superloop Network Card
QPC444, QPC50, QPC53	MIG03417	Conference/TDS Card

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Ordering

The appropriate ordering codes must be used on the purchase order to obtain the special pricing. Failure to do so will result in Distributor being billed full Net Distributor Price (NDP) for the order. Credit will not be issued if order is placed incorrectly.

A list of expected equipment returns must be provided to Inside Sales at the time of order placement. See Telephone/EPE to IPE Product Return Form located at the end of the section.

All Migration pricing orders must include the system serial number of the existing system.

All products included on a PO utilizing this migration policy must be installed at a single customer location. Discounts are to be used only for equipment sold to end users, they cannot be used to purchase equipment for Distributor inventories.

Migration credits are applied at Gross Distributor Price (GDP). Volume Purchase Plan (VPP) discounts are applied after credits.

The Distributor purchase order must be received by the appropriate Nortel Inside Sales representative. The Telephone/EPE to IPE Product Return Form must accompany the PO and be sent to the following address:

Nortel Networks Inside Sales
2305 Mission College Blvd.
Santa Clara, CA 95054-1591

The Distributor cannot cancel or return any portion of the PO pertaining to the purchase requirements for migration credits. Doing so will result in billing the Distributor at standard Net Distributor Price (NDP). Distributors may not supply any portion of the program purchase requirements from their inventory or return Telephones or EPE from their inventory. Any trade-in equipment shortages will be considered a violation of the Terms and Conditions of this policy.

Shipment lead times on orders placed under this program may vary from standard shipment lead times.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Equipment Returns

The Telephone/EPE to IPE program requires that the participating Distributor return the replaced Meridian 1 and Meridian SL-1 hardware as specified in Telephone/EPE to IPE Product Return Form to Nortel within 60 days of shipment. Extensions may be requested by contacting Letty Terrazas at 408-495-5165.

Upon approval, a Return Authorization (RA) number must be obtained from Inside Sales and noted on the product return form.

Returned equipment must be packaged with an Telephone/EPE to IPE Product Return Form and be labeled with the proper Return Authorization number. See the section "Equipment Return Procedure," for complete instructions.

It is the Distributor's responsibility to ensure proper packaging of the replaced Meridian 1/Meridian SL-1 equipment. All returned equipment must be packaged adequately to prevent damage to the enclosed components. If the components are received at Nortel Networks damaged or otherwise non-reusable, the Distributor shall be billed full Net Distributor Price and will not receive the requested program discounts.

The replaced hardware must be returned to the following address:

Nortel Networks Repair and
Distribution Center (NRDC)
Attn: EPE to IPE Migration
917 Airpark Center
Nashville, TN 37217
1-800-321-2649

Nortel Networks will incur the normal and customary cost of shipping the returned equipment to Nashville. Nortel Networks will only pay the normal and customary cost of shipping the returned equipment. If the equipment pick up and shipment requires excessive effort, Distributor will be billed for any charges over the normal and customary cost.

All returned hardware becomes the property of Nortel Networks. All returned equipment must be in working order.

Returned equipment does not create any form of discount balance for future redemption, and discount eligibility cannot be transferred between customers.

Failure to return the replaced Telephones or EPE will result in the participating Distributor being billed full Net Distributor Price (NDP), for the Meridian 1 hardware ordered. Restocking charges will apply to returns not completed within 60 days of shipment.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Equipment Return Procedure Migration Policy

The following are the Equipment Return Procedures for the Migration Policies.

1. The completed Distributor Purchase Order is received in Inside Sales (Santa Clara) for processing.
2. Completed Telephone/EPE to IPE Product Return Form is received in Inside Sales (Santa Clara).
3. The Distributor order is verified by Inside Sales for migration eligibility.
4. Upon approval a Return Authorization (RA) number is assigned to the order and noted on the Telephone/EPE to IPE Product Return Form.
5. Inside Sales sends the completed Telephone/EPE to IPE Product Return Form to the appropriate Distributor purchasing agent.
6. When the equipment is properly packaged, labeled and ready for pick up, the Distributor contacts Nortel Networks providing pick up address, contact name and telephone number. For your convenience we have made available a toll free number, 1-800-321-2649, for use while the Migration policies are in effect. Upon hearing the voice announcement, depress 5 for Nashville Repair, then depress 5 for the Traffic Coordinator.

   Note: It is the Distributor's responsibility to ensure proper packaging of the replaced Meridian 1/Meridian SL-1 equipment. The Telephone/EPE to IPE Product Return Form must be included with the returned equipment. All returned equipment must be packaged adequately to prevent damage to the enclosed components. If the components are received at Nortel Networks damaged or otherwise non-reusable, the Distributor shall be billed full Net Distributor Price (NDP) and will not receive the requested program discounts.
7. Nortel Networks contacts a delivery service and makes the necessary arrangements for pick up and shipment of the Meridian 1/Meridian SL-1 equipment to the Repair and Return Center in Nashville. Nortel Networks will incur the normal and customary cost of shipping the returned equipment to Nashville.

   Note: Nortel Networks pays only the normal and customary cost of shipping the returned equipment. If the equipment pick up and shipment requires excessive effort, Distributor will be billed for any charges over the normal and customary cost.
8. Nortel Networks contacts the Distributor, relaying necessary shipping information and pick up date.

   Note: If the replaced Telephones or EPE is not returned within 60 days of shipment of the new Meridian 1 equipment, the Distributor will be billed full Net Distributor Price (NDP) and will not receive the requested migration credits. Equipment return extensions may be required by contacting Letty Terrazas at 408-495-5165.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

CPE TO IPE
PRODUCT RETURN FORM

THIS FORM MUST ACCOMPANY ALL ORDERS

Reference Number:
(Must have both) Distributor P.O. Number: _____
Switch Serial Number: _____

Customer/Location:
Proposed De-Installation Date: _____
Customer Name: _____
Customer Address: _____

Contact Name: _____
Telephone Number: _____ FAX Number: _____

Distributor Contact/Purchasing Agent:
Name: _____ Phone Number: _____
Company: _____ FAX Number: _____

Product Return Information:
Number of Parts: _____ Total Phones: _____ Total Loops: _____

Quantity	Part #	Quantity	Part #

Attach additional sheets as needed.

The replaced equipment must be returned within 60 days. The replaced equipment must be returned to:

Northern Telecom
917 Airpark Center
Nashville, TN 37217
Return Authorization Number:

When the replaced equipment is properly packaged and ready for pick-up, call 1-800-321-2649 (Express 5, then 5 again) to arrange pick-up and shipment to Northern Telecom. For an equipment return extension or questions regarding this policy, please contact Mavis Franks at (408) 565-3092.

Nortel use only:

Date Received	Approved	Verified

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

EPE to IPE Migration Credit Worksheet

Lines/Trunks/DTR Ports

Part Code	Description	Ports	X Qty = Part/Loop Credit
QPC60	100/2500 Line Card	4	
QPC61	SL-1 Line Card	4	
QPC71	E&M/GX/Page Trunk Card	2	
QPC72	Loop Signaling Trunk	2	
QPC74	RAN Trunk Card	4	
QPC79	DTR	1	
QPC192	QPX Line Card	4	
QPC219	CO/FX/WATS Trunk Card	2	
QPC237	4W E&M Trunk Card	2	
QPC239	Dictation Trunk Card	2	
QPC256	Release Link Trunk	2	
QPC287	Message Waiting Line Card	4	
QPC297	Supervisor Line Card	2	
QPC311	Data Line Card	2	
QPC353	Modem Pool Line Card	4	
QPC422	Tone Detector	2	
QPC436	Async Data Line Card	4	
QPC432	Data Line Card	4	
QPC449	Loop Signaling Trunk Card	4	
QPC450	CO/FX/WATS Trunk Card	4	
QPC451	SL-1 Line Card	8	
QPC452	500/2500 Line Card	8	
QPC494	Message Waiting Line Card	8	
QPC574	DTR	2	
QPC578	Digital Line Card	8	
QPC664	500/2500 Line Card	16	
QPC710	DTR Daughter Board	2	
QPC723	ASync Data Line Card	4	
QPC786	Message Waiting Line Card	16	
QPC930	Message Waiting Line Card	16	

Network Codes

QPC362	Conference/Network Card	2	
QPC376	Dual Network Card	2	
QPC414	Network Card	2	
NT8D04	Superloop Network Card	4	
NT8D17	Conference/TDS Card	2	
NT7D16	Data Access Card	8	
NT8D02	Digital Line Card	16	
NT8D09	Message Waiting Line Card	16	
NT8D14	Universal Trunk Card	8	
NT8D15	E&M/Page Trunk Card	4	
NT8D16	DTR	8	

Total Ports Returned _____ Total Ports Purchased _____

Total Loops Returned _____ Total Loops Returned _____

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Integrated Applications
Meridian Integrated Personal Call Director

S ➤	NT5G71AA	MIPCD Spare Base Card	7,000.00	D
S ➤	NT5G91AB	MIPCD PCMCIA Drive	1,400.00	D
S ✓ ➤	NTZB77AA	Meridian Integrated Personal Call Director, 8 ports 50 users	7,500.00	D
S ✓ ➤	NTZB78AA	Meridian Integrated Personal Call Director, 16 ports 100 users	14,500.00	D
S ✓ ➤	NTZB79AA	Meridian Integrated Personal Call Director, 24 ports 150 users	21,000.00	D
S ✓ ➤	NTZB80AA	Meridian Integrated Personal Call Director, 32 ports 200 users	27,000.00	D
S ➤	NTZB87AA	MIPCD 50 Users Expansion	3,300.00	D
S ➤	NTZB88AA	MIPCD 8 Port Upgrade	8,000.00	D
S ➤	NTZB88BA	MIPCD 16 Port Upgrade	15,000.00	D
S ➤	NTZB88CA	MIPCD 24 port Upgrade	20,000.00	D

Meridian Integrated Applications Miscellaneous

S	NT5D52AC	Universal MIxx Ethernet Adapter (for IPE Modules)	230.00	D
S	NT5D52BC	Universal MIxx Ethernet Adapter (Option 11)	230.00	D

Components
Cards

S ➤	A0634492	Fiber Remote Multi-IPE Interface - Redundant Option (Single Mode)	10,000.00	I
S ➤	A0634493	Fiber Remote Multi-IPE Interface - Redundant Option (Multi Mode)	10,000.00	I
S	A0683638	8MB PCMCIA Flash Card	600.00	H
S	A0688017	MVME167-33 Processor Card (M68040, 33Mhz, 16MB)	10,500.00	D
S ➤	A0773054	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	15,000.00	I
S ➤	A0773055	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	10,000.00	I
S ➤	A0773056	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	15,000.00	I
S ➤	A0773059	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	10,000.00	I
S ✓ ➤ ⊗	A0810496	CP PII Call Processor Card (128MB Memory)	14,500.00	I
B ➤	AS1460	Line-side T1 Interface Assembly (21-81)	5,400.00	I
B ➤	AS1461	Line-side T1 Interface Assembly (11)	5,400.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT0961AA	Meridian ITG 2.0 Pentium 24 Port Card. Single IPE card that includes hardware and gateway software to support 24 simultaneous voice over IP calls.	6,500.00	D
S ➤	NT1P61CA	Fiber Superloop Network Card	5,500.00	I
S ➤	NT1P62EA	Fiber Remote Peripheral Controller Card	5,500.00	I
S ➤	NT1R20AB	Intelligent OPS Line Card	3,000.00	I
S ✓ ➤ ⊗	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	2,200.00	I
S ✓ ➤ ⊗	NT4N66AB	cPCI Core Network Interface Transition Card	500.00	I
S ➤ ⊗	NT4N67AA	cPCI System Utility Card	1,000.00	I
S ➤ ⊗	NT4N68AA	cPCI System Utility Transition Card	1,000.00	I
S ➤	NT5D03FB	68060 Enhanced 128MB Call Processor	11,500.00	I
S ➤	NT5D03PB	68060 Enhanced 160MB Call Processor	12,000.00	I
S ➤	NT5D11AE	Line-Side T1 Interface Card	5,000.00	I
B ✓ ➤	NT5D12AG	Dual Port DTI/PRI (DDP) Card	11,500.00	I
S ➤	NT5D13AA	Line-Side T1 Interface Cable	200.00	D
S ➤	NT5D14AD	Line-Side T1 Interface Card (Option 11/11E/11C)	5,000.00	I
S ➤	NT5D30AA	Dual Intergroup Switch	4,400.00	I
S ➤	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card	7,000.00	D
S ➤	NT5D60AA	CLASS Modem card	4,000.00	D
S ➤	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive	1,400.00	D
S	NT5D64CA	Local Mini Carrier Interface Card (Options 21-81)	5,800.00	I
S ➤	NT5D65CA	Local Mini Carrier Extender Card (Options 21-81)	1,750.00	D
S	NT5D67CA	Remote Mini Carrier Interface Card	7,000.00	I
S	NT5D68CA	Local Mini Carrier Interface Card (Option 11)	5,800.00	I
S ➤	NT5D69CA	Local Mini Carrier Extender Card (Option 11)	1,750.00	D
S ➤	NT5D97AA	2.0MB Dual Port DTI/PRI. E1 connections for North America	14,375.00	I
S ➤	NT5G11AA	MICA Pack without Security Device	5,500.00	D
S ➤	NT5G31AA	MICA PCMCIA Hard Drive Replacement (includes MICA software)	3,500.00	D
S ➤	NT5G32AA	MICA PCMCIA Flash Card (with MICA software included)	2,500.00	D
S	NT5G92AA	MICB Software Upgrade Kit	400.00	H
S ✓	NT5G95AA	PCMCIA Flash Card Upgrade, MIPCD	400.00	H
S † ➤	NT6D11AF	D-Channel Handler Card	4,500.00	I
S ➤	NT6D6003	Core Bus Terminator	800.00	I
S ➤	NT6D70AA	S/T Interface Line Card (SILC)	3,500.00	I
S ➤	NT6D71AA	U-Interface Line Card (UILC)	3,800.00	I
S ➤	NT6D73AA	Multi-Purpose ISDN Signaling Processor (MISP)	3,500.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT6D80AB	Multi-Purpose Serial Data Link (MSDL)	4,500.00	I
S ➤	NT6D81AA	Power Regulator Card	250.00	I
S ➤	NT7D16BA	Data Access Card	2,000.00	I
S ➤	NT7R51AD	Local Carrier Interface Card	8,000.00	I
S ➤	NT7R52AD	Remote Carrier Interface Card	8,000.00	I
S ➤	NT8D01BC	Controller - Four Card	4,500.00	I
S ➤	NT8D04BA	SuperLoop Network Card	3,500.00	I
S ✓ ➤	NT8D09BA	Analog Message Waiting Line Card	3,500.00	I
S ✓ ➤	NT8D14BB	Universal Trunk Card	3,950.00	I
S ✓ ➤	NT8D15AK	E&M Trunk Card	2,933.00	I
S ➤	NT8D16AB	Digitone Receiver Card	2,500.00	I
S ➤	NT8D17FA	Conference/TDS Card	5,000.00	I
S	NT8D41BA	Quad SDI Paddle Board	2,850.00	I
S	NT8R17AB	IP Line Card, Spare	5,000.00	D
S ➤	NTAG26AB	Multi-Frequency IPE Receiver Card (4 Channel)	4,100.00	I
S ➤	NTAG36AC	Meridian Integrated RAN (Release 2) Base Spare Card	2,200.00	D
S ➤	NTAK02BC	SDI/DCH Card	3,000.00	I
S ➤	NTAK03DA	TDS/DTR Card	1,700.00	I
S ✓ † ➤	NTAK09DA	DTI/PRI Card	4,000.00	H
S	NTAK10DC	2.0 MB DTI Card with Clock Controller	4,000.00	I
S	NTAK20AD	Clock Controller Card	1,000.00	I
S ➤	NTAK93AB	DCHI Card	1,000.00	I
S ➤	NTBK22AA	Option 11E MISP Circuit Card	3,500.00	I
S ➤	NTBK45AC	System Core Pack	3,200.00	I
S ➤	NTBK47AB	Expansion Daughterboard	600.00	I
S ➤	NTBK50AA	2.0MB Primary Rate Interface Card	3,750.00	I
S	NTBK51AA	Downloadable DCHI for DDP	2,250.00	I
S	NTBK51BA	Option 11 Downloadable DCHI	1,150.00	I
S ➤	NTCW80CA	Meridian IP Telephony Gateway (ITG) Base Card	3,500.00	D
S ➤	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	4,575.00	I
S ➤	NTDK18AA	Cabinet Upgrade Kit	850.00	I
S ➤	NTDK19AA	SSC Upgrade Kit	800.00	I
S ➤	NTDK20EA	Option 11C System Core Card	4,000.00	I
S ➤	NTDK21AA	Option 11C- Blank Software Daughterboard	1,300.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTDK22AA	30 Ft. Fiber Daughterboard - Multi Mode	1,000.00	I
S ➤	NTDK23AA	30 Ft. Fiber Receiver Card	1,000.00	I
S ✓ ➤	NTDK23BA	30 Ft. Fiber Receiver Card	1,000.00	I
S ➤	NTDK24AB	2 Mile Fiber Daughterboard - Multi-Mode	4,000.00	I
S	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	4,000.00	I
S ➤	NTDK26AA	Backwards Compatible Daughterboard	600.00	I
S ➤	NTDK48AA	Main Cabinet Cable Kit	200.00	D
S ✓ ➤	NTDK79AA	2 Mile Fiber Daughterboard Single Mode	4,000.00	I
S ✓ ➤	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	4,000.00	I
N ➤	NTDK81AA	Option 11C Blank Software Daughterboard	1,300.00	I
S ➤	NTDK84AA	30 Ft. DUAL Port Fiber Daughterboard	1,600.00	I
S ➤	NTDK85AA	2 Mile Multi Mode DUAL Port Fiber Daughterboard	6,000.00	I
S ➤	NTDK97AB	Option 11C Mini System Controller Card (Blank)	4,000.00	I
S	NTJG06AC	MIRAN 1.56 (Upissue) 8MB PCMCIA Card	600.00	H
S ➤	NTLT83AA	MIRAN to MIRAN Release 2 Card Upgrade Kit	3,600.00	D
S ➤	NTNH13AA	Meridian IP Telecommuter Client Application CD. Meridian IP Telecommuter Client Application CD - Replacement copy	25.00	D
B ➤	NTRB21AA	T1 Multipurpose Digital Interface (TMDI)	3,200.00	I
S ✓ ➤	NTRB33AA	Fiber Junctor Interface Card (FIJI)	4,400.00	I
S ✓ ➤	NTRB34AA	Core-to-Network Interface Card (CNI-3)	2,200.00	I
S ➤	NTRE39AA	Optical Cable Management Card (OCMC)	50.00	I
B † ➤	NTSK11AK	Option 11C Software Daughterboard - Release 24.24	1,400.00	I
B ✓ ➤	NTSK11AL	Option 11C Software Daughterboard - Release 25	1,400.00	I
B ✓ ➤	NTSK11AN	Option 11C Software Daughterboard - Release 25	1,400.00	I
B ★ ➤	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo	1,400.00	I
S ✓	NTSK11BA	Option 11C Release 22.08 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BB	Option 11C Release 22.16 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BC	Option 11C Release 22.46 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BF	Option 11C Release 23.18 Programmed PCMCIA Card	1,500.00	I
S ✓	NTSK11BG	Option 11C Release 23.35 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BH	Option 11C Release 23.55 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BK	Option 11C Release 24.24 Programmed PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BL	Option 11C Release 25 Programmed 40MB PCMCIA Card	1,500.00	I
B ✓ ➤	NTSK11BN	Option 11C Release 25 Programmed PCMCIA Card	1,500.00	I
S ✓	NTTK13AA	Option 11C 48MB Software Daughterboard (Blank)	1,380.00	I
S ➤	NTVP1000	Meridian Integrated RAN (Release 2) Small (5 Channels)	3,600.00	D
S ➤	NTVP1001	Meridian Integrated RAN (Release 2) Medium (6 Channels)	5,400.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTVP1002	Meridian Integrated RAN (Release 2) Large (10 Channels)	6,400.00	D
S ➤	NTVP1010	Meridian Integrated RAN (Release 2) Small to Medium Upgrade	1,800.00	D
S ➤	NTVP1011	Meridian Integrated RAN (Release 2) Medium to Large Upgrade	1,000.00	D
S ➤	NTVP1012	Meridian Integrated RAN (Release 2) Small to Large Upgrade	2,800.00	D
S ➤	NTWE07AA	ITG 2.0 Pre-programmed Q.SIG D-Channel Interface PCMCIA Card	1,500.00	D
S ➤	NTZB01AA	Meridian Integrated Conference Bridge (Release 2) 12 Port Card	12,000.00	D
S ➤	NTZB01BA	Meridian Integrated Conference Bridge (Release 2) 16 Port Card	16,000.00	D
S ➤	NTZB01CA	Meridian Integrated Conference Bridge (Release 2) 24 Port Card	24,000.00	D
S ➤	NTZB01DA	Meridian Integrated Conference Bridge (Release 2) 32 Port Card	32,000.00	D
S ➤	NTZB02AA	Meridian Integrated Conference Bridge (Release 2) 12 to 16 Port Upgrade	4,000.00	D
S ➤	NTZB02BA	Meridian Integrated Conference Bridge (Release 2) 12 to 24 Port Upgrade	12,000.00	D
S ➤	NTZB02CA	Meridian Integrated Conference Bridge (Release 2) 12 to 32 Port Upgrade	20,000.00	D
S ➤	NTZB02DA	Meridian Integrated Conference Bridge (Release 2) 16 to 24 Port Upgrade	8,000.00	D
S ➤	NTZB02EA	Meridian Integrated Conference Bridge (Release 2) 16 to 32 Port Upgrade	16,000.00	D
S ➤	NTZB02FA	Meridian Integrated Conference Bridge (Release 2) 24 to 32 Port Upgrade	8,000.00	D
S ✓ ➤	NTZB91AA	MICA PCMCIA Hard Drive with 5 Ports	6,594.00	D
S ✓ ➤	NTZB91BA	MICA PCMCIA Hard Drive with 8 Ports	9,475.00	D
S ✓ ➤	NTZB91CA	MICA PCMCIA Hard Drive with 12 Ports	12,995.00	D
S ✓ ➤	NTZB91DA	MICA PCMCIA Hard Drive with 16 Ports	15,995.00	D
S ✓ ➤	NTZB91EA	MICA PCMCIA Hard Drive with 20 Ports	18,595.00	D
S ✓ ➤	NTZB91FA	MICA PCMCIA Hard Drive with 24 Ports	20,795.00	D
S ✓ ➤	NTZB91GA	MICA PCMCIA Hard Drive with 28 Ports	22,595.00	D
S ✓ ➤	NTZB91HA	MICA PCMCIA Hard Drive with 32 Ports	23,995.00	D
S ✓ ➤	NTZB92AA	MICA PCMCIA Flash with 5 Ports	5,000.00	D
S ✓ ➤	NTZB92BA	MICA PCMCIA Flash with 8 Ports	7,880.00	D
S ✓ ➤	NTZB92CA	MICA PCMCIA Flash with 12 Ports	11,400.00	D
S ✓ ➤	NTZB92DA	MICA PCMCIA Flash with 16 Ports	14,400.00	D
S ✓ ➤	NTZB92EA	MICA PCMCIA Flash with 20 Ports	17,000.00	D
S ✓ ➤	NTZB92FA	MICA PCMCIA Flash with 24 Ports	19,200.00	D
S ✓ ➤	NTZB92GA	MICA PCMCIA Flash with 28 Ports	21,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTZB92HA	MICA PCMCIA Flash with 32 Ports	22,400.00	D
S ➤	NTZB93AA	MICA Upgrade add 3 ports	3,000.00	D
S ➤	NTZB93BA	MICA Upgrade add 4 ports	4,000.00	D
S ➤	NTZB93CA	MICA Upgrade add 8 ports	8,000.00	D
S ➤	NTZB93DA	MICA Upgrade add 16 ports	15,200.00	D
S ➤	NTZB93EA	MICA Upgrade add 24 ports	21,600.00	D
S ➤	NTZB94AA	Meridian Integrated Conference Bridge (Release 2) 42 Port Card	42,000.00	D
S ➤	NTZB94BA	Meridian Integrated Conference Bridge (Release 2) 50 Port Card	50,000.00	D
S ➤	NTZB94CA	Meridian Integrated Conference Bridge (Release 2) 62 Port Card	62,000.00	D
S ➤	NTZB95AA	Meridian Integrated Conference Bridge (Release 2) 12 to 42 Port Upgrade	30,000.00	D
S ➤	NTZB95BA	Meridian Integrated Conference Bridge (Release 2) 12 to 50 Port Upgrade	38,000.00	D
S ➤	NTZB95CA	Meridian Integrated Conference Bridge (Release 2) 12 to 62 Port Upgrade	50,000.00	D
S ➤	NTZB95DA	Meridian Integrated Conference Bridge (Release 2) 16 to 42 Port Upgrade	26,000.00	D
S ➤	NTZB95EA	Meridian Integrated Conference Bridge (Release 2) 16 to 50 Port Upgrade	34,000.00	D
S ➤	NTZB95FA	Meridian Integrated Conference Bridge (Release 2) 16 to 62 Port Upgrade	46,000.00	D
S ➤	NTZB95GA	Meridian Integrated Conference Bridge (Release 2) 24 to 42 Port Upgrade	18,000.00	D
S ➤	NTZB95HA	Meridian Integrated Conference Bridge (Release 2) 24 to 50 Port Upgrade	26,000.00	D
S ➤	NTZB95JA	Meridian Integrated Conference Bridge (Release 2) 24 to 62 Port Upgrade	38,000.00	D
S ➤	NTZB95KA	Meridian Integrated Conference Bridge (Release 2) 32 to 42 Port Upgrade	10,000.00	D
S ➤	NTZB95LA	Meridian Integrated Conference Bridge (Release 2) 32 to 50 Port Upgrade	18,000.00	D
S ➤	NTZB95MA	Meridian Integrated Conference Bridge (Release 2) 32 to 62 Port Upgrade	30,000.00	D
S ➤	NTZB95NA	Meridian Integrated Conference Bridge (Release 2) 42 to 50 Port Upgrade	8,000.00	D
S ➤	NTZB95PA	Meridian Integrated Conference Bridge (Release 2) 42 to 62 Port Upgrade	20,000.00	D
S ➤	NTZB95QA	Meridian Integrated Conference Bridge (Release 2) 50 to 62 Port Upgrade	12,000.00	D
S ➤	NTZB96AA	Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) PCMCIA Upgrade Kit	3,000.00	D
S ➤	NTZB96BA	Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) Card Upgrade Kit	9,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTZC12CA	Meridian IP Telephony Gateway (ITG) Small and Large Systems Package	3,290.00	D
S ➤	NTZC13BA	Meridian IP Telephony Gateway (ITG) Card. The Meridian ITG is a single IPE card that includes the hardware and software to support 8 simultaneous voice over IP trunk calls.	3,160.00	D
S ➤	NTZC14AA	Meridian Integrated IP Telephony Gateway (ITG) PCMCIA Card	800.00	H
S ➤	NTZC19AA	Meridian IP Telecommuter PCMCIA Card	800.00	D
S ➤	NTZC44AA	Meridian ITG 2.0 ISDN Large Systems Package. ITG 2.0 large system package contains 24-port card, PCMCIA with D-CH, the appropriate cables and NTP.	7,300.00	D
S ➤	NTZC44BA	Meridian ITG 2.0 ISDN Small Systems Package. ITG 2.0 ISDN small systems contains 24-port card, PCMCIA with D-CH, the appropriate cables and NTP.	7,300.00	D
S ➤	NTZC45AA	Meridian ITG 2.0 Small and Large Systems 24-Port Package. For ITG 2.0 small and large systems contains 24-port card and the appropriate cables (without D-Channel or NTP).	6,590.00	D
S ➤	NTZC47AA	Meridian ITG 2.0 Large Systems Upgrade Kit from ITG 1.0 to ITG 2.0. Large systems upgrade kit contains PCMCIA with D-CH, the appropriate cables and NTP.	900.00	D
S ➤	NTZC47BA	Meridian ITG 2.0 Small Systems Upgrade Kit from ITG 1.0 to ITG 2.0. Small systems upgrade kit contains PCMCIA with D-CH, the appropriate cables and NTP.	900.00	D
S ➤	NTZC62AA	Meridian Integrated Voice Services, 2 Port	5,000.00	D
S ➤	NTZC62BA	Meridian Integrated Voice Services, 4 Port	7,500.00	D
S ➤	NTZC62CA	Meridian Integrated Voice Services, 8 Port	10,500.00	D
S ➤	NTZC63AA	Meridian Integrated Voice Services, 2 to 4 Port Upgrade	3,000.00	D
S ➤	NTZC63BA	Meridian Integrated Voice Services, 2 to 8 Port Upgrade	6,000.00	D
S ➤	NTZC63CA	Meridian Integrated Voice Services, 4 to 8 Port Upgrade	4,500.00	D
S ➤	NTZC65AA	IP Telecommuter System Package	12,500.00	D
S ✓ ➤	NTZC75AA	32MB DRAM SIMM Upgrade Kit	350.00	D
S ✓ ➤	NTZC76AA	32MB Flash Memory Upgrade Kit	700.00	D
S ✓ ➤	NTZC77AA	ESD/DRAM SIMM Accessory Kit	200.00	D
S Δ	P0815404	Line-Side T1 Interface Card Description, Installation and Maintenance	12.00	H
S ➤ Δ	P0850716	Option 11C Programming Fee for PCMCIA Card	500.00	H
S ➤ ⊗	P0906308	cPCI Card Slot Filler Panel	35.00	D
S	QPC247A	Keyboard with Dial Pad, (QCW3/QCW4)	300.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	QPC414C	Network Card	2,000.00	I
S	QPC417A	Junctor Board	1,400.00	I
S ➤	QPC43R	Peripheral Signaling	800.00	I
S ➤	QPC441F	Three-Port Extender	2,000.00	I
S ➤	QPC444A	Conference Card	2,900.00	I
S ➤	QPC471H	Clock Controller	1,500.00	I
S ➤	QPC477A9	Bus Terminating Unit (BTU)	400.00	I
S ➤	QPC477B10	Bus Terminating Unit (BTU)	400.00	I
S † ➤	QPC584M	Mass Storage Interface Card	1,400.00	I
S	QPC702A1	PE Backplane	1,675.00	I
S ➤	QPC720F	Primary Rate Interface Card	4,500.00	I
S ➤	QPC841C	Four-Port SDI	3,500.00	I
S ➤	QPC84S	Power Monitor Pack	1,000.00	I

Column/Module/Card Cages Products

S ➤	NT0X21AV	System 600/48 & MPP 600 Seismic Anchor	50.00	H
S ➤	NT1R89AA	IPE Cardcage Expansion Kit (AC)	1,100.00	D
S ➤	NT1R89BA	IPE Cardcage Expansion Kit (DC)	1,100.00	D
S	NT1R90BA	Cardcage Upgrade Parts Kit	1,100.00	D
S ➤ ⊗	NT4N46AA	cPCI Core/Network Card Cage AC/DC	6,000.00	I
S ➤ ⊗	NT4N97AA	cPCI Upgrade Kit AC	1,000.00	I
S ➤ ⊗	NT4N97BA	cPCI Upgrade Kit DC	1,000.00	I
S	NT5D2104	Core/Network Cardcage (AC/DC)	4,500.00	I
S ➤	NT5D40AA	Hybrids Kit	400.00	D
S	NT5D85AA	Local Mini Carrier Interface Cable	400.00	D
S ➤	NT5D86AA	Local Mini Carrier Extender Cable	400.00	D
S	NT5D87AA	Remote Mini Carrier Interface Cable	400.00	D
S ➤	NT7D00AA	Top Cap AC	750.00	I
S ➤	NT7D00BA	Top Cap DC	750.00	I
S ➤	NT7D0902	Rear Mount Conduit/Wiring Kit	80.00	I
S ➤	NT7D09CA	Pedestal DC	1,750.00	I
S ➤	NT8D1303	Peripheral Equipment Cardcage (AC/DC)	4,000.00	I
S ➤	NT8D13AA	Peripheral Equipment Module AC	7,000.00	I
S ➤	NT8D13DC	Peripheral Equipment Module DC	7,000.00	I
S ➤	NT8D27BB	Pedestal AC	1,750.00	I
S ➤	NT8D3507	Network Cardcage (AC/DC)	4,000.00	I
S ➤	NT8D35BA	Network Module AC	5,000.00	I
S ➤	NT8D35EA	Network Module DC	5,000.00	I

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT8D36AA	Inter Group Module	3,000.00	I
S ➤	NT8D3703	Intelligent Peripheral Equipment Cardcage (AC/DC)	4,000.00	I
S ➤	NT8D37BA	Intelligent Peripheral Equipment Module AC	6,000.00	I
S ➤	NT8D37EC	Intelligent Peripheral Equipment Module DC	6,000.00	I
S ➤	NT8D46AC	Thermostat Harness	80.00	I
S ➤	NT8D46AM	Air Probe Harness	80.00	I
S ➤	NT8D46DC	DC Thermostat Harness.	80.00	I
S ➤	NT8D49AA	Column Spacer Kit (2.75 In.)	350.00	I
S ➤	NT8D49BA	Column Spacer Kit (5.25 In.)	350.00	I
S ➤	NT8D63AA	Overhead Cable Tray Kit	560.00	I
S ➤	NT8D64BD	Module Expansion Rods	400.00	I
S	NT8D64BE	Seismic Bracing Anchor Kit (OSHPD)	100.00	H
S ➤	NT8D64BF	Floor Mounting Kit (Non-Seismic)	200.00	I
S ➤	NT8D64CA	Earthquake Bracing Kit (2 Module Column)	1,400.00	I
S ➤	NT8D64CB	Earthquake Bracing Kit (3 Module Column)	1,420.00	I
S ➤	NT8D64CC	Earthquake Bracing Kit (4 Module Column)	1,450.00	I
S	NT8D64CD	Earthquake Bracing Kit (1 Module Column)	1,200.00	I
S	NT8D64CE	Seismic Bracing Anchor Kit (Bellcore)	300.00	H
S ➤	NT9D15AA	Front/Rear Cover	170.00	I
S ➤	NT9D18AA	Module Side Cover	175.00	I
S ➤	NTRD25AA	Pedestal Assembly AC	6,800.00	I
S ✓ ➤	NTRD25BA	Pedestal Assembly DC	6,000.00	I
S ➤	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module. Includes: - Attendant PC LAN Interface Module Software- Installation Guide	1,720.00	D
S ➤	P0699851	Top Cap Cable Egress Panel	60.00	I
S ➤	P0701352	Earthquake Bracing Rod (3 Module)	50.00	I
S ➤	P0701353	Earthquake Bracing Rod (4 Module)	60.00	I

Cooling Units

S ➤	NT8D52AB	Pedestal Blower Unit AC	2,775.00	I
S ➤	NT8D52DD	Pedestal Blower Unit DC	2,775.00	I
S ➤	P0699798	Cooling Unit Filter Assembly	75.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Data Products				
S ➤	A0344336	DB25 Male Pin Connector (AILU) (M232-422A)	125.00	D
S ➤	A0344337	DB25 Female Pin Connector (AILU) (F232-422A)	125.00	D
S ➤	NTND36AA	Meridian Communications Unit	850.00	D
Disk/Tape Drives				
S ➤ ⊗	NT4N43AA	cPCI Multi-Media Disk Unit	4,000.00	I
S ➤	NT5D61AB	IODU/C Pack	7,800.00	I
Power/Rectifier Products				
S † ➤	A0354954	Rectifier, 100 Amp	4,600.00	H
S ➤	A0367916	Power Supply - 48V DC	650.00	I
B ➤	A0620100	Replacement Battery (For NTAK75AA/AB)	260.00	H
S	A0762506	AC/DC Power Converter	650.00	I
S ➤	NT0R71AA	-48volt Rectifier	2,500.00	H
S ➤	NT0R72AA	-52volt Rectifier	2,100.00	H
S ➤	NT4N50AA	Power Distribution Unit DC	1,700.00	I
S ➤	NT5C06CC	MPR25E Modular Power Rectifier, 25 Amps	1,900.00	H
S ➤	NT5C07AC	50 Amp Rectifier	3,000.00	H
S ➤	NT5C10CC1	MPS75 Modular Power Shelf, 75 Amps	800.00	H
S ➤	NT5C11BC	MFA150 Battery Tray	100.00	H
S ➤	NT5C12AC	MPS150 Modular Power Shelf 23" Rackmount	850.00	H
S ➤	NT6C14PA	System 600/48 LVD Interface Circuit Pack	120.00	H
S ➤	NT6C14PE	System 600/48 Supplemental Cabinet Adaptor	100.00	H
S ➤	NT6C14PF	Alarm and Control Circuit Pack for MPP600 and MFA150	350.00	H
S ➤	NT6C14PG	Meter Circuit Pack for MPP600 and MFA150	300.00	H
S ➤	NT6C25FF	System 600/48 Front Access Controller	1,700.00	H
S ➤	NT6C25PC	System 600/48 Control Circuit Pack	1,300.00	H
S ➤	NT6C25PD	System 600/48 Fuse Circuit Pack	945.00	H
S ➤	NT6C40CF	Seismic Rack (23 In. x 4 Ft.)	300.00	H
S ➤	NT6D40BA	Peripheral Equipment Power Supply DC	4,000.00	I
S ➤	NT6D41AD	Common Equipment Power Supply DC	4,000.00	I
S ⊗	NT6D41CA	Core/Network Power Supply DC	4,000.00	I
S ➤	NT6D42CD	Ringing Generator DC	1,700.00	I
S ➤	NT6D5303	Ground Bar/LRE - Large	475.00	H
S ➤	NT6D5304	Ground Bar/LRE - Small	475.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	NT6D54AA	Rectifier Wiring Kit	30.00	I
S † ➤	NT7D1201	Rectifier Support/Air Baffle	100.00	H
S † ➤	NT7D12AA	Rectifier Rack	770.00	H
S ➤	NT8D06AB	Peripheral Equipment Power Supply AC	4,000.00	I
S ➤	NT8D21AB	Ringing Generator AC	1,700.00	I
S ➤	NT8D29AB	Common Equipment Power Supply AC	4,000.00	I
S ⊗	NT8D29BA	Core/Network Power Supply AC	4,000.00	I
S ➤	NT8D40AA	Power Cord AC (230V)	120.00	I
S ➤	NT8D53CA	Power Distribution Unit AC	2,500.00	I
S ➤	NT8D56AA	Common Equipment Module Power Distribution Unit	400.00	I
S ➤	NT8D57AA	Peripheral Equipment Module Power Distribution Unit	400.00	I
S	NTDK72AA	DC/DC Power Supply	1,500.00	I
B ➤	NTDK78AA	AC/DC Power Supply	1,460.00	I
S † ➤	P0703905	Connector Adapter Panel Housing	30.00	I
S † ➤	P0703906	Adapter Housing	60.00	I
S † ➤	P0703960	DTI/PRA Adapter Plate Package	20.00	I
S † ➤	P0703961	SDI Adapter Plate Package	20.00	I
S ➤	P0704511	Connector Housing Package	90.00	I
S ➤	P0727842	EMI Shield (Plastic Type)	110.00	I
S ➤	P0727843	EMI Shield (Metal Type)	110.00	I
S ➤	P0729843	Spare Circuit Breaker Kit, 5 Amp	45.00	H
S ➤	P0729846	Spare Circuit Breaker Kit, 20 Amp	45.00	H
S ➤	P0729847	Spare Circuit Breaker Kit, 30 Amp	45.00	H
S ➤	P0730064	Lug Kit, Screw-Type #8	14.00	H
S ➤	P0730252	MFA Spare Fuse Kit	50.00	H
S	P0743482	Spare Circuit Breaker Kit, 50 Amp - MPP600/MFA150	45.00	H
S ➤	P0744873	System 600/48 Isolation Kit	95.00	H
S ➤	P0745716	Universal I/O Panel	35.00	I
S ➤	P0746602	Circuit Breaker Kit, 5 AMP - 600/48	50.00	H
S ➤	P0746603	Circuit Breaker Kit, 10 AMP - 600/48	50.00	H
S ➤	P0746604	Circuit Breaker Kit, 15 AMP - 600/48	50.00	H
S ➤	P0746605	Circuit Breaker Kit, 20 AMP - 600/48	50.00	H
S ➤	P0746607	Circuit Breaker Kit, 30 AMP - 600/48	50.00	H
S ➤	P0746608	Circuit Breaker Kit, 50 AMP - 600/48	50.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	P0816367	System 600/48 DC Duct	300.00	H
S	QBL12F	Battery Distribution Box	2,750.00	H
S †	QBL15H	Battery Distribution Box	1,850.00	H
S ➤	QCAD321A	Junction Box QBL15	90.00	H
S † ➤	QFF1A	Fuse, 1.33 Amp	3.00	I
S ➤	QFF1AB	1 1/3 Amp Fuse	5.00	H
S † ➤	QFF1B	Fuse, 2. Amp	5.00	I
S † ➤	QFF1C	Fuse, 3. Amp	2.00	I
S † ➤	QFF1D	Fuse, 5. Amp	17.00	I
S † ➤	QFF1E	Fuse, .180 Amp	5.00	I
S † ➤	QFF1F	Fuse, .25 Amp	5.00	I
S † ➤	QFF1G	Fuse, .50 Amp	3.00	I
S ➤	QPF23A	Terminating Plug	160.00	I
S ➤	QPF36B	Terminating Plug	15.00	I

Shelves/Tiers

S ➤	A0634494	Fiber Remote Multi-IPE Interface - Rack Mount Shelf Option	1,500.00	I

Cables

S	A0100025	Alarm/Modem Cable (25 Ft.)	25.00	D
S † ➤	A0237451	Cable, Connector (16 Ft.) (M/M), TTY RS-232 (5.25m)	110.00	D
S † ➤	A0263854	Cable, Connector (16 Ft.) (M/F), TTY RS-232 (5.25m)	110.00	D
S ➤	A0275286	ADM Set Interconnect Cord NE-M4QD (21 In.)	5.00	D
S ➤	A0300752	RS232 - V.35 Adapter Cable for HSDM (Male)	175.00	D
B ➤	A0300753	RS232 - V.35 Adapter Cable for HSDM (Female)	175.00	D
S † ➤	A0318423	Filter Connector (50 Conductor) (EMI)	50.00	D
S ➤	A0326761	Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh to Digital Set)	40.00	D
S ➤	A0326762	Apple Macintosh Interface Cable DIN 8 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC)	40.00	D
S ➤	A0326763	Apple Macintosh Interface Cable DIN8/DB25 (Macintosh to Digital Set)	40.00	D
S ➤	A0361365	RJ45 Cable	60.00	D
S † ➤	A0369107	Sub-D Filter Connector (25 Conductor)	50.00	D
S ➤	A0632902	33 Ft. Plastic Fiber Cable (11E/11C)	160.00	D
S ➤	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft.)	300.00	D
S ➤	A0634496	Remote FRMII Cable (30 ft.)	300.00	D
S ➤	A0757981	FRMII System Monitor Isolator	550.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	A0757982	FRMII MMI/Modem Isolator	375.00	D
S ➤	A0761993	FRMII Alarm Cable (32 Ft.)	170.00	D
S ➤	A0766331	Maintenance Interface Cable	200.00	D
S ➤	A0811762	Fiber Network Fabric Adapter Panel	100.00	D
S ➤	AS1079	MSDL Intercabinet Cable Kit	450.00	D
S ➤	AS1175	Fiber Interface Kit	2,200.00	I
S ➤	NT1P63CA	Electro-Optical Interface Packlet	5,000.00	I
S ➤	NT1P75AA	EOI to I/O Panel Optical Cable (Single Mode)	750.00	D
S ➤	NT1P75BA	EOI to I/O Panel Optical Cable (Multi Mode)	750.00	D
S ➤	NT1P76AA	Fiber Superloop to System Monitor & SDI Cable	200.00	D
S ➤	NT1P78AA	Fiber Controller to System Monitor & SDI Cable	200.00	D
S ➤	NT1P79AA	EOI to Fiber Management Optical Cable (Single Mode)	750.00	D
S ➤	NT1P79BA	EOI to Fiber Management Optical Cable (Multi Mode)	750.00	D
S ➤	NT1P84AA	Power Cable	35.00	D
S ➤	NT1P85AA	Auxiliary Cable	60.00	D
B ➤	NT1P87AA	Remote Cable Kit	225.00	D
S ➤	NT1R03HF	Modem Cable	60.00	D
S ➤	NT1R04AA	Clock Controller to I/O Panel Cable	50.00	D
S ➤	NT1R05AA	Inter-Cabinet Clock Reference Cable	100.00	D
S ➤ ⊗	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In.)	170.00	D
S ➤ ⊗	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In.)	170.00	D
S ⊗	NT4N89AA	System Utility to XSM Cable	70.00	D
S ➤ ⊗ Δ	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In.)	175.00	D
S ⊗	NT4N92AA	MMDU Data Cable for CD and Hard Drive	70.00	D
S ➤ ⊗	NT4N93AA	MMDU Data Cable for Floppy Drive	70.00	D
S ➤ ⊗	NT4N95AA	MMDU Power Cable	70.00	D
S ➤ ⊗	NT4N96AA	cCNI to I/O Panel Cable (2 Ft.)	160.00	D
S	NT5D16BA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.)	370.00	D
S	NT5D16DA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.) ST, STE, RT	200.00	D
S ➤	NT5D16EA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.) NT, XT	370.00	D
S	NT5D17AA	Meridian 1 Trunk Tip/Ring Cable (50 Ft.)	300.00	D
S ➤	NT5D19AA	PC Maintenance Cable	80.00	D
S	NT7D58BB	ESDI 25 pin Female to 15 pin Male Link Cable (20")	50.00	D
S ➤	NT7D89CA	CP to I/O Panel RS232 Cable	170.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ ⊗	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in./1m)	175.00	D
S	NT7R66AA	SDI Cable Kit (10 Ft.)	110.00	D
S	NT7R66BA	MMI Cable Kit (32 Ft.)	140.00	D
S	NT7R66BB	MMI Cable Kit (32 ft.)	140.00	D
S	NT7R86AA	Auxiliary Alarm Cable (48 Ft.)	170.00	D
S	NT7R87AA	T1 Carrier Link Cable Kit (32 Ft.)	200.00	D
S	NT7R87BA	T1 Link Cable Kit (32 Ft.)	220.00	D
S	NT7R94AA	Carrier Wall Mount Cable Kit	600.00	D
S ➤	NT8D46AA	System Monitor Column Cable (30 In.)	35.00	D
S ➤	NT8D46AB	System Monitor Jumper Cable (11 In.)	40.00	D
S ➤	NT8D46AD	System Monitor to SDI Cable (60 In.)	60.00	D
S ➤	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In.)	40.00	D
S ➤	NT8D46AJ	System Monitor to UPS (Best) Cable (45 Ft.)	85.00	D
S ➤	NT8D46AL	System Monitor Serial Link Cable (7 Ft.)	10.00	D
S ➤	NT8D46AP	Extended System Monitor Serial Link Cable (25 Ft.)	15.00	D
S ➤	NT8D46AQ	System Monitor to UPS (Exide) Cable (45 Ft.)	50.00	D
S ➤	NT8D46AS	System Monitor Inter-CPU Cable (30 In.)	60.00	D
S † ➤	NT8D46AT	System Monitor to QBL15 Cable (32 Ft.)	110.00	D
S ➤	NT8D46AU	System Monitor to UPS (Alpha) Cable (45 Ft.)	90.00	D
S ➤	NT8D46AV	System Monitor to Power Cabinet Cable (32 Ft.)	110.00	D
S ➤	NT8D46AW	System Monitor to QBL12 Cable (32 Ft.)	110.00	D
S ➤	NT8D46AX	Alarm Interface Cable (45 Ft.)	70.00	D
S ➤	NT8D46AY	Alarm Interface Cable (45 Ft.)	70.00	D
S ➤	NT8D46BA	Alarm Monitor Cable Harness	70.00	D
S ➤	NT8D46BB	Alarm Monitor Cable Harness	70.00	D
S ➤	NT8D46BC	Alarm Monitor Cable (6 Ft.)	70.00	D
S ➤	NT8D46BD	Alarm Monitor Cable (1 Ft.)	70.00	D
S ➤	NT8D46BE	Alarm Monitor Cable (10 Ft.)	70.00	D
S ➤	NT8D46BF	Alarm Monitor Cable (1 Ft.)	70.00	D
S ➤	NT8D46BG	Alarm Monitor Cable Harness	70.00	D
S ➤	NT8D46BH	System Monitor to MDF Cable (32 Ft.)	70.00	D
S ➤	NT8D46BJ	Alarm Monitor Cable (1 Ft.)	70.00	D
S ➤	NT8D46BM	Alarm Monitor Cable (1 Ft.)	70.00	D
S ➤	NT8D46BV	System Monitor to Power Cabinet Cable (64 Ft.)	150.00	D
S ➤	NT8D46CH	Alarm Monitor Cable (12 Ft.)	70.00	D
S ➤	NT8D46CV	System Monitor to Power Cabinet Cable (100 Ft.)	210.00	D
S ➤	NT8D46DH	System Monitor to MDF Cable (150 Ft.)	140.00	D
S ➤	NT8D46EH	System Monitor to MDF Cable (100 Ft.)	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT8D7217	Cable - 2.0MB DDP I/O to MDF 50 Ft.	160.00	D
S ➤	NT8D73AD	Inter-Cabinet Network Cable (6 Ft.)	170.00	D
S ➤	NT8D73AF	Inter-Cabinet Network Cable (12 Ft.)	180.00	D
S ➤	NT8D73AL	Inter-Cabinet Network Cable (20 Ft.)	210.00	D
S ➤	NT8D73AS	Inter-Cabinet Network Cable (30 Ft.)	260.00	D
S ➤	NT8D74BC	Clock Controller to Junctor Cable (4 Ft.)	55.00	D
S ➤	NT8D74BD	Clock Controller to Junctor Cable (6 Ft.)	55.00	D
S ➤	NT8D74BE	Clock Controller to Junctor Cable (8 Ft.)	60.00	D
S ➤	NT8D74BF	Clock Controller to Junctor Cable (10 Ft.)	60.00	D
S ➤	NT8D75BC	Clock Controller to Clock Controller Cable (4 Ft.)	60.00	D
S ➤	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft.)	40.00	D
S ➤	NT8D76BC	cCNI to 3PE or IGS to IGM Cable (4 Ft.)	40.00	D
S ➤	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft.)	40.00	D
S ➤	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft.)	40.00	D
S ➤	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft.)	40.00	D
S ➤	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft.)	50.00	D
S ➤	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft.)	50.00	D
S ➤	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft.)	50.00	D
S	NT8D76BR	cCNI to 3PE or IGS to IGM Cable (25ft/7.6M)	60.00	D
S	NT8D76BS	cCNI to 3PE or IGS to IGM Cable (50ft./15.2M)	60.00	D
S ➤	NT8D77BA	Female Telco Cable (3 Ft.)	30.00	D
S ➤	NT8D77BB	Female Telco Cable (2 Ft.)	30.00	D
S † ➤	NT8D77BC	Female Telco Cable (4 Ft.)	40.00	D
S ➤	NT8D77BD	Female Telco Cable (6 Ft.)	40.00	D
S ➤	NT8D78AA	CPU Cable (2 In.)	50.00	D
S ➤	NT8D79AB	PRI/DTI To Clock Controller Cable (2 Ft.)	40.00	D
S ➤	NT8D79AC	PRI/DTI To Clock Controller Cable (4 Ft.)	45.00	D
S ➤	NT8D79AD	PRI/DTI To Clock Controller Cable (6 Ft.)	45.00	D
S ➤	NT8D79AE	PRI/DTI To Clock Controller Cable (8 Ft.)	50.00	D
S ➤	NT8D79AF	PRI/DTI To Clock Controller Cable (10 Ft.)	50.00	D
S † ➤	NT8D80BC	CPU/MDU Interface Cable (4 Ft.)	30.00	D
S † ➤	NT8D80BD	CPU/MDU Interface Cable (6 Ft.)	35.00	D
S † ➤	NT8D80BE	CPU/MDU Interface Cable (8 Ft.)	35.00	D
S ➤	NT8D80BF	CPU Interface Cable (10 Ft.)	40.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT8D80BG	CPU Interface Cable (12 Ft.)	40.00	D
S ➤	NT8D80BJ	CPU Interface Cable (16 Ft.)	45.00	D
S ➤	NT8D80BL	CPU Interface Cable (20 Ft.)	50.00	D
S ➤	NT8D80BP	CPU Interface Cable (25 Ft.)	50.00	D
S ➤	NT8D80BZ	CPU Interface Cable (5 Ft.)	35.00	D
S † ➤	NT8D81AA	Tip and Ring Cable (20 In.)	75.00	D
S ➤	NT8D82AD	SDI to I/O Cable (6 Ft.)	160.00	D
S ➤	NT8D83AD	PRI/DTI to I/O Cable (6 Ft.)	100.00	D
S ➤	NT8D84AA	SDI Paddleboard to I/O Cable (18 In.)	90.00	D
S ➤	NT8D85BB	Network to PE Cable (2 Ft.)	30.00	D
S ➤	NT8D85BC	Network to PE Cable (4 Ft.)	30.00	D
S ➤	NT8D85BD	Network to PE Cable (6 Ft.)	35.00	D
S ➤	NT8D85BE	Network to PE Cable (8 Ft.)	35.00	D
S ➤	NT8D85BF	Network to PE Cable (10 Ft.)	40.00	D
S ➤	NT8D85BJ	Network to PE Cable (16 Ft.)	40.00	D
S ➤	NT8D85BL	Network to PE Cable (20 Ft.)	45.00	D
S ➤	NT8D85BP	Network to PE Cable (25 Ft.)	45.00	D
S ➤	NT8D85BV	Network to PE Cable (45 Ft.)	55.00	D
S ➤	NT8D85BZ	CPU Interface Cable (5 Ft.)	35.00	D
S ➤	NT8D86BD	Network to I/O Cable (6 Ft.)	75.00	D
S ➤	NT8D88AC	Network to I/O Cable (5 Ft.)	50.00	D
S ➤	NT8D88AD	Network to I/O Cable (6 Ft.)	60.00	D
S ➤	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft.)	80.00	D
S ➤	NT8D91AC	Network to Controller Cable (4 Ft.)	55.00	D
S ➤	NT8D91AD	Network to Controller Cable (6 Ft.)	55.00	D
S ➤	NT8D91AE	Network to Controller Cable (8 Ft.)	60.00	D
S ➤	NT8D91AF	Network to Controller Cable (10 Ft.)	60.00	D
S ➤	NT8D91AG	Network to Controller Cable (12 Ft.)	65.00	D
S ➤	NT8D91AJ	Network to Controller Cable (16 Ft.)	65.00	D
S ➤	NT8D91AP	Network to Controller Cable (25 Ft.)	80.00	D
S ➤	NT8D91AV	Network to Controller Cable (45 Ft.)	100.00	D
S ➤	NT8D92AB	Controller to I/O Cable (20 Inch)	60.00	D
S ➤	NT8D93AJ	2 Port SDI I/O to DTE/DCE Cable (16 Ft.)	60.00	D
S ➤	NT8D93AW	2 Port SDI I/O to DTE/DCE Cable (48 Ft.)	90.00	D
S ➤	NT8D95AJ	SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Male)	60.00	D
S ➤	NT8D95AT	SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Male)	90.00	D
S ➤	NT8D95AW	SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Male)	110.00	D
S ➤	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Female)	60.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT8D95BT	SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Female)	90.00	D
S ➤	NT8D95BW	SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Female)	110.00	D
S ➤	NT8D96AB	SDI Multi-Port Cable (2 Ft.)	90.00	D
S ➤	NT8D98AD	Inter-Cabinet Network Cable (6 Ft.)	150.00	D
S ➤	NT8D98AF	Inter-Cabinet Network Cable (12 Ft.)	170.00	D
S ➤	NT8D98AL	Inter-Cabinet Network Cable (20 Ft.)	190.00	D
S ➤	NT8D98AS	Inter-Cabinet Network Cable (30 Ft.)	220.00	D
S	NT8D98AT	Inter-Cabinet Network Cable (38 Ft.)	250.00	D
S ➤	NT8D99AB	CPU or Network to Network Cable (2 Ft.)	25.00	D
S ➤	NT8D99AC	CPU or Network to Network Cable (4 Ft.)	25.00	D
S ➤	NT8D99AD	CPU or Network to Network Cable (6 Ft.)	30.00	D
S	NT9D38AA	RS232 - V.35 Adapter Cable for MCA/MCU (Female)	175.00	D
S	NT9D39AA	RS232 - V.35 Adapter Cable for MCA/MCU (Male)	175.00	D
S ➤	NT9D89CA	CNI-3 TO 3PE/EMSI TO MDU Cable (8 Ft.)	150.00	D
S ➤	NT9D89DA	CNI-3 TO 3PE/EMSI TO MDU Cable (10 Ft.)	150.00	D
S ➤	NT9D89EA	CNI-3 TO 3PE/EMSI TO MDU Cable (12 Ft.)	150.00	D
S ➤	NT9D89FA	CNI-3 TO 3PE/EMSI TO MDU Cable (25 Ft.)	160.00	D
S ➤	NT9D89GA	CNI-3 TO 3PE/EMSI TO MDU Cable (50 Ft.)	160.00	D
S ➤	NT9J93AD	PRI/DTI Echo Canceler to I/O Cable (6 Ft.)	60.00	D
S ➤	NT9J96AC	Intra-Cabinet Network Cable (40 In.)	90.00	D
S ➤	NT9J96AD	Intra-Cabinet Network Cable (70 In.)	90.00	D
S ➤	NT9J96AE	Intra-Cabinet Network Cable (85 In.)	90.00	D
S ➤	NT9J96AG	Intra-Cabinet Network Cable (12 Ft.)	100.00	D
S ➤	NT9J96AH	Intra-Cabinet Network Cable (14 Ft.)	100.00	D
S ➤	NT9J96AJ	Intra-Cabinet Network Cable (16 Ft.)	100.00	D
S ➤	NT9J97AC	Intra-Cabinet Network Cable (40 In.)	80.00	D
S ➤	NT9J97AD	Intra-Cabinet Network Cable (70 In.)	80.00	D
S ➤	NT9J97AE	Intra-Cabinet Network Cable (85 In.)	90.00	D
S ➤	NT9J97AG	Intra-Cabinet Network Cable (12 Ft.)	90.00	D
S ➤	NT9J97AH	Intra-Cabinet Network Cable (14 Ft.)	90.00	D
S ➤	NT9J97AJ	Intra-Cabinet Network Cable (16 Ft.)	100.00	D
S ➤	NT9J98AC	Intra-Cabinet Network Cable (40 In.)	100.00	D
S ➤	NT9J98AD	Intra-Cabinet Network Cable (70 In.)	100.00	D
S ➤	NT9J98AE	Intra-Cabinet Network Cable (85 In.)	110.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9J99AC	Intra-Cabinet Network Cable (40 In.)	90.00	D
S ➤	NT9J99AD	Intra-Cabinet Network Cable (70 In.)	100.00	D
S ➤	NT9J99AE	Intra-Cabinet Network Cable (85 In.)	110.00	D
S ➤	NTAG81AA	Audio Cable	45.00	D
S ➤	NTAG81BA	Maintenance Extender Cable	100.00	D
S ➤	NTAG81CA	PC Maintenance Cable	80.00	D
S ➤	NTAG81DA	VLAN Maintenance Cable	150.00	D
S	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	120.00	D
S	NTAK0420	Power Cable	60.00	D
S ➤	NTAK1104	PFTU/Console Power Cable	60.00	D
S ➤	NTAK1108	SDI Cable	40.00	D
S ➤	NTAK1204	Expansion Cable - Copper (7 Ft.)	160.00	D
B	NTAK19EC	2 Port SDI Cable (6 Ft.)	160.00	D
S ➤	NTAK19FB	4 Port SDI Cable	200.00	D
S ➤	NTAK98AA	Power Supply Cable	40.00	D
S ➤	NTBK04AA	1.544 MByte Carrier Cable	300.00	D
S	NTBK05CA	Cable 20 Ft. Coax - 2.0MB DTI/PRI to MDF	180.00	D
S	NTBK05DA	2.0MB DTI/PRI Twisted Pair Cable	180.00	D
S ➤	NTBK48AA	3-port SDI Cable (1.5m or 5 Ft.)	180.00	D
S ➤	NTBK54AB	Main Fiber Interface (MFI) Kit	590.00	D
S ➤	NTBK55AB	Expansion Fiber Interface (EFI) Kit	550.00	D
S ➤	NTBK62AB	MFI/EFI Power Cable	90.00	D
S ➤	NTBK81AA	Fiber Management Kit	50.00	D
S	NTCG03AA	DDP to Clock Controller Cable (14 Ft.)	75.00	D
S	NTCG03AB	DDP to Clock Controller Cable (2 Ft. 8 In.)	50.00	D
S	NTCG03AC	DDP to Clock Controller Cable (4 Ft.)	55.00	D
S	NTCG03AD	DDP to Clock Controller Cable (7 Ft.)	60.00	D
S ➤	NTCK45AA	Cable - 2.0MB DDP to I/O 8 Ft.	130.00	D
S	NTCK46AA	DDP to DCHI Cable (6 Ft.)	130.00	D
S	NTCK46AB	DDP to DCHI Cable (18 Ft.)	160.00	D
S	NTCK46AC	DDP to DCHI Cable (35 Ft.)	180.00	D
S	NTCK46AD	DDP to DCHI Cable (50 Ft.)	200.00	D
S ➤	NTCK78AA	Cable - 2.0MB DDP to MDF 50 Ft.	220.00	D
S ➤	NTCK79AA	Cable - 2.0MB DDP Coax to LTU 50 Ft.	325.00	D
S	NTCK80AA	DDP to MSDL Cable (6 Ft.)	130.00	D
S	NTCK80AB	DDP to MSDL Cable (18 Ft.)	160.00	D
S	NTCK80AC	DDP to MSDL Cable (35 Ft.)	180.00	D
S	NTCK80AD	DDP to MSDL Cable (50 Ft.)	200.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTCW84EA	Meridian ITG 2.0 D-Channel PCMCIA Pigtail Cable. The pigtail cable connects the PCMCIA D-Channel card to the motherboard for packetizing and compression.	40.00	D
S ➤	NTCW84KA	Meridian ITG 2.0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter. The cable is used for providing D-Channel capability to the LAN/WAN environment.	180.00	D
S ➤	NTCW84LA	Meridian ITG 2.0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA). The cable is used specifically for providing D-Channel capability to the LAN/WAN environment for ITG 1.0 (8-port).	180.00	D
S ➤	NTCW84MA	Meridian ITG 2.0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack. The cable is used specifically for providing D-Channel capability to the LAN/WAN environment for ITG 1.0 (8-ports).	180.00	D
S ➤	NTDK27AA	Ethernet Adapter Cable	75.00	D
S ➤	NTDK49AA	Expansion Cabinet Cable Kit	100.00	D
S	NTDK88AA	Option 11C Mini Main Chassis Cable Kit	130.00	I
S	NTDK89AA	Option 11C Mini Chassis Expander Cable Kit	130.00	I
S	NTMF94DA	Meridian ITG Backplane and D-Sub Com Port Cable	180.00	D
S ➤	NTMF94EA	Meridian ITG 2.0 ELAN, TLAN, RS232 Port Cable. The cable is used for connecting to the LAN/WAN environment (for cards without the D-Channel).	180.00	D
S ➤	NTND11BA	CP to CP Cable (6 Ft.)	170.00	D
S ➤	NTND13BC	IOP to IOP SCSI Cable (6 Ft.)	170.00	D
S	NTND14BA	CNI to 3PE Cable (5 Ft.)	150.00	D
S ➤	NTND14BB	CNI to 3PE Cable (10 Ft.)	150.00	D
S ➤	NTND14BC	CNI to 3PE Cable (12 Ft.)	150.00	D
S ➤	NTND14BD	CNI to 3PE Cable (12 Ft.)	160.00	D
S ➤	NTND14BE	CNI to 3PE Cable (25 Ft.)	160.00	D
S ➤	NTND14BG	CNI-3 to 3PE (35 Ft.)	160.00	D
S ➤	NTND14BX	CNI-3 to 3PE Cable (50 Ft.)	160.00	D
S ➤	NTND26AA	MSDL DCHI Interface Cable (6 Ft.)	130.00	D
S ➤	NTND26AB	MSDL DCHI Interface Cable (18 Ft.)	160.00	D
S ➤	NTND26AC	MSDL DCHI Interface Cable (35 Ft.)	180.00	D
S ➤	NTND26AD	MSDL DCHI Interface Cable (50 Ft.)	200.00	D
S ➤	NTND27AB	MSDL to I/O Panel Cable (6 Ft.)	150.00	D
S ➤	NTND28BB	Inter-Cabinet Clock Cable (16 Ft.)	180.00	D
S ➤	NTND28BC	Inter-Cabinet Network Cable (22 Ft.)	300.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTND29AA	CPU Interface Cable (6 Ft.)	35.00	D
S ➤	NTND30AA	Junctor to I/O Housing Cable (6 Ft.)	35.00	D
S ➤	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	4,700.00	D
S ➤	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	4,000.00	I
S ➤	NTND94DA	CNI to I/O Panel Ethernet Cable (20 In.)	100.00	D
S ➤	NTND95AA	3PE to I/O Housing Cable (8 Ft.)	140.00	D
S ➤ ⊗	NTRC17AA	CP PII Ethernet to Ethernet Cable (8.5 Ft./3m)	90.00	D
S ✓ ➤	NTRC46AA	Clock to FIJI Cable, (4 Ft.-4.5 Ft.)	55.00	D
S ✓ ➤	NTRC46BA	Clock to FIJI Cable, (5.5 Ft.-8 Ft.)	60.00	D
S ➤	NTRC46CA	Clock to FIJI Cable, (22 Ft.)	60.00	D
S ✓ ➤	NTRC47AA	FIJI to FIJI Synch Cable	50.00	D
S ✓ ➤	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft./2M)	40.00	D
S ✓ ➤	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft./3M)	50.00	D
S ✓ ➤	NTRC48CA	FIJI to FIJI Fiber Ring Cable, (12 Ft./3.6M)	50.00	D
S ✓ ➤	NTRC48DA	FIJI to FIJI Fiber Ring Cable, (14 Ft./4.2M)	50.00	D
S ✓ ➤	NTRC48EA	FIJI to FIJI Fiber Ring Cable, (19 Ft./6M)	60.00	D
S ✓ ➤	NTRC48FA	FIJI to FIJI Fiber Ring Cable, (26 Ft./8M)	60.00	D
S ✓ ➤	NTRC48GA	FIJI to FIJI Fiber Ring Cable, (32 Ft./10M)	60.00	D
S ✓ ➤	NTRC48HA	FIJI Fiber Ring Cable, (50 Ft.)	60.00	D
S ✓ ➤	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft.)	50.00	D
S ✓ ➤	NTRC49BA	Fiber Network Clock-Clock Synch Cable, (20 Ft.)	60.00	D
S ➤ ⊗	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	60.00	D
S ✓	NTTK14AA	Option 11C Mini Power Cord Kit	20.00	I
S ➤	NTWE04AC	Meridian ITG 2.0 Inter-Cabinet Cable 10 Ft. (Optional)	80.00	D
S ➤	NTWE04AD	Meridian ITG 2.0 Intra-Cabinet Cable 1 Ft.	50.00	D
S ➤	P0649968	Ribbon Cable, RS232, (Male/Male) 25 Pin, Straight-Through (6 Ft.)	35.00	D
S † ➤	QCAD109A	Cable Adapter	110.00	D
S †	QCAD111A	Cable, Connector (QSP43)	440.00	D
S ➤	QCAD125A	Cable, Connector (10 Ft.) (Female/Female) (Clock to Clock)	100.00	D
S † ➤	QCAD128A	Cable, Connector (7 Ft.) (Male/Female) (DTI to I/O Panel)	60.00	H
S ➤	QCAD129A	Cable, Connector (7 Ft.) (Male/Female) (PRI/DTI to Echo Canceler)	60.00	D
S ➤	QCAD133A	PRI/DTI I/O Cable (50 Ft.)	150.00	D
S † ➤	QCAD139A	Power Adapter Cable	110.00	D
S † ➤	QCAD190A	Cable, Connector (74 In.) (Male/Male)	50.00	D
S † ➤	QCAD193A	Cable, Connector (61 In.) (Male/Male)	50.00	D
S † ➤	QCAD196A	Cable, Connector (48 In.) (Male/Male)	40.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	QCAD25AA	Power Adapter Cable	100.00	D
S ➤	QCAD274A	Rectifier Cords, 20 Amp, 225V	70.00	D
S ➤	QCAD277A	Power Connector Cable (2nd Module)	40.00	D
S ➤	QCAD278A	Power Connector Cable (Basic)	20.00	D
S ➤	QCAD284A	Power Adapter Cable	70.00	D
S † ➤	QCAD294B2	Power Fail Transfer Cable (50 Ft.)	70.00	D
S † ➤	QCAD306B	Power Connector Cable (QSD73)	30.00	D
S † ➤	QCAD309A	Alarm Adapter Cable	40.00	D
S † ➤	QCAD310A	Ground Extension Cable	30.00	D
S † ➤	QCAD313A	Power & Signaling Cable (Tier 3)	50.00	D
S ➤	QCAD318A	Telecom 25 Pair (50-Pin) to 6DB-25 Female Connector	100.00	D
S ➤	QCAD319A	Telecom 25 Pair (50-Pin) to 6DB-25 Male Connector	100.00	D
S † ➤	QCAD325A	Cable	180.00	D
S ➤	QCAD332A	Triple SDI Cable (Internal)	80.00	D
S ➤	QCAD42A	Cable, Intra-Cabinet (25 Conductor 95 In.) (EMI)	50.00	D

Miscellaneous

S ➤	A0355200	Power Fail Transfer Unit	800.00	I
S ➤	A0361709	Caster (1)	50.00	I
S	A0377992	Black Box ABCDE Switch	180.00	H
S ➤	A0378252	Battery. Battery	60.00	I
S ➤	A0379431	OPS Protector Device	100.00	I
S ➤	A0381016	Null Modem Connector, (Female/Female)	35.00	D
S ➤	A0601396	Modem Eliminator Male to Female	15.00	D
S ➤	A0601397	Modem Eliminator Female to Female	15.00	D
S ➤	A0619621	RJ45/RS232 Connector	15.00	D
S ➤	A0638645	External Modem (14,400 bps, V.32 bis with V.42 bis)	370.00	H
B	A0728841	Citizen Printer	400.00	H
S † ➤	MVC01561	Connector Hardware Package (50 Conductor)	5.00	D
S † ➤	MVC01562	Connector Hardware Package (25 Conductor)	10.00	D
S ➤	NT0962AA	Meridian ITG 2.0 486 Software Upgrade PCMCIA Card. The PCMCIA card is only ordered when the customer needs an up-issue for ITG 2.0 software (ITG 8-port trunk card).	850.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT0963AA	Meridian ITG 2.0 Pentium Software Upgrade PCMCIA Card. The PCMCIA card is only ordered when the customer needs an up-issue for ITG 2.0 software (card is optional).	850.00	H
S ➤	NT1P6501	Two Optical Adaptors Kit	300.00	I
S ➤	NT1P6601	Four Optical Adaptors Kit	600.00	I
B	NT1R91AA	Modem Kit	1,250.00	D
S ➤ ⊗	NT4N6809	Security Device Holder	120.00	D
S ⊗	NT4N71BA	cPCI LED/LCD Display Panel	350.00	I
S ➤	NT5D90BA	Software Installation Kit (Non-Autovon)	650.00	H
S	NT5G15AA	Meridian Integrated Voice Services (MIVS) SPARE	3,800.00	D
S	NT5G33AA	Meridian Integrated Voice Services (MIVS) PCMCIA	1,400.00	D
S	NT6D72AA	Basic Rate Signaling Concentrator	6,700.00	I
S ➤	NT7D05AA	Filler Panel - Ringing Generator	50.00	I
S ➤	NT7D06AA	Filler Panel	35.00	D
S ➤	NT7D0902	Rear Mount Conduit/Wiring Kit	80.00	I
S ➤	NT8D1107	SuperLoop Adapter Plate	8.00	I
S ➤	NT8D22AC	System Monitor	1,010.00	I
S ➤	NT8D27BB	Pedestal AC	1,750.00	I
S ➤	NT8D31AA	Blank Faceplate (0.875 In.)	45.00	I
S ➤	NT8D31AB	Blank Faceplate (1 In.)	55.00	I
S ➤	NT8D31AD	Blank Faceplate (2 In.)	65.00	I
S ➤	NT8D6401	Insulating Washer Kit	45.00	I
S ★ ➤ Δ	NT8D64BH	Floor Module Anchor Hole Template	150.00	H
S ➤	NT9D1501	Door Panel Lock Latch Kit	4.00	H
B ➤	NTAK11BD	Main/Expansion Cabinet	2,500.00	I
S ➤	NTAK21BA	Expansion Cartridge	300.00	I
S ➤	NTAK27AA	Option 11 Cabinet Pedestal	440.00	I
S ➤	NTAK28AB	Battery Junction Box	170.00	H
S ➤	NTAK75AB	2-4 Hour Battery Back-Up Unit	2,225.00	H
S ➤	NTAK76AB	15-30 Minute Battery Back-up Unit	550.00	H
S ➤	NTAK80AA	Option 11 System Back-Up Cartridge	550.00	I
S ➤	NTAK9204	OPS Cable	40.00	D
S ➤	NTAK92BA	OPS Protection Module	1,675.00	I
S ➤	NTBK80AA	Ground Bar	75.00	D
S ➤	NTCW84JA	Meridian ITG 2.0 I/O Panel Mounting Connector. The connector is used for large systems to filter out extraneous frequencies.	40.00	D
S ➤	NTDK30AA	Database Upgrade Tool	200.00	I
S ➤	NTDK68AA	16MB SIMM	850.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTND20AA	Alarm Terminator	50.00	I
S	NTRE18AA	Front/Rear Cover	170.00	I
S ➤	NTSF6851	Internet Registration Kit	50.00	H
S ✓	NTTK08AA	Option 11C Mini Vertical Wall Mount Kit	60.00	I
S ✓	NTTK09AA	Option 11C Mini 19 Inch Rack Mount Kit	80.00	I
S	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	13.00	I
S ✓	NTTK11AA	Option 11C Mini Horizontal Wall Mount Kit	80.00	I
S ✓	NTTK24AA	Option 11C Mini Fiber Cable Management Kit	50.00	I
S Δ	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package	50.00	H
S ✓ ➤	NTZC91BA	Software Installation Kit (Non-Autovon)	650.00	H
S †	P0593977	Faceplate - ADM Hinged Control Cover - Black	5.00	D
S † ➤	P0639984	Adapter Plate for SDI Filter Connector	5.00	I
S † ➤	P0641477	Mounting Bracket Lower SDI Connector	10.00	I
S † ➤	P0642917	50 Pin Connector Cover Plate	15.00	I
S ➤	P0643763	Filter, PRI/DTI I/O	200.00	I
S ➤	P0660405	Field Failure Report Tag (Telephone and Console Equipment)	No charge	
S † ➤	P0677580	Cabinet Grounding Package #1	No charge	
S † ➤	P0677587	Cabinet Grounding Package #2	No charge	
S † ➤	P0677588	Cabinet Grounding Package #3	No charge	
S ➤	P0678258	Filter Connector	100.00	I
S ➤	P0691037	Ground Lug	20.00	D
S † ➤	P0696547	Connector Housing (Side Panel)	90.00	I
S † ➤	P0697550	Connector Adapter Bracket	45.00	I
S † ➤	P0697559	Mounting Bracket	25.00	I
S † ➤	P0697707	Connector Cover Panel	140.00	I
S † ➤	P0702380	Connector Housing (Top Panel)	90.00	I
S † ➤	P0703905	Connector Adapter Panel Housing	30.00	I
S † ➤	P0703906	Adapter Housing	60.00	I
S † ➤	P0703960	DTI/PRA Adapter Plate Package	20.00	I
S ➤	P0704511	Connector Housing Package	90.00	I
B	P0714224	MDF Locking Bar Restraint Bracket. MDF Locking Bar Restraint Bracket is used to secure MDF cables in the Option 11 cabinet.	34.00	I
S	P0714236	Mounting Bracket	50.00	I
S	P0715802	Alignment Bracket (Expansion Cabinet)	15.00	I

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ Δ	P0722849	Designation Label, EMSI	1.00	D
S ➤ Δ	P0722850	Designation Label, EMSI	1.00	D
S ➤	P0723459	Blank Packlet for EOI	80.00	D
S ➤	P0733203	Meridian 1 Logo Insert (Aqua Blue)	5.00	H
S ✓ ➤	P0738866	Label Kit for Inter-Cabinet Cables	125.00	D
S ➤	P0741489	Backplane Cable Extraction Tool	75.00	D
S ➤	P0745713	Growth I/O Panel	35.00	I
S ➤	P0803870	Filler Plate For Fiber Controller	80.00	D
S Δ	P0816832	Fiber Routing Guide	20.00	H
S ➤	P0870718	Blank Insert (Light Gray)	5.00	H
S	P0904477	Dark Gray UEM Overlay Kit	75.00	D
S	P0904478	Light Gray UEM Overlay Kit	75.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Telephones and Attendant Products
M3900 Series

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTMN31BA66	Meridian M3901 Entry, Platinum	80.00	D
S ➤	NTMN31BA70	Meridian M3901 Entry, Charcoal	80.00	D
S ➤	NTMN32BA66	Meridian M3902 Basic, Platinum	165.00	D
S ➤	NTMN32BA70	Meridian M3902 Basic, Charcoal	165.00	D
S ➤	NTMN33BA66	Meridian M3903 Enhanced, Release 1, Platinum	335.00	D
S ➤	NTMN33BA70	Meridian M3903 Enhanced, Release 1, Charcoal	335.00	D
S ➤	NTMN33FA66	Meridian M3903 Enhanced, Release 2, Platinum	335.00	D
S ➤	NTMN33FA70	Meridian M3903 Enhanced, Release 2, Charcoal	335.00	D
S ➤	NTMN34BA66	Meridian M3904 Professional, Release 1, Platinum	550.00	D
S ➤	NTMN34BA70	Meridian M3904 Professional, Release 1, Charcoal	550.00	D
S ➤	NTMN34FA66	Meridian M3904 Professional, Release 2, Platinum	550.00	D
S ➤	NTMN34FA70	Meridian M3904 Professional, Release 2, Charcoal	550.00	D
S ➤	NTMN35BA66	Meridian M3905 Call Center, Release 1, Platinum	550.00	D
S ➤	NTMN35BA70	Meridian M3905 Call Center, Release 1, Charcoal	550.00	D
S ★ ➤	NTMN35FA-66	Meridian M3905 Call Center, Release 2, Platinum	550.00	D
S ★ ➤	NTMN35FA-70	Meridian M3905 Call Center, Release 2, Charcoal	550.00	D

Optional/Value Added Components

S	NT1F04GA66	Shoulder Rest, Platinum (M3900 Series)	16.00	D
S	NT1F04GA70	Shoulder Rest, Charcoal (M3900 Series)	16.00	D
S ➤	NTMN13AA66	Footstand, Platinum (M3901, M3902)	8.00	D
S ➤	NTMN13AA70	Footstand, Charcoal (M3901, M3902)	8.00	D
S ➤	NTMN14AA66	Footstand, Platinum (M3903, M3904, M3905)	8.00	D
S ➤	NTMN14AA70	Footstand, Charcoal (M3903, M3904, M3905)	8.00	D
S ➤	NTMN15AA66	Meridian Wall Mount Kit, Platinum (M3903, M3904, M3905)	10.00	D
S ➤	NTMN15AA70	Meridian Wall Mount Kit, Charcoal (M3903, M3904, M3905)	10.00	D
S	NTMN37AA66	Key-based Expansion Module Without Footstand, Platinum	150.00	D
S ➤	NTMN37AA70	Key-based Expansion Module Without Footstand, Charcoal	150.00	D
S ➤	NTMN38AA66	Key-based Expansion Module Kit 1, Platinum	10.00	D
S ➤	NTMN38AA70	Key-based Expansion Module Kit 1, Charcoal	10.00	D
S ➤	NTMN38BA66	Key-based Expansion Module Kit 2, Platinum	12.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTMN38BA70	Key-based Expansion Module Kit 2, Charcoal	12.00	D
S ➤	NTMN59AA66	Meridian External Alerter and Recording Interface, Platinum (M3900 Series)	100.00	D
S ➤	NTMN59AA70	Meridian External Alerter and Recording Interface, Charcoal (M3900 Series)	100.00	D
S ➤	NTMN67AA66	Meridian Display-Based Expansion Module, Platinum (M3900 Series)	170.00	D
S ➤	NTMN67AA70	Meridian Display-Based Expansion Module, Charcoal (M3900 Series)	170.00	D
S ➤	NTMN68AA66	Meridian Analog Terminal Adapter (ATA), Platinum (M3900 Series)	190.00	D
S ➤	NTMN68AA70	Meridian Analog Terminal Adapter (ATA), Charcoal (M3900 Series)	190.00	D
S ✓ ➤	NTMN71AA66	Meridian Accessory Connection Module (ACM), Platinum (M3900 Series)	35.00	D
S ✓ ➤	NTMN71AA70	Meridian Accessory Connection Module (ACM), Charcoal (M3900 Series)	35.00	D
S ➤	NTMN82AA66	Meridian Personal Directory PC Utility, Platinum (M3900 Series)	100.00	D
S ➤	NTMN82AA70	Meridian Personal Directory PC Utility, Charcoal (M3900 Series)	100.00	D
S ✓ ➤ ⊗ Δ	NTSF8519	Enable Package 381, 382 for M3900 Sets Phase II	No charge	

Meridian Modular Telephones

S ➤	AS103003	Centralized Answering Position Packages (M2616), Black	830.00	D
S ➤	AS103035	Centralized Answering Position Packages (M2616), Ash	830.00	D
S ➤	AS103093	Centralized Answering Position Packages (M2616), Gray	830.00	D
S ➤	NT9K05AA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	135.00	D
S ➤	NT9K05AA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	135.00	D
S ➤	NT9K05AA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	135.00	D
S ➤	NT9K08AA03	Meridian M2008 Standard Business Telephone, Basic, Black	175.00	D
S ➤	NT9K08AA35	Meridian M2008 Standard Business Telephone, Basic, Ash	175.00	D
S ➤	NT9K08AA93	Meridian M2008 Standard Business Telephone, Basic, Gray	175.00	D
S ➤	NT9K08AB03	Meridian M2008HF Standard Business Telephone, Basic, Black	240.00	D
S ➤	NT9K08AB35	Meridian M2008HF Standard Business Telephone, Basic, Ash	240.00	D
S ➤	NT9K08AB93	Meridian M2008HF Standard Business Telephone, Basic, Gray	240.00	D
S ➤	NT9K08AC03	Meridian M2008 Standard Business Telephone with Display, Black	350.00	D
S ➤	NT9K08AC35	Meridian M2008 Standard Business Telephone with Display, Ash	350.00	D
S ➤	NT9K08AC93	Meridian M2008 Standard Business Telephone with Display, Gray	350.00	D
S ➤	NT9K08AD03	Meridian M2008HF Standard Business Telephone with Display, Black	390.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9K08AD35	Meridian M2008HF Standard Business Telephone with Display, Ash	390.00	D
S ➤	NT9K08AD93	Meridian M2008HF Standard Business Telephone with Display, Gray	390.00	D
S ➤	NT9K16AA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	400.00	D
S ➤	NT9K16AA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	400.00	D
S ➤	NT9K16AA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	400.00	D
S ➤	NT9K16AC03	Meridian M2616 Performance-Plus Telephone with Display, Black	525.00	D
S ➤	NT9K16AC35	Meridian M2616 Performance-Plus Telephone with Display, Ash	525.00	D
S ➤	NT9K16AC93	Meridian M2616 Performance-Plus Telephone with Display, Gray	525.00	D
S ➤	NT9K18AC03	Meridian M2216ACD Telephone, Black	525.00	D
S ➤	NT9K18AC35	Meridian M2216ACD Telephone, Ash	525.00	D
S ➤	NT9K18AC93	Meridian M2216ACD Telephone, Grey	525.00	D
S ➤	NTZK20AA35	Meridian M2016S Secure Telephone, Basic, Ash	830.00	D

Optional/Value Added Components

S ➤	A0652365	Meridian M2616CT 700 mAh Battery, Gray (Standard)	40.00	D
S ➤	A0652369	Meridian M2616CT 700 mAh Battery, Black (Standard)	40.00	D
S ➤	A0729362	Meridian M2616CT 700 mAh Battery, Ash (Standard)	40.00	D
S	NT2K22VH03	Meridian Key Expansion Module, Black, (M2000 Series)	160.00	D
S	NT2K22VH35	Meridian Key Expansion Module, Ash, (M2000 Series)	160.00	D
S	NT2K22VH93	Meridian Key Expansion Module, Gray (M2000 Series)	160.00	D
S ➤	NT2K28AB03	Meridian Display Option, Black (10 Language)	200.00	D
S ➤	NT2K28AB35	Meridian Display Option, Ash (10 Language)	200.00	D
S ➤	NT2K28AB93	Meridian Display Option, Gray (10 Language)	200.00	D
S ➤	NT2K28AD03	Meridian Display Option, Black (3 Language)	190.00	D
S ➤	NT2K28AD35	Meridian Display Option, Ash (3 Language)	190.00	D
S ➤	NT2K28AD93	Meridian Display Option, Gray (3 Language)	190.00	D
S ➤	NT2K28KB-03	Meridian Japanese Display Option, Black	200.00	D
S ➤	NT2K28KB-35	Meridian Japanese Display Option, Ash	200.00	D
S ➤	NT2K28KB-93	Meridian Japanese Display Option, Gray	200.00	D
B ➤	NT2K40WA	External Alerter Interface (M2000 Series)	40.00	D
B † ➤	NT2K65XR	Meridian Communications Adapter (M2000 Series)	300.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT2K68AA	Analog Terminal Adapter (ATA) (M2000 Series)	190.00	D
B ➤	NT2K69AA	Meridian Communications Adapter (MCA) (M2000 Series). This is a vintage update of the MCA (NT2K65XR). See Notes in Reference Section.	300.00	D
S ➤	NT2K83AA03	ATA/MCA Footstand, Black (M2006, M2008, M2008HF). Compatible with Meridian Modular Telephones (M2006, M2008, M2008HF) used with ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	NT2K83AA35	ATA/MCA Footstand, Ash (M2006, M2008, M2008HF). Compatible with Meridian Modular Telephones (M2006, M2008, M2008HF) used with ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	NT2K83AA93	ATA/MCA Footstand, Gray (M2006, M2008, M2008HF). Compatible with Meridian Modular Telephones (M2006, M2008, M2008HF) used with ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	NT2K83BA03	ATA/MCA Footstand, Black (M2616, M2216ACD). Compatible with Meridian Modular Telephones (M2616 and M2216ACD) used with ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	NT2K83BA35	ATA/MCA Footstand, Ash (M2616, M2216ACD). Compatible with Meridian Modular Telephones (M2616 and M2216ACD) used with ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	NT2K83BA93	ATA/MCA Footstand, Gray (M2616, M2216ACD). Compatible with Meridian Modular Telephones (M2616,M2216ACD) using ATA or MCA (NT2K65 or NT2K69)	8.00	D
S ➤	P0780103	Single Key Expansion Module Footstand, Black (M2000 Series)	10.00	D
S ➤	P0780135	Single Key Expansion Module Footstand, Ash, (M2000 Series)	10.00	D
S ➤	P0780193	Single Key Expansion Module Footstand, Gray, (M2000 Series)	10.00	D
S ➤	P0780203	Double Key Expansion Module Footstand, Black (M2000 Series)	20.00	D
S ➤	P0780235	Double Key Expansion Module Footstand, Ash (M2000 Series)	20.00	D
S ➤	P0780293	Double Key Expansion Module Footstand, Gray (M2000 Series)	20.00	D

Meridian Digital Telephones

S ➤	NT1F21AE03	Meridian M2317 Intelligent Telephone, Black	625.00	D
S ➤	NT1F21AE35	Meridian M2317 Intelligent Telephone, Ash	625.00	D
S ➤	NT1F21AE93	Meridian M2317 Intelligent Telephone, Gray	625.00	D
S ➤	NT1F21ME03	Meridian M2317 Intelligent Telephone with Data, Black	925.00	D
S ➤	NT1F21ME35	Meridian M2317 Intelligent Telephone with Data, Ash	925.00	D
S ➤	NT1F21ME93	Meridian M2317 Intelligent Telephone with Data, Gray	925.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Optional/Value Added Components				
S ➤	NT1F09AC	Asynchronous Data Option (M2009, M2112, M2018, M2317)	300.00	D
Consoles				
S § ➤	AS1066	Special Meridian 1 Attendant PC with Digital Line Card. Includes: - Attendant PC Interface Unit - Attendant PC Software - On-line Tutorial - Handset and cord - RS232 cable - Meridian 1 system cable - Unit and software installation and user documentation	6,600.00	I
S ➤	NT3G40BB35	Busy Lamp Field/Console Graphics Module	2,250.00	D
S ➤	NT6G00AF35	M2250 Attendant Console	3,400.00	D
S ➤	NT9D08AA	DSS-9000 Direct Station Select Unit	2,160.00	D
S ✓ ➤	NTZC35AA	Meridian 1 Attendant Hospitality Services 1 Console Bundle	9,000.00	D
S ➤	NTZC35BA	Meridian 1 Attendant Hospitality Services 2 Console Bundle	17,200.00	D
S ✓ ➤	NTZC35CA	Meridian 1 Attendant Hospitality Services 3 Console Bundle	28,500.00	D
S ✓ ➤	NTZC35DA	Meridian 1 Attendant Hospitality Services Large (4) Console Bundle	37,000.00	D
S ✓ ➤	NTZC35EA	Meridian 1 Attendant Hospitality Services Large Expansion Bundle	7,000.00	D
S ✓ ➤	NTZC36AA	Meridian 1 Attendant Hospitality Services 1 Console Software Bundle	6,000.00	D
S ➤	NTZC36BA	Meridian 1 Attendant Hospitality Services 2 Console Software Bundle	9,200.00	D
S ✓ ➤	NTZC36CA	Meridian 1 Attendant Hospitality Services 3 Console Software Bundle	15,000.00	D
S ✓ ➤	NTZC36DA	Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle	25,000.00	D
S ➤	NTZC36EA	Meridian 1 Attendant Hospitality Services Large Software Expansion Bundle	3,500.00	D
S ➤	NTZC37AA	Meridian 1 Attendant Hospitality Services Software for Expansion from 1 to 2 Console Bundle	3,500.00	D
S ✓ ➤	NTZC37BA	Meridian 1 Attendant Hospitality Services Software for Expansion from 2 to 3 Console Bundle	7,000.00	D
S ✓ ➤	NTZC37CA	Meridian 1 Attendant Hospitality Services Software for Expansion from 3 to 4 Console Bundle	10,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTZR07BA	Meridian 1 Attendant PC. Includes: - Attendant PC Interface Unit - Attendant PC Software - On-line Tutorial - Handset and cord - RS232 cable - Meridian 1 system cable - Unit and software installation and user documentation	4,500.00	D
S ➤	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module. Includes: - Attendant PC LAN Interface Module Software- Installation Guide	1,720.00	D
S	P0889883	Meridian 1 Attendant PC/Hospitality Software Quick Start Guide	10.00	H
S	P0889884	Meridian 1 Attendant PC/Hospitality User Guide	20.00	H
S	P0889885	Meridian 1 Attendant PC/Hospitality Installation Quick Start Guide	10.00	H

Accessories/Replacement Parts

Headset Products

Cords

S ➤	A0274225	Handset Cord, 6 Ft. Ash (M2000 Series)	3.00	D
S ➤	A0314408	Handset Cord (6 Ft.) - Gray, (M2000 Series)	3.00	D
S ➤	A0318327	Handset Cord (9 Ft.) (Standard) - Ash, (M2000 Series)	4.00	D
S ➤	A0318330	Handset Cord (9 Ft.) (Standard) - Gray, (M2000 Series)	4.00	D
S ➤	A0327128	Handset Cord (6 Ft.) - Black, (M2000 Series)	3.00	D
S ➤	A0334590	Handset Cord (9 Ft.) (Standard) - Black, (M2000 Series)	4.00	D
S ➤	A0346862	6-Conductor Line Cord (7 Ft. for M2000 telephones requiring external power, standard for M3902, M3903, M3904, and M3905)	7.00	D
S ➤	A0346863	6-Conductor Line Cord (14 Ft. for M2000 Series requiring external power and M3902, M3903, M3904 and M3905)	12.00	D
S ➤	A0634101	2-Conductor Line Cord (25 Ft.) Satin, (M2000 Series and M3901)	10.00	D
S ➤	A0720557	Handset Cord, Platinum, 12 Ft. (M3900 Series)	7.00	D
S ➤	A0720558	Handset Cord, Charcoal, 12 Ft. (M3900 Series)	7.00	D
S ➤	A0720559	Handset Cord, Platinum, 9 Ft. (Standard, M3900 Series)	4.00	D
S ➤	A0720560	Handset Cord, Charcoal, 9 Ft. (Standard, M3900 Series)	4.00	D
S ➤	A0720561	Handset Cord, Platinum, 6 Ft. (M3900 Series)	3.00	D
S ➤	A0720562	Handset Cord, Charcoal, 6 Ft. (M3900 Series)	3.00	D
S	NTAG95AA	Meridian 1 Attendant PC Handset Cord with PJ-Type Plug	40.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Handsets				
S ➤	NT0C09EA03	Legacy Handset, Black (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D
S ➤	NT0C09EA35	Legacy Handset, Ash (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D
S ➤	NT0C09EA93	Legacy Handset, Gray (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D
S ➤	NT0C09EL-93	Legacy Handset, Gray (NT2K & NT9K Models M2006, M2008, M2616, M2216 ACD-1)	20.00	D
S ➤	NT0C09EL03	Legacy Handset, Black (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)	20.00	D
S ➤	NT0C09EL35	Legacy Handset, Ash (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)	20.00	D
S ✓ ➤	NTMN17AA66	Handset, Platinum (M3900 Series)	40.00	D
S ✓ ➤	NTMN17AA70	Handset, Charcoal (M3900 Series)	40.00	D
S ✓ ➤	NTMN18AA66	Handset Kit, Platinum (M3905)	42.00	D
S ✓ ➤	NTMN18AA70	Handset Kit, Charcoal (M3905)	42.00	D
Designation Material				
S ➤	A0387583	Auto Dial Key Cap Package (50/PK)	14.00	D
S ➤	A0387586	Hot Line Key Cap Package (50/PK)	14.00	D
S ➤	A0387588	Display Queue Key Cap Package (50/PK)	14.00	D
S ➤	A0387590	Display Agent Key Cap Package (50/PK)	14.00	D
S ➤	A0387592	Agent Key Cap Package (50/PK)	14.00	D
S ➤	A0387595	Waiting Key Cap Package (50/PK)	14.00	D
S ➤	A0387596	Answer Agent Key Cap Package (50/PK)	14.00	D
S ➤	A0387598	Position Busy Key Cap Package (50/PK)	14.00	D
S ➤	A0387599	Message Indicator Key Cap Package (50/PK)	14.00	D
S ➤	A0387603	Group Call Key Cap Package (50/PK)	14.00	D
S ➤	A0387604	Emergency Key Cap Package (50/PK)	14.00	D
S ➤	A0387606	Program Key Cap Package (50/PK)	14.00	D
S ➤	A0387607	Supervisor Key Cap Package (50/PK)	14.00	D
S ➤	A0387608	Charge Key Cap Package (50/PK)	14.00	D
S ➤	A0387609	Group Pickup Key Cap Package (50/PK)	14.00	D
S ➤	A0387610	Not Ready Key Cap Package (50/PK)	14.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	A0387611	DN Pickup Key Cap Package (50/PK)	14.00	D
S ➤	A0387613	In-Calls Key Cap Package (50/PK)	14.00	D
S ➤	A0387614	Observe Key Cap Package (50/PK)	14.00	D
S ➤	A0387616	Night Key Cap Package (50/PK)	14.00	D
S ➤	A0387624	Trace Key Cap Package (50/PK)	14.00	D
S ➤	A0387629	Privacy Release Key Cap Package (50/PK)	14.00	D
S ➤	A0387631	Park Key Cap Package (50/PK)	14.00	D
S ➤	A0387634	Stored Number Redial Key Cap Package (50/PK)	14.00	D
S ➤	A0387635	Last Number Redial Key Cap Package (50/PK)	14.00	D
S ➤	A0387637	Display Key Cap Package (50/PK)	14.00	D
S ➤	A0387638	Make Set Busy Key Cap Package (50/PK)	14.00	D
S ➤	A0387639	Ring Again Key Cap Package (50/PK)	14.00	D
S ➤	A0390595	Hold Key Cap Package (15/PK)	14.00	D
S ➤	A0397705	Release Key Cap Package (50/PK)	14.00	D
S	A0615902	Literature Pack (M2006, M2008)	10.00	D
S § ➤	AS1182	Pre-Printed Feature Key Cap Package (1 PK of 11 Key Caps, A0637619). Includes: - Call Pickup - Conference - Display - Emergency - Forward - Message - Park - Ring Again - Speed Call - Transfer - Voice Call	No charge	
S ✓ ➤	NT2F78AA	Feature Card Label Sheet (M3901, Package of 25 P0906396)	35.00	D
S ✓ ➤	NT2F83AA	Telephone Number Sheet (M3900 Series, Package of 15 P0888695)	50.00	D
S ➤	NT2F84AA	Clear Window Menu Cover, M3901, Package of 15	15.00	D
S	NT2K80AD	Literature Pack (M2216-ACD 1/2)	10.00	D
S	NT2K80GB	Literature Pack (M2616, M2016S)	10.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	NT5F52AA	Pre-Printed Feature Key Cap Package (15 Packages of 11 Key Caps Each). Includes: - Call Pickup - Conference - Display - Emergency - Forward - Message - Park - Ring Again - Speed Call - Transfer - Voice Call	25.00	D
S ➤	NTMN0006	Key Cap Package (M3905)	5.00	D
S ✓ ➤	NTMN16AA66	Brandline Insert, Platinum (Package of 250 P0904456, M3900 Series)	180.00	H
S ✓ ➤	NTMN16AA70	Brandline Insert, Charcoal (Package of 250 P0904455, M3900 Series)	180.00	H
S ➤	NTZR50AA03	Blank Brandline Insert, Black (Package of 250 P0784403) (M2000 Series)	45.00	D
S ➤	NTZR50AA35	Blank Brand Line Insert, Ash, (M2000 Series)	45.00	D
S ➤	NTZR50AA93	Blank Brand Line Insert, Gray (Package of 250 P0784493) (M2000 Series)	45.00	D
N ➤	P0652720	Telephone Number Lens (1 each, Standard for all Meridian Digital Telephones and Attendant Consoles) (M2000 Series)	2.00	D
S	P0688609	Literature Pack (M2317)	8.00	D
S ➤	P0694698	Key Cap, Orange with Clear Window (1 each, Standard for all Meridian)	.35	D
S ➤	P0699124	Designation Tabs (1 each, M2250/M1250)	30.00	D
S ➤	P0700563	Key Cap, Red with Clear Window (1 each, Standard for all Meridian)	.35	D
B Δ	P0705800	Key Caps, Green	.50	D
N ✓ ➤	P0705801	Clear Feature Key Caps (1 each, standard for M2000 Series and Attendant Consoles)	.50	D
S †	P0714688	CPLUS PC Key Cap Labels (each) (for PC keyboard)	70.00	D
S	P0714694	DSS-9000 Key Number Labels-Enhanced Mode	15.00	D
S	P0714695	DSS-9000 Key Number Labels-Standard Mode	15.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	P0731813	Quick Installation Pre-Printed Keycaps (10 Cards of 10 Pre-Printed Keycaps). Includes: - Call Pick-up - Conference - Forward - Handsfree Mute - Transfer - Hold - Message - Program - Ring Again - Speed Call	30.00	D
S	P0732496	Feature Key Designation Labels with Telephone Number Card (25/PK)	25.00	D

Miscellaneous

S ➤	A0288529	Jumpers (8/PK) (M2000 Series)	30.00	D
S ➤	A0336406	Power Supply	30.00	D
S ➤	A0336823	Multi-Output Power Supply (MOPS)	60.00	D
S ➤	A0348785	Handset Cord with PJ Type Plug (M2250/M1250)	25.00	D
S ➤	A0367335	Wall Transformer, 110VAC-26.7VAC, (used with NT2K10xx)	40.00	D
S ➤	A0367601	Power Supply 16V (BLF/CGM)	40.00	D
S ➤	A0377172	Transformer, 24V AC (M1250/DSS-9000)	50.00	D
S ➤	A0688664	ATA/MCA Transformer. ATA/MCA Transformer is required for use with the ATA or MCA (NT2K69AA)	40.00	D
S	A0725342	Meridian 1 Attendant PC Software Tutorial	8.00	H
S ➤	NT2K03BA	Key Expansion Module Cable, (M2000 Series)	5.00	D
S ➤	NT2K10WD	Power Supply Board, (M2000 Series NT2K65 and NT2K40)	80.00	D
S ➤	NT2K71AA	ATA/MCA Jumper Kit. Jumper Kit used for ATA and MCA (NT2K69AA) when installing on Meridian Modular Telephone with a date code prior to May 6, 1998.	5.00	D
S ➤	NT3G30AA35	Adjustable Stand (M2250/M1250)	270.00	D
S ➤	NT7G10AA	M2250 Attendant Supervisory Module	600.00	D
S	NT9D13AA	M1250/M2250 Attendant Line Cord	40.00	D
S ➤	NTMN19AA	Key Cap Tool (M3905)	25.00	D
S ➤	NTMN80AA	Wall Transformer (M3900 Series)	40.00	D
N ✓ ➤	P0680793	Wall Mount Handset Clip (1 each, for all Meridian Digital Telephones)	1.00	D
S ➤	P0723443	Power Supply Board Cable (M2000 Series)	5.00	D
S	P0729469	DSS-9000 Key Cap Remover Tool	25.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	P0738600	Display Option Cable	5.00	D
S ➤	P0768143	Attendant Administration Overlay	90.00	D
S ➤	P0784503	Top Cover Filler Plate, Black (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D
S ➤	P0784535	Top Cover Filler Plate, Ash (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D
S ➤	P0784593	Top Cover Filler Plate, Gray (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D
S	P0828635	Meridian 1 Attendant PC Blank Brandline Insert (Package of 1). Blank brandline insert which can be used by distributors or customers to customize the name that appears on the Meridian 1 Attendant PC interface unit.	1.50	D
S ➤	P0960326	Rubber Feet (100 each, for all Meridian Digital Telephones)	30.00	D

Documentation

S ✓ § ➤ Δ	NT2F7903	Meridian M3901, 2,3,4 User Guide Release 2, (Package of 5 P0987180) No Charge	No charge	
S ➤ Δ	NT2F79AB	Meridian M3901, 2,3,4 User Guide, Release 2 (Package of 5 P0987180)	20.00	H
S ✓ § ➤ Δ	NT2F8003	Meridian M3905 User Guide (Package of 5 P0907181) No Charge	No charge	
S ✓ ➤ Δ	NT2F80AB	Meridian M3905 User Guide (Package of 5 P0907181)	20.00	H
S ➤ Δ	NT2F81AB	Meridian M3905 Series Quick Reference Guide, Release 2 (Package of 15 P0907178)	28.00	H
S ★ ➤ Δ	NT2F82AB	Meridian M3905 Quick Reference Guide (Package of 15 P0907179)	28.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Message Processing - Applications

Message Processing - Applications

Message Processing products include the following:

- Meridian Mail Card Option, and the Modular Option EC 11 for the Option 11 PBX
- Modular Option EC for Meridian 1 Options 21 - 81
- Meridian Mail Modular GP for SL-100, DMS-100, DMS-10, AT&T, ROLM, PBXs, and AT&T Centrex
- Messenger
- CallPilot
- Message Services Module (MSM) for the SL-100, DMS-100 and AT&T Centrex
- Meridian IVR

Message Services Module (MSM)

The Message Services Module (MSM) is a large stand-alone voice messaging system with supernode packaging and components. It is fully redundant, NEBS- (Network Equipment Building Specification) compliant and Bellcore-Certified.

System Compatibility

This system was introduced beginning with Meridian Mail Release 9 software. The MSM system is compatible with the following switching systems:

- DMS 100
- SL-100
- AT&T 1AEss
- AT&T 5ESS (using a SMDI integration)
- AT&T System 75, 85, and Definity
- Rolm 8000, 9000, 9750, and 9751 (using Meridian Mail Connections integration)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

System Capacity

The system ranges in size from 48 ports to 192 ports and grows in 24-port increments. Hours of storage range from 150 to 1600, growing in 150-hour increments. All storage is shadowed.

Contact

For information on pricing and ordering MSM system packages, please contact:

Nortel Inc.
SL100 Sales Support
2221 Lakeside Boulevard
Mail Stop 1201
Richardson, Texas 75082

Meridian Mail Release 13

Summary of Features

The following is a summary of the enhancements offered in Meridian Mail Release 13:

Core MM13 Features are:

- 30 Digit RN PIN and Callback Numbers
- Deletion of Unread Messages
- Disable Message Reception
- Message Sort Order
- MMUI Volume Control
- MMUI Speed Control Enhancement
- Multiple MWI DNs
- Nested SDLs
- RN Class of Service
- Personal Mailbox Administration (PMA)

Web-PC Features are:

Web OA&M

Personal Mailbox Administration (PMA)

SNMP Support

Text Notification

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Mail Upgrades/Expansions

Charges for Release Updates and Feature Additions

To determine the appropriate software update charge for a release update and/or feature addition, identify the applicable order codes and pricing. In addition, the SERV0019 software service transaction fee of $500 must be included. When ordering port and/or node expansions, the no charge Meridian Mail hardware service keycode SERV0020 must be ordered. The Meridian Mail Site Profile must be included in all orders.

Service Transaction Fees

Only one Meridian Mail software service transaction fee is applied per processed order. An order may include one or more of a requested feature, service or release update.

Meridian Mail software service transactions may include one or more of the following services:

Example of updates/feature additions/deletions

Service	Example
Release/Issue Update	Release 12 to Release 13
Feature Addition/Deletion	Adding "Networking"
Material Replacement	Worn or damaged tape

Examples of Meridian Mail Upgrades

Adding a New Feature

An end-user with a Meridian Mail Release 13 system wishes to purchase Networking software.

1. Choose the Networking Software (SWXXXXX)
2. Add the Software Service Transaction Fee
3. Calculate:

$ SWXXXX	Networking Software RTU Fee
(+) $SERV0019	Software Service Transaction Fee
$ YYYY	Total CLP

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Updating Release and Adding a New Feature

An end-user with a Meridian Mail Release 10 system wishes to purchase Release 13 and add the Networking software.

1. Choose the "Release 10 to 13" order code (NTXXXXXX)
2. Add the Networking Software (SWXXXXX)
3. Add the Software Service Transaction Fee
4. Calculate:

$ NTXXXXXX	Software/Hardware Upgrade Fee
(+)$ SWXXXXX	Networking Software RTU Fee
(+)$ SERV0019	Software Service Transaction Fee
$ YYYY	Total CLP

Expanding Ports

An end-user with a Meridian Mail Release 13 system wishes to purchase eight additional ports without any additional features.

1. Choose the eight-port Voice Processing Package (NTXXXXXX)
2. Add the Hardware Key Code Service
3. Calculate:

$ NTXXXXXX	8-port Voice Processing Package
(+) $SERV0020	Hardware Key Code Service
$ YYYY	Total CLP

Updating Release and Adding a New Feature

An end-user with a Meridian Mail Release 8 system wishes to purchase Release 12 and add Networking software.

1. Choose "FROM" Release 8 "TO" Release 12 order code (U72XX)
2. Calculate:

$ SWXXXX	Networking Software RTU Fee
(+)$ U72XX	Software Update Fee
(+)$SERV0019	Software Service Transaction Fee
$ YYYY	Total CLP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Mail Factory Upgrade Service

In response to distributor requests for assistance with bringing new products to market, Nortel introduces a service solution for distributors to utilize when upgrading existing Meridian Mail customers. Meridian Mail systems are sophisticated products that require previous training and experience. Meridian Mail Factory Upgrade Services can help you upgrade your customers to the latest Meridian Mail release knowing that Nortel has partnered with you to make the upgrade successful.

Meridian Mail Upgrade Service

This program is designed to help you, the distributor, deliver service excellence and increase your customer satisfaction. You need to capture the current customer information on a site profile form, send it to our factory service engineer for scheduling, then send a copy of the sites Meridian Mail database on tape accompanied with a purchase order and site profile into Santa Clara. Upon receipt of the tape a factory-service engineer performs the release upgrade and/or functionality expansion on the software at the Santa Clara manufacturing facility. The tape containing the updated software is then returned to site personnel for installation at the end-user site. The factory-service engineer is available for any follow-up questions or concerns during the installation of updated tapes.

Note: Release-to-release upgrades are only made to the latest release of the Meridian Mail software. This upgrade service covers only the Meridian Mail software. The distributor still needs to handle any hardware upgrades and/or changes.

System Port Charge for Meridian Mail Upgrades

The Santa Clara manufacturing facility performs the Meridian Mail software release-to-release upgrade for customers. The following charges are based on the physical port count of the current Meridian Mail system used.

Order Code	Ports	CLP
SV000099	2-24	$2,000
SV000100	25-48	$4,000
SV000101	49-64	$6,000
SV000102	65-96	$8,000

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Mail Factory Upgrade Service

The Santa Clara manufacturing facility performs software functionality enhancements or modifications for the customer. Factory upgrade service includes the following expansions.

- Software expansion of nodes and ports
- Software expansion of storage and languages
- Features

The following table lists the order information for Meridian Mail Factory Upgrade Service.

Order code	Description	CLP
SV000098	Meridian Mail Factory Upgrade Service	$200 (Note)
Note 1: The $200 charge is per functionality or modification required, and is not to exceed $1,000 regardless of the required functionality additions or modifications. 0All changes are in addition to Right-to-Use (RTU) and software service transaction fees, etc.		

Example of Meridian Mail Factory Upgrade Service

Upgrading to a current Meridian Mail release with a node expansion and functionality addition.

An end user with a Meridian Mail Release 7 system wishes to upgrade to Release 13 and add the Networking feature as well as expand their system from three nodes to four nodes and currently they have 36 ports.

Order	Description	Amount	Purpose
SV000100	Meridian Mail 25-48 Upgrade Service Charge	$4,000.00	For 36 ports
SV000098	Meridian Functionality Service Fee	800.00	For the following items at $200.00 each: - networking - node expansion - upgrade (Rls 7 to Rls 8) - upgrade (Rls 8 to Rls 13)
	Total	$4,800.00	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Configuration Rules for the MC Upgrades Tool

When the distributor is configuring a Meridian Mail Upgrade order, ask the distributor if they would like to purchase a Meridian Mail Factory Upgrade Service package.

If the customer is doing any of the following items: expansions, additions or software upgrades, use the calculations above to determine the Upgrade Service total.

For example, a customer wants to upgrade the following items:

- Upgrade from Release 5 to Release 13
- Add a node
- Expand the number of ports from eight to 12 ports

The upgrade is as follows:

Upgrade	Amount
Release 5 to Release 7	$200.00
Release 7 to Release 8	200.00
Release 8 to Release 13	200.00
Port expansion	200.00
Node expansion	200.00
SV000099 for eight ports	2,000.00
Total	$3,000.00

Meridian Mail Platform Migration

For detailed information on current migration programs, refer to your Meridian 1 Marketing Programs. A platform migration may be used to migrate between Meridian Mail hardware platforms due to increased capacity, ports/storage, or to take advantage of current software/hardware technology.

CallPilot

CallPilot Release 1.06

The order codes that appear in this section are unique to CallPilot Release 1.06. These codes should be used to order CallPilot 1.06 systems until CallPilot Release 1.07 codes are removed from controlled release. Please refer to Sales & Marketing Bulletin 1271-G Rev 1 for detailed ordering procedures using these codes.

S ✓ ➤ Δ	NTRG11AB	CallPilot Basic Administration Documentation Package - English	115.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤ Δ	NTRG11AC	CallPilot Basic Administration Documentation Package - English	500.00	H
S ✓ ➤	NTUB14AB	CallPilot 1.06 Keycode Package	15.00	D
S ✓ ➤	NTUB60AB	CallPilot MPB-16	2,500.00	D
S ✓ ➤	NTZE01AA	CallPilot IPE Base System - English	20,000.00	D
S ✓ ➤	NTZE02AA	CallPilot Tower System - English	45,000.00	D
S ✓ ➤	NTZE03AA	CallPilot Rack Mount System DC - English	75,000.00	D
S ✓ ➤	NTZE04AA	CallPilot Rack Mount System AC - English	75,000.00	D
S ✓ ➤	NTZE08AA	CallPilot Storage Expansion - 10 hours	500.00	D
S ✓ ➤	NTZE08BA	CallPilot Storage Expansion - 50 Hours	1,250.00	D
S ✓ ➤	NTZE10AA	CallPilot FAX Capability -20 Users	1,000.00	D
S ✓ ➤	NTZE10BA	CallPilot FAX Capability - 50 Users	1,500.00	D
S ✓ ➤	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	2,000.00	D
S ✓ ➤	NTZE11BA	CallPilot Desktop Messaging Capability - 50 Users	3,500.00	D
S ✓ ➤	NTZE12AA	CallPilot Speech Activated Messaging Capability - 20 Users	3,000.00	D
S ✓ ➤	NTZE12BA	CallPilot Speech Activated Messaging Capability - 50 Users	4,500.00	D
S ✓ ➤	NTZE13AA	CallPilot Networking, 1 to 24 Channels	3,000.00	D
S ✓ ➤	NTZE13BA	CallPilot Networking, 25 to 48 Channels	2,000.00	D
S ✓ ➤	NTZE13CA	CallPilot Networking, 49 to 96 Channels	3,000.00	D
S ✓ ➤	NTZE14AA	CallPilot NMS Networking, 1 to 24 Channels	7,000.00	D
S ✓ ➤	NTZE14BA	CallPilot NMS Networking, 25 to 48 Channels	4,000.00	D
S ✓ ➤	NTZE14CA	CallPilot NMS Networking, 49 to 96 Channels	4,000.00	D
S ➤	NTZE16AA	CallPilot Additional Prompt Language	600.00	D
S ✓ ➤	NTZE16BA	CallPilot Speech Activated Messaging Vocabulary	600.00	D
S ✓ ➤ Δ	NTZE25AA	CallPilot Conversion 4 Voice Channels to 4 Fax Channels	No charge	
S ✓ ➤ Δ	NTZE25BA	CallPilot Conversion 4 Voice Channels to 2 Speech Channels	No charge	
S ✓ ➤ Δ	NTZE26AA	CallPilot Conversion 4 Fax Channels to 4 Voice Channels	No charge	
S ✓ ➤ Δ	NTZE27BA	CallPilot Conversion 2 Speech Channels to 4 Voice Channels	No charge	

CallPilot Systems

S ★ Δ	NTZE4004	CallPilot Bulk - System Order Code	No charge	
S ★ ➤ ⊗	NTZE80AA	CallPilot 1.07 IPE Base Package	9,000.00	D
S ★ ➤ ⊗	NTZE81AA	CallPilot 1.07 702t Base Package	21,000.00	D
S ★ ➤ ⊗	NTZE82AA	CallPilot 1.07 1001rp DC Base Package	51,000.00	D
S ★ ➤ ⊗	NTZE83AA	CallPilot 1.07 1001rp AC Base Package	51,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Systems Software

Meridian 1 Option 11C Systems

Meridian 1 Option 11C systems equipped with General Business or Enhanced Business Features Set must include NTSF8615 on the order. If Enterprise or NAS/VNS Features set is equipped, NTSF8615 is not required.

Meridian 1 Option 51C/61C/81/81C Systems

When CallPilot is equipped on an Option 51C/61C/81/81C, the system S0005915 CallPilot Connectivity Features Package must be included on the order.

CallPilot Hardware

Expansion Hardware

S ➤	NTRB18CA	MGate Card	500.00	D
S ✓ ➤	NTRH01AA	CallPilot MPC-8	500.00	D
S ✓	NTRH20BA	MPB 16-4	2,300.00	D
S ➤	NTUB57AB	CallPilot MGate Kit	500.00	D

LAN Connection Hardware

S ✓ ➤	NTRH9010	PCI Token Ring Network Card	520.00	D
S ✓ ➤	NTRH9036	CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack	250.00	D
S ✓ ➤	NTRH9069	Transceiver (MAU to 10 Base T)	95.00	D
S ✓ ➤	NTUB51AA	CallPilot Token Ring LAN Kit - IPE Systems	870.00	D
S ✓ ➤	NTUB52AA	CallPilot Ethernet LAN Connection Kit - IPE Systems	415.00	D
S ★ ➤ ⊗ Δ	NTUB71AA	CallPilot 1.07 GB, 200i Token Ring LAN Option	No charge	
S ★ ➤ ⊗ Δ	NTUB72AA	CallPilot 1.07 GB, 200i Ethernet LAN Option	No charge	
S ★ ➤ ⊗ Δ	NTUB73AA	CallPilot 1.07 GB, 700/1000 Series Token Ring LAN Option	No charge	
S ★ ➤ ⊗ Δ	NTUB74AA	CallPilot 1.07 GB, 700/1000 Series Ethernet LAN Option	No charge	

Miscellaneous Hardware

S ★	A0620530	Modem for SMDI Link in T1 Application	2,450.00	D
S ✓ ➤	A0676108	DC Power Supply for Rack Cabinet	1,025.00	D
S ✓ ➤	A0677506	Dry Clean Cartridge	150.00	D
S ✓ ➤	A0677508	13GB Data Cartridge	170.00	D
S ✓	A0681164	Alarm Status Module	1,180.00	D
S ✓ ➤	A0681326	Hot-Swap Fan Assembly	580.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	A0681873	CallPilot Power Supply AC - Rack System	3,500.00	D
S ✓	A0683743	Video Card Adapter	310.00	D
S ➤	A0684753	68 pin Wide SCSI Cable	160.00	H
S ✓	A0723663	48V DC 400W Load Sharing Hot Swap Power Supply. 48V DC 400W load sharing hot swap power supply	3,580.00	D
S ✓ ➤	A0725949	DC Power Cable for PS400-48 Power Supply	160.00	D
S ✓	A0729069	M/M Wide-Nar SCSI Adapter	150.00	D
S ✓	A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems	80.00	D
S ➤	A0735349	128 MB DIMM	2,100.00	D
S ✓	A0738130	128MB DIMM	800.00	D
S ✓ Δ	A0741561	300W Power Supply	155.00	H
S	A0741567	Fan Module Assembly	200.00	D
S ✓ Δ	A0741576	Fan Assembly	10.00	H
S ✓ ➤	A0744456	CallPilot 128 MB DIMM	1,090.00	D
S ✓	A0766163	CallPilot DSE Extender Cable - 100 Ft.	200.00	D
S ✓ ➤	A0766182	Dual Pentium II CPU	20,000.00	D
S ✓ ➤	A0766997	Wide SCSI Terminator	55.00	D
S ✓ ➤	A0769312	SCSI Adapter	50.00	D
S ✓ ➤	A0780247	Data Cartridge	85.00	D
S ✓	A0797941	Rack Rails	340.00	D
S	A0802022	128 MB SDRAM	2,300.00	D
S	A0803022	128 MB SDRAM	3,400.00	D
S ✓	A0805092	Pentium III SBC 500MHz CPU	2,600.00	D
S ✓ ➤	A0805434	Power Supply AC - 500 Watts	1,750.00	D
S ★	A0813446	256 MB SDRAM	2,050.00	D
S ✓	NTRH0911	Cable Assembly, Breakout Box InterconnectCable, 15 Ft.	150.00	D
S ✓ ➤	NTRH09AA	Breakout Panel Assembly	370.00	D
S ✓ ➤	NTRH1405	CallPilot Internal Ethernet Cabling (IPE System)	30.00	D
S ✓ ➤	NTRH1406	CallPilot Token Ring Cabling (IPE System)	125.00	D
S ✓	NTRH14AA	200 Series Base System Assembly	3,620.00	D
S ✓ ➤	NTRH16BA	Hard Drive Data Cable	35.00	D
S ➤	NTRH2010	CallPilot MGate Cable - 20 Ft.	115.00	D
S ➤	NTRH2011	CallPilot MPB-16 Cable	80.00	D
S ★	NTRH21CA	MPB 16-2T Carrier Card	1,410.00	D
S	NTRH8003	SCSI RAID Drivers	12.00	D
S	NTRH8032	1001rp PII SBC BIOS 1001rp AC and DC	3.00	D
S	NTRH8042	Pentium III BIOS	3.00	D
S ➤	NTRH9003	4GB SCSI Hot Swap Disk Drive	2,260.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTRH9011	14" SVGA Color Monitor	380.00	D
S ✓ † ➤	NTRH9013	OIVR 2 x Hardware - Keyboard	60.00	D
S ✓ ➤	NTRH9014	Three Button Mouse	90.00	D
S ✓ ➤	NTRH9016	External Modem 33.6	280.00	D
S ✓ ➤	NTRH9032	700 Series DC Power Converter	3,000.00	D
S ✓ ➤	NTRH9035	IDE CD-ROM Drive	275.00	H
S ➤	NTRH9037	CallPilot CD ROM DRIVE	820.00	D
S ✓	NTRH9038	CallPilot External SCSI Tape Drive, 4GB (IPE System)	1,900.00	D
S ✓ ➤	NTRH9039	CallPilot Ethernet Adaptor PCMCIA (IPE System)	390.00	D
S ✓ ➤	NTRH9040	Callpilot Token Ring Adapter PCMCIA (IPE System)	750.00	D
S ➤	NTRH9048	101 Enhanced Keyboard	560.00	D
S ✓ ➤	NTRH9049	4 GB IDE Drive for the 200i System	370.00	D
S ✓	NTRH9053	9 GB Disk Hot Swap	1,100.00	D
S ✓	NTRH9054	9 GB SCSI Disk	1,120.00	D
S ✓ ➤	NTRH9055	CallPilot ATA Drive with Programmed Flash	300.00	D
S ✓	NTRH9057	VTG VB2002	5,000.00	D
S ✓	NTRH9059	VTG VB2007	5,000.00	D
S ★	NTRH9060	VTG VB2009	5,000.00	D
S ★	NTRH9065	Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card	3,550.00	D
S ✓ ➤	NTRH9068	Dual Pentium III SBC	6,950.00	D
S ✓ ➤	NTRH9069	Transceiver (MAU to 10 Base T)	95.00	D
S ✓ ➤	NTUB16AA	CallPilot External Modem Kit	300.00	D
S ✓ ➤	NTUB53AA	CallPilot External Tape Drive - IPE Systems	2,240.00	D
S ✓ ➤	NTUB54AA	CallPilot Recovery Kit - IPE	1,060.00	D
S ✓ ➤	NTUB55AA	CallPilot Tower/Rack Internal Tape Drive Kit	5,200.00	D
S ✓ ➤	NTUB56AA	CallPilot 14" Monitor Kit	600.00	D
S ✓ ➤	NTUB59AA	CallPilot CD ROM Drive	700.00	D
S ★ ➤ ⊗ Δ	NTUB81AA	DSP Connectivity Package - Digitel	No charge	
S ★ ➤ ⊗ Δ	NTUB83AA	DSP Connectivity Option - MSL-100	No charge	
S ➤	NTZE24AA	CallPilot IPE Spares Package	10,000.00	D
S ➤	NTZE24BA	CallPilot Tower Spares Package	15,000.00	D
S ➤	NTZE24CA	CallPilot Rack Mount AC Spares Package	50,000.00	D
S ➤	NTZE24DA	CallPilot Rack Mount DC Spares Package	50,000.00	D
S ✓ ➤ Δ	NTZE29AA	CallPilot to Meridian 1 Integration	500.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description		CLP	Distr. Disc.
S ★ ➤ Δ	NTZE29BA	CallPilot to Lucent (2 Wire) Integration		5,000.00	D
S ★ ➤ Δ	NTZE29CA	CallPilot to Siemens/Rolm Integration		4,000.00	D
S ★ ➤ Δ	NTZE29DA	CallPilot to Mitel Integration		4,000.00	D
S ★ ➤ Δ	NTZE29EA	CallPilot to Nortel SL-100 Integration		5,000.00	D
S ➤	NTZE30AA	CallPilot Integration Suite	∞	No charge	
S ★ ➤ ⊗ Δ	NTZE99BA	CallPilot 1.07 GB, DSE Connectivity Option - Lucent 2 Wire		No charge	
S ★ ➤ ⊗ Δ	NTZE99CA	CallPilot 1.07 GB, DSE Connectivity Option - Siemens/ROLM		No charge	
S ★ ➤ ⊗ Δ	NTZE99DA	CallPilot 1.07 GB, DSE Connectivity Option - Mitel		No charge	
S ★ ➤ ⊗ Δ	NTZE99EA	CallPilot 1.07 GB, T1 (SL-100) Connectivity Option - SL-100		No charge	
S ✓ ➤	P0684414	Hard Drive Power Cable		17.00	D
S ★	P0913184	CallPilot 1.07 Feature Operations Video		115.00	H

Cables

S ✓ ➤	A0601464	Modem Cable, 10 Ft. DB9 Female to DB25 Male		25.00	D
S ✓ ➤	A0648372	4 Ft. Ethernet Cable, Category 5		10.00	D
S ✓ ➤	A0648374	2 Ft. Ethernet Cable, Category 5		10.00	D
S ✓ ➤	A0648375	7 Ft. Ethernet Cable, Category 5		10.00	D
S ✓ ➤	A0648377	10 Ft. Ethernet Cable, Category 5		10.00	D
S ✓ ➤	A0648378	15 Ft. Ethernet Cable, Category 5		10.00	D
S ✓ ➤	A0648379	25 Ft. Ethernet Cable, Category 5		15.00	D
S	A0684761	IDE Cable to CD ROM 702t/1001rp		30.00	D
S ✓	A0684822	F/F Wide to Narrow SCSI Cable Adapter		140.00	D
S ✓	A0685305	Floppy Cable		35.00	D
S ✓	A0741572	Floppy Cable		35.00	D
S ✓	A0769310	14 Foot, Shielded Ethernet Cable		25.00	D
S	A0772567	Wide SCSI Cable		580.00	D
S ★	A0788107	T1 2 Pair Cable with RJ48 Connector		80.00	D
S ✓ ➤	A0788129	Shielded 9-Drop Wide SCSI Cable		320.00	D
S ✓	A0788131	9 Drop SC Bus Cable		30.00	D
S ★	A0788198	VTG Adapter Cable		170.00	D
S ✓	A0806019	IDE Cable to CD ROM		180.00	D
S ✓	NTRH0910	Break Interconnect Cable (6 Ft.)		150.00	D
S ★	NTRH0914	Analog Loop Start Cable		170.00	D
S ★	NTRH0915	CT to CT Bus Cable		90.00	D
S ✓ ➤	NTRH1407	CallPilot Intermediate SCSI Cable		180.00	D
S ✓ ➤	NTRH1408	CallPilot Intermediate SCSI Cable		110.00	D
S ✓ ➤	NTRH1409	CallPilot Intermediate SCSI Cable		110.00	D
S	NTRH2012	CallPilot MGate Cable - 20ft		300.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NTRH2013	Dual DSX30XV Interconnect Cable	500.00	D

Raid Kits

S ✓ ➤	NTRH9007	SCSI RAID Controller	2,180.00	H
S ✓ ➤	NTUB58AA	CallPilot 700 Series RAID Kit	5,000.00	D

CallPilot Software

S ★ ➤	NTRH8101	Application Server Master Driver CD Bootable	10.00	H
S ★	NTUB20AD	CallPilot 1.07 IPE Base Server Software Assembly	70.00	D
S ★	NTUB22AD	CallPilot 1.07 Base Software Assembly	85.00	H
S ★ ➤	NTUB44BC	CallPilot 1.07 Language Prompts CD Sets (3)	30.00	D

Expansion Software

S ★ ➤ Δ	NTUB80AA	CallPilot 1.07 GB, MPC-8 - Expand Option (No Charge)	No charge	

Channels

S ✓ ➤	NTZE07AA	CallPilot 4 Voice Channels	8,000.00	D
S ✓ ➤	NTZE07BA	CallPilot 2 FAX Channels	8,000.00	D
S ✓ ➤	NTZE07CA	CallPilot 1 Speech Activated Messaging Channel	8,000.00	D
S ★ ➤	NTZE07EA	CallPilot 2 Voice Channels	4,000.00	D

Storage Expansions Per Seat Clients

S ★	NTZE19AA	CallPilot Multimedia Mailboxes with Voice - 20 Users	1,000.00	D
S ★	NTZE19BA	CallPilot Multimedia Mailboxes with Voice - 50 Users	2,000.00	D
S ★	NTZE19CA	CallPilot Multimedia Mailboxes with Voice - 100 Users	3,500.00	D
S ★	NTZE19DA	CallPilot Multimedia Mailboxes with Voice - 200 Users	6,000.00	D
S ★	NTZE19EA	CallPilot Multimedia Mailboxes with Voice - 500 Users	12,500.00	D
S ★	NTZE19FA	CallPilot Multimedia Mailboxes with Voice - 1000 Users	22,000.00	D
S ★	NTZE19GA	CallPilot Multimedia Mailboxes with Voice - 5000 Users	100,000.00	D
S ★	NTZE19HA	CallPilot Multimedia Mailboxes with Voice - 10,000 Users	165,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
FAX Users				
S ✓ ➤	NTZE10CA	CallPilot FAX Capability - 100 Users	2,500.00	D
S ✓ ➤	NTZE10DA	CallPilot FAX Capability - 200 Users	4,500.00	D
S ✓ ➤	NTZE10EA	CallPilot FAX Capability - 500 Users	8,000.00	D
S ✓ ➤	NTZE10FA	CallPilot FAX Capability - 1000 Users	14,000.00	D
S ★ Δ	NTZE10HA	CallPilot Fax Capability - 20 Users	1,000.00	D
S ★	NTZE10JA	CallPilot 5000 Fax Users	50,000.00	D
S ★ Δ	NTZE10KA	CallPilot Fax Capability - 200 Users	4,500.00	D
Desktop Messaging Users				
S ✓ ➤	NTZE11CA	CallPilot Desktop Messaging Capability - 100 Users	6,000.00	D
S ✓ ➤	NTZE11DA	CallPilot Desktop Messaging Capability - 200 Users	11,000.00	D
S ✓ ➤	NTZE11EA	CallPilot Desktop Messaging Capability - 500 Users	25,000.00	D
S ✓ ➤	NTZE11FA	CallPilot Desktop Messaging Capability - 1000 Users	40,000.00	D
S ★ Δ	NTZE11HA	CallPilot Desktop Messaging Capability - 20 Users	2,000.00	D
S ★	NTZE11JA	CallPilot Desktop Messaging Capability - 5000 Users	125,000.00	D
S ★ Δ	NTZE11KA	CallPilot Desktop Messaging Capability - 200 Users	11,000.00	D
Speech Activated Messaging Users				
S ✓ ➤	NTZE12CA	CallPilot Speech Activated Messaging Capability - 100 Users	7,500.00	D
S ✓ ➤	NTZE12DA	CallPilot Speech Activated Messaging Capability - 200 Users	14,000.00	D
S ✓ ➤	NTZE12EA	CallPilot Speech Activated Messaging Capability - 500 Users	32,000.00	D
S ✓ ➤	NTZE12FA	CallPilot Speech Activated Messaging Capability - 1000 Users	53,000.00	D
S ★ Δ	NTZE12HA	CallPilot Speech Activated Messaging Capability - 20 Users	3,000.00	D
S ★	NTZE12JA	CallPilot Speech Activated Messaging Capability - 5000 Users	130,000.00	D
S ★ Δ	NTZE12KA	CallPilot Speech Activated Messaging Capability - 200 Users	14,000.00	D
Software Options				
Networking				
S ★	NTZE13DA	CallPilot Networking (EN, AMIS, VPIM) 1 to 96 Channels	8,000.00	D
S ★ ➤	NTZE14DA	CallPilot NMS Networking, 1 to 96 Channels	5,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Network Message Service				
Miscellaneous Software Options				
S ✓	NT3R9501	Software Assembly, Emergency Repair Disks	3.00	D
S	NTRH8025	702t BIOS	10.00	D
S	NTRH8026	702t System Setup Utility	10.00	D
S ✓ ➤	NTRH8027	Windows NT 4.0 OS Recovery CD	10.00	D
S ✓	NTRH8033	Windows NT 4.0 Install Diskette	10.00	D
S ✓	NTUB24AB	CallPilot 1.07 Meridian Mail to CallPilot Migration Tape	50.00	D
S ★ ➤	NTUB40AC	CallPilot 1.07 Server Software CD	10.00	D
S ★ ➤	NTUB41AC	CallPilot 1.07 Administration Client CD	10.00	D
S ★ ➤	NTUB42AC	CallPilot 1.07 Desktop Messaging CD	10.00	D
S ➤	NTUB43AA	CallPilot 1.0 Patch Software	120.00	D
S ★ ➤	NTUB43AC	CallPilot 1.07 PEP Software CD	10.00	D
S ★	NTUB44AC	CallPilot 1.07 Language Prompts CD	15.00	D
S ★ ➤	NTUB45AC	CallPilot 1.07 Web Messaging CD	10.00	D
S ✓ ➤	NTZE15AA	CallPilot Applications Builder FAX Option	3,000.00	D
S ★	NTZE25CA	CallPilot Conversion 4 Voice Channels to 2 Fax Channels	500.00	D
S ★	NTZE25DA	CallPilot Conversion 4 Voice Channels to 1 Speech Channel	500.00	D
S ✓ ➤ Δ	NTZE26BA	CallPilot Conversion 2 Fax Channels to 1 Speech Channel	500.00	D
S ★	NTZE26CA	CallPilot Conversion 2 Fax Channels to 4 Voice Channels	500.00	D
S ✓ ➤ Δ	NTZE27AA	CallPilot Conversion 1 Speech Channel to 2 Fax Channels	500.00	D
S ★	NTZE27CA	CallPilot Conversion 1 Speech Channel to 4 Voice Channels	500.00	D
S ★ ➤	NTZE31AA	IPE CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	80.00	D
S ★ ➤	NTZE31BA	Tower/Rack CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	85.00	D
S ➤ ⊗	NTZE39AA	CallPilot 1.07 to Meridian 1 Integration Software	No charge	
S ★ ➤ ⊗	NTZE39BA	CallPilot 1.07 to Lucent (2 Wire) Integration Software	No charge	
S ★ ➤ ⊗	NTZE39CA	CallPilot 1.07 to Siemens/Rolm Integration Software	No charge	
S ★ ➤ ⊗	NTZE39DA	CallPilot 1.07 to Mitel Integration Software	No charge	
S ★ ➤ ⊗	NTZE39EA	CallPilot 1.07 to SL-100 Integration Software	No charge	
S ★ Δ	NTZE4001	CallPilot 1.07 New System Ordering Code	No charge	
S ★ ➤ Δ	NTZE4002	CallPilot 1.07 Upgrade Ordering Code	No charge	
S ★ Δ	NTZE4003	CallPilot Platform Migration Order Code	No charge	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CallPilot Documentation

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	NT1344AA	Teleset Guide Package - Latin American Spanish	280.00	H
S ★ ➤	NTJR27AA	CallPilot 1.07 Telset User Guide Package - Canadian French	100.00	H
S ★ Δ	NTJR48AA	CallPilot Telset Guide Package (Quantity 10), English	90.00	H
S ★ ➤ ⊗ Δ	NTRG08AD	CallPilot 1.07 IPE (200i) Base Documentation Package	380.00	H
S ★ ➤ ⊗	NTRG09AD	702t Base Documentation Package, English	380.00	H
S ★ ➤ ⊗	NTRG10AD	CallPilot 1.07 1001rp Base Documentation Package, English	380.00	H
S ➤ Δ	NTRG12AA	CallPilot Advanced Administration Documentation Package - English	245.00	H
S Δ	NTRG13AA	CallPilot Telset Guide Package	30.00	H
S ➤ Δ	NTRG13AB	CallPilot Telset Guides, English, Quantity 15	50.00	H
S ➤ Δ	NTRG13BB	CallPilot Telset Guides, French, Quantity 15	70.00	H
S ➤ Δ	NTRG14AA	CallPilot AMIS Networking Documentation Package - English	60.00	H
S ✓ ➤ Δ	NTRG14AC	CallPilot 1.07 Networking Package	100.00	H
S ➤ Δ	NTRG15AA	CallPilot Enterprise Networking Documentation Package - English	60.00	H
S ★ ➤ Δ	NTRG15AC	CallPilot 1.07 Installation and Configuration Guide Package	110.00	H
S ➤ Δ	NTRG16AA	CallPilot VPIM Networking Documentation Package - English	60.00	H
S ★ ➤ Δ	NTRG16AC	CallPilot 1.07 702t Installation and Configuration Guide Package	110.00	H
S ➤ Δ	NTRG17AA	CallPilot NMS Networking Documentation Package - English	60.00	H
S ★ ➤ Δ	NTRG17AC	CallPilot 1.07 1001rp Installation and Configuration Guide	110.00	H
S ➤ Δ	NTRG18AA	CallPilot Integrated AMIS Networking Documentation Package - English	60.00	H
S ➤ Δ	NTRG19AB	CallPilot Documentation CD ROM	35.00	H
S ★ ➤ Δ	NTRG19AC	CallPilot 1.07 Documentation CD-ROM	25.00	H
S ➤ Δ	NTRG19AD	CallPilot 1.06 Documentation CD-ROM	21.00	H
S ➤	NTRG20AA	CallPilot Installation Worksheet Package	20.00	H
S ➤ Δ	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25	100.00	H
S ★ ➤ Δ	NTRG22AC	CallPilot 1.07 Desktop Messaging Quick Reference Guide, Quantity 10	50.00	H
S ➤ Δ	NTRG22BA	Desktop Messaging Quick Reference Guide, Quantity 100	400.00	H
S ➤ Δ	NTRG22CB	Desktop Messaging Quick Reference Guide French - Package of 25	240.00	H
S ➤ Δ	NTRG22DB	Desktop Messaging Quick Reference Guide - French - Package of 100	950.00	H
S ★ ➤ Δ	NTRG22EC	CallPilot 1.07 Desktop Quick Reference Guide Package, French	50.00	H
S	NTUB42AB	CallPilot 1.06 Desktop Messaging CD (English & French)	10.00	D
S ➤	NTUB46AB	CallPilot 1.06 Administration Client CD Assembly	20.00	D
S Δ	NTVB01AA	CallPilot Asia Pacific Language Prompts CD ROM	8.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	NTVB02AA	CallPilot Asia Pacific Desktop Client CD ROM	8.00	H
S Δ	NTVB03AA	CallPilot Asia Pacific Language & Desktop Client CD ROM	8.00	H
S ➤ Δ	P0884895	CallPilot 200 Series Installation Guide	30.00	H
S ➤ Δ	P0884909	702t Installation and Maintenance Guide	50.00	H
S ➤ Δ	P0886124	CallPilot Planning and Engineering Guide	20.00	H
S ➤ Δ	P0886126	CallPilot Basic Administration Guide	10.00	H
S Δ	P0886127	CallPilot Speech Recognition Users Guide	8.00	H
S Δ	P0886128	CallPilot Telset Quick Reference Guide	8.00	H
S Δ	P0886130	CallPilot Advanced Administration Guide - Volume 1	40.00	H
S Δ	P0886132	CallPilot Advanced Administration Guide - Volume 2	35.00	H
S Δ	P0886133	CallPilot Reporter Guide	35.00	H
S Δ	P0886135	CallPilot Applications Builder Guide	35.00	H
S Δ	P0886138	Meridian Mail to Nortel CallPilot Migration Guide	10.00	H
S Δ	P0886141	CallPilot Desktop Messaging - MS Exchange Guide	30.00	H
S Δ	P0886142	CallPilot Desktop Messaging - Lotus Notes Guide	30.00	H
S Δ	P0886143	CallPilot Internet Messaging Guide	30.00	H
S ✓ Δ	P0886144	CallPilot Network Planning Guide	20.00	H
S ✓ Δ	P0886145	CallPilot NMS Installation and Administration Guide	20.00	H
S ✓ Δ	P0886146	CallPilot AMIS Installation and Administration Guide	20.00	H
S ✓ Δ	P0886147	CallPilot Enterprise Networking Installation and Administration Guide	20.00	H
S ✓ Δ	P0886148	CallPilot Integrated AMIS Installation and Administration Guide	20.00	H
S ✓ Δ	P0886149	CallPilot VPIM Networking Package	20.00	H
S ➤ Δ	P0886776	CallPilot 1001rp Installation Guide	30.00	H
S ➤ Δ	P0903073	CallPilot Software Installation Guide	10.00	H
S ➤ Δ	P0903074	CallPilot Maintenance and Diagnostic Guide	20.00	H
S ➤	P0903075	CallPilot 200 Series Installation Guide	35.00	H
S Δ	P0905519	Desktop Messaging for Lotus Notes - Latin American Spanish	110.00	H
S Δ	P0905560	Desktop Messaging for Microsoft Exchange/Outlook - Latin American Spanish	110.00	H
S Δ	P0905610	Multimedia Messaging User Guide - Latin American Spanish	30.00	H
S Δ	P0905622	Multimedia Messaging Quick Reference Card - Latin American Spanish	30.00	H
S ★ ➤ Δ	P0905783	CallPilot 1.07 Installation and configuration Switch Set Up	10.00	H
S ★ Δ	P0905786	CallPilot 1.07 200i Installation and Configuration Server Hardware Guide	30.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ★ Δ	P0905787	CallPilot 702t Installation and Configuration Server Hardware - Part 2	30.00	H
S ➤ Δ	P0905788	CallPilot 1001rp Installation and Configuration Server Hardware	30.00	H
S ★ ➤ Δ	P0905789	CallPilot 1.07 Planning and Engineering Guide	15.00	H
S ★ ➤ Δ	P0905790	CallPilot 1.07 Getting Started Guide	10.00	H
S ★ ➤ Δ	P0905791	CallPilot 1.07 Monitoring and Security for Administrators	22.00	H
S ★ ➤ Δ	P0905796	CallPilot 1.07 Administrators Guide	60.00	H
S ★ ➤ Δ	P0905797	CallPilot 1.07 Client Software Installation	35.00	H
S ★ Δ	P0905798	CallPilot 1.07 Reporter Guide	15.00	H
S ★ ➤ Δ	P0905799	CallPilot 1.07 Applications Builder Guide	50.00	H
S ★ Δ	P0905800	CallPilot 1.07 Meridian Mail to CallPilot Migration Guide	15.00	H
S ★ Δ	P0905810	CallPilot 1.07 Desktop Messaging Software Installation and Maintenance Guide	15.00	H
S Δ	P0905816	Desktop Messaging Guide for MS Exchange - French	15.00	H
S Δ	P0905817	Desktop Messaging Guide for Lotus Notes - French	15.00	H
S Δ	P0907827	CallPilot What's New for Release 1.06	10.00	H
S Δ	P0907828	CallPilot Desktop Messaging for Exchange/Outlook 1.06	20.00	H
S Δ	P0907829	CallPilot Desktop Messaging for Lotus Notes - 1.06	20.00	H
S Δ	P0907831	CallPilot Desktop Messaging for Internet Mail Clients - 1.06	20.00	H
S Δ	P0907840	CallPilot 1001rp Installation and Maintenance Guide - 1.06	30.00	H
S Δ	P0909234	Large Keypad Template	4.00	H
S Δ	P0909235	Small Keypad Template	4.00	H
S Δ	P0909939	CallPilot Advanced Administration Guide, Volume 1 - French	35.00	H
S Δ	P0909940	CallPilot Advanced Administration Guide, Volume 2 - French	35.00	H
S Δ	P0909941	CallPilot Applications Builder Guide	40.00	H
S Δ	P0909947	Basic Administration Guide - French	20.00	H
S ★ Δ	P0914300	Installation Flowchart and Worksheets - Part 1 (English)	20.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Mail Hardware - Option 11C Mini

Base Platform Packages - Meridian Mail Mini

S ✓ ➤	NTTS36AA	External RSM Breakout Assembly (4 RS-232 Ports)	750.00	D
S ★ ➤	NTTS50AA	Meridian Mail Mini Networking Package	1,100.00	D
S ➤	NTZC51BA	2 Full Service Ports - Ports 3 & 4, 7 & 8 or 11 & 12	4,500.00	D
S ✓ § ➤	NTZC57AA	Meridian Mail Release 13 Base Software	1,000.00	D
S ✓ § ➤	NTZC58AA	Meridian Mail Mini Option, 2 Ports, 2 Hours Package	9,750.00	D
S ✓ § ➤	NTZC58BA	Meridian Mail Mini Option, 4 Ports, 5 Hours Package	13,000.00	D
S ✓ § ➤	NTZC58CA	Meridian Mail Mini Option, 8 Ports, 5 Hours Package	22,000.00	D
S ➤	NTZC59AA	Meridian Mail Expanded Storage Software Level 0-1	1,500.00	D
S § Δ	P0906932	Meridian Mail Release 13 Keycode	No charge	

Meridian Mail-Option 11

Language Tapes

S ➤	NT5R36BC	Meridian Mail Master Tape, North American 2 - Release 11.19. Prompt Set Includes: - North American English - American Spanish - Canadian French - Brazilian Portuguese - Message Agent	100.00	D
S ➤	NT5R36CC	Meridian Mail Master Tape, European 1 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Female) - German - Italian - Euro French - Dutch	100.00	D
S ➤	NT5R36DC	Meridian Mail Master Tape, European 2 - Release 11.19. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R36EC	Meridian Mail Master Tape, European 3 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Male) - Arabic - Portuguese - Turkish - Euro Spanish	100.00	D
S ➤	NT5R36FC	Meridian Mail Master Tape, European 4 - Release 11.19. Prompt Set Includes: - North American English - German - Russian - Polish - Czech	100.00	D
S ➤	NT5R36GC	Meridian Mail Master Tape, European 5 - Release 11.19. Prompt Set Includes: - North American English - Hungarian - German	100.00	D
S ➤	NT5R36HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19. Prompt Set Includes: - North American English - Mandarin - Taiwan-Mandarin - Japanese - Korean - Thai	100.00	D
S ➤	NT5R36JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19. Prompt Set Includes: - North American English - Australasian - Mandarin - Taiwan mandarin - Japanese - BBC English	100.00	D
S ➤	NT5R45AC	Meridian Mail Master Tape, North American 1 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -German -Japanese	100.00	D
S ➤	NT5R45BC	Meridian Mail Master Tape, North American 2 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -Message Agent	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R45CC	Meridian Mail Master Tape, European 1 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Female) -German -Italian -Euro French -Dutch	100.00	D
S ➤	NT5R45DC	Meridian Mail Master Tape, European 2 - Release 12.13. Prompt Set Includes: -North American English -Swedish -Norwegian -Danish -Finnish -Irish English	100.00	D
S ➤	NT5R45EC	Meridian Mail Master Tape, European 3 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Male) -Arabic -Portuguese -Turkish -Euro Spanish	100.00	D
S ➤	NT5R45FC	Meridian Mail Master Tape, European 4 - Release 12.13. Prompt Set Includes: -North American English -German -Russian -Polish -Czech	100.00	D
S ➤	NT5R45GC	Meridian Mail Master Tape, European 5 - Release 12.13. Prompt Set Includes: -North American English -German -Hungarian	100.00	D
S ➤	NT5R45HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13. Prompt Set Includes: -North American English -Mandarin -Taiwan-Mandarin -Japanese -Korean -Thai	100.00	D

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R45JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13. Prompt Set Includes: -North American English -Australasian -Mandarin -Taiwan Mandarin -Japanese -BBC English	100.00	D
S ★	NT6R47AD	MM13.13 Master Tape NA 1	100.00	D
S ★	NT6R47BD	MM Release 13.13 Master Tape NA 2	100.00	D
S ★	NT6R47CD	MM Release 13.13 Master Tape Europe 1	100.00	D
S ★	NT6R47DD	MM Release 13.13 Master Tape Europe 2	100.00	D
S ★	NT6R47ED	MM Release 13.13 Master Tape Europe 3	100.00	D
S ★	NT6R47FD	MM Release 13.13 Master Tape Europe 4	100.00	D
S ★	NT6R47GD	MM Release 13.13 Master Tape Europe 5	100.00	D
S ★	NT6R47HD	MM Release 13.13 Master Tape Asia/Pacific 1	100.00	D
S ★	NT6R47JD	MM Release 13.13 Master Tape Asia/Pacific 2	100.00	D
S	NTAK72BT	Meridian Mail, Release 9.66 Master Tape, European 1 Card Option. Prompt Set Includes: - English - Italian - German - French-European - Dutch - UK English (Female)	100.00	D
S	NTAK72CT	Meridian Mail, Release 9.66 Master Tape, European 2 Card Option. Prompt Set Includes: - English - Danish - Finnish - Norwegian - Irish - Swedish	100.00	D
S	NTAK72DT	Meridian Mail, Release 9.66 Master Tape, Asia/Pacific Card Option. Prompt Set Includes: - English - Japanese - Taiwan Mandarin - Mandarin PRC - Australian - Korean	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTAK72GN	Meridian Mail Release 10.11 Master Tape European Card Option. Prompt Set Includes: - North American English - Euro English (Female) - German - Euro French - Dutch	100.00	D
S	NTAK72GT	Meridian Mail, Release 9.66 Master Tape, North American Card Option. Prompt Set Includes: - English - French-Canadian - Spanish-Latin American - Portuegese-Brazil - Japanese - German	100.00	D
S ➤	NTAK72HN	Meridian Mail Release 10.11 Master Tape European 2 Card Option. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D
S ➤	NTAK72KN	Meridian Mail Release 10.11 Master Tape Asia/Pacific Card Option. Prompt Set Includes: - North American English - Japanese - Taiwan Mandarin - Mandarin - Australasian	100.00	D
S	NTAK72KT	Meridian Mail, Release 9.66 Master Tape, European 3 Card Option. Prompt Set Includes: - English - UK English (Male) - Arabic - Portuguese - Spanish-European - Turkish	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTAK72LN	Meridian Mail Release 10.11 Master Tape North American Card Option. Prompt Set Includes: - North American English - Canadian French - Latin American Spanish - Japanese - German	100.00	D
S	NTAK72LT	Meridian Mail, Release 9.66 Master Tape, European 4 Card Option. Prompt Set includes: - English - Russian - Czech - Polish - German	100.00	D
S ➤	NTAK72PN	Meridian Mail Release 10.11 Master Tape European 3 Card Option. Prompt Set Includes: - North American English - European Spanish - Turkish - Arabic - Portuguese - EuroEnglish (Male)	100.00	D

Meridian Mail Hardware-Option 11

Base Platform Packages-Card Option

S § ➤	NTZC49AA	Enhanced Meridian Mail Card Option 4-12 Ports, 5/10/24/54 Hours Package	13,000.00	D

Base System Software

S ✓ § ➤	NTZC57AA	Meridian Mail Release 13 Base Software	1,000.00	D

Optional Features

S ➤	NT8R20AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ➤	NTS130AA	Personal Mailbox Administration	500.00	D
S ➤	NTS132AA	Meridian Mail Option 11 AutoAdmin Software Package - MM13	2,300.00	D
S ➤	NTZD62AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ➤	SW7104B	Meridian Mail Option 11 Fax on Demand Software	2,500.00	D
S ➤	SW7109	Meridian Mail Option 11 Additional Language	600.00	D
S ➤	SW7110	Meridian Mail Option 11 Dual Language Prompt	No charge	
B ➤	SW7111B	Meridian Mail Option 11 HVS Software	1,100.00	D
S ➤	SW7113D	Meridian Mail Option 11 Voice Forms	2,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	SW7114F	Meridian Mail Option 11 Multi-Customer	500.00	D
S ➤	SW7117C	Meridian Mail Option 11 ACCESS Enable Option	No charge	
S ➤	SW7119	Meridian Mail Option 11 AutoAdmin Link Software	1,500.00	D
S ➤ Δ	SW7121	Meridian Mail Option 11 Outcalling	No charge	
S ➤	SW7122	Meridian Mail Option 11 VMUIF	100.00	D

Networking Software

S ➤	NT3R71AA	Meridian Mail Net Gateway	3,000.00	D
S ➤	SW7112B	Meridian Mail Option 11 Networking Software, Release 11 or Later	2,200.00	D
S ➤	SW7115B	Meridian Mail Option 11 AMIS Networking	4,000.00	D
S ➤	SW7116	Meridian Mail Option 11 Network Message Service Software	5,000.00	D
S ➤	SW7123	Meridian Mail Option 11 Network Message Services, Prime Site, Release 11 and Later	3,000.00	D
S ➤	SW7124	Meridian Mail Option 11 Network Message Services, Remote Site, Release 11 and Later	2,000.00	D

Enhanced Reporting Software - Meridian Mail Reporter

S ➤	NTS133AA	Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12, 13)	1,000.00	D
S ➤	NTZD61AA	Meridian Mail Reporter Single Site Software, Option 11 MM13	1,600.00	D
S ➤	NTZD61BA	Meridian Mail Reporter Multi Site Software, Option 11 - MM13	2,100.00	D
S ➤ Δ	SVC1006	Meridian Mail Reporter One Year Extended Service Plan	250.00	H
S ➤	SW7118	Meridian Mail AdminPlus Enable Option	800.00	D

Software Administration Fees

B ➤ Δ	SERV0019	Meridian Mail Software Service Transaction Fee. - Issue/Release Update - Feature Addition/Expanded Storage - Tape Replacement, Additional Languages	500.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
System Expansions				
Ports/Storage				
Ports				
Card Option Pre-Release 9				
S † ➤	NTAK16AB	C25 Voice Processor Card	4,500.00	D
Card Option Release 9 and Later				
S ➤	AS7120	2 Port Full Service Voice Processing Package, Card Option	4,500.00	D
S ➤	AS7121	2 Port Basic Service Voice Processing Package, Card Option	1,400.00	D
S ➤	AS7122	6-8 Port Full Service Voice Processing Expansion Package, Card Option	4,500.00	D
S ➤	AS7123	6-8 Port Basic Service Voice Processing Expansion Package, Card Option	1,400.00	D
S ➤	NTZC50AA	Enhanced Card Option 2 Basic Service Ports - Ports 5 and 6 or 9 and 10	1,400.00	D
S ➤	NTZC50BA	Enhanced Card Option 2 Basic Service Ports - Ports 7 and 8 or 11 and 12	1,400.00	D
S ➤	NTZC51AA	2 Full Services Ports - Ports 5 & 6 or 9 & 10	4,500.00	D
S ➤	NTZC51BA	2 Full Service Ports - Ports 3 & 4, 7 & 8 or 11 & 12	4,500.00	D
Basic to Full Service Upgrade				
S ➤	SW7151	Meridian Mail Card Option Basic to Full Service License Fee Upgrade	1,550.00	D
Hardware Key Code Service				
S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service. - port expansions/node expansions	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Expanded Storage Software

Meridian Mail 11 Card Option storage

Volume storage level	Minimum disk drive	Storage hours
User	• Speed Control • Call Answering without Personal Verification	Message playback control Express Message Sender receives Personal Greeting when Personal Verification turned off
Mobility	Outcalling Pager Enhancements	CLID and MM DN sent - Digital Pagers Voice Message sent - "New" Voice Pagers
Networking Message Management	Broadcast Messaging by Network/NMS site	
System Administration	Meridian Mail AutoAdmin	• Batch processing administration tool (Add/Delete/Change mailboxes via ASCII file) Single Meridian Mail location Centralized Meridian Mail administration tool
—Personal Distribution List editing		

S ➤	SW7102	Meridian Mail Card Option Expanded Storage Software Level 1-2	1,500.00	D
S ➤	SW7103	Meridian Mail Card Option Expanded Storage Software Level 2-3	3,000.00	D
S ➤	SW7140	Meridian Mail Card Option Expanded Storage Software Level 3-4	3,000.00	D

System Upgrades

Software Release Updates

S ✓ ➤	NTZD63AA	Meridian Mail Card Option Release 6 to Release 13 Upgrade	1,700.00	D
S ✓ ➤	NTZD63BA	Meridian Mail Card Option Release 8/9/10/11/12 to Release 13 Upgrade	1,200.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Components				
Component Packages				
S ➤	AS7011	DEC Terminal Package	700.00	H
S ➤	AS7101	HVS Hardware Package	1,300.00	D
S ★	NT6R16AB	PC Pack, Entopia MMP40, Card Option (Any Slot)	10,000.00	D
Component Cards				
S ➤	NTAK13AA	Power Board	980.00	D
S ➤	NTAK14BA	68K Processor Pack	3,600.00	D
S † ➤	NTAK15AB	Digital Voice Processor Card	4,500.00	D
S § ➤	NTMW03AA	4-Port DSP Daughter Card	4,500.00	D
Disk Drives				
S ✓ ➤	NTDK74AB	Card Option 4.5GB Disk Drive	1,200.00	D
Tape Drives/Accessories				
S ➤	A0368760	DC6250 250MB Back Up Tape	50.00	H
S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H
S ➤	A0633585	Tandberg Tape Drive Cleaning Kit	84.00	H
S ➤	A0721902	Tandberg Tape Drive Unit - External	2,800.00	D
B ➤	NTAK30DB	External Tape Drive Package, Tandberg	2,800.00	D
S ➤	NTAK39AB	Tape Drive Wall Mounting Kit	65.00	D
Cables				
S ➤	A0351509	Gender Changer (Female/Female)	20.00	D
S ➤	A0376171	Powell DEC Cable	45.00	H
S ➤	A0379350	25 Pair Double Ended Cable	135.00	D
S ➤	A0379351	25 Pair Single Ended Cable	135.00	D
S	NT6P0122	Network to I/O Cable Assembly	100.00	D
S ✓ ➤	NTAK1305	SCSI Cable (6 Ft.)	115.00	D
S ➤	NTAK36AA	Peripheral Cable Female	90.00	D
S ➤	NTAK37AA	Peripheral Cable Male	90.00	D
S ★	NTTK44AA	RSM Cable	120.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Miscellaneous				
S ➤	A0379412	220V Power Cord	15.00	D
S ➤	A0379673	SCSI Terminator	50.00	D
S ➤	A0383526	VT520 Video Terminal	650.00	H
S	NT6R16AA	Enhanced Processor for Card Option Systems	10,000.00	D
S ➤	NTAK17AB	Meridian Mail Card Option Base Pack, 2-6 Ports	560.00	D
S ➤	NTAK17BB	Meridian Mail Card Option Base Package, 8-12 Ports	560.00	D
B ➤	NTAK18BA	RS232C Service Module	550.00	D
S ➤	NTDK66AB	Meridian Mail Modem Package	200.00	H

Meridian Mail - Option 11 (EC11)

Language Tapes

S ➤	NT5R33AU	Meridian Mail Release 10.11 Master Tape North American. Prompt Set Includes: - North American English - Canadian French - German - Latin American Spanish - Japanese	100.00	D
S ➤	NT5R33CU	Meridian Mail Release 10.11 Master Tape European 1. Prompt Set Includes: - North American English - Euro English (Female) - German - Euro French - Dutch - Italian	100.00	D
S ➤	NT5R33DU	Meridian Mail Release 10.11 Master Tape European 2. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D
S ➤	NT5R33FU	Meridian Mail Release 10.11 Master Tape European 4. Promp Set Includes: - North American English - Hungarian - German - Russian	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R33GU	Meridian Mail Release 10.11 Master Tape Asia/Pacific. Prompt Set Includes: - North American English - Japanese - Mandarin - Taiwan Mandarin - Australasian English	100.00	D
S ➤	NT5R36BC	Meridian Mail Master Tape, North American 2 - Release 11.19. Prompt Set Includes: - North American English - American Spanish - Canadian French - Brazilian Portuguese - Message Agent	100.00	D
S ➤	NT5R36CC	Meridian Mail Master Tape, European 1 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Female) - German - Italian - Euro French - Dutch	100.00	D
S ➤	NT5R36DC	Meridian Mail Master Tape, European 2 - Release 11.19. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D
S ➤	NT5R36EC	Meridian Mail Master Tape, European 3 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Male) - Arabic - Portuguese - Turkish - Euro Spanish	100.00	D
S ➤	NT5R36FC	Meridian Mail Master Tape, European 4 - Release 11.19. Prompt Set Includes: - North American English - German - Russian - Polish - Czech	100.00	D
S ➤	NT5R36GC	Meridian Mail Master Tape, European 5 - Release 11.19. Prompt Set Includes: - North American English - Hungarian - German	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R36HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19. Prompt Set Includes: - North American English - Mandarin - Taiwan-Mandarin - Japanese - Korean - Thai	100.00	D
S ➤	NT5R36JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19. Prompt Set Includes: - North American English - Australasian - Mandarin - Taiwan mandarin - Japanese - BBC English	100.00	D
S ➤	NT5R45AC	Meridian Mail Master Tape, North American 1 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -German -Japanese	100.00	D
S ➤	NT5R45BC	Meridian Mail Master Tape, North American 2 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -Message Agent	100.00	D
S ➤	NT5R45CC	Meridian Mail Master Tape, European 1 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Female) -German -Italian -Euro French -Dutch	100.00	D
S ➤	NT5R45DC	Meridian Mail Master Tape, European 2 - Release 12.13. Prompt Set Includes: -North American English -Swedish -Norwegian -Danish -Finnish -Irish English	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R45EC	Meridian Mail Master Tape, European 3 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Male) -Arabic -Portuguese -Turkish -Euro Spanish	100.00	D
S ➤	NT5R45FC	Meridian Mail Master Tape, European 4 - Release 12.13. Prompt Set Includes: -North American English -German -Russian -Polish -Czech	100.00	D
S ➤	NT5R45GC	Meridian Mail Master Tape, European 5 - Release 12.13. Prompt Set Includes: -North American English -German -Hungarian	100.00	D
S ➤	NT5R45HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13. Prompt Set Includes: -North American English -Mandarin -Taiwan-Mandarin -Japanese -Korean -Thai	100.00	D
S ➤	NT5R45JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13. Prompt Set Includes: -North American English -Australasian -Mandarin -Taiwan Mandarin -Japanese -BBC English	100.00	D
S ★	NT6R47AD	MM13.13 Master Tape NA 1	100.00	D
S ★	NT6R47BD	MM Release 13.13 Master Tape NA 2	100.00	D
S ★	NT6R47CD	MM Release 13.13 Master Tape Europe 1	100.00	D
S ★	NT6R47DD	MM Release 13.13 Master Tape Europe 2	100.00	D
S ★	NT6R47ED	MM Release 13.13 Master Tape Europe 3	100.00	D
S ★	NT6R47FD	MM Release 13.13 Master Tape Europe 4	100.00	D
S ★	NT6R47GD	MM Release 13.13 Master Tape Europe 5	100.00	D
S ★	NT6R47HD	MM Release 13.13 Master Tape Asia/Pacific 1	100.00	D
S ★	NT6R47JD	MM Release 13.13 Master Tape Asia/Pacific 2	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NTAK72BT	Meridian Mail, Release 9.66 Master Tape, European 1 Card Option. Prompt Set Includes: - English - Italian - German - French-European - Dutch - UK English (Female)	100.00	D
S	NTAK72CT	Meridian Mail, Release 9.66 Master Tape, European 2 Card Option. Prompt Set Includes: - English - Danish - Finnish - Norwegian - Irish - Swedish	100.00	D
S	NTAK72DT	Meridian Mail, Release 9.66 Master Tape, Asia/Pacific Card Option. Prompt Set Includes: - English - Japanese - Taiwan Mandarin - Mandarin PRC - Australian - Korean	100.00	D
S	NTAK72GT	Meridian Mail, Release 9.66 Master Tape, North American Card Option. Prompt Set Includes: - English - French-Canadian - Spanish-Latin American - Portuegese-Brazil - Japanese - German	100.00	D
S	NTAK72KT	Meridian Mail, Release 9.66 Master Tape, European 3 Card Option. Prompt Set Includes: - English - UK English (Male) - Arabic - Portuguese - Spanish-European - Turkish	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NTAK72LT	Meridian Mail, Release 9.66 Master Tape, European 4 Card Option. Prompt Set includes: - English - Russian - Czech - Polish - German	100.00	D
S ➤	NTAK72QN	Meridian Mail Release 10.11 Master Tape European 4 Card Option. Promp Set Includes: - North American English - Hungarian - German - Russian	100.00	D

Meridian Mail Hardware - Option 11 - EC11

Base Platform Packages - EC11

S ➤	SY7210	Enhanced Meridian Mail EC11 8-24 Port, 11/24/36/54/100/200 Hour Package	2,900.00	D
S ➤	SY7211	Enhanced Meridian Mail EC11 24-48 port, 26/54/84/114/200/ 400 Hour Package	15,100.00	D

Base System Software

S ➤	NTZC57BA	Meridian Mail EC11 Base Software, Release 13	2,000.00	D

Optional Features

S ➤	NT8R20AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ➤	NTS130AA	Personal Mailbox Administration	500.00	D
S ➤	NTS132AA	Meridian Mail Option 11 AutoAdmin Software Package - MM13	2,300.00	D
S ➤	NTZD62AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ➤	SW7007	Secured Messaging Software	2,200.00	D
S ➤	SW7104B	Meridian Mail Option 11 Fax on Demand Software	2,500.00	D
S ➤	SW7109	Meridian Mail Option 11 Additional Language	600.00	D
S ➤	SW7110	Meridian Mail Option 11 Dual Language Prompt	No charge	
B ➤	SW7111B	Meridian Mail Option 11 HVS Software	1,100.00	D
S ➤	SW7113D	Meridian Mail Option 11 Voice Forms	2,000.00	D
S ➤	SW7114F	Meridian Mail Option 11 Multi-Customer	500.00	D
S ➤	SW7117C	Meridian Mail Option 11 ACCESS Enable Option	No charge	
S ➤	SW7119	Meridian Mail Option 11 AutoAdmin Link Software	1,500.00	D
S ➤ Δ	SW7121	Meridian Mail Option 11 Outcalling	No charge	
S ➤	SW7122	Meridian Mail Option 11 VMUIF	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Networking Software				
S ➤	NT3R71AA	Meridian Mail Net Gateway	3,000.00	D
S ➤	SW7112B	Meridian Mail Option 11 Networking Software, Release 11 or Later	2,200.00	D
S ➤	SW7115B	Meridian Mail Option 11 AMIS Networking	4,000.00	D
S ➤	SW7116	Meridian Mail Option 11 Network Message Service Software	5,000.00	D
S ➤	SW7123	Meridian Mail Option 11 Network Message Services, Prime Site, Release 11 and Later	3,000.00	D
S ➤	SW7124	Meridian Mail Option 11 Network Message Services, Remote Site, Release 11 and Later	2,000.00	D
Enhanced Reporting Software - Meridian Mail Reporter				
S ➤	NTS133AA	Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12, 13)	1,000.00	D
S ➤	NTZD61AA	Meridian Mail Reporter Single Site Software, Option 11 MM13	1,600.00	D
S ➤	NTZD61BA	Meridian Mail Reporter Multi Site Software, Option 11 - MM13	2,100.00	D
S ➤ Δ	SVC1006	Meridian Mail Reporter One Year Extended Service Plan	250.00	H
S ➤	SW7118	Meridian Mail AdminPlus Enable Option	800.00	D
Software Administrative Fees				
B ➤ Δ	SERV0019	Meridian Mail Software Service Transaction Fee. - Issue/Release Update - Feature Addition/Expanded Storage - Tape Replacement, Additional Languages	500.00	H

Optional Hardware

Disk Shadowing

S ➤	NT6P44BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power	2,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

System Expansions

Ports/Nodes/Storage

Meridian Mail capacity by node

Nodes	Card option	Modular Option / Modular Option GP	EC11 (Note) EC/ MMP40
1	12	12	24
2	NA	24	48
3	NA	32	48
4	NA	48	72
5	NA	64	96
Note: The maximum nodes supported on the EC11 is two (48 ports).			

Ports

S ➤	AS7108	4 Port Full Service Voice Processing Package, EC/EC11	14,000.00	D
S ➤	AS7109	4 Port Basic Service Voice Processing Package, EC/EC11	4,800.00	D
S ➤	AS7110	8 Port Full Service Voice Processing Package, EC/EC11	27,000.00	D
S ➤	AS7111	8 Port Basic Service Voice Processing Package, EC/EC11	8,600.00	D
S ➤	NTRB18AA	MGate Card	500.00	D

Basic to Full Service Upgrade

S ➤	SW7065	Meridian Mail Basic to Full Service per Port Software Upgrade	2,300.00	D

Hardware Key Code Service

S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service. - port expansions/node expansions	No charge	

Node Expansions
Expansion Packages

S ➤	AS7100	Meridian Mail EC11 1 to 2 Node Expansion Package	12,200.00	D
S ➤	NTZC52AA	Enhanced Meridian Mail EC11 1 to 2 Node Expansion Package	12,200.00	D
S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service. - port expansions/node expansions	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Storage Expansion

Meridian Mail 11 storage capacity

Volume storage level	Minimum disk drive	1 node hours	2 node (Note) hours	3 node hours	4 node hours	5 node hours
1	300 MB	11	26	30	45	60
2	300 MB	24	54	60	90	120
3	600 MB	36	84	90	120	180
4	600 MB	54	114	120	180	240
5	1.0 GB	100	200	200	300	400
6	2.0 GB	200	400	400	600	800
Note: The maximum capacity of the EC11 is two nodes, there fore 400 hours is maximum available storage.						

Expanded Storage Software

S ➤	SW7049	Meridian Mail Expanded Storage Software Level 1-2	7,500.00	D
S ➤	SW7054	Meridian Mail Expanded Storage Software Level 2-3	7,500.00	D
S ➤	SW7055	Meridian Mail Expanded Storage Software Level 3-4	7,500.00	D
S ➤	SW7056	Meridian Mail Expanded Storage Software Level 4-5	10,000.00	D
S ➤	SW7059	Meridian Mail Expanded Storage Software Level 5-6	10,000.00	D

Platform Migrations to Modular Option EC

S ➤	U7018001	Meridian Mail EC11 to EC Migration 4-24 Port AC Package	6,500.00	D
S ➤	U7018002	Meridian Mail EC11 to EC Migration 4-24 Port DC Package	6,500.00	D
S ➤	U7018003	Meridian Mail EC11 to EC Migration 28-48 Port AC Package	11,000.00	D
S ➤	U7018004	Meridian Mail EC11 to EC Migration 28-48 Port DC Package	11,000.00	D

System Upgrades

Software Release Update

S ✓ ➤	NTZD65AA	Meridian Mail EC11 Release 10, 11, or 12 to Release 13 Upgrade	1,200.00	D

Components

Component Packages

S ➤	AS7010	Meridian Mail Modular HVS Package	800.00	D
S ➤	AS7012	Meridian Mail Networking Modem Package	550.00	H
S ➤	AS7083	Meridian Mail EC11 Spares Package	8,500.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Cards				
S ➤	NT6P42AA	Utility Card without Modem	2,200.00	D
S ➤	NT6P97AA	MMP40 Processor, Modular EC/EC11	3,500.00	D
S ➤	NT6R15AA	Enhanced Processor for Meridian Mail EC	3,500.00	D
S ➤	NTDK36AA	Bus Terminator	200.00	D
S ➤	NTRB18AA	MGate Card	500.00	D
Disk Drives				
S ➤	NT6P07BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive	1,500.00	D
S ➤	NT6P44BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power	2,000.00	D
Tape Drive/Accessories				
S ➤	A0368760	DC6250 250MB Back Up Tape	50.00	H
S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H
S ➤	A0633585	Tandberg Tape Drive Cleaning Kit	84.00	H
S ➤	A0721902	Tandberg Tape Drive Unit - External	2,800.00	D
B ➤	NTAK30DB	External Tape Drive Package, Tandberg	2,800.00	D
S ➤	NTAK39AB	Tape Drive Wall Mounting Kit	65.00	D
Cables				
S ➤	A0351509	Gender Changer (Female/Female)	20.00	D
S ➤	A0376171	Powell DEC Cable	45.00	H
S ➤	NT6P0110	4 Port RS232 Cable	100.00	D
S ➤	NTAK98AA	Power Supply Cable	40.00	D
S ➤	NTDK3302	NLI Cable 10 Ft.	150.00	D
S ➤	NTDK3303	NLI Cable 20 Ft.	150.00	D
S ➤	NTDK3304	NLI Cable 30 Ft.	150.00	D
S ➤	NTDK58AA	RSM 4 Port Breakout Cable	300.00	H
S ➤	NTDK59AA	Alarm/Modem Cable Assembly-Initial Caps only	100.00	D
S ➤	NTND91AA	RS232 Straight Cable (10 Ft.)	65.00	D
S ➤	NTND91AB	RS232 Straight Cable (25 Ft.)	110.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Miscellaneous				
S ➤	A0379673	SCSI Terminator	50.00	D
S ➤	A0383526	VT520 Video Terminal	650.00	H
S ➤	NT3M50AD	Black Box ABC Switch	120.00	H
S ➤	NTDK32AA	EC11 Backplane and Cabinet Assembly	3,500.00	D
S ➤	NTDK35AA	AC/DC Power Supply	1,000.00	D
S ➤	NTDK66AB	Meridian Mail Modem Package	200.00	H
S ➤	NTND93AA	Null Modem Adapter	80.00	H
S ➤ Δ	NTUB24AA	Meridian Mail to CallPilot Migration Utility Tape and Documentation	No charge	

Meridian Mail-Option 21-81 (Modular Option EC/Modular Option GP/ Modular Option)

Stand Alone

Language Tapes

S ➤	NT5R33AU	Meridian Mail Release 10.11 Master Tape North American. Prompt Set Includes: - North American English - Canadian French - German - Latin American Spanish - Japanese	100.00	D
S ➤	NT5R33BU	Meridian Mail Release 10.11 Master Tape - North American 2. Promp Set Includes: - North American English - Canadian French - Latin American Spanish - Message Agent	100.00	D
S ➤	NT5R33CU	Meridian Mail Release 10.11 Master Tape European 1. Prompt Set Includes: - North American English - Euro English (Female) - German - Euro French - Dutch - Italian	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R33DU	Meridian Mail Release 10.11 Master Tape European 2. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D
S ➤	NT5R33EU	Meridian Mail Release 10.11 Master Tape European 3. Prompt Set Includes: - North American English - European Spanish - Turkish - Arabic - Portuguese - EuroEnglish (Male)	100.00	D
S ➤	NT5R33FU	Meridian Mail Release 10.11 Master Tape European 4. Promp Set Includes: - North American English - Hungarian - German - Russian	100.00	D
S ➤	NT5R33GU	Meridian Mail Release 10.11 Master Tape Asia/Pacific. Prompt Set Includes: - North American English - Japanese - Mandarin - Taiwan Mandarin - Australasian English	100.00	D
S	NT5R35AD	Meridian Mail, Release 9.66 Master Tape, North American. Prompt Set Includes: - English - French-Canadian - Spanish-Latin American - Portuguese-Brazil - Japanese - German	100.00	D
S	NT5R35CD	Meridian Mail, Release 9.66 Master Tape, European 1. Prompt Set Includes: - English - Italian - German - French-European - Dutch - UK English (Female)	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NT5R35DD	Meridian Mail, Release 9.66 Master Tape, European 2. Prompt Set Includes: - English - Danish - Finnish - Norwegian - Irish - Swedish	100.00	D
S	NT5R35ED	Meridian Mail, Release 9.66 Master Tape, European 3. Prompt Set Includes: - English - UK English (Male) - Arabic - Portuguese - Spanish - European - Turkish	100.00	D
S	NT5R35LD	Meridian Mail, Release 9.66 Master Tape, Asia/Pacific 1. Prompt Set Includes : - English - Japanese - Taiwan Mandarin - Korean - Mandarin PRC - Australian	100.00	D
S ➤	NT5R36BC	Meridian Mail Master Tape, North American 2 - Release 11.19. Prompt Set Includes: - North American English - American Spanish - Canadian French - Brazilian Portuguese - Message Agent	100.00	D
S ➤	NT5R36CC	Meridian Mail Master Tape, European 1 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Female) - German - Italian - Euro French - Dutch	100.00	D
S ➤	NT5R36DC	Meridian Mail Master Tape, European 2 - Release 11.19. Prompt Set Includes: - North American English - Swedish - Norwegian - Danish - Finnish - Irish English	100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R36EC	Meridian Mail Master Tape, European 3 - Release 11.19. Prompt Set Includes: - North American English - Euro English (Male) - Arabic - Portuguese - Turkish - Euro Spanish	100.00	D
S ➤	NT5R36FC	Meridian Mail Master Tape, European 4 - Release 11.19. Prompt Set Includes: - North American English - German - Russian - Polish - Czech	100.00	D
S ➤	NT5R36GC	Meridian Mail Master Tape, European 5 - Release 11.19. Prompt Set Includes: - North American English - Hungarian - German	100.00	D
S ➤	NT5R36HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19. Prompt Set Includes: - North American English - Mandarin - Taiwan-Mandarin - Japanese - Korean - Thai	100.00	D
S ➤	NT5R36JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19. Prompt Set Includes: - North American English - Australasian - Mandarin - Taiwan mandarin - Japanese - BBC English	100.00	D
S ➤	NT5R45AC	Meridian Mail Master Tape, North American 1 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -German -Japanese	100.00	D
S ➤	NT5R45BC	Meridian Mail Master Tape, North American 2 - Release 12.13. Prompt Set Includes: -North American English -Canadian French -American Spanish -Brazilian Portuguese -Message Agent	100.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R45CC	Meridian Mail Master Tape, European 1 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Female) -German -Italian -Euro French -Dutch	100.00	D
S ➤	NT5R45DC	Meridian Mail Master Tape, European 2 - Release 12.13. Prompt Set Includes: -North American English -Swedish -Norwegian -Danish -Finnish -Irish English	100.00	D
S ➤	NT5R45EC	Meridian Mail Master Tape, European 3 - Release 12.13. Prompt Set Includes: -North American English -Euro English (Male) -Arabic -Portuguese -Turkish -Euro Spanish	100.00	D
S ➤	NT5R45FC	Meridian Mail Master Tape, European 4 - Release 12.13. Prompt Set Includes: -North American English -German -Russian -Polish -Czech	100.00	D
S ➤	NT5R45GC	Meridian Mail Master Tape, European 5 - Release 12.13. Prompt Set Includes: -North American English -German -Hungarian	100.00	D
S ➤	NT5R45HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13. Prompt Set Includes: -North American English -Mandarin -Taiwan-Mandarin -Japanese -Korean -Thai	100.00	D

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT5R45JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13. Prompt Set Includes: -North American English -Australasian -Mandarin -Taiwan Mandarin -Japanese -BBC English	100.00	D
S ★	NT6R47AD	MM13.13 Master Tape NA 1	100.00	D
S ★	NT6R47BD	MM Release 13.13 Master Tape NA 2	100.00	D
S ★	NT6R47CD	MM Release 13.13 Master Tape Europe 1	100.00	D
S ★	NT6R47DD	MM Release 13.13 Master Tape Europe 2	100.00	D
S ★	NT6R47ED	MM Release 13.13 Master Tape Europe 3	100.00	D
S ★	NT6R47FD	MM Release 13.13 Master Tape Europe 4	100.00	D
S ★	NT6R47GD	MM Release 13.13 Master Tape Europe 5	100.00	D
S ★	NT6R47HD	MM Release 13.13 Master Tape Asia/Pacific 1	100.00	D
S ★	NT6R47JD	MM Release 13.13 Master Tape Asia/Pacific 2	100.00	D
S ➤	NTAK72QN	Meridian Mail Release 10.11 Master Tape European 4 Card Option. Promp Set Includes: - North American English - Hungarian - German - Russian	100.00	D

Meridian Mail Hardware

Base Platform Packages

Modular EC

S ➤	SY7020A	Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/ 200 Hour Package AC	11,000.00	D
S ➤	SY7020D	Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/ 200 Hour Package DC	11,000.00	D
S ➤	SY7021A	Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/ 200/400 Hour Package AC	22,000.00	D
S ➤	SY7021D	Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/ 200/400 Hour Package DC	22,000.00	D
S ➤	SY7022A	Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package AC	30,000.00	D
S ➤	SY7022D	Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package, DC	30,000.00	D
S ➤	SY7023A	Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/ 300/600 Hour Package AC	39,000.00	D
S ➤	SY7023D	Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/ 300/600 Hour Package DC	39,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	SY7024A	Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/ 400/800 Hour Package AC	46,000.00	D
S ➤	SY7024D	Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/ 400/800 Hour Package DC	46,000.00	D

Modular GP

S ➤	SY7075D	Enhanced Meridian Mail Modular GP 4-12 Port 11/24/36/54/100/ 200 Hours Package DC	11,000.00	D
S ➤	SY7076D	Enhanced Meridian Mail Modular GP 16-24 Port 26/54/84/114/ 200/400 Hours Package DC	22,000.00	D
S ➤	SY7077D	Enhanced Meridian Mail Modular GP 28-32 Port 30/60/90/120/ 200/400 Hours Package DC	30,000.00	D
S ➤	SY7078D	Enhanced Meridian Mail Modular GP 36-48 Port 45/90/120/180/ 300/600 Hours Package DC	40,000.00	D
S ➤	SY7079D	Enhanced Meridian Mail Modular GP 52-64 Port 60/120/180/ 240/400/800 Hours Package DC	46,000.00	D

Non Northern PBX/Modular Option GP Connectivity
Meridian Mail Connections
Connections Software

S ➤	SW7061	Meridian Mail SMDI Connections Software	No charge	

Meridian Mail Software
Base System Software

S ✓ ➤	NTZR57CA	Meridian Mail Release 13 Base Software	2,000.00	D

Optional Features

S ➤	NT8R20AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ➤	NTS134AA	Software Feature, Personal Mailbox Administration (PMA)	1,000.00	D
S ➤	NTS136AA	Meridian Mail AutoAdmin Software Package EC, Modular Option, GP	3,300.00	D
S ➤	NTZD62AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D
S ✓ ➤ Δ	NTZD67AA	Meridian Mail Release 8, 9, 10, 11, or 12 to Release 13 Migration, Options, Modular Option to Modular EC	1,200.00	D
S ➤	SW7004B	Hospitality Voice Services Software	2,200.00	D
S ➤	SW7007	Secured Messaging Software	2,200.00	D
S ➤	SW7023	Meridian Mail Additional Language	600.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	SW7024	Meridian Mail Dual Language Prompt	No charge	
S ➤	SW7030E	Meridian Mail ACCESS Enable Option	No charge	
S ➤	SW7040D	Meridian Mail Voice Forms	2,000.00	D
S ➤	SW7041G	Meridian Mail Multi-Customer	500.00	D
S ➤	SW7043	Meridian Mail Multiple Administration	500.00	D
S ➤	SW7057B	Meridian Mail Fax on Demand Software	5,000.00	D
S ➤	SW7058	Meridian Mail Outcalling	No charge	
S ➤	SW7060	Meridian Mail SMDI Software	5,000.00	D
S ➤	SW7062	Meridian Mail GP Multi-SMDI Software	3,000.00	D
S ➤	SW7072	Meridian Mail VMUIF	100.00	D
S ➤	SW7074	Meridian Mail AutoAdmin Link Software	2,500.00	D
Networking Software				
S ➤	NT3R71AA	Meridian Mail Net Gateway	3,000.00	D
S ➤	SW7008	Network Message Service Software	11,000.00	D
S ➤	SW7008B	Network Message Services Prime Site Software, Release 11 and Later	5,000.00	D
S ➤	SW7010B	Meridian Mail Networking/Enterprise Networking	2,200.00	D
S ➤	SW7035C	Meridian Mail AMIS Networking (Virtual Node)	5,000.00	D
S ➤	SW7042B	Meridian Mail AMIS Open Networking	3,000.00	D
S ➤	SW7068	Network Message Services Remote Site Software, Release 11	2,000.00	D
Enhanced Reporting Software - Meridian Mail Reporter				
S ➤	NTS137AA	Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package	1,000.00	D
S ➤	NTZD66AA	Meridian Mail Reporter Single Site Software MM13	2,800.00	D
S ➤	NTZD66BA	Meridian Mail Reporter Multi Site Software Release 13	3,300.00	D
S ➤ Δ	SVC1006	Meridian Mail Reporter One Year Extended Service Plan	250.00	H
S ➤	SW7009D	AdminPlus Enable Option	2,000.00	D
Software Administration Fees				
B ➤ Δ	SERV0019	Meridian Mail Software Service Transaction Fee. - Issue/Release Update - Feature Addition/Expanded Storage - Tape Replacement, Additional Languages	500.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Optional Hardware				
Disk Shadowing				
Modular Option EC				
S ➤	AS7031A	Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package AC	8,500.00	D
S ➤	AS7031D	Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package DC	8,500.00	D
S ➤	AS7033A	Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package AC	4,500.00	D
S ➤	AS7033D	Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package DC	4,500.00	D
S ➤	NT6P44BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power	2,000.00	D
Modular Option GP				
S ➤	NT6D48FA	4.5GB Modular Hard Disk Drive	1,500.00	D
Modular Option				
S ➤	AS7029	Meridian Mail 2GB Disk Shadowing Prime Node Package	5,000.00	D
S ➤	AS7037A	Meridian Mail 2GB Disk Shadowing Voice Node Package AC	4,500.00	D
S ➤	AS7037D	Meridian Mail 2GB Disk Shadowing Voice Node Package DC	4,500.00	D
System Expansions				
Ports/Nodes/Storage				
Ports				
Modular Option EC Pre-Release 9				
S ➤	NT6P04AA	VP4 Card	14,000.00	D
S ➤	NT6P08AA	VP8 Card	27,000.00	D
Modular Option EC Release 9 and Later				
S ➤	AS7108	4 Port Full Service Voice Processing Package, EC/EC11	14,000.00	D
S ➤	AS7109	4 Port Basic Service Voice Processing Package, EC/EC11	4,800.00	D
S ➤	AS7110	8 Port Full Service Voice Processing Package, EC/EC11	27,000.00	D
S ➤	AS7111	8 Port Basic Service Voice Processing Package, EC/EC11	8,600.00	D
S † ➤	AS7116	4 to 8 Port Full Service Voice Processing Expansion Package, EC/EC11	15,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	AS7117	4 to 8 Port Basic Service Voice Processing Expansion Package, EC/EC 11	5,800.00	D
Modular Option GP Release 9 and Later				
S ➤	AS7112	4 Port Full Service Voice Processing Package, Modular GP	14,000.00	D
S ➤	AS7113	4 Port Basic Service Voice Processing Package, Modular GP	4,800.00	D
Modular Option Release 9 and Later				
S ➤	AS7114	4 Port Full Service Voice Processing Package, Options	14,000.00	D
S ➤	AS7115	4 Port Basic Service Voice Processing Package, Options	4,800.00	D
Basic to Full Service Upgrade - All				
S ➤	SW7065	Meridian Mail Basic to Full Service per Port Software Upgrade	2,300.00	D
Hardware Key Code Service - All				
S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service. - port expansions/node expansions	No charge	

Node Expansions

Meridian Mail Port capacity by node

Nodes	Card option	Modular Option/ Modular Option GP	EC11 (note) EC/MMP40
1	12	12	24
2	NA	24	48
3	NA	32	48
4	NA	48	72
5	NA	64	96
Note: The maximum nodes supported on the EC11 is two (48 ports).			

Node Expansion package requirements

Expansion	1-2 nodes	2-3 nodes	3-4 nodes	4-5 nodes
EC (MMP40) Unshadowed	AS7023A/D	AS7025 (Note)	AS7021A/D	AS7023A/D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Node Expansion package requirements

Expansion	1-2 nodes	2-3 nodes	3-4 nodes	4-5 nodes
EC (MMP40) Shadowed	AS7023A/D	AS7021A/D (Note)	AS7023A/D	AS7021A/D
EC 11	AS7100	N/A	N/A	N/A
Modular Option	AS7043A/D	AS7044A/D	AS7045A/D	AS7046A/D
Modular Option GP	AS7047D	AS7048D	AS7049D	AS7050D
Note: Expanding a Modular Option EC from a two-to a three-node system does not provide any additional ports. Expanding a system from three nodes to four nodes provides additional ports.				

Hardware Key Code Service

S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service. - port expansions/node expansions	No charge

Modular Option EC

Position/node relationship

Position	Unshadowed	Shadowed
1	Node 4	Node 3, 5
2	Node 2, 5	Node 2, 4
3	Node 3	N/A
Note: This table shows the node being added and the position relationship as referenced in the expansion package below.		

S ➤	AS7021A	Meridian Mail Modular EC Node Expansion 1st Position Package AC	12,500.00	D
S ➤	AS7021D	Meridian Mail Modular EC Node Expansion 1st Position Package DC	12,500.00	D
S ➤	AS7023A	Meridian Mail Modular EC Node Expansion 2nd Position Package AC	12,500.00	D
S ➤	AS7023D	Meridian Mail Modular EC Node Expansion 2nd Position Package DC	12,500.00	D
S ➤	AS7025	Meridian Mail Modular EC Node Expansion 3rd Position Package	10,500.00	D
S ➤	NTZC53AA	Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package AC	12,500.00	D
S ➤	NTZC53BA	Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package DC	12,500.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTZC54AA	Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package AC	12,500.00	D
S ➤	NTZC54BA	Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package DC	12,500.00	D
S ➤	NTZC55AA	Enhanced Meridian Mail Modular EC Node Expansion 3rd Position Package	10,500.00	D
Modular Option GP				
S ➤	AS7047D	Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC	11,250.00	D
S ➤	AS7048D	Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC	11,250.00	D
S ➤	AS7049D	Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC	12,250.00	D
S ➤	AS7050D	Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC	15,250.00	D
S ➤	NTZC56AA	Enhanced Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC	11,250.00	D
S ➤	NTZC56BA	Enhanced Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC	11,250.00	D
S ➤	NTZC56CA	Enhanced Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC	12,250.00	D
S ➤	NTZC56DA	Enhanced Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC	15,250.00	D
Modular Option				
S ➤	AS7043A	Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package AC	11,250.00	D
S ➤	AS7043D	Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package DC	11,250.00	D
S ➤	AS7044A	Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package AC	12,250.00	D
S ➤	AS7044D	Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package DC	12,250.00	D
S ➤	AS7045A	Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package AC	12,250.00	D
S ➤	AS7045D	Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package DC	12,250.00	D
S ➤	AS7046A	Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package AC	10,250.00	D
S ➤	AS7046D	Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package DC	10,250.00	D
S ➤	NTZD71AA	Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package AC	11,250.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTZD71BA	Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package DC	11,250.00	D
S ➤	NTZD72AA	Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package AC	12,250.00	D
S ➤	NTZD72BA	Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package DC	12,250.00	D
S ➤	NTZD73AA	Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package AC	12,250.00	D
S ➤	NTZD73BA	Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package DC	12,250.00	D
S ➤	NTZD74AA	Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package AC	10,250.00	D
S ➤	NTZD74BA	Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package DC	10,250.00	D

Storage Expansion

The following table depicts the storage capacity options available on installed Modular Option ED, EC11, Modular Option, and Modular Option GP systems running Meridian Mail 11 software.

Meridian Mail 11 storage capacity

Volume storage level	Minimum disk drive	1 node hours	2 node (Note) hours	3 node hours	4 node hours	5 node hours
1	300 MB	11	26	30	45	60
2	300 MB	24	54	60	90	120
3	600 MB	36	84	90	120	180
4	600 MB	54	114	120	180	240
5	1.0 GB	100	200	200	300	400
6	2.0 GB	200	400	400	600	800
Note: The maximum capacity of the EC11 is two nodes, therefore 400 hours is maximum available storage.						

Expanded Storage Software

S ➤	SW7049	Meridian Mail Expanded Storage Software Level 1-2	7,500.00	D
S ➤	SW7054	Meridian Mail Expanded Storage Software Level 2-3	7,500.00	D
S ➤	SW7055	Meridian Mail Expanded Storage Software Level 3-4	7,500.00	D
S ➤	SW7056	Meridian Mail Expanded Storage Software Level 4-5	10,000.00	D
S ➤	SW7059	Meridian Mail Expanded Storage Software Level 5-6	10,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

System Upgrades

Hardware - Disk/Tape Drive and Processors

Modular Option EC

Disk Drive Storage	Node 1	Node 2	Node 3	Node 4	Node 5
U7202	X	X		X	X
U7203			X		

S ➤	NT6P05BA	Tandberg EC Tape Drive Unit, EC	3,000.00	D
S ➤	U7202	Meridian Mail Modular EC 2GB Disk Drive Upgrade	1,500.00	D
S ➤	U7203	Meridian Mail Modular EC 2GB Disk Drive with Power Upgrade	2,000.00	D

Modular Option GP/Modular Option

S ➤	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	3,000.00	D
S ➤	NT6D48GA	Tandberg Tape and 4.5GB Disk Drive Unit, Modular Option	5,000.00	D
S ➤	U7207	Meridian Mail Modular Option 2GB Disk Drive Upgrade	1,500.00	D

Processor Upgrades

S ➤	NTZD75AA	Enhanced Processor Upgrade, EC	3,500.00	D
S ➤	NTZD75BA	Enhanced Processor Upgrade, Modular Option, Modular Option GP	3,500.00	D

Software Upgrades

Modular Option EC

S ➤ Δ	NT5R3501	Meridian Mail EC 9.19 to 9.66 Upgrade Keycode	No charge	
S ✓ ➤	NTZD68AA	Meridian Mail EC Release 8, 9.19 to Release 13 Upgrade	5,400.00	D
S ✓ ➤	NTZD68BA	Meridian Mail EC Release 9.58 and Later/Release 10/11/12 to Release 13 Upgrade	1,700.00	D

Modular Option GP

S ✓ ➤	NTZD69AA	Meridian Mail Release 4 to Release 13 Software Migration, GP to Modular GP	6,700.00	D
S ✓ ➤	NTZD69BA	Meridian Mail Modular GP Release 5 to Release 13 Upgrade or Migration from GP to Modular GP	6,700.00	D
S ✓ ➤	NTZD69CA	Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP	6,000.00	D
S ✓ ➤	NTZD69DA	Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP	5,400.00	D
S ✓ ➤	NTZD69EA	Meridian Mail Modular GP Release 9/10/11/12 to Release 13 Upgrade or Migration from GP to Modular GP	1,700.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Modular Option				
S ✓ ➤	NTZD70AA	Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option	6,700.00	D
S ✓ ➤	NTZD70BA	Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option	6,000.00	D
S ✓ ➤	NTZD70CA	Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option	5,400.00	D
S ✓ ➤	NTZD70DA	Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option	1,700.00	D

Platform Migration

Migration to a Modular Option

Migration Hardware

S ➤	U7014A	Meridian Mail Migration to Modular Option Prime Node, 300MB Package AC	8,000.00	D
S ➤	U7014D	Meridian Mail Migration to Modular Option Prime Node, 300MB Package DC	8,000.00	D
S ➤	U7015A	Meridian Mail Migration to Modular Option Voice Node, 300MB Package AC	6,000.00	D
S ➤	U7015D	Meridian Mail Migration to Modular Option Voice Node, 300MB Package DC	6,000.00	D
S ➤	U7016A	Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package AC	8,000.00	D
S ➤	U7016D	Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package DC	8,000.00	D
S ➤	U7017A	Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package AC	6,000.00	D
S ➤	U7017D	Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package DC	6,000.00	D

Processor Upgrade

S ➤	NTZD75BA	Enhanced Processor Upgrade, Modular Option, Modular Option GP	3,500.00	D

Disk Drive Upgrade (only required if existing disk drive is 155MB)

S ➤	U7207	Meridian Mail Modular Option 2GB Disk Drive Upgrade	1,500.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Migration to a Modular Option GP				
Migration Hardware				
S ➤	U7068D	Meridian Mail Migration to Modular Option GP Prime Node, 300MB Package DC	8,000.00	D
S ➤	U7069D	Meridian Mail Migration to Modular Option GP Voice Node, 300MB Package DC	7,000.00	D
S ➤	U7070	Meridian Mail Migration to Modular Option GP Prime Node, 600MB/1GB Package DC	8,000.00	D
S ➤	U7071D	Meridian Mail Migration to Modular Option GP Voice Node, 600MB/1GB Package DC	7,000.00	D
Processor Upgrade				
S ➤	NTZD75BA	Enhanced Processor Upgrade, Modular Option, Modular Option GP	3,500.00	D
Disk Drive Upgrade (only required if existing disk drive is 155MB)				
S ➤	U7207	Meridian Mail Modular Option 2GB Disk Drive Upgrade	1,500.00	D
Migration Software				
Modular Option EC				
S ➤ Δ	63015	Meridian Mail Release 3 to Release 7 Software Migration, from Options to Modular EC	500.00	H
S ➤ Δ	63016	Meridian Mail Release 4 to Release 7 Software Migration, from Options to Modular EC	500.00	H
S ➤ Δ	63017	Meridian Mail Release 5 to Release 7 Software Migration, from Options, Modular Option to Modular EC	500.00	H
S ➤ Δ	63031	Meridian Mail Release 6 to Release 8 Software Migration, from Options to Modular EC	500.00	H
S ➤ Δ	63033	Meridian Mail Release 7 to Release 8 Software Migration, from Options to Modular EC	500.00	H
S ➤ Δ	63060	Meridian Mail Release 6/7 to Release 8 Software Migration, from Modular Option to Modular EC	500.00	H
S ➤	SW7050	Meridian Mail Migration	No charge	
Modular Option GP				
S ✓ ➤	NTZD69CA	Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP	6,000.00	D
S ✓ ➤	NTZD69DA	Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP	5,400.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Modular Option				
S ✓ ➤	NTZD70AA	Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option	6,700.00	D
S ✓ ➤	NTZD70BA	Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option	6,000.00	D
S ✓ ➤	NTZD70CA	Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option	5,400.00	D
S ✓ ➤	NTZD70DA	Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option	1,700.00	D
S ✓ ➤	NTZD70EA	Meridian Mail Release 3 to Release 13 Software Migration, from Options to Modular Option	6,700.00	D
S ✓ ➤	NTZD70FA	Meridian Mail Release 4 to Release 13 Software Migration, from Options to Modular Option	6,700.00	D
Components				
Component Packages				
S ➤	AS7010	Meridian Mail Modular HVS Package	800.00	D
S ➤	AS7012	Meridian Mail Networking Modem Package	550.00	H
S ➤	AS7015	Meridian Mail Modular RSM Package	2,100.00	D
S ➤	AS7070D	Meridian Mail Modular GP Spares Package	10,000.00	D
S ➤	AS7080	Meridian Mail Modular Option EC/EC11 Spares Package 1	8,000.00	D
S ➤	AS7081	Meridian Mail Modular Option EC/EC11 Spares Package 2	13,000.00	D
S ➤	AS7082	Meridian Mail Alternative Remote Access Package	2,300.00	D
Cards				
S ➤	NT4R01AC	Network Voice Processor	14,000.00	D
S ➤	NT4R03AB	RS232C Service Module	2,000.00	D
S ➤	NT4R04AB	General Purpose Signal Processor	14,000.00	D
S † ➤	NT4R08AA	HABC (High Availability Bus Controller)	2,750.00	D
S † ➤	NT4R10AA	HABC Terminator	100.00	D
S ➤	NT4R11AA	ESBC Terminator	100.00	D
S ➤	NT4R45AA	MMP40 Processor, Classic	3,500.00	D
S § ➤	NT6D41BA	Meridian Mail Modular GP Power Supply DC	3,000.00	D
S ➤	NT6P04AA	VP4 Card	14,000.00	D
S ➤	NT6P08AA	VP8 Card	27,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT6P42AA	Utility Card without Modem	2,200.00	D
S ➤	NT6P97AA	MMP40 Processor, Modular EC/EC11	3,500.00	D
S ✓ ➤	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	3,500.00	D
S ➤	NT6R15AA	Enhanced Processor for Meridian Mail EC	3,500.00	D

Disk Drives

S ➤	NT4R28BA	Tandberg Tape Drive Unit Options (ST/RT, NT/XT)	3,000.00	D
S ➤	NT6D48FA	4.5GB Modular Hard Disk Drive	1,500.00	D
S ➤	NT6P07BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive	1,500.00	D
S ➤	NT6P44BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power	2,000.00	D

Tape Drive/Accessories

S † ➤	A0326745	DC300 XLP Back-Up Tape	45.00	D
S ➤	A0368760	DC6250 250MB Back Up Tape	50.00	H
S ➤	A0378220	Tape Drive Cleaning Kit	110.00	D
S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H
S ➤	NT4R28BA	Tandberg Tape Drive Unit Options (ST/RT, NT/XT)	3,000.00	D
S ➤	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	3,000.00	D
S ➤	NT6D48GA	Tandberg Tape and 4.5GB Disk Drive Unit, Modular Option	5,000.00	D
S ➤	NT6P05BA	Tandberg EC Tape Drive Unit, EC	3,000.00	D

Cables

S ➤	A0351509	Gender Changer (Female/Female)	20.00	D
S ➤	A0376171	Powell DEC Cable	45.00	H
S ➤	A0385576	DB25F-DB9F Cable Adapter	69.00	D
S ➤	NT1R03DB	Straight Through RS232 Cable Male/Male (2 Ft.)	65.00	D
S ➤	NT1R03EP	Straight Through RS232 Cable Male/Female (25 Ft.)	200.00	D
S ➤	NT4R20AA	RSM Fanout Cable (25 Ft.)	65.00	D
S ➤	NT4R20AB	RSM Cable (50 Ft.)	80.00	D
S ➤	NT4R2102	Dual Network/Intra-Connection Cable (Cantilever)	85.00	D
S † ➤	NT4R35AA	Meridian Mail Bus Cable - Two Nodes	35.00	D
S † ➤	NT4R36AA	Meridian Mail Bus Cable - Five Nodes	35.00	D
S † ➤	NT4R37AA	RSM Alarm Adapter Cable	40.00	D
S † ➤	NT4R58AB	RSM Cable	65.00	D
S † ➤	NT4R59AA	CSL Cable	60.00	D
S † ➤	NT4R60AA	CRT Cable	60.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	NT4R61AA	NVP Daisychain Cable	110.00	D
S † ➤	NT6D4406	RSM Cable	80.00	D
S ➤	NT6D4407	GSP Cable	100.00	D
S † ➤	NT6D4408	NVP Cable	65.00	D
S † ➤	NT6D4409	SCSI Cable	50.00	D
S † ➤	NT6D4410	DVS Bus Cable	40.00	D
S † ➤	NT6D4411	DVS Bus Cable (57 Inches)	60.00	D
S † ➤	NT6D4412	DVS Bus Cable (Internal) (132 Inches)	60.00	D
S † ➤	NT6D4415	DVS Bus Cable (6 Ft.)	60.00	D
S ➤	NT6D4417	SCSI/Backplane Cable	50.00	D
S † ➤	NT6D4418	SCSI/Daisy Chain Cable	60.00	D
S † ➤	NT6D4419	RS232-Y Cable	75.00	D
S ➤	NT6P0104	Address Bus Jumper Cable	150.00	D
S ➤	NT6P0109	5 Port RS232 Cable	120.00	D
S ➤	NT6P0110	4 Port RS232 Cable	100.00	D
S ➤	NT6P0112	Alarm Cable	60.00	D
S ➤	NT6P0113	Interconnect Cable	100.00	D
S	NT6P0122	Network to I/O Cable Assembly	100.00	D
S	NT6P0123	Backplane to I/O Cable	100.00	D
S	NT6P0124	External Voice Bus Cable (2.5 Ft.)	120.00	D
S	NT6P0125	External Voice Bus Cable (5Ft.)	130.00	D
S	NT6P0126	External Voice Bus Cable (10Ft.)	140.00	D
S ➤	NT7D99AA	Null Modem Cable (10 Ft.)	60.00	D
S ➤	NTDK58AA	RSM 4 Port Breakout Cable	300.00	H
S ➤	NTND82AA	RS232 Null Modem Cable (10 Ft.)	45.00	D
S	NTND82AB	RS232 Null Modem Cable (25 Ft.)	75.00	D
S ➤	NTND91AA	RS232 Straight Cable (10 Ft.)	65.00	D
S ➤	NTND91AB	RS232 Straight Cable (25 Ft.)	110.00	D
S ➤	NTND94DA	CNI to I/O Panel Ethernet Cable (20 In.)	100.00	D
S ➤	P0695167	CRT Cable	60.00	D
S ➤	P0695169	SCSI Daisychain Cable	60.00	D
S ➤	P0695822	AML Link Cable	50.00	D
S ➤	P0695823	NVP Daisychain Cable	60.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Miscellaneous				
S ➤	A0383526	VT520 Video Terminal	650.00	H
S	A0621070	Serial-Parallel Converter for Printers	150.00	H
S ➤	NT3M50AD	Black Box ABC Switch	120.00	H
S ➤	NT6D44AA	Meridian Mail Module AC	5,000.00	D
S ➤	NT6D44DC	Meridian Mail Module DC	5,000.00	D
S ➤	NT6D54CA	Backplane Stiffener Kit	40.00	D
S	NT6P0106	External Voice Bus Terminator	100.00	D
S	NT6P01AA	Meridian Mail EC Module DC	4,000.00	D
S	NT6P01BA	Meridian Mail EC Module AC	4,000.00	D
S ➤	NT7D06AA	Filler Panel	35.00	D
S ➤	NT8D31AE	Tape Drive Blank Faceplate	80.00	D
S ➤	NT9D99AA	RSM Installation Kit - Modular	55.00	D
S ➤	NTDK66AB	Meridian Mail Modem Package	200.00	H
S ➤	NTND93AA	Null Modem Adapter	80.00	H
S ➤ Δ	NTUB24AA	Meridian Mail to CallPilot Migration Utility Tape and Documentation	No charge	

Meridian Text Telephony System

System Packages

Hardware Upgrades

S ➤	NTZB05MA	Meridian Text Telephony System TDD/TTY Modem. MTTS Modem and keycode for adding additional modem channels to the MTTS system	540.00	H

Additional Software Clients

S ➤	NTZB05AA	Meridian Text Telephony System PC Client Package - 25 Users	3,800.00	D
S ➤	NTZB05BA	Meridian Text Telephony System PC Client Package - 50 Users	6,800.00	D
S ➤	NTZB05CA	Meridian Text Telephony System PC Client Package - 100 Users	10,800.00	D
S ➤	NTZB05DA	Meridian Text Telephony System PC Client Package - 250 Users	23,000.00	D

Documentation

S Δ	P0885159	MTTS 1.0 User Guide	10.00	H
S Δ	P0885160	MTTS 1.0 Administration Guide	20.00	H
S Δ	P0885161	MTTS 1.0 Installation Guide	20.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Symposium Messenger

Software Packages

S ➤	NTVM0036	Messenger 2.0 Mac Client Package - 100 Users	7,000.00	D
S ➤	NTVM0061	Messenger 4.0 Windows Client Package - 25	2,500.00	D
S ➤	NTVM00JB	Messenger Fax on Demand Software	5,000.00	D
S ➤	NTVM15BA	Messenger 4.0 Server Software and 4 Port Card - Brooktrout	6,000.00	H

Symposium Assistant

Software Packages

S ➤	NTVA0002	Assistant 100 User License	5,000.00	D

Messenger Software Upgrades

S ➤	NTVM00SD	Messenger Software Brooktrout Upgrade Kit 2.0/3.0 to 4.0	500.00	D
S ➤	NTVM00SE	Messenger Software Audiofax Upgrade Kit 2.0/3.0 to 4.0	500.00	D
S † ➤ Δ	NTVM00SG	Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (For Customers Under Maintenance or Warranty)	No charge	
S † ➤	NTVM00SH	Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (Customer Not Under Maintenance or Warranty)	500.00	D
S † ➤ Δ	NTVM00SJ	Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Under Maintenance or Warranty)	No charge	
S † ➤	NTVM00SK	Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Not Under Maintenance or Warranty)	500.00	D

Hardware Packages

Servers

Meridian Application Server Spares

S † ➤	NT5P41AZ	4 Port Fax Modem Card AudioFax	5,000.00	H
S ➤	NT5P41ZR	Brooktrout 4 Port Fax Card	5,000.00	H
S ➤	NTVM00KA	Uninterruptible Power Supply (UPS) Kit for Messenger Server	1,000.00	H
S ✓ ➤	NTVM00YA	32 MB Memory Upgrade	2,500.00	H
S ➤	NTVM00YB	64 MB Memory Upgrade Package	3,500.00	H
S ➤	NTVM00ZF	MAS Model 500 2GB Hard Drive Option	2,250.00	H
S ➤	NTVM00ZG	MAS Model 501 2GB Hard Drive Option	2,250.00	H
S ➤	NTVM15CA	Messenger 4.0 Server Software Only Kit - Brooktrout	6,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTVM17AA	Audiofax Server Software Only (Kit)	3,500.00	H
S ➤	NTVM18AA	MAS-Model 100 Spares Kit	6,000.00	H
S ➤	NTVM19AA	MAS-Model 500 Spares Package	10,000.00	H
S ➤	NTVM19AB	MAS Model 501 Spares Kit	10,000.00	H
S ➤	NTVM4019	Ethernet LAN Interface Board	300.00	H
S ➤	NTVM4024	Token Ring LAN Interface Board	1,000.00	H

Messenger Services and Documentation

S ➤ Δ	SV000020	Messenger 4.0: On-site Administration and User Training	4,000.00	H
S ➤ Δ	SV000024	MAS Premium Warranty Upgrade: Extended Telephone Support	1,200.00	H
S ➤ Δ	SV000025	MAS Premium Warranty Upgrade; Onsite Removal/ Replacement	3,500.00	H
S ➤ Δ	SV000026	MAS Post Warranty Service	5,000.00	H
S ➤ Δ	SV000027	MAS Post Warranty Premium Service	6,000.00	H
S ➤ Δ	SV000110	Messenger Post Warranty Phone 8-5	3,000.00	H
S ➤ Δ	SV000111	Messenger Post Warranty Phone 7x24	4,000.00	H
S ➤ Δ	SV000112	Messenger Installation Phone Support	3,000.00	H
S ➤ Δ	SV000181	Service Code for Telephone Support to Add Additional User Client License(s) Req. if adding clients to existing systems. Service Code for Telephone Support to Add Additional User Client License(s) Required if adding clients to existing systems	300.00	H
S Δ	SV000251	Additional One Day On-Site Messenger Training	1,500.00	H
S † ➤ Δ	SV000276	Messenger 2.0/3.0 to 4.0 On-Site Migration Support	3,000.00	H
S † ➤ Δ	SV000278	Messenger 2.0/3.0 Maintenance Release--Phone Installation Support for Customers Under Warranty or Maintenance	No charge	
S † ➤ Δ	SV000279	Messenger 2.0/3.0 Maintenance Release--Installation Phone Support for Customers NOT under Warranty or Maintenance	750.00	H
S † ➤ Δ	SV000280	Messenger 2.0/3.0 Maintenance Release--On-Site Installation Support for Customers NOT under Warranty or Maintenance	1,500.00	H

Messenger and Assistant Documentation

S ➤ Δ	NTVM0101	Messenger Quick Reference Card - 25 Pack	25.00	H
S ➤ Δ	NTVM0103	Messenger Quick Reference Card - 100 Pack	100.00	H
S ➤	NTVM60AA	Messenger Computer Based Training	200.00	H
S Δ	P0871231	MAS Installation and Maintenance Guide	40.00	H
S Δ	P0881354	Messenger 4.0 Administration Guide	25.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian IVR Release 2 Integrated

Components

S ➤	A0369788	UDS V.3225 Synchronous Modem	1,000.00	H
S	A0609639	DEC Style Keyboard	350.00	D
S	A0609641	Mouse	275.00	D
S	A0639226	MRS/Tower or MRS/Rack Token Ring Controller	No charge	
S ➤	AS8600	17 In. Color X-Terminal with DEC Style Keyboard	4,600.00	H
S ➤	NT7D19RA	Meridian IVR Applications Module	3,825.00	D

Open IVR

Optional System Packages

S ➤ Δ	A0639225	MRS Tower/Rack Disk Drive (1.05GB)	2,100.00	H
S ➤	A0659125	OIVR 2 x Hardware - Cabinet Rail Assembly	500.00	H
S ➤	NT7D47BB	Ethernet Cable (100 Ft.)	250.00	D
S	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	175.00	D
S	NT7D95AA	Transition Cable	125.00	D
S ✓ ➤	NTAK40AA	Networking Hardware Kit	1,100.00	D
S	NTND82AB	RS232 Null Modem Cable (25 Ft.)	75.00	D

Components

S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H
S ➤	A0633585	Tandberg Tape Drive Cleaning Kit	84.00	H
S ➤ Δ	A0639229	AP Token Ring Lan Interface Kit	860.00	H
S ➤	A0674453	33.6 KBPS External Data/Fax Modem	370.00	H
S ➤	NT3R67AA	OIVR 2 x Hardware - MRS System Recovery Software Ethernet	No charge	
S ➤	NT3R67BA	OIVR 2 x Hardware - MRS System Recovery Software Token Ring	No charge	
S ➤	NT3R75AA	OIVR 2.X Hardware - MRS/Tower or MRS/Rack Ethernet Lan Interface	375.00	H
S ➤	NT3R75BA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Token Ring LAN Interface	1,150.00	H
S ➤ Δ	NT7D47BA	Ethernet Cable (Thinnet 50 Ft.) and Terminator	100.00	H
S ✓ ➤	NTAK40AA	Networking Hardware Kit	1,100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	NTZK14AA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Disk Drive (1.05GB)	2,100.00	H

Spares

S ✓ ➤	A0601464	Modem Cable, 10 Ft. DB9 Female to DB25 Male	25.00	D
S † ➤	A0622896	OIVR 2 x Hardware - Tape Drive (2.5GB)	945.00	H
S	A0636813	T1 Port Assembly (24 ports)	14,815.00	H
S Δ	A0638483	Keyboard	60.00	H
S ➤	A0638645	External Modem (14,400 bps, V.32 bis with V.42 bis)	370.00	H
S † ➤	A0639513	OIVR 2.X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)	80.00	H
S † ➤	A0639530	OIVR 2 x Hardware - 256KB L2 Async Cache for AP or MRS/AP	125.00	H
S † ➤	A0639569	OIVR 2 x Hardware - Expansion RAM - 8MB SIMM with Parity	445.00	H
S ➤	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity	300.00	H
S † ➤ Δ	A0640190	OIVR 2 x Hardware - MRS/Tower Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - SCSI Cable - Floppy Cable	10,000.00	H
S † ➤ Δ	A0640192	OIVR 2 x Hardware - MRS/Rack DC Spares Kit. - CPU Module and Memory - DC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - SCSI Cable - Floppy Cable	10,650.00	H
S † ➤ Δ	A0640194	OIVR 2 x Hardware - MRS/Rack AC Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - Floppy cable	10,000.00	H
B ➤	A0646699	Key and Lock Master	70.00	H
S † ➤	A0646715	OIVR 2 x Hardware - Drive LED Panel for AP or MRS/AP	45.00	H
S † ➤	A0647317	OIVR 2 x Hardware - Fan (100cfm)	85.00	H
S † ➤	A0650996	OIVR 2 x Hardware - 12-port Loopstart Network Interface Module	2,965.00	H
S † ➤	A0651032	OIVR 2 x Hardware - VRP Voice Recognition Card	5,370.00	H
S † ➤	A0651035	OIVR 2 x Hardware - 12-port Voice Processing Card	5,185.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	A0651036	OIVR 2 x Hardware - Serial I/O Controller for MRS	75.00	H
S † ➤	A0651037	OIVR 2 x Hardware - SCSI Disk Controller for MRS	685.00	H
S † ➤	A0651038	OIVR 2 x Hardware - 1.05GB Disk Drive (Tower)	1,575.00	H
S † ➤	A0651039	OIVR 2 x Hardware - 1.05GB Disk Drive (Rack)	1,575.00	H
S † ➤	A0651040	OIVR 2 x Hardware - Ethernet Controller for MRS	400.00	H
S † ➤	A0651041	OIVR 2 x Hardware - Token Ring Controller for MRS	1,250.00	H
S † ➤	A0651060	OIVR 2 x Hardware - CPU Module with no Memory	2,925.00	H
S † ➤	A0651062	OIVR 2 x Hardware - CPU Module with 32MB Memory	7,410.00	H
S † ➤	A0651064	OIVR 2 x Hardware - 450W Power Supply (Tower)	1,710.00	H
S † ➤	A0651350	OIVR 2 x Hardware - Digiboard DTE 8 Port DB25 Male Cable	125.00	H
B	A0651681	RT Clock Chip	35.00	H
S † ➤	A0652239	OIVR 2 x Hardware - Floppy Drive, 3.5 In.	140.00	H
S † ➤	A0652633	OIVR 2 x Hardware - 2 Port Brooktrout Fax Card	4,200.00	H
S † ➤	A0652634	OIVR 2 x Hardware - 4 Port Brooktrout Fax Card	8,400.00	H
S † ➤	A0652635	OIVR 2 x Hardware - 8 Port Brooktrout Fax Card	16,800.00	H
S † ➤	A0652638	OIVR 2 x Hardware - Apertus Communications Board (SDLC)	1,945.00	H
S † ➤	A0652681	OIVR 2 x Hardware - 350W DC Power Supply (Rack)	2,000.00	H
S † ➤	A0652687	OIVR 2 x Hardware - Redundant DC Power Supply for MRS/ Rack	2,000.00	H
S † ➤	A0652688	OIVR 2 x Hardware - 350W AC Power Supply (Rack)	1,370.00	H
S	A0654949	MRS to UPS Communications Cable	80.00	H
S † ➤	A0656847	OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP	925.00	H
S † ➤	A0656874	OIVR 2 x Hardware - Cable, LCD for AP or MRS/AP	110.00	H
S † ➤	A0657566	OIVR 2 x Hardware - 10 position Connector PEB Cable	60.00	H
S † ➤	A0657728	OIVR 2 x Hardware - MRS to Terminal Cable (DB25F to DB25M)	25.00	H
S † ➤	A0657730	OIVR 2 x Hardware - Loopstart Interface Cable (DB25F to RJ23X)	245.00	H
S † ➤	A0657777	OIVR 2 x Hardware - CPU Module Battery for MRS	40.00	H
S † ➤	A0658110	OIVR 2 x Hardware - MRS/Tower Air Filter	25.00	H
S † ➤	A0658485	OIVR 2 x Hardware - 6 Ft. SCSI Cable for MRS	50.00	H
S † ➤	A0658488	OIVR 2 x Hardware - Floppy Cable for MRS	45.00	H
S † ➤	A0658655	OIVR 2 x Hardware - Keylock Adapter	125.00	H
S † ➤	A0658690	OIVR 2 x Hardware - MRS/Rack Fan Assembly	245.00	H
S † ➤	A0658957	OIVR 2 x Hardware - Floppy Disk Drive for MRS	140.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	A0659158	OIVR 2 x Hardware - Riser Board for AP or MRS/AP	100.00	H
S ➤ Δ	A0666779	CPU Kit Including Installed Heatsink Adhesive and Clip for Pentium Processor	345.00	H
S † ➤	NT3R23AA	OIVR 2 x Hardware - MRS/AP or AP Ethernet LAN Interface	250.00	H
S † ➤ Δ	NT3R23BA	OIVR 2.x Hardware - MRS/AP or AP Token Ring LAN Interface	880.00	H
S † ➤ Δ	NT3R83AA	OIVR 2 x Hardware - Voice and Data Storage (1GB) for MRS/AP or AP	1,575.00	H
S	NTV403TA	Token Ring Adapter Kit	880.00	H
S ➤	NTVE9932	Modem Cable Spare (DB9F to DB25M)	37.00	H

Documentation

S ✓ Δ	P0875922	Meridian Mail Release 12 System Administration Tools Guide	20.00	H

SYMPOSIUM Professional Services - IVR Services

S ➤ Δ	SV000175	Nortel IVR CompuCALL Integration Package	25,000.00	H
S ➤	SV000176	CCIP - CompuCALL Agent/Port License	100.00	H
S ➤ Δ	SV000177	Web Call Back	12,000.00	H
S ➤ Δ	SV000252	Message Taker	12,000.00	H
S ➤ Δ	SV000253	Voice Form	12,000.00	H
S ➤ Δ	SV000254	Agent Whisper	8,000.00	H
S ➤ Δ	SV000255	CCIP Screen Pop.	15,000.00	H
S ➤ Δ	SV000257	TAPI Integration - Remote Installation	9,000.00	H
S ➤ Δ	SV000259	TAPI Integration - Solution Pro	19,500.00	H
S ➤ Δ	SV000260	ACD Fax Pop	40,000.00	H
S ➤ Δ	SV000261	Enhanced IVR Reports	15,000.00	H
S ➤ Δ	SV000262	Follow Me Service	8,500.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

SYMPOSIUM

SYMPOSIUM OPEN IVR 4.0

Common Options

S ➤	NTV400KA	Keylock	185.00	H
S ➤	NTV400LA	License File	9.00	H
S ➤	NTV401PA	Supplementary Patch CD	No charge	
S ➤	NTV401SA	System Recovery Boot Package	145.00	H
S ➤ Δ	NTV402AA	Base Documentation Package, North America	320.00	H
S ➤ Δ	NTV402CA	Full Documentation Package (CD)	46.00	H
S ➤	NTV403EA	Ethernet Adapter Kit	350.00	H
S	NTV403TA	Token Ring Adapter Kit	880.00	H
S ➤	NTV404LA	Monitor - 21"	3,200.00	H
S ➤	NTV404MA	Monitor - 17"	1,220.00	H
S ➤	NTV404SA	Monitor - 14"	360.00	H
S ➤	NTV405UA	Uninterruptible Power Supply (UPS) 110V - OIVR 4.0 Tower AP, MRS/AP, or MRS/Tower	950.00	H
S ➤	NTV406CA	SCSI CD-ROM Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	320.00	H
S ➤	NTV406DA	SCSI DAT Tape Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	1,180.00	H
S ➤	NTV406RA	SCSI 4.5GB Hard Drive for OIVR 4.0 MRS/Rack and Rack AP	630.00	H
S ➤	NTV406TA	SCSI 4.5GB Hard Drive for OIVR 4.0 Tower AP, MRS/AP, MRS/Tower	640.00	H
S ➤	NTV407MA	64MB RAM Expansion for OIVR 4.0 AP, MRS/AP and MRS	570.00	H
S ✓ ➤	NTV460SA	Software-Based Disk Mirroring License RTU - OIVR 4.0 AP, MRS, or MRS/AP	3,490.00	H

AP and AP - Unique Options

S ➤	NTV410BA	Base AP (700tp), 0 Port - Global	16,800.00	D
S ➤	NTV411NA	Regional Supplement to Base AP - North America	650.00	H
S ✓ ➤	NTV412RA	AP Redundancy - 1 Voice Port RTU for 1 AP	170.00	H
S ➤	NTV413AA	Base AP/Rack, AC, Global	21,300.00	D
S ➤	NTV413DA	Base AP/Rack, DC, Global	22,100.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
MRS Tower - Unique Options				
S ➤	NTV420AA	Base MRS/Tower, 0 Port - Global	17,730.00	D
S ➤	NTV420KA	Keyboard and Mouse for Base MRS/Tower	130.00	H
S ➤	NTV421NA	Regional Supplement to Base MRS/Tower - North America	275.00	H
MRS/Rack and MRS/Rack - Unique Options				
S ➤	NTV430AA	Base MRS/Rack, AC, 0 Port - Global	19,880.00	D
S ➤	NTV430DA	Base MRS/Rack, DC, 0 Port - Global	20,665.00	D
S ➤	NTV430RA	Redundant DC Power for Base MRS/Rack or Rack AP	2,110.00	H
S ➤	NTV430SA	Redundant AC Power for Base MRS/Rack or Rack AP	1,890.00	H
S ➤	NTV431NA	Regional Supplement to Base MRS/Rack (AC or DC) - North America	275.00	H
MRS/AP and MRS/AP - Unique Options				
S ➤	NTV440BA	Base MRS/AP (700tp), 0 Port - Global	16,800.00	D
S ➤	NTV441NA	Regional Supplement to Base MRS/AP - North America	650.00	H
AP and MRS/AP Options				
S ✓ ➤	NTV450CA	Custom Cell Builder RTU - 1 AP (or MRS/AP)	2,670.00	D
S ➤	NTV450LA	Development License - 4 Users	26,680.00	D
S ✓ ➤	NTV450MA	Development License Upgrade - 1 to 4 Users	22,810.00	D
S ✓ ➤	NTV450PA	Prompt Manager and Loading Tool - 1 AP (or MRS/AP)	2,560.00	D
S ✓ ➤	NTV450SA	Development License - 1 User	20,810.00	D
S ➤	NTV452EA	Host Connectivity Hardware - Ethernet Adapter Kit (For TN3270 or TN5250 Option)	350.00	H
S ➤	NTV452SA	Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option)	1,650.00	H
S ➤	NTV452TA	Host Connectivity Hardware - Token Ring Adapter Kit (For SNA3270 or SNA5250 Option)	880.00	H
S ➤	NTV452VA	Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)	1,580.00	H
S ➤	NTV452WA	Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)	940.00	H
S ➤	NTV453AA	Host Connectivity Software - SNA3270 - Base and 16 Session RTU	12,000.00	D
S ➤	NTV453BA	Host Connectivity Software - TN3270 - Base and 16 Session RTU	12,000.00	D
S ➤	NTV453SA	Host Connectivity Software - SNA3270 - 16 Session RTU Expansion	10,625.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTV453TA	Host Connectivity Software - TN3270 - 16 Session RTU Expansion	10,500.00	D
S ✓ ➤	NTV454VA	Host Connectivity Software - VT100 - 16 Session Base RTU	7,550.00	D
S ✓ ➤	NTV454WA	Host Connectivity Software - VT100 - 16 Session RTU Expansion	7,550.00	D
S ✓ ➤	NTV455AA	Host Connectivity Software - SNA5250 - Base and 16 Session RTU	12,000.00	D
S ✓ ➤	NTV455BA	Host Connectivity Software - TN5250 - Base and 16 Session RTU	12,500.00	D
S ✓ ➤	NTV455SA	Host Connectivity Software - SNA5250 - 16 Session RTU Expansion	10,500.00	D
S ✓ ➤	NTV455TA	Host Connectivity Software - TN5250 - 16 Session RTU Expansion	10,500.00	D
S ➤	NTV456AA	Database Connectivity Software - INFORMIX - RTU	5,250.00	D
S ➤	NTV456BA	Database Connectivity Software - INGRES - RTU	5,250.00	D
S ➤	NTV456CA	Database Connectivity Software - ORACLE - RTU	5,250.00	D
S ➤	NTV456DA	Database Connectivity Software - SYBASE - RTU	5,250.00	D
S ➤	NTV456MA	Database Connectivity Software - Microsoft SQL Server - RTU	6,750.00	D
S ✓ ➤	NTV457PA	PureSpeech Recite Development Kit - 1 AP RTU	16,370.00	H
S ➤	NTV457WA	Web Integration Software - 1 AP RTU	13,000.00	D
S ➤	NTV482SA	Integration Package for Meridian Link (SCCS Version) - Base and 4 Port RTU. Integration Package for Meridian Link (SCCS Version) - Base and 4 Port RTU	400.00	D
S ➤	NTV482TA	Integration Package for Meridian Link (SCCS Version) - 4 Port Expansion RTU. Integration Package for Meridian Link (SCCS Version) - 4 Port Expansion RTU	375.00	D

MRS Tower, MRS/Rack and MRS/AP Options

S ➤	NTV460AA	ADSI License RTU - 1 AP (or MRS/AP)	15,700.00	D
S ✓ ➤	NTV461NA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America	23,520.00	H
S ✓ ➤	NTV461PA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America - Pulse Detection	26,360.00	H
S ✓ ➤	NTV462NA	Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America	33,620.00	H
S ➤	NTV462PA	North American ISDN PRI Option for 24 Port T1 Card	2,200.00	H
S ➤	NTV462TA	Line Side T1 Support - RTU For 24 Port T1 - Spanish	880.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTV464NA	Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA	6,250.00	H
S ➤	NTV464ZA	Dial Pulse Detection for any 4 Port Loopstart Card	1,825.00	H
S ✓ ➤	NTV467LA	Fax - Gammalink - 12 Port Card and 12 Port RTU	34,170.00	D
S ✓ ➤	NTV467MA	Fax - Gammalink - 6 Port Card and 6 Port RTU	17,610.00	D
S ✓ ➤	NTV467SA	Fax - Gammalink - 4 Port Card and 4 Port RTU	12,810.00	D
S ✓ ➤	NTV468CA	Text to Speech - TrueVoice - Base Card and 2 Port RTU	14,200.00	D
S ✓ ➤	NTV468LA	Text to Speech - L and H - Base Card and 6 Port RTU	22,520.00	D
S ✓ ➤	NTV468PA	Speech Recognition - PureSpeech Recite - Continuous Digits - Base Card and 2 Port RTU	15,000.00	D
S ✓ ➤	NTV468QA	Speech Recognition - PureSpeech Recite - Lite - Base Card and 2 Port RTU	18,790.00	D
S ✓ ➤	NTV468RA	Speech Recognition - PureSpeech Recite - Pro - Base Card and 2 Port RTU	21,600.00	D
S ✓ ➤	NTV468SA	Speech Recognition - PureSpeech Recite - IQ - Base Card and 2 Port RTU	24,250.00	D
S ✓ ➤	NTV468TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - Base Card and 2 Port RTU	15,610.00	D
S ✓ ➤	NTV468UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - Base Card and 2 Port RTU	20,160.00	D
S ✓ ➤	NTV468VA	Speech Recognition - VCS for Antares - Discrete - Base Card and 4 Port RTU	18,670.00	D
S ✓ ➤	NTV468WA	Speech Recognition - VCS for Antares - Continuous - Base Card and 2 Port RTU	14,960.00	D
S ✓ ➤	NTV468YA	Speech Recognition - PureSpeech Recite - LA Spanish - Pro - Base Card and 2 Port RTU	23,540.00	D
S ✓ ➤	NTV468ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - Base Card and 2 Port RTU	26,710.00	D
S ✓ ➤	NTV469CA	Text to Speech - TruVoice - 2 Port RTU Expansion	5,420.00	D
S ✓ ➤	NTV469LA	Text to Speech - L and H - 6 Port RTU Expansion	13,010.00	D
S ✓ ➤	NTV469PA	Speech Recognition - PureSpeech - Continuous Digits - 2 Port RTU Expansion	6,220.00	D
S ✓ ➤	NTV469QA	Speech Recognition - PureSpeech Recite - Lite - 2 Port RTU Expansion	10,010.00	D
S ✓ ➤	NTV469RA	Speech Recognition - PureSpeech Recite - Pro - 2 Port RTU Expansion	12,830.00	D
S ✓ ➤	NTV469SA	Speech Recognition - PureSpeech Recite - IQ - 2 Port RTU Expansion	15,470.00	D
S ✓ ➤	NTV469TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	6,840.00	D
S ✓ ➤	NTV469UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - 2 Port RTU Expansion	11,380.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTV469VA	Speech Recognition - VCS for Antares - Discrete - 4 Port RTU Expansion	9,890.00	D
S ✓ ➤	NTV469WA	Speech Recognition - VCS for Antares - Continuous - 2 Port RTU Expansion	6,180.00	D
S ✓ ➤	NTV469YA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	14,770.00	D
S ✓ ➤	NTV469ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - 2 Port RTU Expansion	17,940.00	D

PEB-Based MRS or MRS/AP Expansions

S † ➤	NT3R12AA	OIVR 2 x Hardware - 12-Port Loopstart Voice Port Assembly	16,900.00	D
S ➤	NT3R76AA	OIVR 2 x Hardware Fax Support - 2 Ports	6,000.00	D
S ➤	NT3R76BA	OIVR 2 x Hardware Fax Support - 4 Ports	12,000.00	D
S ➤	NT3R76CA	OIVR 2 x Hardware Fax Support - 8 Ports	24,000.00	D
S † ➤	NT3R77AA	OIVR 2 x Hardware - Discrete Speech Recognition - 4 Ports	14,300.00	D
S † ➤	NT3R77BA	OIVR 2 x Hardware - Discrete Speech Recognition - 4 Port Expansion	14,300.00	D
S † ➤	NT3R78AA	OIVR 2 x Hardware - Continuous Speech Recognition - 2 Ports	14,300.00	D
S † ➤	NT3R78BA	OIVR 2 x Hardware - Continuous Speech Recognition 2 Port Expansion	14,300.00	D
S † ➤	NT3R79BA	OIVR 2 x Hardware - Text-to-Speech 4 Port Expansion	17,200.00	D
S ✓ ➤	NTV462NA	Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America	33,620.00	H
S ✓ ➤	NTV464NA	Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA	6,250.00	H
S ➤	NTV481PA	Pentium SBC Upgrade for PEB-based MRS	2,995.00	H

Site Options

S ➤	NTV472AA	AC Rack Cabinet - Full Assembly	5,965.00	H
S ➤	NTV472BA	AC Rack Cabinet - Expansion	2,625.00	H
S ➤	NTV472DA	DC Rack Cabinet - Full Assembly	5,985.00	H
S ➤	NTV472YA	DC Rack Cabinet - Expansion	2,645.00	H
S ➤	NTV474NA	(UPS) Shared Rack Model - 110V - Up to 4 MRS/Rack or AP/ Rack Shelves	3,400.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Application, Upgrade and Bundled Packages				
S ➤	NTV481CA	Software Upgrade - Open IVR 2.01/2.5 to 4.0 (PEB) - Media (CD) and 1 AP or MRS/AP RTU	4,500.00	D
S ➤	NTV481DA	Release 2.X Development to Release 4.0 Development Upgrade	470.00	D
S ➤	NTV481HA	Software Upgrade - Host Connectivity Software Upgrade - R2 AP or MRS/AP	130.00	D
S ➤	NTV481LA	Software Upgrade - OPEN IVR 2.01/2.5 to 4.0 (PEB) - L and H TTS Dongle Replacement	130.00	D
S ➤	NTV481UA	Software Upgrade - UPS Software Upgrade - R2 AP, MRS/AP	130.00	D
S ➤	NTV482MA	Integration Package for Meridian Link - Media (CD) and 4 Port Base RTU	400.00	D
S ➤	NTV482NA	Integration Package for Meridian Link - 4 Port Expansion RTU	375.00	D
Spares Packages				
S ➤	NTV404LA	Monitor - 21"	3,200.00	H
S ➤	NTV404MA	Monitor - 17"	1,220.00	H
S ➤	NTV404SA	Monitor - 14"	360.00	H
S ➤	NTV406CA	SCSI CD-ROM Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	320.00	H
S ➤	NTV406DA	SCSI DAT Tape Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	1,180.00	H
S ➤	NTV406RA	SCSI 4.5GB Hard Drive for OIVR 4.0 MRS/Rack and Rack AP	630.00	H
S ➤	NTV406TA	SCSI 4.5GB Hard Drive for OIVR 4.0 Tower AP, MRS/AP, MRS/Tower	640.00	H
S ➤	NTV481SA	Software Upgrade - OPEN IVR 2.0/2.5 to 4.0 (PEB) - Serial Board Upgrade for R2 MRS with Speech Recognition Option	90.00	H
S ➤	NTV491NA	Voice Port Assembly - 16 Port Loopstart Spare - North America	3,995.00	H
S ➤	NTV491PA	Voice Port Assembly - 16 Port Loopstart Spare - North America - PULSE DETECTION	5,435.00	H
S ➤	NTV492NA	Voice Port Assembly - 24 Port T1 Spare - North America	4,995.00	H
S ➤	NTV494NA	Voice Port Assembly - 4 Port Loopstart Spare - North America and CALA	1,200.00	H
S ➤	NTV497LA	Fax - Gammalink - 12 Port Card Spare	7,150.00	H
S ➤	NTV497MA	Fax - Gammalink - 6 Port Card Spare	3,800.00	H
S ➤	NTV497SA	Fax - Gammalink - 4 Port Card Spare	3,050.00	H
S ➤	NTV498PA	DSP Card Spare for Speech Recognition or Text-to-Speech	4,750.00	H
S ➤	NTVE9009	PCI 10MB Ethernet Adapter Spare	250.00	H
S ➤	NTVE9013	101 Enhanced Keyboard Spare	50.00	H
S ➤	NTVE9014	3-Button Mouse Spare	75.00	H
S ➤	NTVE9016	External Modem Spare	275.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTVE9041	PCI Video Adapter Spare for OIVR 4.0 AP, MRS/AP, or MRS	100.00	H
S ➤	NTVE9044	Rackmount Keyboard Drawer Spare	285.00	H
S ➤	NTVE9045	19" Rackmount Monitor Enclosure Spare	365.00	H
S ➤	NTVE9901	Ethernet Cable 25 Ft. Spare	6.00	H
S ➤	NTVE9903	32MB Expansion RAM for MRS/Tower or MRS/Rack Spare	285.00	H
S ➤	NTVE9906	Base Chassis for OIVR 4.0 Tower AP and MRS/Tower Spare	3,150.00	H
S ➤	NTVE9907	Base Single Board Computer for MRS/Tower or MRS/Rack Spare	1,900.00	H
S	NTVE9908	Wide to Narrow SCSI Cable Adapter Spare	85.00	H
S ➤	NTVE9909	AT to PS/2 Keyboard Cable Adapter Spare	7.00	H
S ➤	NTVE9910	Wide SCSI Cable - 68 Pin Spare	200.00	H
S ➤	NTVE9911	Base Chassis for MRS/Rack - AC Power Spare	7,400.00	H
S ➤	NTVE9912	System Peripheral Switch - 8 Way Spare	1,750.00	H
S ➤	NTVE9913	Base Chassis for MRS/Rack - DC Power Spare	7,950.00	H
S ➤	NTVE9915	Rackmount Cabinet for MRS/Rack - 21" Spare	2,200.00	H
S ➤	NTVE9917	Front or Rear Door Kit for Rack Cabinet Spare	370.00	H
S ➤	NTVE9919	Power Bar - 6 Outlets - 2 Meters Cable Spare	225.00	H
S ➤	NTVE9921	DC Power Supply for Rack Cabinet Spare	225.00	H
S ➤	NTVE9923	16MB Expansion RAM for OPEN IVR 2 x AP or MRS/AP Spare	275.00	H
S ➤	NTVE9924	Blank DAT Tape - 4/8GB Spare	35.00	H
S ➤	NTVE9925	Blank QIC Tape - 2.5GB Spare	75.00	H
S ➤	NTVE9926	Head Cleaner DAT Tape Spare	25.00	H
S ➤	NTVE9927	48V DC 400W Load Sharing Hot Swap Power Supply Spare	2,125.00	H
S ➤	NTVE9928	DC Power Cable for PS400-48 Power Supply Spare	100.00	H
S	NTVE9933	Power Supply without 3.3V Output (3 Rail) Spare	1,360.00	H
S	NTVE9934	Fan Filter Air Spare OIVR 4 MRS/Rack or Rack AP	11.00	H
S	NTVE9935	Fan Filter Air (2) Spare OIVR 4 MRS/Rack or Rack AP	11.00	H
S	NTVE9936	Assembly DC Entry Spare	740.00	H
S	NTVE9937	16/1/3 Passive Backplane Spare OIVR 4 MRS/Rack or Rack AP	688.00	H
S Δ	NTVE9938	Hard Drive Mounting Screw for Hot Swappable Drive (1000rp) Spare MRS/Rack or Rack AP	No charge	
S	NTVE9939	Alarm Status Board Spare OIVR 4 MRS/Rack or Rack AP	661.00	H
S	NTVE9940	Fan Module (each) Spare OIVR 4 MRS/Rack or Rack AP	312.00	H
S	NTVE9941	SCSI Backplane Spare OIVR 4 MRS/Rack or Rack AP	459.00	H
S	NTVE9942	Assembly AC Entry Spare OIVR 4 MRS/Rack or Rack AP	277.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NTVE9943	6 Drive SCSI Rack Assembly Spare OIVR 4	459.00	H
S	NTVE9944	SCSI Rack Drive Carrier (each) Spare OIVR 4	70.00	H
S	NTVE9945	Power Supply 350W Spare OIVR 4 AP, MRS/AP	523.00	H
S	NTVE9946	Assembly 3-Fan 62XX Spare OIVR 4 AP, MRS/AP, MRS Tower	239.00	H
S	NTVE9947	Fan Air Filter Spare OIVR 4 AP, MRS/AP, MRS Tower	18.00	H
S	NTVE9951	Share UPS Spare for OIVR 4.0 MRS/Rack or Rack AP	460.00	H
S	NTVE9952	Simple Signaling Cable for OIVR 4.0 Rack UPS	45.00	H
S	NTVE9953	Keyboard/Monitor/Mouse Cable, Switch Box-to-Peripherals	165.00	H
S	NTVE9954	UPS Smart Signalling Cable Spare	46.00	H
S	NTVE9955	-5V ISA Card Spare for Rack AP and MRS/Rack	130.00	H
S	NTVE9957	Rack AP or MRS/Rack Server-to-Switch Box Cable Spare	165.00	H
S	NTVE9958	Tower AP or Tower MRS/AP Wide SCSI Terminator Spare	32.00	H

PEB-Based Spares

S † ➤	A0622896	OIVR 2 x Hardware - Tape Drive (2.5GB)	945.00	H
S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H
S ➤	A0633585	Tandberg Tape Drive Cleaning Kit	84.00	H
S	A0636813	T1 Port Assembly (24 ports)	14,815.00	H
S Δ	A0638483	Keyboard	60.00	H
S ➤ Δ	A0639229	AP Token Ring Lan Interface Kit	860.00	H
S † ➤	A0639513	OIVR 2.X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)	80.00	H
S † ➤	A0639530	OIVR 2 x Hardware - 256KB L2 Async Cache for AP or MRS/ AP	125.00	H
S † ➤	A0639569	OIVR 2 x Hardware - Expansion RAM - 8MB SIMM with Parity	445.00	H
S ➤	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity	300.00	H
S † ➤ Δ	A0640190	OIVR 2 x Hardware - MRS/Tower Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - SCSI Cable - Floppy Cable	10,000.00	H
S † ➤ Δ	A0640192	OIVR 2 x Hardware - MRS/Rack DC Spares Kit. - CPU Module and Memory - DC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - SCSI Cable - Floppy Cable	10,650.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤ Δ	A0640194	OIVR 2 x Hardware - MRS/Rack AC Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - Floppy cable	10,000.00	H
B ➤	A0646699	Key and Lock Master	70.00	H
S † ➤	A0646715	OIVR 2 x Hardware - Drive LED Panel for AP or MRS/AP	45.00	H
S † ➤	A0647317	OIVR 2 x Hardware - Fan (100cfm)	85.00	H
S † ➤	A0650996	OIVR 2 x Hardware - 12-port Loopstart Network Interface Module	2,965.00	H
S † ➤	A0651032	OIVR 2 x Hardware - VRP Voice Recognition Card	5,370.00	H
S † ➤	A0651035	OIVR 2 x Hardware - 12-port Voice Processing Card	5,185.00	H
S † ➤	A0651036	OIVR 2 x Hardware - Serial I/O Controller for MRS	75.00	H
S † ➤	A0651037	OIVR 2 x Hardware - SCSI Disk Controller for MRS	685.00	H
S † ➤	A0651038	OIVR 2 x Hardware - 1.05GB Disk Drive (Tower)	1,575.00	H
S † ➤	A0651039	OIVR 2 x Hardware - 1.05GB Disk Drive (Rack)	1,575.00	H
S † ➤	A0651040	OIVR 2 x Hardware - Ethernet Controller for MRS	400.00	H
S † ➤	A0651041	OIVR 2 x Hardware - Token Ring Controller for MRS	1,250.00	H
S † ➤	A0651060	OIVR 2 x Hardware - CPU Module with no Memory	2,925.00	H
S † ➤	A0651062	OIVR 2 x Hardware - CPU Module with 32MB Memory	7,410.00	H
S † ➤	A0651064	OIVR 2 x Hardware - 450W Power Supply (Tower)	1,710.00	H
S † ➤	A0651350	OIVR 2 x Hardware - Digiboard DTE 8 Port DB25 Male Cable	125.00	H
B	A0651681	RT Clock Chip	35.00	H
S † ➤	A0652633	OIVR 2 x Hardware - 2 Port Brooktrout Fax Card	4,200.00	H
S † ➤	A0652634	OIVR 2 x Hardware - 4 Port Brooktrout Fax Card	8,400.00	H
S † ➤	A0652635	OIVR 2 x Hardware - 8 Port Brooktrout Fax Card	16,800.00	H
S † ➤	A0652638	OIVR 2 x Hardware - Apertus Communications Board (SDLC)	1,945.00	H
S † ➤	A0652681	OIVR 2 x Hardware - 350W DC Power Supply (Rack)	2,000.00	H
S † ➤	A0652687	OIVR 2 x Hardware - Redundant DC Power Supply for MRS/ Rack	2,000.00	H
S † ➤	A0652688	OIVR 2 x Hardware - 350W AC Power Supply (Rack)	1,370.00	H
S	A0654949	MRS to UPS Communications Cable	80.00	H
S † ➤	A0656847	OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP	925.00	H
S † ➤	A0656874	OIVR 2 x Hardware - Cable, LCD for AP or MRS/AP	110.00	H
S † ➤	A0657566	OIVR 2 x Hardware - 10 position Connector PEB Cable	60.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	A0657728	OIVR 2 x Hardware - MRS to Terminal Cable (DB25F to DB25M)	25.00	H
S † ➤	A0657730	OIVR 2 x Hardware - Loopstart Interface Cable (DB25F to RJ23X)	245.00	H
S † ➤	A0657777	OIVR 2 x Hardware - CPU Module Battery for MRS	40.00	H
S † ➤	A0658110	OIVR 2 x Hardware - MRS/Tower Air Filter	25.00	H
S † ➤	A0658485	OIVR 2 x Hardware - 6 Ft. SCSI Cable for MRS	50.00	H
S † ➤	A0658488	OIVR 2 x Hardware - Floppy Cable for MRS	45.00	H
S † ➤	A0658655	OIVR 2 x Hardware - Keylock Adapter	125.00	H
S † ➤	A0658690	OIVR 2 x Hardware - MRS/Rack Fan Assembly	245.00	H
S † ➤	A0658957	OIVR 2 x Hardware - Floppy Disk Drive for MRS	140.00	H
S ➤	A0659125	OIVR 2 x Hardware - Cabinet Rail Assembly	500.00	H
S † ➤	A0659158	OIVR 2 x Hardware - Riser Board for AP or MRS/AP	100.00	H
S ➤ Δ	A0666779	CPU Kit Including Installed Heatsink Adhesive and Clip for Pentium Processor	345.00	H
S † ➤ Δ	NT3R23BA	OIVR 2.x Hardware - MRS/AP or AP Token Ring LAN Interface	880.00	H
S ➤	NT3R67AA	OIVR 2 x Hardware - MRS System Recovery Software Ethernet	No charge	
S ➤	NT3R67BA	OIVR 2 x Hardware - MRS System Recovery Software Token Ring	No charge	
S ➤	NT3R75AA	OIVR 2.X Hardware - MRS/Tower or MRS/Rack Ethernet Lan Interface	375.00	H
S ➤	NT3R75BA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Token Ring LAN Interface	1,150.00	H
S ✓ † ➤	NTRH9013	OIVR 2 x Hardware - Keyboard	60.00	D
S † ➤	NTZK14AA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Disk Drive (1.05GB)	2,100.00	H

Documentation Spares Packages

S Δ	NTVE8202	OPEN IVR Release 4 - Product Guide	47.00	H
S Δ	NTVE8203	OPEN IVR Release 4 - System Administration Guide	47.00	H
S Δ	NTVE8204	OPEN IVR Release 4 - Installation, Upgrade and Maintenance	47.00	H
S Δ	NTVE8205	OPEN IVR Release 4 - Planning and Engineering Guide	47.00	H
S Δ	NTVE8206	OPEN IVR Release 4 - Error Messages Guide	47.00	H
S Δ	NTVE8207	OPEN IVR Release 4 - Service Console Interface Guide	47.00	H
S Δ	NTVE8208	OPEN IVR Release 4 - Cell Catalog Guide	47.00	H
S Δ	NTVE8209	OPEN IVR Release 4 - Application Development Guide	47.00	H
S Δ	NTVE8210	OPEN IVR Release 4 - Web Option Guide	47.00	H
S Δ	NTVE8211	OPEN IVR Release 4 - Fax Option Guide	47.00	H
S Δ	NTVE8212	OPEN IVR Release 4 - Speech Recognition Guide	47.00	H
S Δ	NTVE8213	OPEN IVR Release 4 - Text-To-Speech Guide	47.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	NTVE8214	SOIVR 4.0 - CAS & ISDN Signaling Option Guide	47.00	H
S Δ	NTVE8215	OPEN IVR Release 4 - Integration Package for Meridian Link Guide	47.00	H
S Δ	NTVE8218	OPEN IVR Release 4 - Prompt Import Utility Guide	47.00	H
S Δ	NTVE8221	OPEN IVR Release 4 - VT100 Configuration and Development Guide	47.00	H
S Δ	NTVE8224	Integration Package for Meridian Link (SCCS Version) User Guide. Integration Package for Meridian Link (SCCS Version) User Guide	47.00	H
S Δ	NTVE8227	OPEN IVR Release 4 - SNA Host Communications Guide	47.00	H

SYMPOSIUM Integrated IVR Release 2.2

Integrated IVR Release 2.2 System Information

Integrated IVR Release 2.2 is the evolution of Nortel's Meridian IVR Release 2. Integrated IVR Release 2.2 is part of Nortel's SYMPOSIUM portfolio of products.

Integrated IVR Release 2.2 is a Year 2000 compliant product available only as an upgrade to Meridian IVR Release 1 and Meridian IVR Release 2 customers.

Upgrades from Meridian IVR Release 1 to Meridian IVR Release 2 are no longer possible.

The addition of features and/or capacity to existing Meridian IVR Release 2 systems is possible but new orders of Meridian IVR Release 2 are no longer possible.

Integrated IVR Release 2.2 continues to use the same advanced open platform (Application Processor or AP) that is currently used by the Meridian IVR Release 2 product. It also introduces a number of improvements to the platform including the addition of a CDROM drive, a higher capacity hard drive and an increase in the standard available on-board RAM.

Integrated IVR Release 2.2 supports the functionality currently offered by Meridian IVR Release 1 and Meridian IVR Release 2 systems. It is based on a new, Year 2000 compliant version of the SCO UNIX operating system. Its features include a wide variety of enhanced LAN and Host computer connectivity protocols, advanced fax capabilities, an enhanced Graphical User Interface (GUI) for even easier application development, multi-lingual voice prompt capabilities, a multi-lingual GUI, enhanced reporting and statistics, local or remote database access using Sybase, Informix, Ingres, or Oracle SQL databases and the capacity to support 96 ports on a single AP.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 and Meridian Mail Considerations for Integrated IVR Release 2.2

Meridian 1 X11 Hardware and Software

Generic X11 Release 14 or later software.

Bundled software features include:

- Hold in Queue for IVR, package 218 (optional) X11 Release 18 or later.
- ACCESS enable software on Meridian Mail if not already equipped.

Note: Hold in Queue for IVR is a "no charge" option, however, if not all chargeable prerequisites are on your system profile, this software option number 218 will remain as an IOU from Nortel Networks. CCR Release 2 and Meridian Mail Release 8 are prerequisites for this feature. Bundled only on system types Option 21-81.

Meridian Mail Hardware and Software

- Release 9.66 or later software, with ACCESS Enable Option for Meridian 1 Option 21-81.
- Release 9.66 or later software, with ACCESS Enable Option for Meridian 1 Option 11.
- Meridian Mail system equipped with RSM card (for Modular EC systems, equipped on the utility card).
- RSM cards are available as part of the Distributed Networking Kit Packages. Refer to the Meridian Mail Section for pricing and ordering information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

The following table summarizes the compatible Meridian Mail software releases.

			Meridian Mail					Access Links		
Meridian Mail Platform	Switch I/F	Max. Ports	MM 9	MM 9.2	MM 9.4	MM 9.5	MM 9.6	MM 10-12	MM 8-9	MM 10-12[1]	# of APS
8 Meg Card Option	AML/ CSL	12			x		x	x	1	2	1
Modular Option Classic	AML/ CSL	64							2		1
Modular Option Classic (with MMP40)	AML/ CSL	64				x	x	x	2	8	1
Shelf Option	AML/ CSL	24							1		1
Shelf Option/MMP40	AML/ CSL	24				x	x	x[2]	1	6[2]	1
Modular Option EC	AML/ CSL	64	x			x	x		2		1
Modular Option EC (with MMP40)	AML/ CSL	96				x	x	x	2	8	1
Modular Option GP	SMDI	64							2		1
Modular Option GP (with MMP40)	SMDI	64				x	x	x	2	8	1
Message Services Module	SMDI	192		X			x	x	4	8	2

Note 1: A maximum of 8 links are supported from a single application processor.

Note 2: Access link determines number of channels supported across link.

Note 3: The earliest release of Meridian Mail that is Year 2000 compliant is Release 9.66.

The following table describes the ACCESS link capacity limits for shared and dedicated modes. This table can be used to calculate the correct number of ACCESS links for your system.

For one ACCESS link (in the following mode):	Number of Applications (Channels) at 4,800 bps	Number of Applications (Channels) at 9,600 bps	Number of Applications (Channels) at 19,200 bps (MM10)	Number of Applications (Channels) at 38,400 bps (MM10)
Dedicated mode	18	38	76	96
Shared mode	8	18	38	96

[1] Speed of ACCESS Links will vary according to the number of links and number of Meridian Mail nodes.
[2] Meridian Mail 10 only. Meridian Mail 11 and 12 are not supported on the shelf option with MMP40 platform.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

General Ordering Considerations for Integrated IVR Release 2.2

The purpose of this paragraph is to provide general ordering guidelines for Integrated IVR Release 2.2. Complete ordering information including ordering reles follow in the price book and should be observed when ordering Integrated IVR Release 2.2.

Integrated IVR Release 2.2 is only available as an upgrade from Meridian IVR Release 1 or Meridian IVR Release 2.

The first step in the ordering process is to upgrade the Meridian IVR Release 1 or Meridian IVR Release 2 system to Integrated IVR Release 2.2. There are three upgrade packages available and a few additional upgrade considerations to observe. The three upgrade packages are:

- NTV200AA / A0765550, Upgrade Package from Release 1.0 to Release 2.2
- NTV200BA / A0765551, Upgrade Package from a Release 2.08 Runtime System to a Release 2.2 Runtime System
- NTV200CA / A0765553, Upgrade Package from a Release 2.08 Development System to a Release 2.2 Development Development System

Note that all Release 1 systems are development systems.

The additional upgrade considerations to follow are:

Meridian IVR Release 2.08 systems that have the UPS and/or SNA host communications option must order the upgrade for that option:

NTV201AE / A0765561, SNA (3270/5250) Host Connectivity Upgrade from Release 2.08 to Release 2.2

NTV201AT / A0765581, UPS Software Upgrade from Release 2.08 to Release 2.2

Meridian IVR Release 1 systems that have the SNA host communications option must reorder that option separately from the upgrade package and as per the detailed ordering rules.

A Meridian IVR Release 1 or Release 2 system that has been upgraded to Integrated IVR Release 2.2 retains its original capacity and features. Customers can, at the time of the upgrade order or subsequently, expand the Integrated IVR Release 2.2 system by adding to it the following optional features and/or capacity:

- Voice Prompt/Database Editor (standard on development systems)
- Voice ports
- 3270 or 5250 SNA host communications over Token Ring or SDLC
- VT100 host communications over RS-232
- RDBMS connectivity (Oracle, Sybase, Informix or Ingres)
- Fax

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

- Uninterruptible Power Supply (UPS)
- Audio Line Interface (ALI)
- LAN card (Ethernet or Token Ring)
- Memory (64MB RAM is standard)
- ACCESS Cable Kit

Note that the RDBMS server and client software versions that are supported versions that are supported under Integrated IVR Release 2.2 are different from the versions that are supported under Meridian IVR Release 2. Nortel does not resell the RDBMS software but Meridian IVR Release 2 customers connecting to one of the supported databases should plan on upgrading their RDBMS software when upgrading to Integrated IVR Release 2.2.

Nortel recommends that all customers invest in spare components for their Integrated IVR Release 2.2 system: Power supply and hard disk spares for the AP are highly recommended.

- NTV202AH / A0765598, 525W Power Supply Spare
- NTV202AW / A0765599, 4.5GB SCA UltraSCSI Hard Disk Spare

SYMPOSIUM Integrated IVR Release 2.2 Packages

Options Upgrade

The Host Communications and UPS upgrades are only applicable to Meridian IVR 2.0/I customers that are upgrading to Integrated IVR 2.2. They must be ordered only if the MIVR 2.0/I system had the SNA Host Communications and/or the UPS option.

Options

Voice Prompt/Database Editor

A keycode (P0843070) must also be ordered to activate the Voice Prompt/Database Editor feature. A keycode must be ordered if any of the items on a purchase order require a keycode for activation. Each order can have a maximum of one keycode.

The Voice Prompt/Database Editor feature is standard on development systems.

S ➤	NT3R28AA	Voice Prompt/Database Editor for Run-Time Systems Only	800.00	D

Voice Ports

For example, if a customer wants to upgrade a 16 ports Run Time System to a Development System, the following needs to be done:

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

i) Purchase one NTV201AC IIVR 2.2 Runtime to Development Upgrade Base Package - 4 ports, which includes one:

NTV201AD IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports, for upgrading ports 1 to 4 of the system, together with the SCO Development license.

ii) Purchase three more NTV201AD IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports, for upgrading 3x4=12 ports for port numbers 5 to 16 of the system.

A keycode (P0843070) must also be ordered to activate the conversion to a Development System or expansion of a Development or Runtime System. A keycode must be ordered if any of the items on a purchase order require a keycode for activation. Each order can have a maximum of one keycode.

System maximum is 96 ports for Options 21-81 systems.

S † ➤	NTV201AA	IIVR 2.2 Voice Port Expansion - 4 ports - Development System	5,800.00	D
S † ➤	NTV201AB	IIVR 2.2 Voice Port Expansion - 4 ports - Runtime System	6,100.00	D
S † ➤	NTV201AC	IIVR 2.2 Runtime to Development Upgrade Base Package - 4 ports	2,000.00	D
S † ➤	NTV201AD	IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports	1,500.00	D

Host Communications
VT100

To order VT100 host communications for Integrated IVR Release 2.2, a customer must consider the system's configuration. If the system configuration already includes Digi's PC/Xem board, or if the total number of sessions does not exceed 7, then order:

NTV454VA/A0731788 Host Connectivity Software - VT100 - Base & 16 session

If the number of VT100 sessions required is greater than 7 and the system's configuration does not include Digi's PC/Xem board, then for a new order for VT100 host communications option, order:

NTV452VA/A0731782 Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)

NTV452WA/A0731783 Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)

NTV454VA/A0731788 Host Connectivity Software - VT100 - Base & 16 session

Else for an expansion order for VT100 host communications, order:

NTV452VA / A0731782 Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		NTV452WA / A0731788 Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)		
S ➤	NTV452VA	Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)	1,580.00	H
S ➤	NTV452WA	Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)	940.00	H
S ✓ ➤	NTV454VA	Host Connectivity Software - VT100 - 16 Session Base RTU	7,550.00	D

SNA

Each Integrated IVR Release 2.2 new order for SNA host communications consists of hardware, base software and 16 sessions. Customers can purchase additional sessions for SNA host communications. For example, to purchase 32 sessions of SNA3270 over SDLC, a customer would order one of:

NTV452SA/A0731780 SDLC Adapter Kit for SNA 3270/5250

NTV453AA/A0731784 Host Connectivity Software - SNA3270 - Base & 16 Session

NTV453SA/A0731786 Host Connectivity Software - SNA3270 - 16 Session RTU Expansion

To purchase subsequently a 32 session expansion for SNA3270, a customer would order two of:

NTV453SA/A0731786 Host Connectivity Software - SNA3270 - 16 Session RTU Expansion

NTV453SA/A0731786 Host Connectivity Software - SNA3270 - 16 Session RTU Expansion

S ➤	NTV452SA	Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option)	1,650.00	H
S ➤	NTV452TA	Host Connectivity Hardware - Token Ring Adapter Kit (For SNA3270 or SNA5250 Option)	880.00	H
S ➤	NTV453AA	Host Connectivity Software - SNA3270 - Base and 16 Session RTU	12,000.00	D
S ➤	NTV453SA	Host Connectivity Software - SNA3270 - 16 Session RTU Expansion	10,625.00	D
S ✓ ➤	NTV455AA	Host Connectivity Software - SNA5250 - Base and 16 Session RTU	12,000.00	D
S ✓ ➤	NTV455SA	Host Connectivity Software - SNA5250 - 16 Session RTU Expansion	10,500.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

RDBMS Connectivity

A keycode (P0843070) must also be ordered to activate the RDBMS connectivity A keycode must be ordered if any of the items on a purchase order require a keycode for activation. Each order can have a maximum of one keycode.

This software is used to support the database transactions between the IVR system and the SQL database. This software does not include the database. The customer must purchase their databases directly from the vendor.

S ➤	NTV456AA	Database Connectivity Software - INFORMIX - RTU	5,250.00	D
S ➤	NTV456BA	Database Connectivity Software - INGRES - RTU	5,250.00	D
S ➤	NTV456CA	Database Connectivity Software - ORACLE - RTU	5,250.00	D
S ➤	NTV456DA	Database Connectivity Software - SYBASE - RTU	5,250.00	D

Fax

The customer must provision the software license of the initial two ports and then additional single port expansions up to a maximum of 8 ports for the AP. For example, if a customer wants to have eight fax ports, he would select a NTV201AR/A0765579 IIVR 2.2 Fax Response Software Base Package - 2 ports

for the initial two ports and six of NTV201AS/A0765580 IIVR 2.2 Fax Response Software Expansion - 1 port for the additional six port's software license.

The fax hardware comes in increments of four ports which include a 4-port fax board and a RJ-11 cable In the above example, the customer has purchased the software license of eight fax ports. To have the hardware to support eight ports, two of: NTV201AQ/A0765578 IIVR 2.2 Fax Response Hardware - 4 ports have to be purchased.

A keycode (P0843070) must also be ordered to activate the number of fax ports. A keycode must be ordered if any of the items on a purchase order require a keycode for activation. Each order can have a maximum of one keycode.

S † ➤	NTV201AQ	IIVR 2.2 Fax Response Hardware - 4 ports	4,500.00	H
S † ➤	NTV201AR	IIVR 2.2 Fax Response Software Base Package - 2 ports	4,500.00	D
S † ➤	NTV201AS	IIVR 2.2 Fax Response Software Expansion - 1 port	2,250.00	D

UPS

S ✓ † ➤	NTV201AU	IIVR 2.2 UPS Package	1,260.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Audio Line Interface				
S ➤	NT1R16BB	Meridian IVR Audio Line Interface Kit	300.00	D
LAN Interface				
		Choose one LAN adapter only.		
S ➤	NTV403EA	Ethernet Adapter Kit	350.00	H
S	NTV403TA	Token Ring Adapter Kit	880.00	H
Memory Expansion				
		All systems are equipped with 64MB of memory. Depending on the number of ports as well as feature mix, additional memory may have to be provisioned. Please use the formula in the Integrated IVR 2.2 update documentation to calculate amount of memory required.		
		Maximum amount of RAM on the AP is 128MB.		
S † ➤	NTV201AV	Integrated IVR 2.2 Memory Package 32 MB	500.00	H
Meridian ACCESS Cable Kit				
S ➤	NT8R01AA	Meridian IVR ACCESS Link Cable Kit	575.00	D
Enhancements CD				
S ➤	NTV201BA	IIVR 2.2 Supplementary Patch CD	15.00	H
Hardware				
		Keylock must be initialized with system serial number by NT manufacturing.		
		The Keylock Adapter cannot be ordered except with a keycode (P0843070). The original keylock adapter must be shipped back to Nortel.		
S ➤	A0386050	Keylock Software Security Device	450.00	D
S † ➤	NTV202AB	16MB RAM Spare	225.00	H
S ➤	NTV202AC	256KB L2 Async Cache Spare	125.00	H
S ✓ † ➤	NTV202AD	1000VA UPS Hardware Spare	1,260.00	H
S † ➤	NTV202AE	512KB Video RAM Spare	80.00	H
S † ➤	NTV202AF	Tape Backup Unit Spare	945.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤	NTV202AH	525W Power Supply Spare	925.00	H
S † ➤	NTV202AJ	Digi PC/Xem Spare	1,445.00	H
S † ➤	NTV202AK	IIVR 2.2 Fax Card Spare	4,075.00	H
S † ➤	NTV202AL	Floppy Drive Spare	100.00	H
S † ➤	NTV202AW	4.5GB SCA UltraSCSI Hard Disk Spare	630.00	H
S ➤	NTV452SA	Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option)	1,650.00	H
S ➤	NTVE9009	PCI 10MB Ethernet Adapter Spare	250.00	H
S ➤	NTVE9013	101 Enhanced Keyboard Spare	50.00	H
S ➤	NTVE9014	3-Button Mouse Spare	75.00	H
S ➤	NTVE9016	External Modem Spare	275.00	H
S ➤	P0843070	MIVR Software Reproduction	210.00	H
Software				
S † ➤	NTV202AA	IIVR 2.2 Software Media	65.00	H
Cables				
S ➤	NT8R01AA	Meridian IVR ACCESS Link Cable Kit	575.00	D
S † ➤	NTV202AP	8 port DCE DB25 Octa Cable Spare	125.00	H
S † ➤	NTV202AY	Modem Cable, 10 ft., DB9 Female to DB25 Male	40.00	H
Documentation				
S ➤ Δ	NT3R51AA	IVR Operational Documentation Package	100.00	H
S ➤ Δ	NT3R52AA	IVR Development Documentation Package	100.00	H
S † ➤ Δ	NTV202AM	IIVR 2.2 Update Documentation Package	50.00	H

SYMPOSIUM Call Center

SYMPOSIUM Express Call Center Software

S >> #	NT9F17AA	SYMPOSIUM Express Call Center - 1 Agent Increment	570.00	D
S >> #	NT9F17BA	SYMPOSIUM Express Call Center - 5 Agent Increment	2,300.00	D
S >> #	NT9F17CA	SYMPOSIUM Express Call Center - 10 Agent Increment	4,000.00	D
S >> #	NT9F19AA	SYMPOSIUM Express Call Center Replacement/Up-Issue Software Package	50.00	H
S ➤	NT9F19AB	Symposium Express Call Center 2.0 Replacement/Up-Issue Software Package	50.00	H
S >> # Δ	NTHF01AA	Symposium Express Call Center Release 1.0 Server Application CD		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S >> #	NTHF02AA	SYMPOSIUM Express Call Center Release 1.0 Client Application CD, English	50.00	H
S ➤	NTHF02AB	SYMPOSIUM Express Call Center Release 2.0 Client Application CD, English	50.00	H
S >> #	NTHF03AA	SYMPOSIUM Express Call Center Supplementary CD	50.00	H
S ➤	NTHF03AB	Symposium Express Call Center Supplementary CD	50.00	H
S ➤	NTHF24AB	SYMPOSIUM Express Call Center Release 2.0 Base System	8,000.00	D
S ➤	NTHF28AB	Symposium Express Call Center 1 Agent Increment	570.00	D
S ➤	NTHF29AB	Symposium Express Call Center 5 Agent Increment	2,300.00	D
S ➤	NTHF30AB	Symposium Express Call Center 10 Agent Increment	4,000.00	D
S ➤	NTHF63AA	SYMPOSIUM Express Call Center Release 2.0 Base System Upgrade from Release 1.0	600.00	D

SYMPOSIUM Express Call Center Merchandise

S ➤	A0383333	Transceiver	560.00	H
S ✓ ➤	A0645811	Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A	30.00	H
S	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	175.00	D
S ➤	NTDK27AA	Ethernet Adapter Cable	75.00	D
S ✓ ➤	NTHF35AA	SYMPOSIUM Express Call Center LAN Package Option 11C	1,030.00	H
S ✓ ➤	NTHF36AA	SYMPOSIUM Express Call Center LAN Package, Options 61C-81C	1,740.00	H
S ✓ ➤	NTHF69AA	Symposium Express Call Center LAN Package, 51C	1,091.00	H
S ➤ Δ	SV000399	SYMPOSIUM Express Call Center Installation and Configuration Service	5,900.00	H

SYMPOSIUM Express Call Center Documentation

S >> # Δ	NTHF06AA	SYMPOSIUM Express Call Center Documentation CD	50.00	H
S ➤ Δ	NTHF06AB	SYMPOSIUM Express Call Center Documentation CD	50.00	H
S ➤ Δ	NTHF07AC	SYMPOSIUM Express Call Center Documentation Suite	150.00	H
S Δ	P0887335	SYMPOSIUM Express Call Center Planning, Installation and Administration Guide, English	50.00	H
S Δ	P0907622	SYMPOSIUM Express Call Center Management Guide	50.00	H
S Δ	P0907624	SYMPOSIUM Express Call Center Server Reports and Displays Guide	50.00	H
S Δ	P0908782	SYMPOSIUM Express Call Center Task Flow Guide	50.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ Δ	P0909663	Symposium Express Call Center Addendum to Planning, Installation, and Administration Guide	50.00	H

SYMPOSIUM Call Center Server
Server Base Software

S ➤	NT9F41AD	Release 3.0 Base Software and Documentation	3,980.00	D
S ➤	NT9F51AC	SYMPOSIUM Call Center Server Release 1.5 Replacement Software	500.00	D
S Δ	NT9F84AA	Symon View	50.00	H
S Δ	NTZC70AA	Base Software Features Package - Options 153 and 209	No charge	
S Δ	NTZC70BA	Software Features Package (CCS100) - Options 214, 215, 218	No charge	
S Δ	NTZC70CA	Software Features Package (CCS300) - Option 207	No charge	
S Δ	NTZC70DA	Software Features Package (Base) - Options 42, 43, 50, 114, and 155	No charge	

System Software
CCS 100 Software

S ➤	NT9F02AA	Call Center Software 100, New System (1 Agent)	720.00	D
S ✓ ➤	NT9F02BA	Call Center Software 100, New System (10 Agent)	6,528.00	D
S ✓ ➤	NT9F02CA	Call Center Software 100, New System (50 Agent)	29,292.00	D
S ✓ ➤	NT9F02DA	Call Center Software 100, New System (100 Agent)	51,888.00	D
S ✓ ➤	NT9F02EA	Call Center Software 100, New System (500 Agent)	225,900.00	D
S ➤	NT9F02GA	Software Assembly, CCS 100 - New System Software, 5 Agents	3,450.00	D
S ➤	NT9F02HA	Software Assembly, CCS 100 - New System Software, 20 Agents	12,720.00	D
S ➤	NT9F02JA	Software Assembly, CCS 100 - New System Software, 200 Agents	100,800.00	D

CCS 200 Software

S ➤	NT9F03AA	Call Center Software 200, New System (1 Agent)	300.00	D
S ✓ ➤	NT9F03BA	Call Center Software 200, New System (10 Agent)	2,724.00	D
S ✓ ➤	NT9F03CA	Call Center Software 200, New System (50 Agent)	12,204.00	D
S ✓ ➤	NT9F03DA	Call Center Software 200, New System (100 Agent)	21,624.00	D
S ✓ ➤	NT9F03EA	Call Center Software 200, New System (500 Agent)	94,128.00	D
S ➤	NT9F03GA	Software Assembly, CCS 200 - New System Software, 5 Agents	1,440.00	D
S ➤	NT9F03HA	Software Assembly, CCS 200 - New System Software, 20 Agents	5,400.00	D
S ➤	NT9F03JA	Software Assembly, CCS 200 - New System Software, 200 Agents	42,600.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
CCS 300 Software				
S ➤	NT9F04AA	Call Center Software 300, New System (1 Agent)	360.00	D
S ✓ ➤	NT9F04BA	Call Center Software 300, New System (10 Agent)	3,264.00	D
S ✓ ➤	NT9F04CA	Call Center Software 300, New System (50 Agent)	14,652.00	D
S ✓ ➤	NT9F04DA	Call Center Software 300, New System (100 Agent)	25,944.00	D
S ✓ ➤	NT9F04EA	Call Center Software 300, New System (500 Agent)	112,956.00	D
S ➤	NT9F04GA	Software Assembly, CCS 300 - New System Software, 5 Agents	1,800.00	D
S ➤	NT9F04HA	Software Assembly, CCS 300 - New System Software, 20 Agents	6,480.00	D
S ➤	NT9F04JA	Software Assembly, CCS 300 - New System Software, 200 Agents	51,000.00	D
CCS 350 New System Software				
S ➤	NTZD13AF	Marketing Package, SCCS NCC (Network Control Center) Release 3.0 Software	28,000.00	D
Upgrade Software				
Symposium Call Center Server				
S ✓ ➤	NTZD06AF	SCCS Software Upgrade Package, R1.1/1.5 to R3.0	No charge	
S ➤	NTZD10AF	SCCS Software Upgrade Package, R1.0 to R3.0	No charge	
S ➤	NTZD81AA	SCCS Software Upgrade Package for Individual Agents, R1.0/ R1.1/R1.5 to R3.0	125.00	D
MAX 7 or MAX 8 Upgrade to CCS 100				
S ➤	NT9F06AA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1 Agent)	288.00	D
S ➤	NT9F06BA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (10 Agent)	2,616.00	D
S ➤	NT9F06CA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (50 Agent)	11,712.00	D
S ➤	NT9F06DA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (100 Agent).	20,760.00	D
S ➤	NT9F06EA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (500 Agent).	90,360.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9F06GA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 5 Agents	1,452.00	D
S ➤	NT9F06HA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 20 Agents	5,172.00	D
S ➤	NT9F06JA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 200 Agents	41,400.00	D

MAX 6 Upgrade to CCS 100

S ➤	NT9F09AA	Call Center Software 100, Upgrade from MAX 6 (1 Agent)	300.00	D
S ➤	NT9F09BA	Call Center Software 100, Upgrade from MAX 6 (10 Agent)	2,740.00	D
S ➤	NT9F09CA	Call Center Software 100, Upgrade from MAX 6 (50 Agent)	12,300.00	D
S ➤	NT9F09DA	Call Center Software 100, Upgrade from MAX 6 (100 Agent)	21,792.00	D
S ➤	NT9F09EA	Call Center Software 100, Upgrade from MAX 6 (500 Agent)	94,884.00	D
S ➤	NT9F09GA	Software Assembly, CCS 100 Upgrade, MAX 6, 5 Agents	1,572.00	D
S ➤	NT9F09HA	Software Assembly, CCS 100 Upgrade, MAX 6, 20 Agents	5,544.00	D
S ➤	NT9F09JA	Software Assembly, CCS 100 Upgrade, MAX 6, 200 Agents	43,440.00	D

MAX 5 Upgrade to CCS 100

S ➤	NT9F11AA	Call Center Software 100, Upgrade From MAX 5 (1 Agent)	348.00	D
S ➤	NT9F11BA	Call Center Software 100, Upgrade from MAX 5 (10 Agent)	3,204.00	D
S ➤	NT9F11CA	Call Center Software 100, Upgrade from MAX 5 (50 Agent)	14,352.00	D
S ➤	NT9F11DA	Call Center Software 100, Upgrade from MAX 5 (100 Agent)	25,428.00	D
S ➤	NT9F11EA	Call Center Software 100, Upgrade from MAX 5 (500 Agent)	110,688.00	D
S ➤	NT9F11GA	Software Assembly, CCS 100 Upgrade, MAX 5, 5 Agents	1,770.00	D
S ➤	NT9F11HA	Software Assembly, CCS 100 Upgrade, MAX 5, 20 Agents	6,408.00	D
S ➤	NT9F11JA	Software Assembly, CCS 100 Upgrade, MAX 5, 200 Agents	49,800.00	D

MAX Pre-Release 5 or PEP Upgrade to CCS 100

S ➤	NT9F14AA	Call Center Software 100, Upgrade from Max Pre-release 5 or PDP (1 Agent)	444.00	D
S ➤	NT9F14BA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (10 Agent)	4,044.00	D
S ➤	NT9F14CA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (50 Agent)	18,156.00	D
S ➤	NT9F14DA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (100 Agent)	32,172.00	D
S ➤	NT9F14EA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (500 Agent)	140,064.00	D
S ➤	NT9F14GA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 5 Agents	2,148.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9F14HA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 20 Agents	7,932.00	D
S ➤	NT9F14JA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 200 Agents	62,880.00	D

MAX with CCR Upgrade to CCS 200

S ➤	NT9F07AA	Call Center Software 200, Upgrade from MAX and CCR (1 Agent)	120.00	D
S ➤	NT9F07BA	Call Center Software 200, Upgrade from MAX and CCR (10 Agent)	1,092.00	D
S ➤	NT9F07CA	Call Center Software 200, Upgrade from MAX and CCR (50 Agent)	4,884.00	D
S ➤	NT9F07DA	Call Center Software 200, Upgrade from MAX and CCR (100 Agent)	8,652.00	D
S ➤	NT9F07EA	Call Center Software 200, Upgrade from MAX and CCR (500 Agent)	37,656.00	D
S ➤	NT9F07GA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (5 Agents)	660.00	D
S ➤	NT9F07HA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (20 Agents)	2,184.00	D
S ➤	NT9F07JA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (200 Agents)	17,520.00	D

MAX Virtual Upgrade to CCS 200

S ➤	NT9F15AA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1 Agent)	264.00	D
S ➤	NT9F15BA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (10 Agent)	2,340.00	D
S ➤	NT9F15CA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (50 Agent)	10,500.00	D
S ➤	NT9F15DA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (100 Agent)	18,600.00	D
S ➤	NT9F15EA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (500 Agent)	80,952.00	D
S ➤	NT9F15GA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 5 Agents	1,344.00	D
S ➤	NT9F15HA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 20 Agents	4,584.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9F15JA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 200 Agents	36,960.00	D

CCR Upgrade to CCS 100

S ➤	NT9F12AA	Call Center Software 100, Upgrade from CCR only (1 Agent)	384.00	D
S ➤	NT9F12BA	Call Center Software 100, Upgrade from CCR only (10 Agent)	3,528.00	D
S ➤	NT9F12CA	Call Center Software 100, Upgrade from CCR only (50 Agent)	15,816.00	D
S ➤	NT9F12DA	Call Center Software 100, Upgrade from CCR only (100 Agent)	28,020.00	D
S ➤	NT9F12EA	Call Center Software 100, Upgrade from CCR only (500 Agent)	121,992.00	D
S ➤	NT9F12GA	Software Assembly, CCS 100 Upgrade, CCR, 5 Agents	1,740.00	D
S ➤	NT9F12HA	Software Assembly, CCS 100 Upgrade, CCR, 20 Agents	6,330.00	D
S ➤	NT9F12JA	Software Assembly, CCS 100 Upgrade, CCR, 200 Agents	50,280.00	D

CCR Upgrade to CCS 200

S ➤	NT9F13AA	Call Center Software 200, Upgrade from CCR only (1 Agent)	168.00	D
S ➤	NT9F13BA	Call Center Software 200, Upgrade from CCR only (10 Agent)	1,476.00	D
S ➤	NT9F13CA	Call Center Software 200, Upgrade from CCR only (50 Agent)	6,588.00	D
S ➤	NT9F13DA	Call Center Software 200, Upgrade from CCR only (100 Agent)	11,676.00	D
S ➤	NT9F13EA	Call Center Software 200, Upgrade from CCR only (500 Agent)	50,832.00	D
S ➤	NT9F13GA	Software Assembly, CCS 200 Upgrade, CCR, 5 Agents	828.00	D
S ➤	NT9F13HA	Software Assembly, CCS 200 Upgrade, CCR, 20 Agents	2,940.00	D
S ➤	NT9F13JA	Software Assembly, CCS 200 Upgrade, CCR, 200 Agents	22,920.00	D

NACD and NAC to CCS 300

S ➤	NT9F08AA	Call Center Software 300, Upgrade From MAX NACD and/or NAC (1 Agent)	144.00	D
S ➤	NT9F08BA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (10 Agent)	1,308.00	D
S ➤	NT9F08CA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (50 Agent)	5,856.00	D
S ➤	NT9F08DA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (100 Agent)	10,380.00	D
S ➤	NT9F08EA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (500 Agent)	45,180.00	D
S ➤	NT9F08GA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (5 Agents)	750.00	D
S ➤	NT9F08HA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (20 Agents)	2,700.00	D
S ➤	NT9F08JA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (200 Agents)	21,060.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
NACD Upgrade to CCS 300				
S ➤	NT9F08GA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (5 Agents)	750.00	D
S ➤	NT9F08HA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (20 Agents)	2,700.00	D
S ➤	NT9F08JA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (200 Agents)	21,060.00	D
S ➤	NT9F10AA	Call Center Software 300, Upgrade From NACD (1 Agent)	180.00	D
S ➤	NT9F10BA	Call Center Software 300, Upgrade from NACD (10 Agent)	1,632.00	D
S ➤	NT9F10CA	Call Center Software 300, Upgrade from NACD (50 Agent)	7,332.00	D
S ➤	NT9F10DA	Call Center Software 300, Upgrade from NACD (100 Agent)	12,972.00	D
S ➤	NT9F10EA	Call Center Software 300, Upgrade from NACD (500 Agent)	56,484.00	D
S ➤	NT9F10GA	Software Assembly, CCS 300 Upgrade, From NACD, 5 Agents	984.00	D
S ➤	NT9F10HA	Software Assembly, CCS 300 Upgrade, From NACD, 20 Agents	3,276.00	D
S ➤	NT9F10JA	Software Assembly, CCS 300 Upgrade, From NACD, 200 Agents	26,880.00	D
SYMPOSIUM Service Products				
S ➤ Δ	SV000091	SYMPOSIUM TAPI Server, One Additional Year of Software Support	1,200.00	H
S ➤ Δ	SV000117	SYMPOSIUM Transaction Fee	500.00	H
S ➤ Δ	SV000125	SYMPOSIUM Call Center Installation	5,290.00	H
S Δ	SV000288	SYMPOSIUM Call Center Server Client Installation	390.00	H
Server Hardware Complete Systems				
S ✓ ➤	NT9F90AA	SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51	20,370.00	H
S ✓ ➤	NT9F90BA	SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0	20,370.00	H
S ➤	NTZD0001	Marketing Package Symposium Call Center Server, New System	No charge	
S ➤	NTZD0002	Marketing Package Symposium Call Center Server, Upgrade System	No charge	
S	NTZD0003	Marketing Package Symposium Call Center Server, Spare System	No charge	
S ➤	NTZD0004	Marketing Package Symposium Call Center Server, NCC	No charge	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ★ ➤ Δ	NTZD0005	Marketing Package DMS SYMPOSIUM Call Center Server, New System	No charge	
S ✓ ➤	NTZD02AA	SYMPOSIUM Call Center Server, 702t Advanced with Windows NT 3.51	8,100.00	H
S ★ ➤	NTZD02AD	SYMPOSIUM Call Center Server, 702t Advanced	8,100.00	H
S ✓ ➤	NTZD02BA	SYMPOSIUM Call Center Server, 702t Advanced with RAID with Windows NT 3.51	12,500.00	H
S ★ ➤	NTZD02BD	SYMPOSIUM Call Center Server, 702t Advanced with RAID	12,500.00	H

Components Common to all Systems

S ✓ ➤	NT9F27AA	SYMPOSIUM Call Center Server Peripherals Package	1,000.00	H
S ✓ ➤	NT9F27AC	SYMPOSIUM Call Center Server 1003t Peripherals Package	535.00	H
S ➤	NTRH9009	PCI Ethernet Adapter	360.00	H
S ✓ ➤	NTRH9010	PCI Token Ring Network Card	520.00	D

701t / 702t Merchandise

S ✓ ➤	A0627875	Cleaning Cartridge	115.00	D
S ➤	A0660538	Data Cartridge	50.00	H
S ➤	A0670533	SYMPOSIUM Call Center Server 701t 32MB DIMM	700.00	H
S ➤	A0670634	SYMPOSIUM Call Center Server 701t Assembly Peripheral Bay	30.00	H
S ➤	A0670802	SYMPOSIUM Call Center Server 701t CPU 200Mz PPRO 256K L2 Cache	1,600.00	H
S ➤	A0671783	SYMPOSIUM Call Center Server, 701t Fan, 120mm plus Cardguide	200.00	H
S ➤	A0672418	SYMPOSIUM Call Center Server 701t 275W Power Supply	500.00	H
S ➤	A0672941	SYMPOSIUM Call Center Server 701t Front Panel and Cable (Power/Reset Switches + LED)	180.00	H
S ➤	A0683319	SYMPOSIUM Call Center Server 701t SCSI Cable Kit	650.00	H
S ➤	A0684753	68 pin Wide SCSI Cable	160.00	H
S Δ	A0720936	701t 64 MB DIMM	620.00	H
S Δ	A0720937	701t 128 MB DIMM	1,200.00	H
S Δ	A0741558	Front Chassis Cover	80.00	H
S ✓ Δ	A0741561	300W Power Supply	155.00	H
S Δ	A0741570	Chassis Front Panel	35.00	H
S Δ	A0741571	Fan Bracket	40.00	H
S Δ	A0741573	Peripheral Drive Rail	80.00	H
S ✓	A0741574	702t OEM System With no Processor and no Memory	2,500.00	H
S ✓ Δ	A0741576	Fan Assembly	10.00	H
S Δ	A0741577	Front Panel Cable	28.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	A0741579	Chassis Side Access Cover	490.00	H
S Δ	A0741595	64MB SDRAM DIMM	620.00	H
S ➤	NTRH9006	SCSI 3.5 DAT Tape Drive	1,750.00	H
S ➤	NTRH9029	2GB Ultra SCSI Disk Drive	1,250.00	H
S ✓ ➤	NTRH9030	4GB 16Bit Ultra SCSI Disk Drive	2,075.00	H
S ➤	NTRH9031	SYMPOSIUM Call Center Server 701t Platform Server System (32Mb)	5,000.00	H
S ✓ ➤	NTRH9035	IDE CD-ROM Drive	275.00	H

1001t Merchandise

S ✓ ➤	A0677506	Dry Clean Cartridge	150.00	D
S ✓ ➤	A0677508	13GB Data Cartridge	170.00	D
S ➤	A0721792	SYMPOSIUM Call Center Server 1001t Base System	9,100.00	H
S ➤	A0722048	SYMPOSIUM Call Center Server 1001t System Board	4,000.00	H
S ➤	A0722070	SYMPOSIUM Call Center Server 1001t SCRAM Memory Board	350.00	H
S ➤	A0722084	SYMPOSIUM Call Center Server 1001t SCSI Backplane Kit	650.00	H
S ➤	A0722762	SYMPOSIUM Call Center Server 1001t 300Mhz Processor	3,000.00	H
S ➤	A0723759	SYMPOSIUM Call Center Server 1001t Power Supply 360W	500.00	H
S	A0724372	SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Bottom	410.00	H
S	A0724373	SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Top	410.00	H
S	A0724374	SYMPOSIUM Call Center Server 1001t Cable Narrow, SCSI	135.00	H
S	A0724375	SYMPOSIUM Call Center Server 1001t Cable, IDE CD-ROM	135.00	H
S ➤	A0725300	SYMPOSIUM Call Center Server 1001t 32MB SCRAM	600.00	H
S ➤	A0726965	SYMPOSIUM Call Center Server 1001t CPU Retention Mechanism	30.00	H
S	A0726966	SYMPOSIUM Call Center Server 1001t EPAC Blower Duct	555.00	H
S ➤	A0727294	SYMPOSIUM Call Center Server 1001t Redundant Fan Kit	165.00	H
S ➤	A0727295	SYMPOSIUM Call Center Server 1001t Blower	95.00	H
S ➤	A0728440	SYMPOSIUM Call Center Server 1001t Side Cover	400.00	H
S ➤	A0728441	SYMPOSIUM Call Center Server 1001t Top Cover	300.00	H
S ✓	A0729069	M/M Wide-Nar SCSI Adapter	150.00	D
S Δ	A0744720	64 MB SIMM	620.00	H
S ➤	NTRH9002	2GB SCSI SCA Disk Drive	1,320.00	H
S ➤	NTRH9003	4GB SCSI Hot Swap Disk Drive	2,260.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ ➤	NTRH9034	Backup Tape Drive	3,000.00	D

1000t Merchandise

S ✓ ➤	A0627875	Cleaning Cartridge	115.00	D
S ➤	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity	300.00	H
B ➤	A0646699	Key and Lock Master	70.00	H
S † ➤	A0646715	OIVR 2 x Hardware - Drive LED Panel for AP or MRS/AP	45.00	H
S ➤	A0646718	SYMPOSIUM Server, 1000t Peripheral Mounting Rail	30.00	H
S ➤	A0646721	SYMPOSIUM Server, 1000t Foot	30.00	H
S † ➤	A0647317	OIVR 2 x Hardware - Fan (100cfm)	85.00	H
S ➤	A0652237	SYMPOSIUM Server, 1000t Drive Tray	30.00	H
S † ➤	A0656847	OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP	925.00	H
S † ➤	A0656874	OIVR 2 x Hardware - Cable, LCD for AP or MRS/AP	110.00	H
S ➤	A0658342	SYMPOSIUM Server, 1000t XXPress Memory Board with NO DRAM Included	850.00	H
S ➤	A0658874	SYMPOSIUM Server, 1000t - with Chassis, Motherboard, and Floppy Drive Assembly	5,030.00	H
S ➤	A0660524	SYMPOSIUM Server, 1000t XXPress 166 MHz P5 CPU with 512KB Sync Cache	6,270.00	H
S ➤	A0660538	Data Cartridge	50.00	H
S	A0774861	32 MB DIMM	630.00	H
S ➤	NTRH9002	2GB SCSI SCA Disk Drive	1,320.00	H
S ➤	NTRH9003	4GB SCSI Hot Swap Disk Drive	2,260.00	H
S ➤	NTRH9005	SCSI CD-ROM Drive	250.00	H
S ➤	NTRH9006	SCSI 3.5 DAT Tape Drive	1,750.00	H

1003t Merchandise

S ✓	A0797692	SYMPOSIUM Call Center Server 1003t System Board PCA	3,050.00	H
S ✓	A0797705	SYMPOSIUM Call Center Server 1003t Input/Output PCA	1,650.00	H
S ✓	A0797722	SYMPOSIUM Call Center Server 1003t Voltage Regulator Module	118.00	H
S ✓	A0797724	SYMPOSIUM Call Center Server 1003t Memory PCA	165.00	H
S ✓	A0797727	SYMPOSIUM Call Center Server 1003t NetServer Hot-Swap Ultra2 Internal Storage Cage	690.00	H
S ✓	A0797938	SYMPOSIUM Call Center Server 1003t 256MB 50ns EDO DIMM Kit (4x64MB)	1,650.00	H
S ✓	A0797948	SYMPOSIUM Call Center Server 1003t Fan Assembly for Input/ Output, Retainer	76.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓	A0797950	SYMPOSIUM Call Center Server 1003t Fan Assembly for System Board	52.00	H
S ★	A0797971	Pentium III Xeon 500 MHz, 512KB ECC L2 Cache	3,300.00	H
S ★	A0797984	9GB Hot-Swap Ultra2 SCSI LP Hard Disk Drive	3,200.00	H
S ✓	A0798087	SYMPOSIUM Call Center Server 1003t PCI Ethernet Adapter	135.00	H
S ✓	A0798092	SYMPOSIUM Call Center Server 1003t Wide SCSI Host Adapter Board	165.00	H
S ★	A0798117	Non-Hot-Swap Tray	85.00	H
S ★	A0798129	SYMPOSIUM Call Center Server Power Supply Module, 300W	400.00	H
S ✓	A0798155	SYMPOSIUM Call Center Server 1003t Internal SCSI Input/ Output Cable	121.00	H
S ✓	A0798177	SYMPOSIUM Call Center Server 1003t Fan Assembly for CPU	52.00	H
S ✓	A0798258	SYMPOSIUM Call Center Server 1003t NetServer Keyboard	205.00	H
S ✓	A0798259	SYMPOSIUM Call Center Server 1003t 1.44MB Floppy Disk Drive	78.00	H
S ✓	A0798260	SYMPOSIUM Call Center Server 1003t Mini-DIN Mouse	65.00	H
S ✓	A0800927	SYMPOSIUM Call Center Server 1003t 32x MAX EIDE CD-ROM Drive	203.00	H
S ✓	A0801312	SYMPOSIUM Call Center Server 1003t Processor Terminator	52.00	H
S ✓	NTRH9100	SYMPOSIUM Call Center Server 1003t Base System	15,590.00	H

Common Merchandise

S ➤	A0383333	Transceiver	560.00	H
S ✓ ➤	A0601464	Modem Cable, 10 Ft. DB9 Female to DB25 Male	25.00	D
S ✓ ➤	A0645811	Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A	30.00	H
S ✓ ➤	A0648372	4 Ft. Ethernet Cable, Category 5	10.00	D
S ✓ ➤	A0648374	2 Ft. Ethernet Cable, Category 5	10.00	D
S ✓ ➤	A0648375	7 Ft. Ethernet Cable, Category 5	10.00	D
S ✓ ➤	A0648377	10 Ft. Ethernet Cable, Category 5	10.00	D
S ✓ ➤	A0648378	15 Ft. Ethernet Cable, Category 5	10.00	D
S ✓ ➤	A0648379	25 Ft. Ethernet Cable, Category 5	15.00	D
S ➤	A0722476	SYMPOSIUM Call Center Server Terminator Board	70.00	H
S ★	A0744727	128MB SDRAM	1,240.00	H
S ✓ Δ	A0761148	702t CPU 450 MHz Pentium II	1,390.00	H
S	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	175.00	D
S ➤	NT9F43AC	SYMPOSIUM Call Center Release 1.5 Client CD-ROM	50.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT9F46AC	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly	50.00	H
S Δ	NT9F53AA	SCCS Software Assembly, Release 24 X11 PEP CD-ROM	No charge	
S ➤	NTDK27AA	Ethernet Adapter Cable	75.00	D
S ✓ ➤	NTRH9004	3.5" EIDE Floppy Drive	70.00	H
S ✓ ➤	NTRH9007	SCSI RAID Controller	2,180.00	H
S ➤	NTRH9009	PCI Ethernet Adapter	360.00	H
S ✓ ➤	NTRH9010	PCI Token Ring Network Card	520.00	D
S ✓ ➤	NTRH9011	14" SVGA Color Monitor	380.00	D
S ➤	NTRH9012	17" SVGA Color Monitor	1,325.00	H
S ✓ † ➤	NTRH9013	OIVR 2 x Hardware - Keyboard	60.00	D
S ✓ ➤	NTRH9014	Three Button Mouse	90.00	D
S ✓ ➤	NTRH9016	External Modem 33.6	280.00	D
S ✓ ➤	NTRH9017	10 Base T Hub	300.00	D
S ➤	NTRH9027	ACCESS Link Kit for Meridian Mail 8, 9, 10, 11. Includes: - 25 feet straight cable (DB25 M-F) - null modem cable (DB25 M-F) - gender changer (DB25 F-F) - gender changer (DB25 M-M) - DB25 to DB9 adapter (F-F)	50.00	H
S ✓ ➤	NTRH9032	700 Series DC Power Converter	3,000.00	D
S ➤ Δ	NTZD07AA	SYMPOSIUM Call Center Server Graphical Real Time Display CD-ROM	50.00	H
S ➤	NTZD08AA	SYMPOSIUM Call Center Server Windows NT 4.0 Client CD-ROM	50.00	H
S ➤ Δ	NTZD10AA	SCCS Marketing Package, Windows NT 4.0 Client	50.00	H

SYMPOSIUM Call Center Server Documentation

S ➤ Δ	NT6R10AD	SYMPOSIUM Call Center Server Release 1.5 Documentation CD-ROM	250.00	H
S ➤ Δ	NTVF44AA	SYMPOSIUM Call Center Documentation CD-ROM (Multilingual)	50.00	H
S ➤ Δ	P0884909	702t Installation and Maintenance Guide	50.00	H
S ✓	P0911675	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	50.00	H

Release 1

S ➤ Δ	P0876261	SYMPOSIUM Call Center Server Release 1, 701t Maintenance and Diagnostics Guide	50.00	H
S ➤ Δ	P0876262	SYMPOSIUM Call Center Server Release 1, 701t Hardware Installation Guide	50.00	H
S Δ	P0879480	SYMPOSIUM Call Center Server 1001t Hardware Installation Guide	50.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0879481	SYMPOSIUM Call Center Server 1001t Maintenance and Diagnostics Guide	50.00	H

SYMPOSIUM WebResponse Server

S ➤ Δ	NT2F59AA	Application License Kit	No charge	
S ➤	NT2F62AA	SYMPOSIUM WebResponse Server 2 Basic Package	38,000.00	D
S	NT2F63AA	SYMPOSIUM WebResponse Server 2 - One Client Expansion Package	250.00	D
S	NT2F63BA	SYMPOSIUM WebResponse Server 2 - Ten Client Expansion Package	2,000.00	D
S	NT2F63CA	SYMPOSIUM WebResponse Server 2 - Twenty Five Client Expansion Package	2,500.00	D
S ➤	NT2F64CA	SYMPOSIUM WebResponse Server 2 Replacement Package	1,500.00	D
S Δ	NTZB2101	Installation Diskette	No charge	
S ➤	SV000182	SYMPOSIUM WebResponse Server Additional 1 Day Installation Services	1,500.00	H
S † ➤ Δ	SV000183	SYMPOSIUM WebResponse Server Annual Telephone Support	950.00	H
S † ➤ Δ	SV000184	SYMPOSIUM WebResponse Server Installation Service	6,000.00	H

Desktop

SYMPOSIUM Agent

S ➤	NT1F57AA	SYMPOSIUM Agent Package 1 (1-50 Agents). Package 1 is designed for call centers requiring the launching of applications and the retrieval of data for agents with the arrival of inbound telephone calls. Symposium Agent can be customized to use CLID, DNIS, or information collected by Interactive Voice Response (IVR) systems to deliver the applications and data that agents most need for each and every call.	200.00	D
S ➤	NT1F57BA	SYMPOSIUM Agent Package 1 (51-100 Agents). Package 1 is designed for call centers requiring the launching of applications and the retrieval of data for agents with the arrival of inbound telephone calls. Symposium Agent can be customized to use CLID, DNIS, or information collected by Interactive Voice Response (IVR) systems to deliver the applications and data that agents most need for each and every call.	190.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT1F57CA	SYMPOSIUM Agent Package 1 (101-200 Agents). Package 1 is designed for call centers requiring the launching of applications and the retrieval of data for agents with the arrival of inbound telephone calls. Symposium Agent can be customized to use CLID, DNIS, or information collected by Interactive Voice Response (IVR) systems to deliver the applications and data that agents most need for each and every call.	175.00	D
S ➤	NT1F57DA	SYMPOSIUM Agent Package 1 (201 + Agents). Package 1 is designed for call centers requiring the launching of applications and the retrieval of data for agents with the arrival of inbound telephone calls. Symposium Agent can be customized to use CLID, DNIS, or information collected by Interactive Voice Response (IVR) systems to deliver the applications and data that agents most need for each and every call.	150.00	D
S ➤	NT1F58AA	SYMPOSIUM Agent Package 2 (1-50 Agents). Includes functionality of Package 1 along with desktop telephony capabilities. This feature provides all the telephone features on the desktop including make call, answer call, release call, transfer call, conference call and hold/unhold in addition to ACD functions such as login, logout, ready and not ready. It also provides individual agent statistics, dialing plan and call log.	400.00	D
S ➤	NT1F58BA	SYMPOSIUM Agent Package 2 (51-100 Agents). Includes functionality of Package 1 along with desktop telephony capabilities. This feature provides all the telephone features on the desktop including make call, answer call, release call, transfer call, conference call and hold/unhold in addition to ACD functions such as login, logout, ready and not ready. It also provides individual agent statistics, dialing plan and call log.	375.00	D
S ➤	NT1F58CA	SYMPOSIUM Agent Package 2 (101-200 Agents). Includes functionality of Package 1 along with desktop telephony capabilities. This feature provides all the telephone features on the desktop including make call, answer call, release call, transfer call, conference call and hold/unhold in addition to ACD functions such as login, logout, ready and not ready. It also provides individual agent statistics, dialing plan and call log.	345.00	D
S ➤	NT1F58DA	SYMPOSIUM Agent Package 2 (201 + Agents). Includes functionality of Package 1 along with desktop telephony capabilities. This feature provides all the telephone featues on the desktop including make call, answer call, release call, transfer call, conference call and hold/unhold in addition to ACD functions such as login, logout, ready and not ready. It also provides individual agent statistics, dialing plan and call log.	295.00	D
S Δ	NT1F68AA	SYMPOSIUM Agent 1.1 Base Software. Base software (media package) to be ordered in conjunction with NT1F57AA, NT1F57BA, NT1F57CA, NT1F57DA OR NT1F58AA, NT1F58BA, NT1F58CA, NT1F58DA.	No charge	
S ➤	NT1F80AA	SYMPOSIUM Agent Upgrade - Package 1 to 2	325.00	D
S Δ	NT1F86AA	Symposium Agent Upgrade Package 1 to Package 2 - Base Software. Base software to be ordered in conjunction with NT1F80BA or NT1F80CA.	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ Δ	NT2F59AA	Application License Kit	No charge	
S ➤ Δ	NT2F60AA	SYMPOSIUM Agent 2 Base Software. Includes call rule, triggers, and wizards used to present information to agents desktops, agentTelephony (desktop telephony GUI), and agentCompass to assist in navigating agents through various transactions. SYMPOSIUM Agent 2 is also centrally administered.	No charge	
S	NT2F61AA	SYMPOSIUM Agent 2 (1 User)	400.00	D
S	NT2F61BA	SYMPOSIUM Agent 2 (10 Users)	3,750.00	D
S	NT2F61CA	SYMPOSIUM Agent 2 (50 Users)	18,250.00	D
S	NT2F61DA	SYMPOSIUM Agent 2 (100 Users)	34,500.00	D
S	NT2F61EA	SYMPOSIUM Agent 2 (500 Users)	85,000.00	D
S	NT2F64AA	SYMPOSIUM Agent 1.1 Replacement/Up-issue Package	500.00	D
S	NT2F64BA	SYMPOSIUM Agent 2 Replacement/Up-issue Package	500.00	D
S ➤	NT2F65AA	SYMPOSIUM Agent Upgrade Package 1 to Symposium Agent 2	300.00	D
S ➤	NT2F65BA	SYMPOSIUM Agent Upgrade Package 2 to SYMPOSIUM Agent 2	200.00	D
S ➤ Δ	SV000147	SYMPOSIUM Agent Install-Prep	500.00	H
S ➤ Δ	SV000148	SYMPOSIUM Agent Install-Pro	1,500.00	H
S ➤ Δ	SV000149	SYMPOSIUM Agent Software Support	1,200.00	H

SYMPOSIUM FastView

Packages

S Δ	NT1F27BB	SYMPOSIUM FastView Upgrade Software Package 1A	299.00	D
S ➤ Δ	NT1F27EB	SYMPOSIUM FastView New Software Package 1C	535.00	D
S ➤	NTZB11AB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6A (1-19 Units)	850.00	D
S ➤	NTZB11BB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6B (20-49 units)	800.00	D
S ➤	NTZB11CB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6C (50+ Units)	750.00	D
S ➤	NTZB13AB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7A (1-19 Units)	1,100.00	D
S ➤	NTZB13BB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7B (20-49 units)	1,050.00	D
S ➤	NTZB13CB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7C (50+ Units)	1,000.00	D
S ➤	NTZB15AB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8A (1-19 Units)	1,650.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NTZB15BB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8B (20-49 Units)	1,600.00	D
S ➤	NTZB15CB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8C (50+ Units)	1,550.00	D
S ➤	NTZK29AA	SYMPOSIUM FastView New Software, MCA M2216 and Documentation Package 5A (1-19 Units)	1,399.00	D
S ➤	NTZK29BA	SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5B (20-49 Units)	1,349.00	D
S ➤	NTZK29CA	SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5C (50+ Units)	1,299.00	D

Installation

S ➤ Δ	SV000126	SYMPOSIUM FastView INSTALL-PRO Installation 5 to 8 Seats	1,500.00	H
S ➤ Δ	SV000127	SYMPOSIUM FastView INSTALL-PREP Remote Installation	400.00	H
S ➤ Δ	SV000128	SYMPOSIUM FastView Software Support	1,200.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Call Center and CTI Products

Call Center Software Service Transaction Fees

Software service transaction fees are required when processing orders for Call Center software. The following table provides the service fee name and ordering code.

Service transaction fees

Code	Service
SERV0001	ACD-D Auxiliary Processor Software Service Transaction Fee
SERV0005	Meridian MAX Releases 4,6,7 and 8 Software Service Transaction Fee (AM)
SERV0006	Customer Controlled Routing Software Service Transaction Fee
SERV0033	Meridian Link and CCR Co-resident Software Service Transaction Fee
SERV0017	Meridian MAX-IPE/MAX-IPEE Releases 4, 6, 7 and 8 Software Service Transaction Fee
574SL1-1	ACD MAX Software Service Transaction Fee
P0885111	Meridian MAX Release 9 Reproduction/Keycode (IPE/IPEE, SNN/SNNE)
P0889406	Meridian NAC Software Service Transaction Fee (AM)

Meridian MAX

Meridian MAX Release 9 Software Upgrade Matrix

Upgrading to a Meridian MAX-SNN Release 9 system

	Upgrading from Hardware Platform					
Upgrading from Software Release	**MAX-SNN**	**MAX-IPE and MAX-IPEE**	**MAX-SEE and Option 1, 2 Single AM's**	**MAX Option 3, 4 Dual AM's**	**HP Vectra (Single or Dual Tower)**	**PDP-11**
Meridian MAX Release 9		Not Supported Note 2				
Meridian MAX Release 8	NTJH01FA Note 1	Not Supported Note 2				
Meridian MAX Release 7	NTJH01EA Note 1	Not Supported Note 2				
Meridian MAX Release 6	NTJH01DA Note 1	Not Supported Note 2	Not Supported Note 2			
Meridian MAX Release 5	NTJH01DA Note 1	Not Supported Note 2	Not Supported Note 2			
Meridian MAX Release 4.62		Not Supported Note 2				
Meridian MAX Release 3 or 4			Not Supported Note 2	Not Supported Note 2		
ACD-MAX Release 3 or 4					Not Supported Note 2	
ACD-D All Releases						Not Supported Note 2

Note 1: Use existing SNN platform for this upgrade.

Note 2: Upgrade from this system to MAX-SNN not supported. Instead, upgrade to Meridian MAX-SNNE Release 9 System. See the Upgrading to a Meridian MAX-SNNE Release 9 System table.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Upgrading to a Meridian MAX-SNNE Release 9 system

	Upgrading from Hardware Platform					
Upgrading from Software Release	**MAX-SNN and MAX-SNNE**	**MAX-IPE and MAX-IPEE**	**MAX-SEE and Option 1, 2 Single AM's**	**MAX Option 3, 4 Dual AM's**	**HP Vectra (Single or Dual Tower)**	**PDP-11**
Meridian MAX Release 9	NTJH15DA NTJH12AA Note 1	NTJH15AA/ NTJH15BA Note 2				
Meridian MAX Release 8	NTJH15DA NTJH01FA Note 1	NTJH15AA/ NTJH15BA NTJH02FA Note 3				
Meridian MAX Release 7	NTJH15DA NTJH01EA Note 1	NTJH15AA/ NTJH15BA NTJH02EA Note 3				
Meridian MAX Release 6	NTJH15DA NTJH01DA Note 1	NTJH15AA/ NTJH15BA NTJH02DA Note 3	NTJH15CA NTJH01DA			
Meridian MAX Release 5	NTJH15DA NTJH01DA Note 1	NTJH15AA/ NTJH15BA NTJH02DA Note 3	NTJH15CA NTJH01DA			
Meridian MAX Release 4.62		NTJH15AA/ NTJH15BA NTJH02DA Note 3				
Meridian MAX Release 3 or 4			NTJH15CA NTJH01CA	NTJH15CA NTJH01CA		
ACD-MAX Release 3 or 4					NTJH15AA/ NTJH15BA NTJH01BA Note 4	
ACD-D All Releases						NTJH15AA/ NTJH15BA NTJH01AA Note 4

Note 1: MAX 9 software can operate on a MAX-SNN platform. However, if an increase in capacity or performance is required, order NTJH15DA to upgrade a MAX-SNN platform to MAX-SNNE. To order only MAX 9 software for a MAX-SNN platform, see the Upgrading to a Meridian MAX-SNN Release 9 System table.

Note 2: Order either package NTJH12BA (Fundamental), NTJH12CA (Enhanced), or NTJH12DA (Virtual) to migrate from MAX 9 software on an IPE/IPEE platform to the same software level (Fundamental, Enhanced, or Virtual) on an SNNE platform. Use existing Meridian MAX Release 9 Operating System and Application tapes; only a keycode for use with the MAX-SNNE platform will be supplied.

Note 3: This upgrade also requires a software migration package. Order either NTJH12BA (Fundamental), NTJH12CA (Enhanced), or NTJH12DA (Virtual) to migrate from MAX software on the IPE/IPEE platform to the same software level (Fundamental, Enhanced, or Virtual) on an SNNE platform. Although two software packages are ordered, only a single keycode for use with the MAX-SNNE platform will be supplied with new Meridian MAX Release 9 Operating System and Application tapes.

Note 4: No preservation or conversion of customer data is possible with this upgrade. Data collection must be recommenced from scratch once this upgrade is complete.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Upgrading to a Meridian MAX-IPE Release 9 system

	Upgrading from Hardware Platform					
Upgrading from Software Release	**MAX-SNN and MAX-SNNE**	**MAX-IPE**	**MAX-SEE and Option 1, 2 Single AM's**	**MAX Option 3, 4 Dual AM's**	**HP Vectra (Single or Dual Tower)**	**PDP-11**
Meridian MAX Release 9	Not Supported					
Meridian MAX Release 8	Not Supported	NTJH02FA Note 1				
Meridian MAX Release 7	Not Supported	NTJH02EA Note 1				
Meridian MAX Release 6	Not Supported	NTJH02DA Note 1	Not Supported Note 2			
Meridian MAX Release 5	Not Supported	NTJH02DA Note 1	Not Supported Note 2			
Meridian MAX Release 4.62		NTJH02DA Note 1				
Meridian MAX Release 3 or 4			Not Supported Note 2	Not Supported Note 3		
ACD-MAX Release 3 or 4					Not Supported Note 2	
ACD-D All Releases						Not Supported Note 2

Note 1: Use existing IPE platform for this upgrade. Database size after upgrade depends upon the size of the hard disk drive in the existing IPE platform. Both a 1-GByte (or larger) hard disk drive and a 600-MByte cassette tape drive are required to support a 250-MByte database. Disk and tape drives smaller than this support 90-MByte databases.

-Meridian MAX-IPE modules with part numbers A0617009 or A0617010 that were shipped new from the factory before December 1995, contain 240-MByte hard disk drives and therefore, can only support 90-MByte databases. New modules with these part numbers that were shipped after November 1995, support 250-MByte databases.

-All Meridian MAX-IPE modules with part numbers NT1R02AA or NT1R02BA support only 90-MByte databases.

-If the existing IPE platform supports only a 90-MByte database and a 250-MByte database is desired, an upgrade to a Meridian MAX-IPEE is required. See the "Upgrading to a Meridian MAX-IPEE Release 9 System" table.

Note 2: Upgrade from this system to MAX-IPE not supported. Instead, upgrade to Meridian MAX-IPEE Release 9 system. See the "Upgrading to a Meridian MAX-IPEE Release 9 System" table.

Note 3: Upgrade from this system to MAX-IPE not supported. Instead, upgrade to Meridian MAX-SNNE Release 9 system. See the "Upgrading to a Meridian MAX-SNNE Release 9 System" table.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Upgrading to a Meridian MAX-IPEE Release 9 system

	Upgrading for Hardware Platform					
Upgrading from Software Release	**MAX-SNN and MAX-SNNE**	**MAX-IPE and MAX-IPEE**	**MAX-SEE and MAX Option 1, 2 Single AM's**	**MAX Option 3, 4 Dual AM's**	**HP Vectra (Single or Dual Tower)**	**PDP-11**
Meridian MAX Release 9	Not Supported	NTJH93EA/ NTJH93FA Notes 1, 2				
Meridian MAX Release 8	Not Supported	NTJH93EA/ NTJH93FA NTJH02FA Note 2				
Meridian MAX Release 7	Not Supported	NTJH93EA/ NTJH93FA NTJH02EA Note 2				
Meridian MAX Release 6	Not Supported	NTJH93EA/ NTJH93FA NTJH02DA Note 2	NTJH17AA/ NTJH17BA NTJH02DA			
Meridian MAX Release 5	Not Supported	NTJH93EA/ NTJH93FA NTJH02DA Note 2	NTJH17AA/ NTJH17BA NTJH02DA			
Meridian MAX Release 4.62		NTJH93EA/ NTJH93FA NTJH02DA Note 2				
Meridian MAX Release 3 or 4			NTJH17AA/ NTJH17BA NTJH02CA	Not Supported Note 3		
ACD-MAX Release 3 or 4					NTJH17AA/ NTJH17BA NTJH02BA Note 4	
ACD-D All Releases						NTJH17AA/ NTJH17BA NTJH02AA Note 5

Note 1: Use existing Meridian MAX Release 9 Operating System and Application tapes, and keycode when upgrading hardware platform from MAX-IPE to MAX-IPEE. Requires an Installation Upgrade.

Note 2: The MAX-IPEE platform (A0667468 or A0667469) supports a 250-MByte database. However, it may not be necessary to order a MAX-IPEE hardware upgrade (NTJH93EA or NTJH93FA) if the existing MAX-IPE supports a 250-MByte database.-Meridian MAX-IPE modules with part numbers A0617009 or A0617010 that were shipped new from the factory before December 1995, contain 240-MByte hard disk drives and therefore, can only support 90-MByte databases. New modules with these part numbers that were shipped after November 1995, will support 250-MByte databases and therefore, a MAX-IPEE hardware upgrade is not required.-All Meridian MAX-IPE modules with part numbers NT1R02AA or NT1R02BA will only support 90-MByte databases; therefore, a MAX-IPEE hardware upgrade is required.

Note 3: Dual Module MAX Option 3 or 4 systems can only be upgraded to MAX-SNNE platforms. See "Upgrading to a Meridian MAX-SNNE Release 9 System" table.

Note 4: This upgrade involves a two-step database conversion process: First, the ACD-MAX database is converted to MAX 6 (on the IPEE platform) and then the database is converted from MAX 6 to MAX 9. A reusable data conversion kit (AS7506) is required to load the ACD-MAX database from the DC150 tape cartridge into the MAX-IPEE.

Note 5: No preservation or conversion of customer data is poss ble with this upgrade. Data collection must be recommenced from scratch once this upgrade is completed.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Hardware for Meridian MAX Release 9 Systems

Meridian MAX-SNNE System Hardware

S ➤	NTJH15EA	Meridian MAX-SNNE System Hardware, DC Power	25,000.00	D
S ➤	NTJH15FA	Meridian MAX-SNNE System Hardware, AC Power	25,000.00	D

Upgrades to MAX-SNNE System Hardware

S ➤	NTJH15AA	PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power	22,500.00	D
S ➤	NTJH15BA	PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power	22,500.00	D
S ➤	NTJH15CA	Meridian Option MAX/MAX-SEE to Meridian MAX-SNNE Hardware Upgrade	20,000.00	D
S ➤	NTJH15DA	Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade	17,500.00	D

Hardware Expansion Packages for Meridian MAX-SNN and Meridian MAX-SNNE Systems

S ➤	NT6D98AA	8-Channel Asynchronous I/O Card Kit	3,000.00	D

Meridian MAX-IPEE System Hardware

S ➤	NTJH17AA	Meridian MAX-IPEE Module (Option 11)	12,500.00	D
S ➤	NTJH17BA	Meridian MAX-IPEE Module (Option 21-81C)	12,500.00	D

Meridian MAX-IPE to MAX-IPEE Upgrade/Repair Hardware

S ➤ Δ	NTJH93FA	MAX-IPE to IPEE Upgrade Kit #2	725.00	H

Chassis Conversion Kits for Meridian MAX-IPE and MAX-IPEE Modules

S ➤	NTJH93AA	IPE/IPEE Option 11 to Option 21-81C Conversion Kit	1,100.00	D
S ➤	NTJH93BA	IPE/IPEE Option 21-81C to Option 11 Conversion Kit	1,100.00	D

Hardware for Pre-Meridian MAX Release 9 Systems

Expansion Packages for Existing Meridian MAX-SEE, Option MAX, and MAX-SNN Systems

S ➤	AS7512	Meridian MAX Option 1 to Option 2 Expansion Package	3,000.00	D
S ➤	AS7534	Meridian MAX Option 3 to Option 4 Expansion Package	6,000.00	D
S ➤	NT6D98AA	8-Channel Asynchronous I/O Card Kit	3,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian MAX Hardware Spares Packages

S ➤	A0352758	Filler Panel, Application Model	100.00	D
S ➤	AS0071	Meridian MAX-SNN Spares Kit	6,000.00	D
S ➤	AS0074	Meridian MAX-SNNE Spares Kit	6,000.00	D
S ➤	AS7505	Meridian MAX-SEE Spares Kit	6,400.00	D

Meridian MAX Release 9 Software

Meridian MAX-SNNE Release 9 System Software

S ➤	NTJH10AA	Meridian MAX-SNNE Release 9 Fundamental Software	35,000.00	D
S ➤	NTJH10BA	Meridian MAX-SNNE Release 9 Enhanced Software	65,000.00	D
S ➤	NTJH10CA	Meridian MAX-SNNE Release 9 Virtual Software	80,000.00	D

Options for Meridian MAX-SNN and MAX-SNNE Release 9 Software

S ➤	NTJH10DA	Meridian MAX-SNN/SNNE Release 9 Fundamental to Enhanced Feature Level Promotion	35,000.00	D
S ➤	NTJH10EA	Meridian MAX-SNN/SNNE Release 9 Enhanced to Virtual Feature Level Promotion	20,000.00	D
S ➤ Δ	S0005899	NAC Connectivity for Meridian MAX Release 9 Software	No charge	
S ➤ Δ	S0005901	Multiple Queue Assignment (MQA) Reporting for Meridian MAX Release 9 Software	No charge	
S ➤ Δ	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software	3,000.00	D
S ➤	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software	1,500.00	D

Upgrades to Meridian MAX-SNN and MAX-SNNE Release 9 System Software

S ➤	NTJH01AA	ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D
S ➤	NTJH01BA	ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D
S ➤	NTJH01CA	Meridian MAX-AM Release 3 or 4 to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D
S ➤	NTJH01DA	Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	15,000.00	D
S ➤	NTJH01EA	Meridian MAX-SNN Release 7 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	10,000.00	D
S ✓ ➤	NTJH01FA	Meridian MAX-SNN/SNNE Release 8 to Meridian MAX-SNN/ SNNE Release 9 Software Upgrade	7,500.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Migrating Release 9 System Software from Meridian MAX-SNN/IPE/IPEE to Meridian MAX-SNNE				
S ✓ ➤ Δ	NTJH12AA	Meridian MAX Release 9 Software Migration from MAX-SNN to MAX-SNNE	No charge	
S ➤	NTJH12BA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Fundamental to MAX-SNNE Fundamental	35,000.00	D
S ➤	NTJH12CA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Enhanced to MAX-SNNE Enhanced	55,000.00	D
S ➤	NTJH12DA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Virtual to MAX-SNNE Virtual	67,500.00	D
Meridian MAX-IPEE Release 9 System Software				
S ➤	NTJH11AA	Meridian MAX-IPEE Release 9 Fundamental Software	5,000.00	D
S ➤	NTJH11BA	Meridian MAX-IPEE Release 9 Enhanced Software	15,000.00	D
S ➤	NTJH11CA	Meridian MAX-IPEE Release 9 Virtual Software	17,500.00	D
Options for Meridian MAX-IPE and MAX-IPEE Release 9 Software				
S ➤	NTJH11DA	Meridian MAX-IPE/IPEE Release 9 Fundamental to Enhanced Feature Level Promotion	12,500.00	D
S ➤	NTJH11EA	Meridian MAX-IPE/IPEE Release 9 Enhanced to Virtual Feature Level Promotion	5,000.00	D
S ➤ Δ	S0005899	NAC Connectivity for Meridian MAX Release 9 Software	No charge	
S ➤ Δ	S0005901	Multiple Queue Assignment (MQA) Reporting for Meridian MAX Release 9 Software	No charge	
S ➤ Δ	S0005907	10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software	1,000.00	D
Upgrades to Meridian MAX-IPE or MAX-IPEE Release 9 System Software				
S ✓ ➤	NTJH02AA	ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D
S ✓ ➤	NTJH02BA	ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D
S ✓ ➤	NTJH02CA	Meridian MAX-AM Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D
S ➤	NTJH02DA	Meridian MAX-IPE Release 4.62, 5 or 6 to Meridian MAX-IPE/ IPEE Release 9 Software Upgrade	7,500.00	D
S ➤	NTJH02EA	Meridian MAX-IPE/IPEE Release 7 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	6,000.00	D
S ➤	NTJH02FA	Meridian MAX-IPE/IPEE Release 8 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	5,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Media Replacement/Upissues for Meridian MAX Release 9 Software				
S ➤ Δ	NTJH05AA	Meridian MAX-SNN/SNNE Release 9 Software Replacement/ Upissue	No charge	
S ➤ Δ	NTJH05BA	Meridian MAX-IPE/IPEE Release 9 Software Replacement/ Upissue	No charge	

Software for Pre-Meridian MAX Release 9 Systems

Options for Pre-Meridian MAX Release 9 Software

S ➤	SW0064A	Meridian MAX MQA Option for Enhanced and Virtual Software (Release 8)	No charge	
S ➤	SW0071A	Meridian MAX-SNN or MAX-SNNE 100-Agent Increment for Meridian MAX Releases 6, 7, and 8	3,000.00	D
S ➤	SW0072A	Meridian MAX One-Time LAN Connectivity Fee for Release 6	750.00	D
S ➤	SW0073A	Meridian MAX LAN Connectivity Software for Release 6 (Available in Increments of 1-59)	600.00	D
S ➤	SW0074A	Meridian MAX MTE One-Time Enable Fee for Release 6	1,000.00	D
S ➤	SW0081A	8-Channel Asynchronous I/O Software Support for Meridian MAX Releases 6, 7, and 8 (MAX-SNN and MAX-SNNE)	1,500.00	D
S ➤	SW0098A	Meridian MAX MSI Option for Virtual Software (Release 7)	No charge	
S ➤	SW0352A	Meridian MAX MQA Option for Virtual Software (Release 7)	No charge	
S ➤	SW7505B	Meridian MAX Networking for Release 6	3,000.00	D
S ➤	SW7511B	Meridian MAX-IPE or MAX-IPEE 20-Agent Software Increment for Releases 6, 7 and 8	2,000.00	D
S ➤	SW7513A	Meridian MAX-IPE Premium Features for Release 6	3,500.00	D
S ➤	SW7525B	NAC (Release 2) Connectivity Enabler for Meridian MAX Releases 6 and 7	650.00	D
S ➤	SW7525C	NAC Connectivity for Meridian MAX Release 8	No charge	
Media Replacement/Upissues for Pre-Meridian MAX Release 9 Software				
S ➤ Δ	NTJH90AA	Meridian MAX-AM Release 6 Software Media Replacement/ Upissue	No charge	
S ➤ Δ	NTJH91AA	Meridian MAX-IPE Release 6 Software Media Replacement/ Upissue	No charge	
S ➤ Δ	NTJH97AA	Meridian MAX-AM Release 7.5 Software Media Replacement/ Upissue	No charge	
S ➤ Δ	NTJH97BA	Meridian MAX-IPE/IPEE Release 7.5 Software Media Replacement/Upissue	No charge	
S ➤ Δ	NTJH98AA	Meridian MAX-AM Release 8 Software Media Replacement/ Upissue	No charge	
S ➤ Δ	NTJH98BA	Meridian MAX-IPE/IPEE Release 8 Software Media Replacement/Upissue	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Expansion for Pre-Meridian MAX Release 9 Software				
S ➤	SW0093A	Meridian MAX-SNN Release 7 Fundamental to Enhanced Software Option Upgrade	20,000.00	D
S ➤	SW0093B	Meridian MAX-SNN and MAX-SNNE Release 8 Fundamental to Enhanced Software Option Upgrade	35,000.00	D
S ➤	SW0094A	Meridian MAX-SNN Release 7 Enhanced to Virtual Software Option Upgrade	15,000.00	D
S ➤	SW0094B	Meridian MAX-SNN and MAX-SNNE Release 8 Enhanced to Virtual Software Option Upgrade	20,000.00	D
S ➤	SW0096A	Meridian MAX-IPE Release 7 Fundamental to Enhanced Option Upgrade	7,500.00	D
S ➤	SW0096B	Meridian MAX-IPE or MAX-IPEE Release 8 Fundamental to Enhanced Software Option Upgrade	12,500.00	D
S ➤	SW0097A	Meridian MAX-IPE Release 7 Enhanced to Virtual Option Upgrade	5,000.00	D
S ➤	SW0097B	Meridian MAX-IPE or MAX-IPEE Release 8 Enhanced to Virtual Software Option Upgrade	5,000.00	D
Release Upgrades for Pre-Meridian MAX Release 9 Software				
S ➤ Δ	SW0083A	Meridian MAX-SNN Release 5 to 6 Base Software Upgrade (200 Agents)	No charge	
S ➤	SW0085A	Meridian MAX Release 3 or 4 on Option 1 or 2 to MAX-SEE 6 Upgrade (160 Agents)	5,000.00	D
S ➤ Δ	SW0086A	Meridian MAX SEE Release 5 to 6 Software Upgrade (160 Agents)	No charge	
S ➤ Δ	SW0087A	Meridian MAX Release 5 to MAX-IPE Release 6 Base Software Upgrade	No charge	
S ➤	SW7514B	Meridian MAX-IPE Release 4 to MAX-IPE Release 6 Base Software Upgrade	1,000.00	D
Meridian MAX Software Administration Fees				
S ➤ Δ	P0885111	Meridian MAX Release 9 Reproduction/Keycode	500.00	H
S ➤ Δ	SERV0005	Meridian MAX Releases 6, 7 and 8 Software Service Transaction Fee (AM). - Issue/Release Update - Feature Additions/Upgrade - Replacement of Transport Medium	500.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ Δ	SERV0017	Meridian MAX-IPE/MAX-IPEE Releases 6, 7 and 8 Software Service Transaction Fee. - Issue/Release Update - Feature Addition/Expanded Agents - Replacement of Transport Medium	500.00	H

Meridian MAX Software Tools

S ➤	AS0073	Meridian MAX Release 7 Capacity Configurator Tool	No charge	
S ➤	AS0075	Meridian MAX Release 8 Capacity Configurator Tool	No charge	
S ➤ Δ	NT1R76BA	Meridian MAX Release 6 Capacity Configurator Tool	No charge	
S ➤ Δ	NT1R76EB	Meridian MAX Release 9.3 Capacity Configuration Tool	No charge	

Meridian MAX Documentation

Meridian MAX Release 9 Documentation

S ➤ Δ	NT6R41AA	Meridian MAX Release 9 Documentation Package (English)	100.00	H
S ➤ Δ	NT6R43AA	Meridian MAX Release 9 Supervisor's User Guide (English)	50.00	H
S ➤ Δ	NTJH94AA	Meridian MAX Release 9 Supervisor's User Guide (English); Package of 10	400.00	H
S ➤ Δ	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)	50.00	H

Meridian MAX Release 8 Documentation

S ➤ Δ	NT1R37AA	Meridian MAX Release 8 Complete Documentation Package	100.00	D
S ➤ Δ	NT1R39AA	Meridian MAX Release 8 NTPs (English)	50.00	D
S ➤ Δ	NT1R49AA	Meridian MAX Release 8 Supervisors User Guide	50.00	D
S ➤ Δ	P0853412	Meridian MAX 8 Installation Upgrade Guide (English)	50.00	D

Meridian MAX Release 7 Documentation

S ➤ Δ	NT1R93AA	Meridian MAX Release 7 Complete Documentation Package	100.00	H
S ➤ Δ	NT1R94AA	Meridian MAX Release 7 Technical Documentation Package	50.00	H
S ➤ Δ	NT1R95AA	Meridian MAX Release 7 Supervisors User Guide	50.00	H
S ➤ Δ	P0815593	Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX Releases 3 through 6 Systems	50.00	H

Meridian MAX Release 6 Documentation

S Δ	NT1R64AA	Meridian MAX Release 6 NTP Package	100.00	H
S Δ	NT1R65AA	Meridian MAX 6 NTPs	50.00	H
S Δ	NT1R66AA	Meridian MAX Release 6 Supervisor Reference Guide	50.00	H
S Δ	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4.6 & 5 Systems (to Release 6)	50.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0802087	Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 6)	50.00	H
S Δ	P0802089	Meridian MAX Release 6 Supervisors User Guide	50.00	H

Meridian Terminal Emulator (MTE)

MTE Software

MTE Release 9 Software

S ➤	NTJH09AB	Meridian Terminal Emulator (MTE) Release 9.3 Software (Single User)	400.00	D
S ➤	NTJH09BB	Meridian Terminal Emulator (MTE) Release 9.3 Software (System License)	4,000.00	D

Upgrades to MTE Release 9 Software

S ✓ ➤	NTJH09CB	Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (Single User)	100.00	D
S ✓ ➤	NTJH09DB	Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (System License)	1,000.00	D

MTE Release 5 Software

S ➤	NT1R75AA	MTE Release 5 Software (Single User) for DOS	400.00	D

MTE Documentation

MTE Release 9 Documentation

S ✓ § ➤ Δ	NTJH95AA	Meridian Terminal Emulator (MTE) Release 9 User Guide (Multilingual: English, French, Spanish); Package of 10	160.00	H
S ➤ Δ	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide	20.00	H

MTE Release 8 Documentation

S ➤ Δ	NT1R98EA	MTE Release 8 User Guide (Multilingual: English, French, Spanish, German); Package of 10	150.00	H
S ➤ Δ	P0870433	MTE Release 8 User Guide (multilingual: English, French, Spanish, German)	20.00	H

MTE Release 7 Documentation

S Δ	NT1R98AA	MTE Release 7 User Guide (Multilingual: English, French, Spanish, German); Package of 10	150.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0821303	MTE Release 7 User Guide (multilingual: English, French, Spanish, German)	20.00	H

MTE Release 6 Documentation

S Δ	P0815602	MTE Release 6 User Guide	10.00	H

Meridian MAXcaster

B ➤	NT2R81AA	MAXcaster Software and Documentation Package English	13,335.00	D
B ➤	NT2R81BA	MAXcaster Software and Documentation Package French	13,335.00	D
S Δ	P0815375	MAXcaster User Guide English	18.00	H
S Δ	P0815376	MAXcaster User Guide French	18.00	H
S Δ	P0839993	MAXcaster Quick Reference Guide English	10.00	H
S Δ	P0844341	MAXcaster Quick Reference Guide French	10.00	H

ACD-MAX
Software Administrative Fees

S ➤ Δ	574SL1-1	ACD MAX Software Service Transaction Fee. A service charge of $500 per transaction will be billed to all customers requesting one or more of the following support services: - Issue Change Release 2.1 to Release 3.1 - Feature Additions Configuration Control (Ex. 921SL1-1) - Single to Dual Tower Upgrade SW7401 or SW7402 - Replacement of Transport Medium Worn or Damaged Software	500.00	H

ACD-D Auxiliary Processor
Meridian Network Administration Center (NAC)
Base Software

S ➤	SW7426	Network Administration Center Release 2.5 Base Software Package	31,000.00	D
S ➤	SW7427	Network Administration Center Release 2.5 Base Software Upgrade	3,000.00	D

Media Replacement/Upissue for NAC 2.5

S ➤	NTJH92AA	Meridian NAC-AM Release 2.5 Upissue/Software Replacement	No charge	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Hardware Packages				
S ➤	SY7421A	Meridian NAC, Release 2.5 Base System Hardware Platform, AC	30,000.00	D
S ➤	SY7421D	Meridian NAC Release 2.5 Base System Hardware Platform, DC	30,000.00	D
S ➤	U7600A	Meridian NAC Release 2.5 Base Hardware Upgrade Package, AC	20,000.00	D
S ➤	U7600D	Meridian NAC Release 2.5 Base Hardware Upgrade Package, DC	20,000.00	D
NAC Software Services Transaction Fee				
S ➤ Δ	P0889406	Meridian NAC Software Service Transaction Fee (AM)	500.00	H
NAC Documentation				
S ➤ Δ	NT1R31AA	NAC Release 2 Documentation Package (English)	100.00	H
S ➤ Δ	P0886656	NAC 2.5 User Guide Supplement	50.00	H

Meridian Link and CCR Co-Residency

Software

Base Software

Meridian Link, Customer Controlled Routing (CCR) and Meridian Link & CCR Co-Residency are being retired due to a number of key hardware components going End of Life. The details for the announcements are as follows:

New Systems:

- All new sales of Meridian Link 5C, CCR 3C, and Co-Resident 6.42 (Meridian Link 5C & CCR 3C) will cease as of July 31st 2000.
- Hardware packages for the IPEE Platform will cease as of July 31st, 2000.

Hardware and Software Upgrades:

- Hardware upgrades to Meridian Link 5C, CCR 3C, and Co-Residency 6.42 (Meridian Link 5C & CCR 3C) will not be available after July 31st, 2000.
- Software upgrades to Meridian Link 5C and CCR 3C will be available until March 2001.

<u>New Sales after Retirement Date</u>:

Note 1: For customers looking for a Meridian Link and CCR call center

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
		replacement, the options for new system sales are SYMPOSIUM Call Center Server (SCCS) and SYMPOSIUM Express Call Center (SECC). Note 2: The new Meridian Link replacement product is planned for general availability in the third quarter of 2000. Note 3: Refer to Product Bulletin 2000-048.		

Software Release Updates/Migration

S ➤	SW7415A	Customer Controlled Routing Release 3C from 20 to 240 Active Scripts Software Upgrade Package	15,000.00	D
S ➤	SW7416A	Customer Controlled Routing Release 3C with 240 Active Associations Software Upgrade Package	3,000.00	D
S ➤	SW7417A	Meridian Link Release 5C Software Upgrade	1,250.00	D

Software Administrative Fees

N Δ	SERV0004	Same Day Shipment per Order Expedite Fee	200.00	H
B ➤ Δ	SERV0006	Customer Controlled Routing Software Service Transaction Fee. - Issue/Release Update - Feature Addition - Replacement of Transport Medium	500.00	H
S ➤ Δ	SERV0033	Meridian Link & CCR Co-Resident Service Transaction Fee	750.00	H

Support Services

S Δ	SVC1035	Meridian Link INSTALL-ASSIST	995.00	H

SYMPOSIUM TAPI Service Provider

S ➤ Δ	NT2F59AA	Application License Kit	No charge	
S ➤	NT6R50AB	SYMPOSIUM TAPI Service Provider for Meridian 1 Release 2	3,900.00	D
S ➤	NT6R67AA	SYMPOSIUM TAPI Service Provider Release 2, IVR and Networking Option	4,000.00	D
S ➤	NT6R68AA	SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 Direct Connect Option	4,000.00	D
S ➤ Δ	NT6R69AB	SYMPOSIUM TAPI Service Provider Upgrade Software	500.00	H
S ➤ Δ	NT6R79AB	SYMPOSIUM TAPI Service Provider Replacement CD-ROM	500.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Services Available				
S ➤ Δ	SV000088	SYMPOSIUM TAPI Service Provider INSTALL-PREP	900.00	H
S ✓ ➤ Δ	SV000089	SYMPOSIUM TAPI Service Provider INSTALL-PRO	5,900.00	H
Call Center and CTI Products-Merchandise				
Components				
Modules, Shelves and Power Supplies				
S ➤	A0669467	Meridian IPEE Application Module for Option 11	10,000.00	D
S ➤	A0669468	Meridian IPEE Application Module for Options 21-81C	10,000.00	D
S ➤	NT7D18AA	Application Equipment Module AC	2,700.00	D
S ➤	NT7D18AB	Application Equipment Module DC	2,700.00	D
S ➤	NT7D63AA	Application Module Chassis Assembly	3,700.00	D
S ➤	NT7D64AA	Application Module Power Supply AC	2,300.00	D
S ➤	NT7D64DC	Application Module Power Supply DC	2,300.00	D
Disk Drives, Tape Drives and Media				
S † ➤	A0314597	DC600A 60MB Back Up Tape	40.00	D
S ➤	A0352271	150 MByte Data Cassette Tape	50.00	D
S ➤	A0368760	DC6250 250MB Back Up Tape	50.00	H
S Δ	A0605411	600MB Data Cassette Tape	100.00	D
S ➤	A0617011	240MB Hard Disk Drive Unit	3,200.00	D
S ➤ Δ	A0730854	IPEE 1GB Hard Drive Repair Kit	725.00	H
S ➤	AS7506	ACD-MAX/NAC to Meridian MAX-IPEE/NAC 2 Data Conversion Kit	2,800.00	D
S ➤	NT7D62AC	1.2 GByte Hard Disk/155 MByte Tape Drive Assembly	6,000.00	D
S ➤	NT7D62CA	1.2 GByte Hard Disk/600 MByte Tape Drive Assembly	7,000.00	D
S ➤	NT7D62DA	240 MByte Hard Disk/155 MByte Tape Drive Assembly	6,000.00	D
S ➤	NT7D62EA	2.0 GByte Hard Disk/600 MByte Tape Drive Assembly	3,000.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Application Module Cards				
S ➤	A0351166	MVME705B Transition Card (for MVME333)	700.00	D
S ➤	A0351167	MVME712AM Transition Card with Built-in Modem (for MVME147)	1,550.00	D
S ➤	A0351919	MVME147SA-1 Processor Card (M68030, 25Mhz, 8MB)	9,200.00	D
S ➤	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	3,000.00	D
S ➤	A0378688	MVME147SB-1 Processor Card (M68030, 25Mhz, 16MB)	10,400.00	D
S ➤	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	11,000.00	D
S	A0601182	MVME712M Transition Card without built-in modem (for MVME167 and MVME177)	900.00	D
S ➤	A0696008	MVME177-005 Processor Card (M68060, 50 Mhz, 64MB)	10,000.00	D
S ➤	NT6D51AA	Transition Card (for MVME332)	650.00	D
S ➤	NT6D98AA	8-Channel Asynchronous I/O Card Kit	3,000.00	D
Miscellaneous				
S ➤	A0368534	8 Port Terminal Concentrator/FM (TC/FM) (RJ45)	950.00	H
S ➤	A0377957	LAN Transceiver	625.00	D
S ➤	AS0073	Meridian MAX Release 7 Capacity Configurator Tool	No charge	
S ➤	AS0075	Meridian MAX Release 8 Capacity Configurator Tool	No charge	
S ➤ Δ	NT1R76BA	Meridian MAX Release 6 Capacity Configurator Tool	No charge	
S ➤ Δ	NT1R76EB	Meridian MAX Release 9.3 Capacity Configuration Tool	No charge	
S ➤	NT7D18KA	Power Sense Monitor Kit	110.00	D
S ✓ ➤	NTRH9016	External Modem 33.6	280.00	D
Cables and Related Merchandise				
S ➤	A0351509	Gender Changer (Female/Female)	20.00	D
S ➤	A0658493	SCSI Termination, Active	40.00	D
S ➤	AS1050	Host Enhanced Voice Processing Cable Kit	250.00	D
S ➤	NT1R03AA	Shielded 4-Port Octopus Cable with Ethernet	150.00	D
S ➤	NT1R03BA	Shielded 4-Port Octopus Cable without Ethernet	140.00	D
S ➤	NT1R03CA	Extension Cable (2 Ft.)	55.00	D
S ➤	NT1R03DB	Straight Through RS232 Cable Male/Male (2 Ft.)	65.00	D
S ➤	NT1R03DC	Straight Through RS232 Cable Male/Male (4 Ft.)	75.00	D
S ➤	NT1R03DF	Straight Through RS232 Cable Male/Male (10 Ft.)	110.00	D
S ➤	NT1R03DP	Straight Through RS232 Cable Male/Male (25 Ft.)	200.00	D
S ➤	NT1R03DV	Straight Through RS232 Cable Male/Male (45 Ft.)	310.00	D
S ➤	NT1R03EB	Straight Through RS232 Cable Male/Female (2 Ft.)	75.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	NT1R03EC	Straight Through RS232 Cable Male/Female (4 Ft.)	80.00	D
S ➤	NT1R03EF	Straight Through RS232 Cable Male/Female (10 Ft.)	110.00	D
S ➤	NT1R03EP	Straight Through RS232 Cable Male/Female (25 Ft.)	200.00	D
S ➤	NT1R03EV	Straight Through RS232 Cable Male/Female (45 Ft.)	300.00	D
S ➤	NT1R03FP	MDF 50 Pin Cable with Ethernet (25 Ft.)	200.00	D
S ➤	NT1R03FV	MDF 50 Pin Cable with Ethernet (45 Ft.)	150.00	D
S ➤	NT1R03GP	MDF 50 Pin Cable without Ethernet (25 Ft.)	150.00	D
S ➤	NT1R03GV	MDF 50 Pin Cable without Ethernet (10 Ft.)	100.00	D
S ➤	NT7D46AA	SDI I/O Cable	80.00	D
S ➤	NT7D46AD	Application Module to SDI Paddle Board Cable (6 Ft.)	50.00	D
S ➤	NT7D46AF	Application Module to SDI Paddle Board Cable (10 Ft.)	50.00	D
S ➤	NT7D46AL	Application Module to SDI Paddle Board Cable (20 Ft.)	60.00	D
S ➤	NT7D46AT	Application Module to SDI Paddle Board Cable (35 Ft.)	70.00	D
S ➤	NT7D46AV	Application Module to SDI Paddle Board Cable (45 Ft.)	80.00	D
S ➤	NT7D47AG	Ethernet Cable (12 Ft.)	125.00	D
S	NT7D47DA	Ethernet Cable (2 Ft.)	100.00	D
S	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	175.00	D
S ➤	NT7D48AA	Serial I/O Cable	120.00	D
S ➤	NT7D58EB	ESDI Cable (2 Ft.)	50.00	D
S ➤	NT7D58ED	ESDI Cable (6 Ft.)	50.00	D
S ➤	NT7D58EF	ESDI Cable (10 Ft.)	50.00	D
S ➤	NT7D58EL	ESDI Cable (20 Ft.)	60.00	D
S ➤	NT7D58ET	ESDI Cable (35 Ft.)	65.00	D
S ➤	NT7D58EV	ESDI Cable (45 Ft.)	80.00	D
S ➤	NT7D61EB	SDI Cable (2 Ft.)	40.00	D
S ➤	NT7D61ED	SDI Cable (6 Ft.)	45.00	D
S ➤	NT7D61EF	SDI Cable (10 Ft.)	45.00	D
S ➤	NT7D61EL	SDI Cable (20 Ft.)	50.00	D
S ➤	NT7D61ET	SDI Cable (35 Ft.)	60.00	D
S ➤	NT7D61EV	SDI Cable (45 Ft.)	60.00	D
S ➤	NT7D71BA	VME Built-In Modem External Cable	40.00	D
S ➤	NT7D99AA	Null Modem Cable (10 Ft.)	60.00	D
S ➤	NT8D46CD	System Monitor Column Cable (AEM)	40.00	D
S ➤	NT8D96BE	VME Multi-Port Cable	175.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S	NT9D8001	Cable TC/FM to SDI (HSL and Configuration Control) (RJ45 to DB25)	30.00	H
S	NT9D8002	Cable TC/FM to Supervisor PC (Return to Console Link) (RJ45 to DB9)	60.00	H
S	NT9D8003	Cable TC/FM to Printer (RJ45 to DB25)	30.00	H
S	NT9D8004	Cable TC/FM to Terminal (RJ45 to DB25)	60.00	H
S	NT9D9007	Cable TC/FM to Modem (Remote Supervisor) (RJ45 to DB25)	60.00	H
S ➤	NT9D9008	Cable TC/FM to NAC Network Link and Remote Supervisor Log-In Link (RJ45 to DB25)	60.00	H
S ➤	NTAK1118	Modem Cable (DB9 to DB25)	90.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description

eCommerce Solutions

WebShare Products

View Manager

S ➤ Δ	NTY210AA	View Manager with 5 User License
S ➤ Δ	NTY211AA	View Manager with 25 User License
S ➤ Δ	NTY212AA	View Manager with 50 User License
S ➤ Δ	NTY213AA	View Manager with 100 User License
S ➤ Δ	NTY214AA	View Manager with 200 User License
S ➤ Δ	NTY215AA	View Manager with Greater than 200 User License
S ➤ Δ	NTY216AA	View Manager Basic Technical Support
S ➤ Δ	NTY217AA	View Manager Elite Technical Support
S ➤ Δ	NTY218AA	View Manager Custom Configuration
S ➤ Δ	NTY219AA	View Manager OEM Configuration
S ➤ Δ	NTY220AA	View Manager Documentation Set
S ➤ Δ	NTY221AA	View Manager Quick Reference Guides
S ➤ Δ	NTY222AA	View Manager Product Training
S ➤ Δ	NTY223AA	View Manager Consulting and Professional Services
S ➤ Δ	NTY224AA	View Manager Installation Services
S ➤ Δ	NTY230AA	View Manager License Upgrade to 25 Users
S ➤ Δ	NTY231AA	View Manager License Upgrade to 50 Users
S ➤ Δ	NTY232AA	View Manager License Upgrade to 100 Users
S ➤ Δ	NTY233AA	View Manager License Upgrade to 200 Users
S ➤ Δ	NTY278AA	View Manager for Hosted Service Provider

Security and Policy Management

Access Policy Manager

S ➤ Δ	NTY240AA	APM, 1 Server/100 Seat Configuration
S ➤ Δ	NTY241AA	APM, 10 Servers/1000 Seat Configuration
S ➤ Δ	NTY242AA	APM, 25 Servers/2500 Seat Configuration
S ➤ Δ	NTY243AA	APM, 100 Servers/5000 Seat Configuration
S ➤ Δ	NTY244AA	APM, 250 Servers/10000 Seat Configuration
S ➤ Δ	NTY245AA	APM, 500 Servers/25000 Seat Configuration
S ➤ Δ	NTY246AA	APM, Custom Configurations

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Market retired	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description
S ➤ Δ	NTY247AA	APM, Unlimited Configuration
S ➤ Δ	NTY248AA	APM, OEM Configuration
S ➤ Δ	NTY250AA	Legacy Module for APM, 1 Server/100 Seats
S ➤ Δ	NTY251AA	Legacy Module for APM, 10 Servers/1000 Seats
S ➤ Δ	NTY252AA	Legacy Module for APM, 25 Servers/2500 Seats
S ➤ Δ	NTY253AA	Legacy Module for APM, 100 Servers/5000 Seats
S ➤ Δ	NTY254AA	Legacy Module for APM, 250 Servers/10000 Seats
S ➤ Δ	NTY255AA	Legacy Module for APM, 500 Servers/25000 Seats
S ➤ Δ	NTY256AA	Legacy Module for APM, Custom Configuration
S ➤ Δ	NTY257AA	Legacy Module for APM, Unlimited Configuration
S ➤ Δ	NTY260AA	APM Upgrade, 1 Server/100 Seats to 10 Servers/1000 Seats
S ➤ Δ	NTY261AA	APM Upgrade, 10 Servers/1000 Seats to 25 Servers/2500 Seats
S ➤ Δ	NTY262AA	APM Upgrade, 25 Servers/2500 Seats to 100 Servers/5000 Seats
S ➤ Δ	NTY263AA	APM Upgrade, 100 Servers/5000 Seats to 250 Servers/10000 Seats
S ➤ Δ	NTY264AA	APM Upgrade, 250 Servers/10000 Seats to 500 Servers/25000 Seats
S ➤ Δ	NTY265AA	APM Custom Upgrade
S ➤ Δ	NTY270AA	APM, Installation (Mandatory Service, Performed by a Certified APM Installation Engineer)
S ➤ Δ	NTY271AA	APM, Professional Services/System Integration/Consulting
S ➤ Δ	NTY272AA	APM, Product Training
S ➤ Δ	NTY273AA	APM, Full Documentation (Hardcopy)
S ➤ Δ	NTY274AA	APM, Quick Reference Guides (Hardcopy)
S ➤ Δ	NTY275AA	APM, Basic Membership Support Package, Renewed Annually
S ➤ Δ	NTY276AA	APM, Elite Membership Support Package, Renewed Annually
S ➤ Δ	NTY277AA	APM, Service Provider Hosted Model. Nortel Networks will be pleased to provide a quote for APM deployment by a Service Provider.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Other Application Products

Meridian Private-switch Emergency Response

Meridian Private-switch Emergency Response Unit

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	A0660168	Meridian Private-Switch Emergency Response Configuration Software	20.00	D
S ➤	A0660170	Meridian Private-Switch Emergency Response Installation Kit	200.00	D
S ➤	A0660175	Meridian Private-Switch Emergency Response AC Power Supply	300.00	D
S ➤	A0665488	Meridian Private-Switch Emergency Response Unit	14,500.00	D
S ➤	AS1500A	Meridian Private-Switch Emergency Response Unit-AC Version	15,000.00	D

Meridian Private-switch Emergency Notification PC Software

S ➤	A0660171	Meridian Private-Switch Emergency Notification PC Software	4,700.00	D
S ➤	A0660173	Meridian Private-Switch Emergency Notification Installation Kit	200.00	D
S ➤	AS1501	Meridian Private-Switch Emergency Notification PC Software	5,000.00	D

Meridian Private-switch Monitor Software

S	A0665642	Meridian Private-Switch Emergency Notification Event Monitor Software	1,000.00	D

Meridian Private-switch Emergency Documentation

S ➤ Δ	A0660169	Emergency Response Installation/User Guide	80.00	D
S Δ	A0660172	Emergency Notification Installation/User Guide	80.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Market retired	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Remote Solutions

Remote Office 9150 - Solutions for the Small Branch Office

S ✓ ➤	NTQR05AA	Remote Office 9150 8-User VoIP Package - 16 RLC	7,995.00	D
S ✓ ➤	NTQR06AA	Remote Office 9150 8-User Starter Package - 16 RLC	9,145.00	D
S ✓ ➤	NTQR07AA	Remote Office 9150 8-User Starter Package - 32 RLC Option 51-81	11,445.00	D
S ✓ ➤	NTQR08AA	Remote Office 9150 8-User Starter Package - 32 RLC Option 11	11,445.00	D
S ✓ ➤	NTQR09AA	Remote Office 9150 Branch Expansion Package	6,995.00	D
S ✓ ➤	NTQR10AA	Remote Office 9150 8-User Expansion Package	2,195.00	D

Remote Office 9110 and 9115 - Solutions for the Teleworker

S ★ ➤	NTQR11AA	Remote Office 9115 4-User Starter Package - 16 RLC	7,295.00	D
S ★ ➤	NTQR12AA	Remote Office 9115 4-User Expansion Package - 16 RLC	4,485.00	D
S ★ ➤	NTQR14AA	Remote Office 9110 4-User Starter Package - 16 RLC	7,295.00	D
S ★ ➤	NTQR15AA	Remote Office 9110 4-User Expansion Package - 16 RLC	4,485.00	D

Remote Office Components

S ✓ ➤	NTDR68AA	Reach Line Card - 16 Port	5,495.00	D
S ✓ ➤	NTDR69AA	Remote Office 9150 Unit	5,995.00	D
S ✓ ➤	NTDR70AA	Reach Line Card - 32 Port - Option 51-81	6,895.00	D
S ✓ ➤	NTDR71AA	Reach Line Card - 32 Port - Option 11	6,895.00	D
S ✓ ➤	NTDR73AA	DSP Application Module	1,295.00	D
S ✓ ➤	NTDR74AA	BRI Module (U Interface)	1,195.00	D
S ➤	NTDR79AA	Reach Line Card Cable - Basic Version	95.00	D
S ➤	NTDR80AA	Reach Line Card Cable - Enhanced Version	325.00	D
S ✓ ➤	NTDR87AA	Remote Office 9150 Universal Power Supply	260.00	D
S ★ ➤	NTDR88AA	Remote Office 911x North American Power Supply	95.00	D
S ★ ➤	NTQR16AA	Remote Office 9110 Unit with North American Power Supply	845.00	D
S ★ ➤	NTQR17AA	Remote Office 9115 Unit with North American Power Supply	895.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Remote Office Documentation and Training				
S ✓ ➤ Δ	NTDR81AA	Remote Office Product CD-ROM Package	50.00	H
S ➤ Δ	NTDR82AA	MIG Reach Line Card Installation and Administration Guide	20.00	H
S ✓ ➤ Δ	NTDR83AA	Remote Office Technical Training CD-ROM Package	90.00	H
S ✓ ➤ Δ	NTDR84AA	Remote Office 9150 Installation and Administration Guide	30.00	H
S ★ ➤ Δ	NTDR85AA	Remote Office 911x User Guide	30.00	H
Meridian HomeOffice II Remote Equipment				
S ➤	NTQR01AA	Meridian HomeOffice II Router (NTQR03AA) with M2616	2,395.00	D
S ➤	NTQR01BA	Meridian HomeOffice II Router ACD with M2216 Digital Set	2,395.00	D
S	NTQR03AA	Meridian HomeOffice II Router C/W CD-ROM, User Guide; ISDN, Ethernet & Admin Cables; Online Call Keycap & Power Supply	1,950.00	D
Meridian HomeOffice II Host Equipment				
S ➤	NTQR02AA	Meridian HomeOffice II Line Card C/W Management/ Interconnect Cable and Installer Notes	4,760.00	D
Meridian HomeOffice II Documentation and Training				
S Δ	NTDR05AC	Meridian HomeOffice II Planning Guide	27.00	H
S Δ	NTDR06AC	Meridian HomeOffice II Network Administration Guide	27.00	H
S Δ	NTDR07AC	Meridian HomeOffice II Line Card Configuration Guide	27.00	H
S Δ	NTDR15AC	Meridian HomeOffice II User Guide	27.00	H
S Δ	NTDR16AB	CD ROM with Jewel Case	37.00	H
S Δ	NTDR60AA	Self-paced Technical Training CD	99.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Market retired	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian HomeOffice II Additional Items

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	A0292928	110V Power Cord	15.00	D
S	NTDJ65AA	Serial 9 Pin Cable	35.00	D
S	NTDJ66AA	ISDN Cable	50.00	D
S	NTDJ67AA	10BaseT Ethernet Cable, Crossed	25.00	D
S	NTDR50AB	Multi I/O Cable	99.00	D
S	NTDR52AA	Universal Power Supply	124.00	D
S	NTDR58AA	MMI Cable Kit (32 Ft.)	45.00	D
S	NTDR59AA	SDI Cable Kit (10 Ft.)	75.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 System Administration Products

Optivity Telephony Manager (OTM)

New Installation

Status	Order Code	Description	CLP	Distr. Disc.
S ✓	NTTL01AA	OTM 1.0 General, Server, 50 Sets	500.00	D
S ✓	NTTL01BA	OTM 1.0 Enhanced, Server, 50 Sets	600.00	D
S ✓	NTTL01CA	OTM 1.0 Premium, Server, 50 Sets	700.00	D
S ✓	NTTL02AA	OTM 1 x General, 50 Sets Expansion	250.00	D
S ✓	NTTL02BA	OTM 1 x General, 250 Sets Expansion	1,000.00	D
S ✓	NTTL02CA	OTM 1 x General, 1000 Sets Expansion	3,500.00	D
S ✓	NTTL02DA	OTM 1 x General, 5000 Sets Expansion	5,000.00	D
S ✓	NTTL03AA	OTM 1 x Enhanced, 50 Sets Expansion	350.00	D
S ✓	NTTL03BA	OTM 1 x Enhanced, 250 Sets Expansion	1,500.00	D
S ✓	NTTL03CA	OTM 1 x Enhanced, 1000 Sets Expansion	5,000.00	D
S ✓	NTTL03DA	OTM 1 x Enhanced, 5000 Sets Expansion	8,000.00	D
S ✓	NTTL04AA	OTM 1 x Premium, 50 Sets Expansion	500.00	D
S ✓	NTTL04BA	OTM 1 x Premium, 250 Sets Expansion	2,300.00	D
S ✓	NTTL04CA	OTM 1 x Premium, 1000 Sets Expansion	8,000.00	D
S ✓	NTTL04DA	OTM 1 x Premium, 5000 Sets Expansion	12,000.00	D

MAT Upgrades to OTM

S ✓	NTTL08AA	OTM 1.0 General, MAT Upgrade, Server, 50 Sets	300.00	D
S ✓	NTTL08BA	OTM 1.0 Enhanced, MAT Upgrade, Server, 50 Sets	400.00	D
S ✓	NTTL08CA	OTM 1.0 Premium, MAT Upgrade, Server, 50 Sets	500.00	D
S ✓ Δ	NTTL09AA	OTM 1.0 General, MAT Upgrade, 50 Sets Expansion	No charge	
S ✓ Δ	NTTL09BA	OTM 1.0 Enhanced, MAT Upgrade, 50 Sets Expansion	No charge	
S ✓ Δ	NTTL09CA	OTM 1.0 Premium, MAT Upgrade, 50 Sets Expansion	No charge	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
OTM Upgrades				
S ✓	NTTL11AA	OTM 1.0 General to Enhanced Server, 50 Sets	150.00	D
S ✓	NTTL11BA	OTM 1.0 General to Premium Server, 50 Sets	250.00	D
S ✓	NTTL11CA	OTM 1.0 Enhanced to Premium Server, 50 Sets	150.00	D
S ✓	NTTL12AA	OTM 1 x General to Enhanced, 50 Sets Expansion	100.00	D
S ✓	NTTL12BA	OTM 1 x General to Enhanced, 250 Sets Expansion	500.00	D
S ✓	NTTL12CA	OTM 1 x General to Enhanced, 1000 Sets Expansion	1,500.00	D
S ✓	NTTL12DA	OTM 1 x General to Enhanced, 5000 Sets Expansion	3,000.00	D
S ✓	NTTL13AA	OTM 1 x General to Premium, 50 Sets Expansion	250.00	D
S ✓	NTTL13BA	OTM 1 x General to Premium, 250 Sets Expansion	1,300.00	D
S ✓	NTTL13CA	OTM 1 x General to Premium, 1000 Sets Expansion	4,500.00	D
S ✓	NTTL13DA	OTM 1 x General to Premium, 5000 Sets Expansion	7,000.00	D
S ✓	NTTL14AA	OTM 1 x Enhanced to Premium, 50 Sets Expansion	150.00	D
S ✓	NTTL14BA	OTM 1 x Enhanced to Premium, 250 Sets Expansion	800.00	D
S ✓	NTTL14CA	OTM 1 x Enhanced to Premium, 1000 Sets Expansion	3,000.00	D
S ✓	NTTL14DA	OTM 1 x Enhanced to Premium, 5000 Sets Expansion	4,000.00	D
OTM Billing 1.0 Codes - New Installation				
S ✓	NTTL05AA	OTM Billing 1 x General, 100 RU	1,975.00	D
S ✓	NTTL06AA	OTM Billing 1 x General, 250 RU Expansion	1,100.00	D
S ✓	NTTL06BA	OTM Billing 1 x General, 1000 RU Expansion	3,775.00	D
S ✓	NTTL06CA	OTM Billing 1 x General, 5000 RU Expansion	12,000.00	D
S ✓	NTTL06DA	OTM Billing 1 x General, 10000 RU Expansion	17,250.00	D
S ✓	NTTL06EA	OTM Billing 1 x General, 50000 RU Expansion	37,750.00	D
S ➤	NTZK52BA	MDR 2000 Buffer Box 128Kb (117vac/60Hz)	1,825.00	D
S ➤	NTZK52CA	MDR 2000 Buffer Box 512Kb (117vac/60Hz)	2,555.00	D
S ➤	NTZK52DA	MDR 2000 Buffer Box 2 Mb (117vac/60Hz)	3,285.00	D
OTM Application Additions				
S ✓	NTTL17AA	OTM Access Server	1,000.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
MAT to Billing Upgrades				
S ✓	NTTL10AA	OTM Billing 1 x General, MAT Upgrade, 100 RUs	975.00	D
Additional OTM Clients				
S ✓	NTTL18AA	MAT PC Dongle to OTM Client Upgrade	200.00	D
S ✓	NTTL19AA	OTM, Additional Client for One (1) PC	500.00	D
S ✓	NTTL19BA	OTM, Additional Client for Five (5) PCs	2,000.00	D
S ✓	NTTL19CA	OTM, Additional Client for Ten (10) PCs	3,500.00	D
User Guides				
S ✓ Δ	P0910102	OTM 1.0 Installation and Engineering User Guide	50.00	H
S ✓ Δ	P0910103	OTM 1.0 User Guide	50.00	H
Services and Support				
S Δ	SV000397	OTM Service, Rate Tables - MDR	800.00	D
Meridian Administration Tool Release 6				
End-User Base Packages				
S ➤	NTZC01AF	MAT 6, End User Common Services	875.00	D
S ➤ Δ	NTZC01BF	MAT 6, Distributor Common Services	5,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Application Packages				
S ➤	NTZC02AA	MAT 6 Station Administration Module	650.00	D
S ➤	NTZC02BA	MAT 6 Traffic Analysis Module	4,300.00	D
S ➤	NTZC02CA	MAT 6 Call Tracking Module	750.00	D
S ➤	NTZC02DA	MAT 6 Call Accounting Module	1,800.00	D
S ➤	NTZC02EA	MAT 6 ESN Analysis and Reporting Tool Module	2,875.00	D
S ➤	NTZC02FA	MAT 6 Maintenance Windows Module	6,500.00	D
S ➤	NTZC02GA	MAT 6 Alarm Management Module	3,500.00	D
S ✓ ➤ Δ	NTZC03AF	MAT 6, User Guide and CD Package	75.00	H
S ➤	NTZC04AA	MAT 6 Maintenance Marketing Bundle	11,500.00	D
S ➤	NTZC04BA	MAT 6 Administration Marketing Bundle	5,500.00	D
S ➤	NTZC04CA	MAT 6 System Management Marketing Bundle	17,500.00	D
S ➤	NTZC10AF	PC Dongle for One (1) PC and User Guide	500.00	D
S ➤	NTZC10BF	PC Dongles for Five (5) PC and User Guides	2,000.00	D
S ➤	NTZC10CF	PC Dongles for Ten (10) PC and User Guides	3,000.00	D
S ➤	NTZC10DF	PC Dongles for Fifty (50) PC and 30 User Guides	10,000.00	D
S ➤	NTZC10EF	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	37,500.00	D
S ➤	P0876389	MAT 6 End User Five (5) Additional Meridian 1 System Licenses	2,475.00	D
S ➤	P0876390	MAT 6 Call Accounting Mini Expansion License	1,150.00	D
S ➤	P0876391	MAT 6 Call Accounting Small Expansion License	2,300.00	D
S ➤	P0876392	MAT 6 Call Accounting Medium Expansion License	4,000.00	D
S ➤	P0876393	MAT 6 Call Accounting Large Expansion License	9,000.00	D
S ➤	P0876394	MAT 6 Call Accounting Expansion Cap License	13,000.00	D
Upgrades From MAT 5 or MAT 6				
S ➤ Δ	NTZC08AF	MAT 5/6 to MAT 6.X, Flat Fee Upgrade	299.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
Upgrades From MAT 4				
S ➤	NTZC06AA	MAT 6 Station Administration Upgrade	160.00	D
S ➤	NTZC06BA	MAT 6 Traffic Analysis Upgrade	650.00	D
S ➤	NTZC06CA	MAT 6 Call Tracking Upgrade	190.00	D
S ➤	NTZC06DA	MAT 6 Call Accounting Base Upgrade	450.00	D
S ➤ Δ	NTZC07AF	MAT 6, Distributor Single Location Common Services and Station Upgrade	1,000.00	H
S ✓ ➤	NTZC09AF	MAT 6, End User Common Services Upgrade	200.00	D
S ➤	P0876395	MAT 6 End User Site Expansion Upgrade	150.00	D
S ➤ Δ	P0876396	MAT 6 Call Accounting Mini Expansion License Upgrade	No charge	
S ➤ Δ	P0876397	MAT 6 Call Accounting Small Expansion License Upgrade	No charge	
S ➤ Δ	P0876398	MAT 6 Call Accounting Medium Expansion License Upgrade	No charge	
S ➤ Δ	P0876399	MAT 6 Call Accounting Large Expansion License Upgrade	No charge	
S ➤ Δ	P0876400	MAT 6 Call Accounting Expansion Cap License Upgrade	No charge	
Hardware				
S ➤	NTZK52BA	MDR 2000 Buffer Box 128Kb (117vac/60Hz)	1,825.00	D
S ➤	NTZK52CA	MDR 2000 Buffer Box 512Kb (117vac/60Hz)	2,555.00	D
S ➤	NTZK52DA	MDR 2000 Buffer Box 2 Mb (117vac/60Hz)	3,285.00	D

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian Administration Tool Release 4

Upgrades

S ➤	NTZK45BD	MAT Call Accounting Small Expansion	2,300.00	D
S ➤	NTZK45CD	MAT Call Accounting Medium Expansion	4,000.00	D
S ➤	NTZK46AD	MAT Distributor Single Location Station Administration Upgrade	325.00	H
S ➤	NTZK46BD	MAT Distributor Multi-Location Station Administration Upgrade	10,000.00	H
S ➤	NTZK47AD	MAT Single Site Common Services Upgrade	100.00	D
S ➤	NTZK47BD	MAT Multi Site Common Services Upgrade	560.00	D
S ➤	NTZK48AD	MAT Station Administration Upgrade	160.00	D
S ➤	NTZK49AD	MAT Traffic Analysis Upgrade	650.00	D
S ➤	NTZK50AD	MAT Call Tracking Upgrade	190.00	D
S ➤	NTZK51AD	MAT Call Accounting Base Upgrade	450.00	D

Hardware

S ➤	NTZK52BA	MDR 2000 Buffer Box 128Kb (117vac/60Hz)	1,825.00	D
S ➤	NTZK52CA	MDR 2000 Buffer Box 512Kb (117vac/60Hz)	2,555.00	D
S ➤	NTZK52DA	MDR 2000 Buffer Box 2 Mb (117vac/60Hz)	3,285.00	D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Spares Packages

Hardware

Status	Order Code	Description	CLP	Distr. Disc.
S ➤	AS1130	Option 51C/61C/81 CE Spares Package	18,000.00	I
S ➤	AS1132	Option 51C/61C/81C System Spares Package	36,000.00	I
S ➤	AS1208A	Power Supply Spares Package AC	6,000.00	I
S ➤	AS1208D	Power Supply Spares Package DC	6,000.00	I
S ➤	P0729843	Spare Circuit Breaker Kit, 5 Amp	45.00	H
S ➤	P0729846	Spare Circuit Breaker Kit, 20 Amp	45.00	H
S ➤	P0729847	Spare Circuit Breaker Kit, 30 Amp	45.00	H
S ➤	P0730252	MFA Spare Fuse Kit	50.00	H
S	P0743482	Spare Circuit Breaker Kit, 50 Amp - MPP600/MFA150	45.00	H

Meridian Mail

S ➤	AS7070D	Meridian Mail Modular GP Spares Package	10,000.00	D
S ➤	AS7080	Meridian Mail Modular Option EC/EC11 Spares Package 1	8,000.00	D
S ➤	AS7081	Meridian Mail Modular Option EC/EC11 Spares Package 2	13,000.00	D
S ➤	AS7083	Meridian Mail EC11 Spares Package	8,500.00	D

Call Center

S ➤	AS0071	Meridian MAX-SNN Spares Kit	6,000.00	D
S ➤	AS0074	Meridian MAX-SNNE Spares Kit	6,000.00	D
S ➤	AS7505	Meridian MAX-SEE Spares Kit	6,400.00	D

Open IVR

S † ➤ Δ	A0640190	OIVR 2 x Hardware - MRS/Tower Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - SCSI Cable - Floppy Cable	10,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S † ➤ Δ	A0640192	OIVR 2 x Hardware - MRS/Rack DC Spares Kit. - CPU Module and Memory - DC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - SCSI Cable - Floppy Cable	10,650.00	H
S † ➤ Δ	A0640194	OIVR 2 x Hardware - MRS/Rack AC Spares Kit. - CPU Module and Memory - AC Power Supply - Serial I/O Card - SCSI Controller - Ethernet Controller - Floppy cable	10,000.00	H

Symposium Messenger/Assistant

S ➤	NTVM18AA	MAS-Model 100 Spares Kit	6,000.00	H
S ➤	NTVM19AA	MAS-Model 500 Spares Package	10,000.00	H

Meridian Integrated Conference Bridge

S ➤	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card	7,000.00	D
S ➤	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive	1,400.00	D
S	NT5G92AA	MICB Software Upgrade Kit	400.00	H

Meridian Integrated RAN

S	A0683638	8MB PCMCIA Flash Card	600.00	H
S ➤	NTAG36AC	Meridian Integrated RAN (Release 2) Base Spare Card	2,200.00	D
S Δ	P0885702	Meridian Integrated RAN (Release 2) NTP Guide	20.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Meridian 1 Documentation
NTPs

S Δ	A0389770	Application Module NTP	125.00	H
S Δ	NT1F89AA	Meridian Mail Release 12 Overview	15.00	H
S Δ	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	20.00	H
S Δ	NT1F91AA	Meridian Mail Modular Options Manual	20.00	H
S Δ	NT1F92AA	Meridian Mail Release 12 Modular Option GP Manual	20.00	H
S Δ	NT1F93AA	Meridian Mail Release 12 Option 11 EC/EC11 Manual	20.00	H
S ➤ Δ	NT1F97AA	Meridian Mail Release 12 Voice Messaging Package (VMUIF)	30.00	H
S Δ	NT1R57AE	CCR 3B/Link 5 Documentation Package	50.00	H
S Δ	NT1R61AA	NTP Assembly	50.00	H
S Δ	NT1R64AA	Meridian MAX Release 6 NTP Package	100.00	H
S Δ	NT1R65AA	Meridian MAX 6 NTPs	50.00	H
S ✓ ➤ Δ	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	32.00	H
S ➤ Δ	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	25.00	H
S ✓ ➤ Δ	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	35.00	H
S ➤ Δ	NT2F23AA	Meridian Mail Release 13 Option 11 EC (EC11) Manual	21.00	H
S ➤ Δ	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	15.00	H
S ✓ ➤ Δ	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	25.00	H
S ✓ ➤ Δ	NT2F26AA	Meridian Mail Release 13 Call Answering (VMUIF) Package	135.00	H
S ✓ ➤ Δ	NT2F27AA	Meridian Mail Release 13 Voice Messaging (VMUIF) Package	44.00	H
S Δ	NT3R01CA	Meridian IVR Development Module	100.00	H
S Δ	NT3R01DA	Meridian IVR Operational NTPs. Includes: - Meridian IVR General Description - Meridian IVR Installation Guide - Meridian IVR System Administration and Reports	100.00	H
S Δ	NT5F3401	CD-ROM, CD-ROM X11 Release 24, North America	150.00	H
S ➤ Δ	NT5F34AA	Meridian 1 Reference Library, Release 24 and Earlier	250.00	H
S ➤ ⊗ Δ	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	300.00	H
S ✓ Δ	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	40.00	H
S ✓ Δ	NT5F57AA	Meridian Mail Release 12 System Administration Manual Multi-Customer EC, Modular Option, EC11, Card Option	40.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	40.00	H
S Δ	NT5F59AA	Meridian Mail Release 12 System Administration Manual Multi-Customer, Modular Option GP/MSM	40.00	H
S Δ	NT5F81AA	Meridian Mail 11 CD ROM Package (NTPs)	25.00	H
S Δ	NT5F98AA	Meridian Mail Release 12 CD ROM Package (NTPs)	25.00	H
S Δ	NT5R87AA	Meridian Mail Multi-Customer Systems Reference Manual (DMS), Release 9	40.00	H
S Δ	NT5R99AA	Meridian Mail System Administration Reference Manual (DMS), Release 9	30.00	H
B ➤ Δ	NT6R77AD	Option 11C Release 24 English Documentation Package - Binder	90.00	H
S ➤ Δ	NT6R81AA	Meridian Mail Options Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R82AA	Meridian Mail Modular Option GP Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R83AA	Meridian Mail Modular Option EC Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R84AA	Meridian Mail Modular Option Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R85AA	Meridian Mail Multi-Customer System Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R86AA	Meridian Mail System Administration Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R87AA	Meridian Mail Multi-Customer System Reference Manual (DMS), Release 10	40.00	H
S ➤ Δ	NT6R88AA	Meridian Mail ACCESS Developers Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R89AA	Meridian Mail ACCESS Enable Option Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R90AA	Meridian Mail Modular EC Installation & Maintenance Quick Reference Manual, Release 10	30.00	H
S ➤ Δ	NT6R91AA	Meridian Mail SEERS Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R93AA	Meridian Mail Card Option Reference Manual, Release 10	40.00	H
S ➤ Δ	NT6R99AA	Meridian Mail System Administration Reference Manual (DMS), Release 10	40.00	H
S Δ	NTAK82AF	Option 11 NTP Package Release 18	50.00	H
S Δ	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	25.00	H
S ★ ➤ Δ	NTDW81AA	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (CD-ROM)	20.00	H
B ➤ Δ	NTKG80CF	Option 11C Mini Release 25 English Documentation Package, Coil	90.00	H
S ➤ Δ	NTLH02AA	Meridian 1 Reference Library, Release 25	250.00	H
S Δ	NTLH03AA	System Planning and Engineering Guide	50.00	H
S Δ	NTLH04AA	System Installation and Maintenance Guide	50.00	H
S Δ	NTLH05AA	System and Software Upgrade Guide	50.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	NTLH06AA	Remote Peripheral Equipment Guide	50.00	H
S Δ	NTLH08AA	X11 Software Features Guide	50.00	H
S Δ	NTLH09AA	X11 Input/Output Guide	50.00	H
S Δ	NTLH10AA	X11 System Management, Overview, Applications and Security Guide	50.00	H
S Δ	NTLH11AA	X11 Networking Features	50.00	H
S Δ	NTLH12AA	X11 Data Features	50.00	H
S Δ	NTLH13AA	ACD Reference Guides	50.00	H
S Δ	NTLH14AA	X11 Hospitality Features	50.00	H
S ✓ Δ	NTLH16AA	Meridian IP Telecommuter NTP CD ROM	10.00	H
S ➤ Δ	NTSF3001	Package of 10 Option 11C Documentation CD-ROMs	500.00	H
B ➤ Δ	NTTK30AB	Option 11C Release 25 English Documentation Package, Binder	90.00	H
B ➤ Δ	NTTK31AB	Option 11C Release 25 English Documentation Package, Coil	90.00	H
S ➤ Δ	NTTK32CB	Option 11C Customer Documentation Library on CD-ROM, Release 25	75.00	H
N ➤ Δ	NTTK33AB	Option 11C Distributor Technical Library Package, Release 25	70.00	H
S Δ	P0699378	Meridian SL-1 NT Installation and Acceptance	50.00	H
S Δ	P0699379	Meridian SL-1 NT Maintenance	50.00	H
S Δ	P0699380	Meridian SL-1 XT Installation and Acceptance	50.00	H
S Δ	P0699381	Meridian SL-1 XT Maintenance	50.00	H
S Δ	P0699382	Meridian SL-1 ST Installation and Acceptance	50.00	H
S Δ	P0699383	Meridian SL-1 ST Maintenance	50.00	H
S Δ	P0699387	Meridian SL-1 General Information and Engineering	50.00	H
S Δ	P0726664	QCA13 Power System NTP (Set of 2). Includes: - J2412 Power Distribution Plant - NT5C03 Switched Mode Rectifier -48V/50A	16.00	H
S Δ	P0730121	MFA150 User Guide/NTP	25.00	H
S Δ	P0734019	Network Administration Center Connectivity NTP	45.00	H
S Δ	P0734021	Network Administration Center NTP	55.00	H
S Δ	P0735064	Controlling Access Privileges Workbook	50.00	H
S Δ	P0735252	NT7D16 Data Access Card NTP	5.00	H
S Δ	P0739518	Meridian Mail Options Reference Manual	30.00	H
S Δ	P0739520	Meridian Mail GP Reference Manual	30.00	H
S Δ	P0739521	Meridian Mail NTP Card Option	30.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0739575	Empty Compact NTP Binder	10.00	H
S Δ	P0740423	Meridian Mail Modular Option EC Reference Manual	30.00	H
S Δ	P0741295	Meridian Mail Modular GP Reference Manual, Release 8	30.00	H
S Δ	P0741298	Meridian Mail Multi-Customer System Administration Reference Manual	30.00	H
S Δ	P0741301	Meridian Mail Connections Reference Manual (AT&T), Release 9	10.00	H
S Δ	P0741302	Meridian Mail Connections Reference Manual (Rolm), Release 9	10.00	H
S Δ	P0741303	Meridian Mail Connections Reference Manual (NEC), Release 9	10.00	H
S Δ	P0741304	Meridian ACCESS Developers Reference Manual	30.00	H
S Δ	P0741305	Meridian ACCESS Enable Option Reference Manual	20.00	H
S Δ	P0741306	Meridian HVS Administration Reference Manual	20.00	H
S Δ	P0741307	Meridian HVS GAC Reference Manual	10.00	H
S Δ	P0741308	Meridian Voice Forms Reference Manual	20.00	H
S Δ	P0742833	Meridian ACCESS Configuration Guide (NTP 555-7001-3150)	100.00	H
S Δ	P0744255	ACD Agent Single Line Telephone Quick Reference Card (25/PK)	20.00	H
S Δ	P0746527	Meridian Mail Connections Reference Manual AT&T, Release 9	30.00	H
S Δ	P0746528	Meridian Mail Connections Reference Manual ROLM, Release 9	30.00	H
S Δ	P0746529	Meridian Mail Connections Reference Manual NEC, Release 9	30.00	H
S Δ	P0800553	Power Monitor/CE Auxiliary Shelves	12.00	H
S Δ	P0813970	XN/XT Network Module Expansion	12.00	H
S ➤ Δ	P0815188	System 600/48 NTP	20.00	H
S Δ	P0819765	Network Hybrid Installation Procedure	12.00	H
S Δ	P0832159	Meridian Networking Feature Document	15.00	H
B Δ	P0835240	Central Answering Position (Caps)	10.00	H
B Δ	P0835273	Customer Configuration Backup and Restore (Coil)	10.00	H
B Δ	P0835516	X11 Software Input/Output Guide (Coil)	40.00	H
B Δ	P0837621	Option 11E - 1.5MB DTI/PRI Administration and Maintenance (Binder)	10.00	H
B Δ	P0837640	Option 11E - BRI Administration and Maintenance (Binder)	40.00	H
B Δ	P0837647	Option 11E - Technical Reference Guide (Binder)	40.00	H
S Δ	P0849802	Data Input Forms (Release 22)	10.00	H
S Δ	P0865362	Meridian 1 Attendant PC Unit Installation Guide	8.00	H
S Δ	P0868056	Meridian 1 Attendant PC Unit Quick Reference Guide	8.00	H
S Δ	P0874391	Meridian 1 Attendant PC LAN Interface Installation Guide	8.00	H
S Δ	P0875895	Meridian Mail Release 12 Card Option Installation and Maintenance Guide	10.00	H
S	P0878469	Mini Carrier Remote NTP	20.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0885695	MICA NTP	15.00	H
S Δ	P0885702	Meridian Integrated RAN (Release 2) NTP Guide	20.00	H
S Δ	P0889187	Library Navigator, Release 24 and Earlier	50.00	H
S Δ	P0889188	System Planning and Engineering Guide, Release 24 and Earlier	50.00	H
S Δ	P0889189	System Installation and Maintenance Guide, Release 24 and Earlier	50.00	H
S Δ	P0889190	System and Software Upgrade Guide, Release 24 and Earlier	50.00	H
S Δ	P0889191	X11 Software Features Guide, Release 24 and Earlier	50.00	H
S Δ	P0889192	X11 System Management, Overview, Applications and Security Guide, Release 24 and Earlier	50.00	H
S Δ	P0889193	X11 Input/Output Guide, Release 24 and Earlier	50.00	H
S Δ	P0889194	X11 Data Features, Release 24 and Earlier	50.00	H
S Δ	P0889195	X11 Hospitality Features, Release 24 and Earlier	50.00	H
S Δ	P0889196	X11 Networking Features, Release 24 and Earlier	50.00	H
S Δ	P0889197	ISDN Basic Rate Interface, Release 24 and Earlier	50.00	H
S Δ	P0889198	ACD Reference Guide, Release 24 and Earlier	50.00	H
S Δ	P0889200	System Installation and Maintenance, Release 24 and Earlier	25.00	H
S Δ	P0889201	Switch Settings, Card and Product Compatibility, Release 24 and Earlier	25.00	H
S Δ	P0889202	Software Conversion Procedures, Release 24 and Earlier	12.00	H
S Δ	P0889203	X11 Feature Document, Release 24 and Earlier	12.00	H
S Δ	P0889204	X11 Maintenance Programs, Release 24 and Earlier	25.00	H
S Δ	P0889235	X11 Administration Programs, Release 24 and Earlier	25.00	H
S Δ	P0889236	X11 System Messages, Release 24 and Earlier	25.00	H
S Δ	P0889431	System Management Overview, Applications and Security Spirals, Release 24 and Earlier	25.00	H
S	P0889883	Meridian 1 Attendant PC/Hospitality Software Quick Start Guide	10.00	H
S Δ	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	20.00	H
S Δ	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier	50.00	H
S Δ	P0891256	Meridian 1 Attendant PC Software User Guide	15.00	H
S Δ	P0891257	Meridian 1 Attendant PC Software Installation Guide	8.00	H
S Δ	P0891258	Meridian 1 Attendant PC Software Quick Start Guide	8.00	H
S ✓ Δ	P0904485	Modular Option Installation and Maintenance Guide - MM13	20.00	H
S Δ	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13	15.00	H
S Δ	P0904487	Modular Option GP Installation and Maintenance Guide - MM13	12.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ Δ	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide	21.00	H
S ✓ Δ	P0904493	Maintenance Messages (SEERs) - MM13	39.00	H
S ✓ Δ	P0904494	ACCESS Configuration Guide - MM13	32.00	H
S ✓ Δ	P0904567	What's New In Meridian Mail Release 13	8.00	H
S Δ	P0904927	Meridian Mail HVS GAC/Guest Voice Messaging Reference Guide - MM13	10.00	H
S Δ	P0905051	Meridian IP Telephony Gateway (ITG) NTPs. The NTPs are documents used to describe and configure the ITG card and the network environment where it operates.	15.00	H
S ➤ Δ	P0906569	Meridian ITG 2.0 NTP. The NTP is a document used to describe and configure the ITG 2.0 card (24-port) and the network environment where it operates.	20.00	D
S ✓ Δ	P0907072	PC Application Guide - MM13	11.00	H
B Δ	P0907449	Customer Configuration Backup and Restore (Coil)	10.00	H
B Δ	P0907452	Option 11C Release 25 Technical Reference Guide - English	10.00	H
B Δ	P0907453	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	35.00	H
S Δ	P0907454	2.0 MB DTI/PRI Administration/Maintenance Guide	26.00	H
S Δ	P0907455	Option 11C BRI Guide (Release 18 to 24) - English	40.00	H
S	P0909573	Meridian Integrated Voice Services (MIVS) NTP	20.00	H
S Δ	P0910775	X11 Maintenance Programs	25.00	H
S Δ	P0910776	X11 System Messages	25.00	H
S Δ	P0910777	X11 Administration Programs	25.00	H
S Δ	P0910790	Technical Reference Guide, Release 25	50.00	H
B Δ	P0910791	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	50.00	H
B Δ	P0910793	2.0 MB DTI/PRI Administration and Maintenance Guide	50.00	H
B Δ	P0910795	BRI Guide, Release 25	50.00	H
S ★ ➤ Δ	P0910806	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (Paper)	20.00	H
S Δ	P0912432	Library Navigator	50.00	H
S Δ	P0912433	Systems Programming Guide	25.00	H
S Δ	P0912434	Basic Telecom Management Guide	50.00	H
S Δ	P0912435	Network Planning Guide	25.00	H
S Δ	P0912436	Fault Clearing Guide	25.00	H
S Δ	P0912857	NT6D82 Power System	12.00	H
S	P0912861	NT5D61 IODU/C Reference Guide	15.00	H
S ✓ Δ	P0912862	CP Card Field Memory Upgrade Procedure	50.00	H
S ✓ Δ	P0912864	Meridian IP Telecommuter NTP	15.00	H
S ✓ Δ	P0914163	MIPCD NTP Guide (English)	20.00	H
S ✓ Δ	P0914505	MIPCD User Guide (English)	15.00	H
S Δ	P0914553	MIPCD NTP Guide (French)	20.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0914554	MIPCD User Guide (French)	15.00	H
S ➤	SERV0080	CD-ROM Media Request. Service change code for pre-release 23 systems who are upgrading to Release 23 and want software deliverd on CD-ROM format.	No charge	

Information/User Guides

S Δ	A0397852	Customer Controlled Routing User Guide	70.00	H
S Δ	A0672913	MAT 5 User Guides Binder	15.00	H
S § ➤ Δ	AS1082	Meridian Modular Telephone User Guide (Package of 15 P0902627)	No charge	
S § ➤ Δ	AS1083	M2216 ACD Telephone User Guide (Package of 15 P0902629)	No charge	
S § ➤ Δ	AS1084	M2317 Telephone User Guide (15/PK)	No charge	
S Δ	H008	Customer Controlled Routing Call Scripting Flowcharts Job Aid	95.00	H
S Δ	H013	Meridian Mail Modular Option Enhanced Capacity (EC) Installation Photo Guide	350.00	H
S Δ	H014	Meridian Mail Modular Option GP Installation Photo Guide	325.00	H
S Δ	H015	Meridian Mail Release 12 Difference Guide	175.00	H
S Δ	H021	Meridian Mail Train the Trainer	125.00	H
S Δ	H022	Introduction to Meridian Mail Presentation	125.00	H
S Δ	NT1F73AA	MMR CD ROM.	94.00	H
S Δ	NT1R55AB	Customer Controlled Routing Release 3 User Guide	70.00	H
S Δ	NT1R66AA	Meridian MAX Release 6 Supervisor Reference Guide	50.00	H
S ➤ Δ	NT1R93AA	Meridian MAX Release 7 Complete Documentation Package	100.00	H
S ➤ Δ	NT1R94AA	Meridian MAX Release 7 Technical Documentation Package	50.00	H
S ➤ Δ	NT1R95AA	Meridian MAX Release 7 Supervisors User Guide	50.00	H
S ✓ ➤ Δ	NT2F09AA	Alternate User Interface 1 User Guide (15 per Package)	25.00	H
S ➤ Δ	NT2F77AA	External Alerter and Recording Interface User Guide (M3900 Series, Package of 15 P0903793)	12.00	H
S § ➤ Δ	NT2F7901	Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627) N/C	No charge	
S ✓ ➤ Δ	NT2F79AA	Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627)	50.00	H
S ✓ § ➤ Δ	NT2F8001	Meridian M3905 User Guide Release 1 (Package of 15 P0903629) N/C	No charge	
S ✓ ➤ Δ	NT2F80AA	Meridian M3905 User Guide, Release 1 (Package of 15 P0903629)	40.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ➤ Δ	NT2F81AA	Meridian M3900 Series Quick Reference Guide, Release 1 (Package of 15 P0903628)	28.00	H
S ➤ Δ	NT2F82AA	Meridian M3905 Quick Reference Guide, Release 1 (Package of 15 P0903630)	28.00	H
S ➤ Δ	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	20.00	H
S Δ	NT5F49AA	Analog Terminal Adapter Quick Reference Card (Package of 15 P0872254)	12.00	H
S Δ	NT5F50AC	Meridian M2006, M2008, M2008HF & M2616, M2016S User Guide (English) (Package of 15 P0902627)	41.00	H
S Δ	NT5F53AC	Meridian Modular Telephones Quick Reference Guide (English) (Package of 15 P0902628)	28.00	H
S Δ	NT5F54AB	Meridian Communications Adapter User Guide (Package of 15 P0859508)	20.00	H
S Δ	NT5F55AC	M2216ACD Telephone User Guide (English) (Package of 15 P0902629)	30.00	H
S Δ	NT5F82AA	Meridian Mail 11 Modular Option GP Manual	20.00	H
S Δ	NT5F84AA	Meridian Mail 11 Modular Option Manual	20.00	H
S Δ	NT5F85AA	Meridian Mail 11 Administration Manual for Multi-Customer Systems	40.00	H
S Δ	NT5F86AA	Meridian Mail 11 Administration Manual	40.00	H
S Δ	NT5F87AA	Meridian Mail 11 Modular Option GP Administration Manual for Multi-Customer Systems	40.00	H
S ➤ Δ	NT5F88AA	Meridian Mail 11 Voice Messaging Package (15/PK)	15.00	H
S ➤ Δ	NT5F89AA	Meridian Mail 11 Voice Messaging (VMUIF) Package (15/PK)	30.00	H
S ➤ Δ	NT5F91AA	Meridian Mail 11 Call Answering Package (50/PK) (DMS)	100.00	H
S Δ	NT5F93AA	Meridian Mail 11 Card Option Manual	20.00	H
S Δ	NT5F94AA	Meridian Mail 11 Option 11 EC (EC11) Manual	20.00	H
S Δ	NT5F99AA	Meridian Mail 11 Modular Option GP Administration Manual	50.00	H
S ➤ Δ	NT5R46AA	Meridian Mail Networking Services Administration Guide	30.00	H
S ➤ Δ	NT5R98AA	Meridian Mail Multi-Media Services Reference Manual	30.00	H
S ➤ Δ	NT6R49AA	Meridian Mail EC11 Installation and Modification Guide, MM10	30.00	H
S Δ	NT8R03AA	MAT 4 x Common Services User Guide	15.00	H
S Δ	P0635020	AIM Installation Card (15/PK)	1.00	H
S Δ	P0661883	Asynchronous Data Option Installation Procedure (15/PK)	1.00	H
S Δ	P0667329	Attendant Administration User Guide (15/PK)	14.00	H
S Δ	P0673999	Voice Messaging Template (Digital Sets) (100/PK)	42.00	H
S Δ	P0677591	Single Line Telephone User Guide (Trifold) (100/PK)	6.00	H
S Δ	P0687153	RS232 Interface Guide (15/PK)	20.00	H
S Δ	P0689755	ACD-D Supervisor User Guide	13.00	H
S Δ	P0689757	ACD-D Networking User Guide (15/PK)	96.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0690152	ACD Feature Document X11/X37 (15/PK)	38.00	H
S Δ	P0690763	M2317 Telephone Quick Reference Card (100/PK)	24.00	H
S Δ	P0696749	High Speed Data Module User Guide (15/PK)	65.00	H
S Δ	P0701874	X11 Feature Document (Release 12 Supplement) (5/PK)	No charge	
S Δ	P0702800	M1250/M2250 Attendant Administration User Guide (5/PK)	15.00	H
S Δ	P0707593	Meridian Modular Telephone Template (100/PK)	42.00	H
S † Δ	P0707700	Traffic Reporting Documentation (Version 1)	25.00	H
S Δ	P0713674	Meridian Attendant Message Center Slide Presentation	15.00	H
S Δ	P0714692	DSS-9000 User Manual	8.00	H
S Δ	P0714693	DSS-9000 Installation and Maintenance Manual	8.00	H
S Δ	P0723522	X11 Software Guide	40.00	H
S Δ	P0724945	Customer Controlled Routing Release 3B/Link Release 4B Advanced Maintenance Guide	80.00	H
S † Δ	P0728239	CPLUS 2000 User Guide	30.00	H
S † Δ	P0728240	CPLUS 2000 Installation Guide	30.00	H
S Δ	P0730129	Supervisor Users Guide	30.00	H
S Δ	P0731602	Customer Controlled Routing Quick Reference Card	10.00	H
S Δ	P0734380	Meridian ACD Package A-C2 and Network ACD	25.00	H
S	P0735211	Background Terminal User Guide (15/PK)	42.00	H
S Δ	P0735539	M1250/M2250 Attendant Console Quick Reference Card (25/PK)	5.00	H
S Δ	P0736062	BLF/CGM User Guide (5/PK)	10.00	H
S Δ	P0738417	ACD Package C Supervisor User Guide	25.00	H
S Δ	P0738616	Meridian 1 Call Center Testimonial	1.00	H
S Δ	P0739519	Meridian Mail Modular Option Reference Manual, Release 8	30.00	H
S Δ	P0740384	Meridian Mail HVS User Guide, European, French	75.00	H
S Δ	P0740400	Meridian Mail HVS User Guide, American, Spanish	75.00	H
S Δ	P0740420	Meridian SL-1/500 Telephone Extension Designation Cards (1 Box of 1,000 Cards for use with SL-1 QSU Style & Std Analog)	75.00	H
S Δ	P0740421	Meridian/Unity III Designation Cards (1 Box of 1,000 Card for use w/ M2000 Digital Tel. & Unity III)	75.00	H
S Δ	P0741297	Meridian Mail System Administration Reference Manual	30.00	H
S Δ	P0741309	Meridian Voice Forms Transcriber User Guide	10.00	H
S Δ	P0741310	Meridian Voice Forms Implementation User Guide	10.00	H
S Δ	P0741311	Meridian Mail Voice Messaging User Guide (15/PK)	39.00	H
S Δ	P0741565	Meridian Mail Quick Reference Cards (Package of 30)	15.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0743363	Technical Reference Guide	40.00	H
S Δ	P0743364	BRI Administration and Maintenance Guide	40.00	H
S Δ	P0743367	Installation Guide	10.00	H
S Δ	P0743368	Administration Guide	10.00	H
S Δ	P0743369	Fault Clearing Guide	10.00	H
S Δ	P0743512	50 Amp Rectifier Expansion Assembly Installation NTP	20.00	H
S Δ	P0743618	Meridian Mail HVS User Guide, Brazilian, Portuguese	75.00	H
S Δ	P0743724	Meridian Communications Unit User Guide and Meridian Communication Adapter Reference Guide	10.00	H
B Δ	P0745758	Central Answering Position Guide	10.00	H
S Δ	P0746530	Meridian Mail Release 9 HVS GAC User Guide	30.00	H
S Δ	P0746564	Meridian Mail Release 9 Voice Forms Transcriber User Guide	30.00	H
S Δ	P0800567	M2317 Telephone User Guide (15/PK)	50.00	H
S Δ	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4.6 & 5 Systems (to Release 6)	50.00	H
S Δ	P0802087	Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 6)	50.00	H
S Δ	P0802089	Meridian MAX Release 6 Supervisors User Guide	50.00	H
S Δ	P0803126	Release 20 Data Input Forms	10.00	H
S Δ	P0803182	Meridian Mail Modular Option EC Installation & Maintenance Quick Reference Guide, Release 9	30.00	H
S Δ	P0809892	Meridian COMPANION NTP Documentation	80.00	I
S Δ	P0813948	ACD Supervisor Telephone User Guide	30.00	H
S Δ	P0813950	Standard Telephone User Guide	50.00	H
S Δ	P0814833	Meridian 1 Quick Tips Guide	49.00	H
S Δ	P0815375	MAXcaster User Guide English	18.00	H
S Δ	P0815376	MAXcaster User Guide French	18.00	H
S Δ	P0833777	NT5D12 Dual-port DTI/PRI Card Product Description and Installation	10.00	H
S Δ	P0833798	MAT 4 x Station Administration User Guide	10.00	H
S Δ	P0833799	MAT 4 x Traffic Analysis User Guide	10.00	H
S Δ	P0833800	MAT 4 x Call Tracking User Guide	10.00	H
S Δ	P0833801	MAT 4 x Call Accounting User Guide	10.00	H
S Δ	P0833802	MAT 4 x Buffer Box Reference Guide	15.00	H
S Δ	P0834426	Attendant Console User Guide (1/PK)	7.00	H
S Δ	P0835201	FastView User Guide	25.00	H
S Δ	P0839909	Meridian Mail 11 HVS Implementation Guide	20.00	H
S Δ	P0839910	Meridian Mail 11 HVS GAC Guide / Guest Voice Messaging Reference Guide	10.00	H
S Δ	P0839915	Meridian Mail 11 System Installation and Modification Guide	10.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S Δ	P0839920	Meridian Mail 11 Network Planning Guide	10.00	H
S Δ	P0839921	Meridian Mail 11 AMIS Networking Installation and Administration Guide	10.00	H
S Δ	P0839922	Meridian Mail 11 Network Message Services Installation and Administration Guide	10.00	H
S Δ	P0839923	Meridian Mail 11 Networking, Installation and Administration Guide	20.00	H
S Δ	P0839924	Meridian Mail 11 Virtual Node AMIS Networking Installation and Administration Guide	20.00	D
S Δ	P0839925	Meridian Mail 11 Enterprise Networking, Installation and Administration Guide	10.00	H
S Δ	P0839926	Meridian Mail 11 Voice Services Application Guide	20.00	H
S Δ	P0839934	Meridian Mail 11 Fax on Demand Application Guide	10.00	H
S ➤ Δ	P0839941	Meridian Mail 11 Maintenance Messages (SEERS)	25.00	H
S Δ	P0839943	Meridian Mail 11 Voice Messaging Quick Reference Card 30/ Pkg	20.00	H
S Δ	P0839945	Meridian Mail 11 "Updating Voice Menu Prompts" Cards (15/ PK)	5.00	H
S Δ	P0839993	MAXcaster Quick Reference Guide English	10.00	H
S Δ	P0843834	MAT 5 x Station Administration User Guide	10.00	H
S Δ	P0843837	MAT 5 x Call Tracking User Guide	10.00	H
S Δ	P0843840	MAT 5 x Alarm Management User Guide	10.00	H
S Δ	P0844341	MAXcaster Quick Reference Guide French	10.00	H
S ➤ Δ	P0847870	Meridian Mail Reporter 2.0 User Guide	15.00	H
S Δ	P0854560	Customer Controlled Routing Release 3B/Link Release 5B Engineering Guide	70.00	H
S † Δ	P0865356	CPLUS Release 3 User Guide	32.00	H
S † Δ	P0865358	CPLUS Release 3 Installation Guide	32.00	H
S † Δ	P0865359	CPLUS Performer User Guide	32.00	H
S † Δ	P0865360	CPLUS Performer Installation Guide	32.00	H
S † Δ	P0865361	CPLUS LAN Key Installation Guide	32.00	H
S Δ	P0867594	MAT 5 x Traffic Analysis User Guide	10.00	H
S Δ	P0867596	MAT 5 x ESN Analysis and Reporting Tool User Guide	10.00	H
S Δ	P0868359	MAT 5 x Common Services User Guide	15.00	H
S Δ	P0868440	MAT 5 x Maintenance Windows User Guide	10.00	H
S Δ	P0871739	MAT 5 x Call Accounting User Guide	10.00	H
S Δ	P0875113	Data Input Forms (Release 23)	10.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
S ✓ Δ	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	10.00	H
S ✓ Δ	P0875898	Meridian Mail Release 12 Outcalling Application Guide	15.00	H
S ✓ Δ	P0875899	Meridian Mail Release 12 HVS Implementation Guide	20.00	H
S Δ	P0875900	Meridian Mail Release 12 HVS/Guest Voice Messaging Reference Guide	10.00	H
S ✓ Δ	P0875903	Meridian Mail Release 12 Voice Services Application Guide	20.00	H
S ✓ Δ	P0875904	Meridian Mail Release 12 Fax On Demand Application Guide	10.00	H
S ✓ Δ	P0875906	Meridian Mail Release 12 Networking Planning Guide	10.00	H
S ✓ Δ	P0875908	Meridian Mail Release 12 AMIS Networking Installation and Administration Guide	10.00	H
S ✓ Δ	P0875910	Meridian Mail Release 12 Network Message Services Installation and Administration Guide	10.00	H
S ✓ Δ	P0875911	Meridian Mail Release 12 Networking Installation and Administration Guide	20.00	H
S ✓ Δ	P0875912	Meridian Mail AMIS Virtual Node Networking Installation and Administration Guide	20.00	H
S Δ	P0875936	Meridian Mail Release 12 Voice Messaging Quick Reference Card	20.00	H
S Δ	P0875941	Meridian Mail Release 12 Voice Messaging "Updating Voice Menu Prompts" Card	5.00	H
S Δ	P0884613	Alternate User Interface Installation/Administration Guide	20.00	H
S Δ	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	15.00	H
S Δ	P0907146	Meridian Mail Release 13 Feature Operations Video	65.00	H
S	P0907149	Data Input Forms (Release 25)	10.00	H
S Δ	V006-12	Meridian Mail Release 12 Feature Operations Video	95.00	H
S ➤ Δ	V008	Combination: Meridian Mail Overview and Meridian Mail Feature Operations Videos	125.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Collateral Listing

The collateral section consists of materials for the following products.

- Meridian 1: Options 11E-81C
- Meridian Call Center
- Meridian Mail
- Symposium

The collateral section includes the following types of items within each product group.

- Brochures
- Videos
- Demo Disks
- Presentation
- Handbooks

Each item presented in the collateral section has an order code number, product name, description, and cost given.

P0879824
Meridian 1 Option 11C Compact Video
4.30/EA
This VHS tape is 10 minutes, 30 seconds. The video highlights the features of the Option 11C Compact, a comprehensive system designed to meet the needs of small organizations that require up to 116 telephones.

P0906299
Customer Satisfaction Guarantee Program Presentation Folder
1.00/EA
Customer Satisfaction Guarantee Program Presentation Folder

P0906300
Customer Satisfaction Guarantee Program Meridian 1 Insert
.50/EA
Customer Satisfaction Guarantee Program Meridian 1 Insert

P0906301
Customer Satisfaction Guarantee Program Norstar Insert
.50/EA
Customer Satisfaction Guarantee Program Norstar Insert

P0906303
Customer Satisfaction Guarantee Program Applications Insert
.50/EA
Customer Satisfaction Guarantee Program Applications Insert

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.
	P0906304	**Customer Satisfaction Guarantee Program Registration Card Insert .25/EA** Customer Satisfaction Guarantee Program Registration Card Insert		

Ordering Procedures

Follow these procedures when ordering Meridian 1 sales collateral from the Nortel Networks Sales Collateral Catalog.

1. Use the Sales Collateral Order Form when placing orders.
2. If you are a Distributor, include a hard copy of a purchase order.
3. If you want to mail your order, please send the complete form with your purchase order to the following address:

   Nortel Networks

   Attn: Inside Sales Represenative

   200 Athens Way

   Nashville, TN 37228-1397

4. If you would like to fax your order, dial 1-615-734-5898, then choose appropriate menu items. If you have questions about your order, call customer service at 1-800-321-2649 and choose appropriate menu items.

   Note: All brochures are packaged in units of 25, unless otherwise indicated.

Sales Collateral Order Form

Use the following form to place your Sales Collateral orders.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Northern Telecom Order Form

Date: _____ Sent via: ☐ FAX ☐ Mail

Bill To: _____ Ship to: _____

Name _____ Name _____

Company _____ Company _____

Address _____ Address _____

_____ _____

City _____ City _____

State _____ ZIP _____ State _____ ZIP _____

Country _____ Country _____

FAX No. _____ FAX No. _____

Department No. _____ Department No. _____

Order acknowledgments will be sent to bill-to and ship-to addresses.

Authorized by _____ Purchase Order No. _____

Fulfillment Service: (Check one. Fill in date required for rush orders.)

☐ Normal (within two weeks) ☐ Rush_____Date Required

Inventory No.	Description	Quantity	Unit Price	Total Price

Please mail order to:

Northern Telecom Incorporated
Attn: Inside Sales Representative
200 Athens Way
Nashville, TN 37210

FAX Number: 615 734-5898

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

MERIDIAN 1 - Meridian Call Center

Brochures

Note: All brochures in packages of 25 unless otherwise noted.

P0724136
Call Center Business Planning Guide and Tools
6.00/EA
The Call Center Business Planning Guide is a completely updated, 100-page workbook designed to help current and potential customers understand the call center technology available today. In a step-by-step manner, this guide helps customers identify areas their call center that can be improved, and define what technology should be applied while cost-justifying the solution. While the guide is very useful for customers, it is also an excellent tool for distributors. Cost justification and return-on-investment tools in the guide are also included on Mac and DOS 3.5-inch diskettes. What if scenarios can be easily run to determine the financial benefit and payback length of implementing any of Nortel (Northern Telecom) Call Center products. (Microsoft Excel 4.0 is required to run these tools.) (July, 1994).

P0739833
Meridian Call Center Networking Brochure (NAC/NACD)
.60/PK
Two products are covered in this brochure, which highlights the cost efficiencies of networking multiple call center locations: Network ACD (NACD), which allows multiple ACDs to be networked, and Network Administration Center (NAC) which enables management of networked ACDs. (July, 1993). Minimum order quantity is 25; please order in multiples of 25.

P0739834
Meridian Link Brochure
1.19/PK
This brochure introduces customers to Meridian Link, Nortel's phone-to-computer interface for Meridian 1. It describes how Meridian Link can help your customers improve service, reduce operating costs and increase revenue. There are five inserts available for this brochure: four on the connecting to various computing environments (Hewlett-Packard, Digital Equipment Corporation, IBM and Tandem) and one on the Business Affiliate Program. (Updated June, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0739836
NT/HP Alliance Brochure
.66/PK
This brochure explains how Meridian Link works with Hewlett-Packard computers and includes technical specifications. This is an insert to the Meridian Link brochure (P0739834). (July, 1993). Minimum order quantity is 25; please order in multiples of 25.

P0739838
NT/IBM Alliance Brochure
.66/PK
This brochure explains how Meridian Link works with IBM computers and includes technical specifications. This is an insert to the Meridian Link brochure (P0739834). (Updated July,1996). Minimum order quantity is 25; please order in multiples of 25.

P0739839
NT/Tandem Alliance Brochure
.66/PK
This brochure explains how Meridian Link works with Tandem computers and includes technical specifications. This is an insert to the Meridian Link brochure (P0739834). (July, 1993). Minimum order quantity is 25; please order in multiples of 25.

P0744840
Business Affiliates Brochure
.20/PK
This insert to the Meridian Link brochure (P0739834) describes the Business Affiliate program and what it has to offer customers considering computer-to-telephone integration. This program provides application software and application software developers for Meridian Link solutions. (July, 1993). Minimum order quantity is 25; please order in multiples of 25.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0803269
Meridian Call Center Executive Overhead Presentation
150.00/EA
This high-level, overhead presentation is designed to be given to executives, covering business issues addressed by the Meridian Call Center portfolio. Many full-color illustrations. Not available in soft copy.

P0815255
Meridian Call Center Capabilities Guide
1.40/PK
This multi-colored, five-panel brochure provides a quick reference to the call center capabilities, the products and their features. (Updated August, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0817917
Meridian 1 ACD Feature Document - Release 21
9.25/EA
This literature item provides a comprehensive description of Meridian 1 ACD package A, B, C and Meridian MAX features and Meridian MAX reports, as well as overviews of MAXcaster, NAC Networking and CCR features. (August, 1995) (Replaces P0739602).

Customer Testimonials

P0749025
Customer Profile: The Toronto Star
.37/PK
&quotA Step Ahead in Customer Service" The Toronto Star is Canada’s largest daily newspaper, with a weekday circulation of over 500,000 and a Saturday circulation of 800,000. This profile details the results of Brock Telecom developing applications that provide new services for subscribers, and provide an edge over the Toronto Star’s competition. (February, 1994). Minimum order quantity is 25; please order in multiples of 25.

P0807245
1995 TeleProfessional Reprint: Bringing Technologies Together for Maximum Call Center Performance
1.20/PK
This 16-page insert to the March issue of TeleProfessional focuses on bringing various technologies together to solve various business problems, and deliver the ultimate in convenience for callers. This issue contains 5 customer success stories across industries: Distance Learning, Disaster Recovery, Utilities, Banking and Retail. All call center technologies are briefly discussed, including future direction. (March, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0808873
Call Center Journal: Available in all Sizes
.80/PK
This four-color, six-panel, 8.5 x 11-inch issue discusses how Meridian Call Center technology is solving problems - and delivering a competitive difference - regardless of company size. (August, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0808874
Call Center Journal: Making the Perfect Match
.80/PK
This four-color, six-panel, 8.5 x 11-inch issue discusses how Meridian Call Center technology is solving problems - and delivering a competitive difference - regardless of company size. (August, 1995). Minimum order quantity is 25; please order in multiples of 25.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0808875
Call Center Journal: Working With a Net
.80/PK
This four-color, six-panel, 8.5 x 11-inch issue focuses on Meridian Call Center networking solutions. (March, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0808876
Call Center Journal: Financial Powerhouse
.62/PK
This two-color, six-panel, 8.5 x 11-inch issue covers Household Credit Services multi-site integrated Meridian 1 Call Center - and the benefits it provides. (March, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0808877
Call Center Journal: Healthcare - Just What the Dr. Ordered
.48/PK
This two-color, six-panel, 8.5 x 11-inch issue discusses applications for Nortel's voice processing products in the healthcare industry. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0815258
Call Center Journal: Air Miles Program Takes Off
.97/PK
This journal profiles the Air Miles Program at Loyalty Management Group Canada, Inc. (LMGC). A before scenario of LMGC's call center is presented followed by Nortel's complete integrated solution to their problems. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0815259
Call Center Journal: Better By The Minute
1.49/PK
An alliance between Nortel's Call Center Team and Sprint's networking experts provides call center solution for any cost conscious company: the priced per minute call center. The brochure highlights the Nortel/Sprint alliance. It provides a description of the cost efficiency and the technology advantage of a priced-per minute approach. (August, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0815260
Call Center Journal: Move Up To MAX
1.49/PK
For customers who run their call center on Meridian ACD Package C" and need more powerful management tools, buying an add-on package does not add up. Meridian MAX the ultimate MIS solution to upgrading from Package C". This journal provides an overview of Meridian MAX capabilities and benefits versus add-ons. (August, 1995). Minimum order quantity is 25; please order in multiples of 25.

P0815261
Call Center Journal: Beyond Expectation
.28/PK
Two new Signature Service industry groups are benefiting from call center technology: Mutual Fund companies and Insurance companies. This journal emphasizes the call center products and features that are invaluable to the Signature Service industry. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0817920
Call Center Journal: MAXcaster Forecasting
1.58/PK
The secret of successful call center management is accurate forecasting, especially for an attractively priced forecasting package attuned to today's fundamental call center needs: Meridian MAXcaster. This journal highlights the features of Meridian MAXcaster. (1995). Minumum order quantity of 25; please order in multiples of 25.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0819906
Call Center Journal: The CTI Call Center
.78/PK
This journal features an introduction to the benefits of Predictive Dialing and an overview of a Predictive Dialing/CTI implementation in Bell Quebec's call center. Nortel partnered with Canadian LYNX to provide a solution to Bell Quebec's needs: The TelePredicter. Bell Quebec's call center is known as the model office &quotfor future Bell Canada Enterprises' call centers. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0820954
Call Center Journal: Priority Special Report
1.14/PK
This special report is a full-color, 20-page brochure covering three customer call center activities utilizing Nortel solutions. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0843029
Meridian MAXcaster Flyer
1.04/PK
This one-page flyer describes the features of MAXcaster as a tool for call centers. (June, 1996). Minimum order quantity is 25; please order in multiples of 25.

Demos

Sales Training

A0618446
Winning With Application Sales: Meridian Call Center Sales Training Kit (with video)
43.75/EA
This comprehensive course consists of video and workbook, and can be taken at home at your convenience or facilitator-given. The course walks you through start to finish: identifying a customer's business problems, reaching the right contacts - and understanding their mindset, designing the solution - the change in business process - that will solve the problems, and positioning and cost-justifying the solution. Kit also contains the Call Center Business Planning Guide complete with cost justification tools on disk (see listing for full description), sample RFP, presentations and call center product brochures. (1995).

A0622715
Winning With Application Sales: Meridian Call Center Sales Training Kit (without video)
35.50/EA
The same kit as A0618446, but without video for participants of a facilitator-given course. (1995).

Videos

P0817918
Call Center Video "Customer Service Takes Flight"
10.00/EA
This 25-minute video, designed for sales presentations and customer viewing, features call center products: Meridian MAX, Meridian CCR, Meridian LINK, Meridian IVR, Meridian Mail, Meridian Network, ACD and Meridian NAC. The customer testimonial format highlights the following companies: National Fuel, North West Travel, TDGLIS, S&P Data, Loyalty Management Group, West Marine Products and Wells Fargo Bank. (1995).

P0817919
Canadian Tire Video
4.00/EA
This 14-minute video, designed for sales presentations and customer viewing, is a Canadian Tire customer testimonial. The key messages highlight Nortel's market experience, integrated platform and growth capacity. (1995).

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

MERIDIAN 1 - Options 11C through 81C

Business Cases

P0878476
Meridian 1 Option 11C Compact Business Case
1.13/EA
This 12-page, four-color brochure describes scenarios that quantify the benefits that can be achieved with the Option 11C Compact system. The brochure presents single- and multisite scenarios, each with step-by-step calculations to help the end user cost-justify any investment in this product.Minimum order quantity is 25; please order in multiples of 25.

Brochures/Flyers

Note: All brochures in packages of 25 unless otherwise noted.

P0857665
Meridian 1 Option 11C "High Performance in a Small Package" Brochure
1.90/EA
This 12-page, 4-color brochure provides single-site small business customers with an overview of how the Meridian 1 Option 11C provides the power of larger Meridian 1 system, in a small package. Minimum order quantity is 25; please order in multiples of 25.

P0857666
Meridian 1 Option 11C: Building a High-Performance Network Brochure
1.90/EA
This 12-page, 4-color brochure provides multisite business customers with an overview of how they can create a high-performance network using Meridian 1 Option 11C systems, to create a cohesive network linking headquarters to branch offices or to other Meridian 1 locations. (Replaces P0803778). Minimum order quantity is 25; please order in multiples of 25.

P0889249
Meridian 1 Option 11C Compact Hospitality Package Brochure
1.50/EA
This eight-page, four-color brochure describes how small to mid-size hotels and motels can improve their guest services with the Meridian 1 Option 11C Compact Hospitality Package. The brochure describes the features that improve staff productivity and increase guest satisfaction. (25 per package)

P0891204
Meridian Integrated IP Telephony Gateway Flyer
.90/EA
This four-page, four-color flyer describes the features of the Meridian Integrated IP Telephony Gateway(ITG)flyer. It describes how users can reduce communication costs by routing voice and fax traffic over under-utilized bandwidth on existing private IP networks. Minimum order quantity is 25; please order in multiples of 25.

P0891207
Meridian 1 System Specifications Brochure
2.58/EA
This six-panel, trifold brochure explains the Meridian 1 System architecture and includes detailed system specifications. (Replaces P0857668). Minimum Order quantity is 25; please order in multiples of 25.

P0891208
Gray Market Pamphlet for End Users
.95/EA
This trifold, four-color pamphlet takes a closer look at the high cost of unauthorized suppliers. It defines Gray Marketing and describes how end users can protect themselves against gray marketers. Minimum order quantity is 25; please order in multiples of 25.

P0891209
Gray Market Pamphlet for Distributors
.95/EA
Gray Market Pamphlet for Distributors

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0903934
Meridian 1 Option 11C Compact Brochure
1.20/EA
This six-page, four-color brochure describes the Option 11C Compact as a high-quality, affordable system specifically designed for the value-minded business person whose company needs up to 116 telephones. Minimum order quantity is 25; please order in multiples of 25.

Systems

P0857667
Meridian 1 Evergreen By Design Brochure
2.22/EA
This Meridian 1 brochure explains how a customer's Meridian 1 investment is protected by Nortel's "Evergreen" commitment. (Replaces P0739715). Minimum order quantity is 25; please order in multiples of 25.

P0869771
Meridian Integrated Recorded Announcer (MIRAN) Brochure
.50/EA
This brochure provides an overview of the MIRAN integrated solution and includes technical specifications. Minimum order quantity is 25; please order in multiples of 25.

P0869772
Meridian Integrated Conference Bridge (MICB) Brochure
.50/EA
This brochure provides an overview of the on-site conferencing application, MICB, and includes technical specifications. Minimum order quantity is 25; please order in multiples of 25.

P0878478
Meridian 1 Attendant PC Brochure
.30/EA
This four-page, four-color brochure describes the main features of the PC Attendant system and illustrates key screen used by attendants. Minimum order quantity is 25; please order in multiples of 25.

P0887541
Nortel Meridian: Transition to the Year 2000 Video
3.70/EA
This video describes the issues surrounding the transition of Meridian systems to the Year 2000 and tells how Nortel Networks has been addressing these issues. Typical laboratory testing at the Santa Clara facility is included. Running time is 7:32.

Remote Services

P0891206
Meridian 1 Remote Services Portfolio Brochure
1.90/EA
This eight-page, four-color brochure describes the options that can be used singly or in combination to tailor the optimum remote solution for the end user. Descriptions and specs on the following solutions are included: Mini Carrier Remote, Carrier Remote, Line-side T1/E1 Interface, OPS Analog Line Card, Fiber Remote, and Fiber Remote Multi-IPE. Minimum order quantity is 25; please order in multiples of 25.

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

System Management

Guides/Handbooks

Demo Disks

P0853938
Meridian Administration Tools (MAT) Brochure
4.25/EA
This brochure takes a look at Meridian Administration Tools (MAT), a family of integrated Windows-based software tools that bring Graphical User Interface (GUI) simplicity to Meridian 1 system management. In addition to providing an overview of MAT's capabilities, there are individual data sheets on application modules: Station Administration, Traffic Analysis, Call Accounting, Call Tracking, Maintenance Windows, Alarm Management and ESN Reporting and Analysis. Minimum order is 25; please order in multiples of 25.

P0879825
Meridian 1 Option 11C Compact CD-ROM Demo
2.50/EA
This 10-minute CD features the Meridian 1 Option 11C Compact Video running in a CD-ROM interface. Highlighted are the features of the Option 11C Compact, an affordable, comprehensive system designed to meet the needs of small organizations that require up to 116 telephones.

P0891205
Meridian Administration Tools (MAT 6) Demo CD
2.50/EA
This interactive, multimedia demo provides an overview of the capabilities of Meridian Administration Tools, a family of integrated Windows-based software tools that bring Graphical User Interface (GUI) simplicity to Meridian 1 system management. Individual sections deal with each application odule: Station Administration, Traffic Analysis, Call Accounting, Call Tracking, Maintenance Windows, Alarm Management, ESN Reporting and Analysis, as well as the Common Services. Requires a PC to run. (Replaces P0853939).

Meridian Digital Telephones/Attendant Consoles

Brochures/Flyers

P0739720
Meridian Communications Adapter Product Brief
.20/EA
The brief describes the Meridian Communications Adapter, which allows computers and other devices to communicate easily through the telephone network. Minimum order quantity is 25; please order in multiples of 25.

P0739721
Meridian M2250 Attendant Console Product Brief
.21/EA
This 8.5 x 11-inch, full-color, two-page flyer includes information about the M2250 Attendant Console, that can be used with Meridian 1 systems. (Updated Minimum order quantity is 25; please order in multiples of 25.

P0739726
NT-1 Network Terminal Adapter Product Brief
.40/EA
Describes the features of the NT-1 Network Terminal Adapter used in Meridian 1 networking applications. Minimum order quantity is 25; please order in multiples of 25.

P0739727
M2006/M2008/M2008HF & M2616 Digital Telephone Product Brief
.31/EA
This product brief includes photos of each telephone, a design summary and options available for Meridian Digital Telephones. Minimum order quantity is 25; please order in multiples of 25.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0739835
M2216ACD Telephone Product Brief
.20/EA
This product brief describes the features of the M2216ACD Telephone. It includes a design summary and a list of options. Minimum order quantity is 25; please order in multiples of 25.

P0909314
M3900 Series Accessories Product Brief
.17/EA
The M3900 Series Digital Telephones Accessories Product Brief describes the snap-in accessories for the M3900 Series phones. Included is information on the Analog Terminal Adapter (ATA), the Meridian Communications Adapter (MCA. the External Alerter and Recording Interface, the Personal Directory PC Utility, and the Key-based Expansion Module.Minimum order quantity is 25; please order in multiples of 25.

P0909315
M3905 Call Center Meridian Digital Telephone Product Brief
.35/EA
This product brief describes the features and specifications of the M3905 Call Center Meridian Digital Telephone, which is designed for call center agents and supervisors, and features headset jacks for both agent and supervisor and places the six most-needed call center features in a row of keys at the bottom of the deskset for instant access. Minimum order quantity is 25, please order in multiples of 25.

P0909316
M3904 Professional Meridian Digital Telephone Product Brief
.35/EA
This product brief describes the features and specifications of the M3904 Professional Meridian Digital Telephone, designed for busy executives, managers, and administrators and which offers maximum flexibility in a multiline phone. Features described include the display-based interface, self-labeling keys, Personal Directory, Call Log, Smart Mute, and the Key-based Expansion Module. Minimum order quantity is 25; please order in multiples of 25.

P0909317
M3901, M3902, M3903 Meridian Digital Telephones Product Brief
.35/EA
This product brief describes the features and specifications of the M3901 Entry, M3902 Basic, and M3903 Enhanced Meridian Digital Telephones. Features described include the new display-based interface, Call Log, and self-labeling keys and simplified administration. Minimum order quantity is 25; please order in multiples of 25.

P0909318
M3900 Series Meridian Digital Telephones Brochure
1.52/EA
This brochure provides detailed information on the M3900 series Digital Telephones. Included are the M3901 Basic Entry phone, which marks a new point of entry for economical digital phones; the M3902 Basic, which brings display and handsfree capability to the single-line user; the M3903 Enhanced, which delivers high-end features in a mid-range set; the M3904 Professional, which defines a new standard for power, ease, and versatility with the largest display in its class; and the M3905 Call Center, which provides for the specialized needs of call center agents and supervisors. A pocket on the inside back cover is provided to hold flyers/ product briefs, which can be ordered separately. Minimum order quantity is 25; please order in multiples of 25.

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0909319
Meridian Liberation Headsets Product Brief
.80/EA
This two-page, four-color product brief describes the features of the lightweight Liberation Headsets, including the features of the Multi-Purpose Amplifier II (MPA II).(Replaces P0739722). Minimum order quantity is 25; please order in quantities of 25.

ISDN and Data Services

Brochures

Note: All brochures in packages of 25 unless otherwise noted.

P0745631
ISDN Networking Solutions Brochure
.72/EA
Explains how Meridian 1 customers can connect their locations using Nortel's ISDN features and take advantage of feature-rich applications. Minimum order quantity is 25; please order in multiples of 25.

P0745632
ISDN Signaling Link Brochure
.43/EA
Describes Nortel's highly versatile signaling link, which works in conjunction with ISDN Primary Rate Interface to provide ISDN services between Meridian 1 systems. Includes configuration parameters and specifications. Minimum order quantity is 25; please order in multiples of 25.

P0745633
Seamless Transition to ISDN BRI Brochure
.72/EA
Describes Nortel's ISDN Primary Rate Interface (PRI) circuit pack, which supports ISDN clear channel, standard T1, T1 Extended Superframe (ESF) and ESN signaling formats. Minimum order quantity is 25; please order in multiples of 25.

P0745635
Advanced Voice and Data Capabilities w/ISDN BRI
.72/EA
This brochure includes a description of how Nortel's ISDN Basic Rate Interface (BRI) on the Meridian 1 system allows companies to deliver an end-to-end digital connection to the desktop for reliable, high-speed voice and data communications. Minimum order quantity is 25; please order in multiples of 25.

Videos

P0744266
Meridian 1 Digital Telephone Video "Larry Ring Live"
10.00/EA
This video shows customers, through a humorous talk-show format, "Larry Ring Live", the benefits of upgrading from older model telephone sets to Meridian 1 Digital Telephones. Length 13:00.

P0815254
Meridian 1 Release 21 & New Products Video
20.00/EA
This video provides an overview featuring hardware introduction with Release 21 of Option 11C, 68040 Call Processor for Option 81/Option 81C (Option 81X) and Carrier Remote IPE Interface. Length: 11:45 minutes (August, 1995).

P0853936
Meridian 1 New Core Products Video
6.50/EA
This video is a presentation tool for sales channels, Installed Base customers and prospective Meridian 1 customers. It covers new X11 Release 22 features, Option 11C, Option 51C/61C (68040 Call Processor), MAT Release 5 and more. (November, 1996).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0878306
Meridian 1 New Core Products: Racing to Win Video
7.35/EA
This video is a presentation tool for sales channels, installed-base customers, and prospective Meridian 1 customers. It covers new X11 Release 23 features for Options 11C through 81C, 68060 Call Processor, CD-ROM software delivery and more.

Controlling Access Privileges

P0744265
Meridian 1 Toll Fraud Brochure
2.00/PK
This 9 x 12-inch, full-color, eight-page brochure explains how Meridian 1 customers can use system features and a variety of safeguards to help protect their systems from toll fraud. It includes a checklist for toll fraud protection. (December, 1994). Minimum order quantity is 25; please order in multiples of 25.

P0746653
Controlling Access Privileges Workbook
10.00/EA
Description: 9 x 12-inch, spiral-bound booklet. Using this workbook, telecom managers can take the appropriate steps to protect their systems from toll fraud. (March, 1996).

SYMPOSIUM

Brochures

Note: All brochures in packages of 25 unless otherwise noted.

P0839989
Nortel Networks SYMPOSIUM IVR Brochure
2.05/PK
This brochure describes how Nortel SYMPOSIUM IVR can provide a multitude of solutions to address customer's business needs. Detailed descriptions of Integrated IVR and OPEN IVR can be purchased separately and added to a pocket in this main brochure. (August, 1997). Minimum order quantity is 25; please order in multiples of 25.

P0839990
SYMPOSIUM Integrated IVR Data
.28/PK
This data sheet features SYMPOSIUM Integrated IVR functions: Fax Administration, Multi-lingual, SQL Database Connectivity, Computer-Telephony Integration (CTI) and Call Center Integration. The back page covers SYMPOSIUM Integrated IVR system specifications. This data sheet fits in the parent Nortel SYMPOSIUM IVR brochure, P0839989. (August, 1997). Minimum order quantity is 25; please order in multiples of 25.

P0839991
SYMPOSIUM Open IVR Data Sheet
.28/PK
This data sheet features SYMPOSIUM OPEN IVR functionality on Automated Speech Recognition, Text-To-Speech Conversion, Analog Display Services Interface (ADSI) and more. It also includes system specifications. The data sheet fits in the parent Nortel SYMPOSIUM IVR Brochure, P0839989. (August, 1997). Minimum order quantity is 5; please order in multiples of 25.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0859913
SYMPOSIUM FastView/FastView+ Information Sheet
.83/PK
This one-page information sheet gives cost-effective solutions to a highly competitive call center environment by enhancing customer service and increasing agent productivity. (Updated August, 1997). Minimum order quantity is 25; please order in multiples of 25.

P0865353
"IVR delivers to FedEx" Article
.44/PK
This one page article discusses how Nortel's SYMPOSIUM IVR (Interactive Voice Response) system has benefited FedEx in streamlining and placing efficiencies in their call centers. (October, 1996). Minimum order quantity is 25; please order in multiples of 25.

P0871843
SYMPOSIUM Portfolio Package
10.00/EA
This package contains information about the entire portfolio of products and services offered for SYMPOSIUM. The material includes two brochures; SYMPOSIUM Multimedia Communications Applications and SYMPOSIUM Call Center Solutions and seven category sheets; SYMPOSIUM Personal Call Management, SYMPOSIUM IVR, SYMPOSIUM Multimedia Conferencing, SYMPOSIUM Multimedia Toolkits, SYMPOSIUM Multimedia Messaging, SYMPOSIUM Professional Services and SYMPOSIUM Partners Program. (May 1997).

P0871844
Symposium Call Center Server Feature Document
4.00/EA
This feature document provides technical information regarding the Symposium Call Center Server features. This document will address the following topics: Call Processing, Agent/ Supervisor Call Handling, Call Center Management, Integration Capabilities, Script Examples and Report Listings.

P0875712
SYMPOSIUM Remote Agent Sheet
.60/PK
This data sheet highlights the features and benefits to SYMPOSIUM Remote Agent which extends formal call center features and functionality to remote agents. Minimum order quantity is 25; please order in multiples of 25.

P0889981
Sales Trifold-ENFS SCCS Server Hardware & Software Installation
46.00/EA
Sales Trifold-ENFS SCCS Server Hardware & Software Installation

P0889982
Sales Trifold-ENFS SCCS Server Maintenance
46.00/EA
Sales Trifold-ENFS SCCS Server Maintenance

P0889983
Sales Trifold-ENFS SCCS Site Readiness Evaluation
46.00/EA
Sales Trifold-ENFS SCCS Site Readiness Evaluation

P0889984
Sales Trifold-ENFS SCCS Service Overview
46.00/EA
Sales Trifold-ENFS SCCS Service Overview

P0889985
Sales Trifold-SPS SCCS Callflow Design/Database Preparation
46.00/EA
Sales Trifold-SPS SCCS Callflow Design/Database Preparation

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0889987
Sales Trifold-SPS CTI Assessment and Design
1.84/EA
Sales Trifold-SPS CTI Assessment and Design

P0889989
Sales Trifold-SPS SCCS Migration Analysis
1.84/EA
Sales Trifold-SPS SCCS Migration Analysis

P0889990
Sales Trifold-SPS SCCS Post Production Review
1.84/EA
Sales Trifold-SPS SCCS Post Production Review

P0889991
Sales Trifold-SPS SCCS Project Management
1.84/EA
Sales Trifold-SPS SCCS Project Management

P0889992
Sales Trifold-SPS SCCS Remote Database Entry
1.84/EA
Sales Trifold-SPS SCCS Remote Database Entry

P0889993
Sales Trifold-SPS SCCS Script Design & Implementation
1.84/EA
Sales Trifold-SPS SCCS Script Design & Implementation

P0889994
Sales Trifold-SPS SCCS Supervisor Workshop
1.84/EA
Sales Trifold-SPS SCCS Supervisor Workshop

Customer Testimonials

P0807243
Montana State University: SYMPOSIUM Integrated IVR Success Story
1.19/PK
A SYMPOSIUM Integrated IVR story documenting the successful implementation of automated registration in an education environment using Integrated IVR. (1995). Minimum order quantity is 25; please order in multiples of 25.

P0819089
Columbia National Incorporated: SYMPOSIUM Integrated IVR Success Story
1.18/PK
This application brief discusses the unprecedented growth of one of the leading independent mortgage companies: Columbia National Incorporated, who uses Nortel's sophisticated IVR technology. (October, 1995) (25/pkg). Minimum order quantity is 25; please order in multiples of 25.

✓	Revision from Last Issue	§	New system sale only	>> Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤ See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ Distr butor discount category only
S	Santa Clara	N	Nashville	B Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Demo Disks/Audio

P0844036
SYMPOSIUM OPEN IVR Demo Disk and Audio Course
9.50/EA
This package contains an audio cassette explaining SYMPOSIUM OPEN IVR benefits and capabilities. The package also has interactive demonstration diskettes which include a module to simulate building an IVR application. The demonstration diskettes can be ordered separately - P0845109 (August, 1996).

P0845109
SYMPOSIUM Open IVR Demonstration Disks
6.50/EA
Description: two Macintosh and two-IBM PC/Compatible floppy diskettes. This demonstration diskettes package, is an interactive tool designed to support your SYMPOSIUM IVR application needs. It introduces SYMPOSIUM OPEN IVR basics and guides the user through applications development simulation. (August, 1996).

P0877708
SYMPOSIUM IVR CD-ROM Interactive Product Demo
1.72/EA
This CD is available for Macintosh and PC compatible users. This interactive tool lets you create a simple IVR "call flow" or application through the simulation of SYMPOSIUM IVRs through the simulation of SYMPOSIUM IVRs Graphical User Interface (GUI). In addition, you can view three IVR application examples to understand how SYMPOSIUM IVR works. This CD is ordered separately - P0877708 (November 1997).

Videos

P0853937
NortelsSYMPOSIUMIVRCustomerTestimonialVideo'
5.00/EA
This video is a presentation tool to inform customers and end-user s of what the SYMPOSIUM IVR application does and how it can improve company operations and customer satisfaction. (October, 1996).

Training

P0806071
SYMPOSIUM Integrated IVR Tactical Audio Sales Training
29.00/EA
A complete audio tape series on how to effectively sell Integrated IVR, Release 1. The kit includes six audio cassettes and four diskettes (two Macintosh and two IBM compatible). Topics covered on the audio cassettes are: 1. Summary Presentation 2. IVR functions and Market Overview 3. What is SYMPOSIUM Integrated IVR, 4. Prospecting 5. Qualifying 6. Benefits Analysis 7. Competitive Overview 8. Vertical Markets 9. Horizontal Markets 10. Implementing an Integrated IVR Application and 11. Host Connectivity Diskettes contain information on related sales tools and how to obtain them, a customer presentation highlighting the benefits of Integrated IVR, and the scripts for the audio cassettes.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

MERIDIAN 1 - Meridian Multimedia Messaging

Brochures

Note: All brochures in packages of 25 unless otherwise noted.

P0657569
Meridian Mail Reporter Product Sheet
1.14/PK
Minimum order quantity is 25; please order in multiples of 25.

P0739850
Voice Menus and Voice Forms Brochure
.46/PK
This 8.5 x 11-inch, full-color brochure explains the benefits and features of Meridian Mail's Voice Menus and Voice Forms. Minimum order quantity is 25; please order in multiples of 25.

P0741982
Meridian Mail MSM Brochure
.74/PK
This 8.5 x 11-inch, full-color brochure describes the features of Meridian Mail Message Services Module (MSM), which has the capacity to accommodate very large organizations (MSM provides from 48 to 192 ports). Minimum order quantity is 25; please order in multiples of 25.

P0741983
Meridian Mail GP Brochure
.74/PK
This 8.5 x 11-inch, brochure describes Meridian Mail GP, which is compatible with PBXs from other manufacturers as well as Nortel's SL-100 and DMS-100. Minimum order quantity is 25; please order in multiples of 25.

P0743975
Meridian Mail Features and Functionality Brochure
.55/PK
This 8.5 x 11-inch, brochure contains brief descriptions of all the Meridian Mail features. Minimum order quantity is 25; please order in multiples of 25.

P0746049
Making the Most of Voice Mail Brochure
.90/PK
This 8.5 x 4-inch, four-color brochure describes how customers can use voice mail to their advantage and avoid unnecessary problems. Minimum order quantity is 25; please order in multiples of 25.

P0746275
Meridian Messaging Healthcare Solutions Brief
1.00/PK
This two-page, four-color flyer describes applications of Meridian Messaging in the healthcare environment. It includes a chart that visually represents information flow in the applications. Minimum order quantity is 25; please order in multiples of 25.

P0746276
Meridian Messaging General Business Solutions Brief
1.00/PK
This two-page, four-color flyer describes applications of Meridian Messaging in a typical business environment. It includes a chart that visually represents information flow. Minimum order quantity is 25; please order in multiples of 25.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

P0746277
Meridian Messaging Education Solutions Brief
1.00/PK
This two-page, four-color flyer describes applications of Meridian Messaging in an educational setting. It includes a chart that visually represents information flow. Minimum order quantity is 25; please order in multiples of 25.

P0746278
Meridian Messaging Banking Solutions Brief
1.00/PK
This two-page, four-color flyer describes applications of Meridian Messaging in a financial institution. It includes a chart that visually represents information flow. Minimum order quantity is 25; please order in multiples of 25.

P0814188
Protecting Your Voice Mail System Brochure
.84/PK
This 8.5 x 4-inch, four-color brochure highlights the importance of protecting an organization’s voice mail system. The material covers some suggestions on how to protect the system against fraudulent long-distance charges, &quothackers," corporate espionage and malicious system intrusions. Minimum order quantity is 25; please order in multiples of 25.

P0843060
Messenger 2.0 Product Sheet
No charge/PK
This 8.5 x 11-inch, full-color, two-page flyer discusses Messenger 2.0, a Meridian Multimedia Messaging product that allows the user to prioritize, compose, view, print, return and forward all messages in a single window on his or her PC. Several features that enable quicker customer response and save the user time are listed, along with various installation, system and user requirements.

P0873149
Meridian Mail Upgrades Brochure
3.32/PK
This 9 x 11.5-inch, full-color, die-cut brochure outlines the advantages of Meridian Mail Release 11, including Year 2000 compatibility, increased site capacity, toll fraud prevention, time-saving administrative features and other capabilities. It also lists all of the features since Release 7 and discusses the major advantages of each release, emphasizing the need to upgrade. Minimum order quantity is 25; please order in multiples of 25.

P0889986
Sales Trifold-SPS SCCS Call Center Business Assessment
1.84/EA
Sales Trifold-SPS SCCS Call Center Business Assessment

P0889988
Sales Trifold-SPS SCCS HDX Design & Implementation
1.84/EA
Sales Trifold-SPS SCCS HDX Design & Implementation

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

Guides/Handbooks

P0702779
Meridian Mail Voice Menus Applications Guide
40.00/PK
This 8.5 x 11-inch, 32-page guide serves as an idea book for Voice Menu applications as well as documentation on how to create and use Voice Menus.

P0748232
Meridian Message Processing Feature Guide
8.00/EA
This 5 x 7-inch, full-color guide contains a list of Meridian Messaging features, describing each briefly.

P0843987
Meridian MultiMedia Messaging Sales Guide (Shrinkwrapped)
21.51/EA
This 8.5 x 11-inch, shrinkwrapped, and tabbed guide contains a complete sales guide covering vertical markets, competition, and applications for Meridian Multimedia Messaging products including Meridian Mail and Meridian IVR. A sample RFP and overhead presentation information are included. Macintosh- and DOS-formatted diskettes also provide product presentations and a cost justification tool.

Demo Disks

P0821363
Messenger 2.0 Interactive Demo Disks (Macintosh)
4.50/EA
These two Macintosh-formatted floppy diskettes contain interactive demonstrations allowing users to view and try the voice, fax and e-mail capabilities of Messenger 2.0. The diskette has Messenger 2.0 testimonials and applications showing Messenger 2.0 in use. It also has built-in presentations for all the voice, fax and e-mail capabilities of Messenger 2.0.

Videos

P0745957
Meridian Mail: The Electronic Front Door for Business Video
10.00/EA
This VHS tape is 12 minutes. It describes Meridian Mail features and their uses in different business environments. The video contains customer testimonials and application stories.

P0819975
Meridian MultiMedia Messaging Overview Video
2.50/EA
This VHS tape is 13 minutes, 42 seconds. The video highlights the capabilities of Nortel's Meridian Multimedia Messaging portfolio. It shows how users can gain control over today's increasingly complex messaging environment through the use of Meridian Mail, Meridian Mail Reporter, SYMPOSIUM Messenger and SYMPOSIUM Assistant.

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.

CD-ROM

P0821361
Messenger 2.0 Interactive CD-ROM
4.69/EA
This interactive, multiformatted CD-ROM for Windows and Macintosh platforms allows users to view and try the voice, fax and e-mail capabilities of Messenger 2.0. The CD-ROM has Messenger customer testimonials and applications showing Messenger in use. It also includes built-in presentations for all the voice, fax and e-mail capabilities of Messenger; discusses the Messaging product portfolio; and features a video showing the past, present and future of Nortel.

Miscellaneous

P0744752
Nortel Promotional Funds Handbook
20.00/EA
Using this handbook, salespeople can generate ideas about the types of promotions-including advertising, direct mail and public relations-they can implement to increase Meridian 1, Norstar, terminals and VISIT sales. The guide gives information about how to access Nortel promotional funds.

P0844587
Quick Reference Guide - Black Binder
27.00/EA
This guide contains all updated product sections in a deluxe black vinyl binder with 19 black tab indexes. (Replaces P0802296).

P0844588
Update to Black Quick Reference Guide Binder
9.50/EA
This update to the Quick Reference Guide contains all updated product sections with one new black tab indexes-GALILEO. (Replaces P0802297).

P0844589
White Telecom Professional QRG Binder
15.50/EA
This binder contains all updated product sections in a white, vinyl binder with 19 white tab indexes. This Quick Reference Guide (QRG) is useful as a reference tool for telecom mangers or salespeople. (Replaces P0802298 - Redesigned for 1996).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Reference

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

228SL1-1

Description	System Compatibility	Product compatibility	W/S
Connector Housing Box Assembly	LE (96); MS; N; NT; XL (97); XN; XT		W1

Notes:

- Components contained in this assembly are not available individually. May be required when additional PE Shelves or SDI are added.

Qty	Order code	Description	Qty	Order code	Description
3	P0206519	Bracket Mounting Screw	1	P0642939	Bracket MDF Cable Retainer
3	P0242132	Lock Washer	1	P0660436	Filter Connector Housing
2	P0610791	Housing Mounting Screw			

Status
➤ Δ S

574SL1-1

Description	System Compatibility	Product compatibility	W/S
ACD MAX Software Service Transaction Fee	ST	ACD MAX	W0

Notes:

- When ordering an issue or release update, the latest issue of NTPs are not included and must be ordered separately. Please refer to the Documentation section for additional information.
- Applicable per software transaction.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

599SL1-1

Description	System Compatibility	Product compatibility	W/S
Software Service Transaction Fee			W0

Notes:

- When ordering software and hardware upgrades (e.g., Release 20 on a 51C to Release 23 on an 81C), this code will include the complete NTP reference library and a General Release Bulletin.
- When ordering software only upgrades (e.g., Release 20 to Release 23 on the same machine type) or generic updates, customers will receive a set of Condensed NTPs and a General Release Bulletin.
- When ordering capacity changes, feature additions, or software upissues (e.g., Release 23.19 to Release 23.31 on the same machine type), customers will receive a General Release Bulletin.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

63015

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 3 to Release 7 Software Migration, from Options to Modular EC		Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Notes:

- This package must be used in conjunction with a Release 12 system migration.
- TThe Meridian Mail serial number must be provided when ordering this code.he Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

63016

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 4 to Release 7 Software Migration, from Options to Modular EC		Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W0

Notes:

- This package must be used in conjunction with a Release 12 system migration.
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

63017

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 5 to Release 7 Software Migration, from Options, Modular Option to Modular EC		Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W0

Notes:

- This package may only be used in conjunction with a Release 12 system migration for all systems except the Modular Option. The Modular Option may only use this package in conjunction with an Upgrade to MM11.
- The Meridian Mail serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

63031

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 6 to Release 8 Software Migration, from Options to Modular EC		Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W0

Notes:

- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 without 2.5 MB memory card. Systems with ACCESS Enable Option, AdminPlus or HVS features must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 12.
- A vipor tape drive is required during the Release 8 software conversion.
- 63031 may ONLY be used in conjunction with a migration to Meridian Mail Release 12.
- The Meridian Mail serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	1	P0741297	Meridian Mail System Administration Reference Manual
1	P0739518	Meridian Mail Options Reference Manual			

Status
➤ Δ S

63033

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 7 to Release 8 Software Migration, from Options to Modular EC		Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W0

Notes:

- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 without 2.5 MB memory card. Systems with ACCESS Enable Option, AdminPlus or HVS features must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 12.
- A viper tape drive is required during the Release 8 software conversion.
- 63033 may ONLY be used in conjunction with a migration to Meridian Mail Release 12.
- The Meridian Mail serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	1	P0741297	Meridian Mail System Administration Reference Manual
1	P0739518	Meridian Mail Options Reference Manual			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

63060

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 6/7 to Release 8 Software Migration, from Modular Option to Modular EC		Meridian Mail Modular Option; Meridian Mail Modular Option GP	W0

Notes:

- 63060 may ONLY be used in conjunction with an upgrade or migration to Meridian Mail Release 12.
- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 without 2.5 MB memory card. Systems with ACCESS Enable Option, AdminPlus or HVS features must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 12.
- Systems with 155 MB disk drives must upgrade to 2GB disk drives.
- Systems with Flashback tape drives must upgrade to a Tandberg Tape Drive.
- The Meridian Mail serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8			

Status
† ➤ S

A0237451

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (16 Ft.) (M/M), TTY RS-232 (5.25m)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

A0263854

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (16 Ft.) (M/F), TTY RS-232 (5.25m)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

A0274225

Description	System Compatibility	Product compatibility	W/S
Handset Cord, 6 Ft. Ash (M2000 Series)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0275286

Description	System Compatibility	Product compatibility	W/S
ADM Set Interconnect Cord NE-M4QD (21 In.)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

A0288529

Description	System Compatibility	Product compatibility	W/S
Jumpers (8/PK) (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.
- Meridian Modular Telephones without power board.

Status
➤ S

A0292928

Description	System Compatibility	Product compatibility	W/S
110V Power Cord	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W0

Status
➤ S

A0300752

Description	System Compatibility	Product compatibility	W/S
RS232 - V.35 Adapter Cable for HSDM (Male)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ B

A0300753

Description	System Compatibility	Product compatibility	W/S
RS232 - V.35 Adapter Cable for HSDM (Female)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0314408

Description	System Compatibility	Product compatibility	W/S
Handset Cord (6 Ft.) - Gray, (M2000 Series)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Status
† ➤ S

A0314597

Description	System Compatibility	Product compatibility	W/S
DC600A 60MB Back Up Tape			W1

Notes:

- Three tapes are recommended for each ACD-MAX systems. The tapes are used for daily data backup.
- The 60 MB Tape Cartridge is for use with systems equipped with a 60MB tape drive.

Status
➤ S

A0318327

Description	System Compatibility	Product compatibility	W/S
Handset Cord (9 Ft.) (Standard) - Ash, (M2000 Series)		M2006; M2008; M2009; M2016S; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Status
➤ S

A0318330

Description	System Compatibility	Product compatibility	W/S
Handset Cord (9 Ft.) (Standard) - Gray, (M2000 Series)		M2006; M2008; M2009; M2016S; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Status
† ➤ S

A0318423

Description	System Compatibility	Product compatibility	W/S
Filter Connector (50 Conductor) (EMI)	LE (23, 96); M; MS; N; NT; XL (24, 97); XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0326745

Description	System Compatibility	Product compatibility	W/S
DC300 XLP Back-Up Tape		Meridian Mail GP; Meridian Mail MP; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

A0326761

Description	System Compatibility	Product compatibility	W/S
Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh to Digital Set)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

A0326762

Description	System Compatibility	Product compatibility	W/S
Apple Macintosh Interface Cable DIN 8 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

A0326763

Description	System Compatibility	Product compatibility	W/S
Apple Macintosh Interface Cable DIN8/DB25 (Macintosh to Digital Set)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0327128

Description	System Compatibility	Product compatibility	W/S
Handset Cord (6 Ft.) - Black, (M2000 Series)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Status
➤ S

A0334590

Description	System Compatibility	Product compatibility	W/S
Handset Cord (9 Ft.) (Standard) - Black, (M2000 Series)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Status
➤ S

A0336406

Description	System Compatibility	Product compatibility	W/S
Power Supply		M2317	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.

Status
➤ S

A0336823

Description	System Compatibility	Product compatibility	W/S
Multi-Output Power Supply (MOPS)		M2009; M2018; M2112; M2317	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.
- Required when set is equipped with Data Option.

Status
➤ S

A0344336

Description	System Compatibility	Product compatibility	W/S
DB25 Male Pin Connector (AILU) (M232-422A)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0344337

Description	System Compatibility	Product compatibility	W/S
DB25 Female Pin Connector (AILU) (F232-422A)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

A0346862

Description	System Compatibility	Product compatibility	W/S
6-Conductor Line Cord (7 Ft. for M2000 telephones requiring external power, standard for M3902, M3903, M3904, and M3905)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Notes:
- For use with Meridian Digital Telephones that require auxiliary power.
- A 6-conductor line cord is packaged with Meridian Digital Telephones factory equipped with MCA, and with M2216ACD, M2016S and M2317 Telephones.

Status
➤ S

A0346863

Description	System Compatibility	Product compatibility	W/S
6-Conductor Line Cord (14 Ft. for M2000 Series requiring external power and M3902, M3903, M3904 and M3905)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W1

Notes:
- For use with Meridian Digital Telephones that require auxiliary power.

Status
➤ S

A0348785

Description	System Compatibility	Product compatibility	W/S
Handset Cord with PJ Type Plug (M2250/ M1250)		M1250; M2250	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0351166

Description	System Compatibility	Product compatibility	W/S
MVME705B Transition Card (for MVME333)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

A0351167

Description	System Compatibility	Product compatibility	W/S
MVME712AM Transition Card with Built-in Modem (for MVME147)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

A0351509

Description	System Compatibility	Product compatibility	W/S
Gender Changer (Female/Female)		Meridian IVR; Meridian MAX-IPE; Meridian Mail; Meridian Mail EC11	W1

Notes:
- For use with Meridian MAX-IPE to connect printers and supervisor terminals.

Status
➤ S

A0351919

Description	System Compatibility	Product compatibility	W/S
MVME147SA-1 Processor Card (M68030, 25Mhz, 8MB)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT		W1

Status
➤ S

A0352271

Description	System Compatibility	Product compatibility	W/S
150 MByte Data Cassette Tape		Meridian CCR; Meridian Link; Meridian MAX; Meridian MAX-IPE	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0352758

Description	System Compatibility	Product compatibility	W/S
Filler Panel, Application Model		Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX AM; Meridian MAX-SEE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:

- Used to cover blank I/O card slots in the Application Module.
- Required for proper cooling of equipment.
- New systems are equipped with all required filler panels.

Status
† ➤ S

A0354954

Description	System Compatibility	Product compatibility	W/S
Rectifier, 100 Amp	51; 61; 61C; 71; 81; LE; N; NT; VL; VLE; XL; XN; XT	NT6D82	W1

Status
➤ S

A0355200

Description	System Compatibility	Product compatibility	W/S
Power Fail Transfer Unit	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- Requires external -48V power supply when provisioned on an AC system.
- Option 11 Note: Power for PFTU is provided via AUX cable from the Option 11 main cabinet. If more than 1 PFTU is ordered, a Power Supply -48V DC (A0367916) is required. The Power Supply -48V DC will support 5 PTFUs (AC systems only).

Status
➤ S

A0361365

Description	System Compatibility	Product compatibility	W/S
RJ45 Cable		Fiber Remote	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0361709

Description	System Compatibility	Product compatibility	W/S
Caster (1)	21; 21A; 21E		W1

Notes:
- Not for use on columns over two modules high.

Status
➤ S

A0367335

Description	System Compatibility	Product compatibility	W/S
Wall Transformer, 110VAC-26.7VAC, (used with NT2K10xx)	11	M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- This 110V transformer can only be used with the Meridian Modular Telephones. Warning: Use with other telephones will damage the sets.

Status
➤ S

A0367601

Description	System Compatibility	Product compatibility	W/S
Power Supply 16V (BLF/CGM)	11		W1

Status
➤ S

A0367916

Description	System Compatibility	Product compatibility	W/S
Power Supply - 48V DC	11; 21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

A0368534

Description	System Compatibility	Product compatibility	W/S
8 Port Terminal Concentrator/FM (TC/FM) (RJ45)			W1

Notes:
- The following trademark is used with ACD MAX: HP is the trademark for Hewlett-Packard.
- An additional 8 port terminal concentrator is required for configurations using more than five terminals. One 8 port terminal concentrator required for each 8 terminal/printer ports required.
- The 8 Port Terminal Concentrator/FM (TC/FM) is equipped with modem control and the 8 Port Terminal Concentrator (TC) is without modem control.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0368760

Description	System Compatibility	Product compatibility	W/S
DC6250 250MB Back Up Tape		Meridian Mail Card Option; Meridian Mail EC11; Meridian Mail GP; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Notes:
- DC6250 250MB backup tape is only compatible with Viper Tape Drives.

Status
† ➤ S

A0369107

Description	System Compatibility	Product compatibility	W/S
Sub-D Filter Connector (25 Conductor)	71; 81; LE (23, 96); M; MS; N; NT; RT; S; ST; STE; XL (24, 97); XN; XT		W1

Status
➤ S

A0369788

Description	System Compatibility	Product compatibility	W/S
UDS V.3225 Synchronous Modem		Meridian IVR	W1

Notes:
- One NTND91AB RS232 Straight Cable is needed for each UDS Modem. If Meridian IVR requires an asynchronous connection to a remote host, then a customer-supplied asynchronous modem should be used.
- This modem is required only for IVR systems where SNA/SDLC or X.25 synchronous host communications is used and the host being accessed is not local to the IVR system. In these situations, a modem is required to access the host or network via public telephone lines or leased lines. If there is a direct connection to the host, then a modem is not needed. If there are multiple remote hosts connected to the IVR system, then each host connection will require a modem.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0376171

Description	System Compatibility	Product compatibility	W/S
Powell DEC Cable		Meridian Mail Card Option; Meridian Mail EC11 R10; Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

A0376918

Description	System Compatibility	Product compatibility	W/S
MVME332XTS 8-Channel Asynchronous I/O Card	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT	Meridian IVR; Meridian MAX	W1

Notes:

- Each 8-Channel Asynchronous Serial I/O Board requires three (3) VME Multi-port cables (NT8D96BE(A0409374)).
- This card can be provisioned to provide RS232/422 connectivity to a host computer. It provides a maximum of eight (8) serial connections which can be used for a variety of purposes, including host connection. Each 8-Channel Asynchronous Serial I/O Board requires an associated NT6D51AA (A0387982) transition card. It provides three (3) DB-25 connections each of which can be attached to a multi-port cable to carry a total of eight (8) individual RS232 connections to different devices.
- This card is supplied with all development systems. On these systems, the serial ACCESS link from the Meridian Mail system may use one of the ports on the 8-Channel Asynchronous Serial I/O Board or it may use one of the serial ports on the 68040 card. This is a software configurable option. The default configuration is for the ACCESS link to be connected to the 8-Channel Asynchronous Serial I/O Board on developer systems, and connected to the 68040 card on run-time systems. Use of the serial I/O board is recommended for larger IVR systems with large numbers of ports used for IVR. Also, on development systems, the serial connection for the Meridian Mail VT420 system console may be cabled to the 8-Channel Asynchronous Serial I/O Board to allow the display of the Meridian Mail console as a window on the X-terminal. This will only be possible on development systems since only these systems have X-terminals. If this configuration is desired, then a modem eliminator (A0378652) is needed to interface the RS232 straight cable from the Meridian Mail with a connection to the multi-port cable.
- This card also provides a serial port for a printer connection on development systems. Development systems may be shipped with an optional LaserJet printer. While this printer may be connected to the 68040 card, the default configuration will have it connected to port 12 on the 8-Channel Asynchronous Serial I/O Board.
- The MVME332XTS is form, fit and function compatible with the discontinued MVME332XT.

Status
➤ S

A0377172

Description	System Compatibility	Product compatibility	W/S
Transformer, 24V AC (M1250/DSS-9000)		DSS-9000	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0377957

Description	System Compatibility	Product compatibility	W/S
LAN Transceiver		Meridian IVR	W1

Notes:

- Each Meridian IVR Development System comes with an Ethernet (thinnet) transceiver which is used to connect the X-terminal on the Development system to the IVR system. This 802.3 interface can be used for host connectivity to a UNIX machine.

Status
➤ S

A0378220

Description	System Compatibility	Product compatibility	W/S
Tape Drive Cleaning Kit		Meridian Mail Card Option; Meridian Mail EC11 R10	W1

Status
➤ S

A0378252

Description	System Compatibility	Product compatibility	W/S
Battery	21E; STE		W1

Status
➤ S

A0378652

Description	System Compatibility	Product compatibility	W/S
Null Modem Connector, Female/Male	11		W1

Status
➤ S

A0378688

Description	System Compatibility	Product compatibility	W/S
MVME147SB-1 Processor Card (M68030, 25Mhz, 16MB)	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0379350

Description	System Compatibility	Product compatibility	W/S
25 Pair Double Ended Cable		Meridian Mail Card Option	W1

Status
➤ S

A0379351

Description	System Compatibility	Product compatibility	W/S
25 Pair Single Ended Cable		Meridian Mail Card Option	W1

Status
➤ S

A0379412

Description	System Compatibility	Product compatibility	W/S
220V Power Cord		Meridian Mail Card Option	W1

Status
➤ S

A0379431

Description	System Compatibility	Product compatibility	W/S
OPS Protector Device	11		W1

Status
➤ S

A0379589

Description	System Compatibility	Product compatibility	W/S
Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A			W1

Notes:
- This power cord is required to be used with the NTRH9017 10 Base T Hub.

Status
➤ S

A0379673

Description	System Compatibility	Product compatibility	W/S
SCSI Terminator		Meridian Mail Card Option; Meridian Mail EC11	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0381016

Description	System Compatibility	Product compatibility	W/S
Null Modem Connector, (Female/Female)	11		W1

Status
➤ S

A0383333

Description	System Compatibility	Product compatibility	W/S
Transceiver		SYMPOSIUM Call Center Server (ICCM)	W1

Notes:
- AIU male to RJ45 female transceiver.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0383526

Description	System Compatibility	Product compatibility	W/S
VT520 Video Terminal		Meridian Mail; Meridian Mail EC11	W1

Notes:
- A0351509 Gender Changer (Female/Female) required with DEC 520 terminal.

Status
➤ S

A0385576

Description	System Compatibility	Product compatibility	W/S
DB25F-DB9F Cable Adapter		Meridian Mail Card Option; Meridian Mail GP; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0386049

Description	System Compatibility	Product compatibility	W/S
MVME167-34 Processor Card (M68040, 33Mhz, 32MB)		Meridian IVR	W1

Notes:
- Must be installed in VME slot 1.

Status
➤ S

A0386050

Description	System Compatibility	Product compatibility	W/S
Keylock Software Security Device		Meridian IVR	W1

Notes:
- Keylock must be initialized with system serial number by NT manufacturing.
- The IVR ID number must be provided when ordering this code.

Status
➤ S

A0387583

Description	System Compatibility	Product compatibility	W/S
Auto Dial Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387586

Description	System Compatibility	Product compatibility	W/S
Hot Line Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387588

Description	System Compatibility	Product compatibility	W/S
Display Queue Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387590

Description	System Compatibility	Product compatibility	W/S
Display Agent Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387592

Description	System Compatibility	Product compatibility	W/S
Agent Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387595

Description	System Compatibility	Product compatibility	W/S
Waiting Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387596

Description	System Compatibility	Product compatibility	W/S
Answer Agent Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387598

Description	System Compatibility	Product compatibility	W/S
Position Busy Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387599

Description	System Compatibility	Product compatibility	W/S
Message Indicator Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387603

Description	System Compatibility	Product compatibility	W/S
Group Call Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387604

Description	System Compatibility	Product compatibility	W/S
Emergency Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387606

Description	System Compatibility	Product compatibility	W/S
Program Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387607

Description	System Compatibility	Product compatibility	W/S
Supervisor Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387608

Description	System Compatibility	Product compatibility	W/S
Charge Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387609

Description	System Compatibility	Product compatibility	W/S
Group Pickup Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387610

Description	System Compatibility	Product compatibility	W/S
Not Ready Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387611

Description	System Compatibility	Product compatibility	W/S
DN Pickup Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387613

Description	System Compatibility	Product compatibility	W/S
In-Calls Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387614

Description	System Compatibility	Product compatibility	W/S
Observe Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387616

Description	System Compatibility	Product compatibility	W/S
Night Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387624

Description	System Compatibility	Product compatibility	W/S
Trace Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387629

Description	System Compatibility	Product compatibility	W/S
Privacy Release Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387631

Description	System Compatibility	Product compatibility	W/S
Park Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387634

Description	System Compatibility	Product compatibility	W/S
Stored Number Redial Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387635

Description	System Compatibility	Product compatibility	W/S
Last Number Redial Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387637

Description	System Compatibility	Product compatibility	W/S
Display Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0387638

Description	System Compatibility	Product compatibility	W/S
Make Set Busy Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0387639

Description	System Compatibility	Product compatibility	W/S
Ring Again Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0390595

Description	System Compatibility	Product compatibility	W/S
Hold Key Cap Package (15/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0397705

Description	System Compatibility	Product compatibility	W/S
Release Key Cap Package (50/PK)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Status
➤ S

A0601396

Description	System Compatibility	Product compatibility	W/S
Modem Eliminator Male to Female	11; 11E	Fiber Remote	W1

Status
➤ S

A0601397

Description	System Compatibility	Product compatibility	W/S
Modem Eliminator Female to Female	11; 11E	Fiber Remote	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

A0601464

Description	System Compatibility	Product compatibility	W/S
Modem Cable, 10 Ft. DB9 Female to DB25 Male		Meridian MAX R7,8	W1

Status
➤ S

A0617011

Description	System Compatibility	Product compatibility	W/S
240MB Hard Disk Drive Unit		Meridian MAX-IPE	W1

Status
➤ S

A0619621

Description	System Compatibility	Product compatibility	W/S
RJ45/RS232 Connector		Fiber Remote	W1

Status
➤ B

A0620100

Description	System Compatibility	Product compatibility	W/S
Replacement Battery (For NTAK75AA/AB)	11		W1

Notes:

- The original replacement batteries were provided in kits consisting of four (4) batteries. Due to weight constraints the batteries will now be supplied as individual units. Therefore, to obtain a complete set of replacement batteries it will be necessary to order a quantity of four (4) A0620100 batteries.

Status
† ➤ S

A0622896

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Tape Drive (2.5GB)			W1

Notes:

- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

A0627875

Description	System Compatibility	Product compatibility	W/S
Cleaning Cartridge		Meridian MAX R7,8	W1

Notes:
- To be used in conjunction with NTRH9006.

Status
➤ S

A0630697

Description	System Compatibility	Product compatibility	W/S
Magnus 2.5GB Data Cartridge		Meridian IVR R2; Meridian Mail Card Option R8,9,10,11; Meridian Mail EC11 R10,11; Meridian Mail Modular EC R8,9,10,11; Meridian Mail Modular GP R8,9,10,11; Meridian Mail Modular Option R8,9,10,11; Meridian Mail Options (NT/XT) R8,9,10; Meridian Mail Options (ST/RT) R8,9,10; Open IVR R2	W1

Notes:
- Magnus 2.5GB data cartridge is only compatible with the Tandberg Tape Drive.

Status
➤ S

A0632902

Description	System Compatibility	Product compatibility	W/S
33 Ft. Plastic Fiber Cable (11E/11C)	11C; 11C COMPACT; 11E		W1

Notes:
- One fiber cable is required per Option 11E expansion cabinet in a three-cabinet Option 11E configuration.
- One Fiber Management Kit (NTBK81AA) is required per fiber cable utilized.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0633585

Description	System Compatibility	Product compatibility	W/S
Tandberg Tape Drive Cleaning Kit		Meridian IVR R2; Meridian Mail Card Option; Meridian Mail EC11; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Open IVR R2	W1

Status
➤ S

A0634101

Description	System Compatibility	Product compatibility	W/S
2-Conductor Line Cord (25 Ft.) Satin, (M2000 Series and M3901)			W1

Notes:
- For use with Meridian Digital Telephones that do not require auxiliary power.

Status
➤ S

A0634492

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Multi-IPE Interface - Redundant Option (Single Mode)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Status
➤ S

A0634493

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Multi-IPE Interface - Redundant Option (Multi Mode)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Status
➤ S

A0634494

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Multi-IPE Interface - Rack Mount Shelf Option	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0634495

Description	System Compatibility	Product compatibility	W/S
Local Fiber Multi-IPE Interface Cable (30 Ft.)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Status
➤ S

A0634496

Description	System Compatibility	Product compatibility	W/S
Remote FRMII Cable (30 ft.)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Status
➤ S

A0638645

Description	System Compatibility	Product compatibility	W/S
External Modem (14,400 bps, V.32 bis with V.42 bis)		Meridian IVR R2; Open IVR R2	W1

Status
➤ Δ S

A0639225

Description	System Compatibility	Product compatibility	W/S
MRS Tower/Rack Disk Drive (1.05GB)		Open IVR R2	W1

Notes:

- These disks do not have operating system software installed on them. This is the reason for the difference in the number of storage hours between the base system disk drives and these optional drives. The MRS/Tower and MRS/Rack can have any combination of disks up to a maximum of three. The base system includes one hard disk.
- The 1.05GB drive can store approximately 96 hours of voice storage at a sampling rate of 24 kbs.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

A0639229

Description	System Compatibility	Product compatibility	W/S
AP Token Ring Lan Interface Kit		Meridian IVR R2	W1

Notes:
- Required for LAN connectivity.
- The same controller cannot support both host connectivity and native LAN connectivity.

Status
† ➤ S

A0639513

Description	System Compatibility	Product compatibility	W/S
OIVR 2.X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0639530

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 256KB L2 Async Cache for AP or MRS/AP			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0639569

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Expansion RAM - 8MB SIMM with Parity		Meridian MAX R7,8	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0639617

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity		Meridian MAX R7,8	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ Δ S

A0640190

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Tower Spares Kit		Open IVR R2	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ Δ S

A0640192

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Rack DC Spares Kit		Open IVR R2	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ Δ S

A0640194

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Rack AC Spares Kit		Open IVR R2	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
✓ ➤ S

A0645811

Description	System Compatibility	Product compatibility	W/S
Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A			W0

Notes:
- This cable is required for the Hub.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ B

A0646699

Description	System Compatibility	Product compatibility	W/S
Key and Lock Master		Meridian MAX R7,8	W1

Status
† ➤ S

A0646715

Description	System Compatibility	Product compatibility	W/S
OIVR 2.x Hardware - Drive LED Panel for AP or MRS/AP		Meridian MAX R7,8	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0646718

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t Peripheral Mounting Rail		Meridian MAX R7,8	W1

Status
➤ S

A0646721

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t Foot		Meridian MAX R7,8	W1

Status
† ➤ S

A0647317

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Fan (100cfm)		Meridian MAX R7,8	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
✓ ➤ S

A0648372

Description	System Compatibility	Product compatibility	W/S
4 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

A0648374

Description	System Compatibility	Product compatibility	W/S
2 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1/ S1

Status
✓ ➤ S

A0648375

Description	System Compatibility	Product compatibility	W/S
7 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1/ S1

Status
✓ ➤ S

A0648377

Description	System Compatibility	Product compatibility	W/S
10 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1/ S1

Status
✓ ➤ S

A0648378

Description	System Compatibility	Product compatibility	W/S
15 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1/ S1

Status
✓ ➤ S

A0648379

Description	System Compatibility	Product compatibility	W/S
25 Ft. Ethernet Cable, Category 5		Meridian MAX R7,8	W1/ S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0650996

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 12-port Loopstart Network Interface Module			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651032

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - VRP Voice Recognition Card			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651035

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 12-port Voice Processing Card			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651036

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Serial I/O Controller for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651037

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - SCSI Disk Controller for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0651038

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 1.05GB Disk Drive (Tower)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651039

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 1.05GB Disk Drive (Rack)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651040

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Ethernet Controller for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651041

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Token Ring Controller for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0651060

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - CPU Module with no Memory			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651062

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - CPU Module with 32MB Memory			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651064

Description	System Compatibility	Product compatibility	W/S
OIVR 2.x Hardware - 450W Power Supply (Tower)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0651350

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Digiboard DTE 8 Port DB25 Male Cable			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0652237

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t Drive Tray		Meridian MAX R7,8	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0652239

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Floppy Drive, 3.5 In.			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0652365

Description	System Compatibility	Product compatibility	W/S
Meridian M2616CT 700 mAh Battery, Gray (Standard)		M2616CT	W1

Status
➤ S

A0652369

Description	System Compatibility	Product compatibility	W/S
Meridian M2616CT 700 mAh Battery, Black (Standard)		M2616CT	W1

Status
† ➤ S

A0652633

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 2 Port Brooktrout Fax Card			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0652634

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 4 Port Brooktrout Fax Card			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0652635

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 8 Port Brooktrout Fax Card			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0652638

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Apertus Communications Board (SDLC)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0652681

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 350W DC Power Supply (Rack)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0652687

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Redundant DC Power Supply for MRS/Rack			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0652688

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 350W AC Power Supply (Rack)		Open IVR	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0656847

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP		Meridian IVR; Open IVR; SYMPOSIUM Call Center Server (ICCM)	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0656874

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Cable, LCD for AP or MRS/AP		Meridian MAX R7,8	W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0657566

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 10 position Connector PEB Cable			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0657728

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS to Terminal Cable (DB25F to DB25M)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0657730

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Loopstart Interface Cable (DB25F to RJ23X)			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0657777

Description	System Compatibility	Product compatibility	W/S
OIVR 2.x Hardware - CPU Module Battery for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0658110

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Tower Air Filter			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0658342

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t XXPress Memory Board with NO DRAM Included		Meridian MAX R7,8	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0658485

Description	System Compatibility	Product compatibility	W/S
OIVR 2.x Hardware - 6 Ft. SCSI Cable for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
† ➤ S

A0658488

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Floppy Cable for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0658493

Description	System Compatibility	Product compatibility	W/S
SCSI Termination, Active	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Status
† ➤ S

A0658655

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Keylock Adapter		Open IVR R2	W1

Notes:
- Compatible only with OPEN IVR 2.X hardware running OPEN IVR 2.X software.
- The Keylock Adapter must be ordered when an existing system is upgraded with any SQL software option (A0638596, A0638600, A0638602, A0638603) or the Prompt software (A0639335).
- The IVR ID number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0658690

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Rack Fan Assembly			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0658874

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t - with Chassis, Motherboard, and Floppy Drive Assembly		Meridian MAX R7,8	W1

Notes:
- A0658874 includes a chassis, motherboard, floppy drive assembly, daughterboard for memory, and a power supply.

Status
† ➤ S

A0658957

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Floppy Disk Drive for MRS			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0659125

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Cabinet Rail Assembly		Open IVR R2	W1

Notes:
- One cabinet rail assembly is required for each MRS/Rack purchased for installation in the MRS/Rack Cabinet.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

A0659158

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Riser Board for AP or MRS/AP			W1

Notes:
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
➤ S

A0660168

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Response Configuration Software	11C X11 R22; 11E X11 R20,21; 51 X11 R15,16,17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R15,16,17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R15,16,17,18,19,20,21; 81 X11 R18,19,20,21; 81C X11 R21,22; NT X11 R14,15,16,17,18,19,20,21; RT X11 R14,15,16,17,18,19,20,21; ST X11 R14,15,16,17,18,19,20,21; STE X11 R18,19,20,21; XN X11 R14,15,16,17,18,19,20,21; XT X11 R14,15,16,17,18,19,20,21		S3

Status
➤ Δ S

A0660169

Description	System Compatibility	Product compatibility	W/S
Emergency Response Installation/User Guide	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W0

Status
➤ S

A0660170

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Response Installation Kit	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0660171

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Notification PC Software	11 X11 R20; 11C X11 R22; 11E X11 R21; 51 X11 R15,16,17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R15,16,17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R15,16,17,18,19,20,21; 81 X11 R18,19,20,21; 81C X11 R21,22; NT X11 R14,15,16,17,18,19,20,21; RT X11 R14,15,16,17,18,19,20,21; ST X11 R14,15,16,17,18,19,20,21; STE X11 R18,19,20,21; XN X11 R14,15,16,17,18,19,20; XT X11 R14,15,16,17,18,19,20		S3

Status
➤ S

A0660173

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Notification Installation Kit	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W1

Status
➤ S

A0660175

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Response AC Power Supply	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W1

Status
➤ S

A0660524

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Server, 1000t XXPress 166 MHz P5 CPU with 512KB Sync Cache		Meridian MAX R7,8	W1

Notes:

- A0660524 consists of a daughterboard with a CPU.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0660538

Description	System Compatibility	Product compatibility	W/S
Data Cartridge		Meridian MAX R7,8	W1

Notes:
- To be used in conjunction with NTRH9006.

Status
➤ S

A0665488

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Response Unit	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W1

Status
➤ Δ S

A0666779

Description	System Compatibility	Product compatibility	W/S
CPU Kit Including Installed Heatsink Adhesive and Clip for Pentium Processor	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	IVR; Open IVR	W1

Notes:
- This spare part should only be ordered if the warranty period of the IVR Application Processor has expired.

Status
➤ S

A0669467

Description	System Compatibility	Product compatibility	W/S
Meridian IPEE Application Module for Option 11	11; 11C; 11E	Meridian Link; Meridian MAX-CCR; Meridian MAX-IPEE	W1

Status
➤ S

A0669468

Description	System Compatibility	Product compatibility	W/S
Meridian IPEE Application Module for Options 21-81C	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian Link; Meridian MAX-CCR; Meridian MAX-IPEE	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0670533

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t 32MB DIMM	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0670634

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t Assembly Peripheral Bay	11C; 51C; 61C; 81; 81C		W1

Status
➤ S

A0670802

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t CPU 200Mz PPRO 256K L2 Cache	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0671783

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 701t Fan, 120mm plus Cardguide	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0672418

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t 275W Power Supply	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0672941

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t Front Panel and Cable (Power/Reset Switches + LED)	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0674453

Description	System Compatibility	Product compatibility	W/S
33.6 KBPS External Data/Fax Modem	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Open IVR	W3

Status
✓ S

A0676108

Description	System Compatibility	Product compatibility	W/S
DC Power Supply for Rack Cabinet			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ ➤ S

A0677506

Description	System Compatibility	Product compatibility	W/S
Dry Clean Cartridge		Meridian MAX R7,8	W1

Notes:
- To be used in conjunction with NTRH9034.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

A0677508

Description	System Compatibility	Product compatibility	W/S
13GB Data Cartridge		Meridian MAX R7,8	W1

Notes:
- To be used in conjunction with NTRH9034.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓➤ S

A0681326

Description	System Compatibility	Product compatibility	W/S
Hot-Swap Fan Assembly			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

A0683319

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t SCSI Cable Kit	11C; 51C; 61C; 81; 81C		W1

Notes:
- The A0683319 SCSI Cable Kit includes a wide SCSI cable with six connectors, two SCSI wide to narrow adapters, and four railings.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0684753

Description	System Compatibility	Product compatibility	W/S
68 pin Wide SCSI Cable	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0688664

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Transformer			W1

Notes:
- Required for use with the ATA or MCA (NT2K69AA), ordered separately
- Do not use with MCA (NT2K65xx)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0696008

Description	System Compatibility	Product compatibility	W/S
MVME177-005 Processor Card (M68060, 50 Mhz, 64MB)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Status
➤ S

A0720557

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Platinum, 12 Ft. (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
➤ S

A0720558

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Charcoal, 12 Ft. (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
➤ S

A0720559

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Platinum, 9 Ft. (Standard, M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
➤ S

A0720560

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Charcoal, 9 Ft. (Standard, M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0720561

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Platinum, 6 Ft. (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
➤ S

A0720562

Description	System Compatibility	Product compatibility	W/S
Handset Cord, Charcoal, 6 Ft. (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
➤ S

A0721792

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Base System			W1

Notes:
- Includes the motherboard, backplane, two power supplies, three fans, two blowers, CD-ROM IDE, and 3.5 Floppy Drive. Does NOT include CPU, memory or disk drives.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0721902

Description	System Compatibility	Product compatibility	W/S
Tandberg Tape Drive Unit - External		Meridian Mail Card Option R8,10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:
- Tape drive cleaning kits may be purchased separately (A0633585).

Status
➤ S

A0722048

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t System Board			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0722070

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t SCRAM Memory Board			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0722084

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t SCSI Backplane Kit			W1

Notes:
- Includes .5x Drive tray, EMI clips, SCSI cable, and backplane documentation.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0722476

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Terminator Board			W1

Notes:
- Terminator Board fills an open slot on the CPU Board.

Status
➤ S

A0722762

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t 300Mhz Processor			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0723759

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Power Supply 360W			W1

Notes:
- Power cord must be ordered separately (reference A0645811) for this power supply.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0725300

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t 32MB SCRAM			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ S

A0725949

Description	System Compatibility	Product compatibility	W/S
DC Power Cable for PS400-48 Power Supply			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

A0726965

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t CPU Retention Mechanism			W1

Notes:
- Retention Mechanism is on the CPU Board.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0727294

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Redundant Fan Kit			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0727295

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Blower			W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0728440

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Side Cover			W1

Notes:
- Side cover of the 1001t chassis.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

A0728441

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1001t Top Cover			W1

Notes:
- Top cover of the 1001t chassis.
- Contact NRDC for warranty repair/replacement (except DOA).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0729362

Description	System Compatibility	Product compatibility	W/S
Meridian M2616CT 700 mAh Battery, Ash (Standard)		M2616CT	W1

Status
➤ Δ S

A0730854

Description	System Compatibility	Product compatibility	W/S
IPEE 1GB Hard Drive Repair Kit		Meridian MAX-IPEE	W1

Notes:
- This package is for customers that are already on an IPEE and simply need to replace the hard drive for repairs.
- If the customer is on an IPE and needs this part, they must order one of the upgrade packages NTJH93EA or NTJH93FA.
- No keycode is provided with this item.

Status
➤ Δ S

A0734765

Description	System Compatibility	Product compatibility	W/S
Headstart - Verification Package			W0

Notes:
- Configure and test in Nortel Captive Office. 3 days.

Status
➤ Δ S

A0734767

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 32 Hours			W0

Notes:
- Yearly support for fifteen (15) ACD agents and fifteen (15) client PC's. Maximum support time not to exceed 32 hours.

Status
➤ S

A0735349

Description	System Compatibility	Product compatibility	W/S
128 MB DIMM			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

A0744456

Description	System Compatibility	Product compatibility	W/S
CallPilot 128 MB DIMM			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

A0757981

Description	System Compatibility	Product compatibility	W/S
FRMII System Monitor Isolator			W0

Notes:
- This Optical Isolator device and associated cable connects between the I/O panel of the Fiber Remote Multi-IPE Interface unit and the System Monitor on the Meridian 1 equipment to provide greater immunity to damage during high current surge conditions.

Status
➤ S

A0757982

Description	System Compatibility	Product compatibility	W/S
FRMII MMI/Modem Isolator			W0

Notes:
- This Optical Isolator device connects between the I/O Panel of the Fiber Remote Multi-IPE Interface unit and a MMI terminal or modem to provide greater immunity to damage during high current surge conditions.

Status
➤ S

A0761993

Description	System Compatibility	Product compatibility	W/S
FRMII Alarm Cable (32 Ft.)			W0

Notes:
- This cable provides a connection between the Fiber Remote Multi-IPE Interface unit and any external alarm reporting units if required by the customer.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

A0766182

Description	System Compatibility	Product compatibility	W/S
Dual Pentium II CPU			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

A0766331

Description	System Compatibility	Product compatibility	W/S
Maintenance Interface Cable	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Status
✓ S

A0766997

Description	System Compatibility	Product compatibility	W/S
Wide SCSI Terminator			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ S

A0769312

Description	System Compatibility	Product compatibility	W/S
SCSI Adapter			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

A0773054

Description	System Compatibility	Product compatibility	W/S
Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Notes:
- Order one A0757981 FRMII System Monitor Isolator for each local and remote site when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote MMI terminal connection when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote modem connection when power surge protection is required.
- Ensure NT7R66BB MMI Cable is used with A0759609 FRMII units.
- Ensure A0762506 AC/DC Power Converter is used with A0759609 FRMII units if DC power is not provided.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

A0773055

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Notes:

- Order one A0757981 FRMII System Monitor Isolator for each local and remote site when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote MMI terminal connection when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote modem connection when power surge protection is required.
- Ensure NT7R66BB MMI Cable is used with A0759609 FRMII units.
- Ensure A0762506 AC/DC Power Converter is used with A0759609 FRMII units if DC power is not provided.

Status
➤ S

A0773056

Description	System Compatibility	Product compatibility	W/S
Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote	W1

Notes:

- Order one A0757981 FRMII System Monitor Isolator for each local and remote site when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote MMI terminal connection when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote modem connection when power surge protection is required.
- Ensure NT7R66BB MMI Cable is used with A0759609 FRMII units.
- Ensure A0762506 AC/DC Power Converter is used with A0759609 FRMII units if DC power is not provided.

Status
➤ S

A0773059

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote	W1

Notes:

- Order one A0757981 FRMII System Monitor Isolator for each local and remote site when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote MMI terminal connection when power surge protection is required.
- Order one A0757982 FRMII MMI/Modem Isolator for each local and remote modem connection when power surge protection is required.
- Ensure NT7R66BB MMI Cable is used with A0759609 FRMII units.
- Ensure A0762506 AC/DC Power Converter is used with A0759609 FRMII units if DC power is not provided.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

A0774466

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 40 Hours			W0

Notes:
- Yearly support for up to thirty (30) ACD agents and thirty (30) client PC's. Maximum support time not to exceed 40 hours.

Status
➤ Δ S

A0774467

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 45 Hours			W0

Notes:
- Yearly support for up to fifty (50) ACD agents and fifty (50) client PC's. Maximum support time not to exceed 45 hours.

Status
➤ Δ S

A0774468

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 50 Hours			W0

Notes:
- Yearly support for up to one hundred (100) ACD agents and one hundred (100) client PC's. Maximum support time not to exceed 50 hours.

Status
➤ Δ S

A0774469

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 100 Hours			W0

Notes:
- Yearly support for up to two hundres (200) ACD agents and two hundred (200) client PC's. Maximum support time not to exceed 100 hours.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

A0774470

Description	System Compatibility	Product compatibility	W/S
Yearly Support for SYMPOSIUM TAPI Driver up to 200 Hours			W0

Notes:
- Yearly support for up to three hundred (300) ACD agents and three hundred (300) client PC's. Maximum support time not to exceed 200 hours.

Status
➤ Δ S

A0774471

Description	System Compatibility	Product compatibility	W/S
Headstart - Switch Configuration Package			W0

Notes:
- Configuration of customer switch or assist the Telco with configuration/datafill. 1 day.

Status
➤ Δ S

A0774472

Description	System Compatibility	Product compatibility	W/S
Headstart Pre-Installation Package			W0

Notes:
- Coordination of pre-installation activities, auditing the customers existing equipment, testing and verification of the CompuCALL/ICM link, hosting coordination meetings with the customer, system integrator and central office staff, loading required PC software, and assistance in putting the product in service. 3 days, plus actual travel and living expenses. US.

Status
✓ ➤ S

A0780247

Description	System Compatibility	Product compatibility	W/S
Data Cartridge			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

A0788129

Description	System Compatibility	Product compatibility	W/S
Shielded 9-Drop Wide SCSI Cable			W1

Notes:
- This item is used with the NTRH9065 T1 (Dual Span) SL-100 Connectivity Card.
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
✓ ➤ S

A0805434

Description	System Compatibility	Product compatibility	W/S
Power Supply AC - 500 Watts			W1

Notes:
- This part is used with the CallPilot Rack Mount AC System.

Status
✓ ➤ ⊗ S

A0810496

Description	System Compatibility	Product compatibility	W/S
CP PII Call Processor Card (128MB Memory)	81C 3311 R25		W1/ S1

Notes:
- Requires X11 Release 25 or later base software and Software Options 299 and 368

Status
➤ S

A0811762

Description	System Compatibility	Product compatibility	W/S
Fiber Network Fabric Adapter Panel			W0

Notes:
- Customers upgrading to Fiber Network Fabric where network groups do not reside in a continguous column will require Qty 4 Fiber Network Fabric Adapter Panels per upgrade (two per ring).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS0071

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN Spares Kit		Meridian MAX-SNN	W1

Notes:

- Order this spares kit for Meridian MAX SNN systems.
- One spares kit can be located at the Meridian MAX site or alternatively can be located at the distributor premises and cover more than one site within a geographical area. Not included but recommended for consideration as additional spare items are the MVME167 Processor Card (with the memory configuration appropriate for the systems being supported) and the NT7D62CA 1.2 GByte Hard Disk/600 MByte Tape Drive Assembly. Refer to the Merchandise section of the Application Products - Call Center Chapter in Book 1.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT6D51AA	Transition Card (for MVME332)
1	A0601182	MVME712M Transition Card without built-in modem (for MVME167 and MVME177)	1	NT8D96BE	VME Multi-Port Cable
3	A0605411	600MB Data Cassette Tape			

Status
➤ S

AS0073

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 7 Capacity Configurator Tool		Meridian MAX	S3

Notes:

- Microsoft Excel 4.0 is a prerequisite to run this Configuration Tool. This tool works on a PC or a Macintosh and is available in 3.5" floppy disk.
- This is an Excel for Windows program designed to assist distributors in configuring their customers data profile for the Meridian MAX.
- Order when configuring the Meridian MAX Release 7 flexible Capacity Configuration Feature.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS0074

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE Spares Kit	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- One spares kit can be located at the Meridian MAX site or alternatively can be located at the distributor premises and cover more than one site within a geographical area.
- Not included but recommended for consideration as additional spare items are the A0696008 MVME177-005 Processor Card and the NT7D62EA 2.0 Gbyte Hard Disk/600 MByte Tape Drive Assembly. Refer to the Merchandise section of the "Application Products - Call Center" Chapter in Book 1.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT6D51AA	Transition Card (for MVME332)
1	A0601182	MVME712M Transition Card without built-in modem (for MVME167 and MVME177)	1	NT8D96BE	VME Multi-Port Cable
3	A0605411	600MB Data Cassette Tape			

Status
➤ S

AS0075

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 8 Capacity Configurator Tool	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:

- Order when configuring the Meridian MAX Release 8 Flexible Capacity Configuration Feature.
- This is a Microsoft Excel spread sheet program designed to assist distributors in configuring customer data profiles within Meridian MAX Release 8 software.
- Microsoft Excel 4.0 (minimum) is a prerequisite to run this Configurator Tool. This tool works on an Intel-based PC running Microsoft Windows or an Apple Macintosh.
- Includes both PC- and Macintosh-compatible 3.5-inch diskettes and a User Guide.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R76DB	Meridian MAX Release 8 Capacity Configuration Tool			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

AS1006A

Description	System Compatibility	Product compatibility	W/S
Network Group Package AC	71		W1

Notes:

- Requires four NT8D80 CPU/MDU Interface Cables (SBE/3PE) and four NT8D76 IGS to IGM cables; specify length depending on module positions. Appropriate Network Group cable packages may be ordered if default module positioning is used.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	Qty	Order code	Description
2	NT5D30AA	Dual Intergroup Switch	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
2	NT7D06AA	Filler Panel	2	QPC43R	Peripheral Signaling
2	NT8D29AB	Common Equipment Power Supply AC	2	QPC441F	Three-Port Extender
2	NT8D35BA	Network Module AC			

Status
† ➤ S

AS1006D

Description	System Compatibility	Product compatibility	W/S
Network Group Package DC	71		W1

Notes:

- Requires four NT8D80 CPU/MDU Interface Cables (SBE/3PE) and four NT8D76 IGS to IGM cables; specify length depending on module positions. Appropriate Network Group cable packages may be ordered if default module positioning is used.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	Qty	Order code	Description
2	NT5D30AA	Dual Intergroup Switch	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
2	NT6D41AD	Common Equipment Power Supply DC	2	QPC43R	Peripheral Signaling
2	NT7D06AA	Filler Panel	2	QPC441F	Three-Port Extender
2	NT8D35EA	Network Module DC			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1007A

Description	System Compatibility	Product compatibility	W/S
Network Module Package AC	21; 21E; 51; 61; 61C; 71; 81; LE (23); M; MS; N; NT; RT; ST; STE; VLE; XL (25); XN; XT		W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D06AA	Filler Panel	1	NT8D35BA	Network Module AC
1	NT8D29AB	Common Equipment Power Supply AC			

Status
➤ S

AS1007D

Description	System Compatibility	Product compatibility	W/S
Network Module Package DC	21; 21E; 51; 61; 61C; 71; 81; LE (23); M; MS; N; NT; RT; ST; STE; VLE; XL (25); XN; XT		W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D41AD	Common Equipment Power Supply DC	1	NT8D35EA	Network Module DC
1	NT7D06AA	Filler Panel			

Status
§ ➤ S

AS1013

Description	System Compatibility	Product compatibility	W/S
Special Console/Line Card Package	11; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- May only be ordered as part of a new system sale; maximum of one per system.

Qty	Order code	Description	Qty	Order code	Description
1	NT6G00AF35	M2250 Attendant Console	1	NT8D02GA	Digital Line Card (DLC)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1017D

Description	System Compatibility	Product compatibility	W/S
Customer Provided DC Power Assembly	21; 21E; 51; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT8D46AW	System Monitor to QBL12 Cable (32 Ft)	1	QBL12F	Battery Distribution Box

Status
➤ S

AS1019

Description	System Compatibility	Product compatibility	W/S
Network Cable Package - 2nd Group	71		W1

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	4	NT8D80BE	CPU/MDU Interface Cable (8 Ft)

Status
➤ S

AS1020

Description	System Compatibility	Product compatibility	W/S
Network Cable Package - 3rd Group	71		W1

Qty	Order code	Description	Qty	Order code	Description
2	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft)	4	NT8D80BF	CPU Interface Cable (10 Ft)
2	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft)			

Status
➤ S

AS1021

Description	System Compatibility	Product compatibility	W/S
Network Cable Package - 4th Group	71		W1

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	2	NT8D80BJ	CPU Interface Cable (16 Ft)
2	NT8D80BG	CPU Interface Cable (12 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1022

Description	System Compatibility	Product compatibility	W/S
Network Cable Package - 5th Group	71		W1

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft)	4	NT8D80BG	CPU Interface Cable (12 Ft)

Status
➤ S

AS103003

Description	System Compatibility	Product compatibility	W/S
Centralized Answering Position Packages (M2616), Black	11		W1

Qty	Order code	Description	Qty	Order code	Description
2	NT2K22VH03	Meridian Key Expansion Module, Black, (M2000 Series)	1	P0780203	Double Key Expansion Module Footstand, Black (M2000 Series)
1	NT9K16AC03	Meridian M2616 Performance-Plus Telephone with Display, Black			

Status
➤ S

AS103035

Description	System Compatibility	Product compatibility	W/S
Centralized Answering Position Packages (M2616), Ash	11		W1

Qty	Order code	Description	Qty	Order code	Description
2	NT2K22VH35	Meridian Key Expansion Module, Ash, (M2000 Series)	1	P0780235	Double Key Expansion Module Footstand, Ash (M2000 Series)
1	NT9K16AC35	Meridian M2616 Performance-Plus Telephone with Display, Ash			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS103093

Description	System Compatibility	Product compatibility	W/S
Centralized Answering Position Packages (M2616), Gray	11		W1

Qty	Order code	Description	Qty	Order code	Description
2	NT2K22VH93	Meridian Key Expansion Module, Gray (M2000 Series)	1	P0780293	Double Key Expansion Module Footstand, Gray (M2000 Series)
1	NT9K16AC93	Meridian M2616 Performance-Plus Telephone with Display, Gray			

Status
➤ S

AS1039A

Description	System Compatibility	Product compatibility	W/S
Option 81/81C Network Group Assembly AC	81; 81C		W1

Notes:

- This package is for customers wishing to add a network group and utilize an Intergroup Switch Fabric (either QPC412 IGS cards or NT5D30 DIGS cards). Customers who utilize the fiber network fabric (NTRB33 FIJI cards) must order NTHY20AC or NTHY24AC to add an additional network group.
- Network, Conference and Tone & Digit cards must be ordered as separate items.
- Each group requires the addition of four NT8D76 IGS to IGM cables and four NTND14 CNI to 3PE cables, of appropriate length. Appropriate Option 81 Network Cable Packages (AS1040-AS1043) may be ordered if default module positioning is used.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Either CNI-2 Port (NT6D65) or CNI-3 Port (NTRB34) cards can be used to support expansion of systems with Motorola commercial processors. The maximum number of network groups supported on systems with IGS (QPC412) or DIGS (NT5D30) cards is five.
- Systems with Call Processor PII based processors in the Core/Network Modules must use NT4N65 CNI cards.
- NTRB34 (CNI-3 port cards) may be used on systems running X11 Release 24 (or earlier) but only the first two ports on the card can be provisioned.
- X11 Release 25 software is required in order to provision the third port on the CNI-3 (NTRB34) card, for either IGS or fiber network fabric configurations.

Qty	Order code	Description	Qty	Order code	Description
2	NT5D30AA	Dual Intergroup Switch	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
2	NT7D06AA	Filler Panel	2	QPC43R	Peripheral Signaling
2	NT8D29AB	Common Equipment Power Supply AC	2	QPC441F	Three-Port Extender
2	NT8D35BA	Network Module AC			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1039D

Description	System Compatibility	Product compatibility	W/S
Option 81/81C Network Group Assembly DC	81; 81C		W1

Notes:

- This package is compatible with customers wishing to add a network group and utilize an Intergroup Switch Fabric (either QPC412 IGS cards or NT5D30 DIGS cards). Customers who utilize the fiber network fabric (NTRB33 FIJI cards) must order NTHY20DC or NTHY24DC to add an additional network group.
- Network, Conference and Tone & Digit cards must be ordered as separate items.
- Each group requires the addition of four NT8D76 IGS to IGM cables and four NTND14 CNI to 3PE cables, of appropriate length. Appropriate Option 81 Network Cable Packages (AS1040-AS1043) may be ordered if default module positioning is used.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Either CNI-2 Port (NT6D65) or CNI-3 Port (NTRB34) cards can be used to support expansion of systems with Motorola commercial processors. The maximum number of network groups supported on systems with IGS (QPC412) or DIGS (NT5D30) cards is five.
- Systems with Call Processor PII based processors in the Core/Network Modules must use NT4N65 CNI-2 Port cards.
- NTRB34 (CNI-3 Port cards) may be used on systems running X11 Release 24 (or earlier) but only the first two ports on the card can be provisioned.
- X11 Release 25 software is required in order to provision the third port on the CNI-3 port card (NTRB34), for either IGS or fiber network configurations.

Qty	Order code	Description	Qty	Order code	Description
2	NT5D30AA	Dual Intergroup Switch	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
2	NT6D41AD	Common Equipment Power Supply DC	2	QPC43R	Peripheral Signaling
2	NT7D06AA	Filler Panel	2	QPC441F	Three-Port Extender
2	NT8D35EA	Network Module DC			

Status
† ➤ S

AS1040

Description	System Compatibility	Product compatibility	W/S
Option 81 Network Cable Package, 2nd Group	81		W1

Notes:

- This cable package is for an Option 81 system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).

Qty	Order code	Description	Qty	Order code	Description
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	2	NTND14BA	CNI to 3PE Cable (5 Ft)
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	2	NTND14BD	CNI to 3PE Cable (12 Ft)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

AS1041

Description	System Compatibility	Product compatibility	W/S
Option 81 Network Cable Package, 3rd Group	81		W1

Notes:
- This cable package is for Option 81 system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft)	2	NTND14BB	CNI to 3PE Cable (10 Ft)
2	NTND14BA	CNI to 3PE Cable (5 Ft)			

Status
† ➤ S

AS1042

Description	System Compatibility	Product compatibility	W/S
Option 81 Network Cable Package, 4th Group	81		W1

Notes:
- This cable package is for Option 81 system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).

Qty	Order code	Description	Qty	Order code	Description
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	2	NTND14BB	CNI to 3PE Cable (10 Ft)
2	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft)	2	NTND14BC	CNI to 3PE Cable (12 Ft)

Status
† ➤ S

AS1043

Description	System Compatibility	Product compatibility	W/S
Option 81 Network Cable Package, 5th Group	81		W1

Notes:
- This cable package is for Option 81 system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft)	2	NTND14BC	CNI to 3PE Cable (12 Ft)
2	NTND14BB	CNI to 3PE Cable (10 Ft)	2	NTND14BD	CNI to 3PE Cable (12 Ft)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1050

Description	System Compatibility	Product compatibility	W/S
Host Enhanced Voice Processing Cable Kit	21; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; STE; XT	Meridian Link R4; Meridian Mail R8,9,10	W1

Notes:

- This kit consists of two cables required for the use with Meridian Link Host Enhanced Voice Processing.
- Meridian Link Release 4 may be delayed. Meridian Link Release 3 (SW7301C and SW7305C,) may be substituted.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D61DA	Internal Link Module HEVP Cable	1	NTND82AA	RS232 Null Modem Cable (10 Ft)

Status
➤ S

AS1051

Description	System Compatibility	Product compatibility	W/S
4 Port SDI Assembly	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
2	NT8D82AD	SDI to I/O Cable (6 Ft)	1	NT8D96AB	SDI Multi-Port Cable (2 Ft)
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	1	QPC841C	Four-Port SDI

Status
➤ S

AS1052

Description	System Compatibility	Product compatibility	W/S
4 Port SDI Paddle Board Assembly	21; 21E; 51; 61; 61C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT8D41BA	Quad SDI Paddle Board	4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1054A

Description	System Compatibility	Product compatibility	W/S
Intelligent Peripheral Equipment Module Package AC	21; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One NT8D21AA Ringing Generator AC must be added for each IPE Module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator AC must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE module.

Qty	Order code	Description	Qty	Order code	Description
1	NT8D01BC	Controller - Four Card	1	NT8D37BA	Intelligent Peripheral Equipment Module AC
1	NT8D06AB	Peripheral Equipment Power Supply AC			

Status
➤ S

AS1054D

Description	System Compatibility	Product compatibility	W/S
Intelligent Peripheral Equipment Module Package DC	21; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- One NT6D42CB Ringing Generator must be added for each IPE Module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen Tip and Ring cables within the IPE module.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D40BA	Peripheral Equipment Power Supply DC	1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	NT8D01BC	Controller - Four Card			

Status
➤ S

AS1061

Description	System Compatibility	Product compatibility	W/S
PRI Package	21; 21A; 21E; 51; 61; 61C; 71; 81; RT; ST; STE		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT8D83AD	PRI/DTI to I/O Cable (6 Ft)	1	QPC720F	Primary Rate Interface Card
1	QCAD133A	PRI/DTI I/O Cable (50 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

AS1062

Description	System Compatibility	Product compatibility	W/S
PRI Package (2nd Tier)	RT; ST; STE		W1

Qty	Order code	Description	Qty	Order code	Description
1	QCAD133A	PRI/DTI I/O Cable (50 Ft)	1	QPC720F	Primary Rate Interface Card
1	QCAD325A	Cable			

Status
† ➤ S

AS1063

Description	System Compatibility	Product compatibility	W/S
PRI Package (Cabinet)	N; NT; XN; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	P0643763	Filter, PRI/DTI I/O	1	QCAD133A	PRI/DTI I/O Cable (50 Ft)
1	QCAD128A	Cable, Connector (7 Ft) (Male/Female) (DTI to I/O Panel)	1	QPC720F	Primary Rate Interface Card

Status
§ ➤ S

AS1066

Description	System Compatibility	Product compatibility	W/S
Special Meridian 1 Attendant PC with Digital Line Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:
- Customer provided, Windows 95 PC is required.

Qty	Order code	Description	Qty	Order code	Description
1	NT8D02GA	Digital Line Card (DLC)	1	NTZR07BA	Meridian 1 Attendant PC

Status
➤ S

AS1073

Description	System Compatibility	Product compatibility	W/S
SDI/DCH Package	11		W1

Notes:
- The SDI/DCH card consists of up to four serial I/O ports which can be configured as Serial Data Interface (SDI), Enhanced Serial Data Interface (ESDI) or Data Channel Handler (DCH). Up to three SDI/DCH cards may be installed in the Option 11 system. These cards must be installed in the Universal Card slots in the main cabinet.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK02BC	SDI/DCH Card	1	NTAK19FB	4 Port SDI Cable

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ † S

AS1074

Description	System Compatibility	Product compatibility	W/S
DTI/PRI Package	11; 11C; 11E		W1

Notes:

- The NTAK09 is a standard size peripheral equipment circuit card that installs in slots 1 through 9 in the base cabinet only. DTI functionality requires a minimum of NTAK57*C software. Minimal software requirement for PRI functionality is Enhanced Business Software (NTAK57BC). For additional cable length order NT8D97AX.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK09DA	DTI/PRI Card	1	P0907452	Option 11C Release 25 Technical Reference Guide - English
1	NTBK04AA	1 544 MByte Carrier Cable	1	P0907453	1 5 MB DTI/PRI/TMDI Administration and Maintenance Guide

Status
➤ S

AS1078

Description	System Compatibility	Product compatibility	W/S
Network Group Expansion Interface Package	XN; XT (QCA55)		W1

Qty	Order code	Description	Qty	Order code	Description
8	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	1	NTND33BA	Network Group Expansion Interface Kit
1	NTLH05AA	System and Software Upgrade Guide	1	P0889190	System and Software Upgrade Guide, Release 24 and Earlier

Status
➤ S

AS1079

Description	System Compatibility	Product compatibility	W/S
MSDL Intercabinet Cable Kit	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NTND27AB	MSDL to I/O Panel Cable (6 Ft)	1	NTND98AA	PRI DCH to I/O Panel Cable (6 Ft)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1081A

Description	System Compatibility	Product compatibility	W/S
Pedestal/Top Cap Package AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT7D00AA	Top Cap AC	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D22AC	System Monitor	1	NTRD25AA	Pedestal Assembly AC

Status
➤ S

AS1081D

Description	System Compatibility	Product compatibility	W/S
Pedestal/Top Cap Package DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT7D00BA	Top Cap DC	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D22AC	System Monitor	1	NTRD25BA	Pedestal Assembly DC

Status
§ ➤ Δ S

AS1082

Description	System Compatibility	Product compatibility	W/S
Meridian Modular Telephone User Guide (Package of 15 P0902627)			W0

Notes:

- Available with new system orders only; up to the number of sets included with the order.

Qty	Order code	Description	Qty	Order code	Description
15	P0902627	Meridian Digital Telephone User Guide (English)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ Δ S

AS1083

Description	System Compatibility	Product compatibility	W/S
M2216 ACD Telephone User Guide (Package of 15 P0902629)			W0

Notes:
- Available with new system orders only; up to the number of sets included with the order.

Qty	Order code	Description	Qty	Order code	Description
15	P0902629	M2216ACD Telephone User Guide (English)			

Status
§ ➤ Δ S

AS1084

Description	System Compatibility	Product compatibility	W/S
M2317 Telephone User Guide (15/PK)			W0

Notes:
- Available with new system orders only; up to the number of sets included with the order.

Qty	Order code	Description	Qty	Order code	Description
15	P0800567	M2317 Telephone User Guide (15/PK)			

Status
➤ S

AS1087D

Description	System Compatibility	Product compatibility	W/S
Rectifier Rack Assembly	21; 51; 61; 61C		W1

Notes:
- Used only in the Rectifier Rack Assembly.

Qty	Order code	Description	Qty	Order code	Description
1	NT0R72AA	-52volt Rectifier	1	NT7D1204	Rectifier Mounting Hardware Kit
1	NT7D1201	Rectifier Support/Air Baffle	1	QCAD274A	Rectifier Cords, 20 Amp, 225V

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1088D

Description	System Compatibility	Product compatibility	W/S
Rectifier Rack Assembly	21; 51; 61; 61C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT0R72AA	-52volt Rectifier	1	NT7D12AA	Rectifier Rack
1	NT6D54AA	Rectifier Wiring Kit	1	QBL15H	Battery Distribution Box
1	NT7D1201	Rectifier Support/Air Baffle	1	QCAD274A	Rectifier Cords, 20 Amp, 225V
1	NT7D1204	Rectifier Mounting Hardware Kit			

Status
➤ S

AS1089

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Local Package	21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- One NT1P63AA Electro-Optical Interface Packlet is included in this package. If redundant fiber links are required, order one additional NT1P63AA for the local end of each fiber link.
- This package does not include an EOI to I/O Panel Optical Cable. One NT1P75AA EOI to I/O Panel Optical Cable (Single Mode) or one NT1P75BA EOI to I/O Panel Optical Cable (Multi Mode) is required and must be ordered separately. If redundant fiber links are required, order one additional NT1P75AA or NT1P75BA for the local end of each fiber link.
- If the fiber connector type used is not FC/PC, order one NT1P79AA EOI to Fiber Management Optical Cable (Single Mode) or one NT1P79BA EOI to Fiber Management Optical Cable (Multi Mode) for the local end of each fiber link. If redundant fiber links are required, order one additional NT1P79AA or NT1P79BA for the local end of each fiber link.
- Enhanced OA&M features are introduced on Release 22. If required, order SW0049A Remote Software Option.

Qty	Order code	Description	Qty	Order code	Description
1	NT1P61CA	Fiber Superloop Network Card	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT1P63CA	Electro-Optical Interface Packlet	1	P0723459	Blank Packlet for EOI
1	NT1P6601	Four Optical Adaptors Kit	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT1P86AA	Local Cable Kit			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1090A

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Main Wall Mount Remote Package AC	21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- One NT1P63AA Electro-Optical Interface Packlet is included in this package. If redundant fiber links are required, order one additional NT1P63AA for the local end of each fiber link.
- This package does not include an EOI to Fiber Management Optical Cable. One NT1P79AA EOI to Fiber Management Optical Cable (Single Mode) or one NT1P79BA EOI to Fiber Management Optical Cable (Multi Mode) is required and must be ordered separately. If redundant fiber links are required, order one additional NT1P79AA or NT1P79BA for the remote end of each fiber link.

Qty	Order code	Description	Qty	Order code	Description
1	NT1P62EA	Fiber Remote Peripheral Controller Card	1	NTDK78AA	AC/DC Power Supply
1	NT1P63CA	Electro-Optical Interface Packlet	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT1P70AA	Wall Mount Cabinet	1	P0723459	Blank Packlet for EOI
1	NTAK98AA	Power Supply Cable	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

Status
➤ S

AS1090D

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Main Wall Mount Remote Package DC	21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- One NT1P63AA Electro-Optical Interface Packlet is included in this package. If redundant fiber links are required, order one additional NT1P63AA for the local end of each fiber link.
- This package does not include an EOI to Fiber Management Optical Cable. One NT1P79AA EOI to Fiber Management Optical Cable (Single Mode) or one NT1P79BA EOI to Fiber Management Optical Cable (Multi Mode) is required and must be ordered separately. If redundant fiber links are required, order one additional NT1P79AA or NT1P79BA for the remote end of each fiber link.

Qty	Order code	Description	Qty	Order code	Description
1	NT1P62EA	Fiber Remote Peripheral Controller Card	1	NTDK72AA	DC/DC Power Supply
1	NT1P63CA	Electro-Optical Interface Packlet	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT1P70AA	Wall Mount Cabinet	1	P0723459	Blank Packlet for EOI
1	NTAK28AB	Battery Junction Box	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1091A

Description	System Compatibility	Product compatibility	W/S
Expansion Wall Mount Remote Package AC	21E; 51; 51C; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT1P5201	Label Kit	1	NTBK70BA	Expansion Cabinet
1	NTAK1204	Expansion Cable - Copper (7 Ft)	1	NTDK78AA	AC/DC Power Supply
1	NTAK98AA	Power Supply Cable			

Status
➤ S

AS1091D

Description	System Compatibility	Product compatibility	W/S
Expansion Wall Mount Remote Package DC	21E; 51; 51C; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT1P5201	Label Kit	1	NTBK70BA	Expansion Cabinet
1	NTAK1204	Expansion Cable - Copper (7 Ft)	1	NTDK72AA	DC/DC Power Supply
1	NTAK28AB	Battery Junction Box			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1092A

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Floor Standing Remote Package AC	21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- One NT1P63AA Electro-Optical Interface Packlet is included in this package. If redundant fiber links are required, order one additional NT1P63AA for the local end of each fiber link.
- This package does not include an EOI to I/O Panel Optical Cable. One NT1P75AA EOI to I/O Panel Optical Cable (Single Mode) or one NT1P75BA EOI to I/O Panel Optical Cable (Multi Mode) is required and must be ordered separately. If redundant fiber links are required, order one additional NT1P75AA or NT1P75BA for the local end of each fiber link.
- If the fiber connector type used is not FC/PC, order one NT1P79AA EOI to Fiber Management Optical Cable (Single Mode) or one NT1P79BA EOI to Fiber Management Optical Cable (Multi Mode) for the local end of each fiber link. If redundant fiber links are required, order one additional NT1P79AA or NT1P79BA for the local end of each fiber link.
- One NT1P6501 Kit is included in this package. If redundant fiber links are required, order one additional NT1P6501 Kit for the remote end of each fiber link.
- Order one (1) AS1081A Pedestal/Top Cap package AC if required.

Qty	Order code	Description	Qty	Order code	Description
1	A0601396	Modem Eliminator Male to Female	1	NT8D37BA	Intelligent Peripheral Equipment Module AC
1	A0601397	Modem Eliminator Female to Female	2	NT9D18AA	Module Side Cover
1	NT1P62EA	Fiber Remote Peripheral Controller Card	1	NTAK1108	SDI Cable
1	NT1P63CA	Electro-Optical Interface Packlet	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT1P6501	Two Optical Adaptors Kit	1	P0723459	Blank Packlet for EOI
1	NT1P87AA	Remote Cable Kit	1	P0803870	Filler Plate For Fiber Controller
1	NT8D06AB	Peripheral Equipment Power Supply AC	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1092D

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Floor Standing Remote Package DC	21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- One NT1P63AA Electro-Optical Interface Packlet is included in this package. If redundant fiber links are required, order one additional NT1P63AA for the local end of each fiber link.
- This package does not include an EOI to I/O Panel Optical Cable. One NT1P75AA EOI to I/O Panel Optical Cable (Single Mode) or one NT1P75BA EOI to I/O Panel Optical Cable (Multi Mode) is required and must be ordered separately. If redundant fiber links are required, order one additional NT1P75AA or NT1P75BA for the local end of each fiber link.
- If the fiber connector type used is not FC/PC, order one NT1P79AA EOI to Fiber Management Optical Cable (Single Mode) or one NT1P79BA EOI to Fiber Management Optical Cable (Multi Mode) for the local end of each fiber link. If redundant fiber links are required, order one additional NT1P79AA or NT1P79BA for the local end of each fiber link.
- One NT1P6501 Kit is included in this package. If redundant fiber links are required, order one additional NT1P6501 Kit for the remote end of each fiber link.
- Order one (1) AS1081D Pedestal/Top Cap package DC if required.

Qty	Order code	Description	Qty	Order code	Description
1	A0601396	Modem Eliminator Male to Female	1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	A0601397	Modem Eliminator Female to Female	2	NT9D18AA	Module Side Cover
1	NT1P62EA	Fiber Remote Peripheral Controller Card	1	NTAK1108	SDI Cable
1	NT1P63CA	Electro-Optical Interface Packlet	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT1P6501	Two Optical Adaptors Kit	1	P0723459	Blank Packlet for EOI
1	NT1P87AA	Remote Cable Kit	1	P0803870	Filler Plate For Fiber Controller
1	NT6D40BA	Peripheral Equipment Power Supply DC	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

Status
➤ S

AS1093

Description	System Compatibility	Product compatibility	W/S
Carrier Remote Local Package	21E; 51; 51C; 61; 61C; 71; 81; NT; XT		W1

Notes:

- Order the SW0049A Carrier Remote Software Option.
- When installing in SL-1 cabinets, order one NT7R69AA Extension Local Carrier Cable Assembly and one NT7R69BA Extension Local Maintenance Cable Assembly.
- For each T1 link equipped, add the same number of NT7R87AA (T1 Carrier Link Cable Kits).

Qty	Order code	Description	Qty	Order code	Description
1	NT7R51AD	Local Carrier Interface Card	1	NT7R67CA	Local Maintenance/Clock Cable Assembly
1	NT7R66AA	SDI Cable Kit (10 Ft)	1	NT7R67DA	Local External Maintenance Cable Assembly
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT7R67BA	Local Carrier/Monitor Cable Assembly	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1094A

Description	System Compatibility	Product compatibility	W/S
Carrier Remote Main Wall Mount Remote Package AC	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Carrier Remote	W1

Notes:

- For each T1 link equipped, add the same number of NT7R87AA (T1 Carrier Link Cable Kits).
- If auxiliary alarm connections are required, add one NT7R86AA (Auxiliary Alarm Cable).

Qty	Order code	Description	Qty	Order code	Description
1	NT1P70AA	Wall Mount Cabinet	1	NTAK98AA	Power Supply Cable
1	NT7R52AD	Remote Carrier Interface Card	1	NTDK78AA	AC/DC Power Supply
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT7R94AA	Carrier Wall Mount Cable Kit	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

Status
➤ S

AS1094D

Description	System Compatibility	Product compatibility	W/S
Carrier Remote Main Wall Mount Remote Package DC	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Carrier Remote	W1

Notes:

- For each T1 link equipped, add the same number of NT7R87AA (T1 Carrier Link Cable Kits).
- If auxiliary alarm connections are required, add one NT7R86AA (Auxiliary Alarm Cable).

Qty	Order code	Description	Qty	Order code	Description
1	NT1P70AA	Wall Mount Cabinet	1	NTAK28AB	Battery Junction Box
1	NT7R52AD	Remote Carrier Interface Card	1	NTDK72AA	DC/DC Power Supply
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT7R94AA	Carrier Wall Mount Cable Kit	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1095A

Description	System Compatibility	Product compatibility	W/S
Carrier Remote Floor Standing Remote Package AC	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Carrier Remote	W1

Notes:

- Order one AS1081A Pedestal/Top Cap Package AC.
- For each T1 link equipped, add the same number of NT7R87AA (T1 Carrier Link Cable Kits).
- If auxiliary alarm connections are required, add one NT7R86AA (Auxiliary Alarm Cable).

Qty	Order code	Description	Qty	Order code	Description
1	NT7R52AD	Remote Carrier Interface Card	1	NT8D37BA	Intelligent Peripheral Equipment Module AC
1	NT7R66BA	MMI Cable Kit (32 Ft)	2	NT9D18AA	Module Side Cover
1	NT7R68AA	Remote Carrier/Alarm Cable Assembly	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT7R68BA	Remote Maintenance Cable Assembly	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT8D06AB	Peripheral Equipment Power Supply AC			

Status
➤ S

AS1095D

Description	System Compatibility	Product compatibility	W/S
Carrier Remote Floor Standing Remote Package DC	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Carrier Remote	W1

Notes:

- Order one AS1081D Pedestal/Top Cap Package DC.
- For each T1 link equipped, add the same number of NT7R87AA (T1 Carrier Link Cable Kits).
- If auxiliary alarm connections are required, add one NT7R86AA (Auxiliary Alarm Cable).

Qty	Order code	Description	Qty	Order code	Description
1	NT6D40BA	Peripheral Equipment Power Supply DC	1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	NT7R52AD	Remote Carrier Interface Card	2	NT9D18AA	Module Side Cover
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	NTLH06AA	Remote Peripheral Equipment Guide
1	NT7R68AA	Remote Carrier/Alarm Cable Assembly	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT7R68BA	Remote Maintenance Cable Assembly			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1130

Description	System Compatibility	Product compatibility	W/S
Option 51C/61C/81 CE Spares Package	51C; 61C; 81		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D03FB	68060 Enhanced 128MB Call Processor	1	NTRB34AA	Core-to-Network Interface Card (CNI-3)
1	NT5D30AA	Dual Intergroup Switch	1	QPC43R	Peripheral Signaling
1	NT5D61AB	IODU/C Pack	1	QPC441F	Three-Port Extender
1	NT8D04BA	SuperLoop Network Card	1	QPC471H	Clock Controller
1	NT8D17FA	Conference/TDS Card			

Status
➤ S

AS1132

Description	System Compatibility	Product compatibility	W/S
Option 51C/61C/81C System Spares Package	51C; 61C; 81C		W1

Notes:

- This package does not include a Call Processor which must be ordered separately.
- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D30AA	Dual Intergroup Switch	2	NT8D14BB	Universal Trunk Card
1	NT5D61AB	IODU/C Pack	1	NT8D17FA	Conference/TDS Card
1	NT8D01BC	Controller - Four Card	1	NTRB34AA	Core-to-Network Interface Card (CNI-3)
4	NT8D02GA	Digital Line Card (DLC)	2	QPC43R	Peripheral Signaling
1	NT8D04BA	SuperLoop Network Card	1	QPC441F	Three-Port Extender
4	NT8D09BA	Analog Message Waiting Line Card	1	QPC471H	Clock Controller

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1140

Description	System Compatibility	Product compatibility	W/S
Local fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Order one AS1141 Remote Fiber Multi-IPE assembly for each AS1140 package ordered.
- Add one A0634492 Redundant Option (Single Mode) for each A0759612 FRMII unit equipped if redundant fiber links are required.
- This package is provisioned for one network loop. If additional loops are required (maximum of two loops for A0759612 unit), order one NT8D88AD Network to I/O Cable (6 ft.) and one A0634495 Local FRMII cable (30 ft.).
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the local end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
1	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	1	NT8D04BA	SuperLoop Network Card
1	A0757982	FRMII MMI/Modem Isolator	1	NT8D88AD	Network to I/O Cable (6 Ft)
1	A0766331	Maintenance Interface Cable	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0773059	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT7R66AA	SDI Cable Kit (10 Ft)			

Status
➤ S

AS1141

Description	System Compatibility	Product compatibility	W/S
Remote Fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Add one A0634492 Redundant Option (Single Mode) for each A0759612 FRMII unit equipped if redundant fiber links are required.
- Add AS1081A or AS1081D Pedestal/Top Cap Package AC or DC, AS1054A or AS1054D Intelligent Peripheral Equipment Module Package AC or DC, A0634496 Remote FRMII cable and NT8D92AB Controller to I/O cable as required based on customers line size requirements.
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the remote end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
1	A0634496	Remote FRMII Cable (30 ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	1	NT8D92AB	Controller to I/O Cable (20 Inch)
1	A0757982	FRMII MMI/Modem Isolator	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0766331	Maintenance Interface Cable	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	A0773059	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1142

Description	System Compatibility	Product compatibility	W/S
Local Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Order one AS1143 Remote Fiber Multi-IPE Assembly for each AS1142 package ordered.
- Add one A0634493 Redundant Option (Multi Mode) for each A0759620 FRMII unit equipped if redundant fiber links are required.
- This package is provisioned for one network loop. If additional loops are required (maximum of two loops for A0759620 unit), order one NT8D88AD Network to I/O Cable (6 ft.) and one A0634495 Local FRMII cable (30 ft.).
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the local end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
1	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	1	NT8D04BA	SuperLoop Network Card
1	A0757982	FRMII MMI/Modem Isolator	1	NT8D88AD	Network to I/O Cable (6 Ft)
1	A0766331	Maintenance Interface Cable	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0773055	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT7R66AA	SDI Cable Kit (10 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1143

Description	System Compatibility	Product compatibility	W/S
Remote Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Add AS1081A or AS1081D Pedestal/Top Cap Package AC or DC, AS1054A or AS1054D Intelligent Peripheral Equipment Module Package AC or DC, A0634496 Remote FRMII cable and NT8D92AB Controller to I/O cable as required based on customers line size requirements.
- Add one A0634493 Redundant Option (Multi Mode) for each A0759620 FRMII unit equipped if redundant fiber links are required.
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the remote end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
1	A0634496	Remote FRMII Cable (30 ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	1	NT8D92AB	Controller to I/O Cable (20 Inch)
1	A0757982	FRMII MMI/Modem Isolator	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0766331	Maintenance Interface Cable	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	A0773055	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)			

Status
➤ S

AS1144

Description	System Compatibility	Product compatibility	W/S
Local Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Order one AS1145 Remote Fiber Multi-IPE Assembly for each AS1144 package ordered.
- Add one A0634492 Redundant Option (Single Mode) for each A0759609 FRMII unit equipped if redundant fiber links are required.
- This package is provisioned for two network loops. If additional loops are required (maximum of four loops for A0759609 unit), order additional NT8D88AD Network to I/O Cables (6 ft.) and A0634495 Local FRMII cables (30 ft.).
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the local end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
2	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	2	NT8D04BA	SuperLoop Network Card
1	A0757982	FRMII MMI/Modem Isolator	2	NT8D88AD	Network to I/O Cable (6 Ft)
1	A0766331	Maintenance Interface Cable	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0773056	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT7R66AA	SDI Cable Kit (10 Ft)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1145

Description	System Compatibility	Product compatibility	W/S
Remote Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Add AS1081A or AS1081D Pedestal/Top Cap Package AC or DC, AS1054A or AS1054D Intelligent Peripheral Equipment Module Package AC or DC, A0634496 Remote FRMII cable and NT8D92AB Controller to I/O cable as required based on customers line size requirements.
- Add one A0634492 Redundant Option (Single Mode) for each A0759609 FRMII unit equipped if redundant fiber links are required.
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the remote end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
2	A0634496	Remote FRMII Cable (30 ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	2	NT8D92AB	Controller to I/O Cable (20 Inch)
1	A0757982	FRMII MMI/Modem Isolator	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0766331	Maintenance Interface Cable	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	A0773056	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1146

Description	System Compatibility	Product compatibility	W/S
Local Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Order one AS1147 Remote Fiber Multi-IPE Assembly for each AS1146 package ordered.
- Add one A0634493 Redundant Option (Multi Mode) for each A0759618 FRMII unit equipped if redundant fiber links are required.
- This package is provisioned for two network loops. If additional loops are required (maximum of four loops for A0759618 unit), order additional NT8D88AD Network to I/O Cables (6 ft.) and A0634495 Local FRMII cables (30 ft.).
- Add one A0634497 Maintenance Interface cable, if maintenance interface to the A0759618 unit is required at the local end of the system.
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the local end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
2	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	2	NT8D04BA	SuperLoop Network Card
1	A0757982	FRMII MMI/Modem Isolator	2	NT8D88AD	Network to I/O Cable (6 Ft)
1	A0766331	Maintenance Interface Cable	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0773054	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	NT7R66AA	SDI Cable Kit (10 Ft)			

Status
➤ S

AS1147

Description	System Compatibility	Product compatibility	W/S
Remote Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	21E; 51; 51C; 61; 61C; 71; 81; NT; XT	Fiber Remote Multi-IPE Interface	W1

Notes:

- Add AS1081A or AS1081D Pedestal/Top Cap Package AC or DC, AS1054A or AS1054D Intelligent Peripheral Equipment Module Package AC or DC, A0634496 Remote FRMII cable and NT8D92AB Controller to I/O cable as required based on customers line size requirements.
- Add one A0634493 Redundant Option (Multi Mode) for each A0759618 FRMII unit equipped if redundant fiber links are required.
- Add one A0762506 AC/DC Power Converter if auxiliary DC power is not available at the remote end of the system for each FRMII unit equipped.
- Add one A0761993 FRMII Alarm Cable (32 ft.) if connection between the FRMII unit and any external alarm reporting unit is required by the customer.
- If an MMI and modem is connected to the FRMII unit, order one A0757982 MMI/Modem Isolator.

Qty	Order code	Description	Qty	Order code	Description
2	A0634496	Remote FRMII Cable (30 ft)	1	NT7R66BB	MMI Cable Kit (32 ft)
1	A0757981	FRMII System Monitor Isolator	2	NT8D92AB	Controller to I/O Cable (20 Inch)
1	A0757982	FRMII MMI/Modem Isolator	1	NTLH06AA	Remote Peripheral Equipment Guide
1	A0766331	Maintenance Interface Cable	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	A0773054	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1171

Description	System Compatibility	Product compatibility	W/S
Option 11E 1st Expansion Cabinet Package AC	11E		W1

Notes:

- All IPE to support line and trunk configuration should be ordered separately.
- If this package is being used to grow a single-cabinet Option 11 currently on Release 16 or 18 to a two-cabinet system, the U1108 Option 11E Core Upgrade Package is also required.
- This expansion cabinet should be ordered to expand an Option 11 or 11E from a single-cabinet system to a two-cabinet system.
- The NTAK70BC Option 11E Expansion Cabinet Kit includes one (1) NTAK12BB Option 11E Expansion Cabinet, one (1) NTBK47AB Expansion Daughterboard, one (1) NTAK1204 Expansion Cable - Copper (7 Ft.), one (1) Mounting Bracket, and one (1) package of screws.
- If fiber interface is required to connect the main cabinet to the first expansion cabinet, order one (1) AS1175 Fiber Interface Kit.

Qty	Order code	Description	
1	NTAK70BC	Option 11E Expansion Cabinet Kit	
	Each Package Includes:		
	1	NTAK1204	Expansion Cable - Copper (7 Ft)
	1	NTAK12BB	Option 11 Expansion Cabinet
	1	NTBK47AB	Expansion Daughterboard
	1	P0714236	Mounting Bracket
	1	P0715802	Alignment Bracket (Expansion Cabinet)
	1	P0719578	Package of Screws
1	NTAK98AA	Power Supply Cable	
1	NTDK78AA	AC/DC Power Supply	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1172

Description	System Compatibility	Product compatibility	W/S
Option 11E 1st Expansion Cabinet Package DC	11E		W1

Notes:

- All IPE to support line and trunk configuration should be ordered separately.
- If this package is being used to grow a single-cabinet Option 11 currently on Release 16 or 18 to a two-cabinet system, the U1108 Option 11E Core Upgrade Package is also required.
- This expansion cabinet should be ordered to expand an Option 11 or 11E from a single-cabinet system to a two-cabinet system.
- The NTAK70BC Option 11E Expansion Cabinet Kit includes one (1) NTAK12BB Option 11E Expansion Cabinet, one (1) NTBK47AB Expansion Daughterboard, one (1) NTAK1204 Expansion Cable - Copper (7 Ft.), one (1) Mounting Bracket, and one (1) package of screws.
- If fiber interface is required to connect the main cabinet to the first expansion cabinet, order one (1) AS1175 Fiber Interface Kit.

Qty	Order code	Description	
1	NTAK28AB	Battery Junction Box	
1	NTAK70BC	Option 11E Expansion Cabinet Kit	
	Each Package Includes:		
	1	NTAK1204	Expansion Cable - Copper (7 Ft)
	1	NTAK12BB	Option 11 Expansion Cabinet
	1	NTBK47AB	Expansion Daughterboard
	1	P0714236	Mounting Bracket
	1	P0715802	Alignment Bracket (Expansion Cabinet)
	1	P0719578	Package of Screws
1	NTDK72AA	DC/DC Power Supply	

Status
➤ S

AS1173

Description	System Compatibility	Product compatibility	W/S
Option 11E 2nd Expansion Cabinet Package AC	11E		W1

Notes:

- All IPE to support line and trunk configuration should be ordered separately.
- This expansion cabinet should be ordered to expand a current Option 11 or 11E from a two-cabinet system to a three cabinet Option 11E system.
- If this package is being used to grow a two-cabinet Option 11 currently on Release 16 or 18 to a three-cabinet Option 11E system, the Option 11E Core Upgrade package and Release 21 software are also required.
- The NTBK79AA Option 11E Expansion Cabinet Kit includes one (1) NTAK12BB Option 11E Expansion Cabinet, one (1) Mounting Bracket, one (1) Alignment Bracket, and one (1) package of screws.

Qty	Order code	Description	
1	NTAK98AA	Power Supply Cable	
1	NTBK54AB	Main Fiber Interface (MFI) Kit	
	Each Package Includes:		
	1	NTBK62AB	MFI/EFI Power Cable
1	NTBK55AB	Expansion Fiber Interface (EFI) Kit	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)
	1	NTBK62AB	MFI/EFI Power Cable
1	NTBK79AA	Option 11E Expansion Cabinet Kit	
	Each Package Includes:		
	1	NTAK12BB	Option 11 Expansion Cabinet
	1	P0714236	Mounting Bracket
	1	P0715802	Alignment Bracket (Expansion Cabinet)
	1	P0719578	Package of Screws
1	NTBK80AA	Ground Bar	
2	NTBK81AA	Fiber Management Kit	
1	NTDK78AA	AC/DC Power Supply	
1	P0691037	Ground Lug	

Status
➤ S

AS1174

Description	System Compatibility	Product compatibility	W/S
Option 11E 2nd Expansion Cabinet Package DC	11E		W1

Notes:

- All IPE to support line and trunk configuration should be ordered separately.
- If this package is being used to grow a two-cabinet Option 11 currently on Release 16 or 18 to a three-cabinet Option 11E system, the Option 11E Core Upgrade package and Release 21 software are also required.
- This expansion cabinet should be ordered to expand a current Option 11 or 11E from a two-cabinet system to a three cabinet Option 11E system.
- The NTBK79AA Option 11E Expansion Cabinet Kit includes one (1) NTAK12BB Option 11E Expansion Cabinet, one (1) Mounting Bracket, one (1) Alignment Bracket, and one (1) package of screws.

Qty	Order code	Description	
1	NTAK28AB	Battery Junction Box	
1	NTBK54AB	Main Fiber Interface (MFI) Kit	
	Each Package Includes:		
	1	NTBK62AB	MFI/EFI Power Cable
2	NTBK55AB	Expansion Fiber Interface (EFI) Kit	
	Each Package Includes:		
	1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)
	1	NTBK62AB	MFI/EFI Power Cable
1	NTBK79AA	Option 11E Expansion Cabinet Kit	
	Each Package Includes:		
	1	NTAK12BB	Option 11 Expansion Cabinet
	1	P0714236	Mounting Bracket
	1	P0715802	Alignment Bracket (Expansion Cabinet)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0719578	Package of Screws
1	NTBK80AA	Ground Bar	
2	NTBK81AA	Fiber Management Kit	
1	NTDK72AA	DC/DC Power Supply	
1	P0691037	Ground Lug	

Status
➤ S

AS1175

Description	System Compatibility	Product compatibility	W/S
Fiber Interface Kit	11E		W1

Qty	Order code	Description	
1	NTBK47AB	Expansion Daughterboard	
1	NTBK54AB	Main Fiber Interface (MFI) Kit	
	Each Package Includes:		
	1	NTBK62AB	MFI/EFI Power Cable
1	NTBK55AB	Expansion Fiber Interface (EFI) Kit	
	Each Package Includes:		
	1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)
	1	NTBK62AB	MFI/EFI Power Cable
1	NTBK81AA	Fiber Management Kit	

Status
§ ➤ S

AS1182

Description	System Compatibility	Product compatibility	W/S
Pre-Printed Feature Key Cap Package (1 PK of 11 Key Caps, A0637619)			W0

Notes:

- No charge when ordered with new Meridian Digital Telephones in equal quantities, at the time of original order placement. See Sales & Marketing Bulletin 975-G, August 1995, for details.

Status
➤ S

AS1200D

Description	System Compatibility	Product compatibility	W/S
MFA150 Modular Power Assembly - Single Shelf	21; 21E; 51; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT5C06CC	MPR25E Modular Power Rectifier, 25 Amps	1	NT8D46AV	System Monitor to Power Cabinet Cable (32 Ft)
1	NT5C90EF	MFA150 Modular Power, Single Shelf, 75 Amps	1	P0730121	MFA150 User Guide/NTP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1201D

Description	System Compatibility	Product compatibility	W/S
MFA150 Modular Power Assembly - Dual Shelf	21; 21E; 51; 61; 61C; 71; 81		W1

Qty	Order code	Description	Qty	Order code	Description
3	NT5C06CC	MPR25E Modular Power Rectifier, 25 Amps	1	NT8D46AV	System Monitor to Power Cabinet Cable (32 Ft)
1	NT5C90EG	MFA150 Modular Power, Dual Shelf, 150 Amps	1	P0730121	MFA150 User Guide/NTP

Status
➤ S

AS1204D

Description	System Compatibility	Product compatibility	W/S
50 Amp Rectifier Expansion Package		J2412A (QCA13)	W1

Notes:

- For adding a 50 Amp rectifier within QCA13-type main and supplemental cabinets.
- This assembly is a direct replacement for the NT5C03.
- J2412A(QCA13) Power Systems requiring expansion into a supplemental cabinet must use the AS1203D MPP600 Modular Power Package-Supplemental Cabinet.

Qty	Order code	Description	Qty	Order code	Description
1	NT5C07AC	50 Amp Rectifier	1	NT5C12BB	MPS 150 Modular Power Shelf 19 Rackmount

Status
➤ S

AS1208A

Description	System Compatibility	Product compatibility	W/S
Power Supply Spares Package AC	21; 21E; 51; 51C; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT8D06AB	Peripheral Equipment Power Supply AC	1	NT8D29AB	Common Equipment Power Supply AC

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1208D

Description	System Compatibility	Product compatibility	W/S
Power Supply Spares Package DC	21; 21E; 51; 51C; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT6D40BA	Peripheral Equipment Power Supply DC	1	NT6D41AD	Common Equipment Power Supply DC

Status
➤ S

AS1209D

Description	System Compatibility	Product compatibility	W/S
System 600/48 Modular Power Package - Main Cabinet	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- The NT5C91MM includes the following: (10) P0746607 30A Circuit Breakers, (10) A0614339 1 1/3 AMP Fuses, (1) NT6C25FF-61 Front Access Controller, (2) NT5C12AC MPS150 Modular Power Shelf.
- Order 4 QKM176A Seismic Anchor per Main Cabinet if required.
- Order 1 P0744873 Isolation kit if required.

Qty	Order code	Description	Qty	Order code	Description
2	NT5C07AC	50 Amp Rectifier	1	NT8D46AV	System Monitor to Power Cabinet Cable (32 Ft)
1	NT5C91MM	System 600/48 Main Cabinet Assembly	1	P0815188	System 600/48 NTP

Status
➤ S

AS1210D

Description	System Compatibility	Product compatibility	W/S
System 600/48 Modular Power Package - Supplemental Cabinet	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- Order 1 P0744873 Isolation kit if required.
- Order 4 QKM176A Seismic Anchor per Supplemental Cabinet, if required.
- The NT5C91MN includes the following: (8) P0746607 30A Circuit Breakers, (2) NT5C12AC MPS150 Modular Power Shelf.

Qty	Order code	Description	Qty	Order code	Description
1	NT5C07AC	50 Amp Rectifier	1	NT5C91MN	System 600/48 Supplemental Cabinet Assembly

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1240

Description	System Compatibility	Product compatibility	W/S
Option 81C Network Cable Package, 2nd Group	81C		W1

Notes:
- This cable package is for Option 81C system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).
- This cable package is applicable to Option 81C systems remaining on a Motorola Call Processor platform and an IGS based switching fabric. This package is not applicable to Option 81C systems that use CPII or Fiber Network Fabric.

Qty	Order code	Description	Qty	Order code	Description
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	2	NTND14BA	CNI to 3PE Cable (5 Ft)
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	2	NTND14BC	CNI to 3PE Cable (12 Ft)

Status
➤ S

AS1241

Description	System Compatibility	Product compatibility	W/S
Option 81C Network Cable Package, 3rd Group	81C		W1

Notes:
- This cable package is for Option 81C system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).
- This cable package is applicable to Option 81C systems remaining on a Motorola Call Processor platform and an IGS based switching fabric. This package is not applicable to Option 81C systems that use CP PII or Fiber Network Fabric

Qty	Order code	Description	Qty	Order code	Description
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	2	NTND14BA	CNI to 3PE Cable (5 Ft)
2	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft)	2	NTND14BC	CNI to 3PE Cable (12 Ft)

Status
➤ S

AS1242

Description	System Compatibility	Product compatibility	W/S
Option 81C Network Cable Package, 4th Group	81C		W1

Notes:
- This cable package is for Option 81C system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).
- This cable package is applicable to Option 81C systems remaining on a Motorola Call Processor platform and an IGS based switching fabric. This package is not applicable to Option 81C systems that use CP PII or Fiber Network Fabric

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	4	NTND14BC	CNI to 3PE Cable (12 Ft)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1243

Description	System Compatibility	Product compatibility	W/S
Option 81C Network Cable Package, 5th Group	81C		W1

Notes:

- This cable package is for Option 81C system using Intergroup Switch Cards (QPC412) or Dual Intergroup Switch Cards (NT5D30).
- This cable package is applicable to Option 81C systems remaining on a Motorola Call Processor platform and an IGS based switching fabric. This package is not applicable to Option 81C systems that use CP PII or Fiber Network Fabric

Qty	Order code	Description	Qty	Order code	Description
4	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft)	2	NTND14BD	CNI to 3PE Cable (12 Ft)
2	NTND14BC	CNI to 3PE Cable (12 Ft)			

Status
➤ S

AS1250

Description	System Compatibility	Product compatibility	W/S
Option 81C Core/Network Group Kit	71; XN; XT		W1

Notes:

- This package is for Option 81C systems wishing to populate the network portion of the Core/Network Modules.
- Systems wishing to deploy this package should be using either QPC412 (IGS) cards or NT5D30 (DIGS) cards within their network modules.
- Customers wishing to equip the Core/Network Module whose systems use NTRB33 cards (FIJI) should order package NTHY21AA, Option 81C Core/Fiber Network Group 0 Kit.
- Network, Conference and Tone and Digit Cards must be ordered separately as required.

Qty	Order code	Description	Qty	Order code	Description
2	NT5D30AA	Dual Intergroup Switch	2	NT8D99AD	CPU or Network to Network Cable (6 Ft)
4	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	2	QPC43R	Peripheral Signaling
2	NT8D80BZ	CPU Interface Cable (5 Ft)	2	QPC441F	Three-Port Extender

Status
➤ B

AS1460

Description	System Compatibility	Product compatibility	W/S
Line-side T1 Interface Assembly (21-81)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:

- Order one P0815404 Line-side T1 Interface NTP (standalone) for each system site being equipped with the Line-side T1 Interface.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D11AE	Line-Side T1 Interface Card	1	NT7R87BA	T1 Link Cable Kit (32 Ft)
1	NT5D13AA	Line-Side T1 Interface Cable			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ B

AS1461

Description	System Compatibility	Product compatibility	W/S
Line-side T1 Interface Assembly (11)	11C; 11E		W1

Notes:

- Order one P0815404 Line-side T1 Interface NTP (standalone) for each system site being equipped with the Line-side T1 Interface.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D13AA	Line-Side T1 Interface Cable	1	NT7R87BA	T1 Link Cable Kit (32 Ft)
1	NT5D14AD	Line-Side T1 Interface Card (Option 11/11E/11C)			

Status
➤ S

AS1500A

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Response Unit-AC Version	11C; 11E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XN; XT		W1

Qty	Order code	Description	Qty	Order code	Description
1	A0660168	Meridian Private-Switch Emergency Response Configuration Software	1	A0660175	Meridian Private-Switch Emergency Response AC Power Supply
1	A0660169	Emergency Response Installation/User Guide	1	A0665488	Meridian Private-Switch Emergency Response Unit
1	A0660170	Meridian Private-Switch Emergency Response Installation Kit			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS1501

Description	System Compatibility	Product compatibility	W/S
Meridian Private-Switch Emergency Notification PC Software	11C X11 R22; 11E X11 R20,21; 51 X11 R15,16,17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R15,16,17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R15,16,17,18,19,20,21; 81 X11 R18,19,20,21; 81C X11 R21,22; NT X11 R14,15,16,17,18,19,20,21; RT X11 R14,15,16,17,18,19,20,21; ST X11 R14,15,16,17,18,19,20,21; STE X11 R18,19,20,21; XN X11 R14,15,16,17,18,19,20,21; XT X11 R14,15,16,17,18,19,20,21		S3

Qty	Order code	Description	Qty	Order code	Description
1	A0660171	Meridian Private-Switch Emergency Notification PC Software	1	A0660173	Meridian Private-Switch Emergency Notification Installation Kit
1	A0660172	Emergency Notification Installation/User Guide			

Status
➤ S

AS7010

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular HVS Package		Meridian Mail EC11; Meridian Mail Modular EC; Meridian Mail Modular Option	W1

Notes:

- For each modem equipped, an additional RS232 port is required. An additional RSM for Modular Option/Options or a Utility for Modular EC/EC11 may be required for additional ports.

Qty	Order code	Description	Qty	Order code	Description
1	A0237451	Cable, Connector (16 Ft) (M/M), TTY RS-232 (5 25m)	1	A0383526	VT520 Video Terminal
1	A0351509	Gender Changer (Female/Female)	1	NTND82AB	RS232 Null Modem Cable (25 Ft)
1	A0376171	Powell DEC Cable			

Status
➤ S

AS7011

Description	System Compatibility	Product compatibility	W/S
DEC Terminal Package		Meridian Mail Card Option	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)	1	A0383526	VT520 Video Terminal
1	A0376171	Powell DEC Cable			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7012

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Networking Modem Package		Meridian Mail EC11; Meridian Mail GP; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Notes:

- For each modem equipped, an additional RS232 port is required. An additional RSM for Modular Option/Options or a Utility for Modular EC/EC11 may be required for additional ports.

Qty	Order code	Description	
2	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
2	NTND91AA	RS232 Straight Cable (10 Ft)	

Status
➤ S

AS7015

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular RSM Package		Meridian Mail Modular Option	W1

Notes:

- The Meridian Mail Modular Option EC/EC11 platform includes a utility card (NT6P42AA) which provides the RSM functionality and requires the NT6P0109 five-port (or NT6P0110 four-port) cable.

Qty	Order code	Description	Qty	Order code	Description
1	A0361136	50 Position EMI Filter & Mounting	1	NT6D4406	RSM Cable
1	NT4R03AB	RS232C Service Module	1	NT9D99AA	RSM Installation Kit - Modular
1	NT4R20AA	RSM Fanout Cable (25 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7021A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Node Expansion 1st Position Package AC		Meridian Mail Modular EC	W1

Notes:

- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 3 node system to 4 nodes, and Shadowed; 2 node system to 3 nodes and 4 node system to 5 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01BA	Meridian Mail EC Module AC	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

AS7021D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Node Expansion 1st Position Package DC		Meridian Mail Modular EC	W1

Notes:

- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 3 node system to 4 nodes, and Shadowed; 2 node system to 3 nodes and 4 node system to 5 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01AA	Meridian Mail EC Module DC	1	P0834803	Installation Instructions (Jumper)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7023A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Node Expansion 2nd Position Package AC		Meridian Mail Modular EC	W1

Notes:

- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 1 node system to 2 nodes and 4 node system to 5 nodes, and Shadowed; 3 node system to 4 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
2	NT6P0123	Backplane to I/O Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

AS7023D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Node Expansion 2nd Position Package DC		Meridian Mail Modular EC	W1

Notes:

- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 1 node system to 2 nodes and 4 node system to 5 nodes, and Shadowed; 3 node system to 4 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
2	NT6P0123	Backplane to I/O Cable	1	P0834803	Installation Instructions (Jumper)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7025

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Node Expansion 3rd Position Package		Meridian Mail Modular Option EC	W1

Notes:

- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- This package is ordered for the following situations: Unshadowed: 2 node system to 3 nodes.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

AS7029

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 2GB Disk Shadowing Prime Node Package		Meridian Mail Modular Option	W1

Notes:

- This package shadows the prime (1st) node and is required if any of the voice nodes (nodes 2-5) are shadowed.
- If the prime node has either an NT6D47AA 300MB disk drive or NT6D48AA 600MB disk drive, then U7207 Meridian Mail Modular Option 2.0GB Disk Drive Upgrade package is required.
- The NT6D48GA 1.0GB Disk/Tape unit will support shadowing an NT6D47BA 300MB disk drive in the prime node.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	1	NT6D54CA	Backplane Stiffener Kit

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7031A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package AC		Meridian Mail Modular EC	W1

Notes:

- This package is used to shadow the first node (prime) in a 3 or 5 node system. To shadow additional nodes, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required for each node shadowed. NOTE: As a prerequisite for shadowing any voice node, the prime node must be shadowed.

Qty	Order code	Description	Qty	Order code	Description
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01BA	Meridian Mail EC Module AC	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive			

Status
➤ S

AS7031D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package DC		Meridian Mail Modular Option EC	W1

Notes:

- This package is used to shadow the first node (prime) in a 3 or 5 node system. To shadow additional nodes, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required for each node shadowed. NOTE: As a prerequisite for shadowing any voice node, the prime node must be shadowed.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01AA	Meridian Mail EC Module DC			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7033A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package AC		Meridian Mail Modular Option EC	W1

Notes:

- This package is used to shadow the first node (prime) in a 4 node system. To shadow additional nodes, an NT6P44BA Meridian Mail Modular Option EC 2.0GB Hard Disk Drive with Power is required for each node shadowed. NOTE: As a prerequisite for shadowing any voice node, the prime node must be shadowed.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	NT8D29AB	Common Equipment Power Supply AC

Status
➤ S

AS7033D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package DC		Meridian Mail Modular Option EC	W1

Notes:

- This package is used to shadow the first node (prime) in a 4 node system. To shadow additional nodes, an NT6P44BA Meridian Mail Modular Option EC 2.0GB Hard Disk Drive with Power is required for each node shadowed. NOTE: As a prerequisite for shadowing any voice node, the prime node must be shadowed.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive

Status
➤ S

AS7037A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 2GB Disk Shadowing Voice Node Package AC		Meridian Mail Modular Option	W1

Notes:

- In voice nodes, if the drive being shadowed is an NT6D47AA (older version of 300MB drive not supported with disk shadowing), then a U7207 Meridian Mail Modular Option Disk Drive Upgrade package will need to be ordered to replace the NT6D47AA.
- The Disk Shadowing Option is not supported on 600MB drives (either as the shadowed or shadowing drive). In voice nodes, if the drive being shadowed is an NT6D48AA 600MB Disk Drive, then a U7207 Meridian Mail Modular Option Disk Drive Upgrade package will need to be ordered to replace the NT6D48AA.
- This package shadows voice nodes 2-5. Order one (1) package for each shadowed voice node. If any of the voice nodes are shadowed, the prime (1st) node must also be shadowed requiring package NT6D48GA.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R01AA	Load Panel Resistors	1	NT6D54CA	Backplane Stiffener Kit
1	NT6D48FA	4 5GB Modular Hard Disk Drive	1	NT8D29AB	Common Equipment Power Supply AC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7037D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 2GB Disk Shadowing Voice Node Package DC		Meridian Mail Modular Option	W1

Notes:

- In voice nodes, if the drive being shadowed is an NT6D47AA (older version of 300MB drive not supported with disk shadowing), then a U7207 Meridian Mail Modular Option Disk Drive Upgrade package will need to be ordered to replace the NT6D47AA.
- The Disk Shadowing Option is not supported on 600MB drives (either as the shadowed or shadowing drive). In voice nodes, if the drive being shadowed is an NT6D48AA 600MB Disk Drive, then a U7207 Meridian Mail Modular Option Disk Drive Upgrade package will need to be ordered to replace the NT6D48AA.
- This package shadows voice nodes 2-5. Order one (1) package for each shadowed voice node. If any of the voice nodes are shadowed, the prime (1st) node must also be shadowed requiring package NT6D48GA.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R01AA	Load Panel Resistors	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6D54CA	Backplane Stiffener Kit

Status
➤ S

AS7043A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Two node Release 9 and later systems support from 16-24 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4419	RS232-Y Cable
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D44AA	Meridian Mail Module AC
1	NT4R10AA	HABC Terminator	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R11AA	ESBC Terminator	1	NT7D06AA	Filler Panel
1	NT4R45AA	MMP40 Processor, Classic	1	NT8D29AB	Common Equipment Power Supply AC
1	NT4R60AA	CRT Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	2	P0803252	Designation Strip
1	NT6D4417	SCSI/Backplane Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4418	SCSI/Daisy Chain Cable	1	QPF23A	Terminating Plug

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7043D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Two node Release 9 and later systems support from 16-24 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4418	SCSI/Daisy Chain Cable
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D4419	RS232-Y Cable
1	NT4R10AA	HABC Terminator	1	NT6D44DC	Meridian Mail Module DC
1	NT4R11AA	ESBC Terminator	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R45AA	MMP40 Processor, Classic	1	NT7D06AA	Filler Panel
1	NT4R60AA	CRT Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D41AD	Common Equipment Power Supply DC	2	P0803252	Designation Strip
1	NT6D4415	DVS Bus Cable (6 Ft)	1	P0834803	Installation Instructions (Jumper)
1	NT6D4417	SCSI/Backplane Cable	1	QPF23A	Terminating Plug

Status
➤ S

AS7044A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Three node Release 9 and later systems support from 28-32 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4419	RS232-Y Cable
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D44AA	Meridian Mail Module AC
1	NT4R60AA	CRT Cable	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D4407	GSP Cable	1	NT7D06AA	Filler Panel

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	Qty	Order code	Description
1	NT6D4409	SCSI Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4410	DVS Bus Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	2	P0803252	Designation Strip
1	NT6D4417	SCSI/Backplane Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4418	SCSI/Daisy Chain Cable	1	QPF23A	Terminating Plug

Status
➤ S

AS7044D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Three node Release 9 and later systems support from 28-32 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4418	SCSI/Daisy Chain Cable
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D4419	RS232-Y Cable
1	NT4R60AA	CRT Cable	1	NT6D44DC	Meridian Mail Module DC
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D4407	GSP Cable	1	NT7D06AA	Filler Panel
1	NT6D4409	SCSI Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4410	DVS Bus Cable	2	P0803252	Designation Strip
1	NT6D4415	DVS Bus Cable (6 Ft)	1	P0834803	Installation Instructions (Jumper)
1	NT6D4417	SCSI/Backplane Cable	1	QPF23A	Terminating Plug

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7045A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Four node Release 9 and later systems support from 36-48 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R45AA	MMP40 Processor, Classic	1	NT7D06AA	Filler Panel
1	NT4R60AA	CRT Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4418	SCSI/Daisy Chain Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D44AA	Meridian Mail Module AC	1	QPF23A	Terminating Plug

Status
➤ S

AS7045D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Four node Release 9 and later systems support from 36-48 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D44DC	Meridian Mail Module DC
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel
1	NT6D41AD	Common Equipment Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4418	SCSI/Daisy Chain Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4419	RS232-Y Cable	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7046A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Five node Release 9 and later systems support from 52-64 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D44AA	Meridian Mail Module AC
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4418	SCSI/Daisy Chain Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4419	RS232-Y Cable	1	QPF23A	Terminating Plug

Status
➤ S

AS7046D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Five node Release 9 and later systems support from 52-64 ports.
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D44DC	Meridian Mail Module DC
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	Qty	Order code	Description
1	NT6D41AD	Common Equipment Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	2	P0803252	Designation Strip
1	NT6D4417	SCSI/Backplane Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4418	SCSI/Daisy Chain Cable	1	QPF23A	Terminating Plug
1	NT6D4419	RS232-Y Cable			

Status
➤ S

AS7047D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- Two node Release 9 and later systems support from 16-24 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D4417	SCSI/Backplane Cable
1	NT4R10AA	HABC Terminator	1	NT6D4419	RS232-Y Cable
1	NT4R11AA	ESBC Terminator	1	NT6D44BA	Meridian Mail Module DC
1	NT4R45AA	MMP40 Processor, Classic	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4407	GSP Cable	2	NT9D18AA	Module Side Cover
2	NT6D4411	DVS Bus Cable (57 Inches)	1	P0803252	Designation Strip

Status
➤ S

AS7048D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- Three node Release 9 and later systems support from 28-32 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R45AA	MMP40 Processor, Classic	1	NT7D06AA	Filler Panel
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	2	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4407	GSP Cable	2	NT9D18AA	Module Side Cover
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D44BA	Meridian Mail Module DC			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7049D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- Four node Release 9 and later systems support from 36-48 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R45AA	MMP40 Processor, Classic	1	NT7D06AA	Filler Panel
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4407	GSP Cable	2	NT9D18AA	Module Side Cover
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D44BA	Meridian Mail Module DC			

Status
➤ S

AS7050D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- Five node Release 9 and later systems support from 52-64 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT7D00BA	Top Cap DC
1	NT4R45AA	MMP40 Processor, Classic	1	NT7D06AA	Filler Panel
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT8D22AC	System Monitor
1	NT6D4407	GSP Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4411	DVS Bus Cable (57 Inches)	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	Qty	Order code	Description
1	NT6D4412	DVS Bus Cable (Internal) (132 Inches)	1	NT8D46BH	System Monitor to MDF Cable (32 Ft)
1	NT6D4417	SCSI/Backplane Cable	1	NT8D49AA	Column Spacer Kit (2 75 In)
1	NT6D4419	RS232-Y Cable	1	NTRD25BA	Pedestal Assembly DC
1	NT6D44BA	Meridian Mail Module DC	2	P0803252	Designation Strip
1	NT6D48FA	4 5GB Modular Hard Disk Drive	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

AS7070D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Spares Package		Meridian Mail Modular GP	W1

Notes:

- This package may only be purchased in conjunction with a new GP System Package, SY70XX.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R04AB	General Purpose Signal Processor	1	NT4R45AA	MMP40 Processor, Classic
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D41BA	Meridian Mail Modular GP Power Supply DC
1	NT4R10AA	HABC Terminator			

Status
➤ S

AS7080

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option EC/EC11 Spares Package 1		Meridian Mail Modular Option EC	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge	1	NT6P42AA	Utility Card without Modem
1	A0633585	Tandberg Tape Drive Cleaning Kit	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC			

Status
➤ S

AS7081

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option EC/EC11 Spares Package 2		Meridian Mail Modular Option EC	W1

Notes:

- This package may only be purchased in conjunction with a new EC system package, SY70XX.

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge	1	NT6P08AA	VP8 Card
1	A0633585	Tandberg Tape Drive Cleaning Kit	1	NT6P42AA	Utility Card without Modem
1	NT6P04AA	VP4 Card	1	NT6P97AA	MMP40 Processor, Modular EC/EC11
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7082

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Alternative Remote Access Package		Meridian Mail EC; Meridian Mail EC11	W1

Qty	Order code	Description	Qty	Order code	Description
1	NT3M50AD	Black Box ABC Switch	1	NTND91AA	RS232 Straight Cable (10 Ft)
1	NT6P42AA	Utility Card without Modem	1	NTND91AB	RS232 Straight Cable (25 Ft)
1	NTND82AA	RS232 Null Modem Cable (10 Ft)			

Status
➤ S

AS7083

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 Spares Package		Meridian Mail EC11	W1

Notes:
- This package may only be purchased in conjunction with a new EC11 system, SY72XX,

Qty	Order code	Description	Qty	Order code	Description
1	NT6P04AA	VP4 Card	1	NTDK35AA	AC/DC Power Supply
1	NT6P42AA	Utility Card without Modem	1	NTRB18AA	MGate Card
1	NT6P97AA	MMP40 Processor, Modular EC/EC11			

Status
➤ S

AS7100

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 1 to 2 Node Expansion Package		Meridian Mail EC11	W1

Notes:
- An Mgate Card is required for every 16 ports of voice mail. Order additional cards as required.
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	NT6P97AA	MMP40 Processor, Modular EC/EC11

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7101

Description	System Compatibility	Product compatibility	W/S
HVS Hardware Package		Meridian Mail Card Option	W1

Notes:

- Meridian Mail Card Option Networking and Meridian Mail HVS require configuration engineering.
- When Networking is equipped with HVS it applies only to staff mailboxes.
- Both hardware and software are required for Meridian Mail Card Option HVS. A VT420 compatible terminal such as the AS7011 DEC Terminal Package must be purchased separately.
- Meridian Mail Card Option Network Message Services and Meridian Mail Card Option HVS are mutually exclusive on pre-Meridian Mail 11 systems.

Qty	Order code	Description	Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)	2	NTAK36AA	Peripheral Cable Female
1	A0379350	25 Pair Double Ended Cable	1	NTAK37AA	Peripheral Cable Male
1	A0379351	25 Pair Single Ended Cable	1	NTND93AA	Null Modem Adapter
1	NTAK18BA	RS232C Service Module			

Status
➤ S

AS7108

Description	System Compatibility	Product compatibility	W/S
4 Port Full Service Voice Processing Package, EC/EC11		Meridian Mail EC R10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:

- Required for Meridian Mail EC, EC11 Release 9 and later, full service voice processing.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P04AA	VP4 Card	4	SW7063	Meridian Mail Full Service per Port Software

Status
➤ S

AS7109

Description	System Compatibility	Product compatibility	W/S
4 Port Basic Service Voice Processing Package, EC/EC11		Meridian Mail EC R10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:

- Required for Meridian Mail EC, EC11 Release 9 and later, basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those service previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P04AA	VP4 Card	4	SW7064	Meridian Mail Basic Service per Port Software

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7110

Description	System Compatibility	Product compatibility	W/S
8 Port Full Service Voice Processing Package, EC/EC11		Meridian Mail EC R10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:

- Required for Meridian Mail EC, EC11 Release 9 and later, full service voice processing.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P08AA	VP8 Card	8	SW7063	Meridian Mail Full Service per Port Software

Status
➤ S

AS7111

Description	System Compatibility	Product compatibility	W/S
8 Port Basic Service Voice Processing Package, EC/EC11		Meridian Mail EC R10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:

- Required for Meridian Mail EC, EC11 Release 9 and later, basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those service previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P08AA	VP8 Card	8	SW7064	Meridian Mail Basic Service per Port Software

Status
➤ S

AS7112

Description	System Compatibility	Product compatibility	W/S
4 Port Full Service Voice Processing Package, Modular GP		Meridian Mail Modular Option GP R10,11,12	W1

Notes:

- Required for Meridian Mail Modular Option GP Release 9 and later, full service voice processing.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R04AB	General Purpose Signal Processor	4	SW7063	Meridian Mail Full Service per Port Software

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7113

Description	System Compatibility	Product compatibility	W/S
4 Port Basic Service Voice Processing Package, Modular GP		Meridian Mail Modular Option GP R10,11,12	W1

Notes:

- Required for Meridian Mail Modular Option GP Release 9 and later, basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those services previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R04AB	General Purpose Signal Processor	4	SW7064	Meridian Mail Basic Service per Port Software

Status
➤ S

AS7114

Description	System Compatibility	Product compatibility	W/S
4 Port Full Service Voice Processing Package, Options		Meridian Mail Modular Option R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10	W1

Notes:

- Required for Meridian Mail Modular Option, ST/RT, NT/XT Release 9 and later, full service voice processing.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R01AC	Network Voice Processor	4	SW7063	Meridian Mail Full Service per Port Software

Status
➤ S

AS7115

Description	System Compatibility	Product compatibility	W/S
4 Port Basic Service Voice Processing Package, Options		Meridian Mail Modular Option R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10	W1

Notes:

- Required for Meridian Mail Modular Option, ST/RT, NT/XT Release 9 and later, basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those services previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R01AC	Network Voice Processor	4	SW7064	Meridian Mail Basic Service per Port Software

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

AS7116

Description	System Compatibility	Product compatibility	W/S
4 to 8 Port Full Service Voice Processing Expansion Package, EC/EC11		Meridian Mail EC; Meridian Mail EC11	W1

Notes:

- This package is required for existing Meridian Mail EC/EC11 systems that have a VP4 card with associated Port License Fees equipped and require a VP8 in place of the existing VP4.
- This package may only be purchased for existing systems.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P08AA	VP8 Card	4	SW7063	Meridian Mail Full Service per Port Software

Status
† ➤ S

AS7117

Description	System Compatibility	Product compatibility	W/S
4 to 8 Port Basic Service Voice Processing Expansion Package, EC/EC 11		Meridian Mail EC; Meridian Mail EC11	W1

Notes:

- This package is required for existing Meridian Mail EC/EC11 systems that have a VP4 card with associated Port License Fees equipped and require a VP8 in place of the existing VP4.
- This package may only be purchased for existing systems.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an existing Meridian 1 system the Meridian 1 Serial number must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P08AA	VP8 Card	4	SW7064	Meridian Mail Basic Service per Port Software

Status
➤ S

AS7120

Description	System Compatibility	Product compatibility	W/S
2 Port Full Service Voice Processing Package, Card Option		Meridian Mail Card Option R10,11,12	W1

Notes:

- Required for Meridian Mail Card Option Release 9 and later, full service voice processing.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an exsiting Option 11C Site ID must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK16AB	C25 Voice Processor Card	2	SW7105	Meridian Mail Card Option Full Service Port License Fee

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7121

Description	System Compatibility	Product compatibility	W/S
2 Port Basic Service Voice Processing Package, Card Option		Meridian Mail Card Option R9,10,11	W1

Notes:

- Required for Meridian Mail Card Option Release 9 and later, basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those services previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an exsiting Option 11C Site ID must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK16AB	C25 Voice Processor Card	2	SW7150	Meridian Mail Basic Service per Port License Fee

Status
➤ S

AS7122

Description	System Compatibility	Product compatibility	W/S
6-8 Port Full Service Voice Processing Expansion Package, Card Option		Meridian Mail Card Option R10,11,12	W1

Notes:

- Required for Meridian Mail Card Option Release 9 and later, full service voice processing.
- This package is used when expanding the Card Option from 6 to 8 ports.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an exsiting Option 11C Site ID must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK15AB	Digital Voice Processor Card	2	SW7105	Meridian Mail Card Option Full Service Port License Fee
1	NTAK17BB	Meridian Mail Card Option Base Package, 8-12 Ports			

Status
➤ S

AS7123

Description	System Compatibility	Product compatibility	W/S
6-8 Port Basic Service Voice Processing Expansion Package, Card Option		Meridian Mail Card Option R10,11,12	W1

Notes:

- Required for Meridian Mail Card Option Release 9 and later when expanding from 6 to 8 ports, provides 2 ports of basic service voice processing. Basic services include: Access (custom IVR), Announcements, Time-of-day Controllers, Thru-dial, Voice Prompt Maintenance, Remote Activation and Voice Menus. Voice Menus can only consist of those services previously mentioned, if any mailboxes are equipped, full service voice processing is required.
- The Meridian Mail serial number must be provided if ordering this code for addition to an existing Meridian Mail. If this code is ordered as part of a new Meridian Mail system being installed with an exsiting Option 11C Site ID must be provided.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK15AB	Digital Voice Processor Card	2	SW7150	Meridian Mail Basic Service per Port License Fee
1	NTAK17BB	Meridian Mail Card Option Base Package, 8-12 Ports			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7200

Description	System Compatibility	Product compatibility	W/S
Dual Port DTI/PRI Package	21; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- This assembly package includes cables to equip both ports of the Dual Port NT5D12AA.
- Clock controller cables and D channel handler cables should be ordered separately if required.
- Order one (1) P0833777 NT5D12 Dual Port DTI/PRI card NTP for each system type being equipped with the Dual Port DTI/PRI card.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D12AG	Dual Port DTI/PRI (DDP) Card	2	QCAD133A	PRI/DTI I/O Cable (50 Ft)
1	NT5D16BA	Meridian 1 Trunk Tip/Ring Cable (8 Ft)			

Status
➤ S

AS7201

Description	System Compatibility	Product compatibility	W/S
Dual Port DTI/PRI Package (Cabinet)	NT; XT		W1

Notes:

- This assembly package includes cables to equip both ports of the Dual Port NT5D12AA.
- Clock controller cables and D channel handler cables should be ordered separately if required.
- Order one (1) P0833777 NT5D12 Dual Port DTI/PRI card NTP for each system type being equipped with the Dual Port DTI/PRI card.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D12AG	Dual Port DTI/PRI (DDP) Card	2	P0643763	Filter, PRI/DTI I/O
1	NT5D16EA	Meridian 1 Trunk Tip/Ring Cable (8 Ft) NT, XT	2	QCAD133A	PRI/DTI I/O Cable (50 Ft)

Status
➤ S

AS7202

Description	System Compatibility	Product compatibility	W/S
Dual Port DTI/PRI Package (ST, STE, RT)	RT; ST; STE		W1

Notes:

- This assembly package includes cables to equip both ports of the Dual Port NT5D12AA.
- Clock controller cables and D channel handler cables should be ordered separately if required.
- Order one (1) P0833777 NT5D12 Dual Port DTI/PRI card NTP for each system type being equipped with the Dual Port DTI/PRI card.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D12AG	Dual Port DTI/PRI (DDP) Card	2	QCAD133A	PRI/DTI I/O Cable (50 Ft)
1	NT5D16DA	Meridian 1 Trunk Tip/Ring Cable (8 Ft) ST, STE, RT			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7505

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SEE Spares Kit	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; XT	Meridian MAX AM; Meridian MAX-SEE	W1

Notes:

- One spares kit can be located at the Meridian MAX site or alternatively can be located at the distributor premises and cover more than one site within a geographical area. Not included but recommended for consideration as an additional spare item is the MVME147 Processor Card (with the memory configurations appropriate for the systems being supported). Also recommended are the NT7D62DA 240 MByte Hard Disk/155 MByte Tape Drive Assembly (for the SEE running Meridian MAX Release 6.19 or earlier software and for the DEE) and the NT7D62AC 1.2 GByte Hard Disk/155 MByte Tape Drive Assembly (for the SEE running Meridian MAX software later than Release 6.19). Refer to the Merchandise section of the Application Products - Call Center Chapter in Book 1.

Qty	Order code	Description	Qty	Order code	Description
1	A0351167	MVME712AM Transition Card with Built-in Modem (for MVME147)	1	NT6D51AA	Transition Card (for MVME332)
2	A0352271	150 MByte Data Cassette Tape	1	NT8D96BE	VME Multi-Port Cable
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card			

Status
➤ S

AS7506

Description	System Compatibility	Product compatibility	W/S
ACD-MAX/NAC to Meridian MAX-IPEE/ NAC 2 Data Conversion Kit	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; NAC	W1

Notes:

- The software data conversion kit can be reused for multiple system upgrades.
- Requires ACD-MAX to Meridian MAX-IPE/IPEE or ACD-NAC (NAC 1) to Meridian NAC 2 upgrade software and hardware. Consult the Call Center Chapter of this catalog.

Qty	Order code	Description	Qty	Order code	Description
1	A0378469	SCSI Cable	1	NTAK1305	SCSI Cable (6 Ft)
1	A0721902	Tandberg Tape Drive Unit - External			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS7512

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Option 1 to Option 2 Expansion Package		Meridian MAX-SEE	W1

Notes:

- A cable is required between Meridian MAX and a Dual Port SDI Paddle Board (NT8D41) for the High Speed Link and Configuration Control Feature if enabled, the appropriate length (NT8D83AJ,W) cable must be ordered.
- A cable is required between Meridian Max and an SDI Card (QPC139) or a 4 Port SDI Card (QPC841) for the High Speed Link and Configuration Control Feature if enabled, the appropriate length (NT7D58AB,D,F,L,T,V) cable must be ordered.
- An A0351509 Gender Changer (F/F) is required for each supervisor terminal and printer connected to Meridian MAX system.
- A (NT7D58AB,D,F,L,T,V) SDI Cable is required when connecting a PC running Reflections 4+ as a color workstation to Meridian MAX.
- Requires Meridian MAX Release 4 Option 1 to Option 2 Software Expansion (SW7512A).

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	3	NT8D96BE	VME Multi-Port Cable

Status
➤ S

AS7534

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Option 3 to Option 4 Expansion Package		Meridian MAX AM	W1

Notes:

- A cable is required between Meridian MAX and a Dual Port SDI Paddle Board (NT8D41) for the High Speed Link and Configuration Control Feature if enabled, the appropriate length (NT8D83AJ,W) cable must be ordered.
- A cable is required between Meridian Max and an SDI Card (QPC139) or a 4 Port SDI Card (QPC841) for the High Speed Link and Configuration Control Feature if enabled, the appropriate length (NT7D58AB,D,F,L,T,V) cable must be ordered.
- An A0351509 Gender Changer (F/F) is required for each supervisor terminal and printer connected to Meridian MAX system.
- A (NT7D58AB,D,F,L,T,V) SDI Cable is required when connecting a PC running Reflections 4+ as a color workstation to Meridian MAX.
- If Meridian MAX upgrade modules are housed more than 3 feet apart, the following cables are required: Ethernet Cable, 12 ft. (NT7D47AG) and Dual Module Interface Cable, 12 ft. (NT7D97AG).
- Requires Meridian MAX Release 4 Option 3 to Option 4 Software Expansion (SW7534A).

Qty	Order code	Description	Qty	Order code	Description
2	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	6	NT8D96BE	VME Multi-Port Cable

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

AS8600

Description	System Compatibility	Product compatibility	W/S
17 In. Color X-Terminal with DEC Style Keyboard			W1

Notes:
- Includes 12MB of RAM.
- Requires Ethernet Cable NT7D47BA or BB to connect to Meridian IVR.

Qty	Order code	Description	Qty	Order code	Description
1	A0609634	NCX17 Color Monitor	1	A0609639	DEC Style Keyboard
1	A0609635	NCX17 Base	1	A0609641	Mouse

Status
➤ S

E1201A

Description	System Compatibility	Product compatibility	W/S
Column Expansion Package AC	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Notes:
- To be used with Merchandise Orders requiring factory configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D00AA	Top Cap AC	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D22AC	System Monitor	1	NTRD25AA	Pedestal Assembly AC

Status
➤ S

E1201D

Description	System Compatibility	Product compatibility	W/S
Column Expansion Package DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Notes:
- To be used with Merchandise Orders requiring factory configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D00BA	Top Cap DC	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D22AC	System Monitor	1	NTRD25BA	Pedestal Assembly DC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

MVC01561

Description	System Compatibility	Product compatibility	W/S
Connector Hardware Package (50 Conductor)	LE (23, 96); M; MS; N; NT; XL (24, 97); XN; XT		W1

Notes:
- Each package contains mounting hardware for seven (7) (50 conductor) cables.

Status
† ➤ S

MVC01562

Description	System Compatibility	Product compatibility	W/S
Connector Hardware Package (25 Conductor)	LE (23, 96); M; MS; N; NT; RT; S; ST; STE; XL (24, 97); XN; XT		W1

Notes:
- Each package contains mounting hardware for two (2) (25 conductor) cables.

Status
➤ S

NT0961AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Pentium 24 Port Card	11C; 51C; 61C; 81; 81C		W1

Notes:
- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- ISDN/ISL software SW0051 (contains packages 145 and 147) is required.
- Requires an unused D-Channel port on the SDI/D-CH card for Option 11C, and on the MSDL card for large systems.
- Requires Release 25 or greater.
- ITG card occupies 2 slots on the IPE shelf.

Status
➤ S

NT0962AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 486 Software Upgrade PCMCIA Card	11C; 51C; 61C; 81; 81C		W0

Notes:
- Optional - PCMCIA card is only ordered when the customer needs an up-issue and does not have access to the Internet website for software download (This order code is specifically for ITG 8-port trunk card upgraded to have ITG 2.0 ISDN functionality).
- The ITG Security Device ID is requiared when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT0963AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Pentium Software Upgrade PCMCIA Card	11C; 51C; 61C; 81; 81C		W0

Notes:
- Optional - PCMCIA card is only ordered when the customer needs an up-issue and does not have access to the Internet website for software download.
- The ITG Security Device ID is requiared when ordering this code.

Status
➤ S

NT0C09EA03

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Black (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2250; M2317; M2616; M3000	W1

Notes:
- Is not compatible with M2006 (NT2K05XXXX) and M2008 (NT2K08XXXX).

Status
➤ S

NT0C09EA35

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Ash (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2250; M2317; M2616; M3000	W1

Notes:
- Is not compatible with M2006 (NT2K05XXXX) and M2008 (NT2K08XXXX).

Status
➤ S

NT0C09EA93

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Gray (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2250; M2317; M2616; M3000	W1

Notes:
- Is not compatible with M2006 (NT2K05XXXX) and M2008 (NT2K08XXXX).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT0C09EL-93

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Gray (NT2K & NT9K Models M2006, M2008, M2616, M2216 ACD-1)		M2006; M2008; M2216 ACD-1; M2616	W1

Notes:
- Is not compatible with M2006 (NTZK06XXXX), M2008 (NTZK08XXXX) and M2616 (NTZK16XXXX).

Status
➤ S

NT0C09EL03

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Black (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)		M2006; M2008; M2216 ACD-1; M2616	W1

Notes:
- Is not compatible with M2006 (NTZK06XXXX), M2008 (NTZK08XXXX) and M2616 (NTZK16XXXX).

Status
➤ S

NT0C09EL35

Description	System Compatibility	Product compatibility	W/S
Legacy Handset, Ash (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)		M2006; M2008; M2216 ACD-1; M2616	W1

Notes:
- Is not compatible with M2006 (NTZK06XXXX), M2008 (NTZK08XXXX) and M2616 (NTZK16XXXX).

Status
➤ S

NT0R71AA

Description	System Compatibility	Product compatibility	W/S
-48volt Rectifier	21; 21A; 21E; 51; 61; 61C; 71; 81; RT; ST; STE		W1

Notes:
- This product will not be available until October 1, 1994. Until this date, this products predecessor is still available for ordering. Refer to the Manufacture Retired section for details.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT0R72AA

Description	System Compatibility	Product compatibility	W/S
-52volt Rectifier	21; 21E; 51; 61; 61C		W1

Notes:
- This product will not be available until October 1, 1994. Until this date, this products predecessor is still available for ordering. Refer to the Manufacture Retired section for details.

Status
➤ S

NT0X21AV

Description	System Compatibility	Product compatibility	W/S
System 600/48 & MPP 600 Seismic Anchor	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Notes:
- Order 4 NT0X21AV per Main Cabinet or Supplemental Cabinet.

Status
➤ S

NT1F09AC

Description	System Compatibility	Product compatibility	W/S
Asynchronous Data Option (M2009, M2112, M2018, M2317)		M2009; M2018; M2112; M2317	W1

Notes:
- Equipped with Power Supply.

Status
➤ S

NT1F21AE03

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone, Black	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1F21AE35

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone, Ash	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

Status
➤ S

NT1F21AE93

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone, Gray	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

Status
➤ S

NT1F21ME03

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone with Data, Black	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1F21ME35

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone with Data, Ash	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

Status
➤ S

NT1F21ME93

Description	System Compatibility	Product compatibility	W/S
Meridian M2317 Intelligent Telephone with Data, Gray	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XL; XN; XT		W1

Notes:
- Requires Option Group 88, Meridian Digital Telephones and Option 91, Meridian M2317 Intelligent Telephone.
- Option 11 Note: Includes an external power supply.

Status
➤ Δ S

NT1F27EB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software Package 1C			W1/ S3

Notes:
- For MCA ordering, please refer to the notes section of NT2K69AA

Status
➤ S

NT1F57AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 1 (1-50 Agents)			W2

Notes:
- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1F57BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 1 (51-100 Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and Symposium TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires Symposium TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

Status
➤ S

NT1F57CA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 1 (101-200 Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SymposSYMPOSIUM ium TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

Status
➤ S

NT1F57DA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 1 (201 + Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1F58AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 2 (1-50 Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

Status
➤ S

NT1F58BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 2 (51-100 Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

Status
➤ S

NT1F58CA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 2 (101-200 Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1F58DA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Package 2 (201 + Agents)			W2

Notes:

- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and MSL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- Pentium PC/16MB of RAM/CD-ROM Drive.

Qty	Order code	Description	Qty	Order code	Description
1	P0877952	SYMPOSIUM Agent Quick Reference Guide			

Status
➤ S

NT1F80AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Upgrade - Package 1 to 2			W2/ S1

Qty	Order code	Description	Qty	Order code	Description
1	NT1F86AA	Symposium Agent Upgrade Package 1 to Package 2 - Base Software			

Status
➤ Δ S

NT1F97AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 12 Voice Messaging Package (VMUIF)			W0

Qty	Order code	Description	Qty	Order code	Description
15	P0875942	Meridian Mail Release 12 Voice Messaging (VMUIF) User Guide	15	P0875944	Meridian Mail Release 12 Voice Messaging (VMUIF) "At A Glance" Cards
15	P0875943	Meridian Mail Release 12 Voice Messaging (VMUIF) Quick Reference Cards			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1P61CA

Description	System Compatibility	Product compatibility	W/S
Fiber Superloop Network Card	21E; 51; 51C; 61; 61C; 71; 81	Fiber Remote	W0

Status
➤ S

NT1P62EA

Description	System Compatibility	Product compatibility	W/S
Fiber Remote Peripheral Controller Card	21E; 51; 51C; 61; 61C; 71; 81	Fiber Remote	W1

Status
➤ S

NT1P63CA

Description	System Compatibility	Product compatibility	W/S
Electro-Optical Interface Packlet	21; 21E; 51; 51C; 61; 61C; 71; 81	Fiber Remote	W1

Status
➤ S

NT1P6501

Description	System Compatibility	Product compatibility	W/S
Two Optical Adaptors Kit		Fiber Remote	W1

Status
➤ S

NT1P6601

Description	System Compatibility	Product compatibility	W/S
Four Optical Adaptors Kit		Fiber Remote	W1

Status
➤ S

NT1P75AA

Description	System Compatibility	Product compatibility	W/S
EOI to I/O Panel Optical Cable (Single Mode)		Fiber Remote	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1P75BA

Description	System Compatibility	Product compatibility	W/S
EOI to I/O Panel Optical Cable (Multi Mode)		Fiber Remote	W0

Status
➤ S

NT1P76AA

Description	System Compatibility	Product compatibility	W/S
Fiber Superloop to System Monitor & SDI Cable		Fiber Remote	W1

Status
➤ S

NT1P78AA

Description	System Compatibility	Product compatibility	W/S
Fiber Controller to System Monitor & SDI Cable		Fiber Remote	W1

Status
➤ S

NT1P79AA

Description	System Compatibility	Product compatibility	W/S
EOI to Fiber Management Optical Cable (Single Mode)		Fiber Remote	W1

Status
➤ S

NT1P79BA

Description	System Compatibility	Product compatibility	W/S
EOI to Fiber Management Optical Cable (Multi Mode)		Fiber Remote	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1P84AA

Description	System Compatibility	Product compatibility	W/S
Power Cable	11; 11E	Fiber Remote	W1

Status
➤ S

NT1P85AA

Description	System Compatibility	Product compatibility	W/S
Auxiliary Cable	11; 11E	Fiber Remote	W1

Status
➤ B

NT1P87AA

Description	System Compatibility	Product compatibility	W/S
Remote Cable Kit		Fiber Remote	W1

Status
➤ S

NT1R03AA

Description	System Compatibility	Product compatibility	W/S
Shielded 4-Port Octopus Cable with Ethernet		Meridian MAX-IPE	W1

Notes:
- The 4-Port Octopus Cable has female connectors.

Status
➤ S

NT1R03BA

Description	System Compatibility	Product compatibility	W/S
Shielded 4-Port Octopus Cable without Ethernet		Meridian MAX-IPE	W1

Notes:
- The 4-Port Octopus Cable has female connectors.

Status
➤ S

NT1R03CA

Description	System Compatibility	Product compatibility	W/S
Extension Cable (2 Ft.)	11	Meridian MAX-IPE	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R03DB

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/Male (2 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE Module to connect supervisor terminals, printers, Application Module link (AML) connection, Serial Data Interface (SDI) connection, Meridian Link host connection, Host Enhanced Voice Processing connection, and external modem connection.

Status
➤ S

NT1R03DC

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/Male (4 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE Module to connect supervisor terminals, printers, Application Module link (AML) connection, Serial Data Interface (SDI) connection, Meridian Link host connection, Host Enhanced Voice Processing connection, and external modem connection.

Status
➤ S

NT1R03DF

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/Male (10 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE Module to connect supervisor terminals, printers, Application Module link (AML) connection, Serial Data Interface (SDI) connection, Meridian Link host connection, Host Enhanced Voice Processing connection, and external modem connection.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R03DP

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/Male (25 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE Module to connect supervisor terminals, printers, Application Module link (AML) connection, Serial Data Interface (SDI) connection, Meridian Link host connection, Host Enhanced Voice Processing connection, and external modem connection.

Status
➤ S

NT1R03DV

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/Male (45 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE Module to connect supervisor terminals, printers, Application Module link (AML) connection, Serial Data Interface (SDI) connection, Meridian Link host connection, Host Enhanced Voice Processing connection, and external modem connection.

Status
➤ S

NT1R03EB

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/ Female (2 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE module to connect supervisor terminals and printers.

Status
➤ S

NT1R03EC

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/ Female (4 Ft.)		Meridian MAX-IPE	W1

Notes:

- For use with the Meridian Link & CCR-IPE module to connect supervisor terminals and printers.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R03EF

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/ Female (10 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with the Meridian Link & CCR-IPE module to connect supervisor terminals and printers.

Status
➤ S

NT1R03EP

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/ Female (25 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with the Meridian Link & CCR-IPE module to connect supervisor terminals and printers.

Status
➤ S

NT1R03EV

Description	System Compatibility	Product compatibility	W/S
Straight Through RS232 Cable Male/ Female (45 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with the Meridian Link & CCR-IPE module to connect supervisor terminals and printers.

Status
➤ S

NT1R03FP

Description	System Compatibility	Product compatibility	W/S
MDF 50 Pin Cable with Ethernet (25 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with Meridian MAX-IPE to connect supervisor terminals and printers via the MDF.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R03FV

Description	System Compatibility	Product compatibility	W/S
MDF 50 Pin Cable with Ethernet (45 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with Meridian MAX-IPE to connect supervisor terminals and printers via the MDF.

Status
➤ S

NT1R03GP

Description	System Compatibility	Product compatibility	W/S
MDF 50 Pin Cable without Ethernet (25 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with Meridian MAX-IPE to connect supervisor terminals and printers via the MDF.

Status
➤ S

NT1R03GV

Description	System Compatibility	Product compatibility	W/S
MDF 50 Pin Cable without Ethernet (10 Ft.)		Meridian MAX-IPE	W1

Notes:
- For use with Meridian MAX-IPE to connect supervisor terminals and printers via the MDF.

Status
➤ S

NT1R03HF

Description	System Compatibility	Product compatibility	W/S
Modem Cable		Meridian MAX-IPE	W1

Status
➤ S

NT1R04AA

Description	System Compatibility	Product compatibility	W/S
Clock Controller to I/O Panel Cable	81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R05AA

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Clock Reference Cable	81		W1

Status
➤ S

NT1R16BB

Description	System Compatibility	Product compatibility	W/S
Meridian IVR Audio Line Interface Kit		Meridian IVR; Meridian Mail	W1

Notes:

- Provides an interface between standard audio equipment (i.e., audio cassette tape deck, reel-to-reel tape deck) and a Meridian modular telephone, allowing voice prompt recordings to be transferred to Meridian Mail for Voice Menus and/or Meridian IVR applications.
- Includes one (1) headset (binaural) with miniature phone plug.

Qty	Order code	Description	Qty	Order code	Description
1	A0601094	Headset with 1/4 phone plug	1	NT1R16AA	Audio Line Interface Cable

Status
➤ S

NT1R20AB

Description	System Compatibility	Product compatibility	W/S
Intelligent OPS Line Card	11; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT1R29AA

Description	System Compatibility	Product compatibility	W/S
Next Generation Connectivity			S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code as an addition to an existing Meridian 1 System.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT1R31AA

Description	System Compatibility	Product compatibility	W/S
NAC Release 2 Documentation Package (English)	11; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:
- This documentation package is for the base NAC Release 2 software.
- User Guide Supplement P0886656 (ordered separately), when added to this documentation package, provides complete documentation for NAC Release 2.5 software.

Status
➤ Δ S

NT1R37AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 8 Complete Documentation Package	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:
- This package includes one Meridian MAX Release 8 Technical Documentation Package, one Meridian MAX Release 8 Supervisors User Guide, one Meridian MAX 8 Upgrade Guide.

Status
➤ Δ S

NT1R39AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 8 NTPs (English)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:
- This package is a boxed-set of two books: Book 1 553-4001-111 Installation Guide, 553-3201-200 Application Equipment Module (AEM) Installation; Book 2 553-4001-811 Meridian MAX Maintenance and Diagnostics Guide.

Status
➤ Δ S

NT1R49AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 8 Supervisors User Guide	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:
- This package includes one Meridian MAX Release 8 Supervisors User Guide.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT1R59AA

Description	System Compatibility	Product compatibility	W/S
Symposium Call Center Server - Next Generation			S1

Notes:

- The Meridian 1 serial number must be provided when ordering this code as an addition to an existing Meridian 1 System.

Status
➤ S

NT1R75AA

Description	System Compatibility	Product compatibility	W/S
MTE Release 5 Software (Single User) for DOS	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX R5,6	S3

Notes:

- Provides quantity of one (1) MTE software for installation on a PC. Software is supplied on high density diskettes in the 3.5 or 5.25 inch format.
- Can be used in lieu of Reflections 4+.
- Is required on each PC connected to the Meridian MAX via LAN Connectivity.
- Installation of SW0074A is a prerequisite.
- Meridian MAX Release 6 requires MTE Version 5.31 or higher.
- MTE Release 5 software requires the following: MAX 5.27 or later software on the MAX Module, DOS 5.0 or later operating system on the supervisors PC. The MAX Module must be equipped with the Meridian MAX MTE one-time Enable Fee (SW0074A). For use within a LAN environment, very specific requirements must be met. Please refer to the MAX 5, 6, or 7 NTPs for details of LAN connectivity requirements. These include: PC/TCP Release 3.0 or 2.X LAN software for DOS must be installed on the supervisors PC, the MAX Module must also be equipped with the Meridian MAX LAN one-time Connectivity Fee (SW0072A) one per system) and the Meridian MAX LAN Connectivity Software (SW0073A, one per LAN-based supervisor workstation.
- Required on each PC connected to the Meridian MAX via LAN Connectivity.
- Software is supplied on both 3-1/2 and 5-1/4 inch floppy disks.
- MTE Release 5 software requires the following: FTP Software Inc. PC/TCP kernel for DOS 2.05 or higher, an ODI,NDIS or Packet Driver compatible Ethernet LAN card or MS-DOS version 5 or higher, for Meridian MAX Release 6 or earlier, the MAX Module must be equipped with Meridian MAX MTE one-time Enable Fee (SW0074A), for Meridian MAX Release 7, the MAX module must be equipped with "Enhanced" level software, or equivalent upgrade from earlier systems, for use within a LAN environment, the MAX Module operating at Release 6 or earlier must be equipped with the Meridian MAX LAN one-time Connectivity Fee (SW0072A) and the Meridian MAX LAN Connectivity Software (one per LAN-based supervisor workstation, SW0073A), for MAX 7 systems, the MAX module must be equipped with "Enhanced" level software, or equivalent upgrade from earlier systems.
- Reference the MAX 5 Ordering Guide for third party ordering details.
- The NT1R75AA is the DOS Version of Meridian Terminal Emulator (MTE). If you require MTE which is Windows compatible, you must substitute the code NT1R75BA when you place your order. The price for the NTR75BA (Window version) is the same as for the NT1R75AA (DOS version).
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0748127	MTE Documentation			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT1R76BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 6 Capacity Configurator Tool		Meridian MAX	W1

Notes:

- Microsoft Excel 4.0 is a prerequisite to run this Configuration Tool. This tool works on a PC or a Macintosh and is available in 3.5" floppy disk.
- Order when configuring the Meridian MAX Release 6 Flexible Capacity Configuration Feature.
- This is an Excel for Windows program designed to assist distributors in configuring their customers data profile for the Meridian MAX.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R7603	Meridian MAX Release 6 Capacity Calculator Tool PC Disk	1	P0803569	Meridian MAX Release 6 Capacity Calculator Tool Documentation
1	NT1R7604	Meridian MAX Release 6 Capacity Calculator Tool Mac Disk			

Status
➤ Δ S

NT1R76EB

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9.3 Capacity Configuration Tool	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX	W1

Notes:

- Microsoft Excel 4.0 or later is a prerequisite to run this Configuration Tool. This tool works on an Intel-compatible PC and is available on a 3.5" floppy disk.
- Order when configuring the Meridian MAX Release 9 Flexible Capacity Configuration Feature.
- This is an Excel for Windows program designed to assist distributors in configuring their customers data profile for the Meridian MAX.
- Diskette contains user guide file in Adobe Acrobat .pdf format.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R7620	Meridian MAX Release 9 Capacity Configuration Tool Software Assembly, PC Diskette			

Status
➤ S

NT1R89AA

Description	System Compatibility	Product compatibility	W/S
IPE Cardcage Expansion Kit (AC)	81C		W1

Status
➤ S

NT1R89BA

Description	System Compatibility	Product compatibility	W/S
IPE Cardcage Expansion Kit (DC)	81C		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT1R93AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 7 Complete Documentation Package		Meridian MAX	W0

Notes:

- This package includes one Meridian MAX Release 7 Technical Documentation Package, one Meridian MAX Release 7 Supervisors User Guide and one Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX Release 3 through 6.

Status
➤ Δ S

NT1R94AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 7 Technical Documentation Package		Meridian MAX	W0

Notes:

- This package includes one Meridian MAX Overview, One Meridian MAX 7 Installation Guide, one Application Equipment Module Installation guide and one Meridian MAX 7 Maintenance & Diagnostics Guide.

Status
➤ Δ S

NT1R95AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 7 Supervisors User Guide		Meridian MAX	W0

Notes:

- This package includes one Meridian MAX Release 7 Supervisors User Guide.

Status
➤ Δ S

NT1R98EA

Description	System Compatibility	Product compatibility	W/S
MTE Release 8 User Guide (Multilingual: English, French, Spanish, German); Package of 10	11; 11C; 11E; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian CCR	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NT2F09AA

Description	System Compatibility	Product compatibility	W/S
Alternate User Interface 1 User Guide (15 per Package)			W0

Qty	Order code	Description	Qty	Order code	Description
15	P0884614	Alternate User Interface 1 User Guides			

Status
✓ ➤ Δ S

NT2F20AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Modular Option Manual			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904484	Modular Option Site and Installation & Planning Guide - MM13	1	P0904485	Modular Option Installation and Maintenance Guide - MM13

Status
➤ Δ S

NT2F21AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Modular Option GP Manual			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13

Status
✓ ➤ Δ S

NT2F22AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Modular Option EC Manuals			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT2F23AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Option 11 EC (EC11) Manual			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904490	Option 11 EC (EC11) Site and Installation Planning Guide - MM13	1	P0904491	Option 11 EC (EC11) Installation and Maintenance Guide - MM13

Status
➤ Δ S

NT2F24AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Voice Messaging Package (15 Per Package)			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904495	Voice Messaging User Guide - MM13	1	P0904496	Voice Messaging Quick Reference Card - MM13

Status
✓ ➤ Δ S

NT2F25AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 CD ROM Package (NTP)		Meridian Mail	W0

Status
✓ ➤ Δ S

NT2F26AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Call Answering (VMUIF) Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904923	Call Answering User Guide (VMUIF) - MM13	1	P0904924	Call Answering Quick Reference Card (VMUIF) - MM13

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NT2F27AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Voice Messaging (VMUIF) Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0904925	Voice Messaging User Guide (VMUIF) - MM13	1	P0904926	Voice Messaging Quick Reference Guide (VMUIF) Package - MM13

Status
➤ Δ S

NT2F59AA

Description	System Compatibility	Product compatibility	W/S
Application License Kit			W1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code.
- A quantity of one (1) must be ordered for all initial orders of SYMPOSIUM Agent 2, SYMPOSIUM WebResponse Server 2 or SYMPOSIUM TAPI Service Provider (or any combination thereof) for Meridian 1, DMS-Centrex and SL-100.
- The System ID number must be provided for any subsequent SYMPOSIUM Agent 2, SYMPOSIUM WebResponse Server 2 or SYMPOSIUM TAPI Service Provider orders for DMS-Centrex and SL-100.

Status
➤ Δ S

NT2F60AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent 2 Base Software			S2

Notes:

- This base software (media package) must initially be ordered in conjunction with NT2F61AA, NT2F61BA, NT2F61CA, NT2F61DA or NT2F61EA.
- For Meridian 1 requires X11 Release 22 or higher and SYMPOSIUM TAPI Service Provider Release 2 or higher.
- For DMS-100, DMS-500, and Meridian SL-100 requires SYMPOSIUM TAPI Driver for CompuCall or ICM.
- For every new order of SYMPOSIUM Agent or SYMPOSIUM WebResponse Server, the Application License Kit (NT2F59AA) must be added. For all subsequent DMS-Centrex and SL-100 orders of SYMPOSIUM Agent or SYMPOSIUM WebResponse Server, the System ID number must be provided to the customer service rep when placing the order.
- Client: Pentium PC/16MB of RAM/CD-ROM Drive.
- Server: Requires Windows NT Server 4 or above.

Qty	Order code	Description	Qty	Order code	Description
1	NT1F85AC	Symposium Agent 2 0 Media Package	1	P0890127	Symposium TAPI Service Provider and Symposium Agent License Files
1	P0879837	Symposium Agent 2 0 - Sybase RTU			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2F62AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM WebResponse Server 2 Basic Package			S2

Notes:

- Includes 5 clients and software.
- A quantity of one (1) must be ordered for all initial orders of SYMPOSIUM Agent 2, SYMPOSIUM WebResponse Server 2 or SYMPOSIUM TAPI Service Provider (or any combination thereof) for Meridian 1, DMS-Centrex and SL-100.
- The System ID number must be provided for any subsequent SYMPOSIUM Agent 2, SYMPOSIUM WebResponse Server 2 or SYMPOSIUM TAPI Service Provider orders for DMS-Centrex and SL-100.

Qty	Order code	Description	Qty	Order code	Description
1	NT2F73AA	Symposium WebResponse Server 2 PEP			

Status
➤ S

NT2F64CA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM WebResponse Server 2 Replacement Package			S2

Qty	Order code	Description	Qty	Order code	Description
1	NT2F73AA	Symposium WebResponse Server 2 PEP			

Status
➤ S

NT2F65AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Upgrade Package 1 to Symposium Agent 2			S2

Notes:

- A quantity of one (1) must be ordered for each agent.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2F65BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Upgrade Package 2 to SYMPOSIUM Agent 2			S2

Notes:
- A quantity of one (1) must be ordered for each agent.

Status
➤ Δ S

NT2F77AA

Description	System Compatibility	Product compatibility	W/S
External Alerter and Recording Interface User Guide (M3900 Series, Package of 15 P0903793)		M3902; M3903; M3904; M3905	W1

Status
✓ ➤ S

NT2F78AA

Description	System Compatibility	Product compatibility	W/S
Feature Card Label Sheet (M3901, Package of 25 P0906396)		M3901	W1

Notes:
- Each sheet contains 8 English labels.

Status
§ Δ S

NT2F7901

Description	System Compatibility	Product compatibility	W/S
Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627) N/C		M3901; M3902; M3903; M3904	W1

Notes:
- Available with new system orders only; up to the number of sets included with the order.

Status
✓ § ➤ Δ S

NT2F7903

Description	System Compatibility	Product compatibility	W/S
Meridian M3901, 2,3,4 User Guide Release 2, (Package of 5 P0987180) No Charge		M3901; M3902; M3903; M3904	W1

Notes:
- Available with new system orders only; up to the number of sets included with the order.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ Δ S

NT2F79AA

Description	System Compatibility	Product compatibility	W/S
Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627)		M3901; M3902; M3903; M3904	W1

Status
➤ Δ S

NT2F79AB

Description	System Compatibility	Product compatibility	W/S
Meridian M3901, 2,3,4 User Guide, Release 2 (Package of 5 P0987180)		M3901; M3902; M3903; M3904	W1

Status
✓ § Δ S

NT2F8001

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 User Guide Release 1 (Package of 15 P0903629) N/C		M3905	W1

Notes:
- Available with new system orders only; up to the number of sets included with the order.

Status
✓ § ➤ Δ S

NT2F8003

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 User Guide (Package of 5 P0907181) No Charge		M3905	W1

Notes:
- Available with new system orders only; up to the number of sets included with the order.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ Δ S

NT2F80AA

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 User Guide, Release 1 (Package of 15 P0903629)		M3905	W1

Status
✓ ➤ Δ S

NT2F80AB

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 User Guide (Package of 5 P0907181)		M3905	W1

Status
Δ S

NT2F81AA

Description	System Compatibility	Product compatibility	W/S
Meridian M3900 Series Quick Reference Guide, Release 1 (Package of 15 P0903628)		M3902; M3903; M3904	W1

Status
➤ Δ S

NT2F81AB

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Series Quick Reference Guide, Release 2 (Package of 15 P0907178)		M3902; M3903; M3904	W1

Status
Δ S

NT2F82AA

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Quick Reference Guide, Release 1 (Package of 15 P0903630)		M3905	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

NT2F82AB

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Quick Reference Guide (Package of 15 P0907179)		M3905	W1

Status
✓ ➤ S

NT2F83AA

Description	System Compatibility	Product compatibility	W/S
Telephone Number Sheet (M3900 Series, Package of 15 P0888695)		M3901; M3902; M3903; M3904; M3905	W1

Notes:
- Each sheet contains 28 English labels and 28 French labels.

Status
➤ S

NT2F84AA

Description	System Compatibility	Product compatibility	W/S
Clear Window Menu Cover, M3901, Package of 15		M3901	W1

Notes:
- Each package contains 15 menu covers.

Status
➤ S

NT2K03BA

Description	System Compatibility	Product compatibility	W/S
Key Expansion Module Cable, (M2000 Series)			W0

Notes:
- Required for Key Expansion Modules installed on M2616 (NT2K16GXXX and higher) telephones.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2K10WD

Description	System Compatibility	Product compatibility	W/S
Power Supply Board, (M2000 Series NT2K65 and NT2K40)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:

- Requires 110 Volt wall transformer or a closet power source supplied from an outside vendor. For details, please refer to Sales and Marketing Bulletin #590-G, June 1990. NT2K10WD vintage adds P0723443 cable for use with NT2K Meridian Digital Telephones manufactured after June 1995.

Status
➤ S

NT2K28AB03

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Black (10 Language)			W1

Notes:

- If purchased for M2008 (NTZK08AA03), requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA03 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Replaces Special Applications Display and provides functionality required when ACD screen and Hospitality screen enhancements are required with M2008 and M2616 Telephones.

Status
➤ S

NT2K28AB35

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Ash (10 Language)			W1

Notes:

- If purchased for M2008 (NTZK08AA35), requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA35 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Replaces Special Applications Display and provides functionality required when ACD screen and Hospitality screen enhancements are required with M2008 and M2616 Telephones.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2K28AB93

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Gray (10 Language)			W1

Notes:

- If purchased for M2008 (NTZK08AA93), requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA93 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Replaces Special Applications Display and provides functionality required when ACD screen and Hospitality screen enhancements are required with M2008 and M2616 Telephones.

Status
➤ S

NT2K28AD03

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Black (3 Language)			W1

Notes:

- If purchased for M2008 (NTZK08AA03) requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA35 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Equipped as standard with M2216ACD Telephones.

Status
➤ S

NT2K28AD35

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Ash (3 Language)			W1

Notes:

- If purchased for M2008 (NTZK08AA03) requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA35 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Equipped as standard with M2216ACD Telephones.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2K28AD93

Description	System Compatibility	Product compatibility	W/S
Meridian Display Option, Gray (3 Language)			W1

Notes:
- If purchased for M2008 (NTZK08AA03) requires Power Supply Board purchased separately and Transformer 110V (A0367335) if not closet powered. If purchased for M2008 (NT2K08GA35 and later) the Power Supply Board and Transformer 110V/closet power is not required.
- Equipped as standard with M2216ACD Telephones.

Status
➤ S

NT2K28KB-03

Description	System Compatibility	Product compatibility	W/S
Meridian Japanese Display Option, Black		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Status
➤ S

NT2K28KB-35

Description	System Compatibility	Product compatibility	W/S
Meridian Japanese Display Option, Ash		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Status
➤ S

NT2K28KB-93

Description	System Compatibility	Product compatibility	W/S
Meridian Japanese Display Option, Gray		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Status
➤ B

NT2K40WA

Description	System Compatibility	Product compatibility	W/S
External Alerter Interface (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Requires Power Supply Board, purchased separately.
- Option 11 Note: Requires a Transformer, 110V (A0367335).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ B

NT2K65XR

Description	System Compatibility	Product compatibility	W/S
Meridian Communications Adapter (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Requires Power Supply Board, purchased separately.

Status
➤ S

NT2K68AA

Description	System Compatibility	Product compatibility	W/S
Analog Terminal Adapter (ATA) (M2000 Series)		M2006; M2008; M2008HF; M2216 ACD-1; M2616	W1

Notes:
- Requires X11 Release 22 or later software.
- Compatible with Meridian Modular Telephones (M2006, M2008, M2008HF, M2616, M2216ACD)
- In addition to the ATA, Meridian Modular Telephones with a date code prior to May 6,1998 require Jumper Kit (NT2K71AA) and ATA/MCA Footstand (NT2K83AA for M2006/M2008/M2008HF, or NT2K83BA for M2616/M2216ACD Telephones).
- Requires ATA/MCA Transformer (A0688664), ordered separately.
- Cannot be used in conjunction with the Meridian Communications Adapter (MCA).
- Does not support wall mount configuration.
- Does not support the use of Key Expansion Module(s).

Status
➤ B

NT2K69AA

Description	System Compatibility	Product compatibility	W/S
Meridian Communications Adapter (MCA) (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- This version of the Meridian Communications Adapter requires the modified footstand for Meridian Modular Telephones. The modified footstand is standard on all Meridian Modular Telephones with a date code May 6, 1998 or later.
- In addition to the MCA, Meridian Modular Telephones with a date code prior to May 6,1998 require Jumper Kit (NT2K71AA) and ATA/MCA Footstand (NT2K83AA for M2006/M2008/M2008HF, or NT2K83BA for M2616/M2216ACD Telephones).
- Requires ATA/MCA Transformer (A0688664), ordered separately.
- Cannot be used in conjunction with the Analog Terminal Adapter (ATA).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2K71AA

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Jumper Kit			W1

Notes:
- Required when installing an ATA (NT2K68AA) or MCA (NT2K69AA) on Meridian Modular Telephones with a date code prior to May 6, 1998.

Status
➤ S

NT2K83AA03

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Black (M2006, M2008, M2008HF)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2006, M2008 and M2008HF) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6,1998 or later.

Status
➤ S

NT2K83AA35

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Ash (M2006, M2008, M2008HF)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2006, M2008, and M2008HF) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6, 1998 or later.

Status
➤ S

NT2K83AA93

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Gray (M2006, M2008, M2008HF)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2006, M2008, and M2008HF) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6, 1998 or later.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT2K83BA03

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Black (M2616, M2216ACD)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2616 and M2216ACD) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6, 1998 or later.

Status
➤ S

NT2K83BA35

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Ash (M2616, M2216ACD)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2616 and M2216ACD) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6, 1998 or later.

Status
➤ S

NT2K83BA93

Description	System Compatibility	Product compatibility	W/S
ATA/MCA Footstand, Gray (M2616, M2216ACD)			W1

Notes:
- Compatible with Meridian Modular Telephones (M2616 and M2216ACD) used with ATA or MCA (NT2K65 or NT2K69).
- Not for use with Key Expansion Module(s).
- Standard on Meridian Modular Telephones with a date code of May 6, 1998 or later.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ B

NT2R81AA

Description	System Compatibility	Product compatibility	W/S
MAXcaster Software and Documentation Package English		Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Support on Meridian MAX Release 4 and Release 6 and later.
- Windows NT 3.51 or NT 4.0 Workstation required. If used on an NT 4.0 Workstation, a patch to the MAXcaster application is required.
- MAXcaster Security Key Included.

Qty	Order code	Description	Qty	Order code	Description
1	NT2R8103	MAXcaster Patch Disk for Windows NT 4 0	1	NT2R83AA	MAXcaster Documentation English
1	NT2R82AA	MAXcaster Software English (set of six disks)			

Status
➤ B

NT2R81BA

Description	System Compatibility	Product compatibility	W/S
MAXcaster Software and Documentation Package French		Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Support on Meridian MAX Release 4 and Release 6 and later.
- Windows NT 3.51 or NT 4.0 Workstation required. If used on an NT 4.0 Workstation, a patch to the MAXcaster application is required.
- MAXcaster Security Key Included.

Qty	Order code	Description	Qty	Order code	Description
1	NT2R8103	MAXcaster Patch Disk for Windows NT 4 0	1	NT2R83BA	MAXcaster Documentation French
1	NT2R82BA	MAXcaster Software French (set of six disks)			

Status
➤ S

NT3G30AA35

Description	System Compatibility	Product compatibility	W/S
Adjustable Stand (M2250/M1250)		M1250; M2250	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT3G40BB35

Description	System Compatibility	Product compatibility	W/S
Busy Lamp Field/Console Graphics Module		M1250; M2250	W1

Notes:
- Requires X11 Release 14 for M1250 Attendant Console or Release 15 for M2250 Attendant Console.
- A transformer (A0367601) is required.

Status
S

NT3M50AD

Description	System Compatibility	Product compatibility	W/S
Black Box ABC Switch		Meridian Mail EC11 R10; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
† ➤ S

NT3R12AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - 12-Port Loopstart Voice Port Assembly		Open IVR R2	W1

Notes:
- This package is compatible with OPEN IVR 2.01 and 2.5 MRSs and MRS/APs, including those upgraded to OPEN IVR 4.0.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- Network Interfaces (i.e. Loopstart, T1, E1) cannot be mixed within a single MRS/AP, MRS Tower, and MRS Rack system.
- This assembly can be used to expand the MRS/AP, MRS Tower, or MRS Rack Base Runtime or Development System (12 ports loopstart), e.g. NT3R11AA and NT3R10AA. The maximum capacity for a Runtime MRS/AP System is 36 ports loopstart. The maximum capacity for a MRS/AP Development System is 24 ports loopstart.
- This assembly cannot be added to an MRS/AP, MRS Tower or MRS Rack system containing the 4-port loopstart voice port assembly.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0650996	OIVR 2 x Hardware - 12-port Loopstart Network Interface Module	1	A0657730	OIVR 2 x Hardware - Loopstart Interface Cable (DB25F to RJ23X)
1	A0651035	OIVR 2 x Hardware - 12-port Voice Processing Card	12	P0809333	IVR Generator 2 0/S Runtime RTU License (per port)
1	A0657566	OIVR 2 x Hardware - 10 position Connector PEB Cable	12	P0809334	MRS Version 3 0 RTU License (per port)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT3R23AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/AP or AP Ethernet LAN Interface		IVR; Open IVR R2	W1

Notes:

- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- Cabling and connectors are provided for a thinnet Ethernet LAN connection. Cabling/Connectors for other Ethernet LAN connection (e.g. Thickwire or 10BaseT) must be provided by the customer.
- This package is used only to provide a spare LAN card for OPEN IVR 2.01 and 2.5 APs and MRS/APs, including those upgraded to OPEN IVR 4.0, or to provide a separate LAN card for IPML (originally known as CCIP).

Qty	Order code	Description	Qty	Order code	Description
1	A0368824	Ethernet Tee Connector (Thinnet)	1	NT7D47BA	Ethernet Cable (Thinnet 50 Ft) and Terminator
1	A0638565	IVR PCI Ethernet Controller			

Status
† ➤ Δ S

NT3R23BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/AP or AP Token Ring LAN Interface		Meridian IVR R2	W1

Notes:

- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- Cabling, connectors, and hub equipment is not provided for a Token Ring LAN connection. The customer is responsible for providing this equipment.
- This package is used only to provide a spare LAN card for OPEN IVR 2.01 and 2.5 APs and MRS/APs, including those upgraded to OPEN IVR 4.0.

Status
➤ S

NT3R28AA

Description	System Compatibility	Product compatibility	W/S
Voice Prompt/Database Editor for Run-Time Systems Only		IVR R2.2,2.08; Meridian IVR	S3

Notes:

- Required on Run-time systems for editing of Voice Prompts or local database.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0902553	Voice Prompt/Database Editor RTU			

Status
➤ Δ S

NT3R51AA

Description	System Compatibility	Product compatibility	W/S
IVR Operational Documentation Package		Meridian IVR R2	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT3R52AA

Description	System Compatibility	Product compatibility	W/S
IVR Development Documentation Package		Meridian IVR R2	W0

Status
➤ S

NT3R67AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS System Recovery Software Ethernet		Open IVR	W0/ S3

Notes:

- The customer must order either MRS System Recovery Software Ethernet (NT3R67AA) or MRS System Recovery Software Token Ring (NT3R67BA) when ordering an MRS System.
- The MRS System Recovery Software must match the network interface type (i.e. ethernet or token ring) chosen for the MRS system.
- The IVR ID number must be provided when ordering this code.
- The IVR ID number must be provided when ordering this code.

Status
➤ S

NT3R67BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS System Recovery Software Token Ring		Open IVR	W0/ S3

Notes:

- The customer must order either MRS System Recovery Software Ethernet (NT3R67AA) or MRS System Recovery Software Token Ring (NT3R67BA) when ordering an MRS System.
- The MRS System Recovery Software must match the network interface type (i.e. ethernet or token ring) chosen for the MRS system.
- The IVR ID number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT3R71AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Net Gateway	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian Mail Card Option R11,12; Meridian Mail EC R11,12; Meridian Mail EC11 R11,12; Meridian Mail Modular GP R11,12; Meridian Mail Modular Option R11,12	W1

Notes:

- Requires a customer provided NT server.
- Meridian Mail Net Gateway is required at each Meridian Mail site for digital networking.
- Prerequisites are: Meridian Mail Release 11 or 12 and Meridian Mail Networking/Enterprise Networking software.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail system.

Qty	Order code	Description	Qty	Order code	Description
1	A0671761	DIALOGIC 4 VOICE BOARD	1	NT3R96AA	MM NET GATEWAY application CD-ROM PKG
1	A0678907	PC Dongle	1	P0870325	MM Net Gateway Documentation

Status
➤ S

NT3R75AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2.X Hardware - MRS/Tower or MRS/Rack Ethernet Lan Interface		Open IVR R2	W1

Notes:

- The customer must order either an MRS Ethernet Network Controller (NT3R75AA) or an MRS Token Rink Network Controller (NT3R75BA) when ordering an MRS system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 Software.
- The same network interface type (i.e. ethernet or token ring) must be purchased for the Application Processor.

Status
➤ S

NT3R75BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Tower or MRS/Rack Token Ring LAN Interface		Open IVR R2	W1

Notes:

- The customer must order either an MRS Ethernet Network Controller (NT3R75AA) or an MRS Token Rink Network Controller (NT3R75BA) when ordering an MRS system.
- The same network interface type (i.e. ethernet or token ring) must be purchased for the Application Processor.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT3R76AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware Fax Support - 2 Ports		Open IVR R2	S3

Notes:

- Fax resources are sharable only across a single PEB bus within an MRS system and a PEB bus can support a maximum of 24 ports. Resources must be ordered for each PEB bus that requires access to the resource. For example, if a system has two PEB buses, at least two fax boards would have to be ordered to provide fax resources to all the channels in the system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- This package is compatible with OPEN IVR 2.01 and 2.5 MRSs and MRS/APs, including those upgraded to OPEN IVR 4.0.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0638229	Fax Support (2 Channels)	1	NTZK84AB	MRS Version 3 FAX Option Software
1	NTZK84AA	MRS FAX Option Software			

Status
S

NT3R76BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware Fax Support - 4 Ports		Open IVR R2	S3

Notes:

- Fax resources are sharable only across a single PEB bus within an MRS system and a PEB bus can support a maximum of 24 ports. Resources must be ordered for each PEB bus that requires access to the resource. For example, if a system has two PEB buses, at least two fax boards would have to be ordered to provide fax resources to all the channels in the system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- This package is compatible with OPEN IVR 2.01 and 2.5 MRSs and MRS/APs, including those upgraded to OPEN IVR 4.0.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0638231	Fax Support (4 Channels)	1	NTZK84AB	MRS Version 3 FAX Option Software
1	NTZK84AA	MRS FAX Option Software			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NT3R76CA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware Fax Support - 8 Ports		Open IVR R2	S3

Notes:

- Fax resources are sharable only across a single PEB bus within an MRS system and a PEB bus can support a maximum of 24 ports. Resources must be ordered for each PEB bus that requires access to the resource. For example, if a system has two PEB buses, at least two fax boards would have to be ordered to provide fax resources to all the channels in the system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- This package is compatible with OPEN IVR 2.01 and 2.5 MRSs and MRS/APs, including those upgraded to OPEN IVR 4.0.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0638233	Fax Support (8 Channels)	1	NTZK84AB	MRS Version 3 FAX Option Software
1	NTZK84AA	MRS FAX Option Software			

Status
† ➤ S

NT3R77AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Discrete Speech Recognition - 4 Ports		Open IVR R2	S3

Notes:

- Speech Recognition resources are sharable only across a single PEB bus within an MRS system and a PEB bus can support a maximum of 24 ports. Resources must be ordered for each PEB bus that requires access to the resource. For example, if a system has two PEB buses, then at least two VR boards would have to be ordered to provide VR resources to all the channels in the system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- In order for discrete and continuous speech recognition to coexist in the same MRS system they must be installed on separate PEBs.
- This package is compatible with OPEN IVR 2.01 and 2.5 only.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0639210	Discrete Voice Recognition (4 Ports)	1	NTZK79AA	MRS Speech Recognition Option Software
1	NT3R60AA	MRS Discrete Speech Recognition North American Vocabularies	1	NTZK79AB	MRS Version 3 Speech Recognition Software

Status
† ➤ S

NT3R77BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Discrete Speech Recognition - 4 Port Expansion		Open IVR R2	S3

Notes:

- This package is compatible with OPEN IVR 2.01 and 2.5 only.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- In order for discrete and continuous speech recognition to coexist in the same MRS system they must be installed on separate PEBs.
- Discrete Speech Recognition is expandable in increments of four (4) ports up to a maximum of 12 ports per board.
- The IVR ID number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT3R78AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Continuous Speech Recognition - 2 Ports		Open IVR R2	S3

Notes:

- Speech Recognition resources are sharable only across a single PEB bus within an MRS system and a PEB bus can support a maximum of 24 ports. Resources must be ordered for each PEB bus that requires access to the resource. For example, if a system has two PEB buses, then at least two VR boards would have to be ordered to provide VR resources to all the channels in the system.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- In order for discrete and continuous speech recognition to coexist in the same MRS system they must be installed on separate PEBs.
- This package is compatible with OPEN IVR 2.01 and 2.5 only.
- The IVR ID number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0639559	Continuous Voice Recognition (2 ports)	1	NTZK79AB	MRS Version 3 Speech Recognition Software
1	NTZK79AA	MRS Speech Recognition Option Software			

Status
† ➤ S

NT3R78BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Continuous Speech Recognition 2 Port Expansion		Open IVR R2	S3

Notes:

- This package is compatible with OPEN IVR 2.01 and 2.5 only.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- In order for discrete and continuous speech recognition to coexist in the same MRS system they must be installed on separate PEBs.
- Continuous Speech Recognition is expandable in increments of two (2) ports up to a maximum of 6 ports per board.
- The IVR ID number must be provided when ordering this code.

Status
† ➤ S

NT3R79BA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Text-to-Speech 4 Port Expansion		Open IVR R2	S3

Notes:

- Text-to-Speech is expandable in increments of four (4) ports up to a maximum of 16 ports per board.
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.
- This package is compatible with OPEN IVR 2.01 and 2.5 only.
- The IVR ID number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ Δ S

NT3R83AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Voice and Data Storage (1GB) for MRS/AP or AP		Open IVR R2	W1

Notes:

- The 1GB drive can store approximately 96 hours of voice storage at a sampling rate of 24 kbs. These disks do not have operating system software installed on them. This is the reason for the difference in storage between the base system disk drives and these optional drives. The MRS/AP can have one additional disk drive in the system. The MRS/AP can have a maximum of two disks.
- Compatible only with OPEN IVR 2.X hardware running OPEN IVR 2.X software.
- This package is used only for disk storage expansion and sparing and is compatible with OPEN IVR 2.01 and 2.5 only.
- It cannot be used in conjunction with disk mirroring.

Status
➤ ⊗ S

NT4N43AA

Description	System Compatibility	Product compatibility	W/S
cPCI Multi-Media Disk Unit	81C		W1

Notes:

- Requires X11 Release 25 and later base software and Software Options 299 and 368.

Status
➤ ⊗ S

NT4N46AA

Description	System Compatibility	Product compatibility	W/S
cPCI Core/Network Card Cage AC/DC	81C 3311 R25		W1

Status
➤ S

NT4N50AA

Description	System Compatibility	Product compatibility	W/S
Power Distribution Unit DC	11; 21; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; VL; VLE; XL; XN; XT		W1

Notes:

- A0391740 - StarTalk Documentation Kit should be ordered separately.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ S

NT4N65AB

Description	System Compatibility	Product compatibility	W/S
cPCI Core Network Interface Card (2 Ports)	81C		W1

Notes:
- Requires X11 Release 25 and later base software and Software Options 299 and 368.
- Requires one NT4N66AA cPCI CNI Transition Card for each NT4N65AA cPCI Core Network Interface Card (2 Ports) added to the NT4N41 cPCI Core/Network Module.
- This card is compatible for connection to NTRB33AA Fiber Junctor Interface Card (FIJI) as well as NT5D30AA Dual Intergroup Switch cards and QPC412 Intergroup Switch cards.

Status
✓ ➤ ⊗ S

NT4N66AB

Description	System Compatibility	Product compatibility	W/S
cPCI Core Network Interface Transition Card	81C		W1

Notes:
- Used with NT4N65AA cPCI Core Network Interface Card (2 Port).

Status
➤ ⊗ S

NT4N67AA

Description	System Compatibility	Product compatibility	W/S
cPCI System Utility Card	81C		W1

Notes:
- Requires X11 Release 25 and later base software and Software Options 299 and 368.
- Requires one NT4N68AA cPCI System Utility Transition Card if not already equipped in the NT4N41 cPCI Core/Network Module.

Status
➤ ⊗ S

NT4N6809

Description	System Compatibility	Product compatibility	W/S
Security Device Holder			W1

Notes:
- Supported on systems with CP PII Call Processors and cCNI Backplanes only.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NT4N68AA

Description	System Compatibility	Product compatibility	W/S
cPCI System Utility Transition Card	81C		W1

Notes:
- Used with NT4N67AA cPCI System Utility Card.

Status
⊗ S

NT4N88AA

Description	System Compatibility	Product compatibility	W/S
CP PII to I/O Panel DtE Cable (48 In.)	81		W0

Status
⊗ S

NT4N88BA

Description	System Compatibility	Product compatibility	W/S
CP PII to I/O Panel DCE Cable (48 In.)	81		W0

Status
⊗ Δ S

NT4N90AA

Description	System Compatibility	Product compatibility	W/S
CP PII to I/O Panel Ethernet Cable (48 In.)	81		W0

Status
➤ ⊗ S

NT4N93AA

Description	System Compatibility	Product compatibility	W/S
MMDU Data Cable for Floppy Drive	81C 3311 R25		W1

Status
➤ ⊗ S

NT4N95AA

Description	System Compatibility	Product compatibility	W/S
MMDU Power Cable	81C 3311 R25		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NT4N96AA

Description	System Compatibility	Product compatibility	W/S
cCNI to I/O Panel Cable (2 Ft.)	81C 3311 R25		W1

Status
➤ ⊗ S

NT4N97AA

Description	System Compatibility	Product compatibility	W/S
cPCI Upgrade Kit AC	81C 3311 R25		W1

Status
➤ ⊗ S

NT4N97BA

Description	System Compatibility	Product compatibility	W/S
cPCI Upgrade Kit DC	81C 3311 R25		W1

Status
➤ S

NT4R01AC

Description	System Compatibility	Product compatibility	W/S
Network Voice Processor		Meridian Mail Modular Option R8; Meridian Mail Option S R8; Meridian Mail Option X R8; Meridian Mail Options (NT/XT) R8; Meridian Mail Options (ST/RT) R8	W1

Notes:
- Required for Pre-Release 9 systems or spares only.
- Options ST/RT, NT/XT, S and X systems cannot expand beyond 20 ports.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT4R03AB

Description	System Compatibility	Product compatibility	W/S
RS232C Service Module		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NT4R04AB

Description	System Compatibility	Product compatibility	W/S
General Purpose Signal Processor		Meridian Mail GP R8	W0

Notes:
- Required for Pre-Release 9 systems or spares only.

Status
† ➤ S

NT4R08AA

Description	System Compatibility	Product compatibility	W/S
HABC (High Availability Bus Controller)		Meridian Mail GP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Status
† ➤ S

NT4R10AA

Description	System Compatibility	Product compatibility	W/S
HABC Terminator		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT4R11AA

Description	System Compatibility	Product compatibility	W/S
ESBC Terminator		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Status
➤ S

NT4R20AA

Description	System Compatibility	Product compatibility	W/S
RSM Fanout Cable (25 Ft.)		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NT4R20AB

Description	System Compatibility	Product compatibility	W/S
RSM Cable (50 Ft.)		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT4R2102

Description	System Compatibility	Product compatibility	W/S
Dual Network/Intra-Connection Cable (Cantilever)		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NT4R28BA

Description	System Compatibility	Product compatibility	W/S
Tandberg Tape Drive Unit Options (ST/RT, NT/XT)		Meridian Mail Options (NT/XT) R8,9,10; Meridian Mail Options (ST/RT) R8,9,10	W1

Notes:

- A Tape Drive Cleaning Kit (A0633585) must be ordered separately. Optional 2.5 GB Backup data cartridges (A0630697) may also be purchased as required.

Status
† ➤ S

NT4R35AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Bus Cable - Two Nodes		Meridian Mail GP; Meridian Mail Option X	W1

Status
† ➤ S

NT4R36AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Bus Cable - Five Nodes		Meridian Mail GP; Meridian Mail Option X	W1

Status
† ➤ S

NT4R37AA

Description	System Compatibility	Product compatibility	W/S
RSM Alarm Adapter Cable		Meridian Mail GP; Meridian Mail Option X	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT4R45AA

Description	System Compatibility	Product compatibility	W/S
MMP40 Processor, Classic		Meridian Mail Modular Option R9; Meridian Mail Modular Option GP R9; Meridian Mail Options (NT/XT) R9; Meridian Mail Options (ST/RT) R9	W1

Notes:
- Requires Meridian Mail Release 9.5 or later software.

Status
† ➤ S

NT4R58AB

Description	System Compatibility	Product compatibility	W/S
RSM Cable		Meridian Mail MP; Meridian Mail Option S; Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
† ➤ S

NT4R59AA

Description	System Compatibility	Product compatibility	W/S
CSL Cable		Meridian Mail MP; Meridian Mail Option S; Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
† ➤ S

NT4R60AA

Description	System Compatibility	Product compatibility	W/S
CRT Cable		Meridian Mail MP; Meridian Mail Option S; Meridian Mail Options (ST/RT); Meridian Mail SP	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT4R61AA

Description	System Compatibility	Product compatibility	W/S
NVP Daisychain Cable		Meridian Mail MP; Meridian Mail Option S; Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NT5C06CC

Description	System Compatibility	Product compatibility	W/S
MPR25E Modular Power Rectifier, 25 Amps		MFA150	W1

Status
➤ S

NT5C07AC

Description	System Compatibility	Product compatibility	W/S
50 Amp Rectifier		J2412A (QCA13); MPP600	W1

Notes:
- J2412A(QCA13) Power Systems must use the AS1204D 50 Amp Rectifier Expansion Package.

Status
➤ S

NT5C10CC1

Description	System Compatibility	Product compatibility	W/S
MPS75 Modular Power Shelf, 75 Amps		MFA150	W1

Status
➤ S

NT5C11BC

Description	System Compatibility	Product compatibility	W/S
MFA150 Battery Tray		MFA150	W1

Status
➤ S

NT5C12AC

Description	System Compatibility	Product compatibility	W/S
MPS150 Modular Power Shelf 23" Rackmount	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5D03FB

Description	System Compatibility	Product compatibility	W/S
68060 Enhanced 128MB Call Processor			W1

Notes:

- This call processor is supported on Options 51C, 61C systems and 81 and 81C systems with less than six network groups.
- This call processor is recommended for use with Option 51C and 61C systems.
- This processor requires X11 Release 24 or higher.
- Option 61C and 81/81C systems require two identical call processors with the same memory configuration.
- Software Generic 2811 is required if this call processor is used on Option 51C.
- Software Generic 2911 is required if this call processor is used on Option 61C.
- Software Generic 3011 is required if this call processor is used on Option 81 or 81C.
- Feature package number 298 is required if this call processor is used on an Option 81.
- Feature package number 299 is required if this call processor is used on an Option 81C.

Status
➤ S

NT5D03PB

Description	System Compatibility	Product compatibility	W/S
68060 Enhanced 160MB Call Processor			W1

Notes:

- The 68060E 160MB Call Processor is supported on Option 51C, 61C, 81 and 81C systems.
- This call processor is recommended for Option 81 and 81C systems.
- This processor requires X11 Release 24 and higher software.
- Option 61C, 81 and 81C systems require two identical processors with the same memory configuration.
- Software generic 2811 is required if this call processor is used on Option 51C.
- Software generic 2911 is required if this call processor is used on Option 61C.
- Software generic 3011 is required if this call processor is used on Option 81 or 81C.
- Feature package number 298 is required if this call processor is used on an Option 81.
- Feature package number 299 is required if this call processor is used on an Option 81C.

Status
➤ S

NT5D11AE

Description	System Compatibility	Product compatibility	W/S
Line-Side T1 Interface Card	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81		W0

Notes:

- Order one NT5D13AA Line-Side Interface Cable for each NT5D11AE card. Order one P0809479 Line-Side T1 Interface NTP (Standalone) for each system site being equipped with the Line-Side T1 Interface.
- Add one NT7R87BA (T1 Link Cable Kit) if extension of NT5D13 Line-Side T1 Cable is required for connection to auxiliary T1 compatible equipment.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ B

NT5D12AG

Description	System Compatibility	Product compatibility	W/S
Dual Port DTI/PRI (DDP) Card	21; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; STE; XT		W1

Notes:

- The dual port DDP is a single-slot circuit card that provides two ports, each of which is configurable in any combination of 24 DTI channels or 23 B+D PRI channels. The DDP replaces one (1) QPC414 ENET plus two (2) QPC720 PRI/DTI packs providing equivalent functionality. An optional dual-port daughterboard (NTBK51AA) is used for PRI applications as an alternative to existing external D-channel handler packs and associated cables.

Status
➤ S

NT5D13AA

Description	System Compatibility	Product compatibility	W/S
Line-Side T1 Interface Cable	11; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81		W0

Notes:

- One cable is required for each NT5D11AA or NT5D14AA Line-Side T1 Interface Card.
- Add one NT7R87BA (T1 Link Cable Kit) if extension of NT5D13 Line-side T1 Cable is required for connection to auxiliary T1 compatible equipment.

Status
➤ S

NT5D14AD

Description	System Compatibility	Product compatibility	W/S
Line-Side T1 Interface Card (Option 11/ 11E/11C)	11		W1

Notes:

- Order one NT5D13AA Line-Side Interface Cable for each NT5D14AD card. Order one P0809479 Line-Side T1 Interface NTP (Standalone) for each system site being equipped with the Line-Side T1 interface.
- Add one NT7R87BA (T1 Link Cable Kit) if extension of NT5D13 Line-Side T1 cable is required for connection to auxiliary T1 compatible equipment.

Status
➤ S

NT5D16EA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Trunk Tip/Ring Cable (8 Ft.) NT, XT	NT; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5D19AA

Description	System Compatibility	Product compatibility	W/S
PC Maintenance Cable	11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

NT5D30AA

Description	System Compatibility	Product compatibility	W/S
Dual Intergroup Switch	71; 81; 81C		W1

Notes:

- Dual InterGroup Switch (DIGS) is the space switching circuitry for digital speech between groups in a Meridian 1 multi-group system, such as Options 71, 81, and 81C. Each DIGS pack replaces two (2) existing IGS packs (QPC412) on the SL-1 and Meridian 1 systems. The DIGS pack functions as a pair of IGS and is compatible to the QPC412 pack on the SL-1 and Meridian 1 systems.

Status
➤ S

NT5D40AA

Description	System Compatibility	Product compatibility	W/S
Hybrids Kit			W1

Notes:

- This kit is applicable for U9651, U9653 upgrades to Option 81C only. It is used for upgrading QSD39 shelves to house QPC471 clock controllers. Reference specific package notes for further details.

Status
➤ S

NT5D51AC

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) Base Card		Meridian Integrated Conference Bridge	W1

Notes:

- This card has no ports activated and is to be ordered for sparing purposes only. Port activation can only be achieved by using the security keycode and dongle device from an originally purchased MICB 12 port, 16 port, 24 port, 32 port, 42 port, 50 port or 62 port card.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5D60AA

Description	System Compatibility	Product compatibility	W/S
CLASS Modem card	11C; 51C; 61C; 81C		W1

Notes:
- The CLASS Modem Card (XCMC) requires X11 software packages 332 and 333.

Status
➤ S

NT5D61AB

Description	System Compatibility	Product compatibility	W/S
IODU/C Pack	51C; 61C; 81; 81C		W1

Notes:
- IODU/C requires X11 Release 23 Software on CD-ROM media which must be designated on the software order form
- New Option 51C, 61C, and 81C systems on Release 23 are pre-equipped with the IODU/C card(s).
- Hardware upgrade packages to Option 51C, 61C, and 81C systems on Release 23 (with the exception of U9646 and U9654) include the IODU/C card(s).
- If upgrading to IODU/C for the first time, software code SERV0080 must be ordered to indicate a software media change from 4MB Floppy disks to CD-ROM media

Status
➤ S

NT5D62BB

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive			W1

Notes:
- One PCMCIA Drive is shipped with every MICB card. Additional PCMCIA Drives are orderable as spares.

Status
➤ S

NT5D65CA

Description	System Compatibility	Product compatibility	W/S
Local Mini Carrier Extender Card (Options 21-81)			W1

Notes:
- One NT5D86AA (Local Mini Carrier Extender Cable) is required for the first Local Mini Carrier Extender Card and must be ordered separately.
- One Local Mini Carrier Extender Cable can support up to a maximum of three Local Mini Carrier Extender Cards.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5D69CA

Description	System Compatibility	Product compatibility	W/S
Local Mini Carrier Extender Card (Option 11)			W1

Notes:

- One Local Mini Carrier Extender Cable can support up to a maximum of three Local Mini Carrier Extender Cards.
- One NT5D86AA (Local Mini Carrier Extender Cable) is required for the first Local Mini Carrier Extender Card and must be ordered separately.

Status
➤ S

NT5D86AA

Description	System Compatibility	Product compatibility	W/S
Local Mini Carrier Extender Cable			W1

Notes:

- One Local Mini Carrier Extender Cable is required for the first NT5D65AA or NT5D69AA (Local Mini Carrier Extender Card for Options 21-81 or Option 11 respectively).
- One Local Mini Carrier Extender Cable can support up to a maximum of three Local Mini Carrier Extender Cards.

Status
➤ S

NT5D90BA

Description	System Compatibility	Product compatibility	W/S
Software Installation Kit (Non-Autovon)	51C; 61C; 81C		W1

Notes:

- Contains: (1) generic CD-ROM preloaded with the entire X11 Release 23 software portfolio, (3) Install Program diskettes, (3) Database Transfer Utility diskettes, (2) Database diskettes, (1) Distributor Keycode Application diskette, and (1) blank keycode diskette for downloading an electronically retrieved keycode.
- The software installation kit NT5D90BA is orderable as a merchandise item but does not contain an authorized keycode and security device required for software feature activation. To activate specific software features, the keycode and security device must be obtained from a CD-ROM based software order.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT5D97AA

Description	System Compatibility	Product compatibility	W/S
2.0MB Dual Port DTI/PRI	51C; 61C; 81; 81C		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT5F33BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack			W0

Qty	Order code	Description	Qty	Order code	Description
20	P0889997	Meridian Integrated (Release 2) Quick Reference Card			

Status
➤ Δ S

NT5F34AA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Reference Library, Release 24 and Earlier			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0889187	Library Navigator, Release 24 and Earlier	1	P0889194	X11 Data Features, Release 24 and Earlier
1	P0889188	System Planning and Engineering Guide, Release 24 and Earlier	1	P0889195	X11 Hospitality Features, Release 24 and Earlier
1	P0889189	System Installation and Maintenance Guide, Release 24 and Earlier	1	P0889196	X11 Networking Features, Release 24 and Earlier
1	P0889190	System and Software Upgrade Guide, Release 24 and Earlier	1	P0889197	ISDN Basic Rate Interface, Release 24 and Earlier
1	P0889191	X11 Software Features Guide, Release 24 and Earlier	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	P0889192	X11 System Management, Overview, Applications and Security Guide, Release 24 and Earlier	1	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier
1	P0889193	X11 Input/Output Guide, Release 24 and Earlier			

Status
➤ ⊗ Δ S

NT5F36AA

Description	System Compatibility	Product compatibility	W/S
Option 81C (CP PII) Reference Library, Release 25	81C		W0

Notes:

- Used with Option 81C Systems equipped with Call Processor PII equipment.

Qty	Order code	Description	Qty	Order code	Description
1	P0914248	CP PII/FNF System and Software Upgrade Guide	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT5F52AA

Description	System Compatibility	Product compatibility	W/S
Pre-Printed Feature Key Cap Package (15 Packages of 11 Key Caps Each)			W0

Notes:

- NT2K52AA, which includes 15 Packages of A0637619 containing 11 key caps each, is available at the CLP listed for merchandise orders only (for use with installed base telephone sets).

Status
➤ Δ S

NT5F88AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 11 Voice Messaging Package (15/PK)			W0

Qty	Order code	Description	Qty	Order code	Description
15	P0839942	Meridian Mail 11 Voice Messaging User Guide	15	P0839944	Meridian Mail 11 Voice Messaging Template
15	P0839943	Meridian Mail 11 Voice Messaging Quick Reference Card 30/Pkg	15	P0839946	Meridian Mail 11 Voice Messaging "At a Glance" Cards

Status
➤ Δ S

NT5F89AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 11 Voice Messaging (VMUIF) Package (15/PK)			W0

Qty	Order code	Description	Qty	Order code	Description
15	P0839950	Meridian Mail 11 Voice Messaging User Guide (VMUIF)	15	P0839952	Meridian Mail 11 Voice Messaging At a Glance Card (VMUIF)
15	P0839951	Meridian Mail 11 Voice Messaging Quick Reference Card (VMUIF)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT5F91AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 11 Call Answering Package (50/PK) (DMS)			W0

Qty	Order code	Description	Qty	Order code	Description
50	P0839947	Meridian Mail 11 Call Answering User Guide (DMS)	50	P0839949	Meridian Mail 11 Call Answering At a Glance Card (DMS)
50	P0839948	Meridian Mail 11 Call Answering Quick Reference Card (DMS)			

Status
➤ S

NT5G11AA

Description	System Compatibility	Product compatibility	W/S
MICA Pack without Security Device			W1

Notes:

- This card has no ports activated and contains no security device. It is to be ordered for sparing purposes only.

Status
➤ S

NT5G31AA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive Replacement (includes MICA software)			W1

Notes:

- This card has no ports activated and is to be ordered for sparing purposes only. Port activation can only be achieved by using the security keycode and dongle device from an originally purchased MICA. (NTZB91AA, NTZB91BA, NTZB91CA, NTZB91DA, NTZB91EA, NTZB91FA, NTZB91GA, NTZB91HA)

Status
➤ S

NT5G32AA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash Card (with MICA software included)			W1

Notes:

- This card has no ports activated and is to be ordered for sparing purposes only. Port activation can only be achieved by using the security keycode and dongle device from an originally purchased MICA. (NTZB92AA, NTZB92BA, NTZB92CA, NTZB92DA, NTZB92EA, NTZB92FA, NTZB92GA, NTZB92HA)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5G71AA

Description	System Compatibility	Product compatibility	W/S
MIPCD Spare Base Card			W0

Notes:

- This card has no ports activated and is to be ordered for sparing purpose only. Port activation can only be achieved by using the security device from the originally purchased MIPCD 8 port 50 user (NTZB77AA), MIPCD 16 port 100 user (NTZB78AA), MIPCD 24 port 150 user (NTZB79AA) or MIPCD 32 port 200 user (NTZB80AA).

Status
➤ S

NT5G91AB

Description	System Compatibility	Product compatibility	W/S
MIPCD PCMCIA Drive			W0

Notes:

- One PCMCIA Drive is shipped with every MIPCD 8 port 50 user card (NTZB77AA), MIPCD 16 port 100 user card (NTZB78AA), MIPCD 24 port 150 user card (NTZB79AA) and MIPCD 32 port 200 user card (NTZB80AA). Additional PCMCIA drives are orderable as spares.

Status
† ➤ S

NT5P41AZ

Description	System Compatibility	Product compatibility	W/S
4 Port Fax Modem Card AudioFax		Meridian Mail; Messenger	W1

Notes:

- Before ordering additional fax cards, please check your Meridian Application Server for the type of fax cards that have been installed in your system. Messenger systems that were originally shipped before May 1997 will have to order additional Audiofax cards when increasing the number of fax ports. The Audiofax cards and Brooktrout cards are not compatible and cannot work together in the same server.
- Compatible with Model 100, Model 500, & Model 501 servers only.

Status
➤ S

NT5P41ZR

Description	System Compatibility	Product compatibility	W/S
Brooktrout 4 Port Fax Card		Meridian Mail; Messenger	W1

Notes:

- Before ordering additional fax cards, please check your Meridian Application Server for the type of fax cards that have been installed in your system. Messenger systems that were originally shipped before May 1997 will have to order additional Audiofax cards when increasing the number of fax ports. The Audiofax cards and Brooktrout cards are not compatible and cannot work together in the same server.
- Compatible with Model 100, Model 500, & Model 501 servers only.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5P70DA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Driver for ICM with Bay ARN Router			W1

Notes:

- Includes TAPI Driver software and documentation on CD and Bay ARN router. Enables implementation of TAPI server connected to DMS-100/500 or MSL-100 via ICM TCP/IP link. Link provided by service provider. Router connects to server network interface card (NIC) and terminates ICM link. Supports CDN messages.

Status
➤ S

NT5P70EA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Driver for ICM - TCP/IP			W1

Notes:

- Includes TAPI Driver software and documentation on CD. Enables implementation of TAPI server connected to DMS-100/500 or MSL-100 via ICM TCP/IP link. Link provided by service provider. Supports CDN messages.

Status
➤ S

NT5R33AU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape North American		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ S

NT5R33BU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape - North American 2		Meridian Mail Modular Option GP R10	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R33CU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 1		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ S

NT5R33DU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 2		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ S

NT5R33EU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 3		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R33FU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 4		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ S

NT5R33GU

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape Asia/Pacific		Meridian Mail EC11 R10; Meridian Mail Modular Option R10; Meridian Mail Modular Option EC R10; Meridian Mail Modular Option GP R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ Δ S

NT5R3501

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC 9.19 to 9.66 Upgrade Keycode			S1

Notes:

- This code is required when upgrading a Meridian Mail EC from Meridian Mail Release 9.19 to Release 9.66.
- The Meridian Mail serial number must be provided when ordering this code.

Status
§ ➤ S

NT5R36AC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 11.19 Software Tape	11C COMPACT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R36BC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, North American 2 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R36CC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 1 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R36DC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 2 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R36EC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 3 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R36FC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 4 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R36GC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 5 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R36HC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R36JC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19		Meridian Mail Card Option R11; Meridian Mail EC11 R11; Meridian Mail Modular Option R11; Meridian Mail Modular Option EC R11; Meridian Mail Modular Option GP R11	W0

Notes:

- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NT5R45AC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, North American 1 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0/ S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R45BC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, North American 2 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular GP R12.13; Meridian Mail Modular Option R12.13	W0

Status
➤ S

NT5R45CC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 1 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

Status
➤ S

NT5R45DC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 2 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

Status
➤ S

NT5R45EC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 3 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R45FC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 4 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

Status
➤ S

NT5R45GC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, European 5 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

Status
➤ S

NT5R45HC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT5R45JC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13		Meridian Mail Card Option R12.13; Meridian Mail Compact Option R12.13; Meridian Mail EC R12.13; Meridian Mail EC11 R12.13; Meridian Mail Modular Option R12.13; Meridian Mail Modular Option GP R12.13	W0

Status
➤ Δ S

NT5R46AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Networking Services Administration Guide		Meridian Mail Modular EC R9,10	W0

Status
➤ Δ S

NT5R98AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Multi-Media Services Reference Manual		Meridian Mail Modular EC R9,10	W0

Notes:
- The Multi-Media Services Reference Manual contains the Voice Menus, Voice Forms and Fax on Demand Applications Guides.

Status
➤ S

NT6C14PA

Description	System Compatibility	Product compatibility	W/S
System 600/48 LVD Interface Circuit Pack	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT6C14PE

Description	System Compatibility	Product compatibility	W/S
System 600/48 Supplemental Cabinet Adaptor	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6C14PF

Description	System Compatibility	Product compatibility	W/S
Alarm and Control Circuit Pack for MPP600 and MFA150	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT6C14PG

Description	System Compatibility	Product compatibility	W/S
Meter Circuit Pack for MPP600 and MFA150	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT6C25FF

Description	System Compatibility	Product compatibility	W/S
System 600/48 Front Access Controller	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT6C25PC

Description	System Compatibility	Product compatibility	W/S
System 600/48 Control Circuit Pack	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

NT6C25PD

Description	System Compatibility	Product compatibility	W/S
System 600/48 Fuse Circuit Pack	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6C40CF

Description	System Compatibility	Product compatibility	W/S
Seismic Rack (23 In. x 4 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
† ➤ S

NT6D11AF

Description	System Compatibility	Product compatibility	W/S
D-Channel Handler Card	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Notes:

- Requires X11 Release 16 Software.
- An NT6D11AC is required for each different end location. Each NT6D11AC can support up to 15 PRI cards. maximum of 15 D-channel handlers per system. The QPC471 Clock Controller Card is required for PRI.

Status
➤ S

NT6D40BA

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Power Supply DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT6D41AD

Description	System Compatibility	Product compatibility	W/S
Common Equipment Power Supply DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
§ ➤ S

NT6D41BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Power Supply DC		Meridian Mail Modular GP	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6D42CD

Description	System Compatibility	Product compatibility	W/S
Ringing Generator DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

NT6D4406

Description	System Compatibility	Product compatibility	W/S
RSM Cable		Meridian Mail Modular Option	W1

Status
➤ S

NT6D4407

Description	System Compatibility	Product compatibility	W/S
GSP Cable		Meridian Mail Modular Option GP	W0

Status
† ➤ S

NT6D4408

Description	System Compatibility	Product compatibility	W/S
NVP Cable		Meridian Mail Modular Option	W0

Status
† ➤ S

NT6D4409

Description	System Compatibility	Product compatibility	W/S
SCSI Cable		Meridian Mail Modular Option	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT6D4410

Description	System Compatibility	Product compatibility	W/S
DVS Bus Cable		Meridian Mail Modular Option	W1

Status
† ➤ S

NT6D4411

Description	System Compatibility	Product compatibility	W/S
DVS Bus Cable (57 Inches)		Meridian Mail Modular Option	W1

Status
† ➤ S

NT6D4412

Description	System Compatibility	Product compatibility	W/S
DVS Bus Cable (Internal) (132 Inches)		Meridian Mail Modular Option	W1

Status
† ➤ S

NT6D4415

Description	System Compatibility	Product compatibility	W/S
DVS Bus Cable (6 Ft.)		Meridian Mail Modular Option	W1

Status
➤ S

NT6D4417

Description	System Compatibility	Product compatibility	W/S
SCSI/Backplane Cable		Meridian Mail Modular GP R9; Meridian Mail Modular Option R9	W1

Notes:
- Used in conjunction with the MMP40 Processor, NT4R45AA.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT6D4418

Description	System Compatibility	Product compatibility	W/S
SCSI/Daisy Chain Cable		Meridian Mail Options (NT/XT) R9; Meridian Mail Options (ST/RT) R9	W0

Notes:
- Used in conjunction with the MMP40 Processor, NT4R45AA.

Status
† ➤ S

NT6D4419

Description	System Compatibility	Product compatibility	W/S
RS232-Y Cable		Meridian Mail Modular GP R9; Meridian Mail Modular Option R9; Meridian Mail Options (NT/XT) R9; Meridian Mail Options (ST/RT) R9	W0

Notes:
- Used in conjunction with the MMP40 Processor, NT4R45AA.

Status
➤ S

NT6D44AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Module AC		Meridian Mail Modular Option	W1

Status
➤ S

NT6D44DC

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Module DC		Meridian Mail Modular Option	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6D45CA

Description	System Compatibility	Product compatibility	W/S
Tandberg Tape Drive Unit, Modular Option		Meridian Mail GP; Meridian Mail Modular Option; Meridian Mail Modular Option GP	W1

Notes:

- A Tape Drive Cleaning Kit (A0633585) must be ordered separately. Optional 2.5 GB Backup data cartridges (A0630697) may also be purchased as required.
- This tape drive assembly is used for non-shadowed Modular Option and Modular Option GP systems.

Status
➤ S

NT6D48FA

Description	System Compatibility	Product compatibility	W/S
4.5GB Modular Hard Disk Drive		Meridian Mail Modular Option; Meridian Mail Modular Option GP	W1

Status
➤ S

NT6D48GA

Description	System Compatibility	Product compatibility	W/S
Tandberg Tape and 4.5GB Disk Drive Unit, Modular Option		Meridian Mail Modular Option; Meridian Mail Modular Option GP	W1

Notes:

- A Tape Drive Cleaning Kit (A0633585) must be ordered separately. Optional 2.5 GB Backup data cartridges (A0630697) may also be purchased as required.
- This tape drive assembly is used for non-shadowed Modular Option and Modular Option GP systems.

Status
➤ S

NT6D51AA

Description	System Compatibility	Product compatibility	W/S
Transition Card (for MVME332)		Meridian IVR	W1

Notes:

- For use with A0376918 the 8 channel asynchronous I/O board.

Status
➤ S

NT6D5303

Description	System Compatibility	Product compatibility	W/S
Ground Bar/LRE - Large	71; 81; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6D5304

Description	System Compatibility	Product compatibility	W/S
Ground Bar/LRE - Small	21; 21E; 51; 61; 61C; 71; 81		W1

Status
† ➤ S

NT6D54AA

Description	System Compatibility	Product compatibility	W/S
Rectifier Wiring Kit	21; 21E; 51; 61; 61C		W1

Status
➤ S

NT6D54CA

Description	System Compatibility	Product compatibility	W/S
Backplane Stiffener Kit		Meridian Mail Modular GP; Meridian Mail Modular Option	W1

Notes:

- Required for each node with Disk Shadowing on Meridian Mail Modular Option and Modular GP systems.

Status
➤ S

NT6D6003

Description	System Compatibility	Product compatibility	W/S
Core Bus Terminator	61C; 81		W1

Status
➤ S

NT6D70AA

Description	System Compatibility	Product compatibility	W/S
S/T Interface Line Card (SILC)	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6D71AA

Description	System Compatibility	Product compatibility	W/S
U-Interface Line Card (UILC)	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT6D73AA

Description	System Compatibility	Product compatibility	W/S
Multi-Purpose ISDN Signaling Processor (MISP)	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W2

Status
➤ S

NT6D80AB

Description	System Compatibility	Product compatibility	W/S
Multi-Purpose Serial Data Link (MSDL)	21; 21A; 21E; 51; 61; 61C; 71; 81		W2

Notes:

- A separate D-Channel port is required for each different end location. Each D-Channel port can support up to 16 ISDN PRI cards (QPC720). There is a maximum of 64 D-Channel Handler ports per system. The QPC471 Clock Controller Card (qty. 1 or 2) is required for ISDN PRI.

Status
➤ S

NT6D81AA

Description	System Compatibility	Product compatibility	W/S
Power Regulator Card	21; 21A; 21E; 51; 61; 61C; ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6D98AA

Description	System Compatibility	Product compatibility	W/S
8-Channel Asynchronous I/O Card Kit		Meridian MAX-SEE; Meridian MAX-SNN; Meridian MAX-SNNE	W1

Notes:

- Additional cables must be ordered to connect the VME Multiport cables to SDI ports, terminals or printers; for details, please consult the Meridian MAX Ordering Procedures Guide for the MAX Software Release being used.
- Each kit requires one 8-Channel Asynchronous I/O Software Support (SW0081A).
- The base hardware system SY0073A, SY0073D, U0073A or U0073D already contains one (1) 8-Channel Asynchronous I/O board. For these systems, a maximum of four (4) additional NT6D98AA Kits can be ordered for a maximum of forty (40) I/O channels with associated cables.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	3	NT8D96BE	VME Multi-Port Cable

Status
➤ S

NT6G00AF35

Description	System Compatibility	Product compatibility	W/S
M2250 Attendant Console			W1

Notes:

- M2250 is compatible with X11 Release 15 or later software. Requires QPC578D ISDLC or NT8D02AA Digital Line Card and Modular Meridian Terminals Software.
- See "Other Application Products" section for CPLUS Attendant Directory/Message Center Software and Option Packages.

Status
➤ S

NT6P0104

Description	System Compatibility	Product compatibility	W/S
Address Bus Jumper Cable		Meridian Mail Modular EC	W1

Status
➤ S

NT6P0109

Description	System Compatibility	Product compatibility	W/S
5 Port RS232 Cable		Meridian Mail Modular EC	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6P0110

Description	System Compatibility	Product compatibility	W/S
4 Port RS232 Cable		Meridian Mail EC11 R10; Meridian Mail Modular EC	W1

Status
➤ S

NT6P0112

Description	System Compatibility	Product compatibility	W/S
Alarm Cable		Meridian Mail Modular EC	W0

Status
➤ S

NT6P0113

Description	System Compatibility	Product compatibility	W/S
Interconnect Cable		Meridian Mail Modular EC	W1

Status
➤ S

NT6P04AA

Description	System Compatibility	Product compatibility	W/S
VP4 Card		Meridian Mail Modular EC	W0

Notes:
- Required for Pre-Release 9 systems or spares only.

Status
➤ S

NT6P05BA

Description	System Compatibility	Product compatibility	W/S
Tandberg EC Tape Drive Unit, EC		Meridian Mail EC11; Meridian Mail Modular Option EC	W1

Notes:
- A Tape Drive Cleaning Kit (A0633585) must be ordered separately. Optional 2.5 GB Backup data cartridges (A0630697) may also be purchased as required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6P07BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive		Meridian Mail EC11; Meridian Mail Modular EC	W1

Status
➤ S

NT6P08AA

Description	System Compatibility	Product compatibility	W/S
VP8 Card		Meridian Mail Modular EC	W0

Notes:
- Required for Pre-Release 9 systems or spares only.

Status
➤ S

NT6P42AA

Description	System Compatibility	Product compatibility	W/S
Utility Card without Modem		Meridian Mail EC11; Meridian Mail Modular EC	W1

Status
➤ S

NT6P44BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power		Meridian Mail EC11; Meridian Mail Modular EC	W1

Status
➤ S

NT6P97AA

Description	System Compatibility	Product compatibility	W/S
MMP40 Processor, Modular EC/EC11		Meridian Mail EC11; Meridian Mail Modular Option EC	W1

Notes:
- Requires Meridian Mail Release 9.5 or later software.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT6R10AD

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Release 1.5 Documentation CD-ROM		SYMPOSIUM Call Center Server (ICCM)	W0

Notes:

- This package includes one SYMPOSIUM Call Center Documentation Package (English) on a CD-ROM. The SYMPOSIUM Call Center Server documents included on the CD-ROM are as follows: End-to-End Task Flow, SYMPOSIUM and the Meridian 1, Planning and Engineering Guide, Administration Assembly, Installation Assembly, Resource Management Assembly, Diagnostics Guides, and Hardware Installation Guides.
- This CD-ROM is compatible with both PC and Macintosh computers.

Status
✓ ➤ S

NT6R14AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Processor for Modular Option and Modular Option GP			W0

Notes:

- This Enhanced Processor is used with Modular Option and Modular Option GP systems only.
- This processor can be used only on systems with Meridian Mail Software Release 12.13 or higher.
- The Enhanced Processor can not be mixed with other processors on the same system. All processors must be Enhanced on a particular system.

Status
➤ S

NT6R15AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Processor for Meridian Mail EC			W1

Notes:

- This Enhanced Processor is used with EC and EC11 systems only.
- This processor can be used only on systems with Meridian Mail Software Release 12.13 or higher.
- The Enhanced Processor can not be mixed with other processors on the same system. All processors must be Enhanced on a particular system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT6R41AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Documentation Package (English)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:

- This package includes one set of Meridian MAX Release 9 Installation and Maintenance NTP's (2-binder set) and one Meridian MAX Release 9 Supervisor's User Guide (English).

Qty	Order code	Description	Qty	Order code	Description
1	NTLH13AA	ACD Reference Guides	1	P0889198	ACD Reference Guide, Release 24 and Earlier

Status
➤ Δ S

NT6R43AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Supervisor's User Guide (English)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:

- This package includes one Meridian MAX Release 9 Supervisor's User Guide.

Status
➤ Δ S

NT6R49AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 Installation and Modification Guide, MM10		Meridian Mail EC11 R10	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6R50AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider for Meridian 1 Release 2	11C X11 R22,23,24; 11E X11 R20,21; 21E X11 R19,20,21; 51 X11 R19,20,21; 51C X11 R20,21,22,23,24; 61 X11 R19,20,21; 61C X11 R20,21,22,23,24; 71 X11 R19,20,21; 81 X11 R19,20,21,22,23,24; 81C X11 R21,22,23,24; NT X11 R19,21; RT X11 R19,21; STE X11 R19,21; XT X11 R19,21	Meridian Link R5,6; SYMPOSIUM Call Center Server (ICCM)	W0/ S2

Notes:

- Requires NT2F59AA Application License Kit.
- For use with Microsoft Windows NT Version 4.0 or higher(with proper Service pack).
- Requires Meridian Link 5 (Co-residency 6) or higher or Symposium Call Center Server Release 1 or higher.
- For Option 21-81 systems, X11 Release 19 or higher is required and associated Meridian Link prerequisites.
- For Option 11 systems, prerequisites are X11 Release 20 or higher and associated Meridian Link prerequisites.
- One year SYMPOSIUM TAPI Service Provider software support is included. For service to continue, SV000091 must be purchased in subsequent years.
- Recommended: TAPI Service Provider INSTALL-PRO (SV000089) or TAPI Service Provider INSTALL-PREP (SV000088) if distributor is not certified to support installations.
- Provides the physical media containing the SYMPOSIUM TAPI Service Provider Release 2 for Meridian 1 software.
- Includes SYMPOSIUN Agent software and the right to use 5 concurrent seats of SYMPOSIUM Agent Release 1 Package 2.
- The Meridian 1 Serial number must be provided if ordering this code as an addition to an existing Meridian 1 system.

Qty	Order code	Description
5	NT1F58AA	SYMPOSIUM Agent Package 2 (1-50 Agents)
	Each Package Includes:	
	1	P0877952 SYMPOSIUM Agent Quick Reference Guide
1	NT1F85AB	SYMPOSIUM 1 1 Basic Software and Documentation Package
1	NT6R66AB	SYMPOSIUM TAPI Service Provider Release 2, Software and Documentation
1	SV000090	SYMPOSIUM TAPI Service Provider Software Support

Status
➤ S

NT6R67AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider Release 2, IVR and Networking Option		Meridian Link R5,6; SYMPOSIUM Call Center Server (ICCM)	W0/ S2

Notes:

- Requires NT6R50AA or NT6R50AB SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2.
- Activates the IVR and Networking features.
- A new license file will be provided when the option is ordered at a different time than the NT6R50AA or NT6R50AB.
- The Meridian 1 Serial number must be provided if ordering this code as an addition to an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT6R68AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 Direct Connect Option	11C X11 R23,24; 51C X11 R23,24; 61C X11 R23,24; 81 X11 R23,24; 81C X11 R23,24	Meridian Link; SYMPOSIUM Call Center Server (ICCM)	W0/ S2

Notes:

- Requires NT6R50AA or NT6R50AB SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2.
- Activates the ability for SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 to be configured for operation with an ELAN connection to the Meridian 1 processor.
- SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 Host Enhanced Routing capabilities are not supported in the ELAN configuration.
- For Option 11C systems, the X11 Release 23 or higher prerequisite is NTSF8022 Enterprise Software Package.
- For Options 51C, 61C, 81 and 81C systems, the X11 Release 23 or higher prerequisite is SW0221C ACD/Message Processing.
- Activates the X11 R23.3X (or higher) prerequisites Next Generation Connectivity (package 324) and Symposium Call Center (Package 311) unless already activated.
- Activates the first increment (20 ASTs) of Meridian Link Software (SW0251A) unless already activated.
- A new license file will be provided when the option is ordered at a different time than the NT6R50AA or NT6R50AB.
- The Meridian 1 Serial number must be provided if ordering this code as an addition to an existing Meridian 1 system.

Status
➤ Δ S

NT6R69AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider Upgrade Software		Meridian Link; SYMPOSIUM Call Center Server (ICCM)	W0/ S2

Notes:

- For use to upgrade from Meridian 1 TAPI Server Release 1 to SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	
1	NT1F58AA	SYMPOSIUM Agent Package 2 (1-50 Agents)	
	Each Package Includes:		
	1	P0877952	SYMPOSIUM Agent Quick Reference Guide
1	NT1F85AB	SYMPOSIUM 1 1 Basic Software and Documentation Package	
1	NT6R66AB	SYMPOSIUM TAPI Service Provider Release 2, Software and Documentation	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
Δ B

NT6R77AD

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 24 English Documentation Package - Binder			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0907441	Overview, Installation and Programming	1	P0907443	Option 11C Administration & Maintenance I/O Guides
1	P0907442	Post Installation Activities			

Status
Δ B

NT6R78AD

Description	System Compatibility	Product compatibility	W/S
Option 11C R24 English Documentation Package - Coil			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0907446	Planning and Installation Guide			

Status
➤ Δ S

NT6R79AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider Replacement CD-ROM			W0/ S2

Notes:

- To be used to replace SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 and newer.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R66AB	SYMPOSIUM TAPI Service Provider Release 2, Software and Documentation	1	P0890127	Symposium TAPI Service Provider and Symposium Agent License Files

Status
➤ Δ S

NT6R81AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Options Reference Manual, Release 10		Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT6R82AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option GP Reference Manual, Release 10		Meridian Mail Modular GP R10	W0

Status
➤ Δ S

NT6R83AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option EC Reference Manual, Release 10		Meridian Mail Modular EC R10	W0

Status
➤ Δ S

NT6R84AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Reference Manual, Release 10		Meridian Mail Modular Option R10	W0

Status
➤ Δ S

NT6R85AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Multi-Customer System Reference Manual, Release 10		Meridian Mail Card Option R10; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT6R86AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail System Administration Reference Manual, Release 10		Meridian Mail Card Option R10; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ Δ S

NT6R87AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Multi-Customer System Reference Manual (DMS), Release 10		Meridian Mail Modular GP R10	W0

Status
➤ Δ S

NT6R88AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail ACCESS Developers Reference Manual, Release 10		Meridian Mail Card Option R10; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ Δ S

NT6R89AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail ACCESS Enable Option Reference Manual, Release 10		Meridian Mail Card Option R10; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NT6R90AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC Installation & Maintenance Quick Reference Manual, Release 10		Meridian Mail Modular EC R10	W0

Status
➤ Δ S

NT6R91AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail SEERS Reference Manual, Release 10		Meridian Mail Card Option R10; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Status
➤ Δ S

NT6R93AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Reference Manual, Release 10		Meridian Mail Card Option R10	W0

Status
➤ Δ S

NT6R99AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail System Administration Reference Manual (DMS), Release 10		Meridian Mail Modular GP R10	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D00AA

Description	System Compatibility	Product compatibility	W/S
Top Cap AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT7D00BA

Description	System Compatibility	Product compatibility	W/S
Top Cap DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT7D05AA

Description	System Compatibility	Product compatibility	W/S
Filler Panel - Ringing Generator	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT7D06AA

Description	System Compatibility	Product compatibility	W/S
Filler Panel	21; 21E; 51; 61; 61C; 71; 81; LE; M; MS; N; NT; RT; ST; STE; VLE; XL; XN; XT		W1

Status
➤ S

NT7D0902

Description	System Compatibility	Product compatibility	W/S
Rear Mount Conduit/Wiring Kit	11; 21; 51; 61; 61C; 71; A; L; LE; M; MS; N; NT; RT; S; ST; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D09CA

Description	System Compatibility	Product compatibility	W/S
Pedestal DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Notes:

- Diecast Pedestal only. Does not include Pedestal Blower Unit, Power Distribution Unit, or System Monitor. If other items are required, refer to the AS1081A/D.

Status
† ➤ S

NT7D1201

Description	System Compatibility	Product compatibility	W/S
Rectifier Support/Air Baffle	21; 21E; 51; 61; 61C		W1

Status
† ➤ S

NT7D12AA

Description	System Compatibility	Product compatibility	W/S
Rectifier Rack	21; 21E; 51; 61; 61C		W1

Status
➤ S

NT7D16BA

Description	System Compatibility	Product compatibility	W/S
Data Access Card	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- Requires X11 Release 16 Software.
- Compatible with ST/RT/NT/XT systems which have been upgraded to the Meridian 1 and include an IPE shelf.
- Please refer to NTP 553-3001-191 for engineering limitations.
- Option 11 Note: This card may be installed in any one of the available Universal Card slots in the main or expansion cabinet.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D18AA

Description	System Compatibility	Product compatibility	W/S
Application Equipment Module AC	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Status
➤ S

NT7D18AB

Description	System Compatibility	Product compatibility	W/S
Application Equipment Module DC	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX	W1

Notes:

- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Status
➤ S

NT7D18KA

Description	System Compatibility	Product compatibility	W/S
Power Sense Monitor Kit		Meridian MAX	W1

Notes:

- Required only when U0071 is ordered and the original Meridian MAX Release 4 system was equipped with the I/O sub-panel rather than the Universal I/O panel.
- This kit allows mounting of the Power Sense Monitor in the middle of the Application Module as is done in newer systems.

Status
➤ S

NT7D19RA

Description	System Compatibility	Product compatibility	W/S
Meridian IVR Applications Module			W1

Notes:

- Each Meridian IVR module package comes with one MVME-167C-34 CPU card installed in slot 1. There are five slots available for housing either the SNA card, X.25 card or the 8-Channel Asynchronous Serial I/O Board. A maximum of 4 MVME332XT 8-Channel Asynchronous Serial I/O Boards may be housed in the Meridian IVR module. The Meridian IVR module comes pre-configured with certain VME transition cards factory installed. This is the case for all slots except for slot 6. Slot 6 is not automatically shipped with a pre-installed transition card. A transition card may by optionally placed here during the initial system order upon customer request or it can be field installed at a later date.

Qty	Order code	Description	Qty	Order code	Description
1	A0351166	MVME705B Transition Card (for MVME333)	3	NT6D51AA	Transition Card (for MVME332)
1	A0601182	MVME712M Transition Card without built-in modem (for MVME167 and MVME177)	1	NT7D63AB	AM Chassis

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D46AA

Description	System Compatibility	Product compatibility	W/S
SDI I/O Cable	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D46AD

Description	System Compatibility	Product compatibility	W/S
Application Module to SDI Paddle Board Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D46AF

Description	System Compatibility	Product compatibility	W/S
Application Module to SDI Paddle Board Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D46AL

Description	System Compatibility	Product compatibility	W/S
Application Module to SDI Paddle Board Cable (20 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D46AT

Description	System Compatibility	Product compatibility	W/S
Application Module to SDI Paddle Board Cable (35 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D46AV

Description	System Compatibility	Product compatibility	W/S
Application Module to SDI Paddle Board Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D47AG

Description	System Compatibility	Product compatibility	W/S
Ethernet Cable (12 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT		W1

Status
➤ Δ S

NT7D47BA

Description	System Compatibility	Product compatibility	W/S
Ethernet Cable (Thinnet 50 Ft.) and Terminator		Meridian IVR	W1

Notes:

- This cable is required with the MRS/Tower or MRS/Rack if the LAN connection is Ethernet and if the MRS represents the second system behind the Application Processor.

Status
➤ S

NT7D47BB

Description	System Compatibility	Product compatibility	W/S
Ethernet Cable (100 Ft.)		Meridian IVR	W1

Status
➤ S

NT7D48AA

Description	System Compatibility	Product compatibility	W/S
Serial I/O Cable	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D58EB

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (2 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D58ED

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D58EF

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D58EL

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (20 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D58ET

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (35 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D58EV

Description	System Compatibility	Product compatibility	W/S
ESDI Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D61EB

Description	System Compatibility	Product compatibility	W/S
SDI Cable (2 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D61ED

Description	System Compatibility	Product compatibility	W/S
SDI Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D61EF

Description	System Compatibility	Product compatibility	W/S
SDI Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D61EL

Description	System Compatibility	Product compatibility	W/S
SDI Cable (20 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D61ET

Description	System Compatibility	Product compatibility	W/S
SDI Cable (35 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D61EV

Description	System Compatibility	Product compatibility	W/S
SDI Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

NT7D62AC

Description	System Compatibility	Product compatibility	W/S
1.2 GByte Hard Disk/155 MByte Tape Drive Assembly	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX-SEE	W1

Notes:
- Includes SCSI cable.
- Use for Meridian MAX-SEE Release 6.31 or later. For MAX-SEE Release 5 through 6.22 or for Meridian MAX Release 3 or 4 on Options 1,2,3, or 4 MAX systems, use NT7D62DA.

Status
➤ S

NT7D62CA

Description	System Compatibility	Product compatibility	W/S
1.2 GByte Hard Disk/600 MByte Tape Drive Assembly	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:
- Includes SCSI cable.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D62DA

Description	System Compatibility	Product compatibility	W/S
240 MByte Hard Disk/155 MByte Tape Drive Assembly	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SEE	W1

Notes:
- Includes SCSI cable.
- Use for Meridian MAX-SEE Release 5 through 6.22 Systems or for Meridian MAX Release 3 or 4 on Options 1,2,3, or 4 MAX Systems.

Status
➤ S

NT7D62EA

Description	System Compatibility	Product compatibility	W/S
2.0 GByte Hard Disk/600 MByte Tape Drive Assembly	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:
- Includes SCSI cable.

Status
➤ S

NT7D63AA

Description	System Compatibility	Product compatibility	W/S
Application Module Chassis Assembly	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX	W1

Status
➤ S

NT7D64AA

Description	System Compatibility	Product compatibility	W/S
Application Module Power Supply AC	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX	W1

Status
➤ S

NT7D64DC

Description	System Compatibility	Product compatibility	W/S
Application Module Power Supply DC	21; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT	Meridian CCR; Meridian IVR; Meridian Link; Meridian MAX	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7D71BA

Description	System Compatibility	Product compatibility	W/S
VME Built-In Modem External Cable	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT		W1

Status
➤ S

NT7D89CA

Description	System Compatibility	Product compatibility	W/S
CP to I/O Panel RS232 Cable	81		W1

Status
⊗ S

NT7D90DA

Description	System Compatibility	Product compatibility	W/S
IOP to I/O Panel Ethernet Cable (42 in./1m)	81		W1

Status
➤ S

NT7D99AA

Description	System Compatibility	Product compatibility	W/S
Null Modem Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; XT		W1

Status
➤ S

NT7G10AA

Description	System Compatibility	Product compatibility	W/S
M2250 Attendant Supervisory Module		M2250	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7R51AD

Description	System Compatibility	Product compatibility	W/S
Local Carrier Interface Card	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; ST; XT	Carrier Remote	W0

Status
➤ S

NT7R52AD

Description	System Compatibility	Product compatibility	W/S
Remote Carrier Interface Card	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R67BA

Description	System Compatibility	Product compatibility	W/S
Local Carrier/Monitor Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R67CA

Description	System Compatibility	Product compatibility	W/S
Local Maintenance/Clock Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R67DA

Description	System Compatibility	Product compatibility	W/S
Local External Maintenance Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT7R68AA

Description	System Compatibility	Product compatibility	W/S
Remote Carrier/Alarm Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R68BA

Description	System Compatibility	Product compatibility	W/S
Remote Maintenance Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R69AA

Description	System Compatibility	Product compatibility	W/S
Extension Local Carrier Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; STE; XT	Carrier Remote	W1

Status
➤ S

NT7R69BA

Description	System Compatibility	Product compatibility	W/S
Extension Local Maintenance Cable Assembly	21E; 51; 51C; 61; 61C; 71; 81; NT; RT; XT	Carrier Remote	W1

Status
➤ S

NT8D01BC

Description	System Compatibility	Product compatibility	W/S
Controller - Four Card	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT8D02GA

Description	System Compatibility	Product compatibility	W/S
Digital Line Card (DLC)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

NT8D04BA

Description	System Compatibility	Product compatibility	W/S
SuperLoop Network Card	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D06AB

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Power Supply AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
✓ ➤ S

NT8D09BA

Description	System Compatibility	Product compatibility	W/S
Analog Message Waiting Line Card	11; 11C; 11E; 21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- Care should be taken when connecting modems with this line card. Please refer to Product Bulletin #91013, Rev. 1, (Oct. 91) for details.
- Nortel Networks will provide the latest allowable vintage for this product.

Status
➤ S

NT8D1107

Description	System Compatibility	Product compatibility	W/S
SuperLoop Adapter Plate	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D1303

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Cardcage (AC/DC)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D13AA

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Module AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D13DC

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Module DC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
✓ ➤ S

NT8D14BB

Description	System Compatibility	Product compatibility	W/S
Universal Trunk Card	11; 11C; 11E; 21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Notes:

- Nortel Networks will provide the latest allowable vintage for this product.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NT8D15AK

Description	System Compatibility	Product compatibility	W/S
E&M Trunk Card	11; 11C; 11E; 21; 21A; 21E; 51; 61; 61C; 71; 81		W0

Notes:
- NT will provide the latest allowable vintage for this product.

Status
➤ S

NT8D16AB

Description	System Compatibility	Product compatibility	W/S
Digitone Receiver Card	11; 21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Notes:
- NT will provide the latest allowable vintage for this product.

Status
➤ S

NT8D17FA

Description	System Compatibility	Product compatibility	W/S
Conference/TDS Card	21; 21A; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; RT; S; ST; STE; XN; XT		W1

Status
➤ S

NT8D21AB

Description	System Compatibility	Product compatibility	W/S
Ringing Generator AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XT		W1

Status
➤ S

NT8D22AC

Description	System Compatibility	Product compatibility	W/S
System Monitor	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D27BB

Description	System Compatibility	Product compatibility	W/S
Pedestal AC	21; 51; 61; 61C; 71; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D29AB

Description	System Compatibility	Product compatibility	W/S
Common Equipment Power Supply AC	51; 61; 61C; 71; 81; LE; M; MS; N; NT; RT; ST; STE; VLE; XL; XN; XT		W1

Status
➤ S

NT8D31AA

Description	System Compatibility	Product compatibility	W/S
Blank Faceplate (0.875 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D31AB

Description	System Compatibility	Product compatibility	W/S
Blank Faceplate (1 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D31AD

Description	System Compatibility	Product compatibility	W/S
Blank Faceplate (2 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D31AE

Description	System Compatibility	Product compatibility	W/S
Tape Drive Blank Faceplate		Meridian Mail Modular Option	W1

Status
➤ S

NT8D3507

Description	System Compatibility	Product compatibility	W/S
Network Cardcage (AC/DC)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D35BA

Description	System Compatibility	Product compatibility	W/S
Network Module AC	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D35EA

Description	System Compatibility	Product compatibility	W/S
Network Module DC	21; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D36AA

Description	System Compatibility	Product compatibility	W/S
Inter Group Module	81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D3703

Description	System Compatibility	Product compatibility	W/S
Intelligent Peripheral Equipment Cardcage (AC/DC)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D37BA

Description	System Compatibility	Product compatibility	W/S
Intelligent Peripheral Equipment Module AC	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D37EC

Description	System Compatibility	Product compatibility	W/S
Intelligent Peripheral Equipment Module DC	21; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D40AA

Description	System Compatibility	Product compatibility	W/S
Power Cord AC (230V)	21; 21E; 51; 61; 61C; 71; 81; A; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D46AA

Description	System Compatibility	Product compatibility	W/S
System Monitor Column Cable (30 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46AB

Description	System Compatibility	Product compatibility	W/S
System Monitor Jumper Cable (11 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AC

Description	System Compatibility	Product compatibility	W/S
Thermostat Harness	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AD

Description	System Compatibility	Product compatibility	W/S
System Monitor to SDI Cable (60 In.)	21; 21A; 21E; 51; 71; 81		W1

Status
➤ S

NT8D46AG

Description	System Compatibility	Product compatibility	W/S
System Monitor to SDI Paddleboard Cable (34 In.)	21; 21E; 51; 61; 61C		W1

Status
➤ S

NT8D46AJ

Description	System Compatibility	Product compatibility	W/S
System Monitor to UPS (Best) Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AL

Description	System Compatibility	Product compatibility	W/S
System Monitor Serial Link Cable (7 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46AM

Description	System Compatibility	Product compatibility	W/S
Air Probe Harness	21; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AP

Description	System Compatibility	Product compatibility	W/S
Extended System Monitor Serial Link Cable (25 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AQ

Description	System Compatibility	Product compatibility	W/S
System Monitor to UPS (Exide) Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AS

Description	System Compatibility	Product compatibility	W/S
System Monitor Inter-CPU Cable (30 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
† ➤ S

NT8D46AT

Description	System Compatibility	Product compatibility	W/S
System Monitor to QBL15 Cable (32 Ft.)	21; 21E; 51; 61; 61C		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46AU

Description	System Compatibility	Product compatibility	W/S
System Monitor to UPS (Alpha) Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AV

Description	System Compatibility	Product compatibility	W/S
System Monitor to Power Cabinet Cable (32 Ft.)		MFA150; MPP600	W1

Status
➤ S

NT8D46AW

Description	System Compatibility	Product compatibility	W/S
System Monitor to QBL12 Cable (32 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46AX

Description	System Compatibility	Product compatibility	W/S
Alarm Interface Cable (45 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46AY

Description	System Compatibility	Product compatibility	W/S
Alarm Interface Cable (45 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46BA

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable Harness	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BB

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable Harness	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BC

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (6 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BD

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (1 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BE

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (10 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46BF

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (1 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BG

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable Harness	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BH

Description	System Compatibility	Product compatibility	W/S
System Monitor to MDF Cable (32 Ft.)	21; 21E; 51; 61; 61C; 71; 81; RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BJ

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (1 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46BM

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (1 Ft.)	RT; ST; STE		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46BV

Description	System Compatibility	Product compatibility	W/S
System Monitor to Power Cabinet Cable (64 Ft.)		MFA150; MPP600	W1

Status
➤ S

NT8D46CD

Description	System Compatibility	Product compatibility	W/S
System Monitor Column Cable (AEM)	21; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE; NAC	W1

Notes:
- Use this cable to connect from the power monitor circuit card in an Applications Equipment Module (AEM) to the module located above the AEM.

Status
➤ S

NT8D46CH

Description	System Compatibility	Product compatibility	W/S
Alarm Monitor Cable (12 Ft.)	RT; ST		W1

Notes:
- To be used with ST, RT system upgrades which include Meridian 1 modules.

Status
➤ S

NT8D46CV

Description	System Compatibility	Product compatibility	W/S
System Monitor to Power Cabinet Cable (100 Ft.)		MFA150; MPP600	W1

Status
➤ S

NT8D46DC

Description	System Compatibility	Product compatibility	W/S
DC Thermostat Harness	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D46DH

Description	System Compatibility	Product compatibility	W/S
System Monitor to MDF Cable (150 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D46EH

Description	System Compatibility	Product compatibility	W/S
System Monitor to MDF Cable (100 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D49AA

Description	System Compatibility	Product compatibility	W/S
Column Spacer Kit (2.75 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D49BA

Description	System Compatibility	Product compatibility	W/S
Column Spacer Kit (5.25 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D52AB

Description	System Compatibility	Product compatibility	W/S
Pedestal Blower Unit AC	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D52DD

Description	System Compatibility	Product compatibility	W/S
Pedestal Blower Unit DC	21; 21E; 51; 61; 61C; 71; 81; A; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D53CA

Description	System Compatibility	Product compatibility	W/S
Power Distribution Unit AC	21; 21E; 51; 61; 61C; 71; 81; A; L; VL		W1

Status
➤ S

NT8D56AA

Description	System Compatibility	Product compatibility	W/S
Common Equipment Module Power Distribution Unit	21; 21E; 51; 61; 61C; 71; 81; LE; M; MS; N; NT; RT; ST; STE; VLE; XL; XN; XT		W1

Status
➤ S

NT8D57AA

Description	System Compatibility	Product compatibility	W/S
Peripheral Equipment Module Power Distribution Unit	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D63AA

Description	System Compatibility	Product compatibility	W/S
Overhead Cable Tray Kit	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D6401

Description	System Compatibility	Product compatibility	W/S
Insulating Washer Kit	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D64BD

Description	System Compatibility	Product compatibility	W/S
Module Expansion Rods	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D64BF

Description	System Compatibility	Product compatibility	W/S
Floor Mounting Kit (Non-Seismic)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
★ ➤ Δ S

NT8D64BH

Description	System Compatibility	Product compatibility	W/S
Floor Module Anchor Hole Template			W0

Notes:
- This is a mylar template for use in marking holes in a concrete floor for seismic and non-seismic 51-81C module installations.

Status
➤ S

NT8D64CA

Description	System Compatibility	Product compatibility	W/S
Earthquake Bracing Kit (2 Module Column)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D64CB

Description	System Compatibility	Product compatibility	W/S
Earthquake Bracing Kit (3 Module Column)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D64CC

Description	System Compatibility	Product compatibility	W/S
Earthquake Bracing Kit (4 Module Column)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D7217

Description	System Compatibility	Product compatibility	W/S
Cable - 2.0MB DDP I/O to MDF 50 Ft.	51C; 61C; 81; 81C		W1

Status
➤ S

NT8D73AD

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D73AF

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (12 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D73AL

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (20 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D73AS

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (30 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D74BC

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Junctor Cable (4 Ft.)	71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D74BD

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Junctor Cable (6 Ft.)	71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D74BE

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Junctor Cable (8 Ft.)	71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D74BF

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Junctor Cable (10 Ft.)	71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D75BC

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Clock Controller Cable (4 Ft.)	51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D75BD

Description	System Compatibility	Product compatibility	W/S
Clock Controller to Clock Controller Cable (6 Ft.)	51; 61; 61C; 71; 81; N; NT; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D76BC

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (4 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D76BD

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (6 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D76BE

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (8 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D76BF

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (10 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D76BG

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (12 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D76BJ

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (16 Ft.)	71; 81; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D76BP

Description	System Compatibility	Product compatibility	W/S
cCNI to 3PE or IGS to IGM Cable (16 Ft.)	71; 81; XN; XT		W1

Status
➤ S

NT8D77BA

Description	System Compatibility	Product compatibility	W/S
Female Telco Cable (3 Ft.)	21; 21A; 21E; 51; 61; 71; NT; RT; ST; STE; XT		W1

Status
➤ S

NT8D77BB

Description	System Compatibility	Product compatibility	W/S
Female Telco Cable (2 Ft.)	21; 21A; 21E; 51; 61; 71; NT; RT; ST; STE; XT		W1

Status
† ➤ S

NT8D77BC

Description	System Compatibility	Product compatibility	W/S
Female Telco Cable (4 Ft.)	21; 21A; 21E; 51; 61; 71; NT; RT; ST; STE; XT		W1

Status
➤ S

NT8D77BD

Description	System Compatibility	Product compatibility	W/S
Female Telco Cable (6 Ft.)	21; 21A; 21E; 51; 61; 71; NT; RT; ST; STE; XT		W1

Status
➤ S

NT8D78AA

Description	System Compatibility	Product compatibility	W/S
CPU Cable (2 In.)	51; 61; 71; NT; RT; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D79AB

Description	System Compatibility	Product compatibility	W/S
PRI/DTI To Clock Controller Cable (2 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D79AC

Description	System Compatibility	Product compatibility	W/S
PRI/DTI To Clock Controller Cable (4 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D79AD

Description	System Compatibility	Product compatibility	W/S
PRI/DTI To Clock Controller Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D79AE

Description	System Compatibility	Product compatibility	W/S
PRI/DTI To Clock Controller Cable (8 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT8D79AF

Description	System Compatibility	Product compatibility	W/S
PRI/DTI To Clock Controller Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT8D80BC

Description	System Compatibility	Product compatibility	W/S
CPU/MDU Interface Cable (4 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

NT8D80BD

Description	System Compatibility	Product compatibility	W/S
CPU/MDU Interface Cable (6 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

NT8D80BE

Description	System Compatibility	Product compatibility	W/S
CPU/MDU Interface Cable (8 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D80BF

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (10 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D80BG

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (12 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D80BJ

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (16 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D80BL

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (20 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D80BP

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (25 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D80BZ

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (5 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NT8D81AA

Description	System Compatibility	Product compatibility	W/S
Tip and Ring Cable (20 In.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D82AD

Description	System Compatibility	Product compatibility	W/S
SDI to I/O Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D83AD

Description	System Compatibility	Product compatibility	W/S
PRI/DTI to I/O Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; RT; ST; STE		W1

Status
➤ S

NT8D84AA

Description	System Compatibility	Product compatibility	W/S
SDI Paddleboard to I/O Cable (18 In.)	21; 21E; 51; 61; 61C		W1

Status
➤ S

NT8D85BB

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (2 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D85BC

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (4 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BD

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (6 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BE

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (8 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BF

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (10 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D85BJ

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (16 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BL

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (20 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BP

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (25 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BV

Description	System Compatibility	Product compatibility	W/S
Network to PE Cable (45 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D85BZ

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (5 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D86BD

Description	System Compatibility	Product compatibility	W/S
Network to I/O Cable (6 Ft.)	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D88AC

Description	System Compatibility	Product compatibility	W/S
Network to I/O Cable (5 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D88AD

Description	System Compatibility	Product compatibility	W/S
Network to I/O Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D90AF

Description	System Compatibility	Product compatibility	W/S
SDI Multi-Port Extension Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D91AC

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (4 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AD

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AE

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (8 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AF

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (10 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AG

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (12 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D91AJ

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (16 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AP

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (25 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D91AV

Description	System Compatibility	Product compatibility	W/S
Network to Controller Cable (45 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D92AB

Description	System Compatibility	Product compatibility	W/S
Controller to I/O Cable (20 Inch)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D93AJ

Description	System Compatibility	Product compatibility	W/S
2 Port SDI I/O to DTE/DCE Cable (16 Ft.)	21; 21E; 51; 61; 61C		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D93AW

Description	System Compatibility	Product compatibility	W/S
2 Port SDI I/O to DTE/DCE Cable (48 Ft.)	21; 21E; 51; 61; 61C		W1

Status
➤ S

NT8D95AJ

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (16 Ft.) (Male/ Male)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D95AT

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (34 Ft.) (Male/ Male)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D95AW

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (48 Ft.) (Male/ Male)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D95BJ

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (16 Ft.) (Male/ Female)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D95BT

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Female)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D95BW

Description	System Compatibility	Product compatibility	W/S
SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Female)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT8D96AB

Description	System Compatibility	Product compatibility	W/S
SDI Multi-Port Cable (2 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; RT; ST; STE		W1

Status
➤ S

NT8D96BE

Description	System Compatibility	Product compatibility	W/S
VME Multi-Port Cable	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Notes:

- Three (3) VME Multiport Cables are required per one (1) Serial I/O Card (A0376918).

Status
➤ S

NT8D98AD

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8D98AF

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (12 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D98AL

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (20 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D98AS

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (30 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D99AB

Description	System Compatibility	Product compatibility	W/S
CPU or Network to Network Cable (2 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D99AC

Description	System Compatibility	Product compatibility	W/S
CPU or Network to Network Cable (4 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT8D99AD

Description	System Compatibility	Product compatibility	W/S
CPU or Network to Network Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT8R01AA

Description	System Compatibility	Product compatibility	W/S
Meridian IVR ACCESS Link Cable Kit			W1

Notes:
- Optional cable kit to connect the Application Processor to Meridian Mail system.
- Not applicable to Card Option.

Qty	Order code	Description	Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)	1	NT1R03EP	Straight Through RS232 Cable Male/Female (25 Ft)
1	A0385576	DB25F-DB9F Cable Adapter	1	NT7D99AA	Null Modem Cable (10 Ft)
1	NT1R03DP	Straight Through RS232 Cable Male/Male (25 Ft)	1	NTND82AB	RS232 Null Modem Cable (25 Ft)

Status
➤ S

NT8R20AA

Description	System Compatibility	Product compatibility	W/S
Assembly, Meridian Mail Alternate User Interface 1			W0/ S1

Qty	Order code	Description	
1	NT2F09AA	Alternate User Interface 1 User Guide (15 per Package)	
	Each Package Includes:		
	15	P0884614	Alternate User Interface 1 User Guides
1	NT8R2002	CD ROM Meridian Mail Alternate User Interface	
1	P0841936	SYMANTEC pcAnywhere RTU	
1	P0884613	Alternate User Interface Installation/Administration Guide	
1	P0902630	AUI PC Installation Instruction Sheet	

Status
➤ S

NT9D08AA

Description	System Compatibility	Product compatibility	W/S
DSS-9000 Direct Station Select Unit	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; VL; VLE; XL; XN; XT	M1250; M2250	W1

Notes:
- Compatible with M1250/M2250 Attendant Console and requires a 24 Volt AC Transformer.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9D1501

Description	System Compatibility	Product compatibility	W/S
Door Panel Lock Latch Kit	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:
- NT9D1501 contains two (2) door panel lock latches per kit.

Status
➤ S

NT9D15AA

Description	System Compatibility	Product compatibility	W/S
Front/Rear Cover	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

NT9D18AA

Description	System Compatibility	Product compatibility	W/S
Module Side Cover	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

NT9D89CA

Description	System Compatibility	Product compatibility	W/S
CNI-3 TO 3PE/EMSI TO MDU Cable (8 Ft.)	51; 51C; 61; 61C; 71; 81; 81C; NT; RT; XT		W0

Notes:
- This cable supports both EMSI/MDU Cabling and CNI-3 to 3PE Cabling.

Status
➤ S

NT9D89DA

Description	System Compatibility	Product compatibility	W/S
CNI-3 TO 3PE/EMSI TO MDU Cable (10 Ft.)	51; 51C; 61; 61C; 71; 81; 81C; NT; RT; XT		W0

Notes:
- This cable supports both EMSI/MDU Cabling and CNI-3 to 3PE Cabling.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9D89EA

Description	System Compatibility	Product compatibility	W/S
CNI-3 TO 3PE/EMSI TO MDU Cable (12 Ft.)	51; 51C; 61; 61C; 71; 81; 81C; NT; RT; XT		W0

Notes:
- This cable supports both EMSI/MDU Cabling and CNI-3 to 3PE Cabling.

Status
➤ S

NT9D89FA

Description	System Compatibility	Product compatibility	W/S
CNI-3 TO 3PE/EMSI TO MDU Cable (25 Ft.)	51; 51C; 61; 61C; 71; 81; 81C; NT; RT; XT		W0

Notes:
- This cable supports both EMSI/MDU Cabling and CNI-3 to 3PE Cabling.

Status
➤ S

NT9D89GA

Description	System Compatibility	Product compatibility	W/S
CNI-3 TO 3PE/EMSI TO MDU Cable (50 Ft.)	51; 51C; 61; 61C; 71; 81; 81C; NT; RT; XT		W0

Notes:
- This cable supports both EMSI/MDU Cabling and CNI-3 to 3PE Cabling.

Status
➤ S

NT9D9008

Description	System Compatibility	Product compatibility	W/S
Cable TC/FM to NAC Network Link and Remote Supervisor Log-In Link (RJ45 to DB25)		ACD MAX; NAC	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9D99AA

Description	System Compatibility	Product compatibility	W/S
RSM Installation Kit - Modular		Meridian Mail Modular Option	W1

Status
➤ S

NT9F02AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, New System (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- CCS 100 enables the basic call processing, supervision, and MIS capabilities of the SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓➤ S

NT9F02BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, New System (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- CCS 100 enables the basic call processing, supervision, and MIS capabilities of the SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F02CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, New System (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- CCS 100 enables the basic call processing, supervision, and MIS capabilities of the SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of Call Center Software 100 also includes the following X11 prerequisites: Symposium Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software package is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓ ➤ S

NT9F02DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, New System (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- CCS 100 enables the basic call processing, supervision, and MIS capabilities of the SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22 Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NT9F02EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, New System (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- CCS 100 enables the basic call processing, supervision, and MIS capabilities of the SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- Requires SYMPOSIUM Call Center Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software or higher level package is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

NT9F02GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F02HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F02JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F03AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, New System (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- There are no additional X11 prerequisites required for this package.
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- Requires SYMPOSIUM Call Center Server Base Software and CCS 100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓ ➤ S

NT9F03BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, New System (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- There are no additional X11 prerequisites required for this package.
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- Requires SYMPOSIUM Call Center Server Base Software and CCS 100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F03CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, New System (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS 100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓ ➤ S

NT9F03DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, New System (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS 100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓ ➤ S

NT9F03EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, New System (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS 100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F03GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F03HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F03JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F04AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, New System (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 300 is the networking functionality of SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS 100, and CCS 200 as prerequisite. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The initial release of SYMPOSIUM Call Center Server networking will only include Interworking with Network ACD. Additional networking functionality which includes network wide skills-based routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of CCS300 includes the X11 Call Center Networking at no additional charge. The X11 packages SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW0222A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓➤ S

NT9F04BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, New System (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- CCS 300 is the networking functionality of SYMPOSIUM Call Center systems.
- The initial release of SYMPOSIUM Call Center Server networking will only include Interworking with Network ACD. Additional networking functionality which includes network wide skills-based routing will be provided in a future software upissue.
- Requires SYMPOSIUM Base Software, CCS 100, and CCS 200 as prerequisite. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of CCS300 includes the X11 Call Center Networking at no additional charge. The X11 packages SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW0222A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F04CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, New System (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 300 is the networking functionality of SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS 100, and CCS 200 as prerequisite. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The initial release of SYMPOSIUM Call Center Server networking will only include Interworking with Network ACD. Additional networking functionality, which includes network wide skills based routing, will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of CCS300 includes the X11 Call Center Networking at no additional charge. The X11 packages SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW0222A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓ ➤ S

NT9F04DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, New System (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- CCS 300 is the networking functionality of SYMPOSIUM Call Center systems.
- The initial release of SYMPOSIUM Call Center Server networking will only include Interworking with Network ACD. Additional networking functionality, which includes network wide skills based routing, will be provided in a future software upissue.
- Requires SYMPOSIUM Base Software, CCS 100, and CCS 200 as prerequisite. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of CCS300 includes the X11 Call Center Networking at no additional charge. The X11 packages SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW0222A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NT9F04EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, New System (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 300 is the networking functionality of SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS 100, and CCS 200 as prerequisite. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- Transaction fee SV000117, $500.00, applies whenever additional agents or features are added.
- The initial release of SYMPOSIUM Call Center Server networking will only include Interworking with Network ACD. Additional networking functionality, which includes network wide skills based routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C: the purchase of CCS300 includes the X11 Call Center Networking at no additional charge. The X11 packages SW0050B, Networking, SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW0222A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

NT9F04GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 - New System Software, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F04HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 - New System Software, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

Status
➤ S

NT9F04JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 - New System Software, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		W1/ S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F06AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C. The purchase of Call Center Software 100 also includes the following X11 prerequisites: Symposium Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All customers with any version (Fundamental, Enhanced or Virtual) of Meridian MAX 7, 8, and 9 may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F06BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C. The purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All customers with any version (Fundamental, Enhanced or Virtual) of Meridian MAX 7, 8, and 9 may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F06CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C. The purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All customers with any version (Fundamental, Enhanced or Virtual) of Meridian MAX 7, 8, and 9 may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F06DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C. The purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All customers with any version (Fundamental, Enhanced or Virtual) of Meridian MAX 7, 8, and 9 may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F06EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS 100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C. The purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All customers with any version (Fundamental, Enhanced or Virtual) of Meridian MAX 7, 8, and 9 may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

NT9F06GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F06HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F06JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F07AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX and CCR (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- All Meridian MAX users (any Release or version of a Release) who also have CCR may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F07BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX and CCR (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.
- There are no additional X11 prerequisites required for this package.
- All Meridian MAX users (any Release or version of a Release) who also have CCR may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F07CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX and CCR (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- All Meridian MAX users (any Release or version of a Release) who also have CCR may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F07DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX and CCR (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- All Meridian MAX users (any Release or version of a Release) who also have CCR may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F07EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX and CCR (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites required for this package.
- All Meridian MAX users (any Release or version of a Release) who also have CCR may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F07GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (5 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F07HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (20 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F07JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (200 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F08AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade From MAX NACD and/or NAC (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD and Network Administration Center may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F08BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from MAX NACD and/or NAC (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD and Network Administration Center may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F08CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from MAX NACD and/or NAC (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD and Network Administration Center may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F08DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from MAX NACD and/or NAC (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD and Network Administration Center may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F08EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from MAX NACD and/or NAC (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD and Network Administration Center may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F08GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (5 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F08HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (20 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F08JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (200 Agents)	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F09AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 6 (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Que for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software package is required (additional charge).
- All Meridian MAX 6 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F09BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 6 (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Call Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Que for IVR.
- For SYMPOSIUM Call Center system that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All Meridian MAX 6 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F09CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 6 (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center Server. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Card Center Server Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Que for IVR.
- For SYMPOSIUM Call Center system that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All Meridian MAX 6 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F09DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 6 (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Que for IVR.
- For SYMPOSIUM Call Center system that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All Meridian MAX 6 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F09EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 6 (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Que for IVR.
- For SYMPOSIUM Call Center system that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- All Meridian MAX 6 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F09GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 6, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F09HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 6, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F09JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 6, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F10AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade From NACD (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS 300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD may upgrade to this package. In the event that CCS100 is purchased as a "new system" then CCS300 must also be purchased as a "new system".
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F10BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from NACD (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS 300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD may upgrade to this package. In the event that CCS100 is purchased as a "new system" then CCS300 must also be purchased as a "new system".
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F10CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from NACD (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS 300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD may upgrade to this package. In the event that CCS100 is purchased as a "new system" then CCS300 must also be purchased as a "new system".
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F10DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from NACD (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS 300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD may upgrade to this package. In the event that CCS100 is purchased as a "new system" then CCS300 must also be purchased as a "new system".
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F10EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 300, Upgrade from NACD (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C; the purchase of CCS300 includes the X11 prerequisite Call Center Network at no additional charge; and the X11 packages, SW0050B, Networking; SW0051B, ISDN Networking; SW0052D, Private ISDN Networking; and SW022A, Enhanced ACD Overflow are required which are available at an additional charge.
- The initial release of SYMPOSIUM Call Center Server (CCS) networking includes only Interworking with Network ACD. Additional networking functionality which includes Network Wide Skills-based Routing will be provided in a future software upissue.
- CCS300 is the networking functionality for SYMPOSIUM Call Center systems.
- Requires SYMPOSIUM Base Software, CCS100, and CCS200 as prerequisites. CCS100, CCS200, and CCS300 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 and CCS300 must also be set at 200 agents.)
- All customers who have implemented Network ACD may upgrade to this package. In the event that CCS100 is purchased as a "new system" then CCS300 must also be purchased as a "new system".
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F10GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NACD, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F10HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NACD, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F10JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 300 Upgrade, From NACD, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F11AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade From MAX 5 (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1/ S1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX 5 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F11BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 5 (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1/ S1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX 5 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F11CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 5 (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1/ S1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX 5 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F11DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 5 (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1/ S1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX 5 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F11EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX 5 (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1/ S1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX 5 customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F11GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 5, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F11HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 5, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F11JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, MAX 5, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F12AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from CCR only (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100/client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All customers who have implemented a 20 or 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F12BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from CCR only (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100/client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All customers who have implemented a 20 or 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F12CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from CCR only (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100/client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All customers who have implemented a 20 or 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F12DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from CCR only (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100/client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All customers who have implemented a 20 or 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F12EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from CCR only (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100/client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All customers who have implemented a 20 or 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F12GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, CCR, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F12HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, CCR, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F12JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, CCR, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F13AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from CCR only (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisite. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites for this package.
- All customers who have implemented the 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F13BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from CCR only (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisite. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites for this package.
- All customers who have implemented the 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F13CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from CCR only (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisite. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites for this package.
- All customers who have implemented the 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F13DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from CCR only (100 Agent)	11C X11 R22D; 51C X11 R22D; 61 X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisite. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites for this package.
- All customers who have implemented the 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F13EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from CCR only (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R2D2; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisite. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents.)
- There are no additional X11 prerequisites for this package.
- All customers who have implemented the 240 script version of CCR but who do not have any version of Meridian MAX running in their call centers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F13GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, CCR, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F13HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, CCR, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F13JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, CCR, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F14AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from Max Pre-release 5 or PDP (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C the purchase of Call Center Software 100 also includes the following X11 prerequisites: Next Generation Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- All Meridian MAX customers on a version older than Release 5 (not including Release 5) or PDP customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F14BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX customers on a version older than Release 5 (not including Release 5) or PDP customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F14CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX customers on a version older than Release 5 (not including Release 5) or PDP customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F14DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C, the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced customer Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian Option 11C, the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX customers on a version older than Release 5 (not including Release 5) or PDP customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F14EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- For SYMPOSIUM Call Center systems that are used with Meridian 1 Options 51C, 61C, 81, and 81C the purchase of Call Center Software 100 also includes the following X11 prerequisites: SYMPOSIUM Call Center, Enhanced ACD Routing, Enhanced Custom Controlled Routing, and Hold in Queue for IVR.
- For SYMPOSIUM Call Center systems that are used with Meridian 1 Option 11C the X11 Release 22D Enterprise Software is required (additional charge).
- CCS100 enables the basic call processing, supervision, and MIS capabilities of SYMPOSIUM Call Center. This software package enables Call Resource Manager and Real-Time Interface keycodes.
- This package includes 100 client/supervisor sessions. There can only be a total of 100 client/supervisor sessions enabled regardless of the number of agent packages purchased.
- Requires SYMPOSIUM Base Software as a prerequisite.
- All Meridian MAX customers on a version older than Release 5 (not including Release 5) or PDP customers may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F14GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F14HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F14JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F15AA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing. (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents).
- There are no additional X11 prerequisites for this package.
- All Meridian MAX Release 7, 8, and 9 customers using the Virtual package may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F15BA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (10 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing. (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents).
- There are no additional X11 prerequisites for this package.
- All Meridian MAX Release 7, 8, and 9 customers using the Virtual package may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F15CA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (50 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing. (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents).
- There are no additional X11 prerequisites for this package.
- All Meridian MAX Release 7, 8, and 9 customers using the Virtual package may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F15DA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (100 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing. (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents).
- There are no additional X11 prerequisites for this package.
- All Meridian MAX Release 7, 8, and 9 customers using the Virtual package may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F15EA

Description	System Compatibility	Product compatibility	W/S
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (500 Agent)	11C X11 R22D; 51C X11 R22D; 61C X11 R22D; 81 X11 R22D; 81C X11 R22D	Meridian MAX R7,8	W1

Notes:

- CCS200 enables the additional call processing functionality for SYMPOSIUM Call Center systems. This software enables the following keycodes: Individual Call Level Reporting, Host Data Exchange API, Advanced Scripting Commands, Broadcast Announcement, Host Enhanced Routing (Meridian Link), and Host Enhanced Voice Processing. (Meridian Link).
- Requires SYMPOSIUM Base Software and CCS100 as prerequisites. CCS100 and CCS200 agent increments must be set at the same level. (E.g. If CCS100 is set at 200 agents, then CCS200 must be set at 200 agents).
- There are no additional X11 prerequisites for this package.
- All Meridian MAX Release 7, 8, and 9 customers using the Virtual package may upgrade to this package.
- During the initial upgrade, a customer may purchase an unlimited number of agents at the upgrade price. Future upgrades will be charged at New System Prices.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NT9F15GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 5 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F15HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 20 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NT9F15JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 200 Agents	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
>> # S

NT9F17AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center - 1 Agent Increment			W1

Notes:

- The one agent increment can be added to the base package to increase the number of SYMPOSIUM Express Call Center agents, where the number of agents is defined as 'concurrently logged in agents, regardless of agent state.'
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 40 agents is the maximum number of agents supported.

Status
>> # S

NT9F17BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center - 5 Agent Increment			W1

Notes:

- The five agent increment can be added to the base package to increase the number of SYMPOSIUM Express Call Center agents, where the number of agents is defined as 'concurrently logged in agents, regardless of agent state.'
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 40 agents is the maximum number of agents supported.
- The Meridian 1 Serial number must be provided when ordering this code for use with an existing Meridian 1 system.
- The Meridian 1 Serial number must be provided when ordering this code for use with an existing Meridian 1 system or when expanding an existing SECC.

Status
>> # S

NT9F17CA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center - 10 Agent Increment			W1

Notes:

- The ten agent increment can be added to the base package to increase the number of SYMPOSIUM Express Call Center agents, where the number of agents is defined as 'concurrently logged in agents, regardless of agent state.'
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 40 agents is the maximum number of agents supported.
- The Meridian 1 Serial number must be provided when ordering this code for use with an existing Meridian 1 system or when expanding an existing SECC.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
>> # S

NT9F19AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Replacement/Up-Issue Software Package			W0

Notes:

- Orderable as a replacement for the original CDs in case they are lost or damaged.
- A keycode will be issued to match the existing configuration.
- The replacement/up-issue software package cannot be used to increase the agent capacity.
- Additional agent increment packages must be purchased to increase the agent count if the agent count is to be increased.
- The PBX serial number is required to issue the keycode.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTHF01AA	Symposium Express Call Center Release 1 0 Server Application CD	1	NTHF04AA	Symposium Express Call Center Supplementary CD
1	NTHF02AA	SYMPOSIUM Express Call Center Release 1 0 Client Application CD, English			

Status
S

NT9F19AB

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center 2.0 Replacement/Up-Issue Software Package			W0/ S1

Notes:

- Orderable as a replacement for the original CDs in case of loss or damage.
- A keycode will be issued to match the existing PBX configuration. The switch serial number must be provided with the order to issue the keycode.
- The replacement/up-issue software package cannot be used to increase agent capacity.
- Additional agent increment packages must be purchased if the agent count is to be increased.

Qty	Order code	Description	Qty	Order code	Description
1	NTHF01AB	Symposium Express Call Center Release 2 0 Server Application CD	1	NTHF04AB	Symposium Express Call Center Supplementary CD
1	NTHF02AB	SYMPOSIUM Express Call Center Release 2 0 Client Application CD, English			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F27AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Peripherals Package	11C; 51C; 61C; 81; 81C		W1

Notes:

- Must be ordered in conjunction with a SYMPOSIUM Call Center Server hardware platform.

Qty	Order code	Description	Qty	Order code	Description
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male	1	NTRH9014	Three Button Mouse
1	NTRH9011	14" SVGA Color Monitor	1	NTRH9016	External Modem 33 6
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

Status
✓ ➤ S

NT9F27AC

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 1003t Peripherals Package			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male	1	NTRH9016	External Modem 33 6
1	NTRH9011	14" SVGA Color Monitor			

Status
➤ S

NT9F41AD

Description	System Compatibility	Product compatibility	W/S
Release 3.0 Base Software and Documentation	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9F43AC

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Release 1.5 Client CD-ROM			W1

Notes:
- Additional SYMPOSIUM Call Center Client CD-ROMs can be ordered to assist in installation. The server CD-ROM and the client CD-ROM MUST be the same release.
- Transaction fee $99.00.

Status
★ ➤ S

NT9F43AD

Description	System Compatibility	Product compatibility	W/S
DMS SCCS Release 3.0 CD-ROM Client CD (Merchandise)	DMS-100		S1

Status
➤ S

NT9F46AC

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly			W0

Notes:
- The Supplementary CD-ROM Assembly contains two CD-ROMs containing the latest patches for the client and the server.

Status
➤ S

NT9F51AC

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Release 1.5 Replacement Software			S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F90AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51			W1/ S3

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server Hardware with Windows NT 3.51.
- When placing an order for SYMPOSIUM Call Center Server, an identifier must be specified. Choose ONE of the following: NTZD0001 - New SYMPOSIUM Call Center orders - NTZD0002 - Server upgrade order - NTZD0003 - Spare server order - NTZD0004 - NCC server order.
- Requires NT9F27AC Hardware Peripherals Package for 1003t.
- Requires either A0798087, PCI Ethernet Adapter; or NTRH9010, PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	
1	A0677506	Dry Clean Cartridge	
3	A0677508	13GB Data Cartridge	
1	NT3R7207	SYMPOSIUM Call Center Operating System CD	
1	NT3R7208	Microsoft DOS 6 20	
1	NT3R9501	Software Assembly, Emergency Repair Disks	
1	NT9F50AA	SYMPOSIUM Call Center Operating System Diskettes	
1	NT9F9001	Symposium Call Center Server 1003t w/RAID	
	Each Package Includes:		
	1	NTRH9034	Backup Tape Drive
	1	NTRH9100	SYMPOSIUM Call Center Server 1003t Base System
	1	P0911847	Nortel Networks Branding Label
	1	P0911914	SYMPOSIUM Call Center Server 1003t Gasketing
1	NTRH8046	SYMPOSIUM Call Center Server 1003t SCSI Backplane Firmware	
1	P0911675	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NT9F90BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0			W1/ S3

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server Hardware with Windows NT 4.0.
- When placing an order for SYMPOSIUM Call Center Server, an identifier must be specified. Choose ONE of the following: NTZD0001 - New SYMPOSIUM Call Center orders - NTZD0002 - Server upgrade order - NTZD0003 - Spare server order - NTZD0004 - NCC server order.
- Requires NT9F27AC Hardware Peripherals Package for 1003t.
- Requires either A0798087, PCI Ethernet Adapter; or NTRH9010, PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	
1	A0677506	Dry Clean Cartridge	
3	A0677508	13GB Data Cartridge	
1	A0767488	WinNT Certificate of Authenticity	
1	NT3R7208	Microsoft DOS 6 20	
1	NT3R9501	Software Assembly, Emergency Repair Disks	
1	NT9F50AB	SYMPOSIUM Call Center Server Operating System Diskettes, version NT 4 0	
1	NT9F52AB	SYMPOSIUM Call Center Server Operating System CD-Rom, version NT 4 0	
1	NT9F9001	Symposium Call Center Server 1003t w/RAID	
	Each Package Includes:		
	1	NTRH9034	Backup Tape Drive
	1	NTRH9100	SYMPOSIUM Call Center Server 1003t Base System
	1	P0911847	Nortel Networks Branding Label
	1	P0911914	SYMPOSIUM Call Center Server 1003t Gasketing
1	NTRH8046	SYMPOSIUM Call Center Server 1003t SCSI Backplane Firmware	
1	P0911675	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	

Status
➤ S

NT9J93AD

Description	System Compatibility	Product compatibility	W/S
PRI/DTI Echo Canceler to I/O Cable (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; N; NT; XN; XT		W1

Status
➤ S

NT9J96AC

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (40 In.)	A; L; LE; M; MS		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9J96AD

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (70 In.)	A; L; LE; M; MS		W1

Status
➤ S

NT9J96AE

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (85 In.)	A; L; LE; M; MS		W1

Status
➤ S

NT9J96AG

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (12 Ft.)	A; L; LE; M; MS		W1

Status
➤ S

NT9J96AH

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (14 Ft.)	A; L; LE; M; MS		W1

Status
➤ S

NT9J96AJ

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (16 Ft.)	A; L; LE; M; MS		W1

Status
➤ S

NT9J97AC

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (40 In.)	N; NT; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9J97AD

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (70 In.)	N; NT; XN; XT		W1

Status
➤ S

NT9J97AE

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (85 In.)	N; NT; XN; XT		W1

Status
➤ S

NT9J97AG

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (12 Ft.)	N; NT; XN; XT		W1

Status
➤ S

NT9J97AH

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (14 Ft.)	N; NT; XN; XT		W1

Status
➤ S

NT9J97AJ

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (16 Ft.)	N; NT; XN; XT		W1

Status
➤ S

NT9J98AC

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (40 In.)	ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9J98AD

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (70 In.)	ST; STE		W1

Status
➤ S

NT9J98AE

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (85 In.)	ST; STE		W1

Status
➤ S

NT9J99AC

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (40 In.)	ST; STE		W1

Status
➤ S

NT9J99AD

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (70 In.)	ST; STE		W1

Status
➤ S

NT9J99AE

Description	System Compatibility	Product compatibility	W/S
Intra-Cabinet Network Cable (85 In.)	ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K05AA03

Description	System Compatibility	Product compatibility	W/S
Meridian M2006 Single Line Digital Telephone, Basic, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

Status
➤ S

NT9K05AA35

Description	System Compatibility	Product compatibility	W/S
Meridian M2006 Single Line Digital Telephone, Basic, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

Status
➤ S

NT9K05AA93

Description	System Compatibility	Product compatibility	W/S
Meridian M2006 Single Line Digital Telephone, Basic, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

Status
➤ S

NT9K08AA03

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone, Basic, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K08AA35

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone, Basic, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) Notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

Status
➤ S

NT9K08AA93

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone, Basic, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) Notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.

Status
➤ S

NT9K08AB03

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone, Basic, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K08AB35

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone, Basic, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.

Status
➤ S

NT9K08AB93

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone, Basic, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.

Status
➤ S

NT9K08AC03

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone with Display, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) Notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.
- Meridian Display Option (3 language) is standard equipment.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K08AC35

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone with Display, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) Notes.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NT9K08AC93

Description	System Compatibility	Product compatibility	W/S
Meridian M2008 Standard Business Telephone with Display, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MAC (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Meridian Modular options are filed installable by a qualified technician.
- All Meridian Modular options are field installable by a qualified technician.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NT9K08AD03

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone with Display, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.
- Meridian Display Option (3 language) is standard equipment.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K08AD35

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone with Display, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NT9K08AD93

Description	System Compatibility	Product compatibility	W/S
Meridian M2008HF Standard Business Telephone with Display, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Requires X11 Release 14 and later software.
- Modular options are field installable by a qualified technician.
- Backward compatible to all QPC578 vintage line cards.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NT9K16AA03

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone, Basic, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:

- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K16AA35

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone, Basic, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

Status
➤ S

NT9K16AA93

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone, Basic, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- All Meridian Modular options are field installable by a qualified technician.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

Status
➤ S

NT9K16AC03

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone with Display, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K16AC35

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone with Display, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

Status
➤ S

NT9K16AC93

Description	System Compatibility	Product compatibility	W/S
Meridian M2616 Performance-Plus Telephone with Display, Gray	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.

Status
➤ S

NT9K18AC03

Description	System Compatibility	Product compatibility	W/S
Meridian M2216ACD Telephone, Black	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Includes Meridian Display Option.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NT9K18AC35

Description	System Compatibility	Product compatibility	W/S
Meridian M2216ACD Telephone, Ash	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Includes Meridian Display Option.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NT9K18AC93

Description	System Compatibility	Product compatibility	W/S
Meridian M2216ACD Telephone, Grey	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; STE		W1

Notes:
- ATA/MCA (NT2K69AA) ready. Reference ATA/MCA (NT2K69AA) notes.
- Includes Meridian Display Option.
- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- Meridian Display Option (3 language) is standard equipment.

Status
➤ S

NTAG26AB

Description	System Compatibility	Product compatibility	W/S
Multi-Frequency IPE Receiver Card (4 Channel)			W1

Notes:
- The "AB" vintage of the MF receiver (NTAG26) card must be used in situations where the Meridian 1 is acting as a Public Service Answering Point (PSAP).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAG36AC

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Base Spare Card			W1

Notes:

- This card has no ports activated and is to be ordered for sparing purposes only. Port activation can only be achieved by using the security keycode and security device from the originally purchased MIRAN Small Card (NTVP1000), MIRAN Medium Card (NTVP1001), or MIRAN Large Card (NTVP1002).

Status
➤ S

NTAG81AA

Description	System Compatibility	Product compatibility	W/S
Audio Cable	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

NTAG81BA

Description	System Compatibility	Product compatibility	W/S
Maintenance Extender Cable	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

NTAG81CA

Description	System Compatibility	Product compatibility	W/S
PC Maintenance Cable	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

NTAG81DA

Description	System Compatibility	Product compatibility	W/S
VLAN Maintenance Cable	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK02BC

Description	System Compatibility	Product compatibility	W/S
SDI/DCH Card	11; 11C; 11E		W1

Status
➤ S

NTAK03DA

Description	System Compatibility	Product compatibility	W/S
TDS/DTR Card	11; 11C; 11E		W1

Status
✓ † S

NTAK09DA

Description	System Compatibility	Product compatibility	W/S
DTI/PRI Card	11; 11C; 11E		W1

Status
➤ S

NTAK1104

Description	System Compatibility	Product compatibility	W/S
PFTU/Console Power Cable	11; 11C; 11E		W1

Status
➤ S

NTAK1108

Description	System Compatibility	Product compatibility	W/S
SDI Cable	11; 11C; 11E	Fiber Remote	W1

Status
➤ S

NTAK1118

Description	System Compatibility	Product compatibility	W/S
Modem Cable (DB9 to DB25)	11; 11C; 11C COMPACT; 11E		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ B

NTAK11BD

Description	System Compatibility	Product compatibility	W/S
Main/Expansion Cabinet	11C		W1

Status
➤ S

NTAK1204

Description	System Compatibility	Product compatibility	W/S
Expansion Cable - Copper (7 Ft.)	11; 11E		W1

Status
✓ ➤ S

NTAK1305

Description	System Compatibility	Product compatibility	W/S
SCSI Cable (6 Ft.)		Meridian Mail Card Option	W1

Status
➤ S

NTAK13AA

Description	System Compatibility	Product compatibility	W/S
Power Board		Meridian Mail Card Option	W1

Status
➤ S

NTAK14BA

Description	System Compatibility	Product compatibility	W/S
68K Processor Pack		Meridian Mail Card Option	W1

Status
† ➤ S

NTAK15AB

Description	System Compatibility	Product compatibility	W/S
Digital Voice Processor Card		Meridian Mail Card Option R8	W1

Notes:

- Required for Pre-Release 9 systems or for spares.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTAK16AB

Description	System Compatibility	Product compatibility	W/S
C25 Voice Processor Card		Meridian Mail Card Option R8	W0

Notes:
- Required for Pre-Release 9 systems or for spares.
- Each C25 Voice Processor Card provides two additional channels of voice services in the Meridian Mail Card Option system.
- A maximum of two C25 Voice Processor Cards may be installed into the Meridian Mail Card Option system.

Status
➤ S

NTAK17AB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Base Pack, 2-6 Ports		Meridian Mail Card Option	W1

Status
➤ S

NTAK17BB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Base Package, 8-12 Ports		Meridian Mail Card Option	W1

Status
➤ B

NTAK18BA

Description	System Compatibility	Product compatibility	W/S
RS232C Service Module		Meridian Mail Card Option	W1

Status
➤ S

NTAK19FB

Description	System Compatibility	Product compatibility	W/S
4 Port SDI Cable	11; 11C; 11E		W1

Notes:
- used with NTAK02

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK21BA

Description	System Compatibility	Product compatibility	W/S
Expansion Cartridge	11		W1

Status
➤ S

NTAK27AA

Description	System Compatibility	Product compatibility	W/S
Option 11 Cabinet Pedestal	11; 11C; 11E		W1

Notes:
- The Option 11 pedestal is recommended for all Option 11 systems that are not wall-mounted.
- One pedestal is required per cabinet.

Status
➤ S

NTAK28AB

Description	System Compatibility	Product compatibility	W/S
Battery Junction Box	11; 11C; 11E		W1

Notes:
- This package includes a NTAK0420 power cable.
- For DC systems only.

Status
➤ B

NTAK30DB

Description	System Compatibility	Product compatibility	W/S
External Tape Drive Package, Tandberg		Meridian Mail Card Option R8,9,10,11; Meridian Mail EC11 R10,11	W1

Notes:
- The A0721902 also contains a 220V Power cord, SCSI Cable, 2.5GB Tape, and a Tandberg Termination Update Document.
- An external Tape Drive package must be utilized for initial installation of the Meridian Mail software, database backup, restore of information to disk, and software upgrades.

Qty	Order code	Description	Qty	Order code	Description
1	A0721902	Tandberg Tape Drive Unit - External			

Status
➤ S

NTAK36AA

Description	System Compatibility	Product compatibility	W/S
Peripheral Cable Female		Meridian Mail Card Option	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK37AA

Description	System Compatibility	Product compatibility	W/S
Peripheral Cable Male		Meridian Mail Card Option	W1

Status
➤ S

NTAK39AB

Description	System Compatibility	Product compatibility	W/S
Tape Drive Wall Mounting Kit		Meridian Mail Card Option; Meridian Mail EC11	W0

Notes:
- Compatible with NTAK30DB External Tandberg Tape drive only.

Status
✓➤ S

NTAK40AA

Description	System Compatibility	Product compatibility	W/S
Networking Hardware Kit		Meridian Mail Card Option	W1

Notes:
- Required when networking to pre-MM11 Meridian Mail Networking sites.

Qty	Order code	Description	
1	A0379350	25 Pair Double Ended Cable	
1	A0379351	25 Pair Single Ended Cable	
1	NTAK18BA	RS232C Service Module	
1	NTAK37AA	Peripheral Cable Male	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† S

NTAK57AG

Description	System Compatibility	Product compatibility	W/S
General Business Software	11 X11 R18		S1

Notes:
- Option 11 System Software is equipped with 200 Base TNs.

Status
† S

NTAK57BG

Description	System Compatibility	Product compatibility	W/S
Enhanced Business Software	11 X11 R18		S1

Notes:
- Option 11 System Software is equipped with 200 Base TNs.

Status
† S

NTAK57CG

Description	System Compatibility	Product compatibility	W/S
Private Networking Software	11 X11 R18		S1

Notes:
- Requires QPC471B vintage or later if DTI is utilized.

Status
† S

NTAK57DG

Description	System Compatibility	Product compatibility	W/S
Advanced Applications Software	11 X11 R18		S1

Notes:
- Option 11 System Software is equipped with 200 Base TNs.

Status
† S

NTAK57GG

Description	System Compatibility	Product compatibility	W/S
General Business Software (no DISA)	11 X11 R18		S1

Notes:
- Option 11 System Software is equipped with 200 Base TNs.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† S

NTAK57HG

Description	System Compatibility	Product compatibility	W/S
Enhanced Business Software (no DISA)	11 X11 R18		S1

Notes:
- Option 11 System Software is equipped with 200 Base TNs.

Status
† S

NTAK57IG

Description	System Compatibility	Product compatibility	W/S
Private Networking Software (no DISA)	11 X11 R18		S1

Status
➤ S

NTAK72GN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European Card Option		Meridian Mail Card Option R10	W0

Status
➤ S

NTAK72HN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 2 Card Option		Meridian Mail Card Option R10	W0

Status
➤ S

NTAK72KN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape Asia/Pacific Card Option		Meridian Mail Card Option R10	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK72LN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape North American Card Option		Meridian Mail Card Option R10	W0

Notes:
- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.

Status
➤ S

NTAK72PN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 3 Card Option		Meridian Mail Card Option R10	W0

Status
➤ S

NTAK72QN

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 10.11 Master Tape European 4 Card Option		Meridian Mail Card Option R10	W0

Status
➤ S

NTAK75AB

Description	System Compatibility	Product compatibility	W/S
2-4 Hour Battery Back-Up Unit	11; 11C; 11E		W1

Notes:
- Each cabinet requires one NTAK75 unit.
- This package includes a NTAK0420 power cable.

Status
➤ S

NTAK76AB

Description	System Compatibility	Product compatibility	W/S
15-30 Minute Battery Back-up Unit	11; 11C; 11E		W1

Notes:
- This package includes a NTAK0420 power cable.
- Each cabinet requires one NTAK76 unit.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK80AA

Description	System Compatibility	Product compatibility	W/S
Option 11 System Back-Up Cartridge	11		W1

Notes:
- This cartridge is not supported on the Option 11E with X11 Release 20.
- This cartridge is recommended for back-up and restoration of Option 11 system data.

Status
➤ S

NTAK9204

Description	System Compatibility	Product compatibility	W/S
OPS Cable	11		W1

Status
➤ S

NTAK92BA

Description	System Compatibility	Product compatibility	W/S
OPS Protection Module	11; 11C; 11C COMPACT; 11E		W1

Qty	Order code	Description	Qty	Order code	Description
2	NTAK9204	OPS Cable			

Status
➤ S

NTAK93AB

Description	System Compatibility	Product compatibility	W/S
DCHI Card	11; 11C; 11E		W1

Notes:
- A D-Channel is required to support Primary Rate Interface (PRI). The DCHI card attaches to the NTAK09AA PRI/DTI card. Maximum one DCHI per card.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTAK98AA

Description	System Compatibility	Product compatibility	W/S
Power Supply Cable	11; 11C; 11C COMPACT; 11E		W1

Notes:
- Required for use with NTAK04AB - AC/DC Power Supply Unit.

Status
➤ S

NTBK04AA

Description	System Compatibility	Product compatibility	W/S
1.544 MByte Carrier Cable	11		W1

Status
➤ S

NTBK22AA

Description	System Compatibility	Product compatibility	W/S
Option 11E MISP Circuit Card	11; 11C; 11E		W1

Notes:
- This card is required in an Option 11 or 11E system using ISDN Basic Rate (BRI).

Status
➤ S

NTBK45AC

Description	System Compatibility	Product compatibility	W/S
System Core Pack	11E		W1

Notes:
- This component replaces the CPU/Conf card (NTAK01) and one TDS/DTR card (NTAK03) available on the Option 11 with Releases 16 and 18.

Status
➤ S

NTBK47AB

Description	System Compatibility	Product compatibility	W/S
Expansion Daughterboard	11E		W1

Notes:
- This component replaces the Expansion Cartridge available on the Option 11 with Release 16 and 18.
- This component is required in any Option 11E multi-cabinet configuration or a single cabinet configuration requiring additional memory.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTBK48AA

Description	System Compatibility	Product compatibility	W/S
3-port SDI Cable (1.5m or 5 Ft.)	11C; 11C COMPACT; 11E		W1

Notes:

- This component replaces the CPU/Conf card (NTAK01) and one TDS/DTR card (NTAK03) available on the Option 11 with Releases 16 and 18.
- This component replaces the 2-port SDI cable (NTAK19AA) and the 1-port SDI cable (NTAK1118) available on the Option 11 with Releases 16 and 18.

Status
➤ S

NTBK50AA

Description	System Compatibility	Product compatibility	W/S
2.0MB Primary Rate Interface Card	11C		W1

Status
➤ S

NTBK54AB

Description	System Compatibility	Product compatibility	W/S
Main Fiber Interface (MFI) Kit	11E		W1

Notes:

- This package is required to allow the Option 11E Main Cabinet to interface with a fiber connection to either one or two expansion cabinets.
- Only one MFI is required per Option 11E system when a fiber connection between cabinets is used.
- This power cable is required to power one MFI unit.
- One Ground Bar (NTBK80AA) is required to support this MFI unit and the associated EFI unit(s). This item must be ordered in addition to the MFI Kit when the MFI Kit is ordered separately. A ground bar is included in the 2nd Expansion Cabinet assembly package (e.g., AS1173 & AS1174).

Qty	Order code	Description	Qty	Order code	Description
1	NTBK62AB	MFI/EFI Power Cable			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTBK55AB

Description	System Compatibility	Product compatibility	W/S
Expansion Fiber Interface (EFI) Kit	11E		W1

Notes:
- This package is required to allow the Option 11E Main Cabinet to interface with a fiber connection to either one or two expansion cabinets.
- This power cable is required to power one MFI unit.
- Only one EFI is required per Option 11E system when a fiber connection is used.

Qty	Order code	Description	Qty	Order code	Description
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	1	NTBK62AB	MFI/EFI Power Cable

Status
➤ S

NTBK62AB

Description	System Compatibility	Product compatibility	W/S
MFI/EFI Power Cable			W1

Notes:
- This component is required to power one MFI or one EFI unit.

Status
➤ S

NTBK80AA

Description	System Compatibility	Product compatibility	W/S
Ground Bar	11C; 11E		W1

Notes:
- This component is required to properly ground the system when a fiber connection is used between cabinets.

Status
➤ S

NTBK81AA

Description	System Compatibility	Product compatibility	W/S
Fiber Management Kit	11E		W1

Notes:
- The Fiber Management Kit includes a fiber reel/management unit and a grommet to control fiber entering/leaving the cabinet.
- One fiber cable is required per Option 11E expansion cabinet in a three-cabinet Option 11E configuration.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTBK83AG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - General Business Package	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83BG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Enhanced Business Package	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83CG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Enterprise Business Package	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83DG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - General (No DISA)	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTBK83EG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Enhanced (No DISA)	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83FG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Enterprise Business (No DISA)	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83GG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTBK83HG

Description	System Compatibility	Product compatibility	W/S
Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package (No DISA)	11E		S1

Notes:
- The Option 11/11E/11C Site ID is required when ordering this code.

Status
➤ S

NTCK45AA

Description	System Compatibility	Product compatibility	W/S
Cable - 2.0MB DDP to I/O 8 Ft.	51C; 61C; 81; 81C		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTCK78AA

Description	System Compatibility	Product compatibility	W/S
Cable - 2.0MB DDP to MDF 50 Ft.	51C; 61C; 81; 81C		W1

Status
➤ S

NTCK79AA

Description	System Compatibility	Product compatibility	W/S
Cable - 2.0MB DDP Coax to LTU 50 Ft.	51C; 61C; 81; 81C		W1

Status
➤ S

NTCW80CA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Base Card			W1

Notes:
- This card has no ports or software activated and is to be ordered for ITG sparing purposes only. Port activation can only be achieved by using the security keycode and dongle device from the originally purchased Meridian ITG package.

Status
➤ S

NTCW84EA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 D-Channel PCMCIA Pigtail Cable	11C; 51C; 61C; 81; 81C		W0

Notes:
- Required for providing D-Channel capability to the 24-Port ITG 2.0 card.
- The D-Channel PCMCIA card will come with this cable already installed. This order code should be used as a replacement only.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTCW84JA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 I/O Panel Mounting Connector	51C; 61C; 81; 81C		W0

Notes:
- The connector is contained in all large system packages with D-Channel capability (Connector has ITG 2.0 specific filtering).

Status
➤ S

NTCW84KA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter	11C; 51C; 61C; 81; 81C		W0

Notes:
- The cable is required for all packages or cards for providing D-Channel capability to the LAN/WAN environment.

Status
➤ S

NTCW84LA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA)	11C; 51C; 61C; 81; 81C		W0

Notes:
- The cable required ITG card NTCW80CA for all small and large UPGRADE packages for providing D-Channel capability to the LAN/WAN environment.

Status
➤ S

NTCW84MA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack	11C; 51C; 61C; 81; 81C		W0

Notes:
- This cable is required for all small and large upgrade packages with packs NTCW80AA for providing D-Channel capability to the LAN/WAN environment.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK16BA

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini 48 Port Digital Line Card			W1

Notes:
- This pack is unique to Option 11C Mini, and will only function in slot 4 of an Option 11C Mini main chassis.

Status
➤ S

NTDK18AA

Description	System Compatibility	Product compatibility	W/S
Cabinet Upgrade Kit			W1

Notes:
- This is required when an existing cabinet is first being upgraded to support 3 or more expansion cabinets.

Status
➤ S

NTDK19AA

Description	System Compatibility	Product compatibility	W/S
SSC Upgrade Kit			W1

Notes:
- This is required when an NTDK20AB SSC is first being equipped with dual port fiber daughterboards. Not required for NTDK20DA.

Status
➤ S

NTDK20EA

Description	System Compatibility	Product compatibility	W/S
Option 11C System Core Card	11C		W1

Status
➤ S

NTDK21AA

Description	System Compatibility	Product compatibility	W/S
Option 11C- Blank Software Daughterboard	11C; 11C COMPACT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK22AA

Description	System Compatibility	Product compatibility	W/S
30 Ft. Fiber Daughterboard - Multi Mode	11C; 11C COMPACT		W1

Notes:

- 'Single' fiber daughterboards can be connected to a single expansion cabinet. This daughterboard is exactly matched with one fiber expansion cabinet of the corresponding kind (2 mile multimode, 2 mile single mode, 30 feet fiber).

Status
S

NTDK23AA

Description	System Compatibility	Product compatibility	W/S
30 Ft. Fiber Receiver Card	11C		W1

Status
✓➤ S

NTDK23BA

Description	System Compatibility	Product compatibility	W/S
30 Ft. Fiber Receiver Card	11C		W1

Status
➤ S

NTDK24AB

Description	System Compatibility	Product compatibility	W/S
2 Mile Fiber Daughterboard - Multi-Mode	11C		W0

Notes:

- Single' fibre daughterboards can be connected to a single expansion cabinet. This daughterboard is exactly matched with one fibre expansion cabinet of the corresponding kind (2 mile multimode, 2 mile single mode, 30 feet fiber).

Status
➤ S

NTDK26AA

Description	System Compatibility	Product compatibility	W/S
Backwards Compatible Daughterboard	11C		W1

Status
➤ S

NTDK27AA

Description	System Compatibility	Product compatibility	W/S
Ethernet Adapter Cable	11C		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK30AA

Description	System Compatibility	Product compatibility	W/S
Database Upgrade Tool	11C		W1

Status
➤ S

NTDK32AA

Description	System Compatibility	Product compatibility	W/S
EC11 Backplane and Cabinet Assembly		Meridian Mail	W1

Status
➤ S

NTDK3302

Description	System Compatibility	Product compatibility	W/S
NLI Cable 10 Ft.		Meridian Mail	W1

Status
➤ S

NTDK3303

Description	System Compatibility	Product compatibility	W/S
NLI Cable 20 Ft.		Meridian Mail	W1

Status
➤ S

NTDK3304

Description	System Compatibility	Product compatibility	W/S
NLI Cable 30 Ft.	EC11	Meridian Mail	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK35AA

Description	System Compatibility	Product compatibility	W/S
AC/DC Power Supply		Meridian Mail	W1

Status
➤ S

NTDK36AA

Description	System Compatibility	Product compatibility	W/S
Bus Terminator	EC11	Meridian Mail; Meridian Mail EC11 R10	W1

Status
➤ S

NTDK48AA

Description	System Compatibility	Product compatibility	W/S
Main Cabinet Cable Kit	11C		W1

Qty	Order code	Description	Qty	Order code	Description
1	A0601396	Modem Eliminator Male to Female	1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)
1	A0601397	Modem Eliminator Female to Female	1	NTDK27AA	Ethernet Adapter Cable
1	NTAK1104	PFTU/Console Power Cable			

Status
➤ S

NTDK49AA

Description	System Compatibility	Product compatibility	W/S
Expansion Cabinet Cable Kit	11C		W1

Qty	Order code	Description	Qty	Order code	Description
1	A0601396	Modem Eliminator Male to Female	1	NTAK1104	PFTU/Console Power Cable
1	A0601397	Modem Eliminator Female to Female	1	NTAK1118	Modem Cable (DB9 to DB25)

Status
✓ § S

NTDK57AA

Description	System Compatibility	Product compatibility	W/S
Dongle	11C COMPACT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK58AA

Description	System Compatibility	Product compatibility	W/S
RSM 4 Port Breakout Cable		Meridian Mail EC11 R10	W1

Status
➤ S

NTDK59AA

Description	System Compatibility	Product compatibility	W/S
Alarm/Modem Cable Assembly-Initial Caps only		Meridian Mail	W1

Status
➤ S

NTDK66AB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modem Package		Meridian Mail EC11; Meridian Mail GP; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Modular Option EC; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0674453	33 6 KBPS External Data/Fax Modem	1	P0875141	Meridian Mail Modem Setup Document

Status
➤ S

NTDK68AA

Description	System Compatibility	Product compatibility	W/S
16MB SIMM	11C		W1

Notes:

- NTDK68AA is still currently available for Microcell customers running on Release 23 software. We recommend use of NTDK19AA kit which is installable on existing systems. NTDK19AA kit is mandatory for Release 24 LSE systems.

Qty	Order code	Description	Qty	Order code	Description
1	A0662646	16MB SIMM	1	P0854639	Upgrade Faceplate Label
1	P0854638	Memory Upgrade Instructions			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTDK74AB

Description	System Compatibility	Product compatibility	W/S
Card Option 4.5GB Disk Drive	11C; 11C COMPACT	Meridian Mail Card Option; Meridian Mail Compact Option	W1

Status
➤ B

NTDK78AA

Description	System Compatibility	Product compatibility	W/S
AC/DC Power Supply	11; 11C; 11E		W1

Notes:
- Must order associated NTAK98 cable separately.

Status
✓➤ S

NTDK79AA

Description	System Compatibility	Product compatibility	W/S
2 Mile Fiber Daughterboard Single Mode	11C		W1

Status
✓➤ S

NTDK80BA

Description	System Compatibility	Product compatibility	W/S
2 Mile Fiber Receiver Card - Single Mode	11C		W0

Status
➤ N

NTDK81AA

Description	System Compatibility	Product compatibility	W/S
Option 11C Blank Software Daughterboard	11C		W1

Notes:
- Requires Boot Code provided by NTDK20AB Release 11 or later System Core (CPU). Earlier releases of NTDK20AB can be updated from the software PCMCIA card (X11/23.30 or later) in an operating Option 11C.
- Requires X11/23.30 or later software

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDK84AA

Description	System Compatibility	Product compatibility	W/S
30 Ft. DUAL Port Fiber Daughterboard			W1

Notes:

- 'Dual' Fiber daughterboards can be connected to one or two expansion cabinets. This daughterboard may require one or two fiber expansion cabinets of the corresponding kind, depending on how many expansion cabinets are desired.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fiber daughterboard with the order.
- 'Dual' port daughterboard requires an SSC upgrade.

Status
➤ S

NTDK85AA

Description	System Compatibility	Product compatibility	W/S
2 Mile Multi Mode DUAL Port Fiber Daughterboard			W1

Notes:

- 'Dual' fiber daughterboards can be connected to one or two expansion cabinets. This daughterboard may require one or two expansion cabinets of the corresponding kind, depending on how many expansion cabinets are desired.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fiber daughterboard with the order.
- Dual port daughterboard requires an SSC upgrade.

Status
➤ S

NTDK97AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini System Controller Card (Blank)			W1

Notes:

- The Mini System Controller is for use only in an Option 11C Mini Main Chassis.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTDR68AA

Description	System Compatibility	Product compatibility	W/S
Reach Line Card - 16 Port	11; 11C; 11E; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:

- This IPE line card provides 16 ports for remote solution products and/or local digital telephone sets. This card includes the initial capacity to support 4 - Remote Office 9110 & 9115 users, 8 - Remote Office 9150 users, or 12 - MHO II users. Increased user capacity can be added to the line card by adding DSP Application Modules as needed.
- Included with this card is one basic RLC cable (NTDR79AA), a RLC Ethernet Adapter, Installer's notes, and the Remote Office 911x series & RLC release notes.

Status
✓➤ S

NTDR69AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 Unit			W1

Notes:

- Includes Remote Office 9150 unit, Remote Office 9150 power supply, North America power cord,9-pin serial cable, Remote Office 9150 installation & Admin Guide, Remote Office Product CD-ROM, and the Remote Office 911x series, 9150, and RLC release notes.
- This base unit can be configured for up to 32 digital telephones but only has the initial capacity to extend up to 8 simultaneous network access connections to the PBX. If more than 8 users are configured on the Remote Office unit and the Reach Line Card, they will share access to the 8 network access ports. Additional network access ports can be added in 8 port increments up to a total of 32 ports by adding DSP Application Modules.

Status
✓➤ S

NTDR70AA

Description	System Compatibility	Product compatibility	W/S
Reach Line Card - 32 Port - Option 51-81	11; 11C; 11E; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:

- This IPE line card provides 32 ports for remote solution products and/or local digital telephone sets. This card includes the initial capacity to support 4 - Remote Office 9110 & 9115 users, 8 - Remote Office 9150 users, or 12 - MHO II users. Increased user capacity can be added to the line card by adding DSP Application Modules as needed.
- Included with this card is one basic RLC cable (NTDR79AA), a RLC Ethernet Adapter, Installer's notes, and the Remote Office 911x series & RLC release notes.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTDR71AA

Description	System Compatibility	Product compatibility	W/S
Reach Line Card - 32 Port - Option 11	11; 11C; 11E; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:

- This IPE line card provides 32 ports for remote solution products and/or local digital telephone sets. This card includes the initial capacity to support 4 - Remote Office 9110 & 9115 users, 8 - Remote Office 9150 users, or 12 - MHO II users. Increased user capacity can be added to the line card by adding DSP Application Modules as needed.
- Included with this card is one basic RLC cable (NTDR79AA), a RLC Ethernet Adapter, Installer's notes, and the Remote Office 911x series & RLC release notes.

Status
✓ ➤ S

NTDR73AA

Description	System Compatibility	Product compatibility	W/S
DSP Application Module			W0

Notes:

- This module adds more processing power to the Reach Line Card and the Remote Office 9150 to provide additional simultaneous network access connections. It will normally be purchased as part of an expansion package but it is offerred as an individual item for custom configurations.
- Included with this module are the DSP Application Module Installer's Notes.

Status
✓ ➤ S

NTDR74AA

Description	System Compatibility	Product compatibility	W/S
BRI Module (U Interface)			W0

Notes:

- Adds the capacity for one ISDN BRI line to the Remote Office 9150 unit. Up to four total BRI modules can be installed on a single Remote Office 9150 unit.
- Included with this module are the Trunk Interface Module Installer's Notes.
- The module provides an ISDN BRI U Interface to be used in North America.

Status
➤ S

NTDR79AA

Description	System Compatibility	Product compatibility	W/S
Reach Line Card Cable - Basic Version			W0

Notes:

- This cable is included with each Reach Line Card package. It includes a serial interface and an Ethernet interface.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTDR80AA

Description	System Compatibility	Product compatibility	W/S
Reach Line Card Cable - Enhanced Version			W0

Notes:
- This cable is an optional item and provides a serial interface, two Ethernet interfaces, a V.35 interface, and a local telephone interface.

Status
✓ ➤ Δ S

NTDR81AA

Description	System Compatibility	Product compatibility	W/S
Remote Office Product CD-ROM Package			W0

Notes:
- This CD-ROM provides a tutorial about the product and assists in the installation process. It is included with all Remote Office 9150, 9110, 9115, and 9115 HOST units. Additional copies may be desired for training purposes.

Status
➤ Δ S

NTDR82AA

Description	System Compatibility	Product compatibility	W/S
MIG Reach Line Card Installation and Administration Guide			W0

Notes:
- This guide is not included in any product package and must be ordered separately. At least one copy is recommended for each distributor office and each customer PBX site.

Status
✓ ➤ Δ S

NTDR83AA

Description	System Compatibility	Product compatibility	W/S
Remote Office Technical Training CD-ROM Package			W0/ S1

Notes:
- This CD-ROM is the only technical training course available for the Remote Office products. It is recommended that distributors obtain and use this CD-ROM training material.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NTDR84AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 Installation and Administration Guide			W0

Notes:
- This guide is included with each Remote Office 9150 purchase.

Status
★ ➤ Δ S

NTDR85AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 911x User Guide			W0

Notes:
- This guide is included with all Remote Office 9110, 9115, and 9115 HOST units.

Status
✓ ➤ S

NTDR87AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 Universal Power Supply			W0

Notes:
- Line cord is not included.
- This power supply is included in every Remote Office 9150 package. This order number is for spares.

Status
★ ➤ S

NTDR88AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 911x North American Power Supply			W1

Notes:
- This power supply is included with all Remote Office 9110, 9115, and 9115 HOST units. This power supply would primarily be ordered as a spare part item.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTDW80AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	11C X11 R25; 11C COMPACT X11 R25; 51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		W1

Notes:
- This software resides on the NTZC80AA Meridian IP Telephony Gateway (ITG 2.0) Line Card.
-
- The PBX that the customer is installing the card onto must be running X11 Release 25 or greater.

Status
★ ➤ Δ S

NTDW81AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (CD-ROM)	11C X11 R25; 11C COMPACT X11 R25; 51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		W0

Notes:
- This documentation is used for the NTZC80AA Meridian IP Telephony Gateway (ITG 2.0) Line Card.
- The PBX that the customer is installing the card onto must be running X11 Release 25 or greater.

Status
>> # S

NTHF02AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Release 1.0 Client Application CD, English			W1

Notes:
- The client CD is orderable as a replacement for the CD shipped with each new system.
- The client CD is orderable if multiple clients are to be installed concurrently.

Status
S

NTHF02AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Release 2.0 Client Application CD, English			W1

Notes:
- The client CD is orderable as a replacement for the CD shipped with each new system, or if multiple clients are to be installed concurrently.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
>> # S

NTHF03AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Supplementary CD			W1

Notes:
- SYMPOSIUM Express Call Center Supplementary CD provides the most current level of released patches.

Status
S

NTHF03AB

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center Supplementary CD			W1

Notes:
- Symposium Express Call Center PEP CD provides the most current level of released product enhancements for Release 2.

Qty	Order code	Description	Qty	Order code	Description
1	NTHF04AB	Symposium Express Call Center Supplementary CD			

Status
>> # Δ S

NTHF06AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Documentation CD			W0

Notes:
- SYMPOSIUM Express Call Center documentation CD is shipped with every new system. Additional CDs may be ordered. The CD includes: Quick Reference Card; Reports and Displays Guide; Planning, Installation, and Administration Guide; Management Guide; and Task Flow Guide.

Status
➤ Δ S

NTHF06AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Documentation CD			W0

Notes:
- SYMPOSIUM Express Call Center Documentation CD is shipped with every new system. Additional CDs may be ordered. The CD includes: Reports and Displays Guide; Planning, Installation, and Administration Guide; Management Guide; Addendum to PIA Guide, and Task Flow Guide.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
Δ S

NTHF07AC

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Documentation Suite			W0

Notes:

- The suite is a hardcopy of all the available documents.
- The suite includes: Reports and Displays Guide; Planning, Installation, and Administration Guide; Management Guide; Addendum to PIA guide, and Task Flow Guide.

Qty	Order code	Description	Qty	Order code	Description
1	P0887335	SYMPOSIUM Express Call Center Planning, Installation and Administration Guide, English	1	P0908782	SYMPOSIUM Express Call Center Task Flow Guide
1	P0907622	SYMPOSIUM Express Call Center Management Guide	1	P0909663	Symposium Express Call Center Addendum to Planning, Installation, and Administration Guide
1	P0907624	SYMPOSIUM Express Call Center Server Reports and Displays Guide			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTHF24AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Release 2.0 Base System			S1

Notes:

- The base package provides Call Center software for the first 10 agents, where the number of agents is defined as 'concurrently logged in agents, regardless of agent state.'
- Additional agents can be added to this package in 1, 5, or 10 agent increments to a maximum of 150 agents.
- The list of compatible Meridian 1 systems includes Options 11C, 51C, 61C, 81, and 81C.
- A minimum of X11 Release 23.35 for Option 11C and X11 Release 23.37 for Options 51C through 81C software is required. Note: package SW0221C ACD Message Processing must be purchased.
- If 'partial networking' functionality for inbound calls only is required, the NACD packages must be purchased. (refer to Ordering Guide)
- The customer must provide the PC for the server and clients. See notes in the Ordering Guide.
- The X11 prerequisites are required on the Meridian 1 for this system to function at the agent increment size that was purchased. See the Ordering Guide Bulletin and provide a Tape Prep form with the correct options identified.
- Graphical Real Time Display (GRTD) only works on a Win 95 client that is co-resident with a EXPRESS client. It does not function on the client that is co-resident with a server.
- The Meridian 1 system must be equipped with the appropriate Ethernet IOP or IOP/CMDU card to accommodate the connection to the embedded LAN (ELAN). (Refer to Ordering Guide Bulletin)
- A LAN hub and associated cables are required for the connection of the Meridian 1 PBX to the SYMPOSIUM Express Call Center System. (Refer to Ordering Guide Bulletin). A power cord must be added to this package if configurator is not used to configure the system.
- Meridian Mail or MIRAN is required for the announcements, and Voice menus can be used as a front end to the call center. (Refer to Ordering Guide Bulletin)
- This package contains one each of Server, Client, CDoc, PEP, and GRTD CDs.
- The Meridian 1 serial number must be provided when ordering this code for an existing system.

Qty	Order code	Description	
1	NTHF30AB	Symposium Express Call Center 10 Agent Increment	
1	NTZD07AA	SYMPOSIUM Call Center Server Graphical Real Time Display CD-ROM	
1	NTZD51AB	Symposium Express Call Center Base Package	
	Each Package Includes:		
	1	NTHF01AB	Symposium Express Call Center Release 2 0 Server Application CD
	1	NTHF02AB	SYMPOSIUM Express Call Center Release 2 0 Client Application CD, English
	1	NTHF04AB	Symposium Express Call Center Supplementary CD
	1	NTHF06AB	SYMPOSIUM Express Call Center Documentation CD

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTHF28AB

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center 1 Agent Increment			S1

Notes:

- The one agent increment can be added to the base package to increase the number of Symposium Express Call Center agents, where the number of agents is defined as "concurrently logged in agents, regardless of agent state."
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 150 agents is the maximum number of active agents supported.

Status
S

NTHF29AB

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center 5 Agent Increment			S1

Notes:

- The five agent increment can be added to the base package to increase the number of Symposium Express Call Center agents, where the number of agents is defined as "concurrently logged in agents, regardless of agent state."
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 150 agents is the maximum number of active agents supported.

Status
S

NTHF30AB

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center 10 Agent Increment			W1/ S1

Notes:

- The ten agent increment can be added to the base package to increase the number of Symposium Express Call Center agents, where the number of agents is defined as "concurrently logged in agents, regardless of agent state."
- The appropriate level of X11 agent software must be activated in order for this package to be effective.
- 150 agents is the maximum number of active agents supported.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTHF35AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center LAN Package Option 11C			W1

Notes:

- The optional LAN package is a starter package that will work with the Option 11C Compact and the Option 11C. A Power Cord must be ordered for this package to function.

Qty	Order code	Description	Qty	Order code	Description
1	A0648377	10 Ft Ethernet Cable, Category 5	1	NTRH9017	10 Base T Hub
1	A0648379	25 Ft Ethernet Cable, Category 5	1	NTRH9069	Transceiver (MAU to 10 Base T)
1	NTDK27AA	Ethernet Adapter Cable			

Status
✓ S

NTHF36AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center LAN Package, Options 61C-81C			W1

Notes:

- The optional LAN package is a starter package that will work with the Options 61C, 81, and 81C. A Power Cord must be ordered for this package to function.

Qty	Order code	Description	Qty	Order code	Description
2	A0648377	10 Ft Ethernet Cable, Category 5	1	NTRH9017	10 Base T Hub
1	A0648379	25 Ft Ethernet Cable, Category 5	2	NTRH9069	Transceiver (MAU to 10 Base T)
2	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTHF63AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Release 2.0 Base System Upgrade from Release 1.0			S1

Notes:

- This code is provided for existing Release 1.0 sites to upgrade to Release 2.0.
- This software cannot be used to install a new site.
- This package includes base software for 10 agents. It includes one each of Server, Client, CDoc, PEP, and GRTD CDs.

Qty	Order code	Description	
1	NTZD51AB	Symposium Express Call Center Base Package	
	Each Package Includes:		
	1	NTHF01AB	Symposium Express Call Center Release 2 0 Server Application CD
	1	NTHF02AB	SYMPOSIUM Express Call Center Release 2 0 Client Application CD, English
	1	NTHF04AB	Symposium Express Call Center Supplementary CD
	1	NTHF06AB	SYMPOSIUM Express Call Center Documentation CD
1	P0886764	Symposium Express Keycode	

Status
✓ S

NTHF69AA

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center LAN Package, 51C			W1

Notes:

- The optional LAN package is a starter package that will work with the Option 51C. A power cord must be ordered for this package to function.

Qty	Order code	Description	Qty	Order code	Description
1	A0648377	10 Ft Ethernet Cable, Category 5	1	NTRH9017	10 Base T Hub
1	A0648379	25 Ft Ethernet Cable, Category 5	1	NTRH9069	Transceiver (MAU to 10 Base T)
1	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ S

NTHU21AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from XN/ XT/71 (QCA55/108 Cabinets) Module Upgrade Package AC	71 3311 R25; XN 3311 R25; XT 3311 R25		W1

Notes:

- The package is compatible with XN, XT and Option 71 systems whereby the call processor and network group equipment are contained in QCA55/108 type system cabinets. If the call processor and network for the Option 71 is contained in modules, use package NTHU22AC instead of this package.
- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII, SW0013A (299) Option 81C Software Package.
- This package assumes the new NT4N41 Call Processor/Network Modules are positioned side-by-side and within 16 cable feet from the QCA55/108 cabinets and 16 cable feet from the MDF. If the new call processor/network modules are required to be stacked one on top of the other, this arrangement must be completed as part of the upgrade installation. Should the pedestal, top cap and other items included in the package not be used because the call processor/network modules are stacked in a single column, these items may not be returned to Nortel Networks for credit.
- The new NT4N41 Call Processor/Network Modules contain empty network card slots equal to one network group capacity. For IGS based systems, (those utilizing QPC412 or NT5D30 cards), to use the network portion of this module, all network groups must be moved from cabinets to network modules. For systems deploying the fiber network fabric (using NTRB33) cards, existing network groups can be retained in QCA55/108 cabinets with additional network groups housed within modules. This mixed configuration is only supported for systems with the fiber network fabric.
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group, if required. For a four-to-five group system one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered separately.
- This package does not include QPC441 Three Port Extender cards (3PE). If additional QPC441 cards are required, they must be ordered separately and must be a minimum vintage "F" or later.
- Clock Controllers are not included in this package. Clock Controllers must be minimum vintage "H" for QPC471 (US Market) or "F" for QPC775 (Canada) or later. If existing Clock Controllers are not the minimum vintage or later, quantity two (2) must be ordered separately.
- This package includes one NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then one additional NT5D40AA Hybrids Kit is required and must be ordered separately.
- This package assumes reuse of either QPC412 or NT5D30 cards which support IGS network fabrics. IGS based networks can support up to a maximum of five network groups. For these systems, network groups must be housed entirely within cabinets or within modules. Mixed network configurations between cabinets and modules are not supported for IGS based systems.
- Fiber network fabric (i.e., systems utilizing the NTRB33 FIJI card), supports growth up to 8 network groups and supports configurations where network groups may be housed in both cabinets and modules. Fiber network fabric can be ordered separately.
- Existing network groups may be converted to the fiber network fabric using package NTHY23AA. Each fiber group conversion kit contains the equipment needed to convert 1 network group. If adopting, all network groups (existing and new) must employ the fiber network fabric.
- Additional network groups, up to a maximum supported of 8, may be added to fiber network systems using the Fiber Network Group Assembly Package, package NTHY20AC. Should an additional column stack be needed to house the additional network group desired, order NTHY24AC which also includes a Top Cap/Pedestal and IPE Module Assembly.
- The fiber network fabric, if desired, requires the following feature package be ordered to support the fiber fabric and eight network groups (NTS103AA).
- A standalone reference guide for the fiber network fabric is available for order separately. To purchase, order NT5F37AA.
- Relocation of clock controllers may impact clock cabling. If existing clock cabling cannot support the relocated clocks, new clock controller cables (either NT8D74 Clock Controller to IGM Cables or NTRC46 Clock to FIJI) and NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- This package contains two NT4N65 Compact Core Network Interface cards for connection to the first two existing network groups. If the existing system is equipped with three or more network groups, two additional NT4N65 Compact CNI cards are required for each two additional network groups and must be ordered separately. cCNI Transition Cards, NT4N66, are provided for in this package and will sup-

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

port up to eight network groups with Fiber Network Fabric. For network groups 4 and 5, one NTND33CC Upgrade Cable Kit must also be ordered.

- The requirements above assume that all existing network groups (0 through 4) are located in SL-1 style cabinets.
- The requirements above assume that all existing network groups (0 through 4) are located in SL-1 style cabinets.

Qty	Order code	Description	
2	A0369107	Sub-D Filter Connector (25 Conductor)	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
1	NT1R91AA	Modem Kit	
2	NT4N41AA	cPCI Core/Network Module AC	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT5D40AA	Hybrids Kit	
2	NT7D00AA	Top Cap AC	
2	NT8D22AC	System Monitor	
2	NT8D29BA	Core/Network Power Supply AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
1	NT8D49AA	Column Spacer Kit (2 75 In)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
2	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRD25AA	Pedestal Assembly AC	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
2	P0623569	Alarm Terminating Plug	
2	P0699851	Top Cap Cable Egress Panel	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ S

NTHU21DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from XN/ XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC	71 3311 R25; XN 3311 R25; XT 3311 R25		W1

Notes:

- The package is compatible with XN, XT and Option 71 systems whereby the call processor and network group equipment are contained in QCA55/108 type system cabinets. If the call processor and network for the Option 71 are contained in modules, use package NTHU22DC instead of this package.
- This Option 81C package requires the following feature packages be enabled: NTS101AA (Option 368) Call Processor PII, SW0013A (Option 299) Option 81C Software Package.
- This package assumes the new NT4N41 Call Processor/Network Modules are positioned side-by-side and within 16 cable feet from the QCA55/108 cabinets and 16 cable feet from the MDF. If the new call processor/network modules are required to be stacked one on top of the other, this arrangement must be completed as part of the upgrade installation. Should the pedestal, top cap and other items included in the package not be used because the call processor/network modules are stacked in a single column, these items may not be returned to Nortel Networks for credit.
- The new NT4N41 Call Processor/Network Modules contain empty network card slots equal to one network group capacity. For IGS based systems (those utilizing QPC412 or NT5D30 cards) to use the network portion of this module, all network groups must be moved from cabinets to network modules. For systems deploying the fiber network fabric (i.e., systems utilizing NTRB33 FIJI cards), existing network groups can be retained in QCA55/108 cabinets with additional network groups housed within modules. This mixed configuration is only supported for systems that employ the fiber network fabric.
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group, if required. For a four-to-five group system, one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered separately.
- This package does not include QPC441 Three Port Extender cards (3PE). If additional QPC441 cards are required, they must be ordered separately and must be a minimum vintage "F" or later.
- Clock Controllers are not included in this package. Clock Controllers must be minimum vintage "H" for QPC471 (US Market) or "F" for QPC775 (Canada) or later. If existing Clock Controllers are not the minimum vintage or later, quantity two (2) must be ordered separately.
- This package includes one NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then one additional NT5D40AA Hybrids Kit is required and must be ordered separately.
- This package assumes reuse of either QPC412 or NT5D30 cards which support IGS network fabrics. IGS based networks can support up to a maximum of five network groups. For these systems, network groups must be housed entirely within cabinets or within modules. Mixed network configurations between cabinets and modules are not supported for IGS based systems.
- Fiber network fabric (i.e., systems utilizing the NTRB33 FIJI card), supports growth up to 8 network groups and supports configurations where network groups may be housed in both cabinets and modules. Fiber network fabric can be ordered separately.
- Existing network groups may be converted to the fiber network fabric using package NTHY23AA. Each fiber group conversion kit contains the equipment needed to convert 1 network group. If adopting, all network groups (existing and new) must employ the fiber network fabric.
- Additional network groups, up to a maximum supported of 8, may be added to fiber network systems using the Fiber Network Group Assembly Package, package NTHY20DC. Should an additional column stack be required to house the additional network desired, order NTHY24DC which also includes a Top Cap/Pedestal and IPE Module Assembly.
- The fiber network fabric, if desired, requires the following feature package be ordered to support the fiber fabric and eight network groups (NTS103AA).
- A standalone reference guide for the fiber network fabric is available for order separately. To purchase, order NT5F37AA.
- Relocation of clock controllers may impact clock cabling. If existing clock cabling cannot support the relocated clocks, new clock controller cables (either NT8D74 Clock Controller to IGM Cables or NTRC46 Clock to FIJI) and NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- This package contains two NT4N65AA Compact Core Network Interface cards for connection to the first two existing network groups. If the existing system is equipped with three or more network groups, two additional NT4N65AA Compact CNI cards are required for each two additional network groups and must be ordered separately. cCNI Transition Cards, NT4N66, are provisioned within this package and support up to eight netowrk groups with Fiber Network Fabric. For network groups 4 and 5, quantity 1 NTND33CC upgrade cable kit must also be ordered.
- The requirements noted above assume that existing network groups (0 through 4) are located in SL-1 style cabinets.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	A0369107	Sub-D Filter Connector (25 Conductor)	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
1	NT1R91AA	Modem Kit	
2	NT4N41DA	cPCI Core/Network Module DC	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT5D40AA	Hybrids Kit	
2	NT6D41CA	Core/Network Power Supply DC	
2	NT7D00BA	Top Cap DC	
2	NT8D22AC	System Monitor	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
1	NT8D49AA	Column Spacer Kit (2 75 In)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
2	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRD25BA	Pedestal Assembly DC	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
2	P0623569	Alarm Terminating Plug	
2	P0699851	Top Cap Cable Egress Panel	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤⊗S

NTHU22AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Cage Upgrade Package AC	71 3311 R25; 81 3311 R25; 81C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (Option 368) Call Processor PII, SW0013A (Option 299) Option 81C Software Package.
- For Option 81C upgrades, the existing NT5D2101 core/network card cages are replaced with the new call processor/network card cages. The existing conference/TDS, single or dual intergroup switch cards, three port extender, peripheral signaling, SDI paddle boards and DTI/PRI cards, if any of these cards are equipped, are repositioned in the same card slots they previously occupied in the NT5D2101 card cage.
- For Option 81 and module based Option 71 upgrades, the existing common equipment card cages are replaced with the new call processor/network card cages and all existing common equipment cards are discarded except for the clock controller cards. The clock controller cards must be relocated to network modules and may require longer cables that must be ordered separately. If existing clock cabling cannot support the relocated clocks, new clock controller cables (either NT8D74 Clock Controller to IGM Cables for IGS based systems or NTRC46 for fiber network systems using NTRB33 cards) and NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- Clock Controllers are not included in this package. Clock Controllers must be minimum vintage "H" for QPC471 (US Market) or "F" for QPC775 (Canada) or later. If existing Clock Controllers are not the minimum vintage or later, quantity two (2) must be ordered separately.
- If the existing common equipment card cage contains DTI/PRI cards, these cards can be repositioned in the empty network card slots of the new call processor card cage.
- The new call processor/network card cages replace the existing card cages in their same column positions (e.g., new card cages are positioned side-by-side or stacked based on the previous arrangement).
- If the existing system is not equipped with the NT1R91AA Modem Kit, this item must be ordered separately.
- This package contains two NT4N65 Compact Core Network Interface cards for connection to the first two existing network groups. If the existing system is equipped with three or more network groups, two additional NT4N65 Compact CNI cards are required for each additional two network groups. cCNI Transition Cards, NT4N66, are provisioned within this package and will support up to eight network groups with Fiber Network Fabric. In addition, four NT8D76 cables must be ordered separately for each additional network group.
- This package provides only the items required to upgrade the call processor components of the existing system. However, the new call processor/network card cages contain empty network card slots equal to one network group capacity and can be populated with network type cards if required.
- This package does not include QPC441 Three Port Extender cards (3PE). If additional QPC441 cards are required, they must be ordered separately and must be a minimum vintage "F" or later.
- This package assumes reuse of either QPC412 or NT5D30 cards which support IGS network fabrics. IGS based networks can support up to a maximum of five network groups. For these systems, network groups must be housed entirely within cabinets or within modules. Mixed network configurations between cabinets and modules are not supported for IGS based systems.
- Fiber network fabric (i.e., systems utilizing the NTRB33 FIJI card), supports growth up to 8 network groups and supports configurations where network groups may be housed in both cabinets and modules. Fiber network fabric can be ordered separately.
- Existing network groups may be converted to the fiber network fabric using package NTHY23AA. Each fiber group conversion kit contains the equipment needed to convert 1 network group. If adopting, all network groups (existing and new) must employ the fiber network fabric.
- Additional network groups, up to a maximum of 8, may be added to fiber network systems using the Fiber Network Group Assembly Package, NTHY20AC. Should an additional column stack be needed to house the additional network group desired, order NTHY24AC which also includes a Top Cap/Pedestal and IPE Module Assembly.
- The fiber network fabric, if desired, requires the following feature package be ordered to support the fiber fabric and eight network groups (NTS103AA).
- A standalone reference guide for the fiber network fabric is available for order separately. To purchase, order NT5F37AA.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N46AA	cPCI Core/Network Card Cage AC/DC	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
2	NT4N97AA	cPCI Upgrade Kit AC	
2	NT8D29BA	Core/Network Power Supply AC	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
22	P0906308	cPCI Card Slot Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤⊗S

NTHU22DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Upgrade Package DC	71 3311 R25; 81 3311 R25; 81C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (Option 368) Call Processor PII, SW0013A (Option 299) Option 81C Software Package.
- For Option 81C upgrades, the existing NT5D2101 core/network card cages are replaced with the new call processor/network card cages. The existing conference/TDS, single or dual intergroup switch, three port extender, peripheral signaling, SDI paddle boards and DTI/PRI cards, if any of these cards are equipped, are repositioned in the same card slots they previously occupied in the NT5D2101 card cage.
- For Option 81 and module based Option 71 upgrades, the existing common equipment card cages are replaced with the new call processor/network card cages and all existing common equipment cards are discarded except for the clock controller cards. The clock controller cards must be relocated to network modules and may require longer cables that must be ordered separately. If existing clock cabling cannot support the relocated clocks, new clock controller cables (either NT8D74 Clock Controller to IGM Cables for IGS based systems or NTRC46 for fiber network systems using NTRB33 cards) and NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- Clock Controllers are not included in this package. Clock Controllers must be minimum vintage "H" for QPC471 (US Market) or "F" for QPC775 (Canada) or later. If existing Clock Controllers are not the minimum vintage or later, quantity two (2) must be ordered separately.
- If the existing common equipment card cage contains DTI/PRI cards, these cards can be repositioned in the empty network card slots of the new call processor card cage.
- The new call processor/network card cages replace the existing card cages in their same column positions (e.g., new card cages are positioned side-by-side or stacked based on the previous arrangement).
- If the existing system is not equipped with the NT1R91AA Modem Kit, this item must be ordered separately.
- This package contains two NT4N65 Compact Core Network Interface cards for connection to the first two existing network groups. If the existing system is equipped with three or more network groups, two additional NT4N65 Compact CNI cards are required for each additional two network groups. cCNI Transition Cards, NT4N66, are provisioned within this package and will support up to eight network groups with Fiber Network Fabric. In addition, four NT8D76 cables must be ordered separately for each additional network group.
- This package provides only the items required to upgrade the call processor components of the existing system. However, the new call processor/network card cages contain empty network card slots equal to one network group capacity and can be populated with network type cards if required.
- This package does not include QPC441 Three Port Extender cards (3PE). If additional QPC441 cards are required, they must be ordered separately and must be a minimum vintage "F" or later.
- This package assumes reuse of either QPC412 or NT5D30 cards which support IGS network fabrics. IGS based networks can support up to a maximum of five network groups. For these systems, network groups must be housed entirely within cabinets or within modules. Mixed network configurations between cabinets and modules are not supported for IGS based systems.
- Fiber network fabric (i.e., systems utilizing the NTRB33 FIJI card), supports growth up to 8 network groups and supports configurations where network groups may be housed in both cabinets and modules. Fiber network fabric can be ordered separately.
- Existing network groups may be converted to the fiber network fabric using package NTHY23AA. Each fiber group conversion kit contains the equipment needed to convert 1 network group. If adopting, all network groups (existing and new) must be converted to the fiber network fabric.
- Additional network groups, up to a maximum of 8, may be added to fiber network systems using the Fiber Network Group Assembly Package,NTHY20DC. Should an additional column stack be needed to house the additional network group desired, order NTHY24DC which also includes a Top Cap/Pedestal and IPE Module Assembly.
- The fiber network fabric, if desired, requires (NTS103AA) feature package be ordered to support the fiber fabric and eight network groups.
- A standalone reference guide for the fiber network fabric is available for order separately. To purchase, order NT5F37AA.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N46AA	cPCI Core/Network Card Cage AC/DC	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
2	NT4N97BA	cPCI Upgrade Kit DC	
2	NT6D41CA	Core/Network Power Supply DC	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
22	P0906308	cPCI Card Slot Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTHU24AC

Description	System Compatibility	Product compatibility	W/S
Option 81C from Option 61C (NT5D21) Upgrade AC	61C		W1

Notes:

- This Option 81C package requires that the Fiber Network Software Package (NTS103AA) be enabled.
- Option 81C systems utilizing the 68040 Call Processor require X11 Release 25 Software Generic 1911.
- Option 81C systems utilizing the 68060 Call Processor require X11 Release 25 Software Generic 2611.
- Option 81C systems utilizing the 68060E Call Processor require X11 Release 25 Software Generic 3011.
- Memory upgrade kit NTZC75 supports DRAM memory upgrade of existing processors to minimum 80MB DRAM per processor. Depending upon existing processor type, up to three (3) of NTZC75 kits per processor may be required.
- This package assumes that the existing processors with the Option 61C are reused and provides an upgrade to an Option 81C with the fiber network (based on NTRB33 FIJI cards). Customers wishing to deploy the Call Processor PII should order package NTHU22AC if requiring a card cage exchange or NTHU21AC if requiring a module based exchange.
- This package is applicable to Option 61C systems with NT5D21 Core/Network Modules only and assumes these modules are reused. Option 61C systems with NT9D11 Core/Network Modules should order package NTHU28AC.
- This package contains sixteen NT8D18AA Tip and Ring cables within the IPE modules.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes two 3PE (QPC441) cards. If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- The Option 81C requires two (2) Clock Controller cards (QPC471 that are vintage "H" or later). If these cards are not presently equipped in the system to be upgraded, they must be ordered separately.
- Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- One NT8D21AA Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used.
- This package assumes that the existing CNI 2 Port (NT6D65AA) cards will be reused (one for each Core/Network Module) to support the first two network groups. Additional network groups can be supported using combinations of either CNI-2 or CNI-3 (NTRB34) cards. Systems wishing to expand to seven or eight network groups must utilize CNI-3 cards (minimum two of the three total on each side of the core - side 0 and side 1).
- CNI-3 Port Cards must be purchased separately and also reside in the Core/Network Module for Option 81C Systems. Systems using CP PII employ a cPCI version of the CNI-2 port card (NT4N65).
- This package contains two fiber network groups. For additional fiber based network groups, order using either Fiber Network Group Assembly NTHY20AC or the Fiber Network Group Column Package NTHY24AC. The Fiber Network Group Column Package also includes Top Cap/Pedestal and IPE Module Assemblies.
- If the Option 61C system is equipped with two (2) IOP/CMDU Cards (NT5D20) or separate IOP and CMDU Cards (NT6D63 and NT6D64), then two (2) NT5D61AB IODU-C cards must be ordered separately. IODU-C cards are required to support Release 24 and later software.
- This package assumes reuse of existing modems (NT1R91AA). If no modem exists, it must be ordered separately.

Qty	Order code	Description	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT7D00AA	Top Cap AC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
2	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	
2	NTRC48CA	FIJI to FIJI Fiber Ring Cable, (12 Ft /3 6M)	
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)	
1	NTRD25AA	Pedestal Assembly AC	
2	NTRE39AA	Optical Cable Management Card (OCMC)	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTHU24DC

Description	System Compatibility	Product compatibility	W/S
Option 81C from Option 61C (NT5D21) Upgrade DC	61C		W1

Notes:

- This Option 81C package requires that the Fiber Network Software Package (NTS103AA) be enabled.
- Option 81C systems utilizing the 68040 Call Processor require X11 Release 25 Software Generic 1911.
- Option 81C systems utilizing the 68060 Call Processor require X11 Release 25 Software Generic 2611.
- Option 81C systems utilizing the 68060E Call Processor require X11 Release 25 Software Generic 3011.
- Memory upgrade kit NTZC75 supports DRAM memory upgrade of existing processors to minimum 80MB DRAM per processor. Depending upon the existing processor type, up to three (3) of NTZC75 kits per processor may be required.
- This package assumes that the existing processors with the Option 61C are reused and provides an upgrade to an Option 81C with the fiber network (based on NTRB33 FIJI cards). Customers wishing to deploy the Call Processor PII should order package NTHU22DC if requiring a card cage exchange or NTHU21DC if requiring a module based exchange.
- This package is applicable to Option 61C systems with NT5D21 Core/Network Modules only and assumes these modules are reused. Option 61C systems with NT9D11 Core/Network Modules should order package NTHU28DC.
- This package contains sixteen NT8D18AA Tip and Ring cables within the IPE modules.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect.
- This package includes two 3PE (QPC441) cards. If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- The Option 81C requires two (2) Clock Controller cards (QPC471 that are vintage "H" or later). If these cards are not presently equipped in the system to be upgraded, they must be ordered separately.
- Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, NT8D79 PRI/DTI to Clock Controller cables must be ordered separately.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used.
- This package assumes that the existing CNI 2 Port (NT6D65AA) cards will be reused (one for each Core/Network Module) to support the first two network groups. Additional network groups can be supported using combinations of either CNI-2 or CNI-3 (NTRB34) cards. Systems wishing to expand to seven or eight network groups must utilize CNI-3 cards (minimum two of the three total on each side of the core - side 0 and side 1).
- CNI-3 Port Cards must be purchased separately and also reside in the Core/Network Module for Option 81C Systems. Systems using CP PII employ a cPCI version of the CNI-2 port card (NT4N65).
- This package contains two fiber network groups. For additional fiber based network groups, order either the Fiber Network Group Assembly, NTHY20DC or the Fiber Network Group Column Kit NTHY24DC. The Fiber Network Group Column Package also includes Top Cap/Pedestal and IPE Module Assemblies to provide another column stack in which to house the additional network group.
- If the Option 61C system is equipped with two (2) IOP/CMDU Cards (NT5D20) or separate IOP and CMDU Cards (NT6D63 and NT6D64), then two (2) NT5D61AB IODU-C cards must be ordered separately. IODU-C cards are required to support Release 24 and later software.
- This package assumes reuse of existing modems (NT1R91AA).

Qty	Order code	Description	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
1	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
2	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	
2	NTRC48CA	FIJI to FIJI Fiber Ring Cable, (12 Ft /3 6M)	
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)	
1	NTRD25BA	Pedestal Assembly DC	
2	NTRE39AA	Optical Cable Management Card (OCMC)	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTHU28AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/51C or 61C (NT9D11, NT5D21) Upgrade Package AC	51 3311 R25; 51C 3311 R25; 61 3311 R25; 61C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII, NTS103AA (365) Fiber Network Software Package, SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- This package is equipped with two (2) fiber network groups. Additional groups may be ordered using the Fiber Network Group Assembly Package, NTHY20AC. If an additional column is required to house the additional network group, NTHY24AC can be ordered. The NTHY24AC includes Top Cap/Pedestal and IPE Module Assembly and provides an additional column stack to house the additional network group, if needed.
- This package contains two NT4N65 and the associated cables that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with Fiber Network Fabric. Additional network groups require the purchase of two NT4N65 and eight NT8D76 cables which will support two additional network groups. These must be ordered separately.
- This package does not include one additional clock controller card for Option 51/51C Upgrades and must be ordered separately. The minimum vintage of all clock controller cards is H for QPC471 (or F for QPC775).
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- This package assumes the new NT4N46 Card Cage replaces the existing NT6D39, NT9D11 or NT5D21 Card Cage located directly above the existing pedestal and a new NT4N41 module is placed to the left side of the Card Cage that was upgraded with NT4N46. The new NT4N41 module is positioned directly on top of the pedestal that is included in this package. Likewise, the two (2) NT8D35BA network modules are positioned directly on top of the NT4N41AA module. The QPC43, QPC441, and DTI/PRI cards and the second existing NT6D39, NT9D11, or NT5D21 Card Cage are relocated to the NT4N41AA module. For Option 61 or 61C Upgrades, the second existing NT6D39, NT9D11, or NT5D21 Card Cage is not replaced and may be converted to an IPE Card Cage using the NT1R89BA Card Cage Expansion Kit.
- As an option for Option 61 or Option 61C upgrades, the NT4N46 card cage can be removed from the NT4N41 module and used to replace the second NT9D11 or NT5D21 card cage. If this method is chosen, the NT4N41 module enclosure, pedestal, top cap and other items related to these items may not be returned to Nortel Networks for credit.
- This package does not include one additional NT8D17FA, QPC43R or QPC441F cards for Option 51/51C upgrades and must be ordered separately. The minimum vintage of all NT8D17 cards must be "FA". Likewise, all QPC43 cards must all be vintage "R" or later. The minimum vintage for QPC441 cards must be "F" or later.
- Existing QPC412 or NT5D30 Intergroup Switch cards are replaced with NTRB33AA Fiber Junctor Interface (FIJI) cards that are included in this package.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
1	NT4N41AA	cPCI Core/Network Module AC
2	NT4N43AA	cPCI Multi-Media Disk Unit
1	NT4N46AA	cPCI Core/Network Card Cage AC/DC
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT4N97AA	cPCI Upgrade Kit AC	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT7D00AA	Top Cap AC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
2	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D29BA	Core/Network Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
4	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)	
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)	
2	NTRD25AA	Pedestal Assembly AC	
2	NTRE39AA	Optical Cable Management Card (OCMC)	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTHU28DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/51C or 61C (NT9D11, NT5D21) Upgrade Package DC	51 3311 R25; 51C 3311 R25; 61 3311 R25; 61C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (Option 368) Call Processor PII, NTS103AA (Option 365) Fiber Network Software Package, SW0013A (Option 299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- This package is equipped with two (2) fiber network groups. Additional groups may be ordered using the Fiber Network Group Assembly Package, NTHY20DC. If an additional column is required to house the additional network group, NTHY24DC can be ordered. The NTHY24DC includes Top Cap/Pedestal and IPE module assembly and provides and additional column stack to house the additional network group, if needed.
- This package contains two NT4N65 and the associated cables that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Additional network groups require the purchase of two NT4N65 and eight NT8D76 cables which will support two additional groups. These must be ordered separately.
- This package assumes the new NT4N46 Card Cage replaces the existing NT6D39, NT9D11 or NT5D21 Card Cage located directly above the existing pedestal and a new NT4N41 module is placed to the left side of the Card Cage that was upgraded with NT4N46. The new NT4N41 module is positioned directly on top of the pedestal that is included in this package. Likewise, the two (2) NT8D35BA network modules are positioned directly on top of the NT4N41AA module.
- The QPC43, QPC441, and DTI/PRI cards and the second existing NT6D39, NT9D11, or NT5D21 Card Cage are relocated to the NT4N41AA module. For Option 61 or 61C upgrades, the second existing NT6D39, NT9D11, or NT5D21 Card Cage is not replaced and may be converted to an IPE Card Cage using the NT1R89BA Card Cage Expansion Kit.
- As an option for Option 61 or Option 61C upgrades, the NT4N46 card cage can be removed from the NT4N41 module and used to replace the second NT9D11 or NT5D21 card cage. If this method is chosen, the NT4N41 module enclosure, pedestal, top cap and other items related to these items may not be returned to Nortel Networks for credit.
- This package does not include one additional clock controller card for Option 51/51C upgrades and must be ordered separately. The minimum vintage of all clock contoller cards is H for QPC471 (or F for QPC775).
- This package does not include one additional NT8D17FA, QPC43R or QPC441F cards for Option 51/51C upgrades and must be ordered separately. The minimum vintage of all NT8D17 cards must be "FA". The minimum vintage of all QPC43 cards must be "R" or later. The minimum vintage of QPC441 cards must be "F" or later.
- Existing QPC412 or NT5D30 Intergroup Switch cards are replaced with NTRB33AA Fiber Junctor Interface (FIJI) cards that are included in this package.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
1	NT4N41DA	cPCI Core/Network Module DC
2	NT4N43AA	cPCI Multi-Media Disk Unit
1	NT4N46AA	cPCI Core/Network Card Cage AC/DC
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card
2	NT4N67AA	cPCI System Utility Card
2	NT4N6809	Security Device Holder
2	NT4N68AA	cPCI System Utility Transition Card
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT4N97BA	cPCI Upgrade Kit DC	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
2	NT6D41CA	Core/Network Power Supply DC	
1	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
2	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
2	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
4	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)	
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)	
1	NTRD25BA	Pedestal Assembly DC	
2	NTRE39AA	Optical Cable Management Card (OCMC)	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTHU29AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package AC	L 3311 R25; LE 3311 R25; N 3311 R25; NT 3311 R25; VL 3311 R25; VLE 3311 R25; XL 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (Option 368) Call Processor PII, NTS103AA (Option 365) Fiber Network Software Package, SW0013A (Option 299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- This package is equipped with two (2) network groups. Additional groups may be ordered using the Fiber Network Group Assembly Package, NTHY20AC. If the addition of a network group requires an additional column stack, order NTHY24AC which also includes a Top Cap/Pedestal and IPE Module Assembly.
- This package contains two NT4N65 and the associated cabling that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Additional network groups require the purchase of two NT4N65 and eight NT8D76 cables which support two additional network groups. These must be ordered separately.
- Clock controllers are not included in this package. Clock controllers must be minimum vintage "H" or later for QPC471. If existing clock controllers are not the minimum vintage or later, a quantity of two (2) must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- If the new call processor/network modules are required to be stacked one on top of the other, this arrangement must be completed as part of the upgrade installation. Should the pedestal, top cap and other items included in the package not be used, because the call processor/network modules are stacked, please note that these items may not be returned to Nortel Networks for credit.
- This package does not provide the cables and network cards required to reconnect all existing peripheral equipment (EPE) cards contained in QCA cabinets. These requirements must be engineered and ordered separately.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
2	NT4N41AA	cPCI Core/Network Module AC
2	NT4N43AA	cPCI Multi-Media Disk Unit
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card
2	NT4N6809	Security Device Holder
2	NT4N68AA	cPCI System Utility Transition Card
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)
2	NT4N89AA	System Utility to XSM Cable
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)
2	NT7D00AA	Top Cap AC
2	NT7D06AA	Filler Panel
1	NT8D01BC	Controller - Four Card

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D29BA	Core/Network Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)
1	NTRC47AA	FIJI to FIJI Synch Cable
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)
2	NTRD25AA	Pedestal Assembly AC
2	NTRE39AA	Optical Cable Management Card (OCMC)
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
22	P0906308	cPCI Card Slot Filler Panel
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTHU29DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package DC	L 3311 R25; LE 3311 R25; N 3311 R25; NT 3311 R25; VL 3311 R25; VLE 3311 R25; XL 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII, NTS103AA (365) Fiber Network Software Package, SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- This package is equipped with two (2) network groups. Additional groups may be ordered using the Fiber Network Group Expansion Package, NTHY20DC. Should an additional column stack be needed to house the additional network group, order NTHY24DC which also includes a Top Cap/Pedestal and IPE module assembly.
- This package contains two NT4N65 and the associated cabling that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Additional network groups require the purchase of two NT4N65 and eight NT8D76 cables which support two additional network groups. These must be ordered separately.
- Clock controllers are not included in this package. Clock controllers must be minimum vintage "H" or later for QPC471. If existing clock controllers are not the minimum vintage or later, quantity two (2) must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.

Qty	Order code	Description	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
1	NT1R91AA	Modem Kit	
2	NT4N41DA	cPCI Core/Network Module DC	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
2	NT6D41CA	Core/Network Power Supply DC	
2	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)
1	NTRC47AA	FIJI to FIJI Synch Cable
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)
2	NTRD25BA	Pedestal Assembly DC
2	NTRE39AA	Optical Cable Management Card (OCMC)
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
22	P0906308	cPCI Card Slot Filler Panel
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

Status
✓ ➤ ⊗ S

NTHY01AA

Description	System Compatibility	Product compatibility	W/S
Option 81C (CP PII) Systems Spares Package	81C		W1

Qty	Order code	Description	Qty	Order code	Description
1	A0810496	CP PII Call Processor Card (128MB Memory)	1	NT8D09BA	Analog Message Waiting Line Card
1	NT4N43AA	cPCI Multi-Media Disk Unit	1	NT8D14BB	Universal Trunk Card
1	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	2	NT8D17FA	Conference/TDS Card
1	NT4N67AA	cPCI System Utility Card	1	NT8D29BA	Core/Network Power Supply AC
1	NT8D01BC	Controller - Four Card	2	QPC43R	Peripheral Signaling
1	NT8D02GA	Digital Line Card (DLC)	2	QPC441F	Three-Port Extender
1	NT8D04BA	SuperLoop Network Card			

Status
✓ ➤ ⊗ S

NTHY01AC

Description	System Compatibility	Product compatibility	W/S
Option 81C (CP PII) Power Supply Spares Package AC	81C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT8D06AB	Peripheral Equipment Power Supply AC	1	NT8D29BA	Core/Network Power Supply AC
1	NT8D29AB	Common Equipment Power Supply AC			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ S

NTHY01DC

Description	System Compatibility	Product compatibility	W/S
Option 81C (CP PII) Power Supply Spares Package DC	81C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NT6D40BA	Peripheral Equipment Power Supply DC	1	NT6D41CA	Core/Network Power Supply DC
1	NT6D41AD	Common Equipment Power Supply DC			

Status
✓ ➤ S

NTHY20AC

Description	System Compatibility	Product compatibility	W/S
Fiber Network Group Assembly Package AC	81; 81C		W1

Notes:

- This package is for customers wishing to add a network group with room within existing column stacks for the additional network group. Those customers wishing to place the additional network group in a separate column stack to take advantage of simplified cabling, can order package NTHY24AC which includes top cap, pedestal and an IPE Module.
- Fiber ring cables (NTRC48) quantity 2 per network group are configuration dependent and must be ordered separately.
- Network, Conference and Tone & Digit Cards must be ordered as separate items.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package is compatible with X11 Release 25 and later. Feature Package 365 (NTS103AA) is required to support the fiber network fabric.
- Customers wishing to relocate clock controllers may need to order two (2) new Clock to FIJI cables (NTRC46) and one (1) Clock-Clock Synch Cable (NTRC49) of appropriate length.
- One FIJI - FIJI Synch Cable (NTRC47AA) is included in this package to support connection between FIJI cards on side 0 and side 1. One of these cables is required per fiber network group, other than group 0.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI-2 to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI-2 port card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.

Qty	Order code	Description	Qty	Order code	Description
2	NT8D29AB	Common Equipment Power Supply AC	1	NTRC47AA	FIJI to FIJI Synch Cable
2	NT8D35BA	Network Module AC	2	NTRE39AA	Optical Cable Management Card (OCMC)
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	2	QPC43R	Peripheral Signaling
2	NTRB33AA	Fiber Junctor Interface Card (FIJI)	2	QPC441F	Three-Port Extender

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTHY20DC

Description	System Compatibility	Product compatibility	W/S
Fiber Network Group Assembly Package DC	81; 81C		W1

Notes:

- This package is for customers wishing to add a network group with room within existing column stacks for the additional network group. Those customers wishing to place the additional network group in a separate column stack to take advantage of simplified cabling, can order package NTHY24DC which includes top cap, pedestal and an IPE Module.
- Network, Conference and Tone & Digit Cards must be ordered as separate items.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package is compatible with X11 Release 25 and later. Feature Package 365 (NTS103AA) is required to support the fiber network fabric.
- Customers wishing to relocate clock controllers may need to order new two (2) Clock to FIJI cables (NTRC46) and one (1) Clock-Clock Synch Cable (NTRC49) of appropriate length.
- One FIJI - FIJI Synch Cable (NTRC47AA) is included in this package to support connection between FIJI cards on side 0 and side 1. One of these cables is required per fiber network group.
- Fiber ring cables (NTRC48) quantity 2 per network group are configuration dependent and must be ordered separately.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.

Qty	Order code	Description	Qty	Order code	Description
2	NT6D41AD	Common Equipment Power Supply DC	1	NTRC47AA	FIJI to FIJI Synch Cable
2	NT8D35EA	Network Module DC	2	NTRE39AA	Optical Cable Management Card (OCMC)
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	2	QPC43R	Peripheral Signaling
2	NTRB33AA	Fiber Junctor Interface Card (FIJI)	2	QPC441F	Three-Port Extender

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTHY21AA

Description	System Compatibility	Product compatibility	W/S
Option 81C Fiber Core Network Group 0 Kit	81C X11 R25		W1

Notes:

- This package is for customers wishing to equip the network portion of the Core/Network Module or cPCI Core/Network Module Fiber Ring Cables (2-NTRC48) to support Fiber Rings for side 0 and side 1 are configuration dependent and must be ordered separately.
- Systems wishing to deploy this package should be using NTRB33 (FIJI) cards within their network modules. Systems with QPC412 (IGS) cards or NT5D30 (DIGS) cards within their network modules should order AS1250.
- Fiber Ring Cables (2-NTRC48) to support Fiber Rings for side 0 and side 1 are configuration dependent and must be ordered separately.
- Network, Conference and Tone and Digit Cards must be ordered separately as required.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.

Qty	Order code	Description	Qty	Order code	Description
2	NT8D80BZ	CPU Interface Cable (5 Ft)	1	NTRC47AA	FIJI to FIJI Synch Cable
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	2	QPC43R	Peripheral Signaling
2	NTRB33AA	Fiber Junctor Interface Card (FIJI)	2	QPC441F	Three-Port Extender

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTHY23AA

Description	System Compatibility	Product compatibility	W/S
FIJI Group Conversion Kit	81; 81C		W1

Notes:

- This package is compatible with customers on or ordering X11 Release 25 with Option 365 enabled who wish to take advantage of the fiber network fabric for Option 81/81C systems.
- This package is for customers wishing to replace IGS Switching Fabric with the Fiber Network Fabric. It is used to replace IGS (QPC412) or DIGS (NT5D30) cards. This package supports exchange of one existing network group. If converting to the fiber network fabric, each network group (existing or new) must be fiber based.
- To add a new fiber network group to Option 81 or 81C systems, one (1) package NTHY20AC/DC Fiber Network Group Assembly must be purchased. The NTHY20 package includes the network module to house equipment to support the additional network group. For systems who require an additional column stack in which to house the additional network group, NTHY24AC Fiber Network Group Column kit may be ordered instead of NTHY20AC. The NTHY24AC package also includes a Top Cap/Pedestal and IPE Module Assembly.
- This package does not include CNI cards. Systems with NT6D65 cards (2 port CNI cards) can support up to 6 network groups with Release X11 Release 25 and Option 365 enabled (NTS103AA). Should more than six network groups be desired, then CNI-3 Port Cards (NTRB34AA) must replace CNI-2 port cards as required. Mixture of CNI-2 and CNI-3 port cards in the same core or core/network module are supported configurations provided that the same mix of cards resides on each side of the core.
- This package does not include NTRC46 Clock to FIJI Cables. Two (2) NTRC46 of appropriate length must be ordered separately if not already equipped.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.
- This kit does not include Fiber Ring Cables (NTRC48). Two (2) NTRC48 FIJI-to-FIJI Fiber Ring Cables must be ordered for each group that will be converted to Fiber Network Fabric.

Qty	Order code	Description	Qty	Order code	Description
2	NTRB33AA	Fiber Junctor Interface Card (FIJI)	2	NTRE39AA	Optical Cable Management Card (OCMC)
1	NTRC47AA	FIJI to FIJI Synch Cable			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTHY24AC

Description	System Compatibility	Product compatibility	W/S
Fiber Network Group Column Package AC	81; 81C		W1

Notes:

- This package is applicable to systems using a fiber network based on NTRB33 (FIJI cards) where customers wish to provision an additional network group within a separate column stack to take advantage of standardized cabling lengths.
- Network modules should be placed in tier positions (2 and 3). An IPE module is equipped within the package to reside within tier position #1 within a column stack.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package does not include Core-Network Interface Cards (CNI). CNI-2 port cards (NT6D65) support up to two network groups per card. CNI-3 port cards (NTRB34) support up to three network groups per card. CNI-2 and CNI-3 port cards can be co-mingled within 81/81C systems. The mix of cards between CNI-2 and CNI-3 must be the same for both side 0 and side 1 of the Core/Network Modules.
- Customers wishing to relocate clock controllers may need to order new Clock to FIJI cables of greater length (two (2) NTCR46 - one for each clock).
- Relocation of Clock Controllers may require longer NT8D79 PRI/DTI to Clock Controller cables as well as NTRC49 Clock-Clock Synch Cable of appropriate length may be required and must be ordered separately.
- One FIJI - FIJI Synch Cable (NTRC47AA) is included in this package to support connection between FIJI cards on side 0 and side 1. One of these cables is required per fiber network group.
- Fiber ring cables (NTRC48) quantity 2 per network group are configuration dependent and must be ordered separately.
- One NT8D21AB Ringing Generator must be added for each IPE module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE Module.
- Network, Conference and Tone & Digit Cards must be ordered as separate items.
- This package is compatible with X11 Release 25 and later. Feature Package 365 (NTS103AA) to support the fiber ring fabric and must be ordered and enabled on Option 81/81C systems.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D00AA	Top Cap AC	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
1	NT8D01BC	Controller - Four Card	2	NTRB33AA	Fiber Junctor Interface Card (FIJI)
1	NT8D06AB	Peripheral Equipment Power Supply AC	1	NTRC47AA	FIJI to FIJI Synch Cable
1	NT8D22AC	System Monitor	1	NTRD25AA	Pedestal Assembly AC
2	NT8D29AB	Common Equipment Power Supply AC	2	NTRE39AA	Optical Cable Management Card (OCMC)
2	NT8D35BA	Network Module AC	2	QPC43R	Peripheral Signaling
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	2	QPC441F	Three-Port Extender
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTHY24DC

Description	System Compatibility	Product compatibility	W/S
Fiber Network Group Column Package DC	81; 81C		W1

Notes:

- This package is applicable to systems using a fiber network fabric based on NTRB33 (FIJI cards) where customers wish to provision an additional network group within a separate column stack to take advantage of standardized cabling lengths.
- Network modules should be placed in tier positions (2 and 3). An IPE module is equipped within the package to reside within tier position #1 within a column stack.
- One NT6D42CB Ringing Generator must be added for each IPE module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package does not include Core-Network Interface Cards (CNI). CNI-2 port cards (NT6D65) support up to two network groups per card. CNI-3 port cards (NTRB34) support up to three network groups per card. CNI-2 and CNI-3 port cards can be co-mingled within 81/81C systems. The mix of cards between CNI-2 and CNI-3 must be the same for both side 0 and side 1 of the Core/Network Modules.
- Customers wishing to relocate clock controllers may need to order new Clock to FIJI cables of greater length (two (2) NTCR46 - one for each clock).
- Relocation of Clock Controllers may require longer NT8D79 PRI/DTI to Clock Controller cables as well as NTRC49 Clock-Clock Synch Cable of appropriate length may be required and must be ordered separately.
- One FIJI - FIJI Synch Cable (NTRC47AA) is included in this package to support connection between FIJI cards on side 0 and side 1. One of these cables is required per fiber network group.
- Fiber ring cables (NTRC48) quantity 2 per network group are configuration dependent and must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen Tip and Ring cables within the IPE Module.
- Network, Conference and Tone & Digit Cards must be ordered as separate items.
- This package is compatible with X11 Release 25 and later. Feature Package 365 (NTS103AA) to support the fiber ring fabric and must be ordered and enabled on Option 81/81C systems.
- CP PII and Fiber Network Reference Guide, NT5F36AA may be ordered separately if not already on hand (or the former Fiber Network Reference Guide, NT5F37AA is not on hand).
- This kit does not include CNI to 3PE cables (NTND14) or CNI-3 to 3PE Cables (NT9D89), which are configuration dependent and must be ordered separately. NTND14 cables are used to connect the first two ports (0 and 1) from the backplane of either a CNI card (NT6D65) or CNI-3 card (NTRB34) to a 3PE card (QPC441). NT9D89 cables are used to connect the third port (2) from the faceplate of a CNI-3 card to a 3PE card.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D40BA	Peripheral Equipment Power Supply DC	5	NT8D99AB	CPU or Network to Network Cable (2 Ft)
2	NT6D41AD	Common Equipment Power Supply DC	2	NTRB33AA	Fiber Junctor Interface Card (FIJI)
1	NT7D00BA	Top Cap DC	1	NTRC47AA	FIJI to FIJI Synch Cable
1	NT8D01BC	Controller - Four Card	1	NTRD25BA	Pedestal Assembly DC
1	NT8D22AC	System Monitor	2	NTRE39AA	Optical Cable Management Card (OCMC)
2	NT8D35EA	Network Module DC	2	QPC43R	Peripheral Signaling
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	2	QPC441F	Three-Port Extender
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH01AA

Description	System Compatibility	Product compatibility	W/S
ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any ACD-D system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- Requires one of the following hardware upgrades to a Meridian MAX-SNNE: NTJH15BA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power - North America; NTJH15AA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- No preservation or conversion of ACD-D customer data is possible with this upgrade. Customers must start data gathering from scratch once the installation of MAX 9 is complete.
- All upgrades to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced and Virtual software include the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel Networks representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH01BA

Description	System Compatibility	Product compatibility	W/S
ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any ACD-D system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- Requires one of the following hardware upgrades to a Meridian MAX-SNNE: NTJH15BA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power - North America; NTJH15AA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- No preservation or conversion of ACD-D customer data is possible with this upgrade. Customers must start data gathering from scratch once the installation of MAX 9 is complete.
- All upgrades to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced and Virtual software include the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH01CA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-AM Release 3 or 4 to Meridian MAX-SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any Meridian MAX-SEE, or MAX Option 1-4 Release 3 or 4 system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- If upgrading from a MAX-SEE, MAX Option 1, or Option 2 to a MAX-SNNE order the following: NTJH15CA Meridian Option MAX/ MAX-SEE to Meridian MAX-SNNE System Upgrade - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- All upgrades to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Upgrades from any Meridian MAX Option 4 hardware system with 48 asynchronous I/O ports will result in a maximum of 40 ports being equipped on the Meridian MAX-SNNE system. However, up to 60 LAN-based supervisor sessions can be accommodated on the SNNE system with Meridian MAX Release 9.
- Enhanced and Virtual software include the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH01DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any Meridian MAX-SEE/SNN Release 5 or 6 system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- If upgrading from a MAX-SNN to a MAX-SNNE order the following: NTJH15DA Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade - North America.
- If upgrading from a MAX-SEE, MAX Option 1, or Option 2 to a MAX-SNNE order the following: NTJH15CA Meridian Option MAX/MAX-SEE to Meridian MAX-SNNE System Upgrade - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- All upgrades to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced and Virtual software include the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel Networks representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK78AA	AC/DC Power Supply	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)
1	NTJH04AA	MAX 9 SW/DOC Package			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH01EA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN Release 7 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any Meridian MAX-SNN Release 7 system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- If upgrading from a MAX-SNN to a MAX-SNNE order the following: NTJH15DA Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- MAX 7 Fundamental on the SNN/SNNE will be upgraded to MAX 9 Fundamental on the SNN/SNNE, MAX 7 Enhanced on the SNN/SNNE to MAX 9 Enhanced on the SNN/SNNE, and MAX 7 Virtual on the SNN/SNNE to MAX 9 Virtual on the SNN/SNNE. The number of agent positions and number of asynchronous I/O ports provisioned in software for the SNNE will be the same as the number provisioned on the existing SNN/SNNE system to be upgraded.
- Enhanced and Virtual software include the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTJH01FA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN/SNNE Release 8 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any Meridian MAX-SNN/SNNE Release 8 system to a MAX-SNN/SNNE Release 9 system.
- Requires a MAX-SNN/SNNE hardware platform.
- If upgrading from a MAX-SNN to a MAX-SNNE order the following: NTJH15DA Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- MAX 8 Fundamental on the SNN/SNNE will be upgraded to MAX 9 Fundamental on the SNN/SNNE, MAX 8 Enhanced on the SNN/SNNE to MAX 9 Enhanced on the SNN/SNNE, and MAX 8 Virtual on the SNN/SNNE to MAX 9 Virtual on the SNN/SNNE. The number of agent positions and number of asynchronous I/O ports provisioned in software for the SNNE will be the same as the number provisioned on the existing SNN/SNNE system to be upgraded.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTJH02AA

Description	System Compatibility	Product compatibility	W/S
ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Order when upgrading from any ACD-D to a MAX-IPEE Release 9 system.
- Requires the following new hardware system: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- No preservation or conversion of ACD-D customer data is possible with this upgrade. Customers must start data gathering from scratch once the installation of MAX 9 is complete.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- This upgrade to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTJH02BA

Description	System Compatibility	Product compatibility	W/S
ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Order when upgrading from any ACD-MAX to a MAX-IPEE Release 9 system.
- Requires the following new hardware system: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- A Software Data Conversion Kit (AS7506) is temporarily required to convert and move the customer data stored on the ACD-MAX DC150 Tape Cartridge to the Meridian MAX-IPEE system.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- This upgrade is accomplished by first upgrading to Meridian MAX Release 6 (operating system and application software included) and then from Meridian MAX Release 6 to Meridian MAX Release 9.
- This upgrade to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	NTJH04AA	MAX 9 SW/DOC Package
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTJH02CA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-AM Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Order when upgrading from any Meridian MAX Release 3 or 4 system running on MAX-SEE or Option 1-4 to a MAX-IPEE Release 9 system.
- Requires the following new hardware system: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- This upgrade to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH02DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Release 4.62, 5 or 6 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE	S1

Notes:

- Order when upgrading from any Meridian MAX-IPE Release 4.62, 5, or 6 system to Meridian MAX-IPE/IPEE Release 9 system.
- This upgrade requires existing Meridian MAX-IPE or new MAX-IPEE hardware. If the upgrade uses existing MAX-IPE hardware, the MAX database size will be configured to either 90 MB or 250 MB, depending upon the size of the Hard Disk Drive (HDD) installed in the existing MAX-IPE Module. If the module contains either a 180 MB or a 240 MB HDD, then the database will be 90 MB. If the module contains a 1.2 GB HDD, then the database will be 250 MB. If the existing MAX-IPE Module contains either a 180 MB or a 240 MB HDD that is limited to the 90 MB database size but the larger 250 MB database size is desired, upgrade to an IPEE.
- If upgrading from a MAX-IPE to a MAX-IPEE order one of the following: NTJH93EA - IPE to IPEE Upgrade/Repair Kit #1 - Global OR NTJH93FA - IPE to IPEE Upgrade/Repair Kit #2 - Global.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- This upgrade to Meridian MAX Release 9 will result in the provision of MAX 9 software equivalent in feature content and capacity to the MAX 9 Enhanced software package. The number of asynchronous I/O channels and agent positions that will be supported will be determined by their respective numbers on the system to be upgraded.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH02EA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 7 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE	S1

Notes:

- Order when upgrading from any Meridian MAX-IPE/IPEE Release 7 system to a MAX-IPE/IPEE Release 9 system.
- This upgrade requires existing Meridian MAX-IPE or new MAX-IPEE hardware. If the upgrade uses existing MAX-IPE hardware, the MAX database size will be configured to either 90 MB or 250 MB, depending upon the size of the Hard Disk Drive (HDD) installed in the existing MAX-IPE Module. If the module contains either a 180 MB or a 240 MB HDD, then the database will be 90 MB. If the module contains a 1.2 GB HDD, then the database will be 250 MB. If the existing MAX-IPE Module contains either a 180 MB or a 240 MB HDD that is limited to the 90 MB database size but the larger 250 MB database size is desired, upgrade to an IPEE.
- If upgrading from a MAX-IPE to a MAX-IPEE order one of the following: NTJH93EA - IPE to IPEE Upgrade/Repair Kit #1 - Global; NTJH93FA - IPE to IPEE Upgrade/Repair Kit #2 - Global.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- MAX 7 Fundamental on the IPE/IPEE will be upgraded to MAX 9 Fundamental on the IPE/IPEE, MAX 7 Enhanced on the IPE/IPEE to MAX 9 Enhanced on the IPE/IPEE, and MAX 7 Virtual on the IPE/IPEE to MAX 9 Virtual on the IPE/IPEE. The number of agent positions and number of asynchronous I/O ports provisioned in software for the IPE/IPEE will be the same as the number provisioned on the existing IPE/IPEE system to be upgraded.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Virtual software includes MEI-Network, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Both Enhanced and Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH02FA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 8 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE	S1

Notes:

- Order when upgrading from any Meridian MAX-IPE/IPEE Release 8 system to a MAX-IPE/IPEE Release 9 system.
- This upgrade requires existing Meridian MAX-IPE or new MAX-IPEE hardware. If the upgrade uses existing MAX-IPE hardware, the MAX database size will be configured to either 90 MB or 250 MB, depending upon the size of the Hard Disk Drive (HDD) installed in the existing MAX-IPE Module. If the module contains either a 180 MB or a 240 MB HDD, then the database will be 90 MB. If the module contains a 1.2 GB HDD, then the database will be 250 MB. If the existing MAX-IPE Module contains either a 180 MB or a 240 MB HDD that is limited to the 90 MB database size but the larger 250 MB database size is desired, upgrade to an IPEE.
- If upgrading from a MAX-IPE to a MAX-IPEE order one of the following: NTJH93EA - IPE to IPEE Upgrade/Repair Kit #1 - Global; NTJH93FA - IPE to IPEE Upgrade/Repair Kit #2 - Global.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- MAX 8 Fundamental on the IPE/IPEE will be upgraded to MAX 9 Fundamental on the IPE/IPEE, MAX 8 Enhanced on the IPE/IPEE to MAX 9 Enhanced on the IPE/IPEE, and MAX 8 Virtual on the IPE/IPEE to MAX 9 Virtual on the IPE/IPEE. The number of agent positions and number of asynchronous I/O ports provisioned in software for the IPE/IPEE will be the same as the number provisioned on the existing IPE/IPEE system to be upgraded.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Virtual software includes MEI-Network, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Both Enhanced and Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH04AA	MAX 9 SW/DOC Package	1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTJH05AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN/SNNE Release 9 Software Replacement/Upissue	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S1

Notes:

- Order this package to obtain the latest issue of Release 9 if you already have an earlier issue of Release 9 or to obtain replacement media for lost or damaged MAX 9 software tapes.
- Only the current release/issue of MAX 9 software in effect at the time an order is received will be shipped.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111).
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

NTJH05BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 9 Software Replacement/Upissue	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S1

Notes:

- Order this package to obtain the latest issue of Release 9 if you already have an earlier issue of Release 9 or to obtain replacement media for lost or damaged MAX 9 software tapes.
- Only the current release/issue of MAX 9 software in effect at the time an order is received will be shipped.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111).
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH09AB

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9.3 Software (Single User)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX; Meridian MAX-CCR	W0/ S3

Notes:

- This package contains Meridian Terminal Emulator (MTE) Release 9 Software (multilingual) for use on a single supervisor PC workstation and one copy of the MTE Users Guide (multilingual). Software is supplied on 3.5", High-Density, IBM-compatible floppy disks.
- Requires Meridian MAX Release 5.27 (or later) software running on a MAX module.
- When used with Meridian MAX Release 7, the MAX module must be equipped with either Enhanced or Virtual level software.
- MTE Release 9 Software can be used with all three levels of Meridian MAX Release 8 and 9 Software: Fundamental, Enhanced, or Virtual.
- Supervisor PC workstation requirements: Microsoft Windows 3.1, Windows NT 3.5.1, or Windows 95.
- A supervisor PC workstation running MTE Release 9 Software can be connected to a Meridian MAX module through either one of its asynchronous ports (via a PC COM port) or by way of a Local Area Network (LAN). Network topology items, including PC Network Interface Cards (NIC) must be purchased separately.
- When a supervisor PC workstation is connected to the MAX module via a LAN, the network operating system must be compliant with Microsoft Windows Sockets 1.1 (the WINSOCK.DLL file must be loaded on the workstation).
- When the supervisor PC workstation is connected via a LAN to a MAX module running Meridian MAX Release 6 (or earlier) software, the MAX module must be equipped with the Meridian MAX LAN One-Time Connectivity Fee (SW0072A) and there must be one copy of the Meridian MAX Lan Connectivity Software (SW0073A) installed on the MAX module for each LAN based workstation. No separate LAN connectivity software is required in a MAX module to use MTE Release 9 software on a LAN with Meridian MAX Release 7, 8, or 9 Software.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH03AB	Meridian Terminal Emulator (MTE) Release 9 3 Assembly (Single User)	1	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH09BB

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9.3 Software (System License)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX; Meridian MAX-CCR	S3

Notes:

- This package contains Meridian Terminal Emulator (MTE) Release 9 Software (multilingual) for use on all supervisor PC workstations connected to a single Meridian MAX module and ten copies of the MTE Users Guide (multilingual). Software is supplied on a single set of 3.5", High-Density, IBM-compatible floppy disks. (This package is a per MAX license, not a site license.)
- Requires Meridian MAX Release 5.27 (or later) software running on a MAX module.
- When used with Meridian MAX Release 7, the MAX module must be equipped with either Enhanced or Virtual level software.
- MTE Release 9 Software can be used with all three levels of Meridian MAX Release 8 and 9 Software: Fundamental, Enhanced, or Virtual.
- Supervisor PC workstation requirements: Microsoft Windows 3.1, Windows NT 3.5.1, or Windows 95.
- A supervisor PC workstation running MTE Release 9 Software can be connected to a Meridian MAX module through either one of its asynchronous ports (via a PC COM port) or by way of a Local Area Network (LAN). Network topology items, including PC Network Interface Cards (NIC) must be purchased separately.
- When a supervisor PC workstation is connected to the MAX module via a LAN, the network operating system must be compliant with Microsoft Windows Sockets 1.1 (the WINSOCK.DLL file must be loaded on the workstation).
- When the supervisor PC workstation is connected via a LAN to a MAX module running Meridian MAX Release 6 (or earlier) software, the MAX module must be equipped with the Meridian MAX LAN One-Time Connectivity Fee (SW0072A) and there must be one copy of the Meridian MAX Lan Connectivity Software (SW0073A) installed on the MAX module for each LAN based workstation. No separate LAN connectivity software is required in a MAX module to use MTE Release 9 software on a LAN with Meridian MAX Release 7, 8, or 9 Software.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH03BB	Meridian Terminal Emulator (MTE) Release 9 3 Assembly (System License)	10	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTJH09CB

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (Single User)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX; Meridian MAX-CCR	S3

Notes:

- This package contains Meridian Terminal Emulator (MTE) Release 9 Software (multilingual) to upgrade a single supervisor PC workstation running any MTE software prior to Release 9 and one copy of the MTE Users Guide (multilingual). Software is supplied on 3.5", High-Density, IBM-compatible floppy disks.
- Requires Meridian MAX Release 5.27 (or later) software running on a MAX module.
- When used with Meridian MAX Release 7, the MAX module must be equipped with either Enhanced or Virtual level software.
- MTE Release 9 Software can be used with all three levels of Meridian MAX Release 8 and 9 Software: Fundamental, Enhanced, or Virtual.
- Supervisor PC workstation requirements: Microsoft Windows 3.1, Windows NT 3.5.1, or Windows 95.
- A supervisor PC workstation running MTE Release 9 Software can be connected to a Meridian MAX module through either one of its asynchronous ports (via a PC COM port) or by way of a Local Area Network (LAN). Network topology items, including PC Network Interface Cards (NIC) must be purchased separately.
- When a supervisor PC workstation is connected to the MAX module via a LAN, the network operating system must be compliant with Microsoft Windows Sockets 1.1 (the WINSOCK.DLL file must be loaded on the workstation).
- When the supervisor PC workstation is connected via a LAN to a MAX module running Meridian MAX Release 6 (or earlier) software, the MAX module must be equipped with the Meridian MAX LAN One-Time Connectivity Fee (SW0072A) and there must be one copy of the Meridian MAX Lan Connectivity Software (SW0073A) installed on the MAX module for each LAN based workstation. No separate LAN connectivity software is required in a MAX module to use MTE Release 9 software on a LAN with Meridian MAX Release 7, 8, or 9 Software.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH03CB	Meridian Terminal Emulator (MTE) Release 9 3 Upgrade Assembly (Single User)	1	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTJH09DB

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (System License)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX; Meridian MAX-CCR	S3

Notes:

- This package contains Meridian Terminal Emulator (MTE) Release 9 Software (multilingual) upgrade for use on all supervisor PC workstations connected to a single Meridian MAX module for which a previous MTE System Package has been purchased and ten copies of the MTE Users Guide (multilingual). Software is supplied on a single set of 3.5", High-Density, IBM-compatible floppy disks. (This package is a per MAX upgrade license, not a site upgrade license.)
- Requires Meridian MAX Release 5.27 (or later) software running on a MAX module.
- When used with Meridian MAX Release 7, the MAX module must be equipped with either Enhanced or Virtual level software.
- MTE Release 9 Software can be used with all three levels of Meridian MAX Release 8 and 9 Software: Fundamental, Enhanced, or Virtual.
- Supervisor PC workstation requirements: Microsoft Windows 3.1, Windows NT 3.5.1, or Windows 95.
- A supervisor PC workstation running MTE Release 9 Software can be connected to a Meridian MAX module through either one of its asynchronous ports (via a PC COM port) or by way of a Local Area Network (LAN). Network topology items, including PC Network Interface Cards (NIC) must be purchased separately.
- When a supervisor PC workstation is connected to the MAX module via a LAN, the network operating system must be compliant with Microsoft Windows Sockets 1.1 (the WINSOCK.DLL file must be loaded on the workstation).
- When the supervisor PC workstation is connected via a LAN to a MAX module running Meridian MAX Release 6 (or earlier) software, the MAX module must be equipped with the Meridian MAX LAN One-Time Connectivity Fee (SW0072A) and there must be one copy of the Meridian MAX Lan Connectivity Software (SW0073A) installed on the MAX module for each LAN based workstation. No separate LAN connectivity software is required in a MAX module to use MTE Release 9 software on a LAN with Meridian MAX Release 7, 8, or 9 Software.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH03DB	Meridian Terminal Emulator (MTE) Release 9 3 Upgrade Assembly (System License)	10	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH10AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE Release 9 Fundamental Software	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Requires one of the following hardware systems: NTJH15AA - Meridian MAX-SNNE System Hardware, AC Power - North America; NTJH15BA - Meridian MAX-SNNE System Hardware, DC Power - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00AA	Meridian MAX-SNNE Release 9 Software	1	S0005897	MTE Connectivity for Meridian MAX Release 9
1	S0005894	5 LAN Session Increment for MTE Release 9	2	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH10BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE Release 9 Enhanced Software	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Requires one of the following hardware systems: NTJH15AA - Meridian MAX-SNNE System Hardware, AC Power - North America; NTJH15BA - Meridian MAX-SNNE System Hardware, DC Power - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00AA	Meridian MAX-SNNE Release 9 Software	1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9
12	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005904	MAX Event Interface (MEI) (Observe) for Meridian MAX Release 9
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9	2	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software
1	S0005897	MTE Connectivity for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH10CA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE Release 9 Virtual Software	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Requires one of the following hardware systems: NTJH15AA - Meridian MAX-SNNE System Hardware, AC Power - North America; NTJH15BA - Meridian MAX-SNNE System Hardware, DC Power - North America.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- Virtual software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C.
- Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00AA	Meridian MAX-SNNE Release 9 Software	1	S0005902	MAX Status Interface (MSI) for Meridian MAX Release 9
12	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005903	MAX Event Interface (MEI) (Network) for Meridian MAX Release 9
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005904	MAX Event Interface (MEI) (Observe) for Meridian MAX Release 9
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9
1	S0005897	MTE Connectivity for Meridian MAX Release 9	10	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH10DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN/SNNE Release 9 Fundamental to Enhanced Feature Level Promotion	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Order to add the capability of using all the features available with Meridian MAX Release 9 Enhanced Software.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
11	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH10EA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN/SNNE Release 9 Enhanced to Virtual Feature Level Promotion	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Order to add the capability of using all the features available with Meridian MAX Release 9 Virtual Software.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- Virtual software includes MEI-Network, which requires X11 Release 19 or later for Option 21-81C.
- Both Enhanced and Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	S0005902	MAX Status Interface (MSI) for Meridian MAX Release 9	8	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software
1	S0005903	MAX Event Interface (MEI) (Network) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH11AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPEE Release 9 Fundamental Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Requires one of the following hardware systems: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11 but is supported on the Option 11E and 11C.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00BA	Meridian MAX-IPEE Release 9 Software	1	S0005897	MTE Connectivity for Meridian MAX Release 9
1	S0005894	5 LAN Session Increment for MTE Release 9	2	S0005907	10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH11BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPEE Release 9 Enhanced Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Requires one of the following hardware systems: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11 but is supported on the Option 11E and 11C.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00BA	Meridian MAX-IPEE Release 9 Software	1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9
4	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005904	MAX Event Interface (MEI) (Observe) for Meridian MAX Release 9
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9	2	S0005907	10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software
1	S0005897	MTE Connectivity for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH11CA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPEE Release 9 Virtual Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Requires one of the following hardware systems: NTJH17AA - Meridian MAX-IPEE Module (Option 11) - North America; NTJH17AA - Meridian MAX-IPEE Module (Option 21-81C) - North America.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11 but is supported on the Option 11E and 11C.
- Virtual software includes MEI-Observe & MEI-Network, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial munber must be provided when ordering this code as part of a Meridian MAX addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH00BA	Meridian MAX-IPEE Release 9 Software	1	S0005902	MAX Status Interface (MSI) for Meridian MAX Release 9
4	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005903	MAX Event Interface (MEI) (Network) for Meridian MAX Release 9
1	S0005895	MAX Configuration Control (CC) for Meridian MAX Release 9	1	S0005904	MAX Event Interface (MEI) (Observe) for Meridian MAX Release 9
1	S0005896	MAX Custom Calculator/Formula Definition (FD) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9
1	S0005897	MTE Connectivity for Meridian MAX Release 9	2	S0005907	10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9	1	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software
1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH11DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 9 Fundamental to Enhanced Feature Level Promotion	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Order to add the capability of using all the features available with Meridian MAX Release 9 Enhanced Software.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- This feature level promotion requires existing Meridian MAX-IPE or new MAX-IPEE hardware. If the upgrade uses existing MAX-IPE hardware, the MAX database size will be configured to either 90 MB or 250 MB, depending upon the size of the Hard Disk Drive (HDD) installed in the existing MAX-IPE Module. If the module contains either a 180 MB or a 240 MB HDD, then the database will be 90 MB. If the module contains a 1.2 GB HDD, then the database will be 250 MB. If the existing MAX-IPE Module contains either a 180 MB or a 240 MB HDD that is limited to the 90 MB database size but the larger 250 MB database size is desired, upgrade to an IPEE.
- If upgrading from a MAX-IPE to a MAX-IPEE order one of the following: NTJH93EA - IPE to IPEE Upgrade/Repair Kit #1 - Global; NTJH93FA - IPE to IPEE Upgrade/Repair Kit #2 - Global.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11 but is supported on the Option 11E and 11C.
- Enhanced software includes MEI-Observe, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	S0005894	5 LAN Session Increment for MTE Release 9	1	S0005900	MAX CCR/EAR Reporting (CCR) for Meridian MAX Release 9
1	S0005898	MAX Network ACD (NACD) for Meridian MAX Release 9	1	S0005905	MAX Data Stream Reporting (DSR) for Meridian MAX Release 9

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH11EA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 9 Enhanced to Virtual Feature Level Promotion	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	S3

Notes:

- Order to add the capability of using all the features available with Meridian MAX Release 9 Virtual Software.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- This feature level promotion requires existing Meridian MAX-IPE or new MAX-IPEE hardware. If the upgrade uses existing MAX-IPE hardware, the MAX database size will be configured to either 90 MB or 250 MB, depending upon the size of the Hard Disk Drive (HDD) installed in the existing MAX-IPE Module. If the module contains either a 180 MB or a 240 MB HDD, then the database will be 90 MB. If the module contains a 1.2 GB HDD, then the database will be 250 MB. If the existing MAX-IPE Module contains either a 180 MB or a 240 MB HDD that is limited to the 90 MB database size but the larger 250 MB database size is desired, upgrade to an IPEE.
- If upgrading from a MAX-IPE to a MAX-IPEE order one of the following: NTJH93EA - IPE to IPEE Upgrade/Repair Kit #1 - Global; NTJH93FA - IPE to IPEE Upgrade/Repair Kit #2 - Global.
- IPEE (Option 11) Requires X11 Release 16 or higher. For X11 Release 16 or 18, then prerequisites are SW1132A Enhanced Business Software Update.
- IPEE (Option 11E) Requires X11 Release 16 or higher. For X11 Release 20, then prerequisite is SW1132E Enhanced Business Software Update. For X11 Release 21, then prerequisites are SW1132E Enhanced Business Software Update, NTBK83BE or NTBK83BG Enhanced Business Software, NTBK83EE or NTBK83EG Enhanced Business Software-no DISA.
- IPEE (Option 11C) Requires X11 Release 16 or higher. For X11 Release 22, then prerequisites are NTSF8021 Enhanced Business Software Package and NTSF8029 Option 11/11E to Option 11C Release 2 Enhanced Business Software Upgrade - Includes MQA.
- IPEE (Options 21-81C) Requires X11 Release 17 or higher. For X11 Release 17, then prerequisites are SW0201B Basic ACD Features (ACD-A), SW0202C Advanced ACD Features (ACD-B), SW0203B ACD Reports (ACD-C1), SW0204A Load Management (ACD-C2), SW0205A ACD Link, and SW0206A MAX Report Enhancements. For X11 Release 18, then prerequisites are SW0221A ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 19, then prerequisites are SW0221B ACD/Message Processing and SW0224A Enhanced Call Center Management. For X11 Release 20, 21, 22, then prerequisites are SW0221C ACD/Message Processing and SW0224A Enhanced Call Center Management.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11 but is supported on the Option 11E and 11C.
- Virtual software includes MEI-Network, which requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Both Enhanced and Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	S0005902	MAX Status Interface (MSI) for Meridian MAX Release 9	1	S0005903	MAX Event Interface (MEI) (Network) for Meridian MAX Release 9

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NTJH12AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Software Migration from MAX-SNN to MAX-SNNE	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S1

Notes:

- Order when upgrading from any Meridian MAX Release 9 system running on MAX-SNN hardware to a MAX-SNNE Release 9 system.
- Requires the NTJH15DA hardware upgrade package from MAX-SNN to MAX-SNNE.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- Fundamental level software includes support for 200 agent positions (minimum), support for 8 asynchronous I/O ports (minimum), Custom Calculator/Formula Definition, Configuration Control, Meridian Terminal Emulator (MTE) enabled, and 5 LAN Sessions.
- Virtual level software includes all items provided in Enhanced software plus support for 1000 agent positions (minimum), MSI, and MEI-Network (1 link).
- Requires X11 Release 17 or later.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements.
- For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- MAX 9 Fundamental on the SNN will be upgraded to MAX 9 Fundamental on the SNNE, MAX 9 Enhanced on the SNN to MAX 9 Enhanced on the SNNE, and MAX 9 Virtual on the SNN to MAX 9 Virtual on the SNNE. The number of agent positions and number of asynchronous I/O ports provisioned in software for the SNNE will be the same as the number provisioned on the existing SNN system to be upgraded.
- Enhanced level software includes all items provided in Fundamental software plus CCR/EAR MIS, Data Stream Reporting, NACD MIS, 60 LAN sessions, MEI-Observe (3 links), the capability to enable NAC Connectivity, and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- Hardware and software to support additional asynchronous I/O ports must be purchased separately. Software to support additional agent positions must be purchased separately.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH12BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Fundamental to MAX-SNNE Fundamental	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Order when migrating from Meridian MAX-IPE hardware running MAX Release 9 Fundamental software to MAX-SNNE hardware running MAX Release 9 Fundamental software.
- Requires one of the following Meridian MAX-SNNE hardware system: NTJH15AA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power - North America; NTJH15BA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power - North America.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- This migration will result in the provision of MAX 9 software for operation on MAX-SNNE hardware that is identical in feature content and capacity to the feature content and capacity of the MAX 9 software on the existing MAX-IPE platform to be upgraded but will provide for 200 agent positions (minimum) and 5 LAN sessions.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- Requires X11 Release 17 or later: For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements. For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management and SW0222A Enhanced ACD Overflow.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH12CA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Enhanced to MAX-SNNE Enhanced	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Order when migrating from Meridian MAX-IPE hardware running MAX Release 9 Enhanced software to MAX-SNNE hardware running MAX Release 9 Enhanced software.
- Requires one of the following Meridian MAX-SNNE hardware system: NTJH15AA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power - North America; NTJH15BA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power - North America.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- Enhanced level software includes all items provided in Fundamental software plus CCR/EAR MIS, Data Stream Reporting, NACD MIS, 60 LAN sessions, MEI-Observe (3 links), the capability to enable NAC Connectivity, and the capability to enable Multiple Queue Assignment.
- Enhanced software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- This migration will result in the provision of MAX 9 software for operation on MAX-SNNE hardware that is identical in feature content and capacity to the feature content and capacity of the MAX 9 software on the existing MAX-IPE platform to be upgraded but will provide for 200 agent positions (minimum) and 60 LAN sessions.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- Requires X11 Release 17 or later: For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements. For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management and SW0222A Enhanced ACD Overflow.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH12DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Virtual to MAX-SNNE Virtual	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	S3

Notes:

- Order when migrating from Meridian MAX-IPE hardware running MAX Release 9 Fundamental software to MAX-SNNE hardware running MAX Release 9 Fundamental software.
- Requires one of the following Meridian MAX-SNNE hardware system: NTJH15AA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power - North America; NTJH15BA PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power - North America.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- Virtual level software includes all items provided in Fundamental software plus CCR/EAR MIS, Data Stream Reporting, NACD MIS, 60 LAN sessions, MEI-Observe (3 links), the capability to enable NAC Connectivity, and the capability to enable Multiple/Queue Assignment.
- Virtual software includes the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable MQA, order S0005901. MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order S0005899.
- This migration will result in the provision of MAX 9 software for operation on MAX-SNNE hardware that is identical in feature content and capacity to the feature content and capacity of the MAX 9 software on the existing MAX-IPE platform to be upgraded but will provide for 1000 agent positions and 60 LAN sessions.
- If currently running 155 MB data cassette tapes, three 600 MB data cassette tapes (A0605411) will be required.
- Requires X11 Release 17 or later: For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0206A MAX Report Enhancements. For Release 18/19/20/21/22, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management and SW0222A Enhanced ACD Overflow.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH15AA

Description	System Compatibility	Product compatibility	W/S
PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Must be housed in the NT7D18AB Applications Equipment Module (DC).
- Requires one of the following software packages: NTJH01AA - ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade - Global; NTJH01BA - ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade - Global; NTJH12BA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Fundamental - North America; NTJH12CA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Enhanced - North America; NTJH12DA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Virtual - North America.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16AA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D61EV SDI Cable (45 ft); three NT8D96BE 4-port Octopus Cables.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D64DC	Application Module Power Supply DC	1	NTJH16AA	SNNE Peripheral Assembly
1	NTJH08AA	SNNE Hardware Assembly - Global			

Status
➤ S

NTJH15BA

Description	System Compatibility	Product compatibility	W/S
PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Must be housed in the NT7D18AA Applications Equipment Module (AC).
- Requires one of the following software packages: NTJH01AA - ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade - Global; NTJH01BA - ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade - Global; NTJH12BA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Fundamental - North America; NTJH12CA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Enhanced - North America; NTJH12DA - Meridian MAX Release 9 Software Migration from Meridian MAX-IPE/IPEE to Meridian MAX-SNNE Virtual - North America.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16AA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D61EV SDI Cable (45 ft); three NT8D96BE 4-port Octopus Cables.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D64AA	Application Module Power Supply AC	1	NTJH16AA	SNNE Peripheral Assembly
1	NTJH08AA	SNNE Hardware Assembly - Global			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH15CA

Description	System Compatibility	Product compatibility	W/S
Meridian Option MAX/MAX-SEE to Meridian MAX-SNNE Hardware Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Existing AC or DC power supply and VME322XT 8-Channel Asynchronous I/O Cards can be reused in the new SNNE system.
- Requires an upgrade from one of the following hardware systems: MAX-SEE, MAX Option 1 or 2.
- Requires one of the following software packages: NTJH01CA - Meridian MAX Release 3 or 4 to Meridian MAX-SNNE Release 9 Software Upgrade - Global; NTJH01DA - Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade - Global.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16BA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D18KA Power Sense Monitor Kit.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH08BA	SEE/Option to SNNE Hardware Assembly - Global	1	NTJH16BA	SEE to SNNE Peripheral Assembly - North America

Status
➤ S

NTJH15DA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Existing AC or DC power supply and VME332XT 8-Channel Asynchronous I/O Cards can be reused in the new SNNE system.
- Requires an upgrade from one of the following hardware systems: MAX-SNN.
- Requires MAX Release 8 or later software. To upgrade MAX 8 to MAX 9, order one of the following software packages: NTJH01DA - Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade - Global; NTJH01EA - Meridian MAX-SNN Release 7 to Meridian MAX SNN/SNNE Release 9 Software Upgrade - Global; NTJH01FA - Meridian MAX-SNN/SNNE Release 8 to Meridian MAX SNN/SNNE Release 9 Software Upgrade - Global; NTJH12AA - Meridian MAX Release 9 Software Migration from Meridian MAX-SNN to Meridian MAX-SNNE - Global.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16AA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D61EV SDI Cable (45 ft); three NT8D96BE 4-port Octopus Cables.

Qty	Order code	Description	Qty	Order code	Description
1	NTJH16CA	SNN to SNNE Peripheral Assembly			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH15EA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE System Hardware, DC Power	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Must be housed in the NT7D18AB Applications Equipment Module (DC).
- Requires one of the following software packages: NTJH10AA - Meridian MAX-SNNE Release 9 Fundamental Software - North America; NTJH10BA - Meridian MAX-SNNE Release 9 Enhanced Software - North America; NTJH10CA - Meridian MAX-SNNE Release 9 Virtual Software - North America.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16AA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D61EV SDI Cable (45 ft); three NT8D96BE 4-port Octopus Cables.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D64DC	Application Module Power Supply DC	1	NTJH16AA	SNNE Peripheral Assembly
1	NTJH08AA	SNNE Hardware Assembly - Global			

Status
➤ S

NTJH15FA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNNE System Hardware, AC Power	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNNE	W1

Notes:

- There must be at least one supervisor terminal and one printer equipped per system.
- Must be housed in the NT7D18AA Applications Equipment Module (AC).
- Requires one of the following software packages: NTJH10AA - Meridian MAX-SNNE Release 9 Fundamental Software - North America; NTJH10BA - Meridian MAX-SNNE Release 9 Enhanced Software - North America; NTJH10CA - Meridian MAX-SNNE Release 9 Virtual Software - North America.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.
- The NTJH16AA Peripheral Assembly contains one USRobotics 33.6 kbps External Modem; one NT7D47EA LAN Transceiver Cable (10 ft); one NT7D61EF SDI Cable (10 ft); one NT7D61EV SDI Cable (45 ft); three NT8D96BE 4-port Octopus Cables.

Qty	Order code	Description	Qty	Order code	Description
1	NT7D64AA	Application Module Power Supply AC	1	NTJH16AA	SNNE Peripheral Assembly
1	NTJH08AA	SNNE Hardware Assembly - Global			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH17AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPEE Module (Option 11)	11; 11C; 11E	Meridian MAX-IPEE	W1

Notes:

- The NTJH18BA IPEE Peripheral Assembly contains one NT1R03HF Modem Cable, one USRobotics 33.6 kbps External Modem; one NT1R03AA 4-Port Octopus Cable W/Ethernet; one NT1R03BA 4-Port Octopus Cable.
- The Meridian 1 Serial number must be provided when ordering this code.
- One (MAX) maintenance console, one supervisor terminal, and one printer must be connected to MAX-IPEE asynchronous I/O ports. Additional supervisor terminals and printers can be connected through other asynchronous I/O ports or through the LAN.
- The MAX maintenance console and all supervisor terminals must be 100% compatible with VT200 terminal specifications.
- Requires one of the following software packages: NTJH02AA - ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH02BA - ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH02CA - Meridian MAX Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH11AA - Meridian MAX-IPEE Release 9 Fundamental Software - North America; NTJH11BA - Meridian MAX-IPEE Release 9 Enhanced Software - North America; NTJH11CA - Meridian MAX-IPEE Release 9 Virtual Software - North America.
- The A0669467 IPEE module occupies 3 consecutive card slots in the IPE shelf of a Meridian 1, Option 11 main or expansion cabinet.
- Includes 8 asynchronous I/O ports and the capability to connect to a LAN.
- Devices that connect to MAX-IPEE asynchronous I/O ports (the MAX maintenance console, supervisor terminals, and printers) require straight-through, RS-232 type cables. Cables of various lengths and connector gender are available. For male-to-male connections, order NT1R03DB, DC, DF, DP, or DV (for 2, 4, 10, 25, or 45 ft. lengths, respectively). For male-to female connections, order NT1R03EB, EC, EF, EP, or EV (for 2, 4, 10, 25, or 45 ft. lengths, respectively).
- The High-Speed Link (HSL) and the Load Management Link (LML) connection at the Option 11 require one NTAK19AA cable (an NTAK19BA may be used instead). Both of these cables are equipped with the Option 11 system. If additional cable length is required, order NT1R03DX cables (one for each link) for connection between the NTAK19AA (or BA) cable and the NT1R03BA octopus cable.
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.

Qty	Order code	Description	Qty	Order code	Description
1	A0669467	Meridian IPEE Application Module for Option 11	1	NTJH18AA	IPEE Peripheral Assembly

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH17BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPEE Module (Option 21-81C)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPEE	W1

Notes:

- One (MAX) maintenance console, one supervisor terminal, and one printer must be connected to MAX-IPEE asynchronous I/O ports. Additional supervisor terminals and printers can be connected through other asynchronous I/O ports or through the LAN.
- The MAX maintenance console and all supervisor terminals must be 100% compatible with VT200 terminal specifications.
- Requires one of the following software packages: NTJH02AA - ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH02BA - ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH02CA - Meridian MAX Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade - Global; NTJH11AA - Meridian MAX-IPEE Release 9 Fundamental Software - North America; NTJH11BA - Meridian MAX-IPEE Release 9 Enhanced Software - North America; NTJH11CA - Meridian MAX-IPEE Release 9 Virtual Software - North America.
- The A0669468 IPEE module occupies 4 consecutive card slots in an IPE shelf of a Meridian 1, Option 21-81C system.
- Includes 8 asynchronous I/O ports and the capability to connect to a LAN.
- Devices that connect to MAX-IPEE asynchronous I/O ports (the MAX maintenance console, supervisor terminals, and printers) require straight-through, RS-232 type cables. Cables of various lengths and connector gender are available. For male-to-male connections, order NT1R03DB, DC, DF, DP, or DV (for 2, 4, 10, 25, or 45 ft. lengths, respectively). For male-to female connections, order NT1R03EB, EC, EF, EP, or EV (for 2, 4, 10, 25, or 45 ft. lengths, respectively).
- Order additional cables for connection of the High-Speed Link (HSL) and the Load Management Link (LML) to the Meridian 1, one for each link. When connecting to an NT8D41 SDI Paddle Board, use an NT8D93AJ or AW (for 16 or 48 ft. lengths, respectively). When connecting to a QPC139 Dual SDI Card or a QPC841 Quad SDI Card, use an NT1R03DB, DC, DF, DP, or DV (for 2, 4, 10, 25, or 45 ft. lengths, respectively).
- For detailed information on system ordering and configuration, consult the Meridian MAX Release 9 Ordering Procedures available from your Nortel representative.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0669468	Meridian IPEE Application Module for Options 21-81C	1	NTJH18AA	IPEE Peripheral Assembly

Status
➤ Δ S

NTJH90AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-AM Release 6 Software Media Replacement/Upissue		Meridian MAX-SEE; Meridian MAX-SNN	S3

Notes:

- Order this package to obtain the latest issue of Release 6 if you already have an earlier issue of Release 6 (i.e. 6.19 or 6.22) or to obtain replacement media for lost or damaged MAX 6 software tapes.
- Only the current release/issue of MAX 6 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0017.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0804348	Meridian MAX Keycode
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTJH91AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Release 6 Software Media Replacement/Upissue	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- Order this package to obtain the latest issue of Release 6 if you already have an earlier issue of Release 6 (i.e. 6.19 or 6.22) or to obtain replacement media for lost or damaged MAX 6 software tapes.
- Only the current release/issue of MAX 6 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0017.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0804348	Meridian MAX Keycode
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

Status
➤ S

NTJH92AA

Description	System Compatibility	Product compatibility	W/S
Meridian NAC-AM Release 2.5 Upissue/ Software Replacement			W0/ S3

Notes:

- Meridian NAC 2.5 software is Year 2000 compliant.
- Meridian NAC Software Service Transaction Fee (AM) P0889406 must be ordered with this package.
- Order this package to upissue from NAC 2.16 software or to replace lost or damaged NAC 2 media. Only NAC 2.5 software will be shipped. Not for upgrading from NAC 1 to 2.5.
- Requires NAC 2 Application Module Hardware.
- Requires MTE Release 9 Software if using PCs for supervisor terminals.
- Requires one (1) NT7D47EA LAN Transceiver Cable (10 ft). If you are upissuing from NAC 2.16 software, order this cable to be able to connect supervisor PCs running MTE 9 or later software and printers via a LAN.
- Nortel Networks recommends implementation of a backup strategy using a minimum of three tapes. Order individual 600 Mbyte tapes (blank) using code A0605411.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R27AB	NAC Release 2 5 Application Tape	1	P0886656	NAC 2 5 User Guide Supplement
1	NT1R28AB	NAC Release 2 5 UNIX O/S Tape			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTJH93AA

Description	System Compatibility	Product compatibility	W/S
IPE/IPEE Option 11 to Option 21-81C Conversion Kit		Meridian MAX-IPEE	W1/ S1

Notes:

- This package is for customers that wish to convert their Option 11 IPE/IPEE to an Option 21-81C IPE/IPEE.
- The customer will need to request a new keycode (SERV0017 in US, P0854020 in Canada) since their Software/Hardware will now be used against a different switch serial ID.
- Customer must supply both the old Option 11 switch serial number and the new large system switch serial number.
- The software must be reinstalled after the module is converted.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0730845	IPE/IPEE Opt 11 to Opt 21-81C Conversion Kit			

Status
➤ S

NTJH93BA

Description	System Compatibility	Product compatibility	W/S
IPE/IPEE Option 21-81C to Option 11 Conversion Kit		Meridian MAX-IPEE	W1/ S1

Notes:

- This package is for customers that wish to convert their Option 21-81C IPE/IPEE to an Option 11 IPE/IPEE.
- The customer will need to request a new keycode (SERV0017 in US, P0854020 in Canada) since their Software/Hardware will now be used against a different switch serial ID.
- Customer must supply both the old large system switch serial number and the new Option 11 switch serial number.
- The software must be reinstalled after the module is converted.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0730846	IPE/IPEE Opt 21-81C to Opt 11 Conversion Kit			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTJH93FA

Description	System Compatibility	Product compatibility	W/S
MAX-IPE to IPEE Upgrade Kit #2		Meridian MAX-IPEE	W1/ S1

Notes:

- This kit is for customers with a MAX-IPE Module (A0617009 or A0617010) that need to upgrade it to a MAX-IPEE.
- Advisement: It may not be necessary to order this MAX-IPE to MAX-IPEE Upgrade Kit if the existing MAX-IPE already supports a 250-Mbyte database. Meridian MAX-IPE modules with part numbers A0617009 or A0617010 that were shipped new from the factory before December 1995 contain 240-MByte hard disk drives and therefore, can only support 90-Mbyte databases. Thus, this upgrade kit should be ordered to upgrade such earlier modules to an IPEE configuration. However, new MAX-IPE modules with these part numbers that were shipped after November 1995 will support 250-Mbyte databases. These later modules contain 1-Gbyte hard disk drives and are already MAX-IPEE-Ready. This upgrade kit is not required for these later modules.
- When ordering, the customer must supply the Meridian 1 PBX serial number and must order code SERV0017 for MAX 8 and earlier or P0885111 for MAX 9 software to obtain a new keycode.
- Customers on MAX 4.62 or MAX 5 will need to upgrade to either MAX 6.31 (order SW7514B) or to the current release of Meridian MAX software.
- Customers on MAX 6.22 will need to upgrade to 6.31 (order NTJH91AA).
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0730854	IPEE 1GB Hard Drive Repair Kit			

Status
➤ Δ S

NTJH94AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Supervisor's User Guide (English); Package of 10			W0

Notes:

- This package contains 10 copies to the English Language Supervisor's User Guide for Meridian MAX Release 9.

Status
✓ § ➤ Δ S

NTJH95AA

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9 User Guide (Multilingual: English, French, Spanish); Package of 10			W0

Notes:

- This package contains 10 copies of the Multilingual (English, French, and Spanish) User Guide for Meridian Terminal Emulator (MTE) Release 9.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTJH97AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-AM Release 7.5 Software Media Replacement/Upissue		Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Order this package to obtain the latest issue of Release 7 software if you already have an earlier issue of Release 7 (i.e. 7.43 to 7.5) or to obtain replacement media for lost or damaged MAX 7 software tapes.
- Only the current release/issue of MAX 7 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0005.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R85AD	Meridian MAX Release 7 5 Application Tape	1	P0820461	Meridian MAX-AM Release 7 5 Keycode
1	NT1R86AD	Meridian MAX Release 7 5 UNIX O/S Tape			

Status
➤ Δ S

NTJH97BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 7.5 Software Media Replacement/Upissue		Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- Order this package to obtain the latest issue of Release 7 software if you already have an earlier issue of Release 7 (i.e. 7.43 to 7.5) or to obtain replacement media for lost or damaged MAX 7 software tapes.
- Only the current release/issue of MAX 7 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0017.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R85AD	Meridian MAX Release 7 5 Application Tape	1	P0820458	Meridian MAX-IPE/IPEE Release 7 5 Keycode
1	NT1R86AD	Meridian MAX Release 7 5 UNIX O/S Tape			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTJH98AA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-AM Release 8 Software Media Replacement/Upissue		Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Order this package to obtain the latest issue of Release 8 software if you already have an earlier issue of Release 8 (i.e. 8.59 to 8.71) or to obtain replacement media for lost or damaged MAX 8 software tapes.
- Only the current release/issue of MAX 8 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0005.
- If upissuing to MAX Release 8.71 or later from an earlier issue of MAX Release 8 software, MTE 8 software will be included to replace MTE 7 software that was pre-packaged with the earlier MAX 8 packages (5 copies of the MTE 8 Single-User License for the Fundamental and Enhanced level packages and 1 copy of the MTE 8 System License for the Virtual level package.) No replacement MTE 8 software will be shipped with this package for any MTE 7 software that was ordered apart from the MAX 8 Fundamental, Enhanced or Virtual Software packages.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R34AB	Meridian MAX Release 8 Application Tape	1	P0854018	Meridian MAX-AM Release 8 Keycode
1	NT1R36AB	Meridian MAX Release 8 UNIX O/S Tape			

Status
➤ Δ S

NTJH98BA

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/IPEE Release 8 Software Media Replacement/Upissue		Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- Order this package to obtain the latest issue of Release 8 software if you already have an earlier issue of Release 8 (i.e. 8.59 to 8.71) or to obtain replacement media for lost or damaged MAX 8 software tapes.
- Only the current release/issue of MAX 8 software in effect at the time an order is received will be shipped.
- Customer must also order Software Service Transaction Fee SERV0017.
- If upissuing to MAX Release 8.71 or later from an earlier issue of MAX Release 8 software, MTE 8 software will be included to replace MTE 7 software that was pre-packaged with the earlier MAX 8 packages (3 copies of the MTE 8 Single-User License for the Fundamental and Enhanced level packages and 1 copy of the MTE 8 System License for the Virtual level package.) No replacement MTE 8 software will be shipped with this package for any MTE 7 software that was ordered apart from the MAX 8 Fundamental, Enhanced or Virtual Software packages.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R34AB	Meridian MAX Release 8 Application Tape	1	P0854019	Meridian MAX-IPE/IPEE Release 8 Keycode
1	NT1R36AB	Meridian MAX Release 8 UNIX O/S Tape			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTJR27AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Telset User Guide Package - Canadian French			W0

Qty	Order code	Description	Qty	Order code	Description
10	P0905813	Multimedia Messaging User Guide, French	10	P0913809	CallPilot 1 07 M2000/M3900 Keypad Template, Canadian French
10	P0905815	Multimedia Messaging Quick Reference Card - French	10	P0913811	CallPilot 1 07 M3000 Keypad Template, Canadian French

Status
➤ Δ B

NTKG80CF

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Release 25 English Documentation Package, Coil			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0907446	Planning and Installation Guide	1	P0907449	Customer Configuration Backup and Restore (Coil)
1	P0907447	Fault and Clearing Guide	1	P0907450	Upgrade Guide
1	P0907448	Central Answering Position Guide	1	P0907451	Option 11C Administration & Maintenance I/O Guides

Status
§ ➤ S

NTKS1002

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact InterOffice Communications Package	11C COMPACT		W1

Notes:

- Software activation keycode.
- Please provide your System Serial ID with your order. NTKS1001 is a prerequisite for this package.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW30DD	Option 11C Compact Inter-Office Communications Feature Set (S/W)	1	P0875913	Meridian Mail Enterprise Networking Installation and Administration Guide Release 12
1	NTMW34AB	Option 11C Compact Option Mail Enterprise Network Keycode			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTKS1005

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Spares Package	11C COMPACT	Meridian Mail Compact Option	W0

Qty	Order code	Description	Qty	Order code	Description
1	NTMW01AA	Option 11C Compact System Core Card	1	NTMW0802	Option 11C Compact Cabinet Fan Assembly
1	NTMW02AB	Meridian Mail Compact Option 68K Memory Card	1	NTMW10AA	Option 11C Compact - 10m Fiber Receiver Card
1	NTMW03AA	4-Port DSP Daughter Card	1	NTMW11AB	Option 11C Compact AC Power Supply

Status
➤ S

NTKS1011

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Advanced Hospitality Communications Package			W0/ S1

Notes:

- The NTKS1010 (Compact Hospitality Communications Package) is a pre-requisite for this package.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Qty	Order code	Description	
1	NTMW30FD	Option 11C Compact Advanced Hospitality Communications Feature Set (S/W)	
1	NTMW38AA	Mini IPE 1 5MB DTI/PRI Package	
	Each Package Includes:		
	1	NTMW04AA	Mini IPE 1 5MB DTI/PRI Card
	1	NTMW37AA	Mini IPE 1 5MB DTI/PRI Cable
	1	P0872788	Mini IPE 1 5 MB DTI/PRI Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTKS1012

Description	System Compatibility	Product compatibility	W/S
Journal Call Accounting Software with Billing			S1

Notes:

- Journal is a PC-based Call Accounting Software package which is provided on a CDROM, and runs on Windows 95/98, and Windows NT operating systems. Please refer to the Journal User Guide P0885219 for minimum PC requirements.
- IMPORTANT CUSTOMER ORDER INFORMATION: It is important to include the following information with your Journal Software order:
- 1. The correct Hotel Name and Telephone Number must be provided in order to obtain accurate Rate Table information.
- 2. In addition, please specify if Time of Day Discounts would be used at the hotel. ie. Time of Day Discount: Yes / No.
- The Time of Day Discount relates to different rates charged to guests depending on when the phone call is made. This feature may depend on the hotelscustomerpolicies.Thereisnoadditionalchargeforthisfeature.'
- The System Site ID must be provided when ordering this package for an existing Meridian system.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW57AA	Journal/Registrar CDROM	1	P0885044	Journal Rate Table (Update)
1	P0885041	Journal Activation Keycode	1	P0885219	Journal Administration and User Guide

Status
➤ S

NTKS1013

Description	System Compatibility	Product compatibility	W/S
Registrar Front Desk Software with Billing			S3

Notes:

- Journal and Registrar software applications are compatible with all Meridian machine types.
- NTKS1012 Journal Call Accounting Software is required in order to run Registrar software.
- The System Site ID must be provided when ordering this package for an existing Meridian system.

Qty	Order code	Description	Qty	Order code	Description
1	P0885040	Registrar Activation Keycode	1	P0885220	Registrar User Guide

Status
➤ S

NTKS1015

Description	System Compatibility	Product compatibility	W/S
Journal/Registrar Software CDROM Up-Issue			W2/ S3

Notes:

- This package provides a Software and Documentation up-issue for Journal and Registrar PC Software. A new keycode is not required with the up-issue.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW57AA	Journal/Registrar CDROM			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTKS2001

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Office Communications Package - Additional 8 TN's	11C COMPACT		W1

Notes:
- Software activation keycode.
- NTKS1001 is a prerequisite for this package.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
§ ➤ S

NTKS2002

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact InterOffice Communications Package - Additional 8 TN's	11C COMPACT		W1

Notes:
- Software activation keycode.
- NTKS1002 is a prerequisite for this package.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ S

NTKS2010

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Hospitality Communications Expansion TN's	11C COMPACT		S1

Notes:
- 11C Compact Hospitality Additional TN's Package for NTKS1010 - Option 11C Compact Hospitality Communications Feature Set.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTKS2011

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Advanced Hospitality Package - Additional 8 TN's			S1

Notes:
- This package provides additional TN's for the NTKS1011 - Option 11C Compact Advanced Hospitality Communications Package.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ Δ S

NTKS2020

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Network Message Communications Expansion TN's (8)	11C COMPACT		S1

Notes:
- Software activation keycode. NTKS1020 is a prerequisite for this package.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ S

NTKS2050

Description	System Compatibility	Product compatibility	W/S
Compact Option Dual Language Prompting	11C COMPACT	Meridian Mail Compact Option R11	S1

Notes:
- NTKS2051 Additional Language Software is a prerequisite.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ S

NTKS2051

Description	System Compatibility	Product compatibility	W/S
Compact Option Additional Language	11C COMPACT	Meridian Mail Compact Option R11	S1

Notes:
- Order one for each additional language required; Maximum of four languages. Two languages comes standard.
- Each additional language reduces storage capacity by three hours.
- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTKS2052

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 11 or Release 12 to Release 13 Compact Option Software Upgrade Package	11C COMPACT	Meridian Mail Compact Option	S1

Notes:
- The Option 11C Compact Site ID must be provided when ordering this code.

Qty	Order code	Description	
1	NTMW18BA	Meridian Mail Compact Option Releaes 13 Software Package	
	Each Package Includes:		
	1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)
	1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)
	1	NT6R47AD	MM13 13 Master Tape NA 1
	1	NTMW56AA	Meridian Mail Compact Option Outcalling Feature
	1	P0873717	Meridian Mail Compact Option System Administration Guide
	1	P0906932	Meridian Mail Release 13 Keycode
1	P0906932	Meridian Mail Release 13 Keycode	

Status
➤ S

NTKS2500

Description	System Compatibility	Product compatibility	W/S
X27 Software Up-issue (within the same Release)			S1

Notes:
- The Option 11C Compact Site ID must be provided when ordering this code.

Status
➤ S

NTKS2501

Description	System Compatibility	Product compatibility	W/S
X27 Software Release Upgrade			S1

Notes:
- The Option 11C Compact Site ID must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTKS3001

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 12 Compact Option 4 Ports 24 Hours Package	11C COMPACT	Meridian Mail Compact Option	W1/ S1

Notes:

- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Qty	Order code	Description	
1	NTMW15AC	Meridian Mail Compact Option Base Hardware Package	
	Each Package Includes:		
	1	NTDK74AB	Card Option 4 5GB Disk Drive
	1	NTMW02AB	Meridian Mail Compact Option 68K Memory Card
	1	NTMW03AA	4-Port DSP Daughter Card
1	NTMW18BA	Meridian Mail Compact Option Releaes 13 Software Package	
	Each Package Includes:		
	1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)
	1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)
	1	NT6R47AD	MM13 13 Master Tape NA 1
	1	NTMW56AA	Meridian Mail Compact Option Outcalling Feature
	1	P0873717	Meridian Mail Compact Option System Administration Guide
	1	P0906932	Meridian Mail Release 13 Keycode

Status
§ ➤ S

NTKS9050

Description	System Compatibility	Product compatibility	W/S
DISA Option 11C Compact	11C COMPACT		W1

Notes:

- This feature must be ordered separately.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ S

NTKS9051

Description	System Compatibility	Product compatibility	W/S
This code allows the addition software packages to be enabled for Inter-Office Feature Set.			S1

Notes:

- NTKS1002 is a prerequisite for this code. If you have the NTKS1020 package you do not need to order this code.
- Turns on additional software packages 175 and 148 for Option 11C Compact Inter-Office Feature Set.
- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTLH02AA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Reference Library, Release 25			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTLH03AA	System Planning and Engineering Guide	1	NTLH11AA	X11 Networking Features
1	NTLH04AA	System Installation and Maintenance Guide	1	NTLH12AA	X11 Data Features
1	NTLH05AA	System and Software Upgrade Guide	1	NTLH13AA	ACD Reference Guides
1	NTLH06AA	Remote Peripheral Equipment Guide	1	NTLH14AA	X11 Hospitality Features
1	NTLH09AA	X11 Input/Output Guide	1	P0912432	Library Navigator
1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide			

Status
➤ S

NTLT83AA

Description	System Compatibility	Product compatibility	W/S
MIRAN to MIRAN Release 2 Card Upgrade Kit			W1

Notes:
- Requires original security device identification number to be submitted to sales representative for NTLT83AA upgrade order processing.
- The MIRAN Security Device ID is required when ordering ths code.

Qty	Order code	Description	Qty	Order code	Description
1	NTAG36AC	Meridian Integrated RAN (Release 2) Base Spare Card	1	P0843071	Keycode Label
1	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	1	P0885702	Meridian Integrated RAN (Release 2) NTP Guide

Status
➤ S

NTMF94EA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 ELAN, TLAN, RS232 Port Cable	11C; 51C; 61C; 81; 81C		W0

Notes:
- The cable required for all packages or cards for connecting to the LAN/WAN environment (for cards without the D-Channel).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN0006

Description	System Compatibility	Product compatibility	W/S
Key Cap Package (M3905)		M3905	W1

Status
➤ S

NTMN13AA66

Description	System Compatibility	Product compatibility	W/S
Footstand, Platinum (M3901, M3902)		M3901; M3902	W1

Status
➤ S

NTMN13AA70

Description	System Compatibility	Product compatibility	W/S
Footstand, Charcoal (M3901, M3902)		M3901; M3902	W1

Status
➤ S

NTMN14AA66

Description	System Compatibility	Product compatibility	W/S
Footstand, Platinum (M3903, M3904, M3905)		M3903; M3904; M3905	W1

Status
➤ S

NTMN14AA70

Description	System Compatibility	Product compatibility	W/S
Footstand, Charcoal (M3903, M3904, M3905)		M3903; M3904; M3905	W1

Status
➤ S

NTMN15AA66

Description	System Compatibility	Product compatibility	W/S
Meridian Wall Mount Kit, Platinum (M3903, M3904, M3905)		M3903; M3904; M3905	W1

Notes:

- Does not support use of accessory cartridges.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN15AA70

Description	System Compatibility	Product compatibility	W/S
Meridian Wall Mount Kit, Charcoal (M3903, M3904, M3905)		M3903; M3904; M3905	W1

Notes:
- Does not support use of accessory cartridges.

Status
✓ ➤ S

NTMN16AA66

Description	System Compatibility	Product compatibility	W/S
Brandline Insert, Platinum (Package of 250 P0904456, M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
✓ ➤ S

NTMN16AA70

Description	System Compatibility	Product compatibility	W/S
Brandline Insert, Charcoal (Package of 250 P0904455, M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
✓ ➤ S

NTMN17AA66

Description	System Compatibility	Product compatibility	W/S
Handset, Platinum (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

Status
✓ ➤ S

NTMN17AA70

Description	System Compatibility	Product compatibility	W/S
Handset, Charcoal (M3900 Series)		M3901; M3902; M3903; M3904; M3905	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTMN18AA66

Description	System Compatibility	Product compatibility	W/S
Handset Kit, Platinum (M3905)		M3905	W1

Status
✓ ➤ S

NTMN18AA70

Description	System Compatibility	Product compatibility	W/S
Handset Kit, Charcoal (M3905)		M3905	W1

Status
➤ S

NTMN19AA

Description	System Compatibility	Product compatibility	W/S
Key Cap Tool (M3905)		M3905	W1

Status
➤ S

NTMN31BA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3901 Entry, Platinum	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).

Status
➤ S

NTMN31BA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3901 Entry, Charcoal	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN32BA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3902 Basic, Platinum	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Requires Accessory Connection Module if equipped with accessory cartridge.
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN32BA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3902 Basic, Charcoal	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Requires Accessory Connection Module if equipped with accessory cartridge.
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN33BA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3903 Enhanced, Release 1, Platinum	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software
- M3900 series telephones are compatible with the Digital Line Cards (NT8D02xx).
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN33BA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3903 Enhanced, Release 1, Charcoal	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN33FA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3903 Enhanced, Release 2, Platinum	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:
- Requires X11 Release 25 and later software.
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx).
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN33FA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3903 Enhanced, Release 2, Charcoal	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:
- Requires X11 Release 25 and later software.
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx).
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN34BA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3904 Professional, Release 1, Platinum	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:
- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Supports up to (2) Key-based Expansion Modules.
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN34BA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3904 Professional, Release 1, Charcoal	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:

- Requires X11 Release 24 or later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Supports up to (2) Key-based Expansion Modules.
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN34FA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3904 Professional, Release 2, Platinum	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:

- Requires X11 Release 25 and later software.
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx).
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.
- Supports up to two (2) Key-based Expansion Modules or one (1) Display-based Expansion Module.

Status
➤ S

NTMN34FA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3904 Professional, Release 2, Charcoal	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:

- Requires X11 Release 25 and later software.
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx).
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.
- Supports up to two (2) Key-based Expansion Modules or one (1) Display-based Expansion Module.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN35BA66

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Call Center, Release 1, Platinum	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:

- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Suports up to (2) Key-based Expansion Modules.
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
➤ S

NTMN35BA70

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Call Center, Release 1, Charcoal	11C X11; 51C X11; 61C X11; 81 X11; 81C X11		W1

Notes:

- Requires X11 Release 24 and later software.
- M3900 series telephones are compatible with the Digital Line Card (NT8D02xx).
- Supports up to (2) Key-based Expansion Modules.
- Requires Accessory Connection Module if equipped with accessory cartridge(s).
- M3900 series accessory cartridges are field installable.

Status
★ ➤ S

NTMN35FA-66

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Call Center, Release 2, Platinum	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:

- Requires X11 Release 25 and later software
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx)
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s)
- M3900 series accessory cartridges are field installable
- Supports up to two (2) Key-based Expansion Modules or one (1) Display-based Expansion Module

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTMN35FA-70

Description	System Compatibility	Product compatibility	W/S
Meridian M3905 Call Center, Release 2, Charcoal	11C X11 R25; 51C X11 R25; 61C X11 R25; 81C X11 R25		W1

Notes:
- Requires X11 Release 25 and later software
- M3900 series telephones are compatible with Digital Line Cards (NT8D02xx)
- Requires Accessory Connector Module (ACM) if equipped with accessory cartridge(s)
- M3900 series accessory cartridges are field installable
- Supports up to two (2) Key-based Expansion Modules or one (1) Display-based Expansion Module

Status
➤ S

NTMN37AA70

Description	System Compatibility	Product compatibility	W/S
Key-based Expansion Module Without Footstand, Charcoal			W1

Notes:
- For use with M3904 and M3905 phones.

Status
➤ S

NTMN38AA66

Description	System Compatibility	Product compatibility	W/S
Key-based Expansion Module Kit 1, Platinum			W1

Notes:
- For use with M3904 and M3905 phones.

Status
➤ S

NTMN38AA70

Description	System Compatibility	Product compatibility	W/S
Key-based Expansion Module Kit 1, Charcoal			W1

Notes:
- For use with M3904 and M3905 phones.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN38BA66

Description	System Compatibility	Product compatibility	W/S
Key-based Expansion Module Kit 2, Platinum			W1

Notes:
- For use with M3904 and M3905 phones.

Status
➤ S

NTMN38BA70

Description	System Compatibility	Product compatibility	W/S
Key-based Expansion Module Kit 2, Charcoal			W1

Notes:
- For use with M3904 and M3905 phones.

Status
➤ S

NTMN59AA66

Description	System Compatibility	Product compatibility	W/S
Meridian External Alerter and Recording Interface, Platinum (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.
- Does not support Wall Mount configuration.

Status
➤ S

NTMN59AA70

Description	System Compatibility	Product compatibility	W/S
Meridian External Alerter and Recording Interface, Charcoal (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.
- Does not support Wall Mount configuration.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN67AA66

Description	System Compatibility	Product compatibility	W/S
Meridian Display-Based Expansion Module, Platinum (M3900 Series)		M3904; M3905	W1

Notes:
- Maximum of one Display-based Expansion Module per set.
- Does not support Wall Mount configuration.
- Cannot be used in conjunction with Key-based Expansion Module.

Status
➤ S

NTMN67AA70

Description	System Compatibility	Product compatibility	W/S
Meridian Display-Based Expansion Module, Charcoal (M3900 Series)		M3904; M3905	W1

Notes:
- Maximum of one Display-based Expansion Module per set.
- Does not support Wall Mount configuration.
- Cannot be used in conjunction with Key-based Expansion Module.

Status
➤ S

NTMN68AA66

Description	System Compatibility	Product compatibility	W/S
Meridian Analog Terminal Adapter (ATA), Platinum (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- Cannot be used in conjunction with Meridian Communications Adapter.
- Does not support wall mount configuration.
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN68AA70

Description	System Compatibility	Product compatibility	W/S
Meridian Analog Terminal Adapter (ATA), Charcoal (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- Cannot be used in conjunction with Meridian Communications Adapter.
- Does not support wall mount configuration.
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.

Status
✓➤ S

NTMN71AA66

Description	System Compatibility	Product compatibility	W/S
Meridian Accessory Connection Module (ACM), Platinum (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- One (1) ACM supports multiple accessory cartridges per set.
- Requires Wall Transformer (M3900 Series).
- Field installable by a qualified technician.

Status
✓➤ S

NTMN71AA70

Description	System Compatibility	Product compatibility	W/S
Meridian Accessory Connection Module (ACM), Charcoal (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- One (1) ACM supports multiple accessory cartridges per set.
- Requires Wall Transofrmer (M3900 Series).
- Field installable by qualified technician.

Status
➤ S

NTMN80AA

Description	System Compatibility	Product compatibility	W/S
Wall Transformer (M3900 Series)		M3902; M3903; M3904; M3905	W1

Notes:
- Required for use with ATA or MCA, ordered separately.
- Do not use with M2000 series.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTMN82AA66

Description	System Compatibility	Product compatibility	W/S
Meridian Personal Directory PC Utility, Platinum (M3900 Series)		M3904; M3905	W1

Notes:
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.
- Does not support Wall Mount configuration.

Status
➤ S

NTMN82AA70

Description	System Compatibility	Product compatibility	W/S
Meridian Personal Directory PC Utility, Charcoal (M3900 Series)		M3904; M3905	W1

Notes:
- Requires Wall Transformer (M3900 Series).
- Requires Accessory Connection Module.
- Does not support Wall Mount configuration.

Status
S

NTMW01AA

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact System Core Card	11C COMPACT		W1

Status
§ ➤ S

NTMW02AB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Compact Option 68K Memory Card	11C COMPACT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTMW03AA

Description	System Compatibility	Product compatibility	W/S
4-Port DSP Daughter Card	11C COMPACT		W1

Status
S

NTMW04AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 1.5MB DTI/PRI Card	11C COMPACT		W1

Status
S

NTMW05AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 24 Port Digital Line Card	11C COMPACT		W1

Status
S

NTMW06AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 16 Port Analog Line Card	11C COMPACT		W1

Status
S

NTMW07AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 4 Port Trunk/4 Port Line Card	11C COMPACT		W1

Status
† ➤ S

NTMW0802

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Cabinet Fan Assembly	11C COMPACT		W2

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTMW11AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact AC Power Supply	11C COMPACT		W1

Status
§ ➤ S

NTMW14AA

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Expansion Cabinet Package	11C COMPACT		W1

Notes:

- All peripheral equipment line cards should be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	1	NTMW08AA	Option 11C Compact Cabinet Assembly
1	NTAK1118	Modem Cable (DB9 to DB25)	1	NTMW10AA	Option 11C Compact - 10m Fiber Receiver Card
1	NTAK98AA	Power Supply Cable	1	NTMW11AB	Option 11C Compact AC Power Supply
1	NTDK22AA	30 Ft Fiber Daughterboard - Multi Mode	1	NTMW23AA	Option 11C Compact Blank Mail Faceplate

Status
➤ S

NTMW14BA

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Hospitality 10-slot Expansion Cabinet Package			W0

Notes:

- NTMW14BA is an Option 11C Compact Hospitality 10-slot cabinet.

Qty	Order code	Description	Qty	Order code	Description
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	1	NTMW10AA	Option 11C Compact - 10m Fiber Receiver Card
1	NTAK1118	Modem Cable (DB9 to DB25)	1	NTMW11AB	Option 11C Compact AC Power Supply
1	NTAK98AA	Power Supply Cable	1	NTMW35AA	Option 11C Compact Hospitality 10-slot cabinet
1	NTDK22AA	30 Ft Fiber Daughterboard - Multi Mode			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTMW16AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 11 Compact Option Port Expansion (Ports 5 & 6)	11C COMPACT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NTMW03AA	4-Port DSP Daughter Card	1	P0857808	Option 11C Compact MM11 Keycode

Status
§ ➤ S

NTMW16AB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 12 Compact Option Port Expansion (Ports 5 & 6)	11C COMPACT	Meridian Mail Compact Option	W1

Qty	Order code	Description	Qty	Order code	Description
1	NTMW03AA	4-Port DSP Daughter Card	1	P0878733	Meridian Mail Release 12 Keycode

Status
§ ➤ S

NTMW16BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 5 & 6)	11C COMPACT	Meridian Mail Compact Option R13	W1/ S1

Notes:

- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW03AA	4-Port DSP Daughter Card	1	P0906932	Meridian Mail Release 13 Keycode

Status
§ ➤ S

NTMW17AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 11 Compact Option Port Expansion (Ports 7&8)	11C COMPACT		W0/ S1

Qty	Order code	Description	Qty	Order code	Description
1	P0857808	Option 11C Compact MM11 Keycode			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTMW17AB

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 12 Compact Option Port Expansion (Ports 7 & 8)	11C COMPACT	Meridian Mail Compact Option	W1

Qty	Order code	Description	Qty	Order code	Description
1	P0878733	Meridian Mail Release 12 Keycode			

Status
§ ➤ S

NTMW17BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 7 & 8)	11C COMPACT	Meridian Mail Compact Option R13	W1/ S1

Notes:

- The Option 11C Compact Site must be provided if ordering this package for addition to an existing Option 11C Compact system.

Qty	Order code	Description	Qty	Order code	Description
1	P0906932	Meridian Mail Release 13 Keycode			

Status
➤ S

NTMW30AD

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Release 2.0 Programmed Software Daughterboard			W0/ S1

Notes:

- The Option 11C Compact Site ID must be provided if ordering this package for addition to an existing Option 11C Compact system.

Status
➤ S

NTMW30BA

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Software Delivery Card (PCMCIA) Release 1.00	11C COMPACT		W1/ S1

Notes:

- To be used for software upgrades.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTMW37AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 1.5MB DTI/PRI Cable	11C COMPACT		W1

Status
§ ➤ S

NTMW38AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 1.5MB DTI/PRI Package	11C COMPACT		W1

Qty	Order code	Description	Qty	Order code	Description
1	NTMW04AA	Mini IPE 1 5MB DTI/PRI Card	1	P0872788	Mini IPE 1 5 MB DTI/PRI Guide
1	NTMW37AA	Mini IPE 1 5MB DTI/PRI Cable			

Status
➤ Δ S

NTMW43BA

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Customer Documentation Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTMW42CA	Option 11C Compact Documentation Library (CDROM)	1	P0890123	Option 11C Compact Planning and Installation Guide
1	P0872785	Option 11C Compact Set Based Administration	1	P0890125	Multi-Line CAP User Guide
1	P0890121	Option 11C Compact Software Input-Output Guide			

Status
➤ S

NTMW44AA

Description	System Compatibility	Product compatibility	W/S
Mini IPE 4 Port Trunk Card	11C COMPACT		W1

Status
➤ S

NTND11BA

Description	System Compatibility	Product compatibility	W/S
CP to CP Cable (6 Ft.)	61C; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND13BC

Description	System Compatibility	Product compatibility	W/S
IOP to IOP SCSI Cable (6 Ft.)	61C; 81		W1

Status
➤ S

NTND14BB

Description	System Compatibility	Product compatibility	W/S
CNI to 3PE Cable (10 Ft.)	61C; 81		W1

Status
➤ S

NTND14BC

Description	System Compatibility	Product compatibility	W/S
CNI to 3PE Cable (12 Ft.)	61C; 81		W1

Status
➤ S

NTND14BD

Description	System Compatibility	Product compatibility	W/S
CNI to 3PE Cable (12 Ft.)	81		W1

Status
➤ S

NTND14BE

Description	System Compatibility	Product compatibility	W/S
CNI to 3PE Cable (25 Ft.)	81		W1

Status
➤ S

NTND14BG

Description	System Compatibility	Product compatibility	W/S
CNI-3 to 3PE (35 Ft.)	81; 81C		W0

✓ Revision from Last Issue	§ New system sale only	>> Available until stock depleted
★ New product introduction	† Additions & maintenance	➤ See reference book
⊗ Controlled release	# Manufacture discontinued	Δ Distr butor discount category only
S Santa Clara	N Nashville	B Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND14BX

Description	System Compatibility	Product compatibility	W/S
CNI-3 to 3PE Cable (50 Ft.)	81; 81C		W0

Status
➤ S

NTND20AA

Description	System Compatibility	Product compatibility	W/S
Alarm Terminator	RT		W1

Notes:
- Required if the QMM38 is being removed from the RT system as a result of the system being upgraded to Release 15 or later software.

Status
➤ S

NTND26AA

Description	System Compatibility	Product compatibility	W/S
MSDL DCHI Interface Cable (6 Ft.)	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W0

Status
➤ S

NTND26AB

Description	System Compatibility	Product compatibility	W/S
MSDL DCHI Interface Cable (18 Ft.)	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W0

Status
➤ S

NTND26AC

Description	System Compatibility	Product compatibility	W/S
MSDL DCHI Interface Cable (35 Ft.)	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND26AD

Description	System Compatibility	Product compatibility	W/S
MSDL DCHI Interface Cable (50 Ft.)	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W0

Status
➤ S

NTND27AB

Description	System Compatibility	Product compatibility	W/S
MSDL to I/O Panel Cable (6 Ft.)	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		W0

Status
➤ S

NTND28BB

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Clock Cable (16 Ft.)	81		W1

Status
➤ S

NTND28BC

Description	System Compatibility	Product compatibility	W/S
Inter-Cabinet Network Cable (22 Ft.)	81		W1

Status
➤ S

NTND29AA

Description	System Compatibility	Product compatibility	W/S
CPU Interface Cable (6 Ft.)	XN; XT (QCA55)		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND30AA

Description	System Compatibility	Product compatibility	W/S
Junctor to I/O Housing Cable (6 Ft.)	XN; XT (QCA55)		W1

Status
➤ S

NTND33CC

Description	System Compatibility	Product compatibility	W/S
Core-Cabinet Upgrade Cable Kit, Groups 1-4	81; 81C		W1

Notes:
- Contains 22 ft. network inter-cabinet cable assembly.

Status
➤ S

NTND33DA

Description	System Compatibility	Product compatibility	W/S
Option 81C Core Cabinet Cable Kit, Group 0	81C		W1

Notes:
- This cable kit is used for Option 81C upgrades (U9651, U9653, NTHU21AC, NTHU21DC, NTHU29AC, and NTHU29DC) to cable network group 0. This cable kit is not applicable to Option 81 systems. The NTND33BC (Core-Cabinet Cable Kit, Group 0) should be used for cabling network group 0 for Option 81 systems.
- Contains 16 ft. network expansion inter-cabinet cable assembly.

Status
➤ S

NTND36AA

Description	System Compatibility	Product compatibility	W/S
Meridian Communications Unit	11; 21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Notes:
- The NTND36AA connects to the Meridian SL-1 using an Integrated Service Digital Line Card (ISDLC-QPC578) or to a Digital Line Card (NT8D02).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND82AA

Description	System Compatibility	Product compatibility	W/S
RS232 Null Modem Cable (10 Ft.)		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NTND91AA

Description	System Compatibility	Product compatibility	W/S
RS232 Straight Cable (10 Ft.)		Meridian Mail EC11 R10; Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NTND91AB

Description	System Compatibility	Product compatibility	W/S
RS232 Straight Cable (25 Ft.)		Meridian Mail EC11 R10; Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

NTND93AA

Description	System Compatibility	Product compatibility	W/S
Null Modem Adapter		Meridian Mail EC11 R10	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTND94DA

Description	System Compatibility	Product compatibility	W/S
CNI to I/O Panel Ethernet Cable (20 In.)	81		W1

Status
➤ S

NTND95AA

Description	System Compatibility	Product compatibility	W/S
3PE to I/O Housing Cable (8 Ft.)	81		W1

Status
➤ S

NTNH13AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telecommuter Client Application CD			W1

Notes:

- Twenty four copies of the Meridian IP Telecommuter Application CD are included in the Meridian IP Telecommuter Packages. Individual copies of Client Application CDs should only be ordered as replacements.

Status
➤ S

NTQR01AA

Description	System Compatibility	Product compatibility	W/S
Meridian HomeOffice II Router (NTQR03AA) with M2616			W1

Notes:

- Meridian digital telephone M2616 (gray, with display) and NTQR03AA (including: Meridian HomeOffice II Router, NTDR16AD CD-ROM, NTDR15AC User Guide, NTDJ66AA ISDN Cable, NTDJ67AA 10BaseT Ethernet Cable - crossed, NTDJ65AA Serial 9 pin Administration Cable, Online Call Keycap, NTDR52AA Power Supply, A0292928 North America Power Cord and P0886052 Release Notes).

Qty	Order code	Description	Qty	Order code	Description
1	NT9K16AC93	Meridian M2616 Performance-Plus Telephone with Display, Gray	1	NTQR03AA	Meridian HomeOffice II Router C/W CD-ROM, User Guide; ISDN, Ethernet & Admin Cables; Online Call Keycap & Power Supply

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTQR01BA

Description	System Compatibility	Product compatibility	W/S
Meridian HomeOffice II Router ACD with M2216 Digital Set			W1

Notes:

- Meridian digital telephone M2216 (gray, with display) and NTQR03AA (including: Meridian HomeOffice II Router, NTDR16AD CD-ROM, NTDR15AC User Guide, NTDJ66AA ISDN Cable, NTDJ67AA 10BaseT Ethernet Cable - crossed, NTDJ65AA Serial 9 pin Administration Cable, Online Call Keycap, NTDR52AA Power Supply, A0292928 North America Power Cord and P0886052 Release Notes).

Qty	Order code	Description	Qty	Order code	Description
1	NT9K18AC93	Meridian M2216ACD Telephone, Grey	1	NTQR03AA	Meridian HomeOffice II Router C/W CD-ROM, User Guide; ISDN, Ethernet & Admin Cables; Online Call Keycap & Power Supply

Status
➤ S

NTQR02AA

Description	System Compatibility	Product compatibility	W/S
Meridian HomeOffice II Line Card C/W Management/Interconnect Cable and Installer Notes			W1

Notes:

- Meridian HomeOffice II Card C/W NTDR50AB Multi I/O (Management/Interconnect) Cable, P0879714 Install notes with basic information on installation. For detailed provisioning please look into NTDR07AC Line Card Configuration Guide.

Status
✓ ➤ S

NTQR05AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 8-User VoIP Package - 16 RLC			W0

Notes:

- Provides a 10BaseT Ethernet interface for VoIP and a V.35 interface. Does not support local calling or IP-VoiceFlex without adding BRI module.
- Supports up to 8 simultaneous network access ports between sites which can grow in 8 port increments (up to 32 total) with the Remote Office 9150 8-user Expansion Package (NTQR10AA).

Qty	Order code	Description	Qty	Order code	Description
1	NTDR68AA	Reach Line Card - 16 Port	1	NTDR69AA	Remote Office 9150 Unit

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTQR06AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 8-User Starter Package - 16 RLC			W0

Notes:

- Provides a 10BaseT Ethernet interface for VoIP, a V.35 interface, and one ISDN BRI line interface for local calling and IP-VoiceFlex.
- Supports up to 8 simultaneous network access ports between sites which can grow in 8 port increments (up to 16 total based on 16 port RLC) with the Remote Office 9150 8-user Expansion Package (NTQR10AA).
- The BRI lines can grow (to a total of four) in increments of one by adding BRI Interface Modules (NTDR74AA).

Qty	Order code	Description	Qty	Order code	Description
1	NTDR68AA	Reach Line Card - 16 Port	1	NTDR74AA	BRI Module (U Interface)
1	NTDR69AA	Remote Office 9150 Unit			

Status
✓ ➤ S

NTQR07AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 8-User Starter Package - 32 RLC Option 51-81			W0

Notes:

- Provides a 10BaseT Ethernet interface for VoIP, a V.35 interface, and one ISDN BRI line interface for local calling and IP-VoiceFlex.
- Supports up to 8 simultaneous network access ports between sites which can grow in 8 port increments (up to 32 total) with the Remote Office 9150 8-user Expansion Package (NTQR10AA).
- The BRI lines can grow (to a total of four) in increments of one by adding BRI Interface Modules (NTDR74AA).

Qty	Order code	Description	Qty	Order code	Description
1	NTDR69AA	Remote Office 9150 Unit	1	NTDR74AA	BRI Module (U Interface)
1	NTDR70AA	Reach Line Card - 32 Port - Option 51-81			

Status
✓ ➤ S

NTQR08AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 8-User Starter Package - 32 RLC Option 11			W0

Notes:

- Provides a 10BaseT Ethernet interface for VoIP, a V.35 interface, and one ISDN BRI line interface for local calling and IP-VoiceFlex.
- Supports up to 8 simultaneous network access ports between sites which can grow in 8 port increments (up to 32 total) with the Remote Office 9150 8-user Expansion Package (NTQR10AA).
- The BRI lines can grow (to a total of four) in increments of one by adding BRI Interface Modules (NTDR74AA).

Qty	Order code	Description	Qty	Order code	Description
1	NTDR69AA	Remote Office 9150 Unit	1	NTDR74AA	BRI Module (U Interface)
1	NTDR71AA	Reach Line Card - 32 Port - Option 11			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTQR09AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 Branch Expansion Package			W0

Notes:

- Provides a 10BaseT Ethernet interface for VoIP, a V.35 interface, and one ISDN BRI line interface for local calling and IP-VoiceFlex.
- Supports up to 8 simultaneous network access ports between sites which can grow in 8 port increments (up to 32 total) with the Remote Office 9150 8-user Expansion Package (NTQR10AA).
- The BRI lines can grow (to a total of four) in increments of one by adding BRI Interface Modules (NTDR74AA).
- This package is used when a new Remote Office 9150 unit is desired at a remote location but an existing Reach Line Card is available in the host PBX. The DSP Application Module is installed on the Reach Line Card to increase the number of simultaneous network access connection ports.

Qty	Order code	Description	Qty	Order code	Description
1	NTDR69AA	Remote Office 9150 Unit	1	NTDR74AA	BRI Module (U Interface)
1	NTDR73AA	DSP Application Module			

Status
✓ ➤ S

NTQR10AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9150 8-User Expansion Package			W0

Notes:

- This package is used to add 8 more additional simultaneous network access ports between the remote and host locations. One DSP Application Module is installed on the Reach Line Card and the other in the Remote Office 9150 unit.

Qty	Order code	Description	Qty	Order code	Description
2	NTDR73AA	DSP Application Module			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTQR11AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9115 4-User Starter Package - 16 RLC			W0

Notes:

- Each Remote Office 9115 unit provides a 10BaseT Ethernet interface for VoIP and an analog line interface for local calling and IP-Voice-Flex.
- The Reach Line Card supports up to 4 simultaneous network access ports to remote sites over an IP network or over the T1/PRI trunks to the public network. Additional network access ports (in increments of 4) are available with each DSP Application Module added to the Reach Line Card.

Qty	Order code	Description	Qty	Order code	Description
1	NTDR68AA	Reach Line Card - 16 Port	4	NTDR88AA	Remote Office 911x North American Power Supply
4	NTDR77AA	Remote Office 9115 base unit			

Status
★ ➤ S

NTQR12AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9115 4-User Expansion Package - 16 RLC			W0

Notes:

- Each Remote Office 9115 unit provides a 10BaseT Ethernet interface for VoIP and an analog line interface for local calling and IP-Voice-Flex.
- The DSP Application Module is installed on an existing Reach Line Card. It supports up to 4 simultaneous Remote Office 911x network access ports to remote sites over an IP network or over the T1/PRI trunks to the public network. Additional network access ports (in increments of 4) are available with each DSP Application Module added to the Reach Line Card.

Qty	Order code	Description	Qty	Order code	Description
1	NTDR73AA	DSP Application Module	4	NTDR88AA	Remote Office 911x North American Power Supply
4	NTDR77AA	Remote Office 9115 base unit			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTQR14AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9110 4-User Starter Package - 16 RLC			W0

Notes:

- Each Remote Office 9110 unit provides a 10BaseT Ethernet interface for VoIP and an analog line interface for local calling and IP-Voice-Flex.
- The Reach Line Card supports up to 4 simultaneous network access ports to remote sites over an IP network or over the T1/PRI trunks to the public network. Additional network access ports (in increments of 4) are available with each DSP Application Module added to the Reach Line Card.

Qty	Order code	Description	Qty	Order code	Description
1	NTDR68AA	Reach Line Card - 16 Port	4	NTDR88AA	Remote Office 911x North American Power Supply
4	NTDR76AA	Remote Office 9110 base unit			

Status
★ ➤ S

NTQR15AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9110 4-User Expansion Package - 16 RLC			W0

Notes:

- Each Remote Office 9110 unit provides a 10BaseT Ethernet interface for VoIP and an analog line interface for local calling and IP-Voice-Flex.
- The DSP Application Module is installed on an existing Reach Line Card. It supports up to 4 simultaneous Remote Office 911x network access ports to remote sites over an IP network or over the T1/PRI trunks to the public network. Additional network access ports (in increments of 4) are available with each DSP Application Module added to the Reach Line Card.

Qty	Order code	Description	Qty	Order code	Description
1	NTDR73AA	DSP Application Module	4	NTDR88AA	Remote Office 911x North American Power Supply
4	NTDR76AA	Remote Office 9110 base unit			

Status
★ ➤ S

NTQR16AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9110 Unit with North American Power Supply			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTDR76AA	Remote Office 9110 base unit	1	NTDR88AA	Remote Office 911x North American Power Supply

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTQR17AA

Description	System Compatibility	Product compatibility	W/S
Remote Office 9115 Unit with North American Power Supply			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTDR77AA	Remote Office 9115 base unit	1	NTDR88AA	Remote Office 911x North American Power Supply

Status
➤ S

NTRB18AA

Description	System Compatibility	Product compatibility	W/S
MGate Card		Meridian Mail EC11 R10,11	W1

Notes:
- Each Mgate supports 16 voice ports. Order additional cards as required.
- Order one NLI cable (NTDK33xx) with each Mgate purchased.

Status
➤ S

NTRB18CA

Description	System Compatibility	Product compatibility	W/S
MGate Card			W1

Notes:
- This MGate Card is used only on the CallPilot Rack Mount Systems.
- Order 1 MGate Card for every 32 Channels on the Rack Mount System.
- The first MGate Card comes in the base system.

Status
➤ B

NTRB21AA

Description	System Compatibility	Product compatibility	W/S
T1 Multipurpose Digital Interface (TMDI)	11C 2111 R24.24		W1

Notes:
- The NTRB21AA is compatible with X11.24B or higher software only.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRB33AA

Description	System Compatibility	Product compatibility	W/S
Fiber Junctor Interface Card (FIJI)	81; 81C		W1

Notes:
- This card supports the fiber network fabric on Option 81 and 81C systems and is applicable only to such systems currently utilizing NTRB33 cards.

Status
✓ ➤ S

NTRB34AA

Description	System Compatibility	Product compatibility	W/S
Core-to-Network Interface Card (CNI-3)	51C; 61; 81; 81C		W1

Notes:
- This card is supported on Option 51C, 61C, 81 and 81C systems.
- Option 61C systems can utilize either CNI-2 port cards (NT6D65AA) or CNI-3 port cards (NTRB33). Each Core/Network Module in Option 61C systems must house CNI cards of the same kind (i.e., either both must be CNI-2 or both must have CNI-3).
- Option 81 and 81C systems will support mixture of CNI-2 and CNI-3 port cards. The same configuration of CNI-2 and/or CNI-3 port cards must be used in both core modules for Option 81 systems or both core/network modules in Option 81C systems (i.e., side 0 and side 1).
- The faceplate port on the CNI-3 port card can only be utilized by Option 81/81C systems with X11 Release 25 and later software.

Status
➤ ⊗ S

NTRC17AA

Description	System Compatibility	Product compatibility	W/S
CP PII Ethernet to Ethernet Cable (8.5 Ft./ 3m)	81C		W1

Notes:
- Provides the connection between two A0786611 CP PII Call Processor Cards when no external Ethernet connections are equipped.

Status
✓ ➤ S

NTRC46AA

Description	System Compatibility	Product compatibility	W/S
Clock to FIJI Cable, (4 Ft.-4.5 Ft.)	81; 81C		W0

Notes:
- This cable supports a connection between clock controller cards and FIJI cards (NTRB33).
- Systems with Intergroup Switch cards (QPC412) or Dual Intergroup Switch cards (NT5D30) should order NT8D74 Clock to Junctor cables of appropriate length.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRC46BA

Description	System Compatibility	Product compatibility	W/S
Clock to FIJI Cable, (5.5 Ft.-8 Ft.)	81; 81C		W0

Notes:
- This cable supports a connection between clock controller cards and FIJI cards (NTRB33).
- Systems with Intergroup Switch cards (QPC412) or Dual Intergroup Switch cards (NT5D30) should order NT8D74 Clock to Junctor cables of appropriate length.

Status
➤ S

NTRC46CA

Description	System Compatibility	Product compatibility	W/S
Clock to FIJI Cable, (22 Ft.)	81; 81C		W1

Notes:
- This cable supports a connection between clock controller cards and FIJI cards (NTRB33).
- Systems with Intergroup Switch cards (QPC412) or Dual Intergroup Switch cards (NT5D30) should order NT8D74 Clock to Junctor cables of appropriate length.

Status
✓ ➤ S

NTRC47AA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Synch Cable	81; 81C		W1

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.

Status
✓ S

NTRC48AA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (6 Ft./2M)	81; 81C		W0

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRC48BA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (10 Ft./3M)	81; 81C		W0

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ ➤ S

NTRC48CA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (12 Ft./3.6M)	81; 81C		W0

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ S

NTRC48DA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (14 Ft./4.2M)	81; 81C		W0

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ ➤ S

NTRC48EA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (19 Ft./6M)	81; 81C		W0

Notes:
- This cable supports connection between FIJI cards (NTRB33) within a network group and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRC48FA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (26 Ft./8M)	81; 81C		W0

Notes:
- This cable supports connection of FIJI cards (NTRB33) between network groups and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ ➤ S

NTRC48GA

Description	System Compatibility	Product compatibility	W/S
FIJI to FIJI Fiber Ring Cable, (32 Ft./10M)	81; 81C		W1

Notes:
- This cable supports connection of FIJI cards (NTRB33) between network groups and is applicable to 81/81C systems with the fiber network fabric only.
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ ➤ S

NTRC48HA

Description	System Compatibility	Product compatibility	W/S
FIJI Fiber Ring Cable, (50 Ft.)			W0

Notes:
- This cable supports connection of FIJI cards (NTRB33) between network groups and is applicable to Option 81/81C systems with the fiber network fabric only
- Cabling is used from FIJI to FIJI within the same side (either side 0 or side 1) between network groups.

Status
✓ ➤ S

NTRC49AA

Description	System Compatibility	Product compatibility	W/S
Fiber Network Clock-Clock Synch Cable, (6 Ft.)			W0

Notes:
- This cable is applicable to systems utilizing the fiber network fabric based on NTRB33 (FIJI) cards only.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRC49BA

Description	System Compatibility	Product compatibility	W/S
Fiber Network Clock-Clock Synch Cable, (20 Ft.)			W0

Notes:
- This cable is for systems utilizing the fiber network fabric based on NTRB33 (FIJI) cards only.

Status
S

NTRD25AA

Description	System Compatibility	Product compatibility	W/S
Pedestal Assembly AC			W1

Notes:
- This assembly consists of one NT8D27BB (AC Pedestal), one NT8D52AB (AC Blower Module) and one NT8D53CA (AC Power Distribution Unit).
- Repair prices for components within this assembly are listed in the merchandise Price List section by engineering code.

Status
✓ S

NTRD25BA

Description	System Compatibility	Product compatibility	W/S
Pedestal Assembly DC			W1

Notes:
- This assembly consists of one NT7D09CA (DC Pedestal), one NT8D52DD (DC Blower Module) and one NT4N50AA (DC Power Distribution Unit).
- Repair prices for components within this assembly are listed in the merchandise Price List section by engineering code.

Status
➤ S

NTRE39AA

Description	System Compatibility	Product compatibility	W/S
Optical Cable Management Card (OCMC)	81; 81C		W1

Notes:
- This card supports slack management for NTRC48 Fiber Ring Cables.
- Quantity of two (2) per each network group (groups 1 through 7 only) should be ordered if not already provisioned.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTRE40AA

Description	System Compatibility	Product compatibility	W/S
Dual Ethernet Adapter RJ45 for I/O Panel	81C 3311 R25		W1

Status
★ ⊗ Δ S

NTRG08AD

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 IPE (200i) Base Documentation Package			W0

Qty	Order code	Description	
1	NTJR48AA	CallPilot Telset Guide Package (Quantity 10), English	
1	NTRG15AC	CallPilot 1 07 Installation and Configuration Guide Package	
	Each Package Includes:		
	1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up
	1	P0905786	CallPilot 1 07 200i Installation and Configuration Server Hardware Guide
	1	P0905797	CallPilot 1 07 Client Software Installation
	1	P0912732	200i Server Maintenance & Diagnostics Guide
	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905789	CallPilot 1 07 Planning and Engineering Guide	
1	P0905790	CallPilot 1 07 Getting Started Guide	
1	P0905791	CallPilot 1 07 Monitoring and Security for Administrators	
1	P0905796	CallPilot 1 07 Administrators Guide	
1	P0905798	CallPilot 1 07 Reporter Guide	
1	P0905799	CallPilot 1 07 Applications Builder Guide	
1	P0905800	CallPilot 1 07 Meridian Mail to CallPilot Migration Guide	
1	P0905810	CallPilot 1 07 Desktop Messaging Software Installation and Maintenance Guide	

Status
★ ⊗ S

NTRG09AD

Description	System Compatibility	Product compatibility	W/S
702t Base Documentation Package, English			W0

Qty	Order code	Description	
1	NTJR48AA	CallPilot Telset Guide Package (Quantity 10), English	
1	NTRG16AC	CallPilot 1 07 702t Installation and Configuration Guide Package	
	Each Package Includes:		
	1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up
	1	P0905787	CallPilot 702t Installation and Configuration Server Hardware - Part 2

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0905797	CallPilot 1 07 Client Software Installation
	1	P0912733	702t Server Maintenance & Diagnostics Guide - Part 5
	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905789	CallPilot 1 07 Planning and Engineering Guide	
1	P0905790	CallPilot 1 07 Getting Started Guide	
1	P0905791	CallPilot 1 07 Monitoring and Security for Administrators	
1	P0905796	CallPilot 1 07 Administrators Guide	
1	P0905798	CallPilot 1 07 Reporter Guide	
1	P0905799	CallPilot 1 07 Applications Builder Guide	
1	P0905800	CallPilot 1 07 Meridian Mail to CallPilot Migration Guide	
1	P0905810	CallPilot 1 07 Desktop Messaging Software Installation and Maintenance Guide	

Status
★ ⊗ S

NTRG10AD

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 1001rp Base Documentation Package, English			W0

Qty	Order code	Description	
1	NTJR48AA	CallPilot Telset Guide Package (Quantity 10), English	
1	NTRG17AC	CallPilot 1 07 1001rp Installation and Configuration Guide	
	Each Package Includes:		
	1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up
	1	P0905788	CallPilot 1001rp Installation and Configuration Server Hardware
	1	P0905797	CallPilot 1 07 Client Software Installation
	1	P0912734	1001rp Server Maintenance & Diagnostic Guide
	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905789	CallPilot 1 07 Planning and Engineering Guide	
1	P0905790	CallPilot 1 07 Getting Started Guide	
1	P0905791	CallPilot 1 07 Monitoring and Security for Administrators	
1	P0905796	CallPilot 1 07 Administrators Guide	
1	P0905798	CallPilot 1 07 Reporter Guide	
1	P0905799	CallPilot 1 07 Applications Builder Guide	
1	P0905800	CallPilot 1 07 Meridian Mail to CallPilot Migration Guide	
1	P0905810	CallPilot 1 07 Desktop Messaging Software Installation and Maintenance Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ Δ S

NTRG11AB

Description	System Compatibility	Product compatibility	W/S
CallPilot Basic Administration Documentation Package - English			W0

Notes:

- One (1) each of this package is included in the IPE, Tower, and Rack Mount English Systems.

Qty	Order code	Description	
1	NTRG13AA	CallPilot Telset Guide Package	
1	NTRG19AB	CallPilot Documentation CD ROM	
1	NTRG20AA	CallPilot Installation Worksheet Package	
	Each Package Includes:		
	1	P0903076	Installation Checklist
	1	P0903077	Upgrade Checklist
	1	P0903078	Network Planning Worksheet for IPE Systems
	1	P0903079	Network Planning Worksheet for Tower and Rack Systems
1	P0886124	CallPilot Planning and Engineering Guide	
1	P0886126	CallPilot Basic Administration Guide	
1	P0903073	CallPilot Software Installation Guide	
1	P0903074	CallPilot Maintenance and Diagnostic Guide	

Status
✓ Δ S

NTRG11AC

Description	System Compatibility	Product compatibility	W/S
CallPilot Basic Administration Documentation Package - English			W0

Notes:

- One (1) each of this package is included in the IPE, Tower, and Rack Mount English Systems.

Qty	Order code	Description	
1	NTRG13AB	CallPilot Telset Guides, English, Quantity 15	
	Each Package Includes:		
	15	P0673999	Voice Messaging Template (Digital Sets) (100/PK)
	15	P0707593	Meridian Modular Telephone Template (100/PK)
1	NTRG19AD	CallPilot 1 06 Documentation CD-ROM	
	Each Package Includes:		
	1	A0631053	Jewel Box Case
	1	A0631056	CD Tray for Single CD, Black
	1	NTRG1904	CallPillot 1 06 Diskette
	1	P0907833	CallPilot 1 06 CD ROM Cover/Disk Art
	1	P0907834	CallPilot 1 06 CD ROM Back Insert
1	NTRG20AA	CallPilot Installation Worksheet Package	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0903076	Installation Checklist
	1	P0903077	Upgrade Checklist
	1	P0903078	Network Planning Worksheet for IPE Systems
	1	P0903079	Network Planning Worksheet for Tower and Rack Systems
1	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25	
	Each Package Includes:		
	25	P0905784	Desktop Messaging Quick Reference Guide
1	P0886124	CallPilot Planning and Engineering Guide	
1	P0886126	CallPilot Basic Administration Guide	
1	P0886130	CallPilot Advanced Administration Guide - Volume 1	
1	P0886132	CallPilot Advanced Administration Guide - Volume 2	
1	P0903073	CallPilot Software Installation Guide	
1	P0903074	CallPilot Maintenance and Diagnostic Guide	
1	P0907827	CallPilot What's New for Release 1 06	

Status
➤ Δ S

NTRG12AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Advanced Administration Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886130	CallPilot Advanced Administration Guide - Volume 1	1	P0886135	CallPilot Applications Builder Guide
1	P0886132	CallPilot Advanced Administration Guide - Volume 2	1	P0886138	Meridian Mail to Nortel CallPilot Migration Guide
1	P0886133	CallPilot Reporter Guide	1	P0903074	CallPilot Maintenance and Diagnostic Guide

Status
➤ Δ S

NTRG13AB

Description	System Compatibility	Product compatibility	W/S
CallPilot Telset Guides, English, Quantity 15			W0

Notes:

- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Qty	Order code	Description	Qty	Order code	Description
15	P0673999	Voice Messaging Template (Digital Sets) (100/PK)	15	P0707593	Meridian Modular Telephone Template (100/PK)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTRG13BB

Description	System Compatibility	Product compatibility	W/S
CallPilot Telset Guides, French, Quantity 15			W0

Qty	Order code	Description	Qty	Order code	Description
15	P0905813	Multimedia Messaging User Guide, French	15	P0909788	Small Keypad Template - French
15	P0905815	Multimedia Messaging Quick Reference Card - French	15	P0909948	Speech Activated Messaging User Guide - French
15	P0909787	Large Keypad Template - French			

Status
➤ Δ S

NTRG14AA

Description	System Compatibility	Product compatibility	W/S
CallPilot AMIS Networking Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886146	CallPilot AMIS Installation and Administration Guide

Status
✓ ➤ Δ S

NTRG14AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Networking Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886147	CallPilot Enterprise Networking Installation and Administration Guide
1	P0886145	CallPilot NMS Installation and Administration Guide	1	P0886148	CallPilot Integrated AMIS Installation and Administration Guide
1	P0886146	CallPilot AMIS Installation and Administration Guide	1	P0886149	CallPilot VPIM Networking Package

Status
➤ Δ S

NTRG15AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Enterprise Networking Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886147	CallPilot Enterprise Networking Installation and Administration Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

NTRG15AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Installation and Configuration Guide Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up	1	P0912732	200i Server Maintenance & Diagnostics Guide
1	P0905786	CallPilot 1 07 200i Installation and Configuration Server Hardware Guide	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905797	CallPilot 1 07 Client Software Installation			

Status
➤ Δ S

NTRG16AA

Description	System Compatibility	Product compatibility	W/S
CallPilot VPIM Networking Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886149	CallPilot VPIM Networking Package

Status
★ ➤ Δ S

NTRG16AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 702t Installation and Configuration Guide Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up	1	P0912733	702t Server Maintenance & Diagnostics Guide - Part 5
1	P0905787	CallPilot 702t Installation and Configuration Server Hardware - Part 2	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905797	CallPilot 1 07 Client Software Installation			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTRG17AA

Description	System Compatibility	Product compatibility	W/S
CallPilot NMS Networking Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886145	CallPilot NMS Installation and Administration Guide

Status
★ ➤ Δ S

NTRG17AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 1001rp Installation and Configuration Guide			W0

Notes:

- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Qty	Order code	Description	Qty	Order code	Description
1	P0905783	CallPilot 1 07 Installation and configuration Switch Set Up	1	P0912734	1001rp Server Maintenance & Diagnostic Guide
1	P0905788	CallPilot 1001rp Installation and Configuration Server Hardware	1	P0914300	Installation Flowchart and Worksheets - Part 1 (English)
1	P0905797	CallPilot 1 07 Client Software Installation			

Status
➤ Δ S

NTRG18AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Integrated AMIS Networking Documentation Package - English			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0886144	CallPilot Network Planning Guide	1	P0886148	CallPilot Integrated AMIS Installation and Administration Guide

Status
➤ Δ S

NTRG19AB

Description	System Compatibility	Product compatibility	W/S
CallPilot Documentation CD ROM			W0

Notes:

- One (1) copy of the CallPilot Documentation CD ROM is included in the IPE Base System, Tower Base System, and Rack Base System.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

NTRG19AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Documentation CD-ROM			W0

Notes:

- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
➤ Δ S

NTRG19AD

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.06 Documentation CD-ROM			W0

Qty	Order code	Description	Qty	Order code	Description
1	A0631053	Jewel Box Case	1	P0907833	CallPilot 1 06 CD ROM Cover/Disk Art
1	A0631056	CD Tray for Single CD, Black	1	P0907834	CallPilot 1 06 CD ROM Back Insert
1	NTRG1904	CallPillot 1 06 Diskette			

Status
➤ S

NTRG20AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Installation Worksheet Package			W0

Notes:

- This package comes with the base system.

Qty	Order code	Description	Qty	Order code	Description
1	P0903076	Installation Checklist	1	P0903078	Network Planning Worksheet for IPE Systems
1	P0903077	Upgrade Checklist	1	P0903079	Network Planning Worksheet for Tower and Rack Systems

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTRG22AA

Description	System Compatibility	Product compatibility	W/S
Desktop Messaging Quick Reference Guide, Quantity 25			W0

Qty	Order code	Description	Qty	Order code	Description
25	P0905784	Desktop Messaging Quick Reference Guide			

Status
★ ➤ Δ S

NTRG22AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Desktop Messaging Quick Reference Guide, Quantity 10			W0

Qty	Order code	Description	Qty	Order code	Description
10	P0907835	Desktop Quick Reference Guide 1 07			

Status
➤ Δ S

NTRG22BA

Description	System Compatibility	Product compatibility	W/S
Desktop Messaging Quick Reference Guide, Quantity 100			W0

Qty	Order code	Description	Qty	Order code	Description
100	P0905784	Desktop Messaging Quick Reference Guide			

Status
➤ Δ S

NTRG22CB

Description	System Compatibility	Product compatibility	W/S
Desktop Messaging Quick Reference Guide French - Package of 25			W0

Qty	Order code	Description	Qty	Order code	Description
25	P0909938	Desktop Quick Reference Guide - French			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTRG22DB

Description	System Compatibility	Product compatibility	W/S
Desktop Messaging Quick Reference Guide - French - Package of 100			W0

Qty	Order code	Description	Qty	Order code	Description
100	P0909938	Desktop Quick Reference Guide - French			

Status
★ ➤ Δ S

NTRG22EC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Desktop Quick Reference Guide Package, French			W0

Qty	Order code	Description	Qty	Order code	Description
10	P0912909	CallPilot Desktop Quick Reference Guide French			

Status
✓ ➤ S

NTRH01AA

Description	System Compatibility	Product compatibility	W/S
CallPilot MPC-8			W1/ S1

Notes:

- The CallPilot IPE System comes with 8 MPU slots. Order 1 MPC-8 for every 8 MPU slots required beyond the first 8.
- The CallPilot Tower and Rack Systems come with 16 MPU slots. Order 1 MPC-8 for every 8 MPU slots required between 9 and 48 MPUs. An MPB-16 is added for MPU Slots 49 - 64. Then order 1 MPC-8 for every 8 MPU slots for every 8 MPU slots required between 65 and 96 MPUs.

Status
✓ S

NTRH09AA

Description	System Compatibility	Product compatibility	W/S
Breakout Panel Assembly			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH0910	Break Interconnect Cable (6 Ft)			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTRH1405

Description	System Compatibility	Product compatibility	W/S
CallPilot Internal Ethernet Cabling (IPE System)			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ S

NTRH1406

Description	System Compatibility	Product compatibility	W/S
CallPilot Token Ring Cabling (IPE System)			W0

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ ➤ S

NTRH1407

Description	System Compatibility	Product compatibility	W/S
CallPilot Intermediate SCSI Cable			W1

Notes:
- For use with the Option 11C and CallPilot.

Status
✓ ➤ S

NTRH1408

Description	System Compatibility	Product compatibility	W/S
CallPilot Intermediate SCSI Cable			W1

Notes:
- Used with the Options 51C - 81C and CallPilot.

Status
✓ ➤ S

NTRH1409

Description	System Compatibility	Product compatibility	W/S
CallPilot Intermediate SCSI Cable			W1

Notes:
- Used with Options 51C - 81C and CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTRH16BA

Description	System Compatibility	Product compatibility	W/S
Hard Drive Data Cable			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
S

NTRH2010

Description	System Compatibility	Product compatibility	W/S
CallPilot MGate Cable - 20 Ft.			W0

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.
- This cable is used with the NTRH20AA vintage of the MPB-16

Status
S

NTRH2011

Description	System Compatibility	Product compatibility	W/S
CallPilot MPB-16 Cable			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ S

NTRH8027

Description	System Compatibility	Product compatibility	W/S
Windows NT 4.0 OS Recovery CD			W0/ S1

Notes:
- This CD is included in the base CallPilot system package.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTRH8101

Description	System Compatibility	Product compatibility	W/S
Application Server Master Driver CD Bootable			S1

Notes:
- This CD is included in the base CallPilot system package.

Status
➤ S

NTRH9002

Description	System Compatibility	Product compatibility	W/S
2GB SCSI SCA Disk Drive	11C COMPACT	Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

NTRH9003

Description	System Compatibility	Product compatibility	W/S
4GB SCSI Hot Swap Disk Drive		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).
- This part used by the Call Pilot Rack System.

Status
✓ ➤ S

NTRH9004

Description	System Compatibility	Product compatibility	W/S
3.5" EIDE Floppy Drive		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
➤ S

NTRH9005

Description	System Compatibility	Product compatibility	W/S
SCSI CD-ROM Drive		Meridian MAX R7,8	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTRH9006

Description	System Compatibility	Product compatibility	W/S
SCSI 3.5 DAT Tape Drive		Meridian MAX R7,8	W1

Status
✓ ➤ S

NTRH9007

Description	System Compatibility	Product compatibility	W/S
SCSI RAID Controller		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).
- This part is used by the Call Pilot Tower and Rack Systems.

Status
➤ S

NTRH9009

Description	System Compatibility	Product compatibility	W/S
PCI Ethernet Adapter	11C X11 R22; 51C X11 R22; 61C X11 R22; 81 X11 R22; 81C X11 R22	Meridian MAX R7,8	W1

Notes:
- A dedicated network interface card is required to support the customer's LAN. Either NTRH9009, PCI Ethernet Adapter or NTRH9010, Token Ring Adapter must be used in conjunction with the following SYMPOSIUM Call Center Servers: NT9F28AA 701t Advanced and NT9F28BA 701t Advanced with RAID to support connectivity for the customer's LAN.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ ➤ S

NTRH9010

Description	System Compatibility	Product compatibility	W/S
PCI Token Ring Network Card	11C X11 R22; 51C X11 R22; 61C X11 R22; 81 X11 R22; 81C X11 R22	Meridian MAX R7,8	W1

Notes:
- A dedicated network interface card is required to support the customer's LAN. Either NTRH9009, PCI Ethernet Adapter or NTRH9010, Token Ring Adapter must be used in conjunction with the following SYMPOSIUM Call Center Servers: NT9F28AA 701t Advanced and NT9F28BA 701t Advanced with RAID to support connectivity for the customer's LAN.
- Contact NRDC for warranty repair/replacement (except DOA).
- When 1.07 becomes available in late November, CallPilot will be able to connect to non-Meridian 1 PBXs. When connecting to a non-Meridian 1 PBX, one 10/100base T Ethernet NIC is available for connection to the customers LAN and does not need to be ordered seperately. If the customer's LAN is Token Ring, the Token Ring Adapter must still be ordered.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTRH9011

Description	System Compatibility	Product compatibility	W/S
14" SVGA Color Monitor		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).
- This monitor used with the CallPilot IPE, Tower and Rack systems.
- NTRH9011 included in the NTUB56AA CallPilot 14" Monitor Package for the IPE and Tower systems.
- Order 1 of this part number for the CallPilot Rack system in conjunction with the NTRH9048 Keyboard with built in Mouse.

Status
➤ S

NTRH9012

Description	System Compatibility	Product compatibility	W/S
17" SVGA Color Monitor		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ † ➤ S

NTRH9013

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - Keyboard		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).
- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software or OPEN IVR 4.0 software.

Status
✓ ➤ S

NTRH9014

Description	System Compatibility	Product compatibility	W/S
Three Button Mouse		Meridian MAX R7,8	W0

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ ➤ S

NTRH9016

Description	System Compatibility	Product compatibility	W/S
External Modem 33.6		Meridian MAX R7,8	W1

Notes:
- A modem cable must be ordered separately (reference A0601464) for this modem.
- Contact NRDC for warranty repair/replacement (except DOA).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTRH9017

Description	System Compatibility	Product compatibility	W/S
10 Base T Hub		Meridian MAX R7,8	W1

Notes:
- Power cord must be ordered separately (reference A0645811) for this hub.

Status
➤ S

NTRH9027

Description	System Compatibility	Product compatibility	W/S
ACCESS Link Kit for Meridian Mail 8, 9, 10, 11		Meridian MAX R7,8	W1

Notes:
- This ACCESS Cable Kit is required for connectivity to Meridian Mail 8, 9, 10 and 11. It contains the cables and components that will ensure the connectivity between the SYMPOSIUM Call Center server and the data ports of the Meridian Mail systems.
- To enable Meridian Mail with Meridian 1 Option 11C, 51C, 61C, 81, and 81C, this ACCESS Cable Kit and SW7030 ACCESS Enable Software are required.

Status
➤ S

NTRH9029

Description	System Compatibility	Product compatibility	W/S
2GB Ultra SCSI Disk Drive	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ S

NTRH9030

Description	System Compatibility	Product compatibility	W/S
4GB 16Bit Ultra SCSI Disk Drive	11C; 51C; 61C; 81; 81C		W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTRH9031

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server 701t Platform Server System (32Mb)	11C; 51C; 61C; 81; 81C		W1

Notes:
- NTRH9031 includes a chassis, motherboard, 32MB RAM, floppy drive assembly, CPU, CD-ROM drive and a power supply.
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ ➤ S

NTRH9032

Description	System Compatibility	Product compatibility	W/S
700 Series DC Power Converter		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ ➤ S

NTRH9034

Description	System Compatibility	Product compatibility	W/S
Backup Tape Drive		Meridian MAX R7,8	W1

Notes:
- Contact NRDC for warranty repair/replacement (except DOA).

Status
✓ ➤ S

NTRH9035

Description	System Compatibility	Product compatibility	W/S
IDE CD-ROM Drive	11C; 51C; 61C; 81; 81C		W1

Status
✓ ➤ S

NTRH9036

Description	System Compatibility	Product compatibility	W/S
CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack			W1

Notes:
- When 1.07 becomes available in late November, CallPilot will be able to connect to non-Meridian 1 PBXs. When connecting to a non-Meridian 1 PBX, one 10/100base T Ethernet NIC is available for connection to the customers LAN and does not need to be ordered seperately. If the customer's LAN is Token Ring, the Token Ring Adapter must still be ordered.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTRH9037

Description	System Compatibility	Product compatibility	W/S
CallPilot CD ROM DRIVE			W0

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ S

NTRH9039

Description	System Compatibility	Product compatibility	W/S
CallPilot Ethernet Adaptor PCMCIA (IPE System)			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ S

NTRH9040

Description	System Compatibility	Product compatibility	W/S
Callpilot Token Ring Adapter PCMCIA (IPE System)			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
S

NTRH9048

Description	System Compatibility	Product compatibility	W/S
101 Enhanced Keyboard			W1

Notes:
- This Keyboard is used with the Nortel Call Pilot Rack System in conjunction with the NTRH9011 14" Monitor. 1 of this part is included in the base system of the Nortel Call Pilot Rack Base System
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTRH9049

Description	System Compatibility	Product compatibility	W/S
4 GB IDE Drive for the 200i System			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
✓ ➤ S

NTRH9055

Description	System Compatibility	Product compatibility	W/S
CallPilot ATA Drive with Programmed Flash			W1

Notes:
- This package is used with CallPilot IPE Systems only.

Status
✓ ➤ S

NTRH9068

Description	System Compatibility	Product compatibility	W/S
Dual Pentium III SBC			W1

Notes:
- This part is used in the CallPilot Rack Mount Systems.

Qty	Order code	Description	Qty	Order code	Description
1	A0685305	Floppy Cable	1	A0806019	IDE Cable to CD ROM
2	A0805092	Pentium III SBC 500MHz CPU			

Status
✓ ➤ S

NTRH9069

Description	System Compatibility	Product compatibility	W/S
Transceiver (MAU to 10 Base T)			W1

Notes:
- This Transceiver is used to connect the Meridian 1 CPU to the E LAN.

Status
★ ➤ S

NTRK26AA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (1 Agent)	DMS-100		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTRK26BA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (10 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK26CA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (50 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK26DA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (100 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK26EA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (500 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK26GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (5 Agents)	DMS-100		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTRK26HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (20 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK26JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 100 - New System Software (200 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27AA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (1 Agent)	DMS-100		S1

Status
★ ➤ S

NTRK27BA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (10 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27CA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (50 Agents)	DMS-100		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTRK27DA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (100 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27EA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (500 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27GA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (5 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27HA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (20 Agents)	DMS-100		S1

Status
★ ➤ S

NTRK27JA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, CCS 200 - New System Software (200 Agents)	DMS-100		S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTS101AA

Description	System Compatibility	Product compatibility	W/S
Call Processor II	81C 3311; 81C X11 R25		S1

Notes:
- Requires prerequisites SW0000L, SW0013A.
- The Meridian 1 Serial number must be provided when ordering this code as an addition to an existing Meridian 1 system.

Status
⊗ S

NTS102AA

Description	System Compatibility	Product compatibility	W/S
Corporate Directory, Virtual Office	51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		S1

Notes:
- Requires prerequisite SW0000L.
- The Meridian 1 Serial number must be provided when ordering this codes as an addtion to an existing Meridian 1 system.

Status
➤ Δ S

NTS103AA

Description	System Compatibility	Product compatibility	W/S
Fiber Network	81 X11 R25; 81C X11 R25		S1

Notes:
- Requires prerequisite SW0000L.
- The Meridian 1 Serial number must provided when ordering this codes as an addition to an existing Meridian 1 system.

Status
➤ S

NTS130AA

Description	System Compatibility	Product compatibility	W/S
Personal Mailbox Administration			S1

Notes:
- This feature requires Meridian Mail Release 13 or higher.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordered as part of a new Meridian Mail for an existing PBX.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTS132AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 AutoAdmin Software Package - MM13		Meridian Mail Card Option R12; Meridian Mail EC11 R12	S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code isThe Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordered as part of a new Meridian Mail for an existing PBX. ordered as part of a new Meridian Mail for an existing PBX.

Status
➤ S

NTS133AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12, 13)		Meridian Mail Card Option; Meridian Mail EC11	S1

Notes:

- Meridian Mail Multi-Site Reporter will re-use the RSM, MMP40, or Enhanced Processor data port that was used on the Meridian Mail Single-Site Reporter.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordered as part of a new Meridian Mail for an existing PBX.ordered as part of a new Meridian Mail for an existing PBX.

Qty	Order code	Description	Qty	Order code	Description
1	NT8R15BA	Meridian Mail Reporter Release 2 1, Software Multi-Site North America Package			

Status
➤ S

NTS134AA

Description	System Compatibility	Product compatibility	W/S
Software Feature, Personal Mailbox Administration (PMA)			S1

Notes:

- Requires Meridian Mail Release 13 or higher.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordereThe Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordered as part of a new Meridian Mail for an existing PBX.d as part of a new Meridian Mail for an existing PBX.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTS136AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail AutoAdmin Software Package EC, Modular Option, GP		Meridian Mail Modular EC R12; Meridian Mail Modular GP R12; Meridian Mail Modular Option R12	S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail. The Meridian 1 serial number is required if this code is ordered as part of a new Meridian Mail for an existing PBX.

Status
➤ S

NTS137AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package		Meridian Mail Card Option; Meridian Mail EC11; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Options (ST/RT, NT/XT)	W1

Notes:

- Requires NTZD66AA to be installed before this can be ordered.
- Meridian Mail Reporter Single-Site to Multi-Site Upgrade will use the data port currently being used by the Existing Single-Site Reporter Software.
- The Meridian Mail serial number must be provided when ordering this code.

Status
§ ➤ S

NTSF1030

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Chassis Package			W0

Notes:

- The NTSF1030 package is the main chassis for an Option 11C Mini.
- This package comes equipped with a 48-port digital line card in the fourth slot.
- One of the Option 11C Mini Software packages (NTSF8101, NTSF8102, NTSF8103, or NTSF8104) is a prerequisite package for the NTSF1030.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit
1	NTDK88AA	Option 11C Mini Main Chassis Cable Kit	1	NTTK14AA	Option 11C Mini Power Cord Kit
1	NTDK91BA	Option 11C Mini Main Chassis			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ S

NTSF1031

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Chassis Package with SSC			W0

Notes:

- This package provides an Option 11C Mini Chassis with an Option 11C SSC pack which is needed to support the addition of fiber expansion chassis packages NTSF2200, NTSF2201, and NTSF2202. For software, one of the Option 11C new system software packages must be ordered with this package. Do not order the Option 11C Mini software packages with this package.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit
1	NTDK20EA	Option 11C System Core Card	1	NTTK14AA	Option 11C Mini Power Cord Kit
1	NTDK88AA	Option 11C Mini Main Chassis Cable Kit	1	NTTK24AA	Option 11C Mini Fiber Cable Management Kit
1	NTDK91BA	Option 11C Mini Main Chassis			

Status
➤ S

NTSF1032

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Chassis Expander Package			W0

Notes:

- The NTSF1032 package provides 4 additional IPE slots, including slot 10 for Meridian Mail voice mail. A chassis expander package can be added to each Option 11C Mini Main (NTDK91AB) chassis - called up in each of the NTSF1030, NTSF2200, NTSF2201, and NTSF2202 packages.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK89AA	Option 11C Mini Chassis Expander Cable Kit	1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit
1	NTDK92BA	Mini Chassis Expander	1	NTTK14AA	Option 11C Mini Power Cord Kit

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF1033

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Chassis CPU Upgrade Package			W1/ S1

Notes:

- This package is required to expand the Option 11C Mini beyond a 2 chassis configuration to support fiber expansion chassis packages (NTSF2200, NTSF2201, and NTSF2202).

Qty	Order code	Description	Qty	Order code	Description
1	NTDK20EA	Option 11C System Core Card	1	NTTK24AA	Option 11C Mini Fiber Cable Management Kit
1	NTTK13AA	Option 11C 48MB Software Daughterboard (Blank)	1	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package

Status
➤ S

NTSF1101

Description	System Compatibility	Product compatibility	W/S
Option 11C Single Cabinet AC	11C		W1

Notes:

- All systems require choice of one (1) Option 11C System Software Package.
- All IPE to support line and trunk configuration should be ordered separately.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK98AA	Power Supply Cable	
1	NTDK20EA	Option 11C System Core Card	
1	NTDK48AA	Main Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)
	1	NTDK27AA	Ethernet Adapter Cable
1	NTDK78AA	AC/DC Power Supply	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF1102

Description	System Compatibility	Product compatibility	W/S
Option 11C Single Cabinet DC	11C		W1

Notes:

- All systems require choice of one (1) Option 11C System Software Package.
- All IPE to support line and trunk configuration should be ordered separately.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK28AB	Battery Junction Box	
1	NTDK20EA	Option 11C System Core Card	
1	NTDK48AA	Main Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)
	1	NTDK27AA	Ethernet Adapter Cable
1	NTDK72AA	DC/DC Power Supply	

Status
➤ S

NTSF2101

Description	System Compatibility	Product compatibility	W/S
Option 11C - 30 Ft. Expansion Cabinet AC	11C		W1

Notes:

- All IPE to support line and trunk configuration should be ordered separately.
- Different types of fiber connectivity can co-exist, i.e., a system can be configured with a 30 feet fiber connectivity to local expansion cabinet and 2 mile fiber connectivity (single mode or multi mode) to the remote expansion cabinet.
- Fiber Daughterboards are not part of package and must be ordered separately if required.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.

Qty	Order code	Description
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)
1	NTAK11BD	Main/Expansion Cabinet
1	NTAK98AA	Power Supply Cable
1	NTBK80AA	Ground Bar
1	NTDK23BA	30 Ft Fiber Receiver Card
1	NTDK49AA	Expansion Cabinet Cable Kit

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK78AA	AC/DC Power Supply	

Status
➤ S

NTSF2102

Description	System Compatibility	Product compatibility	W/S
Option 11C - 30 Ft. Expansion Cabinet DC	11C		W1

Notes:

- All IPE to support line and trunk configurations should be ordered separately.
- Different types of fiber connectivity can co-exist, i.e., a system can be configured with a 30 foot fiber connectivity to local expansion cabinet and 2 mile fiber connectivity to the remote expansion cabinet.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.
- Fiber Daughterboards are not part of package and must be ordered separately if required.

Qty	Order code	Description	
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK28AB	Battery Junction Box	
1	NTBK80AA	Ground Bar	
1	NTDK23BA	30 Ft Fiber Receiver Card	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK72AA	DC/DC Power Supply	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF2103

Description	System Compatibility	Product compatibility	W/S
Option 11C - 2 Mile Expansion Cabinet AC	11C		W1

Notes:

- All IPE to support line and trunk configurations should be ordered separately.
- Fiber Daughterboards are not part of package and must be ordered separately if required.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK98AA	Power Supply Cable	
1	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK78AA	AC/DC Power Supply	

Status
➤ S

NTSF2104

Description	System Compatibility	Product compatibility	W/S
Option 11C - 2 Mile Expansion Cabinet DC	11C		W1

Notes:

- All IPE to support line and trunk configurations should be ordered separately.
- Both types of fiber connectivity can co-exist, i.e., a system can be configured with a 30 foot fiber connectivity to local expansion cabinet and 2 mile fiber connectivity to the remote expansion cabinet.
- 2 Mile Glass Fiber Cable - The cable is standard 62.5/125 um glass multimode duplex cable with ST style connectors. The cable is not provided by Nortel. Potential vendors are Hewlett Packard or AMP.
- Fiber Daughterboards are not part of package and must be ordered separately if required.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.

Qty	Order code	Description
1	NTAK11BD	Main/Expansion Cabinet
1	NTAK28AB	Battery Junction Box
1	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode
1	NTDK49AA	Expansion Cabinet Cable Kit
	Each Package Includes:	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK72AA	DC/DC Power Supply	

Status
➤ S

NTSF2105

Description	System Compatibility	Product compatibility	W/S
Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber)			W1

Notes:

- All IPE to support line and trunk configurations should be ordered separately.
- Both types of fiber connectivity can co-exist, i.e., a system can be configured with a 30 feet fiber connectivity to local expansion cabinet and 2 mile fiber connectivity to the remote expansion cabinet.
- 2 Mile Glass Fiber Cable - The cable is standard 62.5/125 um glass singlemode cable with ST style connectors. The cable is not provided by Nortel Networks. Potential vendors are Hewlett Packard or AMP.
- Fiber Daughterboards are not part of package and must be ordered separately if required.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK98AA	Power Supply Cable	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK78AA	AC/DC Power Supply	
1	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF2106

Description	System Compatibility	Product compatibility	W/S
Option 11C - 2 Mile Expansion Cabinet Single Mode DC			W1

Notes:

- All IPE to support line and trunk configurations should be ordered separately.
- Both types of fiber connectivity can co-exist, i.e., a system can be configured with a 30 foot fiber connectivity to local expansion cabinet and 2 mile fiber connectivity to the remote expansion cabinet.
- 2 Mile Glass Fiber Cable - The cable is standard 62.5/125 um glass singlemode cable with ST style connectors. The cable is not provided by Nortel Networks. Potential vendors are Hewlett Packard or AMP.
- Fiber Daughterboards are not part of package and must be ordered separately if required.
- If the system being expanded has a dual daughterboard of the corresponding kind with an unused port, then it is not necessary to include a fibre daughterboard with the order.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTAK28AB	Battery Junction Box	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK72AA	DC/DC Power Supply	
1	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF2200

Description	System Compatibility	Product compatibility	W/S
Chassis Fiber Expansion Package (30 Ft.)			W1

Notes:

- The NTSF1031 (Option 11C Mini Supporting Fiber Expansion Package) or the NTSF1033 (MSC to SSC upgrade package) is a prerequisite for connecting this expansion package from a Mini Main Chassis.
- This package comes equipped with a 48-port digital line card in slot 4.
- The Small System Controller fiber transmitter daughterboard must be purchased separately (either NTDK22 - single port, or NTDK84 - dual port) if necessary.
- This package can be used in place of an Option 11C Expansion Cabinet to expand an Option 11C system (Release 22 to current).

Qty	Order code	Description	
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	
1	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	
1	NTDK23BA	30 Ft Fiber Receiver Card	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK91BA	Option 11C Mini Main Chassis	
1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	
1	NTTK14AA	Option 11C Mini Power Cord Kit	
1	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package	

Status
➤ S

NTSF2201

Description	System Compatibility	Product compatibility	W/S
Chassis Fiber Expansion Package (2mi. Multi-Mode)			W1

Notes:

- The NTSF1031 (Option 11C Mini Supporting Fiber Expansion Package) or the NTSF1033 (MSC to SSC upgrade package) is a prerequisite for connecting this expansion package from a Mini Main Chassis.
- This package comes equipped with a 48-port digital line card in slot 4.
- The Small System Controller fiber transmitter daughterboard must be purchased separately (either NTDK23 - single port, or NTDK85 - dual port) if necessary.
- This package can be used in place of an Option 11C Expansion Cabinet, to expand an Option 11C system (Release 22 to current).

Qty	Order code	Description	
1	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	
1	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK91BA	Option 11C Mini Main Chassis	
1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	
1	NTTK14AA	Option 11C Mini Power Cord Kit	
1	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package	

Status
➤ S

NTSF2202

Description	System Compatibility	Product compatibility	W/S
Chassis Fiber Expansion Package (2mi. Single-Mode)			W1

Notes:

- The NTSF1031 (Option 11C Mini Supporting Fiber Expansion Package) or the NTSF1033 (MSC to SSC upgrade package) is a prerequisite for connecting this expansion package from a Mini Main Chassis.
- This package comes equipped with a 48-port digital line card in slot 4.
- The Small System Controller fiber transmitter daughterboard must be purchased separately (NTDK79 - only the single port option is available at this time).
- This package can be used in place of an Option 11C Expansion Cabinet, to expand an Option 11C system (Release 22 to current).

Qty	Order code	Description	
1	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	
1	NTDK91BA	Option 11C Mini Main Chassis	
1	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	
1	NTTK14AA	Option 11C Mini Power Cord Kit	
1	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTSF3001

Description	System Compatibility	Product compatibility	W/S
Package of 10 Option 11C Documentation CD-ROMs	11C		W0/ S1

Qty	Order code	Description	Qty	Order code	Description
10	NTLH01AA	CD-ROM, X11 Release 25			

Status
➤ S

NTSF3100

Description	System Compatibility	Product compatibility	W/S
2.0MB DTI Package Option 11C	11C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NTAK10DC	2 0 MB DTI Card with Clock Controller	1	P0907454	2 0 MB DTI/PRI Administration/Maintenance Guide
1	NTBK05DA	2 0MB DTI/PRI Twisted Pair Cable			

Status
➤ S

NTSF3101

Description	System Compatibility	Product compatibility	W/S
2.0MB PRI Package Option 11C	11C		W1

Qty	Order code	Description	Qty	Order code	Description
1	NTBK05DA	2 0MB DTI/PRI Twisted Pair Cable	1	P0907454	2 0 MB DTI/PRI Administration/Maintenance Guide
1	NTBK50AA	2 0MB Primary Rate Interface Card			

Status
➤ S

NTSF6001

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Single Cabinet Upgrade	11C		W1

Notes:

- Requires Applicable Release 22 Software Update to be ordered with this package.
- Use this package when upgrading a single cabinet 11/11E to a single cabinet 11C cabinet.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	1	NTDK27AA	Ethernet Adapter Cable
1	NTDK20EA	Option 11C System Core Card			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF6002

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Two Cabinet Copper Upgrade	11C		W1

Notes:

- Requires Applicable Release 22 Software Update to be ordered with this package.
- Use this package when upgrading a dual cabinet Copper 11/11E to a dual cabinet Copper 11C cabinet.
- This configuration does not allow Ethernet connection, if Ethernet connection is required an Option 11/11E to 11C Ethernet Upgrade is required (NTSF6003 or NTSF6004).
- Documentation Packages must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	1	NTDK26AA	Backwards Compatible Daughterboard
1	NTDK20EA	Option 11C System Core Card			

Status
➤ S

NTSF6003

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Two Cabinet Fiber Upgrade (30 Ft.)	11C		W1

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a dual cabinet Fibre 11/11E to a dual cabinet Ethernet 11C cabinet.
- Documentation Packages must be ordered separately.
- Assumes NTAK11BD will replace existing second cabinet and re-use existing power supply.

Qty	Order code	Description
1	A0632902	33 Ft Plastic Fiber Cable (11E/11C)
1	NTAK11BD	Main/Expansion Cabinet
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)
1	NTBK80AA	Ground Bar
1	NTDK18AA	Cabinet Upgrade Kit
1	NTDK20EA	Option 11C System Core Card
1	NTDK22AA	30 Ft Fiber Daughterboard - Multi Mode
1	NTDK23BA	30 Ft Fiber Receiver Card
1	NTDK27AA	Ethernet Adapter Cable
1	NTDK49AA	Expansion Cabinet Cable Kit
	Each Package Includes:	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
2	P0816832	Fiber Routing Guide	

Status
➤ S

NTSF6004

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Two Cabinet Fiber Upgrade (2 mile)	11C		W1

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a dual cabinet Fibre 11/11E to a dual cabinet Ethernet 11C cabinet.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
1	NTAK11BD	Main/Expansion Cabinet	
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	
1	NTDK18AA	Cabinet Upgrade Kit	
1	NTDK20EA	Option 11C System Core Card	
1	NTDK24AB	2 Mile Fiber Daughterboard - Multi-Mode	
1	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	
1	NTDK27AA	Ethernet Adapter Cable	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
2	P0816832	Fiber Routing Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF6005

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Three Cabinet Fiber Upgrade (30 Ft.)	11C		W1

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a three cabinet Fibre 11/11E to a three cabinet Ethernet 11C cabinet.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
2	A0632902	33 Ft Plastic Fiber Cable (11E/11C)	
2	NTAK11BD	Main/Expansion Cabinet	
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	
1	NTBK80AA	Ground Bar	
1	NTDK18AA	Cabinet Upgrade Kit	
1	NTDK20EA	Option 11C System Core Card	
2	NTDK23BA	30 Ft Fiber Receiver Card	
1	NTDK27AA	Ethernet Adapter Cable	
2	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK84AA	30 Ft DUAL Port Fiber Daughterboard	
4	P0816832	Fiber Routing Guide	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF6006

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Three Cabinet Fiber Upgrade (2 mile)	11C		W1

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a three cabinet Fibre 11/11E to a three cabinet Ethernet 11C cabinet.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
2	NTAK11BD	Main/Expansion Cabinet	
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	
1	NTDK18AA	Cabinet Upgrade Kit	
1	NTDK20EA	Option 11C System Core Card	
2	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	
1	NTDK27AA	Ethernet Adapter Cable	
2	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK85AA	2 Mile Multi Mode DUAL Port Fiber Daughterboard	
4	P0816832	Fiber Routing Guide	

Status
➤ S

NTSF6007

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C - Two Cabinet Ethernet Upgrade (2 Mile - Single Mode Fiber)	11C		W0

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a dual cabinet 11/11E to a dual cabinet Fiber 11C.
- Documentation Packages must be ordered separately.
- Glass Fiber (up to 3km) is to be supplied by distributor.

Qty	Order code	Description
1	NTAK11BD	Main/Expansion Cabinet
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)
1	NTDK18AA	Cabinet Upgrade Kit
1	NTDK20EA	Option 11C System Core Card
1	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode
1	NTDK27AA	Ethernet Adapter Cable

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
1	NTDK79AA	2 Mile Fiber Daughterboard Single Mode	
1	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	
2	P0816832	Fiber Routing Guide	

Status
➤ S

NTSF6008

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to 11C Three Cabinet Single Mode Fiber Upgrade (2 Mile)	11C		W0

Notes:

- This package requires an Option 11/11E to 11C Software Upgrade package to be ordered.
- Use this package when upgrading a three cabinet Fiber 11/11E to a three cabinet Ethernet 11C cabinet using single mode fiber.
- Documentation Packages must be ordered separately.

Qty	Order code	Description	
2	NTAK11BD	Main/Expansion Cabinet	
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	
1	NTDK18AA	Cabinet Upgrade Kit	
1	NTDK20EA	Option 11C System Core Card	
1	NTDK27AA	Ethernet Adapter Cable	
2	NTDK49AA	Expansion Cabinet Cable Kit	
	Each Package Includes:		
	1	A0601396	Modem Eliminator Male to Female
	1	A0601397	Modem Eliminator Female to Female
	1	NTAK1104	PFTU/Console Power Cable
	1	NTAK1118	Modem Cable (DB9 to DB25)
2	NTDK79AA	2 Mile Fiber Daughterboard Single Mode	
2	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	
4	P0816832	Fiber Routing Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTSF6501

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact to Option 11C Migration Package	11C		W1/ S1

Notes:

- The Option 11C Compact Site ID must be provided when ordering this code.

Qty	Order code	Description	
1	AS7120	2 Port Full Service Voice Processing Package, Card Option	
	Each Package Includes:		
	1	NTAK16AB	C25 Voice Processor Card
	2	SW7105	Meridian Mail Card Option Full Service Port License Fee
1	NT8D02GA	Digital Line Card (DLC)	
1	NT8D09BA	Analog Message Waiting Line Card	
1	NT8D14BB	Universal Trunk Card	
1	NTSF1101	Option 11C Single Cabinet AC	
	Each Package Includes:		
	1	NTAK11BD	Main/Expansion Cabinet
	1	NTAK98AA	Power Supply Cable
	1	NTDK20EA	Option 11C System Core Card
	1	NTDK48AA	Main Cabinet Cable Kit
	1	NTDK78AA	AC/DC Power Supply
1	NTSF8021	Option 11C Enhanced Business Software Package	
	Each Package Includes:		
	1	NTDK57AA	Dongle
	1	NTLH01AA	CD-ROM, X11 Release 25
	1	NTSF8102	Option 11C 100 Additional TNs - Enhanced Business
	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
	1	NTSK11DP	Option 11C Enhanced Business Feature Set - Release 25 Combo
1	NTZC49AA	Enhanced Meridian Mail Card Option 4-12 Ports, 5/10/24/54 Hours Package	
	Each Package Includes:		
	1	NT6R16AA	Enhanced Processor for Card Option Systems
	1	NTDK74AB	Card Option 4 5GB Disk Drive
	4	SW7105	Meridian Mail Card Option Full Service Port License Fee
1	SW7102	Meridian Mail Card Option Expanded Storage Software Level 1-2	
1	SW7103	Meridian Mail Card Option Expanded Storage Software Level 2-3	
2	SW7105	Meridian Mail Card Option Full Service Port License Fee	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ B

NTSF6800

Description	System Compatibility	Product compatibility	W/S
Option 11C TMDI Package (1.5MB DTI/ PRI)			W1

Notes:

- The NTSF6800 package containing an NTRB21AA is compatible with X11.24.24 or higher software.
- The NTRB21AA TMDI card provides DTI/PRI functionality. To enable the D-Channel, an NTSF8730 must be ordered for each D-Channel required on a TMDI.

Qty	Order code	Description	Qty	Order code	Description
1	NTRB21AA	T1 Multipurpose Digital Interface (TMDI)	1	P0907453	1 5 MB DTI/PRI/TMDI Administration and Maintenance Guide

Status
➤ S

NTSF6851

Description	System Compatibility	Product compatibility	W/S
Internet Registration Kit			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0866882	User ID and Password Sheet	1	P0866883	Product Bulletin

Status
✓ ➤ S

NTSF8011

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini General Business Software Package			W1/ S1

Notes:

- For use on Option 11C Mini.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11CP	Option 11C General Business Feature Set - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11ZN	Release 25 Programmed Mini System Controller Pack

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8012

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Enhanced Business Software Package			W1/ S1

Notes:
- For use on Option 11C Mini.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11DP	Option 11C Enhanced Business Feature Set - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11ZN	Release 25 Programmed Mini System Controller Pack

Status
✓ ➤ S

NTSF8013

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini Enterprise Business Software Package			W1/ S1

Notes:
- For use on Option 11C Mini.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11EP	Option 11C Enterprise Business Feature Set - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11ZN	Release 25 Programmed Mini System Controller Pack

Status
✓ ➤ S

NTSF8014

Description	System Compatibility	Product compatibility	W/S
Option 11C Mini NAS/VNS Software Package			W1/ S1

Notes:
- For use on Option 11C Mini.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11FP	Option 11C NAS/VNS Feature Set - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11ZN	Release 25 Programmed Mini System Controller Pack

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8020

Description	System Compatibility	Product compatibility	W/S
Option 11C General Business Software Package	11C		S1

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11CP	Option 11C General Business Feature Set - Release 25 Combo
1	NTSF8101	Option 11C 100 Additional TNs - General Business			

Status
✓ ➤ S

NTSF8021

Description	System Compatibility	Product compatibility	W/S
Option 11C Enhanced Business Software Package			S1

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11DP	Option 11C Enhanced Business Feature Set - Release 25 Combo
1	NTSF8102	Option 11C 100 Additional TNs - Enhanced Business			

Status
✓ ➤ S

NTSF8022

Description	System Compatibility	Product compatibility	W/S
Option 11C Enterprise Software Package	11C		S1

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11EP	Option 11C Enterprise Business Feature Set - Release 25 Combo
1	NTSF8103	Option 11C 100 Additional TNs - Enterprise			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8023

Description	System Compatibility	Product compatibility	W/S
Option 11C NAS/VNS Software Package	11C		S1

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11FP	Option 11C NAS/VNS Feature Set - Release 25 Combo
1	NTSF8104	Option 11C 100 Additional TNs - NAS/VNS			

Status
✓ ➤ S

NTSF8028

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to Option 11C General Business Software Upgrade	11C		S1

Notes:

- Order this package to upgrade from Option 11 or 11E to Option 11C.
- A hardware upgrade package is also required and must be ordered separately.
- The original software cartridge must be returned for a credit to be issued.
- The Option 11/11E Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11CP	Option 11C General Business Feature Set - Release 25 Combo

Status
✓ ➤ S

NTSF8029

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to Option 11C Enhanced Business Software Upgrade	11C X11		S1

Notes:

- Order this package to upgrade from Option 11 or 11E to Option 11C.
- A hardware upgrade package is also required and must be ordered separately.
- The original software cartridge must be returned for a credit to be issued.
- The Option 11/11E Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11DP	Option 11C Enhanced Business Feature Set - Release 25 Combo

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8030

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to Option 11C Enterprise Software Upgrade	11C		S1

Notes:

- Order this package to upgrade from Option 11 or 11E to Option 11C.
- A hardware upgrade package is also required and must be ordered separately.
- The original software cartridge must be returned for a credit to be issued.
- The Option 11/11E Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11EP	Option 11C Enterprise Business Feature Set - Release 25 Combo

Status
✓ ➤ S

NTSF8031

Description	System Compatibility	Product compatibility	W/S
Option 11/11E to Option 11C NAS/VNS Software Upgrade	11C		S1

Notes:

- Order this package to upgrade from Option 11 or 11E to Option 11C.
- A hardware upgrade package is also required and must be ordered separately.
- The original software cartridge must be returned for a credit to be issued.
- The Option 11/11E Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo
1	NTLH01AA	CD-ROM, X11 Release 25	1	NTSK11FP	Option 11C NAS/VNS Feature Set - Release 25 Combo

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8048

Description	System Compatibility	Product compatibility	W/S
Option 11C General Business Software Feature Upgrade	11C; 11C X11 R22,25; X11		S1

Notes:

- The PCMCIA card which contains the software must be acquired separately by: 1. Purchasing an NTSK11Bx programmed PCMCIA card 2. Sending an existing PCMCIA card back to Nortel for re-programming (Include P0850716 on your order) 3. Distributor can program existing PCMCIA card by downloading software from the internet or copying software from another PCMCIA card (Internet registration kit number NTSF6851).
- The Option 11/11E/11C Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTSK11CP	Option 11C General Business Feature Set - Release 25 Combo			

Status
✓ ➤ S

NTSF8049

Description	System Compatibility	Product compatibility	W/S
Option 11C Enhanced Business Software Feature Upgrade	11C; 11C X11 R22,25; X11		S1

Notes:

- The PCMCIA card which contains the software must be acquired separately by: 1. Purchasing an NTSK11BG card 2. Sending an existing PCMCIA card back to Nortel for re-programming (Include P0850716 on your order) 3. Distributor can program existing PCMCIA card by downloading software from the internet or copying software from another PCMCIA card (Internet registration kit number NTSF6851).
- The Option 11/11E/11C Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTSK11DP	Option 11C Enhanced Business Feature Set - Release 25 Combo			

Status
✓ ➤ S

NTSF8050

Description	System Compatibility	Product compatibility	W/S
Option 11C Enterprise Software Feature Upgrade	11C; 11C X11 R22,25; X11		S1

Notes:

- The PCMCIA card which contains the software must be acquired separately by: 1. Purchasing an NTSK11BG card 2. Sending an existing PCMCIA card back to Nortel for re-programming (Include P0850716 on your order) 3. Distributor can program existing PCMCIA card by downloading software from the internet or copying software from another PCMCIA card (Internet registration kit number NTSF6851).
- The Option 11/11E/11C Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11EP	Option 11C Enterprise Business Feature Set - Release 25 Combo

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTSF8051

Description	System Compatibility	Product compatibility	W/S
Option 11C NAS/VNS Software Feature Upgrade	11C; 11C X11 R22		S1

Notes:

- The PCMCIA card which contains the software must be acquired separately by: 1. Purchasing an NTSK11BG card 2. Sending an existing PCMCIA card back to Nortel for re-programming (Include P0850716 on your order) 3. Distributor can program existing PCMCIA card by downloading software from the internet or copying software from another PCMCIA card (Internet registration kit number NTSF6851).
- The Option 11/11E/11C Site Id is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTSK11FP	Option 11C NAS/VNS Feature Set - Release 25 Combo

Status
➤ S

NTSF8101

Description	System Compatibility	Product compatibility	W/S
Option 11C 100 Additional TNs - General Business	11C; 11C X11 R22		S1

Notes:

- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ S

NTSF8102

Description	System Compatibility	Product compatibility	W/S
Option 11C 100 Additional TNs - Enhanced Business	11C; 11C X11 R22		S1

Notes:

- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ S

NTSF8103

Description	System Compatibility	Product compatibility	W/S
Option 11C 100 Additional TNs - Enterprise	11C; 11C X11 R22		S1

Notes:

- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF8104

Description	System Compatibility	Product compatibility	W/S
Option 11C 100 Additional TNs - NAS/ VNS	11C; 11C X11 R22		S1

Notes:
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ S

NTSF8501

Description	System Compatibility	Product compatibility	W/S
Option 11C Package #22 - DISA	11C; 11C X11 R22		S1

Notes:
- This feature must be ordered separately and can be ordered with any base Option 11C Release 22 Software Package.
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ Δ S

NTSF8508

Description	System Compatibility	Product compatibility	W/S
AST (100 Increment)	11C		S1

Notes:
- This feature must be ordered separately and can be ordered with any Option 11C Release 22 or later Software Package.
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ Δ S

NTSF8509

Description	System Compatibility	Product compatibility	W/S
Call Identification (CALL-ID Package 247)	11C		W0

Notes:
- This feature can be ordered for Release 22.08D General Business or Enhanced Business sites requiring Meridian Mail Password Suppression (included on other feature sets and other issues of software).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTSF8512

Description	System Compatibility	Product compatibility	W/S
Option 11C Electronic Brandlining - Display Customization	11C		W0/ S1

Notes:
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ Δ S

NTSF8513

Description	System Compatibility	Product compatibility	W/S
Option 11C RAN Connections for Release 23.18	11C		W0

Notes:
- This code can be used to change the number of default RAN Connections from 10 to 12 on Release 23.18 sites only. Later issues of software are already set to 12.

Status
➤ S

NTSF8514

Description	System Compatibility	Product compatibility	W/S
Increment the Option 11C RAN Connections ISM parameter by 1	11C; 11C X11 R23		S1

Notes:
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
➤ S

NTSF8516

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 23 for CallPilot (Keycode only)			W0

Notes:
- Must be ordered with CallPilot having General or Enhanced Packages software, higher software will not need NTSF8516.
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ Δ S

NTSF8519

Description	System Compatibility	Product compatibility	W/S
Enable Package 381, 382 for M3900 Sets Phase II			S1

Notes:
- This package will generate a keycode which enables software package 381 and 382 for M3900 sets Phase II.

Status
➤ S

NTSF8702

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Upissue Keycode			S1

Notes:
- Credit will be issued for your current software load.
- The PCMCIA card which contains the software must be acquired separately by:
- 1. Purchasing an NTSK11BN card. 2. Sending an existing PCMCIA card back to Nortel Networks for re-programming (include P0850716 on your order). 3. Distributor can program existing PCMCIA card by downloading software from the internet (http://www.nortelnetworks.com/servsup/esd/meridian1/) or copying software from another PCMCIA card.
- The Option 11/11E/11C Site Id is required when ordering this code.

Status
➤ S

NTSF8712

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Upgrade Fee to Current	11C		W0/ S1

Notes:
- Current feature set will be maintained unless a Software Feature Package is ordered in addition to this package.
- Credit will be issued for your current software load.
- Please note that the particular software may also require a new software daughterboard. (see compatibility table).
- Software Daughterboard Capacity Introduced on Compatible with
- NTDK21AA 32 Meg Rls 22.08D Rls 22.08D -23.55
- NTDK81AA 40 Meg Rls 23.18 Rls 23.18 - 24.24
- NTTK13AA 48 Meg Rls 24.24 Rls 24.24 - 25
- The PCMCIA card which contains the software must be acquired separately by:
- 1. Purchasing an NTSK11BN card. 2. Sending an existing PCMCIA card back to Nortel Networks for re-programming (include P0850716 on your order). 3. Distributor can program existing PCMCIA card by downloading software from the internet (http://www.nortelnetworks.com/servsup/esd/meridian1/) or copying software from another PCMCIA card.
- The Option 11/11E/11C Site Id is required when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ B

NTSF8722

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Rls 24C Upissue Keycode			S1

Notes:

- This code to be used to upgrade Opt 11C Rls 24 software to 24C (25.08)only
- The PCMCIA card which contains the software must be acquired separately by:
- 1. Purchasing an NTSK11BL PCMCIA card. 2. Sending an existing PCMCIA card back to Nortel Networks for re-programming (include P0850716 on your order). 3. Distributor can program existing PCMCIA card by downloading software from the internet (http://www.nortelnetworks.com/servsup/esd/meridian1/) or copying software from another PCMCIA card.
- The Option 11C Site Id is required when ordering this code.

Status
➤ B

NTSF8730

Description	System Compatibility	Product compatibility	W/S
Option 11C TMDI D-Channels Keycode	11C 2111 R24.24		S1

Notes:

- The NTSF8730 TMDI D-Channels ISM parameter and order code is used to add individual D-Channels to NTRB21AA cards only. Existing D-Channel daughterboards are not effected by this code.
- The Option 11/11E/11C Site Id is required if ordering this code for addition to an existing system.

Status
† ➤ S

NTSK11AA

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 22.08D	11C		W1

Notes:

- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTSK11AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 22.16	11C		W1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
† ➤ S

NTSK11AC

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 22.46	11C		W1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
† ➤ S

NTSK11AF

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 23.18	11C		W1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
† ➤ S

NTSK11AG

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 23.35	11C		W1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTSK11AH

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 23.55	11C		W1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
† B

NTSK11AK

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 24.24	11C		W1/ S1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
✓ B

NTSK11AL

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 25	11C		W1/ S1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- Option 11/11E/11C Site ID required if ordering for replacement of an OBF.

Status
✓ ➤ B

NTSK11AN

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 25	11C		W1/ S1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID is required if ordering for replacement of an OBF.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ B

NTSK11AP

Description	System Compatibility	Product compatibility	W/S
Option 11C Software Daughterboard - Release 25 Combo	11C		W1/ S1

Notes:
- Programmed software daughterboards are offered for sparing and replacement use. The site must already have a valid security device and keycode.
- The Option 11/11E/11C Site ID is required if ordering for replacement of an OBF.

Status
✓ ➤ B

NTSK11BH

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 23.55 Programmed PCMCIA Card			W0/ S1

Notes:
- NTSK11BH is a 40MB programmed PCMCIA flash memory card. It is programmed with Option 11C, X11 Release 23C software.
- Release 23.4x software will be available in December 1998.

Status
✓ ➤ B

NTSK11BK

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 24.24 Programmed PCMCIA Card	11C		W0/ S1

Status
✓ B

NTSK11BL

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 25 Programmed 40MB PCMCIA Card	11C		W0/ S1

Status
✓ ➤ B

NTSK11BN

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 25 Programmed PCMCIA Card	11C		W0/ S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NTSW31AA

Description	System Compatibility	Product compatibility	W/S
Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08)			W0/ S1

Notes:

- This code is used only when upgrading Opt 51C-81C machines from Rls 24 to Rls 24C (25.08)
- When ordering this code, the customer will receive: the software CD ROM, the Rls 25 documentation CD ROM & install disks, the Rls 24C GRB and the site keycode file.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
✓ ➤ S

NTSZ00AC

Description	System Compatibility	Product compatibility	W/S
Option 81C 68060 Enhanced Call Process New System Pkg AC (IGS Network Included)	81C X11 R25		W1

Notes:

- This package includes the fiber network fabric to support two network groups and can support a maximum of eight network groups.
- X11 Release 25 or later software is required to support this package.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- This package includes two 68060E Call Processors.
- This package contains two NTRB34AA Core-to-Network Interface packs (one per core/network module) which can support up to three network groups(Groups "0","1","2").
- Two additional CNI-3 packs are required to support network groups four through six (Groups "3","4","5") and must be ordered separately.
- Two additional CNI-3 packs are required to support network groups seven and eight (Groups "6","7") and must be ordered separately.
- This package is equipped with two network groups. Additional network groups may be ordered using the Fiber Network Group Expansion Package, NTHY20AC, or the Fiber Network Group Column Package, NTHY24AC.
- This package does not contain clock controllers. Quanity 2 of either QPC471 Vintage "H" or later (US Market), or QPC 775 "F" or later (Canada) must be purchased separately.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
2	NT5D03PB	68060 Enhanced 160MB Call Processor	
2	NT5D21AA	Core/Network Module AC	
2	NT5D61AB	IODU/C Pack	
1	NT5D84AA	Keycode Security Device Kit	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
2	NT7D00AA	Top Cap AC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
4	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)
2	NTRD25AA	Pedestal Assembly AC
2	NTRE39AA	Optical Cable Management Card (OCMC)
1	NTZC91BA	Software Installation Kit (Non-Autovon)
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

Status
✓➤ S

NTSZ00DC

Description	System Compatibility	Product compatibility	W/S
Option 81C New System Package DC	81C X11 R25		W1

Notes:

- This package includes the fiber network fabric to support two network groups and can support a maximum of eight network groups.
- X11 Release 25 or later software is required to support this package.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- This package includes two 68060E Call Processors.
- This package contains two NTRB34AA Core-to-Network Interface packs (one per core/network module) which can support up to three network groups (Groups "0", "1", "2").
- Two additional CNI-3 packs are required to support network groups four through six (Groups "3", "4", "5") and must be ordered separately.
- Two additional CNI-3 packs are required to support network groups seven and eight (Groups "6", "7") and must be ordered separately.
- This package is equipped with two network groups. Additional network groups may be ordered using the Fiber Network Group Expansion Package, NTHY20DC, or the Fiber Network Group Column Package, NTHY24DC.
- This package does not contain clock controllers. Quantity 2 of either QPC471 Vintage "H" or later (US Market) or QPC 775 Vintage "F" or later (Canada) must be purchased separately.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
2	NT5D03PB	68060 Enhanced 160MB Call Processor	
2	NT5D21DA	Core/Network Module DC	
2	NT5D61AB	IODU/C Pack	
1	NT5D84AA	Keycode Security Device Kit	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT6D40BA	Peripheral Equipment Power Supply DC	
4	NT6D41AD	Common Equipment Power Supply DC	
2	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)
2	NTRD25BA	Pedestal Assembly DC
2	NTRE39AA	Optical Cable Management Card (OCMC)
1	NTZC91BA	Software Installation Kit (Non-Autovon)
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

Status
✓ ➤ ⊗ S

NTSZ25AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII New System Package AC (Fiber Network Fabric Included)	81C X11 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII, NTS103AA (365) Fiber Network Software Package, SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- This package is equipped with two (2) network groups. Additional groups may be ordered using the Fiber Network Group Expansion Package, NTHY20AC, or the Fiber Network Group Column Package, NTHY24AC.
- This package contains two NT4N65 cards and the cabling associated with them that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Note that additional networks groups, beyond the first two included in this package, require the purchase of two NT4N65 cards which will support two additional network groups. These can be ordered separately. In addition, four NT8D76 cables must be ordered separately for each additional network group.
- Clock controllers are not included in this package and must be ordered separately. Two (2) QPC471'H' vintage or later must be ordered.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
2	NT4N41AA	cPCI Core/Network Module AC
2	NT4N43AA	cPCI Multi-Media Disk Unit
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card
2	NT4N67AA	cPCI System Utility Card
2	NT4N6809	Security Device Holder
2	NT4N68AA	cPCI System Utility Transition Card

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT5D84AA	Keycode Security Device Kit	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
2	NT7D00AA	Top Cap AC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D29BA	Core/Network Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)	
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)	
2	NTRD25AA	Pedestal Assembly AC	
2	NTRE39AA	Optical Cable Management Card (OCMC)	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
1	NTZC91BA	Software Installation Kit (Non-Autovon)	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	
4	QPC43R	Peripheral Signaling	
4	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ ⊗ S

NTSZ25DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII New System Package DC (Fiber Network Fabric Included)	81C X11 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII, NTS103AA (365) Fiber Network Software Package, SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C and the fiber network fabric is eight groups with X11 Release 25 or later software.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- This package is equipped with two (2) network groups. Additional groups may be ordered using the Fiber Network Group Expansion Package, NTHY20DC, or the Fiber Network Group Column Package, NTHY24DC.
- This package contains two NT4N65 cards and the cabling associated with them that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Note that additional network groups, beyond the first two included in this package, require the purchase of two NT4N65 cards which will support two additional network groups. These can be ordered separately. In addition, four NT8D76 cables must be ordered separately for each additional network group.
- Clock controllers are not included in this package and must be ordered separately. Two (2) QPC471'H' vintage or later must be ordered.

Qty	Order code	Description	
2	A0810496	CP PII Call Processor Card (128MB Memory)	
1	NT1R91AA	Modem Kit	
2	NT4N41DA	cPCI Core/Network Module DC	
2	NT4N43AA	cPCI Multi-Media Disk Unit	
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	
8	NT4N66AB	cPCI Core Network Interface Transition Card	
2	NT4N67AA	cPCI System Utility Card	
2	NT4N6809	Security Device Holder	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
1	NT5D84AA	Keycode Security Device Kit	
1	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	
	Each Package Includes:		
	1	P0914248	CP PII/FNF System and Software Upgrade Guide
	1	P0914249	CP PII Description, Installation and Administration Guide (incl IGS and Fiber Network)
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
2	NT6D41CA	Core/Network Power Supply DC	
2	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
2	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft)	
2	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
4	NTRB33AA	Fiber Junctor Interface Card (FIJI)	
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRC46BA	Clock to FIJI Cable, (5 5 Ft -8 Ft)	
1	NTRC47AA	FIJI to FIJI Synch Cable	
2	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft /2M)	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft /3M)
1	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft)
2	NTRD25BA	Pedestal Assembly DC
2	NTRE39AA	Optical Cable Management Card (OCMC)
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel
1	NTZC91BA	Software Installation Kit (Non-Autovon)
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
22	P0906308	cPCI Card Slot Filler Panel
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

Status
✓➤⊗S

NTSZ26AC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII New System Package AC (IGS Network Included)	81C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) Call Processor PII and SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C systems that are equipped with the Intergroup Module (IGM) and IGS or DIGS cards is five with X11 Release 25 or later software.
- Fiber Network Fabric Hardware and Software Option 365 cannot co-exist on Option 81C systems equipped with Call Processor PII hardware and CP PII Software Option 368. Fiber Network Fabric and Call Processor PII are mutually exclusive at this time.
- The junctor board in the Junctor Module requires Quantity 4 QPF36 Terminating Plugs for each unequipped network group and must be ordered separately.
- This package is equipped with two (2) network groups. Additional IGS based network groups may be ordered using QCA6645 Network Group Assembly Package AC.
- This package contains two NT4N65 cards and the cabling associated with them that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which will support up to eight network groups with the Fiber Network Fabric. Note that additional network groups, beyond the first two included in this package, require the purchase of two NT4N65 cards which will support two additional network groups. These can be ordered separately. In addition, four NT8D76 cables must be ordered separately for each additional network group.
- This package does not include clock controllers which must be ordered separately. Two (2) QPC471'H' vintage or later must be ordered.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-by-side must be ordered separately.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel Ringing Generator must be equipped.
- This package includes sixteen (16) NT8D81AA Tip and Ring Cables within the IPE Module.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
2	NT4N41AA	cPCI Core/Network Module AC
2	NT4N43AA	cPCI Multi-Media Disk Unit
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card
2	NT4N67AA	cPCI System Utility Card
2	NT4N6809	Security Device Holder

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT4N68AA	cPCI System Utility Transition Card	
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)	
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)	
2	NT4N89AA	System Utility to XSM Cable	
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)	
4	NT5D30AA	Dual Intergroup Switch	
1	NT5D84AA	Keycode Security Device Kit	
2	NT7D00AA	Top Cap AC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D29BA	Core/Network Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D36AA	Inter Group Module	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
6	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	
2	NTRD25AA	Pedestal Assembly AC	
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	
1	NTZC91BA	Software Installation Kit (Non-Autovon)	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
22	P0906308	cPCI Card Slot Filler Panel	
4	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ ⊗ S

NTSZ26DC

Description	System Compatibility	Product compatibility	W/S
Option 81C Call Processor PII New System DC (IGS Network Included)	81C 3311 R25		W1

Notes:

- This Option 81C package requires the following feature packages be enabled: NTS101AA (368) CP PII and SW0013A (299) Option 81C Software Package.
- The maximum number of network groups supported on Option 81C systems that are equipped with Intergroup Modules (IGM) and IGS or DIGS cards is five with X11 Release 25 or later software.
- Fiber Network Fabric hardware and Fiber Network Fabric Software Option 365 cannot co-exist on Option 81C systems with CP PII hardware and CP PII Software Option 368. Fiber Network Fabric and CP PII are mutually exclusive on the same system at this time.
- The Junctor Board in the Junctor Module requires four QPF36 Terminating Plugs for each unequipped network group and must be ordered separately.
- This package is equipped with two (2) network groups. Additional groups may be ordered using the AS1039D Network Group Assembly Package DC.
- This package contains two (2) NT4N65 cards that provide CNI to 3PE connections for the first two network groups. This package also contains cCNI Transition Cards, NT4N66, which can support up to eight network groups with the Fiber Network Fabric. Additional network groups require the purchase of two NT4N65 cards which support two additional groups. These are ordered separately. In addition, four (4) NT8D76 cables must be ordered separately for each additional network group.
- This package does not include clock controllers. Two (2) QPC471'H' or later vintage must be ordered separately.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides and to connect modules side-by-side must be ordered separately.
- This package includes sixteen (16) NT8D81AA Tip and Ring Cables within the IPE Module.

Qty	Order code	Description
2	A0810496	CP PII Call Processor Card (128MB Memory)
1	NT1R91AA	Modem Kit
2	NT4N41DA	cPCI Core/Network Module DC
2	NT4N43AA	cPCI Multi-Media Disk Unit
2	NT4N65AB	cPCI Core Network Interface Card (2 Ports)
8	NT4N66AB	cPCI Core Network Interface Transition Card
2	NT4N67AA	cPCI System Utility Card
2	NT4N6809	Security Device Holder
2	NT4N68AA	cPCI System Utility Transition Card
2	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In)
2	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In)
2	NT4N89AA	System Utility to XSM Cable
2	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In)
4	NT5D30AA	Dual Intergroup Switch
1	NT5D84AA	Keycode Security Device Kit
1	NT6D40BA	Peripheral Equipment Power Supply DC
2	NT6D41AD	Common Equipment Power Supply DC
2	NT6D41CA	Core/Network Power Supply DC

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
2	NT8D35EA	Network Module DC	
1	NT8D36AA	Inter Group Module	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
6	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTLH15AA	CP PII with IGS Reference Library	
	Each Package Includes:		
	1	P0905705	CP PII Upgrades Guide
	1	P0905706	CP PII Description, Installation and Administration Guide
2	NTRC17AA	CP PII Ethernet to Ethernet Cable (8 5 Ft /3m)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRD25BA	Pedestal Assembly DC
2	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel
1	NTZC91BA	Software Installation Kit (Non-Autovon)
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
22	P0906308	cPCI Card Slot Filler Panel
1	QPC417A	Junctor Board
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender

Status
➤ Δ B

NTTK30AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 25 English Documentation Package, Binder			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0907441	Overview, Installation and Programming	1	P0907443	Option 11C Administration & Maintenance I/O Guides
1	P0907442	Post Installation Activities			

Status
➤ Δ B

NTTK31AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Release 25 English Documentation Package, Coil			W0

Qty	Order code	Description	Qty	Order code	Description
1	P0907446	Planning and Installation Guide	1	P0907449	Customer Configuration Backup and Restore (Coil)
1	P0907447	Fault and Clearing Guide	1	P0907450	Upgrade Guide
1	P0907448	Central Answering Position Guide	1	P0907451	Option 11C Administration & Maintenance I/O Guides

Status
➤ Δ S

NTTK32CB

Description	System Compatibility	Product compatibility	W/S
Option 11C Customer Documentation Library on CD-ROM, Release 25	11C		W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ N

NTTK33AB

Description	System Compatibility	Product compatibility	W/S
Option 11C Distributor Technical Library Package, Release 25			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTLH08AA	X11 Software Features Guide	1	P0910790	Technical Reference Guide, Release 25
1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide			

Status
★ ➤ S

NTTK45AA

Description	System Compatibility	Product compatibility	W/S
Option 11C 48MB Blank PCMCIA Memory Card Assembly			W0

Notes:

- This part replaces the A0633651 40MB PCMCIA memory card used on Option 11C and Option 11C Mini.

Status
✓ ➤ S

NTTS36AA

Description	System Compatibility	Product compatibility	W/S
External RSM Breakout Assembly (4 RS-232 Ports)			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTTK40AA	Meridian Mail Mini RS-232 Serial Module	1	NTTK44AA	RSM Cable

Status
★ ➤ S

NTTS50AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Mini Networking Package		Meridian Mail R12.14,13.12	W1

Qty	Order code	Description
1	NTAK37AA	Peripheral Cable Male
1	NTDK58AA	RSM 4 Port Breakout Cable
1	NTDK66AB	Meridian Mail Modem Package

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTTK40AA	Meridian Mail Mini RS-232 Serial Module	
1	NTTK44AA	RSM Cable	

Status
✓ S

NTUB14AB

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.06 Keycode Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	P0910030	Keycode, CallPilot 1 06

Status
✓ ➤ S

NTUB16AA

Description	System Compatibility	Product compatibility	W/S
CallPilot External Modem Kit			W1/ S1

Notes:

- 1 NTUB16AA External Modem Kit is included in the Base Systems of the IPE, Tower, and Rack Mount Systems.

Qty	Order code	Description	Qty	Order code	Description
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male	1	NTRH9016	External Modem 33 6

Status
➤ Δ S

NTUB24AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail to CallPilot Migration Utility Tape and Documentation			S1

Notes:

- The part is required to migrate from a Classic Meridian Mail to a CallPilot. Order 1 per system to be migrated.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTUB40AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Server Software CD			W0

Notes:
- This CD is included in the base CallPilot system package.

Status
★ ➤ S

NTUB41AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Administration Client CD			W0

Notes:
- This CD is included in the base CallPilot system package.

Status
★ ➤ S

NTUB42AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Desktop Messaging CD			W0

Notes:
- This CD is included in the base CallPilot system package.

Status
➤ S

NTUB43AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.0 Patch Software			S1

Notes:
- This item provides the latest software patches available for the CallPilot Systems.

Status
★ ➤ S

NTUB43AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 PEP Software CD			W0

Notes:
- This CD is included in the base CallPilot system package.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTUB44BC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Language Prompts CD Sets (3)			S1

Notes:
- This CD is included in the base CallPilot system package.

Status
★ ➤ S

NTUB45AC

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Web Messaging CD			W0

Notes:
- This CD is included in the base CallPilot system package.

Status
➤ S

NTUB46AB

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.06 Administration Client CD Assembly			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTRH8043	MAS Admin Client 1 06 SW	1	NTUB41AB	CallPilot 1 06 Admin Client CD

Status
✓ ➤ S

NTUB51AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Token Ring LAN Kit - IPE Systems			W1

Notes:
- Use this package to connect the CallPilot IPE System to a customer provided Token Ring LAN.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH1406	CallPilot Token Ring Cabling (IPE System)	1	NTRH9040	Callpilot Token Ring Adapter PCMCIA (IPE System)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTUB52AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Ethernet LAN Connection Kit - IPE Systems			W1

Notes:

- Use this package to connect a CallPilot IPE System to a customer provided Ethernet LAN.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH1405	CallPilot Internal Ethernet Cabling (IPE System)	1	NTRH9039	CallPilot Ethernet Adaptor PCMCIA (IPE System)

Status
✓ ➤ S

NTUB53AA

Description	System Compatibility	Product compatibility	W/S
CallPilot External Tape Drive - IPE Systems			W1/ S1

Notes:

- This package used with the CallPilot IPE System.

Qty	Order code	Description	Qty	Order code	Description
1	A0627875	Cleaning Cartridge	1	NTAK1305	SCSI Cable (6 Ft)
1	A0769312	SCSI Adapter	1	NTRH9038	CallPilot External SCSI Tape Drive, 4GB (IPE System)
1	A0780247	Data Cartridge			

Status
✓ ➤ S

NTUB54AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Recovery Kit - IPE			W1/ S1

Notes:

- This Kit used with CallPilot IPE Systems only.

Qty	Order code	Description	
1	NTRH9055	CallPilot ATA Drive with Programmed Flash	
1	NTUB59AA	CallPilot CD ROM Drive	
	Each Package Includes:		
	1	NTAK1305	SCSI Cable (6 Ft)
	1	NTRH9037	CallPilot CD ROM DRIVE

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTUB55AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Tower/Rack Internal Tape Drive Kit			W1

Notes:

- This package is used with CallPilot Tower and Rack Mount Systems.

Qty	Order code	Description	Qty	Order code	Description
1	A0677506	Dry Clean Cartridge	1	A0766997	Wide SCSI Terminator
1	A0677508	13GB Data Cartridge	1	A0788129	Shielded 9-Drop Wide SCSI Cable
1	A0684822	F/F Wide to Narrow SCSI Cable Adapter	1	NTRH9034	Backup Tape Drive
1	A0729069	M/M Wide-Nar SCSI Adapter			

Status
✓ ➤ S

NTUB56AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 14" Monitor Kit			W1/ S1

Notes:

- This package is optional for the CallPilot IPE System.
- 1 of this package is included in the CallPilot Tower System.
- The CallPilot Rack Mount system does not use this package. Order NTRH9011 14" Monitor and NTRH9048 Keyboard with built in Mouse for the Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9011	14 SVGA Color Monitor	1	NTRH9014	Three Button Mouse
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTUB57AB

Description	System Compatibility	Product compatibility	W/S
CallPilot MGate Kit			W1

Notes:

- This package is used with the Tower and Rack Mount Systems only.
- Base systems include 1 MGate card. Order an additional one when increasing capacity from 32 channels to 33 or greater, and from 64 channels to 65 or greater.

Qty	Order code	Description	Qty	Order code	Description
1	NTRB18CA	MGate Card	1	NTRH2013	Dual DSX30XV Interconnect Cable
1	NTRH2012	CallPilot MGate Cable - 20ft			

Status
✓➤ S

NTUB58AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 700 Series RAID Kit			W1

Notes:

- RAID kit option MUST be ordered with a new Tower system, it cannot be added later. RAID kit includes a RAID controller and 3 Disk Drives.

Qty	Order code	Description	Qty	Order code	Description
1	A0766997	Wide SCSI Terminator	1	NTRH9007	SCSI RAID Controller
1	A0788129	Shielded 9-Drop Wide SCSI Cable	1	NTRH9054	9 GB SCSI Disk

Status
✓➤ S

NTUB59AA

Description	System Compatibility	Product compatibility	W/S
CallPilot CD ROM Drive			W1/ S1

Notes:

- Used with CallPilot IPE Systems only.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK1305	SCSI Cable (6 Ft)	1	NTRH9037	CallPilot CD ROM DRIVE

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTUB60AB

Description	System Compatibility	Product compatibility	W/S
CallPilot MPB-16			W1

Notes:

- This package is used with the CallPilot Tower and Rack Mount System only.
- The MPB-16 comes with 16 MPUs equipped plus the connections for up to 4 each MPC-8 daughterboards. Each MPC-8 provides 8 MPUs. An MPB-16 equipped with 4 each MPC-8s provides 48 MPUs. The Rack Mount system comes equipped with one MPB-16 in the base system. A second MPB-16 needs to be added when a system requires more than 48 MPUs.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH2011	CallPilot MPB-16 Cable	1	NTRH20AB	CallPilot MPB-16

Status
★ ⊗ Δ S

NTUB71AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, 200i Token Ring LAN Option			W1

Notes:

- IPE Token Ring LAN kit supports 4 mbps only.

Qty	Order code	Description	
1	NTUB51AA	CallPilot Token Ring LAN Kit - IPE Systems	
	Each Package Includes:		
	1	NTRH1406	CallPilot Token Ring Cabling (IPE System)
	1	NTRH9040	Callpilot Token Ring Adapter PCMCIA (IPE System)

Status
★ ⊗ Δ S

NTUB72AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, 200i Ethernet LAN Option			W1

Notes:

- IPE Ethernet LAN kit supports 10BaseT only.

Qty	Order code	Description	
1	NTUB52AA	CallPilot Ethernet LAN Connection Kit - IPE Systems	
	Each Package Includes:		
	1	NTRH1405	CallPilot Internal Ethernet Cabling (IPE System)
	1	NTRH9039	CallPilot Ethernet Adaptor PCMCIA (IPE System)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ Δ S

NTUB73AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, 700/1000 Series Token Ring LAN Option			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9010	PCI Token Ring Network Card			

Status
★ ⊗ Δ S

NTUB74AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, 700/1000 Series Ethernet LAN Option			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9036	CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack			

Status
★ ➤ Δ S

NTUB80AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, MPC-8 - Expand Option (No Charge)			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH01AA	CallPilot MPC-8			

Status
★ ⊗ Δ S

NTUB81AA

Description	System Compatibility	Product compatibility	W/S
DSP Connectivity Package - Digitel			W1

Notes:

- Package provides 48 MPU of DSP capacity.

Qty	Order code	Description	Qty	Order code	Description
4	NTRH01AA	CallPilot MPC-8	1	NTRH20AB	CallPilot MPB-16

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ Δ S

NTUB83AA

Description	System Compatibility	Product compatibility	W/S
DSP Connectivity Option - MSL-100			W1

Notes:
- Package provides 48 MPU of DSP capacity.

Qty	Order code	Description	Qty	Order code	Description
4	NTRH01AA	CallPilot MPC-8	1	NTRH20BA	MPB 16-4

Status
★ ➤ S

NTUF24AA

Description	System Compatibility	Product compatibility	W/S
DMS SCCS Release 3 CD-ROM Document CD (Merchandise)	DMS-100		W0/ S1

Status
† S

NTV200AA

Description	System Compatibility	Product compatibility	W/S
Upgrade Package IIVR Release 1 to Release 2.2			W1

Notes:
- Meridian IVR Release 1 customers with the host communications option must also order the host communications option from the "Options" section.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description
1	A0386050	Keylock Software Security Device
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male
1	A0622896	OIVR 2 x Hardware - Tape Drive (2 5GB)
1	A0630697	Magnus 2 5GB Data Cartridge
1	A0639513	OIVR 2 X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)
1	A0737612	Barracuda 4 5GB 16Bit Ultra SCSI Disk Drive
4	A0739438	16 MB RAM for IIVR 2 2
4	A0741573	Peripheral Drive Rail
1	NT3R44AA	IVR Gen 2 0/I Development Software Upgrade from Release 1
1	NT3R51AA	IVR Operational Documentation Package
1	NT3R52AA	IVR Development Documentation Package

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NT7D61BB	Keylock Cable DB15(M)-DB25(F)
1	NTRH9005	SCSI CD-ROM Drive
1	NTRH9012	17" SVGA Color Monitor
1	NTRH9013	OIVR 2 x Hardware - Keyboard
1	NTRH9014	Three Button Mouse
1	NTRH9016	External Modem 33 6
1	NTRH9021	700t Entry Level Platform
1	NTV202AS	IIVR 2 2 BIOS 1 00 17 Update Diskette
1	NTV290AA	IIVR 2 2 OS/System Image & Application CD
1	NTV290AM	MIVR 2 2 Upissue Guide
1	NTV291AA	IIVR 2 2 System Voice Prompts Tape
1	NTV291AM	MIVR 2 2 Planning & Engineering Guide
1	NTV292AA	IIVR 2 2 Release Supplement CD
1	NTV293AA	IIVR 2 2 Boot Diskette
1	NTV294AA	IIVR 2 2 Root File System Diskette
1	NTVE6001	Serial Card - 16 Async Ports - Base Card
1	NTVE6008	Serial Card - 16 Async Ports - Expansion Module
1	NTVE8146	OPEN IVR 4 0 System Configuration Utility Vers 3 40 Overlay 1 03 for R2 AP, MRS/AP
12	P0206518	Drive Mounting Screw for CDROM and DAT Drive
12	P0670931	Hard Drive mounting screw for 1000rp and 1001r
1	P0843070	MIVR Software Reproduction
	Each Package Includes:	
	1	P0823114 Software Keycode Label
1	P0881234	SCO OpenServer 5 - Base - 1 User
1	P0881235	SCO OpenServer 5 - Development Option

Status
† S

NTV200BA

Description	System Compatibility	Product compatibility	W/S
Runtime System Upgrade Package Release 2.08 to Release 2.2			W1

Notes:

- Meridian IVR Release 2.08 customers that currently have the SNA host communications option and/or the UPS option must also order those options' upgrade packages from the "Options Upgrade" section.
- Meridian IVR Release 2.08 customers can and must use the Release 2.08 system keycode when upgrading to Integrated IVR Release 2.2.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge	1	NTV291AM	MIVR 2 2 Planning & Engineering Guide
1	A0737612	Barracuda 4 5GB 16Bit Ultra SCSI Disk Drive	1	NTV292AA	IIVR 2 2 Release Supplement CD
2	A0739438	16 MB RAM for IIVR 2 2	1	NTV293AA	IIVR 2 2 Boot Diskette
2	A0741573	Peripheral Drive Rail	1	NTV294AA	IIVR 2 2 Root File System Diskette

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9005	SCSI CD-ROM Drive	1	NTVE8146	OPEN IVR 4 0 System Configuration Utility Vers 3 40 Overlay 1 03 for R2 AP, MRS/AP
1	NTV202AS	IIVR 2 2 BIOS 1 00 17 Update Diskette	12	P0206518	Drive Mounting Screw for CDROM and DAT Drive
1	NTV290AA	IIVR 2 2 OS/System Image & Application CD	12	P0670931	Hard Drive mounting screw for 1000rp and 1001r
1	NTV290AM	MIVR 2 2 Upissue Guide	1	P0881234	SCO OpenServer 5 - Base - 1 User
1	NTV291AA	IIVR 2 2 System Voice Prompts Tape			

Status
† S

NTV200CA

Description	System Compatibility	Product compatibility	W/S
Development System Upgrade Package Release 2.08 to Release 2.2			W1

Notes:

- Meridian IVR Release 2.08 customers that currently have the SNA host communications option and/or the UPS option must also order those options' upgrade packages from the "Options Upgrade" section.
- Meridian IVR Release 2.08 customers can and must use the Release 2.08 system keycode when upgrading to Integrated IVR Release 2.2.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge	1	NTV291AM	MIVR 2 2 Planning & Engineering Guide
1	A0737612	Barracuda 4 5GB 16Bit Ultra SCSI Disk Drive	1	NTV292AA	IIVR 2 2 Release Supplement CD
2	A0739438	16 MB RAM for IIVR 2 2	1	NTV293AA	IIVR 2 2 Boot Diskette
2	A0741573	Peripheral Drive Rail	1	NTV294AA	IIVR 2 2 Root File System Diskette
1	NTRH9005	SCSI CD-ROM Drive	1	NTVE8146	OPEN IVR 4 0 System Configuration Utility Vers 3 40 Overlay 1 03 for R2 AP, MRS/AP
1	NTV202AS	IIVR 2 2 BIOS 1 00 17 Update Diskette	12	P0206518	Drive Mounting Screw for CDROM and DAT Drive
1	NTV290AA	IIVR 2 2 OS/System Image & Application CD	12	P0670931	Hard Drive mounting screw for 1000rp and 1001r
1	NTV290AM	MIVR 2 2 Upissue Guide	1	P0881234	SCO OpenServer 5 - Base - 1 User
1	NTV291AA	IIVR 2 2 System Voice Prompts Tape	1	P0881235	SCO OpenServer 5 - Development Option

Status
† ➤ S

NTV201AA

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Voice Port Expansion - 4 ports - Development System			W1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0902554	IIVR 2 2 Voice Port Expansion - 4 ports RTU - Development System			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTV201AB

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Voice Port Expansion - 4 ports - Runtime System			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0902555	IIVR 2 2 Voice Port Expansion - 4 ports RTU - Runtime System			

Status
† ➤ S

NTV201AC

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Runtime to Development Upgrade Base Package - 4 ports			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description
1	NT3R52AA	IVR Development Documentation Package
1	NTV201AD	IIVR 2 2 Runtime to Development Upgrade Expansion - 4 ports
	Each Package Includes:	
	1	P0902556 IIVR 2 2 Runtime to Development Upgrade Expansion - 4 ports RTU
1	P0881235	SCO OpenServer 5 - Development Option
1	P0902556	IIVR 2 2 Runtime to Development Upgrade Expansion - 4 ports RTU

Status
† ➤ S

NTV201AD

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0902556	IIVR 2 2 Runtime to Development Upgrade Expansion - 4 ports RTU			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† S

NTV201AE

Description	System Compatibility	Product compatibility	W/S
SNA (3270/5250) Host Connectivity Upgrade from Release 2.08 to Release 2.2			S3

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8132	OPEN IVR 4 0 Host Communications Software and Documentation Apertus SNA CD 1/1			

Status
† ➤ S

NTV201AQ

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Fax Response Hardware - 4 ports			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
4	A0346862	6-Conductor Line Cord (7 Ft for M2000 telephones requiring external power, standard for M3902, M3903, M3904, and M3905)	1	A0638637	Meridian IVR 4 Port FAX Hardware

Status
† ➤ S

NTV201AR

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Fax Response Software Base Package - 2 ports			S3

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTV201AS

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Fax Response Software Expansion - 1 port			S3

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
† S

NTV201AT

Description	System Compatibility	Product compatibility	W/S
UPS Software Upgrade from Release 2.08 to Release 2.2			W0

Notes:
- The Host Communications and UPS upgrades are only applicable to Meridian IVR 2.0/I customers that are upgrading to Integrated IVR 2.2. They must be ordered only if the MIVR 2.0/I system had the SNA Host Communications and/or the UPS option.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8108	Base Software Media (CD) - PowerChute			

Status
✓ † ➤ S

NTV201AU

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 UPS Package			W1

Notes:
- A keycode (P0843070) must also be ordered to activate the UPS feature. A keycode must be ordered if any of the items on a purchase order require a keycode for activation. Each order can have a maximum of one keycode.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)	1	NTVE8108	Base Software Media (CD) - PowerChute
1	A0656287	OIVR 2 x Hardware UPS for AP and MRS/AP			

Status
† ➤ S

NTV201AV

Description	System Compatibility	Product compatibility	W/S
Integrated IVR 2.2 Memory Package 32 MB			W1

Qty	Order code	Description	Qty	Order code	Description
2	A0739438	16 MB RAM for IIVR 2 2			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV201BA

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Supplementary Patch CD			W1

Notes:

- The purpose of the release supplement CD is to make available to Nortel's customers the latest fixes/enhancements to the product. Customers are strongly encouraged to consult Nortel's IVR bulletins for the latest fixes and enhancements to the IVR products.

Qty	Order code	Description	Qty	Order code	Description
1	NTV292AA	IIVR 2 2 Release Supplement CD			

Status
† ➤ S

NTV202AA

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Software Media			S3

Notes:

- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTV202AS	IIVR 2 2 BIOS 1 00 17 Update Diskette	1	NTV293AA	IIVR 2 2 Boot Diskette
1	NTV290AA	IIVR 2 2 OS/System Image & Application CD	1	NTV294AA	IIVR 2 2 Root File System Diskette
1	NTV291AA	IIVR 2 2 System Voice Prompts Tape	1	NTVE8146	OPEN IVR 4 0 System Configuration Utility Vers 3 40 Overlay 1 03 for R2 AP, MRS/AP
1	NTV292AA	IIVR 2 2 Release Supplement CD			

Status
† ➤ S

NTV202AB

Description	System Compatibility	Product compatibility	W/S
16MB RAM Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0739438	16 MB RAM for IIVR 2 2			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV202AC

Description	System Compatibility	Product compatibility	W/S
256KB L2 Async Cache Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0639530	OIVR 2 x Hardware - 256KB L2 Async Cache for AP or MRS/AP			

Status
✓ † ➤ S

NTV202AD

Description	System Compatibility	Product compatibility	W/S
1000VA UPS Hardware Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0656287	OIVR 2 x Hardware UPS for AP and MRS/AP			

Status
† ➤ S

NTV202AE

Description	System Compatibility	Product compatibility	W/S
512KB Video RAM Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0639513	OIVR 2 X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)			

Status
† ➤ S

NTV202AF

Description	System Compatibility	Product compatibility	W/S
Tape Backup Unit Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0622896	OIVR 2 x Hardware - Tape Drive (2 5GB)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

NTV202AH

Description	System Compatibility	Product compatibility	W/S
525W Power Supply Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0656847	OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP			

Status
† ➤ S

NTV202AJ

Description	System Compatibility	Product compatibility	W/S
Digi PC/Xem Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6001	Serial Card - 16 Async Ports - Base Card			

Status
† ➤ S

NTV202AK

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Fax Card Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0638637	Meridian IVR 4 Port FAX Hardware			

Status
† ➤ S

NTV202AL

Description	System Compatibility	Product compatibility	W/S
Floppy Drive Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0652239	OIVR 2 x Hardware - Floppy Drive, 3 5 In			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ Δ S

NTV202AM

Description	System Compatibility	Product compatibility	W/S
IIVR 2.2 Update Documentation Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTV290AM	MIVR 2 2 Upissue Guide	1	NTV291AM	MIVR 2 2 Planning & Engineering Guide

Status
† ➤ S

NTV202AP

Description	System Compatibility	Product compatibility	W/S
8 port DCE DB25 Octa Cable Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0651353	8 Port DCE DB25 Male Cable Used on Digiboard PC/8e 8 Port Communications Card			

Status
† ➤ S

NTV202AW

Description	System Compatibility	Product compatibility	W/S
4.5GB SCA UltraSCSI Hard Disk Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0737612	Barracuda 4 5GB 16Bit Ultra SCSI Disk Drive			

Status
† ➤ S

NTV202AY

Description	System Compatibility	Product compatibility	W/S
Modem Cable, 10 ft., DB9 Female to DB25 Male			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV400KA

Description	System Compatibility	Product compatibility	W/S
Keylock			W1

Notes:
- Compatible only with OPEN IVR 4.0 hardware and software.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6004	Keylock - Parallel Port			

Status
➤ S

NTV400LA

Description	System Compatibility	Product compatibility	W/S
License File			W1/ S2

Notes:
- Compatible with OPEN IVR 4.0 software.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8001	License File - Floppy			

Status
➤ S

NTV401PA

Description	System Compatibility	Product compatibility	W/S
Supplementary Patch CD			W0

Notes:
- Limit of 5 Supplementary Patch CDs per order.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV401SA

Description	System Compatibility	Product compatibility	W/S
System Recovery Boot Package			W1/ S2

Qty	Order code	Description	Qty	Order code	Description
1	NTV40100	System Recovery Boot Assembly			

Status
➤ Δ S

NTV402AA

Description	System Compatibility	Product compatibility	W/S
Base Documentation Package, North America			W0

Qty	Order code	Description	Qty	Order code	Description
1	NTV40210	Senior Level Assembly, Base Documentation, North America			

Status
➤ Δ S

NTV402CA

Description	System Compatibility	Product compatibility	W/S
Full Documentation Package (CD)			W1/ S2

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8226	SOIVR 4 0 - Full Documentation Package - CD			

Status
➤ S

NTV403EA

Description	System Compatibility	Product compatibility	W/S
Ethernet Adapter Kit			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0648379	25 Ft Ethernet Cable, Category 5	2	NTVE6006	Ethernet Tee Connector (Thinnet)
1	NTRH9009	PCI Ethernet Adapter	1	NTVE6007	Ethernet Cable (Thinnet, 50 Ft) and Terminator

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV404LA

Description	System Compatibility	Product compatibility	W/S
Monitor - 21"			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6005	Monitor - 21 SVGA Multisync			

Status
➤ S

NTV404MA

Description	System Compatibility	Product compatibility	W/S
Monitor - 17"			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9012	17 SVGA Color Monitor			

Status
➤ S

NTV404SA

Description	System Compatibility	Product compatibility	W/S
Monitor - 14"			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9011	14 SVGA Color Monitor			

Status
➤ S

NTV405UA

Description	System Compatibility	Product compatibility	W/S
Uninterruptible Power Supply (UPS) 110V - OIVR 4.0 Tower AP, MRS/AP, or MRS/ Tower		3X8 R5,7; Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6009	Uninterruptible Power Supply - 700 VAC - 110V - Tower	1	NTVE8108	Base Software Media (CD) - PowerChute

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV406CA

Description	System Compatibility	Product compatibility	W/S
SCSI CD-ROM Drive for AP, MRS/AP, MRS/Tower, MRS/Rack			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9005	SCSI CD-ROM Drive			

Status
➤ S

NTV406DA

Description	System Compatibility	Product compatibility	W/S
SCSI DAT Tape Drive for AP, MRS/AP, MRS/Tower, MRS/Rack			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9006	SCSI 3 5 DAT Tape Drive			

Status
➤ S

NTV406RA

Description	System Compatibility	Product compatibility	W/S
SCSI 4.5GB Hard Drive for OIVR 4.0 MRS/Rack and Rack AP		Open IVR R2,4	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0737612	Barracuda 4 5GB 16Bit Ultra SCSI Disk Drive	1	NTRH9003	4GB SCSI Hot Swap Disk Drive

Status
➤ S

NTV406TA

Description	System Compatibility	Product compatibility	W/S
SCSI 4.5GB Hard Drive for OIVR 4.0 Tower AP, MRS/AP, MRS/Tower		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0729948	4 5GB SCSI SCA Disk Drive	1	NTRH9030	4GB 16Bit Ultra SCSI Disk Drive

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV407MA

Description	System Compatibility	Product compatibility	W/S
64MB RAM Expansion for OIVR 4.0 AP, MRS/AP and MRS		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
2	A0684497	32MB Expansion RAM for MRS/Tower or MRS/Rack			

Status
➤ S

NTV410BA

Description	System Compatibility	Product compatibility	W/S
Base AP (700tp), 0 Port - Global			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter	1	NTV41000	Senior Level Assembly, Base AP Media
1	NTRH9013	OIVR 2 x Hardware - Keyboard	1	NTV41020	Senior Level Assembly, Base AP Software
1	NTRH9014	Three Button Mouse	1	NTV41040	Senior Level Assembly, Base AP (700tp) Hardware

Status
➤ S

NTV411NA

Description	System Compatibility	Product compatibility	W/S
Regional Supplement to Base AP - North America			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9016	External Modem 33 6	1	NTVE8226	SOIVR 4 0 - Full Documentation Package - CD
1	NTV40210	Senior Level Assembly, Base Documentation, North America			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV412RA

Description	System Compatibility	Product compatibility	W/S
AP Redundancy - 1 Voice Port RTU for 1 AP			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	P0881014	Redundant AP - Runtime - 1 Voice Port RTU			

Status
➤ S

NTV413AA

Description	System Compatibility	Product compatibility	W/S
Base AP/Rack, AC, Global			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter	1	NTV41310	Senior Level Assembly, Hardware For Base AP/Rack, AC
1	NTV41020	Senior Level Assembly, Base AP Software	1	NTV43000	Senior Level Assembly, Base MRS/Rack Media

Status
➤ S

NTV413DA

Description	System Compatibility	Product compatibility	W/S
Base AP/Rack, DC, Global			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter	1	NTV41330	Senior Level Assembly, Hardware for Base AP/Rack, DC
1	NTV41020	Senior Level Assembly, Base AP Software	1	NTV43000	Senior Level Assembly, Base MRS/Rack Media

Status
➤ S

NTV420AA

Description	System Compatibility	Product compatibility	W/S
Base MRS/Tower, 0 Port - Global			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTV42000	Senior Level Assembly, Base MRS/Tower Media	1	NTV42020	Senior Level Assembly, Base MRS/Tower Software
1	NTV42010	Senior Level Assembly, Base MRS/Tower Hardware			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV420KA

Description	System Compatibility	Product compatibility	W/S
Keyboard and Mouse for Base MRS/Tower			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter	1	NTRH9014	Three Button Mouse
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

Status
➤ S

NTV421NA

Description	System Compatibility	Product compatibility	W/S
Regional Supplement to Base MRS/Tower - North America			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9016	External Modem 33 6			

Status
➤ S

NTV430AA

Description	System Compatibility	Product compatibility	W/S
Base MRS/Rack, AC, 0 Port - Global			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTV43000	Senior Level Assembly, Base MRS/Rack Media	1	NTV43020	Senior Level Assembly, Base MRS/Rack (AC) Software
1	NTV43010	Senior Level Assembly, Base MRS/Rack (AC) Hardware			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV430DA

Description	System Compatibility	Product compatibility	W/S
Base MRS/Rack, DC, 0 Port - Global			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTV43000	Senior Level Assembly, Base MRS/Rack Media	1	NTV43040	Senior Level Assembly, Base MRS/RACK (DC) Software
1	NTV43030	Senior Level Assembly, Base MRS/RACK (DC) Hardware			

Status
➤ S

NTV430RA

Description	System Compatibility	Product compatibility	W/S
Redundant DC Power for Base MRS/Rack or Rack AP			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	A0723663	48V DC 400W Load Sharing Hot Swap Power Supply			

Status
➤ S

NTV430SA

Description	System Compatibility	Product compatibility	W/S
Redundant AC Power for Base MRS/Rack or Rack AP			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	A0681873	CallPilot Power Supply AC - Rack System			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV431NA

Description	System Compatibility	Product compatibility	W/S
Regional Supplement to Base MRS/Rack (AC or DC) - North America			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9016	External Modem 33 6			

Status
➤ S

NTV440BA

Description	System Compatibility	Product compatibility	W/S
Base MRS/AP (700tp), 0 Port - Global			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter	1	NTV44000	Senior Level Assembly, Base MRS/AP Media
1	NTRH9013	OIVR 2 x Hardware - Keyboard	1	NTV44020	Senior Level Assembly, Base MRS/AP Software
1	NTRH9014	Three Button Mouse	1	NTV44040	Senior Level Assembly, Base MRS/AP (700tp) Hardware

Status
➤ S

NTV441NA

Description	System Compatibility	Product compatibility	W/S
Regional Supplement to Base MRS/AP - North America			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9016	External Modem 33 6	1	NTVE8226	SOIVR 4 0 - Full Documentation Package - CD
1	NTV40210	Senior Level Assembly, Base Documentation, North America			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV450CA

Description	System Compatibility	Product compatibility	W/S
Custom Cell Builder RTU - 1 AP (or MRS/AP)			W1/S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV450LA

Description	System Compatibility	Product compatibility	W/S
Development License - 4 Users			S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	P0881235	SCO OpenServer 5 - Development Option	1	P0883267	Base AP - Direct Upgrade from Runtime to 4 Developer - 1 AP (or MRS/AP) RTU

Status
✓ ➤ S

NTV450MA

Description	System Compatibility	Product compatibility	W/S
Development License Upgrade - 1 to 4 Users			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV450PA

Description	System Compatibility	Product compatibility	W/S
Prompt Manager and Loading Tool - 1 AP (or MRS/AP)			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV450SA

Description	System Compatibility	Product compatibility	W/S
Development License - 1 User			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV452EA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Hardware - Ethernet Adapter Kit (For TN3270 or TN5250 Option)			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	A0648379	25 Ft Ethernet Cable, Category 5	1	NTVE6006	Ethernet Tee Connector (Thinnet)
1	NTRH9009	PCI Ethernet Adapter	1	NTVE6007	Ethernet Cable (Thinnet, 50 Ft) and Terminator

Status
➤ S

NTV452SA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option)			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6002	SDLC Card - 2 Sync Ports			

Status
➤ S

NTV452TA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Hardware - Token Ring Adapter Kit (For SNA3270 or SNA5250 Option)		Open IVR R4	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV452VA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6001	Serial Card - 16 Async Ports - Base Card			

Status
➤ S

NTV452WA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE6008	Serial Card - 16 Async Ports - Expansion Module			

Status
➤ S

NTV453AA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - SNA3270 - Base and 16 Session RTU			W1/ S1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8107	Base Software Media (CD) - Express			

Status
➤ S

NTV453BA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - TN3270 - Base and 16 Session RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8107	Base Software Media (CD) - Express			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV453SA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - SNA3270 - 16 Session RTU Expansion			W1/ S2

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV453TA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - TN3270 - 16 Session RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV454VA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - VT100 - 16 Session Base RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV454WA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - VT100 - 16 Session RTU Expansion			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV455AA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - SNA5250 - Base and 16 Session RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8107	Base Software Media (CD) - Express			

Status
✓ ➤ S

NTV455BA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - TN5250 - Base and 16 Session RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8107	Base Software Media (CD) - Express			

Status
✓ ➤ S

NTV455SA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - SNA5250 - 16 Session RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV455TA

Description	System Compatibility	Product compatibility	W/S
Host Connectivity Software - TN5250 - 16 Session RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV456AA

Description	System Compatibility	Product compatibility	W/S
Database Connectivity Software - INFORMIX - RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV456BA

Description	System Compatibility	Product compatibility	W/S
Database Connectivity Software - INGRES - RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV456CA

Description	System Compatibility	Product compatibility	W/S
Database Connectivity Software - ORACLE - RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV456DA

Description	System Compatibility	Product compatibility	W/S
Database Connectivity Software - SYBASE - RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV456MA

Description	System Compatibility	Product compatibility	W/S
Database Connectivity Software - Microsoft SQL Server - RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8145	OPEN IVR 4 0 Release X XX Supplement CD Version YYY 1/1	1	NTVE8181	SOIVR 4 0 - MSSQL Access Diskette for Windows NT

Status
✓➤ S

NTV457PA

Description	System Compatibility	Product compatibility	W/S
PureSpeech Recite Development Kit - 1 AP RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV457WA

Description	System Compatibility	Product compatibility	W/S
Web Integration Software - 1 AP RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV460AA

Description	System Compatibility	Product compatibility	W/S
ADSI License RTU - 1 AP (or MRS/AP)			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV460SA

Description	System Compatibility	Product compatibility	W/S
Software-Based Disk Mirroring License RTU - OIVR 4.0 AP, MRS, or MRS/AP		Open IVR R4	W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV461NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3017	Voice/Network Card - 16 Port Loopstart - North America	1	NTVE3035	Cable for 16 Port Loopstart Card

Status
✓ ➤ S

NTV461PA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America - Pulse Detection			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3018	Voice/Network Card - 16 Port Loopstart - North America - DPD	1	NTVE3035	Cable for 16 Port Loopstart Card

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV462NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3019	Voice/Network Card - 24 Port T1 - North America			

Status
➤ S

NTV462PA

Description	System Compatibility	Product compatibility	W/S
North American ISDN PRI Option for 24 Port T1 Card			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV462TA

Description	System Compatibility	Product compatibility	W/S
Line Side T1 Support - RTU For 24 Port T1 - Spanish			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV464NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3001	Voice/Network Card - 4 Port Loopstart - North America			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV464ZA

Description	System Compatibility	Product compatibility	W/S
Dial Pulse Detection for any 4 Port Loopstart Card			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV467LA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 12 Port Card and 12 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3033	GammaLink Fax - 12 Port Card			

Status
✓ ➤ S

NTV467MA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 6 Port Card and 6 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3032	GammaLink Fax - 6 Port Card			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV467SA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 4 Port Card and 4 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3031	GammaLink Fax - 4 Port Card			

Status
✓ ➤ S

NTV468CA

Description	System Compatibility	Product compatibility	W/S
Text to Speech - TrueVoice - Base Card and 2 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic	1	NTVE3023	DSP Card - Dongle - Centigram TrueVoice TTS

Status
✓ ➤ S

NTV468LA

Description	System Compatibility	Product compatibility	W/S
Text to Speech - L and H - Base Card and 6 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic	1	NTVE3024	DSP Card - Dongle - L & H TTS

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV468PA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - Continuous Digits - Base Card and 2 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
✓ ➤ S

NTV468QA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - Lite - Base Card and 2 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
✓ ➤ S

NTV468RA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - Pro - Base Card and 2 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV468SA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - IQ - Base Card and 2 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
✓ ➤ S

NTV468TA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - Base Card and 2 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
✓ ➤ S

NTV468UA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Lite - Base Card and 2 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV468VA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - VCS for Antares - Discrete - Base Card and 4 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic	1	NTVE3029	Antares-Based VCS ASR - Discrete - Dongle

Status
✓ ➤ S

NTV468WA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - VCS for Antares - Continuous - Base Card and 2 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic	1	NTVE3030	Antares-Based VCS ASR - Continuous - Dongle

Status
✓ ➤ S

NTV468YA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Pro - Base Card and 2 Port RTU			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV468ZA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - IQ - Base Card and 2 Port RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
✓ ➤ S

NTV469CA

Description	System Compatibility	Product compatibility	W/S
Text to Speech - TruVoice - 2 Port RTU Expansion			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469LA

Description	System Compatibility	Product compatibility	W/S
Text to Speech - L and H - 6 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469PA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech - Continuous Digits - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV469QA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - Lite - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469RA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - Pro - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469SA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - IQ - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469TA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV469UA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Lite - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469VA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - VCS for Antares - Discrete - 4 Port RTU Expansion			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469WA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - VCS for Antares - Continuous - 2 Port RTU Expansion			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
✓ ➤ S

NTV469YA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion			W1/ S1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTV469ZA

Description	System Compatibility	Product compatibility	W/S
Speech Recognition - PureSpeech Recite - LA Spanish - IQ - 2 Port RTU Expansion			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV472AA

Description	System Compatibility	Product compatibility	W/S
AC Rack Cabinet - Full Assembly			W1

Qty	Order code	Description	Qty	Order code	Description
2	A0727289	Power Bar - 6 Outlets - 2 Meter Cable	1	NTRH9014	Three Button Mouse
1	A0761985	Octopus Cable for 8 Port Switchbox	1	NTRH9044	Rackmount Keyboard Drawer
1	NTRE42AA	Cabinet Assembly	1	NTRH9045	19" Rackmount Monitor Enclosure
1	NTRH9011	14" SVGA Color Monitor	1	NTRH9046	8 Port System Peripheral Switch
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

Status
➤ S

NTV472BA

Description	System Compatibility	Product compatibility	W/S
AC Rack Cabinet - Expansion			W1

Qty	Order code	Description	Qty	Order code	Description
2	A0727289	Power Bar - 6 Outlets - 2 Meter Cable	1	NTRE42AA	Cabinet Assembly

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV472DA

Description	System Compatibility	Product compatibility	W/S
DC Rack Cabinet - Full Assembly			W1

Qty	Order code	Description	Qty	Order code	Description
2	A0676108	DC Power Supply for Rack Cabinet	1	NTRH9014	Three Button Mouse
1	A0761985	Octopus Cable for 8 Port Switchbox	1	NTRH9044	Rackmount Keyboard Drawer
1	NTRE42AA	Cabinet Assembly	1	NTRH9045	19" Rackmount Monitor Enclosure
1	NTRH9011	14" SVGA Color Monitor	1	NTRH9046	8 Port System Peripheral Switch
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

Status
➤ S

NTV472YA

Description	System Compatibility	Product compatibility	W/S
DC Rack Cabinet - Expansion			W1

Qty	Order code	Description	Qty	Order code	Description
2	A0676108	DC Power Supply for Rack Cabinet	1	NTRE42AA	Cabinet Assembly

Status
➤ S

NTV474NA

Description	System Compatibility	Product compatibility	W/S
(UPS) Shared Rack Model - 110V - Up to 4 MRS/Rack or AP/Rack Shelves			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTV481CA

Description	System Compatibility	Product compatibility	W/S
Software Upgrade - Open IVR 2.01/2.5 to 4.0 (PEB) - Media (CD) and 1 AP or MRS/AP RTU			W1

Notes:

- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge	1	NTVE8108	Base Software Media (CD) - PowerChute
2	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity	1	NTVE8117	Emergency Boot Floppy for SCSI ALAD
1	NTRH9005	SCSI CD-ROM Drive	1	NTVE8118	Emergency Root Floppy for SCSI ALAD
1	NTRH9030	4GB 16Bit Ultra SCSI Disk Drive	1	NTVE8119	Emergency Boot Floppy for SCSI AD
1	NTVE8101	Base Software Media (CD) - AP	1	NTVE8120	Emergency Root Floppy for SCSI AD
1	NTVE8102	Base Software Media (CD) - MRS	1	NTVE8121	Base Software Boot Floppy for CD
1	NTVE8103	Base Software Media (CD) - MRS/AP	1	NTVE8122	Base Software Boot Floppy for QIC/DAT
1	NTVE8104	Base Software Media (CD) - SCO	1	NTVE8123	Base Software Boot Floppy for Network QIC/DAT
1	NTVE8105	Base Software Media (CD) - SCO Documentation			

Status
S

NTV481DA

Description	System Compatibility	Product compatibility	W/S
Release 2.X Development to Release 4.0 Development Upgrade			S1

Notes:

- This package is required for any R2.X Development System facing upgrade to OPEN IVR 4.0. It basically upgrades the SCO Development Environment from that compatible with SCO 3.2V4.2 (as used in R2X) to that compatible with SCO3.2V5.0.4 (as used in R4.0).
- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0881235	SCO OpenServer 5 - Development Option			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

NTV481HA

Description	System Compatibility	Product compatibility	W/S
Software Upgrade - Host Connectivity Software Upgrade - R2 AP or MRS/AP			S3

Notes:
- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8132	OPEN IVR 4 0 Host Communications Software and Documentation Apertus SNA CD 1/1			

Status
S

NTV481LA

Description	System Compatibility	Product compatibility	W/S
Software Upgrade - OPEN IVR 2.01/2.5 to 4.0 (PEB) - L and H TTS Dongle Replacement			W1

Notes:
- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3024	DSP Card - Dongle - L & H TTS			

Status
➤ S

NTV481PA

Description	System Compatibility	Product compatibility	W/S
Pentium SBC Upgrade for PEB-based MRS			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
2	A0684497	32MB Expansion RAM for MRS/Tower or MRS/Rack	1	P0903050	Open IVR 4 0 MIT Boot Diskette 1/1 - Remote R2 Pentium MRS, SMC Ethernet, CD Installation/Tape Recovery
1	A0729069	M/M Wide-Nar SCSI Adapter	1	P0903051	Open IVR 4 0 MIT Boot Diskette 1/1 - Remote R2 Pentium MRS, Madge Token Ring, CD Installation/Tape Recovery
1	A0735228	233MHz MMX SBC Kit for 700tp/1000rp	1	P0903052	Open IVR 4 0 MIT Root Diskette 1/1 - R2 Pentium MRS, CD Installation/Tape Recovery
1	A0768284	Cable Keyboard and Reset Cable	1	P0903053	Emergency Root Diskette 1/1 - R2 Pentium MRS
1	A0773385	External SCSI 50-pin Connector Bracket and 8-bit External Terminator	1	P0903054	Emergency Boot Diskette 1/1 - R2 Pentium MRS
1	P0902768	Pentium Upgrade Document			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV481SA

Description	System Compatibility	Product compatibility	W/S
Software Upgrade - OPEN IVR 2.0/2.5 to 4.0 (PEB) - Serial Board Upgrade for R2 MRS with Speech Recognition Option			W1

Notes:
- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0686427	Serial I/O Board			

Status
S

NTV481UA

Description	System Compatibility	Product compatibility	W/S
Software Upgrade - UPS Software Upgrade - R2 AP, MRS/AP			S1

Notes:
- The IVR ID must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8108	Base Software Media (CD) - PowerChute			

Status
➤ S

NTV482MA

Description	System Compatibility	Product compatibility	W/S
Integration Package for Meridian Link - Media (CD) and 4 Port Base RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV482NA

Description	System Compatibility	Product compatibility	W/S
Integration Package for Meridian Link - 4 Port Expansion RTU			W1

Notes:
- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV482SA

Description	System Compatibility	Product compatibility	W/S
Integration Package for Meridian Link (SCCS Version) - Base and 4 Port RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Qty	Order code	Description	Qty	Order code	Description
1	NTVE8125	Integration Package for Symposium Link - Media			

Status
➤ S

NTV482TA

Description	System Compatibility	Product compatibility	W/S
Integration Package for Meridian Link (SCCS Version) - 4 Port Expansion RTU			W1

Notes:

- The IVR ID number must be provided if ordering this code for addition to an existing IVR system.

Status
➤ S

NTV491NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 16 Port Loopstart Spare - North America		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3017	Voice/Network Card - 16 Port Loopstart - North America			

Status
➤ S

NTV491PA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 16 Port Loopstart Spare - North America - PULSE DETECTION		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3018	Voice/Network Card - 16 Port Loopstart - North America - DPD			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV492NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 24 Port T1 Spare - North America			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3019	Voice/Network Card - 24 Port T1 - North America			

Status
➤ S

NTV494NA

Description	System Compatibility	Product compatibility	W/S
Voice Port Assembly - 4 Port Loopstart Spare - North America and CALA			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3001	Voice/Network Card - 4 Port Loopstart - North America			

Status
➤ S

NTV497LA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 12 Port Card Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3033	GammaLink Fax - 12 Port Card			

Status
➤ S

NTV497MA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 6 Port Card Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3032	GammaLink Fax - 6 Port Card			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTV497SA

Description	System Compatibility	Product compatibility	W/S
Fax - Gammalink - 4 Port Card Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3031	GammaLink Fax - 4 Port Card			

Status
➤ S

NTV498PA

Description	System Compatibility	Product compatibility	W/S
DSP Card Spare for Speech Recognition or Text-to-Speech			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTVE3022	DSP Card - Generic			

Status
➤ S

NTVA0002

Description	System Compatibility	Product compatibility	W/S
Assistant 100 User License		Meridian Mail Card Option R10; Meridian Mail EC R10; Meridian Mail EC11 R10; Meridian Mail Modular Option R10	S2

Qty	Order code	Description	Qty	Order code	Description
1	NTVA0201	Assistant Windows Client Interface	1	NTVA0302	Assistant 100 Client Software

Status
➤ S

NTVE9009

Description	System Compatibility	Product compatibility	W/S
PCI 10MB Ethernet Adapter Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9009	PCI Ethernet Adapter			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9013

Description	System Compatibility	Product compatibility	W/S
101 Enhanced Keyboard Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9013	OIVR 2 x Hardware - Keyboard			

Status
➤ S

NTVE9014

Description	System Compatibility	Product compatibility	W/S
3-Button Mouse Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9014	Three Button Mouse			

Status
➤ S

NTVE9016

Description	System Compatibility	Product compatibility	W/S
External Modem Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9016	External Modem 33 6			

Status
➤ S

NTVE9041

Description	System Compatibility	Product compatibility	W/S
PCI Video Adapter Spare for OIVR 4.0 AP, MRS/AP, or MRS		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9070	PCI Video Adapter			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9044

Description	System Compatibility	Product compatibility	W/S
Rackmount Keyboard Drawer Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9044	Rackmount Keyboard Drawer			

Status
➤ S

NTVE9045

Description	System Compatibility	Product compatibility	W/S
19" Rackmount Monitor Enclosure Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0722445	19 Rackmount Monitor Enclosure			

Status
➤ S

NTVE9901

Description	System Compatibility	Product compatibility	W/S
Ethernet Cable 25 Ft. Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0648379	25 Ft Ethernet Cable, Category 5			

Status
➤ S

NTVE9903

Description	System Compatibility	Product compatibility	W/S
32MB Expansion RAM for MRS/Tower or MRS/Rack Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0684497	32MB Expansion RAM for MRS/Tower or MRS/Rack			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9906

Description	System Compatibility	Product compatibility	W/S
Base Chassis for OIVR 4.0 Tower AP and MRS/Tower Spare		Open IVR R4	W1

Qty	Order code	Description	Qty	Order code	Description
1	A0686304	Base Chassis for MRS/Tower			

Status
➤ S

NTVE9907

Description	System Compatibility	Product compatibility	W/S
Base Single Board Computer for MRS/ Tower or MRS/Rack Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0683251	Base Single Board Computer for MRS/Tower or MRS/ Rack			

Status
➤ S

NTVE9909

Description	System Compatibility	Product compatibility	W/S
AT to PS/2 Keyboard Cable Adapter Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0685300	AT to PS/2 Keyboard Cable Adapter			

Status
➤ S

NTVE9910

Description	System Compatibility	Product compatibility	W/S
Wide SCSI Cable - 68 Pin Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0684753	68 pin Wide SCSI Cable			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9911

Description	System Compatibility	Product compatibility	W/S
Base Chassis for MRS/Rack - AC Power Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0683163	Base Chassis for MRS/Rack - AC Power			

Status
➤ S

NTVE9912

Description	System Compatibility	Product compatibility	W/S
System Peripheral Switch - 8 Way Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0722439	System Peripheral Switch - 8 Way			

Status
➤ S

NTVE9913

Description	System Compatibility	Product compatibility	W/S
Base Chassis for MRS/Rack - DC Power Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0723644	Base Chassis for MRS/Rack - DC Power			

Status
➤ S

NTVE9915

Description	System Compatibility	Product compatibility	W/S
Rackmount Cabinet for MRS/Rack - 21" Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0720967	Rackmount Cabinet for MRS/Rack - 21 Inch			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9917

Description	System Compatibility	Product compatibility	W/S
Front or Rear Door Kit for Rack Cabinet Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRE45AA	Front or Rear Door Kit for Rack Cabinet			

Status
➤ S

NTVE9919

Description	System Compatibility	Product compatibility	W/S
Power Bar - 6 Outlets - 2 Meters Cable Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0727289	Power Bar - 6 Outlets - 2 Meter Cable			

Status
➤ S

NTVE9921

Description	System Compatibility	Product compatibility	W/S
DC Power Supply for Rack Cabinet Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0676108	DC Power Supply for Rack Cabinet			

Status
➤ S

NTVE9923

Description	System Compatibility	Product compatibility	W/S
16MB Expansion RAM for OPEN IVR 2.x AP or MRS/AP Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9924

Description	System Compatibility	Product compatibility	W/S
Blank DAT Tape - 4/8GB Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0660538	Data Cartridge			

Status
➤ S

NTVE9925

Description	System Compatibility	Product compatibility	W/S
Blank QIC Tape - 2.5GB Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0630697	Magnus 2 5GB Data Cartridge			

Status
➤ S

NTVE9926

Description	System Compatibility	Product compatibility	W/S
Head Cleaner DAT Tape Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0627875	Cleaning Cartridge			

Status
➤ S

NTVE9927

Description	System Compatibility	Product compatibility	W/S
48V DC 400W Load Sharing Hot Swap Power Supply Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0723663	48V DC 400W Load Sharing Hot Swap Power Supply			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVE9928

Description	System Compatibility	Product compatibility	W/S
DC Power Cable for PS400-48 Power Supply Spare			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0725949	DC Power Cable for PS400-48 Power Supply			

Status
➤ S

NTVE9932

Description	System Compatibility	Product compatibility	W/S
Modem Cable Spare (DB9F to DB25M)			W1

Qty	Order code	Description	Qty	Order code	Description
1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male			

Status
➤ Δ S

NTVF44AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Documentation CD-ROM (Multilingual)	11C; 51C; 61C; 81; 81C	SYMPOSIUM Call Center Server (ICCM)	W0

Notes:
- This package includes Multilingual versions of selected documentation.
- This CD-ROM is compatible with both PC and Macintosh computers.

Status
➤ S

NTVM0036

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0 Mac Client Package - 100 Users		Meridian Mail Card Option R10,11; Meridian Mail EC R10,11; Meridian Mail Modular Option R10,11	S2

Notes:
- This option is only available for Installed-base customers. This option is not available for new system sales.

Qty	Order code	Description	Qty	Order code	Description
1	NTVM3201	Macintosh Client, Email, Fax and Voice Mail	1	NTVM3613	Messenger 100 Mailbox Software

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM0061

Description	System Compatibility	Product compatibility	W/S
Messenger 4.0 Windows Client Package - 25		Meridian Mail R11,12	S1

Qty	Order code	Description	
1	NTVM3304	Messenger 4 0 Windows Client CD (Programmed)	
	Each Package Includes:		
	1	A0647171	Raw-Blank CD-ROM Jewel Case
	1	NTVM4201	Messenger Proprietary Client Software
	1	NTVM4210	Messenger 4 0 Lotus Notes Server Software
	1	NTVM4211	Messenger 4 0 Lotus Notes Groupware Client Software
	1	NTVM4212	Messenger 4 0 MAPI Client Software
	1	NTVM4213	Messenger Web Client Software
1	NTVM3902	Messenger 25 User License Software	

Status
➤ S

NTVM00JB

Description	System Compatibility	Product compatibility	W/S
Messenger Fax on Demand Software		Messenger R2.0,3.0,4.0	S1

Notes:
- Compatible with Messenger 2.0/3.0/4.0 only.

Status
➤ S

NTVM00KA

Description	System Compatibility	Product compatibility	W/S
Uninterruptible Power Supply (UPS) Kit for Messenger Server		Messenger	W1

Notes:
- Recommended for orderly shut down only, does not provide reserve power.

Qty	Order code	Description	Qty	Order code	Description
1	A0626335	Powerchute Software	1	A0626706	APC Smart UPS with Cables and Documents

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM00SD

Description	System Compatibility	Product compatibility	W/S
Messenger Software Brooktrout Upgrade Kit 2.0/3.0 to 4.0		Messenger R4.0	S1

Qty	Order code	Description	
1	NTVM09AA	Meridian Link Handler Software	
1	NTVM10BC	Messenger Server Voice & Fax Messaging Software	
1	NTVM30AD	Messenger Brooktrout Fax Management Software	
1	NTVM3304	Messenger 4 0 Windows Client CD (Programmed)	
	Each Package Includes:		
	1	A0647171	Raw-Blank CD-ROM Jewel Case
	1	NTVM4201	Messenger Proprietary Client Software
	1	NTVM4210	Messenger 4 0 Lotus Notes Server Software
	1	NTVM4211	Messenger 4 0 Lotus Notes Groupware Client Software
	1	NTVM4212	Messenger 4 0 MAPI Client Software
	1	NTVM4213	Messenger Web Client Software
1	NTVM50AB	Messenger Telephone / DID Software	
1	NTVM50BB	Messenger Telephone Voice Prompt Software	
1	P0881354	Messenger 4 0 Administration Guide	

Status
➤ S

NTVM00SE

Description	System Compatibility	Product compatibility	W/S
Messenger Software Audiofax Upgrade Kit 2.0/3.0 to 4.0		Messenger R4.0	S1

Qty	Order code	Description	
1	NTVM09AA	Meridian Link Handler Software	
1	NTVM10BC	Messenger Server Voice & Fax Messaging Software	
1	NTVM30AE	Messenger 4 0 Fax Management Software-Audiofax	
1	NTVM3304	Messenger 4 0 Windows Client CD (Programmed)	
	Each Package Includes:		
	1	A0647171	Raw-Blank CD-ROM Jewel Case
	1	NTVM4201	Messenger Proprietary Client Software
	1	NTVM4210	Messenger 4 0 Lotus Notes Server Software
	1	NTVM4211	Messenger 4 0 Lotus Notes Groupware Client Software

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTVM4212	Messenger 4 0 MAPI Client Software
	1	NTVM4213	Messenger Web Client Software
1	NTVM50AB	Messenger Telephone / DID Software	
1	NTVM50BB	Messenger Telephone Voice Prompt Software	
1	P0881354	Messenger 4 0 Administration Guide	

Status
† ➤ Δ S

NTVM00SG

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (For Customers Under Maintenance or Warranty)			S1

Notes:
- Year 2000 Compliant Upgrade Kit.

Qty	Order code	Description	Qty	Order code	Description
1	NTVA09AA	Meridian Link Handler Software	1	NTVM4201	Messenger Proprietary Client Software
1	NTVM10BB	Messenger Voice & Fax Server Software	1	NTVM50AA	Messenger Telephone/DID Software
1	NTVM30AB	Fax Management Software	1	NTVM50BA	Telephone Voice Prompt Software

Status
† ➤ S

NTVM00SH

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (Customer Not Under Maintenance or Warranty)			S1

Notes:
- Year 2000 Compliant Upgrade Kit.

Qty	Order code	Description	Qty	Order code	Description
1	NTVA09AA	Meridian Link Handler Software	1	NTVM4201	Messenger Proprietary Client Software
1	NTVM10BB	Messenger Voice & Fax Server Software	1	NTVM50AA	Messenger Telephone/DID Software
1	NTVM30AB	Fax Management Software	1	NTVM50BA	Telephone Voice Prompt Software

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ Δ S

NTVM00SJ

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Under Maintenance or Warranty)			S1

Notes:
- Year 2000 Compliant Upgrade Kit.

Qty	Order code	Description	Qty	Order code	Description
1	NTVM10BB	Messenger Voice & Fax Server Software	1	NTVM50AA	Messenger Telephone/DID Software
1	NTVM30AC	Fax Management Software	1	NTVM50BA	Telephone Voice Prompt Software
1	NTVM4201	Messenger Proprietary Client Software			

Status
† ➤ S

NTVM00SK

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Not Under Maintenance or Warranty)			S1

Notes:
- Year 2000 Compliant Upgrade Kit.

Qty	Order code	Description	Qty	Order code	Description
1	NTVM10BB	Messenger Voice & Fax Server Software	1	NTVM50AA	Messenger Telephone/DID Software
1	NTVM30AC	Fax Management Software	1	NTVM50BA	Telephone Voice Prompt Software
1	NTVM4201	Messenger Proprietary Client Software			

Status
✓ ➤ S

NTVM00YA

Description	System Compatibility	Product compatibility	W/S
32 MB Memory Upgrade			W0

Notes:
- Compatible with Model 500 server only.

Qty	Order code	Description	Qty	Order code	Description
2	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM00YB

Description	System Compatibility	Product compatibility	W/S
64 MB Memory Upgrade Package			W1

Notes:
- If ordering for memory expansion on the Model 501 Server, ***ONLY 1*** can be ordered.

Qty	Order code	Description	Qty	Order code	Description
2	A0726884	32MB DRAM SIMM			

Status
➤ S

NTVM00ZF

Description	System Compatibility	Product compatibility	W/S
MAS Model 500 2GB Hard Drive Option			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9002	2GB SCSI SCA Disk Drive			

Status
➤ S

NTVM00ZG

Description	System Compatibility	Product compatibility	W/S
MAS Model 501 2GB Hard Drive Option			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTRH9029	2GB Ultra SCSI Disk Drive			

Status
➤ Δ S

NTVM0101

Description	System Compatibility	Product compatibility	W/S
Messenger Quick Reference Card - 25 Pack			W0/ S1

Notes:
- Recommended that the Quick Reference Cards be purchased in conjunction with Messenger 4.0 Client Packages.

Qty	Order code	Description	Qty	Order code	Description
1	P0881353	Messenger 4 0 Quick Reference Card			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTVM0103

Description	System Compatibility	Product compatibility	W/S
Messenger Quick Reference Card - 100 Pack			W0/ S1

Notes:

- Recommended that the Quick Reference Cards be purchased in conjunction with Messenger 4.0 Client Packages.

Qty	Order code	Description	Qty	Order code	Description
1	P0881353	Messenger 4 0 Quick Reference Card			

Status
➤ S

NTVM15BA

Description	System Compatibility	Product compatibility	W/S
Messenger 4.0 Server Software and 4 Port Card - Brooktrout		Meridian Mail Card Option R11,12; Meridian Mail EC R11,12; Meridian Mail Modular Option R11,12	S1

Qty	Order code	Description
1	NT5P41ZR	Brooktrout 4 Port Fax Card
1	NTVM09AA	Meridian Link Handler Software
1	NTVM10BC	Messenger Server Voice & Fax Messaging Software
1	NTVM30AD	Messenger Brooktrout Fax Management Software
1	NTVM50AB	Messenger Telephone / DID Software
1	NTVM50BB	Messenger Telephone Voice Prompt Software
1	NTVM60AA	Messenger Computer Based Training
	Each Package Includes:	
	1	NTVM6001 Administration Training CBT
1	P0881354	Messenger 4 0 Administration Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM15CA

Description	System Compatibility	Product compatibility	W/S
Messenger 4.0 Server Software Only Kit - Brooktrout			S1

Qty	Order code	Description	Qty	Order code	Description
1	NTVM09AA	Meridian Link Handler Software	1	NTVM50AB	Messenger Telephone / DID Software
1	NTVM10BC	Messenger Server Voice & Fax Messaging Software	1	NTVM50BB	Messenger Telephone Voice Prompt Software
1	NTVM30AD	Messenger Brooktrout Fax Management Software	1	P0881354	Messenger 4 0 Administration Guide

Status
✓➤ S

NTVM17AA

Description	System Compatibility	Product compatibility	W/S
Audiofax Server Software Only (Kit)			W0/ S1

Notes:

- Compatible with NTVM15AA Server Software only.
- Compatible with Model 100 & Model 500 servers only.

Qty	Order code	Description	Qty	Order code	Description
1	MM950005	Software Warranty Support	1	NTVM50AA	Messenger Telephone/DID Software
1	NTVA09AA	Meridian Link Handler Software	1	NTVM50BA	Telephone Voice Prompt Software
1	NTVM10BB	Messenger Voice & Fax Server Software	1	P0881354	Messenger 4 0 Administration Guide
1	NTVM30AB	Fax Management Software			

Status
➤ S

NTVM18AA

Description	System Compatibility	Product compatibility	W/S
MAS-Model 100 Spares Kit		Meridian Mail Card Option; Meridian Mail EC; Meridian Mail EC11; Meridian Mail Modular Option EC	W1

Notes:

- Compatible with NTVM12BB.

Qty	Order code	Description	Qty	Order code	Description
1	A0322493	Line Driver Telebyte 201M	1	A0653343	SCSI Adapter
1	A0622896	OIVR 2 x Hardware - Tape Drive (2 5GB)	2	A0653411	8 MB Dram Simm
1	A0626806	Telebyte 209 FP Line Driver	1	A0733483	2GB SCSI HD (Quantum Fireball)
1	A0653335	Intel Base Tower	1	MM950003	Warranty
1	A0653337	Video Card	1	P0835616	256K Cache Memory
1	A0653340	Serial Card			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM19AA

Description	System Compatibility	Product compatibility	W/S
MAS-Model 500 Spares Package		Meridian Mail Card Option; Meridian Mail EC; Meridian Mail EC11; Meridian Mail Modular Option	W1

Notes:

- Compatible with Model 500 server only.

Qty	Order code	Description	Qty	Order code	Description
1	A0322493	Line Driver Telebyte 201M	1	A0652781	Line Driver Female
1	A0622896	OIVR 2 x Hardware - Tape Drive (2 5GB)	1	A0672313	4 Port Digicard
1	A0638645	External Modem (14,400 bps, V 32 bis with V 42 bis)	1	MM950003	Warranty
1	A0639372	SCSI Disk Drive (1 05GB)	1	NTRH9021	700t Entry Level Platform

Status
➤ S

NTVM19AB

Description	System Compatibility	Product compatibility	W/S
MAS Model 501 Spares Kit			W0/ S1

Qty	Order code	Description	Qty	Order code	Description
1	A0322493	Line Driver Telebyte 201M	1	A0686371	Ngen 300p (Trimap)
1	A0622896	OIVR 2 x Hardware - Tape Drive (2 5GB)	1	NTRH9002	2GB SCSI SCA Disk Drive
1	A0652781	Line Driver Female	1	NTRH9029	2GB Ultra SCSI Disk Drive
1	A0653340	Serial Card	1	NTRH9042	SCSI Adapter
1	A0674453	33 6 KBPS External Data/Fax Modem	1	NTVM1002	Kit - boot floppies/emergency tapes for Messenger 4 0
1	A0683743	Video Card Adapter	1	P0866247	Nortel Logo, Intel Platform
1	A0686303	Baseboard	1	P0881238	MAS Model 501 Install Card (hard Copy)

Status
➤ S

NTVM4019

Description	System Compatibility	Product compatibility	W/S
Ethernet LAN Interface Board		Meridian Mail Card Option R10; Meridian Mail EC R10; Meridian Mail EC11 R10; Meridian Mail Modular Option R10	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVM4024

Description	System Compatibility	Product compatibility	W/S
Token Ring LAN Interface Board		Meridian Mail Card Option R10; Meridian Mail EC R10; Meridian Mail EC11 R10; Meridian Mail Modular Option R10	W1

Status
➤ S

NTVM60AA

Description	System Compatibility	Product compatibility	W/S
Messenger Computer Based Training		Messenger	S1

Qty	Order code	Description	Qty	Order code	Description
1	NTVM6001	Administration Training CBT			

Status
➤ S

NTVP1000

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Small (5 Channels)	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires X11 Release 20 software or later.
- To order spare MIRAN base cards, use order code NTAG36AB. NTVP1000 includes in package contents NTAG88AB which consists of the MIRAN base card with a software security device preloaded on the card. MIRAN base card spares are available without the software security device only.

Qty	Order code	Description	Qty	Order code	Description
1	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	1	P0885702	Meridian Integrated RAN (Release 2) NTP Guide
1	NTAG88AC	MIRAN (Release 2) Pack			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVP1001

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Medium (6 Channels)	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires X11 Release 20 software or later.
- To order spare MIRAN base cards, use order code NTAG36AB. NTVP1001 includes in package contents NTAG88AB which consists of the MIRAN base card with a software security device preloaded on the card. MIRAN base card spares are available without the software security device only.

Qty	Order code	Description	Qty	Order code	Description
1	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	1	P0885702	Meridian Integrated RAN (Release 2) NTP Guide
1	NTAG88AC	MIRAN (Release 2) Pack			

Status
➤ S

NTVP1002

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Large (10 Channels)	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires X11 Release 20 software or later.
- To order spare MIRAN base cards, use order code NTAG36AB. NTVP1002 includes in package contents NTAG88AB which consists of the MIRAN base card with a software security device preloaded on the card. MIRAN base card spares are available without the software security device only.

Qty	Order code	Description	Qty	Order code	Description
1	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	1	P0885702	Meridian Integrated RAN (Release 2) NTP Guide
1	NTAG88AC	MIRAN (Release 2) Pack			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTVP1010

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Small to Medium Upgrade	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires original NTVP1000 firmware load and security device identification number to be submitted to sales representative for NTVP1010 upgrade order processing.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0843071	Keycode Label			

Status
➤ S

NTVP1011

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Medium to Large Upgrade	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires original NTVP1001 firmware load and security device identification number to be submitted to sales representative for NTVP1011 upgrade order processing.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0843071	Keycode Label			

Status
➤ S

NTVP1012

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated RAN (Release 2) Small to Large Upgrade	11; 11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Notes:

- Requires original NTVP1000 firmware load and security device identification number to be submitted to sales representative for NTVP1012 upgrade order processing.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0843071	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTWE04AC

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Inter-Cabinet Cable 10 Ft. (Optional)	11C		W0

Notes:
- This cable is OPTIONAL for small systems packages with D-Channel for connecting to the LAN/WAN cable to the SDI/D-CH cable for Option 11C (cable is 10 feet in length and meant for expansion purposes).

Status
➤ S

NTWE04AD

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Intra-Cabinet Cable 1 Ft.	11C		W0

Notes:
- The cable is provided for small systems packages with D-Channel for connecting to the LAN/WAN cable to the SDI/D-CH cable for Option 11C (length is 1 foot).

Status
➤ S

NTWE07AA

Description	System Compatibility	Product compatibility	W/S
ITG 2.0 Pre-programmed Q.SIG D-Channel Interface PCMCIA Card	11C; 51C; 61C; 81; 81C		W0

Notes:
- Required for providing D-Channel capability to the 24-Port ITG 2.0 card.

Status
➤ Δ S

NTY210AA

Description	System Compatibility	Product compatibility	W/S
View Manager with 5 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY211AA

Description	System Compatibility	Product compatibility	W/S
View Manager with 25 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY212AA

Description	System Compatibility	Product compatibility	W/S
View Manager with 50 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY213AA

Description	System Compatibility	Product compatibility	W/S
View Manager with 100 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY214AA

Description	System Compatibility	Product compatibility	W/S
View Manager with 200 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY215AA

Description	System Compatibility	Product compatibility	W/S
View Manager with Greater than 200 User License			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY216AA

Description	System Compatibility	Product compatibility	W/S
View Manager Basic Technical Support			W0

Notes:
- First year's membership included in the purchase price of the View Manager server.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY217AA

Description	System Compatibility	Product compatibility	W/S
View Manager Elite Technical Support			W0

Notes:
- First year's membership is 15% of the View Manager server purchase price.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY218AA

Description	System Compatibility	Product compatibility	W/S
View Manager Custom Configuration			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY219AA

Description	System Compatibility	Product compatibility	W/S
View Manager OEM Configuration			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY220AA

Description	System Compatibility	Product compatibility	W/S
View Manager Documentation Set			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY221AA

Description	System Compatibility	Product compatibility	W/S
View Manager Quick Reference Guides			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY222AA

Description	System Compatibility	Product compatibility	W/S
View Manager Product Training			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY223AA

Description	System Compatibility	Product compatibility	W/S
View Manager Consulting and Professional Services			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY224AA

Description	System Compatibility	Product compatibility	W/S
View Manager Installation Services			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY230AA

Description	System Compatibility	Product compatibility	W/S
View Manager License Upgrade to 25 Users			W0

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY231AA

Description	System Compatibility	Product compatibility	W/S
View Manager License Upgrade to 50 Users			W0

Notes:
- Ownership of a 25 User license is a prerequisite to purchasing a license upgrade to 50 Users.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY232AA

Description	System Compatibility	Product compatibility	W/S
View Manager License Upgrade to 100 Users			W0

Notes:
- Ownership of a 50 User license is a prerequisite to purchasing a license upgrade to 100 Users.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY233AA

Description	System Compatibility	Product compatibility	W/S
View Manager License Upgrade to 200 Users			W0

Notes:
- Ownership of 100 User license is a prerequisite to purchasing a license upgrade to 200 Users.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY240AA

Description	System Compatibility	Product compatibility	W/S
APM, 1 Server/100 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY241AA

Description	System Compatibility	Product compatibility	W/S
APM, 10 Servers/1000 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY242AA

Description	System Compatibility	Product compatibility	W/S
APM, 25 Servers/2500 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY243AA

Description	System Compatibility	Product compatibility	W/S
APM, 100 Servers/5000 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY244AA

Description	System Compatibility	Product compatibility	W/S
APM, 250 Servers/10000 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY245AA

Description	System Compatibility	Product compatibility	W/S
APM, 500 Servers/25000 Seat Configuration			S2

Notes:
- Basic Support is mandatory in year one and is included in the CLP.
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY246AA

Description	System Compatibility	Product compatibility	W/S
APM, Custom Configurations			S2

Notes:
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY247AA

Description	System Compatibility	Product compatibility	W/S
APM, Unlimited Configuration			S2

Notes:
- APM runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY248AA

Description	System Compatibility	Product compatibility	W/S
APM, OEM Configuration			S2

Notes:
- APM runs on any Windows/NT PC or Unix workstation.
- Please direct pricing and order inquiries for these items to 1-800-4NORTEL.

Status
➤ Δ S

NTY250AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 1 Server/100 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY251AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 10 Servers/1000 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY252AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 25 Servers/2500 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY253AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 100 Servers/ 5000 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY254AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 250 Servers/ 10000 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY255AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, 500 Servers/ 25000 Seats			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY256AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, Custom Configuration			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY257AA

Description	System Compatibility	Product compatibility	W/S
Legacy Module for APM, Unlimited Configuration			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY260AA

Description	System Compatibility	Product compatibility	W/S
APM Upgrade, 1 Server/100 Seats to 10 Servers/1000 Seats			S2

Notes:
- Ownership of a 1 server/100 seat configuration license is a prerequisite to purchasing the 10 servers/1000 seats upgrade package.
- CLP includes Basic Support.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY261AA

Description	System Compatibility	Product compatibility	W/S
APM Upgrade, 10 Servers/1000 Seats to 25 Servers/2500 Seats			S2

Notes:
- Ownership of a 10 servers/1000 configuration license is a prerequisite to purchasing the 25 servers/2500 seats upgrade package.
- CLP includes Basic Support.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY262AA

Description	System Compatibility	Product compatibility	W/S
APM Upgrade, 25 Servers/2500 Seats to 100 Servers/5000 Seats			S2

Notes:
- Ownership of a 25 servers/2500 seat configuration license is a prerequisite to purchasing the 100 servers/5000 seats upgrade package.
- CLP includes Basic Support.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY263AA

Description	System Compatibility	Product compatibility	W/S
APM Upgrade, 100 Servers/5000 Seats to 250 Servers/10000 Seats			S2

Notes:
- Ownership of a 100 servers/5000 seat configuration license is a prerequisite to purchasing the 250 servers/10000 seats upgrade package.
- CLP includes Basic Support.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY264AA

Description	System Compatibility	Product compatibility	W/S
APM Upgrade, 250 Servers/10000 Seats to 500 Servers/25000 Seats			S2

Notes:
- Ownership of a 250 servers/10000 seat configuration license is a prerequisite to purchasing the 500 servers/25000 seats upgrade package.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY265AA

Description	System Compatibility	Product compatibility	W/S
APM Custom Upgrade			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY270AA

Description	System Compatibility	Product compatibility	W/S
APM, Installation (Mandatory Service, Performed by a Certified APM Installation Engineer)			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY271AA

Description	System Compatibility	Product compatibility	W/S
APM, Professional Services/System Integration/Consulting			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY272AA

Description	System Compatibility	Product compatibility	W/S
APM, Product Training			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY273AA

Description	System Compatibility	Product compatibility	W/S
APM, Full Documentation (Hardcopy)			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY274AA

Description	System Compatibility	Product compatibility	W/S
APM, Quick Reference Guides (Hardcopy)			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY275AA

Description	System Compatibility	Product compatibility	W/S
APM, Basic Membership Support Package, Renewed Annually			S2

Notes:
- Basic Support:
- 1. Telephone and email support
- - hours of support: 8:00am-5:00pm (EDT)
- - business days (exclude weekends and statutory holidays-Canada)
- 2. Telephone and email support up to 20 incidents during the year.
- 3. Unlimited telephone and email support in first month post installation sign-off.
- Customers must designate prime and alternate (name and telephone number) who will act as the communication link. At no time is the customer to use telephone support as a means to train agents or their employees.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTY276AA

Description	System Compatibility	Product compatibility	W/S
APM, Elite Membership Support Package, Renewed Annually			S2

Notes:
- Premium Support includes in addition to "Basic Membership":
- 1. Extended hours of support 8:00am-8:00pm (EDT)
- 2. Telephone & email support to resolve all incidents during the year.
- Customers must designate prime and alternate (name and telephone number) who will act as the communication link. At no time is the customer to use telephone support as a means to train agents or their employees.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY277AA

Description	System Compatibility	Product compatibility	W/S
APM, Service Provider Hosted Model			S2

Notes:
- Access Policy Manager runs on any Windows/NT PC or Unix workstation.
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

Status
➤ Δ S

NTY278AA

Description	System Compatibility	Product compatibility	W/S
View Manager for Hosted Service Provider			S2

Notes:
- Available through the Enterprise Solutions - Data Products Price Book, or call 1-800-367-0885 for further information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB01AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C which must be purchased separately.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZB01BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C which must be purchased separately.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB01CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 24 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C which must be purchased separately.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZB01DA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 32 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C which must be purchased separately.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB02AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 16 Port Upgrade	11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB02AA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB02BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 24 Port Upgrade	11C; 51C; 61C; 81; 81C		W0

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB02BA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB02CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 32 Port Upgrade	11C; 51C; 61C; 81; 81C		W0

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB02CA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB02DA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 to 24 Port Upgrade	11C; 51C; 61C; 81; 81C		W0

Notes:

- Requires NTZB01BA firmware load and dongle identification number to be submitted to sales representative for NTZB02DA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB02EA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 to 32 Port Upgrade	11C; 51C; 61C; 81; 81C		W0

Notes:

- Requires NTZB01BA firmware load and dongle identification number to be submitted to sales representative for NTZB02EA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB02FA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 24 to 32 Port Upgrade	11C; 51C; 61C; 81; 81C		W0

Notes:

- Requires NTZB01CA firmware load and dongle identification number to be submitted to sales representative for NTZB02FA upgrade order to be processed.
- The MIRAN Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB05AA

Description	System Compatibility	Product compatibility	W/S
Meridian Text Telephony System PC Client Package - 25 Users		Meridian Text Telephony System	S1

Notes:

- This order code is used to add 25 users to the MTTS. A key code will be supplied to increment the number of users on the system.
- The Meridian 1 Serial munber must be provided when ordering this code as an addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	P0882635	MTTS RTU 25 Users			

Status
➤ S

NTZB05BA

Description	System Compatibility	Product compatibility	W/S
Meridian Text Telephony System PC Client Package - 50 Users		Meridian Text Telephony System	S1

Notes:

- This order code is used to add 50 users to the MTTS. A key code will be supplied to increment the number of users on the system.
- The Meridian 1 Serial munber must be provided when ordering this code as an addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	P0882636	MTTS RTU 50 Users			

Status
➤ S

NTZB05CA

Description	System Compatibility	Product compatibility	W/S
Meridian Text Telephony System PC Client Package - 100 Users		Meridian Text Telephony System	S1

Notes:

- This order code is used to add 100 users to the MTTS. A key code will be supplied to increment the number of users on the system.
- The Meridian 1 Serial munber must be provided when ordering this code as an addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	P0882638	MTTS RTU 100 Users			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB05DA

Description	System Compatibility	Product compatibility	W/S
Meridian Text Telephony System PC Client Package - 250 Users		Meridian Text Telephony System	S1

Notes:

- This order code is used to add 250 users to the MTTS. A key code will be supplied to increment the number of users on the system.
- The Meridian 1 Serial munber must be provided when ordering this code as an addition to an existing Meridian 1 system.

Qty	Order code	Description	Qty	Order code	Description
1	P0882639	MTTS RTU 250 Users			

Status
➤ S

NTZB05MA

Description	System Compatibility	Product compatibility	W/S
Meridian Text Telephony System TDD/ TTY Modem			W0

Notes:

- This modem is used to increase the number of communications ports supported by the Meridian Text Telephony System.
- Requires an ISA slot in the MTTS server or an external modem shelf slot.
- Modem will come with a keycode that authorizes use in the MTTS system.

Qty	Order code	Description	Qty	Order code	Description
1	NT2R58AA	Meridian Text Telephony System TDD/TTY Modem	1	P0880331	KeyCode for Meridian Text Telephony System Modems

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB06AB

Description	System Compatibility	Product compatibility	W/S
Mini Local Package (Options 21-81)			W1

Notes:

- A NTZB09AA or NTZB08AA (Mini Remote Package AC or DC respectively) is required with this package and must be ordered separately.
- A Mini Local Package and Mini Remote Package can support up to 2 IPE card slots at the remote location. For additional IPE card capacity, add one (1) NT5D69AA or NT5D65AA (Local Mini Carrier Extender Card for Option 11 or Option 21-81 hosts) for each two additional IPE card slots required at the remote location. Extender cards must be ordered separately.
- Mini Carrier Remote can support up to 3 Local Mini Carrier Extender Cards.
- Add one (1) NT7R87BA (T-1 Link Cable Kit) for each T-1 link equipped if greater cable distance from the NT5D85AA (Local Mini Carrier Extender Cable) is required. The NT7R87BA is not included in this package and must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D64CA	Local Mini Carrier Interface Card (Options 21-81)	1	NT7R66BA	MMI Cable Kit (32 Ft)
1	NT5D85AA	Local Mini Carrier Interface Cable	1	P0878469	Mini Carrier Remote NTP
1	NT7R66AA	SDI Cable Kit (10 Ft)			

Status
➤ S

NTZB07AB

Description	System Compatibility	Product compatibility	W/S
Mini Local Package (Option 11)			W1

Notes:

- A NTZB09AA or NTZB08AA (Mini Remote Package AC or DC respectively) is required with this package and must be ordered separately.
- A Mini Local Package and Mini Remote Package can support up to 2 IPE card slots at the remote location. For additional IPE card capacity, add one (1) NT5D69AA or NT5D65AA (Local Mini Carrier Extender Card for Option 11 or Option 21-81 hosts) for each two additional IPE card slots required at the remote location. Extender cards must be ordered separately.
- Mini Carrier Remote can support up to 3 Local Mini Carrier Extender Cards.
- Add one (1) NT7R87BA (T-1 Link Cable Kit) for each T-1 link equipped if greater cable distance from the NT5D85AA (Local Mini Carrier Interface Cable) is required. The NT7R87BA must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D68CA	Local Mini Carrier Interface Card (Option 11)	1	NT7R66BA	MMI Cable Kit (32 Ft)
1	NT5D85AA	Local Mini Carrier Interface Cable	1	P0878469	Mini Carrier Remote NTP
1	NT7R66AA	SDI Cable Kit (10 Ft)			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB08AA

Description	System Compatibility	Product compatibility	W/S
Mini Remote Package AC			W1

Notes:

- One NTZB06AB or NTZB07AB (Mini-Carrier Local Package for Option 21-81 or Mini-Carrier Local Package Option 11) is required with this package and must be ordered separately.
- For each T1 link equipped between the local and remote site, order two NT7R87BA (T1 Cable Link Kit). The NT7R87BA is not included in this package and must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D67CA	Remote Mini Carrier Interface Card	1	NTAK98AA	Power Supply Cable
1	NT5D87AA	Remote Mini Carrier Interface Cable	1	NTDK78AA	AC/DC Power Supply
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	P0878469	Mini Carrier Remote NTP
1	NTAK11BD	Main/Expansion Cabinet			

Status
➤ S

NTZB09AA

Description	System Compatibility	Product compatibility	W/S
Mini Remote Package DC			W1

Notes:

- One NTZB06AB or NTZB07AB (Mini-Carrier Remote Local Package for Option 21-81 or Mini-Carrier Remote Local Package for Option 11) is required with this package and must be ordered separately.
- For each T1 link equipped between the local and remote site, order two NT7R87BA (T1 Cable Link Kit). The NT7R87BA is not included in this package and must be ordered separately.

Qty	Order code	Description	Qty	Order code	Description
1	NT5D67CA	Remote Mini Carrier Interface Card	1	NTAK28AB	Battery Junction Box
1	NT5D87AA	Remote Mini Carrier Interface Cable	1	NTDK72AA	DC/DC Power Supply
1	NT7R66BA	MMI Cable Kit (32 Ft)	1	P0878469	Mini Carrier Remote NTP
1	NTAK11BD	Main/Expansion Cabinet			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB11AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6A (1-19 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F27GA	FastView+ Software (Upgrade), Communicator Card, and Documentation			

Status
➤ S

NTZB11BB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6B (20-49 units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F27GA	FastView+ Software (Upgrade), Communicator Card, and Documentation			

Status
➤ S

NTZB11CB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6C (50+ Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F27GA	FastView+ Software (Upgrade), Communicator Card, and Documentation			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB13AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7A (1-19 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F65AB	FastView+ Software (New), Communicator Card, and Documentation			

Status
➤ S

NTZB13BB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7B (20-49 units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F65AB	FastView+ Software (New), Communicator Card, and Documentation			

Status
➤ S

NTZB13CB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7C (50+ Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F65AB	FastView+ Software (New), Communicator Card, and Documentation			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB15AB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8A (1-19 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F66AB	FastView+ Software (New), Communicator Card, M2216 and Documentation			

Status
➤ S

NTZB15BB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8B (20-49 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F66AB	FastView+ Software (New), Communicator Card, M2216 and Documentation			

Status
➤ S

NTZB15CB

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8C (50+ Units)			W1/ S2

Qty	Order code	Description	Qty	Order code	Description
1	NT1F66AB	FastView+ Software (New), Communicator Card, M2216 and Documentation			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB77AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Personal Call Director, 8 ports 50 users			W0

Notes:

- Requires X11 Release 17 software or later.
- 100 user maximum on card.
- Cannot configure less than 50 users with this card.
- To order spare MIPCD cards,use order code NT5G71AA. NTZB77AA includes in package contents NT5G71AA which consists of the MIPCD base card with a software security device preloaded on the card. MIPCD base card spares are available without the software only.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G53AB	MIPCD Kit	1	P0914163	MIPCD NTP Guide (English)
1	P0838515	Keycode Label	1	P0914505	MIPCD User Guide (English)

Status
✓ ➤ S

NTZB78AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Personal Call Director, 16 ports 100 users			W0

Notes:

- Requires X11 Release 17 software of later.
- 150 user maximum on card.
- Cannot configure less than 100 users with this card.
- To order spare MIPCD Cards, use order code NT5G71AA. NTZB78AA includes in package contents NT5G71AA which consists of the MIPCD base card with a software security device preloaded on the card. MIPCD base card spares are available without the software only.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G53AB	MIPCD Kit	1	P0914163	MIPCD NTP Guide (English)
1	P0838515	Keycode Label	1	P0914505	MIPCD User Guide (English)
1	P0886008	MIPCD 16 Ports RTU			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB79AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Personal Call Director, 24 ports 150 users			W0

Notes:

- Requires X11 Release 22 or later.
- 250 user maximum on card.
- Cannot configure less than 200 users with this card.
- To order spare MIPCD Cards, use order code NT5G71AA. NTZB80AA includes in package contents NT5G71AA which consists of the MIPCD base card with a software security device preloaded on the card. MIPCD base card spares are available without the software only.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G53AB	MIPCD Kit	1	P0914163	MIPCD NTP Guide (English)
1	P0838515	Keycode Label	1	P0914505	MIPCD User Guide (English)
1	P0886009	MIPCD 24 Ports RTU			

Status
✓ ➤ S

NTZB80AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Personal Call Director, 32 ports 200 users			W0

Notes:

- Requires X11 Release 22 or later.
- 300 user maximum on card.
- Cannot configure less than 200 users with this card.
- To order spare MIPCD Cards, use order code NT5G71AA. NTZB80AA includes in package contents NT5G71AA which consists of the MIPCD base card with a security device preloaded on the card. MIPCD base card spares are available without the software only.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G53AB	MIPCD Kit	1	P0914163	MIPCD NTP Guide (English)
1	P0838515	Keycode Label	1	P0914505	MIPCD User Guide (English)
1	P0886010	MIPCD 32 Ports RTU			

Status
➤ S

NTZB87AA

Description	System Compatibility	Product compatibility	W/S
MIPCD 50 Users Expansion			W0

Notes:

- Requires original MIPCD firmware load and security device identification number to be submitted to sales representative for NTZB88AA upgrade order processing.
- The Meridian Integrated Personal Call Director Security Device ID is required when ordering this code to expand an existing MIPCD application.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB88AA

Description	System Compatibility	Product compatibility	W/S
MIPCD 8 Port Upgrade			W0

Notes:

- Requires original MIPCD firmware load and security device identification number to be submitted to sales representative for NTZB88BA upgrade order processing.
- The Meridian Integrated Personal Call Director Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB88BA

Description	System Compatibility	Product compatibility	W/S
MIPCD 16 Port Upgrade			W0

Notes:

- Requires original MIPCD firmware load and security device identification number to be submitted to sales representative for NTZB88BA upgrade order processing.
- The Meridian Integrated Personal Call Director Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB88CA

Description	System Compatibility	Product compatibility	W/S
MIPCD 24 port Upgrade			W0

Notes:

- Requires original MIPCD firmware load and security device indentification number to be submitted to sales representative for NTZB88CA upgrade order processing.
- The Meridian Integrated Personal Call Director Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB91AA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 5 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB91BA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 8 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB91CA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 12 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB91DA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 16 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB91EA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 20 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB91FA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 24 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB91GA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 28 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB91HA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Hard Drive with 32 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G01AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB92AA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 5 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB92BA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 8 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB92CA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 12 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB92DA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 16 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB92EA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 20 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB92FA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 24 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
✓ ➤ S

NTZB92GA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 28 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZB92HA

Description	System Compatibility	Product compatibility	W/S
MICA PCMCIA Flash with 32 Ports			W1

Notes:

- Requires Ethernet Adapter (NT5D52AA for Options 51C-81C or NT5D52BA for Option 11C).
- MICA requires Software Release 19 or higher for the 5-16 port cards, while Software Release 22 or higher is required for 20, 24, 28 and 32 port cards.
- MICA requires software packages for support, depending on the application (auto attendant, ACD front-end call handler). Refer to the MICA NTP for specific application software requirements.

Qty	Order code	Description	Qty	Order code	Description
1	NT5G03AA	MICA Pack	1	P0885695	MICA NTP
1	P0838515	Keycode Label			

Status
➤ S

NTZB93AA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade add 3 ports			W1

Notes:

- The MICA Security Device ID is required when ordering this code.

Status
➤ S

NTZB93BA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade add 4 ports			W1

Notes:

- The MICA Security Device ID is required when ordering this code.

Status
➤ S

NTZB93CA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade add 8 ports			W1

Notes:

- The MICA Security Device ID is required when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB93DA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade add 16 ports			W1

Notes:
- The MICA Security Device ID is required when ordering this code.

Status
➤ S

NTZB93EA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade add 24 ports			W1

Notes:
- The MICA Security Device ID is required when ordering this code.

Status
✓ ➤ S

NTZB93FA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade Add 27 Ports			W0

Notes:
- The MICA Security Device ID is required when ordering this code.

Status
✓ ➤ S

NTZB93GA

Description	System Compatibility	Product compatibility	W/S
MICA Upgrade Add 12 Ports			W0

Notes:
- The MICA Security Device ID is required when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB94AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 42 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C and Enhanced ACD Overflow SW0222A which must be purchased separately.

Qty	Order code	Description	
2	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZB94BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 50 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C and Enhanced ACD Overflow SW0222A which must be purchased separately.

Qty	Order code	Description	
2	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB94CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 62 Port Card	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; SL-100	Meridian Integrated Conference Bridge	W1

Notes:

- Requires ACD/Message Processing SW0221C and Enhanced ACD Overflow SW0222A which must be purchased separately.

Qty	Order code	Description	
2	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZB95AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 42 Port Upgrade			W1

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB95AA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 50 Port Upgrade			W1

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB95BA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 12 to 62 Port Upgrade			W1

Notes:

- Requires NTZB01AA firmware load and dongle identification number to be submitted to sales representative for NTZB95CA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95DA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 to 42 Port Upgrade			W1

Notes:

- Requires NTZB01BA firmware load and dongle identification number to be submitted to sales representative for NTZB95DA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95EA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 to 50 Port Upgrade			W1

Notes:

- Requires NTZB01BA firmware load and dongle identification number to be submitted to sales representative for NTZB95EA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95FA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 16 to 62 Port Upgrade			W1

Notes:

- Requires NTZB01BA firmware load and dongle identification number to be submitted to sales representative for NTZB95FA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95GA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 24 to 42 Port Upgrade			W1

Notes:

- Requires NTZB01CA firmware load and dongle identification number to be submitted to sales representative for NTZB95GA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95HA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 24 to 50 Port Upgrade			W1

Notes:

- Requires NTZB01CA firmware load and dongle identification number to be submitted to sales representative for NTZB95HA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95JA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 24 to 62 Port Upgrade			W1

Notes:

- Requires NTZB01CA firmware load and dongle identification number to be submitted to sales representative for NTZB95JA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95KA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 32 to 42 Port Upgrade			W1

Notes:

- Requires NTZB01DA firmware load and dongle identification number to be submitted to sales representative for NTZB95KA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95LA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 32 to 50 Port Upgrade			W1

Notes:

- Requires NTZB01DA firmware load and dongle identification number to be submitted to sales representative for NTZB95LA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95MA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 32 to 62 Port Upgrade			W1

Notes:

- Requires NTZB01DA firmware load and dongle identification number to be submitted to sales representative for NTZB95MA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5G10AA	Meridian Integrated Conference Bridge (Rel 2) CD-ROM	
1	P0838515	Keycode Label	

Status
➤ S

NTZB95NA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 42 to 50 Port Upgrade			W1

Notes:

- Requires NTZB94AA firmware load and dongle identification number to be submitted to sales representative for NTZB95NA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZB95PA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 42 to 62 Port Upgrade			W1

Notes:

- Requires NTZB94AA firmware load and dongle identification number to be submitted to sales representative for NTZB95PA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB95QA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge (Release 2) 50 to 62 Port Upgrade			W1

Notes:

- Requires NTZB94BA firmware load and dongle identification number to be submitted to sales representative for NTZB95QA upgrade order to be processed.
- Requires Enhanced ACD Overflow SW0222A which must be purchased separately.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label			

Status
➤ S

NTZB96AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) PCMCIA Upgrade Kit			W1

Notes:

- Requires current MICB firmware load & dongle identification number to be submitted to sales representative for NTZB96AA upgrade order to be processed.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description
1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0838515	Keycode Label	
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZB96BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) Card Upgrade Kit			W1

Notes:

- Requires current MICB firmware load & dongle identification number to be submitted to sales representative for NTZB96BA upgrade order to be processed.
- The MICB Security Device ID is required when ordering this code.

Qty	Order code	Description	
1	NT5D32BB	MICB Kit	
	Each Package Includes:		
	1	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card
	1	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive
1	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	
	Each Package Includes:		
	20	P0889997	Meridian Integrated (Release 2) Quick Reference Card
1	P0838515	Keycode Label	
1	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	
1	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	

Status
➤ S

NTZC01AF

Description	System Compatibility	Product compatibility	W/S
MAT 6, End User Common Services	11; 11C; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; STE; XT; XT (QCA55)		S3

Notes:

- On CD-Rom Only.
- Contains: End-User Common Services and User Guides.
- Supports a single (1) Meridian 1 system.
- All modules require Common Services. All modules must be at the same MAT Release level.
- Contains one PC dongle.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTZC01BF

Description	System Compatibility	Product compatibility	W/S
MAT 6, Distributor Common Services	11; 11C; 11C COMPACT; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XT; XT (QCA55)		S3

Notes:

- On CD-Rom Only.
- Includes 25 PC dongles.
- Contains: Distributor Common Services and User Guide.
- All Modules require common services; all modules must be at same MAT Release level.
- Supports 500 Meridian 1 systems, for distributor use only.

Status
➤ S

NTZC02AA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Station Administration Module	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:

- Contains: Station Administration and User Guide.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC02BA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Traffic Analysis Module	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; ST X11 R14; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:
- Contains: Traffic Analysis and Users Guide.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC02CA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Tracking Module	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:
- Contains: Call Tracking and User Guide.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC02DA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Module	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:
- Contains: Call Accounting and User Guide.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC02EA

Description	System Compatibility	Product compatibility	W/S
MAT 6 ESN Analysis and Reporting Tool Module	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:
- Contains: ESN Analysis and Reporting and User Guide.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC02FA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Maintenance Windows Module	11C X11 R22,23; 51C X11 R22,23; 61C X11 R22,23; 81 X11 R22,23; 81C X11 R22,23		S3

Notes:
- Contains: Maintenance Windows and User Guide.
- Requires Common Services.
- Can only be used with X11 Release 22 or later systems.
- The MAT ID is required when ordering this code for addition to an existing MAT.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC02GA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Alarm Management Module	11C X11 R22,23; 51C X11 R22,23; 61C X11 R22,23; 81 X11 R22,23; 81C X11 R22,23		S3

Notes:
- Contains: Alarm Management and User Guide.
- Can only be used with X11 Release 22 or later systems.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
✓ ➤ Δ S

NTZC03AF

Description	System Compatibility	Product compatibility	W/S
MAT 6, User Guide and CD Package			W3/ S1

Notes:
- Contains MAT 6 User Guide, MAT 6 Installation and Upgrades User Guide, MAT 6 software, and General Release bulletin.
- Use this code to order an additional User Guide and/or copy of software CD (does not include keycode).

Status
➤ S

NTZC04AA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Maintenance Marketing Bundle	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:
- Contains: Alarm Management, ESN Analysis and Reporting, Maintenance Windows, and User Guides.
- Requires Common Services and X11 Release 22 or later.
- The MAT ID is required when ordering this code for addition to an existing MAT.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC04BA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Administration Marketing Bundle	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:

- Contains: Station Administration, Traffic Analysis, Call Accounting Base, Call Tracking, and User Guides.
- Requires Common Services.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC04CA

Description	System Compatibility	Product compatibility	W/S
MAT 6 System Management Marketing Bundle	11 X11 R21; 11C X11 R22,23; 21 X11 R17; 21E X11 R19,21; 51 X11 R17,19,21; 51C X11 R21,22,23; 61 X11 R17,19,21; 61C X11 R21,22,23; 71 X11 R17,19,21; 81 X11 R19,21,23; 81C X11 R21,22,23; NT X11 R17,19,21; RT X11 R17,19,21; STE X11 R19,21; XT X11 R17,19,21; XT (QCA55) X11 R17,19,21		S3

Notes:

- Contains: Station Administration, Traffic Analysis, ESN Analysis and Reporting, Maintenance Windows, Call Accounting Base, Alarm Management, Call Tracking, and User Guides.
- Requires Common Services and X11 Release 22 or later.
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC06AA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Station Administration Upgrade			S3

Notes:

- Contains: Station Administration Upgrade and User Guide.
- Requires Common Services Upgrade.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC06BA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Traffic Analysis Upgrade			S3

Notes:
- Contains: Traffic Analysis Upgrade and User Guide.
- Requires Common Services Upgrade.

Status
➤ S

NTZC06CA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Tracking Upgrade			S3

Notes:
- Contains Call Tracking Upgrade and User Guide.
- Requires Common Services Upgrade.

Status
➤ S

NTZC06DA

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Base Upgrade			S3

Notes:
- Contains Call Accounting Upgrade and User Guide.
- Must also order Call Accounting Expansion Upgrades to keycode correct DN level.
- Includes Rate Table, basic carriers US and Canada.

Status
➤ Δ S

NTZC07AF

Description	System Compatibility	Product compatibility	W/S
MAT 6, Distributor Single Location Common Services and Station Upgrade	11; 11C; 11E; 21; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XT; XT (QCA55)		S3

Notes:
- Upgrades Distributor Single Location on MAT Releases 1-4 to MAT Release 6.
- Includes Distributor Common Services, Station Administration and 25 PC Dongles.
- For Multi-location upgrade, please contact MAT Marketing.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

NTZC08AF

Description	System Compatibility	Product compatibility	W/S
MAT 5/6 to MAT 6.X, Flat Fee Upgrade	11; 11C; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; ST; STE; XT; XT (QCA55)		S3

Notes:

- Upgrades existing MAT Release 5/6 Customers to latest release of MAT 6. Upgrades all modules simultaneously via a flat fee. PC Dongles serial number must be provided when ordering.
- The MAT ID is required when ordering this code.

Status
✓ ➤ S

NTZC09AF

Description	System Compatibility	Product compatibility	W/S
MAT 6, End User Common Services Upgrade			W1/ S3

Notes:

- Contains End-User Common Services Upgrade and User Guide.
- Contains one PC Dongle.
- Upgrades MAT Release 3-4 users.
- All modules must be upgraded simultaneously.

Status
➤ S

NTZC10AF

Description	System Compatibility	Product compatibility	W/S
PC Dongle for One (1) PC and User Guide			W3

Notes:

- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC10BF

Description	System Compatibility	Product compatibility	W/S
PC Dongles for Five (5) PC and User Guides			W3

Notes:

- The MAT ID is required when ordering this code for addition to an existing MAT.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC10CF

Description	System Compatibility	Product compatibility	W/S
PC Dongles for Ten (10) PC and User Guides			W3

Notes:
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC10DF

Description	System Compatibility	Product compatibility	W/S
PC Dongles for Fifty (50) PC and 30 User Guides			W3

Notes:
- The MAT ID is required when ordering this code for addition to an existing MAT.

Status
➤ S

NTZC10EF

Description	System Compatibility	Product compatibility	W/S
PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides			W3

Notes:
- The MAT ID is required when ordering this code for addition to an existing MAT.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC12CA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Small and Large Systems Package	11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; STE; XT		W0

Notes:

- ITG package contains 8 port card, the appropriate cables and NTP.
- MAT Release 6.1 or later is a prerequisite and must be ordered separately.
- Meridian NT, RT, XT, and STE systems must be upgraded to support IPE shelves. The ITG card occupies 2 slots on the IPE shelf.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- Requires Release 21 or greater.

Qty	Order code	Description	
1	NTMF94DA	Meridian ITG Backplane and D-Sub Com Port Cable	
1	NTZC13BA	Meridian IP Telephony Gateway (ITG) Card	
	Each Package Includes:		
	1	NTWH90CA	Meridian IP Telephony Gateway (ITG) Card (Hardware)
	1	P0843071	Keycode Label
1	P0905051	Meridian IP Telephony Gateway (ITG) NTPs	

Status
➤ S

NTZC13BA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Card	11C; 11E; 21E; 51; 51C; 61; 61C; 71; 81; 81C; NT; RT; STE; XT		W0

Notes:

- MAT Release 6.1 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- Meridian NT, RT, XT, and STE systems must be upgraded to support IPE shelves. The ITG card occupies 2 slots on the IPE shelf.
- Requires Release 21 or greater.
- When used with any system requires cables NTMF94DA and NTAG81CA purchased separately.

Qty	Order code	Description	Qty	Order code	Description
1	NTWH90CA	Meridian IP Telephony Gateway (ITG) Card (Hardware)	1	P0843071	Keycode Label

Status
➤ S

NTZC14AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated IP Telephony Gateway (ITG) PCMCIA Card			W0

Notes:

- A PCMCIA card is only ordered when the customer needs an upissue.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC19AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telecommuter PCMCIA Card			W1

Notes:
- A PCMCIA card is only ordered when the customer needs an upissue.

Status
✓➤ S

NTZC35AA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 1 Console Bundle			S3

Notes:
- Provides Meridian 1 Attendant PC and Attendant Hospitality Services software for a one console configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NTZC36AA	Meridian 1 Attendant Hospitality Services 1 Console Software Bundle	1	NTZR07BA	Meridian 1 Attendant PC

Status
➤ S

NTZC35BA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 2 Console Bundle			S3

Notes:
- Provides Meridian 1 Attendant PCs, Attendant Hospitality Services software, and Attendant PC Interface Module for two console configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NTZC36BA	Meridian 1 Attendant Hospitality Services 2 Console Software Bundle	1	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module
1	NTZR07BA	Meridian 1 Attendant PC			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZC35CA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 3 Console Bundle			S3

Notes:

- Provides Meridian 1 Attendant PCs, Attendant Hospitality Services software, and Attendant PC Interface Module for a three console configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NTZC36CA	Meridian 1 Attendant Hospitality Services 3 Console Software Bundle	1	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module
1	NTZR07BA	Meridian 1 Attendant PC			

Status
✓ ➤ S

NTZC35DA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Large (4) Console Bundle			S3

Notes:

- Provides Meridian 1 Attendant PC, Attendant Hospitality Services software, and Attendant PC Interface Module for a four console configuration. Configurations greater than four consoles will build upon this bundle by adding the appropriate numbers of Large expansion bundles (NTZC35EA).

Qty	Order code	Description	Qty	Order code	Description
1	NTZC36DA	Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle	1	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module
1	NTZR07BA	Meridian 1 Attendant PC			

Status
✓ ➤ S

NTZC35EA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Large Expansion Bundle			S3

Notes:

- Provides Attendant PC and Attendant Hospitality Services software to add one console to a Large (4 or greater) console configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NTZC36EA	Meridian 1 Attendant Hospitality Services Large Software Expansion Bundle	1	NTZR07BA	Meridian 1 Attendant PC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZC36AA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 1 Console Software Bundle			S3

Notes:
- Provides Meridian 1 Attendant Hospitality Services software for a one console Attendant PC configuration.

Status
➤ S

NTZC36BA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 2 Console Software Bundle			S3

Notes:
- Provides Meridian 1 Attendant Hospitality Services software for a two console Attendant PC configuration.

Status
✓ ➤ S

NTZC36CA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services 3 Console Software Bundle			S3

Notes:
- Provides Meridian 1 Attendant Hospitality services software for a three console Attendant PC configuration.

Status
✓ ➤ S

NTZC36DA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle			S3

Notes:
- Provides Meridian 1 Attendant Hospitality Services software for a four console Attendant PC configuration.
- Configurations larger than 4 consoles must use this bundle as a building block by adding the appropriate number of Large software expansion bundles (NTZC36EA) and associated Attendant PC units.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC36EA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Large Software Expansion Bundle			S3

Notes:

- Provides Meridian 1 Attendant Hospitality Services software to support the addition of one Attendant PC added to a Large (4) Console Bundle to build larger configurations. One Large Software Expansion Bundle is required for each Attendant PC to be added.

Status
➤ S

NTZC37AA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Software for Expansion from 1 to 2 Console Bundle			S3

Notes:

- Provides Meridian 1 Attendant Hospitality Services software to expand from a 1 console to a 2 console configuration.

Status
✓ ➤ S

NTZC37BA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Software for Expansion from 2 to 3 Console Bundle			S3

Notes:

- Provides Meridian 1 Attendant Hospitality Services software to expand from a 2 console to a 3 console configuration.

Status
✓ ➤ S

NTZC37CA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant Hospitality Services Software for Expansion from 3 to 4 Console Bundle			S3

Notes:

- Provides Meridian 1 Attendant Hospitality Services software to expand from a 3 console to a 4 console configuration.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC44AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 ISDN Large Systems Package	51C; 61C; 81; 81C		W1

Notes:

- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- ISDN software must be configured to enable ISDN features. System must be equipped with a minimum of ISDN Signaling Link. Additional software may be required for enhanced ISDN networking software services.
- Requires an unused D-Channel port on the MSDL card for large systems.
- Requires Release 25 or greater.
- ITG card occupies 2 slots on the IPE shelf.

Qty	Order code	Description	Qty	Order code	Description
1	NT0961AA	Meridian ITG 2 0 Pentium 24 Port Card	1	NTCW84KA	Meridian ITG 2 0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter
1	NTAG81CA	PC Maintenance Cable	1	NTND26AA	MSDL DCHI Interface Cable (6 Ft)
1	NTCW84EA	Meridian ITG 2 0 D-Channel PCMCIA Pigtail Cable	1	NTWE07AA	ITG 2 0 Pre-programmed Q SIG D-Channel Interface PCMCIA Card
1	NTCW84JA	Meridian ITG 2 0 I/O Panel Mounting Connector	1	P0906569	Meridian ITG 2 0 NTP

Status
➤ S

NTZC44BA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 ISDN Small Systems Package	11C		W1

Notes:

- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- ISDN software must be configured to enable ISDN features. System must be equipped with a minimum of ISDN Signaling Link. Additional software may be required for enhanced ISDN networking software services.
- Requires an unused D-Channel port on the SDI/D-CH card for Option 11C.
- Requires Release 25 or greater.
- ITG card occupies 2 slots on the IPE shelf.

Qty	Order code	Description	Qty	Order code	Description
1	NT0961AA	Meridian ITG 2 0 Pentium 24 Port Card	1	NTCW84KA	Meridian ITG 2 0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter
1	NTAG81CA	PC Maintenance Cable	1	NTWE04AD	Meridian ITG 2 0 Intra-Cabinet Cable 1 Ft
1	NTAK19FB	4 Port SDI Cable	1	NTWE07AA	ITG 2 0 Pre-programmed Q SIG D-Channel Interface PCMCIA Card
1	NTCW84EA	Meridian ITG 2 0 D-Channel PCMCIA Pigtail Cable	1	P0906569	Meridian ITG 2 0 NTP

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC45AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Small and Large Systems 24-Port Package	11C; 51C; 61C; 81; 81C		W1

Notes:

- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- Requires Release 25 or greater.
- ITG card occupies 2 slots on the IPE shelf.
- Package does not contain any D-Channel capability or NTP.

Qty	Order code	Description	Qty	Order code	Description
1	NT0961AA	Meridian ITG 2 0 Pentium 24 Port Card	1	NTMF94EA	Meridian ITG 2 0 ELAN, TLAN, RS232 Port Cable
1	NTCW84JA	Meridian ITG 2 0 I/O Panel Mounting Connector			

Status
➤ S

NTZC47AA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Large Systems Upgrade Kit from ITG 1.0 to ITG 2.0	51C; 61C; 81; 81C		W1

Notes:

- The upgrade kit applies to ITG 8-port cards that are to be upgraded to support ISDN functionality.
- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- ISDN software must be configured to enable ISDN features. System must be equipped with a minimum of ISDN Signaling Link. Additional software may be required for enhanced ISDN networking software services.
- Requires an unused D-Channel port on the MSDL card for large systems.
- Requires Release 25 or greater.

Qty	Order code	Description	Qty	Order code	Description
1	NTCW84EA	Meridian ITG 2 0 D-Channel PCMCIA Pigtail Cable	1	NTND26AA	MSDL DCHI Interface Cable (6 Ft)
1	NTCW84LA	Meridian ITG 2 0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA)	1	NTWE07AA	ITG 2 0 Pre-programmed Q SIG D-Channel Interface PCMCIA Card
1	NTCW84MA	Meridian ITG 2 0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack	1	P0906569	Meridian ITG 2 0 NTP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC47BA

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 Small Systems Upgrade Kit from ITG 1.0 to ITG 2.0	11C		W1

Notes:

- The upgrade kit applies to ITG 8-port cards that are to be upgraded to support ISDN functionality.
- MAT Release 6.6 or later is a prerequisite and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms from the ITG card.
- ISDN software must be configured to enable ISDN features. System must be equipped with a minimum of ISDN Signaling Link. Additional software may be required for enhanced ISDN networking software services.
- Requires and unused D-Channel port on the SDI/D-CH card for Option 11C.
- Requires Release 25 or greater.

Qty	Order code	Description	Qty	Order code	Description
1	NTAK19FB	4 Port SDI Cable	1	NTWE04AD	Meridian ITG 2 0 Intra-Cabinet Cable 1 Ft
1	NTCW84EA	Meridian ITG 2 0 D-Channel PCMCIA Pigtail Cable	1	NTWE07AA	ITG 2 0 Pre-programmed Q SIG D-Channel Interface PCMCIA Card
1	NTCW84LA	Meridian ITG 2 0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA)	1	P0906569	Meridian ITG 2 0 NTP
1	NTCW84MA	Meridian ITG 2 0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack			

Status
§ ➤ S

NTZC49AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Card Option 4-12 Ports, 5/10/24/54 Hours Package		Meridian Mail Card Option R12	W1

Notes:

- This package contains four (4) ports and the associated Full Service Port License Fees.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZC57AA).
- For expansion above four (4) ports, order the appropriate Voice Processing Packages.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R16AA	Enhanced Processor for Card Option Systems	4	SW7105	Meridian Mail Card Option Full Service Port License Fee
1	NTDK74AB	Card Option 4 5GB Disk Drive			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC50AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Card Option 2 Basic Service Ports - Ports 5 and 6 or 9 and 10			W1

Notes:

- This package can only be used on Enhanced Card Option systems.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW03AA	4-Port DSP Daughter Card			

Status
➤ S

NTZC50BA

Description	System Compatibility	Product compatibility	W/S
Enhanced Card Option 2 Basic Service Ports - Ports 7 and 8 or 11 and 12			W0

Notes:

- This package can only be used on Enhanced Card Option systems.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail system. If ordering as part of a new Meridian Mail system for an existing Option 11 Site ID is required.

Status
➤ S

NTZC51AA

Description	System Compatibility	Product compatibility	W/S
2 Full Services Ports - Ports 5 & 6 or 9 & 10			W0/ S1

Notes:

- This package used only with the Enhanced Card Option systems.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail system. If ordering as part of a new Meridian Mail system for an existing Option 11 Site ID is required.

Qty	Order code	Description	Qty	Order code	Description
1	NTMW03AA	4-Port DSP Daughter Card	2	SW7105	Meridian Mail Card Option Full Service Port License Fee

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC51BA

Description	System Compatibility	Product compatibility	W/S
2 Full Service Ports - Ports 3 & 4, 7 & 8 or 11 & 12			W0/ S1

Notes:

- This package is only used with Enhanced Card Option systems.
- Ports 3 & 4, 7 & 8, 11 & 12 order NTZC51BA. Ports 5 & 6, 9 & 10 require NTZC51AA.
- The Meridian Mail serial number must be provided when ordering this code as an addition to an existing Meridian Mail system. If ordering as part of a new Meridian Mail system for an existing Option 11 Site ID is required.

Qty	Order code	Description	Qty	Order code	Description
2	SW7105	Meridian Mail Card Option Full Service Port License Fee			

Status
➤ S

NTZC52AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC11 1 to 2 Node Expansion Package		Meridian Mail EC11	W1

Notes:

- This package is used only with the Enhanced EC11 system.
- An MGate Card is required for every 16 ports of voice mail. Order additional cards as required.
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	NT6R15AA	Enhanced Processor for Meridian Mail EC

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC53AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package AC		Meridian Mail Modular EC	W1

Notes:

- This package is used only with Enhanced EC systems.
- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 3 node system to 4 nodes, and Shadowed; 2 node system to 3 nodes and 4 node system to 5 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R15AA	Enhanced Processor for Meridian Mail EC
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01BA	Meridian Mail EC Module AC	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

NTZC53BA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package DC		Meridian Mail Modular EC	W1

Notes:

- This package is used only with Enhanced EC systems.
- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 3 node system to 4 nodes, and Shadowed; 2 node system to 3 nodes and 4 node system to 5 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6R15AA	Enhanced Processor for Meridian Mail EC
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	1	NT7D06AA	Filler Panel
1	NT6P01AA	Meridian Mail EC Module DC	1	P0834803	Installation Instructions (Jumper)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC54AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package AC		Meridian Mail Modular EC	W1

Notes:

- This package is used only for Enhanced EC systems.
- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 1 node system to 2 nodes and 4 node system to 5 nodes, and Shadowed; 3 node system to 4 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R15AA	Enhanced Processor for Meridian Mail EC
2	NT6P0123	Backplane to I/O Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	1	P0834803	Installation Instructions (Jumper)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC54BA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package DC		Meridian Mail Modular EC	W1

Notes:

- This package is used only with Enhanced EC systems.
- If expanding to a 4 node system greater than 48 ports, one (1) NT6P42AA Utility Card is required.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- This package is ordered for the following situations: Unshadowed; 1 node system to 2 nodes and 4 node system to 5 nodes, and Shadowed; 3 node system to 4 nodes. (NOTE: the added node is unshadowed. To shadow the added node, an NT6P44BA Meridian Mail Modular EC 2.0GB Hard Drive with Power is required.)
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6R15AA	Enhanced Processor for Meridian Mail EC
2	NT6P0123	Backplane to I/O Cable	1	P0834803	Installation Instructions (Jumper)

Status
➤ S

NTZC55AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular EC Node Expansion 3rd Position Package		Meridian Mail Modular Option EC	W1

Notes:

- This package is used only with Enhanced EC systems.
- If expanding to a 4th node or beyond 48 ports, one additional QPC414 Network card should be ordered to provide additional network loop(s).
- Expansions can only be performed on MMP40 based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- This package is ordered for the following situations: Unshadowed: 2 node system to 3 nodes.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R15AA	Enhanced Processor for Meridian Mail EC
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	1	P0834803	Installation Instructions (Jumper)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC56AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- This package is used only for Enhanced GP systems.
- Two node Release 9 and later systems support from 16-24 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D4419	RS232-Y Cable
1	NT4R10AA	HABC Terminator	1	NT6D44BA	Meridian Mail Module DC
1	NT4R11AA	ESBC Terminator	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D4407	GSP Cable	1	NT7D06AA	Filler Panel
2	NT6D4411	DVS Bus Cable (57 Inches)	2	NT9D18AA	Module Side Cover
1	NT6D4417	SCSI/Backplane Cable	1	P0803252	Designation Strip

Status
➤ S

NTZC56BA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- This package is only used with Enhanced GP systems.
- Three node Release 9 and later systems support from 28-32 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	Qty	Order code	Description
1	NT6D4407	GSP Cable	2	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	NT9D18AA	Module Side Cover
1	NT6D4419	RS232-Y Cable	2	P0803252	Designation Strip
1	NT6D44BA	Meridian Mail Module DC	1	P0834803	Installation Instructions (Jumper)
1	NT6D48FA	4 5GB Modular Hard Disk Drive			

Status
➤ S

NTZC56CA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- This package is used only with Enhanced GP systems.
- Four node Release 9 and later systems support from 36-48 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4407	GSP Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	NT9D18AA	Module Side Cover
1	NT6D4419	RS232-Y Cable	2	P0803252	Designation Strip
1	NT6D44BA	Meridian Mail Module DC	1	P0834803	Installation Instructions (Jumper)
1	NT6D48FA	4 5GB Modular Hard Disk Drive			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC56DA

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC		Meridian Mail Modular GP	W1

Notes:

- This package is used only with Enhanced GP systems.
- Five node Release 9 and later systems support from 52-64 ports.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT7D00BA	Top Cap DC
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4407	GSP Cable	1	NT8D22AC	System Monitor
1	NT6D4411	DVS Bus Cable (57 Inches)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4412	DVS Bus Cable (Internal) (132 Inches)	1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT6D4417	SCSI/Backplane Cable	1	NT8D46BH	System Monitor to MDF Cable (32 Ft)
1	NT6D4419	RS232-Y Cable	1	NT8D49AA	Column Spacer Kit (2 75 In)
1	NT6D44BA	Meridian Mail Module DC	1	NTRD25BA	Pedestal Assembly DC
1	NT6D48FA	4 5GB Modular Hard Disk Drive	2	P0803252	Designation Strip
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	1	P0834803	Installation Instructions (Jumper)

Status
✓ § ➤ S

NTZC57AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Base Software		Meridian Mail Card Option R13	S1

Notes:

- A maximum of four (4) languages are available per system. If additional languages, not included on this tape are needed, you must order the appropriate Meridian Mail Release 13 master tape that contains the desired language.
- All new systems require Meridian Mail Base Software.
- The following features are not supported on Meridian Mail Release 13 Card Option systems: Multi-Administration and Disk Shadowing.
- The Meridian 1 serial number must be provided when ordering this code to add Meridian Mail to an existing Meridian 1.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R47AD	MM13 13 Master Tape NA 1	1	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide
1	P0735064	Controlling Access Privileges Workbook			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC57BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 Base Software, Release 13		Meridian Mail EC11 R12	W0/ S1

Notes:

- A maximum of four (4) languages are available per system. If additional languages not included on this tape are required, order the appropriate language tape.
- All new systems require Meridian Mail Base Software.
- The Meridian 1 serial number must be provided when ordering this code to add Meridian Mail to an existing Meridian 1.

Qty	Order code	Description	Qty	Order code	Description
1	NT1F93AA	Meridian Mail Release 12 Option 11 EC/EC11 Manual	1	P0735064	Controlling Access Privileges Workbook

Status
✓ § ➤ S

NTZC58AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Mini Option, 2 Ports, 2 Hours Package			W1

Notes:

- Requires Option 11C Mini Chassis Expander Package (NTSF1032) to be ordered or previously ordered.
- The Option 11C Mini site ID must be provided when ordering this code to add Meridian Mail to an existing PBX.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R16AB	PC Pack, Entopia MMP40, Card Option (Any Slot)	1	NTTK12AA	SCSI Tape Drive Cable
1	NTDK74AB	Card Option 4 5GB Disk Drive	2	SW7105	Meridian Mail Card Option Full Service Port License Fee

Status
✓ § ➤ S

NTZC58BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Mini Option, 4 Ports, 5 Hours Package			W1

Notes:

- Requires Option 11C Mini Chassis Expander Package (NTSF1032) to be ordered or previously ordered.
- The Option 11C Mini site ID must be provided when ordering this code to add Meridian Mail to an existing PBX.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R16AB	PC Pack, Entopia MMP40, Card Option (Any Slot)	1	NTTK12AA	SCSI Tape Drive Cable
1	NTDK74AB	Card Option 4 5GB Disk Drive	4	SW7105	Meridian Mail Card Option Full Service Port License Fee

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ § ➤ S

NTZC58CA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Mini Option, 8 Ports, 5 Hours Package			W1

Notes:
- Requires Option 11C Mini Chassis Expander Package (NTSF1032) to be ordered or previously ordered.
- The Option 11C Mini site ID must be provided when ordering this code to add Meridian Mail to an existing PBX.

Qty	Order code	Description	Qty	Order code	Description
1	NT6R16AB	PC Pack, Entopia MMP40, Card Option (Any Slot)	1	NTTK12AA	SCSI Tape Drive Cable
1	NTDK74AB	Card Option 4 5GB Disk Drive	8	SW7105	Meridian Mail Card Option Full Service Port License Fee
1	NTMW03AA	4-Port DSP Daughter Card			

Status
➤ S

NTZC59AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 0-1			S1

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0906932	Meridian Mail Release 13 Keycode			

Status
➤ S

NTZC62AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 2 Port	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:
- Requires the following software packages in addition to the base package:
- Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).

Qty	Order code	Description	Qty	Order code	Description
1	NT5G04AA	Meridian Integrated Voice Services (MIVS) kit	1	P0838515	Keycode Label
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC62BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 4 Port	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:

- Requires the following software packages in addition to the base package:
- Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).

Qty	Order code	Description	Qty	Order code	Description
1	NT5G04AA	Meridian Integrated Voice Services (MIVS) kit	1	P0838515	Keycode Label
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

Status
➤ S

NTZC62CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 8 Port	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:

- Requires the following software packages in addition to the base package:
- Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).

Qty	Order code	Description	Qty	Order code	Description
1	NT5G04AA	Meridian Integrated Voice Services (MIVS) kit	1	P0838515	Keycode Label
1	NTBK48AA	3-port SDI Cable (1 5m or 5 Ft)	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

Status
➤ S

NTZC63AA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 2 to 4 Port Upgrade	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:

- Requires the following software packages in addition to the base package: Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).
- When ordering a MIVS port upgrade (2 to 4, 2 to 8 or 4 to 8 ports), the customer must submit the Security Device ID (8 digits) of the MIVS pack they wish to add more ports to. This will be required because the Security Device ID will be used to generate a new keycode that turns on the additional ports.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC63BA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 2 to 8 Port Upgrade	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:

- Requires the following software packages in addition to the base package: Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).
- When ordering a MIVS port upgrade (2 to 4, 2 to 8 or 4 to 8 ports), the customer must submit the Security Device ID (8 digits) of the MIVS pack they wish to add more ports to. This will be required because the Security Device ID will be used to generate a new keycode that turns on the additional ports.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

Status
➤ S

NTZC63CA

Description	System Compatibility	Product compatibility	W/S
Meridian Integrated Voice Services, 4 to 8 Port Upgrade	11C X11 R19; 51C X11 R19; 61C X11 R19; 81 X11 R19; 81C X11 R19		W3

Notes:

- Requires the following software packages in addition to the base package: Basic Hospitality (SW0060) and ACD/Message Processing (SW0221).
- When ordering a MIVS port upgrade (2 to 4, 2 to 8 or 4 to 8 ports), the customer must submit the Security Device ID (8 digits) of the MIVS pack they wish to add more ports to. This will be required because the Security Device ID will be used to generate a new keycode that turns on the additional ports.

Qty	Order code	Description	Qty	Order code	Description
1	P0838515	Keycode Label	1	P0909573	Meridian Integrated Voice Services (MIVS) NTP

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZC65AA

Description	System Compatibility	Product compatibility	W/S
IP Telecommuter System Package			W1

Notes:

- Meridian 9617 USB Phones must be ordered separately. They are included in Nortel Networks' Consumer Products Product Catalog. Versions compatible with Meridian IP Telecommuter software are NT2N49AA/A0774004 (Chameleon Grey) and NT2N49AB/A0774005 (Black).
- MAT Release 6.5 or later required and must be ordered separately.
- MAT Alarm Management Module must be ordered to receive SNMP alarms for the ITG card.
- The IP Line Card occupies 2 slots on the IPE shelf.
- Requires X11 Release 22 or greater.
- One Liberaton CTI Headset (NTA149BM/A0757152) is included in each Meridian IP Telecommuter Package. It is primarily intended for validating correct installation of the IP Telecommuter application. Additional CTI headsets for use with the Meridian IP Telecommuter soft client must be ordered separately. For example, the Liberation CTI Headset is included in Nortel Networks' Meridian Business Sets Catalog.

Qty	Order code	Description	Qty	Order code	Description
1	NT8R16BB	IP Line Card-Base Card	1	NTMF94DA	Meridian ITG Backplane and D-Sub Com Port Cable
1	NTAG81CA	PC Maintenance Cable	24	NTNH13AA	Meridian IP Telecommuter Client Application CD
1	NTLH16AA	Meridian IP Telecommuter NTP CD ROM			

Status
✓ ➤ S

NTZC75AA

Description	System Compatibility	Product compatibility	W/S
32MB DRAM SIMM Upgrade Kit			W1

Notes:

- This memory Upgrade Kit contains one (1) 32MB SIMM, installation documentation, faceplate labels and anti-static transportation bag.
- This kit supports DRAM memory upgrade of any existing memory configuration of Call Processor 68040 (NT9D19), Call Processor 68060 (NT5D10) or Call Processor 68060E (NT5D03) to one of the following memory configurations: 96 MB (32 flash, 64 DRAM), 112 MB (32 flash, 80 DRAM), 128 MB (64 flash, 64 DRAM), 144 MB (64 flash, 80 DRAM), 160 MB (64 flash, 96 DRAM). Some of the "resulting" memory configuration may not be available; availability depends upon the existing memory configuration of the call processor to be upgraded.
- It may be necessary to purchase more than one (NTZC75AA) kit to accomplish the DRAM memory upgrade.
- It may be necessary to purchase the 32 MB Flash memory upgrade kit (NTZC76AA) to accomplish the Flash portion of the memory upgrade.
- Consult the Meridian Configurator Upgrades System to determine the number of the number of DRAM Memory Upgrade Kits (NTZC75AA) and Flash Memory Upgrade Kits (NTZC76AA) required to upgrade a specific call processor memory configuration to the target memory configuration.
- Concurrent upgrade of one or more DRAM SIMMs and Flash Memory modules is supported by the installation documentation.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZC76AA

Description	System Compatibility	Product compatibility	W/S
32MB Flash Memory Upgrade Kit			W0

Notes:

- This Memory Upgrade Kit contains two (2) 16 MB Flash Modules, installation documentation, faceplate labels and anti-static transportation bag.
- This kit supports Flash Memory upgrade of Call Processor 68040-series "B" (NT9D19), Call Processor 68060 (NT5D10), Call Processor 68060E (NT5D03).
- Please note that this kit does not support 68040-series A (NT9D19). Flash memory upgrades are not supported for this call processor series.
- Consult the Meridian Configurator Upgrades System to determine the number of the number of DRAM Memory Upgrade Kits (NTZC75AA) and Flash Memory Upgrade Kits (NTZC76AA) required to upgrade a specific call processor memory configuration to the target memory configuration.
- Concurrent upgrade of one or more DRAM SIMMs and Flash Memory modules is supported by the installation documentation.

Status
✓ ➤ S

NTZC77AA

Description	System Compatibility	Product compatibility	W/S
ESD/DRAM SIMM Accessory Kit			W1

Notes:

- This kit contains DRAM installation videos, electro static discharge (ESD) wrist strap, ESD mat, ESD grounding cable and anti-static transportation bag.
- This kit is required when handling DRAM SIMM or Flash Memory Modules, unless distributor/customer already possesses same or like product.

Status
★ ➤ S

NTZC80AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	11C X11 R25; 11C COMPACT X11 R25; 51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		W1

Notes:

- This card is for spare purchases or replacement.
- All cables and filters required can be ordered with NTZC81AA Meridian IP Telephony Gateway Line 2.0 Systems Package or ordered separately.
- The PBX that the customer is installing the card onto must be running X11 Release 25 or greater.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZC81AA

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway Line 2.0 Systems Package	11C X11 R25; 11C COMPACT X11 R25; 51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		W1

Notes:

- Refer to the Data Product Catalog when ordering the i2004 Internet Telephone, NTEX00BA.
- The Meridian 1 PBX must be on Release 25 or greater.
- MAT 6.6 or OTM 1.0 is a prerequisite and must be ordered separately. MAT or OTM is not automatically included in this package, however the MAT ITG application is automatically included in MAT 6.6 or OTM 1.0
- The Alarm and Notification application package is not automatically included in MAT 6.6 or OTM 1.0 and must be ordered separately.
- No keycode or security device is utilized on the IP Telephony Gateway Line Card.
- One Internet Telephone Software Parameter must be purchased for each i2004 Internet Telephone provisioned in the network.
- Internet Telephone Software Parameter NTZC82AA is for large systems only (Options 51C, 61C, 81, and 81C), and Internet Telephone Software Parameter NTZC84AA is for small systems only (Options 11C and 11C Compact).
- The product plugs into an IPE shelf. The ITG 2.0 Line Card occupies two IPE slots.

Qty	Order code	Description	Qty	Order code	Description
1	NTAG81CA	PC Maintenance Cable	1	NTDW81AA	Meridian IP Telephony Gateway (ITG) Line 2 0 NTP (CD-ROM)
1	NTCW84JA	Meridian ITG 2 0 I/O Panel Mounting Connector	1	NTMF94EA	Meridian ITG 2 0 ELAN, TLAN, RS232 Port Cable
1	NTDW80AA	Meridian IP Telephony Gateway (ITG) Line 2 0 Software CD-ROM			

Status
★ ➤ Δ S

NTZC82AA

Description	System Compatibility	Product compatibility	W/S
Internet Telephone Software Parameter (Large System)	51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		S2

Notes:

- One Internet Telephone Software Parameter must be purchased for each i2004 Internet Telephone provisioned in the network.
- This software parameter is for Large Systems (Options 51C, 61C, 81, and 81C).

Status
★ ➤ Δ S

NTZC84AA

Description	System Compatibility	Product compatibility	W/S
Internet Telephone Software Parameter (Small System)	11C X11 R25; 11C COMPACT X11 R25		S2

Notes:

- One Internet Telephone Software Parameter must be purchased for each i2004 Internet Telephone provisioned in the network.
- This software parameter is for Small Systems (Options 11C and 11C Compact).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZC91BA

Description	System Compatibility	Product compatibility	W/S
Software Installation Kit (Non-Autovon)	51C; 61C; 81C		W0

Notes:
- The software installation kit NT5D90BA is orderable as a merchandise item but does not contain an authorized keycode and security device required for software feature activation. To activate specific software features, the keycode and security device must be obtained from a CD-ROM based software order.
- Contains: (1) generic CD-ROM preloaded with the entire X11 Release 23 software portfolio, (3) Install Program diskettes, (3) Database Transfer Utility diskettes, (2) Database diskettes, (1) Distributor Keycode Application diskette, and (1) blank keycode diskette for down-loading an electronically retrieved keycode.

Status
➤ S

NTZD0001

Description	System Compatibility	Product compatibility	W/S
Marketing Package Symposium Call Center Server, New System			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to add Symposium to an existing Meridian 1.

Status
➤ S

NTZD0002

Description	System Compatibility	Product compatibility	W/S
Marketing Package Symposium Call Center Server, Upgrade System			W1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

NTZD0004

Description	System Compatibility	Product compatibility	W/S
Marketing Package Symposium Call Center Server, NCC			S1

Notes:
- When ordering this code, the customer must provide a Meridian 1 switch serial number from one of its networked call centers.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

NTZD0005

Description	System Compatibility	Product compatibility	W/S
Marketing Package DMS SYMPOSIUM Call Center Server, New System	DMS-100		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to add SYMPOSIUM to an existing Meridian 1.

Status
★ ➤ Δ S

NTZD0006

Description	System Compatibility	Product compatibility	W/S
Marketing Package DMS SYMPOSIUM Call Center Server, Upgrade System	DMS-100		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to add SYMPOSIUM to an existing Meridian 1.

Status
★ ➤ Δ S

NTZD0007

Description	System Compatibility	Product compatibility	W/S
Marketing Package DMS SYMPOSIUM Call Center Server, Spare System	DMS-100		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to add SYMPOSIUM to an existing Meridian 1.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZD02AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 702t Advanced with Windows NT 3.51	11C X11 R23; 51C X11 R23; 61C X11 R23; 81 X11 R23; 81C X11 R23; X11 X11 R23		W1

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server hardware.
- Requires NT9F27AA Hardware Peripherals Package.
- Requires either NTRH9009--PCI Ethernet Adapter; or NTRH9010--PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- The server platform will operate at 115 VAC or 230 VAC.
- When ordering hardware, ONE of the following identifiers MUST be used: - NTZD0001 - New Symposium Call Center orders - NTZD0002 - for server upgrades - NTZD0003 - for server spare order.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0677506	Dry Clean Cartridge	1	NT9F37AA	SYMPOSIUM Server Advanced
3	A0677508	13GB Data Cartridge	1	NT9F50AA	SYMPOSIUM Call Center Operating System Diskettes
1	NT3R7207	SYMPOSIUM Call Center Operating System CD	1	NTRH7004	702t Platform Configuration Kit
1	NT3R7208	Microsoft DOS 6 20	1	NTRH8017	PC Diagnostics 3 48B
1	NT3R9501	Software Assembly, Emergency Repair Disks	1	P0884909	702t Installation and Maintenance Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZD02AD

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 702t Advanced	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24; X11 X11 R24		W1

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server hardware.
- Requires NT9F27AA Hardware Peripherals Package.
- Requires either NTRH9009--PCI Ethernet Adapter; or NTRH9010--PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- The server platform will operate at 115 VAC or 230 VAC.
- When ordering hardware, ONE of the following identifiers MUST be used: - NTZD0001 - New Symposium Call Center orders - NTZD0002 - for server upgrades - NTZD0003 - for server spare order.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0677506	Dry Clean Cartridge	1	NT9F50AB	SYMPOSIUM Call Center Server Operating System Diskettes, version NT 4 0
3	A0677508	13GB Data Cartridge	1	NT9F52AB	SYMPOSIUM Call Center Server Operating System CD-Rom, version NT 4 0
1	NT3R7208	Microsoft DOS 6 20	1	NTRH7004	702t Platform Configuration Kit
1	NT3R9501	Software Assembly, Emergency Repair Disks	1	NTRH8017	PC Diagnostics 3 48B
1	NT9F37AA	SYMPOSIUM Server Advanced	1	P0884909	702t Installation and Maintenance Guide

Status
✓ ➤ S

NTZD02BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 702t Advanced with RAID with Windows NT 3.51	11C X11 R23; 51C X11 R23; 61C X11 R23; 81 X11 R23; 81C X11 R23; X11 X11 R23		W1

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server hardware.
- Requires NT9F27AA Hardware Peripherals Package.
- Requires either NTRH9009--PCI Ethernet Adapter; or NTRH9010--PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- When ordering hardware, ONE of the following identifiers MUST be used: - NTZD0001 - New Symposium Call Center orders - NTZD0002 - for server upgrade - NTZD0003 - for server spare order.
- The server platform will operate at 115 VAC or 230 VAC.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0677506	Dry Clean Cartridge	1	NT9F37BA	SYMPOSIUM Server Advanced
3	A0677508	13GB Data Cartridge	1	NT9F50AA	SYMPOSIUM Call Center Operating System Diskettes
1	NT3R7207	SYMPOSIUM Call Center Operating System CD	1	NTRH7004	702t Platform Configuration Kit
1	NT3R7208	Microsoft DOS 6 20	1	NTRH8017	PC Diagnostics 3 48B
1	NT3R9501	Software Assembly, Emergency Repair Disks	1	P0884909	702t Installation and Maintenance Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZD02BD

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server, 702t Advanced with RAID	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24; X11 X11 R24		W1

Notes:

- This configuration consists of the SYMPOSIUM Call Center Server hardware.
- Requires NT9F27AA Hardware Peripherals Package.
- Requires either NTRH9009--PCI Ethernet Adapter; or NTRH9010--PCI Token Ring Adapter to support the connectivity to the customer's LAN.
- When ordering hardware, ONE of the following identifiers MUST be used: - NTZD0001 - New Symposium Call Center orders - NTZD0002 - for server upgrade - NTZD0003 - for server spare order.
- The server platform will operate at 115 VAC or 230 VAC.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0677506	Dry Clean Cartridge	1	NT9F50AB	SYMPOSIUM Call Center Server Operating System Diskettes, version NT 4 0
3	A0677508	13GB Data Cartridge	1	NT9F52AB	SYMPOSIUM Call Center Server Operating System CD-Rom, version NT 4 0
1	NT3R7208	Microsoft DOS 6 20	1	NTRH7004	702t Platform Configuration Kit
1	NT3R9501	Software Assembly, Emergency Repair Disks	1	NTRH8017	PC Diagnostics 3 48B
1	NT9F37BA	SYMPOSIUM Server Advanced	1	P0884909	702t Installation and Maintenance Guide

Status
✓ ➤ S

NTZD06AF

Description	System Compatibility	Product compatibility	W/S
SCCS Software Upgrade Package, R1.1/1.5 to R3.0	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ Δ S

NTZD07AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Graphical Real Time Display CD-ROM			W0

Notes:

- Supplementary CD-ROM providing additional SYMPOSIUM Call Center Server real time display enhancements.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD08AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Windows NT 4.0 Client CD-ROM		SYMPOSIUM Call Center Server (ICCM)	W0

Notes:

- Supplementary CD-ROM providing support for Windows NT 4.0 on the SYMPOSIUM Call Center Server Client.
- Each SYMPOSIUM Call Center Server system must have at least one Windows 95 client.

Status
➤ Δ S

NTZD10AA

Description	System Compatibility	Product compatibility	W/S
SCCS Marketing Package, Windows NT 4.0 Client			W1

Qty	Order code	Description	Qty	Order code	Description
1	NTL496AA	Symposium Call Center Server Windows NT 4 0 Client PEP CD Rom	1	NTZD08AA	SYMPOSIUM Call Center Server Windows NT 4 0 Client CD-ROM

Status
➤ S

NTZD10AF

Description	System Compatibility	Product compatibility	W/S
SCCS Software Upgrade Package, R1.0 to R3.0	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
➤ S

NTZD13AF

Description	System Compatibility	Product compatibility	W/S
Marketing Package, SCCS NCC (Network Control Center) Release 3.0 Software	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

Status
★ ➤ S

NTZD21AA

Description	System Compatibility	Product compatibility	W/S
DMS SCCS Release 3.0 Peripherals Package	DMS-100		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZD24AA

Description	System Compatibility	Product compatibility	W/S
Software Assembly, SCCS Release 3 Base Software (DMS/MSL)	DMS-100		S1

Status
★ ➤ S

NTZD26AA

Description	System Compatibility	Product compatibility	W/S
702t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	DMS-100		W1

Status
✓ ➤ S

NTZD27AA

Description	System Compatibility	Product compatibility	W/S
1003t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	DMS-100		W1

Status
➤ S

NTZD61AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter Single Site Software, Option 11 MM13		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W1

Notes:

- Meridian Mail Reporter requires a spare data port for AdminPlus, a spare RSM, Utility, MMP40, or Enhanced Processor data port may be used, based on configuration.
- This Meridian Mail Reporter package includes Reporter Software, AdminPlus Enable Option, and documentation.
- A Meridian Mail Reporter 90 Day Service Plan is included, for an Extended Service Plan, see SVC1006.
- See the "Support" section of the product catalog for a detailed description of the Reporter Service Plan.
- Cable requirements for Meridian Mail Reporter are configuration dependent, refer to the Reporter Product Bulletin, Meridian Configurator or MC Upgrades for details.
- The Meridian Mail Serial number is required when ordering this product for an existing system.

Qty	Order code	Description	Qty	Order code	Description
1	NTDW02AA	Meridian Mail Release 13 Reporter Single Site Software and Documents	1	SVC1005	Meridian Mail Reporter 90 Day Service Plan

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD61BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter Multi Site Software, Option 11 - MM13		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0/ S1

Notes:

- Meridian Mail Reporter requires a spare data port for AdminPlus, a spare RSM, Utility, MMP40, or Enhanced Processor data port may be used, based on configuration.
- This Meridian Mail Reporter package includes Reporter Software, AdminPlus Enable Option for the prime Meridian Mail site, and documentation.
- A Meridian Mail Reporter 90 Day Service Plan is included, for an Extended Service Plan, see SVC1006.
- See the "Support" section of the product catalog for a detailed description of the Reporter Service Plan.
- Cable requirements for Meridian Mail Reporter are configuration dependent, refer to the Reporter Product Bulletin, Meridian Configurator or MC Upgrades for details.
- Meridian Mail Reporter requires Meridian Mail Release 10 or later and AdminPlus with a dedicated 9600 baud modem at all locations. Order AdminPlus Enable Option for remote sites as required.
- The Meridian Mail Serial number is required when ordering this product for an existing system.

Qty	Order code	Description	Qty	Order code	Description
1	NTDW02BA	Meridian Mail Release 13 Multi-Site Software and Documents	1	SVC1005	Meridian Mail Reporter 90 Day Service Plan

Status
➤ S

NTZD62AA

Description	System Compatibility	Product compatibility	W/S
Assembly, Meridian Mail Alternate User Interface 1			W0

Notes:

- The Meridian Mail Serial number is required when ordering this product for an existing system.

Qty	Order code	Description	
1	NT2F09AA	Alternate User Interface 1 User Guide (15 per Package)	
	Each Package Includes:		
	15	P0884614	Alternate User Interface 1 User Guides
1	NT8R2002	CD ROM Meridian Mail Alternate User Interface	
1	NTDW03AA	AUI Software Assembly Key Code	
1	P0841936	SYMANTEC pcAnywhere RTU	
1	P0884613	Alternate User Interface Installation/Administration Guide	
1	P0902630	AUI PC Installation Instruction Sheet	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZD63AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Release 6 to Release 13 Upgrade		Meridian Mail Card Option R6	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system. If additional languages are required, order the appropriate Release 13 language tapes.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTAK72JL	Meridian Mail Card Option Master Tape - North American, Release 8	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTZD63BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Release 8/9/10/ 11/12 to Release 13 Upgrade		Meridian Mail Card Option R8,9,10,11,12	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system. If additional languages are required, order the appropriate Release 13 language tapes.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
✓➤ S

NTZD65AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 Release 10, 11, or 12 to Release 13 Upgrade		Meridian Mail EC11 R10,11	W0/ S1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system. If additional languages are required, order the appropriate Release 13 language tapes.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTZC57AA	Meridian Mail Release 13 Base Software	
	Each Package Includes:		
	1	NT6R47AD	MM13 13 Master Tape NA 1
	1	P0735064	Controlling Access Privileges Workbook
	1	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
➤ S

NTZD66AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter Single Site Software MM13		Meridian Mail Modular Option; Meridian Mail Modular Option EC; Meridian Mail Modular Option GP; Meridian Mail Options (ST/RT, NT/XT)	W1

Notes:

- Meridian Mail Reporter requires a spare data port for AdminPlus, a spare RSM, Utility, or MMP40 data port may be used, based on configuration.
- This Meridian Mail Reporter package includes Reporter Software and documentation.
- A Meridian Mail Reporter 90 Day Service Plan is included. For an Extended Service Plan, see SVC1006.
- See the "Support" section of the product catalog for a detailed description of the Reporter Service Plan.
- Cable requirements for Meridian Mail Reporter are configuration dependent. Refer to the Reporter Product Bulletin, Meridian Configurator or MC Upgrades for details.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDW04AA	MM13 MM Reporter Single SW and Documents	1	SVC1005	Meridian Mail Reporter 90 Day Service Plan

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD66BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter Multi Site Software Release 13		Meridian Mail Modular Option; Meridian Mail Modular Option EC; Meridian Mail Modular Option GP; Meridian Mail Options (ST/RT, NT/XT)	W1

Notes:

- Meridian Mail Reporter requires a spare data port for AdminPlus, a spare RSM, Utility, or MMP40 data port may be used, based on configuration.
- This Meridian Mail Reporter package includes Reporter Software, AdminPlus Enable Option for the prime Meridian Mail site, and documentation.
- A Meridian Mail Reporter 90 Day Service Plan is included. For an Extended Service Plan, see SVC1006.
- See the "Support" section of the product catalog for a detailed description of the Reporter Service Plan.
- Cable requirements for Meridian Mail Reporter are configuration dependent. Refer to the Reporter Product Bulletin, Meridian Configurator or MC Upgrades for details.
- Meridian Mail Reporter requires Meridian Mail Release 10 or later and AdminPlus with a dedicated 9600 baud modem at all locations. Order AdminPlus Enable Option for remote sites as required.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NTDW04BA	MM13 MM Reporter Multi Sites SW and Documents	1	SVC1005	Meridian Mail Reporter 90 Day Service Plan

Status
✓ ➤ Δ S

NTZD67AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 8, 9, 10, 11, or 12 to Release 13 Migration, Options, Modular Option to Modular EC		Meridian Mail Modular Option; Meridian Mail Options (S, ST/RT, NT/XT, X)	W0

Notes:

- The North American Master Tape is included in this package. A maximum of four (4) languages are available per system. If additional languages are required, order the appropriate Release 13 language tapes.
- This software can only be used to support migrations from the Options or Modular Option to the Modular Option EC platform.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM
1	NTND93AA	Null Modem Adapter
1	P0735064	Controlling Access Privileges Workbook
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓➤ S

NTZD68AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC Release 8, 9.19 to Release 13 Upgrade		Meridian Mail EC R8,9.19	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package can only be used for a Modular Option EC Upgrade or Migrations to a Modular Option EC Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
1	P0735064	Controlling Access Privileges Workbook	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	P0803253	Designation Strip
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓ ➤ S

NTZD68BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC Release 9.58 and Later/ Release 10/11/12 to Release 13 Upgrade		Meridian Mail EC R10,11,9.58	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package can only be used for a Modular Option EC Upgrade or Migrations to a Modular Option EC Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZD69AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 4 to Release 13 Software Migration, GP to Modular GP		Meridian Mail GP R4	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- This package can only be used in conjunction with a hardware/software migration to a Modular Option GP when accompanied by an U706X or U707X hardware migration package.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option or AdminPlus can convert to Meridian Mail Release 8 on the way to Meridian Mail Release 13, without 2.5MB memory card. Systems with ACCESS Enable Option or AdminPlus must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	63016	Meridian Mail Release 4 to Release 7 Software Migration, from Options to Modular EC	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
6	P0594340	Clamp Cable	
1	P0735064	Controlling Access Privileges Workbook	
2	P0803252	Designation Strip	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓➤ S

NTZD69BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Release 5 to Release 13 Upgrade or Migration from GP to Modular GP		Meridian Mail GP R5; Meridian Mail Modular GP R5	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- This package may be used for a Modular Option GP Upgrade or Migration from a X Cabinet GP to a Modular Option GP Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option or AdminPlus can convert to Meridian Mail Release 8 on the way to Meridian Mail Release 13, without 2.5MB memory card. Systems with ACCESS Enable Option or AdminPlus must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	63017	Meridian Mail Release 5 to Release 7 Software Migration, from Options, Modular Option to Modular EC	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM
1	NTND93AA	Null Modem Adapter
6	P0594340	Clamp Cable
1	P0735064	Controlling Access Privileges Workbook
2	P0803252	Designation Strip
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓➤ S

NTZD69CA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP		Meridian Mail GP R7; Meridian Mail Modular GP R7	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- This package may be used for a Modular Option GP Upgrade or Migration from a X Cabinet GP to a Modular Option GP Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option or AdminPlus can convert to Meridian Mail Release 8 on the way to Meridian Mail Release 13, without 2.5MB memory card. Systems with ACCESS Enable Option or AdminPlus must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
6	P0594340	Clamp Cable	
1	P0735064	Controlling Access Privileges Workbook	
2	P0803252	Designation Strip	
1	P0834803	Installation Instructions (Jumper)	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
✓➤ S

NTZD69DA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP		Meridian Mail GP R8; Meridian Mail Modular GP R8	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- This package may be used for a Modular Option GP Upgrade or Migration from a X Cabinet GP to a Modular Option GP Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
6	P0594340	Clamp Cable	
1	P0735064	Controlling Access Privileges Workbook	
2	P0803252	Designation Strip	
1	P0834803	Installation Instructions (Jumper)	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
✓ ➤ S

NTZD69EA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular GP Release 9/10/ 11/12 to Release 13 Upgrade or Migration from GP to Modular GP		Meridian Mail Modular GP R9,10,11	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- This package may only be used for a Modular Option GP Upgrade to Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
✓➤ S

NTZD70AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option		Meridian Mail Modular Option R5; Meridian Mail Options (S, ST/RT, NT/XT, X) R5	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package may be used for Modular Option Upgrades or Migrations from a ST/RT, NT/XT, S, X Cabinet to a Modular Option Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 without 2.5MB memory card. Systems with ACCESS Enable Option, AdminPlus or HVS features must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	
	Each Package Includes:		
	1	P0904484	Modular Option Site and Installation & Planning Guide - MM13
	1	P0904485	Modular Option Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
6	P0594340	Clamp Cable	
1	P0735064	Controlling Access Privileges Workbook	
2	P0803252	Designation Strip	
1	P0834803	Installation Instructions (Jumper)	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What’s New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓➤ S

NTZD70BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option		Meridian Mail Modular Option R6,7; Meridian Mail Options (S, ST/RT, NT/XT, X) R7	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package may be used for Modular Option Upgrades or Migrations from a ST/RT, NT/XT, S, X Cabinet to a Modular Option Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 without 2.5MB memory card. Systems with ACCESS Enable Option, AdminPlus or HVS features must have 2.5MB memory card temporarily installed during the upgrade to Meridian Mail Release 8 on the way to Meridian Mail Release 13.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	
	Each Package Includes:		
	1	P0904484	Modular Option Site and Installation & Planning Guide - MM13
	1	P0904485	Modular Option Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
6	P0594340	Clamp Cable	
1	P0735064	Controlling Access Privileges Workbook	
2	P0803252	Designation Strip	
1	P0834803	Installation Instructions (Jumper)	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓ ➤ S

NTZD70CA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option		Meridian Mail Modular Option R8; Meridian Mail Options (S, ST/RT, NT/XT, X) R8	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package may be used for Modular Option Upgrades or Migrations from a ST/RT, NT/XT, S, X Cabinet to a Modular Option Release 13.
- This package contains one Enhanced MMP40 processor upgrade. An Enhanced MMP40 upgrade is required for each node, order additional Enhanced MMP40 upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	
	Each Package Includes:		
	1	P0904484	Modular Option Site and Installation & Planning Guide - MM13
	1	P0904485	Modular Option Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
6	P0594340	Clamp Cable
1	P0735064	Controlling Access Privileges Workbook
2	P0803252	Designation Strip
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓➤ S

NTZD70DA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option		Meridian Mail Modular Option R9,10,11; Meridian Mail Options (ST/RT, NT/XT) R9,10,11	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0351509	Gender Changer (Female/Female)	
1	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	
	Each Package Includes:		
	1	P0904484	Modular Option Site and Installation & Planning Guide - MM13
	1	P0904485	Modular Option Installation and Maintenance Guide - MM13
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓ ➤ S

NTZD70EA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 3 to Release 13 Software Migration, from Options to Modular Option		Meridian Mail Options (S, ST/RT, NT/XT, X) R3	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package is used for Migrations from a ST/RT, NT/XT, S, X Cabinet to a Modular Option Release 13 and must be accompanied by a U701X Modular Option hardware migration package.
- This package contains one Enhanced Processor upgrade. An Enhanced Processor upgrade is required for each node, order additional NTZD75BA Enhanced Processor upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 on the way to Release 13, without a 2.5MB memory card.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT1F91AA	Meridian Mail Modular Options Manual	
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	NTND93AA	Null Modem Adapter	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
6	P0594340	Clamp Cable
1	P0735064	Controlling Access Privileges Workbook
2	P0803252	Designation Strip
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
✓➤ S

NTZD70FA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 4 to Release 13 Software Migration, from Options to Modular Option		Meridian Mail Options (S, ST/RT, NT/XT, X) R4	W1

Notes:

- The North American Master Tape is included in this package. A maximum of four languages are available per system, if additional languages are required, order the appropriate Release 13 language tapes.
- If Integrated Mailbox Administration is to be used, X11 Release 19.23 or later software is required.
- This package is used for Migrations from a ST/RT, NT/XT, S, X Cabinet to a Modular Option Release 13 and must be accompanied by a U701X Modular Option hardware migration package.
- This package contains one Enhanced Processor processor upgrade. An Enhanced Processor upgrade is required for each node, order additional NTZD75BA Enhanced Processor upgrades as required.
- Systems with Flashback Tape Drives must upgrade to a Tandberg Tape Drive.
- Systems with 155MB disk drives must upgrade to 2GB disk drives.
- Systems not running ACCESS Enable Option, AdminPlus or HVS can convert to Meridian Mail Release 8 on the way to Release 13, without a 2.5MB memory card.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	
1	A0292488	Jumper (For ESBC Card)	
1	A0351509	Gender Changer (Female/Female)	
1	NT1F91AA	Meridian Mail Modular Options Manual	
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT5R12AC	Meridian Mail Master Tape - North American, Release 8	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT6R47AD	MM13 13 Master Tape NA 1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM
1	NTND93AA	Null Modem Adapter
6	P0594340	Clamp Cable
1	P0735064	Controlling Access Privileges Workbook
2	P0803252	Designation Strip
1	P0834803	Installation Instructions (Jumper)
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide
1	P0904493	Maintenance Messages (SEERs) - MM13
1	P0904567	What's New In Meridian Mail Release 13
1	P0907072	PC Application Guide - MM13
1	P0907146	Meridian Mail Release 13 Feature Operations Video

Status
➤ S

NTZD71AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Two node Release 9 and later systems support from 16-24 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D44AA	Meridian Mail Module AC
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R10AA	HABC Terminator	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT4R11AA	ESBC Terminator	1	NT7D06AA	Filler Panel
1	NT4R60AA	CRT Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4418	SCSI/Daisy Chain Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4419	RS232-Y Cable	1	QPF23A	Terminating Plug

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD71BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Two node Release 9 and later systems support from 16-24 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4419	RS232-Y Cable
1	NT4R08AA	HABC (High Availability Bus Controller)	1	NT6D44DC	Meridian Mail Module DC
1	NT4R10AA	HABC Terminator	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R11AA	ESBC Terminator	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel
1	NT6D41AD	Common Equipment Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	2	P0803252	Designation Strip
1	NT6D4417	SCSI/Backplane Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4418	SCSI/Daisy Chain Cable	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD72AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Three node Release 9 and later systems support from 28-32 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D44AA	Meridian Mail Module AC
1	NT4R60AA	CRT Cable	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D4407	GSP Cable	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D4409	SCSI Cable	1	NT7D06AA	Filler Panel
1	NT6D4410	DVS Bus Cable	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4418	SCSI/Daisy Chain Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4419	RS232-Y Cable	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD72BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Three node Release 9 and later systems support from 28-32 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D4419	RS232-Y Cable
1	NT4R60AA	CRT Cable	1	NT6D44DC	Meridian Mail Module DC
1	NT6D41AD	Common Equipment Power Supply DC	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT6D4407	GSP Cable	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D4409	SCSI Cable	1	NT7D06AA	Filler Panel
1	NT6D4410	DVS Bus Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4415	DVS Bus Cable (6 Ft)	2	P0803252	Designation Strip
1	NT6D4417	SCSI/Backplane Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4418	SCSI/Daisy Chain Cable	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD73AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Four node Release 9 and later systems support from 36-48 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4417	SCSI/Backplane Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4418	SCSI/Daisy Chain Cable	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4419	RS232-Y Cable	2	P0803252	Designation Strip
1	NT6D44AA	Meridian Mail Module AC	1	P0834803	Installation Instructions (Jumper)
1	NT6D48FA	4 5GB Modular Hard Disk Drive	1	QPF23A	Terminating Plug

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD73BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Four node Release 9 and later systems support from 36-48 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D41AD	Common Equipment Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4418	SCSI/Daisy Chain Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D44DC	Meridian Mail Module DC	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD74AA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package AC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Five node Release 9 and later systems support from 52-64 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D4417	SCSI/Backplane Cable	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4418	SCSI/Daisy Chain Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D44AA	Meridian Mail Module AC	1	QPF23A	Terminating Plug

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD74BA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package DC		Meridian Mail Modular Option	W1

Notes:

- The Enhanced Processor requires Meridian Mail Release 12.13 or higher. At Release 12.13, all processors in a system must be Enhanced Processors to use this package. With Release 13, a mixture of MMP40s and Enhanced Processors are supported on the same system.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Five node Release 9 and later systems support from 52-64 ports.
- Expansions can only be performed on MMP40 or Enhanced Processor based systems.
- Order SERV0020 Meridian Mail Key Code Service (at no charge).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	1	NT6D48FA	4 5GB Modular Hard Disk Drive
1	NT4R60AA	CRT Cable	1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP
1	NT6D41AD	Common Equipment Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4418	SCSI/Daisy Chain Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6D4419	RS232-Y Cable	1	QPF23A	Terminating Plug
1	NT6D44DC	Meridian Mail Module DC			

Status
➤ S

NTZD75AA

Description	System Compatibility	Product compatibility	W/S
Enhanced Processor Upgrade, EC		Meridian Mail Modular Option EC	W1

Notes:

- This package upgrades one node of a Meridian Mail Modular Option EC system with Enhanced Processor hardware.
- An upgrade package must be ordered for each node on the Modular Option EC.
- The Enhanced Processor requires Meridian Mail Release 12.13 or higher.
- Systems with a mixture of MMP40s and Enhanced Processors must be Meridian Mail Release 13 or higher. With Meridian Mail Release 12.13, all processors must be the same type.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	2	P0803253	Designation Strip
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	1	P0834803	Installation Instructions (Jumper)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZD75BA

Description	System Compatibility	Product compatibility	W/S
Enhanced Processor Upgrade, Modular Option, Modular Option GP		Meridian Mail Modular Option; Meridian Mail Modular Option GP	W1

Notes:

- This package upgrades one node of a Meridian Mail Modular Option system with Enhanced Processor hardware.
- An upgrade package must be ordered for each node on the Modular Option.
- The Enhanced Processor requires Meridian Mail Release 12.13 or higher.
- Systems with Meridian Mail Release 12.13 must have either all MMP40s or all Enhanced Processors in every node. If mixed processor types are desired, the system requires Meridian Mail Release 13 or higher.
- The Meridian Mail Serial number is required when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0292488	Jumper (For ESBC Card)	6	P0594340	Clamp Cable
1	NT6D4417	SCSI/Backplane Cable	2	P0803252	Designation Strip
1	NT6D4419	RS232-Y Cable	1	P0834803	Installation Instructions (Jumper)
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP			

Status
➤ S

NTZD81AA

Description	System Compatibility	Product compatibility	W/S
SCCS Software Upgrade Package for Individual Agents, R1.0/R1.1/R1.5 to R3.0	11C X11 R24; 51C X11 R24; 61C X11 R24; 81 X11 R24; 81C X11 R24		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE01AA

Description	System Compatibility	Product compatibility	W/S
CallPilot IPE Base System - English			W1

Notes:

- CallPilot connecting to an Option 51C/61C/81/81C, must include the following: SW0170A - CallPilot Connectivity; NTZE30AA - CallPilot Integration Suite; SW0221C - ACD/Message Processing, provisioned according to the agent level of the system.
- The NTZE01AA CallPilot IPE Base System - English comes equipped with: 4 Voice Channels, 30 hours of storage, 8 MPU Units, Desktop Messaging Capability for 5 Users, 2 Prompt Languages.
- The CallPilot IPE System can be located in any Option 11 or IPE shelf and requires 2 contiguous card slots.
- These systems will not work in an EPE Shelf.
- CallPilot requires X11 Release 23C or higher software on the Meridian 1.
- CallPilot on the Options 51C to 81C requires SW0221C - ACD Message Processing.
- When CallPilot is equipped on an Option 11C, all X11 software pre-requisites are included in the base X11 software.
- When CallPilot is equipped on the Options 51C to 81C, One (1) X11 Option "ACD Message Processing" - SW0221C is required for every 20 Channels.
- When CallPilot connects to an Option 11C, equipped with General Business or Enhanced Business packages, NTSF8516 (Option 11C CallPilot Enable Connectivity) must be included on the order.
- The Meridian 1 Serial number must be provided when ordering to add CallPilot to an existing Meridian 1 system.

Qty	Order code	Description	
1	NTRG11AC	CallPilot Basic Administration Documentation Package - English	
	Each Package Includes:		
	1	NTRG13AB	CallPilot Telset Guides, English, Quantity 15
	1	NTRG19AD	CallPilot 1 06 Documentation CD-ROM
	1	NTRG20AA	CallPilot Installation Worksheet Package
	1	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25
	1	P0886124	CallPilot Planning and Engineering Guide
	1	P0886126	CallPilot Basic Administration Guide
	1	P0886130	CallPilot Advanced Administration Guide - Volume 1
	1	P0886132	CallPilot Advanced Administration Guide - Volume 2
	1	P0903073	CallPilot Software Installation Guide
	1	P0903074	CallPilot Maintenance and Diagnostic Guide
	1	P0907827	CallPilot What’s New for Release 1 06
1	NTRH09AA	Breakout Panel Assembly	
	Each Package Includes:		
	1	NTRH0910	Break Interconnect Cable (6 Ft)
1	NTUB01AA	CallPilot IPE Base Hardware Package	
	Each Package Includes:		
	1	A0738130	128MB DIMM
	1	A0767488	WinNT Certificate of Authenticity
	1	NTRH1407	CallPilot Intermediate SCSI Cable
	1	NTRH1408	CallPilot Intermediate SCSI Cable
	1	NTRH1409	CallPilot Intermediate SCSI Cable
	1	NTRH14AA	200 Series Base System Assembly
	1	NTRH16BA	Hard Drive Data Cable
	1	NTRH9049	4 GB IDE Drive for the 200i System
	1	P0684414	Hard Drive Power Cable

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0841936	SYMANTEC pcAnywhere RTU
	1	P0875668	Insulating Film
	1	P0887449	RTU for DOS 6 20
	1	P0887450	RTU for WinNT Server 4 0
	1	P0887451	RTU for SQL Anywhere
1	NTUB14AB	CallPilot 1 06 Keycode Package	
	Each Package Includes:		
	1	NTDK57AA	Dongle
	1	P0910030	Keycode, CallPilot 1 06
1	NTUB16AA	CallPilot External Modem Kit	
	Each Package Includes:		
	1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male
	1	NTRH9016	External Modem 33 6
1	NTUB20AA	CallPilot IPE Server Software Package	
1	NTUB20AB	CallPilot IPE Server Software Package	
	Each Package Includes:		
	1	NTRH8027	Windows NT 4 0 OS Recovery CD
	1	NTRH8043	MAS Admin Client 1 06 SW
	1	NTRH8044	MAS Server 1 06 SW
	1	NTUB40AB	CallPilot 1 06 Server SW CD
	1	NTUB41AB	CallPilot 1 06 Admin Client CD
	1	NTUB42AB	CallPilot 1 06 Desktop Messaging CD (English & French)
	1	NTUB43AB	CallPilot 1 06 PEP SW CD
	1	NTUB44AB	CallPilot 1 06 Language Prompts
	1	NTUB45AB	CallPilot 1 06 Web Messaging CD (Eng&Fr)
1	NTUB42AA	CallPilot Desktop Client CD	
1	NTZE07AA	CallPilot 4 Voice Channels	
	Each Package Includes:		
	4	NTUB23AA	CallPilot Voice Channel
	2	NTZE06AA	CallPilot MPUs - 2 each
3	NTZE08AA	CallPilot Storage Expansion - 10 hours	
1	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	
2	NTZE16AA	CallPilot Additional Prompt Language	
1	P0903075	CallPilot 200 Series Installation Guide	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE02AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Tower System - English			W1

Notes:

- The NTZE02AA CallPilot Tower Base System - English comes equipped with: 8 Voice Channels, 30 hours of storage, 16 MPU Units, Desktop Messaging Capability for 5 users, 2 Prompt Languages.
- CallPilot requires X11 Release 23C or higher software on the Meridian 1.
- CallPilot on the Options 51C to 81C requires SW0221C - ACD Message Processing.
- When CallPilot is equipped on an Option 11C, all X11 software pre-requisites are included in the base X11 software.
- When CallPilot is equipped on the Options 51C to 81C, One (1) X11 Option "ACD Message Processing" - SW0221C is required for every 20 Channels.
- When CallPilot connects to an Option 11C, equipped with General Business or Enhanced Business packages, NTSF8516 (Option 11C CallPilot Enable Connectivity) must be included on the order.
- CallPilot connecting to an Option 51C/61C/81/81C, must include the following: SW0170A - CallPilot Connectivity; NTZE30AA - CallPilot Integration Suite; SW0221C - ACD/Message Processing, provisioned according to the agent level of the system.
- The Meridian 1 Serial number must be provided when ordering to add CallPilot to an existing Meridian 1 system.

Qty	Order code	Description	
1	NTRG11AC	CallPilot Basic Administration Documentation Package - English	
	Each Package Includes:		
	1	NTRG13AB	CallPilot Telset Guides, English, Quantity 15
	1	NTRG19AD	CallPilot 1 06 Documentation CD-ROM
	1	NTRG20AA	CallPilot Installation Worksheet Package
	1	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25
	1	P0886124	CallPilot Planning and Engineering Guide
	1	P0886126	CallPilot Basic Administration Guide
	1	P0886130	CallPilot Advanced Administration Guide - Volume 1
	1	P0886132	CallPilot Advanced Administration Guide - Volume 2
	1	P0903073	CallPilot Software Installation Guide
	1	P0903074	CallPilot Maintenance and Diagnostic Guide
	1	P0907827	CallPilot What's New for Release 1 06
1	NTUB02AA	702t North American Base System	
	Each Package Includes:		
	1	NTUB06AB	CallPilot 702t Configuration Assembly
1	NTUB14AB	CallPilot 1 06 Keycode Package	
	Each Package Includes:		
	1	NTDK57AA	Dongle
	1	P0910030	Keycode, CallPilot 1 06
1	NTUB16AA	CallPilot External Modem Kit	
	Each Package Includes:		
	1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male
	1	NTRH9016	External Modem 33 6
1	NTUB22AB	CallPilot 1 06 Tower/Rack Base Server Software Assembly	
	Each Package Includes:		
	1	A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems
	1	NT3R9501	Software Assembly, Emergency Repair Disks

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTRH8011	Platform Diskette
	1	NTRH8017	PC Diagnostics 3 48B
	1	NTRH8018	MAS System Report Diskette
	1	NTRH8027	Windows NT 4 0 OS Recovery CD
	1	NTRH8028	CallPilot DOS Floppies
	1	NTRH8033	Windows NT 4 0 Install Diskette
	1	NTRH8043	MAS Admin Client 1 06 SW
	1	NTRH8044	MAS Server 1 06 SW
	1	NTUB40AB	CallPilot 1 06 Server SW CD
	1	NTUB41AB	CallPilot 1 06 Admin Client CD
	1	NTUB42AB	CallPilot 1 06 Desktop Messaging CD (English & French)
	1	NTUB43AB	CallPilot 1 06 PEP SW CD
	1	NTUB44AB	CallPilot 1 06 Language Prompts
	1	NTUB45AB	CallPilot 1 06 Web Messaging CD (Eng&Fr)
1	NTUB42AA	CallPilot Desktop Client CD	
1	NTUB56AA	CallPilot 14" Monitor Kit	
	Each Package Includes:		
	1	NTRH9011	14" SVGA Color Monitor
	1	NTRH9013	OIVR 2 x Hardware - Keyboard
	1	NTRH9014	Three Button Mouse
1	NTUB57AB	CallPilot MGate Kit	
	Each Package Includes:		
	1	NTRB18CA	MGate Card
	1	NTRH2012	CallPilot MGate Cable - 20ft
	1	NTRH2013	Dual DSX30XV Interconnect Cable
2	NTZE07AA	CallPilot 4 Voice Channels	
	Each Package Includes:		
	4	NTUB23AA	CallPilot Voice Channel
	2	NTZE06AA	CallPilot MPUs - 2 each
3	NTZE08AA	CallPilot Storage Expansion - 10 hours	
1	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	
2	NTZE16AA	CallPilot Additional Prompt Language	
1	P0884909	702t Installation and Maintenance Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE03AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Rack Mount System DC - English			W1

Notes:

- The NTZE03AA CallPilot Rack Mount Base System - English comes equipped with: 8 Voice Channels, 30 hours of storage, 16 MPU Units, Desktop Messaging Capability for 5 users, 2 Prompt Languages.
- CallPilot requires X11 Release 23C or higher software on the Meridian 1.
- CallPilot on the Options 51C to 81C requires SW0221C - ACD Message Processing.
- When CallPilot is equipped on an Option 11C, all X11 software pre-requisites are included in the base X11 software.
- When CallPilot is equipped on the Options 51C to 81C, One (1) X11 Option "ACD Message Processing" - SW0221C is required for every 20 Channels.
- When CallPilot connects to an Option 11C, equipped with General Business or Enhanced Business packages, NTSF8516 (Option 11C CallPilot Enable Connectivity) must be included on the order.
- CallPilot connecting to an Option 51C/61C/81/81C, must include the following: SW0170A - CallPilot Connectivity; NTZE30AA - CallPilot Integration Suite; SW0221C - ACD/Message Processing, provisioned according to the agent level of the system.
- The Meridian 1 Serial number must be provided when ordering to add CallPilot to an existing Meridian 1 system.

Qty	Order code	Description	
1	NTRG11AC	CallPilot Basic Administration Documentation Package - English	
	Each Package Includes:		
	1	NTRG13AB	CallPilot Telset Guides, English, Quantity 15
	1	NTRG19AD	CallPilot 1 06 Documentation CD-ROM
	1	NTRG20AA	CallPilot Installation Worksheet Package
	1	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25
	1	P0886124	CallPilot Planning and Engineering Guide
	1	P0886126	CallPilot Basic Administration Guide
	1	P0886130	CallPilot Advanced Administration Guide - Volume 1
	1	P0886132	CallPilot Advanced Administration Guide - Volume 2
	1	P0903073	CallPilot Software Installation Guide
	1	P0903074	CallPilot Maintenance and Diagnostic Guide
	1	P0907827	CallPilot What’s New for Release 1 06
1	NTRH9011	14" SVGA Color Monitor	
1	NTRH9048	101 Enhanced Keyboard	
1	NTUB04AA	1001rp North American Base System DC	
	Each Package Includes:		
	1	NTUB11AA	CallPilot 1001rp Base System
1	NTUB14AB	CallPilot 1 06 Keycode Package	
	Each Package Includes:		
	1	NTDK57AA	Dongle
	1	P0910030	Keycode, CallPilot 1 06
1	NTUB16AA	CallPilot External Modem Kit	
	Each Package Includes:		
	1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male
	1	NTRH9016	External Modem 33 6
1	NTUB22AB	CallPilot 1 06 Tower/Rack Base Server Software Assembly	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems
	1	NT3R9501	Software Assembly, Emergency Repair Disks
	1	NTRH8011	Platform Diskette
	1	NTRH8017	PC Diagnostics 3 48B
	1	NTRH8018	MAS System Report Diskette
	1	NTRH8027	Windows NT 4 0 OS Recovery CD
	1	NTRH8028	CallPilot DOS Floppies
	1	NTRH8033	Windows NT 4 0 Install Diskette
	1	NTRH8043	MAS Admin Client 1 06 SW
	1	NTRH8044	MAS Server 1 06 SW
	1	NTUB40AB	CallPilot 1 06 Server SW CD
	1	NTUB41AB	CallPilot 1 06 Admin Client CD
	1	NTUB42AB	CallPilot 1 06 Desktop Messaging CD (English & French)
	1	NTUB43AB	CallPilot 1 06 PEP SW CD
	1	NTUB44AB	CallPilot 1 06 Language Prompts
	1	NTUB45AB	CallPilot 1 06 Web Messaging CD (Eng&Fr)
1	NTUB42AA	CallPilot Desktop Client CD	
1	NTUB57AB	CallPilot MGate Kit	
	Each Package Includes:		
	1	NTRB18CA	MGate Card
	1	NTRH2012	CallPilot MGate Cable - 20ft
	1	NTRH2013	Dual DSX30XV Interconnect Cable
2	NTZE07AA	CallPilot 4 Voice Channels	
	Each Package Includes:		
	4	NTUB23AA	CallPilot Voice Channel
	2	NTZE06AA	CallPilot MPUs - 2 each
3	NTZE08AA	CallPilot Storage Expansion - 10 hours	
1	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	
2	NTZE16AA	CallPilot Additional Prompt Language	
1	P0907840	CallPilot 1001rp Installation and Maintenance Guide - 1 06	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE04AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Rack Mount System AC - English			W1

Notes:

- The NTZE04AA CallPilot Rack Mount Base System - English comes equipped with: 8 Voice Channels, 30 hours of storage, 16 MPU Units, Desktop Messaging Capability for 5 users, 2 Prompt Languages.
- CallPilot requires X11 Release 23C or higher software on the Meridian 1.
- CallPilot on the Options 51C to 81C requires SW0221C - ACD Message Processing.
- When CallPilot is equipped on an Option 11C, all X11 software pre-requisites are included in the base X11 software.
- When CallPilot is equipped on the Options 51C to 81C, One (1) X11 Option "ACD Message Processing" - SW0221C is required for every 20 Channels.
- When CallPilot connects to an Option 11C, equipped with General Business or Enhanced Business packages, NTSF8516 (Option 11C CallPilot Enable Connectivity) must be included on the order.
- CallPilot connecting to an Option 51C/61C/81/81C, must include the following: SW0170A - CallPilot Connectivity; NTZE30AA - CallPilot Integration Suite; SW0221C - ACD/Message Processing, provisioned according to the agent level of the system.
- The Meridian 1 Serial number must be provided when ordering to add CallPilot to an existing Meridian 1 system.

Qty	Order code	Description	
1	NTRG11AC	CallPilot Basic Administration Documentation Package - English	
	Each Package Includes:		
	1	NTRG13AB	CallPilot Telset Guides, English, Quantity 15
	1	NTRG19AD	CallPilot 1 06 Documentation CD-ROM
	1	NTRG20AA	CallPilot Installation Worksheet Package
	1	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25
	1	P0886124	CallPilot Planning and Engineering Guide
	1	P0886126	CallPilot Basic Administration Guide
	1	P0886130	CallPilot Advanced Administration Guide - Volume 1
	1	P0886132	CallPilot Advanced Administration Guide - Volume 2
	1	P0903073	CallPilot Software Installation Guide
	1	P0903074	CallPilot Maintenance and Diagnostic Guide
	1	P0907827	CallPilot What’s New for Release 1 06
1	NTRH9011	14" SVGA Color Monitor	
1	NTRH9048	101 Enhanced Keyboard	
1	NTUB03AA	1001rp North American Base System	
	Each Package Includes:		
	1	NTUB10AA	CallPilot 1001rp Base System
1	NTUB14AB	CallPilot 1 06 Keycode Package	
	Each Package Includes:		
	1	NTDK57AA	Dongle
	1	P0910030	Keycode, CallPilot 1 06
1	NTUB16AA	CallPilot External Modem Kit	
	Each Package Includes:		
	1	A0601464	Modem Cable, 10 Ft DB9 Female to DB25 Male
	1	NTRH9016	External Modem 33 6
1	NTUB22AB	CallPilot 1 06 Tower/Rack Base Server Software Assembly	
	Each Package Includes:		

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems
	1	NT3R9501	Software Assembly, Emergency Repair Disks
	1	NTRH8011	Platform Diskette
	1	NTRH8017	PC Diagnostics 3 48B
	1	NTRH8018	MAS System Report Diskette
	1	NTRH8027	Windows NT 4 0 OS Recovery CD
	1	NTRH8028	CallPilot DOS Floppies
	1	NTRH8033	Windows NT 4 0 Install Diskette
	1	NTRH8043	MAS Admin Client 1 06 SW
	1	NTRH8044	MAS Server 1 06 SW
	1	NTUB40AB	CallPilot 1 06 Server SW CD
	1	NTUB41AB	CallPilot 1 06 Admin Client CD
	1	NTUB42AB	CallPilot 1 06 Desktop Messaging CD (English & French)
	1	NTUB43AB	CallPilot 1 06 PEP SW CD
	1	NTUB44AB	CallPilot 1 06 Language Prompts
	1	NTUB45AB	CallPilot 1 06 Web Messaging CD (Eng&Fr)
1	NTUB42AA	CallPilot Desktop Client CD	
1	NTUB57AB	CallPilot MGate Kit	
	Each Package Includes:		
	1	NTRB18CA	MGate Card
	1	NTRH2012	CallPilot MGate Cable - 20ft
	1	NTRH2013	Dual DSX30XV Interconnect Cable
2	NTZE07AA	CallPilot 4 Voice Channels	
	Each Package Includes:		
	4	NTUB23AA	CallPilot Voice Channel
	2	NTZE06AA	CallPilot MPUs - 2 each
3	NTZE08AA	CallPilot Storage Expansion - 10 hours	
1	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	
2	NTZE16AA	CallPilot Additional Prompt Language	
1	P0907840	CallPilot 1001rp Installation and Maintenance Guide - 1 06	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZE07AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 4 Voice Channels			S1

Notes:

- This item enables 4 Voice Channels. Each Voice Channel requires one MPU.
- NTUB57AA MGate Kits must be provisioned on the Meridian 1 for the Tower and Rack Mount Systems to provide the physical connection for the Channels. Each MGate provides physical connections for 32 Channels. The Tower and Rack Mount Systems come with 1 MGate included in the Base System.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Qty	Order code	Description	Qty	Order code	Description
4	NTUB23AA	CallPilot Voice Channel	2	NTZE06AA	CallPilot MPUs - 2 each

Status
✓ ➤ S

NTZE07BA

Description	System Compatibility	Product compatibility	W/S
CallPilot 2 FAX Channels			S1

Notes:

- This item enables 2 FAX Channels. Each FAX Channel requires 2 MPUs.
- NTUB57AA MGate Kits must be provisioned on the Meridian-1 for the Tower and Rack Mount Systems to provide the physical connection for the Channels. Each MGate provides physical connections for 32 Channels. The Tower and Rack Mount Systems come with 1 MGate included in the Base System.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Qty	Order code	Description	Qty	Order code	Description
2	NTUB23BA	CallPilot FAX Channel	2	NTZE06AA	CallPilot MPUs - 2 each

Status
✓ ➤ S

NTZE07CA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1 Speech Activated Messaging Channel			S1

Notes:

- This item enables 1 Speech Activation Messaging Channel. Each Speech Activated Messaging Channel requires 4 MPUs.
- NTUB57AA MGate Kits must be provisioned on the Meridian-1 for the Tower and Rack Mount Systems to provide the physical connection for the Channels. Each MGate provides physical connections for 32 Channels. The Tower and Rack Mount Systems come with 1 MGate included in the Base System.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Qty	Order code	Description	Qty	Order code	Description
1	NTUB23CA	CallPilot Speech Recognition Channel	1	P0887448	RTU ASR 1500t
2	NTZE06AA	CallPilot MPUs - 2 each			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZE07EA

Description	System Compatibility	Product compatibility	W/S
CallPilot 2 Voice Channels			W0/ S1

Notes:

- Voice channels can be ordered in 2-channel increments up to 24 voice channels. Voice channels must be provisioned in 4-channel increments above 24 channels.

Status
✓ S

NTZE08AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Storage Expansion - 10 hours			W0/ S1

Notes:

- This part number is used with CallPilot IPE, Tower, and Rack Mount Systems.
- The CallPilot IPE, Tower and Rack Mount Base Systems come with 30 hours of storage.
- Order 1 of the part number for each additional 10 storage hour increment required between 30 and 200 hours.
- The CallPilot IPE System has a maximum of 200 hours storage.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE08BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Storage Expansion - 50 Hours			W0/ S1

Notes:

- This part number used with CallPilot Tower and Rack Mount Systems.
- Order one of this package to expand storage in increments of 50 hours from 200 hours to 1000 hours.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE10AA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability -20 Users			W0/ S1

Notes:
- Order one each of this item to add FAX capability to 5 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE10BA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability - 50 Users			W0/ S1

Notes:
- Order one each of this item to add FAX capability to 25 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE10CA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability - 100 Users			W0/ S1

Notes:
- Order one each of this item to add FAX capability to 50 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE10DA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability - 200 Users			W0/ S1

Notes:
- Order one of this item to add FAX capability to 100 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZE10EA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability - 500 Users			W0/ S1

Notes:

- Order one each of this item to add FAX capability to 500 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE10FA

Description	System Compatibility	Product compatibility	W/S
CallPilot FAX Capability - 1000 Users			W0/ S1

Notes:

- Order one each of this item to add FAX capability to 1000 Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE11AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 20 Users			W0/ S1

Notes:

- Order one each of this item to add Desktop Messaging capability to 5 mailboxes.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE11BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 50 Users			W0/ S1

Notes:
- Order one of this item to add Desktop Messaging capability to 25 mailboxes.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE11CA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 100 Users			W0/ S1

Notes:
- Order one each of this item to add Desktop Messaging capability to 50 Users.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE11DA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 200 Users			W0/ S1

Notes:
- Order one each of this item to add Desktop Messaging capability to 100 Users.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE11EA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 500 Users			W0/ S1

Notes:
- Order one each of this item to add Desktop Messaging capability to 500 Users.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZE11FA

Description	System Compatibility	Product compatibility	W/S
CallPilot Desktop Messaging Capability - 1000 Users			W0/ S1

Notes:

- Order one each of this item to add Desktop Messaging capability to 1000 Users.
- CallPilot IPE has a maximum of 1000 Desktop Users. CallPilot Tower and Rackmount systems have a maximum of 5000 Desktop Users.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE12AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 20 Users			W0/ S1

Notes:

- Order one each of this item to add Speech Activated Messaging capability to 5 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE12BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 50 Users			W0/ S1

Notes:

- Order one each of this item to add Speech Activated Messaging capability to 25 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZE12CA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 100 Users			W0/ S1

Notes:
- Order one each of this item to add Speech Activated Messaging capabilities to 50 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE12DA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 200 Users			W0/ S1

Notes:
- Order one each of this item to add Speech Activated Messaging to 100 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE12EA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 500 Users			W0/ S1

Notes:
- Order one each of this item to add Speech Activated Messaging capability to 500 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ ➤ S

NTZE12FA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Capability - 1000 Users			W0/ S1

Notes:
- Order one each of this item to add Speech Activated Messaging capabilities to 1000 mailboxes.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE13AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Networking, 1 to 24 Channels			W0/ S1

Notes:

- Order one of this item to provision Networking for a system with 1 to 24 Channels.
- This order code provisions Enterprise Networking, AMIS Open Networking, AMIS Integrated Networking, and VPIM Networking software.
- Connection to pre-Meridian Mail Release 11 sites requires AMIS. Modem Based Networking is not supported.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE13BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Networking, 25 to 48 Channels			W0/ S1

Notes:

- This order code provisions Enterprise Networking, AMIS Open Networking, AMIS Integrated Networking and VPIM Networking software.
- Order one of this item to provision Networking on a system with 25 to 48 Channels.
- NTZE13AA is a Pre-requisite. NTZE13AA, Networking 1 to 24 Channels must be equipped on an existing system or ordered with this item.
- Connection to pre-Meridian Mail Release 11 sites requires AMIS. Modem Based Networking is not supported.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE13CA

Description	System Compatibility	Product compatibility	W/S
CallPilot Networking, 49 to 96 Channels			W0/ S1

Notes:

- This order code provisions Enterprise Networking, AMIS Open Networking, AMIS Integrated Networking and VPIM Networking software.
- Order one of this item to provision Networking on a system with 49 to 96 Channels. (See Note 3)
- NTZE13AA and NTZE13BA are Pre-requisites. NTZE13AA, Networking 1 to 24 Channels and NTZE13BA, Networking 25 to 48 Channels must either be equipped on an existing system or ordered with this item.
- Connection to pre-Meridian Mail Release 11 sites requires AMIS. Modem Based Networking is not supported.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE14AA

Description	System Compatibility	Product compatibility	W/S
CallPilot NMS Networking, 1 to 24 Channels			W0/ S1

Notes:

- Order one of this item to provision NMS Networking on a system with 1 to 24 Channels.
- This software is needed in the CallPilot System at the Prime site only (There is no Remote Site Software). Up to 59 Remote Sites are supported. The Main and Remote site(s) also require X11 software Option 175 in the Meridian 1.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE14BA

Description	System Compatibility	Product compatibility	W/S
CallPilot NMS Networking, 25 to 48 Channels			W0/ S1

Notes:

- Order one of this item to provision Networking on a system with 25 to 48 Channels.
- NTZE14AA is a Pre-Requisite for this option. NTZE14AA, NMS Networking 1 to 24 Channels must either be equipped on an existing system or ordered with this item.
- This software is needed in the CallPilot System at the Prime site only (There is no Remote Site Software). Up to 59 Remote Sites are supported. The Main and Remote site(s) also require X11 software Option 175 in the Meridian 1.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
✓ S

NTZE14CA

Description	System Compatibility	Product compatibility	W/S
CallPilot NMS Networking, 49 to 96 Channels			W0/ S1

Notes:

- Order one of this item to provision Networking on a system with 49 to 96 Channels.
- NTZE14AA and NTZE14BA are Pre-Requisites for this option. NTZE14AA, NMS Networking 1 to 24 Channels and NTZE14BA, NMS Networking for 25 to 48 Channels must either be equipped on an existing system or ordered with this item.
- This software is needed in the CallPilot System at the Prime site only (There is no Remote Site Software). Up to 59 Remote Sites are supported. The Main and Remote site(s) also require X11 software Option 175 in the Meridian 1.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZE14DA

Description	System Compatibility	Product compatibility	W/S
CallPilot NMS Networking, 1 to 96 Channels			S1

Notes:

- Network Message Service option supports a maximum of 59 remote sites. The main and remote sites also require X11 software option 175 in the Meridian 1.
- NMS supports only Meridian 1 systems.

Status
✓ ➤ S

NTZE15AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Applications Builder FAX Option			W0/ S1

Notes:

- This item adds FAX options to the Applications Builder that comes with the Base System.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
➤ S

NTZE16AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Additional Prompt Language			S1

Notes:

- The CallPilot Base Systems come with the ability to store up to 2 Prompt Languages. Order 1 of this part number for each additional language required up to a maximum of 6 languages.
- This order code is not used for Speech Activated Messaging. See NTZE16BA to add Speech Activated Messaging Vocabularies.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

NTZE16BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Speech Activated Messaging Vocabulary			S1

Notes:

- The CallPilot Base Systems do not come with any Speech Activated Messaging Vocabularies. Order 1 of this option for each Speech activated Messaging Vocabulary needed, up to a maximum of 3 vocabularies per system.
- The IVR ID must be provided when ordering this code.
- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Status
➤ S

NTZE24AA

Description	System Compatibility	Product compatibility	W/S
CallPilot IPE Spares Package			W1

Notes:

- This spares package is intended for use with the CallPilot IPE System.

Qty	Order code	Description	
1	A0738130	128MB DIMM	
1	NTRH09AA	Breakout Panel Assembly	
	Each Package Includes:		
	1	NTRH0910	Break Interconnect Cable (6 Ft)
1	NTRH1407	CallPilot Intermediate SCSI Cable	
1	NTRH1408	CallPilot Intermediate SCSI Cable	
1	NTRH1409	CallPilot Intermediate SCSI Cable	
1	NTRH14AA	200 Series Base System Assembly	
1	NTRH16BA	Hard Drive Data Cable	
1	P0684414	Hard Drive Power Cable	
1	P0875668	Insulating Film	

Status
➤ S

NTZE24BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Tower Spares Package			W1

Notes:

- This spares package is used with the CallPilot Tower System.

Qty	Order code	Description	Qty	Order code	Description
1	A0648379	25 Ft Ethernet Cable, Category 5	1	A0766997	Wide SCSI Terminator
1	A0741574	702t OEM System With no Processor and no Memory	1	A0772567	Wide SCSI Cable
1	A0744456	CallPilot 128 MB DIMM			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZE24CA

Description	System Compatibility	Product compatibility	W/S
CallPilot Rack Mount AC Spares Package			W1

Notes:

- This spares package is used with the CallPilot Rack Mount AC System.

Qty	Order code	Description	
1	A0648379	25 Ft Ethernet Cable, Category 5	
1	A0681873	CallPilot Power Supply AC - Rack System	
1	A0683743	Video Card Adapter	
1	A0732414	CallPilot 1001rp AC OEM System	
	Each Package Includes:		
	1	A0681164	Alarm Status Module
	1	A0681166	AC Power Entry Module
	1	A0681326	Hot-Swap Fan Assembly
	1	A0797941	Rack Rails
	1	NTRH9004	3 5" EIDE Floppy Drive
1	A0735349	128 MB DIMM	
1	A0766182	Dual Pentium II CPU	
1	A0772567	Wide SCSI Cable	
1	NTRH9035	IDE CD-ROM Drive	

Status
➤ S

NTZE24DA

Description	System Compatibility	Product compatibility	W/S
CallPilot Rack Mount DC Spares Package			W1

Notes:

- This spares package is used with the CallPilot Rack Mount DC System.

Qty	Order code	Description	
1	A0648379	25 Ft Ethernet Cable, Category 5	
1	A0683743	Video Card Adapter	
1	A0723663	48V DC 400W Load Sharing Hot Swap Power Supply	
1	A0725949	DC Power Cable for PS400-48 Power Supply	
1	A0732415	CallPilot 1001rp DC OEM System	
	Each Package Includes:		
	1	A0681164	Alarm Status Module
	1	A0681326	Hot-Swap Fan Assembly

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	A0733623	DC Power Entry Module
	1	A0797941	Rack Rails
	1	NTRH9004	3 5" EIDE Floppy Drive
1	A0735349	128 MB DIMM	
1	A0766182	Dual Pentium II CPU	
1	A0772567	Wide SCSI Cable	
1	NTRH9035	IDE CD-ROM Drive	

Status
✓ Δ S

NTZE25AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 4 Voice Channels to 4 Fax Channels			S1

Notes:
- Used on CallPilot systems to convert 4 existing Voice Channels to 4 Fax Channels.
- The systems MPU capacity must be increased through the purchase of additional MPC-8s and/or MBP-16s.
- If 4 or more Voice Channels have been provisioned, at least 4 Voice Channels must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

Status
✓ Δ S

NTZE25BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 4 Voice Channels to 2 Speech Channels			S1

Notes:
- Used on CallPilot systems to convert 4 existing Voice Channels to 2 Speech Channels.
- The systems MPU capacity must be increased through the purchase of additional MPC-8s and/or MBP-16s.
- If 4 or more Voice Channels have been provisioned, at least 4 Voice Channels must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

Status
✓ Δ S

NTZE26AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 4 Fax Channels to 4 Voice Channels			S1

Notes:
- Used on CallPilot systems to convert 4 existing Fax Channels to 4 Voice Channels.
- The systems MPU capacity must be increased through the purchase of additional MPC-8s and/or MBP-16s.
- If 2 or more Fax Channels have been provisioned, at least 2 Fax Channels must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NTZE26BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 2 Fax Channels to 1 Speech Channel			S1

Notes:

- Used on CallPilot systems to convert 2 existing Fax Channels to 1 Speech Channels.
- The systems MPU Capacity is unchanged.
- If 2 or more Fax Channels have been provisioned, at least 2 Fax Channels must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

Status
✓ ➤ Δ S

NTZE27AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 1 Speech Channel to 2 Fax Channels			S1

Notes:

- Used on CallPilot systems to convert 1 existing Speech Channel to 2 Fax Channels.
- The systems MPU Capacity is unchanged.
- If 1 or more Speech Channel has been provisioned, at 1 Speech Channel must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

Status
✓ Δ S

NTZE27BA

Description	System Compatibility	Product compatibility	W/S
CallPilot Conversion 2 Speech Channels to 4 Voice Channels			S1

Notes:

- Used on CallPilot systems to convert 2 existing Speech Channels to 4 Voice Channels.
- If 1 or more Speech Channel has been provisioned, at 1 Speech Channel must be retained on the system.
- The Meridian 1 Serial Number is required when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ S

NTZE29AA

Description	System Compatibility	Product compatibility	W/S
CallPilot to Meridian 1 Integration			S1

Notes:

- Order this option when connecting the CallPilot to a Meridian 1 PBX.
- CallPilot to Meridian 1 Integration Software (NTZE39AA) must be ordered separately.
- This integration kit provides connection capability for 32 channels per kit.
- Maximum of 3 Meridian 1 kits on the CallPilot Tower System. Maximum of 3 Meridian 1 kits on the CallPilot Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	NTRB18CA	MGate Card	1	NTRH2013	Dual DSX30XV Interconnect Cable
1	NTRH2012	CallPilot MGate Cable - 20ft			

Status
★ ➤ Δ S

NTZE29BA

Description	System Compatibility	Product compatibility	W/S
CallPilot to Lucent (2 Wire) Integration			S1

Notes:

- Order one of this option whenever you are connecting the CallPilot to a Meridian 1.
- Lucent Connectivity Cards must be ordered separately.
- Order this option when connecting the CallPilot to a Lucent PBX using 2 wire integration.
- CallPilot to Lucent (2 Wire) Integration Software (NTZE39BA) must be ordered separately.
- This integration kit provides 8 ports per kit.
- Maximum of 2 Lucent (2 Wire) kits on the CallPilot Tower System. Maximum of 7 Lucent (2 Wire) kits on the CallPilot Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	A0766163	CallPilot DSE Extender Cable - 100 Ft	1	NTRH9060	VTG VB2009

Status
★ ➤ Δ S

NTZE29CA

Description	System Compatibility	Product compatibility	W/S
CallPilot to Siemens/Rolm Integration			S1

Notes:

- Order this option when connecting the CallPilot to a Siemens/Rolm PBX.
- CallPilot to Siemens/Rolm Integration Software (NTZE39CA) must be ordered separately.
- This integration kit provides 8 ports per kit.
- Maximum of 2 Siemens/Rolm kits on the CallPilot Tower System. Maximum of 7 Siemens/Rolm kits on the CallPilot Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	A0766163	CallPilot DSE Extender Cable - 100 Ft	1	NTRH9057	VTG VB2002

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

NTZE29DA

Description	System Compatibility	Product compatibility	W/S
CallPilot to Mitel Integration			S1

Notes:

- Order this option when connecting the CallPilot to a Mitel PBX.
- CallPilot to Mitel Integration Software (NTZE39DA) must be ordered separately.
- This integration kit provides 8 ports per kit.
- Maximum of 2 Mitel kits on the CallPilot Tower System. Maximum of 7 Mitel kits on the CallPilot Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	A0766163	CallPilot DSE Extender Cable - 100 Ft	1	NTRH9059	VTG VB2007

Status
★ ➤ Δ S

NTZE29EA

Description	System Compatibility	Product compatibility	W/S
CallPilot to Nortel SL-100 Integration			S1

Notes:

- Order one of this option whenever you are connecting the CallPilot to a Meridian 1.
- T1 Connectivity Cards must be ordered separately.
- Order this option when connecting the CallPilot to a SL-100 PBX.
- CallPilot to SL-100 Integration Software (NTZE39EA) must be ordered separately.
- Maximum of 2 SL-100 kits on the CallPilot Tower System. Maximum of 2 SL-100 kits on the Call Pilot Rack Mount System.

Qty	Order code	Description	Qty	Order code	Description
1	A0788107	T1 2 Pair Cable with RJ48 Connector	1	NTRH9065	Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card

Status
➤ S

NTZE30AA

Description	System Compatibility	Product compatibility	W/S
CallPilot Integration Suite			W0

Notes:

- The Meridian 1 Serial number must be provided when ordering as part of a CallPilot addition with an existing Meridian 1 system or when adding to an existing CallPilot.

Qty	Order code	Description	Qty	Order code	Description
1	SW0223A	Enhanced ACD Routing	1	SW0227A	Hold in Queue for IVR
1	SW0225B	Enhanced Call Center Routing			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ S

NTZE31AA

Description	System Compatibility	Product compatibility	W/S
IPE CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit			S1

Notes:
- The CallPilot 1.07 Base Documentation Package should also be ordered.

Qty	Order code	Description	Qty	Order code	Description
1	NTUB20AD	CallPilot 1 07 IPE Base Server Software Assembly	1	P0912484	Keycode, CallPilot 1 07

Status
★ ➤ S

NTZE31BA

Description	System Compatibility	Product compatibility	W/S
Tower/Rack CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit			S1

Notes:
- The CallPilot 1.07 Base Documentation Package should be ordered with this upgrade.

Qty	Order code	Description	Qty	Order code	Description
1	NTUB22AD	CallPilot 1 07 Base Software Assembly	1	P0912484	Keycode, CallPilot 1 07

Status
⊗ S

NTZE39AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 to Meridian 1 Integration Software			S1

Notes:
- One (1) of this option is required when connecting a CallPilot 1.07 system to a Meridian 1 PBX.

Status
★ ⊗ S

NTZE39BA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 to Lucent (2 Wire) Integration Software			S1

Notes:
- One (1) of this option is required when connecting a CallPilot 1.07 system to a Lucent (2 Wire) PBX.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ S

NTZE39CA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 to Siemens/Rolm Integration Software			S1

Notes:
- One (1) of this option is required when connecting a CallPilot 1.07 system to a Siemens/Rolm PBX.

Status
★ ⊗ S

NTZE39DA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 to Mitel Integration Software			S1

Notes:
- One (1) of this option is required when connecting a CallPilot 1.07 system to a Mitel PBX.

Status
★ ⊗ S

NTZE39EA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 to SL-100 Integration Software			S1

Notes:
- One (1) of this option is required when connecting a CallPilot 1.07 system to a SL-100 PBX.

Status
★ ➤ Δ S

NTZE4002

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Upgrade Ordering Code			W1

Notes:
- This code is required for upgrades from Release 1.05/6 to Release 1.07, feature expansions, and dongle replacements.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ S

NTZE80AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 IPE Base Package			W1/ S1

Notes:

- Package includes a Windows NT Certificate of Authenticity and RTU licenses for Windows NT Server, DOS 6.2, SQL Anywhere and pcAnywhere32.
- Meridian 1 has hardware and software prerequisites, check the ordering bulletin.
- Package includes 200 hours of storage, 6 prompt languages and 3 speech recognition vocabularies and 24 MPU.
- Package no longer includes mailboxes, 5 desktop messaging seats, modem, MBP-16, MGate card, documentation, monitor, keyboard and mouse. These must be ordered separately.
- CallPilot IPE is applicable only to Meridian 1 systems.

Qty	Order code	Description	
1	NTDK57AA	Dongle	
1	NTRG19AC	CallPilot 1 07 Documentation CD-ROM	
1	NTRH09AA	Breakout Panel Assembly	
	Each Package Includes:		
	1	NTRH0910	Break Interconnect Cable (6 Ft)
1	NTUB01AD	CallPilot 1 07 IPE Base H/W Package	
1	NTUB20AD	CallPilot 1 07 IPE Base Server Software Assembly	
1	NTZE08CA	CallPilot Storage 200 hours	
1	NTZE16AB	CallPilot Voice Prompt Languages - 6 different languages	
1	NTZE16BB	CallPilot Speech Activated Messaging Vocabulary - 3	

Status
★ ⊗ S

NTZE81AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 702t Base Package			W1/ S1

Notes:

- Package includes a Windows NT Certificate of Authenticity and RTU licenses for Windows NT Server, DOS 6.2, SQL Anywhere and pcAnyhwhere32.
- If connecting to a Meridian 1, there are hardware and software prerequisites required, check the ordering bulletin.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTZE08DA	CallPilot Storage 1000 Hours
1	NTRG19AC	CallPilot 1 07 Documentation CD-ROM	1	NTZE16AB	CallPilot Voice Prompt Languages - 6 different languages
1	NTUB02AC	CallPilot 1 07 702t Base Hardware Package	1	NTZE16BB	CallPilot Speech Activated Messaging Vocabulary - 3
1	NTUB22AD	CallPilot 1 07 Base Software Assembly			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ S

NTZE82AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 1001rp DC Base Package			W1/ S1

Notes:

- Package includes a Windows NT Certificate of Authenticity and RTU licenses for Windows NT Server, DOS 6.2, SQL Anywhere and pcAnywhere32.
- If connecting to a Meridian 1, there are hardware and software prerequisites required, check the ordering bulletin.
- Package includes 1,000 hours of storage, 6 prompt languages and 3 speech recognition, vocabularies and 24 MPU.
- Package no longer includes mailboxes, 5 desktop messaging seats, modem, MBP-16, MGate card, documentation, monitor, keyboard and mouse. These must be ordered separately.
- RAID-1 controller and disks are included in the Rackmount Base Package.
- Cabling from the DC power source to PDU of DC Rackmount is not included.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTZE08DA	CallPilot Storage 1000 Hours
1	NTRG19AC	CallPilot 1 07 Documentation CD-ROM	1	NTZE16AB	CallPilot Voice Prompt Languages - 6 different languages
1	NTUB04AC	CallPilot 1 07 1001rp DC Base Hardware Package	1	NTZE16BB	CallPilot Speech Activated Messaging Vocabulary - 3
1	NTUB22AD	CallPilot 1 07 Base Software Assembly			

Status
★ ⊗ S

NTZE83AA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 1001rp AC Base Package			W1/ S1

Notes:

- Package includes a Windows NT Certificate of Authenticity and RTU licenses for Windows NT Server, DOS 6.2, SQL Anywhere and pcAnywhere32.
- If connecting to a Meridian 1, there are hardware and software prerequisites required, check the ordering bulletin.
- Package includes 1,000 hours of storage, 6 prompt languages and 3 speech recognition vocabularies and 24 MPU.
- Package no longer includes mailboxes, 5 desktop messaging seats, modem, MBP-16, MGate card, documentation, monitor, keyboard and mouse. These must be ordered separately.
- RAID-1 controller and disks are included in the Rackmount Base package.

Qty	Order code	Description	Qty	Order code	Description
1	NTDK57AA	Dongle	1	NTZE08DA	CallPilot Storage 1000 Hours
1	NTRG19AC	CallPilot 1 07 Documentation CD-ROM	1	NTZE16AB	CallPilot Voice Prompt Languages - 6 different languages
1	NTUB03AC	CallPilot 1 07 1001rp AC Base Hardware - 500 Wat	1	NTZE16BB	CallPilot Speech Activated Messaging Vocabulary - 3
1	NTUB22AD	CallPilot 1 07 Base Software Assembly			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ Δ S

NTZE99BA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, DSE Connectivity Option - Lucent 2 Wire			W1

Notes:
- Package provides 8 channels of connectivity.

Qty	Order code	Description	
1	NTZE29BA	CallPilot to Lucent (2 Wire) Integration	
	Each Package Includes:		
	1	A0766163	CallPilot DSE Extender Cable - 100 Ft
	1	NTRH9060	VTG VB2009

Status
★ ⊗ Δ S

NTZE99CA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, DSE Connectivity Option - Siemens/ROLM			W1

Notes:
- Package provides 8 channels of connectivity.

Qty	Order code	Description	
1	NTZE29CA	CallPilot to Siemens/Rolm Integration	
	Each Package Includes:		
	1	A0766163	CallPilot DSE Extender Cable - 100 Ft
	1	NTRH9057	VTG VB2002

Status
★ ⊗ Δ S

NTZE99DA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, DSE Connectivity Option - Mitel			W1

Notes:
- Package provides 8 channels of connectivity.

Qty	Order code	Description	
1	NTZE29DA	CallPilot to Mitel Integration	
	Each Package Includes:		
	1	A0766163	CallPilot DSE Extender Cable - 100 Ft
	1	NTRH9059	VTG VB2007

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ⊗ Δ S

NTZE99EA

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 GB, T1 (SL-100) Connectivity Option - SL-100			W1

Notes:

- Package provides 48 channels of connectivity.

Qty	Order code	Description	
1	NTZE29EA	CallPilot to Nortel SL-100 Integration	
	Each Package Includes:		
	1	A0788107	T1 2 Pair Cable with RJ48 Connector
	1	NTRH9065	Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card

Status
† ➤ S

NTZK14AA

Description	System Compatibility	Product compatibility	W/S
OIVR 2 x Hardware - MRS/Tower or MRS/ Rack Disk Drive (1.05GB)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Open IVR	W1

Notes:

- Compatible with OPEN IVR 2.X hardware running OPEN IVR 2.X software.
- The 1.05GB drive can accommodate approximately 96 hours of voice storage at a sampling rate of 24 kbs.
- These disks do not have operating system software installed on them. This is the reason for the difference in storage between the base system disk drives and these optional drives.
- The MRS/Tower and MRS/Rack can have any combination of disks up to a maximum of four. The base system includes one hard disk.
- This package is used only for disk storage expansion and sparing and is compatible with OPEN IVR 2.01 and 2.5 systems, including those upgraded to OPEN IVR 4.0.
- It cannot be used in conjunction with disk mirroring.

Qty	Order code	Description	Qty	Order code	Description
1	A0639225	MRS Tower/Rack Disk Drive (1 05GB)	1	A0680176	MRS/Tower Disk Mounting Brackets

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK20AA35

Description	System Compatibility	Product compatibility	W/S
Meridian M2016S Secure Telephone, Basic, Ash	21; 21A; 21E; 51; 61; 61C; 71; 81; NT; RT; ST; STE; XN; XT		W1

Notes:

- Requires X11 Release 14 and later software.
- Meridian Modular Telephones are backward compatible to all QPC578 vintages.
- The M2112, M2317 and M3000 wall transformer is not compatible with Meridian Modular Telephones. Likewise, the Meridian Modular Telephone wall transformer will damage M2112, M2317 and M3000 sets.
- Includes Power Supply Board. Requires Transformer, 110V (A0367355) or compatible. Nortel does not market a Meridian Modular Telephone compatible power source (QUT1 is NOT compatible).

Status
➤ S

NTZK29AA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, MCA M2216 and Documentation Package 5A (1-19 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F29BB	FastView+ Software (New), MCA, M2216 and Documentation			

Status
➤ S

NTZK29BA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5B (20-49 Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F29BB	FastView+ Software (New), MCA, M2216 and Documentation			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK29CA

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5C (50+ Units)			W1/ S3

Qty	Order code	Description	Qty	Order code	Description
1	NT1F29BB	FastView+ Software (New), MCA, M2216 and Documentation			

Status
➤ S

NTZK37AD

Description	System Compatibility	Product compatibility	W/S
MAT 4 Single Location Distributor Station Administration	11 X11 R23; 11C X11 R23; 11E X11 R23; 21 X11 R23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,17,18,19,20,21,22; RT X11 R14,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		W0/ S3

Notes:

- Distributor Common Services supports 253 Meridian 1 systems/sites.
- Meridian Software License for MAT Single Location with Multiple Users grants the rights to make copies of MAT Distributor Common Services and Station Administration for use by Customer Service Representatives within a single Customer Service Center location.
- Includes one (1) Distributor Common Services, one (1) Station Administration, one (1) Common Services User Guide and one (1) Station Administration User Guide.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK37BD

Description	System Compatibility	Product compatibility	W/S
Mat 4 Multi Location Distribution Station Administration	11 X11 R18,22,23; 11C X11 R22,23; 11E X11 R23; 21 X11 R17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		W0/ S3

Notes:

- Distributor Common Services supports 253 Meridian 1 systems/sites.
- Meridian Software License for MAT Multi-Location with Multiple Users grants the right to make copies of MAT Distributor Common Services and Station Administration for use by Customer Service Representatives supporting any Customer Service Center location within the fifty states and the District of Columbia.
- Includes one (1) Distributor Common Services, one (1) Station Administration, one (1) Common Services User Guide and one (1) Station Administration User Guide.

Status
➤ S

NTZK38AD

Description	System Compatibility	Product compatibility	W/S
MAT 4 End User Single Site Package	11 X11 R18,22,23; 11C X11 R23; 11E X11 R23; 21 X11 R15,16,17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:

- Common Services is required for all modules.
- Single site supports a single Meridian 1 system/site.
- Includes one (1) Single-Site Common Services and one (1) Common Services User Guide.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK38BD

Description	System Compatibility	Product compatibility	W/S
MAT End User Multi Site Package	11 X11 R18,22,23; 11C X11 R22,23; 11E X11 R23; 21 X11 R15,16,17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Common Services is required for all modules.
- Multi-site supports three (3) Meridian 1 systems/sites.
- Includes one (1) Single-Site Common Services and one (1) Common Services User Guide.

Status
➤ S

NTZK39AD

Description	System Compatibility	Product compatibility	W/S
MAT Single to Multi Site Expansion	11 X11 R18,22,23; 11C X11 R22,23; 11E X11 R23; 21 X11 R15,16,17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Expands Single Site Common Services to Multi-site Common Services

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK39BD

Description	System Compatibility	Product compatibility	W/S
MAT Multi Site Expansion	11 X11 R18,22,23; 11C X11 R22,23; 11E X11 R23; 21 X11 R15,16,17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Each Multi-site Expansion adds support for five (5) additional Meridian 1 systems/sites.
- Maximum limit is 253 sites.

Status
➤ S

NTZK39CD

Description	System Compatibility	Product compatibility	W/S
MAT Multi Site Expansion Cap	11 X11 R18,22,23; 11C X11 R22,23; 11E X11 R23; 21 X11 R15,16,17,22,23; 21A X11 R23; 21E X11 R18,19,20,21,22,23; 51 X11 R15,16,17,18,19,20,21,22,23; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22,23; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22,23; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Added to Multi-site Common Services to support 253 Meridian 1 systems/sites.
- Cost effective above 40 additional sites or Multi-site Expansions.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK40AD

Description	System Compatibility	Product compatibility	W/S
MAT Station Administration Module	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires a Common Services.
- For both end-users and distributors.
- Includes one (1) Station Administration and one (1) Station Administration User Guide.

Status
➤ S

NTZK41AD

Description	System Compatibility	Product compatibility	W/S
MAT Traffic Analysis Module	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires a Common Services.
- For both end-users and distributors.
- Includes one (1) Traffic Analysis and one (1) Traffic Analysis User Guide.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK42AD

Description	System Compatibility	Product compatibility	W/S
MAT Call Tracking Module	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires a Common Services.
- For both end-users and distributors.
- Includes one (1) Call Tracking and one (1) Call Tracking User Guide.

Status
➤ S

NTZK43AD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Module Base	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires a Common Services.
- For both end-users and distributors.
- Support up to 100 DNs per Meridian 1 system/site.
- Includes Call Tracking Module.
- Must also order North American Rate Table (NTZK44AA).
- Includes one (1) Call Accounting Base, one (1) Call Tracking, one (1) Call Accounting User Guide and one (1) Call Tracking User Guide.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK44AD

Description	System Compatibility	Product compatibility	W/S
MAT North American Sample Rate Table	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Supports basic carriers for US and Canada.
- Only to be ordered with NTZK43AA, new Call Accounting System, not intended to be used for updates.
- See MAT Distributor Reference Guide for recommendations on updates.

Status
➤ S

NTZK45BD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Small Expansion	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Adds support for 500 additional DNs to Call Accounting Base Module.
- Requires MAT Call Accounting Base Module.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK45CD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Medium Expansion	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires MAT Call Accounting Base Module.
- Adds support for 1000 additional DNs to Call Accounting Base Module.

Status
➤ S

NTZK45DD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Large Expansion	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires MAT Call Accounting Base Module.
- Adds support for 5000 additional DNs to Call Accounting Base Module.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK45ED

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Expansion Cap	11 X11 R18,22; 11C X11 R22,23; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22,23; 61 X11 R17,18,19,22; 61C X11 R20,21,22,23; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22,23; 81C X11 R22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Requires MAT Call Accounting Base Module.
- Adds support to 10000 DN maximum in Call Accounting Base Module.

Status
➤ S

NTZK45FD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Mini Expansion	11 X11 R18,22; 11C X11 R22,23; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22,23; 61 X11 R17,18,19,22; 61C X11 R20,21,22,23; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22; 81C X11 R23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK46AD

Description	System Compatibility	Product compatibility	W/S
MAT Distributor Single Location Station Administration Upgrade	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Upgrades MAT Distributor Single Location Station Administration Package.
- Includes one (1) Distributor Common Services Upgrade, one (1) Station Administration Upgrade, one (1) Common Services User Guide, one (1) Station Administration User Guide and one (1) Single Location License.

Status
➤ S

NTZK46BD

Description	System Compatibility	Product compatibility	W/S
MAT Distributor Multi-Location Station Administration Upgrade	11 X11 R18,22; 11C X11 R22,23; 21 X11 R15,16,17,22; 21E X11 R18,19,20,21,22; 51 X11 R15,16,17,18,19,20,21,22; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21,22; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21,22; 81 X11 R18,19,20,21,22,23; 81C X11 R20,21,22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Upgrades MAT Distributor Multi-Location Station Administration Package.
- Includes one (1) Distributor Common Services Upgrade, one (1) Station Administration Upgrade, one (1) Common Services User Guide, one (1) Station Administration User Guide and one (1) Multi-Location License.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK47AD

Description	System Compatibility	Product compatibility	W/S
MAT Single Site Common Services Upgrade	11 X11 R18,22; 11C X11 R22; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22; 61 X11 R17,18,19,22; 61C X11 R20,21,22; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22; 81C X11 R22; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Upgrades MAT Single Site Common Services.
- Any module upgrade must be accompanied by an upgrade in Common Services.
- All modules must be at the same release level.
- Includes one (1) Single-site Common Services Upgrade and one (1) Common Services User Guide.

Status
➤ S

NTZK47BD

Description	System Compatibility	Product compatibility	W/S
MAT Multi Site Common Services Upgrade	11 X11 R18,22; 11C X11 R22,23; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22,23; 61 X11 R17,18,19,22; 61C X11 R20,21,22,23; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22,23; 81C X11 R22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Any module upgrade must be accompanied by an upgrade in Common Services.
- All modules must be at the same release level.
- Upgrades MAT Multi-Site Common Services.
- Includes one (1) Multi-site Common Services Upgrade and one (1) Common Services User Guide.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK48AD

Description	System Compatibility	Product compatibility	W/S
MAT Station Administration Upgrade	11 X11 R18,22; 11C X11 R22,23; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22,23; 61 X11 R17,18,19,22; 61C X11 R20,21,22,23; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22,23; 81C X11 R22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Any module upgrade must be accompanied by an upgrade in Common Services.
- All modules must be at the same release level.
- Upgrades MAT Station Administration Module.
- Includes one (1) Station Administration Upgrade and one (1) Station Administration User Guide.

Status
➤ S

NTZK49AD

Description	System Compatibility	Product compatibility	W/S
MAT Traffic Analysis Upgrade	11 X11 R18,22; 11C X11 R22; 21 X11 R17,22; 21E X11 R18,19,20,21,22; 51 X11 R17,18,19,22; 51C X11 R20,21,22; 61 X11 R17,18,19,22; 61C X11 R20,21,22; 71 X11 R17,18,19,22; 81 X11 R18,19,20,21,22; 81C X11 R22; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Notes:
- Any module upgrade must be accompanied by an upgrade in Common Services.
- All modules must be at the same release level.
- Upgrades MAT Traffic Analysis Module.
- Includes one (1) Traffic Analysis Upgrade and one (1) Traffic Analysis User Guide.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK50AD

Description	System Compatibility	Product compatibility	W/S
MAT Call Tracking Upgrade	11C X11 R22,23; 51C X11 R22,23; 61C X11 R22,23; 81 X11 R23; 81C X11 R22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Status
➤ S

NTZK51AD

Description	System Compatibility	Product compatibility	W/S
MAT Call Accounting Base Upgrade	11C X11 R22,23; 51C X11 R22,23; 61C X11 R22,23; 81 X11 R23; 81C X11 R22,23; NT X11 R14,15,16,17,18,19,20,21,22; RT X11 R14,15,16,17,18,19,20,21,22; ST X11 R14,15,16,17,22; STE X11 R18,19,20,21,22; XT X11 R14,15,16,17,18,19,20,21,22		S3

Status
➤ S

NTZK52BA

Description	System Compatibility	Product compatibility	W/S
MDR 2000 Buffer Box 128Kb (117vac/ 60Hz)			W3

Notes:

- Includes one (1) Buffer Box 128Kb and one (1) MDR 2000 Quick Reference.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZK52CA

Description	System Compatibility	Product compatibility	W/S
MDR 2000 Buffer Box 512Kb (117vac/ 60Hz)			W3

Notes:
- Includes one (1) Buffer Box 512Kb and one (1) MDR 2000 Quick Reference.

Status
➤ S

NTZK52DA

Description	System Compatibility	Product compatibility	W/S
MDR 2000 Buffer Box 2 Mb (117vac/ 60Hz)			W3

Notes:
- Includes one (1) Buffer Box 2MB and 1 MDR 2000 Quick Reference.

Status
➤ S

NTZR07BA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant PC	11 X11 R16,18; 11C X11 R22,23; 11E X11 R20,21; 21 X11 R15,16,17; 21A X11 R15,16,17; 21E X11 R18,19,20,21; 51 X11 R15,16,17,18,19,20,21; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21; 81 X11 R18,19,20,21,22,23; 81C X11 R21,22,23		W1

Notes:
- One Meridian 1 Attendant PC package must be purchased for each attendant position.
- Customer provided, Windows 95 PC is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

NTZR09BA

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Attendant PC LAN Interface Module	11 X11 R16,18; 11C X11 R22,23; 11E X11 R20,21; 21 X11 R15,16,17; 21A X11 R15,16,17; 21E X11 R18,19,20,21; 51 X11 R15,16,17,18,19,20,21; 51C X11 R20,21,22,23; 61 X11 R15,16,17,18,19,20,21; 61C X11 R20,21,22,23; 71 X11 R15,16,17,18,19,20,21; 81 X11 R18,19,20,21,22,23; 81C X11 R21,22,23		W1

Notes:

- One Meridian 1 Attendant PC LAN Interface Module supports multiple Meridian 1 Attendant PC positions in a Local Area Network environment.

Status
➤ S

NTZR50AA03

Description	System Compatibility	Product compatibility	W/S
Blank Brandline Insert, Black (Package of 250 P0784403) (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W0

Status
➤ S

NTZR50AA35

Description	System Compatibility	Product compatibility	W/S
Blank Brand Line Insert, Ash, (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W0

Status
➤ S

NTZR50AA93

Description	System Compatibility	Product compatibility	W/S
Blank Brand Line Insert, Gray (Package of 250 P0784493) (M2000 Series)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

NTZR57CA

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Release 13 Base Software		Meridian Mail Modular Option; Meridian Mail Modular Option EC; Meridian Mail Modular Option GP	W0

Notes:

- If Integrated Mailbox Administration feature is to be used, X11 Release 19.2 or later software is required.
- The Meridian 1 Serial number must be provided when ordering this code as an addition to an existing PBX.
- A maximum of four (4) languages are available per system. If additional languages not included on this tape are needed, you must order the appropriate Meridian Mail Release 13 master tape that contains the desired language.
- All new systems require Meridian Mail Base Software.

Qty	Order code	Description	
1	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	
	Each Package Includes:		
	1	P0904495	Voice Messaging User Guide - MM13
	1	P0904496	Voice Messaging Quick Reference Card - MM13
1	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	
1	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	
1	NT6R47AD	MM13 13 Master Tape NA 1	
1	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	
1	P0735064	Controlling Access Privileges Workbook	
1	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	
1	P0875903	Meridian Mail Release 12 Voice Services Application Guide	
1	P0875922	Meridian Mail Release 12 System Administration Tools Guide	
1	P0904493	Maintenance Messages (SEERs) - MM13	
1	P0904567	What's New In Meridian Mail Release 13	
1	P0907072	PC Application Guide - MM13	
1	P0907146	Meridian Mail Release 13 Feature Operations Video	

Status
† ➤ S

P0639984

Description	System Compatibility	Product compatibility	W/S
Adapter Plate for SDI Filter Connector	LE (23, 96); MS; N; NT; XL (24, 97); XN; XT		W1

Status
† ➤ S

P0641477

Description	System Compatibility	Product compatibility	W/S
Mounting Bracket Lower SDI Connector	RT; S; ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

P0642917

Description	System Compatibility	Product compatibility	W/S
50 Pin Connector Cover Plate	LE (23); M; MS; N; NT; XL (24); XN; XT		W1

Notes:
- Requires two (2) push fasteners (P0656064) to mount cover plate.

Status
➤ S

P0643763

Description	System Compatibility	Product compatibility	W/S
Filter, PRI/DTI I/O	MS; N; NT; XN; XT		W1

Status
➤ S

P0649968

Description	System Compatibility	Product compatibility	W/S
Ribbon Cable, RS232, (Male/Male) 25 Pin, Straight-Through (6 Ft.)	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ N

P0652720

Description	System Compatibility	Product compatibility	W/S
Telephone Number Lens (1 each, Standard for all Meridian Digital Telephones and Attendant Consoles) (M2000 Series)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W1

Status
➤ S

P0660405

Description	System Compatibility	Product compatibility	W/S
Field Failure Report Tag (Telephone and Console Equipment)	A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

P0677580

Description	System Compatibility	Product compatibility	W/S
Cabinet Grounding Package #1	LE (23); XL (24)		W1

Status
† ➤ S

P0677587

Description	System Compatibility	Product compatibility	W/S
Cabinet Grounding Package #2	LE (96); M; MS; N; NT; XL (97); XN; XT		W1

Status
† ➤ S

P0677588

Description	System Compatibility	Product compatibility	W/S
Cabinet Grounding Package #3	LE (96); M; MS; N; NT; XL (97); XN; XT		W1

Status
➤ S

P0678258

Description	System Compatibility	Product compatibility	W/S
Filter Connector	RT; ST; STE		W1

Status
✓ ➤ N

P0680793

Description	System Compatibility	Product compatibility	W/S
Wall Mount Handset Clip (1 each, for all Meridian Digital Telephones)		M2006; M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ S

P0684414

Description	System Compatibility	Product compatibility	W/S
Hard Drive Power Cable			W1

Notes:
- The pricing for this part is provided for spares purposes only. This part is only a piece of the main system and is no use on its own.

Status
➤ S

P0691037

Description	System Compatibility	Product compatibility	W/S
Ground Lug	11E		W1

Notes:
- One of these is required per cabinet when a fiber connection is used between cabinets.
- Main cabinets ship with one already installed, as do all current expansion cabinets. Some older expansion cabinets did not include ground lugs.

Status
➤ S

P0694698

Description	System Compatibility	Product compatibility	W/S
Key Cap, Orange with Clear Window (1 each, Standard for all Meridian)		M1250; M2250	W0

Status
➤ S

P0695167

Description	System Compatibility	Product compatibility	W/S
CRT Cable		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0695169

Description	System Compatibility	Product compatibility	W/S
SCSI Daisychain Cable		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

P0695822

Description	System Compatibility	Product compatibility	W/S
AML Link Cable		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
➤ S

P0695823

Description	System Compatibility	Product compatibility	W/S
NVP Daisychain Cable		Meridian Mail GP; Meridian Mail MP; Meridian Mail Modular Option; Meridian Mail Option S; Meridian Mail Option X; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT); Meridian Mail SP	W1

Status
† ➤ S

P0696547

Description	System Compatibility	Product compatibility	W/S
Connector Housing (Side Panel)	LE (23, 96); M; MS; N; NT; VLE; XL (24, 97); XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

P0697550

Description	System Compatibility	Product compatibility	W/S
Connector Adapter Bracket	S		W1

Status
† ➤ S

P0697559

Description	System Compatibility	Product compatibility	W/S
Mounting Bracket	S		W1

Status
† ➤ S

P0697707

Description	System Compatibility	Product compatibility	W/S
Connector Cover Panel	S		W1

Status
➤ S

P0699124

Description	System Compatibility	Product compatibility	W/S
Designation Tabs (1 each, M2250/M1250)		M1250; M2250	W0

Status
➤ S

P0699798

Description	System Compatibility	Product compatibility	W/S
Cooling Unit Filter Assembly	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0699851

Description	System Compatibility	Product compatibility	W/S
Top Cap Cable Egress Panel	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

P0700563

Description	System Compatibility	Product compatibility	W/S
Key Cap, Red with Clear Window (1 each, Standard for all Meridian)		M1250; M2250	W0

Status
➤ S

P0701352

Description	System Compatibility	Product compatibility	W/S
Earthquake Bracing Rod (3 Module)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

P0701353

Description	System Compatibility	Product compatibility	W/S
Earthquake Bracing Rod (4 Module)	21; 21A; 21E; 51; 61; 61C; 71; 81		W1

Status
† ➤ S

P0702380

Description	System Compatibility	Product compatibility	W/S
Connector Housing (Top Panel)	LE (96); MS; N; NT; XL (97); XN; XT		W1

Status
† ➤ S

P0703905

Description	System Compatibility	Product compatibility	W/S
Connector Adapter Panel Housing	LE (23, 96); M; MS; N; NT; VLE; XL (24, 97); XN; XT		W1

Notes:
- Requires 1 per P0703906.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

P0703906

Description	System Compatibility	Product compatibility	W/S
Adapter Housing	LE (23, 96); M; MS; N; NT; VLE; XL (24, 97); XN; XT		W1

Notes:
- Requires 1 per P0703905.

Status
† ➤ S

P0703960

Description	System Compatibility	Product compatibility	W/S
DTI/PRA Adapter Plate Package	MS; N; NT; XN; XT		W1

Status
† ➤ S

P0703961

Description	System Compatibility	Product compatibility	W/S
SDI Adapter Plate Package	LE (23, 96); M; MS; N; NT; S; VLE; XL (24, 97); XN; XT		W1

Status
➤ S

P0704511

Description	System Compatibility	Product compatibility	W/S
Connector Housing Package	LE (96); MS; N; NT; XL (97); XN; XT		W1

Notes:
- Includes P0703846 and P0703847.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ N

P0705801

Description	System Compatibility	Product compatibility	W/S
Clear Feature Key Caps (1 each, standard for M2000 Series and Attendant Consoles)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W1

Status
➤ Δ S

P0722849

Description	System Compatibility	Product compatibility	W/S
Designation Label, EMSI	21; 21E; 51; 61; 71		W1

Status
➤ Δ S

P0722850

Description	System Compatibility	Product compatibility	W/S
Designation Label, EMSI	NT; RT; ST; STE; XT		W1

Status
➤ S

P0723443

Description	System Compatibility	Product compatibility	W/S
Power Supply Board Cable (M2000 Series)			W0

Notes:

- Required for Power Supply Boards (NT2K10WC and below) installed on M2006 (NT2K05GXXX), M2008 (NT2K08GXXX) and M2616 (NT2K16GXXX) telephones.

Status
➤ S

P0723459

Description	System Compatibility	Product compatibility	W/S
Blank Packlet for EOI		Fiber Remote	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0727842

Description	System Compatibility	Product compatibility	W/S
EMI Shield (Plastic Type)	21; 21E; 61; 61C; 71; 81; NT; RT; ST; STE; XT		W1

Status
➤ S

P0727843

Description	System Compatibility	Product compatibility	W/S
EMI Shield (Metal Type)	61; 61C; 71; 81; NT; XT		W1

Status
➤ S

P0729843

Description	System Compatibility	Product compatibility	W/S
Spare Circuit Breaker Kit, 5 Amp		MFA150; MPP600	W1

Status
➤ S

P0729846

Description	System Compatibility	Product compatibility	W/S
Spare Circuit Breaker Kit, 20 Amp		MFA150; MPP600	W1

Status
➤ S

P0729847

Description	System Compatibility	Product compatibility	W/S
Spare Circuit Breaker Kit, 30 Amp		MFA150; MPP600	W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0730064

Description	System Compatibility	Product compatibility	W/S
Lug Kit, Screw-Type #8	21; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

P0730252

Description	System Compatibility	Product compatibility	W/S
MFA Spare Fuse Kit	21; 21E; 51; 61; 61C; 71; 81		W1

Status
➤ S

P0731813

Description	System Compatibility	Product compatibility	W/S
Quick Installation Pre-Printed Keycaps (10 Cards of 10 Pre-Printed Keycaps)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616; M3000	W0

Status
➤ S

P0733203

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Logo Insert (Aqua Blue)	21; 21A; 51; 51C; 61; 61C; 71; 81; 81C		W0

Status
† ➤ S

P0738600

Description	System Compatibility	Product compatibility	W/S
Display Option Cable			W0

Notes:

- Required when Meridian Display Option (NT2K24XX) or Special Applications display (NT2K25XX) are installed on a M2008 (NT2K08GXXX) Telephone.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ S

P0738866

Description	System Compatibility	Product compatibility	W/S
Label Kit for Inter-Cabinet Cables	81; XN; XT (QCA55)		W1

Status
➤ S

P0741489

Description	System Compatibility	Product compatibility	W/S
Backplane Cable Extraction Tool	81		W1

Status
➤ S

P0744873

Description	System Compatibility	Product compatibility	W/S
System 600/48 Isolation Kit	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0745713

Description	System Compatibility	Product compatibility	W/S
Growth I/O Panel	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

Status
➤ S

P0745716

Description	System Compatibility	Product compatibility	W/S
Universal I/O Panel	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0746602

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 5 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0746603

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 10 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0746604

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 15 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0746605

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 20 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0746607

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 30 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ S

P0746608

Description	System Compatibility	Product compatibility	W/S
Circuit Breaker Kit, 50 AMP - 600/48	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0768143

Description	System Compatibility	Product compatibility	W/S
Attendant Administration Overlay		M1250; M2250	W0

Status
➤ S

P0780103

Description	System Compatibility	Product compatibility	W/S
Single Key Expansion Module Footstand, Black (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

Status
➤ S

P0780135

Description	System Compatibility	Product compatibility	W/S
Single Key Expansion Module Footstand, Ash, (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

Status
➤ S

P0780193

Description	System Compatibility	Product compatibility	W/S
Single Key Expansion Module Footstand, Gray, (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0780203

Description	System Compatibility	Product compatibility	W/S
Double Key Expansion Module Footstand, Black (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

Status
➤ S

P0780235

Description	System Compatibility	Product compatibility	W/S
Double Key Expansion Module Footstand, Ash (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

Status
➤ S

P0780293

Description	System Compatibility	Product compatibility	W/S
Double Key Expansion Module Footstand, Gray (M2000 Series)		M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Does not support ATA (NT2K68xx) or MCA (NT2K69xx).

Status
➤ S

P0784503

Description	System Compatibility	Product compatibility	W/S
Top Cover Filler Plate, Black (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S)		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.
- For use on Meridian Modular Telephones when display is removed.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0784535

Description	System Compatibility	Product compatibility	W/S
Top Cover Filler Plate, Ash (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S)		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.
- For use on Meridian Modular Telephones when display is removed.

Status
➤ S

P0784593

Description	System Compatibility	Product compatibility	W/S
Top Cover Filler Plate, Gray (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S)		M2008; M2016S; M2216 ACD-1; M2216 ACD-2; M2616	W1

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.
- For use on Meridian Modular Telephones when display is removed.

Status
➤ S

P0803870

Description	System Compatibility	Product compatibility	W/S
Filler Plate For Fiber Controller		Fiber Remote	W1

Status
➤ Δ S

P0815188

Description	System Compatibility	Product compatibility	W/S
System 600/48 NTP	21; 21E; 51; 51C; 61; 61C; 71; 81		W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0815593

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX Releases 3 through 6 Systems		Meridian MAX-IPE; Meridian MAX-SNN	W0

Notes:
- This package includes one Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX 3 through 6 Systems.

Status
➤ S

P0816367

Description	System Compatibility	Product compatibility	W/S
System 600/48 DC Duct	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
➤ Δ S

P0839941

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 11 Maintenance Messages (SEERS)	11C COMPACT		W0

Status
➤ S

P0843070

Description	System Compatibility	Product compatibility	W/S
MIVR Software Reproduction		Meridian IVR R2	S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0823114	Software Keycode Label			

Status
➤ Δ S

P0847870

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter 2.0 User Guide		Meridian Mail Card Option; Meridian Mail Modular EC; Meridian Mail Modular GP; Meridian Mail Modular Option; Meridian Mail Options (NT/XT); Meridian Mail Options (ST/RT)	W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0850716

Description	System Compatibility	Product compatibility	W/S
Option 11C Programming Fee for PCMCIA Card	11C		W0

Notes:
- Returned PCMCIA cards will be re-programmed to current Software.

Status
➤ Δ S

P0853412

Description	System Compatibility	Product compatibility	W/S
Meridian MAX 8 Installation Upgrade Guide (English)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:
- This package includes one Meridian MAX 8 Upgrade Guide.

Status
➤ Δ S

P0870433

Description	System Compatibility	Product compatibility	W/S
MTE Release 8 User Guide (multilingual: English, French, Spanish, German)		Meridian CCR; Meridian MAX	W0

Status
➤ S

P0870718

Description	System Compatibility	Product compatibility	W/S
Blank Insert (Light Gray)	21; 21A; 51; 51C; 61; 61C; 71; 81; 81C		W0

Status
➤ Δ S

P0872785

Description	System Compatibility	Product compatibility	W/S
Option 11C Compact Set Based Administration	11C COMPACT		W0

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
§ ➤ Δ S

P0872788

Description	System Compatibility	Product compatibility	W/S
Mini IPE 1.5 MB DTI/PRI Guide	11C COMPACT		W0

Status
➤ Δ S

P0873717

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Compact Option System Administration Guide	11C COMPACT		W0

Status
§ ➤ Δ S

P0873719

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Compact Option Enterprise Networking Installation and Administration Guide Release 11	11C COMPACT		W0

Status
➤ Δ S

P0876242

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Release 1, End to End Task Flow	11C; 51C; 61C; 81; 81C		W0

Status
➤ Δ S

P0876261

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Release 1, 701t Maintenance and Diagnostics Guide	11C; 51C; 61C; 81; 81C		W0

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0876262

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Server Release 1, 701t Hardware Installation Guide	11C; 51C; 61C; 81; 81C		W0

Status
➤ S

P0876389

Description	System Compatibility	Product compatibility	W/S
MAT 6 End User Five (5) Additional Meridian 1 System Licenses			S3

Notes:
- Adds support in End-User Common Services for five (5) additional Meridian 1 systems.
- Multiple licenses may be added for a maximum support capacity of 500 Meridian 1 systems.
- The MAT ID is required when ordering this code.

Status
➤ S

P0876390

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Mini Expansion License			S3

Notes:
- Adds support for 250 additional DNs to Call Accounting Base Module.
- The MAT ID is required when ordering this code.

Status
➤ S

P0876391

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Small Expansion License			S3

Notes:
- Adds support for 500 additional DNs to Call Accounting Base Module.
- The MAT ID is required when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

P0876392

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Medium Expansion License			S3

Notes:
- Adds support for 1000 additional DNs to Call Accounting Base Module.
- The MAT ID is required when ordering this code.

Status
➤ S

P0876393

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Large Expansion License			S3

Notes:
- Adds support for 5000 additional DNs to Call Accounting Base Module.
- The MAT ID is required when ordering this code.

Status
➤ S

P0876394

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Expansion Cap License			S3

Notes:
- Adds support to 10000 DNs maximum in Call Accounting Base Module.
- The MAT ID is required when ordering this code.

Status
➤ S

P0876395

Description	System Compatibility	Product compatibility	W/S
MAT 6 End User Site Expansion Upgrade			S3

Notes:
- The MAT ID is required when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0876396

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Mini Expansion License Upgrade			S3

Notes:
- Upgrades MAT 4 Call Accounting Expansions to MAT Release 6.
- The MAT ID is required when ordering this code.

Status
➤ Δ S

P0876397

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Small Expansion License Upgrade			S3

Notes:
- Upgrades MAT 4 Call Accounting Expansions to MAT Release 6.
- The MAT ID is required when ordering this code.

Status
➤ Δ S

P0876398

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Medium Expansion License Upgrade			S3

Notes:
- Upgrades MAT 4 Call Accounting Expansions to MAT Release 6.
- The MAT ID is required when ordering this code.

Status
➤ Δ S

P0876399

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Large Expansion License Upgrade			S3

Notes:
- Upgrades MAT 4 Call Accounting Expansions to MAT Release 6.
- The MAT ID is required when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0876400

Description	System Compatibility	Product compatibility	W/S
MAT 6 Call Accounting Expansion Cap License Upgrade			S3

Notes:
- Upgrades MAT 4 Call Accounting Expansions to MAT Release 6.
- The MAT ID is required when ordering this code.

Status
➤ Δ S

P0881397

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Upgrade Guide (to Release 9)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SEE; Meridian MAX-SNN; Meridian MAX-SNNE	W0

Notes:
- This package includes one Meridian MAX 9 Upgrade Guide.

Status
➤ Δ S

P0881398

Description	System Compatibility	Product compatibility	W/S
Meridian Terminal Emulator (MTE) Release 9 User Guide		Meridian MAX; Meridian MAX-CCR	W0

Status
➤ Δ S

P0884895

Description	System Compatibility	Product compatibility	W/S
CallPilot 200 Series Installation Guide			W0

Notes:
- 1 copy of this guide included in the CallPilot IPE Base System.

Status
➤ Δ S

P0884909

Description	System Compatibility	Product compatibility	W/S
702t Installation and Maintenance Guide			W0

Notes:
- 1 copy of the CallPilot 702t Installation Guide included in the CallPilot Tower Base Systems.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0885044

Description	System Compatibility	Product compatibility	W/S
Journal Rate Table (Update)			S3

Notes:

- This code provides the latest rate table update for Journal Call accounting PC software package (NTKS1012). This code is only ordered separately if the customer requires an update to their rate tables. The rate tables are site specific, any order must identify the end customer site ID.
- The Option 11C Compact Site ID must be provided when ordering this code.

Status
➤ Δ S

P0885111

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 9 Reproduction/ Keycode	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S1

Notes:

- This package should be ordered for: (1) Upissues from an earlier issue of a Meridian MAX release to the latest issue of the same release (i.e. 9.xx to 9.yy); (2) Feature option additions to previously ordered Meridian MAX software; (3) Capacity enhancements to previously ordered Meridian MAX software; (4) Software migrations of a release of Meridian MAX from one hardware platform type to another hardware platform type (i.e. migrations of MAX 9.xx on a MAX-SNN to a MAX 9.xx on a MAX-SNNE); (5) Replacement media for lost or damaged MAX software tapes.
- This package is not added to orders for new Meridian MAX systems.
- This package is not added to orders for software upgrades from one Meridian MAX software release to another release (i.e. MAX 8 to MAX 9).
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

P0885221

Description	System Compatibility	Product compatibility	W/S
Compact Hospitality Meridian Mail Guest Cards (15)			W0

Notes:

- Sold in a quantity of 15.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0886124

Description	System Compatibility	Product compatibility	W/S
CallPilot Planning and Engineering Guide			W0

Notes:
- 1 copy of the CallPilot Planning and Engineering Guide included in the CallPilot IPE, Tower, and Rack Base Systems.

Status
➤ Δ S

P0886126

Description	System Compatibility	Product compatibility	W/S
CallPilot Basic Administration Guide			W0

Notes:
- 1 copy of the CallPilot Basic Administration comes with the IPE, Tower, and Rack Base Systems.

Status
➤ Δ S

P0886656

Description	System Compatibility	Product compatibility	W/S
NAC 2.5 User Guide Supplement	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Status
➤ Δ S

P0886776

Description	System Compatibility	Product compatibility	W/S
CallPilot 1001rp Installation Guide			W0

Notes:
- 1 copy of the CallPilot 1001rp Installation Guide included in the CallPilot Rack Base Systems.

Status
➤ Δ S

P0889406

Description	System Compatibility	Product compatibility	W/S
Meridian NAC Software Service Transaction Fee (AM)	11; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C		W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ N

P0889986

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Call Center Business Assessment			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889987

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS CTI Assessment and Design			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889988

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS HDX Design & Implementation			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889989

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Migration Analysis			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ N

P0889990

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Post Production Review			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889991

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Project Management			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889992

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Remote Database Entry			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889993

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Script Design & Implementation			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

Status
➤ Δ N

P0889994

Description	System Compatibility	Product compatibility	W/S
Sales Trifold-SPS SCCS Supervisor Workshop			W0

Notes:
- Minimum order quantity is 25; please order in multiples of 25.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0903073

Description	System Compatibility	Product compatibility	W/S
CallPilot Software Installation Guide			W0

Notes:
- This manual comes with the base system.

Status
➤ Δ S

P0903074

Description	System Compatibility	Product compatibility	W/S
CallPilot Maintenance and Diagnostic Guide			W0

Notes:
- This manual comes with the base system.

Status
➤ S

P0903075

Description	System Compatibility	Product compatibility	W/S
CallPilot 200 Series Installation Guide			W0

Notes:
- This manual comes with the CallPilot IPE System.

Status
★ ➤ Δ S

P0905783

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Installation and configuration Switch Set Up			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0905788

Description	System Compatibility	Product compatibility	W/S
CallPilot 1001rp Installation and Configuration Server Hardware			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
★ ➤ Δ S

P0905789

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Planning and Engineering Guide			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
★ ➤ Δ S

P0905790

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Getting Started Guide			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
★ ➤ Δ S

P0905791

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Monitoring and Security for Administrators			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
★ ➤ Δ S

P0905796

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Administrators Guide			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
★ ➤ Δ S

P0905797

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Client Software Installation			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
★ ➤ Δ S

P0905799

Description	System Compatibility	Product compatibility	W/S
CallPilot 1.07 Applications Builder Guide			W0

Notes:
- This item is associated with CallPilot software release 1.07 and is not scheduled to be available until late November. A bulletin will be issued to inform you when this part number is available to order.

Status
⊗ S

P0906308

Description	System Compatibility	Product compatibility	W/S
cPCI Card Slot Filler Panel	81; 81C		W1

Notes:
- This item is used to cover empty cPCI card slots in the NT4N41 cPCI Core/Network Modules.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

P0906569

Description	System Compatibility	Product compatibility	W/S
Meridian ITG 2.0 NTP			W0

Notes:
- The NTP is a document used to describe and configure the ITG 2.0 card (24-ports).

Status
Δ S

P0909663

Description	System Compatibility	Product compatibility	W/S
Symposium Express Call Center Addendum to Planning, Installation, and Administration Guide			W0

Notes:
- This document is a paper document orderable as a single item.

Status
★ ➤ Δ S

P0910806

Description	System Compatibility	Product compatibility	W/S
Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (Paper)	11C X11 R25; 11C COMPACT X11 R25; 51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25		W0

Notes:
- This documentation is used for the NTZC80AA Meridian IP Telephony Gateway (ITG 2.0) Line Card.
- The PBX that the customer is installing the card onto must be running X11 Release 25 or greater.

Status
➤ S

P0960326

Description	System Compatibility	Product compatibility	W/S
Rubber Feet (100 each, for all Meridian Digital Telephones)		M2006; M2008; M2009; M2016S; M2018; M2018S; M2112; M2216 ACD-1; M2216 ACD-2; M2317; M2616	W0

Notes:
- Certain miscellaneous items may require additional lead time, which should be verified when placing orders.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

QCAD109A

Description	System Compatibility	Product compatibility	W/S
Cable Adapter	LE (23)		W1

Status
➤ S

QCAD125A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (10 Ft.) (Female/Female) (Clock to Clock)	N; NT; XN; XT		W1

Status
† ➤ S

QCAD128A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (7 Ft.) (Male/Female) (DTI to I/O Panel)	M; MS; NT; XN; XT		W1

Status
➤ S

QCAD129A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (7 Ft.) (Male/Female) (PRI/DTI to Echo Canceler)	N; NT; XN; XT		W1

Status
➤ S

QCAD133A

Description	System Compatibility	Product compatibility	W/S
PRI/DTI I/O Cable (50 Ft.)	11; 21; 21E; 51; 61; 61C; 71; 81; M; MS; N; NT; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

QCAD139A

Description	System Compatibility	Product compatibility	W/S
Power Adapter Cable	N; NT; XN; XT		W1

Status
† ➤ S

QCAD190A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (74 In.) (Male/Male)	MS; N; NT; XN; XT		W1

Status
† ➤ S

QCAD193A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (61 In.) (Male/Male)	MS; N; NT; XN; XT		W1

Status
† ➤ S

QCAD196A

Description	System Compatibility	Product compatibility	W/S
Cable, Connector (48 In.) (Male/Male)	MS; N; NT; XN; XT		W1

Status
➤ S

QCAD25AA

Description	System Compatibility	Product compatibility	W/S
Power Adapter Cable	VLE; XL (24); XN; XT		W1

Status
➤ S

QCAD274A

Description	System Compatibility	Product compatibility	W/S
Rectifier Cords, 20 Amp, 225V	RT; ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QCAD277A

Description	System Compatibility	Product compatibility	W/S
Power Connector Cable (2nd Module)	ST; STE		W1

Status
➤ S

QCAD278A

Description	System Compatibility	Product compatibility	W/S
Power Connector Cable (Basic)	ST; STE		W1

Status
➤ S

QCAD284A

Description	System Compatibility	Product compatibility	W/S
Power Adapter Cable	M		W1

Status
† ➤ S

QCAD294B2

Description	System Compatibility	Product compatibility	W/S
Power Fail Transfer Cable (50 Ft.)	RT; ST; STE		W1

Status
† ➤ S

QCAD306B

Description	System Compatibility	Product compatibility	W/S
Power Connector Cable (QSD73)	RT; ST; STE		W1

Status
† ➤ S

QCAD309A

Description	System Compatibility	Product compatibility	W/S
Alarm Adapter Cable	RT; ST; STE		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

QCAD310A

Description	System Compatibility	Product compatibility	W/S
Ground Extension Cable	RT; ST; STE		W1

Status
† ➤ S

QCAD313A

Description	System Compatibility	Product compatibility	W/S
Power & Signaling Cable (Tier 3)	RT; ST; STE		W1

Status
➤ S

QCAD318A

Description	System Compatibility	Product compatibility	W/S
Telecom 25 Pair (50-Pin) to 6DB-25 Female Connector	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

QCAD319A

Description	System Compatibility	Product compatibility	W/S
Telecom 25 Pair (50-Pin) to 6DB-25 Male Connector	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

QCAD321A

Description	System Compatibility	Product compatibility	W/S
Junction Box QBL15	RT; ST; STE		W1

Status
† ➤ S

QCAD325A

Description	System Compatibility	Product compatibility	W/S
Cable	ST; STE		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QCAD332A

Description	System Compatibility	Product compatibility	W/S
Triple SDI Cable (Internal)	RT; ST; STE		W1

Notes:
- This cable condenses three internal SDI ports to one EMI filter connector and must be paired with QCAD333/NT8D96AB.

Status
➤ S

QCAD42A

Description	System Compatibility	Product compatibility	W/S
Cable, Intra-Cabinet (25 Conductor 95 In.) (EMI)	LE (23, 96); M; MS; N; NT; XL (24, 97); XN; XT		W1

Status
† ➤ S

QFF1A

Description	System Compatibility	Product compatibility	W/S
Fuse, 1.33 Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

QFF1AB

Description	System Compatibility	Product compatibility	W/S
1 1/3 Amp Fuse	21; 21E; 51; 51C; 61; 61C; 71; 81		W1

Status
† ➤ S

QFF1B

Description	System Compatibility	Product compatibility	W/S
Fuse, 2. Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

QFF1C

Description	System Compatibility	Product compatibility	W/S
Fuse, 3. Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

QFF1D

Description	System Compatibility	Product compatibility	W/S
Fuse, 5. Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

QFF1E

Description	System Compatibility	Product compatibility	W/S
Fuse, .180 Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

QFF1F

Description	System Compatibility	Product compatibility	W/S
Fuse, .25 Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
† ➤ S

QFF1G

Description	System Compatibility	Product compatibility	W/S
Fuse, .50 Amp	21; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QPC414C

Description	System Compatibility	Product compatibility	W/S
Network Card	21; 21A; 21E; 51; 61; 61C; 71; 81; LE (23) Upgrade; N; NT; RT; ST; STE; XL (24) Upgrade; XN; XT		W1

Status
➤ S

QPC43R

Description	System Compatibility	Product compatibility	W/S
Peripheral Signaling	51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; VL; VLE; XL; XN; XT		W1

Notes:

- Vintage R or later required for S, MS, N, NT, XN, RT, and XT.

Status
➤ S

QPC441F

Description	System Compatibility	Product compatibility	W/S
Three-Port Extender	51; 61; 61C; 71; 81; LE (23) Upgrade; N; NT; RT; XL (24) Upgrade; XN; XT		W1

Status
➤ S

QPC444A

Description	System Compatibility	Product compatibility	W/S
Conference Card	21; 21A; 21E; 51; 61; 61C; 71; 81; LE (23) Upgrade; N; NT; RT; ST; STE; XL (24) Upgrade; XN; XT		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QPC471H

Description	System Compatibility	Product compatibility	W/S
Clock Controller			W1

Notes:

- QPC471B or later vintage is required for DTI on MS and ST systems. DTI/PRI requires 1 Clock Controller (QPC471) for a half network group; or requires 2 Clock Controllers for a full or multi network group. QPC471 vintage H Clock Controllers must be used in pairs when installed in the full or multi network group systems. No Clock Controllers (QPC471) are required for CPI applications.

Status
➤ S

QPC477A9

Description	System Compatibility	Product compatibility	W/S
Bus Terminating Unit (BTU)	51; 61; 71; 81; 81C; LE (23) Upgrade; N; NT; RT; XL (24) Upgrade; XN; XT		W1

Notes:

- Suffix dependent upon specific CE Shelf position and system type.

Status
➤ S

QPC477B10

Description	System Compatibility	Product compatibility	W/S
Bus Terminating Unit (BTU)	51; 61; 61C; 71; 81; LE (23) Upgrade; N; NT; RT; XL (24) Upgrade; XN; XT		W1

Notes:

- Suffix dependent upon specific CE Shelf position and system type.

Status
† ➤ S

QPC584M

Description	System Compatibility	Product compatibility	W/S
Mass Storage Interface Card			W1

Notes:

- Requires X11 Release 8; vintage E for X11 Release 15+ when used with NT8D69AA.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QPC720F

Description	System Compatibility	Product compatibility	W/S
Primary Rate Interface Card	21; 21A; 21E; 51; 61; 61C; 71; 81; MS; N; NT; RT; ST; STE; XN; XT		W1

Notes:
- Vintage D and later for X11 Release 15+ when used with NT8D68AA.
- QPC720 is compatible with MS system, but only as DTI function and not PRI.

Status
➤ S

QPC841C

Description	System Compatibility	Product compatibility	W/S
Four-Port SDI	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; RT; S; ST; STE; VL; VLE; XL; XN; XT		W1

Status
➤ S

QPC84S

Description	System Compatibility	Product compatibility	W/S
Power Monitor Pack	21; 21A; 21E; 51; 61; 61C; 71; 81; A; L; LE; M; MS; N; NT; S; XL; XN; XT		W1

Notes:
- Vintage P or later required for S, MS, N, XN, NT, XT, LE(96), XL(97).

Status
➤ S

QPF23A

Description	System Compatibility	Product compatibility	W/S
Terminating Plug	A; L; LE (23); M; VL; VLE; XL (24)		W1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

QPF36B

Description	System Compatibility	Product compatibility	W/S
Terminating Plug	XL (24); XN; XT		W1

Status
➤ Δ S

S0005899

Description	System Compatibility	Product compatibility	W/S
NAC Connectivity for Meridian MAX Release 9 Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- This option can only be applied to Meridian MAX-IPE, Meridian MAX-IPEE, Meridian MAX-SNN, or Meridian MAX-SNNE Release 9 Enhanced or Virtual Software.
- This package requires permanent assignment of one asynchronous I/O port for connection to NAC.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

S0005901

Description	System Compatibility	Product compatibility	W/S
Multiple Queue Assignment (MQA) Reporting for Meridian MAX Release 9 Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- Once MAX Multiple Queue Assignment (MQA) for Meridian MAX Release 9 option is enabled, it cannot be disabled.
- MAX Multiple Queue Assignment (MQA) for Meridian MAX Release 9 option can only be applied to Meridian MAX-IPE, Meridian MAX-IPEE, Meridian MAX-SNN, or Meridian MAX-SNNE Release 9 Enhanced or Virtual software, or equivalent.
- Use caution when ordering MQA. The way in which information is displayed when MQA is installed is different than when it is not. If agents will not be logging into multiple queues, Nortel recommends that MQA not be ordered.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

S0005906

Description	System Compatibility	Product compatibility	W/S
100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Required for Meridian MAX Release 9 agent expansions.
- Required to add agents in 100 agent increments beyond what is included in Base system software packages.
- Because base software includes support for 200 agents and the maximum capacity is 1200 agents, a maximum number of ten (10) of S0005906 can be ordered for one Meridian MAX-SNN or MAX-SNNE system.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

S0005907

Description	System Compatibility	Product compatibility	W/S
10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Because Meridian MAX 9 base software includes support for 20 agents and the maximum capacity is 300 agents, a maximum number of twenty-eight (28) S0005907 can be ordered for one Meridian MAX 9 system.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

S0005908

Description	System Compatibility	Product compatibility	W/S
8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- The base software packages for MAX-SNN and MAX-SNNE systems each contain support for 8 I/O channels. Since each new MAX-SNN and MAX-SNNE hardware platform can accommodate a maximum of forty (40) asynchronous I/O channels, a maximum quantity of four (4) each of S0005908 can be ordered for one system.
- Required when adding additional ports to the Meridian MAX Release 9 SNN or SNNE systems.
- Enables operation of one (1) VME322XT 8-Channel Asynchronous I/O Card (A0376918). This card is part of the NT6D98AA kit.
- Customer must also order Meridian MAX Release 9 Reproduction/Keycode (P0885111). Keycode is provided with this package to use with customer's existing Meridian MAX Release 9 software tapes.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SERV0002

Description	System Compatibility	Product compatibility	W/S
Spare set of blank 3.5 inch 4MB floppy diskettes			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0003

Description	System Compatibility	Product compatibility	W/S
Spare set of blank 5.25 in diskettes			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0005

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Releases 6, 7 and 8 Software Service Transaction Fee (AM)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:
- THIS FEE WILL BE ADDED TO ORDERS FOR THE FOLLOWING
- Upgrades from one Meridian MAX release to another release
- Upissues from an earlier issue of a Meridian MAX release to the latest (current) issue of the same release (i.e. 8.xx to 8.yy)
- Feature option additions to previously ordered Meridian MAX software
- Capacity enhancements to previously ordered Meridian MAX software
- Software migrations of a release of Meridian MAX from one hardware platform type to another hardware platform type (i.e. migrations of MAX 8.xx on a MAX-SNN to a MAX 8.xx on a MAX-SNNE)
- Replacement media for lost or damaged MAX software tapes.
- This fee is not added to orders for new Meridian MAX systems.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ B

SERV0006

Description	System Compatibility	Product compatibility	W/S
Customer Controlled Routing Software Service Transaction Fee			

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SERV0017

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE/MAX-IPEE Releases 6, 7 and 8 Software Service Transaction Fee	11 X11 R16,18,19,20,21,22,23; 11C X11 R16,18,19,20,21,22,23; 11E X11 R16,18,19,20,21,22,23; 21 X11 R17,18,19,20,21,22,23; 21A X11 R17,18,19,20,21,22,23; 21E X11 R17,18,19,20,21,22,23; 51 X11 R17,18,19,20,21,22,23; 51C X11 R17,18,19,20,21,22,23; 61 X11 R17,18,19,20,21,22,23; 61C X11 R17,18,19,20,21,22,23; 71 X11 R17,18,19,20,21,22,23; 81 X11 R17,18,19,20,21,22,23; 81C X11 R17,18,19,20,21,22,23	Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- THIS FEE WILL BE ADDED TO ORDERS FOR THE FOLLOWING
- Upgrades from one Meridian MAX release to another release.
- Upissues from an earlier issue of a Meridian MAX release to the latest (current) issue of the same release (i.e. 8.xx to 8.yy)
- Feature option additions to previously ordered Meridian MAX software
- Capacity enhancements to previously ordered Meridian MAX software.
- Software migrations of a release of Meridian MAX from one hardware platform type to another hardware platform type (i.e. migrations of MAX 8.xx on a MAX-IPEE to MAX 8.xx on a MAX-SNNE).
- Replacement media for lost or damaged MAX software tapes
- This fee is not added to orders for new Meridian MAX systems.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ B

SERV0019

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Software Service Transaction Fee		Meridian Mail	

Notes:

- Order SERV0019 for one or more of the following services: Issue/Release Update; Feature Addition/Expanded Storage Software; Replacement of transport Medium.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SERV0020

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Hardware Key Code Service		Meridian Mail	

Notes:
- Order (at no charge) to activate additional ports or nodes afforded by expansion(s).
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0031

Description	System Compatibility	Product compatibility	W/S
In-House Software Conversion Fee			

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0033

Description	System Compatibility	Product compatibility	W/S
Meridian Link & CCR Co-Resident Service Transaction Fee			

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0055

Description	System Compatibility	Product compatibility	W/S
Switch to Switch Conversion Fee			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SERV0056

Description	System Compatibility	Product compatibility	W/S
Loops Requiring Conversion/Balancing			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SERV0058

Description	System Compatibility	Product compatibility	W/S
Loop Conversion Fee			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SERV0080

Description	System Compatibility	Product compatibility	W/S
CD-ROM Media Request	51C; 61C; 81; 81C		S1

Notes:
- This service code is used to identify customers changing from 4MB software delivery to CD-ROM software delivery.
- CD-ROM delivery of software requires IODU/C card (NT5D61).
- SERV0080 code needs to be ordered only once for any given switch (i.e., does not need to be ordered for every CD-ROM upgrade).
- SERV0080 does not replace 599SL1-1 software transaction fee.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ Δ S

SV000020

Description	System Compatibility	Product compatibility	W/S
Messenger 4.0: On-site Administration and User Training			W1

Notes:
- A Nortel-EN/Field Services Professional Services Engineer will provide on-site Messenger training for the customers system administrator at each end users location immediately after installation of the Meridian Application Server. Also included is basic end user training for approximately three (3) client end users. EN/FS will use the Nortel approved System Administrator Training Materials. The class should be limited to a maximum of two (2) end user System Administrators and three (3) client end users.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000024

Description	System Compatibility	Product compatibility	W/S
MAS Premium Warranty Upgrade: Extended Telephone Support			

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customers Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will assist the System Administrator in determining the failing component and send a replacement part to the System Administrator for use in the repair. This warranty service is provided on a seven day a week, twenty-four hour a day basis.

Status
➤ Δ S

SV000025

Description	System Compatibility	Product compatibility	W/S
MAS Premium Warranty Upgrade; Onsite Removal/Replacement			

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customer's Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will dispatch a Nortel-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel-En/Field Services Field Engineer will replace the failing component and verify complete Meridian Application Server operation. This warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

Status
➤ Δ S

SV000026

Description	System Compatibility	Product compatibility	W/S
MAS Post Warranty Service			

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customers Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will dispatch a Nortel-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel-En/Field Services Field Engineer will replace the failing component and verify complete Meridian Application Server operation. This post warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000027

Description	System Compatibility	Product compatibility	W/S
MAS Post Warranty Premium Service			

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customers Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will dispatch a Nortel-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel-En/Field Services Field Engineer will replace the failing component and verify complete Meridian Application Server operation. This post warranty phone support is provided on a seven day a week, twenty-four hour a day basis and the on-site service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

Status
➤ Δ S

SV000088

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider INSTALL-PREP			W0

Notes:

- See Meridian Applications Special Policies section in this price book for additional information.

Status
✓ ➤ Δ S

SV000089

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Service Provider INSTALL-PRO			W0

Notes:

- See Meridian Applications Special Policies section in this price book for additional information.

Status
➤ Δ S

SV000091

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM TAPI Server, One Additional Year of Software Support			W0/ S2

Notes:

- See Meridian Applications Special Policies section in this price book for additional information.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000098

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Functionality Service Fee			W0

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

SV000099

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 2-24 Upgrade Service Charge			W0

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

SV000100

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 25-48 Upgrade Service Charge			W0

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

SV000101

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 49-64 Upgrade Service Charge			W0

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

Status
➤ Δ S

SV000102

Description	System Compatibility	Product compatibility	W/S
Meridian Mail 65-96 Upgrade Service Charge			W0

Notes:
- The Meridian Mail serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000110

Description	System Compatibility	Product compatibility	W/S
Messenger Post Warranty Phone 8-5			W0

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customers Messenger system administrator. The CSC can assist the end users in diagnosing Meridian Application Server and Messenger operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will assist the System Administrator in determining the failing component and send a replacement part to the System Administrator for use in the repair. This post warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

Status
➤ Δ S

SV000111

Description	System Compatibility	Product compatibility	W/S
Messenger Post Warranty Phone 7x24			W0

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customers Messenger system administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. If a hardware failure is assumed, the CSC will assist the System Administrator in determining the failing component and send a replacement part to the System Administrator for use in the repair. This post warranty service is provided on a seven day a week, twenty-four hour a day basis.

Status
➤ Δ S

SV000112

Description	System Compatibility	Product compatibility	W/S
Messenger Installation Phone Support			W0/ S1

Notes:

- Installation Telephone Support while the Distributor performs the on-site installation of the Messenger Meridian Application Server.
- A pre-installation conference call will be coordinated by Nortel technical specialists to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Telephone assistance during the installation will be provided by a fully trained Nortel-EN/Field Services Professional Services Engineer.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000117

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Transaction Fee			W0

Notes:
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	P0841926	Keycode Label for Software			

Status
➤ Δ S

SV000125

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Call Center Installation			W0

Notes:
- Provides support during the installation of the SYMPOSIUM Call Center. An installation statement of work is available from Nortel Enterprise Networks - Field Services (EN/FS, located in Minnetonka, MN).
- Travel and living are additional charges.

Status
➤ Δ S

SV000126

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView INSTALL-PRO Installation 5 to 8 Seats			W0/ S1

Notes:
- At lease one conference call to review the completed Pre-installation checklist prior to Nortel performing on-site installation.
- Installation Project Management from receipt of order through scheduling the installation.
- One eight hour day of on-site software installation activity.
- Normally 5 to 8 seats of FastView can be installed in one day.
- Thirty days of post installation warranty phone support.
- On-site installation is performed during normal business hours.
- Zone 1 installations are within a 75 mile radius of 40 major U.S. cities in which Nortel maintains a field engineering team.
- Zone 1 installations include reasonable travel to and from sites.
- Contact Nortel Enterprise Networks Field Services (612-932-8536) for installation pricing outside of zone 1 locations.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000127

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView INSTALL-PREP Remote Installation			W0/ S1

Notes:

- At least one conference call to review the completed Pre-installation checklist prior to the start of the installation.
- Installation Project Management from receipt of order through scheduling the installation.
- Assistance via phone while the Distributor/End User performs the installation of the five (5) initial seats.
- Thirty days of post installation warranty phone support.
- Installation assistance is performed during normal 8am to 5pm Central Time business hours.

Status
➤ Δ S

SV000128

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM FastView Software Support			W0/ S1

Notes:

- One year of assistance via phone upon successful installation of the initial seats.
- Assistance provided by Nortel's-Enterprise Networks Field Services Customer Support Center (CSC).
- CSC will assist the end users in diagnosing FastView operational problems and then recommend the appropriate course of action to remedy them.
- Telephone assistance is performed during normal 8 to 5 Central Time business hours.

Status
➤ Δ S

SV000147

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Install-Prep			W0

Notes:

- This support includes up to 8 hours of remote coordination of the installation of Symposium Agent application software on the agent's desktop PCs. This support does not cover TAPI Server installation, client server connectivity, installing TAPI Remote Services Provider software on client PCs, or any integration with third-party applications (such as using DDE, OLE, or Keystroke macros).
- One conference call to review the completed pre-installation checklist prior to the start of the installation.
- Assistance via phone while the distributor or end user performs the installation of the five (5) initial clients at a new site. General answers to questions about the installation of Symposium Agent will be answered however, this does not include specific questions about implementation with Symposium Agent and end user's databases.
- Installation assistance is performed during normal 8a.m. - 5p.m. business hours (Central time).

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000148

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Install-Pro			W0/ S1

Notes:

- At least one conference call to review the completed pre-installation checklist prior to Nortel Networks performing on-site installation.
- Installation coordination from receipt of order through completion of installation.
- Installation of Symposium Agent using Windows 95 Note Pad as the database to provide operational verification. Assistance with the implementation of Symposium Agent integrations with end user's applications and databases is not included.
- Normally 5 to 8 seats of Symposium Agent can be installed in one day.
- On-site installation is performed during normal business hours.
- Zone 1 installations are within a 75 mile radius of 40 major U.S. cities in which Nortel maintains a field engineering team.
- Zone 1 installations include reasonable travel to and from sites.
- Contact Nortel Enterprise Networks Field Services (612-932-8536) for installation pricing outside of zone 1 locations.

Status
➤ Δ S

SV000149

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Agent Software Support			W0

Notes:

- One year of software support is offered with Symposium Agent. The service is effective 10 business days after the product is shipped by Nortel Networks. To continue receiving this support, SV000149 can be purchased for each installation site on an annual basis. This software support includes the following services: Assisting end users or distributor support personnel with general answers to questions about the installation of Symposium Agent. Accepting the first call for help from a distributor support technician or end user's lead operator. Assisting end users in general use of Symposium Agent operation. Assistance with the implementation of Symposium Agent integrations with end user's applications and databases is not included. Accepting problem reports and design change requests and submitting them to the appropriate Nortel Networks design organization. Provision of any generally released up-issues or problem fixes. Telephone assistance is available during normal 8 a.m. - 5 p.m. business hours (Central time).

Status
➤ Δ S

SV000175

Description	System Compatibility	Product compatibility	W/S
Nortel IVR CompuCALL Integration Package			W0

Notes:

- This toolkit enables superior call center integration in a DMS/SL-100 environment. It uses standard analog voice ports and is capable of many line side features including digital transfer and conferencing capabilities, resource query for hold time in queue, method for delivering screen pops and digital ACD login/logout. Installation and/or customization not included.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SV000176

Description	System Compatibility	Product compatibility	W/S
CCIP - CompuCALL Agent/Port License			W0

Notes:

- The purchase of this license is required for every voice port/agent being monitored by CCIP. It is purchased in conjunction with the Nortel IVR CompuCALL Integration Package, SV000175.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000177

Description	System Compatibility	Product compatibility	W/S
Web Call Back			W0

Notes:

- This application module gives an Internet surfer the ability to request a live call back at a specified time through a web page. The IVR application will listen to web requests and automatically reserve an agent to call back the caller.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000181

Description	System Compatibility	Product compatibility	W/S
Service Code for Telephone Support to Add Additional User Client License(s) Req. if adding clients to existing systems			W0

Notes:

- Customer Support Center will provide Telephone support for Customers or Distributors who are adding additional user client license(s) to the MAS server.
- The service provided will include assisting the installing person with the addition of the licenses, helping to validate the addition of the licenses, and explaining the procedures to do a backup to ensure the new license information is retained.
- This is a required service when ordering an increase in client licenses.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SV000182

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM WebResponse Server Additional 1 Day Installation Services			W0

Notes:

- Includes (1) one eight hour day of on-site software installation activity performed by a fully trained Nortel-EN/Field Services Professional Services Engineer. The installation charges include installation of SYMPOSIUM WebResponse Server client software and the Sybase client software onto the end user PCs. The Professional Services Engineer will then perform the appropriate operational verification. Normally (5) five to (8) eight seats can be installed in one day. On-site installation is performed during normal business hours.

Status
† ➤ Δ S

SV000183

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM WebResponse Server Annual Telephone Support			W0

Notes:

- The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customer's SYMPOSIUM WebResponse Server administrator. The CSC can assist the end users in diagnosing SYMPOSIUM WebResponse Server operational problems and recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. This cursory level of telephone support will involve general answers to questions about the operation of SYMPOSIUM WebResponse Server and direct the callers to the appropriate documentation when applicable. The telephone support will not provide specific answers about implementation of SYMPOSIUM WebResponse Server product in that end user's applicable. This service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday. If expert support is required, the caller will be directed to Nortel's SYMPOSIUM Professional Services organization where a quote for these expert services can be provided.

Status
† ➤ Δ S

SV000184

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM WebResponse Server Installation Service			W0

Notes:

- A Nortel-EN/Field Services Technical Specialist will provide at least (2) two pre-installation conference calls to assist the end user/Distributor in readying the customer provided Windows NT Server, the end user's LAN/WAN/Internet environment and the client PCs for use with SYMPOSIUM WebResponse Server. Complete SYMPOSIUM WebResponse Server installation activities will be performed by a fully trained Nortel-EN/Field Services Professional Services Engineer. The on-site installation service includes a maximum of five (5) days of labor on the end user's premises to verify that the customer supplied Windows NT Server has a working TCP/IP network connection. A Nortel Professional Services Engineer will then load and configure the Sybase software and the SYMPOSIUM WebResponse Server software onto the customer supplied Windows NT Server. Installation also includes the loading and configuring of approximately five (5) client end users with the SYMPOSIUM WebResponse Server client software, the Sybase client software and then develop 1 (one) basic Web form. The end user/Distributor is responsible for the configuring of additional SYMPOSIUM WebResponse Server clients. On the Web site server, the Nortel Professional Services Engineer will assist the customer as they load and configure the CGI software onto the customer's Web site and also assist the customer as they load and configure the Entrust software. The Nortel Professional Service Engineers will verify that a "Web surfer" can complete the generic form and then verify that this generic form is received as a transaction at the SYMPOSIUM WebResponse Server client PC and that the client PC can process the transaction to closure.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000252

Description	System Compatibility	Product compatibility	W/S
Message Taker			W0

Notes:
- An application that determines and speaks the average wait time to a caller and offers the caller the options to either wait for an agent (hold in queue for IVR) or leave a message for an agent to call them back at a specified time.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000253

Description	System Compatibility	Product compatibility	W/S
Voice Form			W0

Notes:
- This flexible application module on Open IVR offers editing capability for callers, statistics, several retrieval methods, (i.e. by date, language) and multiple points of administration.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000254

Description	System Compatibility	Product compatibility	W/S
Agent Whisper			W0

Notes:
- The application module whispers important information such as CLID, DNIS, or other unique information such as Account Number by voice prompts or Text-to-Speech to agents therefore reducing call handling time.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000255

Description	System Compatibility	Product compatibility	W/S
CCIP Screen Pop			W0

Notes:
- This application module will allow CCIP IVR the ability to attach data to a call and subsequently provide a screen pop to an Agent Desktop running a CCIP client.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000257

Description	System Compatibility	Product compatibility	W/S
TAPI Integration - Remote Installation			W0

Notes:
- This application module will allow TAPI/S and IVR the ability to attach data to a call. This will allow the capability of building sophisticated/integrated Screen Pop applications with TAPI compliant desktops. This includes the TAPI Integration Package, and Nortel installs the package remotely via modem download.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000259

Description	System Compatibility	Product compatibility	W/S
TAPI Integration - Solution Pro			W0

Notes:
- This application module will allow TAPI/S and IVR the ability to attach data to a call. This will allow the capability of building sophisticated/integrated Screen Pop applications with TAPI compliant desktops. This is a complete IVR solution based on the TAPI Integration Package. Nortel installs and configures the IVR system (8 IVR ports), installs and configures TAPI Server S/W, installs and configures TAPI clients (up to 20 TAPI Remote Service Provider and Symposium Agent clients) and provides up to 2 hours of customization to the sample application.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000260

Description	System Compatibility	Product compatibility	W/S
ACD Fax Pop			W0

Notes:
- This application module allows inbound faxes to be evenly distributed amongst a pool of ACD agents. Agents can view, edit, and print these faxes as they are received.
- Implementation not included.
- To order call SYMPOSIUM Professional Services, 1-800-467-0273.

Status
➤ Δ S

SV000261

Description	System Compatibility	Product compatibility	W/S
Enhanced IVR Reports			W0

Notes:
- This application module enables a call center manager to see and compare the number of callers taking the various branches of their IVR applications, with results saved in Excel spreadsheet.
- Implementation not included.
- To order call Symposium Professional Services, 1-800-467-0273.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000262

Description	System Compatibility	Product compatibility	W/S
Follow Me Service			W0

Notes:

- This application module allows an individual to remotely direct calls to a specific location. The application keeps custom profiles of phone numbers and current locations. Self-administered by end users.
- Implementation not included.
- To order call Symposium Professional Services, 1-800-467-0273.

Status
† ➤ Δ S

SV000276

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 to 4.0 On-Site Migration Support			W0

Notes:

- Messenger 2.0/3.0 to 4.0 onsite Migration Support. A pre-upgrade conference call will be coordinated by Nortel technical specialists to ensure site readiness for the upgrade. Complete Release 4.0 Messenger server software upgrade activities will be performed by a fully trained Nortel-EN Field Services Professional Services Engineer (PSE). Software upgrade activities include the loading and configuring of the Messenger Release 4.0 server software and the loading and configuring of approximately three (3) client end users with the Release 4.0 Messenger client software. The end user/Distributor is responsible for the addition of subsequent Messenger clients to the Messenger server. This service includes the integrity of all Messenger 2.0/3.0 database information. Training is not included in this service. It can be ordered via SV000251.

Status
† ➤ Δ S

SV000277

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 to 4.0 Migration Phone Support			W0

Notes:

- Messenger 2.0/3.0 to 4.0 Migration-Phone Support. A pre-upgrade conference call will be coordinated by Nortel technical specialists to ensure site readiness for the upgrade. Telephone assistance during the installation will be provided by a fully trained Nortel-EN Field Services Professional Services Engineer to the on-site Distributor technician.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ Δ S

SV000278

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Release--Phone Installation Support for Customers Under Warranty or Maintenance			W0

Notes:

- Messenger 2.0/3.0 Maintenance Release - Phone Installation Support for Customers under Warranty or Maintenance. Nortel-EN Field Services technical specialists will provide telephone assistance for end user or Distributor technicians as they install the Maintenance Release for Messenger Release 2.0/3.0. The service provided will include assisting the installing person with the installation of the Maintenance Release, helping to validate the maintenance release and explaining the procedures to do a backup to ensure the new maintenance release is retained.

Status
† ➤ Δ S

SV000279

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Release--Installation Phone Support for Customers NOT under Warranty or Maintenance			W0

Notes:

- Messenger 2.0/3.0 Maintenance Release - Installation Phone Support for Customers NOT under Warranty or Maintenance. Nortel-EN Field Services technical specialists will provide telephone assistance for end user or Distributor technicians as they install the Maintenance Release for Messenger Release 2.0/3.0. The service provided will include assisting the installing person with the installation of the Maintenance Release, helping to validate the maintenance release and explaining the procedures to do a backup to ensure the new maintenance release is retained.

Status
† ➤ Δ S

SV000280

Description	System Compatibility	Product compatibility	W/S
Messenger 2.0/3.0 Maintenance Release--On-Site Installation Support for Customers NOT under Warranty or Maintenance			W0

Notes:

- Messenger 2.0/3.0 Maintenance Release - On site Installation Support for Customers NOT under Warranty or Maintenance. A Nortel-EN Field Services Professional Services Engineer will work on-site with the Messenger system administrator to perform the on-site activities necessary to install the maintenance release on the Messenger System Release 2.0/3.0. The service provided would include installing the Maintenance Release, validating the maintenance release and performing a backup to ensure the new maintenance release is retained. Training is not included in this service. It can be ordered via SV000251.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SV000399

Description	System Compatibility	Product compatibility	W/S
SYMPOSIUM Express Call Center Installation and Configuration Service	11C COMPACT; 51C; 61C; 81; 81C		W0

Notes:

- Installation Project Management from receipt of order through scheduling the installation.
- Initial conference call to assist the end user/distributor in understanding the guidelines specified in the Pre-Installation Checklist.
- A Global Customer Services (GCS) Professional Services Engineer will travel to the end user location to provide up to three eight-hour days (normal business hours) of on-site installation activities: -Assist the Distributor's Technician/End User's LAN Administrator in the installation and configuration of the customer provided Windows NT Server as per the loading and configuring specification required for the Express application. -The GCS Engineer will also assist in the installation and configuration of the Express Server/Client application software on the server, the SECC client software on the Client Personal Computer, and configuration of the Meridian 1 and Meridian Mail resource configuration.
- The GCS Engineer will also provide an overview of how to administrate the call center, create user-defined reports, start displays, how to modify the call routing parameters, such as the hours of operation and non-business days, and how to perform daily and full backup.
- The price includes travel for installs within zone 1 (75 miles or less from a Global Customer Service Field Office). Outside of 75 miles, additional charges for travel and living will apply and vary depending on the location. -Zone 1 installations include reasonable travel to and from sites. Additional charges may apply if reasonable travel is not available. -Contact Nortel Global Customer Services Field Services (612-932-8536) for travel and living pricing outside of zone 1 locations.

Status
✓ ➤ Δ N

SVC0001

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Security Audit Per Hour			W0

Notes:

- For systems configured as multi-customer an individual audit must be performed for each customer. Audits should be ordered based on the number of lines for each customer.

Status
✓ ➤ Δ N

SVC0007

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Security Consulting per day plus travel and expense			W0

Notes:

- For systems configured as multi-customer an individual audit must be performed for each customer. Audits should be ordered based on the number of lines for each customer.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
✓ ➤ Δ N

SVC0010

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Security Seminar (per day) Plus Travel and Expense for One Consultant			W0

Notes:
- For systems configured as multi-customer an individual audit must be performed for each customer. Audits should be ordered based on the number of lines for each customer.

Status
➤ Δ S

SVC1006

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Reporter One Year Extended Service Plan		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10	

Notes:
- See the "Support" section of the product catalog for a detailed description of Meridian Mail Reporter Service Plan provided.
- 90 day Service Plan is standard with Meridian Mail Reporter, when the Extended Service Plan is purchased, Meridian Mail Reporter service is 90 days plus one year for a total of 15 months.

Status
➤ S

SW0000C

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Release 17 Base Software	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

Status
➤ S

SW0000E

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Release 19 Base Software	21E; 51; 61; 61C; 71; 81; NT; RT; STE; XT		S1

Notes:
- STADATA has not been updated to include X11 Release 19 features.
- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0000G

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Release 21 Base Software	21E X11 R21; 51 X11 R21; 51C X11 R21; 61 X11 R21; 61C X11 R21; 71 X11 R21; 81 X11 R21; NT X11 R21; RT X11 R21; STE X11 R21; XT X11 R21		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

Status
➤ S

SW0000H

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Release 22 Base Software	51C X11 R22; 61C X11 R22; 81 X11 R22; 81C X11 R22	ACD MAX R4; CCR R3; MAT R5; Meridian IVR R1,2,3; Meridian Link R2,3,4,5,4B; Meridian MAX R4,5,6,7,8; Meridian Mail R9,10; NAC R1,2; Open IVR R2	S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0000J

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Base System Software: Release 23	51C X11 R23; 61C X11 R23; 81 X11 R23; 81C X11 R23	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:

- Please be advised that the Symposium Call Center Server will only be supported on X11 Release 22 until further notice. X11 Release 22 software will automatically be substituted on any order that includes Symposium Call Center Server. Any new features introduced with X11 Release 23 accompanying such an order will automatically be deleted. In addition, for Meridian 1 Options 51C-81C, an IOP/CMDU (4 Mb floppy drive) will be substituted for the IODUC (CD ROM drive).

Status
➤ S

SW0000K

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Base System Software: Release 24	51C X11 R23; 61C X11 R23; 81 X11 R23; 81C X11 R23	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0000L

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Base System Software: Release 25	51C X11 R25; 61C X11 R25; 81 X11 R25; 81C X11 R25; X11 X11 R25	CPLUS (base) R3.11; CPLUS LAN Key R1.0; CPLUS Performer R1.0; CallPilot R1.0; IVR R1,2; Integrated IVR R1,2.2; M911 R1,2; MAT NT Workstation R4.0; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7,6.1,6.4,6.5,6.6; Meridian 1 TAPI Server R1,2; Meridian CCR R2,3; Meridian IVR R1,2,3; Meridian Link R2,4,5; Meridian MAX R3,4,6,7,8,9; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; Multimedia SYMPOSIUM Conference R4,5; NAC R1,2,2.5; Open IVR R2,4; SYMPOSIUM Agent R1,2; SYMPOSIUM Call Center Server (ICCM) R1,1.1,1.5; SYMPOSIUM Call Manager R4,5; SYMPOSIUM Communicator R1,2; SYMPOSIUM Desktop TAPI Service Provider R1,2; SYMPOSIUM Express Call Center R1; SYMPOSIUM Fast Call/Fast View (Windows only) R1.1; SYMPOSIUM Messenger R3,4; SYMPOSIUM TAPI Service Provider R2	W0/ S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code to increase the TNs on an existing Meridian 1 system.

Status
† ➤ S

SW0001A

Description	System Compatibility	Product compatibility	W/S
Special Application Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be porvided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0003A

Description	System Compatibility	Product compatibility	W/S
NARS/CDR Format	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R20,21,22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21; 81C X11 R20,21,22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- Option 57 is removed from Base Software when provisioned.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0005A

Description	System Compatibility	Product compatibility	W/S
DN Expansion	21 X11 R17; 21A X11 R17; 21E X11 R18,19; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,22,23,24; 81C X11 R22,23,24; NT X11 R17,18,19; RT X11 R17,18,19; ST X11 R17; STE X11 R18,19; XT X11 R17,18,19		S1

Notes:

- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0006A

Description	System Compatibility	Product compatibility	W/S
Automatic Trunk Maintenance	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:

- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0008A

Description	System Compatibility	Product compatibility	W/S
Multi-Customer	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0009A

Description	System Compatibility	Product compatibility	W/S
Multi-Tenant	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0010A

Description	System Compatibility	Product compatibility	W/S
Automatic Number Identification (ANI)	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0011A

Description	System Compatibility	Product compatibility	W/S
Option 81 - Required for Option 81	51C X11 R22,23,24,25; 61C X11 R22,23,24,25; 81 X11 R22,23,24,25; 81C X11 R22,23,24,25		S1

Notes:
- Cannot be configured with SW0013A (Option 81C on Release 21). This option package is used to distinguish Option 81 from Option 81C.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SW0013A

Description	System Compatibility	Product compatibility	W/S
Option 81C - Required for Option 81C	51C X11 R22,23,24,25; 61C X11 R22,23,24,25; 81 X11 R22,23,24,25; 81C X11 R21,22,23,24,25		S1

Notes:
- Cannot be configured with SW0011A (Option 81 on Release 21). This option package is used to distinguish Option 81C from Option 81.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0015A

Description	System Compatibility	Product compatibility	W/S
SNMP Open Alarms	51C X11 R22,23,24,25; 61C X11 R22,23,24,25; 81 X11 R22,23,24,25; 81C X11 R22,23,24,25	ACD MAX R4; CCR R3; MAT R5; Meridian IVR R1,2,3; Meridian Link R2,3,4,5,4B; Meridian MAX R4,5,6,7; Meridian Mail R9,10; NAC R1,2; Open IVR R2	S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0016A

Description	System Compatibility	Product compatibility	W/S
MAT Data Buffering and Access	51C; 61C; 81; 81C		S1

Notes:
- Supported on X11 Release 24 and later.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0017A

Description	System Compatibility	Product compatibility	W/S
Hospitality/Healthcare Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0018A

Description	System Compatibility	Product compatibility	W/S
Property Management Systems Interface	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0017A Hospitality/Healthcare Features is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0019A

Description	System Compatibility	Product compatibility	W/S
Attendant Overflow Position	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0020A

Description	System Compatibility	Product compatibility	W/S
Supervisory Console	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- All non-M2250 consoles must be equipped with QPC297 H/M Attendant Line Card with X11 Release 16 or earlier.
- The Attendant Supervisory Module (NT7G10AA) may be used in conjunction with M2250 consoles and digital line cards on systems running X11 Release 16 or later.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0021A

Description	System Compatibility	Product compatibility	W/S
Attendant Alternative Answer	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0022A

Description	System Compatibility	Product compatibility	W/S
RPE	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0024A

Description	System Compatibility	Product compatibility	W/S
Line Load Control	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0025A

Description	System Compatibility	Product compatibility	W/S
CAS - Main	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0026A

Description	System Compatibility	Product compatibility	W/S
CAS - Remote	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0028A

Description	System Compatibility	Product compatibility	W/S
Fast TDS	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; XT X11 R17,18,19,20,21		S1

Notes:
- Automatically provisioned on all new systems. Requires NT8D17CA Conference/TDS Card or QPC609 Fast TDS.
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0029B

Description	System Compatibility	Product compatibility	W/S
Advanced Hospitality Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0018A Property Management Systems Interface (PMSI) is required for Maid ID functionality.
- SW0017A Hospitality/Healthcare Features is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0030A

Description	System Compatibility	Product compatibility	W/S
Flexible Tones and Cadences	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23; 61 X11 R17,18,19; 61C X11 R20,21,22,23; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23; 81C X11 R22,23; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.

Status
➤ S

SW0030B

Description	System Compatibility	Product compatibility	W/S
Flexible Tones and Cadences	51C X11 R24,25; 61C X11 R24,25; 81 X11 R24; 81C X11 R24,25		S1

Notes:
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0031A

Description	System Compatibility	Product compatibility	W/S
Hospitality Screen Enhancements	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:

- Requires use of Special Applications Display.
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0032A

Description	System Compatibility	Product compatibility	W/S
CAS - Main/Remote	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- Cannot be provisioned with SW0033A Attendant Overflow Position with X11 R23.37 and earlier software. Can be provisioned with SW0033A Attendant Overflow Position with X11 R23.55 and later software.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0033A

Description	System Compatibility	Product compatibility	W/S
Attendant Overflow Position	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- Cannot be configured with SW0055A Network Attendant Service.
- Cannot be provisioned with SW0032A Centralized Attendant Services with X11 Release 23.37 and earlier software. Can be provisioned with SW0032A Centralized Attendant Services with X11 Release 23.55 and later software.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0034A

Description	System Compatibility	Product compatibility	W/S
Line Load Control	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0040A

Description	System Compatibility	Product compatibility	W/S
CLASS Software	51C X11 R23,24,25; 61C X11 R23,24,25; 81 X11 R23,24,25; 81C X11 R23,24,25		S1

Notes:

- Requires a minimum of one CLASS Modem Card per system.
- ISDN Networking (SW0051X) software required to receive Automatic Number Identification (ANI) or Calling Line Identification (CLID) from the public network or through a Meridian 1 private ISDN network.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0041A

Description	System Compatibility	Product compatibility	W/S
NARS	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0042A

Description	System Compatibility	Product compatibility	W/S
Coordinated Dialing Plan	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0043A

Description	System Compatibility	Product compatibility	W/S
Network Authorization Code	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0044A

Description	System Compatibility	Product compatibility	W/S
Basic ESN Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0045A

Description	System Compatibility	Product compatibility	W/S
Advanced ESN Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0046A

Description	System Compatibility	Product compatibility	W/S
Feature Group D	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:
- QPC916 Multi-Frequency Receiver Card with a non-IPE Peripheral Equipment shelf or module is required.
- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0047A

Description	System Compatibility	Product compatibility	W/S
Direct Inward System Access (DISA)	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19; 51C X11 R22,23,24,25; 61 X11 R17,18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R17,18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R17,18,19,20,21; RT X11 R17,18,19,20,21; ST X11 R17; STE X11 R18,19,20,21; XT X11 R17,18,19,20,21		S1

Notes:

- System compatibility is STE or 21E for Release 18 and 19, not ST, 21 or 21A. System compatibility is ST, 21A and 21 for Release 17, not STE or 21E.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0048A

Description	System Compatibility	Product compatibility	W/S
Meridian COMPANION CLID/CPND/ Privacy	21E X11 R20,21; 51 X11 R20,21; 51C X11 R20,21,22,23,24,25; 61 X11 R20,21; 61C X11 R20,21,22,23,24,25; 71 X11 R20,21; 81 X11 R20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R20,21; RT X11 R20,21; STE X11 R20,21; XT X11 R20,21		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0049A

Description	System Compatibility	Product compatibility	W/S
Remote Software Option	21E X11 R21; 51 X11 R21; 51C X11 R21,22,23,24,25; 61 X11 R21; 61C X11 R21,22,23,24,25; 71 X11 R21; 81 X11 R21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R21; RT X11 R21; STE X11 R21; XT X11 R21		S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0050A

Description	System Compatibility	Product compatibility	W/S
Networking	21E X11 R19; 51 X11 R19; 61 X11 R19; 61C; 71 X11 R19; 81 X11 R19; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0050B

Description	System Compatibility	Product compatibility	W/S
Networking	21E X11 R19; 51 X11 R19; 51C X11 R22,23,24,25; 61 X11 R19; 61C X11 R22,23,24,25; 71 X11 R19; 81 X11 R19,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0051A

Description	System Compatibility	Product compatibility	W/S
ISDN Networking	21E X11 R18,19,20; 51 X11 R18,19; 61 X11 R18,19; 61C X11 R20; 71 X11 R18,19; 81 X11 R18,19,20; NT X11 R18,19,20; RT X11 R18,19,20; STE X11 R18,19,20; XT X11 R18,19,20		S1

Notes:
- Requires QPC757D or later DCHI card or NT6D80AA MSDL Card. QPC757E or later DCHI card or NT6D80AA MSDL card required for Network Name Display functionality.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0051B

Description	System Compatibility	Product compatibility	W/S
ISDN Networking	21E X11 R21; 51 X11 R21; 51C X11 R22,23,24,25; 61 X11 R21; 61C X11 R21,22,23,24,25; 71 X11 R21; 81 X11 R21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R21; RT X11 R21; STE X11 R21; XT X11 R21		S1

Notes:

- Requires QPC757D or later DCHI card or NT6D80AA MSDL Card. QPC757E or later DCHI card or NT6D80AA MSDL card required for Network Name Display functionality.
- SW0050 is a prerequisite for this package.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0052A

Description	System Compatibility	Product compatibility	W/S
Private ISDN Networking	21E X11 R19; 51 X11 R19; 61 X11 R19; 61C; 71 X11 R19; 81 X11 R19; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19		S1

Notes:

- SW0051A ISDN Networking is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0052D

Description	System Compatibility	Product compatibility	W/S
Private ISDN Networking	21E; 51; 51C X11 R22,23; 61; 61C X11 R22,23; 71; 81 X11 R22,23; 81C X11 R22,23; NT; RT; STE; XT		S1

Notes:

- Requires SW0051B (ISDN Networking).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0053A

Description	System Compatibility	Product compatibility	W/S
Public ISDN Access	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22; 61 X11 R18,19; 61C X11 R20,21,22; 71 X11 R18,19; 81 X11 R18,19,20,21,22; 81C X11 R22; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- SW0051A ISDN Networking is a prerequisite.
- SW0221A or SW0221B ACD/Message Processing required for In-Band ANI functionality.
- D-Channel Interface not required for In-Band ANI only functionality.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0053B

Description	System Compatibility	Product compatibility	W/S
Public ISDN Access	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:

- SW0051A ISDN Networking is a prerequisite.
- SW0221A or SW0221B ACD/Message Processing required for In-Band ANI functionality.
- D-Channel Interface not required for In-Band ANI only functionality.
- NI-2 Call by Call Service Selection requires Release 23.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0055A

Description	System Compatibility	Product compatibility	W/S
Network Attendant Services	21E X11 R20,21; 51C X11 R20,21,22,23,24,25; 61C X11 R20,21,22,23,24,25; 81 X11 R20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R20,21; RT X11 R20,21; STE X11 R20,21; XT X11 R20,21		S1

Notes:

- SW0051A ISDN Networking, SW0052B Private ISDN Networking are prerequisites.
- Mutually exclusive with SW0032A Centralized Attendant Service and SW0033A Attendant Overflow Position.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0057A

Description	System Compatibility	Product compatibility	W/S
Virtual Network Service	21 X11 R21; 51 X11 R21; 51C X11 R21,22,23,24,25; 61 X11 R21; 61C X11 R21,22,23,24,25; 71 X11 R21; 81 X11 R21,22,23,24,25; 81C X11 R21,22,23,24,25; NT X11 R21; RT X11 R21; STE X11 R21; XT X11 R21		S1

Notes:

- Maximum TN level=10 TN levels. Requires SW0051B (ISDN Networking), SW0052C (Private ISDN Networking), and SW0055A (Network Attendant Services) for Release 21. For Release 20, requires SW0051A instead of SW0051B.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0059B

Description	System Compatibility	Product compatibility	W/S
Network Message Services	21E X11 R19,20,21; 51 X11 R19; 51C X11 R20,21,22,23,24,25; 61 X11 R19; 61C X11 R20,21,22,23,24,25; 71 X11 R19; 81 X11 R19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S1

Notes:

- Pre-requisites: SW0051A ISDN Networking; SW0052A or SW0052B Private ISDN Networking; and SW0221A, SW0221B or SW0221C ACD/Message Processing.
- Meridian Mail requirements: for Meridian 1 to Meridian 1 interworking, requires Meridian Mail Release 7 or later; for Meridian 1 to Meridian SL-100/DMS interworking, requires Meridian Mail Release 8 or later.
- Interworking with Meridian SL-100/DMS-100 requires X11 Release 19 or later software or Meridian 1 and BCS 36 software or later on the Meridian SL-100 or DMS-100.
- Required at originating and terminating nodes; not required at tandem-only nodes.
- Northern Telecom does not guarantee functionality of Network Message Services used with Non-Meridian Mail voice messaging systems.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0060A

Description	System Compatibility	Product compatibility	W/S
Basic Hospitality	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23; 61 X11 R18,19; 61C X11 R20,21,22,23; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23; 81C X11 R22,23; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0060B

Description	System Compatibility	Product compatibility	W/S
Basic Hospitality	51C X11 R24,25; 61C X11 R24,25; 81 X11 R24,25; 81C X11 R24,25		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0061B

Description	System Compatibility	Product compatibility	W/S
Advanced Hospitality/PMSI	21E X11 R19,20,21; 51 X11 R19; 51C X11 R22,23,24,25; 61 X11 R19; 61C X11 R20,21,22,23,24,25; 71 X11 R19; 81 X11 R19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S1

Notes:
- SW0060A Basic Hospitality is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0062A

Description	System Compatibility	Product compatibility	W/S
Hospitality Voice Services	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:
- SW0060A Basic Hospitality and SW0221A or SW0221B ACD/Messaging Processing are prerequisites.
- Meridian Mail Release 6 or Release 8 with HVS software is required.
- SW0061A Advanced Hospitality/PMSI software is required for PMSI line enhancement functionality.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0064A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX MQA Option for Enhanced and Virtual Software (Release 8)	11C X11 R22; 51C X11 R21,22; 61C X11 R21,22; 81 X11 R21,22; 81C X11 R21,22	Meridian MAX-IPE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- Once this option is enabled, it cannot be disabled.
- This option can only be applied to Meridian MAX-IPE, Meridian MAX-SNN, or Meridian MAX-SNNE Release 8 Enhanced or Virtual software, or equivalent.
- Use caution when ordering MQA. The way in which information is displayed when MQA is installed is different than when it is not. If agents will not be logging into multiple queues, NORTEL recommends that MQA not be ordered.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0071A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN or MAX-SNNE 100-Agent Increment for Meridian MAX Releases 6, 7, and 8		Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- Required for Meridian MAX Release 5, 6, 7 and 8 agent expansions.
- Required to add agents in 100 agent increments beyond what is included in Base system software packages.
- Because base software includes support for 200 agents and the maximum capacity is 1200 agents; a maximum number of ten (10) of SW0071A can be ordered for one Meridian MAX-SNN or MAX-SNNE system.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0072A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX One-Time LAN Connectivity Fee for Release 6		Meridian MAX-IPE; Meridian MAX-SNN	S3

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Only one needs to be ordered per system to enable LAN connectivity.
- Available on the SNN and IPE system only.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0073A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX LAN Connectivity Software for Release 6 (Available in Increments of 1-59)		Meridian MAX-IPE; Meridian MAX-SNN	S3

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Allows for connection of one (1) PC to the LAN.
- Requires SW0072A, the one-time LAN Connectivity Fee.
- Available on the SNN and IPE systems only.
- Each LAN-connected PC must be equipped with Meridian Terminal Emulator (MTE) software, either NT1R75AA or NT1R75CA.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0074A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX MTE One-Time Enable Fee for Release 6		Meridian MAX-IPE; Meridian MAX-SNN	S3

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Can be used in lieu of Reflections 4+.
- For MTE software packages, order required quantity of NT1R75AA or NT1R75CA.
- Only one SW0074A MTE Enable option is required per Meridian MAX system.
- Is required on each PC connected to the Meridian MAX LAN.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0081A

Description	System Compatibility	Product compatibility	W/S
8-Channel Asynchronous I/O Software Support for Meridian MAX Releases 6, 7, and 8 (MAX-SNN and MAX-SNNE)		Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- The base software packages for MAX-SNN and MAX-SNNE systems each contain support for 8 I/O channels. Since each new MAX-SNN and MAX-SNNE hardware platform can accommodate a maximum of forty (40) asynchronous I/O channels, a maximum quantity of four (4) each of SW0081A can be ordered for one system.
- Required when adding additional ports to the Meridian MAX Release 5, 6, 7 or 8 SNN or SNNE systems.
- Enables operation of one (1) VME332XT 8-Channel Asynchronous I/O Card (A0376918). This card is part of the NT6D98AA kit.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SW0083A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN Release 5 to 6 Base Software Upgrade (200 Agents)		Meridian MAX	W1/ S3

Notes:

- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22/23) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality.
- For Release 18/19/20/21/22/23, prerequisites are SW0021A ACD/Message Processing (Release 18 only), SW0021B ACD/Message Processing (Release 19 only), SW0021C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX), SW0206A MAX Report Enhancements, and SW0207A Enhanced ACD Overflow.
- Requires X11 Release 17 or later for Option 21-81.
- Order this package when upgrading an existing MAX-SNN Release system to Meridian MAX Release 6.
- Requires Meridian MAX 5.25 or Higher to upgrade to MAX Release 6.
- Minimum MTE release supported is 5.31.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0605411	600MB Data Cassette Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R64AA	Meridian MAX Release 6 NTP Package	1	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4 6 & 5 Systems (to Release 6)
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0085A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 3 or 4 on Option 1 or 2 to MAX-SEE 6 Upgrade (160 Agents)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SEE	W1/ S3

Notes:

- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX), SW0206A MAX Report Enhancements, and SW0207A Enhanced ACD Overflow.
- Requires X11 Release 17 or later for Option 21-81.
- Does not allow for LAN or Network Administration Center connectivity.
- Includes support for 160 Agents; this is also the maximum number of Agents allowed.
- Includes Custom Calculator, Configuration Control, CCR/EAR MIS, Data Stream Reporting.
- To upgrade an existing Meridian MAX Release 3/4 System to Release 6. Only applies to single module systems that require no more than 8 I/O channels.
- For Release 18/19/20/21/22/23, prerequisites are SW0021A ACD/Message Processing (Release 18 only), SW0021B ACD/Message Processing (Release 19 only), SW0021C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0352271	150 MByte Data Cassette Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R64AA	Meridian MAX Release 6 NTP Package	1	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4 6 & 5 Systems (to Release 6)
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SW0086A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX SEE Release 5 to 6 Software Upgrade (160 Agents)	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SEE	S3

Notes:

- Maximum number of 8-Port Asynchronous I/O Cards allowed on MAX-SEE platform is (1).
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX), SW0206A MAX Report Enhancements, and SW0207A Enhanced ACD Overflow.
- Requires X11 Release 17 or later for Option 21-81.
- Does not allow for LAN or Network Administration Center connectivity.
- Includes support for 160 Agents; this is also the maximum number of Agents allowed.
- To upgrade an existing Meridian MAX-SEE System running on Release 5 to Release 6.
- For Release 18/19/20/21/22/23, prerequisites are SW0021A ACD/Message Processing (Release 18 only), SW0021B ACD/Message Processing (Release 19 only), SW0021C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0352271	150 MByte Data Cassette Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R64AA	Meridian MAX Release 6 NTP Package	1	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4 6 & 5 Systems (to Release 6)
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ Δ S

SW0087A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Release 5 to MAX-IPE Release 6 Base Software Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX; Meridian MAX-IPE	S3

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Option 11: Enhanced Business Software is required on the Option 11 system to fully use the features for a non-networked call center.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX), SW0206A MAX Report Enhancements, and SW0207A Enhanced ACD Overflow.
- Requires Meridian MAX 5.25 or Higher to upgrade to MAX Release 6.
- MTE Software packages must be upgraded to MTE Version 5.31.
- For Release 18/19/20/21/22/23, prerequisites are SW0021A ACD/Message Processing (Release 18 only), SW0021B ACD/Message Processing (Release 19 only), SW0021C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22/23) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is not supported on the Option 11, but is supported on the Option 11E and 11C.
- Order this package when upgrading an existing MAX-IPE Release 5 system to Release 6.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0605411	600MB Data Cassette Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R64AA	Meridian MAX Release 6 NTP Package	1	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4 6 & 5 Systems (to Release 6)
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

Status
➤ S

SW0093A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN Release 7 Fundamental to Enhanced Software Option Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN	S3

Notes:

- This option adds support to the Meridian MAX-SNN Release 7 Fundamental Software Package for 59 LAN Sessions, Custom Calculator/Formula Definition, Datastream Reporting, CCR/EAR MIS, MTE and NACD MIS.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0093B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN and MAX-SNNE Release 8 Fundamental to Enhanced Software Option Upgrade	21 X11 R17; 21A X11 R1717; 21E X11 R18,19,20,21; 51 X11 R17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R17,18,19,20,21; 81 X11 R18,19,20,21,22; 81C X11 R21,22	Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- To enable MQA order SW0064A, MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- This option adds support to the Meridian MAX-SNN and MAX-SNNE Release 8 Fundamental Software Package for 59 LAN Sessions, Datastream Reporting, CCR/EAR MIS, NACD MIS, MEI-Observe (3 links), the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable NAC Connectivity, order SW7525C.
- MEI-Observe requires X11 Release 19 or later for Option 21-81C.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0094A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN Release 7 Enhanced to Virtual Software Option Upgrade	21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-SNN	S3

Notes:

- MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- This option adds support to the Meridian MAX-SNN Release 7 Enhanced Software package for NAC Connectivity. To enable MQA order SW0352A. To enable MSI order SW0098A.
- MQA and MSI are mutually exclusive.
- NAC and MSI are mutually exclusive; if MSI is ordered than NAC Connectivity will be disabled.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0094B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-SNN and MAX-SNNE Release 8 Enhanced to Virtual Software Option Upgrade	21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R17,18,19,20,21; 81 X11 R18,19,20,21,22; 81C X11 R21,22	Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- To enable MQA order SW0064A, MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- To enable NAC Connectivity, order SW7525C.
- MEI-Observe and MEI-Network require X11 Release 19 or later for Option 21-81C.
- This option adds support to the Meridian MAX-SNN and MAX-SNNE Release 8 Enhanced Software package for MSI, MEI-Network, 1000 agents and the Meridian Terminal Emulator (MTE) Release 8 System Package.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0096A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Release 7 Fundamental to Enhanced Option Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE	S3

Notes:

- This option adds support to the Meridian MAX-IPE Release 7 Fundamental software package for 19 LAN sessions, Custom Calculator/ Formula Definition, Data Stream Reporting, CCR/EAR MIS, MTE and NACD MIS.
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0096B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE or MAX-IPEE Release 8 Fundamental to Enhanced Software Option Upgrade	11 X11 R18; 11C X11 R22; 11E X11 R20,21; 21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R17,18,19,20,21; 81 X11 R18,19,20,21,22; 81C X11 R21,22	Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:

- To enable MQA order SW0064A, MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- This option adds support to the Meridian MAX-IPE Release 8 Fundamental Software Package for 19 LAN Sessions, Datastream Reporting, CCR/EAR MIS, NACD MIS, MEI-Observe (3 links), the capability to enable NAC Connectivity and the capability to enable Multiple Queue Assignment.
- To enable NAC Connectivity, order SW7525C.
- MEI-Observe requires X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0097A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Release 7 Enhanced to Virtual Option Upgrade	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE	S3

Notes:

- MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- MQA and MSI are mutually exclusive.
- NAC and MSI are mutually exclusive; if MSI is ordered than NAC Connectivity will be disabled.
- This option adds support to the Meridian MAX -IPE Release 7 Enhanced Software package for NAC Connectivity. To enable MQA order SW0352A. To enable MSI order SW0098A.
- The Meridian 1 Serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0097B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE or MAX-IPEE Release 8 Enhanced to Virtual Software Option Upgrade	11 X11 R18; 11C X11 R22; 11E X11 R20,21; 21 X11 R17; 21A X11 R17; 21E X11 R18,19,20,21; 51 X11 R17,18,19,20,21; 51C X11 R20,21,22; 61 X11 R17,18,19,20,21; 61C X11 R20,21,22; 71 X11 R17,18,19,20,21; 81 X11 R18,19,20,21,22; 81C X11 R21,22	Meridian MAX-IPE; Meridian MAX-IPEE	S3

Notes:
- To enable MQA order SW0064A, MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- This option adds support to the Meridian MAX-IPE Release 8 Enhanced Software package for MSI and MEI-Network.
- To enable NAC Connectivity, order SW7525C.
- MEI-Observe and MEI-Network require X11 Release 19 or later for Option 21-81C or X11 Release 20 or later for Option 11, 11E, 11C.
- Includes MTE Release 8 System Package.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW0098A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX MSI Option for Virtual Software (Release 7)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN	S3

Notes:
- This option can only be applied to Meridian MAX-SNN or Meridian MAX-IPE Release 7 Virtual Software, or equivalent. It enables the MSI option and disables the NAC Connectivity option.
- This cannot be ordered in conjunction with Meridian MAX MQA Option for Virtual Software (SW0352A).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0101B

Description	System Compatibility	Product compatibility	W/S
Basic Rate Interface	21E X11 R19; 51 X11 R19; 61 X11 R19; 61C; 71 X11 R19; 81 X11 R19; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19		S1

Notes:
- Includes ISDN BRI Capacity Enhancements plus BRI Supplementary Services.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0101C

Description	System Compatibility	Product compatibility	W/S
Basic Rate Interface	21E X11 R20,21; 51C X11 R20,21,22,23,24,25; 61C X11 R20,21,22,23,24,25; 81 X11 R20,21,22,23,24,25; 81C X11 R21,22,23,24,25; NT X11 R20,21; RT X11 R20,21; STE X11 R20,21; XT X11 R20,21		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0102A

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Packet Handler	21E X11 R19,20,21; 51 X11 R19; 51C X11 R22,23,24,25; 61 X11 R19; 61C X11 R20,21,22,23,24,25; 71 X11 R19; 81 X11 R19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S1

Notes:
- Prerequisites include: SW0101C Basic Rate Interface and NT6D73AA Multi-purpose ISDN Signaling Processor (MISP) - this card must be dedicated to the MPH application.
- Order 1 MPH software package per 50 DSLs used to carry MPH data.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0104A

Description	System Compatibility	Product compatibility	W/S
Q.Sig ISDN Networking Software	51C X11 R22,23; 61C X11 R22,23; 81 X11 R22,23; 81C X11 R22,23	ACD MAX R4; CCR R3; MAT R5; Meridian IVR R1,2,3; Meridian Link R2,3,4,5,4B; Meridian MAX R4,5,6,7; Meridian Mail R9,10; NAC R1,2; Open IVR R2	S1

Notes:
- Requires SW0051B.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0104B

Description	System Compatibility	Product compatibility	W/S
Q.Sig ISDN Networking Software	51C X11 R24,25; 61C X11 R24,25; 81 X11 R24,25; 81C X11 R24,25	ACD MAX R4; CCR R3; MAT R5; Meridian IVR R1,2,3; Meridian Link R2,3,4,5,4B; Meridian MAX R4,5,6,7; Meridian Mail R9,10; NAC R1,2; Open IVR R2	S1

Notes:
- Requires SW0052D and SW0051B.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0105A

Description	System Compatibility	Product compatibility	W/S
ISDN Q.Sig Supplementary Services	51C X11 R22,23,24,25; 61C X11 R22,23,24,25; 81 X11 R22,23,24,25; 81C X11 R22,23,24,25	ACD MAX R4; CCR R3; MAT R5; Meridian IVR R1,2,3; Meridian Link R2,3,4,5,4B; Meridian MAX R4,5,6,7; Meridian Mail R9,10; NAC R1,2; Open IVR R2	S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0110A

Description	System Compatibility	Product compatibility	W/S
2.0 MB DTI/PRI Networking	51C X11 R23; 61C X11 R23; 81 X11 R23; 81C X11 R23		S1

Notes:
- SW0051 ISDN Networking is a prerequisite for this feature.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0150A

Description	System Compatibility	Product compatibility	W/S
Recorded Announcement Broadcast	51C X11 R23,24,25; 61C X11 R23,24,25; 81 X11 R23,24,25; 81C X11 R23,24,25	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:

- This feature is purchased in increments of 1 RAN Connections (e.g., Purchasing one unit of SW0150A will allow 1 RAN Connections, 2 units of SW0150A will allow 2 RAN Connections etc.).
- Total number of RAN Connections purchased will be independent of overall system TN counter.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0155A

Description	System Compatibility	Product compatibility	W/S
Music Broadcast	51C X11 R23,24,25; 61C X11 R23,24,25; 81 X11 R23,24,25; 81C X11 R23,24,25	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:

- This feature is purchased in increments of 1 Music Connection per package (e.g., Purchasing one unit of SW0155A will allow 1 Music Connection, 2 units of SW0150A will allow 2 Music Connections etc.).
- Total number of Music Connections purchased will be independent of overall system TN counter.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0165A

Description	System Compatibility	Product compatibility	W/S
Emergency Services Access (ESA) Enhanced Services	51C X11 R23,24,25; 61C X11 R23,24,25; 81 X11 R23,24,25; 81C X11 R23,24,25	ACD MAX R4; CPLUS (base) R3.14.18; IVR R1,2; M911 R2; MAT Windows 3.1 R4.7; MAT Windows 95/98 R5.7; Meridian 1 TAPI Server R1; Meridian CCR R3; Meridian IVR R1,2,3; Meridian Link R6; Meridian Mail R8,9,10,11; Meridian Mail Card Option R8,9,10,11; NAC R1,2; Nortel Multimedia H.320 R1.1; Open IVR R2; SYMPOSIUM Call Center Server (ICCM) R1; Visit Messenger R2; Visit Personal Assistant R1; Visit Video - Mac R2.1; Visit Voice - Windows R4	W0/ S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0170A

Description	System Compatibility	Product compatibility	W/S
Call Pilot Connectivity			S1

Notes:
- NTZE30AA, CallPilot Integration Suite is a prerequisite.
- SW0221C is required.
- Must be ordered with CallPilot.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0201B

Description	System Compatibility	Product compatibility	W/S
Basic ACD Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0202C

Description	System Compatibility	Product compatibility	W/S
Advanced ACD Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- Special Application Features is required for Name Display for DNIS functionality.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0203B

Description	System Compatibility	Product compatibility	W/S
ACD Reports Feature	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0204A

Description	System Compatibility	Product compatibility	W/S
ACD Load Management (ACD-C2)	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- ACD Reports (ACD C1) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0205A

Description	System Compatibility	Product compatibility	W/S
ACD Link (MAX/ACD-D)	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- ACD Reports (ACD C1) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- ACD Load Management (ACD C2) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0206A

Description	System Compatibility	Product compatibility	W/S
ACD D/MAX Report Enhancements	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- ACD Reports (ACD C1) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- ACD Load Management (ACD C2) is a prerequisite.
- ACD Link (MAX/ACD D) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0207A

Description	System Compatibility	Product compatibility	W/S
Enhanced ACD Overflow	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- ACD Timed Overflow is a prerequisite.
- If ACD MAX/Meridian MAX is equipped, ACD MAX/Meridian MAX must be configured with the Networking Option software options (923SL1-1 or 926SL1-1/SW7505A, SW7506A or SW7507A).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0208A

Description	System Compatibility	Product compatibility	W/S
ACD Timed Overflow	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- Basic ACD Features (ACD A) is a prerequisite.
- For Auxiliary Processor Application, minimum requirement is ACD D Generic 9000 Release 8 software.
- Advanced ACD Features (ACD B) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0209A

Description	System Compatibility	Product compatibility	W/S
Network ACD	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- Basic ACD Features (ACD A) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- ACD Timed Overflow is a prerequisite.
- SW0300C Basic ISDN Features is a prerequisite.
- NARS or CDP is a prerequisite at each site.
- PRI or ISDN Signaling Link is a prerequisite.
- Basic ESN Features is a prerequisite.
- Enhanced Overflow is a prerequisite.
- SW0303B Advanced ISDN Features is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0210A

Description	System Compatibility	Product compatibility	W/S
Enhanced ACD Routing	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- When used with ACD MAX or Meridian MAX, Release 4 software is required.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0211A

Description	System Compatibility	Product compatibility	W/S
Enhanced Call Treatment	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- Advanced ACD Features (ACD B) is a prerequisite.
- Enhanced ACD Routing Option (SW0210A) is a prerequisite.
- Customer Controlled Routing Hardware and Software are prerequisites.
- When used with ACD MAX or Meridian MAX, Release 4 software is required.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0221B

Description	System Compatibility	Product compatibility	W/S
ACD/Message Processing	21E X11 R19; 51 X11 R19; 61 X11 R19; 61C; 71 X11 R19; 81 X11 R19; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19	Meridian CCR; Meridian Link	S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0221C

Description	System Compatibility	Product compatibility	W/S
ACD/Message Processing	11C X11 R23; 21E X11 R20,21; 51C X11 R20,21,22,23,24,25; 61C X11 R20,21,22,23,24,25; 71 X11 R21; 81 X11 R20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R20,21; RT X11 R20,21; STE X11 R20,21; XT X11 R20,21	Meridian CCR; Meridian Link	S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0222A

Description	System Compatibility	Product compatibility	W/S
Enhanced ACD Overflow	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:
- When used with ACD MAX or Meridian MAX, MAX Networking Software is required.
- SW0221A or SW0221B ACD/Message Processing is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0223A

Description	System Compatibility	Product compatibility	W/S
Enhanced ACD Routing	11C X11 R23; 21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21	Meridian CCR; Meridian Link	S1

Notes:

- When used with ACD MAX or Meridian MAX, Release 4 software is required.
- SW0221A or SW0221B ACD/Message Processing is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0224A

Description	System Compatibility	Product compatibility	W/S
Enhanced Call Center Management	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- For MAX functionality, Meridian MAX, Meridian IPE or ACD-MAX is required.
- SW0221A or SW0221B ACD/Message Processing is a prerequisite.
- Optional prerequisite of SW0221 depending on functionality required.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0225B

Description	System Compatibility	Product compatibility	W/S
Enhanced Call Center Routing	11C X11 R23; 21E X11 R19,20,21; 51 X11 R19; 51C X11 R22,23,24,25; 61 X11 R19; 61C X11 R20,21,22,23,24,25; 71 X11 R19; 81 X11 R19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21	Meridian CCR; Meridian Link	S1

Notes:

- SW0221B ACD/Message Processing and SW0223A Enhanced ACD Routing are prerequisites.
- CCR Application Module required for Enhanced Call Center Routing functionality.
- When used with Meridian MAX or ACD-MAX, Release 4 or later software is required.
- Optional prerequisite of SW0221 depending on functionality required.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0226A

Description	System Compatibility	Product compatibility	W/S
Call Center Networking	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- When used with ACD MAX or Meridian MAX, MAX Networking Software is required.
- SW0221A or SW0221B ACD/Message Processing, SW0222A Enhanced ACD Overflow, SW0050A Networking, SW0051A ISDN Networking, and SW0052A Private ISDN Networking are prerequisites.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0227A

Description	System Compatibility	Product compatibility	W/S
Hold in Queue for IVR	21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21		S1

Notes:

- CCR Application Module, Enhanced ACD Routing (SW0223A) are prerequisites.
- Meridian Mail Release 8, Meridian IVR Release 1 or compatible third party Interactive Voice Response system is required.
- Not supported on ACD-MAX.
- Meridian MAX Release 4 is required.
- SW0221A or SW0221B ACD/Message Processing and SW0225A or SW0025B Enhanced Call Center Routing are prerequisites.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0228A

Description	System Compatibility	Product compatibility	W/S
CCR-NACD Interworking	51C X11 R22,23,24,25; 61C X11 R22,23,24,25; 81 X11 R22,23,24,25; 81C X11 R22,23,24,25	Meridian CCR R2	S1

Notes:

- Prerequisites are SW0225B Enhanced Call Center Routing and SW0226A Call Center Networking.
- Requires X11 Release 22 (upissue).
- Meridian MAX Release 8 (or later) software is a prerequisite if Meridian MAX is to be used to report on CCR-NACD calls.
- The remote target node does not require any X11 software changes to support the CCR-NACD Interworking feature.
- No hardware or software changes are required to the CCR Application Module.
- X11 software option number for CCR-NACD Interworking is 321.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ ⊗ S

SW0229A

Description	System Compatibility	Product compatibility	W/S
Meridian 911	21E X11 R19; 51 X11 R19; 61 X11 R19; 61C; 71 X11 R19; 81 X11 R19; NT X11 R19; RT X11 R19; STE X11 R19; XT X11 R19		S1

Notes:

- Requires SW0221B (ACD/Message Processing), SW0223A (Enhanced ACD Routing), and SW0251A (Meridian Link Module Software).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0229C

Description	System Compatibility	Product compatibility	W/S
Meridian 911	21E; 51; 51C X11 R22,23,24; 61; 61C X11 R22,23,24; 71; 81 X11 R22,23,24; 81C X11 R22,23,24; NT; RT; STE; XT		S1

Notes:
- Requires SW0221C (ACD/Message Processing), SW0223A (Enhanced ACD Routing) and SW0251A (Meridian Link Module Software).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
✓➤ S

SW0229D

Description	System Compatibility	Product compatibility	W/S
Meridian 911	21E; 51; 51C X11 R22,23,24,25; 61; 61C X11 R22,23,24,25; 71; 81 X11 R22,23,24,25; 81C X11 R22,23,24,25; NT; RT; STE; XT		S1

Notes:
- Requires SW0221C (ACD/Message Processing), SW0223A (Enhanced ACD Routing) and SW0251A (Meridian Link Module Software).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0230A

Description	System Compatibility	Product compatibility	W/S
Multiple Queue Assignment	51C X11 R21,22,23,24,25; 61C X11 R21,22,23,24,25; 81 X11 R21,22,23,24,25; 81C X11 R21,22,23,24,25		S1

Notes:
- Requires SW0221C (ACD/Message Processing) and SW0224A (Enhanced Call Center Management).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0234A

Description	System Compatibility	Product compatibility	W/S
Electronic Brandlining - Display Customization	51C; 61C; 81; 81C		W0/ S1

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW0251A

Description	System Compatibility	Product compatibility	W/S
Meridian Link Module Software	11C X11 R23; 21E X11 R18,19,20,21; 51 X11 R18,19; 51C X11 R22,23,24,25; 61 X11 R18,19; 61C X11 R20,21,22,23,24,25; 71 X11 R18,19; 81 X11 R18,19,20,21,22,23,24,25; 81C X11 R22,23,24,25; NT X11 R18,19,20,21; RT X11 R18,19,20,21; STE X11 R18,19,20,21; XT X11 R18,19,20,21	Meridian Link	S1

Notes:
- SW0221A or SW0221B ACD/Message Processing is a prerequisite.

Status
† ➤ S

SW0300C

Description	System Compatibility	Product compatibility	W/S
Basic ISDN Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- ISDN functionality requires SW0301A Primary Rate Interworking Access or SW0302A ISDN Signaling Link application software.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0301A

Description	System Compatibility	Product compatibility	W/S
Primary Rate Access	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0300C Basic ISDN Features is a prerequisite.
- X11 Release 15 and later PRI or ISL applications require QPC757 Vintage D or later.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0302A

Description	System Compatibility	Product compatibility	W/S
ISDN Signaling Link	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0300C Basic ISDN Features is a prerequisite.
- X11 Release 15 and later PRI or ISL applications require QPC757 Vintage D or later.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0303B

Description	System Compatibility	Product compatibility	W/S
Advanced ISDN Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0300C Basic ISDN Features is a prerequisite.
- X11 Release 15 and later PRI or ISL applications require QPC757 Vintage D or later.
- NARS or CDP is a prerequisite at each site, however, all switches should be NARS only or CDP only.
- SW0301A Primary Rate Interface or SW0302A ISDN Signaling Link is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0304B

Description	System Compatibility	Product compatibility	W/S
Inter-Exchange Carrier/In-Band ANI	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- SW0300C Basic ISDN Features and SW0301A Primary Rate Interface are prerequisites.
- For In-Band ANI functionality, Basic ACD (ACD A) and Advanced ACD Features are required.
- QPC757 (DCHI) is not required for In-Band ANI.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0305A

Description	System Compatibility	Product compatibility	W/S
Call by Call Service	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- SW0300C Basic ISDN Features and SW0301A Primary Rate Interface are prerequisites.
- X11 Release 15 and later PRI or ISL applications require QPC757 Vintage D or later.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0306A

Description	System Compatibility	Product compatibility	W/S
Network Message Services	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:

- SW0300C Basic ISDN Features is a prerequisite.
- SW0303B Advanced ISDN Features is a prerequisite.
- Network Message Services is required at the originating and terminating nodes; it is not required for tandem-only nodes.
- SW0301A Primary Rate Interface or SW0302A ISDN Signaling Link is a prerequisite.
- Requires Meridian Mail Release 7.
- Northern Telecom cannot support Network Message Services when configured with Non-Meridian Mail systems (third-party voice processing systems) as Northern Telecom cannot guarantee the level of functionality.
- For Network Meridian Mail Applications the terminating node has Basic ACD features (ACD A). IVMS Link, Meridian Mail Link, and X11 Release 16 or later software are prerequisites. The originating node has Basic ACD features (ACD A) and X11 Release 16 or later software as prerequisites.
- For Network Message Center non-ACD applications the terminating and originating node have X11 Release 15 or later software as prerequisites.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW0352A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX MQA Option for Virtual Software (Release 7)	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-SNN	S3

Notes:

- MQA requires X11 Release 21 or later with SW0230A Multiple Queue Assignment.
- This option can only be applied to Meridian MAX-SNN or Meridian MAX-IPE Release 7 Virtual Software, or equivalent.
- Once this option is enabled, it cannot be disabled.
- This cannot be ordered in conjunction with Meridian MAX MSI Option for Virtual Software (SW0098A).
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0401A

Description	System Compatibility	Product compatibility	W/S
Auxiliary Processor Link	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0402A

Description	System Compatibility	Product compatibility	W/S
IVMS Link	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0403A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Link	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- IVMS Link is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
† ➤ S

SW0406C

Description	System Compatibility	Product compatibility	W/S
Meridian Link Module Software	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- IVMS Link is a prerequisite.
- Meridian Mail Link is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW0407A

Description	System Compatibility	Product compatibility	W/S
Meridian Hospitality Voice Services Features	21 X11 R17; 21A X11 R17; 51 X11 R17; 61 X11 R17; 71 X11 R17; NT X11 R17; RT X11 R17; ST X11 R17; XT X11 R17		S1

Notes:
- Basic ACD Features (ACD A) is a prerequisite.
- IVMS Link is a prerequisite.
- Meridian Mail Link is a prerequisite.
- Hospitality/Healthcare Features & PMSI are prerequisites if PMSI line enhancement functionality is required.
- Requires Meridian Mail Release 6 or Release 8 and HVS software.
- Auxiliary Processor Link is a prerequisite.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
† ➤ S

SW1037A

Description	System Compatibility	Product compatibility	W/S
Meridian Manager Replacement Package	21; 21A; 51; 61; 61C; 71; A; L; LE; M; MS; N; NT; RT; S; ST; VL; VLE; XL; XN; XT		S3

Status
➤ S

SW1121E

Description	System Compatibility	Product compatibility	W/S
General Business Software (Add. 100 TNs)	11; 11E		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW1122E

Description	System Compatibility	Product compatibility	W/S
Enhanced Business Software (Add. 100 TNs)	11; 11E		S1

Notes:
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW1126D

Description	System Compatibility	Product compatibility	W/S
Enterprise Business Software (Add. 100 TNs)	11E		S1

Notes:
- This package works with both the Enterprise Business and Enterprise Business (no DISA) packages.
- Provides an additional 100 TNs.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW1127D

Description	System Compatibility	Product compatibility	W/S
NAS Software (Add. 100 TNs)	11E		S1

Notes:
- This package works with both the NAS and NAS (no DISA) special application packages.
- Provides an additional 100 TNs.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW1131E

Description	System Compatibility	Product compatibility	W/S
General Business Software Update	11E		S1

Notes:

- Updates are used to: 1) Move a system from one feature set to another (e.g. General Business to Enhanced Business), and 2) move a system from one software issue to another (e.g. from NTAK83AA to NTAK83AH).
- When ordering a software update, you must provide either the Option 11 system serial ID or the following information 1) the current software feature set (e.g. General Business or Enhanced Business); 2) the current terminal number (TN) level (e.g., 200 TNs or 300 TNs; and 3) whether Meridian Mail Card Option is implemented. If so, you must state whether it includes HVS or Networking. Order one of the update numbers, and a new cartridge will be shipped to you.
- A credit equal to the current price of the existing software as listed in the Product Catalog will be issued upon return of the old cartridge.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW1132E

Description	System Compatibility	Product compatibility	W/S
Enhanced Business Software Update	11E X11 R20,21		S1

Notes:

- Updates are used to: 1) Move a system from one feature set to another (e.g. General Business to Enhanced Business), and 2) move a system from one software issue to another (e.g. from NTAK83AA to NTAK83AH).
- When ordering a software update, you must provide either the Option 11 system serial ID or the following information 1) the current software feature set (e.g. General Business or Enhanced Business); 2) the current terminal number (TN) level (e.g., 200 TNs or 300 TNs; and 3) whether Meridian Mail Card Option is implemented. If so, you must state whether it includes HVS or Networking. Order one of the update numbers, and a new cartridge will be shipped to you.
- A credit equal to the current price of the existing software as listed in the Product Catalog will be issued upon return of the old cartridge.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW1141D

Description	System Compatibility	Product compatibility	W/S
Enterprise Business Software Update	11E X11 R20,21		S1

Notes:

- With all software updates, customer must return old software cartridge for credit.
- If Enterprise Business software update (SW1141A) is ordered, customer will be credited price originally paid for Release 16 or 18 software (except if Advanced Application software was originally ordered.
- If customer upgrades to a less expensive software package (i.e., currently on Advanced Application package and upgrading to Enterprise Business package), customer will be charged $1,000 CLP (Discount I) more than what was originally paid in order to receive the new software update.
- Updates are used to: 1) Move a system from one feature set to another (e.g. General Business to Enhanced Business), and 2) move a system from one software issue to another (e.g. from NTAK83AA to NTAK83AH).
- When ordering a software update, you must provide either the Option 11 system serial ID or the following information 1) the current software feature set (e.g. General Business or Enhanced Business); 2) the current terminal number (TN) level (e.g., 200 TNs or 300 TNs; and 3) whether Meridian Mail Card Option is implemented. If so, you must state whether it includes HVS or Networking. Order one of the update numbers, and a new cartridge will be shipped to you.
- A credit equal to the current price of the existing software as listed in the Product Catalog will be issued upon return of the old cartridge.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW1142D

Description	System Compatibility	Product compatibility	W/S
NAS Software Update	11E X11 R20,21		S1

Notes:

- Updates are used to: 1) Move a system from one feature set to another (e.g. General Business to Enhanced Business), and 2) move a system from one software issue to another (e.g. from NTAK83AA to NTAK83AH).
- When ordering a software update, you must provide either the Option 11 system serial ID or the following information 1) the current software feature set (e.g. General Business or Enhanced Business); 2) the current terminal number (TN) level (e.g., 200 TNs or 300 TNs; and 3) whether Meridian Mail Card Option is implemented. If so, you must state whether it includes HVS or Networking. Order one of the update numbers, and a new cartridge will be shipped to you.
- A credit equal to the current price of the existing software as listed in the Product Catalog will be issued upon return of the old cartridge.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW7004B

Description	System Compatibility	Product compatibility	W/S
Hospitality Voice Services Software		Meridian Mail Modular EC R8,9,10,11,12; Meridian Mail Modular Option R8,9,10,11,12; Meridian Mail Modular Option GP R8,9,10,11,12	W0

Notes:

- HVS Documentation is not included and must be ordered separately, if required.
- Adding HVS software to an installed system requires complete software re-load and database re-build. Nortel recommends adding HVS software when the system is originally purchased if the capability is to be added in the future.
- This option requires X11 Release 16 Software or later and Meridian HVS Features (SW0062A or SW0407A).
- HVS is not available with Network Message Services on pre-Release 11 Meridian Mail Systems.
- Hospitality Voice Services requires AS7010 HVS Package.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW7007

Description	System Compatibility	Product compatibility	W/S
Secured Messaging Software		Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7008

Description	System Compatibility	Product compatibility	W/S
Network Message Service Software		Meridian Mail EC R10; Meridian Mail Modular Option R10; Meridian Mail Option X R10; Meridian Mail Options (ST/RT) R10	W0

Notes:

- This feature is incompatible with Meridian Mail Multi-Customer.
- Network Message Services Software and HVS are mutually exclusive on pre-Release 11 systems.
- If one or more Meridian Mail sites networked with Meridian Mail Networking (SW7010) are also running Network Message Services (SW7008), all networked Meridian Mail sites must be converted to Meridian Mail Release 7 or later.
- Network Message Service requires X11 Release 16, or later with Network Message Service enabling options, Option 175.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW7008B

Description	System Compatibility	Product compatibility	W/S
Network Message Services Prime Site Software, Release 11 and Later		Meridian Mail Modular Option R11,12; Meridian Mail Modular Option EC R11,12	W0

Notes:

- NMS documentation is not included and must be ordered separately, if required.
- Requires purchase of at least one Network Message Service Remote Site Software option.
- If one or more Meridian Mail sites networked with Meridian Mail Networking are also running Network Message Services, all networked Meridian Mail sites must be converted to Meridian Mail Release 7 or later.
- Network Message Service requires X11 Release 17 or later with NMS enabling options (Option 175).
- This feature is incompatible with Meridian Mail Multi-Customer.
- The Meridian 1 Serial number must be provided when ordering this code for an existing Meridian 1 system.

Status
➤ S

SW7009D

Description	System Compatibility	Product compatibility	W/S
AdminPlus Enable Option		Meridian Mail EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W1

Notes:

- Requires Meridian Mail Reporter Single Site or Multi Site PC Software Package.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7010B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Networking/Enterprise Networking		Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Option S R10; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	W0

Notes:

- Networking Documentation is not included and must be ordered separately if required.
- In a multi-customer environment, only one customer can have Networking.
- If one or more Meridian Mail sites networked with Meridian Mail Networking are also running Network Message Services, all networked Meridian Mail sites must be converted to Meridian Mail Release 7 or later.
- AS7012 Meridian Mail Networking Modem Package is required when networked to pre-Release 11 systems.
- For Modular Option systems with HVS, system resources may limit the availability of certain features and capabilities, based on the configuration.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7023

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Additional Language		Meridian Mail EC11 R11; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R12; Meridian Mail Modular Option GP R12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- Order one for each additional language required; maximum of four (4) languages. One language comes standard.
- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7024

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Dual Language Prompt		Meridian Mail EC11 R11; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R12; Meridian Mail Modular Option GP R12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- SW7023 Additional Language Software is a prerequisite.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7030E

Description	System Compatibility	Product compatibility	W/S
Meridian Mail ACCESS Enable Option		Meridian Mail Modular EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- Access documentation is not included and must be ordered separately, if required.
- Requires X11 Release 14 or later software.
- Meridian Mail systems with ACCESS Enable Option cannot be used with Meridian Mail AdminPlus Enable Software on pre-MM10 systems.
- The maximum number of ports that can be used for Meridian ACCESS applications in a one or two node Meridian Mail configuration is one (1); three nodes or greater support a maximum of two Meridian ACCESS ports with MM10 and later, a max of eight (8) access links may be equipped.
- Meridian Mail systems Release 9 and earlier, with ACCESS Enable Option cannot be used with Meridian Mail AdminPlus Enable Software (SW7009).
- For Modular Option systems with HVS, system resources may limit the availability of certain features and capabilities, based on the configuration.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7035C

Description	System Compatibility	Product compatibility	W/S
Meridian Mail AMIS Networking (Virtual Node)		Meridian Mail GP R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Option S R10,11,12; Meridian Mail Option X R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10,11,12	S1

Notes:

- Meridian Mail AMIS Networking documentation is not included and must be ordered separately, if required.
- Combines AMIS and Networking / Enterprise Networking software options into a single package. Replaces the need to order AMIS and Networking / Enterprise Networking separately.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7040D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Voice Forms		Meridian Mail GP R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Option S R10,11,12; Meridian Mail Option X R10,11,12; Meridian Mail Options (NT/XT) R10,11,12; Meridian Mail Options (ST/RT) R10,11,12	S1

Notes:

- Meridian Mail Voice Forms documentation is not included and must be ordered separately if required.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7041G

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Multi-Customer		Meridian Mail GP R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Option S R10,11,12; Meridian Mail Option X R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10,11,12	W1/ S1

Notes:

- This feature is incompatible with Network Message Service.
- In a multi-customer environment, only one customer can have Hospitality Voice Service. In a multi-customer environment, only one customer can have Networking.
- Documentation is not included. Order Documentation separately as required.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7042B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail AMIS Open Networking		Meridian Mail GP R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Option S R10,11,12; Meridian Mail Option X R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10,11,12	W1/ S1

Notes:

- Option systems require a 32K NVP card (NT4R01AC).
- For systems with HVS, system resources may limit the availability of certain features and capabilities, based on the configuration.
- To implement AMIS virtual node networking, order SW7035C which includes Meridian Mail AMIS Open Networking and Meridian Mail Networking.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7043

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Multiple Administration		Meridian Mail Modular EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- For Modular Option systems with HVS, system resources may limit the availability of certain features and capabilities, based on the configuration.
- One (1) Administrative Terminal is supported per node.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7049

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 1-2		Meridian Mail EC11 R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option GP R11; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- Expands minimum of 600MB systems from base storage level to the second storage hour level noted in each base platform package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7050

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration		Meridian Mail Modular EC	W0

Notes:

- SW7050 is required when ordering a migration from the Options or Modular Option to a Modular Option EC and migrations from the Card Option to the EC11.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7054

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 2-3		Meridian Mail EC11 R10,11,12; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R11,12; Meridian Mail Modular Option GP R11; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- SW7049 Expanded Storage Level 1-2 is a prerequisite.
- Expands 600MB and 1.0GB disk systems to third storage hour level noted in each base platform package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7055

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 3-4		Meridian Mail EC11 R10,11,12; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R11,12; Meridian Mail Modular Option GP R11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- SW7054 Expanded Storage Level 2-3 is a prerequisite.
- Expands minimum of 600MB systems to third storage hour level noted in each base platform package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7056

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 4-5		Meridian Mail EC11 R10,11,12; Meridian Mail Modular EC R10; Meridian Mail Modular GP R10; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R11,12; Meridian Mail Modular Option GP R11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- SW7055 Expanded Storage Level 3-4 is a prerequisite.
- Modular Option and Modular Option GP systems require Release 8.28 or later.
- Expands minimum of 1.0GB systems to fifth storage hour level noted in each base platform package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7057B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Fax on Demand Software		Meridian Mail Modular EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option EC R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10,11,12	W1/ S1

Notes:

- Fax On Demand documentation is not included and must be ordered separately, if required
- Requires one (1) or more software defined multimedia ports to be configured. Each multimedia port requires two (2) full service ports.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7058

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Outcalling		Meridian Mail Modular EC R10,11,12; Meridian Mail Modular GP R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- This option is only used to add Outcalling to systems already running Release 8 or later.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7059

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Expanded Storage Software Level 5-6		Meridian Mail EC11 R11,12; Meridian Mail Modular Option R11,12; Meridian Mail Modular Option EC R11,12; Meridian Mail Modular Option GP R11,12	W0

Notes:

- SW7056 Expanded Storage Software level 4-5 and a 2GB disk drive are prerequisites.
- Expands minimum of 2.0 GB disk drive systems to the sixth storage hour level noted in each base platform description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7060

Description	System Compatibility	Product compatibility	W/S
Meridian Mail SMDI Software		Meridian Mail Modular GP R9,10,11,12	S1

Notes:

- All systems without Connections capability require SW7060 SMDI software. All systems with Connections capability require SW7061 SMDI/Connections software.
- SMDI/Connections software is not compatible with Network Message Service or Hospitality Voice Services.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7061

Description	System Compatibility	Product compatibility	W/S
Meridian Mail SMDI Connections Software		Meridian Mail Modular GP R10,11,12	S1

Notes:

- SMDI/Connections software is not compatible with Network Message Service or Hospitality Voice Services.
- Required only to support Connections (Meridian Mail connected to non-Northern PBX).
- At least one Connections hardware package must be ordered separately.
- Appropriate Meridian Mail Connections Reference Manual must be ordered separately.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7062

Description	System Compatibility	Product compatibility	W/S
Meridian Mail GP Multi-SMDI Software		Meridian Mail Modular GP R10,11,12	S1

Notes:

- This feature is incompatible with Network Message Services and Hospitality Voice Services.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7065

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Basic to Full Service per Port Software Upgrade		Meridian Mail EC11 R10,11,12; Meridian Mail Modular EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (NT/XT) R10; Meridian Mail Options (ST/RT) R10	S1

Notes:

- This upgrade is applied only to systems with ports operating with Basic Service License Fees.
- The Meridian Mail serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7068

Description	System Compatibility	Product compatibility	W/S
Network Message Services Remote Site Software, Release 11		Meridian Mail Modular Option R11,12; Meridian Mail Modular Option EC R11,12; Meridian Mail Modular Option GP R11,12	W0

Notes:

- Required for each Network Message Service Remote Site.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7072

Description	System Compatibility	Product compatibility	W/S
Meridian Mail VMUIF		Meridian Mail EC R10,11,12; Meridian Mail Modular Option R10,11,12; Meridian Mail Modular Option GP R10,11,12; Meridian Mail Options (ST/RT, NT/XT) R10,11,12	W1/ S1

Notes:

- VMUIF user guides are not included and must be ordered separately, if required.
- The Multi-customer software feature is required for existing systems adding VMUIF and new systems which will use both the MMUI and VMUIF user interfaces. Multi-Customer is not required for new systems installing only the VMUIF interface.
- VMUIF mail boxes are not compatible with Meridian Mail Proprietary Networking. If networking is required for VMUIF mailboxes, order AMIS-Networking.
- When adding VMUIF, all NVP cards equipped must be 32K NVPs.
- he Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

Status
➤ S

SW7074

Description	System Compatibility	Product compatibility	W/S
Meridian Mail AutoAdmin Link Software		Meridian Mail Modular EC R12; Meridian Mail Modular Option R12; Meridian Mail Modular Option GP R12	S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Meridian 1 the Meridian 1 serial number is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7102

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Expanded Storage Software Level 1-2		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	S1

Notes:

- This software is required to utilize the second storage hour level noted in the base platform system package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7103

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Expanded Storage Software Level 2-3		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	S1

Notes:

- SW7102 Expanded Storage Software Level 1-2 is a prerequisite.
- This software is required to utilize the third storage hour level noted in the base platform system package description.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7104B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Fax on Demand Software		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W1/ S1

Notes:

- Fax On Demand documentation is not included and must be ordered separately, if required.
- Requires one or more multimedia ports to be configured. Each multimedia port requires two full service ports.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7109

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Additional Language		Meridian Mail Card Option R8,10,11,12; Meridian Mail EC11 R10,11,12	S1

Notes:

- Order one for each additional language required; maximum of four languages. One language comes standard.
- For Release 8 Card Option systems with HVS, system resources may limit the availability of certain features and capabilities based on the configuration.
- Each additional language reduces storage capacity by three hours.
- One North American Master Tape is shipped with every system. Order additional Master Tape(s) separately, if required, based on language combination. A maximum of four (4) languages are available per system.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7110

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Dual Language Prompt		Meridian Mail Card Option R8,10,11,12; Meridian Mail EC11 R10,11,12	S1

Notes:

- SW7109 Additional Language Software is a prerequisite.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ B

SW7111B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 HVS Software		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W1/ S1

Notes:

- HVS documentation is not included and must be ordered separately as required.
- For Release 8 Card Option systems with HVS, system resources may limit the availability of certain features and capabilities based on the configuration.
- Adding HVS software to an installed system requires complete software re-load and database re-build. Nortel recommends adding HVS software when the system is originally purchased if HVS will be required in the future.
- Meridian Mail Card Option HVS requires configuration engineering.
- The required RS232C Service Module (RSM) and its associated cable are available in the HVS Hardware Kit.
- Both hardware and software are required for Meridian Mail Card Option HVS. A VT420 compatible terminal such as the AS7011 DEC Terminal Package must be purchased separately.
- HVS is not compatible with Network Message Services on pre-MM11 systems. HVS quest mailboxes are not supported at Meridian 1 remote systems.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7112B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Networking Software, Release 11 or Later		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W1/ S1

Notes:

- The networking features for Option 11 Meridian Mail are activated on the base software with a keycode.
- The required RS232C Service Module (RSM) and its associated cable are available in the HVS Hardware Kit.
- Meridian Mail Networking / Enterprise Networking requires configuration engineering.
- SW7112B requires a networking modem package when networking to pre-Release 11 sites.
- Networking documentation is not included and must be ordered separately as required.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7113D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Voice Forms		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W1/ S1

Notes:

- Voice Forms documentation is not included and must be ordered separately as required.
- For pre-Release 9 Card Option systems with HVS, system resources may limit the availability of certain features and capabilities based on the configuration.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7114F

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Multi-Customer		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0

Notes:

- Multi-Customer documentation is not included and must be ordered separately as required
- This feature is incompatible with Network Message Services.
- In a Multi-Customer environment, only one customer can have Hospitality Voice Services. In a Multi-customer environment, only one customer can have Networking.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7115B

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 AMIS Networking		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0

Notes:

- Amis Networking documentation is not included and must be ordered separately as required.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7116

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Network Message Service Software		Meridian Mail Card Option R10; Meridian Mail EC11 R10	W0

Notes:

- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7117C

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 ACCESS Enable Option		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0/ S2

Notes:

- Access documentation is not included and must be ordered separately as required.
- The required RS232C Service Module (RSM) and its associated cable are available in the HVS Hardware Kit.
- The access enable option requires the installation of a RSM card, NTAK18BA or later.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7118

Description	System Compatibility	Product compatibility	W/S
Meridian Mail AdminPlus Enable Option		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0

Notes:

- Requires Meridian Mail Reporter Single Site or Multi Site PC Software Package.
- Multi-site requires Meridian Mail Release 10 or later, and the AdminPlus Enable Option at all locations.
- Card option systems must be equipped with a RSM card with a spare data port.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7119

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 AutoAdmin Link Software			S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ Δ S

SW7121

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Outcalling		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7122

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 VMUIF		Meridian Mail Card Option R10,11,12; Meridian Mail EC11 R10,11,12	W0

Notes:

- VMUIF user guides/documentation are not included and must be ordered separately as required.
- The Multi-Customer software feature is required for existing systems adding VMUIF and new systems which will use both the MMUI and VMUIF user interfaces. Multi-Customer is not required for new systems installing only the VMUIF interface.
- VMUIF mailboxes are not compatible with Meridian Mail Proprietary Networking. If networking is required for VMUIF mailboxes, order AMIS-Networking.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Qty	Order code	Description	
1	NT1F97AA	Meridian Mail Release 12 Voice Messaging Package (VMUIF)	
	Each Package Includes:		
	15	P0875942	Meridian Mail Release 12 Voice Messaging (VMUIF) User Guide
	15	P0875943	Meridian Mail Release 12 Voice Messaging (VMUIF) Quick Reference Cards
	15	P0875944	Meridian Mail Release 12 Voice Messaging (VMUIF) "At A Glance" Cards

Status
➤ S

SW7123

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Network Message Services, Prime Site, Release 11 and Later		Meridian Mail Card Option R11,12; Meridian Mail EC11 R11,12	W0

Notes:

- Requires purchase of at least one Network Message Services Remote Site software.
- NMS documentation is not included and must be ordered separately as required.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7124

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Option 11 Network Message Services, Remote Site, Release 11 and Later		Meridian Mail Card Option R12; Meridian Mail EC11 R12	W0

Notes:

- Required for each Network Message Service Remote Site.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7140

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Expanded Storage Software Level 3-4		Meridian Mail Card Option R12	W0

Notes:

- SW7103 Expanded Storage Software Level 2-3 is a prerequisite.
- The Meridian Mail serial number must be provided when ordering this code for an existing Meridian Mail. If ordered as part of a new Meridian Mail system for an existing Option 11 the Option 11 Site ID is required.

Status
➤ S

SW7151

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Card Option Basic to Full Service License Fee Upgrade			S1

Notes:

- The Meridian Mail serial number must be provided when ordering this code.

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7415A

Description	System Compatibility	Product compatibility	W/S
Customer Controlled Routing Release 3C from 20 to 240 Active Scripts Software Upgrade Package	11C X11 R22,23,24; 11E X11 R20,21; 21E X11 R19,20,21; 51 X11 R19,20,21; 51C X11 R20,21,22,23,24; 61 X11 R19,20,21; 61C X11 R20,21,22,23,24; 71 X11 R19,20,21; 81 X11 R19,20,21,22,23,24; 81C X11 R21,22,23,24; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S3

Notes:

- Meridian MAX Release 4 or later is a prerequisite if Meridian MAX is to be used to report on Customer Controlled Routing activity.
- For operation of the CCR Hold in Queue for IVR feature, the prerequisite is SW0227A Hold in Queue for IVR.
- For X11 Releases 20 and higher, prerequisites are SW0221C ACD/Message Processing, SW0223A Enhanced ACD Routing, and SW0225B Enhanced Call Center Routing.
- For Option 11 systems, the X11 Release 22 and higher prerequisite is NTSF8022 Enterprise Software Package.
- For X11 Release 19, prerequisites are SW0221B ACD/Message Processing, SW0223A Enhanced ACD Routing, and SW0225B Enhanced Call Center Routing.
- For Option 11 systems, the X11 Release 20 prerequisite is NTBK83CA Enterprise Business package.
- For Option 11 systems, the X11 Release 21 prerequisite is NTBK83CG Enterprise Business Package
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	NT1R56AE	CCR 3B and Link 5 Documentation Package			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7416A

Description	System Compatibility	Product compatibility	W/S
Customer Controlled Routing Release 3C with 240 Active Associations Software Upgrade Package	11C X11 R22,23,24; 11E X11 R20,21; 21E X11 R19,20,21; 51 X11 R19,20,21; 51C X11 R20,21,22,23,24; 61 X11 R19,20,21; 61C X11 R20,21,22,23,24; 71 X11 R19,20,21; 81 X11 R19,20,21,22,23,24; 81C X11 R21,22,23,24; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S3

Notes:

- To be used when upgrading any CCR Release 2 or Release 3A system to CCR Release 3B.
- Meridian MAX Release 4 or later is a prerequisite if Meridian MAX is to be used to report on Customer Controlled Routing activity.
- For operation of the CCR Hold in Queue for IVR feature, the prerequisite is SW0227A Hold in Queue for IVR.
- For Option 11 systems, the X11 Release 22 and higher, prerequisite is NTSF8022 Enterprise Software Package.
- For X11 Releases 20 and higher, prerequisites are SW0221C ACD/Message Processing, SW0223A Enhanced ACD Routing, and SW0225B Enhanced Call Center Routing.
- For X11 Release 19, prerequisites are SW0221B ACD/Message Processing, SW0223A Enhanced ACD Routing, and SW0225B Enhanced Call Center Routing.
- For Option 11 systems, the X11 Release 21 prerequisite is NTBK83CG Enterprise Business Package.
- For Option 11 systems, the X11 Release 20 prerequisite is NTBK83CA Enterprise Business package.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0352271	150 MByte Data Cassette Tape	1	NT2R51AF	Meridian Link/CCR Co-Resident Application Tape Assembly
1	A0605411	600MB Data Cassette Tape	1	NTND46AF	UNIX R3V7 1
1	NT1R56AE	CCR 3B and Link 5 Documentation Package			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7417A

Description	System Compatibility	Product compatibility	W/S
Meridian Link Release 5C Software Upgrade	11C X11 R22,23,24; 11E X11 R20,21; 21E X11 R19,20,21; 51 X11 R19,20,21; 51C X11 R20,21,22,23,24; 61 X11 R19,20,21; 61C X11 R20,21,22,23,24; 71 X11 R19,20,21; 81 X11 R19,20,21,22,23,24; 81C X11 R20,21,22,23,24; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21		S2

Notes:

- Requires the SY1222, SY1223, SY1220, SY1221, SY7411A, SY7411D, SY1200A, or SY1200D hardware.
- For Options 21-81 systems, prerequisites are Release 19 or later system software, SW0221B or SW0221C ACD/Message Processing, SW0251A Meridian Link Module software options, SW0223A Enhanced ACD Routing, and SW0225B Enhanced Call Center Routing.
- For use in conjunction with products provided by Nortel strategic alliance partners or otherwise licensed end users or applications providers.
- For Option 11 systems, prerequisites are X11 Release 20 or later and the NTBK83CA Enterprise Business package.
- For Options 21-81, please refer to the ACD/Message Processing and Meridian Link Associated Station (AST) feature section in the System Software Section for detailed requirements.
- To operate Host Enhanced Voice Processing, Options 11-81 systems must be equipped with a Meridian Mail system, Meridian Mail Release 8 or later software, and the SW7030 ACCESS Enable Option.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	A0352271	150 MByte Data Cassette Tape	1	NT2R51AF	Meridian Link/CCR Co-Resident Application Tape Assembly
1	A0605411	600MB Data Cassette Tape	1	NTND46AF	UNIX R3V7 1
1	NT1R56AE	CCR 3B and Link 5 Documentation Package			

Status
➤ S

SW7426

Description	System Compatibility	Product compatibility	W/S
Network Administration Center Release 2.5 Base Software Package			S3

Notes:

- Requires SY7421A, SY7421D, U7600A or U7600D hardware platform.
- Includes Custom Calculator, Configuration Control, CCR/EAR MIS.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0605411	600MB Data Cassette Tape	1	NT1R31AA	NAC Release 2 Documentation Package (English)
1	NT1R27AB	NAC Release 2 5 Application Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R28AB	NAC Release 2 5 UNIX O/S Tape	1	P0886656	NAC 2 5 User Guide Supplement

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7427

Description	System Compatibility	Product compatibility	W/S
Network Administration Center Release 2.5 Base Software Upgrade			S3

Notes:

- Requires SY7421A, SY7421D, U7600A or U7600D hardware platform.
- Includes Custom Calculator, Configuration Control, CCR/EAR MIS.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0605411	600MB Data Cassette Tape	1	NT1R31AA	NAC Release 2 Documentation Package (English)
1	NT1R27AB	NAC Release 2 5 Application Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R28AB	NAC Release 2 5 UNIX O/S Tape	1	P0886656	NAC 2 5 User Guide Supplement

Status
➤ S

SW7464

Description	System Compatibility	Product compatibility	W/S
Meridian Link & CCR Co-Resident AST/ Agent Software Level	11C X11 R22,23,24; 11E X11 R20,21; 21E X11 R19,20,21; 51 X11 R19,20,21; 51C X11 R20,21,22,23,24; 61 X11 R19,20,21; 61C X11 R20,21,22,23,24; 71 X11 R19,20,21; 81 X11 R19,20,21,22,23,24; 81C X11 R21,22,23,24; NT X11 R19,20,21; RT X11 R19,20,21; STE X11 R19,20,21; XT X11 R19,20,21	Meridian Link	S3

Notes:

- To be used when ordering SW7460 and SW7461 Meridian Link & CCR Co-Resident Software packages only.
- Agent/AST features prices are in increments of 20 from 1 to 200 agents/ASTs and increments of 100 above 200 agents/ASTs.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
1	SW0223A	Enhanced ACD Routing	1	SW0227A	Hold in Queue for IVR
1	SW0225B	Enhanced Call Center Routing	1	SW0251A	Meridian Link Module Software

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7505B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX Networking for Release 6		Meridian MAX-IPE; Meridian MAX-SEE; Meridian MAX-SNN	W1/ S3

Notes:

- This package is required if Enhanced ACD Overflow (SW0207A or SW0222A) or Call Center Networking (SW0209A or SW0226A) is equipped on the Meridian 1 PBX.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW7511B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE or MAX-IPEE 20-Agent Software Increment for Releases 6, 7 and 8		Meridian MAX-IPE; Meridian MAX-IPEE	S1

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- Because all Meridian MAX 7 and MAX 8 base software includes support for 20 agents and the maximum capacity is 200 agents, a maximum number of nine (9) SW7511B can be ordered for one Meridian MAX 7 system. However, MAX 5 and 6 Base Software does not include agents, thus a maximum of ten (10) SW7511B can be ordered for a MAX 5 or 6 system.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW7513A

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Premium Features for Release 6		Meridian MAX-IPE	S3

Notes:

- Includes Configuration Control, Custom Calculator, and CCR Support. (CCR Support is not supported on the Option 11 but is supported on the Option 11E and 11C.)
- The Meridian 1 Serial number must be provided when ordering this code.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7514B

Description	System Compatibility	Product compatibility	W/S
Meridian MAX-IPE Release 4 to MAX-IPE Release 6 Base Software Upgrade	11 X11 R16,18,19,20,21,22,23; 11C X11 R16,18,19,20,21,22,23; 11E X11 R16,18,19,20,21,22,23; 21 X11 R17,18,19,20,21,22,23; 21A X11 R17,18,19,20,21,22,23; 21E X11 R17,18,19,20,21,22,23; 51 X11 R17,18,19,20,21,22,23; 51C X11 R17,18,19,20,21,22,23; 61 X11 R17,18,19,20,21,22,23; 61C X11 R17,18,19,20,21,22,23; 71 X11 R17,18,19,20,21,22,23; 81 X11 R17,18,19,20,21,22,23; 81C X11 R17,18,19,20,21,22,23	Meridian MAX; Meridian MAX-IPE; Meridian MAX-IPEE	W1

Notes:

- Requires X11 Release 17 or later for Option 21-81. Requires X11 Release 16 or later for Option 11.
- For X11 Release 17, prerequisites are SW0201B Basic ACD Features, SW0202C Advanced ACD Features, SW0203B ACD Reports Features, SW0204A ACD Load Management, SW0205A ACD Link (MAX) and SW0207A Enhanced ACD Overflow.
- Software Service Transaction Fee SERV0017 must be ordered with this package.
- Option 11: the Enhanced Business Software NTAK57BD (Release 16) or NTAK57BE (Release 18) is required on the Option 11 system to fully use the features for a non-networked call center.
- For X11 Release 18/19/20/21/22/23, prerequisites are SW0221A ACD/Message Processing (Release 18 only), SW0221B ACD/Message Processing (Release 19 only), SW0221C ACD/Message Processing (Release 20 and above), SW0224A Enhanced Call Center Management, and SW0222A Enhanced ACD Overflow.
- In order for Customer Controlled Routing support to function, SW0223A Enhanced ACD Routing (Release 18/19/20/21/22/23) or SW0210A (Release 17) is a prerequisite. Customer Controlled Routing hardware and application software are required for full CCR functionality. CCR is currently not supported on Option 11E and 11C.
- To upgrade an existing Meridian MAX-IPE system running on Release 4.62 to Release 6.
- Only MTE Release 5.31, or later, is supported by this release of MAX software.
- The Meridian 1 Serial number must be provided when ordering this code.

Qty	Order code	Description	Qty	Order code	Description
3	A0605411	600MB Data Cassette Tape	1	NTLH13AA	ACD Reference Guides
1	NT1R64AA	Meridian MAX Release 6 NTP Package	1	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4 6 & 5 Systems (to Release 6)
1	NT1R79AC	Meridian MAX Release 6 Application Tape	1	P0889198	ACD Reference Guide, Release 24 and Earlier
1	NT1R81AC	Meridian MAX Release 6 UNIX O/S Tape			

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SW7525B

Description	System Compatibility	Product compatibility	W/S
NAC (Release 2) Connectivity Enabler for Meridian MAX Releases 6 and 7	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX	S3

Notes:

- Requires Meridian MAX Release 6 software for SNN and IPE Systems.
- Requires Meridian MAX Release 4.30 for Meridian MAX Release 4 systems.
- Requires NAC Release 2 hardware and software packages. For detailed information on system configuration, consult the NAC Release 2 Ordering Procedures for New Systems, Expansions, Migrations and Upgrades.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SW7525C

Description	System Compatibility	Product compatibility	W/S
NAC Connectivity for Meridian MAX Release 8	11; 11C; 11E; 21; 21A; 21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian MAX-IPE; Meridian MAX-IPEE; Meridian MAX-SNN; Meridian MAX-SNNE	S3

Notes:

- This option can only be applied to Meridian MAX-IPE, Meridian MAX-IPEE, Meridian MAX-SNN, or Meridian MAX-SNNE Release 8 Enhanced or Virtual Software.
- This package requires permanent assignment of one asynchronous I/O port for connection to NAC.
- The Meridian 1 Serial number must be provided when ordering this code.

Status
➤ S

SY1009A

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Option 51C System Package AC	51C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE module.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
1	NT5D21AA	Core/Network Module AC
1	NT5D61AB	IODU/C Pack
1	NT5D90BA	Software Installation Kit (Non-Autovon)
1	NT5D9602	Keycode Security Device Kit
1	NT7D00AA	Top Cap AC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
1	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
1	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D77BD	Female Telco Cable (6 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
4	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25AA	Pedestal Assembly AC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY1009D

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Option 51C System Package DC	51C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE module.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
1	NT5D21DA	Core/Network Module DC	
1	NT5D61AB	IODU/C Pack	
1	NT5D90BA	Software Installation Kit (Non-Autovon)	
1	NT5D9602	Keycode Security Device Kit	
1	NT6D40BA	Peripheral Equipment Power Supply DC	
1	NT6D41AD	Common Equipment Power Supply DC	
1	NT7D00BA	Top Cap DC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D77BD	Female Telco Cable (6 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
4	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

Status
➤ S

SY1016A

Description	System Compatibility	Product compatibility	W/S
Option 61C System Package AC	61C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT8D21AA Ringing Generator AC must be added for each IPE Module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator AC must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE module.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 61C minimum memory requirements for the current software release.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21AA	Core/Network Module AC
2	NT5D61AB	IODU/C Pack
2	NT5D84AA	Keycode Security Device Kit
2	NT5D90BA	Software Installation Kit (Non-Autovon)
1	NT7D00AA	Top Cap AC
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
1	NT8D06AB	Peripheral Equipment Power Supply AC
2	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
2	NT8D29AB	Common Equipment Power Supply AC
1	NT8D37BA	Intelligent Peripheral Equipment Module AC
1	NT8D41BA	Quad SDI Paddle Board
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)
2	NT8D80BZ	CPU Interface Cable (5 Ft)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25AA	Pedestal Assembly AC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY1016D

Description	System Compatibility	Product compatibility	W/S
Option 61C System Package DC	61C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT6D42CC Ringing Generator DC must be added for each IPE Module housing analog type peripheral cards. Otherwise, one NT7D05AA Filler Panel-Ringing Generator DC must be equipped.
- This package includes sixteen Tip and Ring cables within the IPE module.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 61C minimum memory requirements for the current software release.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
2	NT5D21DA	Core/Network Module DC	
2	NT5D61AB	IODU/C Pack	
2	NT5D84AA	Keycode Security Device Kit	
2	NT5D90BA	Software Installation Kit (Non-Autovon)	
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
1	NT7D00BA	Top Cap DC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
2	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

Status
➤ S

SY1025A

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Option 81C System Package AC	81C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- The Junctor requires four QPF36 Terminating plugs for each unequipped network group; these must be ordered separately.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 81C minimum memory requirements for the current software release.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21AA	Core/Network Module AC
4	NT5D30AA	Dual Intergroup Switch
2	NT5D61AB	IODU/C Pack
2	NT5D84AA	Keycode Security Device Kit
2	NT5D90BA	Software Installation Kit (Non-Autovon)
2	NT7D00AA	Top Cap AC
2	NT7D06AA	Filler Panel
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
1	NT8D06AB	Peripheral Equipment Power Supply AC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
4	NT8D17FA	Conference/TDS Card	
2	NT8D22AC	System Monitor	
4	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D36AA	Inter Group Module	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
4	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)
2	NTRD25AA	Pedestal Assembly AC
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
1	QPC417A	Junctor Board
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender
2	QPC471H	Clock Controller

Status
➤ S

SY1025D

Description	System Compatibility	Product compatibility	W/S
Meridian 1 Option 81C System Package DC	81C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- The Junctor requires four QPF36 Terminating plugs for each unequipped network group; these must be ordered separately.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 81C minimum memory requirements for the current software release.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21DA	Core/Network Module DC
4	NT5D30AA	Dual Intergroup Switch
2	NT5D61AB	IODU/C Pack
2	NT5D84AA	Keycode Security Device Kit
2	NT5D90BA	Software Installation Kit (Non-Autovon)
1	NT6D40BA	Peripheral Equipment Power Supply DC
4	NT6D41AD	Common Equipment Power Supply DC
2	NT7D00BA	Top Cap DC
2	NT7D06AA	Filler Panel
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
4	NT8D17FA	Conference/TDS Card
2	NT8D22AC	System Monitor
2	NT8D35EA	Network Module DC
1	NT8D36AA	Inter Group Module
1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	NT8D41BA	Quad SDI Paddle Board
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
4	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AD	Network to Controller Cable (6 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC417A	Junctor Board	
4	QPC43R	Peripheral Signaling	
4	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY1222

Description	System Compatibility	Product compatibility	W/S
Meridian Link & CCR-IPEE Module (Option 11)	11C; 11E	Meridian CCR; Meridian Link	W1

Notes:

- Each system must have either a DEC 420 terminal or a HP700/32 equipped as the system console terminal. An appropriate system console terminal cable must also be equipped (NT1R03DB, C, F, P, V straight through M-M or NT1R03EB, C, F, P, V straight through M-F).
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the Application Module Link (AML) connection.
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the Serial Data Interface (SDI) connection.
- To use the Host Enhanced Voice Processing feature of Meridian Link Release 4B, an appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the connection to the Meridian Mail system.
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the Meridian Link host connection.
- The A0669467 IPEE module occupies 3 consecutive card slots in the IPE Shelf of a Meridian 1, Option 11 main or expansion cabinet.
- For detailed information on system configuration, please consult the Meridian Link and CCR Co-Resident Ordering Procedures Bulletin.
- An appropriate length and gender cable (NT1R03DB, C, F, P, V straight through M-M or NT1R03EB, C, F, P, V straight through M-F) is required for each supervisor terminal, personal computer, and printer connected to a Meridian Link & CCR-IPEE Module.

Qty	Order code	Description	Qty	Order code	Description
1	A0669467	Meridian IPEE Application Module for Option 11	2	NT1R03CA	Extension Cable (2 Ft)
1	NT1R03AA	Shielded 4-Port Octopus Cable with Ethernet	1	NT1R03HF	Modem Cable
1	NT1R03BA	Shielded 4-Port Octopus Cable without Ethernet	1	NTRH9016	External Modem 33 6

Status
➤ S

SY1223

Description	System Compatibility	Product compatibility	W/S
Meridian Link & CCR-IPEE Module (Option 21-81C)	21E; 51; 51C; 61; 61C; 71; 81; 81C	Meridian CCR; Meridian Link	W1

Notes:

- Each system must have either a DEC 420 terminal or a HP700/32 equipped as the system console terminal. An appropriate system console terminal cable must also be equipped (NT1R03DB, C, F, P, V straight through M-M or NT1R03EB, C, F, P, V straight through M-F).
- An appropriate length and gender cable (NT1R03DB, C, F, P, V straight through M-M or NT1R03EB, C, F, P, V straight through M-F) is required for each supervisor terminal, personal computer, and printer connected to a Meridian Link & CCR-IPEE Module.
- For detailed information on system configuration, please consult the Meridian Link and CCR Co-Resident Ordering Procedures Bulletin.
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the Application Module Link (AML) connection.
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the Serial Data Interface (SDI) connection.
- To use the Host Enhanced Voice Processing feature of Meridian Link Release 4B, an appropriate length (NT1R03DB, C, F, P, V straight through M-M) cable is required for the connection to the Meridian Mail system.
- An appropriate length (NT1R03DB, C, F, P, V straight through M-M Male) cable is required for the Meridian Link host connection.
- The A0669468 IPEE module occupies 4 consecutive card slots in an IPE Shelf of a Meridian 1, Option 21-81C system.

Qty	Order code	Description	Qty	Order code	Description
1	A0669468	Meridian IPEE Application Module for Options 21-81C	1	NT1R03HF	Modem Cable
1	NT1R03AA	Shielded 4-Port Octopus Cable with Ethernet	1	NTRH9016	External Modem 33 6
1	NT1R03BA	Shielded 4-Port Octopus Cable without Ethernet			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7020A

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/200 Hour Package AC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
1	NT6P01BA	Meridian Mail EC Module AC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT7D06AA	Filler Panel	
1	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
1	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
2	P0803253	Designation Strip	
1	QPC414C	Network Card	

Status
➤ S

SY7020D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/200 Hour Package DC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D41AD	Common Equipment Power Supply DC	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
1	NT6P01AA	Meridian Mail EC Module DC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT6P42AA	Utility Card without Modem	
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT7D06AA	Filler Panel	
1	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
1	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
2	P0803253	Designation Strip	
1	QPC414C	Network Card	

Status
➤ S

SY7021A

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/200/400 Hour Package AC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
1	NT6P01BA	Meridian Mail EC Module AC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
2	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
2	NT6R15AA	Enhanced Processor for Meridian Mail EC	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
2	P0803253	Designation Strip	
1	QPC414C	Network Card	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7021D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/200/400 Hour Package DC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (SW7000X).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
2	NT6D41AD	Common Equipment Power Supply DC	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
1	NT6P01AA	Meridian Mail EC Module DC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
2	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
2	NT6R15AA	Enhanced Processor for Meridian Mail EC	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
2	P0803253	Designation Strip	
1	QPC414C	Network Card	

Status
➤ S

SY7022A

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/ 200/400 Hour Package AC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- This package is only intended for 3 node Modular Option and Option X cabinet platform migration and supports 28-48 port configurations.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT6P01BA	Meridian Mail EC Module AC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
2	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
3	NT6R15AA	Enhanced Processor for Meridian Mail EC	
2	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
3	P0803253	Designation Strip	
1	QPC414C	Network Card	

Status
➤ S

SY7022D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/ 200/400 Hour Package, DC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- This package is only intended for 3 node Modular Option and X cabinet platform migration and supports 28-48 port configurations.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description
1	A0100025	Alarm/Modem Cable (25 Ft)
1	A0376171	Powell DEC Cable
1	A0378999	Static Wrist Strap (10 Ft)
1	A0383526	VT520 Video Terminal
2	A0630697	Magnus 2 5GB Data Cartridge

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
2	NT6D41AD	Common Equipment Power Supply DC	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
1	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	
1	NT6P01AA	Meridian Mail EC Module DC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
2	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
3	NT6R15AA	Enhanced Processor for Meridian Mail EC	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
3	P0803253	Designation Strip	
1	QPC414C	Network Card	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7023A

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/300/600 Hour Package AC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
2	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	
2	NT6P01BA	Meridian Mail EC Module AC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
3	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
2	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
4	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT7D06AA	Filler Panel	
3	NT8D29AB	Common Equipment Power Supply AC	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
4	P0803253	Designation Strip	
2	QPC414C	Network Card	

Status
➤ S

SY7023D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/300/600 Hour Package DC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
3	NT6D41AD	Common Equipment Power Supply DC	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
2	NT6P0109	5 Port RS232 Cable	
1	NT6P0110	4 Port RS232 Cable	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT6P0112	Alarm Cable	
2	NT6P0124	External Voice Bus Cable (2 5 Ft)	
2	NT6P01AA	Meridian Mail EC Module DC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
3	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
2	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
4	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NT7D06AA	Filler Panel	
2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
2	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
4	P0803253	Designation Strip	
2	QPC414C	Network Card	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7024A

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/400/800 Hour Package AC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
2	NT6P0109	5 Port RS232 Cable	
2	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	
3	NT6P0124	External Voice Bus Cable (2 5 Ft)	
2	NT6P01BA	Meridian Mail EC Module AC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
4	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
2	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
5	NT6R15AA	Enhanced Processor for Meridian Mail EC	
4	NT8D29AB	Common Equipment Power Supply AC	
3	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
3	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
4	P0803253	Designation Strip	
2	QPC414C	Network Card	

Status
➤ S

SY7024D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/400/800 Hour Package DC		Meridian Mail Modular EC R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- If required, pedestal/top cap hardware must be ordered separately.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description	
1	A0100025	Alarm/Modem Cable (25 Ft)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	
	Each Package Includes:		
	1	P0904488	Modular Option EC Site and Installation & Planning Guide - MM13
	1	P0904489	Modular Option EC Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
4	NT6D41AD	Common Equipment Power Supply DC	
1	NT6D4410	DVS Bus Cable	
1	NT6P0106	External Voice Bus Terminator	
2	NT6P0109	5 Port RS232 Cable	
2	NT6P0110	4 Port RS232 Cable	
1	NT6P0112	Alarm Cable	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
3	NT6P0124	External Voice Bus Cable (2 5 Ft)	
2	NT6P01AA	Meridian Mail EC Module DC	
1	NT6P05BA	Tandberg EC Tape Drive Unit, EC	
4	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
2	NT6P42AA	Utility Card without Modem	
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power	
5	NT6R15AA	Enhanced Processor for Meridian Mail EC	
3	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)	
3	NT8D86BD	Network to I/O Cable (6 Ft)	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	P0695822	AML Link Cable	
4	P0803253	Designation Strip	
2	QPC414C	Network Card	

Status
➤ S

SY7075D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP 4-12 Port 11/24/36/54/100/200 Hours Package DC	ATT; DMS-10; DMS-100; NEC; ROLM	Meridian Mail Modular GP	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- If connecting with an ATT, NEC or Rolm system, SW7061 SMDI/Connections software and the appropriate Connections hardware are required.
- Modular GP systems are only equipped as DC powered systems, an appropriate AC to DC rectifier such as the MFA150 is required and must be ordered separately for use in AC powered applications.

Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)
1	A0376171	Powell DEC Cable
1	A0378999	Static Wrist Strap (10 Ft)
1	A0383526	VT520 Video Terminal
2	A0630697	Magnus 2 5GB Data Cartridge
1	A0633585	Tandberg Tape Drive Cleaning Kit
1	A0728841	Citizen Printer
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual
	Each Package Includes:	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT4R03AB	RS232C Service Module	
1	NT4R20AA	RSM Fanout Cable (25 Ft)	
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	
1	NT6D4406	RSM Cable	
1	NT6D4407	GSP Cable	
1	NT6D4417	SCSI/Backplane Cable	
1	NT6D4419	RS232-Y Cable	
1	NT6D44BA	Meridian Mail Module DC	
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	
1	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT7D00BA	Top Cap DC	
1	NT7D06AA	Filler Panel	
1	NT8D22AC	System Monitor	
1	NT8D31AE	Tape Drive Blank Faceplate	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
2	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
2	NT9D18AA	Module Side Cover	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	NTRD25BA	Pedestal Assembly DC	
6	P0594340	Clamp Cable	
2	P0803252	Designation Strip	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7076D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP 16-24 Port 26/54/84/114/200/400 Hours Package DC	ATT; DMS-10; DMS-100; NEC; ROLM	Meridian Mail Modular Option GP	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- If connecting with an ATT, NEC or Rolm system, SW7061 SMDI/Connections software and the appropriate Connections hardware are required.
- Modular GP systems are only equipped as DC powered systems, an appropriate AC to DC rectifier such as the MFA150 is required and must be ordered separately for use in AC powered applications.

Qty	Order code	Description	
1	A0351509	Gender Changer (Female/Female)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT4R03AB	RS232C Service Module	
1	NT4R08AA	HABC (High Availability Bus Controller)	
1	NT4R10AA	HABC Terminator	
1	NT4R11AA	ESBC Terminator	
1	NT4R20AA	RSM Fanout Cable (25 Ft)	
2	NT6D41BA	Meridian Mail Modular GP Power Supply DC	
1	NT6D4406	RSM Cable	
2	NT6D4407	GSP Cable	
2	NT6D4411	DVS Bus Cable (57 Inches)	
2	NT6D4417	SCSI/Backplane Cable	
2	NT6D4419	RS232-Y Cable	
2	NT6D44BA	Meridian Mail Module DC	
1	NT6D48FA	4 5GB Modular Hard Disk Drive	
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	
2	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT7D00BA	Top Cap DC	
2	NT7D06AA	Filler Panel	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D22AC	System Monitor	
1	NT8D31AE	Tape Drive Blank Faceplate	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
2	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
4	NT9D18AA	Module Side Cover	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	NTRD25BA	Pedestal Assembly DC	
12	P0594340	Clamp Cable	
4	P0803252	Designation Strip	

Status
➤ S

SY7077D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP 28-32 Port 30/60/90/120/200/400 Hours Package DC	ATT; DMS-10; DMS-100; NEC; ROLM	Meridian Mail Modular GP	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- If connecting with an ATT, NEC or Rolm system, SW7061 SMDI/Connections software and the appropriate Connections hardware are required.
- Modular GP systems are only equipped as DC powered systems, an appropriate AC to DC rectifier such as the MFA150 is required and must be ordered separately for use in AC powered applications.

Qty	Order code	Description
1	A0351509	Gender Changer (Female/Female)
1	A0376171	Powell DEC Cable
1	A0378999	Static Wrist Strap (10 Ft)
1	A0383526	VT520 Video Terminal
2	A0630697	Magnus 2 5GB Data Cartridge
1	A0633585	Tandberg Tape Drive Cleaning Kit
1	A0728841	Citizen Printer
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual
	Each Package Includes:	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT4R03AB	RS232C Service Module	
1	NT4R08AA	HABC (High Availability Bus Controller)	
1	NT4R10AA	HABC Terminator	
1	NT4R11AA	ESBC Terminator	
1	NT4R20AA	RSM Fanout Cable (25 Ft)	
3	NT6D41BA	Meridian Mail Modular GP Power Supply DC	
1	NT6D4406	RSM Cable	
3	NT6D4407	GSP Cable	
2	NT6D4411	DVS Bus Cable (57 Inches)	
3	NT6D4417	SCSI/Backplane Cable	
3	NT6D4419	RS232-Y Cable	
3	NT6D44BA	Meridian Mail Module DC	
2	NT6D48FA	4 5GB Modular Hard Disk Drive	
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	
3	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT7D00BA	Top Cap DC	
3	NT7D06AA	Filler Panel	
1	NT8D22AC	System Monitor	
3	NT8D31AE	Tape Drive Blank Faceplate	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
2	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
6	NT9D18AA	Module Side Cover	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	NTRD25BA	Pedestal Assembly DC	
18	P0594340	Clamp Cable	
6	P0803252	Designation Strip	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7078D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP 36-48 Port 45/90/120/180/300/600 Hours Package DC	ATT; DMS-10; DMS-100; NEC; ROLM	Meridian Mail Modular GP	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- If connecting with an ATT, NEC or Rolm system, SW7061 SMDI/Connections software and the appropriate Connections hardware are required.
- Modular GP systems are only equipped as DC powered systems, an appropriate AC to DC rectifier such as the MFA150 is required and must be ordered separately for use in AC powered applications.

Qty	Order code	Description	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	
1	NT4R03AB	RS232C Service Module	
1	NT4R08AA	HABC (High Availability Bus Controller)	
1	NT4R10AA	HABC Terminator	
1	NT4R11AA	ESBC Terminator	
1	NT4R20AA	RSM Fanout Cable (25 Ft)	
4	NT6D41BA	Meridian Mail Modular GP Power Supply DC	
1	NT6D4406	RSM Cable	
2	NT6D4407	GSP Cable	
2	NT6D4411	DVS Bus Cable (57 Inches)	
4	NT6D4417	SCSI/Backplane Cable	
4	NT6D4419	RS232-Y Cable	
4	NT6D44BA	Meridian Mail Module DC	
3	NT6D48FA	4 5GB Modular Hard Disk Drive	
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	
4	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT7D00BA	Top Cap DC	
4	NT7D06AA	Filler Panel	
1	NT8D22AC	System Monitor	
4	NT8D31AE	Tape Drive Blank Faceplate	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
2	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
2	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	NTRD25BA	Pedestal Assembly DC	
24	P0594340	Clamp Cable	
8	P0803252	Designation Strip	

Status
➤ S

SY7079D

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail Modular GP 52-64 Port 60/120/180/240/400/800 Hours Package DC	ATT; DMS-10; DMS-100; NEC; ROLM	Meridian Mail Modular GP	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- All new Meridian Mail systems require Meridian Mail Base Software (NTZR57CA).
- If connecting with an ATT, NEC or Rolm system, SW7061 SMDI/Connections software and the appropriate Connections hardware are required.
- Modular GP systems are only equipped as DC powered systems, an appropriate AC to DC rectifier such as the MFA150 is required and must be ordered separately for use in AC powered applications.

Qty	Order code	Description	
1	A0351509	Gender Changer (Female/Female)	
1	A0376171	Powell DEC Cable	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
2	A0630697	Magnus 2 5GB Data Cartridge	
1	A0633585	Tandberg Tape Drive Cleaning Kit	
1	A0728841	Citizen Printer	
1	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	
	Each Package Includes:		
	1	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13
	1	P0904487	Modular Option GP Installation and Maintenance Guide - MM13
1	NT3M50AD	Black Box ABC Switch	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT4R03AB	RS232C Service Module	
1	NT4R08AA	HABC (High Availability Bus Controller)	
1	NT4R10AA	HABC Terminator	
1	NT4R11AA	ESBC Terminator	
1	NT4R20AA	RSM Fanout Cable (25 Ft)	
5	NT6D41BA	Meridian Mail Modular GP Power Supply DC	
1	NT6D4406	RSM Cable	
2	NT6D4407	GSP Cable	
2	NT6D4411	DVS Bus Cable (57 Inches)	
1	NT6D4412	DVS Bus Cable (Internal) (132 Inches)	
5	NT6D4417	SCSI/Backplane Cable	
5	NT6D4419	RS232-Y Cable	
5	NT6D44BA	Meridian Mail Module DC	
4	NT6D48FA	4 5GB Modular Hard Disk Drive	
1	NT6D48GA	Tandberg Tape and 4 5GB Disk Drive Unit, Modular Option	
5	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	
1	NT7D00BA	Top Cap DC	
5	NT7D06AA	Filler Panel	
2	NT8D22AC	System Monitor	
5	NT8D31AE	Tape Drive Blank Faceplate	
2	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
3	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
6	NT9D18AA	Module Side Cover	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
1	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
2	NTRD25BA	Pedestal Assembly DC	
30	P0594340	Clamp Cable	
10	P0803252	Designation Strip	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7210

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC11 8-24 Port, 11/24/36/54/100/200 Hour Package		Meridian Mail EC11 R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- A minimum of 8 ports must be ordered.
- All new Meridian Mail EC11 systems require Meridian Mail Base Software (NTZC57BA).
- AML link connectivity is achieved using a port on the NTAK02 (DCH/SDI) card on the Option 11.
- This system is equipped with one Mgate card. Each Mgate supports 16 voice ports. Order additional cards as required.
- The SDI/DCH 4 port cable (NTAK19FB) is used to provide connectivity for the AML link.
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- A tape drive is not included, if one is required to install or backup the EC11, both the external Tandberg tape drive or the external Viper tape drive are supported.

Qty	Order code	Description	
2	A0351509	Gender Changer (Female/Female)	
1	A0376171	Powell DEC Cable	
1	A0376979	SCSI Terminator	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
1	A0728841	Citizen Printer	
1	NT3M50AD	Black Box ABC Switch	
1	NT6P0110	4 Port RS232 Cable	
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
1	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NTAK98AA	Power Supply Cable	
1	NTDK32AA	EC11 Backplane and Cabinet Assembly	
1	NTDK3302	NLI Cable 10 Ft	
1	NTDK35AA	AC/DC Power Supply	
1	NTDK36AA	Bus Terminator	
1	NTDK59AA	Alarm/Modem Cable Assembly-Initial Caps only	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
3	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
1	NTRB18AA	MGate Card	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7211

Description	System Compatibility	Product compatibility	W/S
Enhanced Meridian Mail EC11 24-48 port, 26/54/84/114/200/400 Hour Package		Meridian Mail EC11 R12	W1

Notes:

- This package contains the new Enhanced Meridian Mail Processor.
- A minimum of 8 ports must be ordered.
- All new Meridian Mail EC11 systems require Meridian Mail Base Software (NTZC57BA).
- AML link connectivity is achieved using a port on the NTAK02 (DCH/SDI) card on the Option 11.
- The SDI/DCH 4 port cable (NTAK19FB) is used to provide connectivity for the AML link.
- This system is equipped with two Mgate cards. Each Mgate supports 16 voice ports. Order additional cards as required.
- Zero (0) ports are included in this package. Full and Basic Port Voice Processing Packages must be ordered separately to support the configuration.
- A tape drive is not included, if one is required to install or backup the EC11, both the external Tandberg tape drive or the external Viper tape drive are supported.

Qty	Order code	Description	
2	A0351509	Gender Changer (Female/Female)	
1	A0376171	Powell DEC Cable	
1	A0376979	SCSI Terminator	
1	A0378999	Static Wrist Strap (10 Ft)	
1	A0383526	VT520 Video Terminal	
1	A0728841	Citizen Printer	
1	NT3M50AD	Black Box ABC Switch	
1	NT6P0110	4 Port RS232 Cable	
2	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive	
1	NT6P42AA	Utility Card without Modem	
2	NT6R15AA	Enhanced Processor for Meridian Mail EC	
1	NTAK98AA	Power Supply Cable	
1	NTDK32AA	EC11 Backplane and Cabinet Assembly	
1	NTDK3302	NLI Cable 10 Ft	
1	NTDK35AA	AC/DC Power Supply	
1	NTDK36AA	Bus Terminator	
1	NTDK59AA	Alarm/Modem Cable Assembly-Initial Caps only	
1	NTDK66AB	Meridian Mail Modem Package	
	Each Package Includes:		
	1	A0674453	33 6 KBPS External Data/Fax Modem
	1	P0875141	Meridian Mail Modem Setup Document
1	NTND91AA	RS232 Straight Cable (10 Ft)	
3	NTND91AB	RS232 Straight Cable (25 Ft)	
1	NTND93AA	Null Modem Adapter	
2	NTRB18AA	MGate Card	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7412

Description	System Compatibility	Product compatibility	W/S
Customer Controlled Routing Release 3 High Capacity Hardware Package	11E; 21; 21E; 51; 61; 71; 81; NT; RT; ST; STE; XT	Meridian CCR	W1

Notes:

- The CCR Release 3 High Capacity Hardware Package is strongly recommended for CCR systems configured with an Option 81 PBX. For detailed information on configuration of CCR system, please refer to the Meridian Link/Customer Controlled Routing/Engineering Guide. NTP Section # 553-3202-151; Order Code P0747014.

Qty	Order code	Description	Qty	Order code	Description
1	A0688017	MVME167-33 Processor Card (M68040, 33Mhz, 16MB)			

Status
➤ S

SY7421A

Description	System Compatibility	Product compatibility	W/S
Meridian NAC, Release 2.5 Base System Hardware Platform, AC		NAC R2	W1

Notes:

- Must be housed in the NT7D18AA Application Equipment Module (AC).
- There must be at least one supervisor terminal and one printer equipped per system.
- Requires SW7426 NAC Release 2.5 Base Software Package.
- For detailed information on system configuration, please consult the NAC Release 2 Ordering Procedures for New Systems, Expansions, Migrations and Upgrades.
- Includes one VME332XT 8 Channel Asynchronous I/O Board, UDS 2440 Modem, a 10 Ft. modem cable, and a 45 Ft. System Console cable.
- There must be at least one system console equipped per system.
- There must be a Network link from NAC Release 2.5 to each Meridian MAX (AM) Release 4.3 or later node. Meridian MAX-IPE/IPEE Release 6, or later, can also be connected to NAC Release 2.5.
- ACD MAX Release 1 through Release 4 and Meridian MAX Release 3 are not supported with NAC Release 2.5.
- Optional Remote Supervisor Login Links can be configured between NAC Release 2.5 and each MAX node.
- Order NT6D98AA 8 Channel Asynchronous Kit, if additional I/O ports are required for Network links, Remote Login Supervisor Links, Supervisor terminals and printers. Up to 40 I/O ports can be configured.
- Order AS1081A or AS1081D Pedestal and Top Cap Assembly as required.
- Order NT9D18AA Module Side Cover as required.
- The modem provided in this package is for remote diagnostics. Order additional modems for Network links, Remote Supervisor login and dial-up supervisors.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT7D61EV	SDI Cable (45 Ft)
1	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	1	NT7D62CA	1 2 GByte Hard Disk/600 MByte Tape Drive Assembly
1	NT7D19SA	Meridian MAX Release 5 Applications Module	1	NT7D64AA	Application Module Power Supply AC
1	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	3	NT8D96BE	VME Multi-Port Cable
1	NT7D61EF	SDI Cable (10 Ft)	1	NTRH9016	External Modem 33 6

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

SY7421D

Description	System Compatibility	Product compatibility	W/S
Meridian NAC Release 2.5 Base System Hardware Platform, DC		NAC R2	W1

Notes:

- Must be housed in the NT7D18AB Application Equipment Module (DC).
- There must be at least one supervisor terminal and one printer equipped per system.
- Requires SW7426 NAC Release 2.5 Base Software Package.
- For detailed information on system configuration, please consult the NAC Release 2 Ordering Procedures for New Systems, Expansions, Migrations and Upgrades.
- Includes one VME332XT 8 Channel Asynchronous I/O Board, UDS 2440 Modem, a 10 Ft. modem cable, and a 45 Ft. System Console cable.
- There must be at least one system console equipped per system.
- There must be a Network link from NAC Release 2.5 to each Meridian MAX (AM) Release 4.3 or later node. Meridian MAX-IPE/IPEE Release 6, or later, can also be connected to NAC Release 2.5.
- ACD MAX Release 1 through Release 4 and Meridian MAX Release 3 are not supported with NAC Release 2.5.
- Optional Remote Supervisor Login Links can be configured between NAC Release 2.5 and each MAX node.
- Order NT6D98AA 8 Channel Asynchronous Kit, if additional I/O ports are required for Network links, Remote Login Supervisor Links, Supervisor terminals and printers. Up to 40 I/O ports can be configured.
- Order AS1081A or AS1081D Pedestal and Top Cap Assembly as required.
- Order NT9D18AA Module Side Cover as required.
- The modem provided in this package is for remote diagnostics. Order additional modems for Network links, Remote Supervisor login and dial-up supervisors.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT7D61EV	SDI Cable (45 Ft)
1	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	1	NT7D62CA	1 2 GByte Hard Disk/600 MByte Tape Drive Assembly
1	NT7D19SA	Meridian MAX Release 5 Applications Module	1	NT7D64DC	Application Module Power Supply DC
1	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	3	NT8D96BE	VME Multi-Port Cable
1	NT7D61EF	SDI Cable (10 Ft)	1	NTRH9016	External Modem 33 6

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7014A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Prime Node, 300MB Package AC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	2	NT8D29AB	Common Equipment Power Supply AC
1	NT6D44AA	Meridian Mail Module AC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	P0739519	Meridian Mail Modular Option Reference Manual, Release 8
1	NT6D4701	Blank Hard Disk Assembly, 300MB	1	QPF23A	Terminating Plug
1	NT7D06AA	Filler Panel			

Status
➤ S

U7014D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Prime Node, 300MB Package DC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT7D06AA	Filler Panel
2	NT6D41AD	Common Equipment Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D44DC	Meridian Mail Module DC	1	P0739519	Meridian Mail Modular Option Reference Manual, Release 8
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	QPF23A	Terminating Plug
1	NT6D4701	Blank Hard Disk Assembly, 300MB			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7015A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Voice Node, 300MB Package AC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D4701	Blank Hard Disk Assembly, 300MB
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D44AA	Meridian Mail Module AC	1	NT8D31AE	Tape Drive Blank Faceplate

Status
➤ S

U7015D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Voice Node, 300MB Package DC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D44DC	Meridian Mail Module DC
1	NT4R60AA	CRT Cable	1	NT6D4701	Blank Hard Disk Assembly, 300MB
1	NT6D41AD	Common Equipment Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7016A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package AC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	2	NT8D29AB	Common Equipment Power Supply AC
1	NT6D44AA	Meridian Mail Module AC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	P0739519	Meridian Mail Modular Option Reference Manual, Release 8
1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB	1	QPF23A	Terminating Plug
1	NT7D06AA	Filler Panel			

Status
➤ S

U7016D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package DC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT7D06AA	Filler Panel
2	NT6D41AD	Common Equipment Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D44DC	Meridian Mail Module DC	1	P0739519	Meridian Mail Modular Option Reference Manual, Release 8
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	QPF23A	Terminating Plug
1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7017A

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package AC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB
1	NT4R60AA	CRT Cable	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D29AB	Common Equipment Power Supply AC
1	NT6D44AA	Meridian Mail Module AC	1	NT8D31AE	Tape Drive Blank Faceplate

Status
➤ S

U7017D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package DC		Meridian Mail Options (S, ST/RT, NT/XT, X)	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D44DC	Meridian Mail Module DC
1	NT4R60AA	CRT Cable	1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB
1	NT6D41AD	Common Equipment Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
S

U7018001

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 to EC Migration 4-24 Port AC Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	A0100025	Alarm/Modem Cable (25 Ft)	1	NT6P05BA	Tandberg EC Tape Drive Unit, EC
2	A0630697	Magnus 2 5GB Data Cartridge	1	NT7D06AA	Filler Panel
1	A0633585	Tandberg Tape Drive Cleaning Kit	1	NT8D29AB	Common Equipment Power Supply AC
1	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	1	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)
1	NT6D4410	DVS Bus Cable	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6P0106	External Voice Bus Terminator	1	P0695822	AML Link Cable
1	NT6P0109	5 Port RS232 Cable	2	P0803253	Designation Strip
1	NT6P0112	Alarm Cable	1	QPC414C	Network Card
1	NT6P01BA	Meridian Mail EC Module AC			

Status
➤ S

U7018002

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 to EC Migration 4-24 Port DC Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	A0100025	Alarm/Modem Cable (25 Ft)	1	NT6P01AA	Meridian Mail EC Module DC
2	A0630697	Magnus 2 5GB Data Cartridge	1	NT6P05BA	Tandberg EC Tape Drive Unit, EC
1	A0633585	Tandberg Tape Drive Cleaning Kit	1	NT7D06AA	Filler Panel
1	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	1	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)
1	NT6D41AD	Common Equipment Power Supply DC	1	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4410	DVS Bus Cable	1	P0695822	AML Link Cable
1	NT6P0106	External Voice Bus Terminator	2	P0803253	Designation Strip
1	NT6P0109	5 Port RS232 Cable	1	QPC414C	Network Card
1	NT6P0112	Alarm Cable			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7018003

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 to EC Migration 28-48 Port AC Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	A0100025	Alarm/Modem Cable (25 Ft)	1	NT6P01BA	Meridian Mail EC Module AC
2	A0630697	Magnus 2 5GB Data Cartridge	1	NT6P05BA	Tandberg EC Tape Drive Unit, EC
1	A0633585	Tandberg Tape Drive Cleaning Kit	2	NT8D29AB	Common Equipment Power Supply AC
1	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)
1	NT6D4410	DVS Bus Cable	2	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6P0106	External Voice Bus Terminator	1	P0695822	AML Link Cable
1	NT6P0109	5 Port RS232 Cable	2	P0803253	Designation Strip
1	NT6P0112	Alarm Cable	1	QPC414C	Network Card

Status
➤ S

U7018004

Description	System Compatibility	Product compatibility	W/S
Meridian Mail EC11 to EC Migration 28-48 Port DC Package			W0

Qty	Order code	Description	Qty	Order code	Description
1	A0100025	Alarm/Modem Cable (25 Ft)	1	NT6P0112	Alarm Cable
2	A0630697	Magnus 2 5GB Data Cartridge	1	NT6P01AA	Meridian Mail EC Module DC
1	A0633585	Tandberg Tape Drive Cleaning Kit	1	NT6P05BA	Tandberg EC Tape Drive Unit, EC
1	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	2	NT8D73AF	Inter-Cabinet Network Cable (12 Ft)
1	NT6D41AD	Common Equipment Power Supply DC	2	NT8D86BD	Network to I/O Cable (6 Ft)
1	NT6D4410	DVS Bus Cable	1	P0695822	AML Link Cable
1	NT6P0106	External Voice Bus Terminator	2	P0803253	Designation Strip
1	NT6P0109	5 Port RS232 Cable	1	QPC414C	Network Card

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7068D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option GP Prime Node, 300MB Package DC		Meridian Mail GP	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT7D06AA	Filler Panel
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D44BA	Meridian Mail Module DC	1	P0741295	Meridian Mail Modular GP Reference Manual, Release 8
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	QPF23A	Terminating Plug
1	NT6D4701	Blank Hard Disk Assembly, 300MB			

Status
➤ S

U7069D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option GP Voice Node, 300MB Package DC		Meridian Mail GP	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D44BA	Meridian Mail Module DC
1	NT4R60AA	CRT Cable	1	NT6D4701	Blank Hard Disk Assembly, 300MB
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7070

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option GP Prime Node, 600MB/1GB Package DC		Meridian Mail GP	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT7D06AA	Filler Panel
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT8D31AE	Tape Drive Blank Faceplate
1	NT6D44BA	Meridian Mail Module DC	1	P0741295	Meridian Mail Modular GP Reference Manual, Release 8
1	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	1	QPF23A	Terminating Plug
1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB			

Status
➤ S

U7071D

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Migration to Modular Option GP Voice Node, 600MB/1GB Package DC		Meridian Mail GP	W1

Notes:

- If required, pedestal and top cap hardware must be ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- A U7XXX software upgrade package to Release 12 must accompany this hardware migration package.

Qty	Order code	Description	Qty	Order code	Description
2	A0368760	DC6250 250MB Back Up Tape	1	NT6D44BA	Meridian Mail Module DC
1	NT4R60AA	CRT Cable	1	NT6D4801	Blank Hard Disk Assembly, 600MB/1 0GB
1	NT6D41BA	Meridian Mail Modular GP Power Supply DC	1	NT7D06AA	Filler Panel
1	NT6D4415	DVS Bus Cable (6 Ft)	1	NT8D31AE	Tape Drive Blank Faceplate

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7202

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Drive Upgrade		Meridian Mail EC11; Meridian Mail Modular EC	W1

Notes:

- This upgrade is applicable to un-shadowed Nodes 1, 2, 4 & 5.
- Equivalent storage software level will be maintained with disk upgrade.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P07BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive			

Status
➤ S

U7203

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular EC 2GB Disk Drive with Power Upgrade		Meridian Mail EC11; Meridian Mail Modular EC	W1

Notes:

- This upgrade is applicable to Node 3.
- Equivalent storage software level will be maintained with disk upgrade.

Qty	Order code	Description	Qty	Order code	Description
1	NT6P44BA	Meridian Mail Modular EC/EC11 4 5GB Hard Disk Drive with Power			

Status
➤ S

U7207

Description	System Compatibility	Product compatibility	W/S
Meridian Mail Modular Option 2GB Disk Drive Upgrade		Meridian Mail Modular GP; Meridian Mail Modular Option	W1

Notes:

- If the existing system has 5 hours of storage, an expansion to 11 hours of storage will be provided with this upgrade at no additional charge.
- Equivalent storage software level will be maintained with disk upgrade.

Qty	Order code	Description	Qty	Order code	Description
1	NT6D48FA	4 5GB Modular Hard Disk Drive			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7600A

Description	System Compatibility	Product compatibility	W/S
Meridian NAC Release 2.5 Base Hardware Upgrade Package, AC			W1

Notes:

- Must be housed in the NT7D18AA Application Equipment Module (AC).
- There must be at least one supervisor terminal and one printer equipped per system.
- Requires SW7426 NAC Release 2.5 Base Software Package.
- For detailed information on system configuration, please consult the NAC Release 2 Ordering Procedures for New Systems, Expansions, Migrations and Upgrades.
- Includes one VME332XT 8 Channel Asynchronous I/O Board, UDS 2440 Modem, a 10 Ft. modem cable, and a 45 Ft. System Console cable.
- There must be at least one system console equipped per system.
- There must be a Network link from NAC Release 2.5 to each Meridian MAX (AM) Release 4.3 or later node. Meridian MAX-IPE/IPEE Release 6, or later, can also be connected to NAC Release 2.5.
- ACD MAX Release 1 through Release 4 and Meridian MAX Release 3 are not supported with NAC Release 2.5.
- Optional Remote Supervisor Login Links can be configured between NAC Release 2.5 and each MAX node.
- Order NT6D98AA 8 Channel Asynchronous Kit, if additional I/O ports are required for Network links, Remote Login Supervisor Links, Supervisor terminals and printers. Up to 40 I/O ports can be configured.
- Order AS1081A or AS1081D Pedestal and Top Cap Assembly as required.
- Order NT9D18AA Module Side Cover as required.
- The modem provided in this package is for remote diagnostics. Order additional modems for Network links, Remote Supervisor login and dial-up supervisors.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT7D61EV	SDI Cable (45 Ft)
1	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	1	NT7D62CA	1 2 GByte Hard Disk/600 MByte Tape Drive Assembly
1	NT7D19SA	Meridian MAX Release 5 Applications Module	1	NT7D64AA	Application Module Power Supply AC
1	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	3	NT8D96BE	VME Multi-Port Cable
1	NT7D61EF	SDI Cable (10 Ft)	1	NTRH9016	External Modem 33 6

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U7600D

Description	System Compatibility	Product compatibility	W/S
Meridian NAC Release 2.5 Base Hardware Upgrade Package, DC			W1

Notes:

- Must be housed in the NT7D18AB Application Equipment Module (DC).
- There must be at least one supervisor terminal and one printer equipped per system.
- Requires SW7426 NAC Release 2.5 Base Software Package.
- For detailed information on system configuration, please consult the NAC Release 2 Ordering Procedures for New Systems, Expansions, Migrations and Upgrades.
- Includes one VME332XT 8 Channel Asynchronous I/O Board, UDS 2440 Modem, a 10 Ft. modem cable, and a 45 Ft. System Console cable.
- There must be at least one system console equipped per system.
- There must be a Network link from NAC Release 2.5 to each Meridian MAX (AM) Release 4.3 or later node. Meridian MAX-IPE/IPEE Release 6, or later, can also be connected to NAC Release 2.5.
- ACD MAX Release 1 through Release 4 and Meridian MAX Release 3 are not supported with NAC Release 2.5.
- Optional Remote Supervisor Login Links can be configured between NAC Release 2.5 and each MAX node.
- Order NT6D98AA 8 Channel Asynchronous Kit, if additional I/O ports are required for Network links, Remote Login Supervisor Links, Supervisor terminals and printers. Up to 40 I/O ports can be configured.
- Order AS1081A or AS1081D Pedestal and Top Cap Assembly as required.
- Order NT9D18AA Module Side Cover as required.
- The modem provided in this package is for remote diagnostics. Order additional modems for Network links, Remote Supervisor login and dial-up supervisors.

Qty	Order code	Description	Qty	Order code	Description
1	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	1	NT7D61EV	SDI Cable (45 Ft)
1	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	1	NT7D62CA	1 2 GByte Hard Disk/600 MByte Tape Drive Assembly
1	NT7D19SA	Meridian MAX Release 5 Applications Module	1	NT7D64DC	Application Module Power Supply DC
1	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	3	NT8D96BE	VME Multi-Port Cable
1	NT7D61EF	SDI Cable (10 Ft)	1	NTRH9016	External Modem 33 6

Status
† ➤ S

U9620

Description	System Compatibility	Product compatibility	W/S
Connector Mounting Kit	S		W1

Qty	Order code	Description	Qty	Order code	Description
2	P0697550	Connector Adapter Bracket	1	P0697707	Connector Cover Panel
2	P0697559	Mounting Bracket			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9639A

Description	System Compatibility	Product compatibility	W/S
Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/21A/21/21E Upgrade Package AC	21; 21A; 21E; A; L; LE (23, 96); M; MS; N; NT; RT; S; ST; STE		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One NT8D21AA Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used.
- One SuperLoop Network Card, IPE module, power supply, and cable is included in the above package to provide replacement card slot availability for the existing IPE cards contained in the unused NT8D11 Module.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21AA	Core/Network Module AC
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack
1	NT7D00AA	Top Cap AC
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
1	NT8D06AB	Peripheral Equipment Power Supply AC
2	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
2	NT8D29AB	Common Equipment Power Supply AC
1	NT8D37BA	Intelligent Peripheral Equipment Module AC
1	NT8D41BA	Quad SDI Paddle Board
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)
2	NT8D80BZ	CPU Interface Cable (5 Ft)
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)
1	NT8D91AE	Network to Controller Cable (8 Ft)
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)
6	NT9D18AA	Module Side Cover
1	NTLH02AA	Meridian 1 Reference Library, Release 25
	Each Package Includes:	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTND14BC	CNI to 3PE Cable (12 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25AA	Pedestal Assembly AC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9639D

Description	System Compatibility	Product compatibility	W/S
Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/21A/21/21E Upgrade Package DC	21; 21A; 21E; A; L; LE (23, 96); M; MS; N; NT; RT; S; ST; STE		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- One NT6D42CC Ringing Generator DC must be added for each IPE module in which analog type peripheral cards are to be used.
- To extend alarm and trip leads from the system monitor to the external power equipment, the appropriate system monitor cable (NT8D46) must be determined and ordered separately.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One SuperLoop Network Card, IPE module, power supply, and cable is included in the above package to provide replacement card slot availability for the existing IPE cards contained in the unused NT8D11 Module.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21DA	Core/Network Module DC
2	NT5D61AB	IODU/C Pack
1	NT6D40BA	Peripheral Equipment Power Supply DC
2	NT6D41AD	Common Equipment Power Supply DC
1	NT7D00BA	Top Cap DC
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
2	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	NT8D41BA	Quad SDI Paddle Board
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)
2	NT8D80BZ	CPU Interface Cable (5 Ft)
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)
1	NT8D91AE	Network to Controller Cable (8 Ft)
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)
6	NT9D18AA	Module Side Cover
1	NTLH02AA	Meridian 1 Reference Library, Release 25

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTND14BC	CNI to 3PE Cable (12 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
2	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

Status
➤ S

U9640

Description	System Compatibility	Product compatibility	W/S
Option 61C from Option 61 Cardcage Upgrade Package AC/DC	61		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately.

Qty	Order code	Description
2	NT1R90BA	Cardcage Upgrade Parts Kit
1	NT1R91AA	Modem Kit
2	NT5D2104	Core/Network Cardcage (AC/DC)
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack
2	NT7D89CA	CP to I/O Panel RS232 Cable
2	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in /1m)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	P0712003	Instruction Package	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9641A

Description	System Compatibility	Product compatibility	W/S
Option 61C from Option 51 Upgrade Package AC	51		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- This package assumes that the QPC477B10 vintage is installed in the existing Option 51. The B10 vintage is the minimum vintage required for Option 61C.
- This package assumes that the QPC441F vintage is installed in the existing Option 51. The F vintage is the minimum vintage required for Option 61C.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One NT8D21AA Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
2	NT5D21AA	Core/Network Module AC	
1	NT5D50AA	SCSI Extension Cable	
2	NT5D61AB	IODU/C Pack	
1	NT7D00AA	Top Cap AC	
1	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)
2	NTND14BB	CNI to 3PE Cable (10 Ft)
2	NTND14BC	CNI to 3PE Cable (12 Ft)
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)
1	NTRD25AA	Pedestal Assembly AC
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
1	QPC43R	Peripheral Signaling
2	QPC441F	Three-Port Extender
2	QPC471H	Clock Controller

Status
➤ S

U9641D

Description	System Compatibility	Product compatibility	W/S
Option 61C from Option 51 Upgrade Package DC	51		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- One NT6D42CC Ringing Generator DC must be added for each IPE module in which analog type peripheral cards are to be used.
- This package assumes that the QPC477B10 vintage is installed in the existing Option 51. The B10 vintage is the minimum vintage required for Option 61C.
- This package assumes that the QPC441F vintage is installed in the existing Option 51. The F vintage is the minimum vintage required for Option 61C.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21DA	Core/Network Module DC
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack
2	NT6D41AD	Common Equipment Power Supply DC
1	NT7D00BA	Top Cap DC
1	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
2	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTND14BC	CNI to 3PE Cable (12 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
2	QPC441F	Three-Port Extender	
2	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9643A

Description	System Compatibility	Product compatibility	W/S
Option 51C from A/M/S/MS/ST/STE/21A/ 21/21E Upgrade Package AC	21; 21A; 21E; A; M; MS; S; ST; STE		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
1	NT5D21AA	Core/Network Module AC	
1	NT5D50AA	SCSI Extension Cable	
1	NT5D61AB	IODU/C Pack	
1	NT7D00AA	Top Cap AC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
1	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
1	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
4	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25AA	Pedestal Assembly AC	
1	P0678258	Filter Connector	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

Status
➤ S

U9643D

Description	System Compatibility	Product compatibility	W/S
Option 51C from A/M/S/MS/ST/STE/21A/ 21/21E Upgrade Package DC	21; 21A; 21E; A; M; MS; S; ST; STE		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- If upgrading from an Option 21A, one AS1004 Pedestal/Top Cap Assembly must be ordered.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
1	NT5D21DA	Core/Network Module DC
1	NT5D61AB	IODU/C Pack
1	NT6D40BA	Peripheral Equipment Power Supply DC
1	NT6D41AD	Common Equipment Power Supply DC
1	NT7D00BA	Top Cap DC
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
1	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
1	NT8D37EC	Intelligent Peripheral Equipment Module DC
1	NT8D41BA	Quad SDI Paddle Board

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
3	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
4	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0678258	Filter Connector	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9644A

Description	System Compatibility	Product compatibility	W/S
Option 51C from Option 21/21E Cardcage Upgrade Package AC	21; 21E		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package assumes the existing system does not contain more than 3 modules in order to allow for the addition of one IPE module as part of the upgrade. The additional IPE module is required due to the loss of the IPE slots originally provided in the Option 21 or 21E card cage being replaced. If the existing system is already 4 modules high, additional equipment such as pedestal, top cap, blower, etc., must be engineered and ordered to support the new IPE module.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One SuperLoop Network Card, IPE module, power supply, and cable is included in the above package to provide replacement card slot availability for the existing IPE cards contained in the unused NT8D11 Module.

Qty	Order code	Description	
1	NT1R90BA	Cardcage Upgrade Parts Kit	
1	NT1R91AA	Modem Kit	
1	NT5D2104	Core/Network Cardcage (AC/DC)	
1	NT5D50AA	SCSI Extension Cable	
1	NT5D61AB	IODU/C Pack	
1	NT7D89CA	CP to I/O Panel RS232 Cable	
1	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in /1m)	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
1	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D40AU	MPDU to CEPS Cable Harness	
1	NT8D56AA	Common Equipment Module Power Distribution Unit	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
2	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	P0745716	Universal I/O Panel	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

Status
➤ S

U9644D

Description	System Compatibility	Product compatibility	W/S
Option 51C from Option 21/21E Cardcage Upgrade Package DC	21; 21E		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package assumes the existing system does not contain more than 3 modules in order to allow for the addition of one IPE module as part of the upgrade. The additional IPE module is required due to the loss of the IPE slots originally provided in the Option 21 or 21E card cage being replaced. If the existing system is already 4 modules high, additional equipment such as pedestal, top cap, blower, etc., must be engineered and ordered to support the new IPE module.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- One SuperLoop Network Card, IPE module, power supply, and cable is included in the above package to provide replacement card slot availability for the existing IPE cards contained in the unused NT8D11 Module.

Qty	Order code	Description
1	NT1R90BA	Cardcage Upgrade Parts Kit
1	NT1R91AA	Modem Kit
1	NT5D2104	Core/Network Cardcage (AC/DC)
1	NT5D50AA	SCSI Extension Cable
1	NT5D61AB	IODU/C Pack
1	NT6D40BA	Peripheral Equipment Power Supply DC
1	NT6D41AD	Common Equipment Power Supply DC
1	NT7D11AG	Power Harness to Backplane Cable
1	NT7D89CA	CP to I/O Panel RS232 Cable
1	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in /1m)
1	NT8D01BC	Controller - Four Card

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D40AU	MPDU to CEPS Cable Harness	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
2	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	P0745716	Universal I/O Panel	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

Status
➤ S

U9645

Description	System Compatibility	Product compatibility	W/S
Option 51C from Option 51 Cardcage Upgrade Package AC/DC	51		W1

Notes:

- Option 51C requires one Call Processor. The Call Processor is not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes. See Call Processor notes to determine which Call Processors meet the Option 51C minimum memory requirements for the current software release.
- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.

Qty	Order code	Description
1	NT1R90BA	Cardcage Upgrade Parts Kit
1	NT1R91AA	Modem Kit
1	NT5D2104	Core/Network Cardcage (AC/DC)
1	NT5D50AA	SCSI Extension Cable
1	NT5D61AB	IODU/C Pack
1	NT7D89CA	CP to I/O Panel RS232 Cable
1	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in /1m)
1	NTLH02AA	Meridian 1 Reference Library, Release 25

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9646A

Description	System Compatibility	Product compatibility	W/S
Option 61C from Option 51C Upgrade Package AC	51C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Memory upgrade kit NTZC75 supports DRAM memory upgrades of commercial call processors. Consult the latest Product Bulletin on Memory Upgrade Requirements.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- Option 61C systems utilizing 68040 call processor requires X11 Release 22 Software Generic 2311.
- Two IODU/C (NT5D61) cards are required. One is included in the package. The second may be provisioned from existing equipment or must be ordered separately.

Qty	Order code	Description	
1	NT5D21AA	Core/Network Module AC	
1	NT5D61AB	IODU/C Pack	
1	NT7D00AA	Top Cap AC	
1	NT8D17FA	Conference/TDS Card	
1	NT8D22AC	System Monitor	
1	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)
1	NTRD25AA	Pedestal Assembly AC
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
1	QPC43R	Peripheral Signaling
1	QPC441F	Three-Port Extender
1	QPC471H	Clock Controller

Status
➤ S

U9646D

Description	System Compatibility	Product compatibility	W/S
Option 61C from Option 51C Upgrade Package DC	51C		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- Two IODU/C(NT5D61) cards are required. One is included in the package. The second may be provisioned from existing equipment or must be ordered separately.
- Option 61C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Memory upgrade kit NTZC75 supports DRAM memory upgrades of commercial call processors. Consult the latest Product Bulletin on memory upgrade requirements.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.

Qty	Order code	Description
1	NT5D21DA	Core/Network Module DC
1	NT5D61AB	IODU/C Pack
1	NT6D41AD	Common Equipment Power Supply DC
1	NT7D00BA	Top Cap DC
1	NT8D17FA	Conference/TDS Card
1	NT8D22AC	System Monitor
1	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In)
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)
1	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft)
2	NT8D80BZ	CPU Interface Cable (5 Ft)
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)
1	NTLH02AA	Meridian 1 Reference Library, Release 25

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
1	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	
1	P0712003	Instruction Package	
1	P0738686	Meridian 1 Pallet Ramp Set	
1	QPC43R	Peripheral Signaling	
1	QPC441F	Three-Port Extender	
1	QPC471H	Clock Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9650A

Description	System Compatibility	Product compatibility	W/S
Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/71 Core and Network Upgrade Package AC	71; L; LE (23, 96); N; NT; VL; VLE; XL; XN; XT		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- For upgrades from an Option 71, this package is compatible only with systems that have been previously upgraded to Option 71, where the common equipment is still cabinet-based. Package U9652 should be used for upgrades from module-based Option 71 systems.
- This package contains two network groups. Network Modules for additional groups, if required, should be ordered using package AS1039A.
- Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or completely in modules. Mixed network configurations are not supported (i.e. network groups in both cabinets and modules).
- This package contains four NTND14 CNI to 3PE cables and eight NT8D76 IGS to IGM Cables for the first two network groups. Cables for additional groups must be ordered separately.
- Inter-Cabinet cables for connection of network equipment in modules to peripheral equipment in cabinets or modules must be determined and ordered separately.
- This package includes four (Qty 4) QPC441 cards (3PE). If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- The Junctor requires four QPF36 Terminating plugs for each unequipped network group; these must be ordered separately.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21AA	Core/Network Module AC
4	NT5D30AA	Dual Intergroup Switch
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack
2	NT7D00AA	Top Cap AC
2	NT7D06AA	Filler Panel
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
1	NT8D06AB	Peripheral Equipment Power Supply AC
4	NT8D17FA	Conference/TDS Card

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT8D22AC	System Monitor	
4	NT8D29AB	Common Equipment Power Supply AC	
2	NT8D35BA	Network Module AC	
1	NT8D36AA	Inter Group Module	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
4	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
1	NT8D82AD	SDI to I/O Cable (6 Ft)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRD25AA	Pedestal Assembly AC	
2	P0623569	Alarm Terminating Plug	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
1	QPC417A	Junctor Board
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender
2	QPC471H	Clock Controller

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9650D

Description	System Compatibility	Product compatibility	W/S
Option 81C from L/LE(23,96)/N/VL/VLE/ XL(24,97)/NT/XN/XT/71 Core and Network Upgrade Package DC	71; L; LE (23, 96); N; NT; VL; VLE; XL (24, 97); XN; XT		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- For upgrades from an Option 71, this package is compatible only with systems that have been previously upgraded to Option 71, where the common equipment is still cabinet-based. Package U9652 should be used for upgrades from module-based Option 71 systems.
- Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or completely in modules. Mixed network configurations are not supported (i.e. network groups in both cabinets and modules).
- This package contains four NTND14 CNI to 3PE cables and eight NT8D76 IGS to IGM Cables for the first two network groups. Cables for additional groups must be ordered separately.
- Inter-Cabinet cables for connection of network equipment in modules to peripheral equipment in cabinets or modules must be determined and ordered separately.
- This package includes four (Qty 4) QPC441 cards (3PE). If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- This package contains two network groups. If network modules for additional groups are required, they should be ordered using package AS1039D.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- The Junctor requires four QPF36 Terminating plugs for each unequipped network group; these must be ordered separately.
- For upgrades removing the existing CPU and continuing to utilize the CPE/PE cabinet, refer to product bulletin 91014.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.

Qty	Order code	Description
1	NT1R91AA	Modem Kit
2	NT5D21DA	Core/Network Module DC
4	NT5D30AA	Dual Intergroup Switch
2	NT5D61AB	IODU/C Pack
1	NT6D40BA	Peripheral Equipment Power Supply DC
4	NT6D41AD	Common Equipment Power Supply DC
2	NT7D00BA	Top Cap DC
2	NT7D06AA	Filler Panel
1	NT8D01BC	Controller - Four Card
1	NT8D04BA	SuperLoop Network Card
4	NT8D17FA	Conference/TDS Card
2	NT8D22AC	System Monitor
2	NT8D35EA	Network Module DC
1	NT8D36AA	Inter Group Module
1	NT8D37EC	Intelligent Peripheral Equipment Module DC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
2	NT8D49AA	Column Spacer Kit (2 75 In)	
1	NT8D74BD	Clock Controller to Junctor Cable (6 Ft)	
1	NT8D74BE	Clock Controller to Junctor Cable (8 Ft)	
2	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft)	
4	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft)	
2	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft)	
2	NT8D80BZ	CPU Interface Cable (5 Ft)	
1	NT8D82AD	SDI to I/O Cable (6 Ft)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft)	
1	NT8D91AE	Network to Controller Cable (8 Ft)	
5	NT8D99AB	CPU or Network to Network Cable (2 Ft)	
2	NT8D99AD	CPU or Network to Network Cable (6 Ft)	
8	NT9D18AA	Module Side Cover	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BB	CNI to 3PE Cable (10 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRD25BA	Pedestal Assembly DC	
2	P0623569	Alarm Terminating Plug	
1	P0712003	Instruction Package	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
1	P0738686	Meridian 1 Pallet Ramp Set
1	QPC417A	Junctor Board
4	QPC43R	Peripheral Signaling
4	QPC441F	Three-Port Extender
2	QPC471H	Clock Controller

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9651A

Description	System Compatibility	Product compatibility	W/S
Option 81C from XN/XT/71 Core Upgrade Package AC (Dual Column)	71; XN; XT		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package is compatible only with XN and XT systems housed in QCA55 and QCA108 cabinets, and with systems that have been upgraded to Option 71 where the common equipment resides in QCA55 and QCA108 cabinets. Package U9652 should be used for upgrades from module based Option 71 systems.
- This package does not include an additional network group. Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or housed completely in modules. Mixed network configurations are not supported (i.e., network groups in both cabinets and modules).
- This package contains the equipment required to complete a core upgrade from a dual column XN/XT or Option 71 to an Option 81C. For those customers moving their networks to modules, this package does not include the hardware required to equip the network group in the Core/Network Modules. To equip the network group in the Core/Network Modules, AS1250 Option 81C Core/Network Group Package (Qty 1) must be ordered separately.
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group if added. For a four-to-five group system one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered.
- This package includes (Qty 1) NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then an additional NT5D40AA Hybrids Kit (Qty 1) is required and must be ordered separately.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- This package does not include QPC441 (3PE) cards. If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- Inter-Cabinet cables for connection of network equipment in cabinets to peripheral equipment in cabinets or modules must be determined and ordered separately.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT1R91AA	Modem Kit	
2	NT5D21AA	Core/Network Module AC	
1	NT5D40AA	Hybrids Kit	
1	NT5D50AA	SCSI Extension Cable	
2	NT5D61AB	IODU/C Pack	
2	NT7D00AA	Top Cap AC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
2	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
1	NT8D49AA	Column Spacer Kit (2 75 In)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D92AB	Controller to I/O Cable (20 Inch)	
1	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft) (Male/Female)	
1	NT8D98AS	Inter-Cabinet Network Cable (30 Ft)	
4	NT9D18AA	Module Side Cover	
1	NT9J97AE	Intra-Cabinet Network Cable (85 In)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRD25AA	Pedestal Assembly AC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	P0623569	Alarm Terminating Plug
2	P0699851	Top Cap Cable Egress Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
2	QPC471H	Clock Controller

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9651D

Description	System Compatibility	Product compatibility	W/S
Option 81C from XN/XT/71 Core Upgrade Package DC (Dual Column)	71; XN; XT		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- This package is compatible only with XN and XT systems housed in QCA55 and QCA108 cabinets, and with systems that have been upgraded to Option 71 where the common equipment resides in QCA55 and QCA108 cabinets. Package U9652 should be used for upgrades from module based Option 71 systems.
- This package does not include an additional network group. Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or housed completely in modules. Mixed network configurations are not supported (i.e., network groups in both cabinets and modules).
- This package contains the equipment required to complete a core upgrade from a dual column XN/XT or Option 71 to an Option 81C. For those customers moving their networks to modules, this package does not include the hardware required to equip the network group in the Core/Network Modules. To equip the network group in the Core/Network Modules, AS1250 Option 81C Core/Network Group Package (Qty 1) must be ordered separately.
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group if added. For a four-to-five group system one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered.
- This package includes (Qty 1) NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then an additional NT5D40AA Hybrids Kit (Qty 1) is required and must be ordered separately.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- This package does not include 3PE (QPC441) cards. If 3PE cards are required, they must be ordered separately. Vintage must be "F" of later.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. Call Processor memory requirements and X11 software generic requirements are defined in the Call Processor product notes.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- Inter-Cabinet cables for connection of network equipment in cabinets to peripheral equipment in cabinets or modules must be determined and ordered separately.

Qty	Order code	Description
2	A0369107	Sub-D Filter Connector (25 Conductor)
1	NT1R91AA	Modem Kit
2	NT5D21DA	Core/Network Module DC
1	NT5D40AA	Hybrids Kit
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack
1	NT6D40BA	Peripheral Equipment Power Supply DC
2	NT6D41AD	Common Equipment Power Supply DC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	NT7D00BA	Top Cap DC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
2	NT8D22AC	System Monitor	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46AS	System Monitor Inter-CPU Cable (30 In)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
1	NT8D49AA	Column Spacer Kit (2 75 In)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D92AB	Controller to I/O Cable (20 Inch)	
1	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft) (Male/Female)	
1	NT8D98AS	Inter-Cabinet Network Cable (30 Ft)	
4	NT9D18AA	Module Side Cover	
1	NT9J97AE	Intra-Cabinet Network Cable (85 In)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
2	NTRD25BA	Pedestal Assembly DC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	P0623569	Alarm Terminating Plug
2	P0699851	Top Cap Cable Egress Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
2	QPC471H	Clock Controller

Status
➤ S

U9652

Description	System Compatibility	Product compatibility	W/S
Option 81C from Option 71 Card Cage Upgrade Package AC/DC	71		W1

Notes:

- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- This package contains the equipment required to complete a core upgrade from an Option 71 to an Option 81C. This package does not include the hardware required to equip the network group in the Core/Network Modules. To equip the network group in the Core/Network Modules, AS1250 Option 81C Core/Network Group Package (Qty 1) must be ordered separately.
- The Option 81C requires (Qty 2) Clock Controller cards QPC471 that are vintage "H" or later. If these cards are not presently equipped in the system to be upgraded, they must be ordered separately.
- This package does not include 3PE (QPC441) cards. If 3PE cards are required, they must be ordered separately. Vintage must be "F" of later.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 81C minimum memory requirements for the current software release.
- This package contains four NTND14 CNI to 3PE cables for the first network group. Cables for additional groups must be ordered separately.
- The contents of the package assume that the NT8D29 or NT6D41 Common Equipment Power Supplies from the existing Option 71 will be reused.

Qty	Order code	Description	
2	NT1R90BA	Cardcage Upgrade Parts Kit	
1	NT1R91AA	Modem Kit	
2	NT5D2104	Core/Network Cardcage (AC/DC)	
1	NT5D50AA	SCSI Extension Cable	
2	NT5D61AB	IODU/C Pack	
2	NT7D89CA	CP to I/O Panel RS232 Cable	
2	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in /1m)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
2	NTND14BA	CNI to 3PE Cable (5 Ft)	
2	NTND14BC	CNI to 3PE Cable (12 Ft)	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	P0738866	Label Kit for Inter-Cabinet Cables	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9653A

Description	System Compatibility	Product compatibility	W/S
Option 81C from XN/XT/71 Core Upgrade Package AC (Single Column)	71; XN; XT		W1

Notes:

- One NT8D21AB Ringing Generator AC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- This package is compatible only with XN and XT systems housed in QCA55 and QCA108 cabinets, and with systems that have been upgraded to Option 71 where the common equipment resides in QCA55 and QCA108 cabinets. Package U9652 should be used for upgrades from module based Option 71 systems.
- This package does not include an additional network group. Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or housed completely in modules. Mixed network configurations are not supported (i.e., network groups in both cabinets and modules).
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group if added. For a four-to-five group system one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered.
- This package includes (Qty 1) NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then an additional NT5D40AA Hybrids Kit (Qty 1) is required and must be ordered separately.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- This package is a single column version of package U9651A, and may be used when sufficient floor space is not available for two columns. With this package, separate power feeds may be provided to the two (2) Core Modules, but the Blower Unit, Power Distribution, and System Monitor are not redundant.
- This package does not include 3PE (QPC441) cards. If 3PE cards are required, they must be ordered separately. Vintage must be "F" of later.
- This package contains the equipment required to complete a core upgrade from a single column XN/XT or Option 71 to an Option 81C. For those customers moving their networks to modules, this package does not include the hardware required to equip the network group in the Core/Network Modules. To equip the network group in the Core/Network Modules, AS1250 Option 81C Core/Network Group Package (Qty 1) must be ordered separately.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 81C minimum memory requirements for the current software release.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- Inter-Cabinet cables for connection of network equipment in cabinets to peripheral equipment in cabinets or modules must be determined and ordered separately.

Qty	Order code	Description
2	A0369107	Sub-D Filter Connector (25 Conductor)
1	NT1R91AA	Modem Kit
2	NT5D21AA	Core/Network Module AC
1	NT5D40AA	Hybrids Kit
1	NT5D50AA	SCSI Extension Cable
2	NT5D61AB	IODU/C Pack

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
1	NT7D00AA	Top Cap AC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D06AB	Peripheral Equipment Power Supply AC	
1	NT8D22AC	System Monitor	
2	NT8D29AB	Common Equipment Power Supply AC	
1	NT8D37BA	Intelligent Peripheral Equipment Module AC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D92AB	Controller to I/O Cable (20 Inch)	
1	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft) (Male/Female)	
1	NT8D98AS	Inter-Cabinet Network Cable (30 Ft)	
6	NT9D18AA	Module Side Cover	
1	NT9J97AE	Intra-Cabinet Network Cable (85 In)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25AA	Pedestal Assembly AC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	P0623569	Alarm Terminating Plug
1	P0699851	Top Cap Cable Egress Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
2	QPC471H	Clock Controller

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status
➤ S

U9653D

Description	System Compatibility	Product compatibility	W/S
Option 81C from XN/XT/71 Core Upgrade Package DC (Single Column)	71; XN; XT		W1

Notes:

- One NT6D42CD Ringing Generator DC must be added for each IPE Module in which analog type peripheral cards are to be used. Otherwise, one NT7D05AA Filler Panel-Ringing Generator must be equipped.
- NTRB34AA Core-Network Interface Card 3-Port (CNI-3) has replaced NT6D65 Core-Network Interface Card. Only Option 81/81C systems utilizing Release 25 or later software can enable the 3rd port on the faceplate of the CNI 3-Port card.
- This package contains two NTRB34AA Core-to-Network Interface Cards 3-Port (CNI-3). With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- This package is compatible only with XN and XT systems housed in QCA55 and QCA108 cabinets, and with systems that have been upgraded to Option 71 where the common equipment resides in QCA55 and QCA108 cabinets. Package U9652 should be used for upgrades from module based Option 71 systems.
- This package does not include an additional network group. Network groups (whether existing with the current system or added at a later time) must be housed completely in cabinets or housed completely in modules. Mixed network configurations are not supported (i.e., network groups in both cabinets and modules).
- This package contains one NTND33DA Option 81C Core-Cabinet Upgrade Cable Kit, Group 0 for inter-cabinet (i.e. cabinet to module) cabling of the first network group and one NTND33CC Core-Cabinet Upgrade Cable Kit, Groups 1-4 that supports cabling of the second network group and will support a third network group if added. For a four-to-five group system one additional NTND33CC Upgrade Cable Kit, Groups 1-4 must be ordered.
- This package includes (Qty 1) NT5D40AA Hybrids Kit to upgrade the QSD39 Network shelf that will house the QPC471 Clock Controller. If the second QPC471 Clock Controller will also be installed in a QSD39 Network Shelf rather than the typical QSD40 Shelf, then an additional NT5D40AA Hybrids Kit (Qty 1) is required and must be ordered separately.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- This package is a single column version of package U9651D, and may be used when sufficient floor space is not available for two columns. With this package, separate power feeds may be provided to the two (2) Core Modules, but the Blower Unit, Power Distribution, and System Monitor are not redundant.
- This package does not include 3PE (QPC441) cards. If 3PE cards are required, they must be ordered separately. Vintage must be "F" of later.
- This package contains the equipment required to complete a core upgrade from a single column XN/XT or Option 71 to an Option 81C. For those customers moving their networks to modules, this package does not include the hardware required to equip the network group in the Core/Network Modules. To equip the network group in the Core/Network Modules, AS1250 Option 81C Core/Network Group Package (Qty 1) must be ordered separately.
- Option 81C requires two identical Call Processors with the same memory configuration. The Call Processors are not included in the above package and must be ordered separately. See Call Processor notes to determine which Call Processors meet the Option 81C minimum memory requirements for the current software release.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes sixteen NT8D81AA Tip and Ring Cables within the IPE Module.
- Inter-Cabinet cables for connection of network equipment in cabinets to peripheral equipment in cabinets or modules must be determined and ordered separately.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description	
2	A0369107	Sub-D Filter Connector (25 Conductor)	
1	NT1R91AA	Modem Kit	
2	NT5D21DA	Core/Network Module DC	
1	NT5D40AA	Hybrids Kit	
1	NT5D50AA	SCSI Extension Cable	
2	NT5D61AB	IODU/C Pack	
1	NT6D40BA	Peripheral Equipment Power Supply DC	
2	NT6D41AD	Common Equipment Power Supply DC	
1	NT7D00BA	Top Cap DC	
1	NT8D01BC	Controller - Four Card	
1	NT8D04BA	SuperLoop Network Card	
1	NT8D22AC	System Monitor	
1	NT8D37EC	Intelligent Peripheral Equipment Module DC	
1	NT8D41BA	Quad SDI Paddle Board	
1	NT8D46AD	System Monitor to SDI Cable (60 In)	
1	NT8D46AL	System Monitor Serial Link Cable (7 Ft)	
1	NT8D46BH	System Monitor to MDF Cable (32 Ft)	
4	NT8D84AA	SDI Paddleboard to I/O Cable (18 In)	
1	NT8D92AB	Controller to I/O Cable (20 Inch)	
1	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft) (Male/Female)	
1	NT8D98AS	Inter-Cabinet Network Cable (30 Ft)	
6	NT9D18AA	Module Side Cover	
1	NT9J97AE	Intra-Cabinet Network Cable (85 In)	
1	NTLH02AA	Meridian 1 Reference Library, Release 25	
	Each Package Includes:		
	1	NTLH03AA	System Planning and Engineering Guide
	1	NTLH04AA	System Installation and Maintenance Guide
	1	NTLH05AA	System and Software Upgrade Guide
	1	NTLH06AA	Remote Peripheral Equipment Guide
	1	NTLH09AA	X11 Input/Output Guide
	1	NTLH10AA	X11 System Management, Overview, Applications and Security Guide
	1	NTLH11AA	X11 Networking Features
	1	NTLH12AA	X11 Data Features
	1	NTLH13AA	ACD Reference Guides
	1	NTLH14AA	X11 Hospitality Features
	1	P0912432	Library Navigator
2	NTND11BA	CP to CP Cable (6 Ft)	
1	NTND13BC	IOP to IOP SCSI Cable (6 Ft)	
1	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	
1	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	
2	NTRB34AA	Core-to-Network Interface Card (CNI-3)	
1	NTRD25BA	Pedestal Assembly DC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Qty	Order code	Description
2	P0623569	Alarm Terminating Plug
1	P0699851	Top Cap Cable Egress Panel
1	P0712003	Instruction Package
1	P0738686	Meridian 1 Pallet Ramp Set
2	QPC471H	Clock Controller

Status
➤ S

U9654A

Description	System Compatibility	Product compatibility	W/S
Option 81C from Option 61C Upgrade (Package #1) AC	61C		W1

Notes:

- This package contains sixteen NT8D18AA Tip and Ring cables within the IPE modules.
- This package is for Option 61C systems that are currently equipped with 2 Core/Network Modules (NT5D21) and 2 of IODU/C (NT5D61). This package assumes these will be reused. If the Option 61C is equipped with 2 Core/Network Modules (NT5D21) and either 2 IOP/CMDU or, 2 IOP (NT6D63) and 2 CMDU (NT6D64), U9655A should be ordered. If the Option 61C is equipped with 2 Core/Network Modules (NT9D19), then U9656A should be ordered.
- Additional NT9D18AA Module Side Covers and NT8D49AA Column Spacer Kits to cover all exposed sides of modules and to connect modules side-to-side must be determined and ordered separately.
- This package includes two 3PE (QPC441) cards. If additional 3PE cards are required, they must be ordered separately. Vintage must be "F" or later.
- Upgrades to Option 81C require relocation of Clock Controller cards (QPC471) from the core to a network group. Any network shelf or network module can be used to house the Clock Controllers provided that one clock is located in side zero and one clock is located in side 1. Relocation of clock controllers may impact clock cabling. If existing cabling cannot support the relocated clocks, new clock controller cables (NT8D74 Clock Controller to Junctor and NT8D79 PRI/DTI to Clock Controller) must be ordered separately.
- The Option 81C requires (Qty 2) Clock Controller cards QPC471 that are vintage "H" or later. If these cards are not presently equipped in the system to be upgraded, they must be ordered separately.
- This package assumes that the existing CNI (NT6D65AA) cards will be reused (one for each Core/Network Module) to support the first two network groups. With Release 25 or later software, the CNI-3 cards can support up to three network groups per card. Two additional NTRB34AA cards are required to support network groups three, four and five. The maximum number of network groups supported on Option 81C systems with IGS switching (QPC412 or NT5D30 cards) in the system is five.
- This package assumes that existing NT5D21 Core/Network Modules remain stacked in the same column, Customers wishing to reconfigure their NT5D21 Core/Network Modules (i.e., placing Core/Network Modules side-by-side) to take advantage of separate column redundancy must order the following items: NT1R90BA Field Upgrade Parts Kit Qty 1, NT1R89AA IPE Cardcage Expansion Kit Qty 1, NT8D99AD CPU to Network Cable 6 Ft. Qty 2 and NT8D46AS System Monitor Inter-CPU Cable 30 in. Qty 1. These items are used to perform a cardcage exchange between the new IPE m

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Price List

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	228SL1-1	Connector Housing Box Assembly	140.00	I	N/A	
S ➤ Δ	574SL1-1	ACD MAX Software Service Transaction Fee	500.00	H	N/A	
S ➤ Δ	599SL1-1	Software Service Transaction Fee	650.00	H	N/A	
S ➤ Δ	63015	Meridian Mail Release 3 to Release 7 Software Migration, from Options to Modular EC	500.00	H	N/A	
S ➤ Δ	63016	Meridian Mail Release 4 to Release 7 Software Migration, from Options to Modular EC	500.00	H	N/A	
S ➤ Δ	63017	Meridian Mail Release 5 to Release 7 Software Migration, from Options, Modular Option to Modular EC	500.00	H	N/A	
S ➤ Δ	63031	Meridian Mail Release 6 to Release 8 Software Migration, from Options to Modular EC	500.00	H	N/A	
S ➤ Δ	63033	Meridian Mail Release 7 to Release 8 Software Migration, from Options to Modular EC	500.00	H	N/A	
S ➤ Δ	63060	Meridian Mail Release 6/7 to Release 8 Software Migration, from Modular Option to Modular EC	500.00	H	N/A	
S	A0100025	Alarm/Modem Cable (25 Ft.)	25.00	D	N/A	
S † ➤	A0237451	Cable, Connector (16 Ft.) (M/M), TTY RS-232 (5.25m)	110.00	D	N/A	
S † ➤	A0263854	Cable, Connector (16 Ft.) (M/F), TTY RS-232 (5.25m)	110.00	D	N/A	
S ➤	A0274225	Handset Cord, 6 Ft. Ash (M2000 Series)	3.00	D	N/A	
S ➤	A0275286	ADM Set Interconnect Cord NE-M4QD (21 In.)	5.00	D	N/A	
S ➤	A0288529	Jumpers (8/PK) (M2000 Series)	30.00	D	N/A	
S ➤	A0292928	110V Power Cord	15.00	D	N/A	
S #	A0297075	Buffer Interface Converter (Room Status & Maid Status)	MD		380.00	H
S #	A0298626	Protocol Convertor-ASCII SNA/SDLC	MD		810.00	H
S #	A0298627	Protocol Convertor-ASCII SNA/SDLC	MD		810.00	H
S #	A0298628	Protocol Convertor-ASCII SNA/SDLC	MD		810.00	H
S #	A0298629	Protocol Convertor-ASCII SNA/SDLC	MD		810.00	H
S #	A0298634	Protocol Convertor-ASCII BISC 110V	MD		810.00	H
S #	A0298635	Protocol Convertor-ASCII BISC 110V	MD		810.00	H
S #	A0298636	Protocol Convertor-ASCII BISC 220V	MD		810.00	H
S #	A0298637	Protocol Convertor-ASCII BISC 220V	MD		810.00	H
S #	A0298638	Protocol Convertor-ASCII SNA/SDLC	MD		810.00	H
S #	A0298639	Protocol Converter-ASCII SNA/SDLC	MD		810.00	H
S #	A0298640	Protocol Convertor SNA/SDLC SL-174	MD		810.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	A0298641	Protocol Converter SNA/SDLC SL-174	MD		810.00	H
S ➤	A0300752	RS232 - V.35 Adapter Cable for HSDM (Male)	175.00	D	N/A	
B ➤	A0300753	RS232 - V.35 Adapter Cable for HSDM (Female)	175.00	D	N/A	
S ➤	A0314408	Handset Cord (6 Ft.) - Gray, (M2000 Series)	3.00	D	N/A	
S † ➤	A0314597	DC600A 60MB Back Up Tape	40.00	D	N/A	
S ➤	A0318327	Handset Cord (9 Ft.) (Standard) - Ash, (M2000 Series)	4.00	D	N/A	
S ➤	A0318330	Handset Cord (9 Ft.) (Standard) - Gray, (M2000 Series)	4.00	D	N/A	
S † ➤	A0318423	Filter Connector (50 Conductor) (EMI)	50.00	D	N/A	
S #	A0319032	SLX25-108A X.25 Gateway (PAD) 8 Ports 110V	MD		975.00	H
S #	A0319033	SLX25-116A X.25 Gateway (PAD) 16 Ports 110V	MD		1,300.00	H
S #	A0320897	DEC 320 Terminal	MD		200.00	H
S #	A0322433	Protocol Converter - ASCII to SNA/SDLC 110V Desk Mount	MD		810.00	H
S #	A0322434	Protocol Converter - ASCII to SNA/SDLC 110V Rack Mount	MD		810.00	H
S #	A0322435	Protocol Converter - ASCII SNA/SDLC 220V Desk Mount	MD		810.00	H
S #	A0322436	Protocol Converter - ASCII SNA/SDLC 220V Rack Mount	MD		810.00	H
S #	A0326595	Protocol Converter - ASCII to Bisynchronous 110V Desk Mount	MD		810.00	H
S #	A0326596	Protocol Converter - ASCII to Bisynchronous 110V Rack Mount	MD		810.00	H
S #	A0326597	Protocol Converter - ASCII to Bisynchronous 220V Desk Mount	MD		810.00	H
S #	A0326598	Protocol Converter - ASCII to Bisynchronous 220V Rack Mount	MD		810.00	H
S † ➤	A0326745	DC300 XLP Back-Up Tape	45.00	D	N/A	
S ➤	A0326761	Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh to Digital Set)	40.00	D	N/A	
S ➤	A0326762	Apple Macintosh Interface Cable DIN 8 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC)	40.00	D	N/A	
S ➤	A0326763	Apple Macintosh Interface Cable DIN8/DB25 (Macintosh to Digital Set)	40.00	D	N/A	
S #	A0326766	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/ SDLC 110V Desk Mount	MD		810.00	H
S #	A0326767	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/ SDLC 110V Rack Mount	MD		810.00	H
S #	A0326768	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/ SDLC 220V Desk Mount	MD		810.00	H
S #	A0326769	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/ SDLC 220V Rack Mount	MD		810.00	H
S ➤	A0327128	Handset Cord (6 Ft.) - Black, (M2000 Series)	3.00	D	N/A	
S ➤	A0334590	Handset Cord (9 Ft.) (Standard) - Black, (M2000 Series)	4.00	D	N/A	
S ➤	A0336406	Power Supply	30.00	D	N/A	
S ➤	A0336823	Multi-Output Power Supply (MOPS)	60.00	D	N/A	
S # Δ	A0336858	70MB Disk ST506 (SA210) Expansion Drive	MD		960.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S # Δ	A0336859	120MB Disk ST506 (SA211) Expansion Drive	MD		1,490.00	H
S # Δ	A0336860	157MB Disk ST506 (SA212) Expansion Drive	MD		2,830.00	H
S # Δ	A0336861	BNS/DTS 2MB Memory (SA241) Expansion Board	MD		225.00	H
S # Δ	A0336908	4-Line Serial Communications Adapter (NM100)	MD		505.00	H
S # Δ	A0336909	Bisynchronous Serial Communications Adapter (NM115)	MD		535.00	H
S # Δ	A0336910	X.25 Communications Adapter (NM127)	MD		535.00	H
S ➤	A0344336	DB25 Male Pin Connector (AILU) (M232-422A)	125.00	D	N/A	
S ➤	A0344337	DB25 Female Pin Connector (AILU) (F232-422A)	125.00	D	N/A	
S #	A0345290	Professional Billing Firmware Cartridge	MD		375.00	H
S #	A0345291	Lodging Firmware Cartridge	MD		375.00	H
S #	A0345292	General Business Firmware Cartridge	MD		375.00	H
S #	A0345383	TDR 600 Basic Unit	MD		385.00	H
S #	A0345384	TDR 1000 Basic Unit	MD		550.00	H
S #	A0345385	M7000 Memory Expansion Module	MD		330.00	H
S ➤	A0346862	6-Conductor Line Cord (7 Ft. for M2000 telephones requiring external power, standard for M3902, M3903, M3904, and M3905)	7.00	D	N/A	
S ➤	A0346863	6-Conductor Line Cord (14 Ft. for M2000 Series requiring external power and M3902, M3903, M3904 and M3905)	12.00	D	N/A	
S ➤	A0348785	Handset Cord with PJ Type Plug (M2250/M1250)	25.00	D	N/A	
S ➤	A0351166	MVME705B Transition Card (for MVME333)	700.00	D	200.00	H
S ➤	A0351167	MVME712AM Transition Card with Built-in Modem (for MVME147)	1,550.00	D	350.00	H
S #	A0351356	3.5 Inch Digital Cassette Tape Drive	MD		510.00	H
B #	A0351371	300MB Disk Drive	MD		3,500.00	H
S ➤	A0351509	Gender Changer (Female/Female)	20.00	D	N/A	
S ➤	A0351919	MVME147SA-1 Processor Card (M68030, 25Mhz, 8MB)	9,200.00	D	1,950.00	H
S #	A0352209	3270 Communications Controller with Transition Card	MD		800.00	H
S #	A0352210	MVME X.25 Communications Card Kit (MVME333, MVME705, Cable)	MD		800.00	H
S ➤	A0352271	150 MByte Data Cassette Tape	50.00	D	N/A	
S ➤	A0352758	Filler Panel, Application Model	100.00	D	N/A	
S † ➤	A0354954	Rectifier, 100 Amp	4,600.00	H	N/A	
S ➤	A0355200	Power Fail Transfer Unit	800.00	I	N/A	
S ➤	A0360824	UDS 2440 Modem	810.00	D	175.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	A0361365	RJ45 Cable	60.00	D	N/A	
S ➤	A0361709	Caster (1)	50.00	I	N/A	
S ➤	A0367335	Wall Transformer, 110VAC-26.7VAC, (used with NT2K10xx)	40.00	D	N/A	
S ➤	A0367601	Power Supply 16V (BLF/CGM)	40.00	D	N/A	
S ➤	A0367916	Power Supply - 48V DC	650.00	I	N/A	
S ➤	A0368534	8 Port Terminal Concentrator/FM (TC/FM) (RJ45)	950.00	H	N/A	
S ➤	A0368760	DC6250 250MB Back Up Tape	50.00	H	N/A	
S † ➤	A0369107	Sub-D Filter Connector (25 Conductor)	50.00	D	N/A	
S ➤	A0369788	UDS V.3225 Synchronous Modem	1,000.00	H	N/A	
S ➤	A0376171	Powell DEC Cable	45.00	H	N/A	
S #	A0376839	DEC 420 Terminal	MD		200.00	H
S ➤	A0376918	MVME332XTS 8-Channel Asynchronous I/O Card	3,000.00	D	420.00	H
S #	A0377097	M3000 Directory Archiver	MD		80.00	H
S ➤	A0377172	Transformer, 24V AC (M1250/DSS-9000)	50.00	D	N/A	
N #	A0377786	80MB Disk Drive	MD		650.00	H
S ➤	A0377957	LAN Transceiver	625.00	D	185.00	H
S	A0377992	Black Box ABCDE Switch	180.00	H	N/A	
S ➤	A0378220	Tape Drive Cleaning Kit	110.00	D	N/A	
S ➤	A0378252	Battery	60.00	I	N/A	
S ➤	A0378652	Null Modem Connector, Female/Male	35.00	D	N/A	
S ➤	A0378688	MVME147SB-1 Processor Card (M68030, 25Mhz, 16MB)	10,400.00	D	2,100.00	H
S ➤	A0379350	25 Pair Double Ended Cable	135.00	D	N/A	
S ➤	A0379351	25 Pair Single Ended Cable	135.00	D	N/A	
S ➤	A0379412	220V Power Cord	15.00	D	N/A	
S ➤	A0379431	OPS Protector Device	100.00	I	N/A	
S ➤	A0379589	Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A	25.00	H	N/A	
S ➤	A0379673	SCSI Terminator	50.00	D	N/A	
S #	A0380908	AT&T Connections Hardware Package	MD		1,250.00	H
S ➤	A0381016	Null Modem Connector, (Female/Female)	35.00	D	N/A	
S #	A0381458	Ventel 9600 Plus Modem	MD		250.00	H
S ➤	A0383333	Transceiver	560.00	H	N/A	
S #	A0383524	Rolm Connections Hardware Kit	MD		1,250.00	H
S ➤	A0383526	VT520 Video Terminal	650.00	H	210.00	H
S #	A0383534	NEC Connections Hardware Kit	MD		1,250.00	H
S ➤	A0385576	DB25F-DB9F Cable Adapter	69.00	D	N/A	
S ➤	A0386049	MVME167-34 Processor Card (M68040, 33Mhz, 32MB)	11,000.00	D	3,300.00	H
S ➤	A0386050	Keylock Software Security Device	450.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	A0386101	NCD X-Terminal (17 In. Color/8MB)	MD		1,400.00	H
S ➤	A0387583	Auto Dial Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387586	Hot Line Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387588	Display Queue Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387590	Display Agent Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387592	Agent Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387595	Waiting Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387596	Answer Agent Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387598	Position Busy Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387599	Message Indicator Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387603	Group Call Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387604	Emergency Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387606	Program Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387607	Supervisor Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387608	Charge Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387609	Group Pickup Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387610	Not Ready Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387611	DN Pickup Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387613	In-Calls Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387614	Observe Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387616	Night Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387624	Trace Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387629	Privacy Release Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387631	Park Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387634	Stored Number Redial Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387635	Last Number Redial Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387637	Display Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387638	Make Set Busy Key Cap Package (50/PK)	14.00	D	N/A	
S ➤	A0387639	Ring Again Key Cap Package (50/PK)	14.00	D	N/A	
S Δ	A0389770	Application Module NTP	125.00	H	N/A	
S ➤	A0390595	Hold Key Cap Package (15/PK)	14.00	D	N/A	
S ➤	A0397705	Release Key Cap Package (50/PK)	14.00	D	N/A	
S Δ	A0397852	Customer Controlled Routing User Guide	70.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	A0600069	Meridian IPE Application Module without Tape/Disk for Option 21-81	MD		1,750.00	H
S #	A0600181	MVME167-03 Processor Card (M68040, 25 Mhz, 16MByte)	MD		3,150.00	H
S #	A0600398	NCD X-Terminal (15 In. Mono/8MB)	MD		900.00	H
S #	A0600711	3270 Communications Controller	MD		600.00	H
S #	A0600712	X.25 Communications Controller	MD		600.00	H
S	A0601182	MVME712M Transition Card without built-in modem (for MVME167 and MVME177)	900.00	D	275.00	H
S ➤	A0601396	Modem Eliminator Male to Female	15.00	D	N/A	
S ➤	A0601397	Modem Eliminator Female to Female	15.00	D	N/A	
S ✓ ➤	A0601464	Modem Cable, 10 Ft. DB9 Female to DB25 Male	25.00	D	N/A	
B #	A0602257	300MB Disk Drive	MD		1,750.00	H
B #	A0603704	300MB Disk Drive	MD		1,750.00	H
S Δ	A0605411	600MB Data Cassette Tape	100.00	D	N/A	
S	A0609639	DEC Style Keyboard	350.00	D	N/A	
S	A0609641	Mouse	275.00	D	N/A	
S	A0615902	Literature Pack (M2006, M2008)	10.00	D	N/A	
S ➤	A0617011	240MB Hard Disk Drive Unit	3,200.00	D	N/A	
N Δ	A0618446	Winning With Application Sales: Meridian Call Center Sales Training Kit (with video)	43.75	H	N/A	
S ➤	A0619621	RJ45/RS232 Connector	15.00	D	N/A	
B ➤	A0620100	Replacement Battery (For NTAK75AA/AB)	260.00	H	N/A	
S ★	A0620530	Modem for SMDI Link in T1 Application	2,450.00	D	N/A	
S	A0621070	Serial-Parallel Converter for Printers	150.00	H	N/A	
N Δ	A0622715	Winning With Application Sales: Meridian Call Center Sales Training Kit (without video)	35.50	H	N/A	
S † ➤	A0622896	OIVR 2 x Hardware - Tape Drive (2.5GB)	945.00	H	N/A	
S ✓ ➤	A0627875	Cleaning Cartridge	115.00	D	N/A	
S ➤	A0630697	Magnus 2.5GB Data Cartridge	105.00	H	N/A	
S #	A0630704	300MB Disk Drive	MD		1,750.00	H
S ➤	A0632902	33 Ft. Plastic Fiber Cable (11E/11C)	160.00	D	N/A	
S ➤	A0633585	Tandberg Tape Drive Cleaning Kit	84.00	H	N/A	
S ➤	A0634101	2-Conductor Line Cord (25 Ft.) Satin, (M2000 Series and M3901)	10.00	D	N/A	
S #	A0634488	Fiber Remote Multi-IPE Interface - Single Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0634489	Fiber Remote Multi-IPE Interface - Single Mode (1-2 Superloops)	MD		3,000.00	H
S #	A0634490	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0634491	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	MD		3,000.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	A0634492	Fiber Remote Multi-IPE Interface - Redundant Option (Single Mode)	10,000.00	I	1,500.00	H
S ➤	A0634493	Fiber Remote Multi-IPE Interface - Redundant Option (Multi Mode)	10,000.00	I	1,200.00	H
S ➤	A0634494	Fiber Remote Multi-IPE Interface - Rack Mount Shelf Option	1,500.00	I	N/A	
S ➤	A0634495	Local Fiber Multi-IPE Interface Cable (30 Ft.)	300.00	D	N/A	
S ➤	A0634496	Remote FRMII Cable (30 ft.)	300.00	D	N/A	
S	A0636813	T1 Port Assembly (24 ports)	14,815.00	H	N/A	
S #	A0637905	Tandberg Tape Drive Unit - External	MD		525.00	H
S Δ	A0638483	Keyboard	60.00	H	N/A	
S ➤	A0638645	External Modem (14,400 bps, V.32 bis with V.42 bis)	370.00	H	N/A	
S ➤ Δ	A0639225	MRS Tower/Rack Disk Drive (1.05GB)	2,100.00	H	N/A	
S	A0639226	MRS/Tower or MRS/Rack Token Ring Controller	No charge		N/A	
S ➤ Δ	A0639229	AP Token Ring Lan Interface Kit	860.00	H	N/A	
S † ➤	A0639513	OIVR 2.X Hardware - Video DRAM Expansion (512KB to 1MB Expansion)	80.00	H	N/A	
S † ➤	A0639530	OIVR 2 x Hardware - 256KB L2 Async Cache for AP or MRS/ AP	125.00	H	N/A	
S † ➤	A0639569	OIVR 2 x Hardware - Expansion RAM - 8MB SIMM with Parity	445.00	H	N/A	
S ➤	A0639617	OIVR 2 x Hardware - Expansion RAM - 16MB SIMM with Parity	300.00	H	N/A	
S † ➤ Δ	A0640190	OIVR 2 x Hardware - MRS/Tower Spares Kit	10,000.00	H	N/A	
S † ➤ Δ	A0640192	OIVR 2 x Hardware - MRS/Rack DC Spares Kit	10,650.00	H	N/A	
S † ➤ Δ	A0640194	OIVR 2 x Hardware - MRS/Rack AC Spares Kit	10,000.00	H	N/A	
B #	A0645393	300MB Disk Drive	MD		1,000.00	H
S ✓ ➤	A0645811	Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A	30.00	H	N/A	
B ➤	A0646699	Key and Lock Master	70.00	H	N/A	
S † ➤	A0646715	OIVR 2 x Hardware - Drive LED Panel for AP or MRS/AP	45.00	H	N/A	
S ➤	A0646718	SYMPOSIUM Server, 1000t Peripheral Mounting Rail	30.00	H	N/A	
S ➤	A0646721	SYMPOSIUM Server, 1000t Foot	30.00	H	N/A	
S #	A0647283	SYMPOSIUM Server, 1000t Chassis Assembly, No Power Supply	MD		690.00	H
S † ➤	A0647317	OIVR 2 x Hardware - Fan (100cfm)	85.00	H	N/A	
S ✓ ➤	A0648372	4 Ft. Ethernet Cable, Category 5	10.00	D	N/A	
S ✓ ➤	A0648374	2 Ft. Ethernet Cable, Category 5	10.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	A0648375	7 Ft. Ethernet Cable, Category 5	10.00	D	N/A	
S ✓ ➤	A0648377	10 Ft. Ethernet Cable, Category 5	10.00	D	N/A	
S ✓ ➤	A0648378	15 Ft. Ethernet Cable, Category 5	10.00	D	N/A	
S ✓ ➤	A0648379	25 Ft. Ethernet Cable, Category 5	15.00	D	N/A	
S #	A0650990	24 Port T1 Board	MD		7,000.00	H
S † ➤	A0650996	OIVR 2 x Hardware - 12-port Loopstart Network Interface Module	2,965.00	H	N/A	
S † ➤	A0651032	OIVR 2 x Hardware - VRP Voice Recognition Card	5,370.00	H	N/A	
S † ➤	A0651035	OIVR 2 x Hardware - 12-port Voice Processing Card	5,185.00	H	N/A	
S † ➤	A0651036	OIVR 2 x Hardware - Serial I/O Controller for MRS	75.00	H	N/A	
S † ➤	A0651037	OIVR 2 x Hardware - SCSI Disk Controller for MRS	685.00	H	N/A	
S † ➤	A0651038	OIVR 2 x Hardware - 1.05GB Disk Drive (Tower)	1,575.00	H	N/A	
S † ➤	A0651039	OIVR 2 x Hardware - 1.05GB Disk Drive (Rack)	1,575.00	H	N/A	
S † ➤	A0651040	OIVR 2 x Hardware - Ethernet Controller for MRS	400.00	H	N/A	
S † ➤	A0651041	OIVR 2 x Hardware - Token Ring Controller for MRS	1,250.00	H	N/A	
S † ➤	A0651060	OIVR 2 x Hardware - CPU Module with no Memory	2,925.00	H	N/A	
S † ➤	A0651062	OIVR 2 x Hardware - CPU Module with 32MB Memory	7,410.00	H	N/A	
S † ➤	A0651064	OIVR 2 x Hardware - 450W Power Supply (Tower)	1,710.00	H	N/A	
S † ➤	A0651350	OIVR 2 x Hardware - Digiboard DTE 8 Port DB25 Male Cable	125.00	H	N/A	
B	A0651681	RT Clock Chip	35.00	H	N/A	
S ➤	A0652237	SYMPOSIUM Server, 1000t Drive Tray	30.00	H	N/A	
S † ➤	A0652239	OIVR 2 x Hardware - Floppy Drive, 3.5 In.	140.00	H	N/A	
S ➤	A0652365	Meridian M2616CT 700 mAh Battery, Gray (Standard)	40.00	D	N/A	
S ➤	A0652369	Meridian M2616CT 700 mAh Battery, Black (Standard)	40.00	D	N/A	
S † ➤	A0652633	OIVR 2 x Hardware - 2 Port Brooktrout Fax Card	4,200.00	H	N/A	
S † ➤	A0652634	OIVR 2 x Hardware - 4 Port Brooktrout Fax Card	8,400.00	H	N/A	
S † ➤	A0652635	OIVR 2 x Hardware - 8 Port Brooktrout Fax Card	16,800.00	H	N/A	
S † ➤	A0652638	OIVR 2 x Hardware - Apertus Communications Board (SDLC)	1,945.00	H	N/A	
S † ➤	A0652681	OIVR 2 x Hardware - 350W DC Power Supply (Rack)	2,000.00	H	N/A	
S † ➤	A0652687	OIVR 2 x Hardware - Redundant DC Power Supply for MRS/ Rack	2,000.00	H	N/A	
S † ➤	A0652688	OIVR 2 x Hardware - 350W AC Power Supply (Rack)	1,370.00	H	N/A	
S	A0654949	MRS to UPS Communications Cable	80.00	H	N/A	
S † ➤	A0656847	OIVR 2 x Hardware - Power Supply, 525W for AP or MRS/AP	925.00	H	N/A	
S † ➤	A0656874	OIVR 2 x Hardware - Cable, LCD for AP or MRS/AP	110.00	H	N/A	
S † ➤	A0657566	OIVR 2 x Hardware - 10 position Connector PEB Cable	60.00	H	N/A	
S † ➤	A0657728	OIVR 2 x Hardware - MRS to Terminal Cable (DB25F to DB25M)	25.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	A0657730	OIVR 2 x Hardware - Loopstart Interface Cable (DB25F to RJ23X)	245.00	H	N/A	
S † ➤	A0657777	OIVR 2 x Hardware - CPU Module Battery for MRS	40.00	H	N/A	
S † ➤	A0658110	OIVR 2 x Hardware - MRS/Tower Air Filter	25.00	H	N/A	
S ➤	A0658342	SYMPOSIUM Server, 1000t XXPress Memory Board with NO DRAM Included	850.00	H	595.00	H
S † ➤	A0658485	OIVR 2 x Hardware - 6 Ft. SCSI Cable for MRS	50.00	H	N/A	
S † ➤	A0658488	OIVR 2 x Hardware - Floppy Cable for MRS	45.00	H	N/A	
S ➤	A0658493	SCSI Termination, Active	40.00	D	N/A	
S † ➤	A0658655	OIVR 2 x Hardware - Keylock Adapter	125.00	H	N/A	
S † ➤	A0658690	OIVR 2 x Hardware - MRS/Rack Fan Assembly	245.00	H	N/A	
S ➤	A0658874	SYMPOSIUM Server, 1000t - with Chassis, Motherboard, and Floppy Drive Assembly	5,030.00	H	2,550.00	H
S † ➤	A0658957	OIVR 2 x Hardware - Floppy Disk Drive for MRS	140.00	H	N/A	
S ➤	A0659125	OIVR 2 x Hardware - Cabinet Rail Assembly	500.00	H	N/A	
S † ➤	A0659158	OIVR 2 x Hardware - Riser Board for AP or MRS/AP	100.00	H	N/A	
S #	A0660167	Meridian Private-Switch Emergency Response Unit	MD		3,000.00	H
S ➤	A0660168	Meridian Private-Switch Emergency Response Configuration Software	20.00	D	N/A	
S ➤ Δ	A0660169	Emergency Response Installation/User Guide	80.00	D	N/A	
S ➤	A0660170	Meridian Private-Switch Emergency Response Installation Kit	200.00	D	N/A	
S ➤	A0660171	Meridian Private-Switch Emergency Notification PC Software	4,700.00	D	N/A	
S Δ	A0660172	Emergency Notification Installation/User Guide	80.00	D	N/A	
S ➤	A0660173	Meridian Private-Switch Emergency Notification Installation Kit	200.00	D	N/A	
S ➤	A0660175	Meridian Private-Switch Emergency Response AC Power Supply	300.00	D	N/A	
S ➤	A0660524	SYMPOSIUM Server, 1000t XXPress 166 MHz P5 CPU with 512KB Sync Cache	6,270.00	H	4,390.00	H
S ➤	A0660538	Data Cartridge	50.00	H	N/A	
S ➤	A0665488	Meridian Private-Switch Emergency Response Unit	14,500.00	D	3,000.00	H
S	A0665642	Meridian Private-Switch Emergency Notification Event Monitor Software	1,000.00	D	N/A	
S ➤ Δ	A0666779	CPU Kit Including Installed Heatsink Adhesive and Clip for Pentium Processor	345.00	H	345.00	H
S ➤	A0669467	Meridian IPEE Application Module for Option 11	10,000.00	D	4,000.00	H
S ➤	A0669468	Meridian IPEE Application Module for Options 21-81C	10,000.00	D	4,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	A0670533	SYMPOSIUM Call Center Server 701t 32MB DIMM	700.00	H	N/A	
S ➤	A0670634	SYMPOSIUM Call Center Server 701t Assembly Peripheral Bay	30.00	H	N/A	
S ➤	A0670802	SYMPOSIUM Call Center Server 701t CPU 200Mz PPRO 256K L2 Cache	1,600.00	H	1,120.00	H
S ➤	A0671783	SYMPOSIUM Call Center Server, 701t Fan, 120mm plus Cardguide	200.00	H	N/A	
S ➤	A0672418	SYMPOSIUM Call Center Server 701t 275W Power Supply	500.00	H	350.00	H
S Δ	A0672913	MAT 5 User Guides Binder	15.00	H	N/A	
S ➤	A0672941	SYMPOSIUM Call Center Server 701t Front Panel and Cable (Power/Reset Switches + LED)	180.00	H	N/A	
S ➤	A0674453	33.6 KBPS External Data/Fax Modem	370.00	H	281.25	H
S ✓ ➤	A0676108	DC Power Supply for Rack Cabinet	1,025.00	D	N/A	
S ✓ ➤	A0677506	Dry Clean Cartridge	150.00	D	N/A	
S ✓ ➤	A0677508	13GB Data Cartridge	170.00	D	N/A	
S ✓	A0681164	Alarm Status Module	1,180.00	D	N/A	
S ✓ ➤	A0681326	Hot-Swap Fan Assembly	580.00	D	N/A	
S	A0681873	CallPilot Power Supply AC - Rack System	3,500.00	D	N/A	
S ➤	A0683319	SYMPOSIUM Call Center Server 701t SCSI Cable Kit	650.00	H	N/A	
S	A0683638	8MB PCMCIA Flash Card	600.00	H	N/A	
S ✓	A0683743	Video Card Adapter	310.00	D	N/A	
S ➤	A0684753	68 pin Wide SCSI Cable	160.00	H	N/A	
S	A0684761	IDE Cable to CD ROM 702t/1001rp	30.00	D	N/A	
S ✓	A0684822	F/F Wide to Narrow SCSI Cable Adapter	140.00	D	N/A	
S ✓	A0685305	Floppy Cable	35.00	D	N/A	
S	A0688017	MVME167-33 Processor Card (M68040, 33Mhz, 16MB)	10,500.00	D	3,150.00	H
S ➤	A0688664	ATA/MCA Transformer	40.00	D	N/A	
S ➤	A0696008	MVME177-005 Processor Card (M68060, 50 Mhz, 64MB)	10,000.00	D	N/A	
S ➤	A0720557	Handset Cord, Platinum, 12 Ft. (M3900 Series)	7.00	D	N/A	
S ➤	A0720558	Handset Cord, Charcoal, 12 Ft. (M3900 Series)	7.00	D	N/A	
S ➤	A0720559	Handset Cord, Platinum, 9 Ft. (Standard, M3900 Series)	4.00	D	N/A	
S ➤	A0720560	Handset Cord, Charcoal, 9 Ft. (Standard, M3900 Series)	4.00	D	N/A	
S ➤	A0720561	Handset Cord, Platinum, 6 Ft. (M3900 Series)	3.00	D	N/A	
S ➤	A0720562	Handset Cord, Charcoal, 6 Ft. (M3900 Series)	3.00	D	N/A	
S Δ	A0720936	701t 64 MB DIMM	620.00	H	N/A	
S Δ	A0720937	701t 128 MB DIMM	1,200.00	H	N/A	
S ➤	A0721792	SYMPOSIUM Call Center Server 1001t Base System	9,100.00	H	2,550.00	H
S ➤	A0721902	Tandberg Tape Drive Unit - External	2,800.00	D	525.00	H
S ➤	A0722048	SYMPOSIUM Call Center Server 1001t System Board	4,000.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	A0722070	SYMPOSIUM Call Center Server 1001t SCRAM Memory Board	350.00	H	N/A	
S ➤	A0722084	SYMPOSIUM Call Center Server 1001t SCSI Backplane Kit	650.00	H	N/A	
S ➤	A0722476	SYMPOSIUM Call Center Server Terminator Board	70.00	H	N/A	
S ➤	A0722762	SYMPOSIUM Call Center Server 1001t 300Mhz Processor	3,000.00	H	N/A	
S ✓	A0723663	48V DC 400W Load Sharing Hot Swap Power Supply	3,580.00	D	900.00	H
S ➤	A0723759	SYMPOSIUM Call Center Server 1001t Power Supply 360W	500.00	H	N/A	
S	A0724372	SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Bottom	410.00	H	N/A	
S	A0724373	SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Top	410.00	H	N/A	
S	A0724374	SYMPOSIUM Call Center Server 1001t Cable Narrow, SCSI	135.00	H	N/A	
S	A0724375	SYMPOSIUM Call Center Server 1001t Cable, IDE CD-ROM	135.00	H	N/A	
S ➤	A0725300	SYMPOSIUM Call Center Server 1001t 32MB SCRAM	600.00	H	N/A	
S	A0725342	Meridian 1 Attendant PC Software Tutorial	8.00	H	N/A	
S ✓ ➤	A0725949	DC Power Cable for PS400-48 Power Supply	160.00	D	N/A	
S ➤	A0726965	SYMPOSIUM Call Center Server 1001t CPU Retention Mechanism	30.00	H	N/A	
S	A0726966	SYMPOSIUM Call Center Server 1001t EPAC Blower Duct	555.00	H	N/A	
S ➤	A0727294	SYMPOSIUM Call Center Server 1001t Redundant Fan Kit	165.00	H	N/A	
S ➤	A0727295	SYMPOSIUM Call Center Server 1001t Blower	95.00	H	N/A	
S ➤	A0728440	SYMPOSIUM Call Center Server 1001t Side Cover	400.00	H	N/A	
S ➤	A0728441	SYMPOSIUM Call Center Server 1001t Top Cover	300.00	H	N/A	
B	A0728841	Citizen Printer	400.00	H	N/A	
S ✓	A0729069	M/M Wide-Nar SCSI Adapter	150.00	D	N/A	
S ➤	A0729362	Meridian M2616CT 700 mAh Battery, Ash (Standard)	40.00	D	N/A	
S ➤ Δ	A0730854	IPEE 1GB Hard Drive Repair Kit	725.00	H	N/A	
S ✓	A0731666	CallPilot Dongle Serial Adapter - Tower/Rack Systems	80.00	D	N/A	
S #	A0732456	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0732458	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	MD		3,000.00	H
S #	A0732527	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0732528	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	MD		3,000.00	H
S ➤ Δ	A0734765	Headstart - Verification Package	4,000.00	H	N/A	
S ➤ Δ	A0734767	Yearly Support for SYMPOSIUM TAPI Driver up to 32 Hours	2,000.00	H	N/A	
S ➤	A0735349	128 MB DIMM	2,100.00	D	N/A	
S ✓	A0738130	128MB DIMM	800.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	A0741558	Front Chassis Cover	80.00	H	N/A	
S ✓ Δ	A0741561	300W Power Supply	155.00	H	N/A	
S	A0741567	Fan Module Assembly	200.00	D	N/A	
S Δ	A0741570	Chassis Front Panel	35.00	H	N/A	
S Δ	A0741571	Fan Bracket	40.00	H	N/A	
S ✓	A0741572	Floppy Cable	35.00	D	N/A	
S Δ	A0741573	Peripheral Drive Rail	80.00	H	N/A	
S ✓	A0741574	702t OEM System With no Processor and no Memory	2,500.00	H	N/A	
S ✓ Δ	A0741576	Fan Assembly	10.00	H	N/A	
S Δ	A0741577	Front Panel Cable	28.00	H	N/A	
S Δ	A0741579	Chassis Side Access Cover	490.00	H	N/A	
S #	A0741582	702t Base System	MD		2,840.00	H
S Δ	A0741595	64MB SDRAM DIMM	620.00	H	N/A	
S ✓ ➤	A0744456	CallPilot 128 MB DIMM	1,090.00	D	N/A	
S Δ	A0744720	64 MB SIMM	620.00	H	N/A	
S ★	A0744727	128MB SDRAM	1,240.00	H	N/A	
S ➤	A0757981	FRMII System Monitor Isolator	550.00	D	N/A	
S ➤	A0757982	FRMII MMI/Modem Isolator	375.00	D	N/A	
S #	A0759609	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0759612	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	MD		3,000.00	H
S #	A0759618	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	MD		3,000.00	H
S #	A0759620	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	MD		3,000.00	H
S ✓ Δ	A0761148	702t CPU 450 MHz Pentium II	1,390.00	H	N/A	
S ➤	A0761993	FRMII Alarm Cable (32 Ft.)	170.00	D	N/A	
S	A0762506	AC/DC Power Converter	650.00	I	N/A	
S ✓	A0766163	CallPilot DSE Extender Cable - 100 Ft.	200.00	D	N/A	
S ✓ ➤	A0766182	Dual Pentium II CPU	20,000.00	D	N/A	
S ➤	A0766331	Maintenance Interface Cable	200.00	D	N/A	
S ✓ ➤	A0766997	Wide SCSI Terminator	55.00	D	N/A	
S ✓	A0769310	14 Foot, Shielded Ethernet Cable	25.00	D	N/A	
S ✓ ➤	A0769312	SCSI Adapter	50.00	D	N/A	
S	A0772567	Wide SCSI Cable	580.00	D	N/A	
S ➤	A0773054	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	15,000.00	I	3,000.00	H
S ➤	A0773055	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	10,000.00	I	3,000.00	H
S ➤	A0773056	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	15,000.00	I	3,000.00	H
S ➤	A0773059	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	10,000.00	I	3,000.00	H
S ➤ Δ	A0774466	Yearly Support for SYMPOSIUM TAPI Driver up to 40 Hours	2,500.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	A0774467	Yearly Support for SYMPOSIUM TAPI Driver up to 45 Hours	3,000.00	H	N/A	
S ➤ Δ	A0774468	Yearly Support for SYMPOSIUM TAPI Driver up to 50 Hours	3,500.00	H	N/A	
S ➤ Δ	A0774469	Yearly Support for SYMPOSIUM TAPI Driver up to 100 Hours	7,000.00	H	N/A	
S ➤ Δ	A0774470	Yearly Support for SYMPOSIUM TAPI Driver up to 200 Hours	14,000.00	H	N/A	
S ➤ Δ	A0774471	Headstart - Switch Configuration Package	1,200.00	H	N/A	
S ➤ Δ	A0774472	Headstart Pre-Installation Package	4,000.00	H	N/A	
S	A0774861	32 MB DIMM	630.00	H	N/A	
S ✓ ➤	A0780247	Data Cartridge	85.00	D	N/A	
S #	A0786611	CP PII Call Processor Card (128MB Memory)	MD		2,000.00	H
S ★	A0788107	T1 2 Pair Cable with RJ48 Connector	80.00	D	N/A	
S ✓ ➤	A0788129	Shielded 9-Drop Wide SCSI Cable	320.00	D	N/A	
S ✓	A0788131	9 Drop SC Bus Cable	30.00	D	N/A	
S ★	A0788198	VTG Adapter Cable	170.00	D	N/A	
S	A0797692	SYMPOSIUM Call Center Server 1003t System Board PCA	3,050.00	H	2,156.50	H
S	A0797705	SYMPOSIUM Call Center Server 1003t Input/Output PCA	1,650.00	H	1,305.25	H
S	A0797722	SYMPOSIUM Call Center Server 1003t Voltage Regulator Module	118.00	H	N/A	
S	A0797724	SYMPOSIUM Call Center Server 1003t Memory PCA	165.00	H	N/A	
S	A0797727	SYMPOSIUM Call Center Server 1003t NetServer Hot-Swap Ultra2 Internal Storage Cage	690.00	H	N/A	
S	A0797938	SYMPOSIUM Call Center Server 1003t 256MB 50ns EDO DIMM Kit (4x64MB)	1,650.00	H	N/A	
S ✓	A0797941	Rack Rails	340.00	D	N/A	
S	A0797948	SYMPOSIUM Call Center Server 1003t Fan Assembly for Input/ Output, Retainer	76.00	H	N/A	
S	A0797950	SYMPOSIUM Call Center Server 1003t Fan Assembly for System Board	52.00	H	N/A	
S ★	A0797971	Pentium III Xeon 500 MHz, 512KB ECC L2 Cache	3,300.00	H	N/A	
S ★	A0797984	9GB Hot-Swap Ultra2 SCSI LP Hard Disk Drive	3,200.00	H	2,099.75	H
S	A0798087	SYMPOSIUM Call Center Server 1003t PCI Ethernet Adapter	135.00	H	N/A	
S	A0798092	SYMPOSIUM Call Center Server 1003t Wide SCSI Host Adapter Board	165.00	H	N/A	
S ★	A0798117	Non-Hot-Swap Tray	85.00	H	N/A	
S ★	A0798129	SYMPOSIUM Call Center Server Power Supply Module, 300W	400.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	A0798155	SYMPOSIUM Call Center Server 1003t Internal SCSI Input/ Output Cable	121.00	H	N/A	
S	A0798177	SYMPOSIUM Call Center Server 1003t Fan Assembly for CPU	52.00	H	N/A	
S	A0798258	SYMPOSIUM Call Center Server 1003t NetServer Keyboard	205.00	H	N/A	
S	A0798259	SYMPOSIUM Call Center Server 1003t 1.44MB Floppy Disk Drive	78.00	H	N/A	
S	A0798260	SYMPOSIUM Call Center Server 1003t Mini-DIN Mouse	65.00	H	N/A	
S	A0800927	SYMPOSIUM Call Center Server 1003t 32x MAX EIDE CD-ROM Drive	203.00	H	N/A	
S	A0801312	SYMPOSIUM Call Center Server 1003t Processor Terminator	52.00	H	N/A	
S	A0802022	128 MB SDRAM	2,300.00	D	N/A	
S	A0803022	128 MB SDRAM	3,400.00	D	N/A	
S ✓	A0805092	Pentium III SBC 500MHz CPU	2,600.00	D	N/A	
S ✓ ➤	A0805434	Power Supply AC - 500 Watts	1,750.00	D	N/A	
S ✓	A0806019	IDE Cable to CD ROM	180.00	D	N/A	
S ➤	A0810496	CP PII Call Processor Card (128MB Memory)	14,500.00	I	2,000.00	H
S ➤	A0811762	Fiber Network Fabric Adapter Panel	100.00	D	N/A	
S ★	A0813446	256 MB SDRAM	2,050.00	D	N/A	
S ➤	AS0071	Meridian MAX-SNN Spares Kit	6,000.00	D	N/A	
S ➤	AS0073	Meridian MAX Release 7 Capacity Configurator Tool	No charge		N/A	
S ➤	AS0074	Meridian MAX-SNNE Spares Kit	6,000.00	D	N/A	
S ➤	AS0075	Meridian MAX Release 8 Capacity Configurator Tool	No charge		N/A	
S † ➤	AS1006A	Network Group Package AC	20,000.00	I	N/A	
S † ➤	AS1006D	Network Group Package DC	20,000.00	I	N/A	
S ➤	AS1007A	Network Module Package AC	6,000.00	I	N/A	
S ➤	AS1007D	Network Module Package DC	6,000.00	I	N/A	
S § ➤	AS1013	Special Console/Line Card Package	5,000.00	I	N/A	
S ➤	AS1017D	Customer Provided DC Power Assembly	2,750.00	H	N/A	
S ➤	AS1019	Network Cable Package - 2nd Group	290.00	D	N/A	
S ➤	AS1020	Network Cable Package - 3rd Group	325.00	D	N/A	
S ➤	AS1021	Network Cable Package - 4th Group	340.00	D	N/A	
S ➤	AS1022	Network Cable Package - 5th Group	350.00	D	N/A	
S ➤	AS103003	Centralized Answering Position Packages (M2616), Black	830.00	D	N/A	
S ➤	AS103035	Centralized Answering Position Packages (M2616), Ash	830.00	D	N/A	
S ➤	AS103093	Centralized Answering Position Packages (M2616), Gray	830.00	D	N/A	
S ➤	AS1039A	Option 81/81C Network Group Assembly AC	20,000.00	I	N/A	
S ➤	AS1039D	Option 81/81C Network Group Assembly DC	20,000.00	I	N/A	
S † ➤	AS1040	Option 81 Network Cable Package, 2nd Group	700.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	AS1041	Option 81 Network Cable Package, 3rd Group	750.00	I	N/A	
S † ➤	AS1042	Option 81 Network Cable Package, 4th Group	780.00	I	N/A	
S † ➤	AS1043	Option 81 Network Cable Package, 5th Group	800.00	I	N/A	
S ➤	AS1050	Host Enhanced Voice Processing Cable Kit	250.00	D	N/A	
S ➤	AS1051	4 Port SDI Assembly	3,100.00	I	N/A	
S ➤	AS1052	4 Port SDI Paddle Board Assembly	3,400.00	I	N/A	
S ➤	AS1054A	Intelligent Peripheral Equipment Module Package AC	12,000.00	I	N/A	
S ➤	AS1054D	Intelligent Peripheral Equipment Module Package DC	12,000.00	I	N/A	
S ➤	AS1061	PRI Package	4,700.00	I	N/A	
S † ➤	AS1062	PRI Package (2nd Tier)	4,875.00	I	N/A	
S † ➤	AS1063	PRI Package (Cabinet)	4,875.00	I	N/A	
S § ➤	AS1066	Special Meridian 1 Attendant PC with Digital Line Card	6,600.00	I	N/A	
S ➤	AS1073	SDI/DCH Package	3,100.00	I	N/A	
S ✓ † ➤	AS1074	DTI/PRI Package	4,160.00	H	N/A	
S ➤	AS1078	Network Group Expansion Interface Package	2,650.00	D	N/A	
S ➤	AS1079	MSDL Intercabinet Cable Kit	450.00	D	N/A	
S ➤	AS1081A	Pedestal/Top Cap Package AC	7,000.00	I	N/A	
S ➤	AS1081D	Pedestal/Top Cap Package DC	7,000.00	I	N/A	
S § ➤ Δ	AS1082	Meridian Modular Telephone User Guide (Package of 15 P0902627)	No charge		N/A	
S § ➤ Δ	AS1083	M2216 ACD Telephone User Guide (Package of 15 P0902629)	No charge		N/A	
S § ➤ Δ	AS1084	M2317 Telephone User Guide (15/PK)	No charge		N/A	
S ➤	AS1087D	Rectifier Rack Assembly	2,150.00	H	N/A	
S ➤	AS1088D	Rectifier Rack Assembly	4,500.00	H	N/A	
S ➤	AS1089	Fiber Remote Local Package	8,750.00	I	N/A	
S ➤	AS1090A	Fiber Remote Main Wall Mount Remote Package AC	11,250.00	I	N/A	
S ➤	AS1090D	Fiber Remote Main Wall Mount Remote Package DC	11,250.00	I	N/A	
S ➤	AS1091A	Expansion Wall Mount Remote Package AC	2,800.00	I	N/A	
S ➤	AS1091D	Expansion Wall Mount Remote Package DC	2,800.00	I	N/A	
S ➤	AS1092A	Fiber Remote Floor Standing Remote Package AC	15,250.00	I	N/A	
S ➤	AS1092D	Fiber Remote Floor Standing Remote Package DC	15,250.00	I	N/A	
S ➤	AS1093	Carrier Remote Local Package	8,750.00	I	N/A	
S ➤	AS1094A	Carrier Remote Main Wall Mount Remote Package AC	11,250.00	I	N/A	
S ➤	AS1094D	Carrier Remote Main Wall Mount Remote Package DC	11,250.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	AS1095A	Carrier Remote Floor Standing Remote Package AC	15,250.00	I	N/A	
S ➤	AS1095D	Carrier Remote Floor Standing Remote Package DC	15,250.00	I	N/A	
S ➤	AS1130	Option 51C/61C/81 CE Spares Package	18,000.00	I	N/A	
S ➤	AS1132	Option 51C/61C/81C System Spares Package	36,000.00	I	N/A	
S ➤	AS1140	Local fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	13,500.00	I	N/A	
S ➤	AS1141	Remote Fiber Multi-IPE Assembly - Single Mode (1-2 Superloops)	10,500.00	I	N/A	
S ➤	AS1142	Local Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	13,500.00	I	N/A	
S ➤	AS1143	Remote Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops)	10,500.00	I	N/A	
S ➤	AS1144	Local Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	22,500.00	I	N/A	
S ➤	AS1145	Remote Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops)	15,500.00	I	N/A	
S ➤	AS1146	Local Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	22,500.00	I	N/A	
S ➤	AS1147	Remote Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops)	15,500.00	I	N/A	
S ➤	AS1171	Option 11E 1st Expansion Cabinet Package AC	4,000.00	I	N/A	
S ➤	AS1172	Option 11E 1st Expansion Cabinet Package DC	4,000.00	I	N/A	
S ➤	AS1173	Option 11E 2nd Expansion Cabinet Package AC	5,335.00	I	N/A	
S ➤	AS1174	Option 11E 2nd Expansion Cabinet Package DC	5,335.00	I	N/A	
S ➤	AS1175	Fiber Interface Kit	2,200.00	I	N/A	
S § ➤	AS1182	Pre-Printed Feature Key Cap Package (1 PK of 11 Key Caps, A0637619)	No charge		N/A	
S ➤	AS1200D	MFA150 Modular Power Assembly - Single Shelf	3,200.00	H	N/A	
S ➤	AS1201D	MFA150 Modular Power Assembly - Dual Shelf	7,400.00	H	N/A	
S ➤	AS1204D	50 Amp Rectifier Expansion Package	5,000.00	H	N/A	
S ➤	AS1208A	Power Supply Spares Package AC	6,000.00	I	N/A	
S ➤	AS1208D	Power Supply Spares Package DC	6,000.00	I	N/A	
S ➤	AS1209D	System 600/48 Modular Power Package - Main Cabinet	12,000.00	H	N/A	
S ➤	AS1210D	System 600/48 Modular Power Package - Supplemental Cabinet	8,000.00	H	N/A	
S ➤	AS1240	Option 81C Network Cable Package, 2nd Group	700.00	I	N/A	
S ➤	AS1241	Option 81C Network Cable Package, 3rd Group	750.00	I	N/A	
S ➤	AS1242	Option 81C Network Cable Package, 4th Group	780.00	I	N/A	
S ➤	AS1243	Option 81C Network Cable Package, 5th Group	800.00	I	N/A	
S ➤	AS1250	Option 81C Core/Network Group Kit	8,500.00	I	N/A	
B ➤	AS1460	Line-side T1 Interface Assembly (21-81)	5,400.00	I	N/A	
B ➤	AS1461	Line-side T1 Interface Assembly (11)	5,400.00	I	N/A	
S ➤	AS1500A	Meridian Private-Switch Emergency Response Unit-AC Version	15,000.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	AS1501	Meridian Private-Switch Emergency Notification PC Software	5,000.00	D	N/A	
S ➤	AS7010	Meridian Mail Modular HVS Package	800.00	D	N/A	
S ➤	AS7011	DEC Terminal Package	700.00	H	N/A	
S ➤	AS7012	Meridian Mail Networking Modem Package	550.00	H	N/A	
S ➤	AS7015	Meridian Mail Modular RSM Package	2,100.00	D	N/A	
S ➤	AS7021A	Meridian Mail Modular EC Node Expansion 1st Position Package AC	12,500.00	D	N/A	
S ➤	AS7021D	Meridian Mail Modular EC Node Expansion 1st Position Package DC	12,500.00	D	N/A	
S ➤	AS7023A	Meridian Mail Modular EC Node Expansion 2nd Position Package AC	12,500.00	D	N/A	
S ➤	AS7023D	Meridian Mail Modular EC Node Expansion 2nd Position Package DC	12,500.00	D	N/A	
S ➤	AS7025	Meridian Mail Modular EC Node Expansion 3rd Position Package	10,500.00	D	N/A	
S ➤	AS7029	Meridian Mail 2GB Disk Shadowing Prime Node Package	5,000.00	D	N/A	
S ➤	AS7031A	Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package AC	8,500.00	D	N/A	
S ➤	AS7031D	Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package DC	8,500.00	D	N/A	
S ➤	AS7033A	Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package AC	4,500.00	D	N/A	
S ➤	AS7033D	Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package DC	4,500.00	D	N/A	
S ➤	AS7037A	Meridian Mail 2GB Disk Shadowing Voice Node Package AC	4,500.00	D	N/A	
S ➤	AS7037D	Meridian Mail 2GB Disk Shadowing Voice Node Package DC	4,500.00	D	N/A	
S ➤	AS7043A	Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package AC	11,250.00	D	N/A	
S ➤	AS7043D	Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	AS7044A	Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package AC	12,250.00	D	N/A	
S ➤	AS7044D	Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package DC	12,250.00	D	N/A	
S ➤	AS7045A	Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package AC	12,250.00	D	N/A	
S ➤	AS7045D	Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package DC	12,250.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	AS7046A	Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package AC	10,250.00	D	N/A	
S ➤	AS7046D	Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package DC	10,250.00	D	N/A	
S ➤	AS7047D	Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	AS7048D	Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	AS7049D	Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC	12,250.00	D	N/A	
S ➤	AS7050D	Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC	15,250.00	D	N/A	
S ➤	AS7070D	Meridian Mail Modular GP Spares Package	10,000.00	D	N/A	
S ➤	AS7080	Meridian Mail Modular Option EC/EC11 Spares Package 1	8,000.00	D	N/A	
S ➤	AS7081	Meridian Mail Modular Option EC/EC11 Spares Package 2	13,000.00	D	N/A	
S ➤	AS7082	Meridian Mail Alternative Remote Access Package	2,300.00	D	N/A	
S ➤	AS7083	Meridian Mail EC11 Spares Package	8,500.00	D	N/A	
S ➤	AS7100	Meridian Mail EC11 1 to 2 Node Expansion Package	12,200.00	D	N/A	
S ➤	AS7101	HVS Hardware Package	1,300.00	D	N/A	
S ➤	AS7108	4 Port Full Service Voice Processing Package, EC/EC11	14,000.00	D	N/A	
S ➤	AS7109	4 Port Basic Service Voice Processing Package, EC/EC11	4,800.00	D	N/A	
S ➤	AS7110	8 Port Full Service Voice Processing Package, EC/EC11	27,000.00	D	N/A	
S ➤	AS7111	8 Port Basic Service Voice Processing Package, EC/EC11	8,600.00	D	N/A	
S ➤	AS7112	4 Port Full Service Voice Processing Package, Modular GP	14,000.00	D	N/A	
S ➤	AS7113	4 Port Basic Service Voice Processing Package, Modular GP	4,800.00	D	N/A	
S ➤	AS7114	4 Port Full Service Voice Processing Package, Options	14,000.00	D	N/A	
S ➤	AS7115	4 Port Basic Service Voice Processing Package, Options	4,800.00	D	N/A	
S † ➤	AS7116	4 to 8 Port Full Service Voice Processing Expansion Package, EC/EC11	15,000.00	D	N/A	
S † ➤	AS7117	4 to 8 Port Basic Service Voice Processing Expansion Package, EC/EC 11	5,800.00	D	N/A	
S ➤	AS7120	2 Port Full Service Voice Processing Package, Card Option	4,500.00	D	N/A	
S ➤	AS7121	2 Port Basic Service Voice Processing Package, Card Option	1,400.00	D	N/A	
S ➤	AS7122	6-8 Port Full Service Voice Processing Expansion Package, Card Option	4,500.00	D	N/A	
S ➤	AS7123	6-8 Port Basic Service Voice Processing Expansion Package, Card Option	1,400.00	D	N/A	
S ➤	AS7200	Dual Port DTI/PRI Package	12,000.00	I	N/A	
S ➤	AS7201	Dual Port DTI/PRI Package (Cabinet)	12,400.00	I	N/A	
S ➤	AS7202	Dual Port DTI/PRI Package (ST, STE, RT)	12,100.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	AS7505	Meridian MAX-SEE Spares Kit	6,400.00	D	N/A	
S ➤	AS7506	ACD-MAX/NAC to Meridian MAX-IPEE/NAC 2 Data Conversion Kit	2,800.00	D	N/A	
S ➤	AS7512	Meridian MAX Option 1 to Option 2 Expansion Package	3,000.00	D	N/A	
S ➤	AS7534	Meridian MAX Option 3 to Option 4 Expansion Package	6,000.00	D	N/A	
S ➤	AS8600	17 In. Color X-Terminal with DEC Style Keyboard	4,600.00	H	N/A	
S #	B0202061	Rectifier J-2357D-1, List 3 for the J-2412A Cabinet (B0210372-B0205582)	MD		2,000.00	H
S #	B0210365	J2412AA-1 Control Panel for J2412A-1 Cabinet	MD		825.00	H
S #	C0046977	HP7970 CDR Tape Unit	MD		480.00	H
S #	C0046980	Static Inverter (CDR)	MD		480.00	H
S # Δ	C2502246	DTS/EXP Power Supply (CS034)	MD		95.00	H
S # Δ	C2502248	DTS Motherboard (CS022)	MD		430.00	H
S # Δ	C2502249	DTS I/O Board Kit (CS024)	MD		160.00	H
S # Δ	C2502252	BNS/DTS Tape Controller Kit (CS013)	MD		185.00	H
S # Δ	C2502253	BNS/DTS Disk Controller Kit (CS018)	MD		310.00	H
S # Δ	C2502255	BNS Power Supply Kit (CS009)	MD		480.00	H
S # Δ	C2502258	BNS Memory Kit (4MB) (CS036)	MD		545.00	H
S # Δ	C2502263	BNS CPU Board Kit (CS015)	MD		375.00	H
S # Δ	C2502265	BNS Backplane Kit (20 Lines)	MD		65.00	H
S # Δ	C2502266	BNS Backplane Kit (16 Lines) (CS001)	MD		55.00	H
S # Δ	C2502271	43MB Kit (CS019)	MD		850.00	H
S # Δ	C2502273	BNS Tape Drive Kit (Full Height) (CS012)	MD		335.00	H
S # Δ	C2502274	DTS Tape Drive Kit (Half Height) (CS030)	MD		335.00	H
S # Δ	C2502491	BNS Front Console Assembly (CS081)	MD		55.00	H
S # Δ	C2502492	EXP Power Load Board Kit (CS046)	MD		20.00	H
S # Δ	C2502493	BNS DC Distribution Board (CS080)	MD		45.00	H
S # Δ	C2502499	DTS 146MB SCSI Disk (CS042)	MD		960.00	H
S # Δ	C2502500	DTS 80MB SCSI Disk (CS041)	MD		480.00	H
S # Δ	C2502501	DTS 52MB SCSI Disk (CS040)	MD		480.00	H
S #	C2502503	Panasonic KX-P1180 Printer	MD		200.00	H
S ➤	E1201A	Column Expansion Package AC	7,000.00	I	N/A	
S ➤	E1201D	Column Expansion Package DC	7,000.00	I	N/A	
S Δ	H008	Customer Controlled Routing Call Scripting Flowcharts Job Aid	95.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	H013	Meridian Mail Modular Option Enhanced Capacity (EC) Installation Photo Guide	350.00	H	N/A	
S Δ	H014	Meridian Mail Modular Option GP Installation Photo Guide	325.00	H	N/A	
S Δ	H015	Meridian Mail Release 12 Difference Guide	175.00	H	N/A	
S Δ	H021	Meridian Mail Train the Trainer	125.00	H	N/A	
S Δ	H022	Introduction to Meridian Mail Presentation	125.00	H	N/A	
S #	MVC00410	Data Modem GDC103A3	MD		140.00	H
S #	MVC01243	Data Modem (GDC103JM)	MD		140.00	H
S † ➤	MVC01561	Connector Hardware Package (50 Conductor)	5.00	D	N/A	
S † ➤	MVC01562	Connector Hardware Package (25 Conductor)	10.00	D	N/A	
S #	MVC02400	600MB Hard Disk	MD		5,000.00	H
S ➤	NT0961AA	Meridian ITG 2.0 Pentium 24 Port Card	6,500.00	D	2,000.00	H
S ➤	NT0962AA	Meridian ITG 2.0 486 Software Upgrade PCMCIA Card	850.00	H	N/A	
S ➤	NT0963AA	Meridian ITG 2.0 Pentium Software Upgrade PCMCIA Card	850.00	H	N/A	
S ➤	NT0C09EA03	Legacy Handset, Black (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D	N/A	
S ➤	NT0C09EA35	Legacy Handset, Ash (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D	N/A	
S ➤	NT0C09EA93	Legacy Handset, Gray (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S)	20.00	D	N/A	
S ➤	NT0C09EL-93	Legacy Handset, Gray (NT2K & NT9K Models M2006, M2008, M2616, M2216 ACD-1)	20.00	D	N/A	
S ➤	NT0C09EL03	Legacy Handset, Black (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)	20.00	D	N/A	
S ➤	NT0C09EL35	Legacy Handset, Ash (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1)	20.00	D	N/A	
S #	NT0R03AA	Transport Terminator	MD		75.00	H
S #	NT0R04AA	Tone Detector	MD		525.00	H
S #	NT0R08AA	Memory 2M	MD		525.00	H
S #	NT0R09AA	Processor 68000	MD		525.00	H
S #	NT0R12AA	Synchronous Data Formatter	MD		525.00	H
S #	NT0R20AA	Transport Repeater	MD		525.00	H
S #	NT0R24AA	Transport Controller	MD		525.00	H
S #	NT0R26AA	DS-1 Assembly	MD		525.00	H
S #	NT0R27AA	Voice Compressor	MD		2,000.00	H
S # Δ	NT0R28AA	LANlink Interface Card	MD		675.00	H
S # Δ	NT0R28AB	LANLink Assembly (NT0R23AB, NT0R25AB)	MD		675.00	H
S # Δ	NT0R28AC	LanLink Assembly (NT0R23AB, NT0R25AB)	MD		675.00	H
S #	NT0R30AA	MASI Assembly	MD		300.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT0R50AA	Power Monitor PCBA	MD		90.00	H
S #	NT0R52AA	Digital Power Unit	MD		190.00	H
S #	NT0R53AA	Disk/Tape Power Unit	MD		190.00	H
S # Δ	NT0R60AA	MacIntosh II Interface Card and Cable	MD		80.00	H
S #	NT0R67AA	InfoLink Interface	MD		150.00	H
S ➤	NT0R71AA	-48volt Rectifier	2,500.00	H	750.00	H
S ➤	NT0R72AA	-52volt Rectifier	2,100.00	H	630.00	H
S ➤	NT0X21AV	System 600/48 & MPP 600 Seismic Anchor	50.00	H	N/A	
S Δ	NT1344AA	Teleset Guide Package - Latin American Spanish	280.00	H	N/A	
S	NT1F04GA66	Shoulder Rest, Platinum (M3900 Series)	16.00	D	No charge	H
S	NT1F04GA70	Shoulder Rest, Charcoal (M3900 Series)	16.00	D	No charge	H
S #	NT1F05AA35	Meridian M2009 Digital Telephone, Ash	MD		65.00	H
S #	NT1F05AA93	Meridian M2009 Digital Telephone, Gray	MD		65.00	H
S #	NT1F05AB03	Meridian M2009 Digital Telephone, Black	MD		65.00	H
S #	NT1F05AB35	Meridian M2009 Digital Telephone, Ash	MD		65.00	H
S #	NT1F05AB93	Meridian M2009 Digital Telephone, Gray	MD		65.00	H
S #	NT1F05AD03	Meridian M2009 Digital Telephone, Black	MD		65.00	H
S #	NT1F05AD35	Meridian M2009 Digital Telephone, Ash	MD		65.00	H
S #	NT1F05AD93	Meridian M2009 Digital Telephone, Gray	MD		65.00	H
S #	NT1F05AE03	Meridian M2009 Digital Telephone, Black	MD		65.00	H
S #	NT1F05AE35	Meridian M2009 Digital Telephone, Ash	MD		65.00	H
S #	NT1F05AE93	Meridian M2009 Digital Telephone, Gray	MD		65.00	H
S #	NT1F05BA35	Meridian M2009 Digital Telephone with Data, Ash	MD		145.00	H
S #	NT1F05BA93	Meridian M2009 Digital Telephone with Data, Gray	MD		145.00	H
S #	NT1F05BB03	Meridian M2009 Digital Telephone with Data, Black	MD		145.00	H
S #	NT1F05BB35	Meridian M2009 Digital Telephone with Data, Ash	MD		145.00	H
S #	NT1F05BB93	Meridian M2009 Digital Telephone with Data, Gray	MD		145.00	H
S #	NT1F05MB03	Meridian M2009 Digital Telephone with Data, Black	MD		145.00	H
S #	NT1F05MB35	Meridian M2009 Digital Telephone with Data, Ash	MD		145.00	H
S #	NT1F05MB93	Meridian M2009 Digital Telephone with Date, Gray	MD		145.00	H
S #	NT1F05MD03	Meridian M2009 Digital Telephone with Data, Black	MD		145.00	H
S #	NT1F05MD35	Meridian M2009 Digital Telephone with Data, Ash	MD		145.00	H
S #	NT1F05MD93	Meridian M2009 Digital Telephone with Data, Gray	MD		145.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT1F05ME03	Meridian M2009 Digital Telephone with Data, Black	MD		145.00	H
S #	NT1F05ME35	Meridian M2009 Digital Telephone with Data, Ash	MD		145.00	H
S #	NT1F05ME93	Meridian M2009 Digital Telephone with Data, Gray	MD		145.00	H
S #	NT1F06AA35	Meridian M2112 Digital Telephone, Ash	MD		90.00	H
S #	NT1F06AA93	Meridian M2112 Digital Telephone, Gray	MD		90.00	H
S #	NT1F06AB03	Meridian M2112 Digital Telephone, Black	MD		90.00	H
S #	NT1F06AB35	Meridian M2112 Digital Telephone, Ash	MD		90.00	H
S #	NT1F06AB93	Meridian M2112 Digital Telephone, Gray	MD		90.00	H
S #	NT1F06AE03	Meridian M2112 Digital Telephone, Black	MD		90.00	H
S #	NT1F06AE35	Meridian M2112 Digital Telephone, Ash	MD		90.00	H
S #	NT1F06AE93	Meridian M2112 Digital Telephone, Gray	MD		90.00	H
S #	NT1F06AF03	Meridian M2112 Digital Telephone, Black	MD		90.00	H
S #	NT1F06AF35	Meridian M2112 Digital Telephone, Ash	MD		90.00	H
S #	NT1F06AF93	Meridian M2112 Digital Telephone, Gray	MD		90.00	H
S #	NT1F06BA35	Meridian M2112 Digital Telephone with Data, Ash	MD		170.00	H
S #	NT1F06BA93	Meridian M2112 Digital Telephone with Data, Gray	MD		170.00	H
S #	NT1F06BB03	Meridian M2112 Digital Telephone with Data, Black	MD		170.00	H
S #	NT1F06BB35	Meridian M2112 Digital Telephone with Data, Ash	MD		170.00	H
S #	NT1F06BB93	Meridian M2112 Digital Telephone with Data, Gray	MD		170.00	H
S #	NT1F06MB03	Meridian M2112 Digital Telephone with Data, Black	MD		170.00	H
S #	NT1F06MB35	Meridian M2112 Digital Telephone with Data, Ash	MD		170.00	H
S #	NT1F06MB93	Meridian M2112 Digital Telephone with Data, Gray	MD		170.00	H
S #	NT1F06ME03	Meridian M2112 Digital Telephone with Data, Black	MD		170.00	H
S #	NT1F06ME35	Meridian M2112 Digital Telephone with Data, Ash	MD		170.00	H
S #	NT1F06ME93	Meridian M2112 Digital Telephone with Data, Gray	MD		170.00	H
S #	NT1F06MF03	Meridian M2112 Digital Telephone with Data, Black	MD		170.00	H
S #	NT1F06MF35	Meridian M2112 Digital Telephone with Data, Ash	MD		170.00	H
S #	NT1F06MF93	Meridian M2112 Digital Telephone with Data, Gray	MD		170.00	H
S #	NT1F07AA03	Meridian M2018 Digital Telephone, Black	MD		115.00	H
S #	NT1F07AA35	Meridian M2018 Digital Telephone, Ash	MD		115.00	H
S #	NT1F07AA93	Meridian M2018 Digital Telephone, Gray	MD		115.00	H
S #	NT1F07AB35	Meridian M2018S Secure Telephone	MD		320.00	H
S #	NT1F07AC03	Meridian M2018 Digital Telephone, Black	MD		115.00	H
S #	NT1F07AC35	Meridian M2018 Digital Telephone, Ash	MD		115.00	H
S #	NT1F07AC93	Meridian M2018 Digital Telephone, Gray	MD		115.00	H
S #	NT1F07BA03	Meridian M2018 Digital Telephone with Data, Black	MD		195.00	H
S #	NT1F07BA35	Meridian M2018 Digital Telephone with Data, Ash	MD		195.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT1F07BA93	Meridian M2018 Digital Telephone with Data, Gray	MD		195.00	H
S #	NT1F07BB35	Meridian M2018S Secure Telephone with Data, Ash	MD		400.00	H
S #	NT1F07MA03	Meridian M2018 Digital Telephone with Data, Black	MD		195.00	H
S #	NT1F07MA35	Meridian M2018 Digital Telephone with Data, Ash	MD		195.00	H
S #	NT1F07MA93	Meridian M2018 Digital Telephone with Data, Gray	MD		195.00	H
S #	NT1F07MC03	Meridian M2018 Digital Telephone with Data, Black	MD		195.00	H
S #	NT1F07MC35	Meridian M2018 Digital Telephone with Data, Ash	MD		195.00	H
S #	NT1F07MC93	Meridian M2018 Digital Telephone with Data, Gray	MD		195.00	H
S #	NT1F09AA	Asynchronous Data Option (M2009, M2112, M2018, M2317)	MD		120.00	H
S ➤	NT1F09AC	Asynchronous Data Option (M2009, M2112, M2018, M2317)	300.00	D	120.00	H
S #	NT1F10AA	Meridian M3000 Asynchronous Data Option	MD		120.00	H
S #	NT1F10AB	Meridian M3000 Asynchronous Data Option	MD		120.00	H
S #	NT1F11AA03	Meridian M3000 Touchphone, Black	MD		400.00	H
S #	NT1F11AB03	Meridian M3000 Touchphone, Black	MD		400.00	H
S #	NT1F11AD03	Meridian M3000 Touchphone, Black	MD		400.00	H
B #	NT1F11AK03	Meridian M3000 Touchphone, Black	MD		400.00	H
S #	NT1F11BA03	Meridian M3000 Touchphone with Data, Black	MD		480.00	H
S #	NT1F11BB03	Meridian M3000 Touchphone with Data, Black	MD		480.00	H
S #	NT1F11MD03	Meridian M3000 Touchphone with Data, Black	MD		480.00	H
B #	NT1F11MK03	Meridian M3000 Touchphone with Data, Black	MD		480.00	H
S #	NT1F21AA03	Meridian M2317 Digital Display Telephone, Black	MD		100.00	H
S #	NT1F21AA35	Meridian M2317 Digital Display Telephone, Ash	MD		100.00	H
S #	NT1F21AA93	Meridian M2317 Digital Display Telephone, Gray	MD		100.00	H
B #	NT1F21AB03	Meridian M2317 Digital Display Telephone, Black	MD		100.00	H
B #	NT1F21AB35	Meridian M2317 Digital Display Telephone, Ash	MD		100.00	H
B #	NT1F21AB93	Meridian M2317 Digital Display Telephone, Gray	MD		100.00	H
S ➤	NT1F21AE03	Meridian M2317 Intelligent Telephone, Black	625.00	D	100.00	H
S ➤	NT1F21AE35	Meridian M2317 Intelligent Telephone, Ash	625.00	D	100.00	H
S ➤	NT1F21AE93	Meridian M2317 Intelligent Telephone, Gray	625.00	D	100.00	H
S #	NT1F21BA03	Meridian M2317 Digital Display Telephone with Data, Black	MD		180.00	H
S #	NT1F21BA35	Meridian M2317 Digital Display Telephone with Data, Ash	MD		180.00	H
S #	NT1F21BA93	Meridian M2317 Digital Display Telephone with Data, Gray	MD		180.00	H
S #	NT1F21MA03	Meridian M2317 Digital Display Telephone with Data, Black	MD		180.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT1F21MA35	Meridian M2317 Digital Display Telephone with Data, Ash	MD		180.00	H
S #	NT1F21MA93	Meridian M2317 Digital Display Telephone with Data, Gray	MD		180.00	H
B #	NT1F21MB03	Meridian M2317 Digital Display Telephone with Data, Black	MD		180.00	H
B #	NT1F21MB35	Meridian M2317 Digital Display Telephone with Data, Ash	MD		180.00	H
B #	NT1F21MB93	Meridian M2317 Digital Display Telephone with Data, Gray	MD		180.00	H
S ➤	NT1F21ME03	Meridian M2317 Intelligent Telephone with Data, Black	925.00	D	180.00	H
S ➤	NT1F21ME35	Meridian M2317 Intelligent Telephone with Data, Ash	925.00	D	180.00	H
S ➤	NT1F21ME93	Meridian M2317 Intelligent Telephone with Data, Gray	925.00	D	180.00	H
S Δ	NT1F27BB	SYMPOSIUM FastView Upgrade Software Package 1A	299.00	D	N/A	
S ➤ Δ	NT1F27EB	SYMPOSIUM FastView New Software Package 1C	535.00	D	N/A	
S ➤	NT1F57AA	SYMPOSIUM Agent Package 1 (1-50 Agents)	200.00	D	N/A	
S ➤	NT1F57BA	SYMPOSIUM Agent Package 1 (51-100 Agents)	190.00	D	N/A	
S ➤	NT1F57CA	SYMPOSIUM Agent Package 1 (101-200 Agents)	175.00	D	N/A	
S ➤	NT1F57DA	SYMPOSIUM Agent Package 1 (201 + Agents)	150.00	D	N/A	
S ➤	NT1F58AA	SYMPOSIUM Agent Package 2 (1-50 Agents)	400.00	D	N/A	
S ➤	NT1F58BA	SYMPOSIUM Agent Package 2 (51-100 Agents)	375.00	D	N/A	
S ➤	NT1F58CA	SYMPOSIUM Agent Package 2 (101-200 Agents)	345.00	D	N/A	
S ➤	NT1F58DA	SYMPOSIUM Agent Package 2 (201 + Agents)	295.00	D	N/A	
S Δ	NT1F68AA	SYMPOSIUM Agent 1.1 Base Software	No charge		N/A	
S Δ	NT1F73AA	MMR CD ROM	94.00	H	N/A	
S ➤	NT1F80AA	SYMPOSIUM Agent Upgrade - Package 1 to 2	325.00	D	N/A	
S Δ	NT1F86AA	Symposium Agent Upgrade Package 1 to Package 2 - Base Software	No charge		N/A	
S Δ	NT1F89AA	Meridian Mail Release 12 Overview	15.00	H	N/A	
S Δ	NT1F90AA	Meridian Mail Release 12 Modular Option EC Manual	20.00	H	N/A	
S Δ	NT1F91AA	Meridian Mail Modular Options Manual	20.00	H	N/A	
S Δ	NT1F92AA	Meridian Mail Release 12 Modular Option GP Manual	20.00	H	N/A	
S Δ	NT1F93AA	Meridian Mail Release 12 Option 11 EC/EC11 Manual	20.00	H	N/A	
S Δ	NT1F94AA	Meridian Mail Release 12 Voice Messaging Package	15.00	H	N/A	
S ➤ Δ	NT1F97AA	Meridian Mail Release 12 Voice Messaging Package (VMUIF)	30.00	H	N/A	
S #	NT1P61AA	Fiber Superloop Network Card	MD		750.00	H
S #	NT1P61BA	Fiber Superloop Network Card	MD		750.00	H
S ➤	NT1P61CA	Fiber Superloop Network Card	5,500.00	I	750.00	H
S #	NT1P62AA	Fiber Peripheral Controller Card	MD		1,245.00	H
S #	NT1P62BA	Fiber Peripheral Controller Card	MD		1,245.00	H
S #	NT1P62CA	Fiber Peripheral Controller Card	MD		1,245.00	H
S ➤	NT1P62EA	Fiber Remote Peripheral Controller Card	5,500.00	I	1,245.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT1P63AA	Electro-Optical Interface Packlet	MD		500.00	H
S ➤	NT1P63CA	Electro-Optical Interface Packlet	5,000.00	I	500.00	H
S ➤	NT1P6501	Two Optical Adaptors Kit	300.00	I	N/A	
S ➤	NT1P6601	Four Optical Adaptors Kit	600.00	I	N/A	
S ➤	NT1P75AA	EOI to I/O Panel Optical Cable (Single Mode)	750.00	D	N/A	
S ➤	NT1P75BA	EOI to I/O Panel Optical Cable (Multi Mode)	750.00	D	N/A	
S ➤	NT1P76AA	Fiber Superloop to System Monitor & SDI Cable	200.00	D	N/A	
S ➤	NT1P78AA	Fiber Controller to System Monitor & SDI Cable	200.00	D	N/A	
S ➤	NT1P79AA	EOI to Fiber Management Optical Cable (Single Mode)	750.00	D	N/A	
S ➤	NT1P79BA	EOI to Fiber Management Optical Cable (Multi Mode)	750.00	D	N/A	
S ➤	NT1P84AA	Power Cable	35.00	D	N/A	
S ➤	NT1P85AA	Auxiliary Cable	60.00	D	N/A	
B ➤	NT1P87AA	Remote Cable Kit	225.00	D	N/A	
S ➤	NT1R03AA	Shielded 4-Port Octopus Cable with Ethernet	150.00	D	N/A	
S ➤	NT1R03BA	Shielded 4-Port Octopus Cable without Ethernet	140.00	D	N/A	
S ➤	NT1R03CA	Extension Cable (2 Ft.)	55.00	D	N/A	
S ➤	NT1R03DB	Straight Through RS232 Cable Male/Male (2 Ft.)	65.00	D	N/A	
S ➤	NT1R03DC	Straight Through RS232 Cable Male/Male (4 Ft.)	75.00	D	N/A	
S ➤	NT1R03DF	Straight Through RS232 Cable Male/Male (10 Ft.)	110.00	D	N/A	
S ➤	NT1R03DP	Straight Through RS232 Cable Male/Male (25 Ft.)	200.00	D	N/A	
S ➤	NT1R03DV	Straight Through RS232 Cable Male/Male (45 Ft.)	310.00	D	N/A	
S ➤	NT1R03EB	Straight Through RS232 Cable Male/Female (2 Ft.)	75.00	D	N/A	
S ➤	NT1R03EC	Straight Through RS232 Cable Male/Female (4 Ft.)	80.00	D	N/A	
S ➤	NT1R03EF	Straight Through RS232 Cable Male/Female (10 Ft.)	110.00	D	N/A	
S ➤	NT1R03EP	Straight Through RS232 Cable Male/Female (25 Ft.)	200.00	D	N/A	
S ➤	NT1R03EV	Straight Through RS232 Cable Male/Female (45 Ft.)	300.00	D	N/A	
S ➤	NT1R03FP	MDF 50 Pin Cable with Ethernet (25 Ft.)	200.00	D	N/A	
S ➤	NT1R03FV	MDF 50 Pin Cable with Ethernet (45 Ft.)	150.00	D	N/A	
S ➤	NT1R03GP	MDF 50 Pin Cable without Ethernet (25 Ft.)	150.00	D	N/A	
S ➤	NT1R03GV	MDF 50 Pin Cable without Ethernet (10 Ft.)	100.00	D	N/A	
S ➤	NT1R03HF	Modem Cable	60.00	D	N/A	
S ➤	NT1R04AA	Clock Controller to I/O Panel Cable	50.00	D	N/A	
S ➤	NT1R05AA	Inter-Cabinet Clock Reference Cable	100.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT1R16BB	Meridian IVR Audio Line Interface Kit	300.00	D	75.00	H
S #	NT1R20AA	Intelligent OPS Line Card	MD		400.00	H
S ➤	NT1R20AB	Intelligent OPS Line Card	3,000.00	I	400.00	H
S ➤	NT1R29AA	Next Generation Connectivity	No charge		N/A	
S ➤ Δ	NT1R31AA	NAC Release 2 Documentation Package (English)	100.00	H	N/A	
S ➤ Δ	NT1R37AA	Meridian MAX Release 8 Complete Documentation Package	100.00	D	N/A	
S ➤ Δ	NT1R39AA	Meridian MAX Release 8 NTPs (English)	50.00	D	N/A	
S ➤ Δ	NT1R49AA	Meridian MAX Release 8 Supervisors User Guide	50.00	D	N/A	
S Δ	NT1R55AB	Customer Controlled Routing Release 3 User Guide	70.00	H	N/A	
S Δ	NT1R56AE	CCR 3B and Link 5 Documentation Package	No charge		No charge	H
S Δ	NT1R57AE	CCR 3B/Link 5 Documentation Package	50.00	H	N/A	
S ✓ ➤	NT1R59AA	Symposium Call Center Server - Next Generation	No charge		N/A	
S Δ	NT1R61AA	NTP Assembly	50.00	H	N/A	
S Δ	NT1R64AA	Meridian MAX Release 6 NTP Package	100.00	H	N/A	
S Δ	NT1R65AA	Meridian MAX 6 NTPs	50.00	H	N/A	
S Δ	NT1R66AA	Meridian MAX Release 6 Supervisor Reference Guide	50.00	H	N/A	
S ➤	NT1R75AA	MTE Release 5 Software (Single User) for DOS	400.00	D	N/A	
S ➤ Δ	NT1R76BA	Meridian MAX Release 6 Capacity Configurator Tool	No charge		N/A	
S ➤ Δ	NT1R76EB	Meridian MAX Release 9.3 Capacity Configuration Tool	No charge		N/A	
S ➤	NT1R89AA	IPE Cardcage Expansion Kit (AC)	1,100.00	D	N/A	
S ➤	NT1R89BA	IPE Cardcage Expansion Kit (DC)	1,100.00	D	N/A	
S	NT1R90BA	Cardcage Upgrade Parts Kit	1,100.00	D	N/A	
B	NT1R91AA	Modem Kit	1,250.00	D	N/A	
S ➤ Δ	NT1R93AA	Meridian MAX Release 7 Complete Documentation Package	100.00	H	N/A	
S ➤ Δ	NT1R94AA	Meridian MAX Release 7 Technical Documentation Package	50.00	H	N/A	
S ➤ Δ	NT1R95AA	Meridian MAX Release 7 Supervisors User Guide	50.00	H	N/A	
S Δ	NT1R98AA	MTE Release 7 User Guide (Multilingual: English, French, Spanish, German); Package of 10	150.00	H	N/A	
S ➤ Δ	NT1R98EA	MTE Release 8 User Guide (Multilingual: English, French, Spanish, German); Package of 10	150.00	H	N/A	
S ➤ Δ	NT2F09AA	Alternate User Interface 1 User Guide (15 per Package)	25.00	H	N/A	
S ➤ Δ	NT2F20AA	Meridian Mail Release 13 Modular Option Manual	32.00	H	N/A	
S ➤ Δ	NT2F21AA	Meridian Mail Release 13 Modular Option GP Manual	25.00	H	N/A	
S ➤ Δ	NT2F22AA	Meridian Mail Release 13 Modular Option EC Manuals	35.00	H	N/A	
S ➤ Δ	NT2F23AA	Meridian Mail Release 13 Option 11 EC (EC11) Manual	21.00	H	N/A	
S ➤ Δ	NT2F24AA	Meridian Mail Release 13 Voice Messaging Package (15 Per Package)	15.00	H	N/A	
S ➤ Δ	NT2F25AA	Meridian Mail Release 13 CD ROM Package (NTP)	25.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	NT2F26AA	Meridian Mail Release 13 Call Answering (VMUIF) Package	135.00	H	N/A	
S ➤ Δ	NT2F27AA	Meridian Mail Release 13 Voice Messaging (VMUIF) Package	44.00	H	N/A	
S ➤ Δ	NT2F59AA	Application License Kit	No charge		N/A	
S ➤ Δ	NT2F60AA	SYMPOSIUM Agent 2 Base Software	No charge		N/A	
S	NT2F61AA	SYMPOSIUM Agent 2 (1 User)	400.00	D	N/A	
S	NT2F61BA	SYMPOSIUM Agent 2 (10 Users)	3,750.00	D	N/A	
S	NT2F61CA	SYMPOSIUM Agent 2 (50 Users)	18,250.00	D	N/A	
S	NT2F61DA	SYMPOSIUM Agent 2 (100 Users)	34,500.00	D	N/A	
S	NT2F61EA	SYMPOSIUM Agent 2 (500 Users)	85,000.00	D	N/A	
S ➤	NT2F62AA	SYMPOSIUM WebResponse Server 2 Basic Package	38,000.00	D	N/A	
S	NT2F63AA	SYMPOSIUM WebResponse Server 2 - One Client Expansion Package	250.00	D	N/A	
S	NT2F63BA	SYMPOSIUM WebResponse Server 2 - Ten Client Expansion Package	2,000.00	D	N/A	
S	NT2F63CA	SYMPOSIUM WebResponse Server 2 - Twenty Five Client Expansion Package	2,500.00	D	N/A	
S	NT2F64AA	SYMPOSIUM Agent 1.1 Replacement/Up-issue Package	500.00	D	N/A	
S	NT2F64BA	SYMPOSIUM Agent 2 Replacement/Up-issue Package	500.00	D	N/A	
S ➤	NT2F64CA	SYMPOSIUM WebResponse Server 2 Replacement Package	1,500.00	D	N/A	
S ➤	NT2F65AA	SYMPOSIUM Agent Upgrade Package 1 to Symposium Agent 2	300.00	D	N/A	
S ➤	NT2F65BA	SYMPOSIUM Agent Upgrade Package 2 to SYMPOSIUM Agent 2	200.00	D	N/A	
S	NT2F73AA	Symposium WebResponse Server 2 PEP	No charge		No charge	H
S ➤ Δ	NT2F77AA	External Alerter and Recording Interface User Guide (M3900 Series, Package of 15 P0903793)	12.00	H	N/A	
S ✓ ➤	NT2F78AA	Feature Card Label Sheet (M3901, Package of 25 P0906396)	35.00	D	N/A	
S § ➤ Δ	NT2F7901	Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627) N/C	No charge		N/A	
S § ➤ Δ	NT2F7903	Meridian M3901, 2,3,4 User Guide Release 2, (Package of 5 P0987180) No Charge	No charge		N/A	
S ✓ ➤ Δ	NT2F79AA	Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627)	50.00	H	N/A	
S ➤ Δ	NT2F79AB	Meridian M3901, 2,3,4 User Guide, Release 2 (Package of 5 P0987180)	20.00	H	N/A	
S ✓ § ➤ Δ	NT2F8001	Meridian M3905 User Guide Release 1 (Package of 15 P0903629) N/C	No charge		N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ § ➤ Δ	NT2F8003	Meridian M3905 User Guide (Package of 5 P0907181) No Charge	No charge		N/A	
S ✓ ➤ Δ	NT2F80AA	Meridian M3905 User Guide, Release 1 (Package of 15 P0903629)	40.00	H	N/A	
S ✓ ➤ Δ	NT2F80AB	Meridian M3905 User Guide (Package of 5 P0907181)	20.00	H	N/A	
S ➤ Δ	NT2F81AA	Meridian M3900 Series Quick Reference Guide, Release 1 (Package of 15 P0903628)	28.00	H	N/A	
S ➤ Δ	NT2F81AB	Meridian M3905 Series Quick Reference Guide, Release 2 (Package of 15 P0907178)	28.00	H	N/A	
S ➤ Δ	NT2F82AA	Meridian M3905 Quick Reference Guide, Release 1 (Package of 15 P0903630)	28.00	H	N/A	
S ★ ➤ Δ	NT2F82AB	Meridian M3905 Quick Reference Guide (Package of 15 P0907179)	28.00	H	N/A	
S ✓ ➤	NT2F83AA	Telephone Number Sheet (M3900 Series, Package of 15 P0888695)	50.00	D	N/A	
S ➤	NT2F84AA	Clear Window Menu Cover, M3901, Package of 15	15.00	D	N/A	
S #	NT2G00AA35	Attendant Console M1250	MD		345.00	H
S #	NT2G00AC35	Attendant Console M1250	MD		345.00	H
S ➤	NT2K03BA	Key Expansion Module Cable, (M2000 Series)	5.00	D	N/A	
S #	NT2K05GA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	MD		55.00	H
S #	NT2K05GA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	MD		55.00	H
S #	NT2K05GA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	MD		55.00	H
S #	NT2K05GD03	Meridian M2006 Single Line Digital Telephone, Basic, Black	MD		55.00	H
S #	NT2K05GD35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	MD		55.00	H
S #	NT2K05GD93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	MD		55.00	H
S #	NT2K05GT03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	MD		145.00	H
S #	NT2K05GT35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	MD		145.00	H
S #	NT2K05GT93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	MD		145.00	H
S #	NT2K05GV03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	MD		145.00	H
S #	NT2K05GV35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	MD		145.00	H
S #	NT2K05GV93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	MD		145.00	H
S #	NT2K08GA03	Meridian M2008 Standard Business Telephone, Basic, Black	MD		65.00	H
S #	NT2K08GA35	Meridian M2008 Standard Business Telephone, Basic, Ash	MD		65.00	H
S #	NT2K08GA93	Meridian M2008 Standard Business Telephone, Basic, Gray	MD		65.00	H
B #	NT2K08GB03	Meridian M2008HF Standard Business Telephone, Basic, Black	MD		70.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NT2K08GB35	Meridian M2008HF Standard Business Telephone, Basic, Ash	MD		70.00	H
B #	NT2K08GB93	Meridian M2008HF Standard Business Telephone, Basic, Gray	MD		70.00	H
B #	NT2K08GC03	Meridian M2008HF Standard Business Telephone, Basic, Black	MD		70.00	H
B #	NT2K08GC35	Meridian M2008HF Standard Business Telephone, Basic, Ash	MD		70.00	H
B #	NT2K08GC93	Meridian M2008HF Standard Business Telephone, Basic, Gray	MD		70.00	H
S #	NT2K08GD03	Meridian M2008 Standard Business Telephone, Basic, Black	MD		65.00	H
S #	NT2K08GD35	Meridian M2008 Standard Business Telephone, Basic, Ash	MD		65.00	H
S #	NT2K08GD93	Meridian M2008 Standard Business Telephone, Basic, Gray	MD		65.00	H
S #	NT2K08GG03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	MD		200.00	H
S #	NT2K08GG35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	MD		200.00	H
S #	NT2K08GG93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	MD		200.00	H
S #	NT2K08GH03	Meridian M2008 Standard Business Telephone with Display, Black	MD		95.00	H
S #	NT2K08GH35	Meridian M2008 Standard Business Telephone with Display, Ash	MD		95.00	H
S #	NT2K08GH93	Meridian M2008 Standard Business Telephone with Display, Gray	MD		95.00	H
B #	NT2K08GK03	Meridian M2008HF Standard Business Telephone with Display, Black	MD		70.00	H
B #	NT2K08GK35	Meridian M2008HF Standard Business Telephone with Display, Ash	MD		70.00	H
B #	NT2K08GK93	Meridian M2008HF Standard Business Telephone with Display, Gray	MD		70.00	H
B #	NT2K08GL03	Meridian M2008HF Standard Business Telephone with Display, Black	MD		70.00	H
B #	NT2K08GL35	Meridian M2008HF Standard Business Telephone with Display, Ash	MD		70.00	H
B #	NT2K08GL93	Meridian M2008HF Standard Business Telephone with Display, Gray	MD		70.00	H
S #	NT2K08GN03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	MD		200.00	H
S #	NT2K08GN35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	MD		200.00	H
S #	NT2K08GN93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	MD		200.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NT2K08GP03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	MD		70.00	H
B #	NT2K08GP35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	MD		70.00	H
B #	NT2K08GP93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	MD		70.00	H
S #	NT2K08GR03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	MD		200.00	H
S #	NT2K08GR35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	MD		200.00	H
S #	NT2K08GR93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	MD		200.00	H
B #	NT2K08GS03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	MD		70.00	H
B #	NT2K08GS35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	MD		70.00	H
B #	NT2K08GS93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	MD		70.00	H
S #	NT2K08GT03	Meridian M2008 Standard Business Telephone with MCA Data, Black	MD		150.00	H
S #	NT2K08GT35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	MD		150.00	H
S #	NT2K08GT93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	MD		150.00	H
B #	NT2K08GU03	Meridian M2008HF Standard Business Telephone with MCA Data, Black	MD		70.00	H
B #	NT2K08GU35	Meridian M2008HF Standard Business Telephone with MCA Data, Ash	MD		70.00	H
B #	NT2K08GU93	Meridian M2008HF Standard Business Telephone with MCA Data, Gray	MD		70.00	H
S #	NT2K08GV03	Meridian M2008 Standard Business Telephone with MCA Data, Black	MD		150.00	H
S #	NT2K08GV35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	MD		150.00	H
S #	NT2K08GV93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	MD		150.00	H
B #	NT2K08GX03	Meridian M2008HF Standard Business Telephone with MCA Data, Black	MD		70.00	H
B #	NT2K08GX35	Meridian M2008HF Standard Business Telephone with MCA Data, Ash	MD		70.00	H
B #	NT2K08GX93	Meridian M2008HF Standard Business Telephone with MCA Data, Gray	MD		70.00	H
S #	NT2K08XE03	Meridian M2008 Standard Business Telephone with Display, Black	MD		95.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT2K08XE35	Meridian M2008 Standard Business Telephone with Display, Ash	MD		95.00	H
S #	NT2K08XE93	Meridian M2008 Standard Business Telephone with Display, Gray	MD		95.00	H
S #	NT2K08XF03	Meridian M2008 Standard Business Telephone with Display, Black	MD		95.00	H
S #	NT2K08XF35	Meridian M2008 Standard Business Telephone with Display, Ash	MD		95.00	H
S #	NT2K08XF93	Meridian M2008 Standard Business Telephone with Display, Gray	MD		95.00	H
S #	NT2K08ZC03	Meridian M2008HF Standard Business Telephone, Basic, Black	MD		70.00	H
S #	NT2K08ZC35	Meridian M2008HF Standard Business Telephone, Basic, Ash	MD		70.00	H
S #	NT2K08ZC93	Meridian M2008HF Standard Business Telephone, Basic, Gray	MD		70.00	H
S #	NT2K08ZL03	Meridian M2008HF Standard Business Telephone with Display, Black	MD		70.00	H
S #	NT2K08ZL35	Meridian M2008HF Standard Business Telephone with Display, Ash	MD		70.00	H
S #	NT2K08ZL93	Meridian M2008HF Standard Business Telephone with Display, Gray	MD		70.00	H
S #	NT2K08ZS03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	MD		70.00	H
S #	NT2K08ZS35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	MD		70.00	H
S #	NT2K08ZS93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	MD		70.00	H
S #	NT2K10WA	Power Supply Board	MD		40.00	H
S #	NT2K10WB	Power Supply Board	MD		40.00	H
B #	NT2K10WC	Power Supply Board	MD		40.00	H
S ➤	NT2K10WD	Power Supply Board, (M2000 Series NT2K65 and NT2K40)	80.00	D	40.00	H
S #	NT2K16GA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	MD		70.00	H
S #	NT2K16GA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	MD		70.00	H
S #	NT2K16GA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	MD		70.00	H
S #	NT2K16GD03	Meridian M2616 Performance-Plus Telephone, Basic, Black	MD		70.00	H
S #	NT2K16GD35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	MD		70.00	H
S #	NT2K16GD93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	MD		70.00	H
S #	NT2K16GG03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	MD		255.00	H
S #	NT2K16GG35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	MD		255.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT2K16GG93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	MD		255.00	H
B #	NT2K16GH03	Meridian M2616 Performance-Plus Telephone with Display, Black	MD		100.00	H
B #	NT2K16GH35	Meridian M2616 Performance-Plus Telephone with Display, Ash	MD		100.00	H
B #	NT2K16GH93	Meridian M2616 Performance-Plus Telephone with Display, Gray	MD		100.00	H
S #	NT2K16GN03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	MD		255.00	H
S #	NT2K16GN35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	MD		255.00	H
S #	NT2K16GN93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	MD		255.00	H
S #	NT2K16GR03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	MD		255.00	H
S #	NT2K16GR35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	MD		255.00	H
S #	NT2K16GR93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	MD		255.00	H
S #	NT2K16GT03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	MD		180.00	H
S #	NT2K16GT35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	MD		180.00	H
S #	NT2K16GT93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	MD		180.00	H
S #	NT2K16GV03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	MD		180.00	H
S #	NT2K16GV35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	MD		180.00	H
S #	NT2K16GV93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	MD		180.00	H
B #	NT2K16XE03	Meridian M2616 Performance-Plus Telephone with Display, Black	MD		100.00	H
B #	NT2K16XE35	Meridian M2616 Performance-Plus Telephone with Display, Ash	MD		100.00	H
B #	NT2K16XE93	Meridian M2616 Performance-Plus Telephone with Display, Gray	MD		100.00	H
S #	NT2K16XF03	Meridian M2616 Performance-Plus Telephone with Display, Black	MD		100.00	H
S #	NT2K16XF35	Meridian M2616 Performance-Plus Telephone with Display, Ash	MD		100.00	H
S #	NT2K16XF93	Meridian M2616 Performance-Plus Telephone with Display, Gray	MD		100.00	H
S #	NT2K18GG03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	MD		240.00	H
S #	NT2K18GG35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	MD		240.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT2K18GG93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	MD		240.00	H
S #	NT2K18GH03	Meridian M2216 ACD-1 Basic Telephone, Black	MD		160.00	H
S #	NT2K18GH35	Meridian M2216 ACD-1 Basic Telephone, Ash	MD		160.00	H
S #	NT2K18GH93	Meridian M2216 ACD-1 Basic Telephone, Gray	MD		160.00	H
S #	NT2K18GN03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	MD		240.00	H
S #	NT2K18GN35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	MD		240.00	H
S #	NT2K18GN93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	MD		240.00	H
S #	NT2K18GR03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	MD		240.00	H
S #	NT2K18GR35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	MD		240.00	H
S #	NT2K18GR93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	MD		240.00	H
S #	NT2K18XE03	Meridian M2216 ACD-1 Basic Telephone, Black	MD		160.00	H
S #	NT2K18XE35	Meridian M2216 ACD-1 Basic Telephone, Ash	MD		160.00	H
S #	NT2K18XE93	Meridian M2216 ACD-1 Basic Telephone, Gray	MD		160.00	H
S #	NT2K18XF03	Meridian M2216 ACD-1 Basic Telephone, Black	MD		160.00	H
S #	NT2K18XF35	Meridian M2216 ACD-1 Basic Telephone, Ash	MD		160.00	H
S #	NT2K18XF93	Meridian M2216 ACD-1 Basic Telephone, Gray	MD		160.00	H
S	NT2K22VH03	Meridian Key Expansion Module, Black, (M2000 Series)	160.00	D	120.00	H
S	NT2K22VH35	Meridian Key Expansion Module, Ash, (M2000 Series)	160.00	D	120.00	H
S	NT2K22VH93	Meridian Key Expansion Module, Gray (M2000 Series)	160.00	D	120.00	H
B #	NT2K22WA03	Meridian Key Expansion Module, Black	MD		120.00	H
B #	NT2K22WA35	Meridian Key Expansion Module, Ash	MD		120.00	H
B #	NT2K22WA93	Meridian Key Expansion Module, Gray	MD		120.00	H
S #	NT2K22XH03	Meridian Key Expansion Module, Black	MD		120.00	H
S #	NT2K22XH35	Meridian Key Expansion Module, Ash	MD		120.00	H
S #	NT2K22XH93	Meridian Key Expansion Module, Gray	MD		120.00	H
S #	NT2K24WA03	Meridian Display Option, Black	MD		65.00	H
S #	NT2K24WA35	Meridian Display Option, Ash	MD		65.00	H
S #	NT2K24WA93	Meridian Display Option, Gray	MD		65.00	H
S #	NT2K25YH03	ACD Display Option, Black	MD		100.00	H
S #	NT2K25YH35	ACD Display Option, Ash	MD		100.00	H
S #	NT2K25YH93	ACD Display Option, Gray	MD		100.00	H
S #	NT2K25YJ03	Meridian ACD Display Option, Black	MD		100.00	H
S #	NT2K25YJ35	Meridian ACD Display Option, Ash	MD		100.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT2K25YJ93	Meridian ACD Display Option, Gray	MD		100.00	H
B #	NT2K25YL03	Special Applications Display, Black	MD		100.00	H
B #	NT2K25YL35	Special Applications Display, Ash	MD		100.00	H
B #	NT2K25YL93	Special Applications Display, Gray	MD		100.00	H
S #	NT2K28AA03	Meridian Display Option, Black	MD		80.00	H
S #	NT2K28AA35	Meridian Display Option, Ash	MD		80.00	H
S #	NT2K28AA93	Meridian Display Option, Gray	MD		80.00	H
S ➤	NT2K28AB03	Meridian Display Option, Black (10 Language)	200.00	D	80.00	H
S ➤	NT2K28AB35	Meridian Display Option, Ash (10 Language)	200.00	D	80.00	H
S ➤	NT2K28AB93	Meridian Display Option, Gray (10 Language)	200.00	D	80.00	H
S #	NT2K28AC03	Meridian Display Option, Black (3 Language)	MD		80.00	H
S #	NT2K28AC35	Meridian Display Option, Ash (3 Language)	MD		80.00	H
S #	NT2K28AC93	Meridian Display Option, Gray (3 Language)	MD		80.00	H
S ➤	NT2K28AD03	Meridian Display Option, Black (3 Language)	190.00	D	80.00	H
S ➤	NT2K28AD35	Meridian Display Option, Ash (3 Language)	190.00	D	80.00	H
S ➤	NT2K28AD93	Meridian Display Option, Gray (3 Language)	190.00	D	80.00	H
S ➤	NT2K28KB-03	Meridian Japanese Display Option, Black	200.00	D	N/A	
S ➤	NT2K28KB-35	Meridian Japanese Display Option, Ash	200.00	D	N/A	
S ➤	NT2K28KB-93	Meridian Japanese Display Option, Gray	200.00	D	N/A	
S Δ	NT2K33AA	US Meridian 1 Product Catalog Binder Set	50.00	H	N/A	
S Δ	NT2K34AA	US Meridian 1 Product Catalog Contents	150.00	H	N/A	
S #	NT2K36AA03	Meridian M2616CT (Cordless Telephone), Black	MD		350.00	H
S #	NT2K36AA35	Meridian M2616CT (Cordless Telephone), Ash	MD		350.00	H
S #	NT2K36AA93	Meridian M2616CT (Cordless Telephone), Gray	MD		350.00	H
B ➤	NT2K40WA	External Alerter Interface (M2000 Series)	40.00	D	20.00	H
S #	NT2K64WA	Meridian Programmable Data Adapter	MD		120.00	H
S #	NT2K64WB	Meridian Programmable Data Adapter	MD		120.00	H
S #	NT2K64WC	Meridian Programmable Data Adapter	MD		120.00	H
S #	NT2K65XH	Meridian Communications Adapter	MD		120.00	H
B #	NT2K65XJ	Meridian Communications Adapter	MD		120.00	H
B † ➤	NT2K65XR	Meridian Communications Adapter (M2000 Series)	300.00	D	120.00	H
S ➤	NT2K68AA	Analog Terminal Adapter (ATA) (M2000 Series)	190.00	D	120.00	H
B ➤	NT2K69AA	Meridian Communications Adapter (MCA) (M2000 Series)	300.00	D	120.00	H
S ➤	NT2K71AA	ATA/MCA Jumper Kit	5.00	D	N/A	
S	NT2K80AD	Literature Pack (M2216-ACD 1/2)	10.00	D	N/A	
S	NT2K80GB	Literature Pack (M2616, M2016S)	10.00	D	N/A	
S ➤	NT2K83AA03	ATA/MCA Footstand, Black (M2006, M2008, M2008HF)	8.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT2K83AA35	ATA/MCA Footstand, Ash (M2006, M2008, M2008HF)	8.00	D	N/A	
S ➤	NT2K83AA93	ATA/MCA Footstand, Gray (M2006, M2008, M2008HF)	8.00	D	N/A	
S ➤	NT2K83BA03	ATA/MCA Footstand, Black (M2616, M2216ACD)	8.00	D	N/A	
S ➤	NT2K83BA35	ATA/MCA Footstand, Ash (M2616, M2216ACD)	8.00	D	N/A	
S ➤	NT2K83BA93	ATA/MCA Footstand, Gray (M2616, M2216ACD)	8.00	D	N/A	
S #	NT2R03AA	Power Distribution Unit	MD		150.00	H
S #	NT2R07AA	Digital Shelf	MD		525.00	H
S # Δ	NT2R15AA	LANSTAR 8 Kit	MD		100.00	H
S # Δ	NT2R23AA	Blower Unit	MD		150.00	H
S #	NT2R24AA	Disk/Tape Shelf	MD		525.00	H
S #	NT2R50AA	50M Streaming Tape	MD		250.00	H
S #	NT2R70AA	234M Disk	MD		2,000.00	H
B ➤	NT2R81AA	MAXcaster Software and Documentation Package English	13,335.00	D	N/A	
B ➤	NT2R81BA	MAXcaster Software and Documentation Package French	13,335.00	D	N/A	
S # Δ	NT2R8601	Audio Interface Unit Hardware	MD		150.00	H
S	NT2R99AA	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly	50.00	H	N/A	
S ➤	NT3G30AA35	Adjustable Stand (M2250/M1250)	270.00	D	N/A	
S #	NT3G40AB35	Busy Lamp Field/Console Graphics Module	MD		600.00	H
S ➤	NT3G40BB35	Busy Lamp Field/Console Graphics Module	2,250.00	D	600.00	H
S # Δ	NT3M36AE	LANSTAR PS/2 MC Adapter Card	MD		150.00	H
S #	NT3M50AC	UDS Modem	MD		230.00	H
S ➤	NT3M50AD	Black Box ABC Switch	120.00	H	N/A	
S Δ	NT3R01CA	Meridian IVR Development Module	100.00	H	N/A	
S Δ	NT3R01DA	Meridian IVR Operational NTPs	100.00	H	N/A	
S † ➤	NT3R12AA	OIVR 2 x Hardware - 12-Port Loopstart Voice Port Assembly	16,900.00	D	N/A	
S † ➤	NT3R23AA	OIVR 2 x Hardware - MRS/AP or AP Ethernet LAN Interface	250.00	H	N/A	
S † ➤ Δ	NT3R23BA	OIVR 2.x Hardware - MRS/AP or AP Token Ring LAN Interface	880.00	H	N/A	
S ➤	NT3R28AA	Voice Prompt/Database Editor for Run-Time Systems Only	800.00	D	N/A	
S ➤ Δ	NT3R51AA	IVR Operational Documentation Package	100.00	H	N/A	
S ➤ Δ	NT3R52AA	IVR Development Documentation Package	100.00	H	N/A	
S #	NT3R53CA	CCIP Meridian 1 Connectivity, Initial 12 Ports	MD		No charge	H
S ➤	NT3R67AA	OIVR 2 x Hardware - MRS System Recovery Software Ethernet	No charge		N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT3R67BA	OIVR 2 x Hardware - MRS System Recovery Software Token Ring	No charge		N/A	
S ➤	NT3R71AA	Meridian Mail Net Gateway	3,000.00	D	700.00	H
S ➤	NT3R75AA	OIVR 2.X Hardware - MRS/Tower or MRS/Rack Ethernet Lan Interface	375.00	H	N/A	
S ➤	NT3R75BA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Token Ring LAN Interface	1,150.00	H	N/A	
S ➤	NT3R76AA	OIVR 2 x Hardware Fax Support - 2 Ports	6,000.00	D	N/A	
S ➤	NT3R76BA	OIVR 2 x Hardware Fax Support - 4 Ports	12,000.00	D	N/A	
S ➤	NT3R76CA	OIVR 2 x Hardware Fax Support - 8 Ports	24,000.00	D	N/A	
S † ➤	NT3R77AA	OIVR 2 x Hardware - Discrete Speech Recognition - 4 Ports	14,300.00	D	N/A	
S † ➤	NT3R77BA	OIVR 2 x Hardware - Discrete Speech Recognition - 4 Port Expansion	14,300.00	D	N/A	
S † ➤	NT3R78AA	OIVR 2 x Hardware - Continuous Speech Recognition - 2 Ports	14,300.00	D	N/A	
S † ➤	NT3R78BA	OIVR 2 x Hardware - Continuous Speech Recognition 2 Port Expansion	14,300.00	D	N/A	
S † ➤	NT3R79BA	OIVR 2 x Hardware - Text-to-Speech 4 Port Expansion	17,200.00	D	N/A	
S † ➤ Δ	NT3R83AA	OIVR 2 x Hardware - Voice and Data Storage (1GB) for MRS/ AP or AP	1,575.00	H	N/A	
S ✓	NT3R9501	Software Assembly, Emergency Repair Disks	3.00	D	N/A	
S #	NT4G08BA	187 MB Hard Disk Assembly	MD		1,300.00	H
S #	NT4G08BB	350 MB Hard Disk Assembly	MD		5,000.00	H
S #	NT4G08CA	Tape Assembly	MD		800.00	H
S #	NT4G13EB	Power Supply	MD		350.00	H
S #	NT4G25CB	2 Meg Memory	MD		250.00	H
S #	NT4G26AC	SCSI RAM	MD		250.00	H
S # Δ	NT4G46JD	LANSTAR PS/2 MC Adapter Card	MD		130.00	H
S # Δ	NT4G46KD	PS/2 MC Adapter Card	MD		175.00	H
S #	NT4G59AC	ESBC	MD		550.00	H
S #	NT4G59AF	2 Meg Memory	MD		400.00	H
S #	NT4G59AG	SCSI RAM	MD		500.00	H
S ➤	NT4N43AA	cPCI Multi-Media Disk Unit	4,000.00	I	350.00	H
S ➤	NT4N46AA	cPCI Core/Network Card Cage AC/DC	6,000.00	I	1,410.00	H
S ➤	NT4N50AA	Power Distribution Unit DC	1,700.00	I	300.00	H
S ✓ #	NT4N65AA	cPCI Core Network Interface Card (2 Ports)	MD		350.00	H
S ➤	NT4N65AB	cPCI Core Network Interface Card (2 Ports)	2,200.00	I	425.00	H
S ✓ #	NT4N66AA	cPCI Core Network Interface Transition Card	MD		115.00	H
S ➤	NT4N66AB	cPCI Core Network Interface Transition Card	500.00	I	N/A	
S ➤	NT4N67AA	cPCI System Utility Card	1,000.00	I	350.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT4N6809	Security Device Holder	120.00	D	N/A	
S ➤	NT4N68AA	cPCI System Utility Transition Card	1,000.00	I	115.00	H
S	NT4N71BA	cPCI LED/LCD Display Panel	350.00	I	N/A	
S ➤	NT4N88AA	CP PII to I/O Panel DtE Cable (48 In.)	170.00	D	N/A	
S ➤	NT4N88BA	CP PII to I/O Panel DCE Cable (48 In.)	170.00	D	N/A	
S	NT4N89AA	System Utility to XSM Cable	70.00	D	N/A	
S ➤ Δ	NT4N90AA	CP PII to I/O Panel Ethernet Cable (48 In.)	175.00	D	N/A	
S	NT4N92AA	MMDU Data Cable for CD and Hard Drive	70.00	D	N/A	
S ➤	NT4N93AA	MMDU Data Cable for Floppy Drive	70.00	D	N/A	
S ➤	NT4N95AA	MMDU Power Cable	70.00	D	N/A	
S ➤	NT4N96AA	cCNI to I/O Panel Cable (2 Ft.)	160.00	D	N/A	
S ➤	NT4N97AA	cPCI Upgrade Kit AC	1,000.00	I	N/A	
S ➤	NT4N97BA	cPCI Upgrade Kit DC	1,000.00	I	N/A	
S #	NT4R01AA	Network Voice Processor	MD		500.00	H
S ➤	NT4R01AC	Network Voice Processor	14,000.00	D	500.00	H
S #	NT4R03AA	RS232C Service Module	MD		300.00	H
S ➤	NT4R03AB	RS232C Service Module	2,000.00	D	300.00	H
S ➤	NT4R04AB	General Purpose Signal Processor	14,000.00	D	500.00	H
S #	NT4R05AA	PE Shelf (Center Mount)	MD		350.00	H
S #	NT4R05AB	Meridian Mail PE Shelf (Center)	MD		350.00	H
S #	NT4R06AA	PE Shelf (Cantilever)	MD		350.00	H
S #	NT4R06AB	Meridian Mail PE Shelf (Cantilever)	MD		350.00	H
S † ➤	NT4R08AA	HABC (High Availability Bus Controller)	2,750.00	D	340.00	H
S #	NT4R09AA	ESBC (Bus)	MD		500.00	H
S #	NT4R09BA	ESBC (Bus)	MD		500.00	H
S † ➤	NT4R10AA	HABC Terminator	100.00	D	N/A	
S ➤	NT4R11AA	ESBC Terminator	100.00	D	N/A	
S ➤	NT4R20AA	RSM Fanout Cable (25 Ft.)	65.00	D	N/A	
S ➤	NT4R20AB	RSM Cable (50 Ft.)	80.00	D	N/A	
S ➤	NT4R2102	Dual Network/Intra-Connection Cable (Cantilever)	85.00	D	N/A	
S #	NT4R2106	155MB Hard Disk Assembly	MD		2,000.00	H
S #	NT4R2107	300MB Hard Disk Drive	MD		1,000.00	H
S #	NT4R2108	600MB Hard Disk Drive	MD		1,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT4R2109	1.0GB Hard Disk Drive	MD		1,000.00	H
S #	NT4R28AA	Tape Drive	MD		525.00	H
S #	NT4R28AB	Tape Drive Unit	MD		630.00	H
S #	NT4R28AC	Tape Drive Unit	MD		630.00	H
S ➤	NT4R28BA	Tandberg Tape Drive Unit Options (ST/RT, NT/XT)	3,000.00	D	525.00	H
S #	NT4R32AA	Power Supply	MD		125.00	H
S † ➤	NT4R35AA	Meridian Mail Bus Cable - Two Nodes	35.00	D	N/A	
S † ➤	NT4R36AA	Meridian Mail Bus Cable - Five Nodes	35.00	D	N/A	
S † ➤	NT4R37AA	RSM Alarm Adapter Cable	40.00	D	N/A	
S #	NT4R44AA	2 Meg Memory	MD		400.00	H
S ➤	NT4R45AA	MMP40 Processor, Classic	3,500.00	D	530.00	H
S † ➤	NT4R58AB	RSM Cable	65.00	D	N/A	
S † ➤	NT4R59AA	CSL Cable	60.00	D	N/A	
S † ➤	NT4R60AA	CRT Cable	60.00	D	N/A	
S † ➤	NT4R61AA	NVP Daisychain Cable	110.00	D	N/A	
S #	NT4R71AA	2.5MB Memory	MD		500.00	H
S #	NT5C03BJ	Rectifier, 50 Amp	MD		1,000.00	H
S #	NT5C03CH	50 Amp Rectifier	MD		1,000.00	H
S #	NT5C04CA	Control Card for NT5C03 Rectifier	MD		240.00	H
S #	NT5C06CA	MPR25E Modular Power Rectifier, 25 Amps	MD		830.00	H
S ➤	NT5C06CC	MPR25E Modular Power Rectifier, 25 Amps	1,900.00	H	830.00	H
S ➤	NT5C07AC	50 Amp Rectifier	3,000.00	H	1,650.00	H
S ➤	NT5C10CC1	MPS75 Modular Power Shelf, 75 Amps	800.00	H	N/A	
S ➤	NT5C11BC	MFA150 Battery Tray	100.00	H	N/A	
S ➤	NT5C12AC	MPS150 Modular Power Shelf 23" Rackmount	850.00	H	N/A	
S #	NT5D03AA	68060 Enhanced 48MB Call Processor	MD		2,000.00	H
S #	NT5D03BA	68060 Enhanced 64MB Call Processor	MD		2,000.00	H
S #	NT5D03CA	68060 Enhanced 80MB Call Processor	MD		2,000.00	H
S #	NT5D03EA	68060 Enhanced 112MB Call Processor	MD		2,000.00	H
S #	NT5D03FA	68060 Enhanced 128MB Call Processor	MD		2,000.00	H
S ➤	NT5D03FB	68060 Enhanced 128MB Call Processor	11,500.00	I	2,000.00	H
S ➤	NT5D03PB	68060 Enhanced 160MB Call Processor	12,000.00	I	2,000.00	H
S #	NT5D10AA	68060/48MB Call Processor	MD		2,000.00	H
S #	NT5D10CA	68060/64MB Call Processor	MD		2,000.00	H
S #	NT5D10EA	68060/80MB Call Processor	MD		2,000.00	H
S #	NT5D10JA	68060/112MB Call Processor	MD		2,000.00	H
S #	NT5D11AA	Line-Side T1 Interface Card	MD		400.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT5D11AB	Line-Side T1 Interface Card	MD		400.00	H
S #	NT5D11AC	Line-Side T1 Interface Card	MD		400.00	H
S #	NT5D11AD	Line-Side T1 Interface Card	MD		400.00	H
S ➤	NT5D11AE	Line-Side T1 Interface Card	5,000.00	I	400.00	H
S #	NT5D12AA	Dual-Port DTI/PRI (DDP) Card	MD		1,000.00	H
S #	NT5D12AB	Dual-Port DTI/PRI (DDP) Card	MD		1,000.00	H
S #	NT5D12AC	Dual-Port DTI/PRI (DDP) Card	MD		1,000.00	H
S #	NT5D12AD	Dual-Port DTI/PRI (DDP) Card	MD		1,000.00	H
S ✓ #	NT5D12AF	Dual Port DTI/PRI (DDP) Card	MD		1,000.00	H
B ➤	NT5D12AG	Dual Port DTI/PRI (DDP) Card	11,500.00	I	1,000.00	H
S ➤	NT5D13AA	Line-Side T1 Interface Cable	200.00	D	N/A	
S #	NT5D14AA	Line-side T1 Interface Card (Option 11)	MD		400.00	H
S #	NT5D14AB	Line-Side T1 Interface Card (Option 11/11E/11C)	MD		400.00	H
S #	NT5D14AC	Line-Side T1 Interface Card (Option 11/11E/11C)	MD		400.00	H
S ➤	NT5D14AD	Line-Side T1 Interface Card (Option 11/11E/11C)	5,000.00	I	400.00	H
S	NT5D16BA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.)	370.00	D	N/A	
S	NT5D16DA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.) ST, STE, RT	200.00	D	N/A	
S ➤	NT5D16EA	Meridian 1 Trunk Tip/Ring Cable (8 Ft.) NT, XT	370.00	D	N/A	
S	NT5D17AA	Meridian 1 Trunk Tip/Ring Cable (50 Ft.)	300.00	D	N/A	
S ➤	NT5D19AA	PC Maintenance Cable	80.00	D	N/A	
S #	NT5D20AA	IOP/CMDU Card	MD		350.00	H
S #	NT5D20BA	IOP/CMDU Card	MD		350.00	H
S	NT5D2104	Core/Network Cardcage (AC/DC)	4,500.00	I	N/A	
S ➤	NT5D30AA	Dual Intergroup Switch	4,400.00	I	350.00	H
S ➤	NT5D40AA	Hybrids Kit	400.00	D	N/A	
S #	NT5D51AA	Meridian Integrated Conference Bridge Base Card	MD		2,500.00	H
S #	NT5D51AB	Meridian Integrated Conference Bridge (Release 2) Base Card	MD		2,500.00	H
S ➤	NT5D51AC	Meridian Integrated Conference Bridge (Release 2) Base Card	7,000.00	D	2,500.00	H
S	NT5D52AC	Universal MIxx Ethernet Adapter (for IPE Modules)	230.00	D	N/A	
S	NT5D52BC	Universal MIxx Ethernet Adapter (Option 11)	230.00	D	N/A	
S ➤	NT5D60AA	CLASS Modem card	4,000.00	D	N/A	
S #	NT5D61AA	Input/Output Drive Unit with CD-ROM	MD		350.00	H
S ➤	NT5D61AB	IODU/C Pack	7,800.00	I	350.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT5D62BB	Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive	1,400.00	D	N/A	
S #	NT5D64AA	Local Mini Carrier Interface Card (Options 21-81)	MD		700.00	H
S #	NT5D64BA	Local Mini Carrier Interface Card (Options 21-81)	MD		700.00	H
S	NT5D64CA	Local Mini Carrier Interface Card (Options 21-81)	5,800.00	I	700.00	H
S #	NT5D65AA	Local Mini Carrier Extender Card (Options 21-81)	MD		600.00	H
S #	NT5D65BA	Local Mini Carrier Extender Card (Options 21-81)	MD		600.00	H
S ➤	NT5D65CA	Local Mini Carrier Extender Card (Options 21-81)	1,750.00	D	600.00	H
S #	NT5D67AA	Remote Mini Carrier Interface Card	MD		700.00	H
S #	NT5D67BA	Remote Mini Carrier Interface Card	MD		700.00	H
S	NT5D67CA	Remote Mini Carrier Interface Card	7,000.00	I	700.00	H
S #	NT5D68AA	Local Mini Carrier Interface Card (Option 11)	MD		700.00	H
S #	NT5D68BA	Local Mini Carrier Interface Card (Option 11)	MD		700.00	H
S	NT5D68CA	Local Mini Carrier Interface Card (Option 11)	5,800.00	I	700.00	H
S #	NT5D69AA	Local Mini Carrier Extender Card (Option 11)	MD		600.00	H
S #	NT5D69BA	Local Mini Carrier Extender Card (Option 11)	MD		600.00	H
S ➤	NT5D69CA	Local Mini Carrier Extender Card (Option 11)	1,750.00	D	600.00	H
S	NT5D85AA	Local Mini Carrier Interface Cable	400.00	D	N/A	
S ➤	NT5D86AA	Local Mini Carrier Extender Cable	400.00	D	N/A	
S	NT5D87AA	Remote Mini Carrier Interface Cable	400.00	D	N/A	
S ➤	NT5D90BA	Software Installation Kit (Non-Autovon)	650.00	H	N/A	
S ➤	NT5D97AA	2.0MB Dual Port DTI/PRI	14,375.00	I	500.00	H
S ➤ Δ	NT5F33BA	Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack	20.00	H	N/A	
S Δ	NT5F3401	CD-ROM, CD-ROM X11 Release 24, North America	150.00	H	N/A	
S ➤ Δ	NT5F34AA	Meridian 1 Reference Library, Release 24 and Earlier	250.00	H	N/A	
S ➤ Δ	NT5F36AA	Option 81C (CP PII) Reference Library, Release 25	300.00	H	N/A	
S Δ	NT5F49AA	Analog Terminal Adapter Quick Reference Card (Package of 15 P0872254)	12.00	H	N/A	
S Δ	NT5F50AC	Meridian M2006, M2008, M2008HF & M2616, M2016S User Guide (English) (Package of 15 P0902627)	41.00	H	N/A	
S † ➤	NT5F52AA	Pre-Printed Feature Key Cap Package (15 Packages of 11 Key Caps Each)	25.00	D	N/A	
S Δ	NT5F53AC	Meridian Modular Telephones Quick Reference Guide (English) (Package of 15 P0902628)	28.00	H	N/A	
S Δ	NT5F54AB	Meridian Communications Adapter User Guide (Package of 15 P0859508)	20.00	H	N/A	
S Δ	NT5F55AC	M2216ACD Telephone User Guide (English) (Package of 15 P0902629)	30.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	NT5F56AA	Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option	40.00	H	N/A	
S Δ	NT5F57AA	Meridian Mail Release 12 System Administration Manual Multi-Customer EC, Modular Option, EC11, Card Option	40.00	H	N/A	
S Δ	NT5F58AA	Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM	40.00	H	N/A	
S Δ	NT5F59AA	Meridian Mail Release 12 System Administration Manual Multi-Customer, Modular Option GP/MSM	40.00	H	N/A	
S Δ	NT5F81AA	Meridian Mail 11 CD ROM Package (NTPs)	25.00	H	N/A	
S Δ	NT5F82AA	Meridian Mail 11 Modular Option GP Manual	20.00	H	N/A	
S Δ	NT5F84AA	Meridian Mail 11 Modular Option Manual	20.00	H	N/A	
S Δ	NT5F85AA	Meridian Mail 11 Administration Manual for Multi-Customer Systems	40.00	H	N/A	
S Δ	NT5F86AA	Meridian Mail 11 Administration Manual	40.00	H	N/A	
S Δ	NT5F87AA	Meridian Mail 11 Modular Option GP Administration Manual for Multi-Customer Systems	40.00	H	N/A	
S ➤ Δ	NT5F88AA	Meridian Mail 11 Voice Messaging Package (15/PK)	15.00	H	N/A	
S ➤ Δ	NT5F89AA	Meridian Mail 11 Voice Messaging (VMUIF) Package (15/PK)	30.00	H	N/A	
S ➤ Δ	NT5F91AA	Meridian Mail 11 Call Answering Package (50/PK) (DMS)	100.00	H	N/A	
S Δ	NT5F93AA	Meridian Mail 11 Card Option Manual	20.00	H	N/A	
S Δ	NT5F94AA	Meridian Mail 11 Option 11 EC (EC11) Manual	20.00	H	N/A	
S Δ	NT5F98AA	Meridian Mail Release 12 CD ROM Package (NTPs)	25.00	H	N/A	
S Δ	NT5F99AA	Meridian Mail 11 Modular Option GP Administration Manual	50.00	H	N/A	
S	NT5G01AA	MICA Pack	N/A		2,910.00	H
S	NT5G03AA	MICA Pack	N/A		2,910.00	H
S ➤	NT5G11AA	MICA Pack without Security Device	5,500.00	D	2,400.00	H
S	NT5G15AA	Meridian Integrated Voice Services (MIVS) SPARE	3,800.00	D	N/A	
S ➤	NT5G31AA	MICA PCMCIA Hard Drive Replacement (includes MICA software)	3,500.00	D	N/A	
S ➤	NT5G32AA	MICA PCMCIA Flash Card (with MICA software included)	2,500.00	D	N/A	
S	NT5G33AA	Meridian Integrated Voice Services (MIVS) PCMCIA	1,400.00	D	N/A	
S ➤	NT5G71AA	MIPCD Spare Base Card	7,000.00	D	2,500.00	H
S ➤	NT5G91AB	MIPCD PCMCIA Drive	1,400.00	D	N/A	
S	NT5G92AA	MICB Software Upgrade Kit	400.00	H	N/A	
S	NT5G95AA	PCMCIA Flash Card Upgrade, MIPCD	400.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NT5P41AQ	Cable: PC serial/modem (DB25/DB25)	39.00	D	N/A	
S † ➤	NT5P41AZ	4 Port Fax Modem Card AudioFax	5,000.00	H	N/A	
S ➤	NT5P41ZR	Brooktrout 4 Port Fax Card	5,000.00	H	N/A	
S ➤	NT5P70DA	SYMPOSIUM TAPI Driver for ICM with Bay ARN Router	5,995.00	G	N/A	
S ➤	NT5P70EA	SYMPOSIUM TAPI Driver for ICM - TCP/IP	2,895.00	G	N/A	
S # Δ	NT5R05AA	LANSTAR Blower	MD		500.00	H
S ➤	NT5R33AU	Meridian Mail Release 10.11 Master Tape North American	100.00	D	N/A	
S ➤	NT5R33BU	Meridian Mail Release 10.11 Master Tape - North American 2	100.00	D	N/A	
S ➤	NT5R33CU	Meridian Mail Release 10.11 Master Tape European 1	100.00	D	N/A	
S ➤	NT5R33DU	Meridian Mail Release 10.11 Master Tape European 2	100.00	D	N/A	
S ➤	NT5R33EU	Meridian Mail Release 10.11 Master Tape European 3	100.00	D	N/A	
S ➤	NT5R33FU	Meridian Mail Release 10.11 Master Tape European 4	100.00	D	N/A	
S ➤	NT5R33GU	Meridian Mail Release 10.11 Master Tape Asia/Pacific	100.00	D	N/A	
S ➤ Δ	NT5R3501	Meridian Mail EC 9.19 to 9.66 Upgrade Keycode	No charge		N/A	
S	NT5R35AD	Meridian Mail, Release 9.66 Master Tape, North American	100.00	D	N/A	
S	NT5R35CD	Meridian Mail, Release 9.66 Master Tape, European 1	100.00	D	N/A	
S	NT5R35DD	Meridian Mail, Release 9.66 Master Tape, European 2	100.00	D	N/A	
S	NT5R35ED	Meridian Mail, Release 9.66 Master Tape, European 3	100.00	D	N/A	
S	NT5R35LD	Meridian Mail, Release 9.66 Master Tape, Asia/Pacific 1	100.00	D	N/A	
S § ➤	NT5R36AC	Meridian Mail Release 11.19 Software Tape	100.00	D	N/A	
S ➤	NT5R36BC	Meridian Mail Master Tape, North American 2 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36CC	Meridian Mail Master Tape, European 1 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36DC	Meridian Mail Master Tape, European 2 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36EC	Meridian Mail Master Tape, European 3 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36FC	Meridian Mail Master Tape, European 4 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36GC	Meridian Mail Master Tape, European 5 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19	100.00	D	N/A	
S ➤	NT5R36JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19	100.00	D	N/A	
S ➤	NT5R45AC	Meridian Mail Master Tape, North American 1 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45BC	Meridian Mail Master Tape, North American 2 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45CC	Meridian Mail Master Tape, European 1 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45DC	Meridian Mail Master Tape, European 2 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45EC	Meridian Mail Master Tape, European 3 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45FC	Meridian Mail Master Tape, European 4 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45GC	Meridian Mail Master Tape, European 5 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45HC	Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13	100.00	D	N/A	
S ➤	NT5R45JC	Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13	100.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	NT5R46AA	Meridian Mail Networking Services Administration Guide	30.00	H	N/A	
S # Δ	NT5R55AB	Mac SCSI Kit	MD		140.00	H
S # Δ	NT5R63AA	Controller/Monitor PCBA	MD		200.00	H
S # Δ	NT5R64AA	Power Supply Assembly	MD		250.00	H
S Δ	NT5R87AA	Meridian Mail Multi-Customer Systems Reference Manual (DMS), Release 9	40.00	H	N/A	
S ➤ Δ	NT5R98AA	Meridian Mail Multi-Media Services Reference Manual	30.00	H	N/A	
S Δ	NT5R99AA	Meridian Mail System Administration Reference Manual (DMS), Release 9	30.00	H	N/A	
S ➤	NT6C14PA	System 600/48 LVD Interface Circuit Pack	120.00	H	N/A	
S ➤	NT6C14PE	System 600/48 Supplemental Cabinet Adaptor	100.00	H	N/A	
S ➤	NT6C14PF	Alarm and Control Circuit Pack for MPP600 and MFA150	350.00	H	190.00	H
S ➤	NT6C14PG	Meter Circuit Pack for MPP600 and MFA150	300.00	H	170.00	H
S ➤	NT6C25FF	System 600/48 Front Access Controller	1,700.00	H	900.00	H
S ➤	NT6C25PC	System 600/48 Control Circuit Pack	1,300.00	H	N/A	
S ➤	NT6C25PD	System 600/48 Fuse Circuit Pack	945.00	H	520.00	H
S ➤	NT6C40CF	Seismic Rack (23 In. x 4 Ft.)	300.00	H	N/A	
S # Δ	NT6D00AB	LANSTAR 16 Kit	MD		150.00	H
S #	NT6D11AB	D-Channel Handler Card	MD		470.00	H
S #	NT6D11AC	D-Channel Handler Card	MD		470.00	H
S † ➤	NT6D11AF	D-Channel Handler Card	4,500.00	I	525.00	H
S #	NT6D3903	CPU/Network Cardcage (AC/DC)	MD		650.00	H
S #	NT6D3906	CPU/Network Cardcage (AC/DC)	MD		650.00	H
S #	NT6D40AA	Peripheral Equipment Power Supply DC	MD		650.00	H
S #	NT6D40AB	Peripheral Equipment Power Supply DC	MD		650.00	H
S #	NT6D40AD	Peripheral Equipment Power Supply DC	MD		650.00	H
S ➤	NT6D40BA	Peripheral Equipment Power Supply DC	4,000.00	I	650.00	H
S #	NT6D41AA	Common Equipment Power Supply DC	MD		328.00	H
S #	NT6D41AB	Common Equipment Power Supply DC	MD		500.00	H
S ➤	NT6D41AD	Common Equipment Power Supply DC	4,000.00	I	400.00	H
S § ➤	NT6D41BA	Meridian Mail Modular GP Power Supply DC	3,000.00	D	650.00	H
S	NT6D41CA	Core/Network Power Supply DC	4,000.00	I	500.00	H
S #	NT6D42CB	Ringing Generator DC	MD		350.00	H
S #	NT6D42CC	Ringing Generator DC	MD		350.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT6D42CD	Ringing Generator DC	1,700.00	I	350.00	H
S #	NT6D43AA	Common/Peripheral Equipment Power Supply DC	MD		650.00	H
S † ➤	NT6D4406	RSM Cable	80.00	D	N/A	
S ➤	NT6D4407	GSP Cable	100.00	D	N/A	
S † ➤	NT6D4408	NVP Cable	65.00	D	N/A	
S † ➤	NT6D4409	SCSI Cable	50.00	D	N/A	
S † ➤	NT6D4410	DVS Bus Cable	40.00	D	N/A	
S † ➤	NT6D4411	DVS Bus Cable (57 Inches)	60.00	D	N/A	
S † ➤	NT6D4412	DVS Bus Cable (Internal) (132 Inches)	60.00	D	N/A	
S † ➤	NT6D4415	DVS Bus Cable (6 Ft.)	60.00	D	N/A	
S ➤	NT6D4417	SCSI/Backplane Cable	50.00	D	N/A	
S † ➤	NT6D4418	SCSI/Daisy Chain Cable	60.00	D	N/A	
S † ➤	NT6D4419	RS232-Y Cable	75.00	D	N/A	
S ➤	NT6D44AA	Meridian Mail Module AC	5,000.00	D	N/A	
S ➤	NT6D44DC	Meridian Mail Module DC	5,000.00	D	N/A	
S #	NT6D45AA	Tape Drive Unit	MD		525.00	H
S ➤	NT6D45CA	Tandberg Tape Drive Unit, Modular Option	3,000.00	D	525.00	H
S #	NT6D46AA	155MB Hard Disk Drive	MD		1,400.00	H
S #	NT6D47AA	300MB Hard Disk Drive	MD		1,000.00	H
S #	NT6D47BA	300MB Hard Disk Drive	MD		1,000.00	H
S #	NT6D47DA	Meridian Mail Modular 300MB Hard Disk/Tape Drive Unit	MD		1,000.00	H
S #	NT6D48AA	600MB Hard Disk Drive	MD		1,000.00	H
S #	NT6D48BA	1.0GB Hard Disk Drive	MD		1,000.00	H
S #	NT6D48DA	Meridian Mail Modular 1.0GB Hard Disk/Tape Drive Unit	MD		1,000.00	H
S #	NT6D48EA	Tandberg Tape & Disk Drive Unit, Modular Option	MD		1,000.00	H
S ➤	NT6D48FA	4.5GB Modular Hard Disk Drive	1,500.00	D	1,000.00	H
S ➤	NT6D48GA	Tandberg Tape and 4.5GB Disk Drive Unit, Modular Option	5,000.00	D	2,500.00	H
S ➤	NT6D51AA	Transition Card (for MVME332)	650.00	D	N/A	
S #	NT6D52AA	-52V/30 Amp Rectifier	MD		625.00	H
S #	NT6D52BA	Rectifier, -52V/30 Amp	MD		625.00	H
S ➤	NT6D5303	Ground Bar/LRE - Large	475.00	H	N/A	
S ➤	NT6D5304	Ground Bar/LRE - Small	475.00	H	N/A	
S † ➤	NT6D54AA	Rectifier Wiring Kit	30.00	I	N/A	
S ➤	NT6D54CA	Backplane Stiffener Kit	40.00	D	N/A	
S ➤	NT6D6003	Core Bus Terminator	800.00	I	N/A	
S #	NT6D63AA	Input/Output Processor Card (IOP)	MD		350.00	H
S #	NT6D63BA	Input/Output Processor Card (IOP)	MD		350.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT6D64AA	Core Multi-Drive Unit (CMDU)	MD		350.00	H
S #	NT6D65AA	Core-to-Network Interface Card (CNI)	MD		350.00	H
S #	NT6D65AB	Core-to-Network Interface Card (CNI)	MD		350.00	H
S #	NT6D66AA	24MB Call Processor Card (CP)	MD		1,135.00	H
S #	NT6D66DA	48MB Call Processor Card (CP) 81/81C Systems with 68030/ 48MB CP Requires X11 Release 21 Software Generic 1611	MD		1,135.00	H
S ➤	NT6D70AA	S/T Interface Line Card (SILC)	3,500.00	I	500.00	H
S ➤	NT6D71AA	U-Interface Line Card (UILC)	3,800.00	I	700.00	H
S	NT6D72AA	Basic Rate Signaling Concentrator	6,700.00	I	N/A	
S ➤	NT6D73AA	Multi-Purpose ISDN Signaling Processor (MISP)	3,500.00	I	700.00	H
S #	NT6D80AA	Multi-Purpose Serial Data Link (MSDL)	MD		950.00	H
S ➤	NT6D80AB	Multi-Purpose Serial Data Link (MSDL)	4,500.00	I	950.00	H
S ➤	NT6D81AA	Power Regulator Card	250.00	I	N/A	
S ➤	NT6D98AA	8-Channel Asynchronous I/O Card Kit	3,000.00	D	3,000.00	H
S #	NT6G00AA35	M2250 Attendant Console	MD		310.00	H
S #	NT6G00AC35	M2250 Attendant Console	MD		310.00	H
S #	NT6G00AD35	M2250 Attendant Console	MD		310.00	H
B #	NT6G00AE35	M2250 Attendant Console	MD		310.00	H
S ➤	NT6G00AF35	M2250 Attendant Console	3,400.00	D	310.00	H
S ➤	NT6P0104	Address Bus Jumper Cable	150.00	D	N/A	
S	NT6P0106	External Voice Bus Terminator	100.00	D	N/A	
S ➤	NT6P0109	5 Port RS232 Cable	120.00	D	N/A	
S ➤	NT6P0110	4 Port RS232 Cable	100.00	D	N/A	
S ➤	NT6P0112	Alarm Cable	60.00	D	N/A	
S ➤	NT6P0113	Interconnect Cable	100.00	D	N/A	
S	NT6P0122	Network to I/O Cable Assembly	100.00	D	N/A	
S	NT6P0123	Backplane to I/O Cable	100.00	D	N/A	
S	NT6P0124	External Voice Bus Cable (2.5 Ft.)	120.00	D	N/A	
S	NT6P0125	External Voice Bus Cable (5Ft.)	130.00	D	N/A	
S	NT6P0126	External Voice Bus Cable (10Ft.)	140.00	D	N/A	
S	NT6P01AA	Meridian Mail EC Module DC	4,000.00	D	N/A	
S	NT6P01BA	Meridian Mail EC Module AC	4,000.00	D	N/A	
S #	NT6P02AA	68K Processor Card	MD		900.00	H
S #	NT6P03AA	Utility Card with Modem	MD		475.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT6P04AA	VP4 Card	14,000.00	D	1,400.00	H
S #	NT6P05AA	Meridian Mail Modular EC Tape Drive Unit	MD		630.00	H
S ➤	NT6P05BA	Tandberg EC Tape Drive Unit, EC	3,000.00	D	525.00	H
S #	NT6P06AA	Meridian Mail Modular EC 300MB Hard Disk Drive	MD		1,000.00	H
S #	NT6P07AA	Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive	MD		1,000.00	H
S ➤	NT6P07BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive	1,500.00	D	1,000.00	H
S ➤	NT6P08AA	VP8 Card	27,000.00	D	2,100.00	H
S ➤	NT6P42AA	Utility Card without Modem	2,200.00	D	400.00	H
S #	NT6P43AA	Meridian Mail Modular EC 300MB Hard Disk Drive with Power	MD		1,000.00	H
S #	NT6P44AA	Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive with Power	MD		1,000.00	H
S ➤	NT6P44BA	Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power	2,000.00	D	1,300.00	H
S ➤	NT6P97AA	MMP40 Processor, Modular EC/EC11	3,500.00	D	400.00	H
S ➤ Δ	NT6R10AD	SYMPOSIUM Call Center Server Release 1.5 Documentation CD-ROM	250.00	H	N/A	
S ➤	NT6R14AA	Enhanced Processor for Modular Option and Modular Option GP	3,500.00	D	N/A	
S ➤	NT6R15AA	Enhanced Processor for Meridian Mail EC	3,500.00	D	N/A	
S	NT6R16AA	Enhanced Processor for Card Option Systems	10,000.00	D	N/A	
S ★	NT6R16AB	PC Pack, Entopia MMP40, Card Option (Any Slot)	10,000.00	D	N/A	
S #	NT6R17AA	Meridian Mail Compact Option Enhanced 68K Memory and 4-Port DSP Unit	MD		545.00	H
S ➤ Δ	NT6R41AA	Meridian MAX Release 9 Documentation Package (English)	100.00	H	N/A	
S ➤ Δ	NT6R43AA	Meridian MAX Release 9 Supervisor’s User Guide (English)	50.00	H	N/A	
S ★	NT6R47AD	MM13.13 Master Tape NA 1	100.00	D	N/A	
S ★	NT6R47BD	MM Release 13.13 Master Tape NA 2	100.00	D	N/A	
S ★	NT6R47CD	MM Release 13.13 Master Tape Europe 1	100.00	D	N/A	
S ★	NT6R47DD	MM Release 13.13 Master Tape Europe 2	100.00	D	N/A	
S ★	NT6R47ED	MM Release 13.13 Master Tape Europe 3	100.00	D	N/A	
S ★	NT6R47FD	MM Release 13.13 Master Tape Europe 4	100.00	D	N/A	
S ★	NT6R47GD	MM Release 13.13 Master Tape Europe 5	100.00	D	N/A	
S ★	NT6R47HD	MM Release 13.13 Master Tape Asia/Pacific 1	100.00	D	N/A	
S ★	NT6R47JD	MM Release 13.13 Master Tape Asia/Pacific 2	100.00	D	N/A	
S ➤ Δ	NT6R49AA	Meridian Mail EC11 Installation and Modification Guide, MM10	30.00	H	N/A	
S ➤	NT6R50AB	SYMPOSIUM TAPI Service Provider for Meridian 1 Release 2	3,900.00	D	N/A	
S ➤	NT6R67AA	SYMPOSIUM TAPI Service Provider Release 2, IVR and Networking Option	4,000.00	D	N/A	
S ➤	NT6R68AA	SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 Direct Connect Option	4,000.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	NT6R69AB	SYMPOSIUM TAPI Service Provider Upgrade Software	500.00	H	N/A	
B ➤ Δ	NT6R77AD	Option 11C Release 24 English Documentation Package - Binder	90.00	H	N/A	
B ➤ Δ	NT6R78AD	Option 11C R24 English Documentation Package - Coil	90.00	H	N/A	
S ➤ Δ	NT6R79AB	SYMPOSIUM TAPI Service Provider Replacement CD-ROM	500.00	H	N/A	
S ➤ Δ	NT6R81AA	Meridian Mail Options Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R82AA	Meridian Mail Modular Option GP Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R83AA	Meridian Mail Modular Option EC Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R84AA	Meridian Mail Modular Option Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R85AA	Meridian Mail Multi-Customer System Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R86AA	Meridian Mail System Administration Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R87AA	Meridian Mail Multi-Customer System Reference Manual (DMS), Release 10	40.00	H	N/A	
S ➤ Δ	NT6R88AA	Meridian Mail ACCESS Developers Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R89AA	Meridian Mail ACCESS Enable Option Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R90AA	Meridian Mail Modular EC Installation & Maintenance Quick Reference Manual, Release 10	30.00	H	N/A	
S ➤ Δ	NT6R91AA	Meridian Mail SEERS Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R93AA	Meridian Mail Card Option Reference Manual, Release 10	40.00	H	N/A	
S ➤ Δ	NT6R99AA	Meridian Mail System Administration Reference Manual (DMS), Release 10	40.00	H	N/A	
S ➤	NT7D00AA	Top Cap AC	750.00	I	N/A	
S ➤	NT7D00BA	Top Cap DC	750.00	I	N/A	
S #	NT7D03AA	Ringing Generator DC	MD		350.00	H
S #	NT7D04AA	Common/Peripheral Equipment Power Supply	MD		650.00	H
S #	NT7D04AB	Common/Peripheral Equipment Power Supply DC	MD		650.00	H
S ➤	NT7D05AA	Filler Panel - Ringing Generator	50.00	I	N/A	
S ➤	NT7D06AA	Filler Panel	35.00	D	N/A	
S ➤	NT7D0902	Rear Mount Conduit/Wiring Kit	80.00	I	N/A	
S ➤	NT7D09CA	Pedestal DC	1,750.00	I	N/A	
S #	NT7D10AA	Power Distribution Unit DC	MD		480.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT7D10CA	System Monitor Panel	MD		480.00	H
S † ➤	NT7D1201	Rectifier Support/Air Baffle	100.00	H	N/A	
S † ➤	NT7D12AA	Rectifier Rack	770.00	H	N/A	
S #	NT7D14AA	Common/Peripheral Equipment Power Supply AC	MD		650.00	H
S #	NT7D15AA	System Monitor - Option 21A	MD		140.00	H
S #	NT7D15AB	System Monitor - Option 21A	MD		140.00	H
S #	NT7D16AA	Data Access Card	MD		360.00	H
S #	NT7D16AB	Data Access Card	MD		360.00	H
S ➤	NT7D16BA	Data Access Card	2,000.00	I	360.00	H
S ➤	NT7D18AA	Application Equipment Module AC	2,700.00	D	2,400.00	H
S ➤	NT7D18AB	Application Equipment Module DC	2,700.00	D	2,400.00	H
S ➤	NT7D18KA	Power Sense Monitor Kit	110.00	D	N/A	
S #	NT7D19PA	Meridian IVR Applications Module	MD		1,500.00	H
S ➤	NT7D19RA	Meridian IVR Applications Module	3,825.00	D	1,500.00	H
S #	NT7D44AA	Power Monitor/Common Equipment Auxiliary Shelf (Cantilever)	MD		400.00	H
S #	NT7D44BA	Power Monitor/Common Equipment Auxiliary Shelf (Cantilever)	MD		400.00	H
S #	NT7D45AA	Power Monitor/Common Equipment Auxiliary Shelf (Center)	MD		400.00	H
S ➤	NT7D46AA	SDI I/O Cable	80.00	D	N/A	
S ➤	NT7D46AD	Application Module to SDI Paddle Board Cable (6 Ft.)	50.00	D	N/A	
S ➤	NT7D46AF	Application Module to SDI Paddle Board Cable (10 Ft.)	50.00	D	N/A	
S ➤	NT7D46AL	Application Module to SDI Paddle Board Cable (20 Ft.)	60.00	D	N/A	
S ➤	NT7D46AT	Application Module to SDI Paddle Board Cable (35 Ft.)	70.00	D	N/A	
S ➤	NT7D46AV	Application Module to SDI Paddle Board Cable (45 Ft.)	80.00	D	N/A	
S ➤	NT7D47AG	Ethernet Cable (12 Ft.)	125.00	D	N/A	
S ➤ Δ	NT7D47BA	Ethernet Cable (Thinnet 50 Ft.) and Terminator	100.00	H	N/A	
S ➤	NT7D47BB	Ethernet Cable (100 Ft.)	250.00	D	N/A	
S	NT7D47DA	Ethernet Cable (2 Ft.)	100.00	D	N/A	
S	NT7D47EA	VME - Ethernet Cable, I/O to Transceiver	175.00	D	N/A	
S ➤	NT7D48AA	Serial I/O Cable	120.00	D	N/A	
S	NT7D58BB	ESDI 25 pin Female to 15 pin Male Link Cable (20")	50.00	D	N/A	
S ➤	NT7D58EB	ESDI Cable (2 Ft.)	50.00	D	N/A	
S ➤	NT7D58ED	ESDI Cable (6 Ft.)	50.00	D	N/A	
S ➤	NT7D58EF	ESDI Cable (10 Ft.)	50.00	D	N/A	
S ➤	NT7D58EL	ESDI Cable (20 Ft.)	60.00	D	N/A	
S ➤	NT7D58ET	ESDI Cable (35 Ft.)	65.00	D	N/A	
S ➤	NT7D58EV	ESDI Cable (45 Ft.)	80.00	D	N/A	
S ➤	NT7D61EB	SDI Cable (2 Ft.)	40.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT7D61ED	SDI Cable (6 Ft.)	45.00	D	N/A	
S ➤	NT7D61EF	SDI Cable (10 Ft.)	45.00	D	N/A	
S ➤	NT7D61EL	SDI Cable (20 Ft.)	50.00	D	N/A	
S ➤	NT7D61ET	SDI Cable (35 Ft.)	60.00	D	N/A	
S ➤	NT7D61EV	SDI Cable (45 Ft.)	60.00	D	N/A	
S #	NT7D62AA	105MB Disk/150MB Tape Assembly	MD		2,150.00	H
S #	NT7D62AB	172MB Disk/Tape Unit	MD		2,240.00	H
S ➤	NT7D62AC	1.2 GByte Hard Disk/155 MByte Tape Drive Assembly	6,000.00	D	1,800.00	H
S ➤	NT7D62CA	1.2 GByte Hard Disk/600 MByte Tape Drive Assembly	7,000.00	D	2,100.00	H
S ➤	NT7D62DA	240 MByte Hard Disk/155 MByte Tape Drive Assembly	6,000.00	D	N/A	
S ➤	NT7D62EA	2.0 GByte Hard Disk/600 MByte Tape Drive Assembly	3,000.00	D	N/A	
S ➤	NT7D63AA	Application Module Chassis Assembly	3,700.00	D	1,050.00	H
S ➤	NT7D64AA	Application Module Power Supply AC	2,300.00	D	650.00	H
S ➤	NT7D64DC	Application Module Power Supply DC	2,300.00	D	650.00	H
S #	NT7D67CA	Power Distribution Unit DC	MD		300.00	H
S #	NT7D67CB	Power Distribution Unit DC	MD		300.00	H
S ➤	NT7D71BA	VME Built-In Modem External Cable	40.00	D	N/A	
S ➤	NT7D89CA	CP to I/O Panel RS232 Cable	170.00	D	N/A	
S ➤	NT7D90DA	IOP to I/O Panel Ethernet Cable (42 in./1m)	175.00	D	N/A	
S	NT7D95AA	Transition Cable	125.00	D	N/A	
S ➤	NT7D99AA	Null Modem Cable (10 Ft.)	60.00	D	N/A	
S ➤	NT7G10AA	M2250 Attendant Supervisory Module	600.00	D	170.00	H
S #	NT7R51AA	Local Carrier Interface Card	MD		1,245.00	H
S #	NT7R51AB	Local Carrier Interface Card	MD		1,245.00	H
S #	NT7R51AC	Local Carrier Interface Card	MD		1,245.00	H
S ➤	NT7R51AD	Local Carrier Interface Card	8,000.00	I	1,245.00	H
S #	NT7R52AA	Remote Carrier Interface Card	MD		1,245.00	H
S #	NT7R52AB	Remote Carrier Interface Card	MD		1,245.00	H
S #	NT7R52AC	Remote Carrier Interface Card	MD		1,245.00	H
S ➤	NT7R52AD	Remote Carrier Interface Card	8,000.00	I	1,245.00	H
S	NT7R66AA	SDI Cable Kit (10 Ft.)	110.00	D	N/A	
S	NT7R66BA	MMI Cable Kit (32 Ft.)	140.00	D	N/A	
S	NT7R66BB	MMI Cable Kit (32 ft.)	140.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT7R67BA	Local Carrier/Monitor Cable Assembly	300.00	D	N/A	
S ➤	NT7R67CA	Local Maintenance/Clock Cable Assembly	200.00	D	N/A	
S ➤	NT7R67DA	Local External Maintenance Cable Assembly	200.00	D	N/A	
S ➤	NT7R68AA	Remote Carrier/Alarm Cable Assembly	300.00	D	N/A	
S ➤	NT7R68BA	Remote Maintenance Cable Assembly	200.00	D	N/A	
S ➤	NT7R69AA	Extension Local Carrier Cable Assembly	150.00	D	N/A	
S ➤	NT7R69BA	Extension Local Maintenance Cable Assembly	150.00	D	N/A	
S	NT7R86AA	Auxiliary Alarm Cable (48 Ft.)	170.00	D	N/A	
S	NT7R87AA	T1 Carrier Link Cable Kit (32 Ft.)	200.00	D	N/A	
S	NT7R87BA	T1 Link Cable Kit (32 Ft.)	220.00	D	N/A	
S	NT7R94AA	Carrier Wall Mount Cable Kit	600.00	D	N/A	
S #	NT8D01AC	Controller - Four Card	MD		700.00	H
S #	NT8D01AD	Controller - Two Card	MD		700.00	H
S ➤	NT8D01BC	Controller - Four Card	4,500.00	I	700.00	H
S #	NT8D02AA	Digital Line Card	MD		375.00	H
B #	NT8D02AB	Digital Line Card	MD		375.00	H
S #	NT8D02EA	Digital Line Card	MD		375.00	H
S #	NT8D02EB	Digital Line Card	MD		375.00	H
S ➤	NT8D02GA	Digital Line Card (DLC)	3,500.00	I	375.00	H
S #	NT8D03AA	Analog Line Card	MD		350.00	H
S #	NT8D03AB	Analog Line Card	MD		350.00	H
S #	NT8D03AE	Analog Line Card	MD		350.00	H
S #	NT8D03AJ	Analog Line Card	MD		350.00	H
S #	NT8D04AA	SuperLoop Network Card	MD		500.00	H
S ➤	NT8D04BA	SuperLoop Network Card	3,500.00	I	500.00	H
S #	NT8D06AA	Peripheral Equipment Power Supply AC	MD		650.00	H
S ➤	NT8D06AB	Peripheral Equipment Power Supply AC	4,000.00	I	650.00	H
S #	NT8D09AB	Analog Message Waiting Line Card	MD		295.00	H
S #	NT8D09AD	Analog Message Waiting Line Card	MD		295.00	H
S #	NT8D09AG	Analog Message Waiting Line Card	MD		295.00	H
B #	NT8D09AJ	Analog Message Waiting Line Card	MD		295.00	H
S #	NT8D09AK	Analog Message Waiting Line Card	MD		295.00	H
S #	NT8D09AL	Analog Message Waiting Line Card	MD		295.00	H
S ➤	NT8D09BA	Analog Message Waiting Line Card	3,500.00	I	295.00	H
S #	NT8D1103	CE/PE Cardcage (AC/DC)	MD		650.00	H
S ➤	NT8D1107	SuperLoop Adapter Plate	8.00	I	N/A	
S ➤	NT8D1303	Peripheral Equipment Cardcage (AC/DC)	4,000.00	I	650.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT8D13AA	Peripheral Equipment Module AC	7,000.00	I	N/A	
S ➤	NT8D13DC	Peripheral Equipment Module DC	7,000.00	I	N/A	
S #	NT8D14AA	Universal Trunk Card	MD		400.00	H
S #	NT8D14AE	Universal Trunk Card	MD		400.00	H
B #	NT8D14AH	Universal Trunk Card	MD		400.00	H
B #	NT8D14AJ	Universal Trunk Card	MD		400.00	H
B #	NT8D14AK	Universal Trunk Card	MD		400.00	H
B #	NT8D14BA	Universal Trunk Card	MD		400.00	H
S ✓ ➤	NT8D14BB	Universal Trunk Card	3,950.00	I	400.00	H
B #	NT8D15AA	E&M Trunk Card	MD		475.00	H
B #	NT8D15AH	E&M Trunk Card	MD		475.00	H
B #	NT8D15AJ	E&M Trunk Card	MD		475.00	H
S ✓ ➤	NT8D15AK	E&M Trunk Card	2,933.00	I	475.00	H
S #	NT8D16AA	Digitone Receiver Card	MD		500.00	H
S ➤	NT8D16AB	Digitone Receiver Card	2,500.00	I	500.00	H
S #	NT8D17AA	Conference/TDS Card	MD		500.00	H
S #	NT8D17CA	Conference/TDS Card	MD		500.00	H
S #	NT8D17EA	Conference/TDS Card	MD		500.00	H
S ➤	NT8D17FA	Conference/TDS Card	5,000.00	I	500.00	H
S #	NT8D18AA	Network/DTR Card	MD		525.00	H
S #	NT8D18AB	Network/DTR Card	MD		525.00	H
S #	NT8D19AA	Memory/Peripheral Signaling Card	MD		510.00	H
S #	NT8D21AA	Ringing Generator AC	MD		350.00	H
S ➤	NT8D21AB	Ringing Generator AC	1,700.00	I	350.00	H
S #	NT8D22AB	System Monitor	MD		320.00	H
S ➤	NT8D22AC	System Monitor	1,010.00	I	320.00	H
S ➤	NT8D27BB	Pedestal AC	1,750.00	I	N/A	
S #	NT8D29AA	Common Equipment Power Supply AC	MD		650.00	H
S ➤	NT8D29AB	Common Equipment Power Supply AC	4,000.00	I	650.00	H
S	NT8D29BA	Core/Network Power Supply AC	4,000.00	I	650.00	H
S ➤	NT8D31AA	Blank Faceplate (0.875 In.)	45.00	I	N/A	
S ➤	NT8D31AB	Blank Faceplate (1 In.)	55.00	I	N/A	
S ➤	NT8D31AD	Blank Faceplate (2 In.)	65.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT8D31AE	Tape Drive Blank Faceplate	80.00	D	N/A	
S #	NT8D3403	CPU Cardcage (AC/DC)	MD		650.00	H
S #	NT8D3503	Network Cardcage (AC/DC)	MD		650.00	H
S ➤	NT8D3507	Network Cardcage (AC/DC)	4,000.00	I	650.00	H
S ➤	NT8D35BA	Network Module AC	5,000.00	I	N/A	
S ➤	NT8D35EA	Network Module DC	5,000.00	I	N/A	
S ➤	NT8D36AA	Inter Group Module	3,000.00	I	N/A	
S ➤	NT8D3703	Intelligent Peripheral Equipment Cardcage (AC/DC)	4,000.00	I	650.00	H
S ➤	NT8D37BA	Intelligent Peripheral Equipment Module AC	6,000.00	I	N/A	
S ➤	NT8D37EC	Intelligent Peripheral Equipment Module DC	6,000.00	I	N/A	
S ➤	NT8D40AA	Power Cord AC (230V)	120.00	I	N/A	
S #	NT8D41AA	Dual Port SDI Paddle Board	MD		130.00	H
S	NT8D41BA	Quad SDI Paddle Board	2,850.00	I	130.00	H
S ➤	NT8D46AA	System Monitor Column Cable (30 In.)	35.00	D	N/A	
S ➤	NT8D46AB	System Monitor Jumper Cable (11 In.)	40.00	D	N/A	
S ➤	NT8D46AC	Thermostat Harness	80.00	I	N/A	
S ➤	NT8D46AD	System Monitor to SDI Cable (60 In.)	60.00	D	N/A	
S ➤	NT8D46AG	System Monitor to SDI Paddleboard Cable (34 In.)	40.00	D	N/A	
S ➤	NT8D46AJ	System Monitor to UPS (Best) Cable (45 Ft.)	85.00	D	N/A	
S ➤	NT8D46AL	System Monitor Serial Link Cable (7 Ft.)	10.00	D	N/A	
S ➤	NT8D46AM	Air Probe Harness	80.00	I	N/A	
S ➤	NT8D46AP	Extended System Monitor Serial Link Cable (25 Ft.)	15.00	D	N/A	
S ➤	NT8D46AQ	System Monitor to UPS (Exide) Cable (45 Ft.)	50.00	D	N/A	
S ➤	NT8D46AS	System Monitor Inter-CPU Cable (30 In.)	60.00	D	N/A	
S † ➤	NT8D46AT	System Monitor to QBL15 Cable (32 Ft.)	110.00	D	N/A	
S ➤	NT8D46AU	System Monitor to UPS (Alpha) Cable (45 Ft.)	90.00	D	N/A	
S ➤	NT8D46AV	System Monitor to Power Cabinet Cable (32 Ft.)	110.00	D	N/A	
S ➤	NT8D46AW	System Monitor to QBL12 Cable (32 Ft.)	110.00	D	N/A	
S ➤	NT8D46AX	Alarm Interface Cable (45 Ft.)	70.00	D	N/A	
S ➤	NT8D46AY	Alarm Interface Cable (45 Ft.)	70.00	D	N/A	
S ➤	NT8D46BA	Alarm Monitor Cable Harness	70.00	D	N/A	
S ➤	NT8D46BB	Alarm Monitor Cable Harness	70.00	D	N/A	
S ➤	NT8D46BC	Alarm Monitor Cable (6 Ft.)	70.00	D	N/A	
S ➤	NT8D46BD	Alarm Monitor Cable (1 Ft.)	70.00	D	N/A	
S ➤	NT8D46BE	Alarm Monitor Cable (10 Ft.)	70.00	D	N/A	
S ➤	NT8D46BF	Alarm Monitor Cable (1 Ft.)	70.00	D	N/A	
S ➤	NT8D46BG	Alarm Monitor Cable Harness	70.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT8D46BH	System Monitor to MDF Cable (32 Ft.)	70.00	D	N/A	
S ➤	NT8D46BJ	Alarm Monitor Cable (1 Ft.)	70.00	D	N/A	
S ➤	NT8D46BM	Alarm Monitor Cable (1 Ft.)	70.00	D	N/A	
S ➤	NT8D46BV	System Monitor to Power Cabinet Cable (64 Ft.)	150.00	D	N/A	
S ➤	NT8D46CD	System Monitor Column Cable (AEM)	40.00	D	N/A	
S ➤	NT8D46CH	Alarm Monitor Cable (12 Ft.)	70.00	D	N/A	
S ➤	NT8D46CV	System Monitor to Power Cabinet Cable (100 Ft.)	210.00	D	N/A	
S ➤	NT8D46DC	DC Thermostat Harness	80.00	I	N/A	
S ➤	NT8D46DH	System Monitor to MDF Cable (150 Ft.)	140.00	D	N/A	
S ➤	NT8D46EH	System Monitor to MDF Cable (100 Ft.)	100.00	D	N/A	
S ➤	NT8D49AA	Column Spacer Kit (2.75 In.)	350.00	I	N/A	
S ➤	NT8D49BA	Column Spacer Kit (5.25 In.)	350.00	I	N/A	
S #	NT8D52AA	Pedestal Blower Unit AC	MD		750.00	H
S ➤	NT8D52AB	Pedestal Blower Unit AC	2,775.00	I	750.00	H
S #	NT8D52DC	Pedestal Blower Unit DC	MD		750.00	H
S ➤	NT8D52DD	Pedestal Blower Unit DC	2,775.00	I	750.00	H
B #	NT8D53AB	Power Distribution Unit AC	MD		450.00	H
S #	NT8D53BB	Power Distribution Unit AC	MD		450.00	H
S ➤	NT8D53CA	Power Distribution Unit AC	2,500.00	I	450.00	H
S ➤	NT8D56AA	Common Equipment Module Power Distribution Unit	400.00	I	N/A	
S ➤	NT8D57AA	Peripheral Equipment Module Power Distribution Unit	400.00	I	N/A	
S ➤	NT8D63AA	Overhead Cable Tray Kit	560.00	I	N/A	
S ➤	NT8D6401	Insulating Washer Kit	45.00	I	N/A	
S ➤	NT8D64BD	Module Expansion Rods	400.00	I	N/A	
S	NT8D64BE	Seismic Bracing Anchor Kit (OSHPD)	100.00	H	N/A	
S ➤	NT8D64BF	Floor Mounting Kit (Non-Seismic)	200.00	I	N/A	
S ★ ➤ Δ	NT8D64BH	Floor Module Anchor Hole Template	150.00	H	N/A	
S ➤	NT8D64CA	Earthquake Bracing Kit (2 Module Column)	1,400.00	I	N/A	
S ➤	NT8D64CB	Earthquake Bracing Kit (3 Module Column)	1,420.00	I	N/A	
S ➤	NT8D64CC	Earthquake Bracing Kit (4 Module Column)	1,450.00	I	N/A	
S	NT8D64CD	Earthquake Bracing Kit (1 Module Column)	1,200.00	I	N/A	
S	NT8D64CE	Seismic Bracing Anchor Kit (Bellcore)	300.00	H	N/A	
S #	NT8D68AA	Floppy Disk Unit	MD		235.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NT8D69AA	Multi Disk Unit	MD		695.00	H
S ➤	NT8D7217	Cable - 2.0MB DDP I/O to MDF 50 Ft.	160.00	D	N/A	
S ➤	NT8D73AD	Inter-Cabinet Network Cable (6 Ft.)	170.00	D	N/A	
S ➤	NT8D73AF	Inter-Cabinet Network Cable (12 Ft.)	180.00	D	N/A	
S ➤	NT8D73AL	Inter-Cabinet Network Cable (20 Ft.)	210.00	D	N/A	
S ➤	NT8D73AS	Inter-Cabinet Network Cable (30 Ft.)	260.00	D	N/A	
S ➤	NT8D74BC	Clock Controller to Junctor Cable (4 Ft.)	55.00	D	N/A	
S ➤	NT8D74BD	Clock Controller to Junctor Cable (6 Ft.)	55.00	D	N/A	
S ➤	NT8D74BE	Clock Controller to Junctor Cable (8 Ft.)	60.00	D	N/A	
S ➤	NT8D74BF	Clock Controller to Junctor Cable (10 Ft.)	60.00	D	N/A	
S ➤	NT8D75BC	Clock Controller to Clock Controller Cable (4 Ft.)	60.00	D	N/A	
S ➤	NT8D75BD	Clock Controller to Clock Controller Cable (6 Ft.)	40.00	D	N/A	
S ➤	NT8D76BC	cCNI to 3PE or IGS to IGM Cable (4 Ft.)	40.00	D	N/A	
S ➤	NT8D76BD	cCNI to 3PE or IGS to IGM Cable (6 Ft.)	40.00	D	N/A	
S ➤	NT8D76BE	cCNI to 3PE or IGS to IGM Cable (8 Ft.)	40.00	D	N/A	
S ➤	NT8D76BF	cCNI to 3PE or IGS to IGM Cable (10 Ft.)	40.00	D	N/A	
S ➤	NT8D76BG	cCNI to 3PE or IGS to IGM Cable (12 Ft.)	50.00	D	N/A	
S ➤	NT8D76BJ	cCNI to 3PE or IGS to IGM Cable (16 Ft.)	50.00	D	N/A	
S ➤	NT8D76BP	cCNI to 3PE or IGS to IGM Cable (16 Ft.)	50.00	D	N/A	
S	NT8D76BR	cCNI to 3PE or IGS to IGM Cable (25ft/7.6M)	60.00	D	N/A	
S	NT8D76BS	cCNI to 3PE or IGS to IGM Cable (50ft./15.2M)	60.00	D	N/A	
S ➤	NT8D77BA	Female Telco Cable (3 Ft.)	30.00	D	N/A	
S ➤	NT8D77BB	Female Telco Cable (2 Ft.)	30.00	D	N/A	
S † ➤	NT8D77BC	Female Telco Cable (4 Ft.)	40.00	D	N/A	
S ➤	NT8D77BD	Female Telco Cable (6 Ft.)	40.00	D	N/A	
S ➤	NT8D78AA	CPU Cable (2 In.)	50.00	D	N/A	
S ➤	NT8D79AB	PRI/DTI To Clock Controller Cable (2 Ft.)	40.00	D	N/A	
S ➤	NT8D79AC	PRI/DTI To Clock Controller Cable (4 Ft.)	45.00	D	N/A	
S ➤	NT8D79AD	PRI/DTI To Clock Controller Cable (6 Ft.)	45.00	D	N/A	
S ➤	NT8D79AE	PRI/DTI To Clock Controller Cable (8 Ft.)	50.00	D	N/A	
S ➤	NT8D79AF	PRI/DTI To Clock Controller Cable (10 Ft.)	50.00	D	N/A	
S † ➤	NT8D80BC	CPU/MDU Interface Cable (4 Ft.)	30.00	D	N/A	
S † ➤	NT8D80BD	CPU/MDU Interface Cable (6 Ft.)	35.00	D	N/A	
S † ➤	NT8D80BE	CPU/MDU Interface Cable (8 Ft.)	35.00	D	N/A	
S ➤	NT8D80BF	CPU Interface Cable (10 Ft.)	40.00	D	N/A	
S ➤	NT8D80BG	CPU Interface Cable (12 Ft.)	40.00	D	N/A	
S ➤	NT8D80BJ	CPU Interface Cable (16 Ft.)	45.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT8D80BL	CPU Interface Cable (20 Ft.)	50.00	D	N/A	
S ➤	NT8D80BP	CPU Interface Cable (25 Ft.)	50.00	D	N/A	
S ➤	NT8D80BZ	CPU Interface Cable (5 Ft.)	35.00	D	N/A	
S † ➤	NT8D81AA	Tip and Ring Cable (20 In.)	75.00	D	N/A	
S ➤	NT8D82AD	SDI to I/O Cable (6 Ft.)	160.00	D	N/A	
S ➤	NT8D83AD	PRI/DTI to I/O Cable (6 Ft.)	100.00	D	N/A	
S ➤	NT8D84AA	SDI Paddleboard to I/O Cable (18 In.)	90.00	D	N/A	
S ➤	NT8D85BB	Network to PE Cable (2 Ft.)	30.00	D	N/A	
S ➤	NT8D85BC	Network to PE Cable (4 Ft.)	30.00	D	N/A	
S ➤	NT8D85BD	Network to PE Cable (6 Ft.)	35.00	D	N/A	
S ➤	NT8D85BE	Network to PE Cable (8 Ft.)	35.00	D	N/A	
S ➤	NT8D85BF	Network to PE Cable (10 Ft.)	40.00	D	N/A	
S ➤	NT8D85BJ	Network to PE Cable (16 Ft.)	40.00	D	N/A	
S ➤	NT8D85BL	Network to PE Cable (20 Ft.)	45.00	D	N/A	
S ➤	NT8D85BP	Network to PE Cable (25 Ft.)	45.00	D	N/A	
S ➤	NT8D85BV	Network to PE Cable (45 Ft.)	55.00	D	N/A	
S ➤	NT8D85BZ	CPU Interface Cable (5 Ft.)	35.00	D	N/A	
S ➤	NT8D86BD	Network to I/O Cable (6 Ft.)	75.00	D	N/A	
S ➤	NT8D88AC	Network to I/O Cable (5 Ft.)	50.00	D	N/A	
S ➤	NT8D88AD	Network to I/O Cable (6 Ft.)	60.00	D	N/A	
S ➤	NT8D90AF	SDI Multi-Port Extension Cable (10 Ft.)	80.00	D	N/A	
S ➤	NT8D91AC	Network to Controller Cable (4 Ft.)	55.00	D	N/A	
S ➤	NT8D91AD	Network to Controller Cable (6 Ft.)	55.00	D	N/A	
S ➤	NT8D91AE	Network to Controller Cable (8 Ft.)	60.00	D	N/A	
S ➤	NT8D91AF	Network to Controller Cable (10 Ft.)	60.00	D	N/A	
S ➤	NT8D91AG	Network to Controller Cable (12 Ft.)	65.00	D	N/A	
S ➤	NT8D91AJ	Network to Controller Cable (16 Ft.)	65.00	D	N/A	
S ➤	NT8D91AP	Network to Controller Cable (25 Ft.)	80.00	D	N/A	
S ➤	NT8D91AV	Network to Controller Cable (45 Ft.)	100.00	D	N/A	
S ➤	NT8D92AB	Controller to I/O Cable (20 Inch)	60.00	D	N/A	
S ➤	NT8D93AJ	2 Port SDI I/O to DTE/DCE Cable (16 Ft.)	60.00	D	N/A	
S ➤	NT8D93AW	2 Port SDI I/O to DTE/DCE Cable (48 Ft.)	90.00	D	N/A	
S ➤	NT8D95AJ	SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Male)	60.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT8D95AT	SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Male)	90.00	D	N/A	
S ➤	NT8D95AW	SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Male)	110.00	D	N/A	
S ➤	NT8D95BJ	SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Female)	60.00	D	N/A	
S ➤	NT8D95BT	SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Female)	90.00	D	N/A	
S ➤	NT8D95BW	SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Female)	110.00	D	N/A	
S ➤	NT8D96AB	SDI Multi-Port Cable (2 Ft.)	90.00	D	N/A	
S ➤	NT8D96BE	VME Multi-Port Cable	175.00	D	N/A	
S ➤	NT8D98AD	Inter-Cabinet Network Cable (6 Ft.)	150.00	D	N/A	
S ➤	NT8D98AF	Inter-Cabinet Network Cable (12 Ft.)	170.00	D	N/A	
S ➤	NT8D98AL	Inter-Cabinet Network Cable (20 Ft.)	190.00	D	N/A	
S ➤	NT8D98AS	Inter-Cabinet Network Cable (30 Ft.)	220.00	D	N/A	
S	NT8D98AT	Inter-Cabinet Network Cable (38 Ft.)	250.00	D	N/A	
S ➤	NT8D99AB	CPU or Network to Network Cable (2 Ft.)	25.00	D	N/A	
S ➤	NT8D99AC	CPU or Network to Network Cable (4 Ft.)	25.00	D	N/A	
S ➤	NT8D99AD	CPU or Network to Network Cable (6 Ft.)	30.00	D	N/A	
S #	NT8K90AA35	Meridian M2018S Secure Telephone with Data, Ash	MD		400.00	H
S ➤	NT8R01AA	Meridian IVR ACCESS Link Cable Kit	575.00	D	N/A	
S Δ	NT8R03AA	MAT 4 x Common Services User Guide	15.00	H	N/A	
S #	NT8R17AA	IP Line Card-Spare	MD		1,200.00	H
S	NT8R17AB	IP Line Card, Spare	5,000.00	D	1,200.00	H
S ➤	NT8R20AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D	N/A	
S #	NT9D06AA	DSS-150 Direct Station Select Unit	MD		600.00	H
S ➤	NT9D08AA	DSS-9000 Direct Station Select Unit	2,160.00	D	450.00	H
S	NT9D13AA	M1250/M2250 Attendant Line Cord	40.00	D	N/A	
S ➤	NT9D1501	Door Panel Lock Latch Kit	4.00	H	N/A	
S ➤	NT9D15AA	Front/Rear Cover	170.00	I	N/A	
S ➤	NT9D18AA	Module Side Cover	175.00	I	N/A	
S #	NT9D19AA	68040/48MB Call Processor	MD		2,000.00	H
S #	NT9D19AB	68040/48MB Call Processor	MD		2,000.00	H
S #	NT9D19CA	68040/64MB Call Processor	MD		2,000.00	H
S #	NT9D19CB	68040/64MB Call Processor	MD		2,000.00	H
S #	NT9D19HA	68040/96MB Call Processor	MD		2,000.00	H
S #	NT9D19HB	68040/96MB Call Processor	MD		2,000.00	H
S #	NT9D33AA	Small System Multi Disk Unit	MD		550.00	H
S #	NT9D34AA	Enhanced Mass Storage Interface Card	MD		300.00	H
S	NT9D38AA	RS232 - V.35 Adapter Cable for MCA/MCU (Female)	175.00	D	N/A	
S	NT9D39AA	RS232 - V.35 Adapter Cable for MCA/MCU (Male)	175.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NT9D8001	Cable TC/FM to SDI (HSL and Configuration Control) (RJ45 to DB25)	30.00	H	N/A	
S	NT9D8002	Cable TC/FM to Supervisor PC (Return to Console Link) (RJ45 to DB9)	60.00	H	N/A	
S	NT9D8003	Cable TC/FM to Printer (RJ45 to DB25)	30.00	H	N/A	
S	NT9D8004	Cable TC/FM to Terminal (RJ45 to DB25)	60.00	H	N/A	
S ➤	NT9D89CA	CNI-3 TO 3PE/EMSI TO MDU Cable (8 Ft.)	150.00	D	N/A	
S ➤	NT9D89DA	CNI-3 TO 3PE/EMSI TO MDU Cable (10 Ft.)	150.00	D	N/A	
S ➤	NT9D89EA	CNI-3 TO 3PE/EMSI TO MDU Cable (12 Ft.)	150.00	D	N/A	
S ➤	NT9D89FA	CNI-3 TO 3PE/EMSI TO MDU Cable (25 Ft.)	160.00	D	N/A	
S ➤	NT9D89GA	CNI-3 TO 3PE/EMSI TO MDU Cable (50 Ft.)	160.00	D	N/A	
S	NT9D9007	Cable TC/FM to Modem (Remote Supervisor) (RJ45 to DB25)	60.00	H	N/A	
S ➤	NT9D9008	Cable TC/FM to NAC Network Link and Remote Supervisor Log-In Link (RJ45 to DB25)	60.00	H	N/A	
S ➤	NT9D99AA	RSM Installation Kit - Modular	55.00	D	N/A	
S ➤	NT9F02AA	Call Center Software 100, New System (1 Agent)	720.00	D	N/A	
S ✓ ➤	NT9F02BA	Call Center Software 100, New System (10 Agent)	6,528.00	D	N/A	
S ✓ ➤	NT9F02CA	Call Center Software 100, New System (50 Agent)	29,292.00	D	N/A	
S ✓ ➤	NT9F02DA	Call Center Software 100, New System (100 Agent)	51,888.00	D	N/A	
S ✓ ➤	NT9F02EA	Call Center Software 100, New System (500 Agent)	225,900.00	D	N/A	
S ➤	NT9F02GA	Software Assembly, CCS 100 - New System Software, 5 Agents	3,450.00	D	N/A	
S ➤	NT9F02HA	Software Assembly, CCS 100 - New System Software, 20 Agents	12,720.00	D	N/A	
S ➤	NT9F02JA	Software Assembly, CCS 100 - New System Software, 200 Agents	100,800.00	D	N/A	
S ➤	NT9F03AA	Call Center Software 200, New System (1 Agent)	300.00	D	N/A	
S ✓ ➤	NT9F03BA	Call Center Software 200, New System (10 Agent)	2,724.00	D	N/A	
S ✓ ➤	NT9F03CA	Call Center Software 200, New System (50 Agent)	12,204.00	D	N/A	
S ✓ ➤	NT9F03DA	Call Center Software 200, New System (100 Agent)	21,624.00	D	N/A	
S ✓ ➤	NT9F03EA	Call Center Software 200, New System (500 Agent)	94,128.00	D	N/A	
S ➤	NT9F03GA	Software Assembly, CCS 200 - New System Software, 5 Agents	1,440.00	D	N/A	
S ➤	NT9F03HA	Software Assembly, CCS 200 - New System Software, 20 Agents	5,400.00	D	N/A	
S ➤	NT9F03JA	Software Assembly, CCS 200 - New System Software, 200 Agents	42,600.00	D	N/A	
S ➤	NT9F04AA	Call Center Software 300, New System (1 Agent)	360.00	D	N/A	
S ✓ ➤	NT9F04BA	Call Center Software 300, New System (10 Agent)	3,264.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NT9F04CA	Call Center Software 300, New System (50 Agent)	14,652.00	D	N/A	
S ✓ ➤	NT9F04DA	Call Center Software 300, New System (100 Agent)	25,944.00	D	N/A	
S ✓ ➤	NT9F04EA	Call Center Software 300, New System (500 Agent)	112,956.00	D	N/A	
S ➤	NT9F04GA	Software Assembly, CCS 300 - New System Software, 5 Agents	1,800.00	D	N/A	
S ➤	NT9F04HA	Software Assembly, CCS 300 - New System Software, 20 Agents	6,480.00	D	N/A	
S ➤	NT9F04JA	Software Assembly, CCS 300 - New System Software, 200 Agents	51,000.00	D	N/A	
S ➤	NT9F06AA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1 Agent)	288.00	D	N/A	
S ➤	NT9F06BA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (10 Agent)	2,616.00	D	N/A	
S ➤	NT9F06CA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (50 Agent)	11,712.00	D	N/A	
S ➤	NT9F06DA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (100 Agent)	20,760.00	D	N/A	
S ➤	NT9F06EA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (500 Agent)	90,360.00	D	N/A	
S ➤	NT9F06GA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 5 Agents	1,452.00	D	N/A	
S ➤	NT9F06HA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 20 Agents	5,172.00	D	N/A	
S ➤	NT9F06JA	Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 200 Agents	41,400.00	D	N/A	
S ➤	NT9F07AA	Call Center Software 200, Upgrade from MAX and CCR (1 Agent)	120.00	D	N/A	
S ➤	NT9F07BA	Call Center Software 200, Upgrade from MAX and CCR (10 Agent)	1,092.00	D	N/A	
S ➤	NT9F07CA	Call Center Software 200, Upgrade from MAX and CCR (50 Agent)	4,884.00	D	N/A	
S ➤	NT9F07DA	Call Center Software 200, Upgrade from MAX and CCR (100 Agent)	8,652.00	D	N/A	
S ➤	NT9F07EA	Call Center Software 200, Upgrade from MAX and CCR (500 Agent)	37,656.00	D	N/A	
S ➤	NT9F07GA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (5 Agents)	660.00	D	N/A	
S ➤	NT9F07HA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (20 Agents)	2,184.00	D	N/A	
S ➤	NT9F07JA	Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (200 Agents)	17,520.00	D	N/A	
S ➤	NT9F08AA	Call Center Software 300, Upgrade From MAX NACD and/or NAC (1 Agent)	144.00	D	N/A	
S ➤	NT9F08BA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (10 Agent)	1,308.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT9F08CA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (50 Agent)	5,856.00	D	N/A	
S ➤	NT9F08DA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (100 Agent)	10,380.00	D	N/A	
S ➤	NT9F08EA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (500 Agent)	45,180.00	D	N/A	
S ➤	NT9F08GA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (5 Agents)	750.00	D	N/A	
S ➤	NT9F08HA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (20 Agents)	2,700.00	D	N/A	
S ➤	NT9F08JA	Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (200 Agents)	21,060.00	D	N/A	
S ➤	NT9F09AA	Call Center Software 100, Upgrade from MAX 6 (1 Agent)	300.00	D	N/A	
S ➤	NT9F09BA	Call Center Software 100, Upgrade from MAX 6 (10 Agent)	2,740.00	D	N/A	
S ➤	NT9F09CA	Call Center Software 100, Upgrade from MAX 6 (50 Agent)	12,300.00	D	N/A	
S ➤	NT9F09DA	Call Center Software 100, Upgrade from MAX 6 (100 Agent)	21,792.00	D	N/A	
S ➤	NT9F09EA	Call Center Software 100, Upgrade from MAX 6 (500 Agent)	94,884.00	D	N/A	
S ➤	NT9F09GA	Software Assembly, CCS 100 Upgrade, MAX 6, 5 Agents	1,572.00	D	N/A	
S ➤	NT9F09HA	Software Assembly, CCS 100 Upgrade, MAX 6, 20 Agents	5,544.00	D	N/A	
S ➤	NT9F09JA	Software Assembly, CCS 100 Upgrade, MAX 6, 200 Agents	43,440.00	D	N/A	
S ➤	NT9F10AA	Call Center Software 300, Upgrade From NACD (1 Agent)	180.00	D	N/A	
S ➤	NT9F10BA	Call Center Software 300, Upgrade from NACD (10 Agent)	1,632.00	D	N/A	
S ➤	NT9F10CA	Call Center Software 300, Upgrade from NACD (50 Agent)	7,332.00	D	N/A	
S ➤	NT9F10DA	Call Center Software 300, Upgrade from NACD (100 Agent)	12,972.00	D	N/A	
S ➤	NT9F10EA	Call Center Software 300, Upgrade from NACD (500 Agent)	56,484.00	D	N/A	
S ➤	NT9F10GA	Software Assembly, CCS 300 Upgrade, From NACD, 5 Agents	984.00	D	N/A	
S ➤	NT9F10HA	Software Assembly, CCS 300 Upgrade, From NACD, 20 Agents	3,276.00	D	N/A	
S ➤	NT9F10JA	Software Assembly, CCS 300 Upgrade, From NACD, 200 Agents	26,880.00	D	N/A	
S ➤	NT9F11AA	Call Center Software 100, Upgrade From MAX 5 (1 Agent)	348.00	D	N/A	
S ➤	NT9F11BA	Call Center Software 100, Upgrade from MAX 5 (10 Agent)	3,204.00	D	N/A	
S ➤	NT9F11CA	Call Center Software 100, Upgrade from MAX 5 (50 Agent)	14,352.00	D	N/A	
S ➤	NT9F11DA	Call Center Software 100, Upgrade from MAX 5 (100 Agent)	25,428.00	D	N/A	
S ➤	NT9F11EA	Call Center Software 100, Upgrade from MAX 5 (500 Agent)	110,688.00	D	N/A	
S ➤	NT9F11GA	Software Assembly, CCS 100 Upgrade, MAX 5, 5 Agents	1,770.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT9F11HA	Software Assembly, CCS 100 Upgrade, MAX 5, 20 Agents	6,408.00	D	N/A	
S ➤	NT9F11JA	Software Assembly, CCS 100 Upgrade, MAX 5, 200 Agents	49,800.00	D	N/A	
S ➤	NT9F12AA	Call Center Software 100, Upgrade from CCR only (1 Agent)	384.00	D	N/A	
S ➤	NT9F12BA	Call Center Software 100, Upgrade from CCR only (10 Agent)	3,528.00	D	N/A	
S ➤	NT9F12CA	Call Center Software 100, Upgrade from CCR only (50 Agent)	15,816.00	D	N/A	
S ➤	NT9F12DA	Call Center Software 100, Upgrade from CCR only (100 Agent)	28,020.00	D	N/A	
S ➤	NT9F12EA	Call Center Software 100, Upgrade from CCR only (500 Agent)	121,992.00	D	N/A	
S ➤	NT9F12GA	Software Assembly, CCS 100 Upgrade, CCR, 5 Agents	1,740.00	D	N/A	
S ➤	NT9F12HA	Software Assembly, CCS 100 Upgrade, CCR, 20 Agents	6,330.00	D	N/A	
S ➤	NT9F12JA	Software Assembly, CCS 100 Upgrade, CCR, 200 Agents	50,280.00	D	N/A	
S ➤	NT9F13AA	Call Center Software 200, Upgrade from CCR only (1 Agent)	168.00	D	N/A	
S ➤	NT9F13BA	Call Center Software 200, Upgrade from CCR only (10 Agent)	1,476.00	D	N/A	
S ➤	NT9F13CA	Call Center Software 200, Upgrade from CCR only (50 Agent)	6,588.00	D	N/A	
S ➤	NT9F13DA	Call Center Software 200, Upgrade from CCR only (100 Agent)	11,676.00	D	N/A	
S ➤	NT9F13EA	Call Center Software 200, Upgrade from CCR only (500 Agent)	50,832.00	D	N/A	
S ➤	NT9F13GA	Software Assembly, CCS 200 Upgrade, CCR, 5 Agents	828.00	D	N/A	
S ➤	NT9F13HA	Software Assembly, CCS 200 Upgrade, CCR, 20 Agents	2,940.00	D	N/A	
S ➤	NT9F13JA	Software Assembly, CCS 200 Upgrade, CCR, 200 Agents	22,920.00	D	N/A	
S ➤	NT9F14AA	Call Center Software 100, Upgrade from Max Pre-release 5 or PDP (1 Agent)	444.00	D	N/A	
S ➤	NT9F14BA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (10 Agent)	4,044.00	D	N/A	
S ➤	NT9F14CA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (50 Agent)	18,156.00	D	N/A	
S ➤	NT9F14DA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (100 Agent)	32,172.00	D	N/A	
S ➤	NT9F14EA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (500 Agent)	140,064.00	D	N/A	
S ➤	NT9F14GA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 5 Agents	2,148.00	D	N/A	
S ➤	NT9F14HA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 20 Agents	7,932.00	D	N/A	
S ➤	NT9F14JA	Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 200 Agents	62,880.00	D	N/A	
S ➤	NT9F15AA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1 Agent)	264.00	D	N/A	
S ➤	NT9F15BA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (10 Agent)	2,340.00	D	N/A	
S ➤	NT9F15CA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (50 Agent)	10,500.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT9F15DA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (100 Agent)	18,600.00	D	N/A	
S ➤	NT9F15EA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (500 Agent)	80,952.00	D	N/A	
S ➤	NT9F15GA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 5 Agents	1,344.00	D	N/A	
S ➤	NT9F15HA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 20 Agents	4,584.00	D	N/A	
S ➤	NT9F15JA	Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 200 Agents	36,960.00	D	N/A	
S >> #	NT9F17AA	SYMPOSIUM Express Call Center - 1 Agent Increment	570.00	D	N/A	
S >> #	NT9F17BA	SYMPOSIUM Express Call Center - 5 Agent Increment	2,300.00	D	N/A	
S >> #	NT9F17CA	SYMPOSIUM Express Call Center - 10 Agent Increment	4,000.00	D	N/A	
S >> #	NT9F19AA	SYMPOSIUM Express Call Center Replacement/Up-Issue Software Package	50.00	H	N/A	
S ➤	NT9F19AB	Symposium Express Call Center 2.0 Replacement/Up-Issue Software Package	50.00	H	N/A	
S #	NT9F23AA	SYMPOSIUM Server, 1000t Base	MD		2,000.00	H
S #	NT9F23CA	SYMPOSIUM Server, 1000t Base with RAID	MD		3,075.00	H
S #	NT9F24AA	SYMPOSIUM Server, 1000t Mid	MD		3,050.00	H
S #	NT9F24CA	SYMPOSIUM Server, 1000t Mid with RAID	MD		5,100.00	H
S #	NT9F25AA	SYMPOSIUM Server, 1000t Advanced	MD		4,825.00	H
S #	NT9F26BA	SYMPOSIUM Server, 1000t Dual Processor Upgrade	MD		3,065.00	H
S #	NT9F26CA	SYMPOSIUM Server, 1000t 32 Mb RAM Upgrade	MD		560.00	H
S #	NT9F26EA	SYMPOSIUM Server, 1000t 4 Gb HD Upgrade	MD		1,350.00	H
S #	NT9F26FA	SYMPOSIUM Server, 1000t 26 Gb Tape Upgrade	MD		2,210.00	H
S #	NT9F26GA	SYMPOSIUM Server 1000t, RAID Kit A	MD		3,065.00	H
S #	NT9F26HA	SYMPOSIUM Server 1000t, RAID Kit B	MD		5,760.00	H
S ✓ ➤	NT9F27AA	SYMPOSIUM Call Center Server Peripherals Package	1,000.00	H	700.00	H
S ➤	NT9F27AC	SYMPOSIUM Call Center Server 1003t Peripherals Package	535.00	H	N/A	
S #	NT9F28AA	SYMPOSIUM Call Center Server 701t Advanced	MD		1,500.00	H
S #	NT9F28BA	SYMPOSIUM Call Center Server 701t Advanced with RAID	MD		2,400.00	H
S ➤	NT9F41AD	Release 3.0 Base Software and Documentation	3,980.00	D	N/A	
S ➤	NT9F43AC	SYMPOSIUM Call Center Release 1.5 Client CD-ROM	50.00	H	N/A	
S ★ ➤	NT9F43AD	DMS SCCS Release 3.0 CD-ROM Client CD (Merchandise)	25.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT9F46AC	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly	50.00	H	N/A	
S ➤	NT9F51AC	SYMPOSIUM Call Center Server Release 1.5 Replacement Software	500.00	D	N/A	
S Δ	NT9F53AA	SCCS Software Assembly, Release 24 X11 PEP CD-ROM	No charge		N/A	
S #	NT9F83AA	Meridian Integrated Conference Bridge (Ide@Room Version) 12 Port Card	MD		3,000.00	H
S Δ	NT9F84AA	Symon View	50.00	H	N/A	
S ➤	NT9F90AA	SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51	20,370.00	H	N/A	
S ➤	NT9F90BA	SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0	20,370.00	H	N/A	
S ➤	NT9J93AD	PRI/DTI Echo Canceler to I/O Cable (6 Ft.)	60.00	D	N/A	
S ➤	NT9J96AC	Intra-Cabinet Network Cable (40 In.)	90.00	D	N/A	
S ➤	NT9J96AD	Intra-Cabinet Network Cable (70 In.)	90.00	D	N/A	
S ➤	NT9J96AE	Intra-Cabinet Network Cable (85 In.)	90.00	D	N/A	
S ➤	NT9J96AG	Intra-Cabinet Network Cable (12 Ft.)	100.00	D	N/A	
S ➤	NT9J96AH	Intra-Cabinet Network Cable (14 Ft.)	100.00	D	N/A	
S ➤	NT9J96AJ	Intra-Cabinet Network Cable (16 Ft.)	100.00	D	N/A	
S ➤	NT9J97AC	Intra-Cabinet Network Cable (40 In.)	80.00	D	N/A	
S ➤	NT9J97AD	Intra-Cabinet Network Cable (70 In.)	80.00	D	N/A	
S ➤	NT9J97AE	Intra-Cabinet Network Cable (85 In.)	90.00	D	N/A	
S ➤	NT9J97AG	Intra-Cabinet Network Cable (12 Ft.)	90.00	D	N/A	
S ➤	NT9J97AH	Intra-Cabinet Network Cable (14 Ft.)	90.00	D	N/A	
S ➤	NT9J97AJ	Intra-Cabinet Network Cable (16 Ft.)	100.00	D	N/A	
S ➤	NT9J98AC	Intra-Cabinet Network Cable (40 In.)	100.00	D	N/A	
S ➤	NT9J98AD	Intra-Cabinet Network Cable (70 In.)	100.00	D	N/A	
S ➤	NT9J98AE	Intra-Cabinet Network Cable (85 In.)	110.00	D	N/A	
S ➤	NT9J99AC	Intra-Cabinet Network Cable (40 In.)	90.00	D	N/A	
S ➤	NT9J99AD	Intra-Cabinet Network Cable (70 In.)	100.00	D	N/A	
S ➤	NT9J99AE	Intra-Cabinet Network Cable (85 In.)	110.00	D	N/A	
S ➤	NT9K05AA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	135.00	D	55.00	H
S ➤	NT9K05AA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	135.00	D	55.00	H
S ➤	NT9K05AA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	135.00	D	55.00	H
S ➤	NT9K08AA03	Meridian M2008 Standard Business Telephone, Basic, Black	175.00	D	65.00	H
S ➤	NT9K08AA35	Meridian M2008 Standard Business Telephone, Basic, Ash	175.00	D	65.00	H
S ➤	NT9K08AA93	Meridian M2008 Standard Business Telephone, Basic, Gray	175.00	D	65.00	H
S ➤	NT9K08AB03	Meridian M2008HF Standard Business Telephone, Basic, Black	240.00	D	70.00	H
S ➤	NT9K08AB35	Meridian M2008HF Standard Business Telephone, Basic, Ash	240.00	D	70.00	H
S ➤	NT9K08AB93	Meridian M2008HF Standard Business Telephone, Basic, Gray	240.00	D	70.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NT9K08AC03	Meridian M2008 Standard Business Telephone with Display, Black	350.00	D	95.00	H
S ➤	NT9K08AC35	Meridian M2008 Standard Business Telephone with Display, Ash	350.00	D	95.00	H
S ➤	NT9K08AC93	Meridian M2008 Standard Business Telephone with Display, Gray	350.00	D	95.00	H
S ➤	NT9K08AD03	Meridian M2008HF Standard Business Telephone with Display, Black	390.00	D	70.00	H
S ➤	NT9K08AD35	Meridian M2008HF Standard Business Telephone with Display, Ash	390.00	D	70.00	H
S ➤	NT9K08AD93	Meridian M2008HF Standard Business Telephone with Display, Gray	390.00	D	70.00	H
S ➤	NT9K16AA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	400.00	D	70.00	H
S ➤	NT9K16AA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	400.00	D	70.00	H
S ➤	NT9K16AA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	400.00	D	70.00	H
S ➤	NT9K16AC03	Meridian M2616 Performance-Plus Telephone with Display, Black	525.00	D	100.00	H
S ➤	NT9K16AC35	Meridian M2616 Performance-Plus Telephone with Display, Ash	525.00	D	100.00	H
S ➤	NT9K16AC93	Meridian M2616 Performance-Plus Telephone with Display, Gray	525.00	D	100.00	H
S ➤	NT9K18AC03	Meridian M2216ACD Telephone, Black	525.00	D	160.00	H
S ➤	NT9K18AC35	Meridian M2216ACD Telephone, Ash	525.00	D	160.00	H
S ➤	NT9K18AC93	Meridian M2216ACD Telephone, Grey	525.00	D	160.00	H
S #	NT9N01AA	Multichannel Coax System (MCCS) with One Power Supply	MD		460.00	H
S #	NT9N01BA	Multichannel Coax System (MCCS) with two power supplies	MD		460.00	H
S #	NT9N02	Cluster Interface Card (CIC)	MD		195.00	H
S #	NT9N20	Co-Axial Interface Module (CIM)	MD		300.00	H
S ✓ #	NTAG26AA	MF Receiver Card - IPE	MD		615.00	H
S ➤	NTAG26AB	Multi-Frequency IPE Receiver Card (4 Channel)	4,100.00	I	615.00	H
S #	NTAG36AA	Meridian Integrated RAN Base Card	MD		800.00	H
S #	NTAG36AB	Meridian Integrated RAN (Release 2) Base Card	MD		800.00	H
S ➤	NTAG36AC	Meridian Integrated RAN (Release 2) Base Spare Card	2,200.00	D	800.00	H
S ➤	NTAG81AA	Audio Cable	45.00	D	N/A	
S ➤	NTAG81BA	Maintenance Extender Cable	100.00	D	N/A	
S ➤	NTAG81CA	PC Maintenance Cable	80.00	D	N/A	
S ➤	NTAG81DA	VLAN Maintenance Cable	150.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTAG81GA	Ethernet & DB9 Adapter with 25pr Connector	120.00	D	N/A	
S # Δ	NTAG88AA	MIRAN Pack	MD		800.00	H
S	NTAG95AA	Meridian 1 Attendant PC Handset Cord with PJ-Type Plug	40.00	D	N/A	
N #	NTAK01AA	CPU/CONF Card	MD		525.00	H
S #	NTAK01CA	CPU/Conference Card	MD		525.00	H
N #	NTAK02AA	SDI/DCH Card	MD		525.00	H
S #	NTAK02AB	SDI/DCH Card	MD		525.00	H
S #	NTAK02BB	SDI/DCH Card	MD		525.00	H
S ➤	NTAK02BC	SDI/DCH Card	3,000.00	I	250.00	H
N #	NTAK03AA	TDS/DTR Card	MD		525.00	H
N #	NTAK03BA	TDS/DTR Card	MD		525.00	H
S ➤	NTAK03DA	TDS/DTR Card	1,700.00	I	525.00	H
S	NTAK0420	Power Cable	60.00	D	N/A	
B #	NTAK04AA	AC/DC Power Supply	MD		200.00	H
S #	NTAK05AA	DC/DC Power Supply	MD		200.00	H
B #	NTAK09AA	DTI/PRI Card	MD		400.00	H
S #	NTAK09BA	DTI/PRI Card	MD		450.00	H
S ✓ † ➤	NTAK09DA	DTI/PRI Card	4,000.00	H	450.00	H
S #	NTAK10DB	2.0MB DTI Card with Clock Controller	MD		450.00	H
S	NTAK10DC	2.0 MB DTI Card with Clock Controller	4,000.00	I	450.00	H
S ➤	NTAK1104	PFTU/Console Power Cable	60.00	D	N/A	
S ➤	NTAK1108	SDI Cable	40.00	D	N/A	
S ➤	NTAK1118	Modem Cable (DB9 to DB25)	90.00	D	N/A	
N ➤	NTAK11BB	Option 11E Main Cabinet	N/A		550.00	H
B ➤	NTAK11BD	Main/Expansion Cabinet	2,500.00	I	525.00	H
S ➤	NTAK1204	Expansion Cable - Copper (7 Ft.)	160.00	D	N/A	
S ➤	NTAK12BB	Option 11 Expansion Cabinet	N/A		350.00	H
S ✓ ➤	NTAK1305	SCSI Cable (6 Ft.)	115.00	D	N/A	
S ➤	NTAK13AA	Power Board	980.00	D	200.00	H
N #	NTAK14AA	68K Processor Pack	MD		1,200.00	H
S ➤	NTAK14BA	68K Processor Pack	3,600.00	D	1,200.00	H
N #	NTAK15AA	Digital Voice Processor Card	MD		1,000.00	H
S † ➤	NTAK15AB	Digital Voice Processor Card	4,500.00	D	1,000.00	H
N #	NTAK16AA	C25 Voice Processor Card	MD		1,000.00	H
S † ➤	NTAK16AB	C25 Voice Processor Card	4,500.00	D	1,000.00	H
N #	NTAK17AA	Meridian Mail Card Option Base Pack, 2-6 Ports	MD		110.00	H
S ➤	NTAK17AB	Meridian Mail Card Option Base Pack, 2-6 Ports	560.00	D	110.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTAK17BA	Meridian Mail Card Option Base Package, 8-12 Ports	MD		110.00	H
S ➤	NTAK17BB	Meridian Mail Card Option Base Package, 8-12 Ports	560.00	D	110.00	H
S #	NTAK18AA	RS232C Service Module	MD		110.00	H
B ➤	NTAK18BA	RS232C Service Module	550.00	D	110.00	H
B	NTAK19EC	2 Port SDI Cable (6 Ft.)	160.00	D	N/A	
S ➤	NTAK19FB	4 Port SDI Cable	200.00	D	N/A	
N #	NTAK20AA	Clock Controller Card	MD		225.00	H
B #	NTAK20AB	Clock Controller Card	MD		225.00	H
S #	NTAK20AC	Clock Controller Card	MD		225.00	H
S	NTAK20AD	Clock Controller Card	1,000.00	I	225.00	H
N #	NTAK21AA	Expansion Cartridge	MD		65.00	H
S ➤	NTAK21BA	Expansion Cartridge	300.00	I	65.00	H
S ➤	NTAK27AA	Option 11 Cabinet Pedestal	440.00	I	N/A	
S ➤	NTAK28AB	Battery Junction Box	170.00	H	N/A	
B #	NTAK30CA	External Tape Drive Package	MD		2,400.00	H
B ➤	NTAK30DB	External Tape Drive Package, Tandberg	2,800.00	D	N/A	
S ➤	NTAK36AA	Peripheral Cable Female	90.00	D	N/A	
S ➤	NTAK37AA	Peripheral Cable Male	90.00	D	N/A	
S ➤	NTAK39AB	Tape Drive Wall Mounting Kit	65.00	D	N/A	
S ✓ ➤	NTAK40AA	Networking Hardware Kit	1,100.00	D	N/A	
N #	NTAK57AA	General Business Software	MD		300.00	H
N #	NTAK57AB	General Business Software	MD		300.00	H
N #	NTAK57AC	General Business Software	MD		300.00	H
N #	NTAK57AD	General Business Software	MD		300.00	H
S † ➤	NTAK57AG	General Business Software	2,000.00	I	N/A	
N #	NTAK57BA	Enhanced Business Software	MD		300.00	H
N #	NTAK57BB	Enhanced Business Software	MD		300.00	H
N #	NTAK57BC	Enhanced Business Software	MD		300.00	H
N #	NTAK57BD	Enhanced Business Software	MD		300.00	H
S † ➤	NTAK57BG	Enhanced Business Software	3,500.00	I	N/A	
N #	NTAK57CA	Private Networking Software	MD		300.00	H
N #	NTAK57CB	Private Networking Software	MD		300.00	H
N #	NTAK57CC	Private Networking Software	MD		300.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	NTAK57CG	Private Networking Software	5,500.00	I	N/A	
N #	NTAK57DA	Advanced Applications Software	MD		300.00	H
N #	NTAK57DB	Advanced Application Software	MD		300.00	H
N #	NTAK57DC	Advanced Applications Software	MD		300.00	H
N #	NTAK57DD	Advanced Applications Software	MD		300.00	H
S † ➤	NTAK57DG	Advanced Applications Software	8,500.00	I	N/A	
S † ➤	NTAK57GG	General Business Software (no DISA)	2,000.00	I	N/A	
S † ➤	NTAK57HG	Enhanced Business Software (no DISA)	3,500.00	I	N/A	
S † ➤	NTAK57IG	Private Networking Software (no DISA)	5,500.00	I	N/A	
S	NTAK72BT	Meridian Mail, Release 9.66 Master Tape, European 1 Card Option	100.00	D	N/A	
S	NTAK72CT	Meridian Mail, Release 9.66 Master Tape, European 2 Card Option	100.00	D	N/A	
S	NTAK72DT	Meridian Mail, Release 9.66 Master Tape, Asia/Pacific Card Option	100.00	D	N/A	
S ➤	NTAK72GN	Meridian Mail Release 10.11 Master Tape European Card Option	100.00	D	N/A	
S	NTAK72GT	Meridian Mail, Release 9.66 Master Tape, North American Card Option	100.00	D	N/A	
S ➤	NTAK72HN	Meridian Mail Release 10.11 Master Tape European 2 Card Option	100.00	D	N/A	
S ➤	NTAK72KN	Meridian Mail Release 10.11 Master Tape Asia/Pacific Card Option	100.00	D	N/A	
S	NTAK72KT	Meridian Mail, Release 9.66 Master Tape, European 3 Card Option	100.00	D	N/A	
S ➤	NTAK72LN	Meridian Mail Release 10.11 Master Tape North American Card Option	100.00	D	N/A	
S	NTAK72LT	Meridian Mail, Release 9.66 Master Tape, European 4 Card Option	100.00	D	N/A	
S ➤	NTAK72PN	Meridian Mail Release 10.11 Master Tape European 3 Card Option	100.00	D	N/A	
S ➤	NTAK72QN	Meridian Mail Release 10.11 Master Tape European 4 Card Option	100.00	D	N/A	
S ➤	NTAK75AB	2-4 Hour Battery Back-Up Unit	2,225.00	H	N/A	
S ➤	NTAK76AB	15-30 Minute Battery Back-up Unit	550.00	H	N/A	
S ➤	NTAK80AA	Option 11 System Back-Up Cartridge	550.00	I	150.00	H
S Δ	NTAK82AF	Option 11 NTP Package Release 18	50.00	H	N/A	
S ➤	NTAK9204	OPS Cable	40.00	D	N/A	
S #	NTAK92AA	OPS Protection Module	MD		400.00	H
S #	NTAK92AB	OPS Protection Module	MD		400.00	H
S ➤	NTAK92BA	OPS Protection Module	1,675.00	I	400.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTAK93AA	DCHI Card	MD		225.00	H
S ➤	NTAK93AB	DCHI Card	1,000.00	I	225.00	H
S ➤	NTAK98AA	Power Supply Cable	40.00	D	N/A	
S ➤	NTBK04AA	1.544 MByte Carrier Cable	300.00	D	N/A	
S	NTBK05CA	Cable 20 Ft. Coax - 2.0MB DTI/PRI to MDF	180.00	D	N/A	
S	NTBK05DA	2.0MB DTI/PRI Twisted Pair Cable	180.00	D	N/A	
S ➤	NTBK22AA	Option 11E MISP Circuit Card	3,500.00	I	N/A	
S #	NTBK45AB	System Core Pack	MD		960.00	H
S ➤	NTBK45AC	System Core Pack	3,200.00	I	960.00	H
S ➤	NTBK47AB	Expansion Daughterboard	600.00	I	420.00	H
S ➤	NTBK48AA	3-port SDI Cable (1.5m or 5 Ft.)	180.00	D	N/A	
S ➤	NTBK50AA	2.0MB Primary Rate Interface Card	3,750.00	I	350.00	H
S	NTBK51AA	Downloadable DCHI for DDP	2,250.00	I	400.00	H
S	NTBK51BA	Option 11 Downloadable DCHI	1,150.00	I	300.00	H
S ➤	NTBK54AB	Main Fiber Interface (MFI) Kit	590.00	D	355.00	H
S #	NTBK54AC	Main Fiber Interface (MFI) Kit	MD		355.00	H
S ➤	NTBK55AB	Expansion Fiber Interface (EFI) Kit	550.00	D	330.00	H
S #	NTBK55AC	Expansion Fiber Interface (EFI) Kit	MD		330.00	H
S ➤	NTBK62AB	MFI/EFI Power Cable	90.00	D	N/A	
S ➤	NTBK80AA	Ground Bar	75.00	D	N/A	
S ➤	NTBK81AA	Fiber Management Kit	50.00	D	N/A	
S ➤	NTBK83AG	Release 21 Software Cartridge - General Business Package	2,000.00	I	N/A	
S ➤	NTBK83BG	Release 21 Software Cartridge - Enhanced Business Package	3,500.00	I	N/A	
S ➤	NTBK83CG	Release 21 Software Cartridge - Enterprise Business Package	6,500.00	I	N/A	
S ➤	NTBK83DG	Release 21 Software Cartridge - General (No DISA)	2,000.00	I	N/A	
S ➤	NTBK83EG	Release 21 Software Cartridge - Enhanced (No DISA)	3,500.00	I	N/A	
S ➤	NTBK83FG	Release 21 Software Cartridge - Enterprise Business (No DISA)	6,500.00	I	N/A	
S ➤	NTBK83GG	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package	7,500.00	I	N/A	
S ➤	NTBK83HG	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package (No DISA)	7,500.00	I	N/A	
S	NTCG03AA	DDP to Clock Controller Cable (14 Ft.)	75.00	D	N/A	
S	NTCG03AB	DDP to Clock Controller Cable (2 Ft. 8 In.)	50.00	D	N/A	
S	NTCG03AC	DDP to Clock Controller Cable (4 Ft.)	55.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTCG03AD	DDP to Clock Controller Cable (7 Ft.)	60.00	D	N/A	
S ➤	NTCK45AA	Cable - 2.0MB DDP to I/O 8 Ft.	130.00	D	N/A	
S	NTCK46AA	DDP to DCHI Cable (6 Ft.)	130.00	D	N/A	
S	NTCK46AB	DDP to DCHI Cable (18 Ft.)	160.00	D	N/A	
S	NTCK46AC	DDP to DCHI Cable (35 Ft.)	180.00	D	N/A	
S	NTCK46AD	DDP to DCHI Cable (50 Ft.)	200.00	D	N/A	
S ➤	NTCK78AA	Cable - 2.0MB DDP to MDF 50 Ft.	220.00	D	N/A	
S ➤	NTCK79AA	Cable - 2.0MB DDP Coax to LTU 50 Ft.	325.00	D	N/A	
S	NTCK80AA	DDP to MSDL Cable (6 Ft.)	130.00	D	N/A	
S	NTCK80AB	DDP to MSDL Cable (18 Ft.)	160.00	D	N/A	
S	NTCK80AC	DDP to MSDL Cable (35 Ft.)	180.00	D	N/A	
S	NTCK80AD	DDP to MSDL Cable (50 Ft.)	200.00	D	N/A	
S #	NTCW80AA	Meridian Integrated IP Telephony Gateway (ITG) Base Card	MD		1,700.00	H
S ➤	NTCW80CA	Meridian IP Telephony Gateway (ITG) Base Card	3,500.00	D	1,700.00	H
S ➤	NTCW84EA	Meridian ITG 2.0 D-Channel PCMCIA Pigtail Cable	40.00	D	N/A	
S ➤	NTCW84JA	Meridian ITG 2.0 I/O Panel Mounting Connector	40.00	D	N/A	
S ➤	NTCW84KA	Meridian ITG 2.0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter	180.00	D	N/A	
S ➤	NTCW84LA	Meridian ITG 2.0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA)	180.00	D	N/A	
S ➤	NTCW84MA	Meridian ITG 2.0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack	180.00	D	N/A	
S #	NTDF29AB	Remote Digital Extender Card	MD		750.00	H
S	NTDJ65AA	Serial 9 Pin Cable	35.00	D	N/A	
S	NTDJ66AA	ISDN Cable	50.00	D	N/A	
S	NTDJ67AA	10BaseT Ethernet Cable, Crossed	25.00	D	N/A	
S ➤	NTDK16BA	Option 11C Mini 48 Port Digital Line Card	4,575.00	I	150.00	H
S ➤	NTDK18AA	Cabinet Upgrade Kit	850.00	I	N/A	
S ➤	NTDK19AA	SSC Upgrade Kit	800.00	I	N/A	
S #	NTDK20AB	System Core Card	MD		750.00	H
S #	NTDK20AD	Clock Controller (Stratum 3)	MD		225.00	H
S #	NTDK20DA	System Core Card	MD		650.00	H
S ➤	NTDK20EA	Option 11C System Core Card	4,000.00	I	750.00	H
S ➤	NTDK21AA	Option 11C- Blank Software Daughterboard	1,300.00	I	400.00	H
S ➤	NTDK22AA	30 Ft. Fiber Daughterboard - Multi Mode	1,000.00	I	550.00	H
S ➤	NTDK23AA	30 Ft. Fiber Receiver Card	1,000.00	I	550.00	H
S ➤	NTDK23BA	30 Ft. Fiber Receiver Card	1,000.00	I	145.00	H
S ➤	NTDK24AB	2 Mile Fiber Daughterboard - Multi-Mode	4,000.00	I	1,900.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTDK25AB	2 Mile Fiber Receiver Card - Multi-Mode	MD		1,900.00	H
S	NTDK25BB	Fiber Receiver Pack - 2 Mile Multi-Mode	4,000.00	I	280.00	H
S ➤	NTDK26AA	Backwards Compatible Daughterboard	600.00	I	350.00	H
S ➤	NTDK27AA	Ethernet Adapter Cable	75.00	D	N/A	
S ➤	NTDK30AA	Database Upgrade Tool	200.00	I	40.00	H
S ➤	NTDK32AA	EC11 Backplane and Cabinet Assembly	3,500.00	D	N/A	
S ➤	NTDK3302	NLI Cable 10 Ft.	150.00	D	N/A	
S ➤	NTDK3303	NLI Cable 20 Ft.	150.00	D	N/A	
S ➤	NTDK3304	NLI Cable 30 Ft.	150.00	D	N/A	
S ➤	NTDK35AA	AC/DC Power Supply	1,000.00	D	300.00	H
S ➤	NTDK36AA	Bus Terminator	200.00	D	N/A	
S ➤	NTDK48AA	Main Cabinet Cable Kit	200.00	D	N/A	
S ➤	NTDK49AA	Expansion Cabinet Cable Kit	100.00	D	N/A	
S #	NTDK50BA	Main/Expansion Cabinet	MD		550.00	H
S ✓ § ➤	NTDK57AA	Dongle	10.00	D	N/A	
S ➤	NTDK58AA	RSM 4 Port Breakout Cable	300.00	H	N/A	
S ➤	NTDK59AA	Alarm/Modem Cable Assembly-Initial Caps only	100.00	D	N/A	
S ➤	NTDK66AB	Meridian Mail Modem Package	200.00	H	N/A	
S ➤	NTDK68AA	16MB SIMM	850.00	H	N/A	
S	NTDK72AA	DC/DC Power Supply	1,500.00	I	200.00	H
S ➤	NTDK74AB	Card Option 4.5GB Disk Drive	1,200.00	D	260.00	H
B ➤	NTDK78AA	AC/DC Power Supply	1,460.00	I	200.00	H
S ➤	NTDK79AA	2 Mile Fiber Daughterboard Single Mode	4,000.00	I	940.00	H
S #	NTDK80AA	2 Mile Fiber Receiver Card - Single Mode	MD		940.00	H
S ➤	NTDK80BA	2 Mile Fiber Receiver Card - Single Mode	4,000.00	I	330.00	H
N ➤	NTDK81AA	Option 11C Blank Software Daughterboard	1,300.00	I	600.00	H
S ➤	NTDK84AA	30 Ft. DUAL Port Fiber Daughterboard	1,600.00	I	250.00	H
S ➤	NTDK85AA	2 Mile Multi Mode DUAL Port Fiber Daughterboard	6,000.00	I	480.00	H
S	NTDK88AA	Option 11C Mini Main Chassis Cable Kit	130.00	I	N/A	
S	NTDK89AA	Option 11C Mini Chassis Expander Cable Kit	130.00	I	N/A	
S	NTDK91BA	Option 11C Mini Main Chassis	2,500.00	I	N/A	
S ✓	NTDK92BA	Mini Chassis Expander	2,500.00	I	N/A	
S ➤	NTDK97AB	Option 11C Mini System Controller Card (Blank)	4,000.00	I	570.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTDR02AA	Meridian HomeOffice II Router	MD		1,413.00	H
S Δ	NTDR05AC	Meridian HomeOffice II Planning Guide	27.00	H	N/A	
S Δ	NTDR06AC	Meridian HomeOffice II Network Administration Guide	27.00	H	N/A	
S Δ	NTDR07AC	Meridian HomeOffice II Line Card Configuration Guide	27.00	H	N/A	
S Δ	NTDR15AC	Meridian HomeOffice II User Guide	27.00	H	N/A	
S Δ	NTDR16AB	CD ROM with Jewel Case	37.00	H	N/A	
S	NTDR50AB	Multi I/O Cable	99.00	D	N/A	
S	NTDR52AA	Universal Power Supply	124.00	D	62.00	H
S	NTDR58AA	MMI Cable Kit (32 Ft.)	45.00	D	N/A	
S	NTDR59AA	SDI Cable Kit (10 Ft.)	75.00	D	N/A	
S Δ	NTDR60AA	Self-paced Technical Training CD	99.00	H	N/A	
S ✓ ➤	NTDR68AA	Reach Line Card - 16 Port	5,495.00	D	700.00	H
S ✓ ➤	NTDR69AA	Remote Office 9150 Unit	5,995.00	D	700.00	H
S ✓ ➤	NTDR70AA	Reach Line Card - 32 Port - Option 51-81	6,895.00	D	700.00	H
S ✓ ➤	NTDR71AA	Reach Line Card - 32 Port - Option 11	6,895.00	D	700.00	H
S ✓ ➤	NTDR73AA	DSP Application Module	1,295.00	D	200.00	H
S ✓ ➤	NTDR74AA	BRI Module (U Interface)	1,195.00	D	200.00	H
S ➤	NTDR79AA	Reach Line Card Cable - Basic Version	95.00	D	N/A	
S ➤	NTDR80AA	Reach Line Card Cable - Enhanced Version	325.00	D	N/A	
S ✓ ➤ Δ	NTDR81AA	Remote Office Product CD-ROM Package	50.00	H	N/A	
S ➤ Δ	NTDR82AA	MIG Reach Line Card Installation and Administration Guide	20.00	H	N/A	
S ✓ ➤ Δ	NTDR83AA	Remote Office Technical Training CD-ROM Package	90.00	H	N/A	
S ✓ ➤ Δ	NTDR84AA	Remote Office 9150 Installation and Administration Guide	30.00	H	N/A	
S ★ ➤ Δ	NTDR85AA	Remote Office 911x User Guide	30.00	H	N/A	
S ✓ ➤	NTDR87AA	Remote Office 9150 Universal Power Supply	260.00	D	N/A	
S ★ ➤	NTDR88AA	Remote Office 911x North American Power Supply	95.00	D	N/A	
S Δ	NTDW01AA	Meridian Mail Release 13 PC CD-ROM	25.00	H	N/A	
S ★ ➤	NTDW80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM	80.00	D	N/A	
S ★ ➤ Δ	NTDW81AA	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (CD-ROM)	20.00	H	N/A	
N	NTEX35AA	Nortel's 1-Meg Modem			N/A	
S >> # Δ	NTHF01AA	Symposium Express Call Center Release 1.0 Server Application CD			N/A	
S >> #	NTHF02AA	SYMPOSIUM Express Call Center Release 1.0 Client Application CD, English	50.00	H	N/A	
S ➤	NTHF02AB	SYMPOSIUM Express Call Center Release 2.0 Client Application CD, English	50.00	H	N/A	
S >> #	NTHF03AA	SYMPOSIUM Express Call Center Supplementary CD	50.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTHF03AB	Symposium Express Call Center Supplementary CD	50.00	H	N/A	
S >> # Δ	NTHF06AA	SYMPOSIUM Express Call Center Documentation CD	50.00	H	N/A	
S ➤ Δ	NTHF06AB	SYMPOSIUM Express Call Center Documentation CD	50.00	H	N/A	
S ➤ Δ	NTHF07AC	SYMPOSIUM Express Call Center Documentation Suite	150.00	H	N/A	
S ➤	NTHF24AB	SYMPOSIUM Express Call Center Release 2.0 Base System	8,000.00	D	N/A	
S ➤	NTHF28AB	Symposium Express Call Center 1 Agent Increment	570.00	D	N/A	
S ➤	NTHF29AB	Symposium Express Call Center 5 Agent Increment	2,300.00	D	N/A	
S ➤	NTHF30AB	Symposium Express Call Center 10 Agent Increment	4,000.00	D	N/A	
S ✓ ➤	NTHF35AA	SYMPOSIUM Express Call Center LAN Package Option 11C	1,030.00	H	N/A	
S ✓ ➤	NTHF36AA	SYMPOSIUM Express Call Center LAN Package, Options 61C-81C	1,740.00	H	N/A	
S ➤	NTHF63AA	SYMPOSIUM Express Call Center Release 2.0 Base System Upgrade from Release 1.0	600.00	D	N/A	
S ✓ ➤	NTHF69AA	Symposium Express Call Center LAN Package, 51C	1,091.00	H	N/A	
S ✓ ➤	NTHU21AC	Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package AC	64,000.00	I	N/A	
S ✓ ➤	NTHU21DC	Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC	64,000.00	I	N/A	
S ✓ ➤	NTHU22AC	Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Cage Upgrade Package AC	54,000.00	I	N/A	
S ✓ ➤	NTHU22DC	Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Upgrade Package DC	54,000.00	I	N/A	
S ✓ ➤	NTHU24AC	Option 81C from Option 61C (NT5D21) Upgrade AC	34,000.00	I	N/A	
S ✓ ➤	NTHU24DC	Option 81C from Option 61C (NT5D21) Upgrade DC	34,000.00	I	N/A	
S ➤	NTHU28AC	Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/ 51C or 61C (NT9D11, NT5D21) Upgrade Package AC	77,500.00	I	N/A	
S ➤	NTHU28DC	Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/ 51C or 61C (NT9D11, NT5D21) Upgrade Package DC	77,500.00	I	N/A	
S ➤	NTHU29AC	Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package AC	86,500.00	I	N/A	
S ➤	NTHU29DC	Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package DC	86,500.00	I	N/A	
S ✓ ➤	NTHY01AA	Option 81C (CP PII) Systems Spares Package	45,000.00	I	N/A	
S ➤	NTHY01AC	Option 81C (CP PII) Power Supply Spares Package AC	7,000.00	I	N/A	
S ➤	NTHY01DC	Option 81C (CP PII) Power Supply Spares Package DC	7,000.00	I	N/A	
S ✓ ➤	NTHY20AC	Fiber Network Group Assembly Package AC	20,000.00	I	N/A	

✓ Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★ New product introduction	†	Additions & maintenance	➤	See reference book
⊗ Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTHY20DC	Fiber Network Group Assembly Package DC	20,000.00	I	N/A	
S ✓ ➤	NTHY21AA	Option 81C Fiber Core Network Group 0 Kit	8,500.00	I	N/A	
S ✓ ➤	NTHY23AA	FIJI Group Conversion Kit	7,250.00	I	N/A	
S ✓ ➤	NTHY24AC	Fiber Network Group Column Package AC	37,000.00	I	N/A	
S ✓ ➤	NTHY24DC	Fiber Network Group Column Package DC	37,000.00	I	N/A	
S	NTJG06AC	MIRAN 1.56 (Upissue) 8MB PCMCIA Card	600.00	H	N/A	
S ➤	NTJH01AA	ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D	N/A	
S ➤	NTJH01BA	ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D	N/A	
S ➤	NTJH01CA	Meridian MAX-AM Release 3 or 4 to Meridian MAX-SNNE Release 9 Software Upgrade	20,000.00	D	N/A	
S ➤	NTJH01DA	Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	15,000.00	D	N/A	
S ➤	NTJH01EA	Meridian MAX-SNN Release 7 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade	10,000.00	D	N/A	
S ➤	NTJH01FA	Meridian MAX-SNN/SNNE Release 8 to Meridian MAX-SNN/ SNNE Release 9 Software Upgrade	7,500.00	D	N/A	
S ➤	NTJH02AA	ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D	N/A	
S ➤	NTJH02BA	ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D	N/A	
S ✓ ➤	NTJH02CA	Meridian MAX-AM Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade	10,000.00	D	N/A	
S ➤	NTJH02DA	Meridian MAX-IPE Release 4.62, 5 or 6 to Meridian MAX-IPE/ IPEE Release 9 Software Upgrade	7,500.00	D	N/A	
S ➤	NTJH02EA	Meridian MAX-IPE/IPEE Release 7 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	6,000.00	D	N/A	
S ➤	NTJH02FA	Meridian MAX-IPE/IPEE Release 8 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade	5,000.00	D	N/A	
S ➤ Δ	NTJH05AA	Meridian MAX-SNN/SNNE Release 9 Software Replacement/ Upissue	No charge		N/A	
S ➤ Δ	NTJH05BA	Meridian MAX-IPE/IPEE Release 9 Software Replacement/ Upissue	No charge		N/A	
S ➤	NTJH09AB	Meridian Terminal Emulator (MTE) Release 9.3 Software (Single User)	400.00	D	N/A	
S ➤	NTJH09BB	Meridian Terminal Emulator (MTE) Release 9.3 Software (System License)	4,000.00	D	N/A	
S ➤	NTJH09CB	Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (Single User)	100.00	D	N/A	
S ➤	NTJH09DB	Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (System License)	1,000.00	D	N/A	
S ➤	NTJH10AA	Meridian MAX-SNNE Release 9 Fundamental Software	35,000.00	D	N/A	
S ➤	NTJH10BA	Meridian MAX-SNNE Release 9 Enhanced Software	65,000.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTJH10CA	Meridian MAX-SNNE Release 9 Virtual Software	80,000.00	D	N/A	
S ➤	NTJH10DA	Meridian MAX-SNN/SNNE Release 9 Fundamental to Enhanced Feature Level Promotion	35,000.00	D	N/A	
S ➤	NTJH10EA	Meridian MAX-SNN/SNNE Release 9 Enhanced to Virtual Feature Level Promotion	20,000.00	D	N/A	
S ➤	NTJH11AA	Meridian MAX-IPEE Release 9 Fundamental Software	5,000.00	D	N/A	
S ➤	NTJH11BA	Meridian MAX-IPEE Release 9 Enhanced Software	15,000.00	D	N/A	
S ➤	NTJH11CA	Meridian MAX-IPEE Release 9 Virtual Software	17,500.00	D	N/A	
S ➤	NTJH11DA	Meridian MAX-IPE/IPEE Release 9 Fundamental to Enhanced Feature Level Promotion	12,500.00	D	N/A	
S ➤	NTJH11EA	Meridian MAX-IPE/IPEE Release 9 Enhanced to Virtual Feature Level Promotion	5,000.00	D	N/A	
S ➤ Δ	NTJH12AA	Meridian MAX Release 9 Software Migration from MAX-SNN to MAX-SNNE	No charge		N/A	
S ➤	NTJH12BA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Fundamental to MAX-SNNE Fundamental	35,000.00	D	N/A	
S ➤	NTJH12CA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Enhanced to MAX-SNNE Enhanced	55,000.00	D	N/A	
S ➤	NTJH12DA	Meridian MAX Release 9 Software Migration from MAX-IPE/ IPEE Virtual to MAX-SNNE Virtual	67,500.00	D	N/A	
S ➤	NTJH15AA	PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power	22,500.00	D	N/A	
S ➤	NTJH15BA	PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power	22,500.00	D	N/A	
S ➤	NTJH15CA	Meridian Option MAX/MAX-SEE to Meridian MAX-SNNE Hardware Upgrade	20,000.00	D	N/A	
S ➤	NTJH15DA	Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade	17,500.00	D	N/A	
S ➤	NTJH15EA	Meridian MAX-SNNE System Hardware, DC Power	25,000.00	D	N/A	
S ➤	NTJH15FA	Meridian MAX-SNNE System Hardware, AC Power	25,000.00	D	N/A	
S ➤	NTJH17AA	Meridian MAX-IPEE Module (Option 11)	12,500.00	D	N/A	
S ➤	NTJH17BA	Meridian MAX-IPEE Module (Option 21-81C)	12,500.00	D	N/A	
S ➤ Δ	NTJH90AA	Meridian MAX-AM Release 6 Software Media Replacement/ Upissue	No charge		N/A	
S ➤ Δ	NTJH91AA	Meridian MAX-IPE Release 6 Software Media Replacement/ Upissue	No charge		N/A	
S ➤	NTJH92AA	Meridian NAC-AM Release 2.5 Upissue/Software Replacement	No charge		N/A	
S ➤	NTJH93AA	IPE/IPEE Option 11 to Option 21-81C Conversion Kit	1,100.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTJH93BA	IPE/IPEE Option 21-81C to Option 11 Conversion Kit	1,100.00	D	N/A	
S ➤ Δ	NTJH93FA	MAX-IPE to IPEE Upgrade Kit #2	725.00	H	N/A	
S ➤ Δ	NTJH94AA	Meridian MAX Release 9 Supervisor's User Guide (English); Package of 10	400.00	H	N/A	
S § ➤ Δ	NTJH95AA	Meridian Terminal Emulator (MTE) Release 9 User Guide (Multilingual: English, French, Spanish); Package of 10	160.00	H	N/A	
S ➤ Δ	NTJH97AA	Meridian MAX-AM Release 7.5 Software Media Replacement/ Upissue	No charge		N/A	
S ➤ Δ	NTJH97BA	Meridian MAX-IPE/IPEE Release 7.5 Software Media Replacement/Upissue	No charge		N/A	
S ➤ Δ	NTJH98AA	Meridian MAX-AM Release 8 Software Media Replacement/ Upissue	No charge		N/A	
S ➤ Δ	NTJH98BA	Meridian MAX-IPE/IPEE Release 8 Software Media Replacement/Upissue	No charge		N/A	
S ★ ➤	NTJR27AA	CallPilot 1.07 Telset User Guide Package - Canadian French	100.00	H	N/A	
S ★ Δ	NTJR48AA	CallPilot Telset Guide Package (Quantity 10), English	90.00	H	N/A	
B ➤ Δ	NTKG80CF	Option 11C Mini Release 25 English Documentation Package, Coil	90.00	H	N/A	
S § ➤	NTKS1002	Option 11C Compact InterOffice Communications Package	2,150.00	I	N/A	
S ➤	NTKS1005	Option 11C Compact Spares Package	10,500.00	I	N/A	
S ➤	NTKS1011	Option 11C Compact Advanced Hospitality Communications Package	6,000.00	I	N/A	
S † ➤	NTKS1012	Journal Call Accounting Software with Billing	8,400.00	I	N/A	
S ➤	NTKS1013	Registrar Front Desk Software with Billing	8,400.00	I	N/A	
S ➤	NTKS1015	Journal/Registrar Software CDROM Up-Issue	50.00	H	N/A	
S ➤	NTKS2001	Option 11C Compact Office Communications Package - Additional 8 TN's	1,470.00	I	N/A	
S § ➤	NTKS2002	Option 11C Compact InterOffice Communications Package - Additional 8 TN's	1,870.00	I	N/A	
S ➤	NTKS2010	Option 11C Compact Hospitality Communications Expansion TN's	1,050.00	I	N/A	
S ➤	NTKS2011	Option 11C Compact Advanced Hospitality Package - Additional 8 TN's	2,100.00	I	N/A	
S ➤ Δ	NTKS2020	Option 11C Compact Network Message Communications Expansion TN's (8)	2,057.00	I	N/A	
S ➤	NTKS2050	Compact Option Dual Language Prompting	No charge		N/A	
S ➤	NTKS2051	Compact Option Additional Language	600.00	D	N/A	
S § ➤	NTKS2052	Meridian Mail Release 11 or Release 12 to Release 13 Compact Option Software Upgrade Package	1,000.00	D	N/A	
S ➤	NTKS2500	X27 Software Up-issue (within the same Release)	1,050.00	I	N/A	
S ➤	NTKS2501	X27 Software Release Upgrade	1,300.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S § ➤	NTKS3001	Meridian Mail Release 12 Compact Option 4 Ports 24 Hours Package	10,000.00	D	N/A	
S § ➤	NTKS9050	DISA Option 11C Compact	No charge		N/A	
S ➤	NTKS9051	This code allows the addition software packages to be enabled for Inter-Office Feature Set.	2,000.00	I	N/A	
S Δ	NTLH01AA	CD-ROM, X11 Release 25	150.00	H	N/A	
S ➤ Δ	NTLH02AA	Meridian 1 Reference Library, Release 25	250.00	H	N/A	
S Δ	NTLH03AA	System Planning and Engineering Guide	50.00	H	N/A	
S Δ	NTLH04AA	System Installation and Maintenance Guide	50.00	H	N/A	
S Δ	NTLH05AA	System and Software Upgrade Guide	50.00	H	N/A	
S Δ	NTLH06AA	Remote Peripheral Equipment Guide	50.00	H	N/A	
S Δ	NTLH08AA	X11 Software Features Guide	50.00	H	N/A	
S Δ	NTLH09AA	X11 Input/Output Guide	50.00	H	N/A	
S Δ	NTLH10AA	X11 System Management, Overview, Applications and Security Guide	50.00	H	N/A	
S Δ	NTLH11AA	X11 Networking Features	50.00	H	N/A	
S Δ	NTLH12AA	X11 Data Features	50.00	H	N/A	
S Δ	NTLH13AA	ACD Reference Guides	50.00	H	N/A	
S Δ	NTLH14AA	X11 Hospitality Features	50.00	H	N/A	
S Δ	NTLH16AA	Meridian IP Telecommuter NTP CD ROM	10.00	H	N/A	
S ➤	NTLT83AA	MIRAN to MIRAN Release 2 Card Upgrade Kit	3,600.00	D	N/A	
S #	NTMA09AA	DC Power Converter	MD		750.00	H
S #	NTMA11AA	4-Port DS1 Function Processor	MD		2,200.00	H
S #	NTMA12AA	1-port DS1V Functional Processor	MD		2,200.00	H
S #	NTMA12AC	1-Port DS1V Function Processor	MD		2,200.00	H
S #	NTMA13AA	4-Port DS1C (Channelized) Function Processor	MD		2,200.00	H
S #	NTMA17AA	8-Port V.11 Function Processor	MD		2,200.00	H
S #	NTMA18AA	8-port V.35 Functional Processor	MD		2,200.00	H
S #	NTMA18AB	8-Port V.35 Function Processor	MD		2,200.00	H
S #	NTMA20AA	1-Port DS3 Function Processor	MD		2,200.00	H
S #	NTMA21AA	Control Processor e/w 256 MB Hard Drive	MD		2,200.00	H
S #	NTMA21AB	Control Processor e/w 810 MB Hard Drive	MD		2,200.00	H
S #	NTMA22AA	3-Port DS1 ATM Function Processor	MD		2,200.00	H
S #	NTMA24AA	3-Port DS3 ATM Function Processor	MD		2,200.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTMA49AA	3-Port DS3/E3 Termination Panel	MD		160.00	H
S #	NTMA75AB	V.11 Termination Panel	MD		160.00	H
S #	NTMA76AA	DS1/E1 Termination Panel	MD		160.00	H
S #	NTMA78AB	V.35 Termination Panel	MD		160.00	H
S #	NTMA79AA	DS3/E3 Termination Panel	MD		160.00	H
S	NTMF94DA	Meridian ITG Backplane and D-Sub Com Port Cable	180.00	D	N/A	
S ➤	NTMF94EA	Meridian ITG 2.0 ELAN, TLAN, RS232 Port Cable	180.00	D	N/A	
S ➤	NTMN0006	Key Cap Package (M3905)	5.00	D	N/A	
S ➤	NTMN13AA66	Footstand, Platinum (M3901, M3902)	8.00	D	N/A	
S ➤	NTMN13AA70	Footstand, Charcoal (M3901, M3902)	8.00	D	N/A	
S ➤	NTMN14AA66	Footstand, Platinum (M3903, M3904, M3905)	8.00	D	N/A	
S ➤	NTMN14AA70	Footstand, Charcoal (M3903, M3904, M3905)	8.00	D	N/A	
S ➤	NTMN15AA66	Meridian Wall Mount Kit, Platinum (M3903, M3904, M3905)	10.00	D	N/A	
S ➤	NTMN15AA70	Meridian Wall Mount Kit, Charcoal (M3903, M3904, M3905)	10.00	D	N/A	
S ✓ ➤	NTMN16AA66	Brandline Insert, Platinum (Package of 250 P0904456, M3900 Series)	180.00	H	N/A	
S ✓ ➤	NTMN16AA70	Brandline Insert, Charcoal (Package of 250 P0904455, M3900 Series)	180.00	H	N/A	
S ✓ ➤	NTMN17AA66	Handset, Platinum (M3900 Series)	40.00	D	N/A	
S ✓ ➤	NTMN17AA70	Handset, Charcoal (M3900 Series)	40.00	D	N/A	
S ✓ ➤	NTMN18AA66	Handset Kit, Platinum (M3905)	42.00	D	N/A	
S ✓ ➤	NTMN18AA70	Handset Kit, Charcoal (M3905)	42.00	D	N/A	
S ➤	NTMN19AA	Key Cap Tool (M3905)	25.00	D	N/A	
S ➤	NTMN31BA66	Meridian M3901 Entry, Platinum	80.00	D	35.00	H
S ➤	NTMN31BA70	Meridian M3901 Entry, Charcoal	80.00	D	35.00	H
S ➤	NTMN32BA66	Meridian M3902 Basic, Platinum	165.00	D	60.00	H
S ➤	NTMN32BA70	Meridian M3902 Basic, Charcoal	165.00	D	60.00	H
S ➤	NTMN33BA66	Meridian M3903 Enhanced, Release 1, Platinum	335.00	D	85.00	H
S ➤	NTMN33BA70	Meridian M3903 Enhanced, Release 1, Charcoal	335.00	D	85.00	H
S ➤	NTMN33FA66	Meridian M3903 Enhanced, Release 2, Platinum	335.00	D	85.00	H
S ➤	NTMN33FA70	Meridian M3903 Enhanced, Release 2, Charcoal	335.00	D	85.00	H
S ➤	NTMN34BA66	Meridian M3904 Professional, Release 1, Platinum	550.00	D	120.00	H
S ➤	NTMN34BA70	Meridian M3904 Professional, Release 1, Charcoal	550.00	D	120.00	H
S ➤	NTMN34FA66	Meridian M3904 Professional, Release 2, Platinum	550.00	D	120.00	H
S ➤	NTMN34FA70	Meridian M3904 Professional, Release 2, Charcoal	550.00	D	120.00	H
S ➤	NTMN35BA66	Meridian M3905 Call Center, Release 1, Platinum	550.00	D	120.00	H
S ➤	NTMN35BA70	Meridian M3905 Call Center, Release 1, Charcoal	550.00	D	120.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ★ ➤	NTMN35FA-66	Meridian M3905 Call Center, Release 2, Platinum	550.00	D	120.00	H
S ★ ➤	NTMN35FA-70	Meridian M3905 Call Center, Release 2, Charcoal	550.00	D	120.00	H
S	NTMN37AA66	Key-based Expansion Module Without Footstand, Platinum	150.00	D	No charge	H
S ➤	NTMN37AA70	Key-based Expansion Module Without Footstand, Charcoal	150.00	D	No charge	H
S ➤	NTMN38AA66	Key-based Expansion Module Kit 1, Platinum	10.00	D	No charge	H
S ➤	NTMN38AA70	Key-based Expansion Module Kit 1, Charcoal	10.00	D	No charge	H
S ➤	NTMN38BA66	Key-based Expansion Module Kit 2, Platinum	12.00	D	No charge	H
S ➤	NTMN38BA70	Key-based Expansion Module Kit 2, Charcoal	12.00	D	No charge	H
S ➤	NTMN59AA66	Meridian External Alerter and Recording Interface, Platinum (M3900 Series)	100.00	D	N/A	
S ➤	NTMN59AA70	Meridian External Alerter and Recording Interface, Charcoal (M3900 Series)	100.00	D	N/A	
S ✓ #	NTMN66AA66	Meridian Key-Based Expansion Module, Platinum (M3900 Series)	MD		35.00	H
S ✓ #	NTMN66AA70	Meridian Key-Based Expansion Module, Charcoal (M3900 Series)	MD		35.00	H
S ➤	NTMN67AA66	Meridian Display-Based Expansion Module, Platinum (M3900 Series)	170.00	D	N/A	
S ➤	NTMN67AA70	Meridian Display-Based Expansion Module, Charcoal (M3900 Series)	170.00	D	N/A	
S ➤	NTMN68AA66	Meridian Analog Terminal Adapter (ATA), Platinum (M3900 Series)	190.00	D	40.00	H
S ➤	NTMN68AA70	Meridian Analog Terminal Adapter (ATA), Charcoal (M3900 Series)	190.00	D	40.00	H
S ✓ #	NTMN69AA66	Meridian Communications Adapter (MCA), Platinum (M3900 Series)	MD		70.00	H
S ✓ #	NTMN69AA70	Meridian Communications Adapter (MCA), Charcoal (M3900 Series)	MD		70.00	H
S ✓ ➤	NTMN71AA66	Meridian Accessory Connection Module (ACM), Platinum (M3900 Series)	35.00	D	N/A	
S ✓ ➤	NTMN71AA70	Meridian Accessory Connection Module (ACM), Charcoal (M3900 Series)	35.00	D	N/A	
S ➤	NTMN80AA	Wall Transformer (M3900 Series)	40.00	D	N/A	
S ➤	NTMN82AA66	Meridian Personal Directory PC Utility, Platinum (M3900 Series)	100.00	D	N/A	
S ➤	NTMN82AA70	Meridian Personal Directory PC Utility, Charcoal (M3900 Series)	100.00	D	N/A	
S ➤	NTMW01AA	Option 11C Compact System Core Card	4,000.00	I	750.00	H
S #	NTMW02AA	Meridian Mail Compact Option 68K Memory Card	MD		1,200.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S § ➤	NTMW02AB	Meridian Mail Compact Option 68K Memory Card	3,600.00	D	945.00	H
S § ➤	NTMW03AA	4-Port DSP Daughter Card	4,500.00	D	500.00	H
S ➤	NTMW04AA	Mini IPE 1.5MB DTI/PRI Card	2,400.00	I	450.00	H
S ➤	NTMW05AA	Mini IPE 24 Port Digital Line Card	2,400.00	I	400.00	H
S ➤	NTMW06AA	Mini IPE 16 Port Analog Line Card	2,400.00	I	400.00	H
S ➤	NTMW07AA	Mini IPE 4 Port Trunk/4 Port Line Card	2,150.00	I	500.00	H
S † ➤	NTMW0802	Option 11C Compact Cabinet Fan Assembly	180.00	I	N/A	
S ➤	NTMW08AA	Option 11C Compact Cabinet Assembly	N/A		550.00	H
S ➤	NTMW10AA	Option 11C Compact - 10m Fiber Receiver Card	1,000.00	I	550.00	H
S #	NTMW11AA	Option 11C Compact AC Power Supply	MD		200.00	H
S § ➤	NTMW11AB	Option 11C Compact AC Power Supply	1,460.00	I	200.00	H
S § ➤	NTMW14AA	Option 11C Compact Expansion Cabinet Package	8,000.00	I	N/A	
S ➤	NTMW14BA	Option 11C Compact Hospitality 10-slot Expansion Cabinet Package	8,000.00	I	N/A	
S § ➤	NTMW16AA	Meridian Mail Release 11 Compact Option Port Expansion (Ports 5 & 6)	2,700.00	I	N/A	
S § ➤	NTMW16AB	Meridian Mail Release 12 Compact Option Port Expansion (Ports 5 & 6)	2,700.00	I	N/A	
S § ➤	NTMW16BA	Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 5 & 6)	2,700.00	I	N/A	
S § ➤	NTMW17AA	Meridian Mail Release 11 Compact Option Port Expansion (Ports 7&8)	2,700.00	I	N/A	
S § ➤	NTMW17AB	Meridian Mail Release 12 Compact Option Port Expansion (Ports 7 & 8)	2,700.00	I	N/A	
S § ➤	NTMW17BA	Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 7 & 8)	2,700.00	I	N/A	
S #	NTMW30AC	Option 11C Compact Release 1.10 Programmed Software Daughterboard	MD		475.00	H
S ➤	NTMW30AD	Option 11C Compact Release 2.0 Programmed Software Daughterboard	1,420.00	I	475.00	H
S ➤	NTMW30BA	Option 11C Compact Software Delivery Card (PCMCIA) Release 1.00	1,500.00	I	N/A	
S	NTMW30BB	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.01	1,500.00	I	N/A	
S	NTMW30BC	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.10	1,500.00	I	N/A	
S	NTMW30BD	Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 2.0	1,500.00	I	N/A	
S Δ	NTMW35AA	Option 11C Compact Hospitality 10-slot cabinet	N/A		1,200.00	H
S § ➤	NTMW37AA	Mini IPE 1.5MB DTI/PRI Cable	300.00	D	N/A	
S § ➤	NTMW38AA	Mini IPE 1.5MB DTI/PRI Package	2,400.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	NTMW42CA	Option 11C Compact Documentation Library (CDROM)	55.00	H	N/A	
S ➤ Δ	NTMW43BA	Option 11C Compact Customer Documentation Package	160.00	H	N/A	
S ➤	NTMW44AA	Mini IPE 4 Port Trunk Card	1,700.00	I	345.00	H
S	NTMW50AA	Compact Hospitality RS-232 Serial Module	1,000.00	I	350.00	H
S	NTMW55AA	Compact Hospitality Guest Administration Console RS232 Cable (40 ft.)	75.00	D	N/A	
S #	NTND01BA	Integrated CPU/6 Mbyte Memory Card	MD		350.00	H
S #	NTND01CA	Integrated CPU/12MB Memory Card	MD		350.00	H
S #	NTND02BA	SDI/Peripheral Signaling Card with Battery	MD		350.00	H
S #	NTND05AA	Meridian Mail Modular GP Power Supply DC	MD		650.00	H
S #	NTND08AA	ROM Card	MD		350.00	H
S #	NTND08AB	ROM Card	MD		350.00	H
S #	NTND08AC	ROM Card	MD		350.00	H
S #	NTND08AE	ROM Card	MD		350.00	H
S #	NTND09BA	6 Mbyte Memory Card	MD		350.00	H
S #	NTND09CA	12 Mbyte Memory Card	MD		350.00	H
S #	NTND10AA	Changeover & Memory Arbitrator Card	MD		350.00	H
S ➤	NTND11BA	CP to CP Cable (6 Ft.)	170.00	D	N/A	
S ➤	NTND13BC	IOP to IOP SCSI Cable (6 Ft.)	170.00	D	N/A	
S	NTND14BA	CNI to 3PE Cable (5 Ft.)	150.00	D	N/A	
S ➤	NTND14BB	CNI to 3PE Cable (10 Ft.)	150.00	D	N/A	
S ➤	NTND14BC	CNI to 3PE Cable (12 Ft.)	150.00	D	N/A	
S ➤	NTND14BD	CNI to 3PE Cable (12 Ft.)	160.00	D	N/A	
S ➤	NTND14BE	CNI to 3PE Cable (25 Ft.)	160.00	D	N/A	
S ➤	NTND14BG	CNI-3 to 3PE (35 Ft.)	160.00	D	N/A	
S ➤	NTND14BX	CNI-3 to 3PE Cable (50 Ft.)	160.00	D	N/A	
S #	NTND15AA	4 Mbyte Floppy Disk Unit	MD		200.00	H
S #	NTND16AA	4 Mbyte Multi-Disk Unit	MD		550.00	H
S ➤	NTND20AA	Alarm Terminator	50.00	I	N/A	
S ➤	NTND26AA	MSDL DCHI Interface Cable (6 Ft.)	130.00	D	N/A	
S ➤	NTND26AB	MSDL DCHI Interface Cable (18 Ft.)	160.00	D	N/A	
S ➤	NTND26AC	MSDL DCHI Interface Cable (35 Ft.)	180.00	D	N/A	
S ➤	NTND26AD	MSDL DCHI Interface Cable (50 Ft.)	200.00	D	N/A	
S ➤	NTND27AB	MSDL to I/O Panel Cable (6 Ft.)	150.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTND28BB	Inter-Cabinet Clock Cable (16 Ft.)	180.00	D	N/A	
S ➤	NTND28BC	Inter-Cabinet Network Cable (22 Ft.)	300.00	D	N/A	
S ➤	NTND29AA	CPU Interface Cable (6 Ft.)	35.00	D	N/A	
S ➤	NTND30AA	Junctor to I/O Housing Cable (6 Ft.)	35.00	D	N/A	
S #	NTND31AA	ROM Card	MD		350.00	H
S #	NTND31AB	ROM Card	MD		350.00	H
S ➤	NTND33CC	Core-Cabinet Upgrade Cable Kit, Groups 1-4	4,700.00	D	N/A	
S ➤	NTND33DA	Option 81C Core Cabinet Cable Kit, Group 0	4,000.00	I	N/A	
S ➤	NTND36AA	Meridian Communications Unit	850.00	D	195.00	H
S ➤	NTND82AA	RS232 Null Modem Cable (10 Ft.)	45.00	D	N/A	
S	NTND82AB	RS232 Null Modem Cable (25 Ft.)	75.00	D	N/A	
S ➤	NTND91AA	RS232 Straight Cable (10 Ft.)	65.00	D	N/A	
S ➤	NTND91AB	RS232 Straight Cable (25 Ft.)	110.00	D	N/A	
S ➤	NTND93AA	Null Modem Adapter	80.00	H	N/A	
S ➤	NTND94DA	CNI to I/O Panel Ethernet Cable (20 In.)	100.00	D	N/A	
S ➤	NTND95AA	3PE to I/O Housing Cable (8 Ft.)	140.00	D	N/A	
S ➤	NTNH13AA	Meridian IP Telecommuter Client Application CD	25.00	D	N/A	
S ➤	NTQR01AA	Meridian HomeOffice II Router (NTQR03AA) with M2616	2,395.00	D	N/A	
S ➤	NTQR01BA	Meridian HomeOffice II Router ACD with M2216 Digital Set	2,395.00	D	N/A	
S ➤	NTQR02AA	Meridian HomeOffice II Line Card C/W Management/ Interconnect Cable and Installer Notes	4,760.00	D	750.00	H
S	NTQR03AA	Meridian HomeOffice II Router C/W CD-ROM, User Guide; ISDN, Ethernet & Admin Cables; Online Call Keycap & Power Supply	1,950.00	D	620.00	H
S ✓ ➤	NTQR05AA	Remote Office 9150 8-User VoIP Package - 16 RLC	7,995.00	D	N/A	
S ✓ ➤	NTQR06AA	Remote Office 9150 8-User Starter Package - 16 RLC	9,145.00	D	N/A	
S ✓ ➤	NTQR07AA	Remote Office 9150 8-User Starter Package - 32 RLC Option 51-81	11,445.00	D	N/A	
S ✓ ➤	NTQR08AA	Remote Office 9150 8-User Starter Package - 32 RLC Option 11	11,445.00	D	N/A	
S ✓ ➤	NTQR09AA	Remote Office 9150 Branch Expansion Package	6,995.00	D	N/A	
S ✓ ➤	NTQR10AA	Remote Office 9150 8-User Expansion Package	2,195.00	D	N/A	
S ★ ➤	NTQR11AA	Remote Office 9115 4-User Starter Package - 16 RLC	7,295.00	D	N/A	
S ★ ➤	NTQR12AA	Remote Office 9115 4-User Expansion Package - 16 RLC	4,485.00	D	N/A	
S ★ ➤	NTQR14AA	Remote Office 9110 4-User Starter Package - 16 RLC	7,295.00	D	N/A	
S ★ ➤	NTQR15AA	Remote Office 9110 4-User Expansion Package - 16 RLC	4,485.00	D	N/A	
S ★ ➤	NTQR16AA	Remote Office 9110 Unit with North American Power Supply	845.00	D	150.00	H
S ★ ➤	NTQR17AA	Remote Office 9115 Unit with North American Power Supply	895.00	D	150.00	H
S ➤	NTRB18AA	MGate Card	500.00	D	150.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTRB18BA	CallPilot MGate Card	N/A		175.00	H
S ➤	NTRB18CA	MGate Card	500.00	D	175.00	H
B ➤	NTRB21AA	T1 Multipurpose Digital Interface (TMDI)	3,200.00	I	450.00	H
S ➤	NTRB33AA	Fiber Junctor Interface Card (FIJI)	4,400.00	I	N/A	
S ➤	NTRB34AA	Core-to-Network Interface Card (CNI-3)	2,200.00	I	N/A	
S ➤	NTRC17AA	CP PII Ethernet to Ethernet Cable (8.5 Ft./3m)	90.00	D	N/A	
S ➤	NTRC46AA	Clock to FIJI Cable, (4 Ft.-4.5 Ft.)	55.00	D	N/A	
S ➤	NTRC46BA	Clock to FIJI Cable, (5.5 Ft.-8 Ft.)	60.00	D	N/A	
S ➤	NTRC46CA	Clock to FIJI Cable, (22 Ft.)	60.00	D	N/A	
S ➤	NTRC47AA	FIJI to FIJI Synch Cable	50.00	D	N/A	
S ➤	NTRC48AA	FIJI to FIJI Fiber Ring Cable, (6 Ft./2M)	40.00	D	N/A	
S ➤	NTRC48BA	FIJI to FIJI Fiber Ring Cable, (10 Ft./3M)	50.00	D	N/A	
S ➤	NTRC48CA	FIJI to FIJI Fiber Ring Cable, (12 Ft./3.6M)	50.00	D	N/A	
S ➤	NTRC48DA	FIJI to FIJI Fiber Ring Cable, (14 Ft./4.2M)	50.00	D	N/A	
S ➤	NTRC48EA	FIJI to FIJI Fiber Ring Cable, (19 Ft./6M)	60.00	D	N/A	
S ➤	NTRC48FA	FIJI to FIJI Fiber Ring Cable, (26 Ft./8M)	60.00	D	N/A	
S ➤	NTRC48GA	FIJI to FIJI Fiber Ring Cable, (32 Ft./10M)	60.00	D	N/A	
S ➤	NTRC48HA	FIJI Fiber Ring Cable, (50 Ft.)	60.00	D	N/A	
S ➤	NTRC49AA	Fiber Network Clock-Clock Synch Cable, (6 Ft.)	50.00	D	N/A	
S ➤	NTRC49BA	Fiber Network Clock-Clock Synch Cable, (20 Ft.)	60.00	D	N/A	
S ➤	NTRD25AA	Pedestal Assembly AC	6,800.00	I	N/A	
S ➤	NTRD25BA	Pedestal Assembly DC	6,000.00	I	N/A	
S	NTRE18AA	Front/Rear Cover	170.00	I	N/A	
S ➤	NTRE39AA	Optical Cable Management Card (OCMC)	50.00	I	N/A	
S ➤	NTRE40AA	Dual Ethernet Adapter RJ45 for I/O Panel	60.00	D	N/A	
S ★ ➤ Δ	NTRG08AD	CallPilot 1.07 IPE (200i) Base Documentation Package	380.00	H	N/A	
S ★ ➤	NTRG09AD	702t Base Documentation Package, English	380.00	H	N/A	
S ★ ➤	NTRG10AD	CallPilot 1.07 1001rp Base Documentation Package, English	380.00	H	N/A	
S ✓ ➤ Δ	NTRG11AB	CallPilot Basic Administration Documentation Package - English	115.00	H	N/A	
S ✓ ➤ Δ	NTRG11AC	CallPilot Basic Administration Documentation Package - English	500.00	H	N/A	
S ➤ Δ	NTRG12AA	CallPilot Advanced Administration Documentation Package - English	245.00	H	N/A	
S Δ	NTRG13AA	CallPilot Telset Guide Package	30.00	H	N/A	
S ➤ Δ	NTRG13AB	CallPilot Telset Guides, English, Quantity 15	50.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	NTRG13BB	CallPilot Telset Guides, French, Quantity 15	70.00	H	N/A	
S ➤ Δ	NTRG14AA	CallPilot AMIS Networking Documentation Package - English	60.00	H	N/A	
S ✓ ➤ Δ	NTRG14AC	CallPilot 1.07 Networking Package	100.00	H	N/A	
S ➤ Δ	NTRG15AA	CallPilot Enterprise Networking Documentation Package - English	60.00	H	N/A	
S ★ ➤ Δ	NTRG15AC	CallPilot 1.07 Installation and Configuration Guide Package	110.00	H	N/A	
S ➤ Δ	NTRG16AA	CallPilot VPIM Networking Documentation Package - English	60.00	H	N/A	
S ★ ➤ Δ	NTRG16AC	CallPilot 1.07 702t Installation and Configuration Guide Package	110.00	H	N/A	
S ➤ Δ	NTRG17AA	CallPilot NMS Networking Documentation Package - English	60.00	H	N/A	
S ★ ➤ Δ	NTRG17AC	CallPilot 1.07 1001rp Installation and Configuration Guide	110.00	H	N/A	
S ➤ Δ	NTRG18AA	CallPilot Integrated AMIS Networking Documentation Package - English	60.00	H	N/A	
S ➤ Δ	NTRG19AB	CallPilot Documentation CD ROM	35.00	H	N/A	
S ★ ➤ Δ	NTRG19AC	CallPilot 1.07 Documentation CD-ROM	25.00	H	N/A	
S ➤ Δ	NTRG19AD	CallPilot 1.06 Documentation CD-ROM	21.00	H	N/A	
S ➤	NTRG20AA	CallPilot Installation Worksheet Package	20.00	H	N/A	
S ➤ Δ	NTRG22AA	Desktop Messaging Quick Reference Guide, Quantity 25	100.00	H	N/A	
S ★ ➤ Δ	NTRG22AC	CallPilot 1.07 Desktop Messaging Quick Reference Guide, Quantity 10	50.00	H	N/A	
S ➤ Δ	NTRG22BA	Desktop Messaging Quick Reference Guide, Quantity 100	400.00	H	N/A	
S ➤ Δ	NTRG22CB	Desktop Messaging Quick Reference Guide French - Package of 25	240.00	H	N/A	
S ➤ Δ	NTRG22DB	Desktop Messaging Quick Reference Guide - French - Package of 100	950.00	H	N/A	
S ★ ➤ Δ	NTRG22EC	CallPilot 1.07 Desktop Quick Reference Guide Package, French	50.00	H	N/A	
S ✓ ➤	NTRH01AA	CallPilot MPC-8	500.00	D	N/A	
S ✓	NTRH0910	Break Interconnect Cable (6 Ft.)	150.00	D	N/A	
S ✓	NTRH0911	Cable Assembly, Breakout Box InterconnectCable, 15 Ft.	150.00	D	N/A	
S ★	NTRH0914	Analog Loop Start Cable	170.00	D	N/A	
S ★	NTRH0915	CT to CT Bus Cable	90.00	D	N/A	
S ✓ ➤	NTRH09AA	Breakout Panel Assembly	370.00	D	175.00	H
S ✓ ➤	NTRH1405	CallPilot Internal Ethernet Cabling (IPE System)	30.00	D	N/A	
S ✓ ➤	NTRH1406	CallPilot Token Ring Cabling (IPE System)	125.00	D	N/A	
S ✓ ➤	NTRH1407	CallPilot Intermediate SCSI Cable	180.00	D	N/A	
S ✓ ➤	NTRH1408	CallPilot Intermediate SCSI Cable	110.00	D	N/A	
S ✓ ➤	NTRH1409	CallPilot Intermediate SCSI Cable	110.00	D	N/A	
S ✓	NTRH14AA	200 Series Base System Assembly	3,620.00	D	1,435.00	H
S ✓ ➤	NTRH16BA	Hard Drive Data Cable	35.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTRH2010	CallPilot MGate Cable - 20 Ft.	115.00	D	N/A	
S ➤	NTRH2011	CallPilot MPB-16 Cable	80.00	D	N/A	
S	NTRH2012	CallPilot MGate Cable - 20ft	300.00	D	N/A	
S	NTRH2013	Dual DSX30XV Interconnect Cable	500.00	D	N/A	
S #	NTRH20AA	CallPilot MPB-16	MD		925.00	H
S ✓	NTRH20BA	MPB 16-4	2,300.00	D	N/A	
S ★	NTRH21CA	MPB 16-2T Carrier Card	1,410.00	D	N/A	
S	NTRH8003	SCSI RAID Drivers	12.00	D	N/A	
S	NTRH8025	702t BIOS	10.00	D	N/A	
S	NTRH8026	702t System Setup Utility	10.00	D	N/A	
S ✓ ➤	NTRH8027	Windows NT 4.0 OS Recovery CD	10.00	D	N/A	
S	NTRH8032	1001rp PII SBC BIOS 1001rp AC and DC	3.00	D	N/A	
S ✓	NTRH8033	Windows NT 4.0 Install Diskette	10.00	D	N/A	
S	NTRH8042	Pentium III BIOS	3.00	D	N/A	
S ★ ➤	NTRH8101	Application Server Master Driver CD Bootable	10.00	H	N/A	
S ➤	NTRH9002	2GB SCSI SCA Disk Drive	1,320.00	H	463.00	H
S ➤	NTRH9003	4GB SCSI Hot Swap Disk Drive	2,260.00	H	713.00	H
S ✓ ➤	NTRH9004	3.5" EIDE Floppy Drive	70.00	H	N/A	
S ➤	NTRH9005	SCSI CD-ROM Drive	250.00	H	175.00	H
S ➤	NTRH9006	SCSI 3.5 DAT Tape Drive	1,750.00	H	1,225.00	H
S ✓ ➤	NTRH9007	SCSI RAID Controller	2,180.00	H	1,600.00	H
S ➤	NTRH9009	PCI Ethernet Adapter	360.00	H	250.00	H
S ✓ ➤	NTRH9010	PCI Token Ring Network Card	520.00	D	365.00	H
S ✓ ➤	NTRH9011	14" SVGA Color Monitor	380.00	D	265.00	H
S ➤	NTRH9012	17" SVGA Color Monitor	1,325.00	H	1,270.00	H
S ✓ † ➤	NTRH9013	OIVR 2 x Hardware - Keyboard	60.00	D	N/A	
S ✓ ➤	NTRH9014	Three Button Mouse	90.00	D	N/A	
S ✓ ➤	NTRH9016	External Modem 33.6	280.00	D	315.00	H
S ✓ ➤	NTRH9017	10 Base T Hub	300.00	D	210.00	H
S ➤	NTRH9027	ACCESS Link Kit for Meridian Mail 8, 9, 10, 11	50.00	H	35.00	H
S ➤	NTRH9029	2GB Ultra SCSI Disk Drive	1,250.00	H	463.00	H
S ✓ ➤	NTRH9030	4GB 16Bit Ultra SCSI Disk Drive	2,075.00	H	1,450.00	H
S ➤	NTRH9031	SYMPOSIUM Call Center Server 701t Platform Server System (32Mb)	5,000.00	H	2,550.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTRH9032	700 Series DC Power Converter	3,000.00	D	950.00	H
S #	NTRH9033	AC to DC Inverter for SYMPOSIUM Call Center, 48 to 240 Volt	MD		375.00	H
S ✓ ➤	NTRH9034	Backup Tape Drive	3,000.00	D	1,350.00	H
S ✓ ➤	NTRH9035	IDE CD-ROM Drive	275.00	H	250.00	H
S ✓ ➤	NTRH9036	CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack	250.00	D	N/A	
S ➤	NTRH9037	CallPilot CD ROM DRIVE	820.00	D	N/A	
S ✓	NTRH9038	CallPilot External SCSI Tape Drive, 4GB (IPE System)	1,900.00	D	850.00	H
S ✓ ➤	NTRH9039	CallPilot Ethernet Adaptor PCMCIA (IPE System)	390.00	D	N/A	
S ✓ ➤	NTRH9040	Callpilot Token Ring Adapter PCMCIA (IPE System)	750.00	D	N/A	
S ➤	NTRH9048	101 Enhanced Keyboard	560.00	D	N/A	
S ✓ ➤	NTRH9049	4 GB IDE Drive for the 200i System	370.00	D	N/A	
S ✓	NTRH9053	9 GB Disk Hot Swap	1,100.00	D	N/A	
S ✓	NTRH9054	9 GB SCSI Disk	1,120.00	D	N/A	
S ✓ ➤	NTRH9055	CallPilot ATA Drive with Programmed Flash	300.00	D	N/A	
S ✓	NTRH9057	VTG VB2002	5,000.00	D	N/A	
S ✓	NTRH9059	VTG VB2007	5,000.00	D	N/A	
S ★	NTRH9060	VTG VB2009	5,000.00	D	N/A	
S ★	NTRH9065	Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card	3,550.00	D	N/A	
S ✓ ➤	NTRH9068	Dual Pentium III SBC	6,950.00	D	N/A	
S ✓ ➤	NTRH9069	Transceiver (MAU to 10 Base T)	95.00	D	N/A	
S	NTRH9100	SYMPOSIUM Call Center Server 1003t Base System	15,590.00	H	N/A	
S ★ ➤	NTRK26AA	Software Assembly, CCS 100 - New System Software (1 Agent)	720.00	D	N/A	
S ★ ➤	NTRK26BA	Software Assembly, CCS 100 - New System Software (10 Agents)	6,528.00	D	N/A	
S ★ ➤	NTRK26CA	Software Assembly, CCS 100 - New System Software (50 Agents)	29,292.00	D	N/A	
S ★ ➤	NTRK26DA	Software Assembly, CCS 100 - New System Software (100 Agents)	51,888.00	D	N/A	
S ★ ➤	NTRK26EA	Software Assembly, CCS 100 - New System Software (500 Agents)	225,900.00	D	N/A	
S ★ ➤	NTRK26GA	Software Assembly, CCS 100 - New System Software (5 Agents)	3,450.00	D	N/A	
S ★ ➤	NTRK26HA	Software Assembly, CCS 100 - New System Software (20 Agents)	12,720.00	D	N/A	
S ★ ➤	NTRK26JA	Software Assembly, CCS 100 - New System Software (200 Agents)	100,800.00	D	N/A	
S ★ ➤	NTRK27AA	Software Assembly, CCS 200 - New System Software (1 Agent)	300.00	D	N/A	
S ★ ➤	NTRK27BA	Software Assembly, CCS 200 - New System Software (10 Agents)	2,724.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ★ ➤	NTRK27CA	Software Assembly, CCS 200 - New System Software (50 Agents)	12,204.00	D	N/A	
S ★ ➤	NTRK27DA	Software Assembly, CCS 200 - New System Software (100 Agents)	21,624.00	D	N/A	
S ★ ➤	NTRK27EA	Software Assembly, CCS 200 - New System Software (500 Agents)	94,128.00	D	N/A	
S ★ ➤	NTRK27GA	Software Assembly, CCS 200 - New System Software (5 Agents)	1,440.00	D	N/A	
S ★ ➤	NTRK27HA	Software Assembly, CCS 200 - New System Software (20 Agents)	5,400.00	D	N/A	
S ★ ➤	NTRK27JA	Software Assembly, CCS 200 - New System Software (200 Agents)	42,600.00	D	N/A	
S ➤ Δ	NTS101AA	Call Processor II	No charge		N/A	
S ➤	NTS102AA	Corporate Directory, Virtual Office	500.00	I	N/A	
S ➤ Δ	NTS103AA	Fiber Network	No charge		N/A	
S ➤	NTS130AA	Personal Mailbox Administration	500.00	D	N/A	
S ➤	NTS132AA	Meridian Mail Option 11 AutoAdmin Software Package - MM13	2,300.00	D	N/A	
S ➤	NTS133AA	Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12, 13)	1,000.00	D	N/A	
S ➤	NTS134AA	Software Feature, Personal Mailbox Administration (PMA)	1,000.00	D	N/A	
S ➤	NTS136AA	Meridian Mail AutoAdmin Software Package EC, Modular Option, GP	3,300.00	D	N/A	
S ➤	NTS137AA	Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package	1,000.00	D	N/A	
S § ➤	NTSF1030	Option 11C Mini Chassis Package	4,000.00	I	N/A	
S § ➤	NTSF1031	Option 11C Mini Chassis Package with SSC	7,500.00	I	N/A	
S ➤	NTSF1032	Option 11C Mini Chassis Expander Package	2,500.00	I	N/A	
S ➤	NTSF1033	Option 11C Mini Chassis CPU Upgrade Package	2,400.00	I	N/A	
S ➤	NTSF1101	Option 11C Single Cabinet AC	2,600.00	I	N/A	
S ➤	NTSF1102	Option 11C Single Cabinet DC	2,600.00	I	N/A	
S ➤	NTSF2101	Option 11C - 30 Ft. Expansion Cabinet AC	2,300.00	I	N/A	
S ➤	NTSF2102	Option 11C - 30 Ft. Expansion Cabinet DC	2,300.00	I	N/A	
S ➤	NTSF2103	Option 11C - 2 Mile Expansion Cabinet AC	7,300.00	I	N/A	
S ➤	NTSF2104	Option 11C - 2 Mile Expansion Cabinet DC	7,300.00	I	N/A	
S ➤	NTSF2105	Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber)	7,300.00	I	N/A	
S ➤	NTSF2106	Option 11C - 2 Mile Expansion Cabinet Single Mode DC	7,300.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTSF2200	Chassis Fiber Expansion Package (30 Ft.)	7,500.00	I	N/A	
S ➤	NTSF2201	Chassis Fiber Expansion Package (2mi. Multi-Mode)	10,000.00	I	N/A	
S ➤	NTSF2202	Chassis Fiber Expansion Package (2mi. Single-Mode)	10,000.00	I	N/A	
S ➤ Δ	NTSF3001	Package of 10 Option 11C Documentation CD-ROMs	500.00	H	N/A	
S ➤	NTSF3100	2.0MB DTI Package Option 11C	4,200.00	I	N/A	
S ➤	NTSF3101	2.0MB PRI Package Option 11C	3,950.00	I	N/A	
S ➤	NTSF6001	Option 11/11E to 11C Single Cabinet Upgrade	3,465.00	I	N/A	
S ➤	NTSF6002	Option 11/11E to 11C Two Cabinet Copper Upgrade	3,945.00	I	N/A	
S ➤	NTSF6003	Option 11/11E to 11C Two Cabinet Fiber Upgrade (30 Ft.)	5,500.00	I	N/A	
S ➤	NTSF6004	Option 11/11E to 11C Two Cabinet Fiber Upgrade (2 mile)	12,300.00	I	N/A	
S ➤	NTSF6005	Option 11/11E to 11C Three Cabinet Fiber Upgrade (30 Ft.)	8,000.00	I	N/A	
S ➤	NTSF6006	Option 11/11E to 11C Three Cabinet Fiber Upgrade (2 mile)	17,100.00	I	N/A	
S ➤	NTSF6007	Option 11/11E to 11C - Two Cabinet Ethernet Upgrade (2 Mile - Single Mode Fiber)	12,300.00	I	N/A	
S ➤	NTSF6008	Option 11/11E to 11C Three Cabinet Single Mode Fiber Upgrade (2 Mile)	17,100.00	I	N/A	
S ➤ Δ	NTSF6501	Option 11C Compact to Option 11C Migration Package	17,355.00	H	N/A	
B ➤	NTSF6800	Option 11C TMDI Package (1.5MB DTI/PRI)	3,400.00	I	N/A	
S ➤	NTSF6851	Internet Registration Kit	50.00	H	N/A	
S ✓ ➤	NTSF8011	Option 11C Mini General Business Software Package	1,500.00	I	N/A	
S ✓ ➤	NTSF8012	Option 11C Mini Enhanced Business Software Package	2,400.00	I	N/A	
S ✓ ➤	NTSF8013	Option 11C Mini Enterprise Business Software Package	4,000.00	I	N/A	
S ✓ ➤	NTSF8014	Option 11C Mini NAS/VNS Software Package	4,675.00	I	N/A	
S ✓ ➤	NTSF8020	Option 11C General Business Software Package	2,000.00	I	N/A	
S ✓ ➤	NTSF8021	Option 11C Enhanced Business Software Package	3,500.00	I	N/A	
S ✓ ➤	NTSF8022	Option 11C Enterprise Software Package	6,500.00	I	N/A	
S ✓ ➤	NTSF8023	Option 11C NAS/VNS Software Package	7,500.00	I	N/A	
S ✓ ➤	NTSF8028	Option 11/11E to Option 11C General Business Software Upgrade	3,000.00	I	N/A	
S ✓ ➤	NTSF8029	Option 11/11E to Option 11C Enhanced Business Software Upgrade	4,500.00	I	N/A	
S ✓ ➤	NTSF8030	Option 11/11E to Option 11C Enterprise Software Upgrade	7,500.00	I	N/A	
S ✓ ➤	NTSF8031	Option 11/11E to Option 11C NAS/VNS Software Upgrade	8,500.00	I	N/A	
S ✓ ➤	NTSF8048	Option 11C General Business Software Feature Upgrade	3,000.00	I	N/A	
S ✓ ➤	NTSF8049	Option 11C Enhanced Business Software Feature Upgrade	4,500.00	I	N/A	
S ✓ ➤	NTSF8050	Option 11C Enterprise Software Feature Upgrade	7,500.00	I	N/A	
S ✓ ➤	NTSF8051	Option 11C NAS/VNS Software Feature Upgrade	8,500.00	I	N/A	
S ➤	NTSF8101	Option 11C 100 Additional TNs - General Business	2,500.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTSF8102	Option 11C 100 Additional TNs - Enhanced Business	4,250.00	I	N/A	
S ➤	NTSF8103	Option 11C 100 Additional TNs - Enterprise	7,500.00	I	N/A	
S ➤	NTSF8104	Option 11C 100 Additional TNs - NAS/VNS	8,500.00	I	N/A	
S ➤	NTSF8501	Option 11C Package #22 - DISA	No charge		N/A	
S ➤ Δ	NTSF8508	AST (100 Increment)	No charge		N/A	
S ➤ Δ	NTSF8509	Call Identification (CALL-ID Package 247)	No charge		N/A	
S ➤	NTSF8512	Option 11C Electronic Brandlining - Display Customization	250.00	I	N/A	
S ➤ Δ	NTSF8513	Option 11C RAN Connections for Release 23.18	No charge		N/A	
S ➤	NTSF8514	Increment the Option 11C RAN Connections ISM parameter by 1	400.00	I	N/A	
S ➤	NTSF8516	Option 11C Release 23 for CallPilot (Keycode only)	No charge		N/A	
S ➤ Δ	NTSF8519	Enable Package 381, 382 for M3900 Sets Phase II	No charge		N/A	
S ➤	NTSF8702	Option 11C Software Upissue Keycode	500.00	H	N/A	
S ➤	NTSF8712	Option 11C Software Upgrade Fee to Current	1,000.00	I	N/A	
B ➤	NTSF8722	Option 11C Software Rls 24C Upissue Keycode	500.00	H	N/A	
B ➤	NTSF8730	Option 11C TMDI D-Channels Keycode	655.00	I	N/A	
S † ➤	NTSK11AA	Option 11C Software Daughterboard - Release 22.08D	1,400.00	I	400.00	H
S † ➤	NTSK11AB	Option 11C Software Daughterboard - Release 22.16	1,400.00	I	400.00	H
S † ➤	NTSK11AC	Option 11C Software Daughterboard - Release 22.46	1,400.00	I	400.00	H
S † ➤	NTSK11AF	Option 11C Software Daughterboard - Release 23.18	1,400.00	I	400.00	H
S † ➤	NTSK11AG	Option 11C Software Daughterboard - Release 23.35	1,400.00	I	400.00	H
S † ➤	NTSK11AH	Option 11C Software Daughterboard - Release 23.55	1,400.00	I	400.00	H
B † ➤	NTSK11AK	Option 11C Software Daughterboard - Release 24.24	1,400.00	I	400.00	H
B ✓ ➤	NTSK11AL	Option 11C Software Daughterboard - Release 25	1,400.00	I	400.00	H
B ✓ ➤	NTSK11AN	Option 11C Software Daughterboard - Release 25	1,400.00	I	400.00	H
B ★ ➤	NTSK11AP	Option 11C Software Daughterboard - Release 25 Combo	1,400.00	I	400.00	H
S ✓	NTSK11BA	Option 11C Release 22.08 Programmed PCMCIA Card	1,500.00	I	N/A	
S ✓	NTSK11BB	Option 11C Release 22.16 Programmed PCMCIA Card	1,500.00	I	N/A	
S ✓	NTSK11BC	Option 11C Release 22.46 Programmed PCMCIA Card	1,500.00	I	N/A	
S ✓	NTSK11BF	Option 11C Release 23.18 Programmed PCMCIA Card	1,500.00	I	N/A	
S ✓	NTSK11BG	Option 11C Release 23.35 Programmed PCMCIA Card	1,500.00	I	N/A	
B ✓ ➤	NTSK11BH	Option 11C Release 23.55 Programmed PCMCIA Card	1,500.00	I	N/A	
B ✓ ➤	NTSK11BK	Option 11C Release 24.24 Programmed PCMCIA Card	1,500.00	I	N/A	
B ✓ ➤	NTSK11BL	Option 11C Release 25 Programmed 40MB PCMCIA Card	1,500.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B ✓ ➤	NTSK11BN	Option 11C Release 25 Programmed PCMCIA Card	1,500.00	I	N/A	
S ✓	NTSK11CL	Release 25A US General Business Feature Set			N/A	
S ✓	NTSK11CN	Option 11C General Business Feature Set - Release 25			N/A	
S ✓	NTSK11DL	Release 25A US Enhanced Business Feature Set			N/A	
S ✓	NTSK11DN	Option 11C Enhanced Business Feature Set - Release 25			N/A	
S ✓	NTSK11EL	Release 25A US Enterprise Business Feature Set			N/A	
S ✓	NTSK11EN	Option 11C Enterprise Business Feature Set - Release 25			N/A	
S ✓	NTSK11FL	Release 25A US NAS/VNS Feature Set			N/A	
S ✓	NTSK11FN	Option 11C NAS/VNS Feature Set - Release 25			N/A	
S #	NTSK11ZK	Release 24.24 Programmed Mini System Controller Pack	MD		1,000.00	H
S	NTSK11ZN	Release 25 Programmed Mini System Controller Pack	1,910.00	I	950.00	H
S ➤ Δ	NTSW31AA	Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08)	650.00	H	N/A	
S ✓ ➤	NTSZ00AC	Option 81C 68060 Enhanced Call Process New System Pkg AC (IGS Network Included)	86,500.00	I	N/A	
S ✓ ➤	NTSZ00DC	Option 81C New System Package DC	86,500.00	I	N/A	
S ✓ ➤	NTSZ25AC	Option 81C Call Processor PII New System Package AC (Fiber Network Fabric Included)	86,500.00	I	N/A	
S ➤	NTSZ25DC	Option 81C Call Processor PII New System Package DC (Fiber Network Fabric Included)	86,500.00	I	N/A	
S ✓ ➤	NTSZ26AC	Option 81C Call Processor PII New System Package AC (IGS Network Included)	86,500.00	I	N/A	
S ✓ ➤	NTSZ26DC	Option 81C Call Processor PII New System DC (IGS Network Included)	86,500.00	I	N/A	
S	NTTK08AA	Option 11C Mini Vertical Wall Mount Kit	60.00	I	N/A	
S	NTTK09AA	Option 11C Mini 19 Inch Rack Mount Kit	80.00	I	N/A	
S	NTTK10AA	Option 11C Mini Shelf Table Mount Kit	13.00	I	N/A	
S	NTTK11AA	Option 11C Mini Horizontal Wall Mount Kit	80.00	I	N/A	
S	NTTK13AA	Option 11C 48MB Software Daughterboard (Blank)	1,380.00	I	675.00	H
S	NTTK14AA	Option 11C Mini Power Cord Kit	20.00	I	N/A	
S	NTTK24AA	Option 11C Mini Fiber Cable Management Kit	50.00	I	N/A	
B ➤ Δ	NTTK30AB	Option 11C Release 25 English Documentation Package, Binder	90.00	H	N/A	
B ➤ Δ	NTTK31AB	Option 11C Release 25 English Documentation Package, Coil	90.00	H	N/A	
S ➤ Δ	NTTK32CB	Option 11C Customer Documentation Library on CD-ROM, Release 25	75.00	H	N/A	
N ➤ Δ	NTTK33AB	Option 11C Distributor Technical Library Package, Release 25	70.00	H	N/A	
S Δ	NTTK38AB	Option 11C Mini Fiber Expansion Documentation Package	50.00	H	N/A	
S ★	NTTK44AA	RSM Cable	120.00	D	N/A	
S ★ ➤	NTTK45AA	Option 11C 48MB Blank PCMCIA Memory Card Assembly	650.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTTL01AA	OTM 1.0 General, Server, 50 Sets	500.00	D	N/A	
S	NTTL01BA	OTM 1.0 Enhanced, Server, 50 Sets	600.00	D	N/A	
S	NTTL01CA	OTM 1.0 Premium, Server, 50 Sets	700.00	D	N/A	
S	NTTL02AA	OTM 1 x General, 50 Sets Expansion	250.00	D	N/A	
S	NTTL02BA	OTM 1 x General, 250 Sets Expansion	1,000.00	D	N/A	
S	NTTL02CA	OTM 1 x General, 1000 Sets Expansion	3,500.00	D	N/A	
S	NTTL02DA	OTM 1 x General, 5000 Sets Expansion	5,000.00	D	N/A	
S	NTTL03AA	OTM 1 x Enhanced, 50 Sets Expansion	350.00	D	N/A	
S	NTTL03BA	OTM 1 x Enhanced, 250 Sets Expansion	1,500.00	D	N/A	
S	NTTL03CA	OTM 1 x Enhanced, 1000 Sets Expansion	5,000.00	D	N/A	
S	NTTL03DA	OTM 1 x Enhanced, 5000 Sets Expansion	8,000.00	D	N/A	
S	NTTL04AA	OTM 1 x Premium, 50 Sets Expansion	500.00	D	N/A	
S	NTTL04BA	OTM 1 x Premium, 250 Sets Expansion	2,300.00	D	N/A	
S	NTTL04CA	OTM 1 x Premium, 1000 Sets Expansion	8,000.00	D	N/A	
S	NTTL04DA	OTM 1 x Premium, 5000 Sets Expansion	12,000.00	D	N/A	
S ✓	NTTL05AA	OTM Billing 1 x General, 100 RU	1,975.00	D	N/A	
S ✓	NTTL06AA	OTM Billing 1 x General, 250 RU Expansion	1,100.00	D	N/A	
S ✓	NTTL06BA	OTM Billing 1 x General, 1000 RU Expansion	3,775.00	D	N/A	
S ✓	NTTL06CA	OTM Billing 1 x General, 5000 RU Expansion	12,000.00	D	N/A	
S ✓	NTTL06DA	OTM Billing 1 x General, 10000 RU Expansion	17,250.00	D	N/A	
S ✓	NTTL06EA	OTM Billing 1 x General, 50000 RU Expansion	37,750.00	D	N/A	
S	NTTL08AA	OTM 1.0 General, MAT Upgrade, Server, 50 Sets	300.00	D	N/A	
S	NTTL08BA	OTM 1.0 Enhanced, MAT Upgrade, Server, 50 Sets	400.00	D	N/A	
S	NTTL08CA	OTM 1.0 Premium, MAT Upgrade, Server, 50 Sets	500.00	D	N/A	
S Δ	NTTL09AA	OTM 1.0 General, MAT Upgrade, 50 Sets Expansion	No charge		N/A	
S Δ	NTTL09BA	OTM 1.0 Enhanced, MAT Upgrade, 50 Sets Expansion	No charge		N/A	
S Δ	NTTL09CA	OTM 1.0 Premium, MAT Upgrade, 50 Sets Expansion	No charge		N/A	
S ✓	NTTL10AA	OTM Billing 1 x General, MAT Upgrade, 100 RUs	975.00	D	N/A	
S	NTTL11AA	OTM 1.0 General to Enhanced Server, 50 Sets	150.00	D	N/A	
S	NTTL11BA	OTM 1.0 General to Premium Server, 50 Sets	250.00	D	N/A	
S	NTTL11CA	OTM 1.0 Enhanced to Premium Server, 50 Sets	150.00	D	N/A	
S	NTTL12AA	OTM 1 x General to Enhanced, 50 Sets Expansion	100.00	D	N/A	
S	NTTL12BA	OTM 1 x General to Enhanced, 250 Sets Expansion	500.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTTL12CA	OTM 1 x General to Enhanced, 1000 Sets Expansion	1,500.00	D	N/A	
S	NTTL12DA	OTM 1 x General to Enhanced, 5000 Sets Expansion	3,000.00	D	N/A	
S	NTTL13AA	OTM 1 x General to Premium, 50 Sets Expansion	250.00	D	N/A	
S	NTTL13BA	OTM 1 x General to Premium, 250 Sets Expansion	1,300.00	D	N/A	
S	NTTL13CA	OTM 1 x General to Premium, 1000 Sets Expansion	4,500.00	D	N/A	
S	NTTL13DA	OTM 1 x General to Premium, 5000 Sets Expansion	7,000.00	D	N/A	
S	NTTL14AA	OTM 1 x Enhanced to Premium, 50 Sets Expansion	150.00	D	N/A	
S	NTTL14BA	OTM 1 x Enhanced to Premium, 250 Sets Expansion	800.00	D	N/A	
S	NTTL14CA	OTM 1 x Enhanced to Premium, 1000 Sets Expansion	3,000.00	D	N/A	
S	NTTL14DA	OTM 1 x Enhanced to Premium, 5000 Sets Expansion	4,000.00	D	N/A	
S	NTTL17AA	OTM Access Server	1,000.00	D	N/A	
S	NTTL18AA	MAT PC Dongle to OTM Client Upgrade	200.00	D	N/A	
S	NTTL19AA	OTM, Additional Client for One (1) PC	500.00	D	N/A	
S	NTTL19BA	OTM, Additional Client for Five (5) PCs	2,000.00	D	N/A	
S	NTTL19CA	OTM, Additional Client for Ten (10) PCs	3,500.00	D	N/A	
S ✓ ➤	NTTS36AA	External RSM Breakout Assembly (4 RS-232 Ports)	750.00	D	N/A	
S ★ ➤	NTTS50AA	Meridian Mail Mini Networking Package	1,100.00	D	N/A	
S ✓ ➤	NTUB14AB	CallPilot 1.06 Keycode Package	15.00	D	N/A	
S ✓ ➤	NTUB16AA	CallPilot External Modem Kit	300.00	D	N/A	
S ★	NTUB20AD	CallPilot 1.07 IPE Base Server Software Assembly	70.00	D	N/A	
S ★	NTUB22AD	CallPilot 1.07 Base Software Assembly	85.00	H	N/A	
S ➤ Δ	NTUB24AA	Meridian Mail to CallPilot Migration Utility Tape and Documentation	No charge		N/A	
S	NTUB24AB	CallPilot 1.07 Meridian Mail to CallPilot Migration Tape	50.00	D	N/A	
S ★ ➤	NTUB40AC	CallPilot 1.07 Server Software CD	10.00	D	N/A	
S ★ ➤	NTUB41AC	CallPilot 1.07 Administration Client CD	10.00	D	N/A	
S	NTUB42AB	CallPilot 1.06 Desktop Messaging CD (English & French)	10.00	D	N/A	
S ★ ➤	NTUB42AC	CallPilot 1.07 Desktop Messaging CD	10.00	D	N/A	
S ➤	NTUB43AA	CallPilot 1.0 Patch Software	120.00	D	N/A	
S ★ ➤	NTUB43AC	CallPilot 1.07 PEP Software CD	10.00	D	N/A	
S ★	NTUB44AC	CallPilot 1.07 Language Prompts CD	15.00	D	N/A	
S ★ ➤	NTUB44BC	CallPilot 1.07 Language Prompts CD Sets (3)	30.00	D	N/A	
S ★ ➤	NTUB45AC	CallPilot 1.07 Web Messaging CD	10.00	D	N/A	
S ➤	NTUB46AB	CallPilot 1.06 Administration Client CD Assembly	20.00	D	N/A	
S ✓ ➤	NTUB51AA	CallPilot Token Ring LAN Kit - IPE Systems	870.00	D	N/A	
S ✓ ➤	NTUB52AA	CallPilot Ethernet LAN Connection Kit - IPE Systems	415.00	D	N/A	
S ✓ ➤	NTUB53AA	CallPilot External Tape Drive - IPE Systems	2,240.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTUB54AA	CallPilot Recovery Kit - IPE	1,060.00	D	N/A	
S ✓ ➤	NTUB55AA	CallPilot Tower/Rack Internal Tape Drive Kit	5,200.00	D	N/A	
S ✓ ➤	NTUB56AA	CallPilot 14" Monitor Kit	600.00	D	N/A	
S ➤	NTUB57AB	CallPilot MGate Kit	500.00	D	N/A	
S ✓ ➤	NTUB58AA	CallPilot 700 Series RAID Kit	5,000.00	D	N/A	
S ✓ ➤	NTUB59AA	CallPilot CD ROM Drive	700.00	D	N/A	
S ✓ ➤	NTUB60AB	CallPilot MPB-16	2,500.00	D	N/A	
S ★ ➤ Δ	NTUB71AA	CallPilot 1.07 GB, 200i Token Ring LAN Option	No charge		N/A	
S ★ ➤ Δ	NTUB72AA	CallPilot 1.07 GB, 200i Ethernet LAN Option	No charge		N/A	
S ★ ➤ Δ	NTUB73AA	CallPilot 1.07 GB, 700/1000 Series Token Ring LAN Option	No charge		N/A	
S ★ ➤ Δ	NTUB74AA	CallPilot 1.07 GB, 700/1000 Series Ethernet LAN Option	No charge		N/A	
S ★ ➤ Δ	NTUB80AA	CallPilot 1.07 GB, MPC-8 - Expand Option (No Charge)	No charge		N/A	
S ★ ➤ Δ	NTUB81AA	DSP Connectivity Package - Digitel	No charge		N/A	
S ★ ➤ Δ	NTUB83AA	DSP Connectivity Option - MSL-100	No charge		N/A	
S ★ ➤	NTUF24AA	DMS SCCS Release 3 CD-ROM Document CD (Merchandise)	25.00	D	N/A	
S † ➤	NTV200AA	Upgrade Package IIVR Release 1 to Release 2.2	37,000.00	D	N/A	
S † ➤	NTV200BA	Runtime System Upgrade Package Release 2.08 to Release 2.2	4,500.00	D	N/A	
S † ➤	NTV200CA	Development System Upgrade Package Release 2.08 to Release 2.2	4,970.00	D	N/A	
S † ➤	NTV201AA	IIVR 2.2 Voice Port Expansion - 4 ports - Development System	5,800.00	D	N/A	
S † ➤	NTV201AB	IIVR 2.2 Voice Port Expansion - 4 ports - Runtime System	6,100.00	D	N/A	
S † ➤	NTV201AC	IIVR 2.2 Runtime to Development Upgrade Base Package - 4 ports	2,000.00	D	N/A	
S † ➤	NTV201AD	IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports	1,500.00	D	N/A	
S † ➤	NTV201AE	SNA (3270/5250) Host Connectivity Upgrade from Release 2.08 to Release 2.2	130.00	D	N/A	
S † ➤	NTV201AQ	IIVR 2.2 Fax Response Hardware - 4 ports	4,500.00	H	N/A	
S † ➤	NTV201AR	IIVR 2.2 Fax Response Software Base Package - 2 ports	4,500.00	D	N/A	
S † ➤	NTV201AS	IIVR 2.2 Fax Response Software Expansion - 1 port	2,250.00	D	N/A	
S † ➤	NTV201AT	UPS Software Upgrade from Release 2.08 to Release 2.2	130.00	D	N/A	
S ✓ † ➤	NTV201AU	IIVR 2.2 UPS Package	1,260.00	H	N/A	
S † ➤	NTV201AV	Integrated IVR 2.2 Memory Package 32 MB	500.00	H	N/A	
S ➤	NTV201BA	IIVR 2.2 Supplementary Patch CD	15.00	H	N/A	
S † ➤	NTV202AA	IIVR 2.2 Software Media	65.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	NTV202AB	16MB RAM Spare	225.00	H	N/A	
S ➤	NTV202AC	256KB L2 Async Cache Spare	125.00	H	N/A	
S ✓ † ➤	NTV202AD	1000VA UPS Hardware Spare	1,260.00	H	N/A	
S † ➤	NTV202AE	512KB Video RAM Spare	80.00	H	N/A	
S † ➤	NTV202AF	Tape Backup Unit Spare	945.00	H	N/A	
S † ➤	NTV202AH	525W Power Supply Spare	925.00	H	N/A	
S † ➤	NTV202AJ	Digi PC/Xem Spare	1,445.00	H	N/A	
S † ➤	NTV202AK	IIVR 2.2 Fax Card Spare	4,075.00	H	N/A	
S † ➤	NTV202AL	Floppy Drive Spare	100.00	H	N/A	
S † ➤ Δ	NTV202AM	IIVR 2.2 Update Documentation Package	50.00	H	N/A	
S † ➤	NTV202AP	8 port DCE DB25 Octa Cable Spare	125.00	H	N/A	
S † ➤	NTV202AW	4.5GB SCA UltraSCSI Hard Disk Spare	630.00	H	N/A	
S † ➤	NTV202AY	Modem Cable, 10 ft., DB9 Female to DB25 Male	40.00	H	N/A	
S ➤	NTV400KA	Keylock	185.00	H	100.00	H
S ➤	NTV400LA	License File	9.00	H	N/A	
S ➤	NTV401PA	Supplementary Patch CD	No charge		N/A	
S ➤	NTV401SA	System Recovery Boot Package	145.00	H	39.00	H
S ➤ Δ	NTV402AA	Base Documentation Package, North America	320.00	H	N/A	
S ➤ Δ	NTV402CA	Full Documentation Package (CD)	46.00	H	N/A	
S ➤	NTV403EA	Ethernet Adapter Kit	350.00	H	145.00	H
S	NTV403TA	Token Ring Adapter Kit	880.00	H	527.00	H
S ➤	NTV404LA	Monitor - 21"	3,200.00	H	1,900.00	H
S ➤	NTV404MA	Monitor - 17"	1,220.00	H	655.00	H
S ➤	NTV404SA	Monitor - 14"	360.00	H	212.00	H
S ➤	NTV405UA	Uninterruptible Power Supply (UPS) 110V - OIVR 4.0 Tower AP, MRS/AP, or MRS/Tower	950.00	H	562.00	H
S #	NTV405VA	Uninterruptible Power Supply (UPS) Tower Model - 220V - 1 AP, MRS/AP, or MRS/Tower	MD		562.00	H
S ➤	NTV406CA	SCSI CD-ROM Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	320.00	H	176.00	H
S ➤	NTV406DA	SCSI DAT Tape Drive for AP, MRS/AP, MRS/Tower, MRS/Rack	1,180.00	H	555.00	H
S ➤	NTV406RA	SCSI 4.5GB Hard Drive for OIVR 4.0 MRS/Rack and Rack AP	630.00	H	639.00	H
S ➤	NTV406TA	SCSI 4.5GB Hard Drive for OIVR 4.0 Tower AP, MRS/AP, MRS/Tower	640.00	H	639.00	H
S ➤	NTV407MA	64MB RAM Expansion for OIVR 4.0 AP, MRS/AP and MRS	570.00	H	N/A	
S ➤	NTV410BA	Base AP (700tp), 0 Port - Global	16,800.00	D	N/A	
S ➤	NTV411NA	Regional Supplement to Base AP - North America	650.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTV412RA	AP Redundancy - 1 Voice Port RTU for 1 AP	170.00	H	N/A	
S ➤	NTV413AA	Base AP/Rack, AC, Global	21,300.00	D	N/A	
S ➤	NTV413DA	Base AP/Rack, DC, Global	22,100.00	D	N/A	
S ➤	NTV420AA	Base MRS/Tower, 0 Port - Global	17,730.00	D	6,188.00	H
S ➤	NTV420KA	Keyboard and Mouse for Base MRS/Tower	130.00	H	N/A	
S ➤	NTV421NA	Regional Supplement to Base MRS/Tower - North America	275.00	H	N/A	
S ➤	NTV430AA	Base MRS/Rack, AC, 0 Port - Global	19,880.00	D	N/A	
S ➤	NTV430DA	Base MRS/Rack, DC, 0 Port - Global	20,665.00	D	N/A	
S ➤	NTV430RA	Redundant DC Power for Base MRS/Rack or Rack AP	2,110.00	H	1,266.00	H
S ➤	NTV430SA	Redundant AC Power for Base MRS/Rack or Rack AP	1,890.00	H	N/A	
S ➤	NTV431NA	Regional Supplement to Base MRS/Rack (AC or DC) - North America	275.00	H	N/A	
S ➤	NTV440BA	Base MRS/AP (700tp), 0 Port - Global	16,800.00	D	N/A	
S ➤	NTV441NA	Regional Supplement to Base MRS/AP - North America	650.00	H	N/A	
S ✓ ➤	NTV450CA	Custom Cell Builder RTU - 1 AP (or MRS/AP)	2,670.00	D	N/A	
S ➤	NTV450LA	Development License - 4 Users	26,680.00	D	N/A	
S ✓ ➤	NTV450MA	Development License Upgrade - 1 to 4 Users	22,810.00	D	N/A	
S ✓ ➤	NTV450PA	Prompt Manager and Loading Tool - 1 AP (or MRS/AP)	2,560.00	D	N/A	
S ✓ ➤	NTV450SA	Development License - 1 User	20,810.00	D	N/A	
S ➤	NTV452EA	Host Connectivity Hardware - Ethernet Adapter Kit (For TN3270 or TN5250 Option)	350.00	H	210.00	H
S ➤	NTV452SA	Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option)	1,650.00	H	985.00	H
S ➤	NTV452TA	Host Connectivity Hardware - Token Ring Adapter Kit (For SNA3270 or SNA5250 Option)	880.00	H	527.00	H
S ➤	NTV452VA	Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option)	1,580.00	H	220.00	H
S ➤	NTV452WA	Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option)	940.00	H	275.00	H
S ➤	NTV453AA	Host Connectivity Software - SNA3270 - Base and 16 Session RTU	12,000.00	D	N/A	
S ➤	NTV453BA	Host Connectivity Software - TN3270 - Base and 16 Session RTU	12,000.00	D	N/A	
S ➤	NTV453SA	Host Connectivity Software - SNA3270 - 16 Session RTU Expansion	10,625.00	D	N/A	
S ➤	NTV453TA	Host Connectivity Software - TN3270 - 16 Session RTU Expansion	10,500.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTV454VA	Host Connectivity Software - VT100 - 16 Session Base RTU	7,550.00	D	N/A	
S ✓ ➤	NTV454WA	Host Connectivity Software - VT100 - 16 Session RTU Expansion	7,550.00	D	N/A	
S ➤	NTV455AA	Host Connectivity Software - SNA5250 - Base and 16 Session RTU	12,000.00	D	N/A	
S ➤	NTV455BA	Host Connectivity Software - TN5250 - Base and 16 Session RTU	12,500.00	D	N/A	
S ➤	NTV455SA	Host Connectivity Software - SNA5250 - 16 Session RTU Expansion	10,500.00	D	N/A	
S ➤	NTV455TA	Host Connectivity Software - TN5250 - 16 Session RTU Expansion	10,500.00	D	N/A	
S ➤	NTV456AA	Database Connectivity Software - INFORMIX - RTU	5,250.00	D	N/A	
S ➤	NTV456BA	Database Connectivity Software - INGRES - RTU	5,250.00	D	N/A	
S ➤	NTV456CA	Database Connectivity Software - ORACLE - RTU	5,250.00	D	N/A	
S ➤	NTV456DA	Database Connectivity Software - SYBASE - RTU	5,250.00	D	N/A	
S ➤	NTV456MA	Database Connectivity Software - Microsoft SQL Server - RTU	6,750.00	D	N/A	
S ✓ ➤	NTV457PA	PureSpeech Recite Development Kit - 1 AP RTU	16,370.00	H	N/A	
S ➤	NTV457WA	Web Integration Software - 1 AP RTU	13,000.00	D	N/A	
S ➤	NTV460AA	ADSI License RTU - 1 AP (or MRS/AP)	15,700.00	D	N/A	
S ✓ ➤	NTV460SA	Software-Based Disk Mirroring License RTU - OIVR 4.0 AP, MRS, or MRS/AP	3,490.00	H	N/A	
S ✓ ➤	NTV461NA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America	23,520.00	H	5,308.00	H
S ✓ ➤	NTV461PA	Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America - Pulse Detection	26,360.00	H	6,893.00	H
S ✓ ➤	NTV462NA	Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America	33,620.00	H	7,377.00	H
S ➤	NTV462PA	North American ISDN PRI Option for 24 Port T1 Card	2,200.00	H	N/A	
S ➤	NTV462TA	Line Side T1 Support - RTU For 24 Port T1 - Spanish	880.00	H	N/A	
S ✓ ➤	NTV464NA	Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA	6,250.00	H	N/A	
S ➤	NTV464ZA	Dial Pulse Detection for any 4 Port Loopstart Card	1,825.00	H	N/A	
S ✓ ➤	NTV467LA	Fax - Gammalink - 12 Port Card and 12 Port RTU	34,170.00	D	6,925.00	H
S ✓ ➤	NTV467MA	Fax - Gammalink - 6 Port Card and 6 Port RTU	17,610.00	D	3,608.00	H
S ✓ ➤	NTV467SA	Fax - Gammalink - 4 Port Card and 4 Port RTU	12,810.00	D	2,706.00	H
S ✓ ➤	NTV468CA	Text to Speech - TrueVoice - Base Card and 2 Port RTU	14,200.00	D	4,247.00	H
S ✓ ➤	NTV468LA	Text to Speech - L and H - Base Card and 6 Port RTU	22,520.00	D	5,398.00	H
S ✓ ➤	NTV468PA	Speech Recognition - PureSpeech Recite - Continuous Digits - Base Card and 2 Port RTU	15,000.00	D	4,369.00	H
S ✓ ➤	NTV468QA	Speech Recognition - PureSpeech Recite - Lite - Base Card and 2 Port RTU	18,790.00	D	5,079.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTV468RA	Speech Recognition - PureSpeech Recite - Pro - Base Card and 2 Port RTU	21,600.00	D	5,608.00	H
S ✓ ➤	NTV468SA	Speech Recognition - PureSpeech Recite - IQ - Base Card and 2 Port RTU	24,250.00	D	6,103.00	H
S ✓ ➤	NTV468TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - Base Card and 2 Port RTU	15,610.00	D	4,439.00	H
S ✓ ➤	NTV468UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - Base Card and 2 Port RTU	20,160.00	D	5,234.00	H
S ✓ ➤	NTV468VA	Speech Recognition - VCS for Antares - Discrete - Base Card and 4 Port RTU	18,670.00	D	5,028.00	H
S ✓ ➤	NTV468WA	Speech Recognition - VCS for Antares - Continuous - Base Card and 2 Port RTU	14,960.00	D	4,379.00	H
S ✓ ➤	NTV468YA	Speech Recognition - PureSpeech Recite - LA Spanish - Pro - Base Card and 2 Port RTU	23,540.00	D	5,826.00	H
S ✓ ➤	NTV468ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - Base Card and 2 Port RTU	26,710.00	D	6,381.00	H
S ✓ ➤	NTV469CA	Text to Speech - TruVoice - 2 Port RTU Expansion	5,420.00	D	N/A	
S ✓ ➤	NTV469LA	Text to Speech - L and H - 6 Port RTU Expansion	13,010.00	D	N/A	
S ✓ ➤	NTV469PA	Speech Recognition - PureSpeech - Continuous Digits - 2 Port RTU Expansion	6,220.00	D	N/A	
S ✓ ➤	NTV469QA	Speech Recognition - PureSpeech Recite - Lite - 2 Port RTU Expansion	10,010.00	D	N/A	
S ✓ ➤	NTV469RA	Speech Recognition - PureSpeech Recite - Pro - 2 Port RTU Expansion	12,830.00	D	N/A	
S ✓ ➤	NTV469SA	Speech Recognition - PureSpeech Recite - IQ - 2 Port RTU Expansion	15,470.00	D	N/A	
S ✓ ➤	NTV469TA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	6,840.00	D	N/A	
S ✓ ➤	NTV469UA	Speech Recognition - PureSpeech Recite - LA Spanish - Lite - 2 Port RTU Expansion	11,380.00	D	N/A	
S ✓ ➤	NTV469VA	Speech Recognition - VCS for Antares - Discrete - 4 Port RTU Expansion	9,890.00	D	N/A	
S ✓ ➤	NTV469WA	Speech Recognition - VCS for Antares - Continuous - 2 Port RTU Expansion	6,180.00	D	N/A	
S ✓ ➤	NTV469YA	Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion	14,770.00	D	N/A	
S ✓ ➤	NTV469ZA	Speech Recognition - PureSpeech Recite - LA Spanish - IQ - 2 Port RTU Expansion	17,940.00	D	N/A	
S ➤	NTV472AA	AC Rack Cabinet - Full Assembly	5,965.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTV472BA	AC Rack Cabinet - Expansion	2,625.00	H	N/A	
S ➤	NTV472DA	DC Rack Cabinet - Full Assembly	5,985.00	H	N/A	
S ➤	NTV472YA	DC Rack Cabinet - Expansion	2,645.00	H	N/A	
S ➤	NTV474NA	(UPS) Shared Rack Model - 110V - Up to 4 MRS/Rack or AP/ Rack Shelves	3,400.00	H	N/A	
S ➤	NTV481CA	Software Upgrade - Open IVR 2.01/2.5 to 4.0 (PEB) - Media (CD) and 1 AP or MRS/AP RTU	4,500.00	D	N/A	
S ➤	NTV481DA	Release 2.X Development to Release 4.0 Development Upgrade	470.00	D	N/A	
S ➤	NTV481HA	Software Upgrade - Host Connectivity Software Upgrade - R2 AP or MRS/AP	130.00	D	N/A	
S ➤	NTV481LA	Software Upgrade - OPEN IVR 2.01/2.5 to 4.0 (PEB) - L and H TTS Dongle Replacement	130.00	D	N/A	
S ➤	NTV481PA	Pentium SBC Upgrade for PEB-based MRS	2,995.00	H	N/A	
S ➤	NTV481SA	Software Upgrade - OPEN IVR 2.0/2.5 to 4.0 (PEB) - Serial Board Upgrade for R2 MRS with Speech Recognition Option	90.00	H	N/A	
S ➤	NTV481UA	Software Upgrade - UPS Software Upgrade - R2 AP, MRS/AP	130.00	D	N/A	
S ➤	NTV482MA	Integration Package for Meridian Link - Media (CD) and 4 Port Base RTU	400.00	D	N/A	
S ➤	NTV482NA	Integration Package for Meridian Link - 4 Port Expansion RTU	375.00	D	N/A	
S ➤	NTV482SA	Integration Package for Meridian Link (SCCS Version) - Base and 4 Port RTU	400.00	D	N/A	
S ➤	NTV482TA	Integration Package for Meridian Link (SCCS Version) - 4 Port Expansion RTU	375.00	D	N/A	
S ➤	NTV491NA	Voice Port Assembly - 16 Port Loopstart Spare - North America	3,995.00	H	2,148.00	H
S ➤	NTV491PA	Voice Port Assembly - 16 Port Loopstart Spare - North America - PULSE DETECTION	5,435.00	H	3,733.00	H
S ➤	NTV492NA	Voice Port Assembly - 24 Port T1 Spare - North America	4,995.00	H	2,885.00	H
S ➤	NTV494NA	Voice Port Assembly - 4 Port Loopstart Spare - North America and CALA	1,200.00	H	710.00	H
S ➤	NTV497LA	Fax - Gammalink - 12 Port Card Spare	7,150.00	H	4,283.00	H
S ➤	NTV497MA	Fax - Gammalink - 6 Port Card Spare	3,800.00	H	2,287.00	H
S ➤	NTV497SA	Fax - Gammalink - 4 Port Card Spare	3,050.00	H	1,826.00	H
S ➤	NTV498PA	DSP Card Spare for Speech Recognition or Text-to-Speech	4,750.00	H	3,242.00	H
S ➤	NTVA0002	Assistant 100 User License	5,000.00	D	N/A	
S Δ	NTVB01AA	CallPilot Asia Pacific Language Prompts CD ROM	8.00	H	N/A	
S Δ	NTVB02AA	CallPilot Asia Pacific Desktop Client CD ROM	8.00	H	N/A	
S Δ	NTVB03AA	CallPilot Asia Pacific Language & Desktop Client CD ROM	8.00	H	N/A	
S Δ	NTVE8202	OPEN IVR Release 4 - Product Guide	47.00	H	N/A	
S Δ	NTVE8203	OPEN IVR Release 4 - System Administration Guide	47.00	H	N/A	
S Δ	NTVE8204	OPEN IVR Release 4 - Installation, Upgrade and Maintenance	47.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	NTVE8205	OPEN IVR Release 4 - Planning and Engineering Guide	47.00	H	N/A	
S Δ	NTVE8206	OPEN IVR Release 4 - Error Messages Guide	47.00	H	N/A	
S Δ	NTVE8207	OPEN IVR Release 4 - Service Console Interface Guide	47.00	H	N/A	
S Δ	NTVE8208	OPEN IVR Release 4 - Cell Catalog Guide	47.00	H	N/A	
S Δ	NTVE8209	OPEN IVR Release 4 - Application Development Guide	47.00	H	N/A	
S Δ	NTVE8210	OPEN IVR Release 4 - Web Option Guide	47.00	H	N/A	
S Δ	NTVE8211	OPEN IVR Release 4 - Fax Option Guide	47.00	H	N/A	
S Δ	NTVE8212	OPEN IVR Release 4 - Speech Recognition Guide	47.00	H	N/A	
S Δ	NTVE8213	OPEN IVR Release 4 - Text-To-Speech Guide	47.00	H	N/A	
S Δ	NTVE8214	SOIVR 4.0 - CAS & ISDN Signaling Option Guide	47.00	H	N/A	
S Δ	NTVE8215	OPEN IVR Release 4 - Integration Package for Meridian Link Guide	47.00	H	N/A	
S Δ	NTVE8218	OPEN IVR Release 4 - Prompt Import Utility Guide	47.00	H	N/A	
S Δ	NTVE8221	OPEN IVR Release 4 - VT100 Configuration and Development Guide	47.00	H	N/A	
S Δ	NTVE8224	Integration Package for Meridian Link (SCCS Version) User Guide	47.00	H	N/A	
S Δ	NTVE8227	OPEN IVR Release 4 - SNA Host Communications Guide	47.00	H	N/A	
S #	NTVE9005	SCSI CD ROM Drive Spare	MD		176.00	H
S #	NTVE9006	3.5" SCSI DAT Tape Drive Spare	MD		555.00	H
S ➤	NTVE9009	PCI 10MB Ethernet Adapter Spare	250.00	H	142.00	H
S #	NTVE9011	14" Monitor Spare	MD		212.00	H
S #	NTVE9012	17" Monitor Spare	MD		655.00	H
S ➤	NTVE9013	101 Enhanced Keyboard Spare	50.00	H	26.00	H
S ➤	NTVE9014	3-Button Mouse Spare	75.00	H	47.00	H
S ➤	NTVE9016	External Modem Spare	275.00	H	160.00	H
S #	NTVE9029	2GB 16BIT Ultra SCSI Disk Drive Spare	MD		534.00	H
S #	NTVE9032	48 VDC TO 120 VAC Static Inverter Spare	MD		1,020.00	H
S ➤	NTVE9041	PCI Video Adapter Spare for OIVR 4.0 AP, MRS/AP, or MRS	100.00	H	N/A	
S ➤	NTVE9044	Rackmount Keyboard Drawer Spare	285.00	H	167.00	H
S ➤	NTVE9045	19" Rackmount Monitor Enclosure Spare	365.00	H	358.00	H
S ➤	NTVE9901	Ethernet Cable 25 Ft. Spare	6.00	H	N/A	
S ➤	NTVE9903	32MB Expansion RAM for MRS/Tower or MRS/Rack Spare	285.00	H	N/A	
S #	NTVE9904	Base Chassis for MRS/AP or AP	MD		887.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTVE9905	Base Single Board Computer for AP or MRS/AP Spare	MD		794.00	H
S ➤	NTVE9906	Base Chassis for OIVR 4.0 Tower AP and MRS/Tower Spare	3,150.00	H	1,893.00	H
S ➤	NTVE9907	Base Single Board Computer for MRS/Tower or MRS/Rack Spare	1,900.00	H	1,921.00	H
S	NTVE9908	Wide to Narrow SCSI Cable Adapter Spare	85.00	H	N/A	
S ➤	NTVE9909	AT to PS/2 Keyboard Cable Adapter Spare	7.00	H	N/A	
S ➤	NTVE9910	Wide SCSI Cable - 68 Pin Spare	200.00	H	N/A	
S ➤	NTVE9911	Base Chassis for MRS/Rack - AC Power Spare	7,400.00	H	4,434.00	H
S ➤	NTVE9912	System Peripheral Switch - 8 Way Spare	1,750.00	H	1,051.00	H
S ➤	NTVE9913	Base Chassis for MRS/Rack - DC Power Spare	7,950.00	H	4,764.00	H
S ➤	NTVE9915	Rackmount Cabinet for MRS/Rack - 21" Spare	2,200.00	H	1,101.00	H
S ➤	NTVE9917	Front or Rear Door Kit for Rack Cabinet Spare	370.00	H	220.00	H
S ➤	NTVE9919	Power Bar - 6 Outlets - 2 Meters Cable Spare	225.00	H	N/A	
S ➤	NTVE9921	DC Power Supply for Rack Cabinet Spare	225.00	H	132.00	H
S ➤	NTVE9923	16MB Expansion RAM for OPEN IVR 2 x AP or MRS/AP Spare	275.00	H	N/A	
S ➤	NTVE9924	Blank DAT Tape - 4/8GB Spare	35.00	H	N/A	
S ➤	NTVE9925	Blank QIC Tape - 2.5GB Spare	75.00	H	N/A	
S ➤	NTVE9926	Head Cleaner DAT Tape Spare	25.00	H	N/A	
S ➤	NTVE9927	48V DC 400W Load Sharing Hot Swap Power Supply Spare	2,125.00	H	1,266.00	H
S ➤	NTVE9928	DC Power Cable for PS400-48 Power Supply Spare	100.00	H	N/A	
S ➤	NTVE9932	Modem Cable Spare (DB9F to DB25M)	37.00	H	N/A	
S	NTVE9933	Power Supply without 3.3V Output (3 Rail) Spare	1,360.00	H	N/A	
S	NTVE9934	Fan Filter Air Spare OIVR 4 MRS/Rack or Rack AP	11.00	H	N/A	
S	NTVE9935	Fan Filter Air (2) Spare OIVR 4 MRS/Rack or Rack AP	11.00	H	N/A	
S	NTVE9936	Assembly DC Entry Spare	740.00	H	N/A	
S	NTVE9937	16/1/3 Passive Backplane Spare OIVR 4 MRS/Rack or Rack AP	688.00	H	N/A	
S Δ	NTVE9938	Hard Drive Mounting Screw for Hot Swappable Drive (1000rp) Spare MRS/Rack or Rack AP	No charge		N/A	
S	NTVE9939	Alarm Status Board Spare OIVR 4 MRS/Rack or Rack AP	661.00	H	N/A	
S	NTVE9940	Fan Module (each) Spare OIVR 4 MRS/Rack or Rack AP	312.00	H	N/A	
S	NTVE9941	SCSI Backplane Spare OIVR 4 MRS/Rack or Rack AP	459.00	H	N/A	
S	NTVE9942	Assembly AC Entry Spare OIVR 4 MRS/Rack or Rack AP	277.00	H	N/A	
S	NTVE9943	6 Drive SCSI Rack Assembly Spare OIVR 4	459.00	H	N/A	
S	NTVE9944	SCSI Rack Drive Carrier (each) Spare OIVR 4	70.00	H	N/A	
S	NTVE9945	Power Supply 350W Spare OIVR 4 AP, MRS/AP	523.00	H	N/A	
S	NTVE9946	Assembly 3-Fan 62XX Spare OIVR 4 AP, MRS/AP, MRS Tower	239.00	H	N/A	
S	NTVE9947	Fan Air Filter Spare OIVR 4 AP, MRS/AP, MRS Tower	18.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	NTVE9951	Share UPS Spare for OIVR 4.0 MRS/Rack or Rack AP	460.00	H	N/A	
S	NTVE9952	Simple Signaling Cable for OIVR 4.0 Rack UPS	45.00	H	N/A	
S	NTVE9953	Keyboard/Monitor/Mouse Cable, Switch Box-to-Peripherals	165.00	H	N/A	
S	NTVE9954	UPS Smart Signalling Cable Spare	46.00	H	N/A	
S	NTVE9955	-5V ISA Card Spare for Rack AP and MRS/Rack	130.00	H	N/A	
S	NTVE9957	Rack AP or MRS/Rack Server-to-Switch Box Cable Spare	165.00	H	N/A	
S	NTVE9958	Tower AP or Tower MRS/AP Wide SCSI Terminator Spare	32.00	H	N/A	
S ➤ Δ	NTVF44AA	SYMPOSIUM Call Center Documentation CD-ROM (Multilingual)	50.00	H	N/A	
S ➤	NTVM0036	Messenger 2.0 Mac Client Package - 100 Users	7,000.00	D	N/A	
S ➤	NTVM0061	Messenger 4.0 Windows Client Package - 25	2,500.00	D	N/A	
S ➤	NTVM00JB	Messenger Fax on Demand Software	5,000.00	D	N/A	
S ➤	NTVM00KA	Uninterruptible Power Supply (UPS) Kit for Messenger Server	1,000.00	H	N/A	
S ➤	NTVM00SD	Messenger Software Brooktrout Upgrade Kit 2.0/3.0 to 4.0	500.00	D	N/A	
S ➤	NTVM00SE	Messenger Software Audiofax Upgrade Kit 2.0/3.0 to 4.0	500.00	D	N/A	
S † ➤ Δ	NTVM00SG	Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (For Customers Under Maintenance or Warranty)	No charge		N/A	
S † ➤	NTVM00SH	Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (Customer Not Under Maintenance or Warranty)	500.00	D	N/A	
S † ➤ Δ	NTVM00SJ	Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Under Maintenance or Warranty)	No charge		N/A	
S † ➤	NTVM00SK	Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Not Under Maintenance or Warranty)	500.00	D	N/A	
S ➤	NTVM00YA	32 MB Memory Upgrade	2,500.00	H	N/A	
S ➤	NTVM00YB	64 MB Memory Upgrade Package	3,500.00	H	N/A	
S ➤	NTVM00ZF	MAS Model 500 2GB Hard Drive Option	2,250.00	H	N/A	
S ➤	NTVM00ZG	MAS Model 501 2GB Hard Drive Option	2,250.00	H	N/A	
S ➤ Δ	NTVM0101	Messenger Quick Reference Card - 25 Pack	25.00	H	N/A	
S ➤ Δ	NTVM0103	Messenger Quick Reference Card - 100 Pack	100.00	H	N/A	
S ➤	NTVM15BA	Messenger 4.0 Server Software and 4 Port Card - Brooktrout	6,000.00	H	N/A	
S ➤	NTVM15CA	Messenger 4.0 Server Software Only Kit - Brooktrout	6,000.00	H	N/A	
S ✓ ➤	NTVM17AA	Audiofax Server Software Only (Kit)	3,500.00	H	N/A	
S ➤	NTVM18AA	MAS-Model 100 Spares Kit	6,000.00	H	N/A	
S ➤	NTVM19AA	MAS-Model 500 Spares Package	10,000.00	H	N/A	
S ➤	NTVM19AB	MAS Model 501 Spares Kit	10,000.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTVM4019	Ethernet LAN Interface Board	300.00	H	N/A	
S ➤	NTVM4024	Token Ring LAN Interface Board	1,000.00	H	N/A	
S ➤	NTVM60AA	Messenger Computer Based Training	200.00	H	N/A	
S ➤	NTVP1000	Meridian Integrated RAN (Release 2) Small (5 Channels)	3,600.00	D	800.00	H
S ➤	NTVP1001	Meridian Integrated RAN (Release 2) Medium (6 Channels)	5,400.00	D	800.00	H
S ➤	NTVP1002	Meridian Integrated RAN (Release 2) Large (10 Channels)	6,400.00	D	800.00	H
S ➤	NTVP1010	Meridian Integrated RAN (Release 2) Small to Medium Upgrade	1,800.00	D	N/A	
S ➤	NTVP1011	Meridian Integrated RAN (Release 2) Medium to Large Upgrade	1,000.00	D	N/A	
S ➤	NTVP1012	Meridian Integrated RAN (Release 2) Small to Large Upgrade	2,800.00	D	N/A	
S ➤	NTWE04AC	Meridian ITG 2.0 Inter-Cabinet Cable 10 Ft. (Optional)	80.00	D	N/A	
S ➤	NTWE04AD	Meridian ITG 2.0 Intra-Cabinet Cable 1 Ft.	50.00	D	N/A	
S ➤	NTWE07AA	ITG 2.0 Pre-programmed Q.SIG D-Channel Interface PCMCIA Card	1,500.00	D	N/A	
S ➤ Δ	NTY210AA	View Manager with 5 User License			N/A	
S ➤ Δ	NTY211AA	View Manager with 25 User License			N/A	
S ➤ Δ	NTY212AA	View Manager with 50 User License			N/A	
S ➤ Δ	NTY213AA	View Manager with 100 User License			N/A	
S ➤ Δ	NTY214AA	View Manager with 200 User License			N/A	
S ➤ Δ	NTY215AA	View Manager with Greater than 200 User License			N/A	
S ➤ Δ	NTY216AA	View Manager Basic Technical Support	N/A	H	N/A	
S ➤ Δ	NTY217AA	View Manager Elite Technical Support	N/A	H	N/A	
S ➤ Δ	NTY218AA	View Manager Custom Configuration	N/A	H	N/A	
S ➤ Δ	NTY219AA	View Manager OEM Configuration	N/A	H	N/A	
S ➤ Δ	NTY220AA	View Manager Documentation Set			N/A	
S ➤ Δ	NTY221AA	View Manager Quick Reference Guides			N/A	
S ➤ Δ	NTY222AA	View Manager Product Training	N/A	H	N/A	
S ➤ Δ	NTY223AA	View Manager Consulting and Professional Services	N/A	H	N/A	
S ➤ Δ	NTY224AA	View Manager Installation Services	N/A	H	N/A	
S ➤ Δ	NTY230AA	View Manager License Upgrade to 25 Users			N/A	
S ➤ Δ	NTY231AA	View Manager License Upgrade to 50 Users			N/A	
S ➤ Δ	NTY232AA	View Manager License Upgrade to 100 Users			N/A	
S ➤ Δ	NTY233AA	View Manager License Upgrade to 200 Users			N/A	
S ➤ Δ	NTY240AA	APM, 1 Server/100 Seat Configuration			N/A	
S ➤ Δ	NTY241AA	APM, 10 Servers/1000 Seat Configuration			N/A	
S ➤ Δ	NTY242AA	APM, 25 Servers/2500 Seat Configuration			N/A	
S ➤ Δ	NTY243AA	APM, 100 Servers/5000 Seat Configuration			N/A	
S ➤ Δ	NTY244AA	APM, 250 Servers/10000 Seat Configuration			N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	NTY245AA	APM, 500 Servers/25000 Seat Configuration	N/A	H	N/A	
S ➤ Δ	NTY246AA	APM, Custom Configurations	N/A	H	N/A	
S ➤ Δ	NTY247AA	APM, Unlimited Configuration	N/A	H	N/A	
S ➤ Δ	NTY248AA	APM, OEM Configuration	N/A	H	N/A	
S ➤ Δ	NTY250AA	Legacy Module for APM, 1 Server/100 Seats	N/A	H	N/A	
S ➤ Δ	NTY251AA	Legacy Module for APM, 10 Servers/1000 Seats	N/A	H	N/A	
S ➤ Δ	NTY252AA	Legacy Module for APM, 25 Servers/2500 Seats	N/A	H	N/A	
S ➤ Δ	NTY253AA	Legacy Module for APM, 100 Servers/5000 Seats	N/A	H	N/A	
S ➤ Δ	NTY254AA	Legacy Module for APM, 250 Servers/10000 Seats	N/A	H	N/A	
S ➤ Δ	NTY255AA	Legacy Module for APM, 500 Servers/25000 Seats	N/A	H	N/A	
S ➤ Δ	NTY256AA	Legacy Module for APM, Custom Configuration	N/A	H	N/A	
S ➤ Δ	NTY257AA	Legacy Module for APM, Unlimited Configuration	N/A	H	N/A	
S ➤ Δ	NTY260AA	APM Upgrade, 1 Server/100 Seats to 10 Servers/1000 Seats			N/A	
S ➤ Δ	NTY261AA	APM Upgrade, 10 Servers/1000 Seats to 25 Servers/2500 Seats			N/A	
S ➤ Δ	NTY262AA	APM Upgrade, 25 Servers/2500 Seats to 100 Servers/5000 Seats			N/A	
S ➤ Δ	NTY263AA	APM Upgrade, 100 Servers/5000 Seats to 250 Servers/10000 Seats			N/A	
S ➤ Δ	NTY264AA	APM Upgrade, 250 Servers/10000 Seats to 500 Servers/25000 Seats	N/A	H	N/A	
S ➤ Δ	NTY265AA	APM Custom Upgrade	N/A	H	N/A	
S ➤ Δ	NTY270AA	APM, Installation (Mandatory Service, Performed by a Certified APM Installation Engineer)	N/A	H	N/A	
S ➤ Δ	NTY271AA	APM, Professional Services/System Integration/Consulting	N/A	H	N/A	
S ➤ Δ	NTY272AA	APM, Product Training			N/A	
S ➤ Δ	NTY273AA	APM, Full Documentation (Hardcopy)			N/A	
S ➤ Δ	NTY274AA	APM, Quick Reference Guides (Hardcopy)			N/A	
S ➤ Δ	NTY275AA	APM, Basic Membership Support Package, Renewed Annually	N/A	H	N/A	
S ➤ Δ	NTY276AA	APM, Elite Membership Support Package, Renewed Annually	N/A	H	N/A	
S ➤ Δ	NTY277AA	APM, Service Provider Hosted Model	N/A	H	N/A	
S ➤ Δ	NTY278AA	View Manager for Hosted Service Provider	N/A	H	N/A	
S ➤	NTZB01AA	Meridian Integrated Conference Bridge (Release 2) 12 Port Card	12,000.00	D	2,400.00	H
S ➤	NTZB01BA	Meridian Integrated Conference Bridge (Release 2) 16 Port Card	16,000.00	D	2,400.00	H
S ➤	NTZB01CA	Meridian Integrated Conference Bridge (Release 2) 24 Port Card	24,000.00	D	2,400.00	H
S ➤	NTZB01DA	Meridian Integrated Conference Bridge (Release 2) 32 Port Card	32,000.00	D	2,400.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZB02AA	Meridian Integrated Conference Bridge (Release 2) 12 to 16 Port Upgrade	4,000.00	D	N/A	
S ➤	NTZB02BA	Meridian Integrated Conference Bridge (Release 2) 12 to 24 Port Upgrade	12,000.00	D	N/A	
S ➤	NTZB02CA	Meridian Integrated Conference Bridge (Release 2) 12 to 32 Port Upgrade	20,000.00	D	N/A	
S ➤	NTZB02DA	Meridian Integrated Conference Bridge (Release 2) 16 to 24 Port Upgrade	8,000.00	D	N/A	
S ➤	NTZB02EA	Meridian Integrated Conference Bridge (Release 2) 16 to 32 Port Upgrade	16,000.00	D	N/A	
S ➤	NTZB02FA	Meridian Integrated Conference Bridge (Release 2) 24 to 32 Port Upgrade	8,000.00	D	N/A	
S ➤	NTZB05AA	Meridian Text Telephony System PC Client Package - 25 Users	3,800.00	D	N/A	
S ➤	NTZB05BA	Meridian Text Telephony System PC Client Package - 50 Users	6,800.00	D	N/A	
S ➤	NTZB05CA	Meridian Text Telephony System PC Client Package - 100 Users	10,800.00	D	N/A	
S ➤	NTZB05DA	Meridian Text Telephony System PC Client Package - 250 Users	23,000.00	D	N/A	
S ➤	NTZB05MA	Meridian Text Telephony System TDD/TTY Modem	540.00	H	N/A	
S ➤	NTZB06AB	Mini Local Package (Options 21-81)	6,000.00	I	N/A	
S ➤	NTZB07AB	Mini Local Package (Option 11)	6,000.00	I	N/A	
S ➤	NTZB08AA	Mini Remote Package AC	8,000.00	I	N/A	
S ➤	NTZB09AA	Mini Remote Package DC	8,000.00	I	N/A	
S ➤	NTZB11AB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6A (1-19 Units)	850.00	D	N/A	
S ➤	NTZB11BB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6B (20-49 units)	800.00	D	N/A	
S ➤	NTZB11CB	SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6C (50+ Units)	750.00	D	N/A	
S ➤	NTZB13AB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7A (1-19 Units)	1,100.00	D	N/A	
S ➤	NTZB13BB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7B (20-49 units)	1,050.00	D	N/A	
S ➤	NTZB13CB	SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7C (50+ Units)	1,000.00	D	N/A	
S ➤	NTZB15AB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8A (1-19 Units)	1,650.00	D	N/A	
S ➤	NTZB15BB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8B (20-49 Units)	1,600.00	D	N/A	
S ➤	NTZB15CB	SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8C (50+ Units)	1,550.00	D	N/A	
S Δ	NTZB2101	Installation Diskette	No charge		N/A	
S #	NTZB22AA	Meridian Integrated Conference Bridge (Ide@Room Version) 24 Port Card	MD		3,000.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	NTZB22DA	Meridian Integrated Conference Bridge (Ide@Room Version) 32 Port Card	MD		3,000.00	H
S ✓ ➤	NTZB77AA	Meridian Integrated Personal Call Director, 8 ports 50 users	7,500.00	D	N/A	
S ✓ ➤	NTZB78AA	Meridian Integrated Personal Call Director, 16 ports 100 users	14,500.00	D	N/A	
S ✓ ➤	NTZB79AA	Meridian Integrated Personal Call Director, 24 ports 150 users	21,000.00	D	N/A	
S ✓ ➤	NTZB80AA	Meridian Integrated Personal Call Director, 32 ports 200 users	27,000.00	D	N/A	
S ➤	NTZB87AA	MIPCD 50 Users Expansion	3,300.00	D	N/A	
S ➤	NTZB88AA	MIPCD 8 Port Upgrade	8,000.00	D	N/A	
S ➤	NTZB88BA	MIPCD 16 Port Upgrade	15,000.00	D	N/A	
S ➤	NTZB88CA	MIPCD 24 port Upgrade	20,000.00	D	N/A	
S ➤	NTZB91AA	MICA PCMCIA Hard Drive with 5 Ports	6,594.00	D	N/A	H
S ➤	NTZB91BA	MICA PCMCIA Hard Drive with 8 Ports	9,475.00	D	N/A	H
S ➤	NTZB91CA	MICA PCMCIA Hard Drive with 12 Ports	12,995.00	D	N/A	H
S ➤	NTZB91DA	MICA PCMCIA Hard Drive with 16 Ports	15,995.00	D	N/A	H
S ➤	NTZB91EA	MICA PCMCIA Hard Drive with 20 Ports	18,595.00	D	N/A	H
S ➤	NTZB91FA	MICA PCMCIA Hard Drive with 24 Ports	20,795.00	D	N/A	H
S ➤	NTZB91GA	MICA PCMCIA Hard Drive with 28 Ports	22,595.00	D	N/A	H
S ➤	NTZB91HA	MICA PCMCIA Hard Drive with 32 Ports	23,995.00	D	N/A	H
S ➤	NTZB92AA	MICA PCMCIA Flash with 5 Ports	5,000.00	D	N/A	H
S ➤	NTZB92BA	MICA PCMCIA Flash with 8 Ports	7,880.00	D	N/A	H
S ➤	NTZB92CA	MICA PCMCIA Flash with 12 Ports	11,400.00	D	N/A	H
S ➤	NTZB92DA	MICA PCMCIA Flash with 16 Ports	14,400.00	D	N/A	H
S ➤	NTZB92EA	MICA PCMCIA Flash with 20 Ports	17,000.00	D	N/A	H
S ➤	NTZB92FA	MICA PCMCIA Flash with 24 Ports	19,200.00	D	N/A	H
S ➤	NTZB92GA	MICA PCMCIA Flash with 28 Ports	21,000.00	D	N/A	H
S ➤	NTZB92HA	MICA PCMCIA Flash with 32 Ports	22,400.00	D	N/A	H
S ➤	NTZB93AA	MICA Upgrade add 3 ports	3,000.00	D	N/A	
S ➤	NTZB93BA	MICA Upgrade add 4 ports	4,000.00	D	N/A	
S ➤	NTZB93CA	MICA Upgrade add 8 ports	8,000.00	D	N/A	
S ➤	NTZB93DA	MICA Upgrade add 16 ports	15,200.00	D	N/A	
S ➤	NTZB93EA	MICA Upgrade add 24 ports	21,600.00	D	N/A	
S ➤	NTZB93FA	MICA Upgrade Add 27 Ports	23,800.00	D	N/A	
S ➤	NTZB93GA	MICA Upgrade Add 12 Ports	11,600.00	D	N/A	
S ➤	NTZB94AA	Meridian Integrated Conference Bridge (Release 2) 42 Port Card	42,000.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZB94BA	Meridian Integrated Conference Bridge (Release 2) 50 Port Card	50,000.00	D	N/A	
S ➤	NTZB94CA	Meridian Integrated Conference Bridge (Release 2) 62 Port Card	62,000.00	D	N/A	
S ➤	NTZB95AA	Meridian Integrated Conference Bridge (Release 2) 12 to 42 Port Upgrade	30,000.00	D	N/A	
S ➤	NTZB95BA	Meridian Integrated Conference Bridge (Release 2) 12 to 50 Port Upgrade	38,000.00	D	N/A	
S ➤	NTZB95CA	Meridian Integrated Conference Bridge (Release 2) 12 to 62 Port Upgrade	50,000.00	D	N/A	
S ➤	NTZB95DA	Meridian Integrated Conference Bridge (Release 2) 16 to 42 Port Upgrade	26,000.00	D	N/A	
S ➤	NTZB95EA	Meridian Integrated Conference Bridge (Release 2) 16 to 50 Port Upgrade	34,000.00	D	N/A	
S ➤	NTZB95FA	Meridian Integrated Conference Bridge (Release 2) 16 to 62 Port Upgrade	46,000.00	D	N/A	
S ➤	NTZB95GA	Meridian Integrated Conference Bridge (Release 2) 24 to 42 Port Upgrade	18,000.00	D	N/A	
S ➤	NTZB95HA	Meridian Integrated Conference Bridge (Release 2) 24 to 50 Port Upgrade	26,000.00	D	N/A	
S ➤	NTZB95JA	Meridian Integrated Conference Bridge (Release 2) 24 to 62 Port Upgrade	38,000.00	D	N/A	
S ➤	NTZB95KA	Meridian Integrated Conference Bridge (Release 2) 32 to 42 Port Upgrade	10,000.00	D	N/A	
S ➤	NTZB95LA	Meridian Integrated Conference Bridge (Release 2) 32 to 50 Port Upgrade	18,000.00	D	N/A	
S ➤	NTZB95MA	Meridian Integrated Conference Bridge (Release 2) 32 to 62 Port Upgrade	30,000.00	D	N/A	
S ➤	NTZB95NA	Meridian Integrated Conference Bridge (Release 2) 42 to 50 Port Upgrade	8,000.00	D	N/A	
S ➤	NTZB95PA	Meridian Integrated Conference Bridge (Release 2) 42 to 62 Port Upgrade	20,000.00	D	N/A	
S ➤	NTZB95QA	Meridian Integrated Conference Bridge (Release 2) 50 to 62 Port Upgrade	12,000.00	D	N/A	
S ➤	NTZB96AA	Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) PCMCIA Upgrade Kit	3,000.00	D	N/A	
S ➤	NTZB96BA	Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) Card Upgrade Kit	9,000.00	D	N/A	
S ➤	NTZC01AF	MAT 6, End User Common Services	875.00	D	N/A	
S ➤ Δ	NTZC01BF	MAT 6, Distributor Common Services	5,000.00	H	N/A	
S ➤	NTZC02AA	MAT 6 Station Administration Module	650.00	D	N/A	
S ➤	NTZC02BA	MAT 6 Traffic Analysis Module	4,300.00	D	N/A	
S ➤	NTZC02CA	MAT 6 Call Tracking Module	750.00	D	N/A	
S ➤	NTZC02DA	MAT 6 Call Accounting Module	1,800.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZC02EA	MAT 6 ESN Analysis and Reporting Tool Module	2,875.00	D	N/A	
S ➤	NTZC02FA	MAT 6 Maintenance Windows Module	6,500.00	D	N/A	
S ➤	NTZC02GA	MAT 6 Alarm Management Module	3,500.00	D	N/A	
S ➤ Δ	NTZC03AF	MAT 6, User Guide and CD Package	75.00	H	N/A	
S ➤	NTZC04AA	MAT 6 Maintenance Marketing Bundle	11,500.00	D	N/A	
S ➤	NTZC04BA	MAT 6 Administration Marketing Bundle	5,500.00	D	N/A	
S ➤	NTZC04CA	MAT 6 System Management Marketing Bundle	17,500.00	D	N/A	
S ➤	NTZC06AA	MAT 6 Station Administration Upgrade	160.00	D	N/A	
S ➤	NTZC06BA	MAT 6 Traffic Analysis Upgrade	650.00	D	N/A	
S ➤	NTZC06CA	MAT 6 Call Tracking Upgrade	190.00	D	N/A	
S ➤	NTZC06DA	MAT 6 Call Accounting Base Upgrade	450.00	D	N/A	
S ➤ Δ	NTZC07AF	MAT 6, Distributor Single Location Common Services and Station Upgrade	1,000.00	H	N/A	
S ➤ Δ	NTZC08AF	MAT 5/6 to MAT 6.X, Flat Fee Upgrade	299.00	H	N/A	
S ➤	NTZC09AF	MAT 6, End User Common Services Upgrade	200.00	D	N/A	
S ➤	NTZC10AF	PC Dongle for One (1) PC and User Guide	500.00	D	N/A	
S ➤	NTZC10BF	PC Dongles for Five (5) PC and User Guides	2,000.00	D	N/A	
S ➤	NTZC10CF	PC Dongles for Ten (10) PC and User Guides	3,000.00	D	N/A	
S ➤	NTZC10DF	PC Dongles for Fifty (50) PC and 30 User Guides	10,000.00	D	N/A	
S ➤	NTZC10EF	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	37,500.00	D	N/A	
S ➤	NTZC12CA	Meridian IP Telephony Gateway (ITG) Small and Large Systems Package	3,290.00	D	N/A	
S #	NTZC13AA	Meridian Integrated IP Telephony Gateway (ITG) Card	MD		1,700.00	H
S ➤	NTZC13BA	Meridian IP Telephony Gateway (ITG) Card	3,160.00	D	1,700.00	H
S ➤	NTZC14AA	Meridian Integrated IP Telephony Gateway (ITG) PCMCIA Card	800.00	H	N/A	
S ➤	NTZC19AA	Meridian IP Telecommuter PCMCIA Card	800.00	D	N/A	
S ✓ ➤	NTZC35AA	Meridian 1 Attendant Hospitality Services 1 Console Bundle	9,000.00	D	N/A	
S ➤	NTZC35BA	Meridian 1 Attendant Hospitality Services 2 Console Bundle	17,200.00	D	N/A	
S ✓ ➤	NTZC35CA	Meridian 1 Attendant Hospitality Services 3 Console Bundle	28,500.00	D	N/A	
S ✓ ➤	NTZC35DA	Meridian 1 Attendant Hospitality Services Large (4) Console Bundle	37,000.00	D	N/A	
S ✓ ➤	NTZC35EA	Meridian 1 Attendant Hospitality Services Large Expansion Bundle	7,000.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTZC36AA	Meridian 1 Attendant Hospitality Services 1 Console Software Bundle	6,000.00	D	N/A	
S ➤	NTZC36BA	Meridian 1 Attendant Hospitality Services 2 Console Software Bundle	9,200.00	D	N/A	
S ✓ ➤	NTZC36CA	Meridian 1 Attendant Hospitality Services 3 Console Software Bundle	15,000.00	D	N/A	
S ✓ ➤	NTZC36DA	Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle	25,000.00	D	N/A	
S ➤	NTZC36EA	Meridian 1 Attendant Hospitality Services Large Software Expansion Bundle	3,500.00	D	N/A	
S ➤	NTZC37AA	Meridian 1 Attendant Hospitality Services Software for Expansion from 1 to 2 Console Bundle	3,500.00	D	N/A	
S ✓ ➤	NTZC37BA	Meridian 1 Attendant Hospitality Services Software for Expansion from 2 to 3 Console Bundle	7,000.00	D	N/A	
S ✓ ➤	NTZC37CA	Meridian 1 Attendant Hospitality Services Software for Expansion from 3 to 4 Console Bundle	10,000.00	D	N/A	
S ➤	NTZC44AA	Meridian ITG 2.0 ISDN Large Systems Package	7,300.00	D	N/A	
S ➤	NTZC44BA	Meridian ITG 2.0 ISDN Small Systems Package	7,300.00	D	N/A	
S ➤	NTZC45AA	Meridian ITG 2.0 Small and Large Systems 24-Port Package	6,590.00	D	N/A	
S ➤	NTZC47AA	Meridian ITG 2.0 Large Systems Upgrade Kit from ITG 1.0 to ITG 2.0	900.00	D	N/A	
S ➤	NTZC47BA	Meridian ITG 2.0 Small Systems Upgrade Kit from ITG 1.0 to ITG 2.0	900.00	D	N/A	
S § ➤	NTZC49AA	Enhanced Meridian Mail Card Option 4-12 Ports, 5/10/24/54 Hours Package	13,000.00	D	N/A	
S ➤	NTZC50AA	Enhanced Card Option 2 Basic Service Ports - Ports 5 and 6 or 9 and 10	1,400.00	D	N/A	
S ➤	NTZC50BA	Enhanced Card Option 2 Basic Service Ports - Ports 7 and 8 or 11 and 12	1,400.00	D	N/A	
S ➤	NTZC51AA	2 Full Services Ports - Ports 5 & 6 or 9 & 10	4,500.00	D	N/A	
S ➤	NTZC51BA	2 Full Service Ports - Ports 3 & 4, 7 & 8 or 11 & 12	4,500.00	D	N/A	
S ➤	NTZC52AA	Enhanced Meridian Mail EC11 1 to 2 Node Expansion Package	12,200.00	D	N/A	
S ➤	NTZC53AA	Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package AC	12,500.00	D	N/A	
S ➤	NTZC53BA	Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package DC	12,500.00	D	N/A	
S ➤	NTZC54AA	Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package AC	12,500.00	D	N/A	
S ➤	NTZC54BA	Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package DC	12,500.00	D	N/A	
S ➤	NTZC55AA	Enhanced Meridian Mail Modular EC Node Expansion 3rd Position Package	10,500.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZC56AA	Enhanced Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	NTZC56BA	Enhanced Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	NTZC56CA	Enhanced Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC	12,250.00	D	N/A	
S ➤	NTZC56DA	Enhanced Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC	15,250.00	D	N/A	
S ✓ § ➤	NTZC57AA	Meridian Mail Release 13 Base Software	1,000.00	D	N/A	
S ➤	NTZC57BA	Meridian Mail EC11 Base Software, Release 13	2,000.00	D	N/A	
S ✓ § ➤	NTZC58AA	Meridian Mail Mini Option, 2 Ports, 2 Hours Package	9,750.00	D	N/A	
S ✓ § ➤	NTZC58BA	Meridian Mail Mini Option, 4 Ports, 5 Hours Package	13,000.00	D	N/A	
S ✓ § ➤	NTZC58CA	Meridian Mail Mini Option, 8 Ports, 5 Hours Package	22,000.00	D	N/A	
S ➤	NTZC59AA	Meridian Mail Expanded Storage Software Level 0-1	1,500.00	D	N/A	
S ➤	NTZC62AA	Meridian Integrated Voice Services, 2 Port	5,000.00	D	1,800.00	H
S ➤	NTZC62BA	Meridian Integrated Voice Services, 4 Port	7,500.00	D	2,500.00	H
S ➤	NTZC62CA	Meridian Integrated Voice Services, 8 Port	10,500.00	D	3,100.00	H
S ➤	NTZC63AA	Meridian Integrated Voice Services, 2 to 4 Port Upgrade	3,000.00	D	N/A	
S ➤	NTZC63BA	Meridian Integrated Voice Services, 2 to 8 Port Upgrade	6,000.00	D	N/A	
S ➤	NTZC63CA	Meridian Integrated Voice Services, 4 to 8 Port Upgrade	4,500.00	D	N/A	
S ➤	NTZC65AA	IP Telecommuter System Package	12,500.00	D	N/A	
S Δ	NTZC70AA	Base Software Features Package - Options 153 and 209	No charge		N/A	
S Δ	NTZC70BA	Software Features Package (CCS100) - Options 214, 215, 218	No charge		N/A	
S Δ	NTZC70CA	Software Features Package (CCS300) - Option 207	No charge		N/A	
S Δ	NTZC70DA	Software Features Package (Base) - Options 42, 43, 50, 114, and 155	No charge		N/A	
S ➤	NTZC75AA	32MB DRAM SIMM Upgrade Kit	350.00	D	N/A	
S ➤	NTZC76AA	32MB Flash Memory Upgrade Kit	700.00	D	N/A	
S ➤	NTZC77AA	ESD/DRAM SIMM Accessory Kit	200.00	D	N/A	
S ★ ➤	NTZC80AA	Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card	6,000.00	D	N/A	
S ★ ➤	NTZC81AA	Meridian IP Telephony Gateway Line 2.0 Systems Package	6,200.00	D	N/A	
S ★ ➤ Δ	NTZC82AA	Internet Telephone Software Parameter (Large System)	90.00	D	N/A	
S ★ ➤ Δ	NTZC84AA	Internet Telephone Software Parameter (Small System)	90.00	D	N/A	
S ➤	NTZC91BA	Software Installation Kit (Non-Autovon)	650.00	H	N/A	
S ➤	NTZD0001	Marketing Package Symposium Call Center Server, New System	No charge		N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZD0002	Marketing Package Symposium Call Center Server, Upgrade System	No charge		N/A	
S	NTZD0003	Marketing Package Symposium Call Center Server, Spare System	No charge		N/A	
S ➤	NTZD0004	Marketing Package Symposium Call Center Server, NCC	No charge		N/A	
S ★ ➤ Δ	NTZD0005	Marketing Package DMS SYMPOSIUM Call Center Server, New System	No charge		N/A	
S ★ ➤ Δ	NTZD0006	Marketing Package DMS SYMPOSIUM Call Center Server, Upgrade System	No charge		N/A	
S ★ ➤ Δ	NTZD0007	Marketing Package DMS SYMPOSIUM Call Center Server, Spare System	No charge		N/A	
S ✓ ➤	NTZD02AA	SYMPOSIUM Call Center Server, 702t Advanced with Windows NT 3.51	8,100.00	H	N/A	
S ★ ➤	NTZD02AD	SYMPOSIUM Call Center Server, 702t Advanced	8,100.00	H	N/A	
S ✓ ➤	NTZD02BA	SYMPOSIUM Call Center Server, 702t Advanced with RAID with Windows NT 3.51	12,500.00	H	N/A	
S ★ ➤	NTZD02BD	SYMPOSIUM Call Center Server, 702t Advanced with RAID	12,500.00	H	N/A	
S ➤	NTZD06AF	SCCS Software Upgrade Package, R1.1/1.5 to R3.0	No charge		N/A	
S ➤ Δ	NTZD07AA	SYMPOSIUM Call Center Server Graphical Real Time Display CD-ROM	50.00	H	N/A	
S ➤	NTZD08AA	SYMPOSIUM Call Center Server Windows NT 4.0 Client CD-ROM	50.00	H	N/A	
S ➤ Δ	NTZD10AA	SCCS Marketing Package, Windows NT 4.0 Client	50.00	H	N/A	
S ➤	NTZD10AF	SCCS Software Upgrade Package, R1.0 to R3.0	No charge		N/A	
S ➤	NTZD13AF	Marketing Package, SCCS NCC (Network Control Center) Release 3.0 Software	28,000.00	D	N/A	
S ★ ➤	NTZD21AA	DMS SCCS Release 3.0 Peripherals Package	1,000.00	D	N/A	
S ★ ➤	NTZD24AA	Software Assembly, SCCS Release 3 Base Software (DMS/MSL)	3,980.00	D	N/A	
S ★ ➤	NTZD26AA	702t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	12,500.00	D	N/A	
S ➤	NTZD27AA	1003t SYMPOSIUM Call Center Server Advanced with RAID (DMS)	24,600.00	D	N/A	
S ➤	NTZD61AA	Meridian Mail Reporter Single Site Software, Option 11 MM13	1,600.00	D	N/A	
S ➤	NTZD61BA	Meridian Mail Reporter Multi Site Software, Option 11 - MM13	2,100.00	D	N/A	
S ➤	NTZD62AA	Assembly, Meridian Mail Alternate User Interface 1	600.00	D	N/A	
S ✓ ➤	NTZD63AA	Meridian Mail Card Option Release 6 to Release 13 Upgrade	1,700.00	D	N/A	
S ✓ ➤	NTZD63BA	Meridian Mail Card Option Release 8/9/10/11/12 to Release 13 Upgrade	1,200.00	D	N/A	
S ✓ ➤	NTZD65AA	Meridian Mail EC11 Release 10, 11, or 12 to Release 13 Upgrade	1,200.00	D	N/A	
S ➤	NTZD66AA	Meridian Mail Reporter Single Site Software MM13	2,800.00	D	N/A	
S ➤	NTZD66BA	Meridian Mail Reporter Multi Site Software Release 13	3,300.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤ Δ	NTZD67AA	Meridian Mail Release 8, 9, 10, 11, or 12 to Release 13 Migration, Options, Modular Option to Modular EC	1,200.00	D	N/A	
S ✓ ➤	NTZD68AA	Meridian Mail EC Release 8, 9.19 to Release 13 Upgrade	5,400.00	D	N/A	
S ✓ ➤	NTZD68BA	Meridian Mail EC Release 9.58 and Later/Release 10/11/12 to Release 13 Upgrade	1,700.00	D	N/A	
S ✓ ➤	NTZD69AA	Meridian Mail Release 4 to Release 13 Software Migration, GP to Modular GP	6,700.00	D	N/A	
S ✓ ➤	NTZD69BA	Meridian Mail Modular GP Release 5 to Release 13 Upgrade or Migration from GP to Modular GP	6,700.00	D	N/A	
S ✓ ➤	NTZD69CA	Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP	6,000.00	D	N/A	
S ✓ ➤	NTZD69DA	Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP	5,400.00	D	N/A	
S ✓ ➤	NTZD69EA	Meridian Mail Modular GP Release 9/10/11/12 to Release 13 Upgrade or Migration from GP to Modular GP	1,700.00	D	N/A	
S ✓ ➤	NTZD70AA	Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option	6,700.00	D	N/A	
S ✓ ➤	NTZD70BA	Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option	6,000.00	D	N/A	
S ✓ ➤	NTZD70CA	Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option	5,400.00	D	N/A	
S ✓ ➤	NTZD70DA	Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option	1,700.00	D	N/A	
S ✓ ➤	NTZD70EA	Meridian Mail Release 3 to Release 13 Software Migration, from Options to Modular Option	6,700.00	D	N/A	
S ✓ ➤	NTZD70FA	Meridian Mail Release 4 to Release 13 Software Migration, from Options to Modular Option	6,700.00	D	N/A	
S ➤	NTZD71AA	Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package AC	11,250.00	D	N/A	
S ➤	NTZD71BA	Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package DC	11,250.00	D	N/A	
S ➤	NTZD72AA	Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package AC	12,250.00	D	N/A	
S ➤	NTZD72BA	Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package DC	12,250.00	D	N/A	
S ➤	NTZD73AA	Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package AC	12,250.00	D	N/A	
S ➤	NTZD73BA	Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package DC	12,250.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZD74AA	Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package AC	10,250.00	D	N/A	
S ➤	NTZD74BA	Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package DC	10,250.00	D	N/A	
S ➤	NTZD75AA	Enhanced Processor Upgrade, EC	3,500.00	D	N/A	
S ➤	NTZD75BA	Enhanced Processor Upgrade, Modular Option, Modular Option GP	3,500.00	D	N/A	
S ➤	NTZD81AA	SCCS Software Upgrade Package for Individual Agents, R1.0/ R1.1/R1.5 to R3.0	125.00	D	N/A	
S ✓ ➤	NTZE01AA	CallPilot IPE Base System - English	20,000.00	D	N/A	
S ✓ ➤	NTZE02AA	CallPilot Tower System - English	45,000.00	D	N/A	
S ✓ ➤	NTZE03AA	CallPilot Rack Mount System DC - English	75,000.00	D	N/A	
S ✓ ➤	NTZE04AA	CallPilot Rack Mount System AC - English	75,000.00	D	N/A	
S ✓ ➤	NTZE07AA	CallPilot 4 Voice Channels	8,000.00	D	N/A	
S ✓ ➤	NTZE07BA	CallPilot 2 FAX Channels	8,000.00	D	N/A	
S ✓ ➤	NTZE07CA	CallPilot 1 Speech Activated Messaging Channel	8,000.00	D	N/A	
S ★ ➤	NTZE07EA	CallPilot 2 Voice Channels	4,000.00	D	N/A	
S ✓ ➤	NTZE08AA	CallPilot Storage Expansion - 10 hours	500.00	D	N/A	
S ✓ ➤	NTZE08BA	CallPilot Storage Expansion - 50 Hours	1,250.00	D	N/A	
S ✓ ➤	NTZE10AA	CallPilot FAX Capability -20 Users	1,000.00	D	N/A	
S ✓ ➤	NTZE10BA	CallPilot FAX Capability - 50 Users	1,500.00	D	N/A	
S ✓ ➤	NTZE10CA	CallPilot FAX Capability - 100 Users	2,500.00	D	N/A	
S ✓ ➤	NTZE10DA	CallPilot FAX Capability - 200 Users	4,500.00	D	N/A	
S ✓ ➤	NTZE10EA	CallPilot FAX Capability - 500 Users	8,000.00	D	N/A	
S ✓ ➤	NTZE10FA	CallPilot FAX Capability - 1000 Users	14,000.00	D	N/A	
S ★ Δ	NTZE10HA	CallPilot Fax Capability - 20 Users	1,000.00	D	N/A	
S ★	NTZE10JA	CallPilot 5000 Fax Users	50,000.00	D	N/A	
S ★ Δ	NTZE10KA	CallPilot Fax Capability - 200 Users	4,500.00	D	N/A	
S ✓ ➤	NTZE11AA	CallPilot Desktop Messaging Capability - 20 Users	2,000.00	D	N/A	
S ✓ ➤	NTZE11BA	CallPilot Desktop Messaging Capability - 50 Users	3,500.00	D	N/A	
S ✓ ➤	NTZE11CA	CallPilot Desktop Messaging Capability - 100 Users	6,000.00	D	N/A	
S ✓ ➤	NTZE11DA	CallPilot Desktop Messaging Capability - 200 Users	11,000.00	D	N/A	
S ➤	NTZE11EA	CallPilot Desktop Messaging Capability - 500 Users	25,000.00	D	N/A	
S ➤	NTZE11FA	CallPilot Desktop Messaging Capability - 1000 Users	40,000.00	D	N/A	
S ★ Δ	NTZE11HA	CallPilot Desktop Messaging Capability - 20 Users	2,000.00	D	N/A	
S ★	NTZE11JA	CallPilot Desktop Messaging Capability - 5000 Users	125,000.00	D	N/A	
S ★ Δ	NTZE11KA	CallPilot Desktop Messaging Capability - 200 Users	11,000.00	D	N/A	
S ✓ ➤	NTZE12AA	CallPilot Speech Activated Messaging Capability - 20 Users	3,000.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ ➤	NTZE12BA	CallPilot Speech Activated Messaging Capability - 50 Users	4,500.00	D	N/A	
S ✓ ➤	NTZE12CA	CallPilot Speech Activated Messaging Capability - 100 Users	7,500.00	D	N/A	
S ✓ ➤	NTZE12DA	CallPilot Speech Activated Messaging Capability - 200 Users	14,000.00	D	N/A	
S ✓ ➤	NTZE12EA	CallPilot Speech Activated Messaging Capability - 500 Users	32,000.00	D	N/A	
S ✓ ➤	NTZE12FA	CallPilot Speech Activated Messaging Capability - 1000 Users	53,000.00	D	N/A	
S ★ Δ	NTZE12HA	CallPilot Speech Activated Messaging Capability - 20 Users	3,000.00	D	N/A	
S ★	NTZE12JA	CallPilot Speech Activated Messaging Capability - 5000 Users	130,000.00	D	N/A	
S ★ Δ	NTZE12KA	CallPilot Speech Activated Messaging Capability - 200 Users	14,000.00	D	N/A	
S ✓ ➤	NTZE13AA	CallPilot Networking, 1 to 24 Channels	3,000.00	D	N/A	
S ✓ ➤	NTZE13BA	CallPilot Networking, 25 to 48 Channels	2,000.00	D	N/A	
S ✓ ➤	NTZE13CA	CallPilot Networking, 49 to 96 Channels	3,000.00	D	N/A	
S ★	NTZE13DA	CallPilot Networking (EN, AMIS, VPIM) 1 to 96 Channels	8,000.00	D	N/A	
S ✓ ➤	NTZE14AA	CallPilot NMS Networking, 1 to 24 Channels	7,000.00	D	N/A	
S ✓ ➤	NTZE14BA	CallPilot NMS Networking, 25 to 48 Channels	4,000.00	D	N/A	
S ✓ ➤	NTZE14CA	CallPilot NMS Networking, 49 to 96 Channels	4,000.00	D	N/A	
S ★ ➤	NTZE14DA	CallPilot NMS Networking, 1 to 96 Channels	5,000.00	D	N/A	
S ➤	NTZE15AA	CallPilot Applications Builder FAX Option	3,000.00	D	N/A	
S ➤	NTZE16AA	CallPilot Additional Prompt Language	600.00	D	N/A	
S ✓ ➤	NTZE16BA	CallPilot Speech Activated Messaging Vocabulary	600.00	D	N/A	
S ★	NTZE19AA	CallPilot Multimedia Mailboxes with Voice - 20 Users	1,000.00	D	N/A	
S ★	NTZE19BA	CallPilot Multimedia Mailboxes with Voice - 50 Users	2,000.00	D	N/A	
S ★	NTZE19CA	CallPilot Multimedia Mailboxes with Voice - 100 Users	3,500.00	D	N/A	
S ★	NTZE19DA	CallPilot Multimedia Mailboxes with Voice - 200 Users	6,000.00	D	N/A	
S ★	NTZE19EA	CallPilot Multimedia Mailboxes with Voice - 500 Users	12,500.00	D	N/A	
S ★	NTZE19FA	CallPilot Multimedia Mailboxes with Voice - 1000 Users	22,000.00	D	N/A	
S ★	NTZE19GA	CallPilot Multimedia Mailboxes with Voice - 5000 Users	100,000.00	D	N/A	
S ★	NTZE19HA	CallPilot Multimedia Mailboxes with Voice - 10,000 Users	165,000.00	D	N/A	
S ➤	NTZE24AA	CallPilot IPE Spares Package	10,000.00	D	N/A	
S ➤	NTZE24BA	CallPilot Tower Spares Package	15,000.00	D	N/A	
S ➤	NTZE24CA	CallPilot Rack Mount AC Spares Package	50,000.00	D	N/A	
S ➤	NTZE24DA	CallPilot Rack Mount DC Spares Package	50,000.00	D	N/A	
S ✓ ➤ Δ	NTZE25AA	CallPilot Conversion 4 Voice Channels to 4 Fax Channels	No charge		N/A	
S ✓ ➤ Δ	NTZE25BA	CallPilot Conversion 4 Voice Channels to 2 Speech Channels	No charge		N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ★	NTZE25CA	CallPilot Conversion 4 Voice Channels to 2 Fax Channels	500.00	D	N/A	
S ★	NTZE25DA	CallPilot Conversion 4 Voice Channels to 1 Speech Channel	500.00	D	N/A	
S ✓ ➤ Δ	NTZE26AA	CallPilot Conversion 4 Fax Channels to 4 Voice Channels	No charge		N/A	
S ✓ ➤ Δ	NTZE26BA	CallPilot Conversion 2 Fax Channels to 1 Speech Channel	500.00	D	N/A	
S ★	NTZE26CA	CallPilot Conversion 2 Fax Channels to 4 Voice Channels	500.00	D	N/A	
S ✓ ➤ Δ	NTZE27AA	CallPilot Conversion 1 Speech Channel to 2 Fax Channels	500.00	D	N/A	
S ✓ ➤ Δ	NTZE27BA	CallPilot Conversion 2 Speech Channels to 4 Voice Channels	No charge		N/A	
S ★	NTZE27CA	CallPilot Conversion 1 Speech Channel to 4 Voice Channels	500.00	D	N/A	
S ✓ ➤ Δ	NTZE29AA	CallPilot to Meridian 1 Integration	500.00	D	N/A	
S ★ ➤ Δ	NTZE29BA	CallPilot to Lucent (2 Wire) Integration	5,000.00	D	N/A	
S ★ ➤ Δ	NTZE29CA	CallPilot to Siemens/Rolm Integration	4,000.00	D	N/A	
S ★ ➤ Δ	NTZE29DA	CallPilot to Mitel Integration	4,000.00	D	N/A	
S ★ ➤ Δ	NTZE29EA	CallPilot to Nortel SL-100 Integration	5,000.00	D	N/A	
S ➤	NTZE30AA	CallPilot Integration Suite	No charge		N/A	
S ★ ➤	NTZE31AA	IPE CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	80.00	D	N/A	
S ★ ➤	NTZE31BA	Tower/Rack CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit	85.00	D	N/A	
S ➤	NTZE39AA	CallPilot 1.07 to Meridian 1 Integration Software	No charge		N/A	
S ★ ➤	NTZE39BA	CallPilot 1.07 to Lucent (2 Wire) Integration Software	No charge		N/A	
S ★ ➤	NTZE39CA	CallPilot 1.07 to Siemens/Rolm Integration Software	No charge		N/A	
S ★ ➤	NTZE39DA	CallPilot 1.07 to Mitel Integration Software	No charge		N/A	
S ★ ➤	NTZE39EA	CallPilot 1.07 to SL-100 Integration Software	No charge		N/A	
S ★ Δ	NTZE4001	CallPilot 1.07 New System Ordering Code	No charge		N/A	
S ★ ➤ Δ	NTZE4002	CallPilot 1.07 Upgrade Ordering Code	No charge		N/A	
S ★ Δ	NTZE4003	CallPilot Platform Migration Order Code	No charge		N/A	
S ★ Δ	NTZE4004	CallPilot Bulk - System Order Code	No charge		N/A	
S ★ ➤	NTZE80AA	CallPilot 1.07 IPE Base Package	9,000.00	D	N/A	
S ★ ➤	NTZE81AA	CallPilot 1.07 702t Base Package	21,000.00	D	N/A	
S ★ ➤	NTZE82AA	CallPilot 1.07 1001rp DC Base Package	51,000.00	D	N/A	
S ★ ➤	NTZE83AA	CallPilot 1.07 1001rp AC Base Package	51,000.00	D	N/A	
S ★ ➤ Δ	NTZE99BA	CallPilot 1.07 GB, DSE Connectivity Option - Lucent 2 Wire	No charge		N/A	
S ★ ➤ Δ	NTZE99CA	CallPilot 1.07 GB, DSE Connectivity Option - Siemens/ROLM	No charge		N/A	
S ★ ➤ Δ	NTZE99DA	CallPilot 1.07 GB, DSE Connectivity Option - Mitel	No charge		N/A	
S ★ ➤ Δ	NTZE99EA	CallPilot 1.07 GB, T1 (SL-100) Connectivity Option - SL-100	No charge		N/A	
B #	NTZK06AA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	MD		55.00	H
B #	NTZK06AA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	MD		55.00	H
B #	NTZK06AA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	MD		55.00	H
B #	NTZK06AB03	Meridian M2006 Single Line Digital Telephone with Data, Black	MD		145.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NTZK06AB35	Meridian M2006 Single Line Digital Telephone with Data, Ash	MD		145.00	H
B #	NTZK06AB93	Meridian M2006 Single Line Digital Telephone with Data, Dolphin Gray	MD		145.00	H
B #	NTZK06AC03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	MD		145.00	H
B #	NTZK06AC35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	MD		145.00	H
B #	NTZK06AC93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	MD		145.00	H
B #	NTZK08AA03	Meridian M2008 Standard Business Telephone, Basic, Black	MD		65.00	H
B #	NTZK08AA35	Meridian M2008 Standard Business Telephone, Basic, Ash	MD		65.00	H
B #	NTZK08AA93	Meridian M2008 Standard Business Telephone, Basic, Gray	MD		65.00	H
B #	NTZK08AB03	Meridian M2008 Standard Business Telephone with Data, Black	MD		150.00	H
B #	NTZK08AB35	Meridian M2008 Standard Business Telephone with Data, Ash	MD		150.00	H
B #	NTZK08AB93	Meridian M2008 Standard Business Telephone with Data, Gray	MD		150.00	H
B #	NTZK08AC03	Meridian M2008 Standard Business Telephone with MCA Data, Black	MD		150.00	H
B #	NTZK08AC35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	MD		150.00	H
B #	NTZK08AC93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	MD		150.00	H
B #	NTZK08BA03	Meridian M2008 Standard Business Telephone with Display, Black	MD		95.00	H
B #	NTZK08BA35	Meridian M2008 Standard Business Telephone with Display, Ash	MD		95.00	H
B #	NTZK08BA93	Meridian M2008 Standard Business Telephone with Display, Gray	MD		95.00	H
B #	NTZK08BB03	Meridian M2008 Standard Business Telephone with Display & Data, Black	MD		200.00	H
B #	NTZK08BB35	Meridian M2008 Standard Business Telephone with Display & Data, Ash	MD		200.00	H
B #	NTZK08BB93	Meridian M2008 Standard Business Telephone with Display & Data, Gray	MD		200.00	H
B #	NTZK08BC03	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Black	MD		200.00	H
B #	NTZK08BC35	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Ash	MD		200.00	H
B #	NTZK08BC93	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Gray	MD		200.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NTZK08CA03	Meridian M2008 Standard Business Telephone with Display, Black	MD		95.00	H
B #	NTZK08CA35	Meridian M2008 Standard Business Telephone with Display, Ash	MD		95.00	H
B #	NTZK08CA93	Meridian M2008 Standard Business Telephone with Display, Gray	MD		95.00	H
B #	NTZK08CC03	Meridian M2008 Standard Business Telephone with Display & MCA Data, Black	MD		200.00	H
B #	NTZK08CC35	Meridian M2008 Standard Business Telephone with Display & MCA Data, Ash	MD		200.00	H
B #	NTZK08CC93	Meridian M2008 Standard Business Telephone with Display & MCA Data, Gray	MD		200.00	H
S † ➤	NTZK14AA	OIVR 2 x Hardware - MRS/Tower or MRS/Rack Disk Drive (1.05GB)	2,100.00	H	N/A	
B #	NTZK16AA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	MD		70.00	H
B #	NTZK16AA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	MD		70.00	H
B #	NTZK16AA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	MD		70.00	H
B #	NTZK16AB03	Meridian M2616 Performance-Plus Telephone with Data, Black	MD		180.00	H
B #	NTZK16AB35	Meridian M2616 Performance-Plus Telephone with Data, Ash	MD		180.00	H
B #	NTZK16AB93	Meridian M2616 Performance-Plus Telephone with Data, Gray	MD		180.00	H
B #	NTZK16AC03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	MD		180.00	H
B #	NTZK16AC35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	MD		180.00	H
B #	NTZK16AC93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	MD		180.00	H
B #	NTZK16BA03	Meridian M2616 Performance-Plus Telephone with Display, Black	MD		100.00	H
B #	NTZK16BA35	Meridian M2616 Performance-Plus Telephone with Display, Ash	MD		100.00	H
B #	NTZK16BA93	Meridian M2616 Performance-Plus Telephone with Display, Gray	MD		100.00	H
B #	NTZK16BB03	Meridian M2616 Performance-Plus Telephone with Display & Data, Black	MD		255.00	H
B #	NTZK16BB35	Meridian M2616 Performance-Plus Telephone with Display & Data, Ash	MD		255.00	H
B #	NTZK16BB93	Meridian M2616 Performance-Plus Telephone with Display & Data, Gray	MD		255.00	H
B #	NTZK16BC03	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Black	MD		255.00	H
B #	NTZK16BC35	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Ash	MD		255.00	H
B #	NTZK16BC93	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Gray	MD		255.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NTZK16CA03	Meridian M2616 Performance-Plus Telephone with Display, Black	MD		100.00	H
B #	NTZK16CA35	Meridian M2616 Performance-Plus Telephone with Display, Ash	MD		100.00	H
B #	NTZK16CA93	Meridian M2616 Performance-Plus Telephone with Display, Gray	MD		100.00	H
B #	NTZK16CC03	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Black	MD		255.00	H
B #	NTZK16CC35	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Ash	MD		255.00	H
B #	NTZK16CC93	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Gray	MD		255.00	H
S #	NTZK20AA03	Meridian M2016S Secure Telephone, Basic, Black	MD		270.00	H
S ➤	NTZK20AA35	Meridian M2016S Secure Telephone, Basic, Ash	830.00	D	270.00	H
S #	NTZK20AA93	Meridian M2016S Secure Telephone, Basic, Gray	MD		270.00	H
S #	NTZK20AB03	Meridian M2016S Secure Telephone with Data, Black	MD		350.00	H
S #	NTZK20AB35	Meridian M2016S Secure Telephone with Data, Ash	MD		350.00	H
S #	NTZK20AB93	Meridian M2016S Secure Telephone with Data, Gray	MD		350.00	H
S #	NTZK20AC03	Meridian M2016S Secure Telephone with MCA Data, Black	MD		350.00	H
S #	NTZK20AC35	Meridian M2016S Secure Telephone with MCA Data, Ash	MD		350.00	H
S #	NTZK20AC93	Meridian M2016S Secure Telephone with MCA Data, Gray	MD		350.00	H
S #	NTZK20BA03	Meridian M2016S Secure Telephone with Display, Black	MD		320.00	H
S #	NTZK20BA35	Meridian M2016S Secure Telephone with Display, Ash	MD		320.00	H
S #	NTZK20BA93	Meridian M2016S Secure Telephone with Display, Gray	MD		320.00	H
S #	NTZK20BB03	Meridian M2016S Secure Telephone with Display & Data, Black	MD		400.00	H
S #	NTZK20BB35	Meridian M2016S Secure Telephone with Display & Data, Ash	MD		400.00	H
S #	NTZK20BB93	Meridian M2016S Secure Telephone with Display & Data, Gray	MD		400.00	H
S #	NTZK20BC03	Meridian M2016S Secure Telephone with Display & MCA Data, Black	MD		400.00	H
S #	NTZK20BC35	Meridian M2016S Secure Telephone with Display & MCA Data, Ash	MD		400.00	H
S #	NTZK20BC93	Meridian M2016S Secure Telephone with Display & MCA Data, Gray	MD		400.00	H
B #	NTZK22AA03	Meridian M2216 ACD-1 Basic Telephone, Black	MD		160.00	H
B #	NTZK22AA35	Meridian M2216 ACD-1 Basic Telephone, Ash	MD		160.00	H
B #	NTZK22AA93	Meridian M2216 ACD-1 Basic Telephone, Gray	MD		160.00	H
B #	NTZK22AB03	Meridian M2216 ACD-1 Telephone with Data, Black	MD		240.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
B #	NTZK22AB35	Meridian M2216 ACD-1 Telephone with Data, Ash	MD		240.00	H
B #	NTZK22AB93	Meridian M2216 ACD-1 Telephone with Data, Gray	MD		240.00	H
B #	NTZK22AC03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	MD		240.00	H
B #	NTZK22AC35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	MD		240.00	H
B #	NTZK22AC93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	MD		240.00	H
S #	NTZK22CA03	Meridian M2216 ACD-1 Basic Telephone, Black	MD		160.00	H
S #	NTZK22CA35	Meridian M2216 ACD-1 Basic Telephone, Ash	MD		160.00	H
S #	NTZK22CA93	Meridian M2216 ACD-1 Basic Telephone, Gray	MD		160.00	H
S #	NTZK22CC03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	MD		240.00	H
S #	NTZK22CC93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	MD		240.00	H
S #	NTZK23AA03	Meridian M2216 ACD-2 Telephone, Basic, Black	MD		210.00	H
S #	NTZK23AA35	Meridian M2216 ACD-2 Telephone, Basic, Ash	MD		210.00	H
S #	NTZK23AA93	Meridian M2216 ACD-2 Telephone, Basic, Gray	MD		210.00	H
S #	NTZK23AB03	Meridian M2216 ACD-2 Telephone with Data, Black	MD		290.00	H
S #	NTZK23AB35	Meridian M2216 ACD-2 Telephone with Data, Ash	MD		290.00	H
S #	NTZK23AB93	Meridian M2216 ACD-2 Telephone with Data, Gray	MD		290.00	H
S #	NTZK23AC03	Meridian M2216 ACD-2 Telephone with MCA Data, Black	MD		290.00	H
S #	NTZK23AC35	Meridian M2216 ACD-2 Telephone with MCA Data, Ash	MD		290.00	H
S #	NTZK23AC93	Meridian M2216 ACD-2 Telephone with MCA Data, Gray	MD		290.00	H
S #	NTZK23CA03	Meridian M2216 ACD-2 Telephone, Basic, Black	MD		210.00	H
S #	NTZK23CA35	Meridian M2216 ACD-2 Telephone, Basic, Ash	MD		210.00	H
S #	NTZK23CA93	Meridian M2216 ACD-2 Telephone, Basic, Gray	MD		210.00	H
S #	NTZK23CC03	Meridian M2216 ACD-2 Telephone with MCA Data, Black	MD		290.00	H
S #	NTZK23CC35	Meridian M2216 ACD-2 Telephone with MCA Data, Ash	MD		290.00	H
S #	NTZK23CC93	Meridian M2216 ACD-2 Telephone with MCA Data, Gray	MD		290.00	H
S ➤	NTZK29AA	SYMPOSIUM FastView New Software, MCA M2216 and Documentation Package 5A (1-19 Units)	1,399.00	D	N/A	
S ➤	NTZK29BA	SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5B (20-49 Units)	1,349.00	D	N/A	
S ➤	NTZK29CA	SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5C (50+ Units)	1,299.00	D	N/A	
S ➤	NTZK37AD	MAT 4 Single Location Distributor Station Administration	3,230.00	H	N/A	
S ➤	NTZK37BD	Mat 4 Multi Location Distribution Station Administration	60,000.00	H	N/A	
S ➤	NTZK38AD	MAT 4 End User Single Site Package	400.00	D	N/A	
S ➤	NTZK38BD	MAT End User Multi Site Package	2,250.00	D	N/A	
S ➤	NTZK39AD	MAT Single to Multi Site Expansion	1,850.00	D	N/A	
S ➤	NTZK39BD	MAT Multi Site Expansion	3,750.00	D	N/A	
S ➤	NTZK39CD	MAT Multi Site Expansion Cap	30,000.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	NTZK40AD	MAT Station Administration Module	650.00	D	N/A	
S ➤	NTZK41AD	MAT Traffic Analysis Module	4,300.00	D	N/A	
S ➤	NTZK42AD	MAT Call Tracking Module	750.00	D	N/A	
S ➤	NTZK43AD	MAT Call Accounting Module Base	1,800.00	D	N/A	
S ➤	NTZK44AD	MAT North American Sample Rate Table	45.00	D	N/A	
S ➤	NTZK45BD	MAT Call Accounting Small Expansion	2,300.00	D	N/A	
S ➤	NTZK45CD	MAT Call Accounting Medium Expansion	4,000.00	D	N/A	
S ➤	NTZK45DD	MAT Call Accounting Large Expansion	9,000.00	D	N/A	
S ➤	NTZK45ED	MAT Call Accounting Expansion Cap	13,000.00	D	N/A	
S ➤	NTZK45FD	MAT Call Accounting Mini Expansion	1,150.00	D	N/A	
S ➤	NTZK46AD	MAT Distributor Single Location Station Administration Upgrade	325.00	H	N/A	
S ➤	NTZK46BD	MAT Distributor Multi-Location Station Administration Upgrade	10,000.00	H	N/A	
S ➤	NTZK47AD	MAT Single Site Common Services Upgrade	100.00	D	N/A	
S ➤	NTZK47BD	MAT Multi Site Common Services Upgrade	560.00	D	N/A	
S ➤	NTZK48AD	MAT Station Administration Upgrade	160.00	D	N/A	
S ➤	NTZK49AD	MAT Traffic Analysis Upgrade	650.00	D	N/A	
S ➤	NTZK50AD	MAT Call Tracking Upgrade	190.00	D	N/A	
S ➤	NTZK51AD	MAT Call Accounting Base Upgrade	450.00	D	N/A	
S ➤	NTZK52BA	MDR 2000 Buffer Box 128Kb (117vac/60Hz)	1,825.00	D	500.00	H
S ➤	NTZK52CA	MDR 2000 Buffer Box 512Kb (117vac/60Hz)	2,555.00	D	650.00	H
S ➤	NTZK52DA	MDR 2000 Buffer Box 2 Mb (117vac/60Hz)	3,285.00	D	830.00	H
S ➤	NTZR07BA	Meridian 1 Attendant PC	4,500.00	D	525.00	H
S ➤	NTZR09BA	Meridian 1 Attendant PC LAN Interface Module	1,720.00	D	N/A	
S	NTZR40BA	DEC Printer	1,000.00	H	N/A	
S ➤	NTZR50AA03	Blank Brandline Insert, Black (Package of 250 P0784403) (M2000 Series)	45.00	D	N/A	
S ➤	NTZR50AA35	Blank Brand Line Insert, Ash, (M2000 Series)	45.00	D	N/A	
S ➤	NTZR50AA93	Blank Brand Line Insert, Gray (Package of 250 P0784493) (M2000 Series)	45.00	D	N/A	
S ✓ ➤	NTZR57CA	Meridian Mail Release 13 Base Software	2,000.00	D	N/A	
S #	NY2K22VH35	Meridian Key Expansion Module, Ash	MD		120.00	H
S #	NY2K22VH93	Meridian Key Expansion Module, Gray	MD		120.00	H
S #	P0562926	Control Card for J2412AA-1, L1, 2, 3 Control Panel	MD		200.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S †	P0593977	Faceplate - ADM Hinged Control Cover - Black	5.00	D	N/A	
S Δ	P0635020	AIM Installation Card (15/PK)	1.00	H	N/A	
S † ➤	P0639984	Adapter Plate for SDI Filter Connector	5.00	I	N/A	
S † ➤	P0641477	Mounting Bracket Lower SDI Connector	10.00	I	N/A	
S † ➤	P0642917	50 Pin Connector Cover Plate	15.00	I	N/A	
S ➤	P0643763	Filter, PRI/DTI I/O	200.00	I	N/A	
S ➤	P0649968	Ribbon Cable, RS232, (Male/Male) 25 Pin, Straight-Through (6 Ft.)	35.00	D	N/A	
N ➤	P0652720	Telephone Number Lens (1 each, Standard for all Meridian Digital Telephones and Attendant Consoles) (M2000 Series)	2.00	D	N/A	
N Δ	P0657569	Meridian Mail Reporter Product Sheet	1.14	H	N/A	
S ➤	P0660405	Field Failure Report Tag (Telephone and Console Equipment)	No charge		N/A	
S Δ	P0661883	Asynchronous Data Option Installation Procedure (15/PK)	1.00	H	N/A	
S Δ	P0667329	Attendant Administration User Guide (15/PK)	14.00	H	N/A	
S Δ	P0673999	Voice Messaging Template (Digital Sets) (100/PK)	42.00	H	N/A	
S #	P0677283	Control Card for J2412AA-1 Control Panel	MD		220.00	H
S † ➤	P0677580	Cabinet Grounding Package #1	No charge		N/A	
S † ➤	P0677587	Cabinet Grounding Package #2	No charge		N/A	
S † ➤	P0677588	Cabinet Grounding Package #3	No charge		N/A	
S Δ	P0677591	Single Line Telephone User Guide (Trifold) (100/PK)	6.00	H	N/A	
S ➤	P0678258	Filter Connector	100.00	I	N/A	
N ✓ ➤	P0680793	Wall Mount Handset Clip (1 each, for all Meridian Digital Telephones)	1.00	D	N/A	
S ✓ ➤	P0684414	Hard Drive Power Cable	17.00	D	N/A	
S Δ	P0687153	RS232 Interface Guide (15/PK)	20.00	H	N/A	
S	P0688609	Literature Pack (M2317)	8.00	D	N/A	
S Δ	P0689755	ACD-D Supervisor User Guide	13.00	H	N/A	
S Δ	P0689757	ACD-D Networking User Guide (15/PK)	96.00	H	N/A	
S Δ	P0690152	ACD Feature Document X11/X37 (15/PK)	38.00	H	N/A	
S Δ	P0690763	M2317 Telephone Quick Reference Card (100/PK)	24.00	H	N/A	
S ➤	P0691037	Ground Lug	20.00	D	N/A	
S ➤	P0694698	Key Cap, Orange with Clear Window (1 each, Standard for all Meridian)	.35	D	N/A	
S ➤	P0695167	CRT Cable	60.00	D	N/A	
S ➤	P0695169	SCSI Daisychain Cable	60.00	D	N/A	
S ➤	P0695822	AML Link Cable	50.00	D	N/A	
S ➤	P0695823	NVP Daisychain Cable	60.00	D	N/A	
S #	P0695826	155MB Hard Disk	MD		2,000.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	P0695827	300MB Hard Disk Assembly	MD		3,500.00	H
S † ➤	P0696547	Connector Housing (Side Panel)	90.00	I	N/A	
S Δ	P0696749	High Speed Data Module User Guide (15/PK)	65.00	H	N/A	
S † ➤	P0697550	Connector Adapter Bracket	45.00	I	N/A	
S † ➤	P0697559	Mounting Bracket	25.00	I	N/A	
S † ➤	P0697707	Connector Cover Panel	140.00	I	N/A	
S ➤	P0699124	Designation Tabs (1 each, M2250/M1250)	30.00	D	N/A	
S Δ	P0699378	Meridian SL-1 NT Installation and Acceptance	50.00	H	N/A	
S Δ	P0699379	Meridian SL-1 NT Maintenance	50.00	H	N/A	
S Δ	P0699380	Meridian SL-1 XT Installation and Acceptance	50.00	H	N/A	
S Δ	P0699381	Meridian SL-1 XT Maintenance	50.00	H	N/A	
S Δ	P0699382	Meridian SL-1 ST Installation and Acceptance	50.00	H	N/A	
S Δ	P0699383	Meridian SL-1 ST Maintenance	50.00	H	N/A	
S Δ	P0699387	Meridian SL-1 General Information and Engineering	50.00	H	N/A	
S ➤	P0699798	Cooling Unit Filter Assembly	75.00	I	N/A	
S ➤	P0699851	Top Cap Cable Egress Panel	60.00	I	N/A	
S ➤	P0700563	Key Cap, Red with Clear Window (1 each, Standard for all Meridian)	.35	D	N/A	
S ➤	P0701352	Earthquake Bracing Rod (3 Module)	50.00	I	N/A	
S ➤	P0701353	Earthquake Bracing Rod (4 Module)	60.00	I	N/A	
S Δ	P0701874	X11 Feature Document (Release 12 Supplement) (5/PK)	No charge		N/A	
S † ➤	P0702380	Connector Housing (Top Panel)	90.00	I	N/A	
N Δ	P0702779	Meridian Mail Voice Menus Applications Guide	40.00	H	N/A	
S Δ	P0702800	M1250/M2250 Attendant Administration User Guide (5/PK)	15.00	H	N/A	
S † ➤	P0703905	Connector Adapter Panel Housing	30.00	I	N/A	
S † ➤	P0703906	Adapter Housing	60.00	I	N/A	
S † ➤	P0703960	DTI/PRA Adapter Plate Package	20.00	I	N/A	
S † ➤	P0703961	SDI Adapter Plate Package	20.00	I	N/A	
S ➤	P0704511	Connector Housing Package	90.00	I	N/A	
B Δ	P0705800	Key Caps, Green	.50	D	N/A	
N ✓ ➤	P0705801	Clear Feature Key Caps (1 each, standard for M2000 Series and Attendant Consoles)	.50	D	N/A	
S Δ	P0707593	Meridian Modular Telephone Template (100/PK)	42.00	H	N/A	
S † Δ	P0707700	Traffic Reporting Documentation (Version 1)	25.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0713674	Meridian Attendant Message Center Slide Presentation	15.00	H	N/A	
B	P0714224	MDF Locking Bar Restraint Bracket	34.00	I	N/A	
S	P0714236	Mounting Bracket	50.00	I	N/A	
S †	P0714688	CPLUS PC Key Cap Labels (each) (for PC keyboard)	70.00	D	N/A	
S Δ	P0714692	DSS-9000 User Manual	8.00	H	N/A	
S Δ	P0714693	DSS-9000 Installation and Maintenance Manual	8.00	H	N/A	
S	P0714694	DSS-9000 Key Number Labels-Enhanced Mode	15.00	D	N/A	
S	P0714695	DSS-9000 Key Number Labels-Standard Mode	15.00	D	N/A	
S	P0715802	Alignment Bracket (Expansion Cabinet)	15.00	I	N/A	
S ➤ Δ	P0722849	Designation Label, EMSI	1.00	D	N/A	
S ➤ Δ	P0722850	Designation Label, EMSI	1.00	D	N/A	
S ➤	P0723443	Power Supply Board Cable (M2000 Series)	5.00	D	N/A	
S ➤	P0723459	Blank Packlet for EOI	80.00	D	N/A	
S Δ	P0723522	X11 Software Guide	40.00	H	N/A	
N Δ	P0724136	Call Center Business Planning Guide and Tools	6.00	H	N/A	
S Δ	P0724945	Customer Controlled Routing Release 3B/Link Release 4B Advanced Maintenance Guide	80.00	H	N/A	
S Δ	P0726664	QCA13 Power System NTP (Set of 2)	16.00	H	N/A	
S ➤	P0727842	EMI Shield (Plastic Type)	110.00	I	N/A	
S ➤	P0727843	EMI Shield (Metal Type)	110.00	I	N/A	
S † Δ	P0728239	CPLUS 2000 User Guide	30.00	H	N/A	
S † Δ	P0728240	CPLUS 2000 Installation Guide	30.00	H	N/A	
S	P0729469	DSS-9000 Key Cap Remover Tool	25.00	D	N/A	
S ➤	P0729843	Spare Circuit Breaker Kit, 5 Amp	45.00	H	N/A	
S ➤	P0729846	Spare Circuit Breaker Kit, 20 Amp	45.00	H	N/A	
S ➤	P0729847	Spare Circuit Breaker Kit, 30 Amp	45.00	H	N/A	
S ➤	P0730064	Lug Kit, Screw-Type #8	14.00	H	N/A	
S Δ	P0730121	MFA150 User Guide/NTP	25.00	H	N/A	
S Δ	P0730129	Supervisor Users Guide	30.00	H	N/A	
S ➤	P0730252	MFA Spare Fuse Kit	50.00	H	N/A	
S Δ	P0731602	Customer Controlled Routing Quick Reference Card	10.00	H	N/A	
S ➤	P0731813	Quick Installation Pre-Printed Keycaps (10 Cards of 10 Pre-Printed Keycaps)	30.00	D	N/A	
S	P0732496	Feature Key Designation Labels with Telephone Number Card (25/PK)	25.00	D	N/A	
S ➤	P0733203	Meridian 1 Logo Insert (Aqua Blue)	5.00	H	N/A	
S Δ	P0734019	Network Administration Center Connectivity NTP	45.00	H	N/A	
S Δ	P0734021	Network Administration Center NTP	55.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0734380	Meridian ACD Package A-C2 and Network ACD	25.00	H	N/A	
S Δ	P0735064	Controlling Access Privileges Workbook	50.00	H	N/A	
S	P0735211	Background Terminal User Guide (15/PK)	42.00	H	N/A	
S Δ	P0735252	NT7D16 Data Access Card NTP	5.00	H	N/A	
S Δ	P0735539	M1250/M2250 Attendant Console Quick Reference Card (25/PK)	5.00	H	N/A	
S Δ	P0736062	BLF/CGM User Guide (5/PK)	10.00	H	N/A	
S Δ	P0738417	ACD Package C Supervisor User Guide	25.00	H	N/A	
S † ➤	P0738600	Display Option Cable	5.00	D	N/A	
S Δ	P0738616	Meridian 1 Call Center Testimonial	1.00	H	N/A	
S ➤	P0738866	Label Kit for Inter-Cabinet Cables	125.00	D	N/A	
S Δ	P0739518	Meridian Mail Options Reference Manual	30.00	H	N/A	
S Δ	P0739519	Meridian Mail Modular Option Reference Manual, Release 8	30.00	H	N/A	
S Δ	P0739520	Meridian Mail GP Reference Manual	30.00	H	N/A	
S Δ	P0739521	Meridian Mail NTP Card Option	30.00	H	N/A	
S Δ	P0739575	Empty Compact NTP Binder	10.00	H	N/A	
N Δ	P0739720	Meridian Communications Adapter Product Brief	.20	H	N/A	
N Δ	P0739721	Meridian M2250 Attendant Console Product Brief	.21	H	N/A	
N Δ	P0739726	NT-1 Network Terminal Adapter Product Brief	.40	H	N/A	
N Δ	P0739727	M2006/M2008/M2008HF & M2616 Digital Telephone Product Brief	.31	H	N/A	
N Δ	P0739833	Meridian Call Center Networking Brochure (NAC/NACD)	.60	H	N/A	
N Δ	P0739834	Meridian Link Brochure	1.19	H	N/A	
N Δ	P0739835	M2216ACD Telephone Product Brief	.20	H	N/A	
N Δ	P0739836	NT/HP Alliance Brochure	.66	H	N/A	
N Δ	P0739838	NT/IBM Alliance Brochure	.66	H	N/A	
N Δ	P0739839	NT/Tandem Alliance Brochure	.66	H	N/A	
N Δ	P0739850	Voice Menus and Voice Forms Brochure	.46	H	N/A	
S Δ	P0740384	Meridian Mail HVS User Guide, European, French	75.00	H	N/A	
S Δ	P0740400	Meridian Mail HVS User Guide, American, Spanish	75.00	H	N/A	
S Δ	P0740420	Meridian SL-1/500 Telephone Extension Designation Cards (1 Box of 1,000 Cards for use with SL-1 QSU Style & Std Analog)	75.00	H	N/A	
S Δ	P0740421	Meridian/Unity III Designation Cards (1 Box of 1,000 Card for use w/ M2000 Digital Tel. & Unity III)	75.00	H	N/A	
S Δ	P0740423	Meridian Mail Modular Option EC Reference Manual	30.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0741295	Meridian Mail Modular GP Reference Manual, Release 8	30.00	H	N/A	
S Δ	P0741297	Meridian Mail System Administration Reference Manual	30.00	H	N/A	
S Δ	P0741298	Meridian Mail Multi-Customer System Administration Reference Manual	30.00	H	N/A	
S Δ	P0741301	Meridian Mail Connections Reference Manual (AT&T), Release 9	10.00	H	N/A	
S Δ	P0741302	Meridian Mail Connections Reference Manual (Rolm), Release 9	10.00	H	N/A	
S Δ	P0741303	Meridian Mail Connections Reference Manual (NEC), Release 9	10.00	H	N/A	
S Δ	P0741304	Meridian ACCESS Developers Reference Manual	30.00	H	N/A	
S Δ	P0741305	Meridian ACCESS Enable Option Reference Manual	20.00	H	N/A	
S Δ	P0741306	Meridian HVS Administration Reference Manual	20.00	H	N/A	
S Δ	P0741307	Meridian HVS GAC Reference Manual	10.00	H	N/A	
S Δ	P0741308	Meridian Voice Forms Reference Manual	20.00	H	N/A	
S Δ	P0741309	Meridian Voice Forms Transcriber User Guide	10.00	H	N/A	
S Δ	P0741310	Meridian Voice Forms Implementation User Guide	10.00	H	N/A	
S Δ	P0741311	Meridian Mail Voice Messaging User Guide (15/PK)	39.00	H	N/A	
S ➤	P0741489	Backplane Cable Extraction Tool	75.00	D	N/A	
S Δ	P0741565	Meridian Mail Quick Reference Cards (Package of 30)	15.00	H	N/A	
N Δ	P0741982	Meridian Mail MSM Brochure	.74	H	N/A	
N Δ	P0741983	Meridian Mail GP Brochure	.74	H	N/A	
S Δ	P0742833	Meridian ACCESS Configuration Guide (NTP 555-7001-3150)	100.00	H	N/A	
S Δ	P0743363	Technical Reference Guide	40.00	H	N/A	
S Δ	P0743364	BRI Administration and Maintenance Guide	40.00	H	N/A	
S Δ	P0743367	Installation Guide	10.00	H	N/A	
S Δ	P0743368	Administration Guide	10.00	H	N/A	
S Δ	P0743369	Fault Clearing Guide	10.00	H	N/A	
S	P0743482	Spare Circuit Breaker Kit, 50 Amp - MPP600/MFA150	45.00	H	N/A	
S Δ	P0743512	50 Amp Rectifier Expansion Assembly Installation NTP	20.00	H	N/A	
S Δ	P0743618	Meridian Mail HVS User Guide, Brazilian, Portuguese	75.00	H	N/A	
S Δ	P0743724	Meridian Communications Unit User Guide and Meridian Communication Adapter Reference Guide	10.00	H	N/A	
N Δ	P0743975	Meridian Mail Features and Functionality Brochure	.55	H	N/A	
S Δ	P0744255	ACD Agent Single Line Telephone Quick Reference Card (25/PK)	20.00	H	N/A	
N Δ	P0744265	Meridian 1 Toll Fraud Brochure	2.00	H	N/A	
N Δ	P0744266	Meridian 1 Digital Telephone Video "Larry Ring Live"	10.00	H	N/A	
N Δ	P0744752	Nortel Promotional Funds Handbook	20.00	H	N/A	
N Δ	P0744840	Business Affiliates Brochure	.20	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	P0744873	System 600/48 Isolation Kit	95.00	H	N/A	
N Δ	P0745631	ISDN Networking Solutions Brochure	.72	H	N/A	
N Δ	P0745632	ISDN Signaling Link Brochure	.43	H	N/A	
N Δ	P0745633	Seamless Transition to ISDN BRI Brochure	.72	H	N/A	
N Δ	P0745635	Advanced Voice and Data Capabilities w/ISDN BRI	.72	H	N/A	
S ➤	P0745713	Growth I/O Panel	35.00	I	N/A	
S ➤	P0745716	Universal I/O Panel	35.00	I	N/A	
B Δ	P0745758	Central Answering Position Guide	10.00	H	N/A	
N Δ	P0745957	Meridian Mail: The Electronic Front Door for Business Video	10.00	H	N/A	
N Δ	P0746049	Making the Most of Voice Mail Brochure	.90	H	N/A	
N Δ	P0746275	Meridian Messaging Healthcare Solutions Brief	1.00	H	N/A	
N Δ	P0746276	Meridian Messaging General Business Solutions Brief	1.00	H	N/A	
N Δ	P0746277	Meridian Messaging Education Solutions Brief	1.00	H	N/A	
N Δ	P0746278	Meridian Messaging Banking Solutions Brief	1.00	H	N/A	
S Δ	P0746527	Meridian Mail Connections Reference Manual AT&T, Release 9	30.00	H	N/A	
S Δ	P0746528	Meridian Mail Connections Reference Manual ROLM, Release 9	30.00	H	N/A	
S Δ	P0746529	Meridian Mail Connections Reference Manual NEC, Release 9	30.00	H	N/A	
S Δ	P0746530	Meridian Mail Release 9 HVS GAC User Guide	30.00	H	N/A	
S Δ	P0746564	Meridian Mail Release 9 Voice Forms Transcriber User Guide	30.00	H	N/A	
S ➤	P0746602	Circuit Breaker Kit, 5 AMP - 600/48	50.00	H	N/A	
S ➤	P0746603	Circuit Breaker Kit, 10 AMP - 600/48	50.00	H	N/A	
S ➤	P0746604	Circuit Breaker Kit, 15 AMP - 600/48	50.00	H	N/A	
S ➤	P0746605	Circuit Breaker Kit, 20 AMP - 600/48	50.00	H	N/A	
S ➤	P0746607	Circuit Breaker Kit, 30 AMP - 600/48	50.00	H	N/A	
S ➤	P0746608	Circuit Breaker Kit, 50 AMP - 600/48	50.00	H	N/A	
N Δ	P0746653	Controlling Access Privileges Workbook	10.00	H	N/A	
N Δ	P0748232	Meridian Message Processing Feature Guide	8.00	H	N/A	
N Δ	P0749025	Customer Profile: The Toronto Star	.37	H	N/A	
S ➤	P0768143	Attendant Administration Overlay	90.00	D	N/A	
S ➤	P0780103	Single Key Expansion Module Footstand, Black (M2000 Series)	10.00	D	N/A	
S ➤	P0780135	Single Key Expansion Module Footstand, Ash, (M2000 Series)	10.00	D	N/A	
S ➤	P0780193	Single Key Expansion Module Footstand, Gray, (M2000 Series)	10.00	D	N/A	
S ➤	P0780203	Double Key Expansion Module Footstand, Black (M2000 Series)	20.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	P0780235	Double Key Expansion Module Footstand, Ash (M2000 Series)	20.00	D	N/A	
S ➤	P0780293	Double Key Expansion Module Footstand, Gray (M2000 Series)	20.00	D	N/A	
S ➤	P0784503	Top Cover Filler Plate, Black (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D	N/A	
S ➤	P0784535	Top Cover Filler Plate, Ash (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D	N/A	
S ➤	P0784593	Top Cover Filler Plate, Gray (1 each for M2006, M2008/ M2008HF, M2216, M2216 ACD and M2016S)	5.00	D	N/A	
S Δ	P0800553	Power Monitor/CE Auxiliary Shelves	12.00	H	N/A	
S Δ	P0800567	M2317 Telephone User Guide (15/PK)	50.00	H	N/A	
S Δ	P0802085	Installation Upgrade for Meridian MAX 3, 4, 4.6 & 5 Systems (to Release 6)	50.00	H	N/A	
S Δ	P0802087	Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 6)	50.00	H	N/A	
S Δ	P0802089	Meridian MAX Release 6 Supervisors User Guide	50.00	H	N/A	
S Δ	P0803126	Release 20 Data Input Forms	10.00	H	N/A	
S Δ	P0803182	Meridian Mail Modular Option EC Installation & Maintenance Quick Reference Guide, Release 9	30.00	H	N/A	
N Δ	P0803269	Meridian Call Center Executive Overhead Presentation	150.00	H	N/A	
S ➤	P0803870	Filler Plate For Fiber Controller	80.00	D	N/A	
N Δ	P0806071	SYMPOSIUM Integrated IVR Tactical Audio Sales Training	29.00	H	N/A	
N Δ	P0807243	Montana State University: SYMPOSIUM Integrated IVR Success Story	1.19	H	N/A	
N Δ	P0807245	1995 TeleProfessional Reprint: Bringing Technologies Together for Maximum Call Center Performance	1.20	H	N/A	
N Δ	P0808873	Call Center Journal: Available in all Sizes	.80	H	N/A	
N Δ	P0808874	Call Center Journal: Making the Perfect Match	.80	H	N/A	
N Δ	P0808875	Call Center Journal: Working With a Net	.80	H	N/A	
N Δ	P0808876	Call Center Journal: Financial Powerhouse	.62	H	N/A	
N Δ	P0808877	Call Center Journal: Healthcare - Just What the Dr. Ordered	.48	H	N/A	
S Δ	P0809892	Meridian COMPANION NTP Documentation	80.00	I	N/A	
S Δ	P0813948	ACD Supervisor Telephone User Guide	30.00	H	N/A	
S Δ	P0813950	Standard Telephone User Guide	50.00	H	N/A	
S Δ	P0813970	XN/XT Network Module Expansion	12.00	H	N/A	
N Δ	P0814188	Protecting Your Voice Mail System Brochure	.84	H	N/A	
S Δ	P0814833	Meridian 1 Quick Tips Guide	49.00	H	N/A	
S ➤ Δ	P0815188	System 600/48 NTP	20.00	H	N/A	
N Δ	P0815254	Meridian 1 Release 21 & New Products Video	20.00	H	N/A	
N Δ	P0815255	Meridian Call Center Capabilities Guide	1.40	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
N Δ	P0815258	Call Center Journal: Air Miles Program Takes Off	.97	H	N/A	
N Δ	P0815259	Call Center Journal: Better By The Minute	1.49	H	N/A	
N Δ	P0815260	Call Center Journal: Move Up To MAX	1.49	H	N/A	
N Δ	P0815261	Call Center Journal: Beyond Expectation	.28	H	N/A	
S Δ	P0815375	MAXcaster User Guide English	18.00	H	N/A	
S Δ	P0815376	MAXcaster User Guide French	18.00	H	N/A	
S Δ	P0815404	Line-Side T1 Interface Card Description, Installation and Maintenance	12.00	H	N/A	
S ➤ Δ	P0815593	Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX Releases 3 through 6 Systems	50.00	H	N/A	
S Δ	P0815602	MTE Release 6 User Guide	10.00	H	N/A	
S ➤	P0816367	System 600/48 DC Duct	300.00	H	N/A	
S Δ	P0816832	Fiber Routing Guide	20.00	H	N/A	
N Δ	P0817917	Meridian 1 ACD Feature Document - Release 21	9.25	H	N/A	
N Δ	P0817918	Call Center Video "Customer Service Takes Flight"	10.00	H	N/A	
N Δ	P0817919	Canadian Tire Video	4.00	H	N/A	
N Δ	P0817920	Call Center Journal: MAXcaster Forecasting	1.58	H	N/A	
N Δ	P0819089	Columbia National Incorporated: SYMPOSIUM Integrated IVR Success Story	1.18	H	N/A	
S Δ	P0819765	Network Hybrid Installation Procedure	12.00	H	N/A	
N Δ	P0819906	Call Center Journal: The CTI Call Center	.78	H	N/A	
N Δ	P0819975	Meridian MultiMedia Messaging Overview Video	2.50	H	N/A	
N Δ	P0820954	Call Center Journal: Priority Special Report	1.14	H	N/A	
S Δ	P0821303	MTE Release 7 User Guide (multilingual: English, French, Spanish, German)	20.00	H	N/A	
N Δ	P0821361	Messenger 2.0 Interactive CD-ROM	4.69	H	N/A	
N Δ	P0821363	Messenger 2.0 Interactive Demo Disks (Macintosh)	4.50	H	N/A	
S	P0828635	Meridian 1 Attendant PC Blank Brandline Insert (Package of 1)	1.50	D	N/A	
S Δ	P0832159	Meridian Networking Feature Document	15.00	H	N/A	
S Δ	P0833777	NT5D12 Dual-port DTI/PRI Card Product Description and Installation	10.00	H	N/A	
S Δ	P0833798	MAT 4 x Station Administration User Guide	10.00	H	N/A	
S Δ	P0833799	MAT 4 x Traffic Analysis User Guide	10.00	H	N/A	
S Δ	P0833800	MAT 4 x Call Tracking User Guide	10.00	H	N/A	
S Δ	P0833801	MAT 4 x Call Accounting User Guide	10.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0833802	MAT 4 x Buffer Box Reference Guide	15.00	H	N/A	
S Δ	P0834426	Attendant Console User Guide (1/PK)	7.00	H	N/A	
S Δ	P0835201	FastView User Guide	25.00	H	N/A	
B Δ	P0835240	Central Answering Position (Caps)	10.00	H	N/A	
B Δ	P0835273	Customer Configuration Backup and Restore (Coil)	10.00	H	N/A	
B Δ	P0835516	X11 Software Input/Output Guide (Coil)	40.00	H	N/A	
B Δ	P0837621	Option 11E - 1.5MB DTI/PRI Administration and Maintenance (Binder)	10.00	H	N/A	
B Δ	P0837640	Option 11E - BRI Administration and Maintenance (Binder)	40.00	H	N/A	
B Δ	P0837647	Option 11E - Technical Reference Guide (Binder)	40.00	H	N/A	
S Δ	P0839909	Meridian Mail 11 HVS Implementation Guide	20.00	H	N/A	
S Δ	P0839910	Meridian Mail 11 HVS GAC Guide / Guest Voice Messaging Reference Guide	10.00	H	N/A	
S Δ	P0839915	Meridian Mail 11 System Installation and Modification Guide	10.00	H	N/A	
S Δ	P0839920	Meridian Mail 11 Network Planning Guide	10.00	H	N/A	
S Δ	P0839921	Meridian Mail 11 AMIS Networking Installation and Administration Guide	10.00	H	N/A	
S Δ	P0839922	Meridian Mail 11 Network Message Services Installation and Administration Guide	10.00	H	N/A	
S Δ	P0839923	Meridian Mail 11 Networking, Installation and Administration Guide	20.00	H	N/A	
S Δ	P0839924	Meridian Mail 11 Virtual Node AMIS Networking Installation and Administration Guide	20.00	D	N/A	
S Δ	P0839925	Meridian Mail 11 Enterprise Networking, Installation and Administration Guide	10.00	H	N/A	
S Δ	P0839926	Meridian Mail 11 Voice Services Application Guide	20.00	H	N/A	
S Δ	P0839934	Meridian Mail 11 Fax on Demand Application Guide	10.00	H	N/A	
S ➤ Δ	P0839941	Meridian Mail 11 Maintenance Messages (SEERS)	25.00	H	N/A	
S Δ	P0839943	Meridian Mail 11 Voice Messaging Quick Reference Card 30/ Pkg	20.00	H	N/A	
S Δ	P0839945	Meridian Mail 11 "Updating Voice Menu Prompts" Cards (15/ PK)	5.00	H	N/A	
N Δ	P0839989	Nortel Networks SYMPOSIUM IVR Brochure	2.05	H	N/A	
N Δ	P0839990	SYMPOSIUM Integrated IVR Data	.28	H	N/A	
N Δ	P0839991	SYMPOSIUM Open IVR Data Sheet	.28	H	N/A	
S Δ	P0839993	MAXcaster Quick Reference Guide English	10.00	H	N/A	
N Δ	P0843029	Meridian MAXcaster Flyer	1.04	H	N/A	
N Δ	P0843060	Messenger 2.0 Product Sheet	No charge		N/A	
S ➤	P0843070	MIVR Software Reproduction	210.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0843834	MAT 5 x Station Administration User Guide	10.00	H	N/A	
S Δ	P0843837	MAT 5 x Call Tracking User Guide	10.00	H	N/A	
S Δ	P0843840	MAT 5 x Alarm Management User Guide	10.00	H	N/A	
N Δ	P0843987	Meridian MultiMedia Messaging Sales Guide (Shrinkwrapped)	21.51	H	N/A	
N Δ	P0844036	SYMPOSIUM OPEN IVR Demo Disk and Audio Course	9.50	H	N/A	
S Δ	P0844341	MAXcaster Quick Reference Guide French	10.00	H	N/A	
N Δ	P0844587	Quick Reference Guide - Black Binder	27.00	H	N/A	
N Δ	P0844588	Update to Black Quick Reference Guide Binder	9.50	H	N/A	
N Δ	P0844589	White Telecom Professional QRG Binder	15.50	H	N/A	
N Δ	P0845109	SYMPOSIUM Open IVR Demonstration Disks	6.50	H	N/A	
S ➤ Δ	P0847870	Meridian Mail Reporter 2.0 User Guide	15.00	H	N/A	
S Δ	P0849802	Data Input Forms (Release 22)	10.00	H	N/A	
S ➤ Δ	P0850716	Option 11C Programming Fee for PCMCIA Card	500.00	H	N/A	
S ➤ Δ	P0853412	Meridian MAX 8 Installation Upgrade Guide (English)	50.00	D	N/A	
N Δ	P0853936	Meridian 1 New Core Products Video	6.50	H	N/A	
N Δ	P0853937	Nortel's SYMPOSIUM IVR Customer Testimonial Video	5.00	H	N/A	
N Δ	P0853938	Meridian Administration Tools (MAT) Brochure	4.25	H	N/A	
S Δ	P0854560	Customer Controlled Routing Release 3B/Link Release 5B Engineering Guide	70.00	H	N/A	
N Δ	P0857665	Meridian 1 Option 11C "High Performance in a Small Package" Brochure	1.90	H	N/A	
N Δ	P0857666	Meridian 1 Option 11C: Building a High-Performance Network Brochure	1.90	H	N/A	
N Δ	P0857667	Meridian 1 Evergreen By Design Brochure	2.22	H	N/A	
N Δ	P0859913	SYMPOSIUM FastView/FastView+ Information Sheet	.83	H	N/A	
N Δ	P0865353	"IVR delivers to FedEx" Article	.44	H	N/A	
S † Δ	P0865356	CPLUS Release 3 User Guide	32.00	H	N/A	
S † Δ	P0865358	CPLUS Release 3 Installation Guide	32.00	H	N/A	
S † Δ	P0865359	CPLUS Performer User Guide	32.00	H	N/A	
S † Δ	P0865360	CPLUS Performer Installation Guide	32.00	H	N/A	
S † Δ	P0865361	CPLUS LAN Key Installation Guide	32.00	H	N/A	
S Δ	P0865362	Meridian 1 Attendant PC Unit Installation Guide	8.00	H	N/A	
S Δ	P0867594	MAT 5 x Traffic Analysis User Guide	10.00	H	N/A	
S Δ	P0867596	MAT 5 x ESN Analysis and Reporting Tool User Guide	10.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0868056	Meridian 1 Attendant PC Unit Quick Reference Guide	8.00	H	N/A	
S Δ	P0868359	MAT 5 x Common Services User Guide	15.00	H	N/A	
S Δ	P0868440	MAT 5 x Maintenance Windows User Guide	10.00	H	N/A	
N Δ	P0869771	Meridian Integrated Recorded Announcer (MIRAN) Brochure	.50	H	N/A	
N Δ	P0869772	Meridian Integrated Conference Bridge (MICB) Brochure	.50	H	N/A	
S ➤ Δ	P0870433	MTE Release 8 User Guide (multilingual: English, French, Spanish, German)	20.00	H	N/A	
S ➤	P0870718	Blank Insert (Light Gray)	5.00	H	N/A	
S Δ	P0871231	MAS Installation and Maintenance Guide	40.00	H	N/A	
S Δ	P0871739	MAT 5 x Call Accounting User Guide	10.00	H	N/A	
N Δ	P0871843	SYMPOSIUM Portfolio Package	10.00	H	N/A	
N Δ	P0871844	Symposium Call Center Server Feature Document	4.00	H	N/A	
S ➤ Δ	P0872785	Option 11C Compact Set Based Administration	20.00	H	N/A	
S § ➤ Δ	P0872788	Mini IPE 1.5 MB DTI/PRI Guide	40.00	H	N/A	
N Δ	P0873149	Meridian Mail Upgrades Brochure	3.32	H	N/A	
S ➤ Δ	P0873717	Meridian Mail Compact Option System Administration Guide	40.00	H	N/A	
S § ➤ Δ	P0873719	Meridian Mail Compact Option Enterprise Networking Installation and Administration Guide Release 11	10.00	H	N/A	
S Δ	P0874391	Meridian 1 Attendant PC LAN Interface Installation Guide	8.00	H	N/A	
S Δ	P0875113	Data Input Forms (Release 23)	10.00	H	N/A	
N Δ	P0875712	SYMPOSIUM Remote Agent Sheet	.60	H	N/A	
S Δ	P0875888	Meridian Mail Release 12 System Installation and Modification Guide	10.00	H	N/A	
S Δ	P0875895	Meridian Mail Release 12 Card Option Installation and Maintenance Guide	10.00	H	N/A	
S Δ	P0875898	Meridian Mail Release 12 Outcalling Application Guide	15.00	H	N/A	
S Δ	P0875899	Meridian Mail Release 12 HVS Implementation Guide	20.00	H	N/A	
S Δ	P0875900	Meridian Mail Release 12 HVS/Guest Voice Messaging Reference Guide	10.00	H	N/A	
S Δ	P0875903	Meridian Mail Release 12 Voice Services Application Guide	20.00	H	N/A	
S Δ	P0875904	Meridian Mail Release 12 Fax On Demand Application Guide	10.00	H	N/A	
S Δ	P0875905	Meridian Mail Release 12 Maintenance Messages (SEERs)	25.00	H	N/A	
S Δ	P0875906	Meridian Mail Release 12 Networking Planning Guide	10.00	H	N/A	
S Δ	P0875908	Meridian Mail Release 12 AMIS Networking Installation and Administration Guide	10.00	H	N/A	
S Δ	P0875910	Meridian Mail Release 12 Network Message Services Installation and Administration Guide	10.00	H	N/A	
S Δ	P0875911	Meridian Mail Release 12 Networking Installation and Administration Guide	20.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0875912	Meridian Mail AMIS Virtual Node Networking Installation and Administration Guide	20.00	H	N/A	
S ✓ Δ	P0875913	Meridian Mail Enterprise Networking Installation and Administration Guide Release 12	10.00	H	N/A	
S ✓ Δ	P0875922	Meridian Mail Release 12 System Administration Tools Guide	20.00	H	N/A	
S Δ	P0875936	Meridian Mail Release 12 Voice Messaging Quick Reference Card	20.00	H	N/A	
S Δ	P0875941	Meridian Mail Release 12 Voice Messaging "Updating Voice Menu Prompts" Card	5.00	H	N/A	
S ➤ Δ	P0876242	SYMPOSIUM Call Center Server Release 1, End to End Task Flow	80.00	H	N/A	
S ➤ Δ	P0876261	SYMPOSIUM Call Center Server Release 1, 701t Maintenance and Diagnostics Guide	50.00	H	N/A	
S ➤ Δ	P0876262	SYMPOSIUM Call Center Server Release 1, 701t Hardware Installation Guide	50.00	H	N/A	
S ➤	P0876389	MAT 6 End User Five (5) Additional Meridian 1 System Licenses	2,475.00	D	N/A	
S ➤	P0876390	MAT 6 Call Accounting Mini Expansion License	1,150.00	D	N/A	
S ➤	P0876391	MAT 6 Call Accounting Small Expansion License	2,300.00	D	N/A	
S ➤	P0876392	MAT 6 Call Accounting Medium Expansion License	4,000.00	D	N/A	
S ➤	P0876393	MAT 6 Call Accounting Large Expansion License	9,000.00	D	N/A	
S ➤	P0876394	MAT 6 Call Accounting Expansion Cap License	13,000.00	D	N/A	
S ➤	P0876395	MAT 6 End User Site Expansion Upgrade	150.00	D	N/A	
S ➤ Δ	P0876396	MAT 6 Call Accounting Mini Expansion License Upgrade	No charge		N/A	
S ➤ Δ	P0876397	MAT 6 Call Accounting Small Expansion License Upgrade	No charge		N/A	
S ➤ Δ	P0876398	MAT 6 Call Accounting Medium Expansion License Upgrade	No charge		N/A	
S ➤ Δ	P0876399	MAT 6 Call Accounting Large Expansion License Upgrade	No charge		N/A	
S ➤ Δ	P0876400	MAT 6 Call Accounting Expansion Cap License Upgrade	No charge		N/A	
N Δ	P0877708	SYMPOSIUM IVR CD-ROM Interactive Product Demo	1.72	H	N/A	
N Δ	P0878306	Meridian 1 New Core Products: Racing to Win Video	7.35	H	N/A	
S	P0878469	Mini Carrier Remote NTP	20.00	H	N/A	
N Δ	P0878476	Meridian 1 Option 11C Compact Business Case	1.13	H	N/A	
N Δ	P0878478	Meridian 1 Attendant PC Brochure	.30	H	N/A	
S Δ	P0879480	SYMPOSIUM Call Center Server 1001t Hardware Installation Guide	50.00	H	N/A	
S Δ	P0879481	SYMPOSIUM Call Center Server 1001t Maintenance and Diagnostics Guide	50.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
N Δ	P0879824	Meridian 1 Option 11C Compact Video	4.30	H	N/A	
N Δ	P0879825	Meridian 1 Option 11C Compact CD-ROM Demo	2.50	H	N/A	
S Δ	P0881354	Messenger 4.0 Administration Guide	25.00	H	N/A	
S ➤ Δ	P0881397	Meridian MAX Release 9 Upgrade Guide (to Release 9)	50.00	H	N/A	
S ➤ Δ	P0881398	Meridian Terminal Emulator (MTE) Release 9 User Guide	20.00	H	N/A	
S Δ	P0884613	Alternate User Interface Installation/Administration Guide	20.00	H	N/A	
S Δ	P0884766	Option 11C Compact NMS Mail Reference Guide	16.00	H	N/A	
S ➤ Δ	P0884895	CallPilot 200 Series Installation Guide	30.00	H	N/A	
S ➤ Δ	P0884909	702t Installation and Maintenance Guide	50.00	H	N/A	
S ➤ Δ	P0885044	Journal Rate Table (Update)	215.00	H	N/A	
S ➤ Δ	P0885111	Meridian MAX Release 9 Reproduction/Keycode	500.00	H	N/A	
S Δ	P0885159	MTTS 1.0 User Guide	10.00	H	N/A	
S Δ	P0885160	MTTS 1.0 Administration Guide	20.00	H	N/A	
S Δ	P0885161	MTTS 1.0 Installation Guide	20.00	H	N/A	
S Δ	P0885216	Option 11C Compact Technical Reference Guide	30.00	H	N/A	
S Δ	P0885219	Journal Administration and User Guide	32.00	H	N/A	
S Δ	P0885220	Registrar User Guide	20.00	H	N/A	
S ➤ Δ	P0885221	Compact Hospitality Meridian Mail Guest Cards (15)	15.00	H	N/A	
S Δ	P0885695	MICA NTP	15.00	H	N/A	
S Δ	P0885702	Meridian Integrated RAN (Release 2) NTP Guide	20.00	H	N/A	
S ➤ Δ	P0886124	CallPilot Planning and Engineering Guide	20.00	H	N/A	
S ➤ Δ	P0886126	CallPilot Basic Administration Guide	10.00	H	N/A	
S Δ	P0886127	CallPilot Speech Recognition Users Guide	8.00	H	N/A	
S Δ	P0886128	CallPilot Telset Quick Reference Guide	8.00	H	N/A	
S Δ	P0886130	CallPilot Advanced Administration Guide - Volume 1	40.00	H	N/A	
S Δ	P0886132	CallPilot Advanced Administration Guide - Volume 2	35.00	H	N/A	
S Δ	P0886133	CallPilot Reporter Guide	35.00	H	N/A	
S Δ	P0886135	CallPilot Applications Builder Guide	35.00	H	N/A	
S Δ	P0886138	Meridian Mail to Nortel CallPilot Migration Guide	10.00	H	N/A	
S Δ	P0886141	CallPilot Desktop Messaging - MS Exchange Guide	30.00	H	N/A	
S Δ	P0886142	CallPilot Desktop Messaging - Lotus Notes Guide	30.00	H	N/A	
S Δ	P0886143	CallPilot Internet Messaging Guide	30.00	H	N/A	
S ✓ Δ	P0886144	CallPilot Network Planning Guide	20.00	H	N/A	
S ✓ Δ	P0886145	CallPilot NMS Installation and Administration Guide	20.00	H	N/A	
S ✓ Δ	P0886146	CallPilot AMIS Installation and Administration Guide	20.00	H	N/A	
S ✓ Δ	P0886147	CallPilot Enterprise Networking Installation and Administration Guide	20.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ✓ Δ	P0886148	CallPilot Integrated AMIS Installation and Administration Guide	20.00	H	N/A	
S ✓ Δ	P0886149	CallPilot VPIM Networking Package	20.00	H	N/A	
S ➤ Δ	P0886656	NAC 2.5 User Guide Supplement	50.00	H	N/A	
S ➤ Δ	P0886776	CallPilot 1001rp Installation Guide	30.00	H	N/A	
S Δ	P0887335	SYMPOSIUM Express Call Center Planning, Installation and Administration Guide, English	50.00	H	N/A	
N Δ	P0887541	Nortel Meridian: Transition to the Year 2000 Video	3.70	H	N/A	
S Δ	P0889187	Library Navigator, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889188	System Planning and Engineering Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889189	System Installation and Maintenance Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889190	System and Software Upgrade Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889191	X11 Software Features Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889192	X11 System Management, Overview, Applications and Security Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889193	X11 Input/Output Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889194	X11 Data Features, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889195	X11 Hospitality Features, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889196	X11 Networking Features, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889197	ISDN Basic Rate Interface, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889198	ACD Reference Guide, Release 24 and Earlier	50.00	H	N/A	
S Δ	P0889200	System Installation and Maintenance, Release 24 and Earlier	25.00	H	N/A	
S Δ	P0889201	Switch Settings, Card and Product Compatibility, Release 24 and Earlier	25.00	H	N/A	
S Δ	P0889202	Software Conversion Procedures, Release 24 and Earlier	12.00	H	N/A	
S Δ	P0889203	X11 Feature Document, Release 24 and Earlier	12.00	H	N/A	
S Δ	P0889204	X11 Maintenance Programs, Release 24 and Earlier	25.00	H	N/A	
S Δ	P0889235	X11 Administration Programs, Release 24 and Earlier	25.00	H	N/A	
S Δ	P0889236	X11 System Messages, Release 24 and Earlier	25.00	H	N/A	
N Δ	P0889249	Meridian 1 Option 11C Compact Hospitality Package Brochure	1.50	H	N/A	
S ➤ Δ	P0889406	Meridian NAC Software Service Transaction Fee (AM)	500.00	H	N/A	
S Δ	P0889431	System Management Overview, Applications and Security Spirals, Release 24 and Earlier	25.00	H	N/A	
S	P0889883	Meridian 1 Attendant PC/Hospitality Software Quick Start Guide	10.00	H	N/A	
S	P0889884	Meridian 1 Attendant PC/Hospitality User Guide	20.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S	P0889885	Meridian 1 Attendant PC/Hospitality Installation Quick Start Guide	10.00	H	N/A	
N Δ	P0889981	Sales Trifold-ENFS SCCS Server Hardware & Software Installation	46.00	H	N/A	
N Δ	P0889982	Sales Trifold-ENFS SCCS Server Maintenance	46.00	H	N/A	
N Δ	P0889983	Sales Trifold-ENFS SCCS Site Readiness Evaluation	46.00	H	N/A	
N Δ	P0889984	Sales Trifold-ENFS SCCS Service Overview	46.00	H	N/A	
N Δ	P0889985	Sales Trifold-SPS SCCS Callflow Design/Database Preparation	46.00	H	N/A	
N ➤ Δ	P0889986	Sales Trifold-SPS SCCS Call Center Business Assessment	1.84	H	N/A	
N ➤ Δ	P0889987	Sales Trifold-SPS CTI Assessment and Design	1.84	H	N/A	
N ➤ Δ	P0889988	Sales Trifold-SPS SCCS HDX Design & Implementation	1.84	H	N/A	
N ➤ Δ	P0889989	Sales Trifold-SPS SCCS Migration Analysis	1.84	H	N/A	
N ➤ Δ	P0889990	Sales Trifold-SPS SCCS Post Production Review	1.84	H	N/A	
N ➤ Δ	P0889991	Sales Trifold-SPS SCCS Project Management	1.84	H	N/A	
N ➤ Δ	P0889992	Sales Trifold-SPS SCCS Remote Database Entry	1.84	H	N/A	
N ➤ Δ	P0889993	Sales Trifold-SPS SCCS Script Design & Implementation	1.84	H	N/A	
N ➤ Δ	P0889994	Sales Trifold-SPS SCCS Supervisor Workshop	1.84	H	N/A	
S Δ	P0889995	Meridian Integrated Conference Bridge (Release 2) NTP Guide	20.00	H	N/A	
S Δ	P0889996	Meridian Integrated Conference Bridge (Release 2) User Guide	15.00	H	N/A	
S Δ	P0890121	Option 11C Compact Software Input-Output Guide	60.00	H	N/A	
S Δ	P0890122	Option 11C Compact Features and Services Guide	40.00	H	N/A	
S Δ	P0890123	Option 11C Compact Planning and Installation Guide	30.00	H	N/A	
S Δ	P0890124	MAT 6 Option 11C Compact Introduction Guide	15.00	H	N/A	
S Δ	P0890125	Multi-Line CAP User Guide	15.00	H	N/A	
S Δ	P0890732	Remote Peripheral Equipment Guide, Release 24 and Earlier	50.00	H	N/A	
N Δ	P0891204	Meridian Integrated IP Telephony Gateway Flyer	.90	H	N/A	
N Δ	P0891205	Meridian Administration Tools (MAT 6) Demo CD	2.50	H	N/A	
N Δ	P0891206	Meridian 1 Remote Services Portfolio Brochure	1.90	H	N/A	
N Δ	P0891207	Meridian 1 System Specifications Brochure	2.58	H	N/A	
N ✓ Δ	P0891208	Gray Market Pamphlet for End Users	.95	H	N/A	
N ✓ Δ	P0891209	Gray Market Pamphlet for Distributors	.95	H	N/A	
S Δ	P0891256	Meridian 1 Attendant PC Software User Guide	15.00	H	N/A	
S Δ	P0891257	Meridian 1 Attendant PC Software Installation Guide	8.00	H	N/A	
S Δ	P0891258	Meridian 1 Attendant PC Software Quick Start Guide	8.00	H	N/A	
S ➤ Δ	P0903073	CallPilot Software Installation Guide	10.00	H	N/A	
S ➤ Δ	P0903074	CallPilot Maintenance and Diagnostic Guide	20.00	H	N/A	
S ➤	P0903075	CallPilot 200 Series Installation Guide	35.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
N Δ	P0903934	Meridian 1 Option 11C Compact Brochure	1.20	H	N/A	
S	P0904477	Dark Gray UEM Overlay Kit	75.00	D	N/A	
S	P0904478	Light Gray UEM Overlay Kit	75.00	D	N/A	
S Δ	P0904485	Modular Option Installation and Maintenance Guide - MM13	20.00	H	N/A	
S Δ	P0904486	Modular Option GP Site and Installation and Planning Guide - MM13	15.00	H	N/A	
S Δ	P0904487	Modular Option GP Installation and Maintenance Guide - MM13	12.00	H	N/A	
S Δ	P0904492	Meridian Mail Release 13 Card Option Installation and Maintenance Guide	21.00	H	N/A	
S Δ	P0904493	Maintenance Messages (SEERs) - MM13	39.00	H	N/A	
S Δ	P0904494	ACCESS Configuration Guide - MM13	32.00	H	N/A	
S Δ	P0904567	What's New In Meridian Mail Release 13	8.00	H	N/A	
S Δ	P0904927	Meridian Mail HVS GAC/Guest Voice Messaging Reference Guide - MM13	10.00	H	N/A	
S Δ	P0905051	Meridian IP Telephony Gateway (ITG) NTPs	15.00	H	N/A	
S Δ	P0905519	Desktop Messaging for Lotus Notes - Latin American Spanish	110.00	H	N/A	
S Δ	P0905560	Desktop Messaging for Microsoft Exchange/Outlook - Latin American Spanish	110.00	H	N/A	
S Δ	P0905610	Multimedia Messaging User Guide - Latin American Spanish	30.00	H	N/A	
S Δ	P0905622	Multimedia Messaging Quick Reference Card - Latin American Spanish	30.00	H	N/A	
S ★ ➤ Δ	P0905783	CallPilot 1.07 Installation and configuration Switch Set Up	10.00	H	N/A	
S ★ Δ	P0905786	CallPilot 1.07 200i Installation and Configuration Server Hardware Guide	30.00	H	N/A	
S ★ Δ	P0905787	CallPilot 702t Installation and Configuration Server Hardware - Part 2	30.00	H	N/A	
S ➤ Δ	P0905788	CallPilot 1001rp Installation and Configuration Server Hardware	30.00	H	N/A	
S ★ ➤ Δ	P0905789	CallPilot 1.07 Planning and Engineering Guide	15.00	H	N/A	
S ★ ➤ Δ	P0905790	CallPilot 1.07 Getting Started Guide	10.00	H	N/A	
S ★ ➤ Δ	P0905791	CallPilot 1.07 Monitoring and Security for Administrators	22.00	H	N/A	
S ★ ➤ Δ	P0905796	CallPilot 1.07 Administrators Guide	60.00	H	N/A	
S ★ ➤ Δ	P0905797	CallPilot 1.07 Client Software Installation	35.00	H	N/A	
S ★ Δ	P0905798	CallPilot 1.07 Reporter Guide	15.00	H	N/A	
S ★ ➤ Δ	P0905799	CallPilot 1.07 Applications Builder Guide	50.00	H	N/A	
S ★ Δ	P0905800	CallPilot 1.07 Meridian Mail to CallPilot Migration Guide	15.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ★ Δ	P0905810	CallPilot 1.07 Desktop Messaging Software Installation and Maintenance Guide	15.00	H	N/A	
S Δ	P0905816	Desktop Messaging Guide for MS Exchange - French	15.00	H	N/A	
S Δ	P0905817	Desktop Messaging Guide for Lotus Notes - French	15.00	H	N/A	
N Δ	P0906299	Customer Satisfaction Guarantee Program Presentation Folder	1.00	H	N/A	
N Δ	P0906300	Customer Satisfaction Guarantee Program Meridian 1 Insert	.50	H	N/A	
N Δ	P0906301	Customer Satisfaction Guarantee Program Norstar Insert	.50	H	N/A	
N Δ	P0906303	Customer Satisfaction Guarantee Program Applications Insert	.50	H	N/A	
N Δ	P0906304	Customer Satisfaction Guarantee Program Registration Card Insert	.25	H	N/A	
S ➤	P0906308	cPCI Card Slot Filler Panel	35.00	D	N/A	
S ➤ Δ	P0906569	Meridian ITG 2.0 NTP	20.00	D	N/A	
S § Δ	P0906932	Meridian Mail Release 13 Keycode	No charge		N/A	
S Δ	P0907072	PC Application Guide - MM13	11.00	H	N/A	
S Δ	P0907146	Meridian Mail Release 13 Feature Operations Video	65.00	H	N/A	
S	P0907149	Data Input Forms (Release 25)	10.00	H	N/A	
B Δ	P0907449	Customer Configuration Backup and Restore (Coil)	10.00	H	N/A	
B Δ	P0907452	Option 11C Release 25 Technical Reference Guide - English	10.00	H	N/A	
B Δ	P0907453	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	35.00	H	N/A	
S Δ	P0907454	2.0 MB DTI/PRI Administration/Maintenance Guide	26.00	H	N/A	
S Δ	P0907455	Option 11C BRI Guide (Release 18 to 24) - English	40.00	H	N/A	
S Δ	P0907622	SYMPOSIUM Express Call Center Management Guide	50.00	H	N/A	
S Δ	P0907624	SYMPOSIUM Express Call Center Server Reports and Displays Guide	50.00	H	N/A	
S Δ	P0907827	CallPilot What’s New for Release 1.06	10.00	H	N/A	
S Δ	P0907828	CallPilot Desktop Messaging for Exchange/Outlook 1.06	20.00	H	N/A	
S Δ	P0907829	CallPilot Desktop Messaging for Lotus Notes - 1.06	20.00	H	N/A	
S Δ	P0907831	CallPilot Desktop Messaging for Internet Mail Clients - 1.06	20.00	H	N/A	
S Δ	P0907840	CallPilot 1001rp Installation and Maintenance Guide - 1.06	30.00	H	N/A	
S Δ	P0908782	SYMPOSIUM Express Call Center Task Flow Guide	50.00	H	N/A	
S Δ	P0909234	Large Keypad Template	4.00	H	N/A	
S Δ	P0909235	Small Keypad Template	4.00	H	N/A	
N Δ	P0909314	M3900 Series Accessories Product Brief	.17	H	N/A	
N Δ	P0909315	M3905 Call Center Meridian Digital Telephone Product Brief	.35	H	N/A	
N Δ	P0909316	M3904 Professional Meridian Digital Telephone Product Brief	.35	H	N/A	
N Δ	P0909317	M3901, M3902, M3903 Meridian Digital Telephones Product Brief	.35	H	N/A	
N Δ	P0909318	M3900 Series Meridian Digital Telephones Brochure	1.52	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
N Δ	P0909319	Meridian Liberation Headsets Product Brief	.80	H	N/A	
S	P0909573	Meridian Integrated Voice Services (MIVS) NTP	20.00	H	N/A	
S ➤ Δ	P0909663	Symposium Express Call Center Addendum to Planning, Installation, and Administration Guide	50.00	H	N/A	
S Δ	P0909939	CallPilot Advanced Administration Guide, Volume 1 - French	35.00	H	N/A	
S Δ	P0909940	CallPilot Advanced Administration Guide, Volume 2 - French	35.00	H	N/A	
S Δ	P0909941	CallPilot Applications Builder Guide	40.00	H	N/A	
S Δ	P0909947	Basic Administration Guide - French	20.00	H	N/A	
S Δ	P0910102	OTM 1.0 Installation and Engineering User Guide	50.00	H	N/A	
S Δ	P0910103	OTM 1.0 User Guide	50.00	H	N/A	
S Δ	P0910775	X11 Maintenance Programs	25.00	H	N/A	
S Δ	P0910776	X11 System Messages	25.00	H	N/A	
S Δ	P0910777	X11 Administration Programs	25.00	H	N/A	
S Δ	P0910790	Technical Reference Guide, Release 25	50.00	H	N/A	
B Δ	P0910791	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	50.00	H	N/A	
B Δ	P0910793	2.0 MB DTI/PRI Administration and Maintenance Guide	50.00	H	N/A	
B Δ	P0910795	BRI Guide, Release 25	50.00	H	N/A	
S ★ ➤ Δ	P0910806	Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (Paper)	20.00	H	N/A	
S	P0911675	SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide	50.00	H	N/A	
S Δ	P0912432	Library Navigator	50.00	H	N/A	
S Δ	P0912433	Systems Programming Guide	25.00	H	N/A	
S Δ	P0912434	Basic Telecom Management Guide	50.00	H	N/A	
S Δ	P0912435	Network Planning Guide	25.00	H	No charge	H
S Δ	P0912436	Fault Clearing Guide	25.00	H	N/A	
S Δ	P0912857	NT6D82 Power System	12.00	H	N/A	
S	P0912861	NT5D61 IODU/C Reference Guide	15.00	H	N/A	
S Δ	P0912862	CP Card Field Memory Upgrade Procedure	50.00	H	N/A	
S Δ	P0912864	Meridian IP Telecommuter NTP	15.00	H	N/A	
S ★	P0913184	CallPilot 1.07 Feature Operations Video	115.00	H	N/A	
S Δ	P0914163	MIPCD NTP Guide (English)	20.00	H	N/A	
S ★ Δ	P0914300	Installation Flowchart and Worksheets - Part 1 (English)	20.00	H	N/A	
S Δ	P0914505	MIPCD User Guide (English)	15.00	H	N/A	
S Δ	P0914553	MIPCD NTP Guide (French)	20.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S Δ	P0914554	MIPCD User Guide (French)	15.00	H	N/A	
S ➤	P0960326	Rubber Feet (100 each, for all Meridian Digital Telephones)	30.00	D	N/A	
S #	QAA29	Adapter	MD		175.00	H
S #	QAA33	Adapter	MD		195.00	H
S #	QAA47A	Power Monitor Adapter	MD		165.00	H
S #	QBL10B	Power Distribution Box (QCA23, QCA28)	MD		250.00	H
S #	QBL11	Power Distribution Box (QCA24)	MD		250.00	H
S	QBL12F	Battery Distribution Box	2,750.00	H	600.00	H
S #	QBL13	Power Distribution Box (QCA25)	MD		250.00	H
S #	QBL14	Power Distribution Box (RPE)	MD		250.00	H
S †	QBL15H	Battery Distribution Box	1,850.00	H	600.00	H
S #	QBL16	150V Power Distribution Box	MD		100.00	H
S #	QBL21	Power Distribution Box	MD		250.00	H
S #	QBL24	Battery Backup Distribution Box	MD		600.00	H
S #	QBL26	Power Distribution Unit	MD		250.00	H
S #	QBL3	Power Distribution Box (QCA6, QCA28)	MD		250.00	H
S #	QBL5	Power Distribution Box (QCA8)	MD		250.00	H
S #	QBL6	Battery Distribution Box	MD		250.00	H
S #	QBL7	Power Distribution Box (QCA10)	MD		250.00	H
S #	QBL8	Power Distribution Box (QCA14)	MD		250.00	H
S #	QBL9	AC Power Distribution Box	MD		90.00	H
S † ➤	QCAD109A	Cable Adapter	110.00	D	N/A	
S †	QCAD111A	Cable, Connector (QSP43)	440.00	D	N/A	
S ➤	QCAD125A	Cable, Connector (10 Ft.) (Female/Female) (Clock to Clock)	100.00	D	N/A	
S † ➤	QCAD128A	Cable, Connector (7 Ft.) (Male/Female) (DTI to I/O Panel)	60.00	H	N/A	
S ➤	QCAD129A	Cable, Connector (7 Ft.) (Male/Female) (PRI/DTI to Echo Canceler)	60.00	D	N/A	
S ➤	QCAD133A	PRI/DTI I/O Cable (50 Ft.)	150.00	D	N/A	
S † ➤	QCAD139A	Power Adapter Cable	110.00	D	N/A	
S † ➤	QCAD190A	Cable, Connector (74 In.) (Male/Male)	50.00	D	N/A	
S † ➤	QCAD193A	Cable, Connector (61 In.) (Male/Male)	50.00	D	N/A	
S † ➤	QCAD196A	Cable, Connector (48 In.) (Male/Male)	40.00	D	N/A	
S ➤	QCAD25AA	Power Adapter Cable	100.00	D	N/A	
S ➤	QCAD274A	Rectifier Cords, 20 Amp, 225V	70.00	D	N/A	
S ➤	QCAD277A	Power Connector Cable (2nd Module)	40.00	D	N/A	
S ➤	QCAD278A	Power Connector Cable (Basic)	20.00	D	N/A	
S ➤	QCAD284A	Power Adapter Cable	70.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	QCAD294B2	Power Fail Transfer Cable (50 Ft.)	70.00	D	N/A	
S † ➤	QCAD306B	Power Connector Cable (QSD73)	30.00	D	N/A	
S † ➤	QCAD309A	Alarm Adapter Cable	40.00	D	N/A	
S † ➤	QCAD310A	Ground Extension Cable	30.00	D	N/A	
S † ➤	QCAD313A	Power & Signaling Cable (Tier 3)	50.00	D	N/A	
S ➤	QCAD318A	Telecom 25 Pair (50-Pin) to 6DB-25 Female Connector	100.00	D	N/A	
S ➤	QCAD319A	Telecom 25 Pair (50-Pin) to 6DB-25 Male Connector	100.00	D	N/A	
S ➤	QCAD321A	Junction Box QBL15	90.00	H	N/A	
S † ➤	QCAD325A	Cable	180.00	D	N/A	
S ➤	QCAD332A	Triple SDI Cable (Internal)	80.00	D	N/A	
S ➤	QCAD42A	Cable, Intra-Cabinet (25 Conductor 95 In.) (EMI)	50.00	D	N/A	
S # Δ	QCN100	Attendant Console	MD		350.00	H
S # Δ	QCN101	Attendant Console	MD		350.00	H
S #	QCN102	Attendant Console	MD		350.00	H
S #	QCW2	Console	MD		240.00	H
S #	QCW3	Console	MD		240.00	H
S #	QCW4	Digit Display Console	MD		240.00	H
S † ➤	QFF1A	Fuse, 1.33 Amp	3.00	I	N/A	
S ➤	QFF1AB	1 1/3 Amp Fuse	5.00	H	N/A	
S † ➤	QFF1B	Fuse, 2. Amp	5.00	I	N/A	
S † ➤	QFF1C	Fuse, 3. Amp	2.00	I	N/A	
S † ➤	QFF1D	Fuse, 5. Amp	17.00	I	N/A	
S † ➤	QFF1E	Fuse, .180 Amp	5.00	I	N/A	
S † ➤	QFF1F	Fuse, .25 Amp	5.00	I	N/A	
S † ➤	QFF1G	Fuse, .50 Amp	3.00	I	N/A	
S #	QKK1	Handsfree Interface Kit	MD		45.00	H
S #	QKK3	Automatic Handsfree Interface Kit	MD		45.00	H
S #	QKK8	Automatic Handsfree Answerback Interface Kit	MD		45.00	H
S #	QKN1	Headset Interface Kit	MD		40.00	H
S #	QMM38	Mass Storage Unit Assembly	MD		300.00	H
S #	QMM43	Mass Storage Assembly	MD		205.00	H
S #	QMM45A	Floppy Disk Module	MD		255.00	H
S #	QMT1	Add-On Module (10 Button)	MD		50.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QMT102	Disk Drive Controller	MD		350.00	H
S #	QMT103	Winchester Hard Disk Assembly	MD		515.00	H
S #	QMT104	Floppy Drive Assembly	MD		220.00	H
S #	QMT11D	Asynchronous/Synchronous Interface Module (ASIM)	MD		220.00	H
S #	QMT12E	V.35 Add-On Data Module	MD		375.00	H
S #	QMT15	Amplified Handset Module (Includes Attendant Handset Assembly)	MD		75.00	H
S #	QMT2	Add-On Module (20 Button)	MD		75.00	H
S #	QMT21	High Speed Data Module (HSDM) 110V Power Supply	MD		300.00	H
S #	QMT21C1	High Speed Data Module (HSDM) 110V Power Supply	MD		300.00	H
S #	QMT3	Lamp Field Array (BLF)	MD		100.00	H
S #	QMT4	Handset Module	MD		50.00	H
S #	QMT7	Add-On Data Module (ADM) (Asynchronous Only)	MD		200.00	H
S #	QMT8	Add-On Data Module (ADM) (Synchronous/Asynchronous)	MD		300.00	H
S #	QMT9	Asynchronous Interface Module (AIM)	MD		200.00	H
S #	QPA57	Function Pack	MD		350.00	H
S #	QPA58	Interface Pack	MD		350.00	H
S #	QPA59	Miscellaneous	MD		350.00	H
S #	QPA62	32K x 17R/W Memory (CDR)	MD		200.00	H
S #	QPC130	CDR Tape Control	MD		95.00	H
S #	QPC131	CDR ROM 1 (Single Port)	MD		110.00	H
S #	QPC132	CDR ROM 2 (Single Port)	MD		95.00	H
S #	QPC135	Fast CPU ALU Low	MD		85.00	H
S #	QPC136	Fast CPU ALU High	MD		90.00	H
S #	QPC137	Fast CPU Control	MD		85.00	H
S #	QPC138	Fast CPU Sequencer	MD		80.00	H
S #	QPC139B	Serial Data Interface (Dual)	MD		150.00	H
S #	QPC155	Fast CE Bus Extender	MD		350.00	H
S #	QPC156	Multigroup Control	MD		80.00	H
S #	QPC157	Multigroup Switch	MD		80.00	H
S #	QPC158	Multigroup Extender	MD		80.00	H
S #	QPC162	AIOD C25 Data Trunk	MD		230.00	H
S #	QPC163	48V Regulator	MD		225.00	H
S #	QPC164	Bus Termination Unit (BTU)	MD		60.00	H
S #	QPC167	Real Time Clock & ROM	MD		135.00	H
S #	QPC171	Battery Monitor	MD		75.00	H
S #	QPC187	Ringing Generator	MD		90.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QPC188D	Battery Monitor	MD		65.00	H
S #	QPC189	MF Sender	MD		135.00	H
S #	QPC190	5/12V Converter Pack	MD		350.00	H
S #	QPC192	OPX Line	MD		105.00	H
S ✓ #	QPC197D	Tone & Digit Switch	MD		195.00	H
S #	QPC199	4K x 16 ROM	MD		110.00	H
S #	QPC212	Real Time Clock & ROM	MD		110.00	H
S #	QPC213	Changeover & Memory Arbitrator	MD		135.00	H
S #	QPC214	Memory Controller	MD		210.00	H
S #	QPC215D	Segmented Bus Extender	MD		180.00	H
S #	QPC216	Three Port Segmented Extender	MD		190.00	H
S #	QPC218	CO/FX/WATS Trunk	MD		100.00	H
S #	QPC219	CO/FX/Trunk with Message Registration Detector Circuit	MD		80.00	H
S #	QPC220	Bus Termination Unit (BTU)	MD		110.00	H
S #	QPC228	CPU Changeover	MD		225.00	H
S #	QPC237E	4 Wire E&M Trunk	MD		100.00	H
S #	QPC239	Dictation Trunk Applique w/DCK Interface	MD		120.00	H
S #	QPC240	ROM 2 Module	MD		120.00	H
S #	QPC241	ROM 3 Module	MD		120.00	H
S #	QPC246	Keyboard (QCW3)	MD		75.00	H
S	QPC247A	Keyboard with Dial Pad, (QCW3/QCW4)	300.00	D	75.00	H
S #	QPC248	Keyboard (QCW3/QCW4)	MD		75.00	H
S #	QPC250	Release Line Trunk	MD		135.00	H
S #	QPC251	Tone and Digit Switch for CAS	MD		145.00	H
S #	QPC264	8K ROM	MD		140.00	H
S #	QPC267	MW/DND Line Card	MD		110.00	H
S #	QPC268	Control Interface and Memory	MD		140.00	H
S #	QPC271	Control and Timing	MD		135.00	H
S #	QPC274	Fan Inverter (QRF8)	MD		100.00	H
S #	QPC297	Supervisory Console	MD		140.00	H
S #	QPC298	3 Port CPU Interconnect	MD		110.00	H
S #	QPC30	4K x 17 R/W Memory	MD		95.00	H
S #	QPC300	8K ROM	MD		205.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QPC301	CDR ROM (Multi-Port)	MD		215.00	H
S #	QPC31	8K x 17 R/W Memory (CDR-Single Port)	MD		110.00	H
S #	QPC311	SL-1 Data Line Card	MD		100.00	H
S #	QPC32	4K x 16 ROM	MD		130.00	H
S #	QPC33	Tape Unit Interface	MD		105.00	H
S #	QPC353	500 Line Card for Modem Pool Interface	MD		165.00	H
S #	QPC362	Conference/Network Card	MD		155.00	H
S #	QPC374	8K ROM	MD		180.00	H
S #	QPC376	Dual Network	MD		175.00	H
S #	QPC387	Peripheral Buffer	MD		155.00	H
S #	QPC39	CDR Timing	MD		115.00	H
S #	QPC397	MCDS - Asynchronous Card	MD		150.00	H
S #	QPC40	Arithmetic Logic Unit (CDR)	MD		110.00	H
S #	QPC41	CPU Miscellaneous Register (CDR)	MD		125.00	H
S #	QPC411	System Clock Generator	MD		140.00	H
S #	QPC412C	Intergroup Switch	MD		235.00	H
S ➤	QPC414C	Network Card	2,000.00	I	200.00	H
S	QPC417A	Junctor Board	1,400.00	I	200.00	H
S #	QPC42	Sequencer (CDR)	MD		110.00	H
S #	QPC420	Keyboard Pack	MD		350.00	H
S #	QPC422	Tone Detector	MD		250.00	H
S #	QPC423	192K Memory	MD		220.00	H
S #	QPC424	Central Processor Unit (CPU)	MD		350.00	H
S #	QPC425	Central Processor Unit (CPU)	MD		250.00	H
S #	QPC426	192K Memory	MD		285.00	H
S #	QPC430	AILC - Asynchronous Interface Line Card	MD		125.00	H
S #	QPC432	Four Port Data Line Card	MD		210.00	H
S ➤	QPC43R	Peripheral Signaling	800.00	I	95.00	H
S #	QPC44	CPU Changeover	MD		110.00	H
S ➤	QPC441F	Three-Port Extender	2,000.00	I	205.00	H
S #	QPC443	Control and Timing	MD		190.00	H
S ➤	QPC444A	Conference Card	2,900.00	I	165.00	H
S #	QPC449C	Loop Signaling Trunk	MD		140.00	H
S #	QPC45	Serial Data Interface (Single) (CDR)	MD		100.00	H
S #	QPC450G	CO/FX/Trunk w/Message Registration Detector Circuit	MD		120.00	H
S #	QPC451	SL-1 Line Card	MD		130.00	H
S #	QPC452	500/2500 Line Card	MD		130.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QPC46	CE Bus Extender	MD		95.00	H
S #	QPC464	Peripheral Buffer	MD		140.00	H
S ➤	QPC471H	Clock Controller	1,500.00	I	200.00	H
S #	QPC472	DTI/CPI Network Carrier Interface	MD		305.00	H
S #	QPC477A10	Bus Terminating Unit (BTU)	MD		110.00	H
S ➤	QPC477A9	Bus Terminating Unit (BTU)	400.00	I	110.00	H
S ➤	QPC477B10	Bus Terminating Unit (BTU)	400.00	I	110.00	H
S #	QPC478	128K Memory	MD		275.00	H
S #	QPC479	128K Memory	MD		215.00	H
S #	QPC486	ROM Card	MD		190.00	H
S #	QPC487	ROM Card	MD		180.00	H
S #	QPC494A	MW/DND Line Card	MD		180.00	H
S #	QPC496A	Pack, CPU Bus Extender, N	MD		200.00	H
S #	QPC50	Network	MD		90.00	H
S #	QPC500	PE Backplane	MD		250.00	H
S #	QPC501	PE Backplane/Expansion	MD		250.00	H
S #	QPC502	Power Backplane	MD		250.00	H
S #	QPC503	CE Backplane Expansion	MD		250.00	H
S #	QPC509	Message Waiting Power Supply	MD		220.00	H
S #	QPC51	64K Memory Module	MD		90.00	H
S #	QPC512	Personal Computer (PC) Interface Card	MD		100.00	H
S #	QPC513H	Enhanced SDI	MD		200.00	H
S #	QPC52	Network Extender	MD		90.00	H
S #	QPC53	Conference	MD		90.00	H
S #	QPC54	Tone and Digit Switch 1	MD		95.00	H
S #	QPC55	Tone and Digit Switch 2	MD		150.00	H
S #	QPC552	Control and Timing	MD		350.00	H
S #	QPC553	Function	MD		350.00	H
S #	QPC554	Interface	MD		350.00	H
S #	QPC555	Miscellaneous	MD		350.00	H
S #	QPC556	Changeover and Memory Arbitrator	MD		325.00	H
S #	QPC557	Control and Timing	MD		350.00	H
S #	QPC571	ROM Card	MD		215.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QPC573	8K ROM Card	MD		350.00	H
S #	QPC574B	Digitone Receiver	MD		210.00	H
S ✓ #	QPC578D	Integrated Service Digital Line Card (ISDLC)	MD		245.00	H
S #	QPC579	Central Processor Unit (CPU)	MD		280.00	H
S #	QPC580	CPU Interface Card	MD		280.00	H
S #	QPC581	Changeover & Memory Arbitrator	MD		350.00	H
S #	QPC583	768K Memory	MD		350.00	H
S † ➤	QPC584M	Mass Storage Interface Card	1,400.00	I	250.00	H
S #	QPC585A	Disk Shelf Power Converter (QMM38)	MD		300.00	H
S #	QPC594	500/2500 Line Card (16 Port)	MD		220.00	H
S #	QPC599	ROM Card	MD		215.00	H
S #	QPC60	500/2500 Line Card	MD		65.00	H
S #	QPC600	ROM Card	MD		240.00	H
S #	QPC601	ROM Card (Memory Enhancement)	MD		265.00	H
S #	QPC602	ROM Card	MD		205.00	H
S #	QPC609D	Fast Tone and Digit Switch	MD		200.00	H
S #	QPC61	SL-1 Line Card	MD		65.00	H
S #	QPC62	1.5M Baud Converter (RPE)	MD		200.00	H
S #	QPC63	Local Carrier Buffer (RPE)	MD		200.00	H
S #	QPC64	Peripheral Buffer	MD		120.00	H
S #	QPC65	Remote Peripheral Switch (RPE)	MD		200.00	H
S #	QPC659E	Dual Loop Peripheral Buffer	MD		200.00	H
S #	QPC66	2M Baud Converter (RPE)	MD		200.00	H
S #	QPC662	ROM Card	MD		350.00	H
S #	QPC67	Carrier Maintenance (RPE)	MD		200.00	H
S #	QPC672	512K Memory Card	MD		250.00	H
S #	QPC673	512K Memory Card	MD		300.00	H
S #	QPC674	256K RAM Memory	MD		300.00	H
S #	QPC687	Central Processor Unit (CPU)	MD		235.00	H
S #	QPC691	5/12V Converter	MD		275.00	H
S #	QPC699	CE Backplane	MD		300.00	H
S #	QPC70	CO/FX/WATS Trunk	MD		100.00	H
S #	QPC700	CE Backplane	MD		300.00	H
S #	QPC701A1	PE Backplane	MD		300.00	H
S	QPC702A1	PE Backplane	1,675.00	I	300.00	H
S #	QPC705	30/150V PE Power Converter	MD		250.00	H
S #	QPC706	Power Converter (All Voltages)	MD		250.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QPC709	Miscellaneous/Peripheral Signaling	MD		200.00	H
S #	QPC710A	Dual Digitone Receiver Daughter Board	MD		160.00	H
S #	QPC717	ROM Card	MD		275.00	H
S #	QPC71H	E&M/DX/Page Trunk	MD		95.00	H
S #	QPC72	Loop Signaling Trunk	MD		90.00	H
S ➤	QPC720F	Primary Rate Interface Card	4,500.00	I	400.00	H
S #	QPC723A	RILC - RS232C Interface Line Card	MD		230.00	H
S #	QPC73	Dictation Trunk Applique	MD		100.00	H
S #	QPC742F	Floppy Disk Interface Card	MD		220.00	H
S #	QPC74C	Recorder Announcement Trunk	MD		170.00	H
S #	QPC75	Rectifier Control (QSD4)	MD		250.00	H
S #	QPC757	D Channel Interface Card	MD		300.00	H
S #	QPC78	Fan Inverter (QSD4)	MD		140.00	H
S #	QPC782	ROM Card	MD		220.00	H
S #	QPC789A	16 Port Message Waiting Line Card	MD		350.00	H
S #	QPC79	Digitone Receiver	MD		95.00	H
S #	QPC80H	10V Converter Pack	MD		275.00	H
S #	QPC814	768K Memory Card	MD		350.00	H
S #	QPC82E	30V Converter Pack	MD		275.00	H
S ➤	QPC841C	Four-Port SDI	3,500.00	I	220.00	H
S ➤	QPC84S	Power Monitor Pack	1,000.00	I	125.00	H
S #	QPC85	5/12V Converter Pack (RPE)	MD		350.00	H
S #	QPC918	High Speed Data Card (2 Port)	MD		240.00	H
S #	QPC930	16 Port Hotel/Motel Message Waiting Line Card	MD		375.00	H
S #	QPC937	ROM Card	MD		350.00	H
S #	QPC939	ROM Card	MD		330.00	H
S #	QPC940	ROM Card	MD		310.00	H
S #	QPC99	Carrier Interface (RPE)	MD		300.00	H
S ➤	QPF23A	Terminating Plug	160.00	I	N/A	
S ➤	QPF36B	Terminating Plug	15.00	I	N/A	
S #	QRF12	48V Rectifier	MD		625.00	H
S #	QRF8	48V Rectifier	MD		625.00	H
S #	QRF9	48V Rectifier	MD		625.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QSD1	Common Equipment Shelf 0 (CDR)	MD		400.00	H
S #	QSD10	Power Converter Shelf (RH Mount)	MD		400.00	H
S #	QSD11	Carrier Shelf 1 (RPE)(RH Mount)	MD		400.00	H
S #	QSD12	CPU/Memory Shelf	MD		400.00	H
S #	QSD13	Segmented Network Shelf 1	MD		400.00	H
S #	QSD14	Memory Shelf	MD		400.00	H
S #	QSD15	Common Equipment Shelf (CPU)	MD		400.00	H
S #	QSD16	Segmented Network Shelf 0	MD		400.00	H
S #	QSD17	Common Equipment Shelf (CPU)	MD		400.00	H
S #	QSD18	Common Equipment Shelf (CPU)	MD		400.00	H
S #	QSD19	Common Equipment Shelf (CPU)	MD		400.00	H
S #	QSD2	Common Equipment Shelf 1	MD		400.00	H
S #	QSD23	Power Control Shelf	MD		400.00	H
S #	QSD26	CERP Shelf	MD		400.00	H
S #	QSD27A	Multi-Channel Data System (MCDS) Shelf	MD		400.00	H
S #	QSD3	Peripheral Equipment Shelf 0 (LH Mount)	MD		400.00	H
S #	QSD31	Peripheral Equipment Shelf	MD		400.00	H
S #	QSD32	Peripheral Equipment Shelf	MD		400.00	H
S #	QSD33	Tape Shelf	MD		400.00	H
S #	QSD34	Peripheral Equipment Shelf (LH Mount)	MD		400.00	H
S #	QSD35	Peripheral Equipment Shelf (RH Mount)	MD		400.00	H
S #	QSD36	Memory Shelf (Center Mount)	MD		400.00	H
S #	QSD37	CPU/Memory Shelf	MD		400.00	H
S #	QSD39	Network Shelf (LH Mount)	MD		400.00	H
S #	QSD4	48V Rectifier Assembly	MD		625.00	H
S #	QSD40	Network Shelf (RH Mount)	MD		400.00	H
S #	QSD54	Network Shelf (RH Mount)	MD		400.00	H
S #	QSD55	Network Shelf (LH Mount)	MD		400.00	H
S #	QSD58	Common Equipment Shelf	MD		400.00	H
S #	QSD59	CPU/Memory Shelf	MD		400.00	H
S #	QSD6	Carrier Shelf 0 (RPE) (LH Mount)	MD		400.00	H
S #	QSD60	CPU/Memory Shelf (Cantilever Mount)	MD		400.00	H
S #	QSD61	CPU/Memory Shelf (Center Mount)	MD		400.00	H
S #	QSD62	CPU/Memory Shelf (Cantilever Mount)	MD		400.00	H
S #	QSD64	Universal Peripheral Equipment Shelf	MD		400.00	H
S ✓ #	QSD65A	Dual Loop PE Shelf	MD		400.00	H
S #	QSD66	PE Expansion Tier	MD		400.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QSD67	Disk Drive Shelf (Cantilever Mount)	MD		400.00	H
S #	QSD68	Disk Drive Shelf/MSU (Center Mount)	MD		400.00	H
S #	QSD7	Peripheral Equipment Shelf 1 (RH Mount)	MD		400.00	H
S #	QSD73	CE/PE Expansion Tier	MD		400.00	H
S #	QSD76	Network/MSU Shelf	MD		400.00	H
S #	QSD79B	Expansion Tier Assembly	MD		400.00	H
S #	QSD80	High Density PE Shelf	MD		400.00	H
S #	QSD81A	CE Shelf (w/Mounting Bracket)	MD		400.00	H
S #	QSD82	H/M PE Shelf System	MD		400.00	H
S #	QSD83	H/M ST Shelf System	MD		400.00	H
S #	QSD9	Common Equipment Shelf 2	MD		400.00	H
S #	QSP31	Network Shelf (RH Mount)	MD		400.00	H
S #	QSP32	Network Shelf (LH Mount)	MD		400.00	H
S #	QSP35	Peripheral Equipment Shelf (RH Mount)	MD		400.00	H
S #	QSP36	Peripheral Equipment Shelf (LH Mount)	MD		400.00	H
S #	QSP39	Common Equipment Shelf	MD		400.00	H
S #	QSP40	Memory Shelf (QCA55)	MD		400.00	H
S #	QSP41	Common Equipment/Memory (QCA58)	MD		400.00	H
S #	QSP43	Power Control (QCA55, QCA58, QCA108, QCA109, QCA96, QCA97)	MD		780.00	H
S #	QSP44	Power Control (QCA74)	MD		780.00	H
S #	QSP45	Tape Unit and Shelf	MD		625.00	H
S # Δ	QSP6	Option Shelf Full Wired/Enhanced	MD		400.00	H
S # Δ	QSP7	Option Shelf Full Wired/Enhanced	MD		400.00	H
S #	QSR2F1	Venture 1 Headset w/5 Ft. Straight Cord	MD		80.00	H
S #	QSR2G1	Venture 1 Headset w/15 Ft. Coiled Cord	MD		80.00	H
S #	QSU1	SL-1 Telephone Set	MD		90.00	H
S #	QSU3	SL-1 Digit Display Phone	MD		130.00	H
S #	QSU60	SL-1 Telephone (Fully Modular)	MD		50.00	H
S #	QSU61	SL-1 Digit Display Telephone	MD		55.00	H
S #	QSU7	SL-1 ACD Telephone (Dual Headset Jack)	MD		90.00	H
S #	QSU71B35	M1109 Compact Telephone, Ash	MD		70.00	H
S #	QSU71B93	M1109 Compact Telephone, Gray	MD		70.00	H
S #	QSU71C35	Meridian M1109 Compact Telephone, Ash	MD		70.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QSU71C93	Meridian M1109 Compact Telephone, Gray	MD		70.00	H
S #	QSY19	MW/DND 150V Power Supply	MD		200.00	H
S #	QSY22	Message Waiting 150V Power Supply	MD		250.00	H
S #	QSY27A	Multi-Channel Data System (MCDS) Power	MD		250.00	H
S #	QUA1	Transfer Unit	MD		380.00	H
S #	QUA5A	Power Fail Transfer Unit	MD		200.00	H
S #	QUA6A	Power Fail Transfer Unit	MD		110.00	H
S #	QUAA3C	Power Unit	MD		300.00	H
S #	QUAA5A	Power Unit	MD		300.00	H
S #	QUD1	Cooling Unit (CDR)	MD		220.00	H
S #	QUD15	Blue Cooling and Cable Routing Panel Assembly	MD		250.00	H
S #	QUD24	Cooling Unit	MD		275.00	H
S #	QUD25	Cooling Unit	MD		220.00	H
S #	QUD3	Cooling Unit	MD		220.00	H
S #	QUD4	Cooling Unit	MD		220.00	H
S #	QUD5	Cooling Unit	MD		220.00	H
S #	QUD6	Cooling Unit	MD		220.00	H
S #	QUD8	Mini Cooling Unit	MD		220.00	H
S #	QUD9	Cooling Unit	MD		220.00	H
S #	QUT1	Centralized Power Unit	MD		250.00	H
S #	QUT2	Power Unit (Fan)	MD		150.00	H
S #	QUT3	Power Unit (Fan & Inverter)	MD		150.00	H
S #	QUW1	Tape Unit & Shelf	MD		500.00	H
S #	QUW3	Mini Tape Unit & Shelf (QCA28)	MD		500.00	H
S #	QUW9	Tape Unit	MD		500.00	H
S #	QUX1	Power Distribution Unit (QCA6, QCA28)	MD		350.00	H
S #	QUX10	Power Distribution Unit (QCA24)	MD		350.00	H
S #	QUX11	Power Distribution Unit (QCA25)	MD		350.00	H
S #	QUX16	Power Distribution Unit (QCA60)	MD		350.00	H
S #	QUX19	Power Distribution Unit (QCA136)	MD		100.00	H
S #	QUX2	Power Distribution Unit (QCA7)	MD		350.00	H
S #	QUX20	Power Distribution Unit (QCA136)	MD		100.00	H
S #	QUX21	Power Distribution Unit (QCA137)	MD		100.00	H
S #	QUX22	Power Distribution Unit (QCA147)	MD		100.00	H
S #	QUX3	Power Distribution Unit (QCA8)	MD		350.00	H
S #	QUX4	Power Distribution Unit (QCA10)	MD		350.00	H
S #	QUX5	Power Distribution Unit (QCA14)	MD		350.00	H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S #	QUX6	Power Distribution Unit (CDR)	MD		100.00	H
S #	QUX9	Power Distribution Unit (QCA23)	MD		350.00	H
S ➤ Δ	S0005899	NAC Connectivity for Meridian MAX Release 9 Software	No charge		N/A	
S ➤ Δ	S0005901	Multiple Queue Assignment (MQA) Reporting for Meridian MAX Release 9 Software	No charge		N/A	
S ➤ Δ	S0005906	100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software	3,000.00	D	N/A	
S ➤ Δ	S0005907	10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software	1,000.00	D	N/A	
S ➤	S0005908	8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software	1,500.00	D	N/A	
S ➤ Δ	SERV0002	Spare set of blank 3.5 inch 4MB floppy diskettes	500.00	H	N/A	
S ➤ Δ	SERV0003	Spare set of blank 5.25 in diskettes	500.00	H	N/A	
N Δ	SERV0004	Same Day Shipment per Order Expedite Fee	200.00	H	N/A	
S ➤ Δ	SERV0005	Meridian MAX Releases 6, 7 and 8 Software Service Transaction Fee (AM)	500.00	H	N/A	
B ➤ Δ	SERV0006	Customer Controlled Routing Software Service Transaction Fee	500.00	H	N/A	
S ➤ Δ	SERV0017	Meridian MAX-IPE/MAX-IPEE Releases 6, 7 and 8 Software Service Transaction Fee	500.00	H	N/A	
B ➤ Δ	SERV0019	Meridian Mail Software Service Transaction Fee	500.00	H	N/A	
S ➤ Δ	SERV0020	Meridian Mail Hardware Key Code Service	No charge		N/A	
S ➤ Δ	SERV0031	In-House Software Conversion Fee	100.00	H	N/A	
S ➤ Δ	SERV0033	Meridian Link & CCR Co-Resident Service Transaction Fee	750.00	H	N/A	
S ➤ Δ	SERV0055	Switch to Switch Conversion Fee	750.00	H	N/A	
S ➤ Δ	SERV0056	Loops Requiring Conversion/Balancing	27.50	H	N/A	
S ➤ Δ	SERV0058	Loop Conversion Fee	850.00	H	N/A	
S ➤	SERV0080	CD-ROM Media Request	No charge		N/A	
S ➤ Δ	SV000020	Messenger 4.0: On-site Administration and User Training	4,000.00	H	N/A	
S ➤ Δ	SV000024	MAS Premium Warranty Upgrade: Extended Telephone Support	1,200.00	H	N/A	
S ➤ Δ	SV000025	MAS Premium Warranty Upgrade; Onsite Removal/Replacement	3,500.00	H	N/A	
S ➤ Δ	SV000026	MAS Post Warranty Service	5,000.00	H	N/A	
S ➤ Δ	SV000027	MAS Post Warranty Premium Service	6,000.00	H	N/A	
S ➤ Δ	SV000088	SYMPOSIUM TAPI Service Provider INSTALL-PREP	900.00	H	N/A	
S ✓ ➤ Δ	SV000089	SYMPOSIUM TAPI Service Provider INSTALL-PRO	5,900.00	H	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	SV000091	SYMPOSIUM TAPI Server, One Additional Year of Software Support	1,200.00	H	N/A	
S ➤ Δ	SV000098	Meridian Mail Functionality Service Fee	1,000.00	H	N/A	
S ➤ Δ	SV000099	Meridian Mail 2-24 Upgrade Service Charge	2,000.00	H	N/A	
S ➤ Δ	SV000100	Meridian Mail 25-48 Upgrade Service Charge	4,000.00	H	N/A	
S ➤ Δ	SV000101	Meridian Mail 49-64 Upgrade Service Charge	6,000.00	H	N/A	
S ➤ Δ	SV000102	Meridian Mail 65-96 Upgrade Service Charge	8,000.00	H	N/A	
S ➤ Δ	SV000110	Messenger Post Warranty Phone 8-5	3,000.00	H	N/A	
S ➤ Δ	SV000111	Messenger Post Warranty Phone 7x24	4,000.00	H	N/A	
S ➤ Δ	SV000112	Messenger Installation Phone Support	3,000.00	H	N/A	
S ➤ Δ	SV000117	SYMPOSIUM Transaction Fee	500.00	H	N/A	
S ➤ Δ	SV000125	SYMPOSIUM Call Center Installation	5,290.00	H	N/A	
S ➤ Δ	SV000126	SYMPOSIUM FastView INSTALL-PRO Installation 5 to 8 Seats	1,500.00	H	N/A	
S ➤ Δ	SV000127	SYMPOSIUM FastView INSTALL-PREP Remote Installation	400.00	H	N/A	
S ➤ Δ	SV000128	SYMPOSIUM FastView Software Support	1,200.00	H	N/A	
S ➤ Δ	SV000147	SYMPOSIUM Agent Install-Prep	500.00	H	N/A	
S ➤ Δ	SV000148	SYMPOSIUM Agent Install-Pro	1,500.00	H	N/A	
S ➤ Δ	SV000149	SYMPOSIUM Agent Software Support	1,200.00	H	N/A	
S ➤ Δ	SV000175	Nortel IVR CompuCALL Integration Package	25,000.00	H	N/A	
S ➤	SV000176	CCIP - CompuCALL Agent/Port License	100.00	H	N/A	
S ➤ Δ	SV000177	Web Call Back	12,000.00	H	N/A	
S ➤ Δ	SV000181	Service Code for Telephone Support to Add Additional User Client License(s) Req. if adding clients to existing systems	300.00	H	N/A	
S ➤	SV000182	SYMPOSIUM WebResponse Server Additional 1 Day Installation Services	1,500.00	H	N/A	
S † ➤ Δ	SV000183	SYMPOSIUM WebResponse Server Annual Telephone Support	950.00	H	N/A	
S † ➤ Δ	SV000184	SYMPOSIUM WebResponse Server Installation Service	6,000.00	H	N/A	
S Δ	SV000251	Additional One Day On-Site Messenger Training	1,500.00	H	N/A	
S ➤ Δ	SV000252	Message Taker	12,000.00	H	N/A	
S ➤ Δ	SV000253	Voice Form	12,000.00	H	N/A	
S ➤ Δ	SV000254	Agent Whisper	8,000.00	H	N/A	
S ➤ Δ	SV000255	CCIP Screen Pop	15,000.00	H	N/A	
S ➤ Δ	SV000257	TAPI Integration - Remote Installation	9,000.00	H	N/A	
S ➤ Δ	SV000259	TAPI Integration - Solution Pro	19,500.00	H	N/A	
S ➤ Δ	SV000260	ACD Fax Pop	40,000.00	H	N/A	
S ➤ Δ	SV000261	Enhanced IVR Reports	15,000.00	H	N/A	
S ➤ Δ	SV000262	Follow Me Service	8,500.00	H	N/A	
S † ➤ Δ	SV000276	Messenger 2.0/3.0 to 4.0 On-Site Migration Support	3,000.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤ Δ	SV000277	Messenger 2.0/3.0 to 4.0 Migration Phone Support	750.00	H	N/A	
S † ➤ Δ	SV000278	Messenger 2.0/3.0 Maintenance Release--Phone Installation Support for Customers Under Warranty or Maintenance	No charge		N/A	
S † ➤ Δ	SV000279	Messenger 2.0/3.0 Maintenance Release--Installation Phone Support for Customers NOT under Warranty or Maintenance	750.00	H	N/A	
S † ➤ Δ	SV000280	Messenger 2.0/3.0 Maintenance Release--On-Site Installation Support for Customers NOT under Warranty or Maintenance	1,500.00	H	N/A	
S Δ	SV000288	SYMPOSIUM Call Center Server Client Installation	390.00	H	N/A	
S Δ	SV000397	OTM Service, Rate Tables - MDR	800.00	D	N/A	
S ➤ Δ	SV000399	SYMPOSIUM Express Call Center Installation and Configuration Service	5,900.00	H	N/A	
N ✓ ➤ Δ	SVC0001	Meridian 1 Security Audit Per Hour	200.00	H	N/A	
N ✓ ➤ Δ	SVC0007	Meridian 1 Security Consulting per day plus travel and expense	1,600.00	H	N/A	
N ✓ ➤ Δ	SVC0010	Meridian 1 Security Seminar (per day) Plus Travel and Expense for One Consultant	1,750.00	H	N/A	
S ➤ Δ	SVC1006	Meridian Mail Reporter One Year Extended Service Plan	250.00	H	N/A	
S Δ	SVC1035	Meridian Link INSTALL-ASSIST	995.00	H	N/A	
S ➤	SW0000C	Meridian 1 Release 17 Base Software	5,750.00	I	N/A	
S ➤	SW0000E	Meridian 1 Release 19 Base Software	5,750.00	I	N/A	
S ➤	SW0000G	Meridian 1 Release 21 Base Software	6,000.00	I	N/A	
S ➤	SW0000H	Meridian 1 Release 22 Base Software	6,000.00	I	N/A	
S ➤	SW0000J	Meridian 1 Base System Software: Release 23	6,000.00	I	N/A	
S ➤	SW0000K	Meridian 1 Base System Software: Release 24	6,000.00	I	N/A	
S ➤	SW0000L	Meridian 1 Base System Software: Release 25	6,000.00	I	N/A	
S † ➤	SW0001A	Special Application Features	800.00	I	N/A	
S ➤	SW0003A	NARS/CDR Format	No charge		N/A	
S ➤	SW0005A	DN Expansion	400.00	I	N/A	
S ➤	SW0006A	Automatic Trunk Maintenance	1,250.00	I	N/A	
S † ➤	SW0008A	Multi-Customer	550.00	I	N/A	
S ➤	SW0009A	Multi-Tenant	1,750.00	I	N/A	
S † ➤	SW0010A	Automatic Number Identification (ANI)	1,650.00	I	N/A	
S ➤	SW0011A	Option 81 - Required for Option 81	No charge		N/A	
S ➤ Δ	SW0013A	Option 81C - Required for Option 81C	No charge		N/A	
S ➤	SW0015A	SNMP Open Alarms	500.00	I	N/A	
S ➤	SW0016A	MAT Data Buffering and Access	1,500.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	SW0017A	Hospitality/Healthcare Features	400.00	I	N/A	
S † ➤	SW0018A	Property Management Systems Interface	900.00	I	N/A	
S † ➤	SW0019A	Attendant Overflow Position	550.00	I	N/A	
S † ➤	SW0020A	Supervisory Console	900.00	I	N/A	
S † ➤	SW0021A	Attendant Alternative Answer	900.00	I	N/A	
S † ➤	SW0022A	RPE	900.00	I	N/A	
S † ➤	SW0024A	Line Load Control	2,750.00	I	N/A	
S † ➤	SW0025A	CAS - Main	2,750.00	I	N/A	
S † ➤	SW0026A	CAS - Remote	1,650.00	I	N/A	
S ➤	SW0028A	Fast TDS	No charge		N/A	
S † ➤	SW0029B	Advanced Hospitality Features	400.00	I	N/A	
S ➤	SW0030A	Flexible Tones and Cadences	800.00	I	N/A	
S ➤	SW0030B	Flexible Tones and Cadences	800.00	I	N/A	
S ➤	SW0031A	Hospitality Screen Enhancements	No charge		N/A	
S ➤	SW0032A	CAS - Main/Remote	500.00	I	N/A	
S ➤	SW0033A	Attendant Overflow Position	300.00	I	N/A	
S ➤	SW0034A	Line Load Control	500.00	I	N/A	
S ➤	SW0040A	CLASS Software	1,750.00	I	N/A	
S † ➤	SW0041A	NARS	900.00	I	N/A	
S † ➤	SW0042A	Coordinated Dialing Plan	900.00	I	N/A	
S † ➤	SW0043A	Network Authorization Code	550.00	I	N/A	
S † ➤	SW0044A	Basic ESN Features	900.00	I	N/A	
S † ➤	SW0045A	Advanced ESN Features	1,100.00	I	N/A	
S ➤	SW0046A	Feature Group D	3,000.00	I	N/A	
S ➤	SW0047A	Direct Inward System Access (DISA)	No charge		N/A	
S ➤	SW0048A	Meridian COMPANION CLID/CPND/Privacy	No charge		N/A	
S ➤	SW0049A	Remote Software Option	250.00	I	N/A	
S ➤	SW0050A	Networking	1,250.00	I	N/A	
S ➤	SW0050B	Networking	1,250.00	I	N/A	
S ➤	SW0051A	ISDN Networking	2,250.00	I	N/A	
S ➤	SW0051B	ISDN Networking	2,250.00	I	N/A	
S ➤	SW0052A	Private ISDN Networking	500.00	I	N/A	
S ➤	SW0052D	Private ISDN Networking	500.00	I	N/A	
S ➤	SW0053A	Public ISDN Access	800.00	I	N/A	
S ➤	SW0053B	Public ISDN Access	800.00	I	N/A	
S ➤	SW0055A	Network Attendant Services	2,500.00	I	N/A	
S ➤	SW0057A	Virtual Network Service	800.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SW0059B	Network Message Services	1,100.00	I	N/A	
S ➤	SW0060A	Basic Hospitality	250.00	I	N/A	
S ➤	SW0060B	Basic Hospitality	250.00	I	N/A	
S ➤	SW0061B	Advanced Hospitality/PMSI	800.00	I	N/A	
S ➤	SW0062A	Hospitality Voice Services	1,500.00	I	N/A	
S ➤	SW0064A	Meridian MAX MQA Option for Enhanced and Virtual Software (Release 8)	No charge		N/A	
S ➤	SW0071A	Meridian MAX-SNN or MAX-SNNE 100-Agent Increment for Meridian MAX Releases 6, 7, and 8	3,000.00	D	N/A	
S ➤	SW0072A	Meridian MAX One-Time LAN Connectivity Fee for Release 6	750.00	D	N/A	
S ➤	SW0073A	Meridian MAX LAN Connectivity Software for Release 6 (Available in Increments of 1-59)	600.00	D	N/A	
S ➤	SW0074A	Meridian MAX MTE One-Time Enable Fee for Release 6	1,000.00	D	N/A	
S ➤	SW0081A	8-Channel Asynchronous I/O Software Support for Meridian MAX Releases 6, 7, and 8 (MAX-SNN and MAX-SNNE)	1,500.00	D	N/A	
S ➤ Δ	SW0083A	Meridian MAX-SNN Release 5 to 6 Base Software Upgrade (200 Agents)	No charge		N/A	
S ➤	SW0085A	Meridian MAX Release 3 or 4 on Option 1 or 2 to MAX-SEE 6 Upgrade (160 Agents)	5,000.00	D	N/A	
S ➤ Δ	SW0086A	Meridian MAX SEE Release 5 to 6 Software Upgrade (160 Agents)	No charge		N/A	
S ➤ Δ	SW0087A	Meridian MAX Release 5 to MAX-IPE Release 6 Base Software Upgrade	No charge		N/A	
S ➤	SW0093A	Meridian MAX-SNN Release 7 Fundamental to Enhanced Software Option Upgrade	20,000.00	D	N/A	
S ➤	SW0093B	Meridian MAX-SNN and MAX-SNNE Release 8 Fundamental to Enhanced Software Option Upgrade	35,000.00	D	N/A	
S ➤	SW0094A	Meridian MAX-SNN Release 7 Enhanced to Virtual Software Option Upgrade	15,000.00	D	N/A	
S ➤	SW0094B	Meridian MAX-SNN and MAX-SNNE Release 8 Enhanced to Virtual Software Option Upgrade	20,000.00	D	N/A	
S ➤	SW0096A	Meridian MAX-IPE Release 7 Fundamental to Enhanced Option Upgrade	7,500.00	D	N/A	
S ➤	SW0096B	Meridian MAX-IPE or MAX-IPEE Release 8 Fundamental to Enhanced Software Option Upgrade	12,500.00	D	N/A	
S ➤	SW0097A	Meridian MAX-IPE Release 7 Enhanced to Virtual Option Upgrade	5,000.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SW0097B	Meridian MAX-IPE or MAX-IPEE Release 8 Enhanced to Virtual Software Option Upgrade	5,000.00	D	N/A	
S ➤	SW0098A	Meridian MAX MSI Option for Virtual Software (Release 7)	No charge		N/A	
S ➤	SW0101B	Basic Rate Interface	500.00	I	N/A	
S ➤	SW0101C	Basic Rate Interface	500.00	I	N/A	
S ➤	SW0102A	Meridian 1 Packet Handler	2,000.00	I	N/A	
S ➤	SW0104A	Q.Sig ISDN Networking Software	2,500.00	I	N/A	
S ➤	SW0104B	Q.Sig ISDN Networking Software	2,500.00	I	N/A	
S ➤	SW0105A	ISDN Q.Sig Supplementary Services	500.00	I	N/A	
S ➤	SW0110A	2.0 MB DTI/PRI Networking	250.00	I	N/A	
S ➤	SW0150A	Recorded Announcement Broadcast	400.00	I	N/A	
S ➤	SW0155A	Music Broadcast	140.00	I	N/A	
S ➤	SW0165A	Emergency Services Access (ESA) Enhanced Services	2,500.00	I	N/A	
S ➤	SW0170A	Call Pilot Connectivity	No charge		No charge	H
S † ➤	SW0201B	Basic ACD Features	300.00	I	N/A	
S † ➤	SW0202C	Advanced ACD Features	900.00	I	N/A	
S † ➤	SW0203B	ACD Reports Feature	1,925.00	I	N/A	
S † ➤	SW0204A	ACD Load Management (ACD-C2)	700.00	I	N/A	
S † ➤	SW0205A	ACD Link (MAX/ACD-D)	300.00	I	N/A	
S † ➤	SW0206A	ACD D/MAX Report Enhancements	300.00	I	N/A	
S † ➤	SW0207A	Enhanced ACD Overflow	900.00	I	N/A	
S † ➤	SW0208A	ACD Timed Overflow	300.00	I	N/A	
S † ➤	SW0209A	Network ACD	6,250.00	I	N/A	
S † ➤	SW0210A	Enhanced ACD Routing	900.00	I	N/A	
S † ➤	SW0211A	Enhanced Call Treatment	3,850.00	I	N/A	
S ➤	SW0221B	ACD/Message Processing	2,000.00	I	N/A	
S ➤	SW0221C	ACD/Message Processing	2,000.00	I	N/A	
S ➤	SW0222A	Enhanced ACD Overflow	No charge		N/A	
S ➤	SW0223A	Enhanced ACD Routing	800.00	I	N/A	
S ➤	SW0224A	Enhanced Call Center Management	2,250.00	I	N/A	
S ➤	SW0225B	Enhanced Call Center Routing	1,700.00	I	N/A	
S ➤	SW0226A	Call Center Networking	5,000.00	I	N/A	
S ➤	SW0227A	Hold in Queue for IVR	No charge		N/A	
S ➤	SW0228A	CCR-NACD Interworking	5,000.00	D	N/A	
S ➤	SW0229A	Meridian 911	4,000.00	I	N/A	
S ➤	SW0229C	Meridian 911	4,000.00	I	N/A	
S ✓ ➤	SW0229D	Meridian 911	50,000.00	I	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SW0230A	Multiple Queue Assignment	1,500.00	I	N/A	
S ➤	SW0234A	Electronic Brandlining - Display Customization	250.00	I	N/A	
S ➤	SW0251A	Meridian Link Module Software	2,000.00	I	N/A	
S † ➤	SW0300C	Basic ISDN Features	550.00	I	N/A	
S † ➤	SW0301A	Primary Rate Access	2,500.00	I	N/A	
S † ➤	SW0302A	ISDN Signaling Link	1,925.00	I	N/A	
S † ➤	SW0303B	Advanced ISDN Features	550.00	I	N/A	
S † ➤	SW0304B	Inter-Exchange Carrier/In-Band ANI	900.00	I	N/A	
S † ➤	SW0305A	Call by Call Service	900.00	I	N/A	
S † ➤	SW0306A	Network Message Services	1,400.00	I	N/A	
S ➤	SW0352A	Meridian MAX MQA Option for Virtual Software (Release 7)	No charge		N/A	
S † ➤	SW0401A	Auxiliary Processor Link	300.00	I	N/A	
S † ➤	SW0402A	IVMS Link	1,100.00	I	N/A	
S † ➤	SW0403A	Meridian Mail Link	300.00	I	N/A	
S † ➤	SW0406C	Meridian Link Module Software	3,300.00	I	N/A	
S † ➤	SW0407A	Meridian Hospitality Voice Services Features	1,650.00	I	N/A	
S † ➤	SW1037A	Meridian Manager Replacement Package	420.00	D	N/A	
S ➤	SW1121E	General Business Software (Add. 100 TNs)	2,000.00	I	N/A	
S ➤	SW1122E	Enhanced Business Software (Add. 100 TNs)	3,500.00	I	N/A	
S ➤	SW1126D	Enterprise Business Software (Add. 100 TNs)	6,500.00	I	N/A	
S ➤	SW1127D	NAS Software (Add. 100 TNs)	7,500.00	I	N/A	
S ➤	SW1131E	General Business Software Update	3,000.00	I	N/A	
S ➤	SW1132E	Enhanced Business Software Update	4,500.00	I	N/A	
S ➤	SW1141D	Enterprise Business Software Update	7,500.00	I	N/A	
S ➤	SW1142D	NAS Software Update	8,500.00	I	N/A	
S ➤	SW7004B	Hospitality Voice Services Software	2,200.00	D	N/A	
S ➤	SW7007	Secured Messaging Software	2,200.00	D	N/A	
S ➤	SW7008	Network Message Service Software	11,000.00	D	N/A	
S ➤	SW7008B	Network Message Services Prime Site Software, Release 11 and Later	5,000.00	D	N/A	
S ➤	SW7009D	AdminPlus Enable Option	2,000.00	D	N/A	
S ➤	SW7010B	Meridian Mail Networking/Enterprise Networking	2,200.00	D	N/A	
S ➤	SW7023	Meridian Mail Additional Language	600.00	D	N/A	
S ➤	SW7024	Meridian Mail Dual Language Prompt	No charge		N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SW7030E	Meridian Mail ACCESS Enable Option	No charge		N/A	
S ➤	SW7035C	Meridian Mail AMIS Networking (Virtual Node)	5,000.00	D	N/A	
S ➤	SW7040D	Meridian Mail Voice Forms	2,000.00	D	N/A	
S ➤	SW7041G	Meridian Mail Multi-Customer	500.00	D	N/A	
S ➤	SW7042B	Meridian Mail AMIS Open Networking	3,000.00	D	N/A	
S ➤	SW7043	Meridian Mail Multiple Administration	500.00	D	N/A	
S ➤	SW7049	Meridian Mail Expanded Storage Software Level 1-2	7,500.00	D	N/A	
S ➤	SW7050	Meridian Mail Migration	No charge		N/A	
S ➤	SW7054	Meridian Mail Expanded Storage Software Level 2-3	7,500.00	D	N/A	
S ➤	SW7055	Meridian Mail Expanded Storage Software Level 3-4	7,500.00	D	N/A	
S ➤	SW7056	Meridian Mail Expanded Storage Software Level 4-5	10,000.00	D	N/A	
S ➤	SW7057B	Meridian Mail Fax on Demand Software	5,000.00	D	N/A	
S ➤	SW7058	Meridian Mail Outcalling	No charge		N/A	
S ➤	SW7059	Meridian Mail Expanded Storage Software Level 5-6	10,000.00	D	N/A	
S ➤	SW7060	Meridian Mail SMDI Software	5,000.00	D	N/A	
S ➤	SW7061	Meridian Mail SMDI Connections Software	No charge		N/A	
S ➤	SW7062	Meridian Mail GP Multi-SMDI Software	3,000.00	D	N/A	
S ➤	SW7065	Meridian Mail Basic to Full Service per Port Software Upgrade	2,300.00	D	N/A	
S ➤	SW7068	Network Message Services Remote Site Software, Release 11	2,000.00	D	N/A	
S ➤	SW7072	Meridian Mail VMUIF	100.00	D	N/A	
S ➤	SW7074	Meridian Mail AutoAdmin Link Software	2,500.00	D	N/A	
S ➤	SW7102	Meridian Mail Card Option Expanded Storage Software Level 1-2	1,500.00	D	N/A	
S ➤	SW7103	Meridian Mail Card Option Expanded Storage Software Level 2-3	3,000.00	D	N/A	
S ➤	SW7104B	Meridian Mail Option 11 Fax on Demand Software	2,500.00	D	N/A	
S ➤	SW7109	Meridian Mail Option 11 Additional Language	600.00	D	N/A	
S ➤	SW7110	Meridian Mail Option 11 Dual Language Prompt	No charge		N/A	
B ➤	SW7111B	Meridian Mail Option 11 HVS Software	1,100.00	D	N/A	
S ➤	SW7112B	Meridian Mail Option 11 Networking Software, Release 11 or Later	2,200.00	D	N/A	
S ➤	SW7113D	Meridian Mail Option 11 Voice Forms	2,000.00	D	N/A	
S ➤	SW7114F	Meridian Mail Option 11 Multi-Customer	500.00	D	N/A	
S ➤	SW7115B	Meridian Mail Option 11 AMIS Networking	4,000.00	D	N/A	
S ➤	SW7116	Meridian Mail Option 11 Network Message Service Software	5,000.00	D	N/A	
S ➤	SW7117C	Meridian Mail Option 11 ACCESS Enable Option	No charge		N/A	
S ➤	SW7118	Meridian Mail AdminPlus Enable Option	800.00	D	N/A	
S ➤	SW7119	Meridian Mail Option 11 AutoAdmin Link Software	1,500.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	SW7121	Meridian Mail Option 11 Outcalling	No charge		N/A	
S ➤	SW7122	Meridian Mail Option 11 VMUIF	100.00	D	N/A	
S ➤	SW7123	Meridian Mail Option 11 Network Message Services, Prime Site, Release 11 and Later	3,000.00	D	N/A	
S ➤	SW7124	Meridian Mail Option 11 Network Message Services, Remote Site, Release 11 and Later	2,000.00	D	N/A	
S ➤	SW7140	Meridian Mail Card Option Expanded Storage Software Level 3-4	3,000.00	D	N/A	
S ➤	SW7151	Meridian Mail Card Option Basic to Full Service License Fee Upgrade	1,550.00	D	N/A	
S ➤	SW7307A	Meridian Link Release 5C Software	2,800.00	D	N/A	
S ➤	SW7413A	Customer Controlled Routing Release 3C with 240 Active Associations Software and Documentation Package	19,000.00	D	N/A	
S ➤	SW7414A	Customer Controlled Routing Release 3C with Twenty (20) Active Scripts Software Documentation Package	9,500.00	D	N/A	
S ➤	SW7415A	Customer Controlled Routing Release 3C from 20 to 240 Active Scripts Software Upgrade Package	15,000.00	D	N/A	
S ➤	SW7416A	Customer Controlled Routing Release 3C with 240 Active Associations Software Upgrade Package	3,000.00	D	N/A	
S ➤	SW7417A	Meridian Link Release 5C Software Upgrade	1,250.00	D	N/A	
S ➤	SW7426	Network Administration Center Release 2.5 Base Software Package	31,000.00	D	N/A	
S ➤	SW7427	Network Administration Center Release 2.5 Base Software Upgrade	3,000.00	D	N/A	
S ➤	SW7460A	Meridian Link 5C & CCR 3C Co-Resident Software (240 scripts)	20,000.00	D	N/A	
S ➤	SW7461A	Meridian Link 5C & CCR 3C Co-Resident Software (20 scripts)	10,000.00	D	N/A	
S ➤	SW7464	Meridian Link & CCR Co-Resident AST/Agent Software Level	4,500.00	I	N/A	
S ➤	SW7505B	Meridian MAX Networking for Release 6	3,000.00	D	N/A	
S ➤	SW7511B	Meridian MAX-IPE or MAX-IPEE 20-Agent Software Increment for Releases 6, 7 and 8	2,000.00	D	N/A	
S ➤	SW7513A	Meridian MAX-IPE Premium Features for Release 6	3,500.00	D	N/A	
S ➤	SW7514B	Meridian MAX-IPE Release 4 to MAX-IPE Release 6 Base Software Upgrade	1,000.00	D	N/A	
S ➤	SW7525B	NAC (Release 2) Connectivity Enabler for Meridian MAX Releases 6 and 7	650.00	D	N/A	
S ➤	SW7525C	NAC Connectivity for Meridian MAX Release 8	No charge		N/A	
S ➤	SY1009A	Meridian 1 Option 51C System Package AC	16,000.00	I	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SY1009D	Meridian 1 Option 51C System Package DC	16,000.00	I	N/A	
S ➤	SY1016A	Option 61C System Package AC	24,000.00	I	N/A	
S ➤	SY1016D	Option 61C System Package DC	24,000.00	I	N/A	
S ➤	SY1025A	Meridian 1 Option 81C System Package AC	60,500.00	I	N/A	
S ➤	SY1025D	Meridian 1 Option 81C System Package DC	60,500.00	I	N/A	
S ➤	SY1222	Meridian Link & CCR-IPEE Module (Option 11)	12,500.00	D	N/A	
S ➤	SY1223	Meridian Link & CCR-IPEE Module (Option 21-81C)	12,500.00	D	N/A	
S ➤	SY7020A	Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/ 200 Hour Package AC	11,000.00	D	N/A	
S ➤	SY7020D	Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/ 200 Hour Package DC	11,000.00	D	N/A	
S ➤	SY7021A	Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/ 200/400 Hour Package AC	22,000.00	D	N/A	
S ➤	SY7021D	Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/ 200/400 Hour Package DC	22,000.00	D	N/A	
S ➤	SY7022A	Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package AC	30,000.00	D	N/A	
S ➤	SY7022D	Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package, DC	30,000.00	D	N/A	
S ➤	SY7023A	Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/ 300/600 Hour Package AC	39,000.00	D	N/A	
S ➤	SY7023D	Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/ 300/600 Hour Package DC	39,000.00	D	N/A	
S ➤	SY7024A	Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/ 400/800 Hour Package AC	46,000.00	D	N/A	
S ➤	SY7024D	Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/ 400/800 Hour Package DC	46,000.00	D	N/A	
S ➤	SY7075D	Enhanced Meridian Mail Modular GP 4-12 Port 11/24/36/54/100/ 200 Hours Package DC	11,000.00	D	N/A	
S ➤	SY7076D	Enhanced Meridian Mail Modular GP 16-24 Port 26/54/84/114/ 200/400 Hours Package DC	22,000.00	D	N/A	
S ➤	SY7077D	Enhanced Meridian Mail Modular GP 28-32 Port 30/60/90/120/ 200/400 Hours Package DC	30,000.00	D	N/A	
S ➤	SY7078D	Enhanced Meridian Mail Modular GP 36-48 Port 45/90/120/180/ 300/600 Hours Package DC	40,000.00	D	N/A	
S ➤	SY7079D	Enhanced Meridian Mail Modular GP 52-64 Port 60/120/180/ 240/400/800 Hours Package DC	46,000.00	D	N/A	
S ➤	SY7210	Enhanced Meridian Mail EC11 8-24 Port, 11/24/36/54/100/200 Hour Package	2,900.00	D	N/A	
S ➤	SY7211	Enhanced Meridian Mail EC11 24-48 port, 26/54/84/114/200/400 Hour Package	15,100.00	D	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤	SY7412	Customer Controlled Routing Release 3 High Capacity Hardware Package	10,250.00	D	N/A	
S ➤	SY7421A	Meridian NAC, Release 2.5 Base System Hardware Platform, AC	30,000.00	D	N/A	
S ➤	SY7421D	Meridian NAC Release 2.5 Base System Hardware Platform, DC	30,000.00	D	N/A	
S ➤	U7014A	Meridian Mail Migration to Modular Option Prime Node, 300MB Package AC	8,000.00	D	N/A	
S ➤	U7014D	Meridian Mail Migration to Modular Option Prime Node, 300MB Package DC	8,000.00	D	N/A	
S ➤	U7015A	Meridian Mail Migration to Modular Option Voice Node, 300MB Package AC	6,000.00	D	N/A	
S ➤	U7015D	Meridian Mail Migration to Modular Option Voice Node, 300MB Package DC	6,000.00	D	N/A	
S ➤	U7016A	Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package AC	8,000.00	D	N/A	
S ➤	U7016D	Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package DC	8,000.00	D	N/A	
S ➤	U7017A	Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package AC	6,000.00	D	N/A	
S ➤	U7017D	Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package DC	6,000.00	D	N/A	
S ➤	U7018001	Meridian Mail EC11 to EC Migration 4-24 Port AC Package	6,500.00	D	N/A	
S ➤	U7018002	Meridian Mail EC11 to EC Migration 4-24 Port DC Package	6,500.00	D	N/A	
S ➤	U7018003	Meridian Mail EC11 to EC Migration 28-48 Port AC Package	11,000.00	D	N/A	
S ➤	U7018004	Meridian Mail EC11 to EC Migration 28-48 Port DC Package	11,000.00	D	N/A	
S ➤	U7068D	Meridian Mail Migration to Modular Option GP Prime Node, 300MB Package DC	8,000.00	D	N/A	
S ➤	U7069D	Meridian Mail Migration to Modular Option GP Voice Node, 300MB Package DC	7,000.00	D	N/A	
S ➤	U7070	Meridian Mail Migration to Modular Option GP Prime Node, 600MB/1GB Package DC	8,000.00	D	N/A	
S ➤	U7071D	Meridian Mail Migration to Modular Option GP Voice Node, 600MB/1GB Package DC	7,000.00	D	N/A	
S ➤	U7202	Meridian Mail Modular EC 2GB Disk Drive Upgrade	1,500.00	D	N/A	
S ➤	U7203	Meridian Mail Modular EC 2GB Disk Drive with Power Upgrade	2,000.00	D	N/A	
S ➤	U7207	Meridian Mail Modular Option 2GB Disk Drive Upgrade	1,500.00	D	N/A	
S ➤	U7600A	Meridian NAC Release 2.5 Base Hardware Upgrade Package, AC	20,000.00	D	N/A	
S ➤	U7600D	Meridian NAC Release 2.5 Base Hardware Upgrade Package, DC	20,000.00	D	N/A	

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S † ➤	U9620	Connector Mounting Kit	160.00	I	N/A	
S ➤	U9639A	Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/ 21A/21/21E Upgrade Package AC	24,000.00	I	N/A	
S ➤	U9639D	Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/ 21A/21/21E Upgrade Package DC	24,000.00	I	N/A	
S ➤	U9640	Option 61C from Option 61 Cardcage Upgrade Package AC/DC	16,500.00	I	N/A	
S ➤	U9641A	Option 61C from Option 51 Upgrade Package AC	18,000.00	I	N/A	
S ➤	U9641D	Option 61C from Option 51 Upgrade Package DC	18,000.00	I	N/A	
S ➤	U9643A	Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package AC	16,000.00	I	N/A	
S ➤	U9643D	Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package DC	16,000.00	I	N/A	
S ➤	U9644A	Option 51C from Option 21/21E Cardcage Upgrade Package AC	16,000.00	I	N/A	
S ➤	U9644D	Option 51C from Option 21/21E Cardcage Upgrade Package DC	16,000.00	I	N/A	
S ➤	U9645	Option 51C from Option 51 Cardcage Upgrade Package AC/DC	8,500.00	I	N/A	
S ➤	U9646A	Option 61C from Option 51C Upgrade Package AC	10,500.00	I	N/A	
S ➤	U9646D	Option 61C from Option 51C Upgrade Package DC	10,500.00	I	N/A	
S ➤	U9650A	Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/ XT/71 Core and Network Upgrade Package AC	60,500.00	I	N/A	
S ➤	U9650D	Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/ XT/71 Core and Network Upgrade Package DC	60,500.00	I	N/A	
S ➤	U9651A	Option 81C from XN/XT/71 Core Upgrade Package AC (Dual Column)	38,000.00	I	N/A	
S ➤	U9651D	Option 81C from XN/XT/71 Core Upgrade Package DC (Dual Column)	38,000.00	I	N/A	
S ➤	U9652	Option 81C from Option 71 Card Cage Upgrade Package AC/DC	25,000.00	I	N/A	
S ➤	U9653A	Option 81C from XN/XT/71 Core Upgrade Package AC (Single Column)	38,000.00	I	N/A	
S ➤	U9653D	Option 81C from XN/XT/71 Core Upgrade Package DC (Single Column)	38,000.00	I	N/A	
S ➤	U9654A	Option 81C from Option 61C Upgrade (Package #1) AC	34,000.00	I	N/A	
S ➤	U9654D	Option 81C from Option 61C Upgrade (Package #1) DC	34,000.00	I	N/A	
S ➤	U9655A	Option 81C from Option 61C Upgrade (Package #2) AC	39,500.00	I	N/A	
S ➤	U9655D	Option 81C from Option 61C Upgrade (Package #2) DC	39,500.00	I	N/A	
S ➤	U9656A	Option 81C from Option 61C Upgrade (Package #3) AC	44,000.00	I	N/A	
S ➤	U9656D	Option 81C from Option 61C Upgrade (Package #3) DC	44,000.00	I	N/A	
S ➤	U9657	Option 81C from Option 81 Card Cage Upgrade Package AC/DC	25,000.00	I	N/A	
S ➤	U9658A	Option 81C from Option 61 (Modular) Upgrade Package AC	48,500.00	I	N/A	
S ➤	U9658D	Option 81C from Option 61 (modular) Upgrade Package DC	48,500.00	I	N/A	
S Δ	V006-12	Meridian Mail Release 12 Feature Operations Video	95.00	H	N/A	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.
S ➤ Δ	V008	Combination: Meridian Mail Overview and Meridian Mail Feature Operations Videos	125.00	H	N/A	
B #	X0645393	1GB Disk Drive	MD		1,000.00	H

✓	Revision from Last Issue	§	New system sale only	>>	Available until stock depleted
★	New product introduction	†	Additions & maintenance	➤	See reference book
⊗	Controlled release	#	Manufacture discontinued	Δ	Distr butor discount category only
S	Santa Clara	N	Nashville	B	Both order locations

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Status	Order Code	Description	CLP	Distr. Disc.	Repair CLP	Distr. Disc.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Manufacture discontinued

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
101SL1-1	Additional Shelf (Memory) Assembly	
102SL1-1	Additional Shelf (Network) Assembly	
103SL1-1	Additional CPU Assembly	
104SL1-1	Additional Shelf (Network) Assembly	
105SL1-1	Option Group 88, Meridian Digital Telephones (S, ST, MS, M)	
106SL1-1	Option Group 89, Meridian M3000 Touchphone (S, ST, MS, M)	
107SL1-1	PRA Packaged Assembly	AS1063
108SL1-1	PRA Packaged Assembly	AS1061
111SL1-1	Pre-Packaged SL-1LE System (100 Lines, 10 CO Trunks, 1 Digit Display	
112SL1-1	Pre-Packaged SL-1LE ACD System (32 Agent Lines, 40 ACD Trunks, Dual CPU)	
113SL1-1	Pre-Packaged SL-1LE System (100 Lines, 10 CO Trunks, 1 Digit Display	
114SL1-1	SL-1LE High Reliability Package (Generic 305)	
115SL1-1	SL-1LE High Traffic Package	
116SL1-1	Pre-Packaged SL-1LE ACD System (32 Agents, 40 Trunks, and Single CPU)	
117SL1-1	High Reliability Package (Generic 309/311)	
118SL1-1	Pre-Packaged SL-1LE Tandem System (8 Lines, 30 Trunks, Single CPU)	
119SL1-1	PRA Packaged Assembly	AS1062
123SL1-1	Option Group 88, Meridian Digital Telephones (LE, N, NT, RT)	
124SL1-1	Option Group 88, Meridian Digital Telephones (VLE, XL, XN, XT)	
125SL1-1	Option Group 89, M3000 Touchphone (LE, N, NT, RT)	
126SL1-1	Option Group 89, Meridian M3000 Touchphone (VLE, XL, XN, XT)	
128SL1-1	Pre-Packaged SL-1LE Hotel/Motel System (96 Lines, 12 Trunks, Digitone,	
129SL1-1	SL-1LE Hotel/Motel CE Expansion Package	
130SL1-1	Pre-packaged SL-1LE Hotel/Motel System	
131SL1-1	Network Group Assembly	
132SL1-1	Option Group 86, Multi-Tenant Service (S, ST, MS, M)	
133SL1-1	Option Group 86, Multi-Tenant Service (LE, N, NT, RT)	
134SL1-1	Option Group 86, Multi-Tenant Service (VLE, XL, XN, XT)	
140SL1-1	Pre-Packaged SL-1N System (104 Lines, 10 CO Trunks, 1 Digit Display	
141SL1-1	Pre-Packaged SL-1N System (104 Lines, 10 CO Trunks, 1 Digit Display	
142SL1-1	Pre-Packaged SL-1N ACD System (32 Agent Lines, 40 ACD Trunks, Single	
143SL1-1	Pre-Packaged SL-1N ACD System (32 Agent Lines, 40 ACD Trunks, Single	
144SL1-1	Pre-packaged SL-1N Tandem System (8 Lines, 30 Trunks, Single CPU, Half	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
146SL1-1	Pre-Packaged SL-1NT System	SY1153
147SL1-1	Pre-Packaged SL-1NT ACD System	SY1153
148SL1-1	SL-1N CE Expansion Package (Single CPU/Half Network Group to Dual	
150SL1-1	SL-1S Special Software Feature Package I	
151SL1-1	SL-1S Special Software Feature Package I	
153SL1-1	Pre-Packaged SL-1S Hotel/Motel System {32 (500/2500) Message Waiting	
154SL1-1	Pre-Packaged SL-1S System {32 (500/2500) Lines, 8 Trunks, Digitone,	
155SL1-1	Pre-Packaged SL-1S System {16 (500/2500) Lines, 16 (SL-1) Lines, 8	
156SL1-1	Pre-Packaged SL-1S System {56 (500/2500) Lines, 12 Trunks, Digitone, 1 Console	
157SL1-1	Pre-Packaged SL-1S System {32 (500/2500) Lines, 24 (SL-1) Lines, 12	
158SL1-1	Pre-Packaged Executive SL-1S {40 (SL-1) Lines, 8 Trunks, 1 Console, 36	
160SL1-1	CDR Cabinet Assembly (Single Port)	
161SL1-1	CDR Cabinet Assembly	
162SL1-1	SL-1S Battery Backup Assembly	
163SL1-1	Pre-Packaged SL-1MS (120 Lines, 20 Trunks, Digitone, 1 Console)	
164SL1-1	Pre-Packaged SL-1MS (180 Lines, 28 Trunks, Digitone, 1 Console)	
165SL1-1	Basic SL-1MS	
166SL1-1	Pre-Packaged SL-1MS (80 Lines, 16 Trunks, Digitone, 1 Console)	
167SL1-1	Pre-Packaged SL-1MS Hotel/Motel System (56 Lines, 12 Trunks, Digitone,	
168SL1-1	Pre-Packaged SL-1MS ACD System (16 Terminal Lines, 20 ACD Trunks, 16	
169SL1-1	Pre-Packaged SL-1S (56 Lines, 12 Trunks, Digitone, 1 Console)	
171SL1-1	SL-1S Special Software Feature Package II	
172SL1-1	SL-1S Special Software Feature Package III	
173SL1-1	SL-1MS Special Software Feature Package II	
174SL1-1	SL-1MS Special Software Feature Package III	
175SL1-1	VL/VLE CE CPU Cabinet Upgrade Assembly	
176SL1-1	Option Group 76, Departmental LDN (S, ST, MS, M)	
177SL1-1	Option Group 76, Departmental LDN (LE, N, NT, RT)	
178SL1-1	Option Group 76, Departmental LDN (VLE, XL, XN, XT)	
180SL1-1	CE Network Cabinet Assembly	
181SL1-1	Network Group Assembly	
182SL1-1	SL-1S Hotel/Motel Software Package	
183SL1-1	SL-1MS Hotel/Motel Software Package	
185SL1-1	VL to VLE/XL Network Group Upgrade Assembly	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
186SL1-1	Pre-Packaged Sl-1MS Hotel/Motel System(120 Lines, 20 Trunks, Digitone,	
187SL1-1	Pre-Packaged SL-1MS Hotel/Motel System (180 Lines, 28 Trunks, Digitone,	
188SL1-1	Pre-Packaged SL-1S Hotel/Motel System {48 (500/2500) Message Waiting	
190SL1-1	L(Single CPU)/LE(Dual CPU) Upgrade Assembly	
191SL1-1	L/LE Upgrade Assembly (Single CPU/Half Network Group)	
192SL1-1	SL-1A/LE Upgrade Assembly (Single CPU/Half Network)	
193SL1-1	Pre-Packaged SL-1S 8x32 Digital System {8 CO Trunks, 24 Digital Lines	
194SL1-1	Pre-Packaged SL-1S 8x32 SL-1 System {8 CO Trunks, 24 SL-1 Lines (23 SL-1	
195SL1-1	L(Dual CPU)/LE(Dual CPU) Upgrade Assembly	
196SL1-1	Option Group 83, ACD/CDR Q Record (S, ST, MS, M)	
197SL1-1	Option Group 83, ACD/CDR Q Record (LE, N, NT, RT)	
198SL1-1	Option Group 83, ACD/CDR Q Record (VLE, XL, XN, XT)	
200SL1-1	PE Cabinet #1 Assembly	
201SL1-1	SL-1ST/RT Expansion Tier Package-1 Shelf	
202SL1-1	4 Port SDI Assembly - EMI	
203SL1-1	Triple SDI Cable Assembly - EMI	
204SL1-1	SL-1ST PE Expansion Assembly - One Shelf (with MDF Assembly)	
205SL1-1	PE Cabinet Assembly	
206SL1-1	PE Cabinet Assembly	
207SL1-1	4 Port SDI Assembly	
210SL1-1	PE Cabinet #2 Assembly	
212SL1-1	Transfer Unit Assembly - EMI	
213SL1-1	Full Featured Software Package	
214SL1-1	Full Featured Software Package	
215SL1-1	PE Cabinet #2 Assembly	
216SL1-1	Full Featured Software Package	
217SL1-1	Basic Software Package	
218SL1-1	Basic Software Package	
219SL1-1	Basic Software Package	
223SL1-1	Resale-of-Services Software Package	
224SL1-1	Resale-of-Services Software Package	
225SL1-1	IMS/Omnifacts Standard Configuration	
226SL1-1	IMS/Omnifacts Standard Configuration	
227SL1-1	Resale-of-Services Software Package	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
229SL1-1	Multi Protocol Communications Controller (MPCC)	
230SL1-1	Connector Housing/SDI Cover Plate Bracket Assembly	
231SL1-1	SL-1 Integrated Voice & Data Station Demonstrator Package	
232SL1-1	SL-1 Integrated Voice & Data Station Demonstrator Retrofit Package	
234SL1-1	LE/N Shelf Upgrade Assembly (Dual CPU)	
235SL1-1	LE/N Cabinet Upgrade Assembly (Dual CPU)	
238SL1-1	VLE or XL/XN Network Group Upgrade Assembly (Shelf Basis)	
239SL1-1	VL, VLE or XL/XN Network Group Upgrade Assembly (Cabinet Basis)	
241SL1-1	Cabinet Panel Upgrade Assembly (Single Bay Cabinet)	
242SL1-1	Cabinet Panel Upgrade Assembly (Double Bay Cabinet)	
243SL1-1	Cabinet Panel Upgrade Assembly (CDR Cabinet)	
244SL1-1	DTI Packaged Assembly	
245SL1-1	L or LE/N CE Shelf Expansion Assembly	
246SL1-1	Single Port SDI Assembly-EMI (CDR)	
247SL1-1	Dual Port SDI Assembly - EMI	207SL1-1
248SL1-1	Transfer Unit Assembly-EMI	
249SL1-1	L or LE/N CE Cabinet Expansion Assembly	
250SL1-1	SL-1S PE Shelf Assembly	
251SL1-1	SL-1S Power Fail Transfer Assembly	
252SL1-1	SL-1S Prepackage Software	
255SL1-1	SL-1S Console Assembly	718SL1-1
256SL1-1	LE/N Shelf Upgrade Assembly (Single CPU)	
257SL1-1	LE/N Cabinet Upgrade Assembly (Single CPU)	
258SL1-1	Option Group 30, PMS Interface (HIS) (S, MS)	
259SL1-1	Option Group 30, PMS Interface (HIS) (LE)	
260SL1-1	Option Group 30, PMS Interface (HIS) (VLE, XL)	
278SL1-1	SL-1ST PE Expansion Assembly-First Shelf	
280SL1-1	SL-1ST Console Assembly	
281SL1-1	DTI Packaged Assembly	
282SL1-1	Option 11 0531 22 Mbyte Add-On Disk Drive (MVC01477)	
285SL1-1	Option 14 80 column 120 CPS Model 6182 (MVC01480) Desktop Printer	
286SL1-1	Option 3	
287SL1-1	SL-1ST Memory Expansion Assembly	
290SL1-1	Option 1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
291SL1-1	Option 2	
293SL1-1	Option 4	
299SL1-1	Option 7	
300SL1-1	Peripheral Shelf Assembly	
301SL1-1	Peripheral Shelf Assembly	344SL1-1
302SL1-1	Option Group 75, PBX Interface (LE, N, NT, RT)	
303SL1-1	Option Group 75, PBX Interface (VLE, XL, XN, XT)	
304SL1-1	Peripheral Shelf Assembly-EMI	
305SL1-1	Option Group 75, PBX Interface (MS, ST)	
306SL1-1	Option Group 35, Callers Name Display (S, MS)	
307SL1-1	Option Group 35, Callers Name Display (LE)	
308SL1-1	Option Group 35, Callers Name Display (VLE, XL)	
309SL1-1	CND Applications Package	
310SL1-1	Basic Program: Generic 737 (M)	
311SL1-1	Basic Program: Generic 337 (LE)	
312SL1-1	Basic Program: Generic 437 (VLE)	
313SL1-1	Basic Program: Generic 637 (XL)	
314SL1-1	Complete Hotel/Motel Package (MS, M)	
315SL1-1	Complete Hotel/Motel Package (LE)	
316SL1-1	Complete Hotel/Motel Package (VLE, XL)	
317SL1-1	Hotel/Motel Package (Basic) (MS, M)	
318SL1-1	Hotel/Motel Package (Basic) (LE)	
319SL1-1	Hotel/Motel Package (Basic) (VLE, XL)	
320SL1-1	Option Group 31, Message Registration (S, MS, M)	
321SL1-1	Option Group 31, Message Registration (LE)	
322SL1-1	Option Group 31, Message Registration (VLE, XL)	
323SL1-1	Option Group 32, 5-Digit Dialing (S, MS, M)	
324SL1-1	Option Group 32, 5-Digit Dialing (LE)	
325SL1-1	Option Group 32, 5-Digit Dialing (VLE, XL)	
326SL1-1	Option Group 33, Call Park (S, MS, M)	
327SL1-1	Option Group 33, Call Park (LE)	
328SL1-1	Option Group 33, Call Park (VLE, XL)	
329SL1-1	Option Group 34, Supervisory Console (S, MS, M)	
330SL1-1	Option Group 34, Supervisory Console (LE)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
331SL1-1	Option Group 34, Supervisory Console (VLE, XL)	
332SL1-1	Option Group 36, Recorded Overflow Announcement (S, MS, M)	
333SL1-1	Option Group 36, Recorded Overflow Announcement (LE)	
334SL1-1	Option Group 36, Recorded Overflow Announcement (VLE, XL)	
335SL1-1	Option Group 49, New Flexible Code Restriction (S, MS, N)	
336SL1-1	Option Group 49, New Flexible Code Restriction (LE)	
337SL1-1	Option Group 49, New Flexible Code Restriction (VLE, XL)	
338SL1-1	Option Group 53, Controlled Class of Service (S, MS, M)	
339SL1-1	Option Group 53, Controlled Class of Service (LE)	
340SL1-1	Option Group 53, Controlled Class of Service (VLE, XL)	
344SL1-1	Peripheral Shelf Assembly	
345SL1-1	Option Group 56, Flexible Hotline (S, MS, M)	
346SL1-1	Option Group 56, Flexible Hotline (LE)	
347SL1-1	Option Group 56, Flexible Hotline (VLE, XL)	
350SL1-1	Option Group 35 & 109, IMS Software (S, ST, MS, M)	
351SL1-1	Option Group 35 & 109, IMS Software (LE, N, NT, RT)	
352SL1-1	Option Group 35 & 109, IMS Software (VLE, XL, XN, XT)	
360SL1-1	IMS Single Attendant (Omninote software)	
361SL1-1	IMS Multi-Attendant (Omninote software)	
370SL1-1	Single-Attendant SL-1M/MS Total Software Package	
371SL1-1	Single-Attendant SL-1LE/N Total Software Package	
372SL1-1	Single-Attendant SL-1VLE/XL/XN Total Software Package	
373SL1-1	Multi-Attendant SL-1M/MS Total Software Package	
374SL1-1	Multi-Attendant SL-1LE/N Total Software Package	
375SL1-1	Multi-Attendant SL-1VLE/XL/XN Total Software Package	
400SL1-1	Pre-Packaged SL-1ST Hotel/Motel System (200 Lines)	SY1151
401SL1-1	SL-1ST Hotel/Motel Software Package	SW0017A
402SL1-1	Pre-Packaged SL-1NT Hotel/Motel System (500 Lines)	SY1153
403SL1-1	Network Assembly	
404SL1-1	SL-1NT Hotel/Motel Software Package	SW0018A
409SL1-1	64K Memory Module Assembly	
410SL1-1	Option Group 65 & 84, Automatic Trunk Maintenance (S, ST, MS, M)	
411SL1-1	Option Group 65 & 84, Automatic Trunk Maintenance (LE, N, NT, RT)	
412SL1-1	Option Group 65 & 84, Automatic Trunk Maintenance (VLE, XL, XN, XT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
413SL1-1	Option Group 81, Controlled Class of Service (S, ST, MS, M)	
414SL1-1	Option Group 81, Controlled Class of Service (LE, N, NT, RT)	
415SL1-1	Option Group 81, Controlled Class of Service (VLE, XL, XN, XT)	
416SL1-1	Option Group 80, Station Category Indication (S, ST, MS, M)	
417SL1-1	Option Group 80, Station Category Indication (LE, N, NT, RT)	
418SL1-1	Option Group 80, Station Category Indication (VLE, XL, XN, XT)	
420SL1-1	Complete Hotel/Motel Program SL-1M (707) (M)	
421SL1-1	Basic Hotel/Motel Program SL-1M (707) (M)	
422SL1-1	Option Group 31, Message Registration (M)	
423SL1-1	Option Group 33, System Park (M)	
424SL1-1	Option Group 37, Automatic Wake-Up (M, S, MS)	
425SL1-1	Option Group 38, Room Status (M, S, MS)	
426SL1-1	Option Group 39, History File (M)	
430SL1-1	Option Group 33, Call Park (S, ST)	
431SL1-1	Option Group 34, System Speed Call (S, ST)	
432SL1-1	Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (S, ST)	
433SL1-1	Option Group 22, Direct Inward System Access (DISA) (S, ST)	
434SL1-1	Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (S, ST)	
435SL1-1	Option Group 74, Distinctive Ringing (S, ST)	
436SL1-1	Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (S, ST)	
437SL1-1	Option Group 41, 44, Automatic Call Distribution (ACD) Package B (S,ST)	
438SL1-1	Option Group 42, Automatic Call Distribution (ACD) Package C1 (S,ST)	
439SL1-1	Option Group 43, Automatic Call Distribution (ACD) Package C2 (S,ST)	
440SL1-1	Option Group 33, Call Park (MS, M)	
441SL1-1	Option Group 33, Call Park (LE, N, NT, RT)	
442SL1-1	Option Group 33, Call Park (VLE, XL, XN, XT)	
443SL1-1	Option Group 34, System Speed Call (MS. M)	
444SL1-1	Option Group 34, System Speed Call (LE, N, NT, RT)	
445SL1-1	Option Group 34, System Speed Call (VLE, XL, XN, XT)	
446SL1-1	Option Group 36, Recorded Overflow Announcement (S, ST, MS, M)	
447SL1-1	Option Group 36, Recorded Overflow Announcement (LE, N, NT, RT)	
448SL1-1	Option Group 36, Recorded Overflow Announcement (VLE, XL, XN, XT)	
449SL1-1	Option Group 49 & 32, New Flexible Code Restriction Package (S, ST, MS, M)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
450SL1-1	Option Group 49 & 32, New Flexible Code Restriction Package (LE, N, NT, RT)	
451SL1-1	Option Group 49 & 32, New Flexible Code Restriction Package (VLE, XL, XN, XT)	
452SL1-1	Option Group 4, 5 & 31	
460SL1-1	Option Group 24, 25 & 63, Network Authorization Code (S, ST)	
461SL1-1	Option Group 4, 5 & 30	
462SL1-1	Option Group 4, 6 & 30	
463SL1-1	Option Group 4, 5, 6 & 30	
464SL1-1	Option Group 28 & 62, Off-Hook Queuing (S, ST)	
465SL1-1	Option Group 14, 28, 32, 58 & 61, NARS (S, ST)	
466SL1-1	Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (S, ST)	
467SL1-1	Option Group 37 & 32, ESN Signaling (S, ST)	
468SL1-1	Option Group 38, ESN Queuing (CBQCM, CCBQ) (S, ST)	
469SL1-1	Option Group 39, Network Speed Call (S, ST)	
470SL1-1	Option Group 67, Network Transfer (S, ST)	
471SL1-1	Option Group 90, Last Number Redial (S, ST, MS, M)	
472SL1-1	Option Group 90, Last Number Redial (LE, N, NT, RT)	
473SL1-1	Option Group 90, Last Number Redial (VLE, XL, XN, XT)	
474SL1-1	Option Group 93, Supervisory Console (S, ST, MS, M)	
475SL1-1	Option Group 93, Supervisory Console (LE, N, NT, RT)	
476SL1-1	Option Group 93, Supervisory Console (VLE, XL, XN, XT)	
477SL1-1	Option Group 92, Pretranslation (S, ST, MS, M)	
478SL1-1	Option Group 92, Pretranslation (LE, N, NT, RT)	
479SL1-1	Option Group 92, Pretranslation (VLE, XL, XN, XT)	
480SL1-1	Option Group 7, 17, 19, 40, 41, 42, 43, 44, 45, 50 & 51	
481SL1-1	Option Group 7,17,19,40,41,42,43,44,45,50 & 51	
482SL1-1	Automatic Call Distributor (ACD) Package D Software for PDP 11/23 Plus	
484SL1-1	Automatic Call Distribution (ACD) Package D Software for PDP 11/44	
495SL1-1	ACD-D Basic Software Package (for Meridian SL-1 MS/ST)	
498SL1-1	ACD-D Basic Software Package (for Meridian SL-1 LE/N/NT)	
499SL1-1	ACD-D Basic Software Package (for Meridian SL-1 XL/XN/NT)	
500SL1-1	Complete H/M Program: Generic 507 (A)	
501SL1-1	Basic H/M Program X07: Generic 507 (A)	
502SL1-1	Option Group 31, Message Registration (A)	
503SL1-1	Option Group 33, System Park (A)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
504SL1-1	Option Group 37, Automatic Wake-Up (A)	
505SL1-1	Option Group 38, Room Status (A)	
506SL1-1	Option Group 64, Stored Number Redial (S, ST, MS, M)	
507SL1-1	Option Group 64, Stored Number Redial (LE, N, NT, RT)	
508SL1-1	Option Group 64, Stored Number Redial (VLE, XL, XN, XT)	
510SL1-1	Complete H/M Program: Generic 307 (LE)	
511SL1-1	Basic H/M Program X07: Generic 307 (LE)	
512SL1-1	Option Group 31, Message Registration (LE)	
513SL1-1	Option Group 33, System Park (LE)	
514SL1-1	Option Group 37, Automatic Wake-Up (LE)	
515SL1-1	Option Group 38, Room Status (LE)	
520SL1-1	Complete H/M Program: Generic 407 (VLE)	
521SL1-1	Basic H/M Program: Generic 407 (VLE)	
522SL1-1	Option Group 31, Message Registration (VLE)	
52310	Voice Messaging 8	
52311	Voice Messaging 16	
52323	Directory Services	
52330	Meridian Mail Option 8	
52331	Meridian Mail MP Option 16	
52332	Meridian Mail MP Option 36	
52333	Meridian Mail MP Option 48	
523SL1-1	Option Group 33, System Park (VLE)	
52410	Meridian connection	
52420	X.25 Gateway	
52430	LSPC Terminal Emulator	
52431	LANSTAR MSNET	
52450	Meridian Mail SP 5 Software	
52451	Meridian Mail SP 11 Software	
52452	Meridian Mail SP 24 Software	
52453	SP 5 to 11 Storage Expansion Software (Expands 5 to 11 Hours)	
52454	SP 11 to 24 Storage Expansion Software (Order with U9100 Upgrade)	
524SL1-1	Option Group 37, Automatic Wake-Up (VLE, XL)	
52500	Meridian Mail SL-1 Option	
52501	Meridian Mail Option	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
52502	Meridian Mail Option	
52503	Meridian Mail Option	
52504	Meridian Mail Option	
525SL1-1	Option Group 38, Room Status (VLE, XL)	
52600	Meridian Mail Option (Option and ST/RT Option) Base Software	
52601	Meridian Mail Option (Option and ST/RT Option) 5 Hour Software	
52602	Meridian Mail Option (Option and ST/RT Option) 5 to 11 Hours Software	
52603	Meridian Mail Option (Option and ST/RT Option) Expanded Storage Software	
52610	Meridian Mail Release 3 to 4 Software service transaction fee	
526SL1-1	Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (LE, N, NT, RT)	
527SL1-1	Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (VLE, XL, XN, XT)	
528SL1-1	Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (LE, N, NT, RT)	
529SL1-1	Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (VLE, XL, XN, XT)	
530SL1-1	Option Group 18, 2500 Set Features (Call Forward, Hold, Speed Call) (LE)	
531SL1-1	Option Group 18, 2500 Set Features (Call Forward, Hold, Speed Call) (VLE)	
532SL1-1	Option Group 46, Basic Message Center (LE, N, NT, RT)	
533SL1-1	Option Group 46, Basic Message Center (VLE, XL, XN, XT)	
534SL1-1	Option Group 41 and 44, Automatic Call Distribution (ACD) Package B (M, MS)	
535SL1-1	Option Group 41 and 42, Automatic Call Distribution (ACD) Package C1 (M,MS)	
536SL1-1	Option Group 43, Automatic Call Distribution (ACD) Package C2 (M,MS)	
537SL1-1	Option Group 44, Music Package (S, MS, M, ST)	
538SL1-1	Option Group 46, Basic Message Center (S, MS, M, ST)	
539SL1-1	Option Group 52, CDR Forced Charge Account (S, MS, M, ST)	
542SL1-1	Basic Program: Generic 737 (M)	
543SL1-1	Complete Hotel/Motel Package (S)	
544SL1-1	Hotel/Motel Package (Basic) (S)	
545SL1-1	Basic Program: Generic 711	
546SL1-1	Option Group 1, Advanced Station Features (S)	
547SL1-1	Option Group 18, 2500 Set Features (S, ST)	
548SL1-1	Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (S, ST)	
549SL1-1	ACD MAX Software New Release Charge	
550SL1-1	Option Group 1, Advanced Station Features (A, M, MS)	
551SL1-1	Option Group 2, Multi-Customer (A, M, S, MS, ST)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
552SL1-1	Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (A, M, MS)	
553SL1-1	Option Group 4 & 6	
554SL1-1	Option Group 4, 5 & 6	
555SL1-1	Option Group 14, Automatic Route Selection (ARS) (A, M, S, MS)	
556SL1-1	Option Group 22, Direct Inward System Access (DISA) (A, MS, M)	
557SL1-1	Option Group 24 & 25, Authorization Code (A, S, MS, M, ST)	
558SL1-1	Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (A, S, MS, M)	
559SL1-1	Option Group 7, 17, 40, & 45, Automatic Call Distribution (ACD) Package A (A, MS, M)	
561SL1-1	OMNIFACTS Basic Capability (Generic 4002)	
562SL1-1	OMNIFACTS Option 1 Enhanced Reports	
563SL1-1	OMNIFACTS Full Featured (Generic 4004)	
569SL1-1	OMNIFACTS Resale of Services (Hobic) (Generic 4005)	
571SL1-1	OMNIFACTS Stand-Alone Automated Directory Look-up (ADLU) (Generic 4008)	
573SL1-1	OMNIFACTS Option 2 Automated Directory Look-Up (ADLU)	
575SL1-1	Factory Data Base (CDR) Set-Up (Optional)	
57600	Meridian Mail SP Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 77, 85)	
57635	Meridian Mail SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 75, 77, 85)	
577SL1-1	OMNIFACTS V&H Coordinate/Costing Module Updates (CDR)	
578SL1-1	OMNIFACTS Application Software Maintenance (Single)	
57935	Meridian Message Center SL-1 Special Software Pkg (7,17,35,109,40,45,46)	
579SL1-1	OMNIFACTS Application Software Maintenance (Multi)	
580SL1-1	Basic Program: Generic 711	
581SL1-1	Basic Program: Generic 311	
582SL1-1	Basic Program: Generic 411	
583SL1-1	Basic Program: Generic 611	
58600	Meridian Mail SP Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 77, 85)	
58635	Meridian Mail SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 75, 77, 85)	
586SL1-1	Option Group 4 & 31	
587SL1-1	Option Group 53, Automatic Set Relocation (S, ST, M, MS)	
588SL1-1	Option Group 53, Automatic Set Relocation (LE, N, NT, RT)	
58935	Meridian Message Center SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46)	
589SL1-1	Option Group 53, Automatic Set Relocation (VLE, XL, XN, XT)	
590SL1-1	Option Group 54, Attendant Administration (S, ST, MS, M)	
591SL1-1	Option Group 54, Attendant Administration (LE, N, NT, RT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
592SL1-1	Option Group 54, Attendant Administration (VLE, XL, XN, XT)	
593SL1-1	Option Group 55, History File (N, NT, RT, XN, XT, LE, VLE, XL)	
594SL1-1	Option Group 56, Attendant Overflow Position (S, ST, MS, M)	
595SL1-1	Option Group 56, Attendant Overflow Position (LE, N, NT, RT)	
59600	Meridian Mail SP Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 77, 85)	
59635	Meridian Mail SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 75, 77, 85)	
596SL1-1	Option Group 56, Attendant Overflow Position (VLE, XL, XN, XT)	
597SL1-1	Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (M, MS)	
598SL1-1	Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (S, ST, MS, M)	
59935	Meridian Message Center SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46)	
60001	Meridian Mail MP Voice Menus Option	
60002	Meridian Mail Common Software Voice Menus Software	
60003	Right to Use Fee/Meridian Mail MP Access Software	
60005	Ready to Use Fee/Meridian Mail PC Software	
60006	Meridian Mail Networking Option	
60008	Access API Ver. 1 Software License	
60010	Meridian Mail Common Software Networking Software	
60013	Meridian Mail Common Software Secured Messaging Software	
60014	Meridian Mail Guest Voice Messaging Software	
60020	Meridian Mail Tape Prep Fee	SERV0018
600SL1-1	Option Group 2, Multi-Customer (L, LE, N, NT, RT)	
601SL1-1	Basic Program: Generic 104/504	
602SL1-1	Option Group 1, Advanced Station Features (L, LE, N, NT, RT)	
603SL1-1	Basic Program: Generic 204	
604SL1-1	Option Group 2, Multi-Customer (VLE, VL, XL, XN, XT)	
605SL1-1	Option Group 1, Advanced Station Features (VL, VLE, XL, XN, XT)	
606SL1-1	Option Group 15, Remote Peripheral Equipment (RPE) (L, LE, N, NT, RT)	
607SL1-1	Option Group 4 & 6	
608SL1-1	Option 4 & 6	
609SL1-1	Option Group 3 Automatic Identification of Outward Dial (AIOD)	
610SL1-1	Option Group 14, Automatic Route Selection (ARS) (L, LE)	
611SL1-1	Option Group 12, Automatic Number Identification (ANI) (L, LE, N, NT, RT)	
612SL1-1	Option Group 3 Automatic Identification of Outward Dial (AIOD)	
613SL1-1	Option Group 14, Automatic Route Selection (ARS) (VL, VLE, XL)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
614SL1-1	Option Group 12, Automatic Number Identification (ANI) (VL, VLE, XL, XN, XT)	
615SL1-1	Option Group 15, Remote Peripheral Equipment (RPE) (VL, VLE, XL, XN, XT)	
618SL1-1	Option Group 7, Recorded Announcement (L, LE)	
619SL1-1	Option Group 7, Recorded Announcement (VL, VLE, XL)	
620SL1-1	Option Group 8	
621SL1-1	Option Group 8	
622SL1-1	Option Group 10	
623SL1-1	Option Group 10	
624SL1-1	Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (L, LE, N, NT, RT)	
625SL1-1	Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (VLE, VL, XL, XN, XT)	
626SL1-1	Option Group 4, 5 & 6	
627SL1-1	Option Group 4, 5 & 6	
628SL1-1	Option Group 9 & 16, Do-Not-Disturb (DND) Group (L, LE, N, NT, RT)	
629SL1-1	Option Group 9 & 16, Do-Not-Disturb (DND) Group (VL, VLE, XL, XN, XT)	
63010	Meridian Mail Release 4 to 5 Software Service Fee	
63011	Meridian Mail Release 3 to 5 Software Service Fee	
63012	Meridian Mail Release 5 to 6 Software Service Fee	63022
63013	Meridian Mail Release 4 to 6 Software Service Fee	63021
63014	Meridian Mail Release 3 to 6 Software Service Fee	63020
63018	SMDI Software	SW7060
63019	Meridian Mail Card Option Release 6 to Release 8 Software Update Fee	U7250
63020	Meridian Mail Release 3 to Release 8 Software Update Fee	
63021	Meridian Mail Release 4 to Release 8 Software Update Fee	63016
63021	Meridian Mail Release 4 to Release 8 Software Update Fee	63024
63022	Meridian Mail Release 5 to Release 8 Software Update Fee	63028
63022	Meridian Mail Release 5 to Release 8 Software Update Fee	63029
63022	Meridian Mail Release 5 to Release 8 Software Update Fee	63030
63023	Meridian Mail Release 6 to Release 8 Software Update Fee	63031
63023	Meridian Mail Release 6 to Release 8 Software Update Fee	63032
63024	Meridian Mail Release 7 to Release 8 Software Update Fee	63033
63024	Meridian Mail Release 7 to Release 8 Software Update Fee	63034
63024	Meridian Mail Release 7 to Release 8 Software Update Fee	63035
63025	Meridian Mail Card Option Release 8 to Release 9 Software Update Fee	63041
63026	Meridian Mail Card Option Release 6 to Release 9 Software Update Fee	63019

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
63026	Meridian Mail Card Option Release 6 to Release 9 Software Update Fee	63041
63027	Meridian Mail Release 8 to Release 9 Software Update Fee, EC	63046
63028	Meridian Mail Release 5 to Release 8 Software Update Fee, Options	63017
63029	Meridian Mail Release 5 to Release 8 Software Update Fee, Modular Option	63017
63030	Meridian Mail Release 5 to Release 8 Software Update Fee, GP	63017
63032	Meridian Mail Release 6 to Release 8 Software Update Fee, Modular Option	63043
63034	Meridian Mail Release 7 to Release 8 Software Update Fee, Modular Option	63044
63035	Meridian Mail Release 7 to Release 8 Software Update Fee, GP	63044
63036	Meridian Mail Release 6/7 to 9 Software Update, Options	63043
63037	Meridian Mail Release 6/7 to 9 Software Update, Modular Option	63044
63038	Meridian Mail Release 8 to 9 Software Update, Options	63048
63039	Meridian Mail Release 8 to 9 Software Update, Modular Option	63047
63040	Meridian Mail Release 8 to 9 Software Update, Modular Option GP	63049
63041	Meridian Mail Card Option Release 8 to Release 10 Software Update Fee	63056
63042	Meridian Mail Card Option Release 9 to Release 10 Software Update Fee	63056
63043	Meridian Mail Release 6/7 to Release 10 Software Update Fee, Options	
63044	Meridian Mail Release 6/7 to Release 10 Software Update Fee, Modular Option	63060
63046	Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option EC	63057
63047	Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option	63058
63048	Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option GP	63059
63049	Meridian Mail Release 8 to Release 10 Software Update Fee, Options (ST/RT, NT/ XT)	
63050	Meridian Mail Option X Cabinet Base Software	
63051	Meridian Mail Option X Cabinet Expanded Storage Software	
63052	Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option EC	63057
63053	Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option	63058
63054	Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option GP	63059
63055	Meridian Mail Release 9 to Release 10 Software Update Fee, Options (ST/RT, NT/ XT)	
63056	Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Card Option	U7251
63057	Meridian Mail Release 8, 9 or 10 to Release 11 Migration, Options, Modular Option to Modular EC	63062
63058	Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Modular Option	U7216
63059	Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Modular Option GP	U7234

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
63061	Meridian Mail Release 10 to Release 11 Software Update Fee, EC11	U7260
63062	Meridian Mail Release 8, 9, 10, or 11 to Release 12 Migration, Options, Modular Option to Modular EC	
630SL1-1	Option Group 13, Route Selection for ANI (L, LE, N, NT, RT)	
631SL1-1	Option Group 13, Route Selection for ANI (VL, VLE, XL, XN, XT)	
632SL1-1	Option Group 47, Automatic Handsfree Answerback (A, S, MS, M, ST)	
633SL1-1	Option Group 48, Group Call (A, S, MS, M, ST)	
634SL1-1	Basic Program: Generic 304	
635SL1-1	Basic Program: 404	
638SL1-1	Option Group 19	
639SL1-1	Option Group 19	
640SL1-1	Option Group 19	
641SL1-1	Option Group 19	
642SL1-1	Option Group 32, Message Waiting (LE)	
643SL1-1	Option Group 32, Message Waiting (VLE)	
644SL1-1	Option Group 47, Automatic Handsfree Answerback (L, LE, N, NT, RT)	
645SL1-1	Option Group 48, Group Call (L, LE, N, NT, RT)	
646SL1-1	Option Group 17	
647SL1-1	Option Group 17	
648SL1-1	Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (L, LE)	
649SL1-1	Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (VL, VLE, XL)	
650SL1-1	Option Group 24 & 25, Authorization Code (L, LE, N, NT, RT)	
651SL1-1	Option Group 24 & 25, Authorization Code (VL, VLE, XN, XT, XL)	
652SL1-1	Option Group 21, Dial Intercom (L, LE, N, NT, RT)	
653SL1-1	Option Group 21, Dial Intercom (VL, VLE, XN, XT, XL)	
654SL1-1	Option Group 22, Direct Inward System Access (DISA) (L, LE, N, NT, RT)	
655SL1-1	Option Group 22, Direct Inward System Access (DISA) (VL, XN, XT, VLE, XL)	
656SL1-1	Option Group 18, 2500 Set Features (A, MS, M)	
657SL1-1	Option Group 18, 2500 Set Features (VL, VLE, XL, XN, XT)	
658SL1-1	Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (L, LE, N, NT, RT)	
659SL1-1	Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (VL, VLE, XN, XT, XL)	
660SL1-1	Option Group 26, Centralized Attendant Service (CAS Main) (L, LE, N, NT, RT)	
661SL1-1	Option Group 26, Centralized Attendant Service (CAS Main) (VL, VLE, XN, XT, XL)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
662SL1-1	Option Group 27, Centralized Attendant Service (CAS Remote) (L, LE, N, NT, RT)	
663SL1-1	Option Group 27, Centralized Attendant Service (CAS Remote) (VL, VLE, XN, XT, XL)	
664SL1-1	Basic Program: Generic 314 (Autovon)	
665SL1-1	Basic Program: Generic 414	
666SL1-1	Option Group 23 & 24, CDR Charge Account Code (L, LE, N, NT, RT)	
667SL1-1	Option Group 23 & 24, CDR Charge Account Code (VL, VLE, XN, XT, XL)	
668SL1-1	Basic Program: Generic 105/305	
669SL1-1	Basic Program: Generic 205/405	
670SL1-1	Option Group 7, 17, 40, 41, 44 and 45, Automatic Call Distribution Package B (LE, N, RT, NT)	
671SL1-1	Option Group 7, 17, 40, 41, 44 and 45, Automatic Call Distribution Package B (VLE, XL, XN, XT)	
672SL1-1	Option Group 44, Music Package (LE, N, NT, RT)	
673SL1-1	Option Group 44, Music Package (VLE, XL, XN, XT)	
674SL1-1	Option Group 20, Office Data Administration System (ODAS) (A, M, S, MS, ST)	
675SL1-1	Option Group 20, Office Data Administration System (ODAS) (L, LE, N, NT, RT)	
676SL1-1	Option Group 47, Automatic Handsfree Answerback (VL, VLE, XN, XT, XL)	
677SL1-1	Option Group 48, Group Call (VL, VLE, XN, XT, XL)	
678SL1-1	Option Group 20, Office Data Administration System (ODAS) (VL, VLE, XL, XN, XT)	
680SL1-1	Option Group 42, Automatic Call Distribution (ACD) Package C1 (LE, N, RT, NT)	
681SL1-1	Option Group 42, Automatic Call Distribution (ACD) Package C1 (VLE, XL, XN, XT)	
683SL1-1	Option Group 18, 2500 Set Features (L, LE, N, NT, RT)	
684SL1-1	Basic Program: Generic 609	
685SL1-1	Basic Program: Generic 309	
686SL1-1	Basic Program: Generic 409	
687SL1-1	Option Group 43, Automatic Call Distribution (ACD) Package C2 (LE, N, RT, NT)	
688SL1-1	Option Group 43, Automatic Call Distribution (ACD) Package C2 (VLE, XL, XN, XT)	
690SL1-1	Option Group 40 & 46, Message Center (L, LE, N, NT, RT)	
691SL1-1	Option Group 40 & 46, Message Center (VL, VLE, XN, XT, XL)	
692SL1-1	Basic Program: Generic 505	
693SL1-1	Option Group 52, CDR Forced Charge Account (LE, N, NT, RT)	
694SL1-1	Option Group 52, CDR Forced Charge Account (VLE, XL, XN, XT)	
706SL1-1	Local Network Interface Assembly	NT7R51AB

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
707SL1-1	Remote Network Interface Assembly	AS1094A
707SL1-1	Remote Network Interface Assembly	AS1094D
707SL1-1	Remote Network Interface Assembly	AS1095A
707SL1-1	Remote Network Interface Assembly	AS1095D
707SL1-1	Remote Network Interface Assembly	NT7R52AB
710SL1-1	Local Carrier Shelf Assembly	NT7R51AB
711SL1-1	Remote Carrier Shelf Assembly	NT7R52AB
718SL1-1	M1250 Meridian SL-1 Attendant Console	
730SL1-1	Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (A, M, MS)	
731SL1-1	Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (L, LE, N, NT, RT)	
732SL1-1	Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (VL, VLE, XL, XN, XT)	
735SL1-1	Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (A, S, MS, M, ST)	
736SL1-1	Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (L, LE, N, NT, RT)	
737SL1-1	Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (VL, VLE, XN, XT, XL)	
739SL1-1	Option 15 - Agent Activity Code Report	
740SL1-1	Basic Program: Generic 811/1111/1311	
745SL1-1	Basic Program: Generic 911/1211	
746SL1-1	Option 11 - Additional VDT (17-32)	
747SL1-1	Option 12 - Additional Agents	
748SL1-1	Option 13 - DNIS Reporting	
749SL1-1	Option 14 - Custom Format Selection	
750SL1-1	Option 1 - Reporting Package	
753SL1-1	Option 4 - Staff Management Aid	
754SL1-1	Option 5 - Enhanced Status Display	
755SL1-1	Option 6 - Expanded Trunk Routes	
756SL1-1	Option 7 - Additional VDT (8-16)	
757SL1-1	Option 8 - Multi-Customer	
758SL1-1	Option 10 - Multi Printers	
759SL1-1	Option 9 - Enhanced Load Management	
766SL1-1	Option Group 70, Flexible Hotline (S, ST, MS, M)	
767SL1-1	Option Group 70, Flexible Hotline (LE, N, NT, RT)	
768SL1-1	Option Group 70, Flexible Hotline (VLE, XL, XN, XT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
769SL1-1	Option Group 71, Deluxe Hold (S, ST, MS, M)	
770SL1-1	Option Group 71, Deluxe Hold (LE, N, NT, RT)	
771SL1-1	Option Group 71, Deluxe Hold (VLE, XL, XN, XT)	
772SL1-1	Option Group 72, Automatic Line Selection (S, ST, MS, M)	
773SL1-1	Option Group 72, Automatic Line Selection (LE, N, NT, RT)	
774SL1-1	Option Group 72, Automatic Line Selection (VLE, XL, XN, XT)	
775SL1-1	Option Group 73, 500 Set Features (S, ST, MS, M)	
776SL1-1	Option Group 73, 500 Set Features (LE, N, NT, RT)	
777SL1-1	Option Group 73, 500 Set Features (VLE, XL, XN, XT)	
778SL1-1	Option Group 74, Distinctive Ringing (MS, M)	
779SL1-1	Option Group 74, Distinctive Ringing (LE, N, NT, RT)	
780SL1-1	Option Group 74, Distinctive Ringing (VLE, XL, XN, XT)	
790SL1-1	A/MS Shelf Upgrade Assembly	
795SL1-1	L/N Cabinet Upgrade Assembly (Single CPU)	
796SL1-1	L/N Cabinet Upgrade Assembly (Dual CPU)	
800SL1-1	SL-1ST Special Software Feature Package I	SW0000A
801SL1-1	SL-1ST Special Software Feature Package II	SW0000A
802SL1-1	SL-1ST Special Software Feature Package III	SW0202A
803SL1-1	SL-1ST Prepackage Software	SW0000A
810SL1-1	SL-1A to SL-1M Hardware Conversion Kit	
811SL1-1	M2000 Mac Pak	
812SL1-1	M3000 Mac Pak	
813SL1-1	Mac Direct-Connect Pak	
814SL1-1	PC Pak	
815SL1-1	LAN-Pak	
816SL1-1	ASCII Pak - Female	
817SL1-1	ASCII Pak-Male	
820SL1-1	PE Shelf Assembly-EMI "A"	
821SL1-1	PE Shelf Assembly-EMI "A & B"	
822SL1-1	Adapter Assembly-EMI	
823SL1-1	Power Shelf Assembly-EMI (QSD10)	
826SL1-1	Option Group 7, Recorded Announcement (A, M)	
827SL1-1	Option Group 9 & 16, Do-Not-Disturb (DND) Group (A, M, S, MS, ST)	
828SL1-1	Option Group 10	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
829SL1-1	Option Group 12, Automatic Number Identification (ANI) (A, M, S, MS, ST)	
830SL1-1	Option Group 15, Remote Peripheral Equipment (RPE) (A, M, MS, ST)	
831SL1-1	Option Group 17	
832SL1-1	Option Group 21, Dial Intercom (A, S, MS, M, ST)	
833SL1-1	Option Group 23 & 24, CDR Charge Account Code (A, S, MS, M, ST)	
834SL1-1	Option Group 26, Centralized Attendant Service (CAS Main) (A, S, MS, M, ST)	
835SL1-1	Option Group 27, Centralized Attendant Service (CAS Remote) (A, S, MS, M, ST)	
836SL1-1	Option Group 40 & 46, Message Center (A, S, MS, M, ST)	
837SL1-1	Option Group 55, History File (S, MS, M, ST)	
838SL1-1	Option Group 13, Route Selection for ANI (A, M, S, MS, ST)	
839SL1-1	Option Group 8	
840SL1-1	Option Group 32, Message Waiting (A)	
850SL1-1	Pre-Packaged SL-1M System (60 Lines, 10 Trunks, 1 Console/Digitone,	
851SL1-1	PE Cabinet Assembly	
852SL1-1	Pre-Packaged Basic SL-1M System (No Lines, Trunks, Digitone or	
853SL1-1	PERP "A" Shelf Assembly	
854SL1-1	SL-1M High Density PE Shelf Assembly (QCA37 Cabinet)	
855SL1-1	Complete Shelf Assembly (PERP A & B)	
856SL1-1	Network Assembly	
859SL1-1	Mini-CDR Package	
861SL1-1	Pre-Packaged SL-1ST 8x32 System with Digital Sets {8 CO Trunks, 24 SL-1	SY1151
862SL1-1	Pre-Packaged SL-1ST 8x32 System with SL-1 Sets {8 CO Trunks, 24 SL-1	SY1151
863SL1-1	Pre-Packaged SL-1ST (52 Lines, 12 Trunks, Digitone, 1 Console)	SY1151
864SL1-1	Pre-Packaged Flexible 8x32 SL-1ST	SY1151
865SL1-1	Pre-Packaged SL-1ST ACD System (16 Terminal Lines, 20 ACD Trunks, 16	SY1151
866SL1-1	SL-1ST/RT Expansion Tier Package- 2 Shelves	
867SL1-1	SL-1ST PE Expansion Assembly - Two Shelf (with MDF Assembly)	866SL1-1
868SL1-1	Dual Port SDI Assembly-EMI	202SL1-1
869SL1-1	SL-1ST/RT Cooling Unit Assembly	
871SL1-1	SL-1ST/RT CE/PE Expansion Tier Package	
872SL1-1	SL-1ST CE/PE Expansion Assembly (with MDF Assembly)	871SL1-1
875SL1-1	Built-In BIX MDF Assembly (for 863SL1-1 SL-1ST)	
876SL1-1	SL-1ST Environmental Improvement Assembly (For One and Two Tier SL-1ST)	
882SL1-1	SL-1 ST/RT Expansion Cabinet Assembly - One Shelf	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
883SL1-1	SL-1 ST/RT Expansion Cabinet Assembly - Two Shelf	
884SL1-1	RPE Cabinet Assembly - Remote (Network Carrier Shelf, 10 PE Card Slots,	
885SL1-1	RPE Cabinet Assembly - Remote (with MDF Assembly)	
886SL1-1	SL-1ST/RT Local RPE/PE Expansion Tier Package	
887SL1-1	Local RPE/PE Expansion Assembly (with MDF Assembly)	886SL1-1
888SL1-1	Remote RPE/PE Expansion Tier Package	
889SL1-1	Remote RPE Expansion Tier (with MDF Assembly)	888SL1-1
891SL1-1	M/MS CE Upgrade Assembly	
892SL1-1	SL-1 MS CE Shelf Expansion Assembly	
894SL1-1	Pre-packaged SL-1RT System	SY1152
895SL1-1	SL-1RT Business Software Feature Prepackage	SW0000A
896SL1-1	SL-1RT Health Care Software Feature Prepackage	SW0000A
900SL1-1	CE CPU Cabinet Assembly	
910SL1-1	VL/XL CE Upgrade Assembly	
920SL1-1	VLE/XL CPU Upgrade Assembly	
921SL1-1	Configuration Control Option Single Tower	
922SL1-1	Custom Calculator Option Single Tower	
923SL1-1	ACD MAX Networking Option Single Tower	
924SL1-1	Configuration Control Option Dual Tower	
925SL1-1	Custom Calculator Option Dual Tower	
926SL1-1	ACD MAX Networking Option Dual Tower	
930SL1-1	Option Group 14, 28, 32, 58 & 61, NARS (LE, N, NT, RT)	
931SL1-1	Option Group 14, 28, 32, 58 & 61, NARS (VLE, XL, XN, XT)	
932SL1-1	Option Group 14, 28, 32, 58 & 61, NARS (MS, M)	
933SL1-1	Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (LE, N, NT, RT)	
934SL1-1	Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (VLE, XL, XN, XT)	
935SL1-1	Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (MS, M)	
936SL1-1	Option Group 28 & 62, Off-Hook Queuing (LE, N, NT, RT)	
937SL1-1	Option Group 28 & 62, Off-Hook Queuing (VLE, XL, XN, XT)	
938SL1-1	Option Group 28 & 62, Off-Hook Queuing (MS, M)	
939SL1-1	Option Group 24, 25 & 63, Network Authorization Code (LE, N, NT, RT)	
940SL1-1	Option Group 24, 25 & 63, Network Authorization Code (VLE, XL, XN, XT)	
941SL1-1	Option Group 24, 25 & 63, Network Authorization Code (MS, M)	
942SL1-1	Option Group 4 & 30	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
943SL1-1	Option Group 4 & 30	
944SL1-1	Option Group 4 & 30	
950SL1-1	Option Group 39, Network Speed Call (LE, N, NT, RT)	
951SL1-1	Option Group 39, Network Speed Call (VLE, XL, XN, XT)	
952SL1-1	Option Group 39, Network Speed Call (MS, M)	
953SL1-1	Option Group 38, ESN Queuing (CBQCM, CCBQ) (LE, N, NT, RT)	
954SL1-1	Option Group 38, ESN Queuing (CBQCM, CCBQ) (VLE, XL, XN, XT)	
955SL1-1	Option Group 38, ESN Queuing (CBQCM, CCBQ) (MS, M)	
956SL1-1	Option Group 37 & 32, ESN Signaling (LE, N, NT, RT)	
957SL1-1	Option Group 37 & 32, ESN Signaling (VLE, XL, XN, XT)	
958SL1-1	Option Group 37 & 32, ESN Signaling (MS, M)	
959SL1-1	VLE/XN Cabinet Upgrade Assembly	
960SL1-1	CE Cabinet Assembly	
961SL1-1	Network Group Assembly	AS1027
961SL1-1	Network Group Assembly	AS1028
961SL1-1	Network Group Assembly	AS1029
962SL1-1	VLE/XN Shelf Upgrade Assembly	
963SL1-1	Network/PE Cabinet Assembly	
964SL1-1	Option Group 4,5 & 30	
965SL1-1	Option Group 4,6 & 30	
966SL1-1	Option Group 4,5,6 & 30	
967SL1-1	Option 4,5,30 & 31	
969SL1-1	Option Group 67, Network Transfer (MS, M)	
970SL1-1	Option Group 4,5 & 30	
971SL1-1	Option Group 4,6 & 30	
972SL1-1	Option Group 4,5,6 & 30	
974SL1-1	Option Group 67, Network Transfer (LE, N, NT, RT)	
975SL1-1	Option Group 4,5 & 30	
976SL1-1	Option Group 4,6 & 30	
977SL1-1	Option Group 4,5,6 & 30	
979SL1-1	Option Group 67, Network Transfer (VLE, XL, XN, XT)	
980SL1-1	XT CE Cabinet Assembly	SY1154
981SL1-1	768K RAM Assembly	
982SL1-1	CE/CPU Cabinet Assembly for Hotel/Motel-Dual CPU	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
983SL1-1	Network/PE Cabinet Assembly for Hotel/Motel	
984SL1-1	Network Group Assembly for Hotel/Motel	
985SL1-1	PE/PRI Cabinet Assembly	
A0110539	Circuit Breaker (CB2)	
A0239439	SL-1 Console Line Cord	
A0247602	Cable, Conn. (1 Ft.)	
A0247603	Cable, Connector (2 Ft.)	NT8D99AB
A0247604	Cable, Conn. (4 Ft.)	NT8D99AC
A0247605	Cable, Connector (10 Ft.)	
A0247606	Cable, Connector (15 Ft.)	
A0247607	Cable, Connector (20 Ft.)	QCAD124A
A0247632	Cable, Connector (25 Ft.)	
A0247633	Cable, Connector (30 Ft.)	
A0247634	Cable, Connector (35 Ft.)	
A0247635	Cable, Connector (40 Ft.)	
A0247636	Cable, Connector (45 Ft.)	
A0247644	Cable, Connector (5 Ft.) (QCB6A) (Tape Interface)	
A0247645	Cable, Connector (1.5 Ft.)	
A0247646	Cable, Connector (4 Ft.)	
A0253756	Cable, Connector (10 Ft.)	
A0253757	Cable, Connector (15 Ft.)	
A0253758	Cable, Connector (20 Ft.)	
A0253778	Cable, Conn. (6 Ft.) (M/M)	NT8D99AD
A0253779	Cable, Connector (6 Ft.)	
A0254746	Cable, Connector (25 Ft.)	
A0254763	Cable, Conn. (2 Ft.)	
A0254951	Line Cord (Silver) (13 Ft.) Spade/Spade (6 Conductor)	
A0256222	Cable, Connector (8 Ft.) (QCB6A) (Tape Interface)	
A0273211	Cord, Assembly RS232 ADM (6 In.) (Male/Female)	
A0273213	ADM Power Cord NE-M2QC (7 Ft.)	
A0274243	Handset Cord, 12 Ft. Ash (M2000 Series)	
A0274934	Jumper Pins	
A0283471	SL-1 Telephone Handset w/QUU1C Fluxcoil (QSU3)	
A0283540	SL-1 Telephone Handset	A0327147

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0283581	Handset Cord (Ash) (5.6 Ft.) Spade/Spade (4 Conductor)	
A0285536	15 Amp Circuit Breaker	
A0286116	Ribbon Cable (QSD31)	
A0287305	Fan, 8 VDC (NT2R23AA)	
A0291215	Connector Bail Lock Kit	
A0291605	Amplified Handset (Spade/Spade)	
A0292116	Hold Down Device	
A0293344	Line Cord/2-Conductor /7 Ft./Satin/Standard (M2000 Series and M3901)	
A0296006	SL-1 Displayphone (NT6K10AB)	
A0296738	Receiver Unit (SL-1 Handset)	
A0297075	Buffer Interface Converter (Room Status & Maid Status)	
A0297366	Filter Connector (25 Conductor) (EMI)	
A0297963	Relay Rack (23 In. x 7 Ft.)	
A0297998	Transformer Power 5/12V QMT11	
A0298000	Caster (Basic Cabinet)	
A0298626	Protocol Convertor-ASCII SNA/SDLC	
A0298627	Protocol Convertor-ASCII SNA/SDLC	
A0298628	Protocol Convertor-ASCII SNA/SDLC	
A0298629	Protocol Convertor-ASCII SNA/SDLC	
A0298634	Protocol Convertor-ASCII BISC 110V	
A0298635	Protocol Convertor-ASCII BISC 110V	
A0298636	Protocol Convertor-ASCII BISC 220V	
A0298637	Protocol Convertor-ASCII BISC 220V	
A0298638	Protocol Convertor-ASCII SNA/SDLC	
A0298639	Protocol Converter-ASCII SNA/SDLC	
A0298640	Protocol Convertor SNA/SDLC SL-174	
A0298641	Protocol Converter SNA/SDLC SL-174	
A0299899	Line Cord/2-Conductor/14 Ft./Satin, (M2000 Series and M3901)	
A0301005	Line Cord (7 Ft.)	
A0302358	212 A/O Modem	
A0310198	SL-1 Displayphone (NT6K10AC)	
A0310532	SL-1 Displayphone (NT6K10AD)	
A0315068	Displayphone 3270 Keycap Kit	
A0317073	System Matrix Printer	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0319032	SLX25-108A X.25 Gateway (PAD) 8 Ports 110V	
A0319033	SLX25-116A X.25 Gateway (PAD) 16 Ports 110V	
A0320897	DEC 320 Terminal	A0376839
A0321130	Fan Unit - Option 21A	
A0322433	Protocol Converter - ASCII to SNA/SDLC 110V Desk Mount	
A0322434	Protocol Converter - ASCII to SNA/SDLC 110V Rack Mount	
A0322435	Protocol Converter - ASCII SNA/SDLC 220V Desk Mount	
A0322436	Protocol Converter - ASCII SNA/SDLC 220V Rack Mount	
A0324084	5-1/4 In. Floppy Diskette	
A0325663	SL-1 Displayphone (NT6K10AE)	
A0325987	CND Applications Software	
A0326595	Protocol Converter - ASCII to Bisynchronous 110V Desk Mount	
A0326596	Protocol Converter - ASCII to Bisynchronous 110V Rack Mount	
A0326597	Protocol Converter - ASCII to Bisynchronous 220V Desk Mount	
A0326598	Protocol Converter - ASCII to Bisynchronous 220V Rack Mount	
A0326760	Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC)	
A0326766	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 110V Desk Mount	
A0326767	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 110V Rack Mount	
A0326768	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 220V Desk Mount	
A0326769	Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 220V Rack Mount	
A0326775	212 A Modem	
A0326800	Power Supply	
A0327123	Handset Cord/12 Ft./Gray, (M2000 Series)	
A0327130	Handset Cord/12 Ft./Black, (M2000 Series)	
A0327146	Handset, Modular	
A0327147	Handset Cord (5 Ft. 6 In.) Spade/Spade	
A0329160	Transmitter Unit (SL-1 Handset)	
A0329723	8-Port Communications Controller Board	
A0329748	DataBase 2 Modem	
A0329944	INMAC Null Modem	
A0329960	Rack 24 Balun	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0336822	Coax Interface Module and ASIM Power Supply	
A0336834	Meridian SL-1 Laser Printer Installation Package	
A0336854	43MB Server/2MB RAM (SA112)	
A0336855	70MB Server/2MB RAM (SA122)	
A0336856	120MB Server/2MB RAM (SA132)	
A0336857	157MB Server/4MB RAM (SA144)	
A0336858	70MB Disk ST506 (SA210) Expansion Drive	
A0336859	120MB Disk ST506 (SA211) Expansion Drive	
A0336860	157MB Disk ST506 (SA212) Expansion Drive	
A0336861	BNS/DTS 2MB Memory (SA241) Expansion Board	
A0336862	BNS/CNS Server Console (SA260)	
A0336863	BNS 4 Drive Capacity (BNX544) 2 157 MB Disk	
A0336864	BNS 8 Drive Capacity (BNX548) 4 157 MB Disk	
A0336865	BNS 4MB Memory (SA242) Expansion Board	
A0336866	BNS 20 Line Serial (BNS290) Communications Option (Factory Installed)	
A0336867	BNS 20 Line Serial (BNS291) Communications Option (Field Installed)	
A0336868	52MB Server/2MB RAM (DTS212)	
A0336869	80MB Server/3MB RAM (DTS223)	
A0336901	146MB Server/3MB RAM (DTS233)	
A0336902	DTS Server Console (SA261)	
A0336903	DTS 3 Drive Capacity (EXP220) 1 80 MB Disk	
A0336904	DTS 3 Drive Capacity (EXP230) 1 146 MB Disk	
A0336905	DTS Uninterruptible (UPS120) Power Supply (UPS) (120V)	
A0336906	DTS Uninterruptible (UPS240) Power Supply (UPS) (240V)	
A0336907	UPS Control Cable (DTS285)	
A0336908	4-Line Serial Communications Adapter (NM100)	
A0336909	Bisynchronous Serial Communications Adapter (NM115)	
A0336910	X.25 Communications Adapter (NM127)	
A0336911	52MB (formatted) SCSI (EXP110) Expansion Disk Drive	
A0336912	RS232 Modem Cable (NM120)	
A0336913	Cartridge Tape - 4MB (AA100)	
A0336914	Cartridge Tape - 60MB (AA101)	
A0336915	80MB (formatted) SCSI (EXP120) Expansion Disk Drive	
A0336916	146MB (formatted) SCSI (EXP130) Expansion Disk Drive	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0336917	VINES/286 Software (VNS286R4)	
A0336918	Banyan Mail (PA100)	
A0336919	Remote Asynchronous Dial-In (NA100)	
A0336920	Network Management (NM130)	
A0336922	Asynchronous Terminal Emulation with File Transfer (HA101)	
A0336923	Kermit File Transfer (HA102)	
A0336924	IBM 3270/SNA Emulation-32 (SNA100)	
A0336925	IBM 3270/SNA Emulation-64 (SNA101)	
A0336926	IBM 3270/SNA Emulation-96 (SNA102)	
A0336927	IBM 3270/SNA Emulation-16 (SNA103)	
A0336928	IBM 3270/BSC Emulation-32 (BSC100)	
A0336929	IBM 3270/BSC Emulation-64 (BSC101)	
A0336930	Server-to-Server/LAN Software (IM100)	
A0336931	Server-to-Server/WAN Software (IM101)	
A0336932	Server-to-Server/X.25 (PDN100)	
A0336982	RILC Patch Panel	
A0336993	Omninet/Corvus Software	
A0336994	VistaLAN/Allen Bradley Software	
A0336995	ProNET/Proteon Software	
A0336996	IBM Token Ring Software	
A0336997	IBM PC Network Software	
A0336998	Ethernet/3Com Software	
A0336999	Ethernet/U-B Software	
A0337000	Ethernet/InterLan Software	
A0339690	Handsets/BTS Style/Push-To-Talk/Black	
A0341310	M1250/M2250 Attendant Line Cord	
A0343001	ARCNET LAN Software	
A0343022	70MB Server/4MB RAM (SA124)	
A0343023	120MB Server/4MB RAM (SA134)	
A0343028	DTS Console Cable (SA282)	
A0343029	BNS/CNS Console Cable (SA280)	
A0343030	BNS/CNS PC Console Cable (SA281)	
A0343031	DTS PC Console Cable (SA283)	
A0345125	HP ThinkJet Printer	A0409894

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0345240	EasyLan with Meridian Extension	
A0345290	Professional Billing Firmware Cartridge	
A0345291	Lodging Firmware Cartridge	
A0345292	General Business Firmware Cartridge	
A0345357	IBM 3270/SNA File Transfer Upgrade (SNA105)	
A0345358	VINES/386 Software (VNS386R4)	
A0345359	TCP/IP Routing (TCP100)	
A0345360	PC/TCP Server Based License Software (TCP120)	
A0345361	TCP/IP Server-to-Server (TCP200)	
A0345362	Network PC Printing (PCP100)	
A0345363	VINES/BNS Software (VNS680)	
A0345364	VINES/DTS Software (VNS681)	
A0345365	LANSTAR PC - Adapter/BANYAN Interface Software (Version 2.11)	
A0345367	80MB Server/4MB RAM (CNS22B)	
A0345370	60MB Tape Backup VINES/286,386 (EXT106)	
A0345371	150MB Tape Backup for VINES/286,386 (EXT115)	
A0345373	6-Serial Line Intelligent Communication Adapter (ICA108)	
A0345374	BNS/CNS Upgrade	
A0345376	4MB Memory Expansion Board (EMB104)	
A0345377	8MB Memory Expansion Board (EMB108)	
A0345378	146MB Server/4MB RAM (CNS42B)	
A0345379	146MB Server/8MB RAM (CNS44B)	
A0345381	146MB Expansion Disk (ESD140)	
A0345383	TDR 600 Basic Unit	
A0345384	TDR 1000 Basic Unit	
A0345385	M7000 Memory Expansion Module	
A0345915	80MB Server/4MB RAM (SAS124)	
A0345916	146MB Server/4MB RAM (SAS144)	
A0345917	80MB Expansion Disk (ESD120)	
A0345919	150MB Tape Drive for CNS/BNS Upgrade (BSU115)	
A0345920	Cartridge Tape - 150MB (AA102) VINES 286/386	
A0345921	VINES/CNS Software (VNS682)	
A0345922	VINES/286,386 UPS (120VAC) (UPS121)	
A0345923	VINES/286,386 UPS (240VAC) (UPS241)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0345924	Connector Cable for VINES 286,386 UPS (VNS285)	
A0345930	43MB	
A0345963	Ventel Modem (EC2400) (Release 6.0)	
A0345985	SFT NetWare V.2.15	
A0345986	Advanced NetWare V.2.15	
A0346864	6-Conductor Line Cord (25 Ft. M2000 Series requiring external power, and for M3902, M3903, M3904 and M3905)	
A0351295	660 MB Server w/8MB Memory and 32KB Cache Memory (CNS64C)	
A0351296	2.2GB Tape Cleaning Cartridge (AA250)	
A0351297	2.2GB Cartridge Tape (10/Pkg) (AA210)	
A0351298	VINES 4.0 Software Upgrade - VINES/386 (SSU-403)	
A0351299	VINES 4.0 Software Upgrade-BNS/DTS (SSU-400)	
A0351300	Token Ring Bridging (TRB100)	
A0351301	VINES Token Ring Bridging Option Guide (DA251-00)	
A0351302	X.29 Option-Asynchronous Term Emulation over X.25 (HA201)	
A0351303	Vines 4.0 Software Upgrade-CNS (SSU-404)	
A0351304	VINES 4.0 Software Upgrade - VINES/386 TEAM (SSU-403T)	
A0351305	VINES 4.0 Software Upgrade - VINES/286 (SSU-402)	
A0351306	VINES 4.0 Software Upgrade - RTS - VINES/386D3 MC (SSU-405RTS)	
A0351307	LAN Driver Documentation Set (DA256-00)	
A0351308	VINES Application Developers Guide & Reference (DA224)	
A0351309	VINES Application Developers Programming Interfaces (DA225)	
A0351310	VINES Users Guide and Command Ref-Diskette (DA222)	
A0351311	Field Service Manual for CNS (DA223)	
A0351312	SMTP Gateway Option Guide (DA241)	
A0351313	VINES 4.0 Software Upgrade - VINES/386D3 MC (SSU-405)	
A0351315	6-Line Serial COM Adapter - MC Servers (ICA210)	
A0351316	1 Yr. Update Subscription - VINES SFT - V386/TEAM (SUP-120)	
A0351317	1 Yr. Update Subscription - VINES SFT-CNS/V386/V386D3 MC (SUP-105)	
A0351318	CNS Memory Expansion 8MB Burst (CNS 486 CPU Only) (EMB208)	
A0351319	CNS Memory Expansion 4MB Burst (CNS 486 CPU Only) (EMB204)	
A0351320	CNS Upgrade to CNS/486-CPU/8MB Burst Memory Expansion (BSU24D)	
A0351321	660 MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS64D)	
A0351322	320MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS54D)	
A0351323	146MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS44D)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0351324	80MB Server w/4MB Memory and 32KB Cache Memory (CNS22C)	
A0351325	2.2GB Cartridge Tape (AA200)	
A0351326	2.2GB Internal Tape Drive for CNS Servers (EXT322)	
A0351356	3.5 Inch Digital Cassette Tape Drive	
A0351371	300MB Disk Drive	A0602257
A0351484	Literature Pack SL-1 Basic	A0351485
A0351485	Accessory Package	
A0352209	3270 Communications Controller with Transition Card	
A0352210	MVME X.25 Communications Card Kit (MVME333, MVME705, Cable)	
A0353378	HP RuggedWriter Printer	
A0353397	TDR 1000 Assembly	
A0353398	TDR 600 Assembly	
A0353670	320 MB Server/8MB RAM (CNS54b)	
A0353671	320MB Expansion Disk (ESD150)	
A0353672	VINES/286 to 386 Upgrade	
A0353673	PC/TCP Server Based Licensed Software with Routing (TCP100)	
A0353674	Serial Communication Installation Guide (DA201-04)	
A0353675	Network Installation Guide VINES 386 (DA203-04)	
A0353676	Network Installation Guide - CNS (DA213-02)	
A0353677	VINES 3.0 Users Guide (DA204)	
A0353678	VINES 3.0 Server Options Guide (DA205)	
A0353679	VINES 3.0 Administration Reference (DA206)	
A0353680	VINES 3.0 Administration Planning Guide (DA207)	
A0353681	3270/SNA Option Guide (DA181-01)	
A0353682	Asynchronous Terminal Emulation Guide (DA183-01)	
A0353683	Banyan EXP-DTS Opt. Installation Document (DA191)	
A0353684	Banyan BNS Option Installation Document (DA192)	
A0353685	Network Management Guide (DA202-01)	
A0353686	Network Mail (DA208-01)	
A0353687	PC Dial-In Guide (DA209-01)	
A0353688	TCP/IP Option Guide (DA212)	
A0353689	External Tape Drive Installation Document (DA219)	
A0354417	HP 700/22 Terminal - Amber	A0376518
A0354454	LANSTAR PC - Adapter/BANYAN Interface Software (Version 3.01)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0354471	Guide to Banyan Publications (DA220-02)	
A0354682	146MB Server/8MB RAM/Cache (CNS44A)	
A0354683	320MB Server/8MB RAM/Cache (CNS54A)	
A0355244	RS232 Straight Cable (10 Ft.)	NTND91AA
A0355245	RS232 Straight Cable (25 Ft.)	NTND91AB
A0361284	EasyLan with Meridian Extension	
A0362142	HP PaintJet	
A0362143	HP DeskJet (Lower Cost Alternative to LaserJet II for Text and Graphics	A0378327
A0362144	HP LaserJet Series II Printer (High Resolution, Publication Quality Text	A0376960
A0362175	8 Port Terminal Concentrator (TC) (RJ-11 Connections)	A0368534
A0365364	Cable TC/FM to Supervisor PC (Return to Console Link) (RJ45 to DB9)	NT9D8002
A0365365	Cable TC/FM to Printer (RJ45 to DB25)	NT9D8003
A0365366	Cable TC/FM to Terminal (RJ45 to DB25)	NT9D8004
A0366311	CPLUS Directory and Messaging PC Software (Release 2)	NT9D07AB
A0367752	Seismic Relay Rack (23 In. x 7 Ft.)	
A0367754	Fan Unit - Option 21A	A0321130
A0368901	Modem Cable (DB9 to DB25)	NTAK1118
A0369284	320MB Server w/8MB Memory and 32KB Cache Memory (CNS54C)	
A0369437	VINES/386 TEAM to VINES/386 Upgrade (UTM386)	
A0369438	VINES/386 Team Software Package (VTM386)	
A0369439	MacVINES Mail Gateway (MAC100)	
A0369440	146 MB Server w/8 MB Memory and 32KB Cache Memory (CNS44C)	
A0369441	VINES Applications Toolkit (VDT100) (CNS/386)	
A0369442	CNS Disk Expansion 660MB SCSI Disk Drive (ESD160)	
A0369443	VINES/386 Microchan Software Package (VNS386D3)	
A0369444	150MB Tape Backup - VINES 386/486 - MC SVRS (EXT215)	
A0369453	MacVines Mail Gateway Administrators Guide (10/PK) (DA232)	
A0369454	MacVines Mail Gateway Users Guide (DA233)	
A0369499	Black Box HP Cable	
A0369706	VINES 4.0 Software Upgrade - RTS - VINES/286 (SSU-402RTS)	
A0369707	VINES 4.0 Software Upgrade - RTS - VINES/386 TEAM (SSU-403TRTS)	
A0369708	VINES 4.0 Software Upgrade - RTS - BNS/DTS (SSU-400RTS)	
A0369709	BNS Upgrade to BNS/386-25 CPU/8MB Memory Expansion (BSU24C)	
A0369710	SMTP Mail Gateway (MGW110)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0369711	VINES 4.0 Software Upgrade - RTS - VINES/386 (SSU-403RTS)	
A0369712	VINES 4.0 Software Upgrade - RTS - CNS (SSU-404RTS)	
A0369779	DC6150 Back-Up Tape	A0368760
A0370853	Cable TC/FM to XSDI (HSL and Configuration Control) (RJ45 to DB9)	
A0370854	Cable TC to XSDI (HSL and Configuration Control) (RJ11 to DB9)	
A0372990	Carbon Copy Software	
A0374277	Cable TC/FM to Modem (Remote Supervisor) (RJ45 to DB25)	NT9D9007
A0376518	HP700/32 Terminal - Amber	
A0376839	DEC 420 Terminal	
A0376960	HP LaserJet Series III Printer (High Resolution, Publication Quality,	A0386003
A0376960	HP LaserJet Series III Printer (High Resolution, Publication Quality,	A0386014
A0377097	M3000 Directory Archiver	
A0377786	80MB Disk Drive	A0351371
A0377787	40 MB Disk Drive	A0378251
A0378002	Liberation Headset, Modular Electret-Earhook, Monaural	
A0378003	Liberation Headset Modular Electret-Earloop, Monaural	
A0378004	Liberation Headset Modular Electret-Headband, Monaural	
A0378005	Liberation Headset PJ327 Carbon-Earhook, Monaural	
A0378006	Liberation Headset PJ327 Carbon-Earloop, Monaural	
A0378007	Liberation Headset PJ327 Carbon-Headband, Monaural	
A0378008	Liberation Multi-Purpose Amplifier (MPA)	NTA149AA
A0378009	Liberation CLASSIC, Monaural, Earhook (All Amplifier Models)	A0651112
A0378010	Liberation CLASSIC, Monaural, Earloop (All Amplifier Models)	A0651112
A0378011	Liberation CLASSIC, Monaural, Headband (All Amplifier Models)	A0722777
A0378012	Liberation Earhook Conversion Kit	A0771059
A0378013	Liberation Earloop Conversion Kit	
A0378014	Liberation Headband Conversion Kit	
A0378015	Liberation Headset Conversion Kit	
A0378016	Clothing Clip (10/PK)	A0384883
A0378017	Earpiece with Foam Cover (10/PK)	
A0378018	Liberation Earpiece Foam Cushion (Pack of 10)	
A0378019	Liberation Headset Extension Cord, 10 Ft. (QD to QD)	
A0378020	RJ11 Adapter for PJ327 Phone	
A0378021	Liberation AC Adapter for MPA	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0378022	Liberation Sales Flyer	
A0378023	Multi Purpose Amplifier (MPA) Sales Flyer	
A0378025	Liberation Training Video	
A0378152	Liberation DIRECT for Norstar, Binaural UNC	A0651110
A0378153	Liberation Headset PJ327 Carbon-Headband, Binaural	
A0378154	Liberation CLASSIC, Binaural UNC, Headband (All Amplifier Models)	A0651111
A0378219	External Tape Drive Carrying Case	
A0378251	170MB Disk Drive	A0351371
A0378327	HP DeskJet 500 Printer	
A0378849	M5000TD-1 V.35 Connector	
A0379976	Customer Controlled Routing Users Guide & A-C2/NACD Documentation	NTND65AB
A0380908	AT&T Connections Hardware Package	
A0381391	UDS FastTalk Modem, 9600 Baud	A0638930
A0381458	Ventel 9600 Plus Modem	NTDK66AA
A0383524	Rolm Connections Hardware Kit	
A0383528	Option 11C Compact Hospitality Guest Administration Console	A0383526
A0383534	NEC Connections Hardware Kit	
A0384883	Liberation Headset Cord Clothing Clip	
A0386003	HP LaserJet 4M Series IV Printer	
A0386014	HP LaserJet IV Series IV Printer	
A0386015	14" SVGA Monitor	
A0386101	NCD X-Terminal (17 In. Color/8MB)	
A0387584	Controlled COS Key Cap Package (50/PK)	
A0387585	CAS Key Cap Package (50/PK)	
A0387587	Interflow Key Cap Package (50/PK)	
A0387589	Attendant Recall Key Cap Package (50/PK)	
A0387591	Message Center Key Cap Package (50/PK)	
A0387593	Calling Number Key Cap Package (50/PK)	
A0387594	Answer Emergency Key Cap Package (50/PK)	
A0387597	Message Cancel Key Cap Package (50/PK)	
A0387600	Message Registration Key Cap Package (50/PK)	
A0387601	Voice Call Key Cap Package (50/PK)	
A0387602	CTX Access Key Cap Package (50/PK)	
A0387605	Status Key Cap Package (50/PK)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0387612	Flash Over Key Cap Package (50/PK)	
A0387615	Override Key Cap Package (50/PK)	
A0387617	Conference Hotline Key Cap Package (50/PK)	
A0387618	Conference Speed Call Key Cap Package (50/PK)	
A0387619	Conference Auto Dial Key Cap Package (50/PK)	
A0387620	Wake Up Key Cap Package (50/PK)	
A0387621	Immediate Key Cap Package (50/PK)	
A0387622	Priority Key Cap Package (50/PK)	
A0387623	Flash Key Cap Package (50/PK)	
A0387625	Auto Answer Key Cap Package (50/PK)	
A0387626	System Speed Call Key Cap Package (50/PK)	
A0387627	Speed Call Key Cap Package (50/PK)	
A0387628	Buzz Key Cap Package (50/PK)	
A0387630	Data Key Cap Package (50/PK)	
A0387632	Call Pickup Key Cap Package (50/PK)	
A0387633	Call Waiting Key Cap Package (50/PK)	
A0387636	Intercom Key Cap Package (50/PK)	
A0387640	Forward Key Cap Package (50/PK)	
A0387641	Conference Key Cap Package (50/PK)	
A0387642	Message Key Cap Package (50/PK)	
A0387643	Transfer Key Cap Package (50/PK)	
A0388536	NT8D96AE VME Multiport Cable	
A0394669	Cable TC/FM to NAC Network Link and Remote Supervisor Log-In Link (RJ45 to DB25)	NT9D9008
A0397391	Handsfree/Mute Key Caps Package (50/PK)	
A0397394	Literature Pack (M2216-ACD 1/2)	NT2K80AD
A0397928	Meridian MAX Release 4 NTPs	
A0399070	Meridian MAX Release 4 Supervisors User Guide	
A0408927	RS232 - V.35 Adapter Cable for MCA/MCU (Female)	NT9D38AA
A0408928	RS232 - V.35 Adapter Cable for MCA/MCU (Male)	NT9D39AA
A0409894	HP ThinkJet Printer	
A0600040	VME Slot Bypass Card	
A0600069	Meridian IPE Application Module without Tape/Disk for Option 21-81	
A0600070	150MB Tape Drive Unit	A0617012
A0600071	180MB Hard Disk Drive Unit	A0617011

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0600074	Meridian IPE Application Module without Tape/Disk for Option 11	
A0600181	MVME167-03 Processor Card (M68040, 25 Mhz, 16MByte)	A0688017
A0600398	NCD X-Terminal (15 In. Mono/8MB)	
A0600711	3270 Communications Controller	
A0600712	X.25 Communications Controller	
A0601164	MVME167A or 02 Processor Card (M68040, 25Mhz, 8MB)	
A0602257	300MB Disk Drive	A0603704
A0602257	300MB Disk Drive	NTDK74AB
A0603704	300MB Disk Drive	A0630704
A0609632	NCD15R 15" Monochrome Monitor (8MB)	
A0609633	NCD15R X-Terminal Base	
A0614339	1 1/3 Amp Fuse	QFF1AB
A0617009	Meridian IPE Application Module for Option 11	A0669467
A0617010	Meridian IPE Application Module for Options 21-81	A0617011
A0617010	Meridian IPE Application Module for Options 21-81	A0669468
A0617012	600MB Tape Drive Unit	
A0619919	M1250/M2250 Attendant Line Cord	NT9D13AA
A0622451	Meridian 1 Reference Library (Release 20)	A0637618
A0623885	9600 Baud Modem	
A0627746	Label Kit	NT1P5201
A0630704	300MB Disk Drive	A0645393
A0632449	Liberation On-Line Indicator for MPAII	
A0633651	40MB PCMCIA Card - Blank	
A0634488	Fiber Remote Multi-IPE Interface - Single Mode (1-4 Superloops)	A0732456
A0634489	Fiber Remote Multi-IPE Interface - Single Mode (1-2 Superloops)	A0732458
A0634490	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	A0732527
A0634491	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	A0732528
A0634497	Maintenance Interface Cable	A0766331
A0634498	AC/DC Power Converter	A0762506
A0637618	Meridian 1 Reference Library (Release 21)	A0643619
A0637723	Redundant Power Supply for DC-powered MRS/Rack	
A0637730	UPS for AC-powered MRS/Tower and MRS/Rack	NT3R74CA
A0637736	UPS for AP or MRS/AP	A0656287
A0637905	Tandberg Tape Drive Unit - External	A0721902

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0638225	MRS Tower/Rack Ethernet Controller	
A0638430	Meridian IVR Serial Board 8 ports with Octa cable	A0651349
A0638465	17" SVGA Monitor	NT3R82BA
A0638486	Mouse - 3-button PS/2-type	A0651329
A0638596	SQL Ingres Database Access	
A0638600	SQL Oracle Database Access	
A0638602	SQL Informix Database Access	
A0638603	SQL Sybase Database Access	
A0638930	Motorola 28.8 Fax/Data Modem	A0638645
A0639011	Audio Interface Unit	NTZK98AA
A0639207	OIVR 2.x Hardware - VT100 Communications Board (16 ports) & Cable	NTV452VA
A0639209	VT100 Communications Board (32 Ports)	
A0639224	50 Hours (1 x 540MB disk)	
A0639230	Base System (Tower)	A0650375
A0639231	Base System Intel 750tMM	
A0639271	Text-To-Speech Expansion (4 ports)	NT3R79BA
A0639272	Discrete Voice Recognition Expansion (4 ports)	NT3R77BA
A0639335	OIVR 2.x Hardware - Prompt Management Software	
A0639546	Continuous Voice Recognition Expansion (2 ports)	NT3R78BA
A0639811	75MHz P5 Processor for Alt/Mag	
A0639812	Meridian IVR Pentium CPU Upgrade, 100MHz	
A0640736	MRS/Rack Cabinet	
A0642533	Meridian Communications Adapter User Guide (Pk of 15 P0744323)	NT5F54AB
A0643619	Meridian 1 Reference Library (Release 21)	A0657076
A0644926	MIVR Operational NTPs	NT3R51AA
A0644928	MIVR Development NTPs	NT3R52AA
A0645393	300MB Disk Drive	NTDK74AB
A0645393	300MB Disk Drive	X0645393
A0647283	SYMPOSIUM Server, 1000t Chassis Assembly, No Power Supply	
A0648522	Liberation DURA PLUS, Monaural NC, Headband (All Amplifier Models)	
A0648523	Liberation DURA PLUS, Binaural NC, Headband (All Amplifier Models)	
A0650990	24 Port T1 Board	NTV492NA
A0651002	Text-to-Speech Card	NTV498PA
A0651108	Liberation Wireless Amplifier (with Base Station)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0651111	Liberation FLEX, Binaural NC, Headband (All Amplifier Models)	
A0651112	Liberation FLEX, Monaural NC, 3 in 1 (All Amplifier Models)	
A0651329	Mouse - 3-Button PS/2-Type	NTVE9014
A0651349	8 Port Digiboard with DCE Octa Cable	
A0652358	Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Gray	
A0652361	Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Black	
A0652628	XIOX External Hacker Deadbolt	
A0652675	Smart Splitter	
A0654392	XIOX Hacker Preventer 32-400 Lines	
A0654393	XIOX Hacker Preventer 401-800 Lines	
A0654394	XIOX Hacker Preventer 801+ Lines	
A0657076	Meridian 1 Reference Library (Release 22)	NT6R40AA
A0657617	4-Port Loopstart Card	NTV494NA
A0657727	Modem Cable (DB9F to DB25M)	NTVE9932
A0658784	Replacement Processor Installation Kit	
A0660140	Meridian M2616CT Wall Transformer (Standard)	
A0660167	Meridian Private-Switch Emergency Response Unit	A0665488
A0660403	3MB PCMCIA Flash Card	
A0667973	4 to 8 Session Expansion for 3270 and 5250	
A0667975	8 to 16 Session Expansion for 3270 and 5250	
A0667976	16 to 32 Session Expansion for 3270 and 5250	
A0668892	Meridian 1 Attendant PC Handset Cord with PJ-Type Plug	NTAG95AA
A0670630	SYMPOSIUM Call Center Server 701t 3.5" Floppy Drive Bracket	
A0670854	SYMPOSIUM Call Center 701t CPU Upgrade Kit without CPU	
A0671007	Key Expansion Module Cable, (M2000 Series)	NT2K03BA
A0687194	Meridian M2616CT 1000 mAh Battery Pack with Vibrate Alerter, Black	
A0687196	Meridian M2616CT 1000 mAh Battery with Vibrate Alerter, Gray	
A0696007	MVME177-004 Processor Card (M68060, 50 Mhz, 32 MByte)	A0696008
A0722776	Liberation PERFORMA, Binaural NC, Headband (All Amplifier Models)	
A0722777	Liberation PERFORMA, Monaural NC, Headband (All Amplifier Models)	
A0724209	Video Card Adapter	
A0728871	128 MB DIMM	
A0729360	Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Ash	
A0729364	Meridian M2616CT 1000 mAh Battery with Vibrate Alerter, Ash	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
A0730856	600MB Tape Drive Repair Kit	
A0732456	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	A0759609
A0732458	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	A0759612
A0732527	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	A0759618
A0732528	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	A0759620
A0741582	702t Base System	
A0743996	Meridian 2616CT Wall Transformer (Standard)	
A0759609	Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops)	A0773056
A0759612	Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops)	A0773059
A0759618	Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops)	A0773054
A0759620	Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops)	A0773055
A0761147	CPU (350Mhz)	
A0767002	SCSI Connector	
A0769307	SCSI Adapter	
A0771059	Liberation Flexible Earhook Conversion Kit	
A0786611	CP PII Call Processor Card (128MB Memory)	A0810496
AS0070	Meridian MAX Release 6 Capacity Configurator Tool	NT1R76BA
AS0072	Meridian MAX Release 5 Capacity Configurator Tool	
AS1001A	Pedestal Assembly AC	AS1081A
AS1001D	Pedestal Assembly DC	AS1081D
AS1002A	Two-Module Pedestal Assembly AC	
AS1002D	Two-Module Pedestal Assembly DC	
AS1004A	Option 21A Pedestal/Top Cap Conversion Package	
AS1005A	Option 51 CPU Redundancy Assembly AC	U9628A
AS1005D	Option 51 CPU Redundancy Assembly DC	U9628D
AS1008	Option 21 CE Spares Package	
AS1009	Option 21 + IPE Module CE Spares Package	
AS1010	Option 51 CE Spares Package	AS1011
AS1011	Option 51/61 CE Spares Package	
AS1012	Option 71 CE Spares Package	
AS101403	Centralized Answering Position Package (M2216ACD-1), Black	
AS101435	Centralized Answering Position Package (M2216ACD-1), Ash	
AS101493	Centralized Answering Position Package (M2216ACD-1), Gray	
AS1015D	Rectifier Rack Assembly	AS1088D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
AS1016D	Rectifier Assembly	AS1087D
AS1018D	Prime Rectifier Cabinet Assembly	AS1100D
AS1018D	Prime Rectifier Cabinet Assembly	AS1101D
AS1023	Modular Macpack	
AS1025	Option 11 CE Spares Package	
AS1027	Network Group 1 or 2 Shelf Assembly	
AS1028	Network Group 3 Shelf Assembly	
AS1029	Network Group 4 Shelf Assembly	
AS1031	Power Monitor/CE Auxiliary Shelf Assembly (Cantilever Mount)	
AS1032	Power Monitor/CE Auxiliary Shelf Assembly (Center Mount)	
AS1035	Option 21E CE Spares Package	
AS1036	Option 51/61 CE Spares Package	
AS1037	Option 71 CE Spares Package	
AS1038	Option 51C/61C/81 CE Spares Package (24 MB CP)	
AS1045	Option 21E System Spares Package	
AS1046	Option 51/61 System Spares Package	
AS1047	Option 71 System Spares Package	
AS1048	Option 51C/61C/81 System Spares Package (24 MB CP)	
AS1053A	Peripheral Equipment Module Package AC	
AS1053D	Peripheral Equipment Module Package DC	
AS1055A	RPE Carrier Module Assembly AC	AS1093
AS1055D	RPE Carrier Module Assembly DC	AS1093
AS1057	Floppy Disk Assembly - Single CPU	
AS1058	Multi Disk Assembly - Single CPU	
AS1059	Floppy Disk Assembly - Dual CPU	
AS1060	Multi Disk Assembly - Dual CPU	
AS1064A	RPE - Remote Package AC	AS1094A
AS1064A	RPE - Remote Package AC	AS1095A
AS1064D	RPE - Remote Package DC	AS1094D
AS1064D	RPE - Remote Package DC	AS1095D
AS1071	Option 11 Expansion Package AC/DC	
AS1072	Option 11 Expansion Package DC/DC	
AS1080	DEC Printer Package	NTZR40BA
AS1100D	Main Power Bay Assembly	AS1202D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
AS1101D	Seismic Main Power Bay Assembly	AS1202D
AS1102D	Supplemental Power Bay Assembly	
AS1103D	Seismic Supplemental Power Bay Assembly	
AS1131	Option 51C/61C/81 System Spares Package	
AS1180	Meridian Mail Quick Reference Cards (PKG of 30)	P0741565
AS1202D	MPP600 Modular Power Package-Main Cabinet	AS1209D
AS1203D	MPP600 Modular Power Package-Supplemental Cabinet	AS1210D
AS1205	Meridian Administration Tools Station Administration Incentive Price Cap	AS1209
AS1206	Meridian Administration Tools Traffic Analysis Incentive Price Cap	AS1210
AS1207	Meridian Administration Tools Station Administration and Traffic Analysis Incentive Price Cap	AS1211
AS1209	Meridian Administration Tools Station Administration Incentive Price Cap	
AS1210	Meridian Administration Tools Traffic Analysis Incentive Price Cap	
AS1211	Meridian Administration Tools Station Administration and Traffic Analysis Incentive Price Cap	
AS1300	Meridian Administration Tools Single Site Station Administration Upgrade	AS1306
AS1301	Meridian Administration Tools Multi-Site Station Administration Upgrade	AS1307
AS1302	Meridian Administration Tools Single Site Traffic Analysis Upgrade	AS1308
AS1303	Meridian Administration Tools Multi Site Traffic Analysis Upgrade	AS1309
AS1304	Meridian Administration Tools Single Site Station Administration and Traffic Analysis Upgrade	AS1310
AS1305	Meridian Administration Tools Single Site Station Administration and Traffic Analysis Upgrade	AS1311
AS1306	Meridian Administration Tools Single Site Station Administration Upgrade	
AS1307	Meridian Administration Tools Multi-Site Station Administration Upgrade	
AS1308	Meridian Administration Tools Single Site Traffic Analysis Upgrade	
AS1309	Meridian Administration Tools Multi Site Traffic Analysis Upgrade	
AS1310	Meridian Administration Tools Single Site Station Administration and Traffic Analysis Upgrade	
AS1311	Meridian Administration Tools Multi Site Station Administration and Traffic Analysis Upgrade	
AS2001A	Special Pedestal Assembly AC	
AS2001D	Special Pedestal Assembly DC	
AS2002A	Special Peripheral Equipment Module Package AC	AS1053A
AS2002D	Special Peripheral Equipment Module Package DC	AS1053D
AS7000A	Meridian Mail Modular Option from 12 to 16 Ports, 300MB Disk, Expansion Package AC	AS7001A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
AS7000D	Meridian Mail Modular Option from 12 to 16 Ports, 300MB Disk, Expansion Package DC	AS7001D
AS7001A	Meridian Mail Modular Option from 1 to 2 Node, Expansion Package AC	AS7043A
AS7001D	Meridian Mail Modular Option from 1 to 2 Node, Expansion Package DC	AS7043D
AS7002A	Meridian Mail Modular Option from 24 to 28 Ports, 300MB Disk, Expansion Package AC	AS7003A
AS7002D	Meridian Mail Modular Option from 24 to 28 Ports, 300MB Disk, Expansion Package DC	AS7003D
AS7003A	Meridian Mail Modular Option from 24 to 28 Ports, 1.0GB Disk, Expansion Package AC	AS7009A
AS7003D	Meridian Mail Modular Option from 24 to 28 Ports, 1.0GB Disk, Expansion Package DC	AS7009D
AS7004A	Meridian Mail Modular Option from 48 to 52 Ports, 300MB Disk, Expansion Package AC	AS7005A
AS7004D	Meridian Mail Modular Option from 48 to 52 Ports, 300MB Disk, Expansion Package DC	AS7005D
AS7005A	Meridian Mail Modular Option from 4 to 5 Node, Expansion Package AC	AS7046A
AS7005D	Meridian Mail Modular Option from 4 to 5 Node, Expansion Package DC	AS7046D
AS7006A	Meridian Mail Modular Option Expansion Package Spares Kit AC	
AS7006D	Meridian Mail Modular Option Expansion Package Spares Kit DC	
AS7007	Meridian Mail Modular Option Expansion Package Networking Kit	AS7008A
AS7007	Meridian Mail Modular Option Expansion Package Networking Kit	AS7008D
AS7007	Meridian Mail Modular Option Expansion Package Networking Kit	AS7012
AS7008A	Meridian Mail Modular Option from 28 to 32 Ports, 300MB Disk, Expansion Package AC	AS7009A
AS7008D	Meridian Mail Modular Option from 28 to 32 Ports, 300MB Disk, Expansion Package DC	AS7009D
AS7009A	Meridian Mail Modular Option from 2 to 3 Node, Expansion Package AC	AS7044A
AS7009D	Meridian Mail Modular Option from 2 to 3 Node, Expansion Package DC	AS7044D
AS7013	Meridian Mail Single Terminal Access Package	AS7011
AS7016	Meridian Mail RSM Package	
AS7018A	Meridian Mail Modular Option from 32 to 36 Ports, 300MB Disk, Expansion Package AC	AS7019A
AS7018D	Meridian Mail Modular Option from 32 to 36 Ports, 300MB Disk, Expansion Package DC	AS7019D
AS7019A	Meridian Mail Modular Option from 3 to 4 Node, Expansion Package AC	AS7045A
AS7019D	Meridian Mail Modular Option from 3 to 4 Node, Expansion Package DC	AS7045D
AS7020A	Meridian Mail Modular EC Node Expansion 1st Position, 300MB Disk, Package AC	AS7021A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
AS7020D	Meridian Mail Modular EC Node Expansion 1st Position, 300MB Disk, Package DC	AS7021D
AS7022A	Meridian Mail Modular EC Node Expansion 2nd Position, 300MB Disk, Package AC	AS7023A
AS7022D	Meridian Mail Modular EC Node Expansion 2nd Position, 300MB Disk, Package DC	AS7023D
AS7024	Meridian Mail Modular EC Node Expansion 3rd Position, 300MB Disk, Package	AS7025
AS7030A	Meridian Mail Modular EC 300MB Disk Shadowing 3/5 Node Package AC	AS7031A
AS7030D	Meridian Mail Modular EC 300MB Disk Shadowing 3/5 Node Package DC	AS7031D
AS7032A	Meridian Mail Modular EC 300MB Disk Shadowing 4 Node Package AC	AS7033A
AS7032D	Meridian Mail Modular EC 300MB Disk Shadowing 4 Node Package DC	AS7033D
AS7036A	Meridian Mail 300MB Disk Shadowing Voice Node Package AC	AS7037A
AS7036D	Meridian Mail 300MB Disk Shadowing Voice Node Package DC	AS7037D
AS7038	Meridian Mail GP from 2 to 3 Node Expansion Package	
AS7039	Meridian Mail GP from 3 to 4 Node Expansion Package	
AS7040	Meridian Mail Modular EC Spares Package 1	AS7080
AS7041	Meridian Mail Modular EC Spares Package 2	AS7081
AS7042	Meridian Mail Modular EC Alternative Remote Access Package	
AS7051	Meridian Mail ST/RT Option MMP40 1 to 2 Node Expansion Package	
AS7052	Meridian Mail Option MMP40 1 to 2 Node Expansion Package (Cantilever Mount)	
AS7053	Meridian Mail Option MMP40 1 to 2 Node Expansion Package (Center Mount)	
AS7054	Meridian Mail X Cabinet from 2 to 3 Node Expansion Package	
AS7055	Meridian Mail X Cabinet from 3 to 4 Node Expansion Package	
AS7060D	Meridian Mail Modular GP from 12 to 16 Ports, 300MB Disk, Expansion Package DC	AS7061D
AS7061D	Meridian Mail Modular GP from 12 to 16 Ports, 1.0GB Disk, Expansion Package DC	AS7047D
AS7062D	Meridian Mail Modular GP from 24 to 28 Ports, 300MB Disk, Expansion Package DC	AS7063D
AS7063D	Meridian Mail Modular GP from 24 to 28 Ports, 1.0GB Disk, Expansion Package DC	AS7048D
AS7064D	Meridian Mail Modular GP from 32 to 36 Ports, 300MB Disk, Expansion Package DC	AS7065D
AS7065D	Meridian Mail Modular GP from 32 to 36 Ports, 1.0GB Disk, Expansion Package DC	AS7049D
AS7066D	Meridian Mail Modular GP from 48 to 52 Ports, 300MB Disk, Expansion Package DC	AS7067D
AS7067D	Meridian Mail Modular GP from 48 to 52 Ports, 1.0GB Disk, Expansion Package DC	AS7050D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
AS7090	VP4 Card - Flexible Assignment	AS7108
AS7090	VP4 Card - Flexible Assignment	AS7109
AS7091	VP8 Card - Flexible Assignment	AS7110
AS7091	VP8 Card - Flexible Assignment	AS7111
AS7092	NVP Card, Flexible Assignment	AS7114
AS7093	GSP Card, Flexible Assignment	AS7112
AS7093	GSP Card, Flexible Assignment	AS7113
AS7102	Meridian Mail Card Option 6 to 8 Port Expansion Package, Release 8	
AS7103	Meridian Mail Card Option 6 to 8 Port Expansion	AS7122
AS7103	Meridian Mail Card Option 6 to 8 Port Expansion	AS7123
AS7104	Meridian Mail Reporter Single Site Software	
AS7105	Meridian Mail Reporter Multi Site Software	
AS7106	Meridian Mail Reporter Single Site Software, Option 11	
AS7107	Meridian Mail Reporter Multi Site Software, Option 11	
AS7124	Meridian Mail AutoAdmin Software Package	
AS7125	Meridian Mail Option 11 AutoAdmin Software Package	
AS7190	C25 Voice Processor Card	AS7120
AS7190	C25 Voice Processor Card	AS7121
AS7309	Meridian Safe 32-400 Lines	
AS7310	Meridian Safe 401-800 Lines	
AS7311	Meridian Safe 801+ Lines	
AS7312	Meridian Safe Advanced Sites 1201+ Lines	
AS7523A	Meridian MAX Option 2 to Option 3 Expansion Package AC	
AS7523D	Meridian MAX Option 2 to Option 3 Expansion Package DC	
AS8601	15" Color X-Terminal Monochrome with DEC Style Keyboard	
B0198494	Rectifier Card for J-2357D-1, List 1 Rectifier	
B0202061	Rectifier J-2357D-1, List 3 for the J-2412A Cabinet (B0210372-B0205582)	
B0202082	Input Bus Bar Assembly for J2412A-1 Cabinet	
B0206661	Rectifier Card for the J-2357D-1, list 3 Rectifier	
B0206675	Discharge/Fuse Panel for J2412A-1 Cabinet	
B0206676	Discharge Terminal Panel #1 for J2412A-1 Cabinet	
B0206677	Discharge Terminal Panel #2 for J2412A-1 Cabinet	
B0206678	Circuit Breaker Panel for J2412A-1 Cabinet	
B0206682	Supplementary Power Cabinet (QCA13) J2412A-1L17/19	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
B0210365	J2412AA-1 Control Panel for J2412A-1 Cabinet	
B0210372	Centralized Power Cabinet (QCA13) J2412A-1L6/18/24	
B0225152	Prime Power Cabinet (QCA13) J2412A-1 L6/18/27/28/29	
B0225153	Supplementary Cabinet	AS1203D
B0225161	Control Panel Assembly	
C0022571	Circuit Breaker (CB1)	
C0035996	Cabinet Door Key	
C0040777	System Tape (450 Ft.)	
C0041748	Cord Assembly (CDR)	
C0045095	Thermostat	
C0045763	Circuit Breaker	
C0046926	Fuse, 100 Amp (For QBL6)	
C0046928	Fuse, 30 Amp (For QBL6)	
C0046930	DC Ammeter (For QBL6)	
C0046977	HP7970 CDR Tape Unit	
C0046980	Static Inverter (CDR)	
C0048650	Magnetic Tape (CDR)	
C0052473	Degausser (CDR)	
C0056273	System Tape 450 Ft.	
C2502242	DTS Power Harness (CS029)	
C2502243	DTS UPS Cable Kit (CS026)	
C2502244	DTS Tape Cable Kit (CS033)	
C2502246	DTS/EXP Power Supply (CS034)	
C2502247	DTS SCSI Cable Kit (CS027)	
C2502248	DTS Motherboard (CS022)	
C2502249	DTS I/O Board Kit (CS024)	
C2502250	DTS Disk Cable Kit (CS028)	
C2502251	DTS Card Guide Kit (CS023)	
C2502252	BNS/DTS Tape Controller Kit (CS013)	
C2502253	BNS/DTS Disk Controller Kit (CS018)	
C2502254	BNS SCSI Cable Kit (CS017)	
C2502255	BNS Power Supply Kit (CS009)	
C2502256	BNS Power Distribution Cable Kit (CS011)	
C2502257	BNS Side and Top Panel Kit (CS038)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
C2502258	BNS Memory Kit (4MB) (CS036)	
C2502259	BNS Fan Kit (220 Volt) (CS006)	
C2502260	BNS Fuse Kit (CS010)	
C2502261	BNS Fan Kit (115 Volt) (CS005)	
C2502262	BNS Disk Cable Kit (CS016)	
C2502263	BNS CPU Board Kit (CS015)	
C2502264	BNS Battery Pack Kit (CS014)	
C2502265	BNS Backplane Kit (20 Lines)	
C2502266	BNS Backplane Kit (16 Lines) (CS001)	
C2502267	BNS Card Guide Kit (CS003)	
C2502268	BNS Keyswitch Kit (CS008)	
C2502269	BNS Latch Release Kit (CS004)	
C2502270	BNS Line Filter Kit (CS007)	
C2502271	43MB Kit (CS019)	
C2502272	DTS Front Panel LED Kit (CS025)	
C2502273	BNS Tape Drive Kit (Full Height) (CS012)	
C2502274	DTS Tape Drive Kit (Half Height) (CS030)	
C2502490	EXP Front Panel LED Kit (CS047)	
C2502491	BNS Front Console Assembly (CS081)	
C2502492	EXP Power Load Board Kit (CS046)	
C2502493	BNS DC Distribution Board (CS080)	
C2502494	BNS Upper Battery Assembly (CS082)	
C2502495	DTS 200 Tape Cable Kit (CS044)	
C2502496	BNS Fuse Holder Kit (CS039)	
C2502497	DTS 200 SCSI Cable Kit (CS043)	
C2502498	EXP SCSI Expansion Cable Kit (CS045)	
C2502499	DTS 146MB SCSI Disk (CS042)	
C2502500	DTS 80MB SCSI Disk (CS041)	
C2502501	DTS 52MB SCSI Disk (CS040)	
C2502503	Panasonic KX-P1180 Printer	
C2502504	AC Outlet Adapter	
C2502505	AC/DC Adapter	
C2502506	Anderson Jacobs Acoustic Modem	
C2502507	Printer Cable (RS232) (18 In.) (Connects TDR to Printer)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
C2502508	CDR/SDI Cable (RS232) (25 Ft.) (Connects SL-1 to TDR)	
C2502509	Modem Cable (RS232) - 18 In. (Connects TDR to modem)	
CPC45	Serial Data Interface (Single) (CDR)	
H009	Meridian Mail Hospitality Voice Services Installation and Administration Study Guide	
H017	Meridian Mail Voice Forms	
H018	Meridian Mail Multi-Customer Administration	
H019	Meridian Mail Security	
H020	Meridian Mail Reports	
INSTFAST	VISIT FastCall Installation - (Per Scheduled 8 Hour Day On-Site, 5 to 8 Seats)	
J0000110	M5000TD-1 Terminal Adapter Release 2	
J0000240	M5317TX, Ash, Release 2	NTFX00PA
J0000241	M5317TX, Black, Release 2	NTFX00PB
J0000242	M5317TDX, Ash, Release 2	NTFX00LE
J0000243	M5317TDX, Black, Release 2	NTFX00LF
M4020	M4020 Terminal	
MVC00165	Cable Assembly (1 Ft.)	A0247602
MVC00166	Cable Assembly (2 Ft.)	A0247603
MVC00410	Data Modem GDC103A3	MVC01243
MVC00947	SL-1 Autovon Feature Document	
MVC01113	Blank Tape (300 Ft.) (Mini-CDR)	
MVC01114	Blank Tape (450 Ft.) (Mini-CDR)	
MVC01119	3M Tape Drive Cleaning Kit	
MVC01121	MW Power Supply P14 Extension Kit Assembly	
MVC01243	Data Modem (GDC103JM)	
MVC01250	X11 Data Input Forms Release 15	P0738425
MVC01305	8.5 x 11 Paper	
MVC01306	11 x 14.875 Paper	
MVC01309	Sprinter Ribbon	
MVC01310	Strider Ribbon	
MVC01312	Quiet Print	
MVC01313	Silent Print	
MVC01314	Strider Vertical Format Tape	
MVC01315	Data Cartridge (XL)	
MVC01316	1200 Ft. Tape (8.5 In.)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
MVC01335	29806 IMS Key Cap Kit	
MVC01347	Quality Audio-Visual	
MVC01421	Filter Connector (50 cond) EMI	A0318423
MVC01498	Uninterruptable Power Supply Unit	
MVC01557	5535 Keyboard w/Keylock	
MVC01906	Screw Package	
MVC02031	COAX Balun	QMT21
MVC02032	TWINAX Balun	QMT21
MVC02033	DUAL COAX Balun	QMT21
MVC02121	Standoff	
MVC02259	Inmac 328 Adapter	A0351509
MVC02400	600MB Hard Disk	
MVC02403	Network Cable NT/XT	
MVC03067	Null Modem Adapter (Male/Female)	NTND93AA
NT0C09BC03	Noisy Location, Handset, Black	
NT0C09BC35	Noisy Location, Handset, Ash	
NT0C09BC93	Noisy Location, Handset, Gray	
NT0C09EK03	Legacy Handset, Black (NT2K models M2006, M2008, M2616, M2216ACD-1	NT0C09EL03
NT0C09EK35	Legacy Handset, Ash (NT2K models M2006, M2008, M2616, M2216ACD-1)	NT0C09EL35
NT0C09EK93	Legacy Handset, Gray (NT2K models M2006, M2008, M2616, M2216 ACD-1	NT0C09EL-93
NT0M96DC	RS232 Cable	
NT0M96DG	RS232 Modem Cable	NTND91AA
NT0M96DQ	10 Ft. M4000 PTR Cable	
NT0M96DT	RS232 Null Modem Cable (50 Ft.)	NTND82AA
NT0M96DU	Null Modem Cable (25 Ft.)	NTND82AB
NT0M96QC	Attendant Handset	
NT0M96QG	Cable	
NT0R03AA	Transport Terminator	
NT0R04AA	Tone Detector	
NT0R08AA	Memory 2M	
NT0R09AA	Processor 68000	
NT0R12AA	Synchronous Data Formatter	
NT0R20AA	Transport Repeater	
NT0R24AA	Transport Controller	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT0R26AA	DS-1 Assembly	
NT0R27AA	Voice Compressor	
NT0R28AA	LANlink Interface Card	
NT0R28AB	LANLink Assembly (NT0R23AB, NT0R25AB)	
NT0R28AC	LanLink Assembly (NT0R23AB, NT0R25AB)	
NT0R30AA	MASI Assembly	
NT0R50AA	Power Monitor PCBA	
NT0R52AA	Digital Power Unit	
NT0R53AA	Disk/Tape Power Unit	
NT0R60AA	MacIntosh II Interface Card and Cable	
NT0R66AA	Memory 6M	
NT0R67AA	InfoLink Interface	
NT0R82AA	Twisted Pair Cable 3 Ft	
NT0R82AB	Twisted Pair Cable 7 Ft	
NT0R82AC	Twisted Pair Cable 14 Ft	
NT0R82AD	Twisted Pair Cable 25 Ft	
NT0R82AE	Twisted Pair Cable 37 Ft	
NT0R82AF	Twisted Pair Cable 50 Ft	
NT1F04HA35	Handsets, BTS Style, Push-To-Talk, Ash	
NT1F04HA93	Handsets, BTS Style, Push-To-Talk, Gray	
NT1F04JA03	Handsets, BTS Style, Push-To-Mute, Black	
NT1F04JA35	Handsets, BTS Style, Push-To-Mute, Ash	
NT1F04JA93	Handsets, BTS Style, Push-To-Mute, Gray	
NT1F04KA35	Handsets, BTS Style, Mercury Switch, Gray	
NT1F05AA35	Meridian M2009 Digital Telephone, Ash	NT1F05AE35
NT1F05AA93	Meridian M2009 Digital Telephone, Gray	NT1F05AE93
NT1F05AB03	Meridian M2009 Digital Telephone, Black	NT1F05AE03
NT1F05AB35	Meridian M2009 Digital Telephone, Ash	NT1F05AE35
NT1F05AB93	Meridian M2009 Digital Telephone, Gray	NT1F05AE93
NT1F05AD03	Meridian M2009 Digital Telephone, Black	NT1F05AE03
NT1F05AD35	Meridian M2009 Digital Telephone, Ash	NT1F05AE35
NT1F05AD93	Meridian M2009 Digital Telephone, Gray	NT1F05AE93
NT1F05AE03	Meridian M2009 Digital Telephone, Black	NTZK08AA03
NT1F05AE35	Meridian M2009 Digital Telephone, Ash	NTZK08AA35

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT1F05AE93	Meridian M2009 Digital Telephone, Gray	NTZK08AA93
NT1F05BA35	Meridian M2009 Digital Telephone with Data, Ash	
NT1F05BA93	Meridian M2009 Digital Telephone with Data, Gray	
NT1F05BB03	Meridian M2009 Digital Telephone with Data, Black	
NT1F05BB35	Meridian M2009 Digital Telephone with Data, Ash	
NT1F05BB93	Meridian M2009 Digital Telephone with Data, Gray	
NT1F05MB03	Meridian M2009 Digital Telephone with Data, Black	NT1F05ME03
NT1F05MB35	Meridian M2009 Digital Telephone with Data, Ash	NT1F05ME35
NT1F05MB93	Meridian M2009 Digital Telephone with Date, Gray	NT1F05ME93
NT1F05MD03	Meridian M2009 Digital Telephone with Data, Black	NT1F05ME03
NT1F05MD35	Meridian M2009 Digital Telephone with Data, Ash	NT1F05ME35
NT1F05MD93	Meridian M2009 Digital Telephone with Data, Gray	NT1F05ME93
NT1F05ME03	Meridian M2009 Digital Telephone with Data, Black	NTZK08AB03
NT1F05ME35	Meridian M2009 Digital Telephone with Data, Ash	NTZK08AB35
NT1F05ME93	Meridian M2009 Digital Telephone with Data, Gray	NTZK08AB93
NT1F06AA35	Meridian M2112 Digital Telephone, Ash	NT1F06AF35
NT1F06AA93	Meridian M2112 Digital Telephone, Gray	NT1F06AF93
NT1F06AB03	Meridian M2112 Digital Telephone, Black	NT1F06AF03
NT1F06AB35	Meridian M2112 Digital Telephone, Ash	NT1F06AF35
NT1F06AB93	Meridian M2112 Digital Telephone, Gray	NT1F06AF93
NT1F06AE03	Meridian M2112 Digital Telephone, Black	NT1F06AF03
NT1F06AE35	Meridian M2112 Digital Telephone, Ash	NT1F06AF35
NT1F06AE93	Meridian M2112 Digital Telephone, Gray	NT1F06AF93
NT1F06AF03	Meridian M2112 Digital Telephone, Black	NTZK16AA03
NT1F06AF35	Meridian M2112 Digital Telephone, Ash	NTZK16AA35
NT1F06AF93	Meridian M2112 Digital Telephone, Gray	NTZK16AA93
NT1F06BA35	Meridian M2112 Digital Telephone with Data, Ash	
NT1F06BA93	Meridian M2112 Digital Telephone with Data, Gray	
NT1F06BB03	Meridian M2112 Digital Telephone with Data, Black	
NT1F06BB35	Meridian M2112 Digital Telephone with Data, Ash	
NT1F06BB93	Meridian M2112 Digital Telephone with Data, Gray	
NT1F06MB03	Meridian M2112 Digital Telephone with Data, Black	NT1F06MF03
NT1F06MB35	Meridian M2112 Digital Telephone with Data, Ash	NT1F06MF35
NT1F06MB93	Meridian M2112 Digital Telephone with Data, Gray	NT1F06MF93

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT1F06ME03	Meridian M2112 Digital Telephone with Data, Black	NT1F06MF03
NT1F06ME35	Meridian M2112 Digital Telephone with Data, Ash	NT1F06MF35
NT1F06ME93	Meridian M2112 Digital Telephone with Data, Gray	NT1F06MF93
NT1F06MF03	Meridian M2112 Digital Telephone with Data, Black	NTZK16AB03
NT1F06MF35	Meridian M2112 Digital Telephone with Data, Ash	NTZK16AB35
NT1F06MF93	Meridian M2112 Digital Telephone with Data, Gray	NTZK16AB93
NT1F07AA03	Meridian M2018 Digital Telephone, Black	NT1F07AC03
NT1F07AA35	Meridian M2018 Digital Telephone, Ash	NT1F07AC35
NT1F07AA93	Meridian M2018 Digital Telephone, Gray	NT1F07AC93
NT1F07AB35	Meridian M2018S Secure Telephone	NT8K90AA35
NT1F07AC03	Meridian M2018 Digital Telephone, Black	NTZK16AA03
NT1F07AC35	Meridian M2018 Digital Telephone, Ash	NTZK16AA35
NT1F07AC93	Meridian M2018 Digital Telephone, Gray	NTZK16AA93
NT1F07BA03	Meridian M2018 Digital Telephone with Data, Black	NT1F07MC03
NT1F07BA35	Meridian M2018 Digital Telephone with Data, Ash	NT1F07MC35
NT1F07BA93	Meridian M2018 Digital Telephone with Data, Gray	NT1F07MC03
NT1F07BB35	Meridian M2018S Secure Telephone with Data, Ash	
NT1F07MA03	Meridian M2018 Digital Telephone with Data, Black	NT1F07MC03
NT1F07MA35	Meridian M2018 Digital Telephone with Data, Ash	NT1F07MC35
NT1F07MA93	Meridian M2018 Digital Telephone with Data, Gray	NT1F07MC93
NT1F07MC03	Meridian M2018 Digital Telephone with Data, Black	NTZK16AB03
NT1F07MC35	Meridian M2018 Digital Telephone with Data, Ash	NTZK16AB35
NT1F07MC93	Meridian M2018 Digital Telephone with Data, Gray	NTZK16AB93
NT1F09AA	Asynchronous Data Option (M2009, M2112, M2018, M2317)	
NT1F10AA	Meridian M3000 Asynchronous Data Option	
NT1F10AB	Meridian M3000 Asynchronous Data Option	
NT1F11AA03	Meridian M3000 Touchphone, Black	NT1F11AK03
NT1F11AB03	Meridian M3000 Touchphone, Black	NT1F11AK03
NT1F11AD03	Meridian M3000 Touchphone, Black	NT1F11AK03
NT1F11AK03	Meridian M3000 Touchphone, Black	
NT1F11BA03	Meridian M3000 Touchphone with Data, Black	NT1F11MK03
NT1F11BB03	Meridian M3000 Touchphone with Data, Black	NT1F11MK03
NT1F11MD03	Meridian M3000 Touchphone with Data, Black	NT1F11MK03
NT1F11MK03	Meridian M3000 Touchphone with Data, Black	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT1F14AA	Kit, Wall Mount	
NT1F21AA03	Meridian M2317 Digital Display Telephone, Black	NT1F21AB03
NT1F21AA35	Meridian M2317 Digital Display Telephone, Ash	NT1F21AB35
NT1F21AA93	Meridian M2317 Digital Display Telephone, Gray	NT1F21AB93
NT1F21AB03	Meridian M2317 Digital Display Telephone, Black	NT1F21AE03
NT1F21AB35	Meridian M2317 Digital Display Telephone, Ash	NT1F21AE35
NT1F21AB93	Meridian M2317 Digital Display Telephone, Gray	NT1F21AE93
NT1F21BA03	Meridian M2317 Digital Display Telephone with Data, Black	NT1F21MB03
NT1F21BA35	Meridian M2317 Digital Display Telephone with Data, Ash	NT1F21MB35
NT1F21BA93	Meridian M2317 Digital Display Telephone with Data, Gray	NT1F21MB93
NT1F21MA03	Meridian M2317 Digital Display Telephone with Data, Black	NT1F21MB03
NT1F21MA35	Meridian M2317 Digital Display Telephone with Data, Ash	NT1F21MB35
NT1F21MA93	Meridian M2317 Digital Display Telephone with Data, Gray	NT1F21MB93
NT1F21MB03	Meridian M2317 Digital Display Telephone with Data, Black	NT1F21ME03
NT1F21MB35	Meridian M2317 Digital Display Telephone with Data, Ash	NT1F21ME35
NT1F21MB93	Meridian M2317 Digital Display Telephone with Data, Gray	NT1F21ME93
NT1F27AA	FastView Software and Documentation	
NT1F27BA	FastView+ Software Upgrade Package and Documentation	NT1F27BB
NT1F27EA	FastView+ Software and Documentation	NT1F27EB
NT1F28BA	FastView+ and MCA Software and Documentation	
NT1F32AA	Remote Agent Hardware and Documentation	
NT1F32BA	Remote Agent Hardware, M2216 and Documentation Marketing Package #1	
NT1F33AA	Remote Agent Hardware, FastView Software and Documentation Marketing Package #2	
NT1F33BA	Remote Agent Hardware, FastView+ Software and Documentation Marketing Package #3	
NT1F34AA	Remote Agent Hardware, FastView Software, MCA, M2216 and Documentation (Marketing Package #4)	
NT1F34BA	Remote Agent Hardware, FastView+ Software, MCA, M2216 and Documentation (Marketing Package #5)	
NT1F35AA	Remote Agent Hardware, FastView Software and Documentation Marketing Package #6	
NT1F35BA	Remote Agent Hardware, FastView Software and Documentation Marketing Package #7	
NT1F4030	Mounting Kit Assembly for QSD81	
NT1F50AA35	Meridian M2018S Secure Telephone, Ash	
NT1F50AB35	Meridian M2018S Secure Telephone with Data, Ash	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT1F59AA	SYMPOSIUM Agent Package 3 (1-50 Agents)	
NT1F59BA	SYMPOSIUM Agent Package 3 (51-100 Agents)	
NT1F59CA	SYMPOSIUM Agent Package 3 (101-200 Agents)	
NT1F59DA	SYMPOSIUM Agent Package 3 (201 + Agents)	
NT1F67AA	SYMPOSIUM Agent Package 1 Base Software	
NT1F69AA	SYMPOSIUM Agent Package 3 Base Software	
NT1F80BA	SYMPOSIUM Agent Upgrade - Package 1 to 3	
NT1F80CA	SYMPOSIUM Agent Upgrade - Package 2 to 3	
NT1F87AA	Symposium Agent Upgrade Package 1 or Package 2 to Package 3 - Base Software	
NT1GS24	Ground Start Bundle	
NT1GS48	Ground Start Bundle	
NT1P61AA	Fiber Superloop Network Card	NT1P61BA
NT1P61BA	Fiber Superloop Network Card	NT1P61CA
NT1P62AA	Fiber Peripheral Controller Card	NT1P62BA
NT1P62BA	Fiber Peripheral Controller Card	NT1P62CA
NT1P62CA	Fiber Peripheral Controller Card	NT1P62EA
NT1P63AA	Electro-Optical Interface Packlet	NT1P63CA
NT1P93AA	Voice Activated Business Directory 4 ports, 500 names	
NT1P93BA	Voice Activated Business Directory 4 ports, 1000 names	
NT1P93CA	Voice Activated Business Directory 4 Ports, 1500 Names	
NT1P94BA	Voice Activated Business Directory 8 Ports, 1000 Names	
NT1P94CA	Voice Activated Business Directory 8 Ports, 1500 Names	
NT1P95AA	Voice Activated Business Directory 4 to 8 Port Expansion Kit	
NT1P98AA	Voice Activated Business Directory 500 Name Expansion Kit	
NT1P98BA	Voice Activated Business Directory 1000 Name Expansion Kit	
NT1P98CA	Voice Activated Business Directory 1500 Name Expansion Kit	
NT1R11AA	Meridian MAX-IPE Supervisors User Guide Release 4.6	
NT1R11CC	Meridian MAX-IPE NTPs Release 4.6	
NT1R20AA	Intelligent OPS Line Card	NT1R20AB
NT1R27AA	Network Administration Center Release 2 Application Tape	NT1R27AB
NT1R28AA	UNIX O/S Tape	NT1R28AB
NT1R32AA	Network Administration Center Release 2 Installation NTP + System Administration and Maintenance Guide	
NT1R33AA	Meridian NAC Release 2 Supervisor’s User Guide (English)	
NT1R34AA	Meridian MAX Release 8 Application Tape	NT1R34AB

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT1R36AA	Meridian MAX Release 8 UNIX O/S Tape	NT1R36AB
NT1R42AA	Application Module Documentation Package	
NT1R43AA	Meridian Link Release 4 Documentation Package	
NT1R54AA	Customer Controlled Routing Release 3 NTPs	
NT1R55AA	Customer Controlled Routing Release 3 User Guide	NT1R55AB
NT1R56AB	CCR 3B & Link 5 Documentation Package	NT1R56AD
NT1R56AB	CCR 3B & Link 5 Documentation Package	NT1R56AE
NT1R56AD	CCR 3B & Link 5 Documentation Package	NT1R56AB
NT1R57AA	Meridian Link & CCR Co-Resident NTPs	NT1R57AB
NT1R57AB	CCR 3B/Link 5 Documentation Package	NT1R57AE
NT1R57AD	CCR 3B/Link 5 Documentation Package	NT1R57AB
NT1R60AA	Meridian MAX Release 5 NTP Package	
NT1R62AA	MAX Release 5 Supervisor Reference Guide	
NT1R67EA	MTE Release 8 Software Upgrade (Single User) for Windows (Multilingual: English, French, Spanish, German)	NTJH09CA
NT1R75BA	Meridian Terminal Emulator (MTE) Release 6 for Windows Software Package	
NT1R75CA	MTE Release 7 Software (Single User) for Windows (Multilingual: English, French, Spanish, German)	NT1R75EA
NT1R75DA	MTE Release 7 Software (Single User) for Windows (English)	
NT1R75EA	MTE Release 8 Software (Single User) for Windows (Multilingual: English, French, Spanish, German)	
NT1R76DA	Meridian MAX Release 8 Capacity Configuration Tool	NT1R76DB
NT1R76EA	Meridian MAX Release 9 Capacity Configuration Tool	NT1R76EB
NT1R79AA	Meridian MAX Release 6 Application Tape	NT1R79AB
NT1R81AA	Meridian MAX Release 6 UNIX O/S Tape	NT1R81AB
NT1R90AA	Option 81 Cardcage Upgrade Parts Kit	
NT1R90CA	IPE Cardcage Expansion Kit	
NT1R96CA	MTE Release 7 Software (System Package) for Windows (Multilingual: English, French, Spanish, German)	
NT1R96DA	MTE Release 7 Software (System Package) for Windows (English)	
NT1R96EA	MTE Release 8 Software (System Package) for Windows (Multilingual: English, French, Spanish, German)	
NT1R97EA	MTE Release 8 Software Upgrade (System Package) for Windows (Multilingual: English, French, Spanish, German)	NTJH09DA
NT1R98BA	MTE Release 7 User Guide (English); Package of 10	
NT2F75AA	Meridian Communications Adapter User Guide (M3900 Series, Package of 15 P0903781)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2F76AA	Meridian Analog Terminal Adapter User Guide (M3900 Series, Package of 15 P0903785)	
NT2G00AA35	Attendant Console M1250	
NT2G00AC35	Attendant Console M1250	
NT2K05GA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	NT2K05GD03
NT2K05GA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	NT2K05GD35
NT2K05GA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	NT2K05GD93
NT2K05GD03	Meridian M2006 Single Line Digital Telephone, Basic, Black	NT9K05AA03
NT2K05GD35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	NT9K05AA35
NT2K05GD93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	NT9K05AA93
NT2K05GT03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	NT2K05GV03
NT2K05GT35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	NT2K05GV35
NT2K05GT93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	NT2K05GV93
NT2K05GV03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	
NT2K05GV35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	
NT2K05GV93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	
NT2K08GA03	Meridian M2008 Standard Business Telephone, Basic, Black	NT2K08GD03
NT2K08GA35	Meridian M2008 Standard Business Telephone, Basic, Ash	NT2K08GD35
NT2K08GA93	Meridian M2008 Standard Business Telephone, Basic, Gray	NT2K08GD93
NT2K08GB03	Meridian M2008HF Standard Business Telephone, Basic, Black	NT2K08GC03
NT2K08GB35	Meridian M2008HF Standard Business Telephone, Basic, Ash	NT2K08GC35
NT2K08GB93	Meridian M2008HF Standard Business Telephone, Basic, Gray	NT2K08GC93
NT2K08GC03	Meridian M2008HF Standard Business Telephone, Basic, Black	NT2K08ZC03
NT2K08GC35	Meridian M2008HF Standard Business Telephone, Basic, Ash	NT2K08ZC35
NT2K08GC93	Meridian M2008HF Standard Business Telephone, Basic, Gray	NT2K08ZC93
NT2K08GD03	Meridian M2008 Standard Business Telephone, Basic, Black	NT9K08AA03
NT2K08GD35	Meridian M2008 Standard Business Telephone, Basic, Ash	NT9K08AA35
NT2K08GD93	Meridian M2008 Standard Business Telephone, Basic, Gray	NT9K08AA93
NT2K08GG03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	
NT2K08GG35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	
NT2K08GG93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	
NT2K08GH03	Meridian M2008 Standard Business Telephone with Display, Black	NT2K08XE03
NT2K08GH35	Meridian M2008 Standard Business Telephone with Display, Ash	NT2K08XE35
NT2K08GH93	Meridian M2008 Standard Business Telephone with Display, Gray	NT2K08XE93
NT2K08GK03	Meridian M2008HF Standard Business Telephone with Display, Black	NT2K08GL03

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2K08GK35	Meridian M2008HF Standard Business Telephone with Display, Ash	NT2K08GL35
NT2K08GK93	Meridian M2008HF Standard Business Telephone with Display, Gray	NT2K08GL93
NT2K08GL03	Meridian M2008HF Standard Business Telephone with Display, Black	NT2K08ZL03
NT2K08GL35	Meridian M2008HF Standard Business Telephone with Display, Ash	NT2K08ZL35
NT2K08GL93	Meridian M2008HF Standard Business Telephone with Display, Gray	NT2K08ZL93
NT2K08GN03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	NT2K08GR03
NT2K08GN35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	NT2K08GR35
NT2K08GN93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	NT2K08GR93
NT2K08GP03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	NT2K08GS03
NT2K08GP35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	NT2K08GS35
NT2K08GP93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	NT2K08GS93
NT2K08GR03	Meridian M2008 Standard Business Telephone with Display and MCA Data, Black	NT2K08GG03
NT2K08GR35	Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash	NT2K08GG35
NT2K08GR93	Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray	NT2K08GG93
NT2K08GS03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	NT2K08ZS03
NT2K08GS35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	NT2K08ZS35
NT2K08GS93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	NT2K08ZS93
NT2K08GT03	Meridian M2008 Standard Business Telephone with MCA Data, Black	NT2K08GV03
NT2K08GT35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	NT2K08GV35
NT2K08GT93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	NT2K08GV93
NT2K08GU03	Meridian M2008HF Standard Business Telephone with MCA Data, Black	NT2K08GX03
NT2K08GU35	Meridian M2008HF Standard Business Telephone with MCA Data, Ash	NT2K08GX35
NT2K08GU93	Meridian M2008HF Standard Business Telephone with MCA Data, Gray	NT2K08GX93
NT2K08GV03	Meridian M2008 Standard Business Telephone with MCA Data, Black	
NT2K08GV35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	
NT2K08GV93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	
NT2K08GX03	Meridian M2008HF Standard Business Telephone with MCA Data, Black	
NT2K08GX35	Meridian M2008HF Standard Business Telephone with MCA Data, Ash	
NT2K08GX93	Meridian M2008HF Standard Business Telephone with MCA Data, Gray	
NT2K08XE03	Meridian M2008 Standard Business Telephone with Display, Black	NT2K08XF03
NT2K08XE35	Meridian M2008 Standard Business Telephone with Display, Ash	NT2K08XF35

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2K08XE93	Meridian M2008 Standard Business Telephone with Display, Gray	NT2K08XF93
NT2K08XF03	Meridian M2008 Standard Business Telephone with Display, Black	NT9K08AC03
NT2K08XF35	Meridian M2008 Standard Business Telephone with Display, Ash	NT9K08AC35
NT2K08XF93	Meridian M2008 Standard Business Telephone with Display, Gray	NT9K08AC93
NT2K08ZC03	Meridian M2008HF Standard Business Telephone, Basic, Black	NT9K08AB03
NT2K08ZC35	Meridian M2008HF Standard Business Telephone, Basic, Ash	NT9K08AB35
NT2K08ZC93	Meridian M2008HF Standard Business Telephone, Basic, Gray	NT9K08AB93
NT2K08ZL03	Meridian M2008HF Standard Business Telephone with Display, Black	NT9K08AD03
NT2K08ZL35	Meridian M2008HF Standard Business Telephone with Display, Ash	NT9K08AD35
NT2K08ZL93	Meridian M2008HF Standard Business Telephone with Display, Gray	NT9K08AD93
NT2K08ZS03	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black	
NT2K08ZS35	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash	
NT2K08ZS93	Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray	
NT2K10WA	Power Supply Board	NT2K10WC
NT2K10WB	Power Supply Board	NT2K10WC
NT2K10WC	Power Supply Board	NT2K10WD
NT2K16GA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	NT2K16GD03
NT2K16GA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	NT2K16GD35
NT2K16GA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	NT2K16GD93
NT2K16GD03	Meridian M2616 Performance-Plus Telephone, Basic, Black	NT9K16AA03
NT2K16GD35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	NT9K16AA35
NT2K16GD93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	NT9K16AA93
NT2K16GG03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	
NT2K16GG35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	
NT2K16GG93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	
NT2K16GH03	Meridian M2616 Performance-Plus Telephone with Display, Black	NT2K16XE03
NT2K16GH35	Meridian M2616 Performance-Plus Telephone with Display, Ash	NT2K16XE35
NT2K16GH93	Meridian M2616 Performance-Plus Telephone with Display, Gray	NT2K16XE93
NT2K16GN03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	NT2K16GR03
NT2K16GN35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	NT2K16GR35
NT2K16GN93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	NT2K16GR93
NT2K16GR03	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black	NT2K16GG03

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2K16GR35	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash	NT2K16GG35
NT2K16GR93	Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray	NT2K16GG93
NT2K16GT03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	NT2K16GV03
NT2K16GT35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	NT2K16GV35
NT2K16GT93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	NT2K16GV93
NT2K16GV03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	
NT2K16GV35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	
NT2K16GV93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	
NT2K16XE03	Meridian M2616 Performance-Plus Telephone with Display, Black	NT2K16XF03
NT2K16XE35	Meridian M2616 Performance-Plus Telephone with Display, Ash	NT2K16XF35
NT2K16XE93	Meridian M2616 Performance-Plus Telephone with Display, Gray	NT2K16XF93
NT2K16XF03	Meridian M2616 Performance-Plus Telephone with Display, Black	NT9K16AC03
NT2K16XF35	Meridian M2616 Performance-Plus Telephone with Display, Ash	NT9K16AC35
NT2K16XF93	Meridian M2616 Performance-Plus Telephone with Display, Gray	NT9K16AC93
NT2K18GG03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	
NT2K18GG35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	
NT2K18GG93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	
NT2K18GH03	Meridian M2216 ACD-1 Basic Telephone, Black	NT2K18XE03
NT2K18GH35	Meridian M2216 ACD-1 Basic Telephone, Ash	NT2K18XE35
NT2K18GH93	Meridian M2216 ACD-1 Basic Telephone, Gray	NT2K18XE93
NT2K18GN03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	NT2K18GR03
NT2K18GN35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	NT2K18GR35
NT2K18GN93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	NT2K18GR93
NT2K18GR03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	NT2K18GG03
NT2K18GR35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	NT2K18GG35
NT2K18GR93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	NT2K18GG93
NT2K18XE03	Meridian M2216 ACD-1 Basic Telephone, Black	NT2K18XF03
NT2K18XE35	Meridian M2216 ACD-1 Basic Telephone, Ash	NT2K18XF35
NT2K18XE93	Meridian M2216 ACD-1 Basic Telephone, Gray	NT2K18XF93
NT2K18XF03	Meridian M2216 ACD-1 Basic Telephone, Black	NT9K18AC03
NT2K18XF35	Meridian M2216 ACD-1 Basic Telephone, Ash	NT9K18AC35
NT2K18XF93	Meridian M2216 ACD-1 Basic Telephone, Gray	NT9K18AC93
NT2K22WA03	Meridian Key Expansion Module, Black	NT2K22XH03
NT2K22WA35	Meridian Key Expansion Module, Ash	NT2K22XH35

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2K22WA93	Meridian Key Expansion Module, Gray	NT2K22XH93
NT2K22XH03	Meridian Key Expansion Module, Black	
NT2K22XH35	Meridian Key Expansion Module, Ash	NY2K22VH35
NT2K22XH93	Meridian Key Expansion Module, Gray	NY2K22VH93
NT2K24KA03	Meridian Japanese Display Option, Black	NT2K28KA03
NT2K24KA35	Meridian Japanese Display Option, Ash	NT2K28KA35
NT2K24KA93	Meridian Japanese Display Option, Gray	NT2K28KA93
NT2K24WA03	Meridian Display Option, Black	NT2K28AA03
NT2K24WA35	Meridian Display Option, Ash	NT2K28AA35
NT2K24WA93	Meridian Display Option, Gray	NT2K28AA93
NT2K25YH03	ACD Display Option, Black	
NT2K25YH35	ACD Display Option, Ash	
NT2K25YH93	ACD Display Option, Gray	
NT2K25YJ03	Meridian ACD Display Option, Black	NT2K25YL03
NT2K25YJ35	Meridian ACD Display Option, Ash	NT2K25YL35
NT2K25YJ93	Meridian ACD Display Option, Gray	NT2K25YL93
NT2K25YL03	Special Applications Display, Black	NT2K28AA03
NT2K25YL35	Special Applications Display, Ash	NT2K28AA35
NT2K25YL93	Special Applications Display, Gray	NT2K28AA93
NT2K28AA03	Meridian Display Option, Black	NT2K28AB03
NT2K28AA35	Meridian Display Option, Ash	NT2K28AB35
NT2K28AA93	Meridian Display Option, Gray	NT2K28AB93
NT2K28AC03	Meridian Display Option, Black (3 Language)	NT2K28AD03
NT2K28AC35	Meridian Display Option, Ash (3 Language)	NT2K28AD35
NT2K28AC93	Meridian Display Option, Gray (3 Language)	NT2K28AD93
NT2K28KA03	Meridian Japanese Display Option, Black	NT2K28KB-03
NT2K28KA35	Meridian Japanese Display Option, Ash	NT2K28KB-35
NT2K28KA93	Meridian Japanese Display Option, Gray	NT2K28KB-93
NT2K36AA03	Meridian M2616CT (Cordless Telephone), Black	
NT2K36AA35	Meridian M2616CT (Cordless Telephone), Ash	
NT2K36AA93	Meridian M2616CT (Cordless Telephone), Gray	
NT2K64WA	Meridian Programmable Data Adapter	NT2K64WB
NT2K64WB	Meridian Programmable Data Adapter	NT2K64WC
NT2K64WC	Meridian Programmable Data Adapter	NT2K65XH

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2K65XH	Meridian Communications Adapter	NT2K65XJ
NT2K65XJ	Meridian Communications Adapter	NT2K65XR
NT2K80AA	Literature Pack (M2616, M2016S)	NT2K80GB
NT2K80AB	Literature Pack (M2006, M2008)	A0615902
NT2K84AA	Meridian M2616CT Handset Accessory Package (Standard)	
NT2R02AA	Basic Cabinet	
NT2R03AA	Power Distribution Unit	
NT2R05AA	Power Monitor Shelf	
NT2R07AA	Digital Shelf	
NT2R08AA	I/O Cable	
NT2R08AC	Infolink Cable	
NT2R08AD	Rectifier Input Cable	
NT2R08AE	Cabinet Harness	
NT2R08AG	DS-1 Cable	
NT2R08AH	Dual Transport Cable	
NT2R08AJ	Single Transport Cable	
NT2R08AK	Power Monitor Comm Cable	
NT2R08AN	LANLink I/o Cable	
NT2R08AR	Processor Cable	
NT2R08AS	DTI Crosscable	
NT2R08AT	SEER Cable	
NT2R08AU	Cable (3-Pos, 50-Pin)	
NT2R08AV	Cable (20-Pos, 20-Pin)	
NT2R08AW	Cable (20-Pin, A-Slot)	
NT2R08AX	Cable (20-Pin, Z-Slot)	
NT2R0901	Power Harness (NT2R24AA)	
NT2R12AA	Power Monitor Backplane	
NT2R15AA	LANSTAR 8 Kit	
NT2R16AA	Blank Faceplate (1.75) (NT2R07AA & NT2R05AA)	
NT2R17AA	Blank Faceplate (2.625) (NT2R07AA & NT2R05AA)	
NT2R18AA	Blank Faceplate (.875) (NT2R07AA & NT2R05AA)	
NT2R19AA	Cabinet Expansion Kit (NT0R02AA) (A0311688)	
NT2R21AA	DC Power Panel	
NT2R22AA	Front Door Assembly (NT2R02AA)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT2R23AA	Blower Unit	
NT2R24AA	Disk/Tape Shelf	
NT2R25AA	P-Bus 5 Segment	
NT2R26AA	P-Bus 4 Segment	
NT2R2703	Cable (3-Pos, 20-Pin)	
NT2R27AA	P-Bus 3 Segment	
NT2R28AA	P-Bus 2 Segment	
NT2R29AA	Rear Door Assembly (NT2R02AA)	
NT2R31AA	Fuse Kit	
NT2R50AA	50M Streaming Tape	
NT2R51AC	Meridian Link/CCR Co-Resident Application Tape Assembly	NT2R51AD
NT2R51AC	Meridian Link/CCR Co-Resident Application Tape Assembly	NT2R51AF
NT2R51AD	Meridian Link/CCR Co-Resident Application Tape Assembly	NT2R51AF
NT2R54AA	3270 Host Communications - SDLC - 4 Ports	
NT2R54BA	3270 Host Communications - SDLC - 8 Ports	
NT2R54CA	3270 Host Communications - SDLC - 16 Ports	
NT2R55AA	3270 Host Communications - Token Ring - 4 Ports	
NT2R55BA	3270 Host Communications - Token Ring - 8 Ports	
NT2R55CA	3270 Host Communications - Token Ring - 16 Ports	
NT2R56AA	5250 Host Communications - SDLC - 4 Ports	
NT2R56BA	5250 Host Communications - SDLC - 8 Ports	
NT2R56CA	5250 Host Communications - SDLC - 16 Ports	
NT2R57AA	5250 Host Communications - Token Ring - 4 Ports	
NT2R57BA	5250 Host Communications - Token Ring - 8 Ports	
NT2R57CA	5250 Host Communication - Token Ring - 16 Ports	
NT2R59AA	SYMPOSIUM TAPI Service Provider Security Device	NT2R59BA
NT2R70AA	234M Disk	
NT2R8601	Audio Interface Unit Hardware	
NT2R96AA	Meridian Text Telephony System - 25 User System Package	
NT2R96BA	Meridian Text Telephony System - 50 User System Package	
NT2R96CA	Meridian Text Telephony System - 100 User System Package	
NT2R96DA	Meridian Text Telephony System - 250 User System Package	
NT2R99BA	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly (French)	
NT3G40AA35	Busy Lamp Field/Console Graphics Module	NT3G40AB35

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT3G40AB35	Busy Lamp Field/Console Graphics Module	NT3G40BB35
NT3M20AA	HP Terminal	A0376839
NT3M36AE	LANSTAR PS/2 MC Adapter Card	
NT3M50AC	UDS Modem	A0345963
NT3M56AC	HP ThinkJet Printer	A0345125
NT3R01EA	3270 SNA SDLC Manuals	
NT3R04AA	OIVR 2.x Hardware - IVR Documentation Package	
NT3R05AA	OIVR 2.x Hardware - IVR Operational Documentation Package	
NT3R06AA	OIVR 2.x Hardware - IVR Development Documentation Package	
NT3R07AA	OIVR 2.x Hardware - IVR Options Documentation Package	
NT3R10AA	MRS/AP Base Development System (12 Ports Loopstart)	
NT3R10BA	MRS/AP Base Development System (8 ports ISDN/BRI, 5 hours)	
NT3R10CA	MRS/AP Base Development System (24 Ports T1)	
NT3R10DA	MRS/AP Base Development System (4 Ports Loopstart)	
NT3R10EA	MRS/AP Base Development System (30 ports E1)	
NT3R11AA	MRS/AP Base Runtime System (12 Ports Loopstart)	
NT3R11BA	MRS/AP Base Runtime System (8 ports ISDN/BRI, 5 hours)	
NT3R11CA	MRS/AP Base Runtime System (24 Ports T1)	
NT3R11DA	MRS/AP Base Runtime System (4 Port Loopstart)	
NT3R11EA	MRS/AP Base Runtime System (30 ports E1)	
NT3R12BA	8-Port ISDN/BRI Voice Port Assembly for MRS/AP	
NT3R12CA	OIVR 2.X Hardware - 24-Port T1 Voice Port Assembly for MRS/AP	NTV462NA
NT3R12DA	OIVR 2.X Hardware - 4-Port Loopstart Voice Assembly for MRS/AP	NTV464NA
NT3R12EA	30-Port E1 Voice Port Assembly for MRS/AP	
NT3R13AA	MRS/Tower Base System (12 Port Loopstart)	
NT3R13BA	MRS/tower Base System (8 port ISDN/BRI, 40 hours)	
NT3R13CA	MRS/Tower Base System (24 Port T1) Assembly	
NT3R13EA	MRS/Tower Base System (30 port E1)	
NT3R14AA	MRS/Rack Base System with AC Power (12 Port Loopstart)	
NT3R14BA	MRS/Rack Base System with AC Power (8 port ISDN/BRI, 40 hours)	
NT3R14CA	MRS/Rack Base System with AC Power (24 Port T1)	
NT3R14EA	MRS/Rack Base System with AC Power (30 port E1)	
NT3R15AA	MRS/Rack Base System with DC Power (12 Port Loopstart)	
NT3R15BA	MRS/Rack Base System with DC Power (8 port ISDN/BRI, 40 hours)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT3R15CA	MRS/Rack Base System with DC Power (24 Port T1)	
NT3R15EA	MRS/Rack Base System with DC Power (30 port E1)	
NT3R16AA	Application Processor - Development	
NT3R16BA	Application Processor - Runtime	
NT3R17AA	12-Port Loopstart Voice Port Assembly for MRS/Tower or MRS/Rack	
NT3R17BA	8-Port ISDN/BRI Voice Port Assembly for MRS/Tower or MRS/Rack	
NT3R17CA	24-Port T1 Voice Port Assembly for MRS/Tower or MRS/Rack	
NT3R17EA	30-Port E1 Voice Port Assembly for MRS/Tower or MRS/Rack	
NT3R18AA	VT100 Host Communications - 8 Ports	
NT3R18BA	VT100 Host Communications - 16 Ports	
NT3R18CA	VT100 Host Communications - 32 Ports	
NT3R19AA	3270 Host Communications - SDLC	
NT3R19BA	3270 Host Communications - Token Ring (32 Sessions)	
NT3R20AA	5250 Host Communications - SDLC	
NT3R20BA	5250 Host Communications - Token Ring	
NT3R24AA	OIVR 2.x Hardware - MRS/AP or AP 32MB Memory Upgrade	NTVE9923
NT3R25AA	Meridian IVR Development System, 4 port, Option 21-81 (75MHz, 32MB RAM)	
NT3R25BA	Meridian IVR Development System, 2 port, Option 11 (75 MHz, 32 MB RAM)	
NT3R25CA	Meridian IVR Development System, 4 port, Option 11-81	
NT3R25DA	Meridian IVR Development System, 2 port, Option 11	NT3R25CA
NT3R26AA	Meridian IVR Run-time System, 4 port, Option 21-81 (75MHz, 32 MB RAM)	
NT3R26BA	Meridian IVR Run-time System, 2 port, Option 11 (75MHz, 32 MB RAM)	
NT3R26CA	Meridian IVR Run-Time System, 4 port, Option 11-81	
NT3R26DA	Meridian IVR Run-Time System, 2 port, Option 11	NT3R26CA
NT3R27AA	Meridian IVR Development System - Upgrade from Release 1 (75MHz, 32 MB RAM)	
NT3R27BA	Meridian IVR Development System-Upgrade from Release 1	
NT3R29AA	Meridian IVR Development 4 Port Expansion Software Option 21-81	
NT3R29CA	Meridian IVR Development 2 port Expansion Software Option 11	
NT3R30AA	Meridian IVR Run-Time 4 Port Expansion Software Option 21-81	
NT3R30CA	Meridian IVR Run-time 2 Port Expansion Software Option 11	
NT3R31AA	Meridian IVR Run-Time to Development System Upgrade, 4 Port Expansion Software, Options 21-81	
NT3R31CA	Meridian IVR Run-time to Development System upgrade, 2 port Expansion Software, Option 11	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT3R32CA	Meridian IVR VT100 Host Communication	
NT3R33AA	Meridian IVR FAX Response Software Initial 2 Ports	
NT3R33BA	Meridian IVR FAX Response Expansion Software, 1 Port	
NT3R34AA	Meridian IVR FAX Response Hardware, 4 Port	
NT3R35AA	Meridian IVR SQL Ingres Database Access	
NT3R35BA	Meridian IVR SQL Oracle Database Access	
NT3R35CA	Meridian IVR SQL Informix Database Access	
NT3R35DA	Meridian IVR SQL Sybase Database Access	
NT3R39AA	32 Session Expansion for 3270 or 5250	
NT3R43AA	Meridian IVR Run-Time to Development System Upgrade, Initial 4 Ports Option 21-81	
NT3R43BA	Meridian IVR Run-time to Development System upgrade, Initial 2 ports Option 11	NT3R43AA
NT3R45AA	Meridian IVR 3270 SNA/SDLC Host Communications	
NT3R45BA	Meridian IVR 3270 Over Token Ring Host Communications	
NT3R45CA	Meridian IVR 5250 over SNA/SDLC Host Communications	
NT3R45DA	Meridian IVR 5250 over Token Ring Host Communication	
NT3R46AA	Meridian IVR Uninterruptible Power Supply (UPS) for Application Processor	
NT3R53CA	CCIP Meridian 1 Connectivity, Initial 12 Ports	
NT3R53DA	CCIP Meridian 1 Connectivity, 12 Port Expansion	
NT3R7201	SYMPOSIUM Call Center Release 1 Capacity Assessment Tool	NT3R7209
NT3R7204	SYMPOSIUM Call Center Release 1 Client Software	
NT3R7209	SYMPOSIUM Call Center Capacity Assessment Tool	NT9F45AB
NT3R7212	SYMPOSIUM Call Center Release 1.0 French Client CD-ROM	
NT3R74AA	OIVR 2.x Hardware - MRS/AP or AP Uninterruptible Power Supply	NTV405UA
NT3R74CA	MRS/Tower or MRS/Rack (AC) Uninterruptible Power Supply	
NT3R79AA	Text-To-Speech (4 ports)	
NT3R80AA	Analog Display Service Interface (ADSI) Support	
NT3R81AA	Disk Mirroring Software for MRS/Tower or MRS/Rack	NT3R81AB
NT3R81AB	Disk Mirroring Software for MRS/Tower or MRS/Rack	
NT3R82BA	MRS/AP or AP 17 Inch SVGA Monitor	NTV404MA
NT3R87AA	OIVR 2.x Hardware - Operational NTP Assembly	
NT3R92AA	MRS/Rack DC Base System (12 port LS) Assembly	NT3R92AB
NT3R92CA	MRS/Rack DC Base System (24 port T1) Assembly	NT3R92CB
NT3R93AA	MRS/Tower Base System (12 port LS) Assembly	NT3R93AB
NT3R93CA	MRS/Tower Base System (24 port T1) Assembly	NT3R93CB

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT3R94AA	MRS/Rack AC Base System (12 port LS) Assembly	NT3R94AB
NT3R94CA	MRS/Rack AC Base System (24 port T1) Assembly	NT3R94CB
NT4G08BA	187 MB Hard Disk Assembly	
NT4G08BB	350 MB Hard Disk Assembly	
NT4G08CA	Tape Assembly	
NT4G09BC	Trunk Cable (15 Ft.)	
NT4G09CC	Trunk Cable (30 Ft.)	
NT4G09DC	Trunk Cable (60 Ft.)	
NT4G09EC	Trunk Cable (90 Ft.)	
NT4G13AJ	110 VAC Power Supply	
NT4G13AK	-48 VDC Wiring Harness	
NT4G13AL	-48 VDC Wiring Harness $725-650 (Replaces NT4G13AK)	
NT4G13BA	MS-1 Cabinet Door Latch	
NT4G13EB	Power Supply	
NT4G13FA	MS-1 Cabinet	
NT4G23AD	Digital Trunk Cable 50 Ft.	
NT4G23AE	Connector Kit	
NT4G23BA	Digital Trunk Line Cable 50 Ft.	
NT4G25CA	Application Processor 3MB	
NT4G25CB	2 Meg Memory	
NT4G26AC	SCSI RAM	
NT4G32BA	Digital Trunk Link SRU	
NT4G40CA	Horizontal Jumper	
NT4G41BA	Vertical Jumper	
NT4G42CA	Input Jumper	
NT4G46CA	LAN Interface Unit	
NT4G46JD	LANSTAR PS/2 MC Adapter Card	
NT4G46KD	PS/2 MC Adapter Card	
NT4G46LD	16 Bit Adapter	
NT4G50DA	-48 VDC Power Converter	
NT4G59AB	Multi-Signal Processor (MSP)	
NT4G59AC	ESBC	NT4R09BA
NT4G59AF	2 Meg Memory	NT4R44AA
NT4G59AG	SCSI RAM	NT4R45AA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT4G81YE	Reservations Software	
NT4N65AA	cPCI Core Network Interface Card (2 Ports)	
NT4N66AA	cPCI Core Network Interface Transition Card	NT4N66AB
NT4R01AA	Network Voice Processor	NT4R01AC
NT4R03AA	RS232C Service Module	NT4R03AB
NT4R04AA	General Purpose Signal Processor	
NT4R05AA	PE Shelf (Center Mount)	
NT4R05AB	Meridian Mail PE Shelf (Center)	
NT4R06AA	PE Shelf (Cantilever)	
NT4R06AB	Meridian Mail PE Shelf (Cantilever)	
NT4R09AA	ESBC (Bus)	NT4R09BA
NT4R09BA	ESBC (Bus)	
NT4R2104	Dual Network/Intra-Connection Cable (Center)	
NT4R2106	155MB Hard Disk Assembly	NT4R2107
NT4R2107	300MB Hard Disk Drive	
NT4R2108	600MB Hard Disk Drive	NT4R2109
NT4R2109	1.0GB Hard Disk Drive	
NT4R28AA	Tape Drive	NT4R28AC
NT4R28AB	Tape Drive Unit	NT4R28BA
NT4R28AC	Tape Drive Unit	NT6D45CA
NT4R30AA	GSP Tier 1 Cable Router	
NT4R30AB	NVP Tier 1 Cable Router	
NT4R30AC	GSP Tier 2 Cable Router	
NT4R30AD	NVP Tier 2 Cable Router	
NT4R30AE	GSP Tier 3 Cable Router	
NT4R30AF	NVP Tier 3 Cable Router	
NT4R32AA	Power Supply	
NT4R33AA	Circuit Breaker Panel	
NT4R44AA	2 Meg Memory	NT4R71AA
NT4R57AA	Meridian Mail Bus Cable	
NT4R58AA	RSM Cable	NT4R58AB
NT4R61BA	NVP Extension Cable	
NT4R68AA	Meridian Access RSM Assembly - Modular	AS7008A
NT4R68AA	Meridian Access RSM Assembly - Modular	AS7008D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT4R69AA	Meridian Access RSM Assembly - Non-Modular	AS7009A
NT4R69AA	Meridian Access RSM Assembly - Non-Modular	AS7009D
NT4R71AA	2.5MB Memory	
NT5C03	Rectifier, 50 Amp	NT5C03BJ
NT5C03BJ	Rectifier, 50 Amp	AS1204D
NT5C03CH	50 Amp Rectifier	AS1204D
NT5C04	Control Card for NT5C03 Rectifier	NT5C04CA
NT5C04CA	Control Card for NT5C03 Rectifier	
NT5C06CA	MPR25E Modular Power Rectifier, 25 Amps	NT5C06CC
NT5C07AB	50 Amp Rectifier	
NT5C10CC	MPS75 Modular Power Shelf, 75 Amps	NT5C10CC1
NT5D03AA	68060 Enhanced 48MB Call Processor	NT5D03FB
NT5D03BA	68060 Enhanced 64MB Call Processor	NT5D03FB
NT5D03CA	68060 Enhanced 80MB Call Processor	NT5D03FB
NT5D03EA	68060 Enhanced 112MB Call Processor	NT5D03FB
NT5D03FA	68060 Enhanced 128MB Call Processor	NT5D03FB
NT5D10AA	68060/48MB Call Processor	
NT5D10CA	68060/64MB Call Processor	
NT5D10EA	68060/80MB Call Processor	
NT5D10JA	68060/112MB Call Processor	
NT5D11AA	Line-Side T1 Interface Card	NT5D11AB
NT5D11AB	Line-Side T1 Interface Card	NT5D11AC
NT5D11AC	Line-Side T1 Interface Card	NT5D11AD
NT5D11AD	Line-Side T1 Interface Card	NT5D11AE
NT5D12AA	Dual-Port DTI/PRI (DDP) Card	NT5D12AB
NT5D12AB	Dual-Port DTI/PRI (DDP) Card	NT5D12AC
NT5D12AC	Dual-Port DTI/PRI (DDP) Card	NT5D12AD
NT5D12AD	Dual-Port DTI/PRI (DDP) Card	NT5D12AF
NT5D12AF	Dual Port DTI/PRI (DDP) Card	
NT5D14AA	Line-side T1 Interface Card (Option 11)	NT5D14AB
NT5D14AB	Line-Side T1 Interface Card (Option 11/11E/11C)	NT5D14AC
NT5D14AB	Line-Side T1 Interface Card (Option 11/11E/11C)	NT5D14AD
NT5D14AC	Line-Side T1 Interface Card (Option 11/11E/11C)	NT5D14AD
NT5D16AA	Meridian 1 Trunk Tip/Ring Cable (8 Ft)	NT5D16BA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5D16CA	Meridian 1 Trunk Tip/Ring Cable (8 Ft) NT, XT	NT5D16EA
NT5D20AA	IOP/CMDU Card	NT5D20BA
NT5D20BA	IOP/CMDU Card	NT5D61AB
NT5D2103	Core/Network Cardcage (AC/DC)	NT5D2104
NT5D51AA	Meridian Integrated Conference Bridge Base Card	
NT5D51AB	Meridian Integrated Conference Bridge (Release 2) Base Card	
NT5D52AA	Ethernet Adapter (Options 21-81C)	NT5D52AB
NT5D52AB	Ethernet Adapter (Options 21-81C)	NT5D52AC
NT5D52BA	Ethernet Adapter for Option 11C	NT5D52BB
NT5D52BB	Ethernet Adapter for Option 11C	NT5D52BC
NT5D61AA	Input/Output Drive Unit with CD-ROM	NT5D61AB
NT5D62AA	Meridian Integrated Conference Bridge PCMCIA Drive	NT5D62BA
NT5D62BA	Meridian Integrated Conference Bridge PCMCIA Drive	NT5D62BB
NT5D64AA	Local Mini Carrier Interface Card (Options 21-81)	NT5D64BA
NT5D64BA	Local Mini Carrier Interface Card (Options 21-81)	NT5D64CA
NT5D65AA	Local Mini Carrier Extender Card (Options 21-81)	NT5D65BA
NT5D65BA	Local Mini Carrier Extender Card (Options 21-81)	NT5D65CA
NT5D67AA	Remote Mini Carrier Interface Card	NT5D67BA
NT5D67BA	Remote Mini Carrier Interface Card	NT5D67CA
NT5D68AA	Local Mini Carrier Interface Card (Option 11)	NT5D68BA
NT5D68BA	Local Mini Carrier Interface Card (Option 11)	NT5D68CA
NT5D69AA	Local Mini Carrier Extender Card (Option 11)	NT5D69BA
NT5D69BA	Local Mini Carrier Extender Card (Option 11)	NT5D69CA
NT5D83AA	Nortel SYMPOSIUM Messenger Demo CD-ROM	
NT5F37AA	Fiber Network Reference Guide	NT5F36AA
NT5F50AA	Meridian M2006, M2008, M2008HF & M2616 User Guide (pk of 15 P0834425)	NT5F50AB
NT5F50AB	Meridian M2006, M2008, M2008HF & M2616 User Guide (Package of 15 P0820918)	
NT5F51AA	Meridian M1006, M2008 and M2616 User Card (Quick Reference Card, Pk of 100 Ea. P0722007)	NT5F53AA
NT5F53AA	Meridian Modular Telephones & Options Quick Reference Guide (Package of 15 ea. P0815252)	NT5F53AC
NT5F55AA	M2216 User Guide (Pk of 15 P0831877)	NT5F55AB
NT5F55AB	M2216 User Guide (Package of 15 P0859507)	NT5F55AC
NT5F69AA	Meridian M2616CT User Guide (Package of 15 of P0838286)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5F83AA	Meridian Mail 11 Modular Option EC Manual (Release 1)	
NT5F90AA	Meridian Mail 11 Overview (Release 11) (All)	
NT5F96AA	Compact Option Mail Documentation Package	
NT5F97AA	Meridian Mail Compact Option User Guide Package	NT1F94AA
NT5G53AA	MIPCD Kit	NT5G53AB
NT5G91AA	MIPCD PCMCIA Drive	NT5G91AB
NT5K1110	Backplane to Network Cable	
NT5P41TC	MAS - Model 500 Serial Card Kit	
NT5P43DF	VISIT FastCall 1.1 without Connectivity	
NT5P44FA	VISIT FastCall 1.1 with TelAdaptor Connectivity	
NT5P44FB	VISIT FastCall 1.1 with MCA Connectivity/cables	
NT5P46FA	VISIT FastCall/NTS Version 1.1	
NT5P46GA	VISIT FastCall/NTS Version 1.1 Upgrade	
NT5P46HA	VISIT FastCall/NTS Upgrade Right to Use	
NT5P46JA	VISIT FastCall/NTS Right To Use	
NT5P46LA	VISIT FastCall/NTS Version 1.1 for Option 11	
NT5P46MA	VISIT FastCall/NTS Right to Use for Option 11	
NT5P46NA	VISIT FastCall/NTS Upgrade Right To Use for Option 11	
NT5P46PA	VISIT FastCall/NTS Version 1.1 Upgrade for Option 11	
NT5P60AA	Meridian 1 NTS Driver	NT5P60AB
NT5P60AB	Meridian 1 NTS Release 2.0 Driver Package	
NT5P60AC	Meridian 1 NTS Release 2.0 IVR Integration Option	
NT5P60AD	Meridian 1 NTS Release 2.0 Meridian Mail Tool Option	
NT5P61AA	Meridian Link TCP/IP Software Upgrade	
NT5P9201	Voice Activated Business Directory Color Monitor	
NT5P9203	Voice Activated Business Directory Back-up Drive	
NT5P92AA	Voice Activated Business Directory 4 ports, 1500 names	
NT5P92AB	Voice Activated Business Directory 4 ports, 4000 names	
NT5P92BA	Voice Activated Business Directory 8 ports, 1500 names	
NT5P92BB	Voice Activated Business Directory 8 ports, 4000 names	
NT5R05AA	LANSTAR Blower	
NT5R07AA	Power Supply (LANSTAR Cabinet)	
NT5R08AA	Power Harness	
NT5R09AA	I/O Cable (33 In.)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5R09AB	I/O Cable (42 In.)	
NT5R09AE	I/O Cable (31 In.)	
NT5R09AF	I/O Cable (40 In.)	
NT5R11AA	Meridian Mail Master Tape - Asia/Pacific	NT5R11BA
NT5R11BA	Meridian Mail Master Tape - Asia/Pacific, Release 8	NT5R11BB
NT5R11BB	Meridian Mail Master Tape - Asia/Pacific, Release 8	
NT5R12AA	Meridian Mail Master Tape - North American, Release 8	NT5R12AB
NT5R12AB	Meridian Mail Master Tape - North American, Release 8	NT5R12AC
NT5R13AA	Meridian Mail Master Tape - European 1, Release 8	NT5R13AB
NT5R13AB	Meridian Mail Master Tape - European 1, Release 8	NT5R13AC
NT5R13AC	Meridian Mail Master Tape - European 1, Release 8	
NT5R13BB	Meridian Mail Master Tape - European 2, Release 8	NT5R13BC
NT5R13BC	Meridian Mail Master Tape - European 2, Release 8	
NT5R13CC	Meridian Mail Master Tape - European 3, Release 8	NT5R13CD
NT5R13CD	Meridian Mail Master Tape - European 3, Release 8	
NT5R16CA	Meridian Mail Master Tape - Asia/Pacific, Release 9	NT5R35FA
NT5R17CA	Meridian Mail Master Tape - North American, Release 9	NT5R35AA
NT5R18HA	Meridian Mail Master Tape - Europe 1, Release 9	NT5R35BA
NT5R18JA	Meridian Mail Master Tape - Europe 2, Release 9	NT5R35CA
NT5R18KA	Meridian Mail Master Tape - Europe 3, Release 9	NT5R35DA
NT5R18LA	Meridian Mail Master Tape - Europe 4, Release 9	NT5R35EA
NT5R33AA	Meridian Mail Master Tape - North America, Release 10	NT5R33AB
NT5R33AB	Meridian Mail Master Tape - North America, Release 10	NT5R33AD
NT5R33AD	Meridian Mail Master Tape - North America, Release 10	NT5R33AS
NT5R33AS	Meridian Mail Master Tape - North America, Release 10	NT5R33AU
NT5R33BA	Meridian Mail Master Tape - Europe 1, Release 10	NT5R33BB
NT5R33BB	Meridian Mail Master Tape - Europe 1, Release 10	NT5R33BD
NT5R33BD	Meridian Mail Master Tape - Europe 1, Release 10	NT5R33BS
NT5R33BS	Meridian Mail Master Tape - Europe 1, Release 10	NT5R33CU
NT5R33CA	Meridian Mail Master Tape - Europe 2, Release 10	NT5R33CB
NT5R33CB	Meridian Mail Master Tape - Europe 2, Release 10	NT5R33CD
NT5R33CD	Meridian Mail Master Tape - Europe 2, Release 10	NT5R33CS
NT5R33CS	Meridian Mail Master Tape - Europe 2, Release 10	NT5R33DU
NT5R33DA	Meridian Mail Master Tape - Europe 3, Release 10	NT5R33DB

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5R33DB	Meridian Mail Master Tape - Europe 3, Release 10	NT5R33DD
NT5R33DD	Meridian Mail Master Tape - Europe 3, Release 10	NT5R33DS
NT5R33DS	Meridian Mail Master Tape - Europe 3, Release 10	NT5R33LS
NT5R33EA	Meridian Mail Master Tape - Europe 4, Release 10	NT5R33EB
NT5R33EB	Meridian Mail Master Tape - Europe 4, Release 10	NT5R33ED
NT5R33ED	Meridian Mail Master Tape - Europe 4, Release 10	NT5R33ES
NT5R33ES	Meridian Mail Master Tape - Europe 4, Release 10	NT5R33JS
NT5R33FA	Meridian Mail Master Tape - Asia/Pacific, Release 10	NT5R33FB
NT5R33FB	Meridian Mail Master Tape - Asia/Pacific, Release 10	NT5R33FD
NT5R33FD	Meridian Mail Master Tape - Asia/Pacific, Release 10	NT5R33FS
NT5R33FS	Meridian Mail Master Tape - Asia/Pacific, Release 10	NT5R33GU
NT5R33GA	Meridian Mail Master Tape - North American (Standalone), Release 10	NT5R33GB
NT5R33GB	Meridian Mail Master Tape - North American (Standalone), Release 10	NT5R33GD
NT5R33GD	Meridian Mail Master Tape - North American (Standalone), Release 10	NT5R33GS
NT5R33GS	Meridian Mail Master Tape - North American (Standalone), Release 10	NT5R33BU
NT5R33JS	Meridian Mail Master Tape - Europe 4, Release 10	NT5R33FU
NT5R33LS	Meridian Mail Master Tape - Europe 3, Release 10	NT5R33EU
NT5R33LS	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72PN
NT5R35AA	Meridian Mail Master Tape - North American, Release 9	NT5R35AB
NT5R35AB	Meridian Mail Master Tape - North American, Release 9	
NT5R35BA	Meridian Mail Master Tape - Europe 1, Release 9	NT5R35BB
NT5R35BB	Meridian Mail Master Tape - Europe 1, Release 9	
NT5R35CA	Meridian Mail Master Tape - Europe 2, Release 9	NT5R35CB
NT5R35CB	Meridian Mail Master Tape - Europe 2, Release 9	
NT5R35DA	Meridian Mail Master Tape - Europe 3, Release 9	NT5R35DB
NT5R35DB	Meridian Mail Master Tape - Europe 3, Release 9	NT5R35PA
NT5R35EA	Meridian Mail Master Tape - Europe 4, Release 9	NT5R35EB
NT5R35EB	Meridian Mail Master Tape - Europe 4, Release 9	NT5R35NA
NT5R35FA	Meridian Mail Master Tape - Asia/Pacific, Release 9	NT5R35FB
NT5R35FB	Meridian Mail Master Tape - Asia/Pacific, Release 9	
NT5R35NA	Meridian Mail Master Tape - Europe 4, Release 9	
NT5R35PA	Meridian Mail Master Tape - Europe 3, Release 9	
NT5R36AA	Meridian Mail Master Tape, North American - Release 11	NT5R36AB
NT5R36AB	Meridian Mail Master Tape, North American - Release 11	NT5R36AC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5R36BA	Meridian Mail Master Tape, North American 2 - Release 11	NT5R36BB
NT5R36BB	Meridian Mail Master Tape, North American 2 - Release 11	NT5R36BC
NT5R36CA	Meridian Mail Master Tape, European 1 - Release 11	NT5R36CB
NT5R36CB	Meridian Mail Master Tape, European 1 - Release 11	NT5R36CC
NT5R36DA	Meridian Mail Master Tape, European 2 - Release 11	NT5R36DB
NT5R36DB	Meridian Mail Master Tape, European 2 - Release 11	NT5R36DC
NT5R36EA	Meridian Mail Master Tape, European 3 - Release 11	NT5R36EB
NT5R36EB	Meridian Mail Master Tape, European 3 - Release 11	NT5R36EC
NT5R36FA	Meridian Mail Master Tape, European 4 - Release 11	NT5R36FB
NT5R36FB	Meridian Mail Master Tape, European 4 - Release 11	NT5R36FC
NT5R36GA	Meridian Mail Master Tape, European 5 - Release 11	NT5R36GB
NT5R36GB	Meridian Mail Master Tape, European 5 - Release 11	NT5R36GC
NT5R36HA	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11	NT5R36HB
NT5R36HB	Meridian Mail Master Tape, Asia/Pacific 1 - Release 11	NT5R36HC
NT5R36JA	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11	NT5R36JB
NT5R36JB	Meridian Mail Master Tape, Asia/Pacific 2 - Release 11	NT5R36JC
NT5R45AA	Meridian Mail Master Tape, North American - Release 12	NT5R45AB
NT5R45AB	Meridian Mail Master Tape, North American - Release 12	NT5R45AC
NT5R45BA	Meridian Mail Master Tape, North American 2 - Release 12	NT5R45BB
NT5R45BB	Meridian Mail Release 12.12 Master Tape North American	NT5R45BC
NT5R45CA	Meridian Mail Master Tape, European 1 - Release 12	NT5R45CB
NT5R45CB	Meridian Mail Release 12.12 Master Tape European1	NT5R45CC
NT5R45DA	Meridian Mail Master Tape, European 2 - Release 12	NT5R45DB
NT5R45DB	Meridian Mail Release 12.12 Master Tape European 2	NT5R45DC
NT5R45EA	Meridian Mail Master Tape, European 3 - Release 12	NT5R45EB
NT5R45EB	Meridian Mail Release 12.12 Master Tape european3	NT5R45EC
NT5R45FA	Meridian Mail Master Tape, European 4 - Release 12	NT5R45FB
NT5R45FB	Meridian Mail Release 12.12 Master Tape European4	NT5R45FC
NT5R45GA	Meridian Mail Master Tape, European 5 - Release 12	NT5R45GB
NT5R45GB	Meridian Mail Release 12.12 Master Tape European 5	NT5R45GC
NT5R45HA	Meridian Mail Master Tape, Asia/Pacific 1 - Release 12	NT5R45HB
NT5R45HB	Meridian Mail Release 12.12 Master Tape Asia/Pacific 1	NT5R45HC
NT5R45JA	Meridian Mail Master Tape, Asia/Pacific 2 - Release 12	NT5R45JB
NT5R45JB	Meridian Mail Release 12.12 Master Tape Asia/Pacific 2	NT5R45JC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT5R52AC	Blank Panel	
NT5R53AB	Power Distribution Panel - 4	
NT5R53AC	LANSTAR/4 Stack Assembly	
NT5R55AB	Mac SCSI Kit	
NT5R56AA	LANSTAR/LAN 100 (60 In.) Cabinet	
NT5R56AB	Power Distribution Panel - 8	
NT5R56AC	LANSTAR/8 Stack Assembly	
NT5R63AA	Controller/Monitor PCBA	
NT5R64AA	Power Supply Assembly	
NT5R70AA	I/O Cable (9 In.)	
NT5R70AB	I/O Cable (9 In.)	
NT5R70AC	Bus Cable	
NT5R82AB	Meridian Mail Modular Option GP Reference Manual, Release 9	
NT5R83AA	Meridian Mail Modular Option EC Release 9 Reference Manual	
NT5R85AA	Meridian Mail Release 9 Multi-customer System Reference Manual	
NT5R86AA	Meridian Mail Release 9 System Administration Reference Manual	
NT5R88AA	Meridian Mail Release 9 ACCESS Developers Reference Manual	A0407674
NT5R88AA	Meridian Mail Release 9 ACCESS Developers Reference Manual	
NT5R89AA	Meridian Mail Release 9 ACCESS Enable Option Reference Manual	A0407675
NT5R89AA	Meridian Mail Release 9 ACCESS Enable Option Reference Manual	
NT5R90AA	AdminPlus Administration Guide, Release 9	P0819082
NT5R91AA	AdminPlus PC Software and NTP, Release 9	
NT5R92AA	Meridian Mail Release 9 HVS Administrative Reference Manual	
NT5R93AA	Meridian Mail Release 9 Card Option Reference Manual	NT5R93CA
NT5R93CA	Meridian Mail Card Option Reference Manual	
NT5R95AA	Meridian Mail Messaging User Guide Package (DMS) (English) (50/Pkg)	
NT5R96AA	Meridian Mail Call Answering User Guide Package (VMUIF), English, (50/Pkg)	
NT6D00AB	LANSTAR 16 Kit	
NT6D00AC	Meridian Telecenter 1.0	NT6D00BC
NT6D00BC	Meridian Telecenter 1.1	
NT6D11AB	D-Channel Handler Card	NT6D11AC
NT6D11AC	D-Channel Handler Card	NT6D11AF
NT6D3903	CPU/Network Cardcage (AC/DC)	NT6D3906
NT6D3906	CPU/Network Cardcage (AC/DC)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT6D40AA	Peripheral Equipment Power Supply DC	NT6D40AB
NT6D40AB	Peripheral Equipment Power Supply DC	NT6D40AD
NT6D40AD	Peripheral Equipment Power Supply DC	NT6D40BA
NT6D41AA	Common Equipment Power Supply DC	NT6D41AB
NT6D41AB	Common Equipment Power Supply DC	NT6D41AD
NT6D42CB	Ringing Generator DC	NT6D42CC
NT6D42CC	Ringing Generator DC	NT6D42CD
NT6D43AA	Common/Peripheral Equipment Power Supply DC	
NT6D45AA	Tape Drive Unit	NT6D45CA
NT6D46AA	155MB Hard Disk Drive	
NT6D47AA	300MB Hard Disk Drive	NT6D47BA
NT6D47BA	300MB Hard Disk Drive	
NT6D47DA	Meridian Mail Modular 300MB Hard Disk/Tape Drive Unit	
NT6D48AA	600MB Hard Disk Drive	NT6D48BA
NT6D48BA	1.0GB Hard Disk Drive	NT6D48FA
NT6D48DA	Meridian Mail Modular 1.0GB Hard Disk/Tape Drive Unit	NT6D48EA
NT6D48EA	Tandberg Tape & Disk Drive Unit, Modular Option	NT6D48GA
NT6D52AA	-52V/30 Amp Rectifier	NT6D52BA
NT6D52BA	Rectifier, -52V/30 Amp	NT0R72AA
NT6D53AA	Junction Box	
NT6D6008	Core CardCage (AC/DC)	
NT6D60DA	Core Module DC	
NT6D63AA	Input/Output Processor Card (IOP)	
NT6D63BA	Input/Output Processor Card (IOP)	
NT6D64AA	Core Multi-Drive Unit (CMDU)	
NT6D65AA	Core-to-Network Interface Card (CNI)	NTRB34AA
NT6D65AB	Core-to-Network Interface Card (CNI)	NTRB34AA
NT6D66AA	24MB Call Processor Card (CP)	
NT6D66DA	48MB Call Processor Card (CP) 81/81C Systems with 68030/48MB CP Requires X11 Release 21 Software Generic 1611	NT5D03BA
NT6D78AA	Carbon Copy Software	A0372990
NT6D80AA	Multi-Purpose Serial Data Link (MSDL)	NT6D80AB
NT6D8201	Control and Distribution Panel	
NT6D8202	Supplemental Distribution Panel	
NT6D8203	Relay Rack	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT6D8204	Seismic Relay Rack	
NT6D8207	First Rectifier O/P Cable	
NT6D8208	Second Rectifier O/P Cable	
NT6D8209	Third Rectifier O/P Cable	
NT6D8211	Parallel Diode Kit	
NT6D8212	Meter Control Panel	
NT6D8213	Spare Fuse & Breaker Kit	
NT6D8215	Seismic Anchor Kit	
NT6G00AA35	M2250 Attendant Console	NT6G00AC35
NT6G00AC35	M2250 Attendant Console	NT6G00AD35
NT6G00AD35	M2250 Attendant Console	NT6G00AE35
NT6G00AE35	M2250 Attendant Console	
NT6G00AF	M2250 Attendant Console	NT6G00AF35
NT6P0111	External Voice Bus Cable (2.5 Ft.)	NT6P0124
NT6P0114	Backplane to I/O Cable	
NT6P0118	External Voice Bus Cable (5Ft.)	NT6P0125
NT6P0119	External Voice Bus Cable (10Ft.)	NT6P0126
NT6P02AA	68K Processor Card	
NT6P03AA	Utility Card with Modem	NT6P42AA
NT6P05AA	Meridian Mail Modular EC Tape Drive Unit	NT6P05BA
NT6P06AA	Meridian Mail Modular EC 300MB Hard Disk Drive	
NT6P07AA	Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive	NT6P07BA
NT6P43AA	Meridian Mail Modular EC 300MB Hard Disk Drive with Power	
NT6P44AA	Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive with Power	NT6P44BA
NT6R00AA	Meridian Mail Option 4 Port 5 Hours Cantilever Mount	
NT6R00AB	Meridian Mail Option 4 Ports 5/11 Hours Package (Cantilever Mount)	SY7010D
NT6R01AA	Meridian Mail Option 4 Port 24 Hours Cantilever Mount	
NT6R01AB	Meridian Mail Option 4 Ports 11/24 Hours Package (Cantilever Mount)	SY7010D
NT6R02AA	Meridian Mail Option 8 Port 11 Hours Cantilever Mount	
NT6R02AB	Meridian Mail Option 4 Ports 36/54 Hours Package (Cantilever Mount)	SY7011D
NT6R03AA	Meridian Mail Option 8 Port 24 Hours Cantilever Mount	
NT6R03AB	Meridian Mail Option 16 Ports 26/54 Hours Package (Cantilever Mount)	SY7012D
NT6R04AA	Meridian Mail Option 12 Port 24 Hours Cantilever Mount	
NT6R04AB	Meridian Mail Option 16 Ports 84/114 Hours Package (Cantilever Mount)	SY7013D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT6R06AA	SYMPOSIUM Call Center Release 1 Capacity Complete Documentation Package (English)	
NT6R06AB	SYMPOSIUM Call Center Server Release 1, Installation Assembly	NT6R06AC
NT6R06AC	SYMPOSIUM Call Center Server Installation Assembly	NT6R06AD
NT6R06AD	SYMPOSIUM Call Center Server Installation Assembly	
NT6R07AA	SYMPOSIUM Call Center Documentation Package (English)	
NT6R0801	SYMPOSIUM Call Center System Administration Documentation Package (English -10)	
NT6R08AA	SYMPOSIUM Call Center Server Release 1, Administration Assembly	NT6R08AB
NT6R08AB	SYMPOSIUM Call Center Server Administration Assembly	NT6R08AD
NT6R08AD	SYMPOSIUM Call Center Server Administration Assembly	
NT6R0901	SYMPOSIUM Call Center System Resource Management Guide (English - 10)	
NT6R09AA	SYMPOSIUM Call Center Resource Management Guide (English)	
NT6R10AA	SYMPOSIUM Call Center Documentation CD-ROM	NT6R10BA
NT6R10BA	SYMPOSIUM Call Center Release 1.1 Documentation CD-ROM	NT6R10AD
NT6R17AA	Meridian Mail Compact Option Enhanced 68K Memory and 4-Port DSP Unit	NTMW02AB
NT6R20AA	Meridian Mail Option 4 Port 5 Hours Center Mount	
NT6R20AB	Meridian Mail Option 4 Ports 5/11 Hours Package (Center Mount)	SY7010D
NT6R21AA	Meridian Mail Option 4 Port 24 Hours Center Mount	
NT6R21AB	Meridian Mail Option 4 Ports 11/24 Hours Package (Center Mount)	SY7010D
NT6R22AA	Meridian Mail Option 8 Port 11 Hours Center Mount	
NT6R22AB	Meridian Mail Option 4 Ports 36/54 Hours Package (Center Mount)	SY7011D
NT6R23AA	Meridian Mail Option 8 Port 24 Hours Center Mount	
NT6R23AB	Meridian Mail Option 16 Ports 26/54 Hours Package (Center Mount)	SY7012D
NT6R24AA	Meridian Mail Option 12 Port 24 Hours Center Mount	
NT6R24AB	Meridian Mail Option 16 Ports 84/114 Hours Package (Center Mount)	SY7013D
NT6R30AB	Meridian Mail Option from 12 to 16 Ports, 300MB Disk, Expansion Package (Cantilever Mount)	NT6R31AB
NT6R31AB	Meridian Mail Option from 12 to 16 Port Expansion Package (Cantilever Mount)	
NT6R32AB	Meridian Mail Option from 12 to 16 Ports, 300MB Disk, Expansion Package (Center Mount)	NT6R33AB
NT6R33AB	Meridian Mail Option from 12 to 16 Port Expansion Package (Center Mount)	
NT6R40AA	Meridian 1 Reference Library (Release 23)	NT5F34AA
NT6R47AA	Meridian Mail Master Tape, North American 1 - Release 13	NT6R47AD
NT6R47BA	Meridian Mail Master Tape, North American 2 - Release 13	NT6R47BD
NT6R47CA	Meridian Mail Master Tape, European 1 - Release 13	NT6R47CD

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT6R47DA	Meridian Mail Master Tape, European 2 - Release 13	NT6R47DD
NT6R47EA	Meridian Mail Master Tape, European 3 - Release 13	NT6R47ED
NT6R47FA	Meridian Mail Master Tape, European 4 - Release 13	NT6R47FD
NT6R47GA	Meridian Mail Master Tape, European 5 - Release 13	NT6R47GD
NT6R47HA	Meridian Mail Master Tape, Asia/Pacific 1 - Release 13	NT6R47HD
NT6R47JA	Meridian Mail Master Tape, Asia/Pacific 2 - Release 13	NT6R47JD
NT6R50AA	SYMPOSIUM TAPI Service Provider for Meridian 1 Release 2	NT6R50AB
NT6R55AA	Meridian 1 TAPI Server Release 1 (Includes One-Year Software Support)	
NT6R56AA	Meridian 1 TAPI Server Release 1 with IVR/Networking Option (Includes One-Year Software Support)	
NT6R60AA	Meridian 1 TAPI Server Documentation	
NT6R6602	SYMPOSIUM TAPI Service Provider Release 2 CD ROM	NT6R6604
NT6R66AA	SYMPOSIUM TAPI Service Provider Release 2, Software and Documentation	NT6R66AB
NT6R69AA	SYMPOSIUM TAPI Service Provider Upgrade Software	NT6R69AB
NT6R77AA	Option 11C Release 22 English Documentation Package - Binder	NT6R77AB
NT6R77AB	Option 11C Release 23 English Documentation Package - Binder	NT6R77AD
NT6R78AA	Option 11C Release 22 English Documentation Package - Coil	NT6R78AB
NT6R78AB	Option 11C Release 23 English Documentation Package - Coil	NT6R78AD
NT6R79AA	SYMPOSIUM TAPI Service Provider Replacement CD-ROM	NT6R79AB
NT6R92AA	OIVR 2.x Hardware - Installation and Maintenance Guide	
NT6R94AA	Meridian Mail EC11 Installation and Modification Guide, MM10	NT6R49AA
NT7D00AC	Top Cap - Option 21A	
NT7D03AA	Ringing Generator DC	NT6D42CB
NT7D04AA	Common/Peripheral Equipment Power Supply	NT7D04AB
NT7D04AB	Common/Peripheral Equipment Power Supply DC	NT6D43AA
NT7D09AA	Pedestal - DC	NT7D09CA
NT7D10AA	Power Distribution Unit DC	NT7D67CB
NT7D10CA	System Monitor Panel	
NT7D14AA	Common/Peripheral Equipment Power Supply AC	
NT7D15AA	System Monitor - Option 21A	NT7D15AB
NT7D15AB	System Monitor - Option 21A	
NT7D16AA	Data Access Card	NT7D16AB
NT7D16AA	Data Access Card	NT7D16BA
NT7D16AB	Data Access Card	NT7D16BA
NT7D17AC	Pedestal Fan Unit AC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT7D17DC	Pedestal Fan Unit DC	
NT7D19PA	Meridian IVR Applications Module	NT7D19RA
NT7D44AA	Power Monitor/Common Equipment Auxiliary Shelf (Cantilever)	NT7D44BA
NT7D44BA	Power Monitor/Common Equipment Auxiliary Shelf (Cantilever)	
NT7D45AA	Power Monitor/Common Equipment Auxiliary Shelf (Center)	
NT7D46AB	Application Module to SDI Paddle Board Cable (2 Ft.)	
NT7D58AB	ESDI Cable (2 Ft.)	NT7D58EB
NT7D58AD	ESDI Cable (6 Ft.)	NT7D58ED
NT7D58AF	ESDI Cable (10 Ft.)	NT7D58EF
NT7D58AL	ESDI Cable (20 Ft.)	NT7D58EL
NT7D58AT	ESDI Cable (35 Ft.)	NT7D58ET
NT7D58AV	ESDI Cable (45 Ft.)	NT7D58EV
NT7D60AA	Modem I/O Cable	
NT7D61AB	SDI Cable (2 Ft.)	NT7D61EB
NT7D61AD	SDI Cable (6 ft.)	NT7D61ED
NT7D61AF	SDI Cable (10 Ft.)	NT7D61EF
NT7D61AL	SDI Cable (20 Ft.)	NT7D61EL
NT7D61AT	SDI Cable (35 Ft.)	NT7D61ET
NT7D61AV	SDI Cable (45 Ft.)	NT7D61EV
NT7D62AA	105MB Disk/150MB Tape Assembly	
NT7D62AB	172MB Disk/Tape Unit	NT7D62AC
NT7D67CA	Power Distribution Unit DC	NT7D67CB
NT7D67CB	Power Distribution Unit DC	
NT7D71AA	External Modem Cable	
NT7D72AA	Meridian Link Module Software/Documentation Package	SW7301B
NT7D73AA	Meridian Link Software	
NT7D74AA	UNIX OS Software	
NT7D75AA	Meridian Link Documentation	
NT7D79AA	I/O Cable	
NT7D89BA	CP to I/O Panel RS232 Cable	NT7D89CA
NT7D90BA	IOP to I/O Panel Ethernet Cable	NT7D90CA
NT7D90CA	IOP to I/O Panel Ethernet Cable	NT7D90DA
NT7D97AG	Dual Module Interface Cable (12 Ft.)	
NT7E74AA	Floor Mounting Kit	NT0X21AV

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT7R27AA	Meridian Administration Tools Single-Site Common Services	NT7R27BA
NT7R27BA	Meridian Administration Tools Single-Site Common Services	NT7R27CA
NT7R27CA	Meridian Administration Tools Single-Site Common Services	NTZK38AA
NT7R28AA	Meridian Administration Tools Multi-Site Common Services	NT7R28BA
NT7R28BA	Meridian Administration Tools Multi-Site Common Services	NT7R28CA
NT7R28CA	Meridian Administration Tools Multi-Site Common Services	NTZK38BA
NT7R29AA	Meridian Administration Tools Distributor Common Services	
NT7R30AA	Meridian Administration Tools Station Administration Module	NT7R30BA
NT7R30BA	Meridian Administration Tools Station Administration Module	NT7R30CA
NT7R30CA	Meridian Administration Tools Station Administration Module	NTZK40AA
NT7R31AA	Meridian Administration Tools Traffic Analysis Module	NT7R31BA
NT7R31BA	Meridian Administration Tools Traffic Analysis Module	NT7R31CA
NT7R31CA	Meridian Administration Tools Traffic Analysis Module	NTZK41AA
NT7R32AA	Meridian Administration Tools Station Administration Module Upgrade	AS1300
NT7R32AA	Meridian Administration Tools Station Administration Module Upgrade	AS1301
NT7R33AA	Meridian Administration Tools Traffic Analysis Module Upgrade	AS1302
NT7R33AA	Meridian Administration Tools Traffic Analysis Module Upgrade	AS1303
NT7R35AA	Meridian Administration Tools Multi-Site Expansion	NT7R35BA
NT7R35BA	Meridian Administration Tools Multi-Site Expansion	NT7R35CA
NT7R35CA	Meridian Administration Tools Multi-Site Expansion	NTZK39BA
NT7R36AA	Meridian Administration Tools Single-Site to Multi-Site Upgrade	NT7R36BA
NT7R36BA	Meridian Administration Tools Single-Site to Multi-Site Upgrade	NT7R36CA
NT7R36CA	Meridian Administration Tools Single-Site to Multi-Site Upgrade	NTZK39AA
NT7R37AA	Meridian Administration Tools Common Services User Guide	NT7R37BA
NT7R37BA	Meridian Administration Tools Common Services User Guide	NT7R37CA
NT7R37CA	Meridian Administration Tools Common Services User Guide	NT8R03AA
NT7R38AA	Meridian Administration Tools Station Administration Module User Guide	NT7R38BA
NT7R38BA	Meridian Administration Tools Station Administration Module User Guide	NT7R38CA
NT7R38CA	Meridian Administration Tools Station Administration Module User Guide	P0833798
NT7R39AA	Meridian Administration Tools Traffic Analysis Module User Guide	NT7R39BA
NT7R39BA	Meridian Administration Tools Traffic Analysis Module User Guide	NT7R39CA
NT7R39CA	Meridian Administration Tools Traffic Analysis Module User Guide	P0833799
NT7R51AA	Local Carrier Interface Card	NT7R51AB
NT7R51AB	Local Carrier Interface Card	NT7R51AC

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT7R51AC	Local Carrier Interface Card	NT7R51AD
NT7R52AA	Remote Carrier Interface Card	NT7R52AB
NT7R52AB	Remote Carrier Interface Card	NT7R52AC
NT7R52AC	Remote Carrier Interface Card	NT7R52AD
NT7R62AA	Remote Carrier Cabinet Panel Assembly	NT7R94AA
NT7R68CA	Remote Carrier/Alarm Cabinet Cable Assembly	NT7R94AA
NT7R68DA	Remote Maintenance Cabinet Cable Assembly	NT7R94AA
NT7R70AA	Meridian Safe Central Site 401-800 Lines	
NT7R70BA	Meridian Safe Central Site 801-1200 Lines	
NT7R70CA	Meridian Safe Central Site 1201+ Lines	
NT7R70DA	Meridian Safe Central Site 32-400 Lines	
NT7R70JA	Meridian Safe Additional Sites 401-800 Lines	
NT7R70KA	Meridian Safe Additional Sites 801-1200 Lines	
NT7R70LA	Meridian Safe Additional Sites 1201+ Lines	
NT7R70MA	Meridian Safe Additional Sites 32-400 Lines	
NT7R7101	XIOX Hacker Tracker	SW1038
NT7R71AA	XIOX Internal Hacker Deadbolt	
NT7R72CA	XIOX Hacker Preventer 1200+ Lines	
NT7R74AA	1 Megabyte Buffer	
NT8D01AC	Controller - Four Card	NT8D01BC
NT8D01AD	Controller - Two Card	NT8D01BC
NT8D02AA	Digital Line Card	NT8D02AB
NT8D02AB	Digital Line Card	NT8D02EA
NT8D02EA	Digital Line Card	NT8D02EB
NT8D02EB	Digital Line Card	
NT8D03AA	Analog Line Card	NT8D03AB
NT8D03AB	Analog Line Card	NT8D03AE
NT8D03AE	Analog Line Card	NT8D03AJ
NT8D03AJ	Analog Line Card	NT8D09AJ
NT8D04AA	SuperLoop Network Card	NT8D04BA
NT8D06AA	Peripheral Equipment Power Supply AC	NT8D06AB
NT8D09AA	Analog Message Waiting Line Card	NT8D09AB
NT8D09AB	Analog Message Waiting Line Card	NT8D09AD
NT8D09AD	Analog Message Waiting Line Card	NT8D09AG

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT8D09AG	Analog Message Waiting Line Card	NT8D09AJ
NT8D09AJ	Analog Message Waiting Line Card	NT8D09AK
NT8D09AK	Analog Message Waiting Line Card	NT8D09AL
NT8D09AL	Analog Message Waiting Line Card	NT8D09BA
NT8D1103	CE/PE Cardcage (AC/DC)	
NT8D11AC	Common, Peripheral Equipment Module AC	NT8D11BC
NT8D11BC	Common/Peripheral Equipment Module AC	
NT8D11DC	Common/Peripheral Equipment Module DC	NT8D11EC
NT8D14AA	Universal Trunk Card	NT8D14AH
NT8D14AE	Universal Trunk Card	NT8D14AH
NT8D14AH	Universal Trunk Card	NT8D14AJ
NT8D14AJ	Universal Trunk Card	NT8D14AK
NT8D14AK	Universal Trunk Card	NT8D14BA
NT8D14BA	Universal Trunk Card	NT8D14BB
NT8D15AA	E&M Trunk Card	NT8D15AH
NT8D15AH	E&M Trunk Card	NT8D15AJ
NT8D15AJ	E&M Trunk Card	NT8D15AK
NT8D16AA	Digitone Receiver Card	NT8D16AB
NT8D17AA	Conference/TDS Card	NT8D17CA
NT8D17CA	Conference/TDS Card	NT8D17EA
NT8D17EA	Conference/TDS Card	NT8D17FA
NT8D18AA	Network/DTR Card	NT8D18AB
NT8D18AB	Network/DTR Card	
NT8D19AA	Memory/Peripheral Signaling Card	
NT8D21AA	Ringing Generator AC	NT8D21AB
NT8D22AB	System Monitor	NT8D22AC
NT8D27AB	Pedestal - AC	NT8D27BB
NT8D29AA	Common Equipment Power Supply AC	NT8D29AB
NT8D3403	CPU Cardcage (AC/DC)	
NT8D34AA	CPU Module AC	
NT8D34DC	CPU Module DC	
NT8D3503	Network Cardcage (AC/DC)	NT8D3507
NT8D35AA	Network Module AC	NT8D35BA
NT8D35DC	Network Module DC	NT8D35EA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT8D37AA	Intelligent Peripheral Equipment Module AC	NT8D37BA
NT8D37DC	Intelligent Peripheral Equipment Module DC	NT8D37EC
NT8D39AA	Power Fail Transfer Unit	
NT8D41AA	Dual Port SDI Paddle Board	
NT8D46AH	Alarm Monitor Cable	NT8D46BH
NT8D46BK	Alarm Monitor Cable (1 Ft.)	
NT8D46BL	Alarm Monitor Cable (1 Ft.)	
NT8D47DC	RPE Carrier Module DC	
NT8D52AA	Pedestal Blower Unit AC	NT8D52AB
NT8D52DC	Pedestal Blower Unit DC	NT8D52DD
NT8D53AB	Power Distribution Unit AC	NT8D53BB
NT8D53AD	Power Distribution Unit - Option 21A	
NT8D53BB	Power Distribution Unit AC	
NT8D55AA	Front/Rear Cover	NT8D55BA
NT8D55BA	Front/Rear Cover	NT9D15AA
NT8D56AC	Common/Peripheral Equipment Module Power Distribution Unit	
NT8D64AA	Earthquake Bracing Kit (Two Module Column)	NT8D64CA
NT8D64AB	Earthquake Bracing Kit (Three Module Column)	NT8D64CB
NT8D64AC	Earthquake Bracing Kit (Four Module Column)	NT8D64CC
NT8D68AA	Floppy Disk Unit	
NT8D69AA	Multi Disk Unit	
NT8D74AC	Clock Controller to Junctor Cable (4 Ft.)	NT8D74BC
NT8D74AD	Clock Controller to Junctor Cable (6 Ft.)	NT8D74BD
NT8D74AE	Clock Controller to Junctor Cable (8 Ft.)	NT8D74BE
NT8D74AF	Clock Controller to Junctor Cable (10 Ft.)	NT8D74BF
NT8D75AC	Clock Controller to Clock Controller Cable (4 Ft.)	NT8D75BC
NT8D75AD	Clock Controller to Clock Controller Cable (6 Ft.)	NT8D75BD
NT8D76AC	Intergroup Switch to Intergroup Module Cable (4 Ft.)	NT8D76BC
NT8D76AD	Intergroup Switch to Intergroup Module Cable (6 Ft.)	NT8D76BD
NT8D76AE	Intergroup Switch to Intergroup Module Cable (8 Ft.)	NT8D76BE
NT8D76AF	Intergroup Switch to Intergroup Module Cable (10 Ft.)	NT8D76BF
NT8D76AG	Intergroup Switch to Intergroup Module Cable (12 Ft.)	NT8D76BG
NT8D76AJ	Intergroup Switch to Intergroup Module Cable (16 Ft.)	NT8D76BJ
NT8D76AL	Intergroup Switch to Intergroup Module Cable (20 Ft.)	NT8D76BP

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT8D76AP	Intergroup Switch to Intergroup Module Cable (25 Ft.)	NT8D76BP
NT8D77AA	Floppy Disk Interface to Floppy Disk Unit (3 Ft.)	NT8D77BA
NT8D77AB	Floppy Disk Interface to Floppy Disk Unit (2 Ft.)	NT8D77BB
NT8D77AC	Floppy Disk Interface to Floppy Disk Unit (4 Ft.)	NT8D77BC
NT8D77AD	Floppy Disk Interface to Floppy Disk Unit (6 Ft.)	NT8D77BD
NT8D80AB	CPU/MDU Interface Cable (2 Ft.)	
NT8D80AC	CPU/MDU Interface Cable (4 Ft.)	NT8D80BC
NT8D80AD	CPU/MDU Interface Cable (6 Ft.)	NT8D80BD
NT8D80AE	CPU/MDU Interface Cable (8Ft.)	NT8D80BE
NT8D80AF	CPU Interface Cable (10 Ft.)	NT8D80BF
NT8D80AG	CPU Interface Cable (12 Ft.)	NT8D80BG
NT8D80AJ	CPU Interface Cable (16 Ft.)	NT8D80BJ
NT8D80AL	CPU Interface Cable (20 Ft.)	NT8D80BL
NT8D80AP	CPU Interface Cable (25 Ft.)	NT8D80BP
NT8D80AZ	CPU Interface Cable (5 Ft.)	NT8D80BZ
NT8D82AC	SDI to I/O Cable (4 Ft.)	NT8D82AD
NT8D83AC	PRI/DTI to I/O Cable (4 Ft.)	NT8D83AD
NT8D85AB	Network to PE Cable (2 Ft.)	NT8D85BB
NT8D85AC	Network to PE Cable (4 Ft.)	NT8D85BC
NT8D85AD	Network to PE Cable (6 Ft.)	NT8D85BD
NT8D85AE	Network to PE Cable (8 Ft.)	NT8D85BE
NT8D85AF	Network to PE Cable (10 Ft.)	NT8D85BF
NT8D85AJ	Network to PE Cable (16 Ft.)	NT8D85BJ
NT8D85AL	Network to PE Cable (20 Ft.)	NT8D85BL
NT8D85AP	Network to PE Cable (25 Ft.)	NT8D85BP
NT8D85AV	Network to PE Cable (45 Ft.)	NT8D85BV
NT8D85AZ	CPU Interface Cable (5 Ft.)	NT8D85BZ
NT8D86AC	Network to I/O Cable (5 Ft.)	NT8D86AD
NT8D86AD	Network to I/O Cable (6 Ft.)	NT8D86BD
NT8D96AE	NT8D96AE VME Multiport Cable	NT8D96BE
NT8D97AX	PRI/DTI I/O to MDF Cable (50 Ft.)	
NT8D99BB	CPU to Network Cable (2 Ft.)	NT8D99AB
NT8D99BD	CPU to Network Cable (6 Ft.)	
NT8K90AA35	Meridian M2018S Secure Telephone with Data, Ash	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT8R04AA	MAT 5.x Common Services User Guide and Binder	A0672913
NT8R04AA	MAT 5.x Common Services User Guide and Binder	P0868359
NT8R11AA	Meridian Mail Reporter Release 1, Software Multi-Site North America Package	NT8R15AA
NT8R11AA	Meridian Mail Reporter Release 1, Software Multi-Site North America Package	
NT8R14AA	Meridian Mail Reporter Release 2.0, Software Single Site North America Package	NT8R14BA
NT8R15AA	Meridian Mail Reporter Release 2.0, Software Multi-Site North America Package	NT8R15BA
NT8R16AA	IP Line Card-Base Card	NT8R16BB
NT8R17AA	IP Line Card-Spare	NT8R17AB
NT8R2001	CD ROM Meridian Mail Alternate User Interface	NT8R2002
NT8R70AA	Meridian IP Telecommuter NTP CD ROM	NTLH16AA
NT8UX0603	NT-Tone Amplified Receiver Module - Black	
NT9D00AA	SP 4 Port/5 Hour Package	
NT9D01AA	SP 8 Port/11 Hour Package	
NT9D02AA	SP 8 Port/24 Hour Package	
NT9D03AA	SP Spares Kit	
NT9D04AA	SP 12 Port/24 Hour Package	
NT9D05AA	SP 4 Port/24 Hour Package	
NT9D06AA	DSS-150 Direct Station Select Unit	
NT9D07AB	CPLUS Release 3 Directory/Message Center PC Software	
NT9D07AC	CPLUS Release 3 to Latest Release 3 Software Upgrade	
NT9D07AD	CPLUS Release 2 to Latest Release 3 Software Upgrade	
NT9D07CA	CPLUS Performer Software	
NT9D07DA	CPLUS LAN Key Software	
NT9D09AA	CPLUS 2000 Directory/Message Center PC Software	
NT9D1103	Core/Network Cardcage (AC/DC)	NT5D2103
NT9D17AA	Module Side Cover	NT9D18AA
NT9D19AA	68040/48MB Call Processor	NT9D19AB
NT9D19AB	68040/48MB Call Processor	
NT9D19CA	68040/64MB Call Processor	NT9D19CB
NT9D19CB	68040/64MB Call Processor	
NT9D19HA	68040/96MB Call Processor	NT9D19HB
NT9D19HB	68040/96MB Call Processor	
NT9D20AA	Meridian Mail ST/RT Option 4 Port 5 Hours Package	
NT9D20AB	Meridian Mail ST/RT and Option 4 Ports 5/11 Hours Package	SY7010D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT9D21AA	Meridian Mail ST/RT Option 4 Port 24 Hours Package	
NT9D21AB	Meridian Mail ST/RT and S Option 4 Ports 11/24 Hours Package	SY7010D
NT9D22AA	Meridian Mail ST/RT Option 8 Port 11 Hours Package	
NT9D22AB	Meridian Mail ST/RT and S Option 4 Port 36/54 Hours Package	SY7011D
NT9D23AA	Meridian Mail ST/RT Option 8 Port 24 Hours Package	
NT9D23AB	Meridian Mail ST/RT and S Option 16 Ports 26/54 Hours Package	SY7012D
NT9D24AA	Meridian Mail ST/RT Option 12 Port 24 Hours Package	
NT9D24AB	Meridian Mail ST/RT and S Option 16 Port 84/114 Hours Package	SY7013D
NT9D25AA	Meridian Mail ST/RT Option Spares Kit Cantilever/Center Mounts	
NT9D25AB	Meridian Mail Option Spares Kit I	
NT9D26AB	Meridian Mail Option Spares Kit II	
NT9D27AB	Meridian Mail ST/RT Option from 12 to 16 Ports, 300MB Disk, Expansion Package	NT9D28AB
NT9D28AB	Meridian Mail ST/RT Option from 12 to 16 Port Expansion Package	
NT9D33AA	Small System Multi Disk Unit	
NT9D34AA	Enhanced Mass Storage Interface Card	
NT9D35AB	Meridian Mail Release 4 to Release 5 Hardware Package	U7001
NT9D36AB	Meridian Mail Release 4 to Release 5 Hardware Package	U7002
NT9D40AA	Meridian Mail Option - S Cabinet 4 Port 5 Hours Package	
NT9D40AB	Meridian Mail Option - S Cabinet 4 Port 5 Hours Package	
NT9D41AA	Meridian Mail Option - S Cabinet 4 Port 24 Hours Package	
NT9D41AB	Meridian Mail Option - S Cabinet 4 Port 11 Hours Package	
NT9D42AA	Meridian Mail Option - S Cabinet 8 Port 11 Hours Package	
NT9D42AB	Meridian Mail Option - S Cabinet 4 Port 36 Hours Package	
NT9D43AA	Meridian Mail Option - S Cabinet 8 Port 24 Hours Package	
NT9D43AB	Meridian Mail Option - S Cabinet 16 Port 26 Hours Package	
NT9D44AA	Meridian Mail Option - S Cabinet 12 Port 24 Hours Package	
NT9D44AB	Meridian Mail Option - S Cabinet 16 Port 84 Hours	
NT9D47AB	EMSI/SMDU Signal Cable (2 Ft.)	
NT9D47AD	EMSI/SMDU Signal Cable (6 Ft.)	
NT9D48AA	Hospitality Voice Services Documentation	
NT9D49AA	Meridian Mail Hospitality Voice Services (HVS) Hardware Kit	AS7010
NT9D49AA	Meridian Mail Hospitality Voice Services (HVS) Hardware Kit	AS7015
NT9D50AA	Meridian Mail GP 4 Ports 11/24 Hours Base Package	SY7060D
NT9D51AA	Meridian Mail GP 4 Ports 36/54 Hours Base Package	SY7061D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT9D52AA	Meridian Mail GP 20 Ports 26/54 Hours Base Package	SY7062D
NT9D53AA	Meridian Mail GP 36 Ports 45/90 Hours Base Package	SY7066D
NT9D54AA	Meridian Mail GP 48 Ports 60/120 Hours Base Package	SY7066D
NT9D55AA	Meridian Mail GP 20 Ports 84/114 Hours Base Package	SY7063D
NT9D56AA	Meridian Mail GP 20 Ports 84/114 Hours Base Package	SY7067D
NT9D57AA	Meridian Mail GP 48 Ports 180/240 Hours Base Package	SY7067D
NT9D58AA	Meridian Mail GP Spares Kit I	
NT9D59AA	Meridian Mail GP Spares Kit II	
NT9D60AA	Meridian Mail GP from 12 to 16 Ports, 300MB Disk, Expansion Package	NT9D61AA
NT9D61AA	Meridian Mail GP from 1 to 2 Node Expansion Package	
NT9D62AA	Meridian Mail GP from 24 to 28 Ports, 300MB Disk, Expansion Package	NT9D63AA
NT9D63AA	Meridian Mail GP from 24 to 28 Ports, 1.0GB Disk, Expansion Package	AS7038
NT9D63AA	Meridian Mail GP from 24 to 28 Ports, 1.0GB Disk, Expansion Package	AS7039
NT9D64AA	Meridian Mail GP from 48 to 52 Ports, 300MB Disk, Expansion Package	NT9D65AA
NT9D65AA	Meridian Mail GP from 4 to 5 Node Expansion Package	
NT9D66AA	SP Networking Package	
NT9D66AB	EMSI/SMDU Power Cable (2 Ft.)	
NT9D66AD	EMSI/SMDU Power Cable (6 Ft.)	
NT9D67AA	Meridian Mail Networking Kit	AS7012
NT9D67AA	Meridian Mail Networking Kit	AS7016
NT9D69AA	Meridian Mail Modem Kit	AS7012
NT9D70AA	Meridian Mail Option - X Cabinet 4 Ports 11/24 Hours Package	
NT9D71AA	Meridian Mail Option - X Cabinet 4 Ports 36/54 Hours Package	
NT9D72AA	Meridian Mail Option - X Cabinet 20 Ports 26/54 Hours Package	
NT9D73AA	Meridian Mail Option - X Cabinet 36 Ports 45/90 Hours Package	
NT9D74AA	Meridian Mail Option - X Cabinet 48 Ports 60/120 Hours Package	
NT9D75AA	Meridian Mail Option - X Cabinet 20 Ports 84/114 Hours Package	
NT9D76AA	Meridian Mail Option - X Cabinet 36 Ports 120/180 Hours Package	
NT9D77AA	Meridian Mail Option - X Cabinet 48 Ports 180/240 Hours Package	
NT9D78AA	Meridian Mail Option - X Cabinet Spares Kit I	
NT9D79AA	Meridian Mail Option - X Cabinet Spares Kit II	
NT9D80AA	Meridian Mail X Cabinet from 12 to 16 Ports, 300MB Disk, Expansion Package	NT9D81AA
NT9D81AA	Meridian Mail X Cabinet from 1 to 2 Node Expansion Package	
NT9D82AA	Meridian Mail X Cabinet from 24 to 28 Ports, 300MB Disk, Expansion Package	NT9D83AA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT9D83AA	Meridian Mail X Cabinet from 24 to 28 Ports, 1.0GB Disk, Expansion Package	AS7054
NT9D83AA	Meridian Mail X Cabinet from 24 to 28 Ports, 1.0GB Disk, Expansion Package	AS7055
NT9D84AA	Meridian Mail X Cabinet from 48 to 52 Ports, 300MB Disk, Expansion Package	NT9D85AA
NT9D85AA	Meridian Mail X Cabinet from 4 to 5 Node Expansion Package	
NT9D86AA	Meridian Mail Option - X Cabinet Upgrade Package	
NT9D89AB	CNI-3 to 3PE/EMSI to MDU Cable (2 Ft.)	
NT9D89AD	CNI-3 to 3PE/EMSI to MDU Cable (6 Ft.)	
NT9D90	HP Vectra Basic System	
NT9D90AB	ACD MAX Dual Tower Hardware Package	
NT9D90AD	ACD MAX Single Tower Hardware Package	
NT9D90AE	ACD MAX Single to Dual Tower Upgrade Package	
NT9D90BA	HP Vectra-Single Tower	
NT9D91AE	ACD MAX Single Tower/Dual Upgrade	
NT9D92AA	ACD MAX Single Tower Software	
NT9D92AB	ACD MAX Dual Tower Software	
NT9F01AA	SYMPOSIUM Call Center Base Software	
NT9F01AB	SYMPOSIUM Call Center Release 1.1 Base Software	
NT9F02FA	Call Center Software 100, New System (1000 Agent)	
NT9F03FA	Call Center Software 200, New System (1000 Agent)	
NT9F04FA	Call Center Software 300, New System (1000 Agent)	
NT9F06FA	Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1000 Agent)	
NT9F07FA	Call Center Software 200, Upgrade from MAX and CCR (1000 Agent)	
NT9F08FA	Call Center Software 300, Upgrade from MAX NACD and/or NAC (1000 Agent)	
NT9F09FA	Call Center Software 100, Upgrade from MAX 6 (1000 Agent)	
NT9F10FA	Call Center Software 300, Upgrade from NACD (1000 Agent)	
NT9F11FA	Call Center Software 100, Upgrade from MAX 5 (1000 Agent)	
NT9F12FA	Call Center Software 100, Upgrade from CCR only (1000 Agent)	
NT9F13FA	Call Center Software 200, Upgrade from CCR only (1000 Agent)	
NT9F14FA	Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (1000 Agent)	
NT9F15FA	Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1000 Agent)	
NT9F23AA	SYMPOSIUM Server, 1000t Base	
NT9F23CA	SYMPOSIUM Server, 1000t Base with RAID	
NT9F24AA	SYMPOSIUM Server, 1000t Mid	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT9F24CA	SYMPOSIUM Server, 1000t Mid with RAID	
NT9F25AA	SYMPOSIUM Server, 1000t Advanced	
NT9F26BA	SYMPOSIUM Server, 1000t Dual Processor Upgrade	
NT9F26CA	SYMPOSIUM Server, 1000t 32 Mb RAM Upgrade	
NT9F26EA	SYMPOSIUM Server, 1000t 4 Gb HD Upgrade	
NT9F26FA	SYMPOSIUM Server, 1000t 26 Gb Tape Upgrade	
NT9F26GA	SYMPOSIUM Server 1000t, RAID Kit A	
NT9F26HA	SYMPOSIUM Server 1000t, RAID Kit B	
NT9F28AA	SYMPOSIUM Call Center Server 701t Advanced	
NT9F28BA	SYMPOSIUM Call Center Server 701t Advanced with RAID	
NT9F28CA	SYMPOSIUM Call Center Server 701t, RAID Kit A	
NT9F30AA	SYMPOSIUM Call Center Server 1001t	
NT9F30AD	SYMPOSIUM Call Center Server 1001t	
NT9F31AA	SYMPOSIUM Call Center Server 1001t with RAID	
NT9F31AD	SYMPOSIUM Call Center Server 1001t with RAID	
NT9F43AA	SYMPOSIUM Call Center Release 1.1 Client CD-ROM	
NT9F45AB	SYMPOSIUM Call Center Capacity Assessment Tool	NT9F45DA
NT9F45AE	SYMPOSIUM Call Center Server Capacity Assessment Tool	
NT9F45DA	SYMPOSIUM Call Center Capacity Assessment Tool	NT9F45AE
NT9F46AA	SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly	
NT9F51AA	SYMPOSIUM Call Center Server Release 1.0 Replacement Software	
NT9F51AB	SYMPOSIUM Call Center Server Release 1.1 Replacement Software	
NT9F81AA	Ide@Room Software and Hardware Bundle including 100 User IDs, a Windows NT Server and 12 Port MICB Card	
NT9F81BA	Ide@Room Software and Hardware Bundle including 300 User IDs, a Windows NT Server and 24 Port MICB Card	
NT9F81CA	Ide@Room Software and Hardware Bundle including 500 User IDs, a Windows NT Server and 32 Port MICB Card	
NT9F81EA	Ide@Room Software with 50 User IDs	
NT9F81FA	Ide@Room Software with 100 User IDs	
NT9F83AA	Meridian Integrated Conference Bridge (Ide@Room Version) 12 Port Card	
NT9F88AA	Ide@Room 100 User IDs Upgrade	
NT9F88BA	Ide@Room 500 User ID Upgrade	
NT9J94AB	RPE to I/O Cable (2 Ft.)	
NT9N01AA	Multichannel Coax System (MCCS) with One Power Supply	QMT21

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NT9N01BA	Multichannel Coax System (MCCS) with two power supplies	QMT21
NT9N02	Cluster Interface Card (CIC)	QMT21
NT9N03	Blank Faceplate (MCCS)	QMT21
NT9N07	MCCS Power Supply (2nd power supply)	QMT21
NT9N20	Co-Axial Interface Module (CIM)	QMT21
NT9N30AA	COAX Cable w/BNC Connectors (8 Ft.)	
NT9N30AB	COAX Cable w/BNC Connectors (16 Ft.)	
NTA149AA	Liberation Multi-Purpose Amplifier II (MPAII)	
NTA149AQ	Liberation Wireless Amplifier Replacement Battery Pack	
NTA149BI	Liberation Voyager 3-in-1 Headset (M2616CT)	
NTA149BM	Liberation CTI Headset	
NTA149BP	Liberation 3-in-1 Direct Connect Headset (Unamplified)	
NTAG26AA	MF Receiver Card - IPE	NTAG26AB
NTAG36AA	Meridian Integrated RAN Base Card	NTAG36AB
NTAG36AB	Meridian Integrated RAN (Release 2) Base Card	NTAG36AC
NTAG88AA	MIRAN Pack	NTAG88AB
NTAG88AB	MIRAN (Release 2) Pack	NTAG88AC
NTAK01AA	CPU/CONF Card	NTAK01CA
NTAK01CA	CPU/Conference Card	
NTAK02AA	SDI/DCH Card	NTAK02AB
NTAK02AB	SDI/DCH Card	NTAK02BB
NTAK02BB	SDI/DCH Card	NTAK02BC
NTAK03AA	TDS/DTR Card	
NTAK03BA	TDS/DTR Card	NTAK03DA
NTAK04AA	AC/DC Power Supply	NTAK04AB
NTAK04AB	AC/DC Power Supply	NTDK78AA
NTAK05AA	DC/DC Power Supply	NTDK72AA
NTAK09AA	DTI/PRI Card	NTAK09BA
NTAK09BA	DTI/PRI Card	NTAK09DA
NTAK10DB	2.0MB DTI Card with Clock Controller	NTAK10DC
NTAK11BA	Option 11 Main Cabinet	NTAK11BB
NTAK12AA	Option 11 Expansion Cabinet	NTAK12BA
NTAK12BA	Option 11 Main Cabinet	NTAK12BB
NTAK14AA	68K Processor Pack	NTAK14BA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTAK15AA	Digital Voice Processor Card	NTAK15AB
NTAK16AA	C25 Voice Processor Card	NTAK16AB
NTAK17AA	Meridian Mail Card Option Base Pack, 2-6 Ports	NTAK17AB
NTAK17BA	Meridian Mail Card Option Base Package, 8-12 Ports	NTAK17BB
NTAK18AA	RS232C Service Module	NTAK18BA
NTAK19AA	2 Port SDI Cable (6 Ft.)	NTAK19EC
NTAK19BA	4 Port SDI Cable	NTAK19FB
NTAK20AA	Clock Controller Card	NTAK20AB
NTAK20AB	Clock Controller Card	NTAK20AC
NTAK20AC	Clock Controller Card	NTAK20AD
NTAK21AA	Expansion Cartridge	NTAK21BA
NTAK28AA	Battery Junction Box	NTAK28AB
NTAK30CA	External Tape Drive Package	
NTAK30DA	External Tape Drive Package, Tandberg	NTAK30DB
NTAK38AA	Meridian Mail Card Option Documentation Package	NTAK38AC
NTAK38AC	Meridian Mail Card Option Documentation Package	
NTAK39AA	Tape Drive Wall Mounting Kit	NTAK39AB
NTAK57AA	General Business Software	
NTAK57AB	General Business Software	
NTAK57AC	General Business Software	NTAK57AD
NTAK57AD	General Business Software	NTAK57AE
NTAK57AE	General Business Software	NTAK57AG
NTAK57BA	Enhanced Business Software	
NTAK57BB	Enhanced Business Software	
NTAK57BC	Enhanced Business Software	NTAK57BD
NTAK57BD	Enhanced Business Software	NTAK57BE
NTAK57BE	Enhanced Business Software	NTAK57BG
NTAK57CA	Private Networking Software	
NTAK57CB	Private Networking Software	
NTAK57CC	Private Networking Software	NTAK57CD
NTAK57CD	Private Networking Software	NTAK57CE
NTAK57CE	Private Networking Software	NTAK57CG
NTAK57DA	Advanced Applications Software	
NTAK57DB	Advanced Application Software	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTAK57DC	Advanced Applications Software	NTAK57DD
NTAK57DD	Advanced Applications Software	NTAK57DE
NTAK57DE	Advanced Applications Software	NTAK57DG
NTAK57GE	General Business Software (no DISA)	NTAK57GG
NTAK57HE	Enhanced Business Software (no DISA)	NTAK57HG
NTAK57IE	Private Networking Software (no DISA)	NTAK57IG
NTAK72AA	Meridian Mail Base Software	SW7100D
NTAK72AC	Meridian Mail Card Option Master Tape - North American, Release 8	NTAK72AL
NTAK72AC	Meridian Mail Card Option Master Tape - North American, Release 8	NTAK72JL
NTAK72AE	Meridian Mail Card Option Master Tape - North American, Release 9	NTAK72AG
NTAK72AG	Meridian Mail Card Option Master Tape - North American, Release 9	NTAK72AM
NTAK72AJ	Meridian Mail Master Tape - North American, Release 10	NTAK72AK
NTAK72AK	Meridian Mail Master Tape - North American, Release 10	NTAK72AP
NTAK72AL	Meridian Mail Card Option Master Tape - North American, Release 8	NTAK72JL
NTAK72AM	Meridian Mail Card Option Master Tape - North American, Release 9	NTAK72AN
NTAK72AM	Meridian Mail Card Option Master Tape - North American, Release 9	NTAK72GT
NTAK72AN	Meridian Mail Card Option Master Tape - North American, Release 9	
NTAK72AP	Meridian Mail Master Tape - North American, Release 10	NTAK72AS
NTAK72AS	Meridian Mail Master Tape - North American, Release 10	NTAK72LN
NTAK72BC	Meridian Mail Card Option Master Tape - European 1	NTAK72BG
NTAK72BG	Meridian Mail Card Option Master Tape - European 1, Release 9	NTAK72BM
NTAK72BJ	Meridian Mail Master Tape - Europe 1, Release 10	NTAK72BK
NTAK72BK	Meridian Mail Master Tape - Europe 1, Release 10	NTAK72BP
NTAK72BM	Meridian Mail Card Option Master Tape - European 1, Release 9	NTAK72BN
NTAK72BN	Meridian Mail Card Option Master Tape - European 1, Release 9	
NTAK72BP	Meridian Mail Master Tape - Europe 1, Release 10	NTAK72BS
NTAK72BS	Meridian Mail Master Tape - Europe 1, Release 10	NTAK72GN
NTAK72CC	Meridian Mail Card Option Master Tape - European 2	NTAK72CG
NTAK72CG	Meridian Mail Card Option Master Tape - European 2, Release 9	NTAK72CM
NTAK72CJ	Meridian Mail Master Tape - Europe 2, Release 10	NTAK72CK
NTAK72CK	Meridian Mail Master Tape - Europe 2, Release 10	NTAK72CP
NTAK72CM	Meridian Mail Card Option Master Tape - European 2, Release 9	NTAK72CN
NTAK72CN	Meridian Mail Card Option Master Tape - European 2, Release 9	
NTAK72CP	Meridian Mail Master Tape - Europe 2, Release 10	NTAK72CS

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTAK72CS	Meridian Mail Master Tape - Europe 2, Release 10	NTAK72HN
NTAK72DC	Meridian Mail Card Option Master Tape - Asia/Pacific	NTAK72DD
NTAK72DD	Meridian Mail Card Option Master Tape - Asia/Pacific	NTAK72DG
NTAK72DG	Meridian Mail Card Option Master Tape - Asia/Pacific, Release 9	NTAK72DM
NTAK72DJ	Meridian Mail Master Tape - Asia/Pacific, Release 10	NTAK72DK
NTAK72DK	Meridian Mail Master Tape - Asia/Pacific, Release 10	NTAK72DP
NTAK72DM	Meridian Mail Card Option Master Tape - Asia/Pacific, Release 9	NTAK72DN
NTAK72DN	Meridian Mail Card Option Master Tape - Asia/Pacific, Release 9	
NTAK72DP	Meridian Mail Master Tape - Asia/Pacific, Release 10	NTAK72DS
NTAK72DS	Meridian Mail Master Tape - Asia/Pacific, Release 10	NTAK72KN
NTAK72EC	Meridian Mail Card Option Master Tape - European 3	NTAK72EG
NTAK72EG	Meridian Mail Card Option Master Tape - European 3, Release 9	NTAK72EM
NTAK72EJ	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72EK
NTAK72EK	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72EP
NTAK72EM	Meridian Mail Card Option Master Tape - European 3, Release 9	NTAK72AN
NTAK72EM	Meridian Mail Card Option Master Tape - European 3, Release 9	NTAK72EN
NTAK72EN	Meridian Mail Card Option Master Tape - European 3, Release 9	NTAK72NM
NTAK72EP	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72ES
NTAK72ES	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72JS
NTAK72FG	Meridian Mail Card Option Master Tape - European 4, Release 9	NTAK72FM
NTAK72FJ	Meridian Mail Master Tape - Europe 4, Release 10	NTAK72FK
NTAK72FK	Meridian Mail Master Tape - Europe 4, Release 10	NTAK72FP
NTAK72FM	Meridian Mail Card Option Master Tape - European 4, Release 9	NTAK72FN
NTAK72FN	Meridian Mail Card Option Master Tape - European 4, Release 9	NTAK72MM
NTAK72FP	Meridian Mail Master Tape - Europe 4, Release 10	NTAK72FS
NTAK72FS	Meridian Mail Master Tape - Europe 4, Release 10	NTAK72HS
NTAK72HS	Meridian Mail Master Tape - Europe 4, Release 10	NTAK72QN
NTAK72JS	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72KS
NTAK72JS	Meridian Mail Master Tape - Europe 3, Release 10	NTAK72PN
NTAK72MM	Meridian Mail Card Option Master Tape - European 4, Release 9	
NTAK72NM	Meridian Mail Card Option Master Tape - European 3, Release 9	NTAK72KT
NTAK75AA	2-4 Hour Battery Back-Up Unit	NTAK75AB
NTAK76AA	15-30 Minute Battery Back-up Unit	NTAK76AB
NTAK82AA	Option 11 Documentation Package	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTAK82AB	Option 11 Documentation Package	NTAK82AD
NTAK82AD	Option 11 NTP Package	NTAK82AE
NTAK82AE	Option 11 NTP Package Release 18	NTAK82AF
NTAK92AA	OPS Protection Module	NTAK92AB
NTAK92AB	OPS Protection Module	NTAK92BA
NTAK93AA	DCHI Card	NTAK93AB
NTBK45AB	System Core Pack	NTBK45AC
NTBK54AC	Main Fiber Interface (MFI) Kit	NTBK54AB
NTBK55AC	Expansion Fiber Interface (EFI) Kit	NTBK55AB
NTBK62AA	MFI/EFI Power Cable	NTBK62AB
NTBK78AA	Fiber Cable (33 Ft.)	A0632902
NTBK83AA	Release 20 Software Cartridge - General	NTBK83AB
NTBK83AB	Release 20 Software Cartridge - General	NTBK83AD
NTBK83AD	Release 21 Software Cartridge - General Business Package	NTBK83AE
NTBK83AE	Release 21 Software Cartridge - General Business Package	NTBK83AG
NTBK83BA	Release 20 Software Cartridge - Enhanced	NTBK83BB
NTBK83BB	Release 20 Software Cartridge - Enhanced	NTBK83BD
NTBK83BD	Release 21 Software Cartridge - Enhanced Business Package	NTBK83BE
NTBK83BE	Release 21 Software Cartridge - Enhanced Business Package	NTBK83BG
NTBK83CA	Release 20 Software Cartridge - Enterprise	NTBK83CB
NTBK83CB	Release 20 Software Cartridge - Enterprise	NTBK83CD
NTBK83CD	Release 21 Software Cartridge - Enterprise Business Package	NTBK83CE
NTBK83CE	Release 21 Software Cartridge - Enterprise Business Package	NTBK83CG
NTBK83DA	Release 20 Software Cartridge - General (No DISA)	NTBK83DB
NTBK83DB	Release 20 Software Cartridge - General (No DISA)	NTBK83DD
NTBK83DD	Release 21 Software Cartridge - General (No DISA)	NTBK83DE
NTBK83DE	Release 21 Software Cartridge - General (No DISA)	NTBK83DG
NTBK83EA	Release 20 Software Cartridge - Enhanced (No DISA)	NTBK83EB
NTBK83EB	Release 20 Software Cartridge - Enhanced (No DISA)	NTBK83ED
NTBK83ED	Release 21 Software Cartridge - Enhanced (No DISA)	NTBK83EE
NTBK83EE	Release 21 Software Cartridge - Enhanced (No DISA)	NTBK83EG
NTBK83FA	Release 20 Software Cartridge - Enterprise (No DISA)	NTBK83FB
NTBK83FB	Release 20 Software Cartridge - Enterprise (No DISA)	NTBK83FD
NTBK83FD	Release 21 Software Cartridge - Enterprise (No DISA)	NTBK83FE

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTBK83FE	Release 21 Software Cartridge - Enterprise Business (No DISA)	NTBK83FG
NTBK83GA	Release 20 Software Cartridge - Network Attendant Service	NTBK83GB
NTBK83GB	Release 20 Software Cartridge - Network Attendant Service	NTBK83GD
NTBK83GD	Release 21 Software Cartridge - Network Attendant Service (NAS)	NTBK83GE
NTBK83GE	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package	NTBK83GG
NTBK83HA	Release 20 Software Cartridge - Network Attendant Service (No DISA)	NTBK83HB
NTBK83HB	Release 20 Software Cartridge - Network Attendant Service (No DISA)	NTBK83HD
NTBK83HD	Release 21 Software Cartridge - Network Attendant Service (No DISA)	NTBK83HE
NTBK83HE	Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package (No DISA)	NTBK83HG
NTBX80AA	NT-1 Stand Alone Unit	
NTBX84AA	NT-1 Basic Unit RM	NTBX84AA
NTBX84BA	Rackmount NT1 Star Card	
NTCW80AA	Meridian Integrated IP Telephony Gateway (ITG) Base Card	NTCW80CA
NTCW84BA	Meridian Integrated IP Telephony Gateway Large System Voice Port Ethernet Cable	NTCW84GA
NTCW84CA	Meridian Integrated IP Telephony Gateway Option 11C/11E Voice Port Ethernet Cable	NTCW84FA
NTCW84FA	Meridian Integrated IP Telephony Gateway Option 11C/11E Voice Port Ethernet Cable	
NTCW84GA	Meridian Integrated IP Telephony Gateway Large System Voice Port Ethernet Cable	
NTDF29AB	Remote Digital Extender Card	NTQR02AA
NTDK01AA	Option 11E - Base Documentation Package (Coil)	NTDK01AB
NTDK01AB	Option 11E - Base Documentation Package (Coil)	NTDK01AC
NTDK01AC	Option 11E - Base Documentation Package (Coil)	
NTDK01BA	Option 11E - Base Documentation Package (Binders)	NTDK01BB
NTDK01BB	Option 11E - Base Documentation Package (Binders)	NTDK01BC
NTDK01BC	Option 11E - Base Documentation Package (Binders)	NT6R77AA
NTDK20AB	System Core Card	NTDK20DA
NTDK20AD	Clock Controller (Stratum 3)	NTAK20AD
NTDK20DA	System Core Card	NTDK20EA
NTDK25AB	2 Mile Fiber Receiver Card - Multi-Mode	NTDK25BB
NTDK50BA	Main/Expansion Cabinet	NTAK11BD
NTDK63BA	Option 11C Distributor Technical Library Package	NTDK63BB
NTDK63BB	Option 11C Distributor Technical Library Package	NTDK63BD
NTDK66AA	Meridian Mail Modem Package	NTDK66AB

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTDK74AA	Card Option 2GB Disk Drive	NTDK74AB
NTDK76AA	Option 11C Customer Documentation Library on CD-ROM	NTDK76AB
NTDK76AB	Option 11C Customer Documentation Library on CD-ROM	NTDK76AD
NTDK76AD	Option 11C Customer Documentation Library on CD-ROM (Release 24)	
NTDK80AA	2 Mile Fiber Receiver Card - Single Mode	NTDK80BA
NTDK90AA	Meridian 1 Distributor Small System Documentation Subscription	
NTDR02AA	Meridian HomeOffice II Router	NTQR03AA
NTDR05AA	Planning Guide	NTDR05AB
NTDR05AB	Planning Guide	
NTDR06AA	Network Administration Guide	NTDR06AB
NTDR06AB	Network Administration Guide	
NTDR07AA	Line Card Configuration Guide	NTDR07AB
NTDR07AB	Line Card Configuration Guide	
NTDR15AA	User Guide	NTDR15AB
NTDR15AB	Meridian HomeOffice II User Guide	
NTDR16AA	CD ROM with Jewel Case	NTDR16AB
NTDR50AA	Multi I/O Cable	NTDR50AB
NTHF07AA	SYMPOSIUM Express Call Center Documentation Suite	NTHF07AC
NTHF23AB	SYMPOSIUM Express Call Center Base System	
NTHF62AA	SYMPOSIUM Express Call Center Upgrade to Release 2.0	NTHF63AA
NTHU21AC	Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package AC	NTHU29AC
NTHU21DC	Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC	NTHU29DC
NTJG06AA	MIRAN 1.53 (Upissue) 8MB PCMCIA Card	NTJG06AC
NTJH03AA	Meridian Terminal Emulator (MTE) Release 9 Assembly (Single User)	NTJH03AB
NTJH03BA	Meridian Terminal Emulator (MTE) Release 9 Assembly (System License)	NTJH03BB
NTJH03CA	Meridian Terminal Emulator (MTE) Release 9 Upgrade Assembly (Single User)	NTJH03CB
NTJH03DA	Meridian Terminal Emulator (MTE) Release 9 Upgrade Assembly (System License)	NTJH03DB
NTJH09AA	Meridian Terminal Emulator (MTE) Release 9 Software (Single User)	
NTJH09BA	Meridian Terminal Emulator (MTE) Release 9 Software (System License)	
NTJH09CA	Meridian Terminal Emulator (MTE) Release 9 Software Upgrade (Single User)	NTJH09CB
NTJH09DA	Meridian Terminal Emulator (MTE) Release 9 Software Upgrade (System License)	NTJH09DB
NTJH93EA	MAX-IPE to IPEE Upgrade Kit #1	
NTKG80CD	Option 11C Mini English Documentation Suite - Release 24 - Coil	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTKG80CE	Option 11C Mini English Documentation Suite - Release 25 - Coil	
NTKS0003	Black Sets	
NTKS0035	Ash Sets	
NTKS0093	Gray Sets	
NTKS0103	Black Sets for Option 11C Compact Hospitality Communications Package - NTKS1010	
NTKS0135	Option 11C Compact Hospitality Digital Sets - Ash	
NTKS0193	Option 11C Compact Hospitality Digital Sets - Grey	
NTKS0303	Black Sets for NTKS1030	
NTKS0335	Ash Sets for NTKS1030	
NTKS0393	Grey Sets for NTKS1030	
NTKS1001	Option 11C Compact Office Communications Package	
NTKS1003	Option 11C Compact Demo Package	
NTKS1010	Option 11C Compact Hospitality Communications Package	
NTKS1020	Option 11C Compact Network Message Communications Package	
NTKS1030	Option 11C Compact Small Call Center Communications Package	
NTKS2030	Option 11C Compact Call Center Communications Expansion TN’s	
NTLH15AA	CP PII with IGS Reference Library	NT5F36AA
NTLT82AA	MIRAN to MIRAN Release 2 PCMCIA Upgrade Kit	
NTMA01AA	DC UEM Assembly	NTMA01BA
NTMA01BA	DC UEM Assembly	NTMA01BB
NTMA02AA	V.35/V.11 Cable (54")	
NTMA03AA	DS1 Cable (54")	
NTMA05AA	V.24 Cable (360")	
NTMA06AA	DS3/E3 Cable (66")	
NTMA07AA	DS3/E3 Control Cable (54")	
NTMA08AA	Power Converter Blank	NTMA08BA
NTMA08BA	Power Converter Blank	
NTMA09AA	DC Power Converter	
NTMA11AA	4-Port DS1 Function Processor	
NTMA12AA	1-port DS1V Functional Processor	NTMA12AC
NTMA12AC	1-Port DS1V Function Processor	
NTMA13AA	4-Port DS1C (Channelized) Function Processor	
NTMA17AA	8-Port V.11 Function Processor	
NTMA18AA	8-port V.35 Functional Processor	NTMA18AB

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTMA18AB	8-Port V.35 Function Processor	
NTMA20AA	1-Port DS3 Function Processor	
NTMA21AA	Control Processor e/w 256 MB Hard Drive	NTMA21AB
NTMA21AB	Control Processor e/w 810 MB Hard Drive	
NTMA22AA	3-Port DS1 ATM Function Processor	
NTMA24AA	3-Port DS3 ATM Function Processor	
NTMA27AA	Blank Pack	
NTMA29AA	DS3/E3 Cable with Ferrite	
NTMA31AA	Alarm Cable	
NTMA32AA	Meridian Passport Module DC Power Harness	
NTMA34AA	XSM Cable with Ferrite	
NTMA36AA	1.5M PRI/DTI To DS1V Cable (10 Ft.)	
NTMA36BA	1.5M PRI/DTI To DS1V Cable (16 Ft.)	
NTMA36CA	1.5M PRI/DTI To DS1V Cable (32 Ft.)	
NTMA49AA	3-Port DS3/E3 Termination Panel	
NTMA50AA	DS3/E3 ATM Control Cable (54")	
NTMA62AA	OC-3 ATM Mixed Mode Function Processor	
NTMA67AA	OC-3 ATM MX Fiber Cable Assembly	
NTMA7001	OC-3 Fiber Interface Package	
NTMA75AA	V.35 Fanout Panel	NTMA75AB
NTMA75AB	V.11 Termination Panel	
NTMA76AA	DS1/E1 Termination Panel	
NTMA78AA	V.35 Fanout Panel	NTMA78AB
NTMA78AB	V.35 Termination Panel	
NTMA79AA	DS3/E3 Termination Panel	
NTMA9011	Meridian Passport Module Package (-48V DC Power)	NTMA9013
NTMA9013	Meridian Passport Module Package (-48V DC Power)	
NTMA9111	Meridian Passport System Package (-48V DC Power) (Free Standing Module)	NTMA9113
NTMA9113	Meridian Passport System Package (-48V DC Power) (Free Standing Module)	
NTMA9901	Meridian Passport Base Information Binder	NTMA9902
NTMA9902	Meridian Passport Description and Installation Binder	NTMA9903
NTMA9903	Meridian Passport Description and Installation Binder	
NTMA9911	Meridian Passport Operations Binder	NTMA9912
NTMA9912	Meridian Passport Operations Binder	NTMA9913

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTMA9913	Meridian Passport Operations Binder	
NTMA9921	Meridian Passport Components Binder	NTMA9922
NTMA9922	Meridian Passport Components Binder	NTMA9923
NTMA9923	Meridian Passport Components Binder	
NTMA9931	Meridian Passport Voice Services Binder	NTMA9932
NTMA9932	Meridian Passport Voice Services Binder	NTMA9933
NTMA9933	Meridian Passport Voice Services Binder	
NTMA9941	Meridian Passport Frame Relay and HDLC Binder	NTMA9942
NTMA9942	Meridian Passport Frame Relay and HDLC Binder	NTMA9943
NTMA9943	Meridian Passport Frame Relay and HDLC Binder	
NTMA9952	Meridian Passport ATM Binder	NTMA9953
NTMA9953	Meridian Passport ATM Binder	
NTMA9991	Meridian Passport System Management Binder	NTMA9992
NTMA9992	Meridian Passport System Management Binder	
NTMA99AA	Meridian Passport and NMS Documentation (CD-ROM)	NTMA99BA
NTMA99BA	Meridian Passport Documentation (CD-ROM)	NTMA99CA
NTMA99CA	Meridian Passport Documentation (CD-ROM)	
NTMF94AA	MIRAN (Release 2) Ethernet & DB9 Adapter	NTMF94BA
NTMF94BA	Meridian Integrated ITG I/O Panel Ethernet and Serial Port Adapter Cable	NTMF94DA
NTMN66AA66	Meridian Key-Based Expansion Module, Platinum (M3900 Series)	
NTMN66AA70	Meridian Key-Based Expansion Module, Charcoal (M3900 Series)	
NTMN69AA66	Meridian Communications Adapter (MCA), Platinum (M3900 Series)	
NTMN69AA70	Meridian Communications Adapter (MCA), Charcoal (M3900 Series)	
NTMS01AA	Meridian Passport Base Software	NTMS01CA
NTMS01CA	Meridian Passport Base Software	
NTMS1001	Meridian Passport Module Software Package	NTMS1101
NTMS1101	Meridian Passport Module Software Package	
NTMS21AA	Path Oriented Routing Software	
NTMS22AA	Connectionless Routing Software	
NTMS2425	Conference Bridge Bundle	
NTMS31AA	Passport (Frame/Cell) Network Trunk Software	
NTMS4001	Meridian Passport Frame Relay Software Package	
NTMS4825	Bridge	
NTMS5001	Voice Package	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTMS54AA	Speech Activity Detection Software	
NTMS61AA	Bit Transparent Data	
NTMS62AA	HDLC Transparent Data	
NTMS71AA	ATM Application Software Package	
NTMS91AA	Network Management System (NMS) Advisor 1	NTMS91DA
NTMS91BA	Network Management System (NMS) Advisor 2	
NTMS91DA	Open Management System - Passport	NTMS91EA
NTMS91EA	Open Management System - Passport	
NTMS92AA	Network Management System (NMS) Expert Advisor	
NTMS93AA	Network Management System (NMS) Architect 1	
NTMS93BA	Network Management System (NMS) Architect 2	
NTMS93CA	Network Management System (NMS) Architect 3	
NTMS94AA	Network Management System (NMS) Accounting Management	
NTMS94BA	Network Management System (NMS) Performance Management	
NTMS95AA	Network Management System (NMS) SNMP Integrator	
NTMS96AA	Network Management System (NMS) LAN Services	
NTMS97AA	Network Management System (NMS) Utilities	
NTMS9801	Meridian Passport Manager for MAT	
NTMS98AA	Network Management System (NMS) Meridian View (per workstation)	
NTMS9901	Meridian Passport Manager Package	
NTMW02AA	Meridian Mail Compact Option 68K Memory Card	NTMW02AB
NTMW11AA	Option 11C Compact AC Power Supply	NTMW11AB
NTMW15AA	Meridian Mail Compact Option Base Hardware Package	NTMW15AC
NTMW18AB	Meridian Mail Compact Option S/W Package.	NTMW18AC
NTMW18AC	Meridian Mail Compact Option S/W Package	NTMW18BA
NTMW30AC	Option 11C Compact Release 1.10 Programmed Software Daughterboard	NTMW30AD
NTMW30CC	Option 11C Compact Office Communications Feature Set (S/W)	NTMW30CD
NTMW30DC	Option 11C Compact Inter-Office Communications Feature Set (S/W)	NTMW30DD
NTMW30EC	Option 11C Compact Hospitality Communications Feature Set (S/W)	NTMW30ED
NTMW30FC	Option 11C Compact Advanced Hospitality Communications Feature Set (S/W)	NTMW30FD
NTMW42AA	Option 11C Compact Documentation - CD ROM	NTMW42BA
NTMW42BA	Option 11C Compact Documentation Library (CDROM)	NTMW42CA
NTMW43AA	Option 11C Compact Customer Documentation Package	NTMW43AB
NTMW43AB	Option 11C Compact Customer Documentation Package	NTMW43BA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTMW45AA	MAT 5.7 Option 11C Compact - Update Disk Package	
NTND01BA	Integrated CPU/6 Mbyte Memory Card	
NTND01CA	Integrated CPU/12MB Memory Card	
NTND02BA	SDI/Peripheral Signaling Card with Battery	
NTND05AA	Meridian Mail Modular GP Power Supply DC	
NTND08AA	ROM Card	NTND08AB
NTND08AB	ROM Card	NTND08AC
NTND08AC	ROM Card	NTND08AE
NTND08AE	ROM Card	
NTND09BA	6 Mbyte Memory Card	NTND09CA
NTND09CA	12 Mbyte Memory Card	
NTND10AA	Changeover & Memory Arbitrator Card	
NTND11AA	CP to CP Cable (6 Ft.)	NTND11BA
NTND13AC	IOP to IOP SCSI Cable (6 Ft.)	NTND13BC
NTND14AB	CNI to 3PE Cable (10 Ft.)	NTND14BB
NTND14AC	CNI to 3PE Cable (12 Ft.)	NTND14BC
NTND14AD	CNI to 3PE Cable (16 Ft.)	NTND14BD
NTND14AE	CNI to 3PE Cable (25 Ft.)	NTND14BE
NTND15AA	4 Mbyte Floppy Disk Unit	
NTND16AA	4 Mbyte Multi-Disk Unit	
NTND21AA	Module Side Cover	NT9D17AA
NTND22AB	Meridian Manager Documentation Package (Version 2)	
NTND28AA	Inter-Cabinet Cable (13 Ft.)	
NTND28BA	Inter-Cabinet Cable (16 Ft.)	
NTND31AA	ROM Card	NTND31AB
NTND31AB	ROM Card	
NTND33AA	Network Group Expansion Interface Kit	NTND33BA
NTND33BB	Core-Cabinet Upgrade Cable Kit, Group 0	NTND33CB
NTND33BC	Core-Cabinet Upgrade Cable Group 1-2	NTND33CC
NTND33BD	Core-Cabinet Upgrade Cable Kit, Groups 3-4	NTND33CD
NTND33CB	Core-Cabinet Upgrade Cable Kit, Group 0	
NTND33CD	Core-Cabinet Upgrade Cable Kit, Groups 3-4	NTND33CC
NTND37AA	Dual Serial Data Interface (SDI) Cable	
NTND46AE	UNIX R3V7.1	NTND46AF

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTND63AA	Meridian MAX Release 4 NTPs	A0397928
NTND64AA	Meridian MAX Release 4 Users Guide Package	
NTND80AA	Option 81 Database Transfer Cable	
NTND94BA	CNI to I/O Panel Ethernet Cable (17 In.)	NTND94DA
NTND94CA	CNI to I/O Panel Ethernet Cable (13 In.)	NTND94DA
NTPD00AA	Network Administration Center Hardware Package	SY7421A
NTPD00AA	Network Administration Center Hardware Package	SY7421D
NTPD01AA	Network Administration Center Software and Documentation Package	SW7426
NTRG11AA	CallPilot Basic Administration Documentation Package - English	NTRG11AB
NTRG19AA	CallPilot Documentation CD ROM	NTRG19AB
NTRH08AA	Pigtail Jumper Block	
NTRH20AA	CallPilot MPB-16	
NTRH9001	1 GB SCSI SCA Disk Drive	
NTRH9026	ISA Token Ring Network Card	
NTRH9033	AC to DC Inverter for SYMPOSIUM Call Center, 48 to 240 Volt	
NTRH9056	VTG VB2001	
NTSF1001	Option 11C Single Cabinet Hardware Package AC	NTSF1101
NTSF1002	Option 11C Single Cabinet Hardware Package DC	NTSF1102
NTSF2001	Option 11C - 30 Ft. Expansion Cabinet AC	NTSF2101
NTSF2002	Option 11C - 30 Ft. Expansion Cabinet DC	NTSF2102
NTSF2003	Option 11C - 2 Mile Expansion Cabinet AC	NTSF2103
NTSF2004	Option 11C - 2 Mile Expansion Cabinet DC	NTSF2104
NTSF2005	Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber)	NTSF2105
NTSF2006	Option 11C - 2 Mile Expansion Cabinet Package DC (Single Mode Fiber)	NTSF2106
NTSF6101	Option 11/11E to 11C Single Cabinet Upgrade	
NTSF6102	Option 11/11E to 11C Two Cabinet Copper	
NTSF6103	Option 11/11E to 11C Two Cabinet Fiber (30 Ft.)	
NTSF6104	Option 11/11E to 11C Two Cabinet Fiber (2 Mile)	
NTSF6105	Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Fiber (30 Ft.)	
NTSF6106	Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Fiber (2 Mile)	
NTSF6107	Option 11/11E 2 Cabinet to Option 11C 2 Cabinet Ethernet (2 Mile Single Mode Fiber)	
NTSF6108	Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Ethernet (2 Mile Single Mode Fiber)	
NTSK11CA	NA Feature Set #1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTSK11CF	NA Feature Set #1	NTSK11CG
NTSK11CG	NA Feature Set #1	NTSK11CH
NTSK11CH	NA General Business Feature Set	NTSK11CK
NTSK11CK	Option 11C General Business Feature Set - Release 24B	NTSK11CN
NTSK11DA	NA Feature Set #2	
NTSK11DF	NA Feature Set #2	NTSK11DG
NTSK11DG	NA Feature Set #2	NTSK11DH
NTSK11DH	NA Enhanced Business Feature Set	NTSK11DK
NTSK11DK	Option 11C Enhanced Business Feature Set - Release 24B	NTSK11DN
NTSK11EA	NA Feature Set #3	
NTSK11EF	NA Feature Set #3	NTSK11EG
NTSK11EG	NA Feature Set #3	NTSK11EH
NTSK11EH	NA Enterprise Business Feature Set	NTSK11EK
NTSK11EK	Option 11C Enterprise Business Feature Set - Release 24B	NTSK11EN
NTSK11FA	NA Feature Set #4	
NTSK11FF	NA Feature Set #4	NTSK11FG
NTSK11FG	NA Feature Set #4	NTSK11FH
NTSK11FH	NA NAS/VNS Feature Set	NTSK11FK
NTSK11FK	Option 11C NAS/VNS Feature Set - Release 24B	NTSK11FN
NTSK11ZK	Release 24.24 Programmed Mini System Controller Pack	
NTTK30AA	Option 11C Release 25 English Documentation Package, Binder	
NTTK31AA	Option 11C Release 25 English Documentation Package, Coil	
NTTK32AB	Option 11C Mini Customer Documentation Library on CD-ROM (Release 24)	
NTUB06AA	CallPilot 702t Configuration Assembly	NTUB06AB
NTUB57AA	CallPilot MGate Kit	NTUB57AB
NTUB60AA	CallPilot MPB-16	NTUB60AB
NTV201AX	IIVR 2.2 Memory Package - 64MB	
NTV202AR	32MB RAM Spare	
NTV403EB	100MB Ethernet Kit	
NTV405VA	Uninterruptible Power Supply (UPS) Tower Model - 220V - 1 AP, MRS/AP, or MRS/Tower	
NTV406PP	SBC for High Performance MRS/AP, AP, and MRS	
NTV406RH	Hard Drive for High Performance Rack AP and MRS/Rack	
NTV406TH	Hard Drive for High Performance MRS/AP, Tower AP, and MRS/Tower	
NTV407AA	64MB RAM Expansion for AP or MRS/AP	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTV407LA	128MB RAM	
NTV407LL	256MB RAM	
NTV410AA	Base AP, Runtime Software, 0 Port-Global	
NTV410HP	High Performance Tower AP (700TP), 0 Port - Global	
NTV413PA	High Performance Rack AP, AC, Global	
NTV413PD	High Performance Rack AP, DC, Global	
NTV420HP	High Performance MRS/Tower, 0 Port - Global	
NTV430PA	High Performance MRS/Rack, AC, 0 Port, Global	
NTV430PD	High Performance MRS/Rack, DC, 0 Port, Global	
NTV430RR	Redundant 500W DC Power for MRS/RACK or Rack AP	
NTV440AA	Base MRS/AP, Runtime Software, 0 Port - Global	
NTV440HP	High Performance MRS/AP (700TP), 0 Port, Global	
NTV454YA	VT100 over TN - Base and 16 Sessions	
NTV454ZA	VT100 over TN - Expansion 16 Sessions	
NTV456EA	OpenLink Database Support	
NTV472EA	Uninterruptible Power Supply (UPS) Shared Rack Model - 220 V - Up to 3 MRS/ Rack or AP/Rack Shelves	
NTV472FA	DC Rack Cabinet - Full Assembly - 220V Inverter	
NTV472NA	Uninterruptible Power Supply (UPS) Shared Rack Model - 110 V - Up to 3 MRS/ Rack or AP/Rack Shelves	NTV474NA
NTV472XA	DC Rack Cabinet - Expansion	
NTV472ZA	DC Rack Cabinet - Expansion - 220V Inverter	
NTV483TA	Integration Package for Nortel TAPI Server - Media (CD) and 4 Port Base RTU	
NTV483UA	Integration Package for Nortel TAPI Server - 4 Port Expansion RTU	
NTVA0001	Assistant 25 User License	
NTVA0004	Assistant 500 User License	
NTVA0006	Assistant 1000 User License	
NTVA0008	Assistant 50 User License	
NTVA0009	Assistant 200 User License	
NTVA01AA	Assistant 1.0 Computer Based Training	
NTVA11AA	Assistant Server Application Software	
NTVB00AA	CallPilot European Language & Desktop Client CD ROM Kit	
NTVE8217	OPEN IVR Release 4 - Audio Interface Guide	
NTVE8219	OPEN IVR Release 4 - Prompt Conversion Guide	
NTVE8220	OPEN IVR Release 4 - Prompt Management Overview Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTVE8225	OPEN IVR Release 4 - Integration Package for Nortel TAPI Server Guide	
NTVE9002	2GB SCSI SCA Disk Drive (Hot Swap) Spare	
NTVE9003	4.5GB SCSI Disk Drive Spare for OIVR 4.0 MRS/Rack or Rack AP	NTV406RA
NTVE9005	SCSI CD ROM Drive Spare	NTV406CA
NTVE9006	3.5" SCSI DAT Tape Drive Spare	NTV406DA
NTVE9011	14" Monitor Spare	NTV404SA
NTVE9012	17" Monitor Spare	NTV404MA
NTVE9026	ISA Token Ring Network Card Spare	NTV403TA
NTVE9029	2GB 16BIT Ultra SCSI Disk Drive Spare	
NTVE9030	4.5GB SCSI SCA Disk Drive Spare for AP, MRS/AP, R4 MRS/Tower	NTV406TA
NTVE9032	48 VDC TO 120 VAC Static Inverter Spare	
NTVE9042	PCI SCSI Adapter Spare	
NTVE9902	32MB Expansion RAM for AP or MRS/AP Spare	
NTVE9904	Base Chassis for MRS/AP or AP	
NTVE9905	Base Single Board Computer for AP or MRS/AP Spare	
NTVE9918	VGA Monitor Cable - 2 Meters Spare	
NTVE9920	VGA Monitor Cable - 4 Meters Spare	
NTVE9922	101 Enhanced Keyboard Spare	
NTVE9930	233MHz MMX SBC Kit for AP (700tp), MRS/AP (700tp), MRS/Tower, MRS/Rack, AP/Rack	
NTVE9931	Monitor - 21" Spare	NTV404LA
NTVE9956	64MB (SIMM) Expansion RAM for AP or MRS/AP	
NTVM0001	VISIT Messenger Visual Voice Messaging Client Package, 100 Users	NTVM0014
NTVM0002	Messenger 1.1 Windows Client Package, 100 Users	
NTVM0003	VISIT Messenger Visual Voice Messaging Client Package, 300 Users	
NTVM0004	VISIT Messenger Visual Voice and FAX Messaging Client Package, 300 Users	
NTVM0005	VISIT Messenger Visual Voice Messaging Client Package, 500 Users	NTVM0016
NTVM0006	VISIT Messenger Visual Voice and FAX Messaging Client Package, 500 Users	NTVM0016
NTVM0007	VISIT Messenger Visual Voice Messaging Client Package, 800 Users	
NTVM0008	VISIT Messenger Visual Voice and FAX Messaging Client Package, 800 Users	
NTVM0009	VISIT Messenger Visual Voice Messaging Client Package, 1000 Users	NTVM0027
NTVM0010	VISIT Messenger Visual Voice and FAX Messaging Client Package, 1000 Users	NTVM0027
NTVM0012	VM 1.1 25 Clients Fax and Voice	
NTVM0013	Messenger 2.0 Windows Client Package - 25 Users	
NTVM0014	Messenger 2.0 Windows Client Package - 100 Users	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTVM0016	Messenger 2.0 Windows Client Package - 500 Users	
NTVM0027	Messenger 2.0 Windows Client Package - 1000 Users	
NTVM0028	Messenger 2.0 Windows Client Package - 50 Users	
NTVM0029	Messenger 2.0 Windows Client Package - 200 Users	
NTVM0030	Messenger 2.0 Windows Client Package - 2000 Users	
NTVM0034	Messenger 2.0 Mac Client Package - 25 Users	
NTVM0035	Messenger 2.0 Mac Client Package - 50 Users	
NTVM0037	Messenger 2.0 Mac Client Package - 200 Users	
NTVM0038	Messenger 2.0 Mac Client Package - 500 Users	
NTVM0039	Messenger 2.0 Mac Client Package - 1000 Users	
NTVM0040	Messenger 2.0 Mac Client Package - 2000 Users	
NTVM0051	Messenger 3.0 Windows Client Package - 25 Users	
NTVM0052	Messenger 3.0 Windows Client Package - 50 Users	
NTVM0053	Messenger 3.0 Windows Client Package - 100 Users	
NTVM0054	Messenger 3.0 Windows Client Package - 200 Users	
NTVM0055	Messenger 3.0 Windows Client Package - 500 Users	
NTVM0056	Messenger 3.0 Windows Client Package - 1000 Users	
NTVM0057	Messenger 3.0 Windows Client Package - 2000 Users	
NTVM0062	Messenger 4.0 Windows Client Package - 50	
NTVM0063	Messenger 4.0 Windows Client Package - 100	
NTVM0064	Messenger 4.0 Windows Client Package - 200	
NTVM0065	Messenger 4.0 Windows Client Package - 500	
NTVM0066	Messenger 4.0 Windows Client Package - 1000	
NTVM0067	Messenger 4.0 Windows Client Package - 2000	
NTVM00AA	Ethernet LAN Interface Card with NETBEUI drivers	
NTVM00BA	Ethernet LAN Interface Card with Netware IPX NetBIOS drivers	
NTVM00CA	Ethernet LAN Interface Card with TCP NetBIOS drivers	
NTVM00DA	Token Ring LAN Interface Card with NETBEUI drivers	
NTVM00EA	Token Ring LAN Interface Card with Netware IPX NetBIOS drivers	
NTVM00FA	Token Ring LAN Interface Card with TCP NetBIOS drivers	
NTVM00GA	Ethernet LAN Interface - Netware SPX	
NTVM00HA	Server Upgrade Kit from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging	
NTVM00JA	Messenger 1.1 Fax on Demand	
NTVM00JC	Messenger 1.1 Fax on Demand Upgrade	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTVM00LA	1 GB Disk Drive	
NTVM00MA	Token Ring LAN Interface - Netware SPX	
NTVM00NA	Ethernet NetBEUI LAN Integration Software	
NTVM00PA	Ethernet Netware SPX LAN Integration Software	
NTVM00RA	Token Ring, NetBEUI LAN Integration Software	
NTVM00SA	Messenger 1.1 to 2.0 Software Upgrade	
NTVM00SB	Messenger 2.0 to 3.0 Software Upgrade	
NTVM00SC	Messenger Software Upgrade Kit Only 1.1 to 3.0	
NTVM00SF	Pentium Platform Based Messenger 1.1 to 4.0 Upgrade	
NTVM00WA	Pentium CPU Upgrade	
NTVM00XA	16 MB Memory Upgrade	
NTVM00ZA	2 GB Hard Drive	
NTVM00ZB	4 GB Hard Drive	
NTVM00ZC	9 GB Hard Drive	
NTVM00ZD	MAS 486/33 Access port upgrade for Visit Messenger 1.1 and Visit Assistant 1.0	
NTVM00ZE	1 GB Hard Drive	
NTVM0100	VISIT Messenger User Guide	
NTVM0200	1.0 Administration Guide	
NTVM0300	VISIT Messenger Server Administration Guide	
NTVM0301	Messenger 2.0/3.0 System Administration Guide	
NTVM12AA	VISIT Messenger Visual Voice Messaging Server Package	
NTVM12BA	VISIT Messenger Visual Voice and Fax Messaging Server Package, 4 Port	
NTVM12BB	Meridian Applications Server Model 100	
NTVM12CA	Meridian Applications Server Model 500	
NTVM12DA	MAS Model 501 Server	
NTVM13AA	Messenger 2.0 Server Software Meridian Mail, Fax, and E-Mail	NTVM15AA
NTVM15AA	Messenger 3.0/2.0 Server Software (Brooktrout)	
NTVM16AA	Messenger 1.1 Server Software Kit	
NTVM3301	Messenger Windows User Interface	NTVM3303
NTVM4022	SCO IPX/SPX LAN Integration Software	
NTVM50UG	Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 100 Users	
NTVM52UG	Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 300 Users	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTVM54UG	Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 500 Users	
NTVM56UG	Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 800 Users	
NTVM58UG	Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 1000 Users	
NTVM6002	Client Training CBT	NTVM6003
NTWH90AA	Meridian Integrated IP Telephony Gateway (ITG) Card (Hardware)	NTWH90CA
NTZB06AA	Mini Local Package (Options 21-81)	NTZB06AB
NTZB07AA	Mini Local Package (Option 11)	NTZB07AB
NTZB20BA	SYMPOSIUM WebResponse Server Basic Package	NT2F62AA
NTZB21AA	SYMPOSIUM WebResponse Server 1 Client Expansion Package	NT2F63AA
NTZB21BA	SYMPOSIUM WebResponse Server 10 Client Expansion Package	NT2F63BA
NTZB21CA	SYMPOSIUM WebResponse Server 25 Client Expansion Package	NT2F63CA
NTZB22AA	Meridian Integrated Conference Bridge (Ide@Room Version) 24 Port Card	
NTZB22BA	Meridian Integrated Conference Bridge (Ide@Room Version) 12 to 24 Port Upgrade	
NTZB22CA	Meridian Integrated Conference Bridge (Ide@Room Version) 12 to 32 Port Upgrade	
NTZB22DA	Meridian Integrated Conference Bridge (Ide@Room Version) 32 Port Card	
NTZB22EA	Meridian Integrated Conference Bridge (Ide@Room version) 16 to 32 port upgrade	
NTZB22FA	Meridian Integrated Conference Bridge (Ide@Room version) 24 to 32 Port Upgrade	
NTZC01AA	MAT 6 End User Common Services	NTZC01AB
NTZC01AB	MAT 6, End User Common Services	NTZC01AC
NTZC01AB	MAT 6, End User Common Services	NTZC01AD
NTZC01AC	MAT 6, End User Common Services	NTZC01AD
NTZC01AD	MAT 6, End User Common Services	NTZC01AF
NTZC01BA	MAT 6 Distributor Common Services	NTZC01BB
NTZC01BB	MAT 6, Distributor Common Services	NTZC01BC
NTZC01BC	MAT 6, Distributor Common Services	NTZC01BD
NTZC01BD	MAT 6, Distributor Common Services	NTZC01BF
NTZC03AA	MAT 6, User Guide and CD Package	NTZC03AC
NTZC03AC	MAT 6, User Guide and CD Package	NTZC03AD
NTZC03AD	MAT 6, User Guide and CD Package	NTZC03AF
NTZC07AA	MAT 6 Distributor Single Location Common Services and Station Upgrade	NTZC07AB
NTZC07AB	MAT 6, Distributor Single Location Common Services and Station Upgrade	NTZC07AC
NTZC07AB	MAT 6, Distributor Single Location Common Services and Station Upgrade	NTZC07AD

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZC07AC	MAT 6, Distributor Single Location Common Services and Station Upgrade	NTZC07AD
NTZC07AD	MAT 6, Distributor Single Location Common Services and Station Upgrade	NTZC07AF
NTZC08AA	MAT 5.x to 6 Flat-fee Upgrade	
NTZC08AB	MAT 5/6 to MAT 6.X, Flat Fee Upgrade	NTZC08AC
NTZC08AC	MAT 5/6 to MAT 6.X, Flat Fee Upgrade	NTZC08AD
NTZC08AD	MAT 5/6 to MAT 6.X, Flat Fee Upgrade	NTZC08AF
NTZC09AA	MAT 6 End User Common Services Upgrade	NTZC09AB
NTZC09AB	MAT 6, End User Common Services Upgrade	NTZC09AC
NTZC09AB	MAT 6, End User Common Services Upgrade	NTZC09AD
NTZC09AC	MAT 6, End User Common Services Upgrade	NTZC09AD
NTZC09AD	MAT 6, End User Common Services Upgrade	NTZC09AF
NTZC10AA	PC Dongle for One (1) PC	NTZC10AB
NTZC10AB	PC Dongle for One (1) PC and User Guide	NTZC10AC
NTZC10AB	PC Dongle for One (1) PC and User Guide	NTZC10AD
NTZC10AC	PC Dongle for One (1) PC and User Guide	NTZC10AD
NTZC10AD	PC Dongle for One (1) PC and User Guide	NTZC10AF
NTZC10BA	PC Dongles for Five (5) PCs	NTZC10BB
NTZC10BB	PC Dongles for Five (5) PC and User Guides	NTZC10BC
NTZC10BB	PC Dongles for Five (5) PC and User Guides	NTZC10BD
NTZC10BC	PC Dongles for Five (5) PC and User Guides	NTZC10BD
NTZC10BD	PC Dongles for Five (5) PC and User Guides	NTZC10BF
NTZC10CA	PC Dongles for Ten (10) PCs	NTZC10CB
NTZC10CB	PC Dongles for Ten (10) PC and User Guides	NTZC10CC
NTZC10CB	PC Dongles for Ten (10) PC and User Guides	NTZC10CD
NTZC10CC	PC Dongles for Ten (10) PC and User Guides	NTZC10CD
NTZC10CD	PC Dongles for Ten (10) PC and User Guides	NTZC10CF
NTZC10DA	PC Dongles for Fifty (50) PCs	NTZC10DB
NTZC10DB	PC Dongles for Fifty (50) PC and 30 User Guides	NTZC10DC
NTZC10DB	PC Dongles for Fifty (50) PC and 30 User Guides	NTZC10DD
NTZC10DC	PC Dongles for Fifty (50) PC and 30 User Guides	NTZC10DD
NTZC10DD	PC Dongles for Fifty (50) PC and 30 User Guides	NTZC10DF
NTZC10EA	PC Dongle for Two Hundred Fifty (250) PCs	NTZC10EB
NTZC10EB	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	NTZC10EC
NTZC10EB	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	NTZC10ED

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZC10EC	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	NTZC10ED
NTZC10ED	PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides	NTZC10EF
NTZC12AA	Meridian Integrated IP Telephony Gateway Large Systems Package	NTZC12CA
NTZC12BA	Meridian Integrated IP Telephony Gateway Option 11C/11E Package	NTZC12CA
NTZC13AA	Meridian Integrated IP Telephony Gateway (ITG) Card	NTZC13BA
NTZC17AA	Meridian IP Telecommuter Option 11C Package	NTZC65AA
NTZC18AA	Meridian IP Telecommuter Large Systems Package	NTZC65AA
NTZC90BB	Software Installation Kit (Non-Autovon)	NTZC91BA
NTZD06AA	SYMPOSIUM Call Center Server Upgrade to Release 1.1	
NTZD06AD	SYMPOSIUM Call Center Server Upgrade from Release 1.0 to Release 1.5	
NTZD06AE	SYMPOSIUM Call Center Server Upgrade from Release 1.1 to Release 1.5	
NTZD11AA	SYMPOSIUM Call Center Server French Release 1.0 Base Software	
NTZD11AD	SYMPOSIUM Call Center Release 1.5 Base Software	
NTZD52AA	SYMPOSIUM Express Call Center Base System	NTHF23AB
NTZD53AA	SYMPOSIUM Express Call Center, Option 11C Compact System	
NTZD80AA	Voice Activated Business Directory Release 1 to Release 2 Upgrade	
NTZE01AB	CallPilot IPE Base System - English	
NTZE02AB	CallPilot Tower System - English	
NTZE03AB	CallPilot Rack Mount System DC - English	
NTZE04AB	CallPilot Rack Mount System AC - English	
NTZE09AA	CallPilot Disk and 50 Hour Storage Expansion - Tower	
NTZE09BA	CallPilot Disk and 50 Hour Storage Expansion - Rack	
NTZK06AA03	Meridian M2006 Single Line Digital Telephone, Basic, Black	NT2K05GA03
NTZK06AA35	Meridian M2006 Single Line Digital Telephone, Basic, Ash	NT2K05GA35
NTZK06AA93	Meridian M2006 Single Line Digital Telephone, Basic, Gray	NT2K05GA93
NTZK06AB03	Meridian M2006 Single Line Digital Telephone with Data, Black	NTZK06AC03
NTZK06AB35	Meridian M2006 Single Line Digital Telephone with Data, Ash	NTZK06AC35
NTZK06AB93	Meridian M2006 Single Line Digital Telephone with Data, Dolphin Gray	NTZK06AC93
NTZK06AC03	Meridian M2006 Single Line Digital Telephone with MCA Data, Black	NT2K05GT03
NTZK06AC35	Meridian M2006 Single Line Digital Telephone with MCA Data, Ash	NT2K05GT35
NTZK06AC93	Meridian M2006 Single Line Digital Telephone with MCA Data, Gray	NT2K05GT93
NTZK0700	Open IVR 2.5 Upgrade Package	
NTZK08AA03	Meridian M2008 Standard Business Telephone, Basic, Black	NT2K08GA03
NTZK08AA35	Meridian M2008 Standard Business Telephone, Basic, Ash	NT2K08GA35

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK08AA93	Meridian M2008 Standard Business Telephone, Basic, Gray	NT2K08GA93
NTZK08AB03	Meridian M2008 Standard Business Telephone with Data, Black	NTZK08AC03
NTZK08AB35	Meridian M2008 Standard Business Telephone with Data, Ash	NTZK08AC35
NTZK08AB93	Meridian M2008 Standard Business Telephone with Data, Gray	NTZK08AC93
NTZK08AC03	Meridian M2008 Standard Business Telephone with MCA Data, Black	NT2K08GT03
NTZK08AC35	Meridian M2008 Standard Business Telephone with MCA Data, Ash	NT2K08GT35
NTZK08AC93	Meridian M2008 Standard Business Telephone with MCA Data, Gray	NT2K08GT93
NTZK08BA03	Meridian M2008 Standard Business Telephone with Display, Black	NTZK08CA03
NTZK08BA35	Meridian M2008 Standard Business Telephone with Display, Ash	NTZK08CA35
NTZK08BA93	Meridian M2008 Standard Business Telephone with Display, Gray	NTZK08CA93
NTZK08BB03	Meridian M2008 Standard Business Telephone with Display & Data, Black	NTZK08BC03
NTZK08BB35	Meridian M2008 Standard Business Telephone with Display & Data, Ash	NTZK08BC35
NTZK08BB93	Meridian M2008 Standard Business Telephone with Display & Data, Gray	NTZK08BC93
NTZK08BC03	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Black	NTZK08CC03
NTZK08BC35	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Ash	NTZK08CC35
NTZK08BC93	Meridian M2008 Standard Business Telephone w/Display & MCA Data, Gray	NTZK08CC93
NTZK08CA03	Meridian M2008 Standard Business Telephone with Display, Black	NT2K08GH03
NTZK08CA35	Meridian M2008 Standard Business Telephone with Display, Ash	NT2K08GH35
NTZK08CA93	Meridian M2008 Standard Business Telephone with Display, Gray	NT2K08GH93
NTZK08CC03	Meridian M2008 Standard Business Telephone with Display & MCA Data, Black	NT2K08GN03
NTZK08CC35	Meridian M2008 Standard Business Telephone with Display & MCA Data, Ash	NT2K08GN35
NTZK08CC93	Meridian M2008 Standard Business Telephone with Display & MCA Data, Gray	NT2K08GN93
NTZK0900	OIVR 2.x Hardware - Digital Prompt Tool Package	
NTZK1000	MRS North American ISDN PRI Option Package	
NTZK13AA	OIVR 2.x Hardware - Runtime to Development Upgrade AP or MRS/AP (includes Prompt Manager)	
NTZK13BA	OIVR 2.x Hardware - Runtime to Development Upgrade AP or MRS/AP (excludes Prompt Manager)	
NTZK16AA03	Meridian M2616 Performance-Plus Telephone, Basic, Black	NT2K16GA03
NTZK16AA35	Meridian M2616 Performance-Plus Telephone, Basic, Ash	NT2K16GA35
NTZK16AA93	Meridian M2616 Performance-Plus Telephone, Basic, Gray	NT2K16GA93
NTZK16AB03	Meridian M2616 Performance-Plus Telephone with Data, Black	NTZK16AC03
NTZK16AB35	Meridian M2616 Performance-Plus Telephone with Data, Ash	NTZK16AC35
NTZK16AB93	Meridian M2616 Performance-Plus Telephone with Data, Gray	NTZK16AC93
NTZK16AC03	Meridian M2616 Performance-Plus Telephone with MCA Data, Black	NT2K16GT03

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK16AC35	Meridian M2616 Performance-Plus Telephone with MCA Data, Ash	NT2K16GT35
NTZK16AC93	Meridian M2616 Performance-Plus Telephone with MCA Data, Gray	NT2K16GT93
NTZK16BA03	Meridian M2616 Performance-Plus Telephone with Display, Black	NTZK16CA03
NTZK16BA35	Meridian M2616 Performance-Plus Telephone with Display, Ash	NTZK16CA35
NTZK16BA93	Meridian M2616 Performance-Plus Telephone with Display, Gray	NTZK16CA93
NTZK16BB03	Meridian M2616 Performance-Plus Telephone with Display & Data, Black	NTZK16BC03
NTZK16BB35	Meridian M2616 Performance-Plus Telephone with Display & Data, Ash	NTZK16BC35
NTZK16BB93	Meridian M2616 Performance-Plus Telephone with Display & Data, Gray	NTZK16BC93
NTZK16BC03	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Black	NTZK16CC03
NTZK16BC35	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Ash	NTZK16CC35
NTZK16BC93	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Gray	NTZK16CC93
NTZK16CA03	Meridian M2616 Performance-Plus Telephone with Display, Black	NT2K16GH03
NTZK16CA35	Meridian M2616 Performance-Plus Telephone with Display, Ash	NT2K16GH35
NTZK16CA93	Meridian M2616 Performance-Plus Telephone with Display, Gray	NT2K16GH93
NTZK16CC03	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Black	NT2K16GN03
NTZK16CC35	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Ash	NT2K16GN35
NTZK16CC93	Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Gray	NT2K16GN93
NTZK20AA03	Meridian M2016S Secure Telephone, Basic, Black	
NTZK20AA93	Meridian M2016S Secure Telephone, Basic, Gray	
NTZK20AB03	Meridian M2016S Secure Telephone with Data, Black	
NTZK20AB35	Meridian M2016S Secure Telephone with Data, Ash	
NTZK20AB93	Meridian M2016S Secure Telephone with Data, Gray	
NTZK20AC03	Meridian M2016S Secure Telephone with MCA Data, Black	
NTZK20AC35	Meridian M2016S Secure Telephone with MCA Data, Ash	
NTZK20AC93	Meridian M2016S Secure Telephone with MCA Data, Gray	
NTZK20BA03	Meridian M2016S Secure Telephone with Display, Black	
NTZK20BA35	Meridian M2016S Secure Telephone with Display, Ash	
NTZK20BA93	Meridian M2016S Secure Telephone with Display, Gray	
NTZK20BB03	Meridian M2016S Secure Telephone with Display & Data, Black	
NTZK20BB35	Meridian M2016S Secure Telephone with Display & Data, Ash	
NTZK20BB93	Meridian M2016S Secure Telephone with Display & Data, Gray	
NTZK20BC03	Meridian M2016S Secure Telephone with Display & MCA Data, Black	
NTZK20BC35	Meridian M2016S Secure Telephone with Display & MCA Data, Ash	
NTZK20BC93	Meridian M2016S Secure Telephone with Display & MCA Data, Gray	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK22AA03	Meridian M2216 ACD-1 Basic Telephone, Black	NTZK22CA03
NTZK22AA35	Meridian M2216 ACD-1 Basic Telephone, Ash	NTZK22CA35
NTZK22AA93	Meridian M2216 ACD-1 Basic Telephone, Gray	NTZK22CA93
NTZK22AB03	Meridian M2216 ACD-1 Telephone with Data, Black	NTZK22AC03
NTZK22AB35	Meridian M2216 ACD-1 Telephone with Data, Ash	NTZK22AC35
NTZK22AB93	Meridian M2216 ACD-1 Telephone with Data, Gray	NTZK22AC93
NTZK22AC03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	NTZK22CC03
NTZK22AC35	Meridian M2216 ACD-1 Telephone with MCA Data, Ash	NT2K18WM35
NTZK22AC93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	NTZK22CC93
NTZK22CA03	Meridian M2216 ACD-1 Basic Telephone, Black	NT2K18GH03
NTZK22CA35	Meridian M2216 ACD-1 Basic Telephone, Ash	NT2K18GH35
NTZK22CA93	Meridian M2216 ACD-1 Basic Telephone, Gray	NT2K18GH93
NTZK22CC03	Meridian M2216 ACD-1 Telephone with MCA Data, Black	NT2K18GN03
NTZK22CC93	Meridian M2216 ACD-1 Telephone with MCA Data, Gray	NT2K18GN93
NTZK23AA03	Meridian M2216 ACD-2 Telephone, Basic, Black	NTZK23CA03
NTZK23AA35	Meridian M2216 ACD-2 Telephone, Basic, Ash	NTZK23CA35
NTZK23AA93	Meridian M2216 ACD-2 Telephone, Basic, Gray	NTZK23CA93
NTZK23AB03	Meridian M2216 ACD-2 Telephone with Data, Black	NTZK23AC03
NTZK23AB35	Meridian M2216 ACD-2 Telephone with Data, Ash	NTZK23AC35
NTZK23AB93	Meridian M2216 ACD-2 Telephone with Data, Gray	NTZK23AC93
NTZK23AC03	Meridian M2216 ACD-2 Telephone with MCA Data, Black	NTZK23CC03
NTZK23AC35	Meridian M2216 ACD-2 Telephone with MCA Data, Ash	NTZK23CC35
NTZK23AC93	Meridian M2216 ACD-2 Telephone with MCA Data, Gray	NTZK23CC93
NTZK23CA03	Meridian M2216 ACD-2 Telephone, Basic, Black	
NTZK23CA35	Meridian M2216 ACD-2 Telephone, Basic, Ash	
NTZK23CA93	Meridian M2216 ACD-2 Telephone, Basic, Gray	
NTZK23CC03	Meridian M2216 ACD-2 Telephone with MCA Data, Black	
NTZK23CC35	Meridian M2216 ACD-2 Telephone with MCA Data, Ash	
NTZK23CC93	Meridian M2216 ACD-2 Telephone with MCA Data, Gray	
NTZK27AA	Symposium FastView New Software with MCA and Documentation Package 3A (1-19 Units)	
NTZK27BA	Symposium FastView New Software, MCA and Documentation Package 3B (20-49 Units)	
NTZK27CA	Symposium FastView New Software, MCA and Documentation Package 3C (50+ units)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK37AA	MAT 4.x Single Location Distributor Station Administration	NTZK37AD
NTZK37BA	MAT 4.x Multi Location Distribution Station Administration	NTZK37BD
NTZK38AA	MAT 4.x End User Single Site Package	NTZK38AD
NTZK38BA	MAT 4.x End User Multi Site Package	NTZK38BD
NTZK39AA	MAT 4.x Single to Multi Site Expansion	NTZK39AD
NTZK39BA	MAT 4.x Multi Site Expansion	NTZK39BD
NTZK39CA	MAT 4.x Multi Site Expansion Cap	NTZK39CD
NTZK40AA	MAT 4.x Station Administration Module	NTZK40AD
NTZK41AA	MAT 4.x Traffic Analysis Module	NTZK41AD
NTZK42AA	MAT 4.x Call Tracking Module	NTZK42AD
NTZK43AA	MAT 4.x Call Accounting Module Base	NTZK43AD
NTZK44AA	MAT 4.x North American Rate Table	NTZK44AD
NTZK45BA	MAT 4.x Call Accounting Small Expansion	NTZK45BD
NTZK45CA	MAT 4.x Call Accounting Medium Expansion	NTZK45CD
NTZK45DA	MAT 4.x Call Accounting Large Expansion	NTZK45DD
NTZK45EA	MAT 4.x Call Accounting Expansion Cap	NTZK45ED
NTZK45FB	MAT 4.x Call Accounting Mini Expansion	NTZK45FD
NTZK46AA	MAT 4.x Distributor Single Location Station Administration Upgrade	NTZK46AD
NTZK46BA	MAT 4.x Distributor Multi Location Station Administration Upgrade	NTZK46BD
NTZK47AA	MAT 4.x Single Site Common Services Upgrade	NTZK47AD
NTZK47BA	MAT 4.x Multi Site Common Services Upgrade	NTZK47BD
NTZK48AA	MAT 4.x Station Administration Upgrade	NTZK48AD
NTZK49AA	MAT 4.x Traffic Analysis Upgrade	NTZK49AD
NTZK50AA	MAT 4.x Call Tracking Upgrade	NTZK50AD
NTZK51AA	MAT 4.x Call Accounting Base Upgrade	NTZK51AD
NTZK53AA	FastView Software, MCA and Documentation Marketing Package #2A (1 to 19 Units)	
NTZK53BA	FastView Software, MCA and Documentation Marketing Package #2B (20 to 49 Units)	
NTZK53CA	FastView Software, MCA and Documentation Marketing Package #2C (50+ Units)	
NTZK55AA	FastView+ Software, MCA and Documentation Marketing Package #3A (1 to 19 Units)	NTZK27AA
NTZK55BA	FastView+ Software, MCA and Documentation Marketing Package #3B (20 to 49 Units)	NTZK27BA
NTZK55CA	FastView+ Software, MCA and Documentation Marketing Package #3C (50+ Units)	NTZK27CA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK57AA	FastView Software, MCA, M2216 and Documentation Marketing Package #4A (1 to 19 Units)	
NTZK57BA	FastView Software, MCA, M2216 and Documentation Marketing Package #4B (20 to 49 Units)	
NTZK57CA	FastView Software, MCA, M2216 and Documentation Marketing Package #4C (50+ Units)	
NTZK59AA	FastView+ Software, MCA, M2216 and Documentation Marketing Package #5A (1 to 19 Units)	NTZK29AA
NTZK59BA	FastView+ Software, MCA, M2216 and Documentation Marketing Package #5B (20 to 49 Units)	NTZK29BA
NTZK59CA	FastView+ Software, MCA, M2216 and Documentation Marketing Package #5C (50+ Units)	NTZK29CA
NTZK63AA	MAT 5 Distributor Common Services	NTZK63AD
NTZK63AD	MAT 5 Distributor Common Services	
NTZK63CA	MAT 5 End User Common Services	NTZK63CD
NTZK63CD	MAT 5 End User Common Services	
NTZK64AA	MAT 5 Station Administration Module	NTZK64AD
NTZK64AD	MAT 5 Station Administration Module	
NTZK64BA	MAT 5 Traffic Analysis Module	NTZK64BD
NTZK64BD	MAT 5 Traffic Analysis Module	
NTZK64CA	MAT 5 Call Tracking Module	NTZK64CD
NTZK64CD	MAT 5 Call Tracking Module	
NTZK64DA	MAT 5 Call Accounting Module	NTZK64DD
NTZK64DD	MAT 5 Call Accounting Module	
NTZK64EA	MAT 5 ESN Analysis and Reporting Tool Module	NTZK64ED
NTZK64ED	MAT 5 ESN Analysis and Reporting Tool Module	
NTZK64FA	MAT 5 Maintenance Windows Module	NTZK64FD
NTZK64FD	MAT 5 Maintenance Windows Module	
NTZK64GA	MAT 5 Alarm Management Module	NTZK64GD
NTZK64GD	MAT 5 Alarm Management Module	
NTZK65AA	MAT 5 End User Common Services Upgrade	NTZK65AD
NTZK65AB	MAT 5 to 5.x Flat-fee Upgrade	NTZK99AD
NTZK65AD	MAT 5 End User Common Services Upgrade	
NTZK65BA	Distributor M1 Common Services and Station Administration Upgrade	NTZK93AB
NTZK66AA	MAT 5 Station Administration Upgrade	NTZK66AD
NTZK66AD	MAT 5 Station Administration Upgrade	
NTZK66BA	MAT 5 Traffic Analysis Upgrade	NTZK66BD

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZK66BD	MAT 5 Traffic Analysis Upgrade	
NTZK66CA	MAT 5 Call Tracking Upgrade	NTZK66CD
NTZK66CD	MAT 5 Call Tracking Upgrade	
NTZK66DA	MAT 5 Call Accounting Base Upgrade	NTZK66DD
NTZK66DD	MAT 5 Call Accounting Base Upgrade	
NTZK67AA	MAT 5 Maintenance Marketing Bundle	NTZK67AD
NTZK67AD	MAT 5 Maintenance Marketing Bundle	
NTZK67CA	MAT 5 Administration Marketing Bundle	NTZK67CD
NTZK67CD	MAT 5 Administration Marketing Bundle	
NTZK67FA	MAT 5 System Management Marketing Bundle	NTZK67FD
NTZK67FD	MAT 5 System Management Marketing Bundle	
NTZK72AA	PC Dongle for One (1) PC	
NTZK72BA	PC Dongles for Ten (10) PCs	
NTZK72DA	PC Dongles for Fifty (50) PCs	
NTZK72FA	PC Dongle for Two Hundred Fifty (250) PCs	
NTZK73BA	PC Dongles for Five (5) PCs	
NTZK80AA	OIVR 2.x Hardware - Discrete Speech Recognition - North American Vocabularies Package	
NTZK81AA	OIVR 2.x Hardware - Continuous Speech Recognition - North American Vocabularies Package	
NTZK86AA	OIVR 2.x Hardware - Text-To-Text Speech - North American Vocabularies Package	
NTZK8900	OIVR 2.x Hardware - Open IVR System Prompts - North America	
NTZK89BB	OIVR 2.x Hardware - International System Prompts	
NTZK91EB	MAT 5 ESN Analysis and Reporting Upgrade	
NTZK91FB	MAT 5 Maintenance Windows Upgrade	
NTZK91GB	MAT 5 Alarm Management Upgrade	
NTZK93AB	MAT 5 Distributor Single Location Common Services and Station Upgrade	NTZK96AD
NTZK95AD	MAT 5 Diskettes	
NTZK96AD	MAT 5 Distributor Single Location Common Services and Station Upgrade	
NTZK98AA	Audio Interface Unit (AIU)	
NTZK99AD	MAT 5 to 5.x Flat-fee Upgrade	
NTZR10AA	Meridian Mail MP Package (4)	
NTZR11AA	Meridian Mail MP Package (8)	
NTZR12AA	Meridian Mail MP Package (12)	
NTZR13AA	Meridian Mail MP Package (16)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZR15AA	LSPC Cabinet Package	
NTZR16AA	Lanstar Cabinet Package (Half Shelf)	NTZR62AA
NTZR17AA	Lanstar Cabinet Package (Full Shelf)	NTZR62AA
NTZR18AA	Cabinet Assembly (w/o Rectifiers)	
NTZR19AA	-48V DC Rectifier Assembly (QRF8)	
NTZR20AA	Power Supply Package (LANSTAR Cabinet)	
NTZR21AA	48MB Memory Upgrade Kit	NTZR21AB
NTZR21AB	48MB Memory Upgrade Kit	NTZR21AC
NTZR21AC	SIMMS Memory Upgrade Kit	NTZR21AD
NTZR21AD	SIMMS Memory Upgrade Kit	
NTZR22AA	Digital Shelf Assembly	
NTZR23AA	Mass Storage 234 Assembly	
NTZR24AA	DS-1 Synchronous/Asynchronous Interface Assembly	
NTZR25AA	DS-1 Synchronous Interface Assembly	
NTZR26AA	Processor 2M Assembly	
NTZR27AA	Processor 4M Assembly	
NTZR28AA	Processor 6M Assembly	
NTZR29AA	Processor 2MS Assembly	
NTZR30AA	Processor 4MS Assembly	
NTZR31AA	Processor 6MS Assembly	
NTZR32AA	Meridian Mail Spares Kit (2 Meg)	
NTZR33AA	P-Bus Kit Assembly, 2-Pos	
NTZR34AA	P-Bus Kit Assembly, 3-Pos	
NTZR35AA	6M Processor Assembly	
NTZR36AA	6MS Processor Assembly	
NTZR37AA	Meridian Mail MP Package (4)	
NTZR37AB	Meridian Mail Package (12)	
NTZR38AA	Meridian Mail Package (20)	
NTZR39AA	Meridian Mail Package (24)	
NTZR40AA	HP ThinkJet Printer	NTZR40BA
NTZR41AA	Service Printer Package	
NTZR42AA	Meridian Lanstar ASCII Terminal Package	
NTZR43AA	LANLink Assembly	
NTZR44AA	LSPC Hardware Package	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
NTZR50AA	16 to 20 Port Expansion Kit	
NTZR51AA	32 to 36 Port Expansion Kit	
NTZR52AA	Meridian Mail Spares Kit (6 Meg)	
NTZR53AA	24 to 28 Port Expansion Kit	
NTZR54AA	36 to 40 Port Expansion Kit	
NTZR55AA	Meridian Mail Networking Hardware Package	
NTZR56AA	Meridian Mail Package (40)	
NTZR57AA	Meridian Mail Package (28)	
NTZR60BA	LAN 100 Base Hub Package	
NTZR61BA	LAN 100 Hub Expansion Package	
NTZR62AA	LAN 100 4 Stack Cabinet Package	
NTZR62BA	LAN 100 8 Stack Cabinet Package	
NTZR63AA	4 Stack Bus Redundancy Package	
NTZR63BA	8 Stack Bus Redundancy Package	
NY2K22VH03	Meridian Key Expansion Module, Black	NT2K22XH03
NY2K22VH35	Meridian Key Expansion Module, Ash	NT2K22VH35
NY2K22VH93	Meridian Key Expansion Module, Gray	NT2K22VH93
P0286117	Lock Washer	
P0515934	Kit, Wall Mount (Single Basic or Display Set)	
P0523535	Filler Plate	P0784535
P0533539	Button	
P0535603	Dial Mechanism Assembly (QCW1, QCW2, QSU1A-QSU1E)	
P0535652	Card Holder Group (Telephone Directory Number)	A0351485
P0536035	Cover (SL-1 Set)	
P0536494	Right Front Panel Assembly	
P0536495	Left Front Panel Assembly	
P0537535	Base (SL-1 Set)	
P0537735	Cover (Add-On Module)	
P0537835	Base (10/20 Button Module, BLF)	
P0537903	Faceplate - 10 Button Module - Black	
P0537926	Faceplate - 10 Button Module - Brown	
P0538003	Faceplate - 20 Button Module - Black	
P0538026	Faceplate - 20 Button Module - Brown	
P0538869	Back Cover	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0544026	Faceplate - QMT3 - BLF (Brown)	
P0544126	Faceplate - QMT4 - Handset Module (Brown)	
P0544435	Base for QCW Console	
P0544535	Cover (Console) (QCW2/QCW3/QCW4)	
P0546135	Insert	
P0547127	Wall Transformer	
P0547128	Power Transformer, 15 Volt	
P0548753	LED Assembly (Console) Single Strip (Row A, B, C & G)	
P0548754	LED Assembly (Console) Single Strip (Row D & E)	
P0548798	LED Assembly (Console) Single Strip (Row F)	
P0548815	Cable Assembly (QCA28 Cabinet)	
P0548834	Hook Switch Assembly (SL-1 Set)	
P0549791	Designation Tabs (Booklet)	
P0549799	Designation Tabs (QSU1/QSU3/QSU60/QSU61)	A0351485
P0552003	Faceplate - Set - Black	
P0552026	Faceplate - Set - Brown	
P0552414	Filter (QUD1) (CDR)	
P0552519	Bracket	
P0552525	Side Panel Assembly	
P0552526	Top Cover	
P0552532	NTP Rack	
P0552536	Fuse Kit	
P0552944	Front Cover Panel	
P0552945	Side Cover Panel	
P0552946	Junction Side	
P0552947	Angle (Cable Rack Support)	
P0552948	Bracket Support (2 In.)	
P0552949	Junction End	
P0552950	Kit Extension (Basic)	
P0552951	Kit Extension (Front, Rear & Junction)	
P0552952	Kit Extension (Back to Back)	
P0552953	Kit Extension (Junction Corner)	
P0559427	Blue Cable Routing Panel Assembly (Center Mount)	
P0559498	Junction Assembly	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0559499	Junction Assembly	
P0560497	BLF Designation Labels	
P0560527	Bracket Assembly (CDR)	
P0560624	BLF Cord Kit	
P0560630	Chassis Assembly (CDR)	
P0562926	Control Card for J2412AA-1, L1, 2, 3 Control Panel	
P0565036	Cap Clear	A0351485
P0565037	Cap Transparent Red	A0351485
P0566916	Bracket Support (11 In.)	
P0567037	Bezel, Collar (Lamp Strip)	
P0567062	Switch Air Flow Assembly (NT2R02AA)	
P0568118	Ground Window Assembly	
P0569864	Telephone Number Card White	A0351485
P0572335	Dummy Faceplate - Single	
P0572336	Dummy Faceplate - Dual	
P0572395	Power Adapter Cable (RPE)/QBL14	
P0572472	Switch and Connector Assembly	
P0575526	Chassis Unit	
P0575529	Filter Unit Assembly	
P0575531	Filter For P0575526, QUD1, QUD3, QUD9	P0650866
P0575570	Plastic Screws	
P0582251	Panel, Hinged Door	
P0582279	Numeric Display Replacement Kit (QCW2)	
P0584534	Plastic Guard - Converter Input (QBL5)	
P0584535	Plastic Guard - Converter Input (QBL14) (RPE)	
P0584536	Plastic Guard - Converter Input (QBL7)	
P0584537	Plastic Guard - Converter Input (QBL13)	
P0584538	Plastic Guard - Converter Input (QBL10, QBL11)	
P0586306	Faceplate - Black	
P0586308	Faceplate - Brown	
P0586309	Cap Amber	A0351485
P0586312	Cap Package	
P0586340	Cap Package (Basic & Display)	A0351485
P0586395	Designation Tabs	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0587440	Ribbon Cable (0.5 Ft.)	
P0593922	ADM 24V Transformer (QMT7/QMT8)	A0377172
P0593940	ADM Black Faceplate (Bare)	
P0593964	Vol. #1 Engineering	
P0593965	Vol. #2 PE Installation/Maintenance	
P0593966	Vol. #3 Software X11 Rls. 1-3	
P0593967	Special Features NTP	P0746460
P0593967	Special Features NTP	P0746462
P0593967	Special Features NTP	P0746463
P0593967	Special Features NTP	P0746464
P0593967	Special Features NTP	P0746465
P0593968	Vol. #4 System Installation/Maintenance	
P0593969	Vol. #4 System Installation/Maintenance	
P0593970	Vol. #4 System Installation/Maintenance	
P0593971	Vol. #4 System Installation/Maintenance	
P0593972	Vol. #4 System Installation/Maintenance	
P0594493	Hinged Door Kit	
P0594497	Plastic Guard - Cabinet Input (QBL10, QBL11, QBL13)	
P0594498	Plastic Guard - Cabinet Input (QBL3, QBL5, QBL7, QBL8, QBL14)	
P0594499	Plastic Guard - Converter Input (QBL3)	
P0595358	Power Shunt Assembly for J2412A-1 Cabinet	
P0595359	Output Bus Bar Assembly for J2412A-1 Cabinet	
P0596156	Designation Tabs (Console/Autovon Function)	
P0613887	Console Overlay	
P0614658	System 600/48 DC Duct	P0816367
P0618693	Vol. #4 System Installation/Maintenance	
P0622357	ADM Synch Switch Setting Label	
P0627392	ADM Instruction Card	
P0627404	ADM Asynchronous Switch Setting Label	
P0629649	Blue Cable Routing Panel Assembly (Cantilever Mount)	
P0630408	Amplified Handset Kit for SL-1 Set	
P0630513	SL-1 Data User Guide (15/PK)	
P0630519	QMT8 Installation Card (15/PK)	
P0631118	CPU Power Adapter	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0631119	CPU Power Adapter	
P0631120	CPU Power Monitor Adapter	
P0631121	CPU Power Monitor Adapter	
P0632657	Side Panel (Single Bay)-EMI	
P0632685	Side Panel (Double Bay)-EMI	
P0632699	SL-1 Station Demonstrator Manual	
P0632974	Vol. #1 Engineering	
P0632975	Vol. #2 PE Installation/Maintenance	
P0632976	Vol. #3 Software X37 Rls. 1-3	
P0632977	Special Features NTP	P0746460
P0632977	Special Features NTP	P0746462
P0632977	Special Features NTP	P0746463
P0632977	Special Features NTP	P0746464
P0632977	Special Features NTP	P0746465
P0633389	QSY22 Mounting Bracket (RH)	
P0634868	Left Mounting Bracket	P0634871
P0634869	Right Mounting Bracket	P0633389
P0634871	QSY22 Mounting Bracket (LH)	
P0634911	Filter Assembly for QUD15	P0650867
P0635684	Directory Faceplate (QSU71)	P0657842
P0635898	Bulkhead Assembly (EMI)	
P0637212	Cover Plate 50 Pin Connector (EMI)	
P0637213	Cover Plate 25 Pin Connector (EMI)	
P0637214	AIM User Guide (15/PK)	
P0637245	QSY22 Mounting Bracket	
P0637674	Clear Feature Key Caps (1 each, standard for all Meridian Digital Telephones and Attendant Consoles)	P0705801
P0637697	Displayphone Key Cap Kit	
P0637959	Power Extension Cable	
P0639986	Bracket for QPC417	
P0641250	Installation NTP	
P0641251	Installation NTP	P0701308
P0641253	Installation NTP	
P0641254	Installation NTP	P0701310
P0641255	Installation NTP	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0641460	Engineering NTP	P0699387
P0641463	Installation NTP	
P0641464	Maintenance NTP	
P0641465	Maintenance NTP	P0701307
P0641466	Maintenance NTP	P0701309
P0641615	Filler Panel Shelf	
P0641638	Filler Panel Blower	
P0641826	DTI Technical Specification	
P0641829	PC Interface Card User Guide (15/PK)	
P0641838	Lanstar 3270 Protocol Converter Technical Specifications	
P0642526	Bracket Support (11 In.)	
P0642924	Overhead Wireway Flange Fitting	
P0643174	Air Filter	
P0643862	Mounting Bracket Upper SDI Connector	
P0645025	Maintenance NTP	
P0645026	Maintenance NTP	
P0645043	Software X11 Rls 4 to 14 NTP	
P0645044	Software X37 Rls 4 + NTP	
P0645045	Maintenance NTP	
P0645717	Shroud B, Big	
P0645723	QMT11 User Guide (15/PK)	
P0645909	COAX Elimination & Switching System Brochure	
P0646995	Cover AC Panel	
P0647281	Air Filter (NT2R02AA)	
P0649527	Cabinet Level Label - 530	
P0649998	AIM Technical Specification	
P0650296	Designation Tabs (QSU71)	P0704654
P0650855	NTP Rack (Single Bay) (White)	
P0650859	NTP Rack (Double Bay) (White)	P0650860
P0650860	Dual NTP Rack (Double) (Gray)	
P0650866	Filter Assembly for P0575526 (QUD5) QUD1, QUD3, QUD9	
P0650867	Filter Assembly for QUD15, QUD20	
P0650879	CPU Power Adapter	
P0650893	LANSTAR ASIM Technical Specification	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0652721	Information Window	
P0652740	Telephone Number Card - Gray	P0732496
P0652741	Information Card Gray/M2009	P0686745
P0652765	Lens, Line Designation	
P0652766	Card, Line Designation	
P0652971	X37 Data Input Forms Release 6	
P0653302	Shroud B, Small	
P0656064	Push Fastener for 50 Pin Connector Cover Plates	
P0656080	SL-1 Data Product Usage and Connectivity	
P0657710	Key Cap, Green with Clear Window (1 each, Standard for all Meridian)	P0705800
P0657840	Directory Insert	
P0657842	Key Cap Package	
P0657886	Terminal Bracket Assembly	
P0658999	Coax Interface Module User Guide (15/PK)	
P0660406	Field Failure Report Tag (Circuit Card and Shelf Equipment)	
P0660427	Side Panel (Left & Right)	
P0660429	Left Side Panel	
P0660431	Front and Rear Fascia Panel	
P0660432	Side Fascia Panel	
P0660433	Side Fascia Panel	
P0660464	Meridian SL-1 Information Sales Handbook	
P0660478	Back Panel	
P0661194	Blank Faceplate (MSU) QMM38	
P0663365	Front & Rear Fascia Panel (CDR)	
P0663367	Right Side Panel	
P0663392	Support Bracket (11 In. Gray)	
P0663399	Right Door Panel Assembly	
P0663400	Left Door Panel Assembly	
P0663401	Gray Cable Routing Panel Assembly (Center Mount)	
P0663402	Gray Cable Routing Panel Assembly (Cantilever Mount)	
P0663404	CDR Door Panel Assembly	
P0663435	ADM Technical Specifications	
P0665351	Information Card/Ash/M2009	P0686745
P0665588	SL-1 Displayphone - AB07 User Guide Supplement	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0665594	Plug Adapter (QUW9)	
P0667282	Top Cover Louver	
P0667297	SL-1 X11 Feature Document	P0746468
P0667321	Regular Telephone User Guide (15/PK)	P0744262
P0667323	SL-1 Digital Display Telephone User Guide (15/PK)	
P0667325	SL-1 Attendant Console User Guide (15/PK)	
P0667334	Background Terminal User Guide X37 (15/PK)	
P0669418	M3000 Touchphone User Guide	P0744261
P0669419	M2000 Series Telephones User Guide (15/PK)	
P0669420	M2000/3000 Telephone Data Option User Guide (15/PK)	
P0671604	Front and Rear Fascia Panel (Blue)	
P0671605	Side Fascia Panel (Blue)	
P0671606	Side Fascia Panel (Blue)	
P0671607	Front and Read Fascia Panel (CDR) (Blue)	
P0673102	Directory Insert, Gray (QSU71)	
P0673966	SL-1 Digital Set w/Data Option Tech	
P0673998	Voice Messaging Template	
P0674953	Installation NTP	P0699378
P0674954	Maintenance NTP	P0699381
P0674955	Maintenance NTP	
P0674956	Installation NTP	P0699380
P0676050	Fred Hutchinson Application Report	
P0676069	SL-1 CDR Product Sales Guide	
P0676070	ACD Product Sales Guide	
P0676071	Lanstar PC Terminal Emulator Guide	
P0676095	Door Panel (L) (EMI) (Blue)	
P0676096	Door Panel (R) (EMI) (Blue)	
P0676097	CDR Door Panel (EMI)	
P0677283	Control Card for J2412AA-1 Control Panel	
P0677315	Mounting Bracket Assembly for QMM45	
P0677581	Asynchronous Interface Line Unit Brochure	
P0677585	Meridian SL-1S Retrofit Package	
P0677592	Multi Line Telephone User Guide (Trifold) (100/PK)	NT5F51AA
P0677593	Lanstar Compat. Guidelines User Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0677799	Interface Connector Bracket	
P0680121	Mini-Terminal Bus Assembly	
P0682732	Screw	
P0682859	DEC/NT Data Connectivity Brochure	
P0682860	Meridian SL-1 & Hewlett Packard	
P0685498	Installation NTP	P0699382
P0685499	Maintenance NTP	P0699383
P0686288	Base Extension	
P0686289	Spacer, Extension (Left)	
P0686290	Spacer, Extension (Right)	
P0686478	Literature Pack (M2018)	
P0686669	EMI Shield	
P0686745	Literature Pack/M2000	
P0686747	Literature Pack (M2112)	
P0686986	SL-1ST Product Sales Guide	
P0686988	SL-1ST Setting a New Standard	
P0687154	M2317 Telephone User Guide (15/PK)	P0744260
P0687341	Lanstar PC Product Sales Guide	
P0687431	Filler Plate	
P0687491	Cloth, Cleaning, Anti-Static	
P0687641	SL-1ST Slide Presentation	
P0687643	Lanstar Data Service Reference Guide/Directions	
P0687644	Lanstar Data Ser. Reference Guide/Directory	
P0688051	ACD 35MM Slide Updates	
P0688053	ACD Quick Reference Guide	
P0688122	ACD Management Reports	
P0688445	Fan Kit Assembly	
P0688542	Users Guide - BNS/DTS/VINES (DA204-01)	
P0688544	Administrators Guide - BNS/DTS/VINES (DA207-01)	
P0688545	Supplement to Administrators Guide (DA206-01)	
P0688546	Server Operations Guide (DA205-03)	
P0688547	Network Installation Guide - Banyan/BNS (DA120)	
P0688548	Network Installation Guide - Banyan/DTS (DA121)	
P0688549	Network Installation Guide - VINES/286 (DA203)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0688550	Banyan Field Service Manual for BNS (DA140)	
P0688551	VINES Programmers Interface (DOS) (DA141)	
P0688552	VINES Architecture Definition (DA142)	
P0688553	Banyan Application Directory (DA150)	
P0688554	Banyan Network Card Configuration	
P0688555	Serial Communications Option Installation (DA180)	
P0688556	3270/BSC Option Guide (DA182-01)	
P0688557	X.25 Option Guide (DA184-03)	
P0688558	Uninterruptible Power Supply Option Installation Documentation (DA185)	
P0688559	BANYAN Option Installation Documentation for NT LANSTAR PC Network	
P0689117	LAN MSNET	
P0689118	NTP PTE LANSTAR Reference Manual	
P0689184	Lan NDP and Installation Guide	
P0689435	SL-ST Article Reprints	
P0689682	Lanstar Appletalk User Guide 2.0	
P0689706	ACD Agents Telephone User Guide (15/PK)	P0744258
P0689707	ACD Supervisors Telephone User Guide (15/PK)	P0744259
P0689753	ACD Package C Supervisors User Guide	P0738417
P0689837	ACD Overview Folder	
P0689838	ACD Package A & B	
P0689839	ACD Package C	
P0689840	ACD Package D	
P0689841	Meridian M2317 Digital Telephone Brochure	
P0689842	Meridian Customer Defined NET	
P0690094	ACD Portfolio Package	
P0690095	Architecture and Evolution Script/Slide X11 R9 ST	
P0693020	Lan Reference Manual - Small Cabinet	
P0693364	ISDN Primary Rate Access Brochure	
P0693365	Meridian Mail SP Reference Manual	
P0693926	Background Terminal User Guide	P0735211
P0693951	ACD Customer Slide Presentation Revision 2	
P0694319	Meridian Electronic Voice Mail Brochure	
P0694608	Voice Service Slide Updates	
P0694609	Voice Service Slide Presen Rev 1	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0694611	Meridian Mail Product Sales Guide Update	
P0694612	Meridian Mail Product Sales Guide Revision 1	
P0694621	Feature Key Label Sheets, ACD	P0732496
P0694682	Engineering Handbook Issue II	
P0694714	Meridian Voice Messaging User Guide - Release 3	
P0694715	Voice Messaging Pocket Guide	
P0694841	Installation Guide	
P0694842	User Guide	
P0695120	LANSTAR Appletalk Bridge (User Guide Included)	
P0695166	CSL Cable	
P0695170	SCSI Tape Cable	
P0695624	Tape Assembly	NT4R28AB
P0695826	155MB Hard Disk	
P0695827	300MB Hard Disk Assembly	
P0696010	"The Value to Strategic Alliances"	
P0696493	DTS/100/200 Hardware Maintenance Manual (DA151)	
P0696494	20-Line Serial Communications Option Installation (DA190)	
P0696591	Meridian SL-1 Overview Brochure	
P0696592	Meridian SL-1 RT Brochure	
P0696752	Meridian SL-RT 35MM Update to ST Customer Presentation	
P0697180	Meridian SL1-ST Sales Feature Sheet	
P0697181	Meridian SL1-RT Sales Feature Sheet	
P0697182	Meridian SL1-NT Sales Feature Sheet	
P0697183	Meridian SL1-XT Sales Feature Sheet	
P0697194	Installation NTP	P0699384
P0697195	Maintenance NTP	P0699385
P0697290	Meridian M3000 Set Sales Flyers	
P0697291	Meridian Attendant Console Sales Feature Sheet	
P0697292	Meridian Set Overview Brochure	
P0697487	ACD MAX Brochure	
P0697511	Meridian Mail Option SFS	
P0697664	ACD MAX 2.0 Supervisors User Guide	
P0697880	Meridian Mail Options Reference Manual	
P0698119	Cooling Unit Cover for QUD9	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0698280	Architect & Evolution Update Release II	
P0698887	Meridian SL-1 System 35MM Upgrade Presentation	
P0698888	Value Added Services & Feature Sales Feature Sheet	
P0698958	ISDN AP Brochure	
P0698959	ISDN Signaling Link Sales Feature Sheet	
P0698960	Meridian Bandwidth Controller Brochure	
P0699029	Quality Assurance Overview	
P0699120	Meridian Mail Slide Updates to Revision 1, Release 4	
P0699121	Data Service Slide Presentation	
P0699122	Updates to Engineering Handbook Issue 2	
P0699345	Digital Tel 35mm Customer Presentation and Script	
P0699384	Meridian SL-1 RT Installation and Acceptance	
P0699385	Meridian SL-1 RT Maintenance	
P0699386	Software X11 Release 4 to 14 - Compact Size	P0748300
P0699388	Special Features - Compact Size	P0746460
P0699388	Special Features - Compact Size	P0746462
P0699388	Special Features - Compact Size	P0746463
P0699388	Special Features - Compact Size	P0746464
P0699388	Special Features - Compact Size	P0746465
P0699724	Module Side Cover	NTND21AA
P0699766	Dual Compact NTP Storage Sleeve	
P0699884	SL-1 Quick Reference Guide 2	
P0700257	Meridian LANSTAR NetWare Installation Supplement	
P0700258	LANSTAR NetWare Driver	
P0700340	Meridian Mail Option NT/XT SFS	
P0700341	Meridian Mail SP SFS	
P0700342	Meridian Mail MP SFS	
P0700724	Power Harness, Main	
P0700725	Power Harness, Fan (Short)	
P0700726	Power Harness, Fan	
P0700727	Power Harness, Shelf (Short)	
P0700728	Power Harness, Shelf	
P0700816	Cable TC to SDI Link (HSL and Configuration Control Link) (RJ-11 to DB25)	
P0700817	Cable TC to Printer (RJ-11 to DB25)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0700818	Cable TC to Terminal (RJ-11 to DB25)	
P0701306	Meridian SL-1 N Installation and Acceptance	
P0701307	Meridian SL-1 N Maintenance	
P0701308	Meridian SL-1 XN Installation and Acceptance	
P0701309	Meridian SL-1 XN Maintenance	
P0701310	Meridian SL-1 MS Installation and Acceptance	
P0701311	Meridian SL-1 MS Maintenance	
P0701381	Meridian Mail MP.4 Install/Software Configuration	
P0701382	Meridian Mail MP.4 Hardware Configuration	
P0701383	Meridian Mail MP.4 Seer Manual	
P0701446	SL-1 Quick Reference Guides 1	
P0701633	Meridian Mail MP.4 Voice Messaging User Guide (15/PK)	
P0701634	Meridian S-1 Evergreen 35MM Presentation/Script	
P0701681	Meridian Mail MP.4 Voice Messaging Pocket Guide (100/PK)	
P0701875	Software X37 Release 4+ NTP	
P0702043	ACD MAX Slide Presentation	
P0702044	Systems in Action Upgrade Flyers	
P0702280	Meridian Mail MP.4 Voice Messaging User Guide	
P0702281	Meridian Mail Voice Messaging Pocket Guide Release 4	
P0702282	Meridian Mail SP and SL-1 Option Reference Manual	
P0702321	NT "Lines of Power" V.H.S. Tape	
P0702574	AdminPlus Administration Guide	
P0702575	AdminPlus PC Software and NTP (Rel. 4)	P0739522
P0702577	Meridian Mail Option Software ACCESS Development Software	
P0702688	Meridian Mail MP ACCESS Software	
P0702689	Meridian Mail PC Software	
P0702942	Lanstar Slide Presentation	
P0703066	ACD MAX Product Sales Guide	
P0703300	ACD MAX Management Reports	
P0703612	Busy Lamp Field Console Graphics User Guide	
P0703633	Meridian M2250 Attendant Console User Guide	
P0703678	Literature Pack	NT2K80AB
P0703680	Literature Pack	NT2K80AA
P0703846	Connector Housing Package (Part of P0704511)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0703991	Meridian Modular Telephone User Guide	P0738418
P0704071	System Overview 35mm Presentation	
P0704094	Meridian Modular Telephone Quick Reference Card (100/PK)	P0722007
P0704096	Meridian Display Module Quick Reference Card (100/PK)	
P0704282	Meridian Manager Brochure	
P0704283	Meridian Manager Demo Disk	
P0704284	Meridian ACD at Mary Kay Cosmetics Video	
P0704285	Meridian Manager Slide Presentation	
P0704407	Meridian SL-1 System Upgrade 35MM Presentation	
P0704514	Meridian SL-1 Data Services Application-Conn Guide	
P0704654	Feature Key Label Sheets (Standard)	P0732496
P0704746	ACD MAX Release 2.0 35MM Presentation	
P0704747	M2216 ACD Telephone User Guide (15/PK)	P0744257
P0704832	Cable TC to Supervisor PC (Return to Console Link) (RJ-11 to DB9)	
P0705038	Upgrade to P0705039	
P0705039	Station Data (STADATA) Base Automatic System	
P0705046	X11 System Message & Option Settings (Release 16)	
P0705052	Literature Pack	
P0705081	Meridian Mail Voice Processing Solutions	
P0705510	Hold Key Caps	
P0705511	Program Key Caps	
P0705512	Handsfree/Mute Key Caps	A0397391
P0705513	Release Key Caps	A0397705
P0705622	ACD MAX Sales Flyer	
P0705623	ACD Sales Guide Updates	
P0705679	Conversion Plate (50 to 36 Pos) Cantilever	
P0705952	M2216 ACD Telephone Quick Reference Card (100/PK)	P0744256
P0705986	Programmable Data Adapter User Guide	P0744323
P0705987	Programmable Data Adapter User Guide	
P0705992	Meridian Manager	SW1020A
P0705993	Meridian Manager	SW1021A
P0705994	Meridian Manager	SW1022A
P0705995	Meridian Manager	SW1026A
P0705996	Meridian Manager	SW1027A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0705997	Meridian Manager	SW1028A
P0705998	Meridian Manager	SW1023A
P0705999	Meridian Manager	SW1024A
P0706000	Meridian Manager	SW1025A
P0706431	Meridian Mail Voice Messaging User Guide (can be used with Release 4,5	P0715983
P0706646	ACD MAX 3.0 Supervisor Guide	
P0706875	BLF/Console Graphics User Guide	P0736062
P0706926	ACD MAX Demo Disk and Cassette	
P0707305	Meridian Mail Options NTP Release 5	
P0707306	Meridian Mail "GP" Reference Manual	
P0707698	Station Administration Documentation (Version 1)	
P0707699	Work Order Systems Documentation (Version 1)	
P0708732	Conversion Plate (50 to 36 Pos) Center	
P0709566	Designation Tabs (M2000 Series)	
P0710203	Meridian Networking Feature Document	
P0710364	Meridian Mail Modular Options Reference Manual Release 5	
P0710422	Meridian 1 Lanstar Brochure	
P0710530	Installation and Maintenance NTP	P0748297
P0710531	Planning and Engineering NTP	P0748299
P0710532	Software X11 Release 1-16 NTP	P0748300
P0710533	Input/Output Guide X11 Release 1-16 NTP	P0746460
P0710534	Special Features NTP	P0746460
P0710534	Special Features NTP	P0746462
P0710534	Special Features NTP	P0746463
P0710534	Special Features NTP	P0746464
P0710534	Special Features NTP	P0746465
P0710535	ACD NTPs (Includes all ACD Packages)	P0746466
P0710536	Meridian Link General Guide	
P0710927	AdminPlus PC Software and NTP (Rel. 5/6)	P0739522
P0710928	Adminplus Administration Guide Release 5 (Document Only)	
P0712139	Meridian 1 Quick Reference Guide Updates	
P0712140	LANSTAR MAC SCSI Flyer	
P0712141	LANSTAR 1000 Sales Flyer	
P0712142	LANSTAR Interface Card Flyer	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0712143	LANSTAR Presentation Folder	
P0712203	Slide Ramp Set	P0738686
P0712690	Drill Fixture	
P0712942	LANSTAR Slide Presentation	
P0713311	NTP Binder (Compact)	
P0713319	Meridian Attendant Message Center Demo Disk	
P0713323	ACD Package D Management Reports	
P0713826	Meridian Mail Options (Networking) Reference Manual Release 6	
P0714208	ACD MAX Release 3.0 NTPs	
P0714359	Meridian Mail Modular Options Reference Manual Release 6	
P0714360	Meridian Mail Modular Option with Guest Voice Messaging Reference Manual	
P0714686	CPLUS Release 2 User Guide	
P0714687	CPLUS Release 2 Installation Guide	
P0714791	Station Administration 1.3 Demonstrator	
P0714793	LANSTAR Application Brief	
P0714848	Traffic Reporting 1.5 Demonstrator	
P0714849	Work Order System 2.3 Demonstrator	
P0714863	Reference Manual for NT6D82 Power System	
P0714864	Reference Manual for 100A Rectifier (A0354954)	
P0715045	X11 Input/Output Reference Guide	P0748304
P0715046	X11 System Messages & Option Settings	P0748304
P0715058	Universal I/O Panel	P0745716
P0715980	Meridian Mail "GP" Reference Manual Release 7	P0741295
P0715981	Meridian Mail Modular Option Reference Manual Release 7	P0739519
P0715982	Meridian Mail Options Reference Manual	P0739518
P0715983	Meridian Mail Voice Messaging User Guide Release 7	P0741311
P0722007	Meridian Modular Telephone Quick Reference Card (100/PK)	NT5F51AA
P0722008	Meridian Modular telephone user guide	NT5F50AA
P0722420	NTP 553-2201-156 XN/XT Network Module Expansion	P0800555
P0722421	X11 Release 18 Non-Option 81 to Release 19 Option 61C Update Package	
P0722422	Condensed maintenance programs	P0800559
P0722423	Condensed administration programs and features implementation	P0800600
P0722848	Designation Strip, Option 21E	
P0724138	M1250/M2250 Attendant Console User Guide	P0800563

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0724352	Network Administration Center Release 2 Supervisors User Guide	NT1R33AA
P0724947	Customer Controlled Routing Release 3B/Link Release 4B Engineering Guide	P0854560
P0725913	Liberation In-Line Amplifier with Mute (M2250, M1250, M2216ACD-2)	
P0725917	Filler Plate for Fiber Controller	P0803870
P0726365	NT6D82 Power System NTP	P0744208
P0727748	Installation Reference Guide	
P0727750	Installation and Maintenance Guide	
P0727752	System Administration Guide	
P0727753	User Reference Card	
P0727766	CPLUS Document Binder	
P0727984	CPLUS LAN Key Installation Guide	P0865361
P0728236	CPLUS Performer User Guide	P0865359
P0728237	CPLUS Performer Installation Guide	P0865360
P0728241	CPLUS Release 3 User Guide	P0865356
P0728242	CPLUS Release 3 Installation Guide	P0865358
P0728489	M1250/M2250 Attendant Console Guide	P0735210
P0728490	Automatic Wake-Up Calls Quick Reference Card (25/PK)	
P0729330	Read Me First Card	
P0729332	Installation Guide	
P0729334	Administration Guide	
P0729336	Fault Clearing Guide	
P0729338	Option 11 Technical Reference Guide	
P0729362	ACD Agent Single Line Telephone Quick Reference Card (25/PK)	P0744255
P0729367	Customer Controlled Routing Users Guide	A0397852
P0729617	Dialing on the Desktop Video	
P0729840	Spare Circuit Breaker Kit, 1 Amp	
P0729844	Spare Circuit Breaker Kit, 10 Amp	
P0729845	Circuit Breaker, 15 Amp	
P0730065	Lug Kit, Crimp-Type #8	
P0730076	M1250/M2250 Attendant Console Quick Reference Card	P0735539
P0730128	Meridian MAX Release 3 NTPs	
P0730351	Central Answering Position Guide (10/PK)	P0745758
P0730610	X11 Software Guide	
P0731580	AdminPlus Administration Guide, Release 7	P0739523

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0731603	AdminPlus PC Software and NTP (Release 7)	P0739522
P0731760	Option 11 Sales Call Sheet (50/PK)	
P0731761	Option 11 Sales Call Sheet Fax Form (50/PK)	
P0732148	ACD MAX Release 4 User Documentation	
P0732177	System Option 21, 51, 61, 71 Installation and Maintenance Guide	P0744217
P0734022	Network Administration Center Supervisors User Guide	
P0734851	X11 Release 16 to Release 17 NTP Update Package	
P0734852	System Option 21, 51, 61, 71 Installation & Maintenance Guide	P0744195
P0734853	System Option 21, 51, 61, 71 Planning and Engineering Guide	P0744197
P0734854	Generic X11 Software Guide	P0744198
P0734855	Generic X11 Input/Output Guide	P0744200
P0734856	Generic X11 Special Features Guide	P0744199
P0734856	Generic X11 Special Features Guide	P0744201
P0734856	Generic X11 Special Features Guide	P0744202
P0734856	Generic X11 Special Features Guide	P0744203
P0734856	Generic X11 Special Features Guide	P0744204
P0734857	ACD Reference Guide	P0744205
P0735209	ACD-C Supervisor User Guide	P0738417
P0735210	M1250/M2250 Attendant Console User Guide (5/PK)	P0724138
P0735300	1.544 Mbit DTI/PRI Administration & Maintenance Guide	P0741131
P0735303	X11 Software Guide	P0740751
P0735304	Read Me First Card (10/PK)	P0741130
P0735305	Installation Guide	P0741129
P0735306	Administration Guide	P0741128
P0735307	Fault Clearing Guide	P0741126
P0735309	Option 11 Technical Reference Guide	P0741127
P0735394	NTP 553-3001-570 Power Monitor/CE Auxiliary Shelves	P0744206
P0735904	X11 Feature Document (Release 17)	P0746468
P0735905	X11 Input/Output Reference Guide	P0748304
P0735906	X11 System Messages & Option Settings	P0748304
P0736063	M3000 Touchphone User Guide	P0744261
P0736064	Meridian MAX Installation and Maintenance Student Guide (for Single (SEE) and Dual (DEE) Module Systems Only)	
P0736220	Blank Diskette Label	
P0737036	X11 Data Input Forms (Release 17)	P0738425

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0738399	System Installation and Maintenance Guide NTP	P0748297
P0738400	Upgrade Engineering & Installation Guide NTP	P0748298
P0738401	System Planning and Engineering Guide NTP	P0748299
P0738402	X11 Software Guide NTP (Release 1-18)	P0748300
P0738403	X11 Input/Output Guide NTP (Release 1-18)	P0748301
P0738404	X11 Data Features Guide NTP	P0746462
P0738405	X11 Hospitality Features Guide NTP	P0746463
P0738406	X11 Networking Features Guide NTP	P0746464
P0738407	Automatic Call Distribution Reference Guide NTP	P0746466
P0738409	ISDN Basic Rate Interface Guide NTP	P0746465
P0738410	Condensed X11 system messages	P0748304
P0738411	Condensed X11 maintenance programs	P0742048
P0738412	Condensed X11 administration programs and feature implementation	P0742737
P0738413	System Option 21, 51, 61, 71 Installation and Maintenance Guide	P0748304
P0738414	X11 feature document	P0744212
P0738418	Meridian Modular telephone user guide	P0722008
P0738420	Meridian Communications adapter user guide (15/PK)	P0744323
P0738421	Meridian Communications adapter quick reference card (25/PK)	P0744329
P0738422	NTP 553-2901-110 ISDN/AP	P0744209
P0738423	NTP 553-3001-110 NT6D82 Power System	P0744208
P0738424	NTP 553-2001-320 Software conversion	P0748303
P0738425	X11 Data input forms (Release 19)	P0744268
P0738426	X11 Release 17 to Release 18 NTP Update Package	P0742129
P0738599	Power Supply Board Cable	P0723443
P0738690	Condensed Switch Settings Card and Product Compatibility	P0744218
P0738832	NTP 553-2201-156 XN/XT Network Module Expansion	P0722420
P0739522	AdminPlus PC Software and NTP (Release 8)	SW7044
P0739522	AdminPlus PC Software and NTP (Release 8)	SW7045
P0739523	AdminPlus Administration Guide, Release 8	P0819082
P0739690	Customer Configuration Backup and Restore Guide	P0800413
P0739719	Meridian 2000 Series Digital Telephones Brochure	
P0739722	Liberation Headset Flyer	
P0739723	CPLUS Flyer	
P0739730	Meridian M2317 Intelligent Telephone Flyer	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0739849	AdminPlus Brochure	
P0740245	M5000TD-1 Release 2 User Guide	P0744293
P0740385	Meridian Mail HVS Collateral, European French	
P0740401	Meridian Mail HVS Collateral, American Spanish	
P0740426	M3000 Touchphone User Guide (15/PK)	P0744261
P0740751	X11 Software Guide	P0723522
P0740839	M5317TDX TSDN BRI Telephone Flyer	
P0740884	STADATA Station Automation System User Guide	
P0741126	Fault Clearing Guide	P0743369
P0741127	Option 11 Technical Reference Guide	
P0741128	Administration Guide	P0743368
P0741129	Installation Guide	P0743367
P0741130	Read Me First Card (10/PK)	
P0741131	1.544 Mbit DTI/PRI Administration & Maintenance Guide	P0800441
P0741522	AdminPlus PC Software and NTP, Release 8	P0739522
P0741670	MPP600 Power System NTP	P0815188
P0741768	Motorola UNIX R3V7 Manuals	
P0741769	Network Services Extension Manuals	
P0741770	Graphical Services Extension Manuals	
P0741771	X Windows/Motif Manuals	
P0742037	System installation and maintenance guide NTP	P0744195
P0742038	Upgrade Engineering and Installation Guide NTP	P0744196
P0742039	System planning and engineering guide NTP	P0744197
P0742040	X11 software features guide NTP	P0744198
P0742041	X11 input/output guide NTP (Release 1-18)	P0744200
P0742042	X11 data features guide NTP	P0744201
P0742043	X11 hospitality features guide NTP	P0744202
P0742044	X11 networking features guide NTP	P0744203
P0742045	ACD Reference Guide NTP	P0744205
P0742046	ISDN Basic Rate Interface Guide NTP	P0744204
P0742047	Condensed X11 system messages	P0744213
P0742048	Condensed X11 maintenance programs	P0744214
P0742049	Condensed system installation and maintenance	P0744217
P0742050	Condensed switch settings, card and product compatibility	P0744218

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0742051	NTP 553-2001-320 Software conversion	P0744211
P0742128	Release 18 (non-Option 81) to Release 18 (with Option 81) NTP Upgrade Package	
P0742129	Release 17 to Release 18 (with Option 18) NTP Update Package	
P0742471	Alarm Cable Kit System 600/48 to MPP600	
P0742473	Control Cable Kit System 600/48 to MPP600	
P0742631	Meridian Networking Feature Document	P0803833
P0742737	Condensed X11 administration programs and features implementation	P0744215
P0742870	Meridian Mail Release 8 Engineering Handbook	
P0743619	Meridian Mail HVS Collateral, Brazilian Portuguese	
P0743664	MAX Release 5 Supervisor User Guide	
P0743683	Meridian MAX Installation Upgrade Guide for Meridian MAX 3.4 and 4.6 systems (to Release 5)	
P0743687	Meridian MAX Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 5)	
P0743899	Alarm Cable System 600/48 to QCA13	
P0744195	System installation and maintenance guide NTP	P0746456
P0744196	System and software update guide NTP	P0746457
P0744197	System planning and engineering guide NTP	P0746458
P0744198	X11 software features guide NTP	P0746459
P0744199	X11 system management guide NTP	P0746460
P0744200	X11 input/output guide NTP	P0746461
P0744201	X11 data features NTP	P0746462
P0744202	X11 hospitality features NTP	P0746463
P0744203	X11 networking features NTP	P0746464
P0744204	ISDN Basic Rate Interface NTP	P0746465
P0744205	ACD Reference Guide NTP	P0746466
P0744206	NTP 553-3001-570 Power Monitor/CE Auxiliary Shelves	P0800553
P0744208	NTP 553-3001-110 NT6D82 Power System	P0800554
P0744209	NTP 553-2901-110 Meridian Link ISDN/AP	
P0744210	NTP 553-2201-156 XN/XT Network Module Expansion	P0722420
P0744211	NTP 553-2001-320 Software conversion	P0746467
P0744212	X11 feature document	P0746468
P0744213	Condensed X11 system messages	P0746469
P0744214	Condensed X11 maintenance programs	P0746470
P0744215	Condensed X11 administration programs and features implementation	P0746471

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0744216	Condensed X11 system management overview, applications and security	P0746472
P0744217	Condensed system installation and maintenance	P0748305
P0744218	Condensed switch settings, card and product compatibility	P0748306
P0744219	X11 Release 18 Option 81 to Release 19 Upgrade Package	
P0744256	M2216 Quick Reference Card (100/PK)	
P0744257	M2216 User Guide (15/PK)	NT5F55AA
P0744258	ACD Agent Telephone User Guide (15/PK)	
P0744259	ACD Supervisor Telephone User Guide (15/PK)	P0813948
P0744260	M2317 Telephone User Guide (15/PK)	P0800567
P0744261	M3000 Touchphone User Guide (15/PK)	P0800569
P0744262	Regular Telephone User Guide (15/PK)	P0800601
P0744268	X11 Data Input Forms (Release 19)	
P0744323	Meridian Communications adapter user guide (15/PK)	A0642533
P0744329	Meridian Communications adapter quick reference card (25/PK)	
P0744808	Conduit Kit - MPP600	
P0746456	System installation and maintenance guide NTP	P0748297
P0746457	System and software update guide NTP	P0748298
P0746458	System planning and engineering guide NTP	P0748299
P0746459	X11 software features guide NTP	P0748300
P0746460	X11 system management, overview, applications and security guide NTP	P0800519
P0746461	X11 input/output guide NTP	P0748301
P0746462	X11 data features NTP	P0800521
P0746463	X11 hospitality features NTP	P0800522
P0746464	X11 networking features NTP	P0800523
P0746465	ISDN Basic Rate Interface NTP	P0800524
P0746466	ACD Reference Guide NTP	P0800525
P0746467	NTP 553-2001-320 Software conversion	P0748303
P0746468	X11 feature document	P0800557
P0746469	Condensed X11 system messages	P0748304
P0746470	Condensed X11 maintenance programs	P0722422
P0746471	Condensed X11 administration programs and features implementation	P0722423
P0746472	Condensed X11 system management overview, applications and security	P0800560
P0746475	X11 Release 19 to Release 19 NANP Update Package	
P0747013	Customer Controlled Routing Release 3 Advanced Maintenance Guide	P0724945

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0747014	Customer Controlled Routing Release 3 Engineering Guide	P0724947
P0747107	Library Navigator NTP	P0748302
P0748297	System installation and maintenance guide NTP	P0800514
P0748298	System and software upgrade guide NTP	P0800515
P0748299	System planning and engineering guide NTP	P0800516
P0748300	X11 software features guide NTP	P0800518
P0748301	X11 input/output guide NTP	P0800520
P0748302	Library Navigator NTP	P0800513
P0748303	NTP 553-2001-320 Software conversion	P0800556
P0748304	Condensed X11 system messages	P0800558
P0748305	Condensed system installation and maintenance	P0800561
P0748306	Condensed switch settings, card and product compatibility	P0800562
P0748307	X11 Release 19 NANP to Release 19 Option 61C Update Package	
P0751003	Tilt Base	
P0778303	Top Cover Filler Plate - Black	P0784503
P0778335	Top Cover Filler Plate - Ash	P0784535
P0778393	Top Cover Filler Plate - Gray	P0784593
P0784403	Blank Brandline Insert, Black	NTZR50AA03
P0784435	Blank Brandline Insert, Ash	NTZR50AA35
P0784493	Blank Brandline Insert, Gray	NTZR50AA93
P0800399	Option 11E - Technical Reference Guide (Coil)	P0809279
P0800406	Option 11E - Read Me First Handbook (Coil)	P0809264
P0800410	Option 11E - Installation Guide (Coil)	P0809265
P0800412	Option 11E - CAP/Central Answering Position (Coil)	P0809259
P0800413	Option 11E - Customer Reconfiguration Backup & Restore (Coil)	P0809260
P0800416	Option 11E - Upgrade Procedures (Coil)	
P0800441	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Coil)	P0809274
P0800442	Option 11E - ISDN BRI Administration & Maintenance (Coil)	P0809276
P0800444	Option 11E - Fault Clearing Guide (Coil)	P0809261
P0800513	Library Navigator	P0813952
P0800514	System installation and maintenance guide	P0813966
P0800515	System and software upgrade guide	P0813967
P0800516	System planning and engineering guide	P0813968
P0800517	Remote Peripheral Equipment Guide	P0813969

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0800518	X11 software features guide	P0813953
P0800519	X11 system management, overview, applications and security guide	P0813954
P0800520	X11 input/output guide	P0813955
P0800521	X11 data features	P0820905
P0800522	X11 hospitality features	P0820906
P0800523	X11 Networking features	P0813956
P0800524	ISDN Basic Rate Interface	P0813957
P0800525	ACD Reference Guide	P0813958
P0800554	NT6D82 Power System	P0912857
P0800555	NTP 553-2201-156 XN/XT Network Module Expansion	P0813970
P0800556	NTP 553-2001-320 Software conversion	P0813959
P0800557	X11 feature document	P0813960
P0800558	Condensed X11 system messages	P0813961
P0800559	Condensed maintenance programs	P0813962
P0800560	Condensed X11 system management overview, applications and security	P0813963
P0800561	Condensed system installation and maintenance	P0813971
P0800562	Condensed switch settings, card and product compatibility	P0813972
P0800563	M1250/M2250 Attendant Console User Guide (1/PK)	P0813951
P0800565	Meridian Modular Telephone User Guide	
P0800569	M3000 Touchphone User Guide	
P0800571	X11 Release 19 with Option 61C to Release 20 Update Package	
P0800600	Condensed administration programs and features implementation	P0813964
P0800601	Regular Telephone User Guide	P0813950
P0802279	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Binder)	P0809280
P0802282	Option 11E - ISDN BRI Administration & Maintenance (Binder)	P0809282
P0802290	Option 11E - Technical Reference Guide (Binder)	P0809285
P0802672	Option 11E - X11 Software Guide (Coil)	P0809287
P0803833	Meridian Networking Feature Document	P0832159
P0805675	VISIT Messenger Demo Disk-PC	
P0805676	VISIT Messenger Demo Disk-MAC	
P0805693	Meridian MAX Demo Disk	P0891205
P0809259	Option 11E - CAP/Central Answering Position (Coil)	
P0809260	Option 11E - Customer Reconfiguration Backup & Restore (Coil)	P0821281
P0809261	Option 11E - Fault Clearing Guide (Coil)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0809263	Option 11E - Upgrade Procedures (Coil)	P0821280
P0809264	General Information and Planning Handbook (Coil)	P0821279
P0809265	Option 11E - Installation Guide (Coil)	P0821268
P0809274	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Coil)	P0821273
P0809276	Option 11E - BRI Administration & Maintenance (Coil)	P0821459
P0809279	Option 11E - Technical Reference Guide (Coil)	P0837650
P0809280	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Binder)	P0821274
P0809282	Option 11E - ISDN BRI Administration & Maintenance (Binder)	P0821458
P0809285	Option 11E - Technical Reference Guide (Binder)	P0837647
P0809287	Option 11E - X11 Software Guide (Coil)	P0821277
P0809479	Line-Side T1 Interface NTP (Standalone)	P0815404
P0811110	NT6D66 CP Card Field Memory Upgrade	P0842837
P0813732	Release 21 Data Input Forms	P0875113
P0813821	Open IVR 2.5 Audio Interface Unit Guide	
P0813947	Release 21 Update package	A0643619
P0813951	Attendant Console User Guide (1/PK)	P0834426
P0813952	Library Navigator	P0820897
P0813953	X11 software features guide	P0813953
P0813953	X11 software features guide	P0820902
P0813954	X11 system management, overview, applications and security guide	P0820903
P0813955	X11 input/output guide	P0820904
P0813956	X11 Networking features	P0820907
P0813957	ISDN Basic Rate Interface	P0820908
P0813958	ACD Reference Guide	P0820909
P0813959	Software conversion procedures	P0820912
P0813960	Feature Document X11 release 21	P0820913
P0813961	X11 system messages	P0820916
P0813962	X11 maintenance programs	P0820914
P0813963	X11 system management overview, applications and security	P0820917
P0813964	X11 administration programs	P0820915
P0813966	System installation and maintenance guide	P0820899
P0813967	System and software upgrade guide	P0820900
P0813968	System planning and engineering guide	P0820898
P0813969	Remote Peripheral Equipment Guide	P0820901

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0813971	System installation and maintenance	P0820910
P0813972	Switch settings, card and product compatibility	P0820911
P0814186	Meridian 1 NTS Network Managers Guide	
P0815275	MAXcaster User Guide English	P0815375
P0815276	MAXcaster User Guide French	P0815376
P0816320	LVD Kit	
P0818829	Carrier Remote IPE Interface NTP	P0842660
P0819082	Meridian Mail Reporter User Guide	P0847870
P0819090	Meridian 1 Remote Services Brochure	
P0820897	Library Navigator	P0842656
P0820898	System planning and engineering guide	P0842657
P0820899	System installation and maintenance guide	P0842658
P0820900	System and software upgrade guide	P0842659
P0820901	Remote Peripheral Equipment Guide	
P0820902	X11 software features guide	P0842661
P0820903	X11 system management, overview, applications and security guide	P0842662
P0820904	X11 input/output guide	P0842663
P0820905	X11 data features	P0868066
P0820906	X11 hospitality features	P0849011
P0820907	X11 Networking features	P0842664
P0820908	ISDN Basic Rate Interface	P0842665
P0820909	ACD Reference Guide	P0842666
P0820910	System installation and maintenance	P0842839
P0820911	Switch settings, card and product compatibility	P0842840
P0820912	Software conversion procedures	P0842841
P0820913	Feature Document X11 release 21	P0842842
P0820914	X11 maintenance programs	P0842843
P0820915	X11 administration programs	P0842844
P0820916	X11 system messages	P0842845
P0820917	X11 system management overview, applications and security	P0849012
P0820918	Meridian Modular Telephone User Guide	P0902627
P0821268	Option 11E - Installation Guide (Coil)	
P0821273	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Coil)	P0837630
P0821274	Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Binder)	P0837621

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0821277	Option 11E - X11 Software Guide (Coil)	
P0821279	General Information and Planning Handbook (Coil)	
P0821280	Option 11E - Upgrade Procedures (Coil)	
P0821281	Option 11E - Customer Reconfiguration Backup & Restore (Coil)	
P0821458	Option 11E - BRI Administration & Maintenance (Binder)	P0837640
P0821459	Option 11E - BRI Administration & Maintenance (Coil)	P0837643
P0832908	Fiber Remote Multi-IPE NTP	P0837440
P0832912	MTE Release 7 User Guide (English)	
P0833297	Fault Clearing Guide (Coil)	
P0833301	Read Me First Handbook	
P0833302	Installation Guide (Coil)	
P0833303	Software Installation Menu	
P0833305	Upgrade Procedures (Coil)	
P0834606	Keycode	
P0834786	Meridian 1 TAPI Server License Agreement	P0814991
P0837440	Fiber Remote Multi-IPE NTP	P0842660
P0837630	Option 11C Release 22 1.5MB DTI/PRI Guide - English	P0875063
P0837637	2.0 MB DTI/PRI Administration/Maintenance Guide	P0907454
P0837643	Option 11C Release 22 BRI Guide - English	P0875061
P0837650	Option 11C Release 22 Technical Reference Guide - English	P0891468
P0838403	Meridian M2616CT Belt Clip, Black	
P0838435	Meridian M2616CT Belt Clip, Ash	
P0838493	Meridian M2616CT Belt Clip, Gray	
P0840491	Meridian 1 Evergreen by Design Video	
P0842656	Library Navigator	P0868057
P0842657	System planning and engineering guide	P0868058
P0842658	System installation and maintenance guide	P0868059
P0842659	System and software upgrade guide	P0868060
P0842660	Remote Peripheral Equipment Guide	P0868061
P0842661	X11 software features guide	P0868062
P0842662	X11 system management, overview, applications and security guide	P0868064
P0842663	X11 input/output guide	P0868065
P0842664	X11 Networking features	P0868068
P0842665	ISDN Basic Rate Interface	P0868069

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0842666	ACD Reference Guide	P0868071
P0842837	CP Card Field Memory Upgrade Procedure	P0868052
P0842838	Meridian Integrated RAN NTP Guide	P0885702
P0842839	System installation and maintenance	P0868044
P0842840	Switch Settings, Card and Product Compatibility	P0868045
P0842841	Software conversion procedures	P0868046
P0842842	Feature Document X11 release 22	P0868047
P0842843	X11 maintenance programs	P0868049
P0842844	X11 administration programs	P0868050
P0842845	X11 system messages	P0868051
P0842849	Meridian Mail Modem Setup Document	P0875141
P0843835	MAT 5.x Traffic Analysis User Guide	P0867594
P0843836	MAT 5.x Call Accounting User Guide	P0867595
P0843838	ESN Analysis and Reporting User Guide	P0867596
P0843839	MAT 5.x Maintenance Windows User Guide	P0868440
P0843875	MAT 5 End User Five (5) Additional M1 System License	P0868347
P0843877	MAT 5 Call Accounting Small Expansion License	P0868349
P0843878	MAT 5 Call Accounting Medium Expansion License	P0868350
P0843879	MAT 5 Call Accounting Large Expansion License	P0868351
P0843880	MAT 5 Call Accounting Expansion Cap License	P0868352
P0845932	MAT 5 Call Accounting Small Expansion License Upgrade	P0868355
P0845933	MAT 5 Call Accounting Medium Expansion License Upgrade	P0868356
P0845934	MAT 5 Call Accounting Large Expansion License Upgrade	P0868357
P0845935	MAT 5 Call Accounting Expansion Cap License Upgrade	P0868358
P0847112	SYMPOSIUM Call Center Server Release 1, Planning & Engineering Guide	
P0847123	SYMPOSIUM Call Center Advanced Maintenance and Diagnostics Guide (English)	
P0849011	X11 hospitality features	P0868067
P0849012	X11 system management overview, applications and security	P0868048
P0850378	MAT 5 Call Accounting Mini Expansion License	P0868348
P0850509	MAT 5 Call Accounting Mini Expansion License Upgrade	P0868354
P0853935	Meridian 1 New Core Product Introductions - Sales & Marketing Readiness Package	
P0853939	Meridian Administration Tools (MAT) Demo Disk	
P0854530	Meridian Administration Tools (MAT) Sales Guide	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0855219	Journal User Guide	P0885219
P0857603	Meridian Integrated Conference Bridge NTP Guide	P0889995
P0857663	Meridian I Option 11C Technical Overview Brochure	
P0857668	Meridian 1 System Specifications Brochure	
P0857669	Meridian 1 Building Communications Solutions Brochure	
P0857833	MAT 5.x ESN Analysis and Reporting Tool User Guide	P0867596
P0858339	Meridian Integrated Conference Bridge User Guide	P0889996
P0858340	Meridian Customer Presentation Kit	
P0859507	M2216 User Guide (15/PK)	P0902629
P0859735	MAT 5 End User Site Expansion Upgrade	P0868353
P0866762	CCIP Meridian 1 Connectivity Documentation	
P0866881	Internet Software Download Guide	
P0867595	MAT 5.x Call Accounting User Guide	P0871739
P0868044	System installation and maintenance	P0889200
P0868045	Switch settings, card and product compatibility	P0889201
P0868046	Software conversion procedures	P0889202
P0868047	Feature Document X11 Release 23	P0889203
P0868048	System management overview, applications & security spirals	P0889431
P0868049	X11 Maintenance Programs	P0889204
P0868050	X11 Administration Programs	P0889235
P0868051	X11 system messages	P0889236
P0868052	CP card field memory upgrade procedure	P0888788
P0868057	Library Navigator	P0889187
P0868058	System planning and engineering guide	P0889188
P0868059	System installation and maintenance guide	P0889189
P0868060	System and Software Upgrade Guide	P0889190
P0868061	Remote Peripheral Equipment Guide	P0890732
P0868062	X11 Software Features Guide	P0889191
P0868064	X11 system management, overview, applications and security guide	P0889192
P0868065	X11 input/output guide	P0889193
P0868066	X11 data features	P0889194
P0868067	X11 hospitality features	P0889195
P0868068	X11 networking features	P0889196
P0868069	ISDN basic rate interface	P0889197

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0868071	ACD Reference Guides	P0889198
P0868347	MAT 5 End User Five (5) Additional M1 System License	
P0868348	MAT 5 Call Accounting Mini Expansion License	
P0868349	MAT 5 Call Accounting Small Expansion License	
P0868350	MAT 5 Call Accounting Medium Expansion License	
P0868351	MAT 5 Call Accounting Large Expansion License	
P0868352	MAT 5 Call Accounting Expansion Cap License	
P0868353	MAT 5 End User Site Expansion Upgrade	
P0868354	MAT 5 Call Accounting Mini Expansion License Upgrade	
P0868355	MAT 5 Call Accounting Small Expansion License Upgrade	
P0868356	MAT 5 Call Accounting Medium Expansion License Upgrade	
P0868357	MAT 5 Call Accounting Large Expansion License Upgrade	
P0868358	MAT 5 Call Accounting Expansion Cap License Upgrade	
P0869327	Open IVR 2.5 North American PRI Guide	
P0870332	SYMPOSIUM Call Center Server Capacity Assessment Guide	P0890035
P0870432	MTE Release 8 User Guide (English)	P0870433
P0870633	CCIP M1 Connectivity Software	
P0870639	IVR Generator Digital Prompt Tool Guide	
P0871232	CCIP Meridian 1 Connectivity Documentation	
P0872703	IODU/C Reference Guide	P0882201
P0872784	Option 11C Compact Software I/O Guides	
P0872786	Option 11C Compact CCBR Guide	
P0872787	Option 11C Compact Central Answering Position Guide	
P0872789	Option 11C Compact Technical Reference Guide	
P0872790	Option 11C Compact Features and Services Guide	
P0872791	Option 11C Compact Planning and Installation Guide	
P0873435	Prompt Transfer Tools Guide for AIU	
P0873891	Meridian 1 Attendant PC S/W Quick Start Guide	P0889883
P0873892	Meridian 1 Attendant PC Software User Guide	P0889884
P0873893	Meridian 1 Attendant PC S/W Installation Guide	P0889885
P0874537	Meridian M2616CT Handset Leather Pouch	
P0875061	Option 11C Release 23 BRI Guide - English	P0891472
P0875063	Option 11C Release 23 1.5MB DTI/PRI Guide - English	P0891469
P0875813	Data Input Forms (Release 23)	P0875113

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0876243	SYMPOSIUM Call Center Server Release 1 and the Meridian 1	P0888010
P0876250	SYMPOSIUM Call Center Release 1, Database Access & Report Management Guide	P0888025
P0876251	SYMPOSIUM Call Center Server Release 1, Historical Statistics Guide	
P0876252	SYMPOSIUM Call Center Server Release 1, Real-Time Display and Statistics Guide	
P0876257	SYMPOSIUM Call Center Server Release 1, Call Center Management Guide	
P0876258	SYMPOSIUM Call Center Server Release 1, Scripting Guide	P0888021
P0876404	MAT 6 User Guide Package	NTZC03AA
P0877889	Meridian Text Telephony System Quick Start Guide	
P0878305	Meridian 1 Option 11C Compact Brochure	P0903934
P0878308	SYMPOSIUM TAPI Service Provider Release 2 Customer Information Label	
P0878479	Meridian 1 Future Direction CD-ROM	
P0879421	Meridian 1 Attendant PC CD-ROM Sales Demo	
P0879709	Meridian 1 Evolution at Yale and SITA Video	
P0882201	IODU/C Reference Guide	
P0884266	SYMPOSIUM Call Center Server Planning and Engineering Guide	P0890034
P0884828	Meridian Integrated IP Telephony Gateway (ITG) NTPs	P0905051
P0885042	MAT 6.1 Compact Introduction Guide	P0890124
P0885212	Multi-Line CAP User Guide	P0890125
P0885213	Set Based Administration Guide	P0872785
P0885214	Option 11C Compact Planning and Installation Guide	P0890123
P0885215	Option 11C Compact Software Input-Output Guide	P0890121
P0885218	Option 11C Compact 1.5MB DTI/PRI Guide	P0872788
P0885697	MIPCD NTP Guide (English)	P0914163
P0885698	MIPCD User Guide (English)	P0891259
P0886005	MIPCD NTP Guide (French)	P0914553
P0886006	MIPCD User Guide (French)	P0914554
P0886125	CallPilot Software Installation Guide	
P0886136	CallPilot Maintenance and Diagnostic Guide	
P0886137	CallPilot Support Tools Guide	
P0886590	Liberation Unamplified Bottom Cord	
P0887067	SYMPOSIUM Express Call Center Quick Reference Card	
P0887069	SYMPOSIUM Express Call Center Task Flow Guide	P0908782
P0887333	SYMPOSIUM Express Call Center Server Reports and Displays Guide	P0907624

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0887334	SYMPOSIUM Express Call Center Management Guide	P0907622
P0888010	SYMPOSIUM Call Center Server Release 1 and the Meridian 1	
P0888012	SYMPOSIUM Call Center Server Back-up and Restore Instructions	
P0888021	SYMPOSIUM Call Center Server Release 1, Scripting Guide	
P0888025	SYMPOSIUM Call Center Server Release 1, Database Access and Report Management Guide	
P0888788	CP Card Field Memory Upgrade Procedure	
P0889199	NT5D61 IODU/C Reference Guide	P0912861
P0889248	Meridian M2616CT Cordless Telephone Flyer	
P0890034	SYMPOSIUM Call Center Server Planning and Engineering Guide	
P0890035	SYMPOSIUM Call Center Server Capacity Assessment Guide	P0903507
P0891259	MIPCD User Guide (English)	P0914505
P0891452	Overview, Installation and Programming	P0907441
P0891453	Post Installation Activities	P0907442
P0891454	Option 11C Administration & Maintenance I/O Guides	P0907443
P0891456	Planning and Installation Guide	P0907446
P0891458	Fault and Clearing Guide	P0907447
P0891460	Central Answering Position Guide	P0907448
P0891463	Customer Configuration Backup and Restore (Coil)	P0907449
P0891465	Upgrade Guide	P0907450
P0891467	Option 11C Administration & Maintenance I/O Guides	P0907451
P0891468	Option 11C Release 24 Technical Reference Guide - English	P0907452
P0891469	1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide	P0907453
P0891472	Option 11C BRI Guide (Release 18 to 24) - English	P0907455
P0902865	Meridian IP Telecommuter NTP	P0912864
P0903507	SYMPOSIUM Call Center Server Capacity Assessment Guide	
P0905818	Desktop Messaging for Internet Client Guide - French	
P0907026	Data Input Forms (Release 24)	
P0907386	Line-Side T1 Interface Card Description, Installation and Maintenance	
P0907437	Option 11C Mini Release 24B Technical Reference Guide - English	
P0909937	What’s New For Release 1.06 - French	
P0909942	Software Installation Guide - French	
P0909943	Maintenance and Diagnostic Guide - French	
P0909944	Planning and Engineering Guide - French	
P0909945	1001rp Installation and Maintenance Guide - French	

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
P0909946	200i Installation and Maintenance Guide - French	
P0910151	702t Installation and Maintenance Guide - French	
P096D326	Rubber Feet (100 each, for all Meridian Digital Telephones)	P0960326
QAA29	Adapter	
QAA33	Adapter	
QAA47A	Power Monitor Adapter	
QBK2	Fuse Block	
QBL10	Power Distribution Box (QCA23, QCA28)	QBL10B
QBL10B	Power Distribution Box (QCA23, QCA28)	
QBL11	Power Distribution Box (QCA24)	
QBL12	Battery Distribution Box	QBL12F
QBL13	Power Distribution Box (QCA25)	
QBL14	Power Distribution Box (RPE)	
QBL15	Battery Distribution Box	QBL15H
QBL16	150V Power Distribution Box	
QBL21	Power Distribution Box	
QBL24	Battery Backup Distribution Box	
QBL26	Power Distribution Unit	
QBL3	Power Distribution Box (QCA6, QCA28)	
QBL5	Power Distribution Box (QCA8)	
QBL6	Battery Distribution Box	
QBL7	Power Distribution Box (QCA10)	
QBL8	Power Distribution Box (QCA14)	
QBL9	AC Power Distribution Box	
QCA137	Expansion Cabinet	
QCA14	CE Network Cabinet	
QCA25	CE Network Cabinet	
QCA37	CE/PE Cabinet	
QCA7	PE Cabinet	
QCA76	Multi-Channel Data System (MCDS) Rack Cabinet	
QCA77	Multi-Channel Data System (MCDS) Desk Cabinet	
QCA8	PE and Power Cabinet	
QCAD109	Cable Adapter	QCAD109A
QCAD110A	Cable, Connector (25 Ft.) (Female/Female)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QCAD110B	Cable, Connector (10 Ft.) F/F	NT8D74AF
QCAD111	Cable, Connector (QSP43)	QCAD111A
QCAD112	Cable, Connector (QBL21)	QCAD112B
QCAD112B	Cable, Connector (QBL21)	
QCAD115	Cable, Intra-Cabinet (50 pin 20 In.)	QCAD201
QCAD116	Cable, Intra-Cabinet (50 pin 40 In.)	QCAD198
QCAD117	Cable, Intra-Cabinet (50 pin 60 In.) (EMI)	
QCAD118	Cable, Intra-Cabinet (50 pin 80 In.) (EMI)	
QCAD119	Cable, Intra-Cabinet (25 pin 65 In.) (EMI)	
QCAD120	Cable, Intra-Cabinet (25 pin 75 In.) (EMI)	
QCAD122A	Cable, Connector (4 Ft.) M/M	NT8D76AC
QCAD122B	Cable, Connector (6 Ft.) M/M	NT8D76AD
QCAD122C	Cable, Connector (10 Ft.) M/M	NT8D76AF
QCAD122D	Cable, Connector (15 Ft.) M/M	NT8D76AJ
QCAD122E	Cable, Connector (20 Ft.) M/M	NT8D76AL
QCAD122F	Cable, Connector (25 Ft.) M/M	NT8D76AP
QCAD123A	Cable, Connector (2 Ft.) M/M	NT8D80AB
QCAD123B	Cable, Connector (3 Ft.) M/M	NT8D80AC
QCAD123C	Cable, Connector (4 Ft.) M/M	NT8D80AC
QCAD123D	Cable, Connector (6 Ft.) M/M	NT8D80AD
QCAD123E	Cable, Conn. (10 Ft.) M/M	NT8D80AF
QCAD123F	Cable, Connector (15 Ft.) M/M	NT8D80AJ
QCAD123G	Cable, Connector (20 Ft.) M/M	NT8D80AL
QCAD123H	Cable, Connector (25 Ft.) M/M	NT8D80AP
QCAD124A	Cable, Connector (3 Ft.) M/M	NT8D85AC
QCAD124B	Cable, Connector (4 Ft.) M/M	NT8D85AC
QCAD124C	Cable, Connector (6 Ft.) M/M	NT8D85AD
QCAD124D	Cable, Connector (10 Ft.) M/M	NT8D85AF
QCAD124E	Cable, Connector (15 Ft.) M/M	NT8D85AJ
QCAD124F	Cable, Connector (20 Ft.) M/M	NT8D85AL
QCAD124G	Cable, Connector (25 Ft.) M/M	NT8D85AP
QCAD124H	Cable, Connector (35 Ft.) M/M	NT8D85AV
QCAD124J	Cable, Connector (45 Ft.) M/M	NT8D85AV
QCAD124K	Cable, Connector (50 Ft.) M/M	NT8D85AV

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QCAD125	Cable, Connector (10 Ft.) (Female/Female) (Clock to Clock)	QCAD125A
QCAD126	Cable, Connector (4.5 Ft.) (M/M) (CE to CE Inter-Connect)	QCAD123C
QCAD128	Cable, Connector (7 Ft.) (Male/Female) (DTI to I/O Panel)	QCAD128A
QCAD129	Cable, Connector (7 Ft.) (Male/Female) (PRI/DTI to Echo Canceler)	QCAD129A
QCAD130	Cable, Connector (7 Ft.) M/M (DTI to Clock)	NT8D79AE
QCAD133	PRI/DTI I/O Cable (50 Ft.)	QCAD133A
QCAD136	Cable Adapter	
QCAD137	Cable, Intra-Cabinet (SDI) (30 In.) (25 cond)	
QCAD138	CPU Power Adapter	QCAD138A
QCAD138A	CPU Power Adapter	
QCAD139	Power Adapter Cable	QCAD139A
QCAD141	CE Power Adapter Cable	QCAD141A
QCAD141A	CE Power Adapter Cable	
QCAD172	Cable, Connector	QCAD172B
QCAD172B	Cable, Connector	
QCAD176	Power Adapter Cable	QCAD176A
QCAD176A	Power Adapter Cable	
QCAD18	Cable, Connector (QSP44)	QCAD18A
QCAD18A	Cable, Connector (QSP44)	
QCAD190	Cable, Connector (74 In.) (Male/Male)	QCAD190A
QCAD191	Cable, Connector (71 In.) (Male/Male)	
QCAD192	Cable, Connector (68 In.) (Male/Male)	
QCAD193	Cable, Connector (61 In.) (Male/Male)	QCAD193A
QCAD194	Cable, Connector (58 In.) (Male/Male)	
QCAD195	Cable, Connector (55 In.) (Male/Male)	
QCAD196	Cable, Connector (48 In.) (Male/Male)	QCAD196A
QCAD197	Cable, Connector (43 In.) M/M	
QCAD198	Cable, Connector (40 In.) M/M	
QCAD199	Cable, Connector (33 In.) (Male/Male)	QCAD199A
QCAD199A	Cable, Connector (33 In.) (Male/Male)	
QCAD200	Cable, Connector (30 In.) M/M	
QCAD201	Cable, Connector (27 In.) M/M	
QCAD206	Cable Adapter	
QCAD209	Mass Storage Unit	QCAD209B

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QCAD209B	Mass Storage Unit	
QCAD240	Cable, CPU Faceplate Ribbon	NT8D78AA
QCAD254	Power Adapter Cable	QCAD254A
QCAD273	Rectifier Cords, 15 Amp, 125V	QCAD273A
QCAD273A	Rectifier Cords, 15 Amp, 125V	
QCAD274	Rectifier Cords, 20 Amp, 225V	QCAD274A
QCAD275	Rectifier Cords, 30 Amp, 125V	QCAD275A
QCAD275A	Rectifier Cords, 30 Amp, 125V	
QCAD276	Power Connector Cable (1st Module)	QCAD276A
QCAD276A	Power Connector Cable (1st Module)	
QCAD277	Power Connector Cable (2nd Module)	QCAD277A
QCAD278	Power Connector Cable (Basic)	QCAD278A
QCAD279	Disk Drive Cable	QCAD279B
QCAD279B	Disk Drive Cable	
QCAD283	Power Connector Cable (QRF12)	QCAD283A
QCAD283A	Power Connector Cable (QRF12)	
QCAD284	Power Adapter Cable	QCAD284A
QCAD287	Power Connector Cable (QUAA3)	QCAD287B
QCAD287B	Power Connector Cable (QUAA3)	
QCAD290	CSL Cable	QCAD290A
QCAD293A1	Connector Cable (34 In.)	
QCAD294B1	Power Fail Transfer Cable (25 Ft.)	QCAD294B2
QCAD294B3	Power Fail Transfer Cable (100 Ft.)	QCAD294B2
QCAD295	Battery Backup Supply Cable	QCAD295A
QCAD295A	Battery Backup Supply Cable	
QCAD299A	Remote RPE Expansion Shelf Power Cable	
QCAD2A	Cable, Connector (10 Ft.)	
QCAD300A	Remote RPE Expansion Shelf Power Cable	
QCAD301	Battery Backup Supply Extension Cable	QCAD301A
QCAD301A	Battery Backup Supply Extension Cable	
QCAD302A1	Fan Interconnect Cable (34 In.)	
QCAD302A2	Fan Interconnect Cable (29 In.)	
QCAD302A3	Fan Interconnect Cable (12 In.)	
QCAD303	Fan Power Cable	QCAD303A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QCAD303A	Fan Power Cable	
QCAD304	Fan Terminating Plug	QCAD304A
QCAD304A	Fan Terminating Plug	
QCAD306	Power Connector Cable (QSD73)	QCAD306B
QCAD308	Power & Signaling Cable (Tier 1 & 2)	QCAD308A
QCAD308A	Power & Signaling Cable (Tier 1 & 2)	
QCAD309	Alarm Adapter Cable	QCAD309A
QCAD310	Ground Extension Cable	QCAD310A
QCAD311A1	Network Cable Intra-Cabinet (40 In.)	NT9J98AC
QCAD311A2	Network Cable Intra-Cabinet (70 In.)	NT9J98AD
QCAD311A3	Network Cable Intra-Cabinet (85 In.)	NT9J98AE
QCAD312A	Network Cable, Intra-Cabinet (6 Ft.)	NT8D73AD
QCAD312B	Network Cable Inter-Cabinet (12 Ft.)	NT8D73AF
QCAD313	Power & Signaling Cable (Tier 3)	QCAD313A
QCAD317	Cable Assembly	NT8D83AD
QCAD318	Telecom 25 Pair (50-Pin) to 6DB-25 Female Connector	QCAD318A
QCAD319	Telecom 25 Pair (50-Pin) to 6DB-25 Male Connector	QCAD319A
QCAD320A	Cable, Connector (2 Ft.)	NT8D77AA
QCAD320B	Cable Connector (6 Ft.)	NT8D77AD
QCAD321	Junction Box QBL15	QCAD321A
QCAD325	Cable	QCAD325A
QCAD328A	Cable (6 Ft.)	
QCAD328B	Cable (18 Ft.)	
QCAD328C	Cable (35 Ft.)	
QCAD328D	Cable (50 Ft.)	
QCAD332	Triple SDI Cable (Internal)	QCAD332A
QCAD333	Triple SDI Cable (External)	NT8D96AB
QCAD339	Shelf Cable	
QCAD349	CE Alarm Adapter Cable	QCAD349A
QCAD349A	CE Alarm Adapter Cable	
QCAD36	Cable, Connector (16 Ft.) (SDI)	NT8D95AJ
QCAD37	Cable, Connector (50 Ft.) (SDI)	NT8D95AW
QCAD42	Cable, Intra-Cabinet (25 Conductor 95 In.) (EMI)	QCAD42A
QCAD5A	RS232 Modem Pool Cable	QCAD5B

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QCAD5B	RS232 Modem Pool Cable	
QCB12A	Cable, Connector (CDR)	
QCB13A	Cable, Connector (CDR)	
QCB7C	Cable, Connector (3 Ft.)	
QCB9A	Cable, Connector (Maintenance)	
QCN100	Attendant Console	
QCN101	Attendant Console	
QCN102	Attendant Console	
QCW2	Console	
QCW3	Console	
QCW4	Digit Display Console	
QKK1	Handsfree Interface Kit	
QKK3	Automatic Handsfree Interface Kit	
QKK8	Automatic Handsfree Answerback Interface Kit	
QKM12A	Peripheral Shelf Adapter	
QKM13A	Light Probe Kit	
QKM176A	System 600/48 Seismic Anchor	NT0X21AV
QKM262A	CND Expansion Kit	
QKM289	Fuse Rating Upgrade Assembly	
QKN1	Headset Interface Kit	
QMM38	Mass Storage Unit Assembly	
QMM42	Security Data Cartridge	QMM42A
QMM43	Mass Storage Assembly	QPC742F
QMM45	Floppy Disk Module	QMM45A
QMM45A	Floppy Disk Module	
QMT1	Add-On Module (10 Button)	NT2K22XH03
QMT1	Add-On Module (10 Button)	NT2K22XH35
QMT1	Add-On Module (10 Button)	NT2K22XH93
QMT102	Disk Drive Controller	
QMT103	Winchester Hard Disk Assembly	
QMT104	Floppy Drive Assembly	
QMT11	Asynchronous/Synchronous Interface Module (ASIM)	QMT11D
QMT11D	Asynchronous/Synchronous Interface Module (ASIM)	
QMT12	V.35 Add-On Data Module	QMT12E

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QMT12E	V.35 Add-On Data Module	
QMT15	Amplified Handset Module (Includes Attendant Handset Assembly)	
QMT2	Add-On Module (20 Button)	NT2K22XH03
QMT2	Add-On Module (20 Button)	NT2K22XH35
QMT2	Add-On Module (20 Button)	NT2K22XH93
QMT21	High Speed Data Module (HSDM) 110V Power Supply	QMT21C1
QMT21C1	High Speed Data Module (HSDM) 110V Power Supply	
QMT3	Lamp Field Array (BLF)	
QMT4	Handset Module	
QMT7	Add-On Data Module (ADM) (Asynchronous Only)	
QMT8	Add-On Data Module (ADM) (Synchronous/Asynchronous)	NT7D16AA
QMT8	Add-On Data Module (ADM) (Synchronous/Asynchronous)	QMT21
QMT8	Add-On Data Module (ADM) (Synchronous/Asynchronous)	QPC723A
QMT9	Asynchronous Interface Module (AIM)	A0344336
QMT9	Asynchronous Interface Module (AIM)	A0344337
QPA57	Function Pack	
QPA58	Interface Pack	
QPA59	Miscellaneous	
QPA62	32K x 17R/W Memory (CDR)	
QPC130	CDR Tape Control	
QPC131	CDR ROM 1 (Single Port)	
QPC132	CDR ROM 2 (Single Port)	
QPC135	Fast CPU ALU Low	
QPC136	Fast CPU ALU High	
QPC137	Fast CPU Control	
QPC138	Fast CPU Sequencer	
QPC139B	Serial Data Interface (Dual)	
QPC155	Fast CE Bus Extender	
QPC156	Multigroup Control	
QPC157	Multigroup Switch	
QPC158	Multigroup Extender	
QPC162	AIOD C25 Data Trunk	
QPC163	48V Regulator	
QPC164	Bus Termination Unit (BTU)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC167	Real Time Clock & ROM	
QPC171	Battery Monitor	
QPC187	Ringing Generator	
QPC188D	Battery Monitor	
QPC189	MF Sender	
QPC190	5/12V Converter Pack	QPC691
QPC192	OPX Line	
QPC197D	Tone & Digit Switch	QPC251
QPC199	4K x 16 ROM	
QPC212	Real Time Clock & ROM	
QPC213	Changeover & Memory Arbitrator	
QPC214	Memory Controller	
QPC215	Segmented Bus Extender	QPC215D
QPC215D	Segmented Bus Extender	
QPC216	Three Port Segmented Extender	
QPC218	CO/FX/WATS Trunk	
QPC219	CO/FX/Trunk with Message Registration Detector Circuit	QPC450G
QPC220	Bus Termination Unit (BTU)	
QPC228	CPU Changeover	
QPC237E	4 Wire E&M Trunk	
QPC239	Dictation Trunk Applique w/DCK Interface	
QPC240	ROM 2 Module	
QPC241	ROM 3 Module	
QPC246	Keyboard (QCW3)	
QPC247	Keyboard with Dial Pad, (QCW3/QCW4)	QPC247A
QPC248	Keyboard (QCW3/QCW4)	
QPC250	Release Line Trunk	
QPC251	Tone and Digit Switch for CAS	
QPC264	8K ROM	
QPC267	MW/DND Line Card	
QPC268	Control Interface and Memory	
QPC271	Control and Timing	
QPC274	Fan Inverter (QRF8)	
QPC297	Supervisory Console	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC298	3 Port CPU Interconnect	
QPC30	4K x 17 R/W Memory	
QPC300	8K ROM	
QPC301	CDR ROM (Multi-Port)	
QPC31	8K x 17 R/W Memory (CDR-Single Port)	
QPC311	SL-1 Data Line Card	QPC432
QPC32	4K x 16 ROM	
QPC33	Tape Unit Interface	
QPC353	500 Line Card for Modem Pool Interface	NT7D16AA
QPC353	500 Line Card for Modem Pool Interface	QPC723A
QPC362	Conference/Network Card	
QPC374	8K ROM	
QPC376	Dual Network	
QPC387	Peripheral Buffer	
QPC39	CDR Timing	
QPC397	MCDS - Asynchronous Card	
QPC40	Arithmetic Logic Unit (CDR)	
QPC41	CPU Miscellaneous Register (CDR)	
QPC411	System Clock Generator	
QPC412C	Intergroup Switch	NT5D30AA
QPC414	Network Card	QPC414C
QPC417	Junctor Board	QPC417A
QPC42	Sequencer (CDR)	
QPC420	Keyboard Pack	
QPC422	Tone Detector	
QPC423	192K Memory	QPC674
QPC424	Central Processor Unit (CPU)	
QPC425	Central Processor Unit (CPU)	
QPC426	192K Memory	
QPC43	Peripheral Signaling	QPC43R
QPC430	AILC - Asynchronous Interface Line Card	
QPC432	Four Port Data Line Card	
QPC44	CPU Changeover	
QPC441	Three-Port Extender	QPC441F

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC443	Control and Timing	QPC600
QPC444	Conference Card	QPC444A
QPC449C	Loop Signaling Trunk	
QPC45	Serial Data Interface (Single) (CDR)	
QPC450G	CO/FX/Trunk w/Message Registration Detector Circuit	
QPC451	SL-1 Line Card	
QPC452	500/2500 Line Card	
QPC46	CE Bus Extender	
QPC464	Peripheral Buffer	
QPC471	Clock Controller	QPC471H
QPC472	DTI/CPI Network Carrier Interface	
QPC477	Bus Terminating Unit (BTU)	QPC477B10
QPC477A10	Bus Terminating Unit (BTU)	
QPC478	128K Memory	QPC674
QPC479	128K Memory	QPC426
QPC486	ROM Card	QPC662
QPC487	ROM Card	QPC782
QPC494A	MW/DND Line Card	
QPC496	Pack, CPU Bus Extender, N	QPC496A
QPC496A	Pack, CPU Bus Extender, N	
QPC50	Network	
QPC500	PE Backplane	
QPC501	PE Backplane/Expansion	
QPC502	Power Backplane	
QPC503	CE Backplane Expansion	QPC699
QPC509	Message Waiting Power Supply	
QPC51	64K Memory Module	
QPC512	Personal Computer (PC) Interface Card	
QPC513	Enhanced SDI	QPC513H
QPC513H	Enhanced SDI	
QPC52	Network Extender	
QPC53	Conference	
QPC54	Tone and Digit Switch 1	
QPC55	Tone and Digit Switch 2	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC552	Control and Timing	
QPC553	Function	
QPC554	Interface	
QPC555	Miscellaneous	
QPC556	Changeover and Memory Arbitrator	
QPC557	Control and Timing	QPC601
QPC571	ROM Card	
QPC573	8K ROM Card	
QPC574B	Digitone Receiver	
QPC578	Integrated Service Digital Line Card (ISDLC)	QPC578D
QPC578D	Integrated Service Digital Line Card (ISDLC)	
QPC579	Central Processor Unit (CPU)	
QPC580	CPU Interface Card	
QPC581	Changeover & Memory Arbitrator	NTND10AA
QPC583	768K Memory	
QPC584	Mass Storage Interface Card	QPC584M
QPC585A	Disk Shelf Power Converter (QMM38)	
QPC594	500/2500 Line Card (16 Port)	
QPC599	ROM Card	
QPC60	500/2500 Line Card	QPC594
QPC600	ROM Card	
QPC601	ROM Card (Memory Enhancement)	
QPC602	ROM Card	
QPC609	Fast Tone and Digit Switch	QPC609D
QPC609D	Fast Tone and Digit Switch	
QPC61	SL-1 Line Card	QPC451
QPC62	1.5M Baud Converter (RPE)	
QPC63	Local Carrier Buffer (RPE)	
QPC64	Peripheral Buffer	
QPC65	Remote Peripheral Switch (RPE)	
QPC659	Dual Loop Peripheral Buffer	QPC659E
QPC659E	Dual Loop Peripheral Buffer	
QPC66	2M Baud Converter (RPE)	
QPC662	ROM Card	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC67	Carrier Maintenance (RPE)	
QPC672	512K Memory Card	
QPC673	512K Memory Card	QPC814
QPC674	256K RAM Memory	
QPC687	Central Processor Unit (CPU)	
QPC691	5/12V Converter	
QPC699	CE Backplane	
QPC70	CO/FX/WATS Trunk	
QPC700	CE Backplane	
QPC701	PE Backplane	QPC701A1
QPC701A1	PE Backplane	
QPC702	PE Backplane	QPC702A1
QPC705	30/150V PE Power Converter	
QPC706	Power Converter (All Voltages)	
QPC709	Miscellaneous/Peripheral Signaling	
QPC710	Dual Digitone Receiver Daughter Board	QPC710A
QPC710A	Dual Digitone Receiver Daughter Board	
QPC717	ROM Card	
QPC71H	E&M/DX/Page Trunk	
QPC72	Loop Signaling Trunk	
QPC720	Primary Rate Interface Card	QPC720F
QPC723A	RILC - RS232C Interface Line Card	
QPC73	Dictation Trunk Applique	
QPC742F	Floppy Disk Interface Card	
QPC74C	Recorder Announcement Trunk	
QPC75	Rectifier Control (QSD4)	
QPC755	Connector Card RPE	
QPC757	D Channel Interface Card	
QPC78	Fan Inverter (QSD4)	
QPC782	ROM Card	
QPC789	16 Port Message Waiting Line Card	QPC789A
QPC789A	16 Port Message Waiting Line Card	
QPC79	Digitone Receiver	QPC574B
QPC80H	10V Converter Pack	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QPC814	768K Memory Card	
QPC82E	30V Converter Pack	
QPC84	Power Monitor Pack	QPC84S
QPC841	Four-Port SDI	QPC841C
QPC85	5/12V Converter Pack (RPE)	QPC691
QPC916	Multi-Frequency Receiver Card	
QPC918	High Speed Data Card (2 Port)	
QPC930	16 Port Hotel/Motel Message Waiting Line Card	
QPC937	ROM Card	QPC717
QPC939	ROM Card	
QPC940	ROM Card	
QPC99	Carrier Interface (RPE)	
QPF23	Terminating Plug	QPF23A
QPF36	Terminating Plug	QPF36B
QPF37	Alarm Termination	
QRF12	48V Rectifier	NT0R71AA
QRF8	48V Rectifier	
QRF9	48V Rectifier	
QSAM3	Group Listening Switch	
QSD1	Common Equipment Shelf 0 (CDR)	
QSD10	Power Converter Shelf (RH Mount)	
QSD11	Carrier Shelf 1 (RPE)(RH Mount)	
QSD12	CPU/Memory Shelf	
QSD13	Segmented Network Shelf 1	
QSD14	Memory Shelf	
QSD15	Common Equipment Shelf (CPU)	
QSD16	Segmented Network Shelf 0	
QSD17	Common Equipment Shelf (CPU)	
QSD18	Common Equipment Shelf (CPU)	
QSD19	Common Equipment Shelf (CPU)	
QSD2	Common Equipment Shelf 1	
QSD23	Power Control Shelf	
QSD26	CERP Shelf	
QSD27	Multi-Channel Data System (MCDS) Shelf	QSD27A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QSD27A	Multi-Channel Data System (MCDS) Shelf	
QSD3	Peripheral Equipment Shelf 0 (LH Mount)	QSD34
QSD31	Peripheral Equipment Shelf	AS1053A
QSD31	Peripheral Equipment Shelf	AS1053D
QSD32	Peripheral Equipment Shelf	
QSD33	Tape Shelf	
QSD34	Peripheral Equipment Shelf (LH Mount)	QSD80
QSD35	Peripheral Equipment Shelf (RH Mount)	QSD80
QSD36	Memory Shelf (Center Mount)	
QSD37	CPU/Memory Shelf	
QSD39	Network Shelf (LH Mount)	
QSD4	48V Rectifier Assembly	QRF8
QSD40	Network Shelf (RH Mount)	
QSD54	Network Shelf (RH Mount)	
QSD55	Network Shelf (LH Mount)	
QSD58	Common Equipment Shelf	
QSD59	CPU/Memory Shelf	
QSD6	Carrier Shelf 0 (RPE) (LH Mount)	
QSD60	CPU/Memory Shelf (Cantilever Mount)	
QSD61	CPU/Memory Shelf (Center Mount)	
QSD62	CPU/Memory Shelf (Cantilever Mount)	
QSD64	Universal Peripheral Equipment Shelf	
QSD65	Dual Loop PE Shelf	QSD65A
QSD65A	Dual Loop PE Shelf	
QSD66	PE Expansion Tier	AS1053A
QSD66	PE Expansion Tier	AS1053D
QSD67	Disk Drive Shelf (Cantilever Mount)	
QSD68	Disk Drive Shelf/MSU (Center Mount)	
QSD69	RPE Expansion Tier	QSD69A1
QSD7	Peripheral Equipment Shelf 1 (RH Mount)	QSD35
QSD73	CE/PE Expansion Tier	
QSD76	Network/MSU Shelf	
QSD79B	Expansion Tier Assembly	
QSD80	High Density PE Shelf	AS1053A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QSD80	High Density PE Shelf	AS1053D
QSD81A	CE Shelf (w/Mounting Bracket)	
QSD82	H/M PE Shelf System	
QSD83	H/M ST Shelf System	
QSD9	Common Equipment Shelf 2	
QSP31	Network Shelf (RH Mount)	
QSP32	Network Shelf (LH Mount)	
QSP35	Peripheral Equipment Shelf (RH Mount)	QSD64
QSP36	Peripheral Equipment Shelf (LH Mount)	QSD64
QSP39	Common Equipment Shelf	
QSP40	Memory Shelf (QCA55)	
QSP41	Common Equipment/Memory (QCA58)	
QSP43	Power Control (QCA55, QCA58, QCA108, QCA109, QCA96, QCA97)	
QSP44	Power Control (QCA74)	
QSP45	Tape Unit and Shelf	
QSP6	Option Shelf Full Wired/Enhanced	
QSP7	Option Shelf Full Wired/Enhanced	
QSR2F1	Venture 1 Headset w/5 Ft. Straight Cord	
QSR2G1	Venture 1 Headset w/15 Ft. Coiled Cord	
QSU1	SL-1 Telephone Set	
QSU3	SL-1 Digit Display Phone	
QSU60	SL-1 Telephone (Fully Modular)	NTZK08BA03
QSU60	SL-1 Telephone (Fully Modular)	NTZK08BA35
QSU60	SL-1 Telephone (Fully Modular)	NTZK08BA93
QSU61	SL-1 Digit Display Telephone	NTZK22AA03
QSU61	SL-1 Digit Display Telephone	NTZK22AA35
QSU61	SL-1 Digit Display Telephone	NTZK22AA93
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK22AA03
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK22AA35
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK22AA93
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK23AA03
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK23AA35
QSU7	SL-1 ACD Telephone (Dual Headset Jack)	NTZK23AA93
QSU71B35	M1109 Compact Telephone, Ash	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QSU71B93	M1109 Compact Telephone, Gray	
QSU71C35	Meridian M1109 Compact Telephone, Ash	NTZK08AA35
QSU71C93	Meridian M1109 Compact Telephone, Gray	NTZK08AA93
QSY19	MW/DND 150V Power Supply	QSY22
QSY22	Message Waiting 150V Power Supply	
QSY27	Multi-Channel Data System (MCDS) Power	QSY27A
QSY27A	Multi-Channel Data System (MCDS) Power	
QUA1	Transfer Unit	
QUA4A1	Power Fail Transfer Unit	
QUA5A	Power Fail Transfer Unit	
QUA6	Power Fail Transfer Unit	QUA6A
QUA6A	Power Fail Transfer Unit	
QUAA3	Power Unit	QUAA3C
QUAA3C	Power Unit	
QUAA5	Power Unit	QUAA5A
QUAA5A	Power Unit	
QUD1	Cooling Unit (CDR)	
QUD15	Blue Cooling and Cable Routing Panel Assembly	QUD20B
QUD20B	Gray Cooling and Cable Routing Panel Assembly	
QUD24	Cooling Unit	QUD25
QUD25	Cooling Unit	
QUD3	Cooling Unit	
QUD4	Cooling Unit	
QUD5	Cooling Unit	
QUD6	Cooling Unit	
QUD8	Mini Cooling Unit	
QUD9	Cooling Unit	
QUT1	Centralized Power Unit	
QUT2	Power Unit (Fan)	
QUT3	Power Unit (Fan & Inverter)	
QUW1	Tape Unit & Shelf	
QUW3	Mini Tape Unit & Shelf (QCA28)	
QUW9	Tape Unit	
QUX1	Power Distribution Unit (QCA6, QCA28)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
QUX10	Power Distribution Unit (QCA24)	
QUX11	Power Distribution Unit (QCA25)	
QUX16	Power Distribution Unit (QCA60)	
QUX19	Power Distribution Unit (QCA136)	
QUX2	Power Distribution Unit (QCA7)	
QUX20	Power Distribution Unit (QCA136)	
QUX21	Power Distribution Unit (QCA137)	
QUX22	Power Distribution Unit (QCA147)	
QUX3	Power Distribution Unit (QCA8)	
QUX4	Power Distribution Unit (QCA10)	
QUX5	Power Distribution Unit (QCA14)	
QUX6	Power Distribution Unit (CDR)	
QUX9	Power Distribution Unit (QCA23)	
R001	Meridian 1 Feature Glossary (Price is Per Set)	
R0059715	Protective Grommet (12-3/4 In. strip lengths)	
S0311110	Option Group 110, Trunk Verification from a Station (LE)	
S0311850	Option Group 19, 50 & 51, ACD Link Software (LE)	
S0411110	Option Group 110, Trunk Verification from a Station (VLE)	
S0411850	Option Group 19, 50, 51, ACD Link Software (VLE)	
S0611110	Option Group 110, Trunk Verification from a Station (XL)	
S0611850	Option Group 19, 50 & 51, ACD Link Software (XL)	
S0711095	Option Group 95, 19, 88, 89, 91, Call Party Name Display (S, MS)	
S0711098	Option Group 98, Dialed Number Identification Service (S, MS)	
S0711100	Option Group 100, 81, 99, Room Status (S, MS)	
S0711101	Option Group 101, 81, 99, Message Registration (S, MS)	
S0711102	Option Group 102, 81, 99, Automatic Wakeup (S, MS)	
S0711103	Option Group 103, 81, 99, Property Management System Interface (S, MS)	
S0711105	Option Group 105, Line Load Control (S, MS)	
S0711107	Option Group 107, Malicious Call Trace (S, MS)	
S0711108	Option Group 108, Internal CDR (S, MS)	
S0711109	Option Group 109, Auxiliary Processor Link (S, MS)	
S0711110	Option Group 110, Trunk Verification from a Station (S, MS)	
S0711111	Option Group 111, ACD Timed Overflow (S, MS)	
S0711113	Option Group 113, Incoming DID Digit Conversion (S, MS)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S0711115	Option Group 115, Directed Call Pickup (S, MS)	
S0711116	Option Group 116, ACD Priority Agents (S, MS)	
S0711119	Option Group 119, Enhanced Music (S, MS)	
S0711150	Option Group 150, Directory Number Expansion (MS)	
S0711151	Option Group 151, Expanded Call Detail Recording (MS)	
S0711837	Complete Hospitality Package (S, MS)	
S0711850	Option Group 19, 50 & 51, ACD Link Software (S, M, MS)	
S0811095	Option Group 95, 19, 88, 89, 91, Call Party Name Display (N)	
S0811098	Option Group 98, Dialed Number Identification Service (N)	
S0811100	Option Group 100, 81, 99, Room Status (N)	
S0811101	Option Group 101, 81, 99, Message Registration (N)	
S0811102	Option Group 102, 81, 99, Automatic Wakeup (N)	
S0811103	Option Group 103, 81, 99, Property Management System Interface (N)	
S0811105	Option Group 105, Line Load Control (N)	
S0811107	Option Group 107, Malicious Call Trace (N)	
S0811108	Option Group 108, Internal CDR (N)	
S0811109	Option Group 109, Auxiliary Processor Link (N)	
S0811110	Option Group 110, Trunk Verification From a Station (N)	
S0811111	Option Group 111, ACD Timed Overflow (N)	
S0811113	Option Group 113, Incoming DID Digit Conversion (N)	
S0811115	Option Group 115, Directed Call Pickup (N)	
S0811116	Option Group 116, ACD Priority Agents (N)	
S0811119	Option Group 119, Enhanced Music (N)	
S0811150	Option Group 150, Directory Number Expansion (N)	
S0811151	Option Group 151, Expanded Call Detail Recording (N)	
S0811157	Centrex Switch Hook Flash	
S0811170	Modular Meridian Terminals	
S0811837	Complete Hospitality Package (N)	
S0811850	Option Group 19, 50 & 51, ACD Link Software (N)	
S0811851	Option Group 114, 155, ACD-D/MAX Report Enhancements (N)	
S0890001	Option Group 145, 146, Primary Rate Access (N)	
S0890002	Option Group 149, Inter-Exchange Carrier (N)	
S0890003	Option Group 147, 145, ISDN Signaling Link (N)	
S0890004	Option Group 148, Advance ISDN Features (N)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S0890005	Option Group 118, Calling Line ID in CDR (N)	
S0890006	Option Group 117, Call By Call Service (N)	
S0911095	Option Group 95, 19, 88, 89, 91, Call Party Name Display (XN)	
S0911098	Option Group 98, Dialed Number Identification Service (XN)	
S0911100	Option Group 100, 81, 99, Room Status (XN)	
S0911101	Option Group 101, 81, 99, Message Registration (XN)	
S0911102	Option Group 102, 81, 99, Automatic Wakeup (XN)	
S0911103	Option Group 103, 81, 99, Property Management System Interface (XN)	
S0911105	Option Group 105, Line Load Control (XN)	
S0911107	Option Group 107, Malicious Call Trace (XN)	
S0911108	Option Group 108, Internal CDR (XN)	
S0911109	Option Group 109, Auxiliary Processor Link (XN)	
S0911110	Option Group 110, Trunk Verification From a Station (XN)	
S0911111	Option Group 111, ACD Timed Overflow (XN)	
S0911113	Option Group 113, Incoming DID Digit Conversion (XN)	
S0911115	Option Group 115, Directed Call Pickup (XN)	
S0911116	Option Group 116, ACD Priority Agents (XN)	
S0911119	Option Group 119, Enhanced Music (XN)	
S0911150	Option Group 150, Directory Number Expansion (XN)	
S0911151	Option Group 151, Expanded Call Detail Recording (XN)	
S0911153	Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (XN)	
S0911157	Option Group 157, Centrex Switch Hook Flash (XN)	
S0911170	Option Group 170, Modular Meridian Terminals (XN)	
S0911837	Complete Hospitality Package (XN)	
S0911850	Option Group 19, 50 & 51, ACD Link Software (XN)	
S0911851	Option Group 114 and 155, ACD-D/MAX Report Enhancements (XN)	
S0990001	Option Group 145 and 146, Primary Rate Access (XN)	
S0990002	Option Group 149, Inter-exchange Carrier (XN)	
S0990003	Option Group 145 and 147, ISDN Signaling Link (XN)	
S0990004	Option Group 148, Advanced ISDN Features (XN)	
S0990005	Option Group 118, Calling Line ID in CDR (XN)	
S0990006	Option Group 117, Call By Call Service (XN)	
S1011000	Basic Program: Generic 1011	
S1011001	Option Group 1, Advanced Station Features (ST)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S1011091	Option Group 91, Meridian M2317 Digital Display Telephone (S, ST, MS, M)	
S1011095	Option Group 95, 19, 88, 89 and 91, Call Party Name Display (ST)	
S1011098	Option Group 98, Dialed Number Identification Service (ST)	
S1011100	Option Group 100, 81 and 99, Room Status (ST)	
S1011101	Option Group 101, 81 and 99, Message Registration (ST)	
S1011102	Option Group 101, 81 and 99, Message Registration (ST)	S1011101
S1011103	Option Group 103, 81, 99, Property Management System Interface (ST)	
S1011105	Option Group 105, Line Load Control (ST)	
S1011107	Option Group 107, Malicious Call Trace (ST)	
S1011108	Option Group 108, Internal CDR (ST)	
S1011109	Option Group 109, Auxiliary Processor Link (ST)	
S1011110	Option Group 110, Trunk Verification From a Station (ST)	
S1011111	Option Group 111, ACD Timed Overflow (ST)	
S1011112	Integrated Services Access	
S1011113	Option Group 113, Incoming DID Digit Conversion (ST)	
S1011115	Option Group 115, Directed Call Pickup (ST)	
S1011116	Option Group 116, ACD Priority Agents (ST)	
S1011119	Option Group 119, Enhanced Music (ST)	
S1011150	Option Group 150, Directory Number Expansion (ST)	
S1011151	Option Group 151, Expanded Call Detail Recording (ST)	
S1011153	Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, and 109, Meridian Link ISDN A/P (ST)	
S1011157	Option Group 157, Centrex Switch Hook Flash (ST)	
S1011170	Option Group 170, Modular Meridian Terminals (ST)	
S1011785	Option Group 77 & 85, Command and Status Link (CSL) (ST, MS)	
S1011837	Complete Hospitality Package (ST)	
S1011850	Option Group 19, 50 & 51, ACD Link Software (ST)	
S1011851	Option Group 114 and 155, ACD-D/MAX Report Enhancements (ST)	
S1090001	Option Group 145 and 146, Primary Rate Access (ST)	
S1090002	Option Group 149, Inter-exchange carrier (ST)	
S1090003	Option Group 145 and 147, ISDN Signaling Link (ST)	
S1090004	Option Group 148, Advance ISDN Features (ST)	
S1090005	Option Group 118. Calling Line ID in CDR (ST)	
S1090006	Option Group 117, Call By Call Service (ST)	
S1111091	Option Group 91, Meridian M2317 Digital Display Telephone (LE, N, NT, RT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S1111095	Option Group 95, 19, 88, 89 and 91, Call Party Name Display (NT)	
S1111098	Option Group 98, Dialed Number Identification Service (NT)	
S1111100	Option Group 100, 81, 99, Room Status (NT)	
S1111101	Option Group 101, 81, 99, Message Registration (NT)	
S1111102	Option Group 102, 81, 99, Automatic Wakeup (NT)	
S1111103	Option Group 103, 81, 99, Property Management System Interface (NT)	
S1111105	Option Group 103, 81, 99, Property Management System Interface (NT)	S1111103
S1111107	Option Group 107, Malicious Call Trace (NT)	
S1111108	Option Group 108, Internal CDR (NT)	
S1111109	Option Group 109, Auxiliary Processor Link (NT)	
S1111110	Option Group 110, Trunk Verification From a Station (NT)	
S1111111	Option Group 111, ACD Timed Overflow (NT)	
S1111112	Integrated Services Access	
S1111113	Option Group 113, Incoming DID Digit Conversion (NT)	
S1111115	Option Group 115, Directed Call Pickup (NT)	
S1111116	Option Group 116, ACD Priority Agents (NT)	
S1111119	Option Group 119, Enhanced Music (NT)	
S1111150	Option Group 150, Directory Number Expansion (NT)	
S1111151	Option Group 151, Expanded Call Detail Recording (NT)	
S1111153	Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85 and 109, Meridian Link ISDN A/P (NT)	
S1111157	Option Group 157, Centrex Switch Hook flash (NT)	
S1111170	Option Group 170, Modular Meridian Terminals (NT)	
S1111785	Option Group 77 & 85, Command and Status Link (CSL) (LE, N, NT, RT)	
S1111837	Complete Hospitality Package (NT)	
S1111850	Option Group 19, 50 & 51, ACD Link Software (NT)	
S1111851	Option Group 114 and 155, ACD-D/MAX Report Enhancements (NT)	
S1190001	Option Group 145 and 146, Primary Rate Access (NT)	
S1190002	Option Group 149, Inter-exchange Carrier (NT)	
S1190003	Option Group 145 and 147, ISDN Signaling Link (NT)	
S1190004	Option Group 148, Advance ISDN Features (NT)	
S1190005	Option Group 118, Calling Line ID in CDR (NT)	
S1190006	Option Group 117, Call By Call Service (NT)	
S1211091	Option Group 91, Meridian M2317 Digital Display Telephone (VLE, XL, XN, XT)	
S1211095	Option Group 95, 19, 88, 89 and 91, Call Party Name Display (XT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S1211098	Option Group 98, Dialed Number Identification Service (XT)	
S1211100	Option Group 100, 81 and 99, Room Status (XT)	
S1211101	Option Group 101, 81 and 99, Message Registration (XT)	
S1211102	Option Group 102, 81 and 99, Automatic Wakeup (XT)	
S1211103	Option Group 103, 81, 99, Property Management System Interface (XT)	
S1211105	Option Group 105, Line Load Control (XT)	
S1211107	Option Group 107, Malicious Call Trace (XT)	
S1211108	Option Group 108, Internal CDR (XT)	
S1211109	Option Group 109, Auxiliary Processor Link (XT)	
S1211110	Option Group 110, Trunk Verification From a Station (XT)	
S1211111	Option Group 111, ACD Timed Overflow (XT)	
S1211112	Integrated Services Access	
S1211113	Option Group 113, Incoming DID Digit Conversion (XT)	
S1211115	Option Group 115, Directed Call Pickup (XT)	
S1211116	Option Group 116, ACD Priority Agents (XT)	
S1211119	Option Group 119, Enhanced Music (XT)	
S1211150	Option Group 150, Directory Number Expansion (XT)	
S1211151	Option Group 151, Expanded Call Detail Recording (XT)	
S1211153	Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (XT)	
S1211157	Option Group 157, Centrex Switch Hook Flash (XT)	
S1211170	Option Group 170, Modular Meridian Terminals (XT)	
S1211785	Option Group 77 & 85, Command and Status Link (CSL) (XL, XN, XT)	
S1211837	Complete Hospitality Package (XT)	
S1211850	Option Group 19, 50 & 51, ACD Link Software (XT)	
S1211851	Option Group 114 and 155, ACD-D/MAX Report Enhancements (XT)	
S1290001	Option Group 145 and 146, Primary Rate Access (XT)	
S1290002	Option Group 149, Inter-exchange Carrier (XT)	
S1290003	Option Group 145 and 147, ISDN Signaling Link (XT)	
S1290004	Option Group 148, Advance ISDN Features (XT)	
S1290005	Option Group 118, Calling Line ID in CDR (XT)	
S1290006	Option Group 117, Call By Call Service (XT)	
S1311095	Option Group 95, 19, 88, 89 and 91, Call Party Name Display (RT)	
S1311098	Option Group 98, Dialed Number Identification Service (RT)	
S1311100	Option Group 100, 81 and 99, Room Status (RT)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
S1311101	Option Group 101, 81 and 99, Message Registration (RT)	
S1311102	Option Group 102, 81 and 99, Automatic Wakeup (RT)	
S1311103	Option Group 103, 81, 99, Property Management System Interface (RT)	
S1311105	Option Group 105, Line Load Control (RT)	
S1311107	Option Group 107, Malicious Call Trace (RT)	
S1311108	Option Group 108, Internal CDR (RT)	
S1311109	Option Group 109, Auxiliary Processor Link (RT)	
S1311110	Option Group 110, Trunk Verification From a Station (RT)	
S1311111	Option Group 111, ACD Timed Overflow (RT)	
S1311113	Option Group 113, Incoming DID Digit Conversion (RT)	
S1311115	Option Group 115, Directed Call Pickup (RT)	
S1311116	Option Group 116, ACD Priority Agents (RT)	
S1311119	Option Group 119, Enhanced Music (RT)	
S1311150	Option Group 150, Directory Number Expansion (RT)	
S1311151	Option Group 151, Expanded Call Detail Recording (RT)	
S1311153	Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (RT)	
S1311157	Option Group 157, Centrex Switch Hook Flash (RT)	
S1311170	Option Group 170, Modular Meridian Terminals (RT)	
S1311837	Complete Hospitality Package (RT)	
S1311850	Option Group 19, 50 & 51, ACD Link Software (RT)	
S1311851	Option Group 114 and 155, ACD-D/MAX Report Enhancements (RT)	
S1390001	Option Group 145 and 146, Primary Rate Access (RT)	
S1390002	Option Group 149, Inter-exchange Carrier (RT)	
S1390003	Option Group 145 and 147, ISDN Signaling Link (RT)	
S1390004	Option Group 148, Advance ISDN Features (RT)	
S1390005	Option Group 118, Calling Line ID in CDR (RT)	
S1390006	Option Group 117, Call By Call Service (RT)	
S7S11087	Option Group 87, Fast TDS (S, ST, MS, M)	
S8311087	Option Group 87, Fast TDS (LE, N, NT, RT)	
S9611087	Option Group 87, Fast TDS (VLE, XL, XN, XT)	
SERP1001	One Year On-Site Maintenance - Single Tower	
SERP1002	One Year On-Site Maintenance - Dual Tower	
SERP1003	One-Year On-Site Maintenance - Network Administration Center	
SERV0001	ACD-D Auxiliary Processor Software Service Transaction Fee	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SERV0007	Meridian Link Software Service Transaction Fee	
SERV0018	Meridian IVR Software Service Transaction Fee	
SERV0025	Expedite Fee for Same Day Shipment	
SERV0030	Meridian Administration Tools Software Service Transaction Fee	
SERV0041	MTE Release 7 Transaction Upgrade Fee	
SERV0042	XIOX $100000 Remote Access Warranty	
SERV0064	Meridian 1 TAPI Server Release 1 Software Service Transaction Fee	
SERV0065	Meridian 1 TAPI Server Release 1 with IVR/Networking Option Software Service Transaction Fee	
SERV3001	Consulting Services (Telephone Support) 1 hour	
SERV3002	Consulting Services (On Site) 1 day	
SV000019	MAS Server Installation and Setup	
SV000021	Messenger 4.0: Installation and Administration and User Training, On-site	
SV000022	Assistant 1.0 Administration and User Training	
SV000023	Assistant 1.0 MAS Installation and Administration and User Training	
SV000069	Messenger and Assistant Install	
SV000072	Installation Upgrade for Visit Messenger 1.0 /1.1 to Visit Messenger 2.0	
SV000073	NTS 1st Year Software Support	
SV000074	NTS Additional One Year for Telephone Software Support	
SV000113	Assistant Post Warranty Phone 8-5	
SV000114	Assistant Post Warranty Phone 7x24	
SV000115	Assistant Installation Phone Support	
SV000118	SYMPOSIUM Call Center Assessment (Mini)	
SV000119	SYMPOSIUM Call Center Assessment (Full)	
SV000120	SYMPOSIUM Call Center Migration Plan	
SV000121	SYMPOSIUM Solution Orientation and Script Design	
SV000122	SYMPOSIUM Script Implementation, Validation and Testing	
SV000123	SYMPOSIUM System Administration Training	
SV000124	SYMPOSIUM Semi-Annual Re-Evaluation	
SV000143	Remote Agent Install PREP	
SV000144	Remote Agent Installation PRO	
SV000145	Remote Agent One Year Support	
SV000281	Ide@Room INSTALL PRO (Hardware and Software)	
SV000282	Ide@Room INSTALL PREP (Hardware and Software)	
SV000283	Ide@Room On-Site Service (Hardware and Software)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SV000284	Ide@Room Telephone Support (Hardware and Software)	
SV000285	Ide@Room Software Only INSTALL PRO	
SV000286	Ide@Room Software Only INSTALL PREP	
SV000287	Ide@Room Software Only Telephone Support	
SV000384	Voice Activated Business Directory Professional Services	
SVC0002	Meridian 1 Security Audit 401 to 800 lines	
SVC0003	Meridian 1 Security Audit 801 to 1200 lines	
SVC0004	Meridian 1 Security Audit 1201 to 2500 lines	
SVC0005	Meridian 1 Security Audit-Meridian Mail Option Additional charges for individual mailbox review (per mailbox)	
SVC0006	Meridian 1 Security Audit Additional charge for database downloading (per hour)	
SVC0009	Meridian 1 Security Audit 2501 + lines	
SVC1001	Telephony Services INSTALL-PRO	
SVC1003	Telephony Services INSTALL-PREP	
SVC1004	Standard Telephony Services Software Support	SV000074
SVC1007	TAPI Server INSTALL-PRO	SV000089
SVC1008	TAPI Server INSTALL-PREP	SV000088
SVC1009	TAPI Server Software Support	SV000090
SVC1017	Remote Agent Install Prep	SV000143
SVC1018	Remote Agent 1 Year Support	SV000145
SVC1019	Remote Agent Installation PRO	SV000144
SVC1101	VISIT FastCall Remote Installation Support	
SW0000A	Meridian Base Software	SW0000C
SW0000B	Meridian Base Software	SW0000C
SW0000D	Meridian 1 Release 18 Base Software	SW0000E
SW0000F	Meridian 1 Release 20 Base Software	
SW0002A	Administrative Enhancements	
SW0023A	Authorization Code	
SW0027A	CDR - Link	
SW0029A	Advanced Hospitality Features	SW0029B
SW0035A	Station Camp-On	
SW0052B	Private ISDN Networking	
SW0052C	Private ISDN Networking	SW0052D
SW0058A	Meridian MAX Release 8 System Software Migration from Meridian MAX-SNN to Meridian MAX-SNNE	NTJH12AA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW0059A	Network Message Services	SW0059B
SW0061A	Advanced Hospitality/PMSI	
SW0065A	Meridian MAX Release 7 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade	NTJH01EA
SW0066A	Meridian MAX R8 System Software Migration from Meridian MAX-IPE or IPEE (Fundamental) to Meridian MAX-SNNE (Fundamental)	NTJH12BA
SW0067A	Meridian MAX Release 7 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade	NTJH02EA
SW0068A	Meridian MAX Release 8 Sys. Software Migration from Meridian MAX-IPE or IPEE (Enhanced) to Meridian MAX-SNNE (Enhanced)	NTJH12CA
SW0069A	Meridian MAX Release 8 System Software Migration from Meridian MAX-IPE or IPEE (Virtual) to Meridian MAX-SNNE (Virtual)	NTJH12DA
SW0070A	Meridian MAX Release 5 Base Software (200 Agents)	SW0070B
SW0070B	Meridian MAX Release 6 Base Software for new Systems (includes 200 Agents)	SW0090A
SW0070B	Meridian MAX Release 6 Base Software for new Systems (includes 200 Agents)	SW0091A
SW0070B	Meridian MAX Release 6 Base Software for new Systems (includes 200 Agents)	SW0092A
SW0075A	Meridian MAX Release 5 Base Software Upgrade (200 Agents)	SW0082A
SW0075A	Meridian MAX Release 5 Base Software Upgrade (200 Agents)	SW0083A
SW0076A	Customer Controlled Routing Conversion Software Kit	
SW0076B	Customer Controlled Routing Conversion Software Kit with 240 Active Associations	
SW0077A	Meridian Link ISDN/AP Conversion Software Kit	
SW0078A	Meridian Link X.25 Conversion Software Kit	
SW0078B	Meridian Link Release X.25 Conversion Software Kit	
SW0079A	Meridian MAX Release 5 Software Upgrade, PDP	SW0084A
SW0080A	Meridian MAX Release 5 Single Module Software Upgrade (160 Agents)	SW0085A
SW0080A	Meridian MAX Release 5 Single Module Software Upgrade (160 Agents)	SW0086A
SW0082A	Meridian MAX Release 4 to 6 Base Software Upgrade (200 Agents)	SW0084B
SW0082B	Meridian MAX Release 6 to MAX-SNN Release 7 Software Upgrade	
SW0082C	Meridian MAX Release 6 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade	NTJH01CA
SW0082C	Meridian MAX Release 6 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade	NTJH01DA
SW0083B	Meridian MAX Release 5 to MAX-SNN Release 7 Software Upgrade	
SW0083C	Meridian MAX Release 5 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade	NTJH01DA
SW0084A	Meridian MAX Release 6 Software Upgrade from a PDP System	SW0350A
SW0084B	Meridian MAX Release 3,4 to MAX-SNN Release 7 Software Upgrade	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW0084C	Meridian MAX Release 3 or 4 to Meridian MAX-SNNE Release 8 Software Upgrade	NTJH01CA
SW0085B	ACD-MAX to Meridian MAX-SNN Release 7 Software Upgrade	
SW0085C	ACD-MAX to Meridian MAX-SNNE Release 8 Software Upgrade	NTJH01BA
SW0088A	Meridian MAX Release 6 to MAX-IPE Release 7 Software Upgrade	
SW0088B	Meridian MAX Release 6 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade	NTJH02DA
SW0089A	Meridian MAX Release 5 to MAX-IPE Release 7 Software Upgrade	
SW0089B	Meridian MAX Release 4.62 or 5 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade	NTJH02DA
SW0090A	Meridian MAX-SNN Release 7 Fundamental Software	
SW0090B	Meridian MAX-SNNE Release 8 Fundamental Software	NTJH10AA
SW0091A	Meridian MAX-SNN Release 7 Enhanced	
SW0091B	Meridian MAX-SNNE Release 8 Enhanced Software	NTJH10BA
SW0092A	Meridian MAX-SNN Release 7 Virtual Software with FastView+	
SW0092B	Meridian MAX-SNNE Release 8 Virtual Software	NTJH10CA
SW0095A	Meridian MAX Release 3 or 4 to Meridian MAX-IPE Release 7 Software Upgrade	
SW0095B	Meridian MAX Release 3 or 4 to Meridian MAX-IPEE Release 8 Software Upgrade	NTJH02CA
SW0099A	ACD-MAX to Meridian MAX-IPE Release 7 Upgrade	
SW0099B	ACD-MAX to Meridian MAX-IPEE Release 8 Software Upgrade	NTJH02BA
SW0101A	Basic Rate Interface	
SW0201A	Basic ACD Features (ACD A)	SW0201B
SW0202A	Advanced ACD Features (ACD B)	SW0202C
SW0202B	Advanced Features	SW0202C
SW0203A	ACD Reports (ACD C1)	SW0203B
SW0221A	ACD/Message Processing	
SW0225A	Enhanced Call Center Routing	
SW0229B	Meridian 911	SW0229C
SW0300A	Basic ISDN Features	SW0300C
SW0300B	Basic ISDN Features	SW0300C
SW0303A	Advanced ISDN Features	SW0303B
SW0304A	Inter-Exchange Carrier	SW0304B
SW0350A	ACD-D to Meridian MAX-SNN Release 7 Software Upgrade	
SW0350B	ACD-D to Meridian MAX-SNNE Release 8 Software Upgrade	NTJH01AA
SW0351A	ACD-D to Meridian MAX-IPE Release 7 Software Upgrade	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW0351B	ACD-D to Meridian MAX-IPEE Release 8 Software Upgrade	NTJH02AA
SW0403B	Meridian Mail Features	
SW0404A	Meridian Link	SW0406C
SW0405A	Meridian Link - ISDN/AP	SW0405B
SW0405B	Meridian Link ISDN/AP	SW0251A
SW0406A	Meridian Link - Server	
SW0406B	Meridian Link Module Software	SW0406C
SW1001A	Meridian Manager Version 2.4	
SW1003A	Station Administration Version Update	
SW1004A	Station Administration 1.2 to 1.3 Upgrade for Enhancements	
SW1005A	Meridian Manager CPU Upgrade	
SW1006A	Station Administration	
SW1007A	Station Administration	
SW1008A	Station Administration	
SW1009A	Traffic Reporting	
SW1010A	Traffic Reporting	
SW1011A	Traffic Reporting	
SW1012A	Traffic Reporting Version Update	
SW1013A	Traffic Reporting Version 1.4 to 1.5 Upgrade	
SW1014A	Work Order Systems	
SW1015A	Work Order Systems	
SW1016A	Work Order Systems	
SW1020A	Meridian Manager Version 2.4	
SW1021A	Meridian Manager Version 2.4	
SW1022A	Meridian Manager Version 2.4	
SW1023A	Meridian Manager Version 2.4	
SW1024A	Meridian Manager Version 2.4	
SW1025A	Meridian Manager Version 2.4	
SW1026A	Meridian Manager Version 2.4	
SW1027A	Meridian Manager Version 2.4	
SW1028A	Meridian Manager Version 2.4	
SW1029A	Work Order System Version Update	
SW1030A	Meridian Manager Version 2.4	
SW1031A	Meridian Manager Version 2.4	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW1032A	Meridian Manager Version 2.4	
SW1033A	Station Administration Version 2.4	
SW1034A	Traffic Reporting Version 2.4	
SW1035A	Work Order System Version 2.4	
SW1036A	Multi-Site Reconfiguration	
SW1038	XIOX Hacker Tracker	
SW1101A	General Business Software (Add. 100 TNs)	
SW1102A	Enhanced Business Software (Add. 100 TNs)	
SW1103A	Private Networking Software (Add. 100 TNs)	
SW1104A	Advanced Applications Software (Add. 100 TNs)	
SW1111A	General Business Software Update	
SW1112A	Enhanced Business Software Update	
SW1113A	Private Networking Software Update	
SW1114A	Advanced Applications Software Update	
SW1121A	General Business Software (Add. 100 TNs)	
SW1121B	General Business Software (Add. 100 TNs)	
SW1121C	General Business Software (Add. 100 TNs)	SW1121E
SW1122A	Enhanced Business Software (Add. 100 TNs)	
SW1122B	Enhanced Business Software (Add. 100 TNs)	
SW1122C	Enhanced Business Software (Add. 100 TNs)	SW1122E
SW1123A	Private Networking Software (Add. 100 TNs)	
SW1124A	Advanced Applications Software (Add. 100 TNs)	
SW1126A	Enterprise Business Software (Add. 100 TNs)	
SW1126B	Enterprise Business Software (Add. 100 TNs)	SW1126D
SW1127A	NAS Software (Add. 100 TNs)	
SW1127B	NAS Software (Add. 100 TNs)	SW1127D
SW1131A	General Business Software Update	
SW1131B	General Business Software Update	SW1131C
SW1131C	General Business Software Update	SW1131E
SW1132A	Enhanced Business Software Update	
SW1132B	Enhanced Business Software Update	SW1132C
SW1132C	Enhanced Business Software Update	SW1132E
SW1133A	Private Networking Software Update	
SW1134A	Advanced Applications Software Update	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW1136A	General Business (no DISA) Software Update	
SW1137A	Enhanced Business (no DISA) Software Update	
SW1138A	Private Networking (no DISA) Software Update	
SW1141A	Enterprise Business Software Update	SW1141B
SW1141B	Enterprise Business Software Update	SW1141D
SW1142A	NAS Software Update	SW1142B
SW1142B	NAS Software Update	SW1142D
SW7000	Meridian Mail Base Software	
SW7000A	Meridian Mail Base Software (Rel. 5)	SW7000C
SW7000B	Meridian Mail Base Software (Rel. 6)	SW7000D
SW7000C	Meridian Mail Base Software (Rel. 7)	SW7000D
SW7000D	Meridian Mail Release 8 Base Software	SW7000E
SW7000E	Meridian Mail Release 9 Base Software	SW7000F
SW7000F	Meridian Mail Release 10 Base Software	SW7000G
SW7000G	Meridian Mail Release 11 Base Software	SW7000H
SW7000H	Meridian Mail Release 12 Base Software	
SW7001	Meridian Mail 5 Hour Base Software	
SW7002	Meridian Mail 5 to 11 Hours Software	U7207
SW7002	Meridian Mail 5 to 11 Hours Software	U7209
SW7003	Meridian Mail Expanded Storage Software	SW7051
SW7004	Hospitality Voice Services Software	SW7004B
SW7004A	Hospitality Voice Services Software, Release 11	SW7004B
SW7005	Voice Menus Software	SW7000D
SW7008A	Network Message Services Prime Site Software, Release 11	SW7008B
SW7009	AdminPlus Enable Software	SW7009A
SW7009	AdminPlus Enable Software	SW7009B
SW7009	AdminPlus Enable Software	SW7009C
SW7009A	Meridian Mail AdminPlus Enable Software, Release 7	SW7009B
SW7009A	Meridian Mail AdminPlus Enable Software, Release 7	SW7009C
SW7009B	Meridian Mail AdminPlus Enable Software, Release 8	SW7009D
SW7009C	Meridian Mail AdminPlus Enable Software, Release 9	SW7009D
SW7010	Meridian Mail Networking	SW7010B
SW7010A	Meridian Mail Networking / Enterprise Networking, Release 11	SW7010B
SW7011B	EuroFrench Prompt - Bilingual	63023

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7011B	EuroFrench Prompt - Bilingual	SW7023
SW7011U	EuroFrench Prompt - Unilingual	63023
SW7011U	EuroFrench Prompt - Unilingual	SW7023
SW7012B	Mandarin Prompt - Bilingual	63023
SW7012B	Mandarin Prompt - Bilingual	SW7023
SW7012U	Mandarin Prompt - Unilingual	63023
SW7012U	Mandarin Prompt - Unilingual	SW7023
SW7013B	Japanese Prompt - Bilingual	63023
SW7013B	Japanese Prompt - Bilingual	SW7023
SW7013U	Japanese Prompt - Unilingual	63023
SW7013U	Japanese Prompt - Unilingual	SW7023
SW7014B	Canadian French Prompt - Bilingual	63023
SW7014B	Canadian French Prompt - Bilingual	SW7023
SW7014U	Canadian French Prompt - Unilingual	63023
SW7014U	Canadian French Prompt - Unilingual	SW7023
SW7015B	Swedish Prompt - Bilingual	63023
SW7015B	Swedish Prompt - Bilingual	SW7023
SW7015U	Swedish Prompt - Unilingual	63023
SW7015U	Swedish Prompt - Unilingual	SW7023
SW7016B	Norwegian Prompt - Bilingual	63023
SW7016B	Norwegian Prompt - Bilingual	SW7023
SW7016U	Norwegian Prompt	63023
SW7016U	Norwegian Prompt	SW7023
SW7017B	Italian Prompt - Bilingual	63023
SW7017B	Italian Prompt - Bilingual	SW7023
SW7017U	Italian Prompt - Unilingual	63023
SW7017U	Italian Prompt - Unilingual	SW7023
SW7018B	Korean Prompt - Bilingual	63023
SW7018B	Korean Prompt - Bilingual	SW7023
SW7018U	Korean Prompt - Unilingual	63023
SW7018U	Korean Prompt - Unilingual	SW7023
SW7019B	Latin American Spanish Prompt - Bilingual	63023
SW7019B	Latin American Spanish Prompt - Bilingual	SW7023
SW7019U	Latin American Spanish Prompt - Unilingual	63023

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7019U	Latin American Spanish Prompt - Unilingual	SW7023
SW7020B	British English Male Prompt - Biligual	63023
SW7020B	British English Male Prompt - Biligual	SW7023
SW7020U	British English Male Prompt - Unilingual	63023
SW7020U	British English Male Prompt - Unilingual	SW7023
SW7021B	British English Female Prompt - Bilingual	63023
SW7021B	British English Female Prompt - Bilingual	SW7023
SW7021U	British English Female Prompt - Unilingual	63023
SW7021U	British English Female Prompt - Unilingual	SW7023
SW7022B	German Prompt - Bilingual	63023
SW7022B	German Prompt - Bilingual	SW7023
SW7022U	German Prompt - Unilingual	63023
SW7022U	German Prompt - Unilingual	SW7023
SW7023B	EuroSpanish Prompt-Bilingual	
SW7023U	EuroSpanish Prompt-Unilingual	
SW7024B	Dutch Prompt-Bilingual	
SW7024U	Dutch Prompt-Unilingual	
SW7025B	Finnish Prompt-Bilingual	
SW7025U	Finnish Prompt-Unilingual	
SW7026B	Taiwan-Mandarin Prompt-Bilingual	
SW7026U	Taiwan-Mandarin Prompt-Unilingual	
SW7028B	Portuguese Prompt-Bilingual	
SW7028U	Portuguese Prompt-Unilingual	
SW7029B	Arabic Prompt-Bilingual	
SW7029U	Arabic Prompt-Unilingual	
SW7030	Meridian Mail Access Enable Option	SW7030A
SW7030	Meridian Mail Access Enable Option	SW7030B
SW7030	Meridian Mail Access Enable Option	SW7030C
SW7030A	Meridian Mail ACCESS Enable Option, Release 7	SW7030B
SW7030A	Meridian Mail ACCESS Enable Option, Release 7	SW7030C
SW7030B	Meridian Mail ACCESS Enable Option, Release 8	SW7030E
SW7030C	Meridian Mail ACCESS Enable Option, Release 9	SW7030E
SW7030D	Meridian Mail ACCESS Enable Option, Release 10 & 11	SW7030E
SW7035	Meridian Mail AMIS Networking (Virtual Node)	SW7035C

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7035A	Meridian Mail AMIS Networking (Virtual Node), Release 11	SW7035C
SW7035B	Danish Prompt-Bilingual	
SW7035U	Danish Prompt-Unilingual	
SW7040	Meridian Voice Forms	SW7040B
SW7040B	Meridian Mail Voice Forms, Release 8	SW7040D
SW7040C	Meridian Mail Voice Forms	SW7040D
SW7041	Meridian Mail Multi-Customer	SW7041B
SW7041B	Meridian Mail Multi-Customer, Release 8	SW7041G
SW7041C	Meridian Mail Multi-Customer, Release 9	SW7041G
SW7041D	Meridian Mail Multi-Customer, Release 10	
SW7041E	Meridian Mail Multi-Customer, Release 11	SW7041G
SW7041F	Meridian Mail Multi-Customer (GP), Release 11	SW7041G
SW7042	Meridian Mail AMIS Open Networking	SW7042B
SW7042A	Meridian Mail AMIS Open Networking, Release 11	SW7042B
SW7044	Meridian Mail Reporter Single Site PC Software Package	SW7066
SW7045	Card Option Expanded Storage Level 1-2	
SW7046	Card Option Expanded Storage Level 2-3	
SW7047	Meridian Mail Reporter Multiple Site PC Software Package	SW7067
SW7051	Meridian Mail Expanded Storage Software Level 1-2	SW7049
SW7052	Meridian Mail Expanded Storage Software Level 2-3	SW7054
SW7052	Meridian Mail Expanded Storage Software Level 2-3	SW7055
SW7052	Meridian Mail Expanded Storage Software Level 2-3	SW7056
SW7053	Multi-SMDI Software	
SW7057	Meridian Mail Fax on Demand Software	SW7057B
SW7057A	Meridian Mail Fax on Demand, Release 11	SW7057B
SW7066	Meridian Mail Reporter 2.0 Single Site PC Software Package	AS7104
SW7066	Meridian Mail Reporter 2.0 Single Site PC Software Package	AS7106
SW7067	Meridian Mail Reporter 2.0 Multiple Site PC Software Package	AS7105
SW7067	Meridian Mail Reporter 2.0 Multiple Site PC Software Package	AS7107
SW7070	Meridian Mail VMUIF	SW7072
SW7100D	Meridian Mail Card Option Release 8 Base Software	SW7100E
SW7100E	Meridian Mail Card Option Release 9 Base Software	SW7100F
SW7100F	Meridian Mail Card Option Release 10 Base Software	SW7100G
SW7100G	Meridian Mail Card Option Release 11 Base Software	SW7100H

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7100H	Meridian Mail Card Option Release 12 Base Software	
SW7101A	ACD D Application Software	
SW7104	Meridian Mail Option 11 Fax on Demand Software, Release 9, 10	SW7104B
SW7104A	Meridian Mail Option 11 Fax on Demand Software, Release 11	SW7104B
SW7111	Meridian Mail Option 11 HVS Software	SW7111B
SW7111A	Meridian Mail Option 11 HVS Software, Release 11	SW7111B
SW7112	Meridian Mail Option 11 Networking Software	SW7112B
SW7112A	Meridian Mail Option 11 Networking/Enterprise Networking Software, Release 11	SW7112B
SW7113	Meridian Mail Card Option Voice Forms	SW7113B
SW7113B	Meridian Mail Card Option Voice Forms Software, Release 8	SW7113D
SW7113C	Meridian Mail Option 11 Voice Forms Software, Release 9-11	SW7113D
SW7114	Meridian Mail Card Option Multi-Customer	SW7114B
SW7114B	Meridian Mail Card Option Multi-Customer, Release 8	SW7114F
SW7114C	Meridian Mail Card Option Multi-Customer, Release 9	SW7114F
SW7114D	Meridian Mail Option 11 Multi-Customer, Release 10	SW7114F
SW7114E	Meridian Mail Option 11 Multi-Customer, Release 11	SW7114F
SW7115	Meridian Mail Option 11 AMIS Networking	SW7115B
SW7115A	Meridian Mail Option 11 AMIS Networking, Release 11	SW7115B
SW7116B	Meridian Mail Card Option Network Message Service Software, Release 8	SW7116
SW7117	Meridian Mail Card Option ACCESS Enable Option, Release 9	SW7117C
SW7117B	Meridian Mail Option 11 ACCESS Enable Option, Release 10 & 11	SW7117C
SW7120	Meridian Mail VMUIF, Option 11	SW7122
SW7200	Meridian IVR Run-Time Base Software (12 Ports)	
SW7201	Meridian IVR Run-Time 4 Port Expansion Software	
SW7202	Meridian IVR Development Base Software (12 Ports)	
SW7203	Meridian IVR Development 4 Port Expansion Software (12 Ports)	
SW7204	Meridian IVR Run-Time to Development Upgrade Software (12 Ports)	
SW7205	Meridian IVR Run-Time to Development Upgrade Software (4 Ports)	
SW7206	3270 SDLC Data Communications Software	
SW7207	3270 BSC Data Communications Software	
SW7208	X.25 Data Communications Software	
SW7209	Basic Port License	
SW7211	IVR 2.0 Application Development Software	
SW7212	Call Center Integration Package (CCIP)-M1 Connectivity Option-4 Port Base	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7213	Call Center Integration Package (CCIP)-M1 Connectivity Option 4 Port Increment	
SW7220	PowerView Banking DTMF Remote Banking - ADMS	
SW7221	PowerView Banking DTMF Bill Payment - ADMS	
SW7222	PowerView Banking ADSI Remote Banking - ADMS	
SW7223	PowerView Banking ADSI Bill Payment - ADMS	
SW7224	PowerView Banking Full Package - ADMS	
SW7301A	ISDN/AP Pass Through Service 95	SW7301B
SW7301B	Meridian Link ISDN/AP Pass Through (For DEC)	
SW7301C	Meridian Link Release 3 ISDN/AP Pass Through Software	SW7301D
SW7301D	Meridian Link Release 4 ISDN/AP Pass Through Software	
SW7302A	In-Bound Call Management Service 97	SW7305B
SW7303A	Out-Bound Call Management Service 98	SW7305B
SW7304A	Link O, A&M Service 1	
SW7305B	Meridian Link X.25 (For IBM, HP, and Tandem)	
SW7305C	Meridian Link Release 3 X.25 Software	SW7305D
SW7305D	Meridian Link Release 4 X.25 Software	
SW7307	Meridian Link Release 4B X.25 Software	
SW7401	ACD MAX Base Software Single to Dual Tower Upgrade	
SW7402	Configuration Control Option - Single to Dual Tower Upgrade	
SW7403	Custom Calculator Option - Single to Dual Tower Upgrade	
SW7404	ACD MAX Networking Option - Single to Dual Tower Upgrade	
SW7410	Customer Controlled Routing Software and Documentation Package	SW7411
SW7411	Customer Controlled Routing Release 3 Software and Documentation Package	
SW7412	Customer Controlled Routing Release 2 to Release 3 Software Upgrade	
SW7413	Customer Controlled Routing Release 3B with 240 Active Associations Software and Documentation Package	SW7413A
SW7414	Customer Controlled Routing Release 3B with twenty (20) Active Scripts Software Documentation Package	SW7414A
SW7415	Customer Controlled Routing Release 3B from 20 to 240 Active Scripts Software Upgrade Package	SW7415A
SW7416	Customer Controlled Routing Release 3B with 240 Active Associations Software Upgrade Package	SW7416A
SW7421	ACD MAX Customer Controlled Routing Support and Reporting Option - Single or Dual Tower	
SW7422	ACD MAX Release 4 Software Upgrade - Single Tower (ACD MAX Release 3 or below to Release 4)	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7423	ACD MAX Release 4 Software Upgrade - Dual Tower (ACD MAX Release 3 or below to Release 4)	
SW7424	ACD MAX Release 4 - Network Administration Center Connectivity	
SW7460	Meridian Link & CCR Co-Resident Software	
SW7461	Meridian Link & CCR Co-Resident Software	
SW7501	Meridian MAX Option 1 Software	
SW7501A	Meridian MAX Release 4 Option 1 Software	
SW7502	Meridian MAX Option 2 Software	
SW7502A	Meridian MAX Release 4 Option 2 Software	
SW7503	Meridian MAX Option 3 Software	
SW7503A	Meridian MAX Release 4 Option 3 Software	
SW7504	pnridian MAX Option 4 Software	
SW7504A	Meridian MAX Release 4 Option 4 Software	
SW7505	Meridian MAX Networking for Option 1 & 2	
SW7505A	Meridian MAX Networking for Release 4, Option 1 & 2	
SW7506	Meridian MAX Networking for Option 3 & 4	
SW7506A	Meridian MAX Networking for Release 4, Option 3 & 4	
SW7507	Meridian MAX Networking Expansion	
SW7507A	Meridian MAX Networking Option 1/2 to Option 3/4 Software Expansion	SW0081A
SW7510A	Meridian MAX-IPE Base Software	SW7510B
SW7510B	Meridian MAX-IPE Release 5 Base Software	SW7510C
SW7510C	Meridian MAX-IPE Release 6 Base Software for new systems	SW7520A
SW7510C	Meridian MAX-IPE Release 6 Base Software for new systems	SW7521A
SW7510C	Meridian MAX-IPE Release 6 Base Software for new systems	SW7522A
SW7511A	Meridian MAX-IPE 20 Agent Software Increment for Release 4	
SW7512	Meridian MAX Option 1 to Option 2 Software Expansion	
SW7512A	Meridian MAX Release 4 Option 1 to Option 2 Software Expansion	
SW7514A	Meridian MAX-IPE Release 5 Base Software Upgrade	SW7514B
SW7520A	Meridian MAX-IPE Release 7 Fundamental Software	
SW7520B	Meridian MAX-IPEE Release 8 Fundamental Software	NTJH11AA
SW7521A	Meridian MAX-IPE Release 7 Enhanced Software	
SW7521B	Meridian MAX-IPEE Release 8 Enhanced Software	NTJH11BA
SW7522A	Meridian MAX-IPE Release 7 Virtual Software with FastView+	
SW7522B	Meridian MAX-IPEE Release 8 Virtual Software	NTJH11CA
SW7523	Meridian MAX Option 2 to Option 3 Software Expansion	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SW7523A	Meridian MAX Release 4 Option 2 to Option 3 Software Expansion	
SW7524A	Meridian MAX 1000 Agent Software for Release 4	
SW7525A	NAC (Release 1) Connectivity Enabler for Meridian MAX	
SW7534	101292an MAX Option 3 to Option 4 Software Expansion	
SW7534A	Meridian MAX Release 4 Option 3 to Option 4 Software Expansion	
SW7551A	Meridian MAX Release 3 to 4 Software Upgrade - Option 1	
SW7552A	Meridian MAX Release 3 to 4 Software Upgrade - Option 2	
SW7553A	Meridian MAX Release 3 to 4 Software Upgrade - Option 3	
SW7554A	Meridian MAX Release 3 to 4 Software Upgrade - Option 4	
SW7700F	EC11 Base System Software Initial Caps	SW7700G
SW7700G	Meridian Mail EC11 Base Software, Release 11	SW7700H
SW7700H	Meridian Mail EC11 Base Software, Release 12	
SY0070A	Meridian MAX-SNN System Hardware, AC Power	
SY0070D	Meridian MAX-SNN System Hardware, DC Power	
SY0073A	Meridian MAX-SNNE System Hardware, AC Power	NTJH15FA
SY0073D	Meridian MAX-SNNE System Hardware, DC Power	NTJH15EA
SY1001A	Meridian 1 System Option 21 AC	SY1011A
SY1001D	Meridian 1 System Option 21 DC	SY1011D
SY1001R	Meridian 1 System Option 21 DC with Rectifiers	
SY1002A	Meridian 1 System Option 21 + IPE Module AC	SY1012A
SY1002D	Meridian 1 System Option 21 + IPE Module DC	SY1012D
SY1002R	Meridian 1 System Option 21 + IPE Module DC with Rectifiers	
SY1003A	Meridian 1 System Option 51 AC	SY1012A
SY1003D	Meridian 1 System Option 51 DC	SY1012D
SY1003R	Meridian 1 System Option 51 DC with Rectifiers	
SY1004A	Meridian 1 System Option 61 AC	SY1013A
SY1004D	Meridian 1 System Option 61 DC	SY1013D
SY1004R	Meridian 1 System Option 61 DC with Rectifiers	
SY1005A	Meridian 1 System Option 71 AC	SY1014A
SY1005D	Meridian 1 System Option 71 DC	SY1014D
SY1005R	Meridian 1 System Option 71 DC with Rectifiers	AS1100D
SY1005R	Meridian 1 System Option 71 DC with Rectifiers	SY1005D
SY1006A	Meridian 1 System Option 21A AC	
SY1007	Option 11 System Package AC/DC	SY1107

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SY1008	Option 11 System Package DC/DC	SY1108
SY1011A	Meridian 1 Option 21E System Package AC	
SY1011D	Meridian 1 Option 21E System Package DC	
SY1012A	Meridian 1 Option 51 System Package AC	
SY1012D	Meridian 1 Option 51 System Package DC	
SY1013A	Meridian 1 Option 61 System Package AC	
SY1013D	Meridian 1 Option 61 System Package DC	
SY1014A	Meridian 1 Option 71 Package AC	SY1015A
SY1014D	Meridian 1 Option 71 Package DC	SY1015D
SY1015A	Meridian 1 Option 81 System Package AC	SY1025A
SY1015D	Meridian 1 Option 81 System Package DC	SY1025D
SY1107	Option 11E System Package AC/DC	
SY1108	Option 11E System Package DC/DC	
SY1151	Meridian 1 ST System Package	SY1003R
SY1152	Meridian 1 RT System Package	SY1004R
SY1153	Meridian 1 NT System Package	SY1004R
SY1154	Meridian 1 XT System Package	SY1005R
SY1200A	Meridian Link Module Package AC	SY7411A
SY1200D	Meridian Link Module Package DC	SY7411D
SY1220	Meridian Link & CCR-IPE Module (Option 11)	SY1222
SY1221	Meridian Link & CCR-IPE Module (Option 21-81)	SY1223
SY7000A	Meridian Mail Modular Option Package 4 Ports 5/11 Hours AC	SY7001A
SY7000D	Meridian Mail Modular Option Package 4 Ports 5/11 Hours DC	SY7001D
SY7001A	Meridian Mail Modular Option Package 4 Ports, 11/24 Hours AC	SY7010A
SY7001D	Meridian Mail Modular Option Package 4 Ports 11/24 Hours DC	SY7010D
SY7002A	Meridian Mail Modular Option Package 4 Ports 36/54 Hours AC	SY7011A
SY7002D	Meridian Mail Modular Option Package 4 Ports 36/54 Hours DC	SY7011D
SY7003A	Meridian Mail Modular Option Package 24 Ports 45/90 Hours AC	SY7012A
SY7003D	Meridian Mail Modular Option Package 24 Ports 45/90 Hours DC	SY7012D
SY7004A	Meridian Mail Modular Option Package 24 Ports 120/180 Hours AC	SY7013A
SY7004D	Meridian Mail Modular Option Package 24 Ports 120/180 Hours DC	SY7013D
SY7005A	Meridian Mail Modular Option Package 16 Ports 26/54 Hours AC	SY7012A
SY7005D	Meridian Mail Modular Option Package 16 Ports 26/54 Hours DC	SY7012D
SY7006A	Meridian Mail Modular Option Package 16 Ports 84/114 Hours AC	SY7013A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SY7006D	Meridian Mail Modular Option Package 16 Ports 84/114 Hours DC	SY7013D
SY7007A	Meridian Mail Modular Option Package 40 Ports 60/120 Hours AC	SY7016A
SY7007D	Meridian Mail Modular Option Package 40 Ports 60/120 Hours DC	SY7016D
SY7008A	Meridian Mail Modular Option Package 40 Ports 180/240 Hours AC	SY7017A
SY7008D	Meridian Mail Modular Option Package 40 Ports 180/240 Hours DC	SY7017D
SY7010A	Meridian Mail Modular EC 4-12 Port 11/24 Hours Package AC	SY7020A
SY7010D	Meridian Mail Modular EC 4-12 Port 11/24 Hours Package DC	SY7020D
SY7011A	Meridian Mail Modular EC 4-12 Port 24/54/100 Hours Package AC	SY7020A
SY7011D	Meridian Mail Modular EC 4-12 Port 24/54/100 Hours Package DC	SY7020D
SY7012A	Meridian Mail Modular EC 16-24 Port 26/54 Hours Package AC	SY7021A
SY7012D	Meridian Mail Modular EC 16-24 Port 26/54 Hours Package DC	SY7021D
SY7013A	Meridian Mail Modular EC 16-24 Port 54/114/200 Hours Package AC	SY7021A
SY7013D	Meridian Mail Modular EC 16-24 Port 54/114/200 Hours Package DC	SY7021D
SY7014A	Meridian Mail Modular EC 28-32 Port 30/60 Hours Package AC	SY7022A
SY7014D	Meridian Mail Modular EC 28-32 Port 30/60 Hours Package DC	SY7022D
SY7015A	Meridian Mail Modular EC 28-32 Port 60/120/200 Hours Package AC	SY7022A
SY7015D	Meridian Mail Modular EC 28-32 Port 60/120/200 Hours Package DC	SY7022D
SY7016A	Meridian Mail Modular EC 36-48 Port 45/90 Hours Package AC	SY7023A
SY7016D	Meridian Mail Modular EC 36-48 Port 45/90 Hours Package DC	SY7023D
SY7017A	Meridian Mail Modular EC 36-48 Port 90/180/300 Hours Package AC	SY7023A
SY7017D	Meridian Mail Modular EC 36-48 Port 90/180/300 Hours Package DC	SY7023D
SY7018A	Meridian Mail Modular EC 52-64 Port 60/120 Hours Package AC	SY7024A
SY7018D	Meridian Mail Modular EC 52-64 Port 60/120 Hours Package DC	SY7024D
SY7019A	Meridian Mail Modular EC 52-64 Port 120/240/400 Hours Package AC	SY7024A
SY7019D	Meridian Mail Modular EC 52-64 Port 120/240/400 Hours Package DC	SY7024D
SY7060D	Meridian Mail Modular GP 4-12 Port 11/24 Hour Package DC	SY7075D
SY7061D	Meridian Mail Modular GP 4-12 Port 24/54 Hour Package DC	SY7075D
SY7062D	Meridian Mail Modular GP 16-24 Port 26/54 Hour Package DC	SY7076D
SY7063D	Meridian Mail Modular GP 16-24 Port 54/114 Hour Package DC	SY7076D
SY7064D	Meridian Mail Modular GP 28-32 Port 30/60 Hour Package DC	SY7077D
SY7065D	Meridian Mail Modular GP 28-32 Port 60/120 Hour Package DC	SY7077D
SY7066D	Meridian Mail Modular GP 36-48 Port 45/90 Hour Package DC	SY7078D
SY7067D	Meridian Mail Modular GP 36-48 Port 90/180 Hour Package DC	SY7078D
SY7068D	Meridian Mail Modular GP 52-64 Port 60/120 Hour Package DC	SY7079D

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
SY7069D	Meridian Mail Modular GP 52-64 Port 120/240 Hour Package DC	SY7079D
SY7101	Meridian Mail Card Option 2 Ports 5 Hours Package	SY7106
SY7102	Meridian Mail Card Option 4 Ports 5 Hours Package	SY7106
SY7103	Meridian Mail Card Option 4 Ports 10 Hours Package	SY7106
SY7104	Meridian Mail Card Option 6 Ports 5 Hours Package	SY7106
SY7105	Meridian Mail Card Option 6 Ports 10 Hours Package	SY7106
SY7106	Meridian Mail Card Option 2-6 Ports, 5/10/24 Hours Package, Release 8	SY7110
SY7107	Meridian Mail Card Option 8-12 Ports, 5/10/24 Hours Package, Release 8	SY7111
SY7108	Meridian Mail Card Option 2-6 Ports, 5/10/24 Hours Package, Release 9	SY7110
SY7109	Meridian Mail Card Option 8-12 Ports, 5/10/24 Hours Package, Release 9	SY7111
SY7110	Meridian Mail Card Option 2-6 Ports, 5/10/24/54 Hours Package	SY7112
SY7111	Meridian Mail Card Option 8-12 Ports, 5/10/24/54 Hours Package	
SY7112	Meridian Mail Card Option 4-6 Ports, 5/10/24/54 Hours Package	NTZC49AA
SY7201A	Meridian IVR Run-Time Hardware Package AC	
SY7201D	Meridian IVR Run-Time Hardware Package DC	
SY7202A	Meridian IVR Development Hardware Package AC	
SY7202D	Meridian IVR Development Hardware Package DC	
SY7410A	Customer Controlled Routing Hardware Package AC	SY7411A
SY7410D	Customer Controlled Routing Hardware Package DC	SY7411D
SY7411A	Meridian Link & CCR-AM Module AC	
SY7411D	Meridian Link & CCR-AM Module DC	
SY7413	Customer Controlled Routing Release 3 Spares Package	
SY7501A	Meridian MAX Option 1 Hardware Package AC	
SY7501D	Meridian MAX Option 1 Hardware Package DC	
SY7502A	Meridian MAX Option 2 Hardware Package AC	
SY7502D	Meridian MAX Option 2 Hardware Package DC	
SY7503A	Meridian MAX Option 3 Hardware Package AC	
SY7503D	Meridian MAX Option 3 Hardware Package DC	
SY7504A	Meridian MAX Option 4 Hardware Package AC	
SY7504D	Meridian MAX Option 4 Hardware Package DC	
SY7505	Meridian MAX-IPE Module (Option 11)	SY7507
SY7506	Meridian MAX-IPE Module (Option 21-81)	SY7508
SY7507	Meridian MAX-IPEE Module (Option 11)	NTJH17AA
SY7508	Meridian MAX-IPEE Module (Option 21-81C)	NTJH17BA

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U0070A	ACD-D, ACD-MAX and MAX-IPE to Meridian MAX-SNN Hardware Upgrade Package, AC Power	
U0070D	ACD-D, ACD-MAX and MAX-IPE to Meridian MAX-SNN Hardware Upgrade Package, DC Power	
U0071	Meridian MAX-SEE (Option 1,2) and MAX-DEE (Option 3,4) to Meridian MAX-SNN Hardware Upgrade Package	
U0073A	PDP-11, HP Vectra, MAX-IPE, and MAX-IPEE to Meridian MAX-SNNE Hardware Upgrade Package, AC Power	NTJH15BA
U0073D	PDP-11, HP Vectra, MAX-IPE, and MAX-IPEE to Meridian MAX-SNNE Hardware Upgrade Package, DC Power	NTJH15AA
U0074	Meridian MAX-SEE (Option 1,2) and MAX-DEE (Option 3,4) to Meridian MAX-SNNE Hardware Upgrade Package	NTJH15CA
U0075	Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade Package	NTJH15DA
U1107	Option 11E Single Cabinet Core Upgrade Package	
U1108	Option 11E Dual Cabinet Core Upgrade Package	
U7000	Meridian Mail Release 8 Hardware Upgrade Package	
U7001	Meridian Mail ST/RT Option Release 8 Tape Drive Upgrade Package	U7004
U7002	Meridian Mail Shelf (NT/XT) Option Release 8 Tape Drive Upgrade Package	U7005
U7003	Meridian Mail GP/X Cabinet Release 8 Tape Drive Upgrade Package	
U7004	Meridian Mail Options (ST/RT) Release 10 Upgrade Package	
U7005	Meridian Mail Options (NT/XT) Release 10 Upgrade Package	
U7006	Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Releases 10, 11, 12)	
U7007	Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12)	
U7010A	Meridian Mail Migration to Modular Option Prime Node, 300MB Package AC	
U7010D	Meridian Mail Migration to Modular Option Prime Node, 300MB Package DC	
U7011A	Meridian Mail Migration to Modular Option Voice Node, 300MB Package AC	
U7011D	Meridian Mail Migration to Modular Option Voice Node, 300MB Package DC	
U7012A	Meridian Mail Migration to Modular Option Prime Node, 1.0GB Package AC	
U7012D	Meridian Mail Migration to Modular Option Prime Node, 1.0GB Package DC	
U7013A	Meridian Mail Migration to Modular Option Voice Node, 1.0GB Package AC	
U7013D	Meridian Mail Migration to Modular Option Voice Node, 1.0GB Package DC	
U7060D	Meridian Mail Migration to Modular GP Prime Node, 300MB Package DC	
U7061D	Meridian Mail Migration to Modular GP Voice Node, 300MB Package DC	
U7062D	Meridian Mail Migration to Modular GP Prime Node, 1.0GB Package DC	
U7063D	Meridian Mail Migration to Modular GP Voice Node, 600MB/1.0GB Package DC	
U7064	MMP40 Upgrade, EC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U7065	MMP40 Upgrade, Option (ST/RT)	
U7066	MMP40 Upgrade, Option (NT/XT)	
U7067	MMP40 Upgrade, Modular Option, Modular Option GP	
U7100A	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	AS7000A
U7100A	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	U7010A
U7100D	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	AS7000D
U7100D	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	U7010D
U7101A	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	AS7001A
U7101A	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	U7010A
U7101D	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	AS7001D
U7101D	Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node	U7010D
U7200A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	AS7002A
U7200A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7010A
U7200A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7011A
U7200D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	AS7002D
U7200D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7010D
U7200D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7011D
U7201A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	AS7003A
U7201A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7010A
U7201A	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7011A
U7201D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	AS7003D
U7201D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7010D
U7201D	Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node	U7011D
U7205	Meridian Mail Modular 1.0GB Disk/Tape Drive Upgrade	
U7206	Meridian Mail Modular Option 300MB Disk Drive Upgrade	U7207
U7208	Meridian Mail 300MB Disk Drive Upgrade	U7209
U7209	Meridian Mail 1.0GB Disk Drive Upgrade	
U7210	Meridian Mail Card Option 1GB Disk Drive Upgrade	NTDK74AA
U7211	Meridian Mail Release 3 to Release 11 Software Migration, from Options to Modular Option	U7217
U7212	Meridian Mail Release 4 to Release 11 Software Migration, from Options to a Modular Option	U7218
U7213	Meridian Mail Modular Option Release 5 to Release 11 Upgrade or Migration from Options to Modular Option	U7219
U7214	Meridian Mail Modular Option Release 6/7 to Release 11 Upgrade or Migration from Options to Modular Option	U7220

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U7215	Meridian Mail Modular Option Release 8 to Release 11 Upgrade or Migration from Options to Modular Option	U7221
U7216	Meridian Mail Modular Option Release 9/10 to Release 11 Upgrade or Migration from Options to Modular Option	U7222
U7217	Meridian Mail Release 3 to Release 12 Software Migration, from Options to Modular Option	NTZD70EA
U7218	Meridian Mail Release 4 to Release 12 Software Migration, from Options to Modular Option	NTZD70FA
U7219	Meridian Mail Modular Option Release 5 to Release 12 Upgrade or Migration from Options to Modular Option	NTZD70AA
U7220	Meridian Mail Modular Option Release 6/7 to Release 12 Upgrade or Migration from Options to Modular Option	NTZD70BA
U7221	Meridian Mail Modular Option Release 8 to Release 12 Upgrade or Migration from Options to Modular Option	NTZD70CA
U7222	Meridian Mail Modular Option Release 9/10/11 to Release 12 Upgrade or Migration from Options to Modular Option	NTZD70DA
U7230	Meridian Mail Release 4 to Release 11 Software Migration, GP to Modular GP	U7235
U7231	Meridian Mail Modular GP Release 5 to Release 11 Upgrade or Migration from GP to Modular GP	U7236
U7232	Meridian Mail Modular GP Release 7 to Release 11 Upgrade or Migration from GP to Modular GP	U7237
U7233	Meridian Mail Modular GP Release 8 to Release 11 Upgrade or Migration from GP to Modular GP	U7238
U7234	Meridian Mail Modular GP Release 9/10 to Release 11 Upgrade or Migration from GP to Modular GP	U7239
U7235	Meridian Mail Release 4 to Release 12 Software Migration, GP to Modular GP	NTZD69AA
U7236	Meridian Mail Modular GP Release 5 to Release 12 Upgrade or Migration from GP to Modular GP	
U7237	Meridian Mail Modular GP Release 7 to Release 12 Upgrade or Migration from GP to Modular GP	NTZD69CA
U7238	Meridian Mail Modular GP Release 8 to Release 12 Upgrade or Migration from GP to Modular GP	
U7239	Meridian Mail Modular GP Release 9/10/11 to Release 12 Upgrade or Migration from GP to Modular GP	
U7240	Meridian Mail EC Release 8, 9.19 to Release 11 Upgrade	U7242
U7241	Meridian Mail EC Release 9.58 and later/Release 10 to Release 11 Upgrade	U7243
U7242	Meridian Mail EC Release 8, 9.19 to Release 12 Upgrade	NTZD68AA
U7243	Meridian Mail EC Release 9.58 and Later/Release 10/11 to Release 12 Upgrade	NTZD68BA
U7250	Meridian Mail Card Option Release 6 to Release 11 Upgrade	U7252
U7251	Meridian Mail Card Option Releases 8, 9, 10 to Release 11 Upgrade	U7253
U7252	Meridian Mail Card Option Release 6 to Release 12 Upgrade	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U7253	Meridian Mail Card Option Releases 8/9/10/11 to Release 12 Upgrade	NTZD63BA
U7260	Meridian Mail EC11 Release 10 to Release 11 Upgrade	U7261
U7261	Meridian Mail EC11 Release 10 to Release 12 Upgrade	
U7301C	Meridian Link Release 3 ISDN/AP Pass Through Software Upgrade	U7301D
U7301D	Meridian Link Release 4 ISDN/AP Pass Through Software Upgrade	
U7305C	Meridian Link Release 3 X.25 Software Upgrade	U7305D
U7305D	Meridian Link Release 4 X.25 Software Upgrade	
U7306	Meridian Link Release 4B X.25 Software Upgrade	
U7405	ACD MAX Release 4 - Single Tower Hardware Upgrade Package	
U7406	ACD MAX Release 4 - Dual Tower Hardware Upgrade Package	
U7502A	Meridian MAX Option 2 Migration Package AC	
U7502D	Meridian MAX Option 2 Migration Package DC	
U7503A	Meridian MAX Option 3 Migration Package AC	
U7503D	Meridian MAX Option 3 Migration Package DC	
U7504	Meridian IPE Application Module Conversion from Option 11 Chassis to Option 21-81 Chassis	NTJH93AA
U9100	350MB Disk Upgrade	
U9101	SL-1 A/M/MS/L/S to ST Additional Network Assembly (QCA36, QCA148	
U9105	A/M/MS/L/S/ST Upgrade Assembly	U9616
U9110	SL-1 A/M/MS/L/LE to ST Shelf Upgrade Package	
U9200	Meridian Mail SL-1 300MB Disk Upgrade	U7208
U9201	Meridian Mail 300MB Disk Upgrade	U7206
U9202	Meridian Mail 600MB Disk Upgrade	U7207
U9246	VL, VLE or XL/XN Memory Expansion Upgrade Assembly	
U9250	Meridian Mail 600MB Disk Upgrade	U7209
U9251	80 MB Disk Drive Upgrade (5 Hours Storage)	U7210
U9252	170 MB Disk Drive Upgrade (10 Hours Storage)	U7210
U9300	SL-1 N to NT Shelf Upgrade Package (QCA23 Cabinet)	
U9301	M/MS/L/LE/NT Cabinet Upgrade Assembly	
U9310	ST/RT Upgrade Assembly	
U9370	VLE/XL/XT Two Network Group Cabinet Upgrade	
U9371	LE/NT Full Network Group Cabinet Upgrade	
U9372	LE/NT Half Network Group Cabinet Upgrade	
U9373	MS/NT Shelf Upgrade Assembly	
U9374	A, S, M/ST Cabinet Upgrade Assembly	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U9375	MS/ST Shelf Upgrade Assembly	
U9400	MP Upgrade to Option X Cabinet 4 Port/11 Hours	
U9401	MP Upgrade to Option X Cabinet 8 Port/11 Hours	
U9402	MP Upgrade to Option X Cabinet 12 Port/11 Hours	
U9403	MP Upgrade to Option X Cabinet 16 Port/26 Hours	
U9404	MP Upgrade to Option X Cabinet 20 Port/26 Hours	
U9405	MP Upgrade to Option X Cabinet 24 Port/45 Hours	
U9406	MP Upgrade to Option X Cabinet 32 Port/45 Hours	
U9407	MP Upgrade to Option X Cabinet 48 Port/45 Hours	
U9410	MP Upgrade to ST/RT Option 4 Port/11 Hours	
U9411	MP Upgrade to ST/RT Option 8 Port/24 Hours	
U9412	MP Upgrade to Option Center 4 Port/11 Hours	
U9413	MP Upgrade to Option Center 8 Port/24 Hours	
U9414	MP Upgrade to Option Cantilever 4 Port/11 Hours	
U9415	MP Upgrade to Option Cantilever 8 Port/24 Hours	
U9500	SL-1 N/XN Floppy Disk Drive (5.25 In.) Upgrade Package	
U9501	SL-1 MS Floppy Disk Drive (5.25 In.) Upgrade Package	
U9502	SL-1 LE/N/VLE/XL/XN Floppy Disk Drive (5.25 In.) Upgrade Package (QCA23, QCA24 Cabinet)	
U9503	SL-1 MS to NT Shelf Upgrade Package	
U9600A	Option 21 Module Upgrade Package AC	U9632
U9600D	Option 21 Module Upgrade Package DC	U9632
U9601A	Option 51 Module Upgrade Package AC	U9624A
U9601D	Option 51 Module Upgrade Package DC	U9624D
U9602A	Option 61 Module Upgrade Package AC	U9626A
U9602D	Option 61 Module Upgrade Package DC	U9626D
U9603A	Option 71 Module Upgrade Package AC	U9637A
U9603D	Option 71 Module Upgrade Package DC	U9637D
U9604A	Option 21 Module Upgrade/Expansion Package AC	U9632
U9604D	Option 21 Module Upgrade/Expansion Package DC	U9632
U9605A	Option 51 Module Upgrade/Expansion Package AC	U9624A
U9605D	Option 51 Module Upgrade/Expansion Package DC	U9624D
U9606A	Option 61 Module Upgrade/Expansion Package AC	U9626A
U9606D	Option 61 Module Upgrade/Expansion Package DC	U9626D
U9607A	Option 71 Module Upgrade/Expansion Package AC	U9637A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U9607D	Option 71 Module Upgrade/Expansion Package DC	U9637D
U9608A	SL-1NT to Option 71 Module Upgrade Package AC	U9636A
U9608D	SL-1NT to Option 71 Module Upgrade Package DC	U9636D
U9609A	SL-1RT to Option 61 Module Upgrade Package AC	U9627A
U9609D	SL-1RT to Option 61 Module Upgrade Package DC	U9627D
U9610	SL-1RT/NT/XT Floppy Disk Drive (3.5 In.)/ROM Upgrade Package	
U9611	SL-1RT/NT/XT Multi Disk Drive (3.5 In.) w/Hard Disk Drive/ROM Upgrade	
U9612	STE/21E Multi Disk Unit and Memory Upgrade Package	U9643A
U9612	STE/21E Multi Disk Unit and Memory Upgrade Package	U9643D
U9612	STE/21E Multi Disk Unit and Memory Upgrade Package	U9644A
U9612	STE/21E Multi Disk Unit and Memory Upgrade Package	U9644D
U9613	STE from ST or 21E from 21A/21 Upgrade Package	U9643A
U9613	STE from ST or 21E from 21A/21 Upgrade Package	U9643D
U9613	STE from ST or 21E from 21A/21 Upgrade Package	U9644A
U9613	STE from ST or 21E from 21A/21 Upgrade Package	U9644D
U9614	SL-1ST Floppy Disk Drive (3.5 In.)/ROM Upgrade Package	
U9615A	Option 21A Module Upgrade Package AC	U9600A
U9616	SL-1 A/M/MS/L/LE/S to ST Upgrade Package	U9601A
U9616	SL-1 A/M/MS/L/LE/S to ST Upgrade Package	U9601D
U9616	SL-1 A/M/MS/L/LE/S to ST Upgrade Package	U9604A
U9616	SL-1 A/M/MS/L/LE/S to ST Upgrade Package	U9604D
U9617	SL-1 M/MS/L/LE to NT Upgrade Package	U9602A
U9617	SL-1 M/MS/L/LE to NT Upgrade Package	U9602D
U9617	SL-1 M/MS/L/LE to NT Upgrade Package	U9606A
U9617	SL-1 M/MS/L/LE to NT Upgrade Package	U9606D
U9618	SL-1 VL/VLE/XL/XN to XT Upgrade Package	U9603A
U9618	SL-1 VL/VLE/XL/XN to XT Upgrade Package	U9603D
U9618	SL-1 VL/VLE/XL/XN to XT Upgrade Package	U9607A
U9618	SL-1 VL/VLE/XL/XN to XT Upgrade Package	U9607D
U9619	SL-1 NT to XT Cabinet Upgrade Package	
U9624A	Option 51 from A/M/S/MS/ST/21A/21/21E Upgrade Package AC	
U9624D	Option 51 from A/M/S/MS/ST/21A/21/21E Upgrade Package DC	
U9625A	Option 51 from Option 21/21E CardCage Upgrade Package AC	
U9625D	Option 51 from Option 21/21E CardCage Upgrade Package DC	

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U9626A	Option 61 from A/M/S/MS/L/LE(23,96)/N/ST/STE/21A/21/21E Upgrade Package AC	U9639A
U9626D	Option 61 from A/M/S/MS/L/LE(23,96)/N/ST/STE/21A/21/21E Upgrade Package DC	U9639D
U9627A	Option 61 from RT Upgrade Package AC	U9639A
U9627D	Option 61 from RT Upgrade Package DC	U9639D
U9628A	Option 61 from Option 51 Upgrade Package AC	U9641A
U9628D	Option 61 from Option 51 Upgrade Package DC	U9641D
U9629A	Option 81 from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/61/71 Core and Network Upgrade Package AC	U9650A
U9629D	Option 81 from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/61/71 Core and Network Upgrade Package DC	U9650D
U9630A	Option 81 from XN/XT/71 Core Upgrade Package AC (Dual Column)	U9651A
U9630D	Option 81 from XN/XT/71 Core Upgrade Package DC (Dual Column)	U9651D
U9631	Option 81 from Option 71 Card Cage Upgrade Package AC/DC	U9652
U9632	STE from ST or Option 21E from Option 21A/21 Upgrade Package	U9613
U9633	Option 51 Multi-Disk Unit, Memory and ROM Upgrade Package	U9645
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9639A
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9639D
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9640
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9650A
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9650D
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9651A
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9651D
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9652
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9653A
U9634	RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package	U9653D
U9635	RT Floppy Disk Unit, Memory and ROM Upgrade Package	U9634
U9636A	Option 71 from NT/61 Upgrade Package AC	U9629A
U9636D	Option 71 from NT/61 Upgrade Package DC	U9629D
U9637A	Option 71 from L/LE(23,96)/N/VL/VLE/XL(24,97)/XN Upgrade Package AC	U9629A
U9637D	Option 71 from L/LE(23,96)/N/VL/VLE/XL(24,97)/XN Upgrade Package DC	U9629D
U9638A	Option 81 from XN/XT/71 Core Upgrade Package AC (Single Column)	U9653A
U9638D	Option 81 from XN/XT/71 Core Upgrade Package DC (Single Column)	U9653D
U9642A	Option 81 from Option 61C Upgrade Package AC	U9654A
U9642A	Option 81 from Option 61C Upgrade Package AC	U9655A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order Code	Description	Replaced By
U9642A	Option 81 from Option 61C Upgrade Package AC	U9656A
U9642D	Option 81 from Option 61C Upgrade Package DC	U9654D
U9642D	Option 81 from Option 61C Upgrade Package DC	U9655D
U9642D	Option 81 from Option 61C Upgrade Package DC	U9656D
U9700	SL-1S Floppy Disk Drive (5.25 In.) Upgrade Package	
U9800	SL-1N to NT Shelf Upgrade Package (QCA58 Cabinet)	
U9801	SL-1LE to NT Shelf Upgrade Package (QCA23 Cabinet)	
U9850	Upgrade Package from 32-800 Lines to 801-1200 Lines	
U9851	Upgrade Package from 801-1200 Lines to 1201+ Lines	
U9900	XN Memory Expansion Upgrade Assembly	
U9901	XN Memory Shelf Upgrade Assembly	
U9902	SL-1XN to XT Shelf Upgrade Package (QCA55 Cabinet)	
U9903	SL-1XN to XT Shelf Upgrade Package (QCA24 Cabinet)	
U9924	VL, VLE, XL, XN/XT Cabinet Upgrade Package	
U9980	NT/XT Cabinet Upgrade Assembly	U9619
V005	Meridian Mail Training Video	V006
V006	Meridian Mail Feature Operations Video	V006-11
V006-11	Meridian Mail 11 Feature Operations Video	
X0645393	1GB Disk Drive	NTDK74AA
X9950745	Liberation Replacement Bottom Cord for MPA/MPAII	P0886590

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

General Section

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

General Policy

About this product catalog

The Nortel Networks U.S. Enterprise Solutions Product Catalog is provided to authorized distributors of Nortel Networks products as the prime source of pricing and ordering policy information. The intention of this catalog is to provide the information required for distributors to successfully execute orders.

Catalog distribution policy

Nortel Networks provides distributors with a reasonable number of product catalogs. Each product catalog is proprietary and provided to distributors as a loan. Upon termination of agreements between Nortel Networks and distributors, distributors are to promptly return all product catalogs to the following address:

Nortel Networks
Commercial Offer Management
P.O. Box 833858, MS: 38D / 02 / D11
Richardson, TX 75083-3858

Products supported by this catalog

This product catalog supports the following products:

- Meridian 1 Options 11 - 81C
- Meridian 1 Options 11/11E/11C
- Meridian SL-1

Definition of business day

All references to “days” within this product catalog are in terms of business days and exclude weekends and holidays.

Holidays

Nortel Networks official holidays in the U.S. market are as follows:

2000 Nortel Networks holiday schedule

Date	Holiday
January 3	New Year’s Day
May 29	Memorial Day
July 4	Independence Day
September 4	Labor Day
November 23, 24	Thanksgiving Break
December 25 - 29	Winter Break

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Time zone abbreviations

The following time zone abbreviations are used throughout this catalog:

- CST= Central Standard Time
- EST= Eastern Standard Time
- PST= Pacific Standard Time

Pricing information

Pricing policies

Nortel Networks issues price updates through this Product Catalog. Price updates are effective on orders received on or after the effective date of the Product Catalog. Any prices obtained from the automated pricing tools or included in POs, bulletins, or presentations do not govern or subordinate the prices contained in this catalog. If there is a conflict, the prices in this catalog are used. The product prices listed are Commercial List Prices (CLP).

The pricing sections in this catalog include:

- Product pricing
- Repair pricing
- Support and service fees
- Licensing and transaction fees
- Standard price items

Distributor discounts

Each Nortel Networks authorized distributor of Enterprise Solutions products is granted a Distributor discount. Distributor discounts are identified by a letter designation as shown below:

- I = 50%
- D = 30%
- H = 0%

Distributor discounts are applied to each product's CLP. The resulting price from application of the Distributor discount is the Gross Distributor Price (GDP). Other discounts may be applied to GDP to arrive at Net Distributor Price (NDP).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Gross Distributor Price/Net Distributor Price calculation

How GDP and NDP are calculated

Commercial List Price (CLP)
less
Distributor Discount
equals
Gross Distributor Price (GDP)
less
Other Discounts (% or $) (e.g., volume purchase plan discount, marketing program discount) [discounts are additive]
Other Discounts (% or $) (e.g., system discount, marketing program discount) [discounts are additive]
equals
Net Distributor Price (NDP)

Non-discountable items

The following items can not be discounted.

- Service fees
- Licensing fee
- Transaction fees
- Standard price items
- Documentation
- Freight charges

Standard price item definition

A standard price item is any merchandise or service, other than hardware or software offered to distributors, under the Distributorship Agreement (e.g., Meridian Configurator, training, collaterals, technical support, and Customer Technical Services [CTCTSS]).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software licenses and right to use fees

The original manufacturer, either Nortel Networks or the third-party manufacturer, offers the end user a license granting the right to use (RTU) certain software.

The Nortel Networks Customer Premises Equipment (CPE) Distributorship Agreement provides that Nortel Networks software is licensed by distributors as Nortel Networks' agent in exchange for a RTU fee. Third-party software is licensed directly to end users in exchange for a RTU fee. The RTU fee entitles and obligates an end user to the Meridian Software License provisions. Distributors have the right to charge end users for such license.

A completed hardware/software registration form for a Meridian 1 system installation is no longer required. Registration of the Meridian 1 system occurs automatically at the time of order acceptance. The PO and Meridian Configurator provides the required system end-user information (name, address, contact name, and phone number).

Any change of system ownership still requires the filing of a Software License Software Transfer Agreement form by the end user.

Old software media must be returned within 45 days of replacement media shipment or applicable software RTU fees are invoiced.

When a system is upgraded and/or the software is updated, and the existing software media is returned to Nortel Networks or third-party manufacturer, the one fee/one system relationship is maintained and the value of all RTU fees on the former system are transferred at existing price levels to the new system.

Meridian Software License Transfer Agreement

End users wishing to transfer Meridian software to another end user must first transfer their license by signing the following "Meridian Software License Transfer Agreement."

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SOFTWARE LICENSE TRANSFER AGREEMENT

NORTEL NETWORKS INC. (“Nortel Networks”) TELECOMMUNICATIONS PRODUCTS

(“TRANSFEREE”)

This Agreement is being executed because TRANSFEREE has purchased one or more voice/data telecommunications system(s) from a previously licensed end-user and requires ancillary rights to use certain Software, proprietary to Nortel Networks or its suppliers, in conjunction with that system or those systems. This Agreement transfers the Software rights of use from the previous end-user to TRANSFEREE and explains the conditions of such transfer.

Nortel Networks has granted a personal, non-exclusive license (1) to use certain Licensed Software, proprietary to Nortel Networks or its suppliers, contained as an integral part of the Hardware; and (2) to install and use each item of Licensed Software not an integral part of the Hardware; and (3) to use the associated documentation. No title, ownership rights, copy rights, patent rights trade secret rights, or other intellectual property right in or to the Licensed Software in whole or in part, have been granted. Such rights shall remain with Nortel Networks or its suppliers. Restrictions such as measured usage of applications based upon number of lines, number of ports, number of terminal numbers assigned, number of users, or other similar measures may limit the right to use Licensed Software. Expansion beyond the specified usage level may require payment of an incremental charge or another license fee.

Nortel Networks considers the Licensed Software to contain “trade secrets” of Nortel Networks and/or its suppliers. Such “trade secrets” include, without limitation thereto, the specific design, structure and logic of individual Licensed Software programs, their interactions with other portions of Licensed Software, both internal and external, and the programming techniques employed therein. In order to maintain the “trade secret” status of the information contained within the Licensed Software, the Licensed Software has been delivered in object code form only.

Nortel Networks or any of its suppliers holding any intellectual property rights in the Licensed Software, and/or any third party owning any intellectual property rights in software from which the Licensed Software was derived, are intended third party beneficiaries of the License. All grants of rights to use intellectual property intended to be accomplished by this transfer of rights are explicitly stated and no additional grants of such rights shall be inferred or created by implication.

TRANSFEREE warrants to Nortel Networks that TRANSFEREE is not purchasing the rights granted by this License transfer in anticipation of reselling such rights.

TRANSFEREE shall:

- Hold the Licensed Software in confidence for the benefit of Nortel Networks and/or its suppliers using no less a degree of care than it uses to protect its own most confidential and valuable information; and
- Keep a current record of the location of each copy of Licensed Software made by it; and
- Use each copy of the Licensed Software only on a single CPU at a time (for this purpose, single CPU shall include systems with redundant processing units); and
- Affix to each copy of Licensed Software made by it, in the same form and location, a reproduction of the copyright notices, trademarks, and all other proprietary legends and/or logos of Nortel Networks and/or its suppliers, appearing on the original copy of such Licensed Software delivered to TRANSFEREE; and retain the same without alteration on all original copies; and
- Issue instructions to each of its authorized employees, agents, and/or representatives to whom software is disclosed, advising them of the confidential nature of such software and to provide them with a summary of the requirements of this license, and
- Return the Licensed Software and all copies through an Authorized Distributor to Nortel Networks at such time as the TRANSFEREE chooses to permanently cease using it.

TRANSFEREE shall not:

- Use the Licensed Software (i) for any purpose other than TRANSFEREE's own internal business purposes and (ii) other than as provided by the transferred License; or
- Allow anyone other than TRANSFEREE's employees, agents and/or representatives with a “need to know” to have physical access to the Licensed Software; or
- Make any copies of the Licensed Software except such limited number of object code copies in machine readable form only, as may be reasonably necessary for execution or archival purposes only; or
- Make any modifications, enhancements, adaptations, or translations to or of the Licensed Software, except for those resulting from those TRANSFEREE interactions with the Licensed Software associated with normal use and explained in the associated documentation; or
- Attempt to reverse engineer, disassemble, reverse translate, decompile, or in any other manner decode the Licensed Software, in order to derive the source code form or for any other reason; or
- Make full or partial copies of any documentation or other similar printed or machine-readable matter provided with Licensed Software unless the same has been supplied in a form by Nortel Networks intended for periodic reproduction of partial copies; or
- Export or re-export the Licensed Software and/or associated documentation from the fifty states of the United States and the District of Columbia.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

TRANSFEREE may assign collectively its rights under this License to any subsequent owner of the Hardware, but not otherwise, subject to the payment of the then current license fee for new users, if any. No such assignment shall be valid until TRANSFEREE (1) has delegated all of its obligations under this License to the intended assignee; and (2) has obtained from such assignee an unconditional written assumption of all such obligations; and (3) has provided Nortel Networks a copy of such assignment, delegation and assumption; and (4) has transferred physical possession of all Licensed Software and all associated documentation to the assignee and destroyed all archival copies. Except as provided, neither the transferred License nor any rights acquired by TRANSFEREE through the License are assignable. Any attempted assignment of rights and/or transfer of Licensed Software not specifically allowed shall be void and conclusively presumed a material breach of the License.

If Nortel Networks (i) claims a material breach of the License, and (ii) provides written notice of such claimed material breach to TRANSFEREE and (iii) observes that such claimed material breach remains uncorrected and/or unmitigated more than thirty (30) days following TRANSFEREE's receipt of written notice specifying in reasonable detail the nature of the claimed material breach, then TRANSFEREE acknowledges that the License may be immediately terminated by Nortel Networks and TRANSFEREE further acknowledges that any such termination shall be without prejudice to any other rights and remedies that Nortel Networks may have at law or in equity.

THE LICENSE DOES NOT CONFER OR GRANT ANY WARRANTY TO CUSTOMER FROM OR BY NORTEL NETWORKS THE LICENSED SOFTWARE IS PROVIDED BY NORTEL NETWORKS "AS IS" AND WITHOUT WARRANTY OF ANY KIND OR NATURE, WRITTEN OR ORAL, EXPRESS OR IMPLIED, INCLUDING (WITHOUT LIMITATION) THE IMPLIED WARRANTIES OF MERCHANTABILITY AND OF FITNESS FOR A PARTICULAR PURPOSE. THIS LIMITATION OF WARRANTIES WAS A MATERIAL FACTOR IN THE ESTABLISHMENT OF THE LICENSE FEE CHARGED FOR EACH SPECIFIC ITEM OF SOFTWARE LICENSED.

IN NO EVENT WILL NORTEL NETWORKS AND/OR NORTEL NETWORK'S SUPPLIERS BE LIABLE TO OR THROUGH CUSTOMER FOR INCIDENTAL, SPECIAL, CONSEQUENTIAL, PUNITIVE, OR EXEMPLARY DAMAGES OF ANY KIND, INCLUDING LOST PROFITS, LOSS OF BUSINESS, OR OTHER ECONOMIC DAMAGE, AND FURTHER INCLUDING INJURY TO PROPERTY, AS A RESULT OF BREACH OF ANY WARRANTY OR ANY OTHER TERMS OF THIS LICENSE, REGARDLESS OF WHETHER NORTEL NETWORKS AND/OR NORTEL NETWORK'S SUPPLIERS WERE ADVISED, HAD OTHER REASON TO KNOW, OR IN FACT KNEW OF THE POSSIBILITY THEREOF. CUSTOMER ACKNOWLEDGES THAT THE FOREGOING SENTENCE REFLECTS AN INFORMED, VOLUNTARY ALLOCATION BETWEEN THE PARTIES OF THE RISKS (KNOWN AND UNKNOWN) THAT MAY EXIST IN CONNECTION WITH THE LICENSE, THAT SUCH VOLUNTARY RISK ALLOCATION WAS A MATERIAL PART OF THE BARGAIN BETWEEN THE PARTIES, AND THAT THE ECONOMIC AND OTHER TERMS OF THE LICENSE WERE NEGOTIATED AND AGREED TO BY THE PARTIES IN RELIANCE ON SUCH VOLUNTARY RISK ALLOCATION.

PLEASE COMPLETE THE REVERSE SIDE

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NORTEL NETWORKS

SOFTWARE LICENSE TRANSFER AGREEMENT
NORTEL NETWORKS PRODUCTS

INCOMPLETE FORMS WILL NOT BE PROCESSED.

Please place a check in the applicable box(es): ❑ System Transfer ❑ Name Change Only ❑ Application Transfer

---

Switch Transfer

System Type: _____ Software Generic: _____ Release: _____ Issue: _____

Switch Serial Number: _____

Option 11, Site ID: _____ Software Cartridge ID: _____

Application Transfer (Meridian Mail, IVR, CallPilot, Symposium, Periphonics, etc.)

Application Type: _____ Application Serial Number: _____

Application Type: _____ Application Serial Number: _____

Switch Serial Number Application moving FROM: _____ System Type: _____

Switch Serial Number Application being moved TO: _____ *(fill-in details in Switch Transfer section)*

End User Data

BOTH THE TRANSFEROR AND TRANSFEREE SIGNATURES ARE REQUIRED BY NORTEL NETWORKS FOR THIS TRANSFER AGREEMENT TO BE VALID.

Transferor (Previous End-User) Company Name, Address, and Telephone Number:

Address: _____

_____ Tel#: ( )

SIGNED: _____ DATE: _____

PRINTED NAME: _____ TITLE: _____

The person who signs below hereby assumes, unconditionally, all of the obligations of the previous end-user (Transferor) as specified in this document and has taken physical possession of all Licensed Software and all associated documentation.

Transferee (New End-User) Company Name, Address, and Telephone Number:

Address: _____

_____ Tel#: ( )

SIGNED: _____ DATE: _____

PRINTED NAME: _____ TITLE: _____

Nortel Networks Authorized Distributor

Company: _____ Office Location: _____

Contact: _____ Telephone Number: _____

MAIL OR FAX COMPLETED AGREEMENT TO:

Nortel Networks
Distribution Management/Contracts
Mailstop 38D/04/C40
2375-A N. Glenville Dr.
Richardson, TX 75082
Telephone: (972) 684-1496 Fax: (972) 684-3758

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Warranties

Hardware warranty period

Hardware under normal use and service is free from defects and faulty workmanship for a period as follows.

Meridian 1 and third-party manufacturer hardware warranty

Code	Warranty period
W0	No Warranty
W1	Whichever period expires first: a. 15 months from date of shipment to distributors b. 12 months from date placed in service with end user
W2	90 days from date of shipment
W3	Warranty provided by third-party manufacturer

Software warranty period

Meridian 1 and third-party manufacturer software warranty

Software Group	Warranty Period
1 & 2	Whichever period expires first: a. 15 months from date of shipment to distributors b. 12 months from date placed in service with end user
3 & 4	Whichever period expires first: a. 150 days from date of shipment to distributors b. 90 days from date placed in service with end user
5	Warranty provided by third-party manufacturer

Damage caused by abuse or natural causes such as flood, lightning, fire, etc., is not covered under Enterprise Solutions product warranty and is non-repairable.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Ordering Process, Policies, and Procedures

Order placement

Order placement methods

Nortel Networks accepts orders placed by any of the following methods:

- Mail
- Facsimile
- Electronic Data Interchange (EDI)

Purchase orders (POs) are processed by assigned Nortel Networks Customer Response Center Representatives or Repair Service Representatives.

Order transaction types

Nortel Networks processes different transaction order types. Each order type requires distributors to contact the appropriate Nortel Networks facility to successfully process an order.

Appropriate order types and contacts are listed in the following tables.

Custom orders	Stock orders	Service orders
Meridian 1 systems (Options 11-81) System upgrades Software updates Meridian 1 application products	Merchandise components Sales collateral	Repair orders Remanufactured equipment Training Technical Support Field Audits Meridian Configurator

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order contacts

The ordering contacts are as follows:

Product/order type	Enterprise Solutions sales collateral	Meridian 1 Options 11 - 81
Custom & stock orders	Enterprise Solutions Customer Response Center 220 Athens Way, Suite 200 Nashville, TN 37228 1-800-321-2649 FAX (615) 734-5992	Enterprise Solutions Customer Response Center 2305 Mission College Blvd Santa Clara, CA 95054-1599 1-800-321-2649 FAX (408) 565-2530
Repair & remanufacture equipment	N/A	Nortel Networks Repair and Distribution Center 640 Massman Drive Nashville, TN 37210 1-800-321-2649
Technical support	N/A	Enterprise Solutions CTS 2100 Lakeside Blvd, MS-A404 Richardson, TX 75082 1-800-766-ETAS 1-800-766-3827 FAX (972) 684-3949
Training	N/A	Meridian Information Products 1057 Sherman Richardson, TX 75081 1-800-775-NTEL (972) 684-8777 FAX (972) 684-8699
Field audits	N/A	Distributor Field Quality 2305 Mission College Blvd Santa Clara, CA 95054-1599 (408) 565-2789 FAX (408) 565-2033

Training

Nortel Networks' North American course offerings that have been updated to include the new Meridian 1 product offerings, plus other related course information can be viewed online at www.nortel.com. From the Nortel home page, choose Enterprise Solutions. Then choose Training and Documentation store. The Nortel Product Training and Documentation Home Page is your 24-hour marketplace for every product we offer.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Required order information

Provide the following information to the appropriate Customer Response Center Representative when placing an order:

Order information

Information	New Systems	Stock Orders	Software Orders	Upgrade Orders
Distributor customer number	R	R	R	R
Bill-to-number	R	R	R	R
Ship-to address (including floor or building)	R	R	R	R
Name of person placing order	R	R	R	R
Name of person responsible for receiving delivery (including phone number) (person to be contacted 24 hours prior to shipment)	R			R
Method of handling/shipment	R	R	R	R
Specific delivery site requirements	R			R
Requested ship date	R	R	R	R
Report 9 from Meridian Configurator	O		O	O
Meridian Configurator Quote and Version Number	O		O	O
System Serial Number			R	R
End-User Name	R		R	R
Current System Type/Option			R	
Current Software Generic and Release/Issue			R	
Current Capacity Limits			A	
List of Current Software Features			R	
Desired Software TN Level			R	
Desired Software ACD Agent Level			R	
Legend: R = Required A = If applicable O = Optional				

Order restrictions

All custom orders have order restrictions (e.g., special information, purchase requirements). Refer to specific pricing sections and/or reference notes for applicable purchase requirements. Refer to specific ordering procedures in this document for special information requirements.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order forms

Depending on the order transaction type, Nortel Networks may also require additional Nortel Networks forms from distributors. Contact your Customer Response Center Representative to ensure all forms are completed prior to ordering.

Order acknowledgment

Nortel Networks may acknowledge order acceptance via verbal communication, written notification and/or electronically. Order acknowledgment includes ship date, content, and official pricing.

Minimum POs

Distributor POs for all new hardware/software must be for a minimum amount of $100.00 at NDP. On any regular sales order of less than $100.00, a $75.00 handling fee will apply (SERV0024). The SERV0024 code must appear on distributor's Purchase Order. This policy does not apply to emergency orders placed after normal business hours or to Sales Collateral orders.

Order changes

Product order change requests

Order change requests are accepted without penalty to distributors if received at least ten days prior to the original scheduled ship date. Change requests must be made to the appropriate Customer Response Center Representative by submitting a PO change notice.

The following conditions apply to change requests received within ten days of the schedule ship date:

Stock product

Stock product change requests may be applied at the discretion of Nortel Networks. A $200.00 handling charge applies to change requests received between two and ten days prior to scheduled ship date. Purchase Order changes are not accepted later than two days prior to the scheduled ship date. The PO change notice must reference the handling charge ordering code (SERV0021).

Custom product

A reconfiguration/re-engineering charge of $1,000.00 (SERV0022) per order plus $1.00 per equipped line and trunk (SERV0023) applies to change requests received within ten days of the scheduled ship date. This policy also applies to software feature changes on new system orders. Change requests resulting in a rescheduled ship date are subject to carrying charges described under "Order rescheduling."

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Change request charges

Codes	Change Request	Price
SERV0021	Stock Product Handling Charge	$200
SERV0022	Custom Product Reconfiguration/Reengineering Charge	$1,000
SERV0023	Custom Product Reconfiguration/Reengineering Per Line Charge	$1.00/Line

Order rescheduling

Distributors may reschedule an order one time (for up to 90 days beyond the original ship date). No penalty is applied to the reschedule provided the request is received a minimum of ten days prior to the original ship date. Reschedule requests received within ten days of the original ship date are subject to carrying charges. Further revisions are treated as cancellations with appropriate cancellation charges applied (refer to Order Cancellation within this section).

Reschedule requests must be submitted to the appropriate Customer Response Center Representative through a PO change notice. Purchase order change notices received within ten days of the original scheduled ship date must include the amount of the appropriate carrying charge.

Carrying charges

Carrying charges apply when distributors delay shipment of an order through a reschedule or reconfiguration received by Nortel Networks within ten days of the original scheduled ship date. Carrying charges are 2% of the NDP and apply to each fiscal month or portion thereof that shipment is delayed.

Order cancellation

A PO change notice is required to cancel an order. The PO change notice must be submitted to the appropriate Customer Response Center Representative.

Cancelled orders are subject to cancellation charges of 15% of the NDP. These charges are applicable on all distributor initiated cancellation requests received after order acceptance by Nortel Networks.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Product delivery

New system orders are shipped to an address within the distributors' territory, as defined in the Nortel Networks CPE Distributorship Agreement, unless previous approval has been obtained. Contact Nortel Networks at the following address to receive pre-approval:

Nortel Networks
Distribution Management
2221 Lakeside Blvd
Richardson, TX 75082
(972) 684-1496

Note: Any exception must be pre-approved.

Standard shipment leadtime

The Nortel Networks standard shipment leadtime is the expected interval between Nortel Networks' official acceptance of an order and the expected date of shipment to distributors, indicated in business days. The following table details the standard shipment leadtime for Enterprise Solutions products.

Enterprise Solutions product	Standard shipment leadtime
Meridian 1 systems	
Option 21E	5 business days
Option 51C/61C/81C	10 business days
Option 11C system/component	5 business days
Option 11C system with application products	10 business days
Meridian 1 software	
Updates	5 business days
System conversions	10 business days
Meridian 1 application products	10 business days
Meridian 1 components	5 business days
Meridian 1 upgrades	10 business days
Repair	10 business days
Enterprise Solutions sales collaterals	5 business days

Partial shipments

Nortel Networks products

If Nortel Networks is unable to completely fill a distributor's order, the order is partially shipped, unless distributors have specified in writing that orders are to be held for complete shipment.

Products manufactured by third parties

Third-party hardware components are shipped to the end user separately from the software and are provided during the installation of the system.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Shipping methods

Nortel Networks ships products FOB (freight on board) factory of origin. Hardware title passes to distributors and acceptance occurs when Nortel Networks surrenders possession to the common carrier, or, if Nortel Networks is acting as carrier, upon departure from its loading dock.

Standard shipping method is “best way” surface freight, unless distributors specify air or other commercially available shipping method; Nortel Networks invoices freight accordingly.

Nortel Networks prepays the common carrier and invoices distributors for all Meridian 1 shipping charges.

Shipment/Order discrepancies

An order discrepancy exists when Nortel Networks shipping documents and/or the equipment received do not agree with distributor’s receiving documents (including references to backorders). Any discrepancies must be filed with the appropriate Customer Response Center Representative within 30 days of distributors receipt of shipment. To resolve order discrepancies, be prepared to provide the PO number or Nortel Networks reference number.

Proof-of-delivery

Proof-of-delivery (POD) is provided upon request. Nortel Networks accepts distributors POD requests up to 90 days from the initial shipping date. No POD requests are considered after the 90-day period.

Product availability limitations

Product availability status

During the product life, it may become necessary for Nortel Networks to limit product availability. The following product statuses indicate limitations on product availability.

Product availability limitations

Product status	Definition
Controlled release	Product available on limited basis only. Distributors must secure controlled release approval from product management prior to order acceptance.
New system sale	Product available with new system sales only
Additions & maintenance	Product available for installed base sales only
Manufacture Discontinued	Product is no longer sold in the US Market. The product is available for repair if it is a repairable item.

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Controlled release products

Nortel Networks reserves the right to release product and/or product improvements under the controlled-release program and to allocate such product to Distributors as best suits the needs of Nortel Networks' product development and testing programs.

Distributors must submit a controlled-release application and a site profile (if applicable) to Santa Clara Customer Response Center. Completed controlled-release applications and applicable site product files should be sent to the following address.

Nortel Networks
Customer Response Center
2305 Mission College Blvd.
Santa Clara, CA 95054-1599

FAX (408) 565-2530

Written acceptance/rejection of controlled-release applications are sent to the originator from Santa Clara Customer Response Center within approximately ten business days of receipt of the application.

Shipment leadtimes for controlled release products

Standard shipment leadtimes do not apply to products on controlled release. The following leadtimes apply instead:

- Standard shipment lead times for controlled-release items are provided on a per quote basis.
- Contact your Customer Response Center Representative for specific ship dates for backorder items.
- Controlled-release items may be differentiated by ship date upon order acknowledgment.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Return Policies and Procedures

Software return policy

When replacement media is received for a Meridian 1 SL-1 or Meridian Applications Product software update, existing floppy disks, tapes, and data cartridges (software media) must be returned to Nortel Networks within 45 days of shipment of the replacement material, referencing the Return Authorization (RA) number provided at the time of order placement. Distributors are charged for any missing software media.

Ship all return software materials to the following address:

Nortel Networks
M1 Credit & DOA Returns
917 Airpark Center Drive
Dock Door J **ONLY**
Nashville, TN 37217
Attn: RA#_____
1-800-321-2649

Equipment return options

Nortel Networks offers various types of product return options:

- Restocking—return of new unused equipment for credit within 60 days of ship date
- Repair—return of damaged or defective equipment for repair
- Advance Replacement—replacement equipment shipped in support of emergency repairs and some updates/upgrades
- Defective on Arrival (DOA) Replacement—replacement equipment shipped in support of DOAs

Return contacts

The following tables list the key phone contacts and shipping locations for the specified equipment return

Returns	Enterprise Solutions Sales Literature	Meridian 1 Option 11-81
Restocking	Multimedia Communications Systems Products Customer Response Center 220 Athens Way Suite 200 Nashville, TN 37228 1-800-321-2649 FAX (615) 734-5992	Nortel Networks Customer Response Center 2305 Mission College Blvd Santa Clara, CA 95054-1599 1-800-321-2649, choice 3 FAX (408) 565-2530

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Returns	Enterprise Solutions Sales Literature	Meridian 1 Option 11-81
Repair & Repair Advanced Replacement	N/A	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37217 1-800-321-2649, choice 5
Defective on Arrival (DOA)	N/A	Nortel Networks Customer Response Center 2305 Mission College Blvd Santa Clara, CA 95054-1599 1-800-321-2649, choice 3
Software Media	N/A	Nortel Networks Customer Response Center 2305 Mission College Blvd Santa Clara, CA 95054 1-800-321-2649, choice 3

Return locations

Return type	Return locations
Restocking (Option 11)	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37210
Restocking (All other M1 products)	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37210
Repair & Repair Advanced Replacement	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37210
Defective on Arrival (DOA)	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37210
Software Media	Nortel Networks M1 Credit & DOA Returns 917 Airpark Center Drive Dock Door J **ONLY** Nashville, TN 37210

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Restocking policies

Restocking charges

The restocking charge applies when customer orders are placed in error, or in excessive quantities for systems or new merchandise, and a return is requested by distributors. Restocking charges apply when a distributor returns new unused products.

Nortel Networks charges a 15% restocking fee for new unused equipment returned within 60 days of ship date. The 15% restocking fee is applied at NDP. Nortel Networks does not accept restocking returns greater than 60 days from ship date.

Restocking process

Nortel Networks issues an RA number from the appropriate Customer Response Center Representative (see previous table) when a distributor requests that materials be returned for credit. Distributors must mark this number on all packages being returned for credit; without it, Nortel Networks cannot issue credit and packages are returned to sender.

The following information is required for a restocking credit return number:

- Distributor name
- Distributor customer billing number
- Original NTI number
- Original PO number
- List of parts to be returned. Include the following items in the list of parts:
  - — order code
  - — quantity

All products must be returned in the original packaging. If the return claim is for a system and/or packaged components, all components, software cartridges, and power supplies must be returned as originally shipped. If returned equipment is not in protective packaging and/or parts or components are missing, or if equipment designated as new unused is returned and appears to be used equipment, Nortel Networks returns the item to distributors. Improper packaging, resulting in obvious damage to equipment, voids the warranty and the equipment is returned to sender.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Repair policies and procedures

Repair and service responsibilities

Distributor responsibility

Nortel Networks assumes no responsibility for service or installation to the ultimate end user of the Enterprise Solutions products. **To ensure continuous service to the end user, distributors are responsible for maintaining sufficient spare stock to replace units which are in the repair or warranty claim process**.

Repair warranty

Nortel Networks warrants Enterprise Solutions hardware and system software for periods outlined in the Warranty section of this document as follows:

- All Repaired equipment carries a full 12-month warranty from the date repaired.
- Standard repair turn around time is 10 working days from receipt of equipment at our warehouse.
- Standard shipping method is surface freight.
- Repair of defective equipment is on a “like-for-like” basis, unless otherwise stated in the product catalog.
- Repair includes cosmetic reconditioning of all items.
- Damage caused by abuse or natural causes such as flood, lightning, fire, etc., is not covered under Enterprise Solutions product warranty and is non-repairable.

Nortel Networks shall provide, at GDP, functionally equivalent repair hardware and/or software to support distributor’s installed base for the product support period specified by the contract annex or new product bulletin. This support continues from the date the product is manufacture discontinued unless otherwise specified.

Products manufactured by third parties

During these product(s) life, their manufacturer(s) may discontinue the product(s). Nortel Networks makes no guarantee as to the availability of any of these products, whether for new system sales or for installed base sales or whether the product(s) is/are available in the U.S. market. However, these products are available for repair if they are repairable items.

Non-repairable parts

Certain items may be determined by the Repair and Distribution Center to be non-repairable. If a non-repairable item fails within the stated warranty period 15 months from the date of shipment to distributor or 12 months from date placed in-service with an end user, whichever period expires first), the equipment is replaced at no charge by Nortel Networks. **If non-repairable equipment fails after the warranty period has expired, distributors may purchase replacement equipment.**

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Repair pricing

In-warranty

There is no charge for repair of Enterprise Solutions hardware and system software that are covered under the standard warranty period. Distributors are charged for any piece parts that are missing from the hardware, software tapes/ cartridges, assembly parts, etc.

Out-of-warranty

For Enterprise Solutions hardware and system software that are not covered by the standard Enterprise Solutions warranty period, distributors are charged according to the repair prices established in the Enterprise Solutions Product Catalog. Distributors are charged for any piece parts that are missing from the hardware, software tapes/cartridges, assembly parts, etc.

Repair agents

Nortel Networks Repair and Distribution Center, Nashville, TN, acts as the sole authorized factory repair agent for the United States market. All Enterprise Solutions equipment claimed to be defective, whether in-warranty or out-of-warranty, is to be shipped prepaid to the following address.

Nortel Networks
Repair and Distribution Center
640 Massman Drive
Nashville, TN 37210

Repair contacts and schedules

The following table shows appropriate contacts and schedules for service repair information.

Repair services

Service type	Schedule
Repair and Distribution Center	7:00 a.m. to 6:00 p.m. CST, Monday - Friday
Information and equipment repair status	(615) 883-9220 or 1-800-321-2649 choice 5
After hours emergency repair	(615) 883-9220 or 1-800-321-2649 Select voice prompt for emergency “Hot Line”

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Repair procedures

Return for Repair Numbers (RR#'s) are not required. Simply send the repair equipment, including a PO and packing list, to the Repair and Distribution Center as outlined in the following steps. If a tracking number is desired or special handling is needed, begin with step 1 for obtaining a RR#, otherwise begin with step 2.

1. Contact the Repair and Distribution Center in Nashville, TN, to secure a Return for Repair number (RR#). Phone 1-800-321-2649 choice 5.

   When requesting a Return for Repair number, please have the following information available:

   - ordering code
   - quantity
   - item description
   - PO number (original and/or new)
   - address where repaired equipment is to be returned
   - distributor's bill to address.

2. All shipments must include a PO and packing slip from distributors with the following information:

   - Distributor's ship to address
   - Return for Repair # (if necessary)
   - Quantity and ordering code of the items being returned
   - PO number
   - Special instructions, if applicable

3. Ship equipment prepaid to the following address.

   Nortel Networks
   Repair and Distribution Center
   640 Massman Drive
   Nashville, TN 37210

   Note: To ensure proper tracking, the RR# must appear on the outside of all packages.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

4. All equipment being returned to Nortel Networks must have a repair tag attached to it. Obtain repair tags from the Nortel Networks Repair and Distribution Center or distributors may use any repair tag of their choice containing similar information. Distributors must be as specific as possible when reporting the exact nature of the problem with the defective equipment.

Emergency repair

1. If a distributor requests equipment to be repaired on an emergency basis, the Repair and Distribution Center expedites the equipment through the repair shop.
2. Shipment is made within two working days of receipt of defective equipment at the Repair and Distribution Center.

   Note: Limitations exist for large volumes.

3. Nortel Networks charges a $100.00 emergency handling fee (SERV0006) to distributors for each emergency repair. Premium freight is the responsibility of distributors (non-discountable).

After Hours Emergency Advance Replacement Policy

If the distributor requires after hours advance replacement of repair parts, they may contact the repair center after normal business hours. The after hours voice menu will instruct the distributor how to contact after hours support within Nortel Networks.

Advance replacement is available only for “service affecting” out of service equipment. Lead-time for advance replacement is 24 hours. **Damage caused by abuse or natural causes such as flood, lightning, fire, etc., is not covered under Nortel Networks product warranty and is non-repairable.** The Distributor should determine the nature of the failure prior to requesting service. If the advance-replaced defective equipment is not returned within 30 days to the Repair and Distribution Center in Nashville, the distributor will be invoiced for the advance replacement at the current non-return billing price. The non-return billing price is determined by the Nashville Repair and Distribution Center and is subject to change depending on equipment availability.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

When requesting equipment, please provide the following information:

- Address where equipment should be shipped
- Contact name and phone number, (fax number and email if available) and after hours point of contact name and phone number
- Bill to address
- Quantity and ordering code of each item
- Special instructions

  Note: Purchase Order shall be provided within the next two business days. Failure to provide a valid Purchase Order could result in the suspension of after hour's service.

An After Hours Service Fee (SERV0005) of $225.00 will be charged per order with an additional Service Fee (SERV0005) of $25.00 per line item. Premium freight is the responsibility of the distributor and is non-discountable.

Repair advance replacement

Repair advance replacement policies

Repair advance replacement equipment is available only for "service affecting" out-of-service equipment. Lead time for advance replacement equipment is 24 hours.

If any advance replaced equipment is not returned within 30 days to the Repair and Distribution Center in Nashville, the distributor is invoiced for the advance replacement at a non-return billing price. The non-return billing price is determined by the Nashville Repair and Distribution Center and is subject to change depending on equipment availability.

Repair advance replacement procedures

Please use the following outlined procedures when requesting an advance replacement.

1. Contact the Repair and Distribution Center in Nashville, TN at 1-800-321-2649, choice 5, to request an Advance Replacement Number (AR#).
2. When requesting an AR number, please have the following information available:
   - Ordering code
   - Item description
   - Nature of the problem
   - PO number
   - Address where equipment should be shipped
   - Distributor's bill-to address.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

3. Upon arrival of the advance replacement equipment at the requested site, immediately return the defective equipment to the following address:

   Nortel Networks
   Repair and Distribution Center
   640 Massman Drive
   Nashville, TN 37210
   Attn: AR#_____
   1-800-321-2649

   Note: The RA number must appear on the outside of all advance replacement equipment that is being returned, otherwise Nortel Networks returns the shipment and the equipment at the distributor's expense.

4. All equipment returned to Nortel Networks requires a repair tag attached to it. Repair tags are available through the Repair and Distribution Center or distributors may use any repair tag of their choice containing similar information. Distributors must be as specific as possible in reporting the exact nature of the problem with the defective equipment. This explanation assists Nortel Networks in identifying and analyzing the reported problem.
5. All shipments must include a packing slip from distributors with the following information:
   - Distributor's address
   - AR number
   - Quantity being returned
   - Ordering code of items being returned
   - PO number

Defective on arrival (DOA)

DOA policies

DOA equipment is new product identified within 90 days of shipment as inoperable at the time of initial installation. DOAs are those items having obvious material defects detected when the item is unpacked, or electronic failures discovered when (or before) the item is placed in-service. DOAs are repaired or replaced by Nortel Networks

- DOAs reported within 90 days from original ship date are replaced with new products and given priority shipment.
- DOAs reported AFTER 90 days are handled under normal warranty coverage. See "Repair warranty" under the "Return Policies and Procedures" section.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

If any DOA replaced equipment is not returned within 45 days to the Repair and Distribution Center in Nashville, the distributor is invoiced for the replacement equipment at the current NDP of the equipment. Returns received after invoicing has occurred are subject to a minimum 15% restocking charge.

In the event of a DOA, distributors are contact the Santa Clara Customer Response Center. Please identify DOA equipment when requesting replacement.

Meridian 1 DOA procedures

The DOA procedures are listed as follows:

1. Contact Customer Response Center at 1-800-321-2649, choice 3, to report a DOA.
2. Provide the following information:
   - Ordering code
   - Item description
   - Original PO number (or NTI number)
   - Address where equipment is to be shipped
   - Distributor bill to number or address
   - PO number for the DOA replacement shipment
3. Upon arrival of the DOA replacement equipment at the requested site, immediately return the defective equipment to the following address:

Nortel Networks
M1 Credit & DOA Returns
917 Airpark Center Drive
Dock Door J **ONLY**
Nashville, TN 37210
Attn: RA#_____
1-800-321-2649

Note: The DOA RA number must appear on the outside of all DOA replacement equipment that is being returned, otherwise the shipment and the equipment are returned at distributor's expense.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

4. All shipments must include a packing slip from distributors with the following information:
   - Distributor's address
   - DOA RA#
   - Quantity of items being returned
   - Ordering code of items being returned
   - PO number
5. Advance replaced DOA equipment must be returned in the original packaging. If the parts or components are missing or if equipment appears to be used, distributors are invoiced. If the advance replacement is an upgrade/ update, distributors are responsible for proper packaging. Improper packaging resulting in obvious damage to the equipment causes the warranty to be voided. If such damage occurs, equipment is returned to the distributor. Contact a Repair Representative at 1-800-321-2649 if new packaging materials are needed.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Standard Price Items

Warranties and disclaimers of warranties

Nortel Networks warrants the services provided under this section are to be provided in a good and workman-like manner.

The warranties and remedies contained in this section constitute the only warranties with respect to the services provided hereunder. The stated warranties are in lieu of all other warranties, written or oral, statutory, express, or implied, including, without limitation thereto, the warranty of merchantability and the warranty of fitness for a particular purpose. Nortel Networks is not be liable to the user or purchaser of such service (whether distributor or end user, as the case may be) for any special, incidental, or consequential damages, of any nature or for any reason, arising out of the performance of the services described hereunder, even if Nortel Networks has been advised of the possibility of such damages.

Technical support

Technical support for authorized distributors is available through the following groups (see Technical Support section for detailed policies, procedures, and fees):

- Customer Technical Services (CTS)
- Enterprise Solutions Field Service (Enterprise Solutions FS) installation and maintenance support
- Customer Quality Engineering Support

Meridian 1 Customer Owned and Maintained System (COAMS)

Objective

Ensure the system integrity of Customer Owned and Maintained Meridian 1 systems through management of a Maintenance Qualification Program for all customer-service technicians.

Note: For a detailed flow of the COAM Program Process, see Appendix A in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document.

Definitions

The following terms are commonly used COAMS terminology.

Customer in Good Standing

A customer meeting the COAMS responsibilities and their financial responsibilities to Nortel Networks.

Customer Owned and Maintained Systems (COAMS)

Meridian 1/SL-1 and associated Nortel Networks hardware and software options and features, owned and maintained by the customer.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Customer Service Report (CSR)
The documenting and tracking of technical problems reported to CTS.

Customer Technical Services (CTS)
Nortel Networks technical support provided to customers for emergencies, cutovers, software updates, and product verification.

Maintenance Qualification Program
Recognized Nortel Networks training courses that must be completed by bonafide employees of the customer, prior to being qualified to maintain a COAMS status. Individual employees must complete required minimum courses. Site specific option training must be completed if utilizing any of the optional features.

Nortel Networks
The Nortel Networks logo and abbreviated name.

Nortel Networks Practices (NTPs)
The NTP documentation system provides operating and maintenance information to Nortel Networks systems users, information for internal functions, and a record of part and current system designs. Included is documentation covering hardware, software, and firmer products, and the methods of assembling, installing, interconnecting, and operating the Nortel Networks products.

Quality Audits
Quality Audits can be performed by Nortel Networks or a certified authorized distributor. A COAMS applicant may need to provide with the COAMS Registration Form, a copy of a Quality Audit Report (if not installed by an Authorized Meridian 1 Distributor) and all outstanding issues must be confirmed or resolved.

Quality Audited Systems
Meridian 1 systems installed by bonafide employees, who have completed the requisite installation training required by the quality certified authorized distribution channel or a Meridian 1 system that has passed a quality audit from a certified quality auditor.

Quality Certified Authorized Distribution Channel
Any Authorized Distributor that has satisfied the requirements to perform Quality Audits and is certified by Nortel Networks.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

COAMS responsibilities

Nortel Networks' COAMS program establishes a business transactional relationship with Nortel Networks' CTS function as it relates to service recovery during the maintenance cycle. The self-maintained end users who elected to participate in the COAMS program are responsible for the following items.

- Maintain a customer in good standing status.
- Maintain the required levels of training to remain qualified for the maintenance qualification program. Training to current level as system evolution dictates and training must be completed prior to the commencement of upgrading.

  Note: See Appendix 2 in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for a complete list of available training courses.

- Establish a service relationship with an Authorized Distributor for products the self-maintained customer, participating in the COAMS program, has elected not to self-support. (Customer elects not to be trained on one product, i.e., Meridian Mail.)
- Provide a modem (2400 baud minimum, 9600 baud minimum for Option 81) to all remote access.
- Maintain product documentation at the current level and releases, as defined by systems profiled.
- Maintain the spare parts essential to maintaining the COAMS specific equipment operational. (See NTP 553-3001-153, Spares Planning section in the *System Planning and Engineering Guide*.)
- Capability of maintaining and servicing the product for the full feature functionality/options, based on Nortel Networks training level.
- Reapply for COAMS participation annually. This may require a certification renewal fee and quality audit, if proper records have not be maintained. (See Attachment 3 in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for Renewal Application form).
- Keep the software release level of the system at or above the sustained level published by Nortel Networks. (See Appendix 8 in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for Hardware and Software Status.)
- Provide critical information about individual sites.

  Example: Site is the hub of a ten-switch network.

  Example: Hospital/24-hour business

- Provide the COAMS company's escalation procedures.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

COAMS policy

The COAMS end user must comply with the procedures provided in this policy to obtain CTS and training support.

Note: Technical support is limited to only the product supported by Meridian 1 CTS.

1. The system(s) must be purchased through, installed, and maintained throughout the warranty period, except for the quality audited systems (see item 4 within this section) by an authorized Meridian Distribution channel.
2. The maintenance must be provided by bonafide employees of the customer, (not including consultants; agents, unless otherwise contractually agreed to by Nortel Networks; subcontractors or any other kind of independent contractor) who have fulfilled all requirements of the Maintenance Qualification Program.

   Note: See Appendix 3, Warranty Information, in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for more warranty information.

3. Used systems must be installed and/or maintained for one year, with the exception of quality audited systems (see item 4 within this section), by an authorized Meridian distribution channel, and must be upgraded to the minimum supported release.
4. Quality audited systems need not be installed and/or maintained by an authorized Meridian distribution channel, however the distribution channel must be currently certified by Nortel Networks to perform quality audits, must support all installation efforts, and must perform a quality audit upon the completion of the installation. A copy of the Quality Audit Report certifying full compliance within Nortel Networks guidelines must be filed by the customer, along with a COAMS registration form, prior to support being rendered by Nortel Networks CTS.

   Note: Quality audit reports must have performed within three months of the COAMS registration request.

5. Only registered employees of COAMS end user, who meet the maintenance qualification program requirements, may maintain COAMS status and obtain support from Nortel Networks CTS and Nortel Networks training departments.

   Note: Registered employees are those identified on the COAMS registration form.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

6. Each COAMS, i.e., PBX, must be registered with Nortel Networks, via individual COAMS registration form (see Attachment 1, COAMS Registration Form in the *MCS Service Customer Owned and Maintained Systems [COAMS] Program* document), which must be signed by an authorized signatory of the COAMS end user and updated whenever the system is upgraded or any other changes to the information required on the form occur. Certification renewal is required annually for each installation site registered as COAMS (see Attachment 3, COAMS Renewal Application Form in the *MCS Service Customer Owned and Maintained Systems [COAMS] Program* document).
7. Provide critical site information.

   Example: Site is hub of a ten-switch network

   Example: Hospital/24-hour business
8. All Meridian 1 software must be obtained through authorized Meridian distribution channels; the relationship with which, is the responsibility of the COAMS end user.

   SL-100 hardware and software repair and return may be obtained directly from Nortel Networks.
9. The current Maintenance Qualification Program Courses and associated courses for options and features contained within the COAMS will be administered by Nortel Networks or its affiliates only.

   Note: See Appendix 2, Training Courses Available, in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for a complete list of training courses offered.
10. All CTS support, including warranty period support, if applicable, is billable, to the customer, at the then current rates and is subject to change without notice. See Appendix 4, Technical Support COAMS, in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document. A valid PO must be provided to CTS, by fax, at the time the service request is placed.

    Note: Additional information must be provided as indicated in the Nortel Networks' Meridian 1 CTS Service Request Guide.
11. Nortel Networks reserves the right to modify or terminate this policy at any time upon written notice to customer.
12. COAMS participants must maintain the required spares, as outlined in the NTP documentation for their specific system type.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

COAMS training

The following training courses are required to be taken, as a minimum, by the system support technicians of any customer who applies for the COAMS program status. Only technicians identified on the COAMS Registration Form, who have taken the appropriate courses for the systems and applications designated on the form is eligible for CTS support.

As additional features and courses become available from time to time, it is the responsibility of the COAMS end user to ensure current training is maintained. Course numbers and titles change periodically.

> ***Note:*** See Appendix 2, Training Courses Available, in the *MCS Service Customer Owned and Maintained Systems (COAMS) Program* document for a complete list of training courses offered.

Minimum course requirement for COAMS participation

The following table provides a listing of the minimum courses required for COAMS participation.

Meridian 1 Options 11-81 switch maintenance

Course number	Course name	Length of course
200	Meridian 1 Familiarization	3 days
263	Meridian 1 Options 21-81	10 days
300	X11 Feature Administration OR Data Base for Technicians	7 days 5 days
320	BARS Feature Administration	8 days
Note: The BARS option may not be used in limited cases. Training requirements for this option are reviewed on an individual basis.		

Training courses available (Meridian 1)

Meridian 1 Options (if equipped)

Course number	Course name	Course length
260	Meridian Data Service Installation, Operation, and Maintenance	5 days
261	Meridian 1 Digital Interface Products	3 days
262	ISDN PRA Installation & Maintenance	3 days
265	ISDN BRI Installation & Maintenance	3 days
266	Meridian Link Installation, Operation, and Maintenance	3 days
321	Network Automatic Route Selection Feature Administration	10 days
340	ACD A-C2 Feature Administration	5 days
343	Meridian MAX Feature Administration	5 days

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Options (if equipped) (Continued)

Course number	Course name	Course length
346	Meridian MAX Installation, Operations and Maintenance	3 days
348	CCR Installation, Operation and Maintenance	3 days
353	CCR Scripting	3 days
361	Meridian Mail Feature Administration	7 days
362	Meridian Mail Installation, Operations and Maintenance	10 days
364	Meridian IVR System Installation and Maintenance	3 days
371	Meridian Mail Network Services	3 days
383	Meridian Administration Tool (MAT)	3 days
224	Option 11 - Installation and Maintenance	5 days
240	Meridian 1 Options 21-81 Maintenance	5 days
253	Option 61C/81 Maintenance and upgrades	4 days
275	Meridian 1 Systems Engineering	3 days
276	Meridian 1 Applications Engineering	3 days
301	X11 Station Moves, Adds, and Changes	4 days
304	X11 Update Seminar - Release 12 to Current	3 days
341	Meridian 1 ACD A-C2 Feature Overview	3 days
354	NAC Feature Administration	3 days
356	Meridian Link/CCR Installation, Operation and Maintenance	5 days
363	Meridian Interactive Voice Response (IVR) Overview and Administration	5 days
366	Meridian IVR Advanced Application	3 days
367	Meridian Mail Release 9 Update	3 days
390	IDSN PRI Application and Feature Administration	5 days

COAMS technical support fees

COAMS technical support fees depend on Meridian 1 product status. See “Meridian 1 hardware/software status” section to determine hardware/software status.

Telephone support

The following table provides the schedule and fees applicable to telephone support.

Telephone support for Meridian 1 (Options 11-81C)

Schedule	Current/active/sustained	Manufacture discontinued
7 a.m. to 7 p.m. CST Monday thru Friday	$300.00 per hour	$600.00 per hour

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Telephone support for Meridian 1 (Options 11-81C)

7 p.m. to 7 a.m. CST Monday thru Saturday	$450.00 per hour	$900.00 per hour
Sunday/Holiday	$600.00 per hour	$1,200.00 per hour
Note: Minimum one hour billing.		

On-site support

The following table provides the schedule and fees applicable to on-site support.

On-site support for Meridian 1 (Options 11-81C)

Schedule	Current/active/sustained	Manufacture discontinued
8 a.m. to 5 p.m. CST Monday thru Friday	$1,650.00 (8 business hours)	Not supported, contact your distributor
5 p.m. to 8 a.m. CST Monday thru Saturday	$325.00 per hour	
Sunday/Holiday	$3,300.00 per day	
Note: Minimum one day billing plus travel and living expenses.		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MERIDIAN 1
CUSTOMER OWNED AND MAINTAINED SYSTEMS (COAMS)
REGISTRATION FORM

Please complete the form in its entirety. Authorized Signature is required. It is advisable that you keep a copy of the completed form for future registration.

System Serial Number: _____

System Type and Model (e.g., Option 11C, SL-1, STE) _____

Software Generic and Issue (e.g. 1811, 19.32) _____

Customer Name:_____

Billing Address: _____

_____

Installation Address:_____

_____

Type of Business _____

Name and Telephone Number of Site Manager: _____

Please include printouts from LD22 REQ TID/REQ PRT TYPE PKG/REQ ISS

and Software Option and Serial Numbers

Name and Address of Distributor From Whom Materials Will Be Obtained:

_____

_____

_____

List of employees authorized under Maintenance Qualification Program (Use separate sheet if necessary.)

	Tech 1	Tech 2	Tech 3	Tech 4
Name:	_____	_____	_____	_____
Social Security #:	_____	_____	_____	_____
Name and Date of Training Courses	_____	_____	_____	_____
	_____	_____	_____	_____
	_____	_____	_____	_____
	_____	_____	_____	_____

I hereby certify that I have read the COAMS policy, agree to its terms and have verified that the above information is accurate and complete.

Signature _____ Date _____

(Authorized Signature Authority) (Title)

RETURN TO

SL-1: Nortel (Nortel Networks)
COAMS Administrator
2100 Lakeside Blvd., Mail Stop: 468/02/A40
Richardson, TX 75082-4399

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Administration Tools

The following list of Meridian Administration Tools (MAT) standard price item packages has been developed for use by authorized Meridian 1 distributors. These packages are not to be resold to end-user customers.

NTZK37AA and NTZK37BA are intended for use by Distributor service personnel who perform pre- or post-installation station administration database programming of Meridian 1 systems.

Order code NTZK37AA requires that a “Meridian Software License for MAT Single Location with Multiple Users” be on file with Nortel Networks for each package purchased. This license is intended to grant the right to make copies of MAT software for use by Customer Service Representatives (CSRs) within a single Customer Service Center location. Please see the referenced software license for complete details.

Order code NTZK37BA requires that a “Meridian Software License for MAT Multi-Location with Multiple Users” be on file with Nortel Networks for each package purchased. This license is intended to grant the right to make copies of MAT software for CSRs supporting any Customer Service Center location within the Distributors’ organization within the fifty states and the District of Columbia. Please see the referenced software license for complete details.

Order codes NTZK46AA and NTZK46BA provide an upgrade to MAT Release 3. See the “Reference Notes” section of the Enterprise Solutions product catalog for complete details.

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

The MAT new sales and upgrade packages and associated pricing are described as follows:

MAT matrix of distributor packages

Order Code	Description	Package contents	CLP (Note 1)
NTZK37AA (Note 2,3)	Single Location Station Administration	Distributor Common Services Station Administration Module Common Services User Guide Station Administration Module User Guide	$3,230
NTZK37BA (Note 2,3)	Multiple Location Station Administration	Distributor Common Services Station Administration Module Common Services User Guide Station Administration Module User Guide	$60,000
NTZK46AA (Note 2,4)	Single Location Station Administration Upgrade	Distributor Common Services Upgrade Station Administration Module Upgrade Common Services User Guide Station Administration Module User Guide	$325
NTZK46BA (Note 2,4)	Multiple Location Station Administration Upgrade	Distributor Common Services Upgrade Station Administration Module Upgrade Common Services User Guide Station Administration Module User Guide	$10,000

Note 1: No discounts apply.

Note 2: For distributor use only. Not to be resold to end-user customers. MAT Release 3 is compatible with X11 Release 14, 17, 19, 20, and 21 on Options 21 through 81. For Option 11, MAT Release 3 is compatible with X11 Release 18, 20, and 21.

Note 3: "MAT Software License for Single Location with Multiple Users" must be on file with Nortel Networks.

Note 4: Upgrades MAT Distributor Common Services and Station Administration Module to Release 3.

Meridian 1 Security Services Offerings

The Meridian 1 Security Services consist of the following items.

- Meridian 1 Security Audit
- Meridian 1 Security Consulting Services
- Meridian 1 Security Seminar

Meridian 1 Security Audit

The audit provides an evaluation of current system configuration providing detailed remote analysis of all sets and trunks on a Meridian 1/SL-1 system. Also included is analysis of the following data.

- Customer
- Configuration
- Route
- Basic/Network Automatic Route Selection
- Direct Inward System Access
- New Flexible Code Restriction

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

- Code Restriction
- System Speed Call
- Automatic Call Distribution
- Basic/Network Authorization Code
- Multi-Tenant information stored in the system data blocks

An analysis of Meridian Mail is also performed which consists of the Voice Menus, Thru-Dialers, FAX on demand, Voice Security Options Screens, and Voice Mailboxes.

Audit results consist of a written report detailing findings of current system configuration and possible vulnerabilities. Accompanying the findings are detailed recommendations for increasing security.

The Meridian 1 Security Audit is performed on customer or distributor provided copies of the required database information. As an option Nortel Networks can download this information, at an additional hourly charge, for customers or distributors who do not have the available resources to download the system data. Meridian Mail data cannot be downloaded into a readable format on a capture file and must be accessed and evaluated on-line. A 1200 baud modem (minimum) is required at the customer's site for system access. Hourly rates apply.

Meridian 1 Security Consulting

Nortel Networks Security Consultants can help develop a corporate security policy or review existing policies and test compliance. We can supplement existing corporate security activities by providing a view from the outside. For large companies we can even provide on-site training for telecommunications managers enabling them to audit their own systems. Our security consulting services are available at a daily rate plus travel and expenses.

Meridian 1 Security Seminars

Nortel Networks Security Consultants also provide Security Seminars. Our program consists of a six hour workshop that details what to review in the Meridian 1 and Meridian Mail systems to ensure that both are secure. The charge for the seminar is provided at the current rate of $1,750.00 as well as travel and living expenses.

For these services contact Global Professional Services 918-971-4811 (ESN 450-5468).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Factory Upgrade Services

The following table provides the available Meridian Mail upgrade services.

Meridian Mail Support Service Packages

Order code	CPC	Description	Unit CLP	Dist. Disc.	Repair CLP
SV000098	A0666818	MM Functionality Service Fee	$1000	H	N/A
SV000099	A0666819	MM 2-24 Upgrade Service Charge	$2,000	H	N/A
SV000100	A0666820	MM 25-48 Upgrade Service Charge	$4,000	H	N/A
SV000101	A0666821	MM 49-64 Upgrade Service Charge	$6,000	H	N/A
SV000102	A0666822	MM 65-96 Upgrade Service Charge	$8,000	H	N/A
Note: Order these service products from Santa Clara.					

Product Catalog

Nortel Networks provides each distributor a reasonable number of product catalogs on CD free of charge. If any distributor experiences any difficulty using the CD, please contact Nortel Networks at 800 321-2649, select 6, then 5.

Along with Nortel Networks' effort to be environmentally responsible, Enterprise Solutions elected to eliminate the paper distribution of the Product Catalog. The Product Catalog is available on CD free-of-charge. The CD format is multi-platform allowing both PC and Macintosh use from one CD. Each CD includes the browser and is password protected.

If you still require a paper copy of the Product Catalog you may order one using the following order codes and the Product Catalog order form provided.

Note 1: Purchase order must be included with your order form.

Note 2: Please send or fax order form to location shown on form as product catalog orders can not be entered via EDI.

Product Catalog order codes

Order Code	Description	Unit price
NT2K33AA	Meridian 1 Product Catalog binder set	$50.00
NT2K34AA	Meridian 1 Product Catalog contents	$150.00

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Nortel Networks
Meridian 1 Product Catalog
Order Form

Date _____

Bill to:		**Ship to:**	
Name		Name	
Company		Company	
Address		Address	
City		City	
State		State	
Country		Country	
Zip		Zip	
Fax #		Fax #	
Department #		Department #	
Phone #		Phone #	
Purchase Order			

Note 1: Postal box address information not valid for shipment.

Note 2: Completed purchase order must be included for order fulfillment. Orders cannot be placed via EDI.

Quantity	Order Code	CPC Code	Description	Unit Price	Total price
	NT2K33AA	A0804711	Meridian 1 Product Catalog binder set	$ 50.00	
	NT2K34AA	A0804713	Meridian 1 Product Catalog contents	$150.00	

Please send order form and purchase order to:

Nortel Networks
220 Athens Way, Suite 200
Nashville, TN 37228

Attn: Inside Sales

You may fax your order to us at 615 432-5722.
Call us at 615 432-5724, if you have any questions.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Support/Installation and Maintenance

Nortel Networks provides support to authorized distributors on the Meridian 1 family of products. The types of support offered are as follows:

- CTS technical support
- Customer quality engineering support
- Field service installation and maintenance

Meridian 1 CTS technical support

Meridian 1 Customer Technical Support (CTS) organization provides comprehensive third-level support for Meridian 1 family of products through Nortel Networks' authorized distributor network. CTS works with distributor authorized callers to assist in problem recovery. Third-level support services include the following items:

- Remote assistance in problem recovery
- On-site assistance in problem recovery
- Patch insertion

CTS is available for service affecting and non-service affecting problem recovery during regular business hours; Monday through Friday from 7:00 a.m. to 6:00 p.m. excluding Nortel Networks holidays. CTS is available for emergency problem recovery 24 hours a day, seven days a week. Service affecting and non-service affecting problems can be raised to emergency priority outside of regular business hours and will be billed accordingly. A valid PO must accompany these escalation before problem recovery can commence.

CTS support can be obtained by calling 1-800-766-ETAS (1-800 766-3827) and selecting the appropriate menu choice. The call will route automatically.

Technical support fees

The priority of the problem, software status, and business hours determine technical support billing. Software status is defined as follows:

- Current
- Active
- Sustained
- Retired

The following table identifies CTS system support for Meridian 1 family of products based on product status:

CTS software status support

Status	CTS support
Active or Sustained	CTS will diagnose and resolve software problems.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CTS software status support

Retired	CTS support is limited to problem diagnosis.

Refer to “Meridian 1 hardware/software status” section for specific hardware/software component status.

The following table provides the schedule and fees for telephone support.

Emergency telephone support

Schedule	Current/active/sustained	Manufacture discontinued
Normal business 7 a.m. to 6 p.m. Monday thru Friday	$150.00 per call	$150.00 per hour
After hours 6 p.m. to 7 a.m. Monday thru Friday	$150.00 per hour	$300.00 per hour
Saturday, Sunday and Holidays	$150.00 per hour	$300.00 per hour

The following table provides schedule and fees for support on service affecting and non-service affecting reported problems.

Non-emergency telephone support

Schedule	Current/active/sustained	Manufacture discontinued
Normal business 7 a.m. to 6 p.m. Monday thru Friday	$150.00 per call	$150.00 per hour
After hours 6 p.m. to 7 a.m. Monday thru Friday	$300.00 per hour	$450.00 per hour
Saturday, Sunday and Holidays	$300.00 per hour	$450.00 per hour
Note: A valid purchase order must accompany after-hours escalations before problem recovery can commence.		

The following table provides schedule and fees for on-site support.

On-site support

Schedule	Current/active/sustained	Manufacture discontinued
Normal business 7 a.m. to 6 p.m. Monday thru Friday	$150.00 per hour	$300.00 per hour
After hours 6 p.m. to 7 a.m. Monday thru Friday	$300.00 per hour	$600.00 per hour
Saturday, Sunday and Holidays	$300.00 per hour	$600.00 per hour
Note: Minimum eight hours billing per day, plus travel and living expenses.		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

The following table provides schedule and fees for installation and upgrade support.

Scheduled Remote Installation and Upgrade Technical Support (Minimum 7 days notice)

Software Only (includes consultation and system review)	Pre-Support $200.00	w/Standby $300.00	w/On-Line Dedicated $600.00
Basic Hardware/ Software (includes consultation and system review)	Pre-Support $300.00	w/Standby $400.00	w/On-Line Dedicated $700.00
Hybrid Hardware/ Software (includes consultation and system review)	Pre-Support $500.00	w/Standby $800.00	w/On-Line Dedicated $1,300.00

Un-scheduled Remote Installation and Upgrade Technical Support

Schedule	Current/active/sustained	Manufacture discontinued
Normal business 7 a.m. to 6 p.m. Monday thru Friday	$150.00 per hour	$300.00 per hour
After hours 6 p.m. to 7 a.m. Monday thru Friday	$300.00 per hour	$600.00 per hour
Saturday, Sunday and Holidays	$600.00 per hour	$900.00 per hour

Meridian 1 Customer Quality Engineering Support

A Nortel Networks Customer Quality Engineering System Evaluation consists of an assessment of the Meridian 1 system and applications for conformance to Nortel Networks NTP recommended installation specifications. A detailed checklist is used to review the core system and auxiliary applications in following areas:

- environmentals
- power
- grounding
- batteries
- modules
- cabling
- preventive maintenance
- system operation
- software

Installation discrepancies and recommended actions are presented in a follow-up report.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Evaluation requests should be directed to the Manager of Nortel Networks Customer Quality Engineering at 408 565-2789. A PO should be provided at the time the request is made. Billing for a customer Quality Evaluation may be waived if the customer is currently working with CTS and the evaluation is required for problem isolation and/or resolution. Evaluations are billed at the following rates.

Customer Quality Engineering Evaluation fee schedule

Schedule	Hourly fee
8 a.m. to 5 p.m. Monday thru Friday	$150.00 per hour
5 p.m. to 8 a.m. Monday thru Friday	$225.00 per hour
Saturday/Sunday/Holiday	$300.00 per hour
Note: Minimum of eight hours billing per day, plus travel and living expenses.	

For additional information regarding the Customer Quality Engineering System Evaluations, please contact the Customer Quality Manager, located at Nortel Networks - Mission Park in Santa Clara, CA at (408) 565-2789.

Field Service Installation and Maintenance

This section describes some of the possible key service activities performed by Nortel Networks with the purchase of installation and/or maintenance services. These fee-based support services are conducted by the Enterprise Solutions Field Services (ESFS) organization.

Nortel Networks' ESFS organization, headquartered in Minnetonka, Minnesota, provides the following types of on-site support services for Meridian products, depending on the product ordered:

- Installation
- Maintenance

Installation and Maintenance quotes

Installation and maintenance are quoted to meet the specific requirements for that location and equipment configuration. Quotes can be obtained by contacting ESFS Marketing Management at the following location:

Enterprise Solutions Field Services
Marketing Management
9701 Data Park
Minnetonka, Minnesota 55343
(612) 932-8110
(FAX) 612-932-8440

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Technical Support services

The ESFS Customer Support Center provides telephone support (i.e. Help Desk, Answers ‘98).

Service locations

Authorized Distributors may order on-site installation and maintenance services from Nortel Networks for products installed within the Continental United States (CONUS).

Locations eligible for Nortel Networks’ support services must be located within 125 miles of a Nortel Networks Service Center. Nortel Networks ESFS Marketing Management, on a case-by-case basis reviews requests for support services for sites further than 125 miles from a Nortel Networks Service Center for eligibility. Call the ESFS Marketing Management at (612) 932-8110.

Nortel Networks Service Center locations can be found in the *Enterprise Solutions Field Services Zone Manual*. Zone Manuals can be obtained by calling Enterprise Solutions FS Account Management at (612) 932-8110.

On-site installation

Pre-Installation services

Pre-installation services may include the following items:

- Coordinate installation activities from system order to the day the equipment arrives
- On-site survey conducted by installation specialist
- Discussion of the preliminary site plan and additional equipment with the Customer’s facilities and space planning personnel for each installation site
- Review interfaces to CPE
- Coordinate the CPE pre-installation activities through the chairmanship of conference calls (between all parties involved in the installation process) to assure all site requirements are met
- Review the installation site environmental conditions (i.e., space location, commercial power, cabling, and grounding)
- Verify the product order
- Verify other factors critical to the installation
- Discuss implementation schedule
- Discuss roles and responsibilities of Distributor/End-User personnel

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Installation services

Installation services may include the following items:

- Physical installation and setup of the product and related peripherals
- On-site verification activities
- System acceptance testing
- System Design Specialist (SDS services may be requested and quoted separately from installation)

A detailed statement of work is developed as part of the product implementation.

Union labor

A thirty percent (30%) surcharge is added to Nortel Networks' current installation prices for installations in locations where union labor is required. Areas affected by this surcharge may include, but are not limited to, New York, Northern New Jersey, Connecticut, Rhode Island, New Hampshire, Massachusetts, Maryland, Washington D.C., and the Chicago, Illinois metropolitan area.

On-site Maintenance definition

The maintenance services provided by Nortel Networks consist of (1) keeping equipment in serviceable condition or (2) restoring equipment to serviceable condition.

Maintenance service levels

The two available service levels are as follows:

- Standard service level
- 7x24 service level is determined case by case.

The Principal Period of Maintenance (PPM) for "standard" service level corrective maintenance is defined as the hours between 8:00 a.m. and 5:00 p.m., local time, Monday through Friday, excluding Nortel Networks' holidays. A "7x24" Service-Level option may be purchased in place of the "standard" service level. The PPM for "7x24" service-level corrective maintenance is defined as 24 hours per day, 7 days per week, 365 days per year.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Maintenance activities

Scheduled maintenance

Pre-planned actions performed to keep equipment in a specified operating condition by means of systematic inspection, detection, and prevention of a failure. Scheduled maintenance is also referred to as preventive maintenance.

Technical/Telephone software support

The ESFS Customer Support Center provides telephone software support. Telephone software support includes the following items:

- End-user/system administrator support for clarification of documentation
- Problem identification and correction
- Delivery of software updates
- Use and navigation of the system User-Machine Interfaces
- Operational measurements
- Starting, stopping, and unloading applications

Standard Technical Software Support is available during normal working hours (8:00 a.m. to 5:00 p.m. Monday to Friday local time) excluding Nortel Networks' holidays. An unlimited number of calls are accepted from the system administrator (one person and alternate per Meridian 1 private branch exchange [PBX], regardless of the number of Client PCs using the TSAPI system) regarding the Meridian Link TCP/IP line, the Meridian 1 NTS Drive, and/or VISIT FastCall.

Remote diagnosis

Nortel Networks provides remote diagnosis to customers regardless of the level-of-service package purchased. Remote diagnosis permits Field Service personnel to dial into a customer's system to obtain the following items.

- pull reports
- collect data
- run diagnostic tests

Remote diagnosis allows ESFS personnel to perform these functions without disruption to the customer's system. The customer is responsible for maintaining the remote access connections at their site to enable the various Nortel Networks support agencies to conduct remote diagnosis.

Corrective maintenance

Corrective maintenance performed, as a result of system failures will have equipment restored to its original condition.

Repair

The restoration or replacement of equipment components as necessitated by wear, tear, damage, or failure to return the equipment to normal operating condition.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Response time targets

Initial response to all service requests is made by telephone to the end-user site contact.

Emergency response time

Response time targets in emergency or critical situations and service affecting/ major situations during the PPM are as follows:

Emergency response time targets

Site Distance	Phone	On-site
0-75 Miles	2 hours	4 hours
76-125 Miles	2 hours	6 hours
Greater than 126 Miles	2 hours	next day
Note: Nortel Networks uses reasonable efforts to provide on-site, same-day service during emergencies when services are required.		

Non-emergency response time

Response time targets in non-service affecting/minor situations during the PPM are as follows:

Non-Emergency response time targets

Site Distance	Phone	On-site
1-75 Miles	4 hours	Next day
76-125 Miles	4 hours	Next day
Greater than 126	4 hours	TBD

Requests for maintenance when an emergency does not exist, shall be deemed a request for corrective maintenance.

On-site service response time

The local Nortel Networks Field Service Manager has sole responsibility for determining availability of Nortel Networks' Service personnel, reporting on-site, during the period after 5:00 p.m. Monday through Friday, on weekends, and designated Nortel Networks' holidays.

Non-contracted emergency service

Nortel Networks provides emergency-related service for customers not desiring or qualifying for Nortel Networks' contracted service and maintenance, during or outside of the PPM, on an "as available" basis only. Current hourly billable rates and trip charges are assessed for such service.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

DEPOT - Maintenance Services

Plan summary

The Depot plan is designed to provide spare parts and phone support only for our customers. Products supported by the Depot plan are, i.e. Meridian Norstar, Meridian 1 and Companion equipment.

On-site service

When requested, Nortel Networks ESFS will respond to onsite requests for maintenance at T&M rates.

Moves, additions, and changes

Time and Material Labor Schedule for Core M1, Norstar and Companion

(includes Meridian Mail and Norstar Mail)

	Hourly Rate	Overtime Rate	Trip Charge
Sites under warranty/ maintenance with ESFS	$65/hour	$97.50/hour	$60/trip
Sunday and Holiday		$130/hour	$85/trip
Note: On-Site Support is a two hour minimum plus travel charge. Travel and Living charges incurred for sites greater than 125 miles, from the nearest service city, will be additional. Help Desk Phone Support is a one hour minimum at the above rates.			

	Hourly Rate	Overtime Rate	Trip Charge
Sites NOT under warranty/ maintenance with ESFS	$75/hour	$112.50/hour	$75/trip
Sunday and Holiday		$150/hour	$100/trip
Note: On-Site Support is a two hour minimum plus travel charge. Travel and Living charges incurred for sites greater than 125 miles, from the nearest service city, will be additional. Help Desk Phone Support is a one hour minimum at the above rates.			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Time and Material Labor Schedule for Applications

(includes Symposium Call Center Server, Messenger, Web Response Server, Agent, Open Integrated Voice Response, Meridian Mail Net Gateway, TAPI Server, Meridian Integrated Meeting Services, Digital Networking, CallPilot, Desk Top Messaging, etc.).

	Hourly Rate	Overtime Rate	Trip Charge
Sites under warranty/ maintenance with ESFS	$100/hour	$150/hour	$100/trip
Sunday and Holiday		$200/hour	$125/trip
Note: On-Site Support is a two hour minimum plus travel charge. Travel and Living charges incurred for sites greater than 125 miles, from the nearest service city, will be additional. Help Desk Phone Support is a one hour minimum at the above rates.			

	Hourly Rate	Overtime Rate	Trip Charge
Sites NOT under warranty/ maintenance with ESFS	$115/hour	$172.50/hour	$115/trip
Sunday and Holiday		$230/hour	$140/trip
Note: On-Site Support is a two hour minimum plus travel charge. Travel and Living charges incurred for sites greater than 125 miles, from the nearest service city, will be additional. Help Desk Phone Support is a one hour minimum at the above rates.			

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System/Software Orders and Upgrades

New system orders

This section outlines the ordering procedures when placing a new system order. Included are the following requirements:

- Distributor information
- Minimum new system order
- Special new system software ordering

When placing a new system order, both hardware and software components must be specified.

New system orders contain the hardware and software required to complete a functioning system configuration.

Meridian 1 Options 11C-81C

Hardware/software registration forms for Meridian 1 installations are not required. Distributors are registered automatically at the time of order acceptance.

General requirements

The general requirements for Meridian 1 Options 11C-81C orders are as follows:

- All new Meridian 1 Option 11C-81C systems must be ordered with software.
- New Meridian 1 systems utilize usage-based software.
- Minimum terminal number (TN) requirements are as follows.
  - 200 TNs for Options 11C, 51C and 61C
  - 1000 TNs for Option 81C
- Hardware and terminal provisioning must be within the guidelines set forth in the “Nortel Networks Publications” (NTPs).
- For each **new system, Meridian Mail and Meridian MAX order**, a hard copy of Report 9 from Meridian Configurator can accompany distributor’s PO.

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System and application software orders

One copy per central processor unit (CPU) of system software material is shipped with each system. The cost of additional diskette copies is $500 per set.

> ***Note:*** Additional copies of the QMM42 (Security Data Cartridge) are not provided.

Additional diskette order code

Code	Diskette type
SERV0002	3-1/2 inch Diskette Set

Each new system shipment includes one copy of the application software material including the installation program and a blank set of software media. Following installation, create a complete backup copy. Keep the original media unaltered and use it for maintenance.

System/software upgrades

System upgrades can include changes to hardware and/or software.

Software updates

Software update orders

Software update orders extend the capabilities of existing software, including updating to new/current releases, adding features, or expanding system capabilities.

Nortel Networks continually generates new software releases, these software enhancements and new features are implemented to meet growing end-user requirements. Nortel Networks recommends generic software updates meet newest capabilities whenever possible.

Software update orders can be grouped into the following five types. These are discussed in detail later in the section:

- Generic updates
- Release updates
- Feature additions/deletions
- Software capacity changes
- Software media replacement

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software update charges

Changes (system upgrades, generic updates, release updates, feature additions/deletions, and/or software capacity increase/decreases) to existing software incur software service transaction fees. The number of software service transaction units (599SL1-1) associated with software enhancements determine the software update charges. The software update charge addresses the costs associated with software changes or system upgrades and may include one or more of the following service fees.

- Software Service Transaction
- In-house conversion transaction
- Software RTU

Some examples of software update charges are as follows:

Example of software update charge services

Service	Example
System Upgrade	SL-1LE to Meridian 1 Option 61C
Generic Update	301 to 6111
Release Update	011.13.62 to 1011.13.71
Issue Update	011.12 to 1011.13
Feature Addition/Deletion	Add a Feature
Capacity Change	Add 100 TNs
Software Media Replacement	Worn or damaged tape/disk/cartridge

In-house conversion charge

Nortel Networks performs an in-house conversion if requested by the Distributor. The charge for this conversion (SERV0031) is $100 per software service transaction unit.

Factory Service Program

The following support service package fees are as follows.

Order Code	Description	Unit CLP	Dist. Disc.	Repair CLP
SERV0055	Switch to Switch Conversion Fee	750.00	H	N/A
SERV0056	Loops requiring conversion/balancing	27.50 per loop	H	N/A
SERV0058	Loop Conversion Fee	850.00	H	N/A
SERV0057	Engineered Upgrades	Quoted only	H	N/A

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Enhanced In-house conversions

Enhanced in-house conversions provide special manipulation of an existing data base versus creating an entirely new data base (see Engineered Upgrades within this section). As part of an enhanced in-house conversion, Nortel Networks can solve simple to complex time-consuming tasks, as shown in the following examples.

Switch conversion pricing and order codes

Order code	Description	Unit Price	Quantity	Total
599SL-1	SW Service Transaction fee	$640.00	steps	
SERV0031	Basic In-house Conversion fee	$100.00	steps	
SERV0055	Switch to Switch Conversion fee	$750.00		$750.00
			Grand Total	

Loop conversion pricing and order codes

Order code	Description	Unit Price	# of Loops	Total
SERV0056	Loops Requiring Conversion/Balancing	$27.50		
SERV0058	Loop Conversion fee	$850.00		$850.00
			Grand Total	

What is included at this price?

Nortel Networks assigns a factory engineer to handle your conversion requirements and provides verbal assistance to your technical staff for the preparation of the customers data. Nortel Networks provides a pre-installation conference call to ensure all the necessary information is obtained, performs the actual conversion for you, and provides a post-installation call to ensure a successful software installation.

What needs to be provided by the Distributor?

Include with your conversion PO a completed Factory Service Checklist. This form can be obtained by called 408-565-2001 or 408-565-1779. Order entry forwards this form onto Factory Services to initiate the work.

Post ordering, the Distributor is required to provide directly to Factory Services the following items:

- Data dump on backup media (LD43), if applicable
- Configuration printout of source switch
- Table indicating the target switch loop configuration, i.e. from > to and new
- Description of cards in each card slot in each loop (needed for before and after verification)

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Send the information to the following address:

Nortel Networks
Enterprise Solutions
2305 Mission College Blvd.
Santa Clara, CA 95052-8173

Attn: Factory Service
M.S. B2440

Engineered Upgrades - Quote basis

If you need assistance with creating a new data base configuration, data base engineering or you are adding feature, e.g.; ACD, BARS, NARS, etc.) to an existing system call Nortel Networks Factory Services fax-on-demand for a quote form (408) 565-1779. Once Factory Services has all the information, we will call you with a custom quote. If the quote is acceptable to you, the checklist and PO are forwarded (via FAX or EDI) to Customer Service in Mission Park with the order code SERV0057.

Applicable systems

The Basic In-house Conversion and Enhanced In-house Conversion target machine types are 21E, 51, 51C, 61, 61C, 71, 81, and 81C. Nortel Networks has the ability to upgrade from previous X11 machine types to the current version of these target systems.

Conversion ordering information

The following table lists the conversion order codes and descriptions.

Order code	Description
599SL-1	Software Service Transaction Unit
SERV0031	Basic In-House Conversion
SERV0055	Switch to Switch Conversion
SERV0056	Loops Requiring Conversion/Balancing
SERV0058	Loop Conversion
SERV0057	Engineered Upgrades - Free Custom Quote > Order Service SERV0057

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MISSION PARK, SANTA CLARA

Enhanced In-House Conversion Checklist
Factory Service
PROVIDE WITH PURCHASE ORDER

NTI #: _____ FSP Control #: _____

Date: _____

Originator Name: _____

Contact Name: _____

Phone Number: _____

Distributor: _____

End-User Company: _____

Required Ship Date: _____

Customer Installation Date: _____

Description of work to be provided:

_____

_____

_____

_____

System Type: _____

System Serial Number: _____

Software Release: _____

Current Loops: _____

Current Options: _____

Peripherals: _____

Aux. Processors: _____

System Password: _____

Post order - forward the following to Nortel Factory Services, 2305 Mission College Blvd., Santa Clara, CA 95052-8173, MS B2440

___ Data dump of backup media, if applicable
___ Configuration printout
___ Table indicating the target switch loop configuration, i.e., from > to and new
___ Description of cards in each card slot in each loop (before and after verification)

_____

For Factory Service Use Only:

Date Order Received: _____ Date Material Received: _____

Solution: _____

Call Back Date: _____

Total Price: _____ Total Hours: _____ Date Returned to Customer: _____

Completed: _____ Date: _____ Engineer: _____

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MISSION PARK, SANTA CLARA

Factory Service

Engineered Upgrade Quote Form

Fax to FSP 408 565-2579

NTI #: _____ FSP Control #: _____

Date: _____

Originator Name: _____

Contact Name: _____

Phone Number: _____

Distributor: _____

End-User Company: _____

Request Return Quote by: _____

Description of work to be accomplished:

_____

_____

_____

_____

System Type: _____

System Serial Number: _____

System Password: _____

Software Release: _____

Current Loops: _____

Current Options: _____

Peripherals: _____

Aux. Processors: _____

_____

For Factory Service Use Only:

Date: _____

Engineer: _____

Solution: _____

Call Back Date: _____

Quoted Price: _____ Projected Time Frame: _____

Anticipated Return to Customer: _____

_____

For Order Entry Use Only:

Date Ordered: _____ Price: _____

Discount: _____ [ ] MSA?

Rep ID: _____

Order Entry: Return this form to Factory Service to begin service.


For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Generic/release updates

Generic update

A software generic is the feature base and system option that a certain family of software is related. The X11 generic software family is the only software generic family that has “releases.” A Generic update is when software capabilities are expanded by changing the software family.



Release update

Within the X11 software generic, a software release is a particular set of features/functionality. A release is a version of software within the X11 generic family. A release update entails a release change within the same generic family.

Generic/release software issues

During the active and sustained software phases, Nortel Networks releases new software issues (or versions) that enhance features and quality in the release. Issue numbers are not necessarily sequential.

The following table lists the latest generic/release available by system type:

Available generic/release types

System	Last software release supported
L, VL, A	X05
M	X11 Release 7
LE, VLE, XL	X11 Release 9
S	X11 Release 12
MS, N	X11 Release 13
XN	X11 Release 14
ST	X11 Release 17
21	X11 Release 17
RT, NT, XT	X11 Release 21
STE, 21E	X11 Release 21
51, 61, 71	X11 Release 21

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Available generic/release types

System	Last software release supported
51C, 61C, 81, 81C	Current Release

Option 11/11E/11C available generic/release types

System	Last software release supported
Option 11	X11 Release 18
Option 11E	X11 Release 21
Option 11C	Current Release

Software service transaction matrix

The software service transaction fees for generic/release updates are based on the generic/release update software service transaction matrix.

Use the following generic/release software service transaction matrix to determine the number of software service transaction units required with generic/release updates. Identify the applicable transaction block on the matrix to determine the appropriate software update charge. The number within each block denotes the software service transaction units required for each type of update. **Each software service transaction unit is multiplied by the rate of $650.**

Generic/release update software service transaction matrix

From	X11.17 (Note 1)	X11.19 (Note 1)	X11.21 (Note 1)	X11.22 (Note 1)	X11.23 (Note 2)	X11.24 (Note 4)	X11.25 (Note 5)
X03 (Note 3)	7	7	7	7	7	7	7
X04 (Note 3)	7	7	7	7	7	7	7
X05 (Note 3)	7	7	7	7	7	7	7
X07 (Hotel/Motel) (Note 3)	6	7	7	7	7	7	7
X37 (Hotel/Motel) (Note 3)	6	7	7	7	7	7	7
X09	6	6	7	7	7	7	7
X11.1	5	6	7	7	7	7	7
X11.2	5	6	6	7	7	7	7
X11.3	5	5	6	6	7	7	7
X11.4	4	5	6	6	6	7	7
X11.5	4	5	5	6	6	6	7

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Generic/release update software service transaction matrix

From	X11.17 (Note 1)	X11.19 (Note 1)	X11.21 (Note 1)	X11.22 (Note 1)	X11.23 (Note 2)	X11.24 (Note 4)	X11.25 (Note 5)
X11.7	4	4	5	5	6	6	6
X11.8	3	4	5	5	5	6	6
X11.9	3	4	4	5	5	5	6
X11.10	3	3	4	4	5	5	5
X11.12	2	3	4	4	4	5	5
X11.13	2	3	3	4	4	4	5
X11.14	2	2	3	3	4	4	4
X11.15	1	2	3	3	3	4	4
X11.16	1	2	2	3	3	3	4
X11.17	1	1	2	2	3	3	3
X11.18		1	2	2	2	3	3
X11.19		1	1	2	2	2	3
X11.20			1	1	2	2	2
X11.21			1	1	1	2	2
X11.22				1	1	1	2
X11.23					1	1	1
X11.24						1	1
X11.25							1

Note 1: Requires 3-1/2 inch 4-Megabyte floppy-disk operation.
Note 2: Available on either 3-1/2 inch 4-Megabyte floppy disks or CD-ROM (CD-ROM requires IODU/C card [NT5D61]).
Note 3: Requires database reconstruction for all systems upgrading from these releases.
Note 4: Requires IODU/C card (NT5D61).
Note 5: Requires IODU/C card (NT5D61) or the CP PII Multi-Media Disk Unit (NT4N43).

Feature addition or deletion

Feature additions are the addition of new features available within software generic/release or in conjunction with generic/release updates. Charges for adding features include the current price (RTU fees) of the feature added, plus the applicable software service transaction fee (minimum $650).

Existing features may be deleted to free additional memory if the feature is no longer required. In this case, the minimum software service transaction fee of $650 applies (599SL1-1). Nortel Networks offers no credit for deleted features. Nortel Networks tracks system features purchased and deleted by system serial number. The end user can reestablish a deleted feature at the minimum software service transaction fee of $650, plus RTU charges due to TN, Automatic Call Distribution (ACD) Agent, or Digital Subscriber Loop (DSL) growth.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Capacity change

System software capacity

Capacity changes are the expansion or reduction of TNs, ACD Agents, and/or DSLs. This can be done within existing system type and software generic/ releases, or in conjunction with release updates and/or system updates.

"Size" the software at a reasonable level to support at least a system's "equipped" port (TN) and ACD-agent capacity as indicated in the following chart.

Terminal Number (TN)

A TN is the software designation of a logical termination point, either physical or virtual, defined in the Meridian 1 software.

Example TNs per interface requirements

Quantity	Interface	TNs
700	Voice Lines	700
128	Trunk Lines	128
3	Consoles	6
325	Voice/Data Lines	650
4	PRA Links	96
12	Meridian Mail Ports	12
20	BRI DSL	40
	TOTAL TNs	1,632

ACD Agent

ACD agent is any TN with a directory number (DN) designated as an ACD DN in Meridian 1 software.

DSL

The software designation of a Basic Rate Interface (BRI) physical connection that accommodates two B-channels.

Capacity expansion/reduction charges

Charges for expanding TN, ACD Agent, and/or DSL capacity include the current price (RTU fees) of all applicable features, plus the software service transaction fee (minimum $650).

For TN, ACD Agent, and/or DSL capacity reductions, the minimum software service transaction fee of $650 applies. Nortel Networks offers no credit for reducing capacities and RTU value is forfeited.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software media replacement

Replacement of worn or damaged software media is invoiced at the minimum software service transaction fee of $650 (599SL1-1). Return all software media (damaged or not) or applicable RTU fees for current features are invoiced. If the software media is lost, Nortel Networks provides replacement media when requested in writing. Media type is based on system type and software release as follows:

- Systems with software below X11 Release 10 were shipped with tapes.
- Systems with X11 Release 10-14 software were either shipped with or have been upgraded to 5-1/4 inch floppy disk drives.
- Systems with X11 Release 15-17 software were either shipped with or have been upgraded to 3-1/2 inch floppy disk drives.
- Systems with X11 Release 18-22 software were either shipped with or have been upgraded to 3-1/2 inch 4-Mbyte floppy disk drives.
- Systems with X11 Release 23 software are shipped with either 3-1/2 inch 4-Mbyte floppy disk drives or CD-ROM drives.
- Systems with X11 Release 24 software are shipped with CD-ROM drives.
- Systems with X11 Release 25 software are shipped with CD-ROM drives or the CP PII Multi-Media Disk Unit.

At times replacement software is replaced with a higher issue; e.g., one damaged X11 Release 15.51 diskette is replaced by a whole set of Release 15.57 diskettes.

Upgrades

Norstar upgrades vary by product type.

Upgrade packages for Norstar are available for all cartridge-based systems. Order the upgrade package for the systems current software level (DR2, DR3, DR4 or Centrex) to get the DR5 or Centrex+ capabilities.

Meridian 1 Option 11 upgrades

Updates are used as follows:

- Move a system from one feature set to another (e.g., General Business to Enhanced Business)
- Move a system from one software release/issue to another (e.g., from Release 21 to Release 22).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Ordering software update

When ordering a software update, you must provide the order information listed in the “Ordering Process and Procedures” section under “Required order information.” Contact Customer Response Center for the appropriate form.

Order one of the software updates using the appropriate order code(s) for the activity requested. For either of the previously mentioned software update activities use one of the software update order codes not a new system order code. When updating a system with one or more additional levels of software (100 TN increments above the base level of 200 TNs) the order codes for both the update and the additional increments(s) must be ordered.

Depending on the Option 11 system type (i.e., Option 11/11E or Option 11C), when a software update is purchased, a new cartridge or new software keycodes may be shipped and an RA number is provided for the return of the used cartridge (Option 11/11E only). Invoicing for the new cartridge/software keycodes and any additional TN increments occurs upon shipment. When the used software cartridge is returned, Nortel Networks issues credit for the then current price of the returned cartridge and any associated additional TNs.

Please refer to the Option 11 Reference and Pricing Reference sections for detailed descriptions of software ordering procedures and codes.

Replacing damaged cartridges (Options 11 and 11E only)

To replace a damaged cartridge, please specify the appropriate order code for a software update/replacement and, if applicable, the order code for the additional TN increments on your PO, then Nortel Networks can ship new cartridge to you. Invoicing for the new cartridge and additional TN increments occurs upon shipment. When the damaged software cartridge is returned to Nortel Networks credit is issued for the current price as listed in the Product Catalog for the returned cartridge and incremental TNs, where applicable.

Replacing damaged Option 11C daughterboards

For an Option 11C daughterboard failure, a blank NTDK21AA daughterboard can be programmed from a PCMCIA card. The security device and keycode can be reused. In the event of a DOA, the complete software package, i.e., NTSF8001, must be replaced.

Updating Meridian Mail Card option

See “Message Processing Products” chapter in the Meridian 1 catalog for detailed information.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Options 21 - 81C upgrades

Applicable RTU fees

Pre-X11 Rel. 23 upgrades to Rel. 23 on CD-ROM media - Special Policy

With the introduction of the IODU/C card and CD-ROM delivery of software on Release 23, a special policy is introduced to ensure the correct software media type is shipped to Option 51C-81C upgrade systems. All Option 51C-81C systems that upgrade to Release 23 from previous releases receive automatically a Release 23 on 4-Mbyte media unless a a new SERV0080 code is ordered to indicate the desire for Release 23 on CD-ROM software. Once this new SERV0080 code has been ordered, all subsequent releases of software will be shipped via CD-ROM format. Only customers who have purchased or plan to purchase an IODU/C card either separately or as part of a system upgrade package should use the SERV0080 order code. The SERV0080 code is offered at no charge.

Pre-X11 Release 22 to X11 Release 22 updates

The end user receives all features on their existing system plus additional options available in the latest equivalent feature offering at no additional charge when updating from pre-X11 Release 22 to X11 Release 22.

Pre-X11 Release 15

Pre-X11 Release 15 software RTU fees are one-time charges to use a feature in conjunction with a specific SL-1 system type/CPU. This one fee/one system relationship necessitates return of all existing software media when a software update order takes place.

X11 Release 15 or 16 to X11 Release 17 - special policy

A special policy exists for X11 Release 15 or 16 systems that exceeded their registered TN capacity allowing for an update to Release 17 at no additional software RTU fee(s). This special policy increases the software TN capacity level supporting the existing number of system TNs meeting end-user’s expectations relative to perceived software capacity.

This policy does not apply, if growth beyond the registered TN capacity has not occurred. Software update orders to these systems are processed in a normal fashion.

This special policy only affects TN capacity. When updating to Release 18, the ACD Agent level must still be selected as described in “Selecting TN and ACD levels for software updates.”

Selecting TN and ACD levels for software updates

When updating software from pre-Release 15 to Release 22, distributors must select the TN level required in all cases and the ACD agent level required when ACD is utilized. When updating to Release 22 from Release 15-17, the ACD agent level must be selected when ACD is utilized in the current system. These levels must be specified when the software update is ordered.

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Exceeding TN/ACD limits on original system

For software updates, additional software RTU charges apply if the TN and/or ACD agent levels selected are greater than the limits (based on the original system type). Refer to the following Software Update/System Capacity Matrix for these limits.

Software update/system capacity matrix

Existing system type	Line size	TN capacity	Free maximum TN level	Agent capacity	Free maximum agent level
S	140	200	2	60	3
A	300	400	4	60	3
M	400	500	5	120	6
MS	400	500	5	120	6
L	1000	1500	11	120	6
LE	1000	1500	11	500	13
N	1200	1500	11	500	13
VL	2500	3000	14	200	10
VLE	3000	4000	16	500	13
XL	4000	5000	18	1000	18
XN	5000	6000	20	1000	18
ST	600	800	8	120	6
STE	N/A (Note 3)	N/A (Note 3)	N/A (Note 3)	N/A (Note 3)	N/A (Note 3)
RT	600	800	8	400	12
NT	1500	2000	12	500	13
XT	7000	8500	25	1000	18
21A	N/A (Note 1)	N/A (Note 1)	N/A (Note 1)	60	3
21	N/A (Note 1)	N/A (Note 1)	N/A (Note 1)	120	6

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software update/system capacity matrix

Existing system type	Line size	TN capacity	Free maximum TN level	Agent capacity	Free maximum agent level
21E	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)
51	N/A (Note 1)	N/A (Note 1)	N/A (Note1)	300	11
51C	N/A (Note 2)	N/A (Note2)	N/A (Note2)	N/A (Note2)	N/A (Note2)
61	N/A (Note 1)	N/A (Note1)	N/A (Note1)	500	13
61C	N/A (Note 2)	N/A (Note2)	N/A (Note2)	N/A (Note2)	N/A (Note2)
71	N/A (Note 1)	N/A (Note 1)	N/A (Note 1)	1000	18
81	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)
81C	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)	N/A (Note 2)

Note 1: Transition policies for TNs are not applicable for Options 21-71 since these systems were introduced with X11 Release 15.

Note 2: Transition policies are not applicable for Options 21E, 51C, 61C, 81, and 81C since these systems were introduced with or after X11 Release 18.

Note 3: Transition policies are not applicable for SL-1 STE since it was introduced with X11 Release 18. This system type cannot be purchased new; it is achieved through upgrading an ST system.

Updating Release 15/16 to Release 17/18

This policy applies to systems updating to Release 17 or 18 from Release 15 or 16 with growth beyond the registered TN capacity. As mentioned previously, existing policies for earlier releases updating to Release 17 or 18 remain unchanged. If you have any questions, call your Nortel Networks Customer Response Center Representative.

Customers who have exceeded their registered TN capacity must provide a software update order form including the system TN count (specific to the current Release of the system) before updating to Release 17 or 18.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

TN count for X11 Rel 15.55 and later through Rel 16 (all issues)

Print out the Incremental Software Management (ISM) information from Overlay 22 to determine the number of system TNs. The actual number of TNs is the sum of the used TNs and ACD agents (AGNT).

Code

TNs	2000	Left	16	Used	1984
AGNT	100	Left	56	Used	44
ACDN	50	Left	16	Used	34

In this example, the system shows the number of TNs to be 1984, but the actual number is 2028, the sum of the TNs and AGNT counts. Therefore, additional TNs are required for this system to run on Release 17 or 18. The solution is to increase the total TN capacity from 2000 to 2500, the next increment. Although ACDNs are listed in the example, they are not used for pricing. Submit the ISM printout with the software update order.

TN count for X11 Release 15 (pre Release 15.55)

The previous example is not a true example as ISM was not implemented until Release 15.55. In releases earlier than X11 Release 15.55 the ISM information that prints the total number of TNs and ACD agents (AGNT) is not available. Instead, we request the complete TN Build (TNB) list printed from Overlay 20 and totaled. Only the first page of the TNB list must be submitted with the order. Do not send the entire TNB list unless requested by Customer Response Center; use the TNB only as a guide for counting the total number of TNs.

Placing software update order

Use the following steps to place a software update order.

1. Find the system TN count.
2. Complete the update order form or indicate directly on the PO the total number of system TNs installed on the system and the new TN capacity required due to growth beyond the registered and purchased capacity.

   Note: The actual number of system TNs is the sum of the used TNs and ACD agents shown on the ISM listing from Overlay 22.

3. In addition, indicate the end user's X11 software release and the current registered (and purchased) TN capacity.
4. Send the Overlay listing described above, the PO, and the completed form.

   Note: In lieu of using the form, include the required information directly on the PO.

Software update order form

Use the following form before updating to Release 17, 19,21, 22, or 23.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

X11 Release 15/16 to Release 17, 19, 21, 22, or 23 software update - TN capacity

This form is only required if registered TN capacity has been exceeded. Include appropriate Overlay listing described in special policy

Provide the following information:

Date:_____ Name: _____

Distributor's Name: _____

Address: _____

Phone Number: _____

End User Name:_____

Current X11 Software Release and Registered TN Capacity:_____

Part 1. Actual System TN Count

Pre-X11 R15.55
TOTAL SYSTEM TN COUNT* _____
REQUIRED TN CAPACITY _____
*From manual total of TNB list

Pre-X11 R15.55 - R16
System TNs** _____
ACD Agents** _____
Total system TNs*** _____
REQUIRED TN CAPACITY
** From Overlay 22 ISM Printout
*** Sum of System TNs and ACD Agent

Part 2. Customer Selected ACD Application Parameter

Only applicable when updating to Release 19 and ACD is being utilized on existing system.

Current System ACD Agent Capacity _____

Selected ACD Agent Capacity _____

The customer can specify the ACD Agent capacity of their current system (refer to Software Update/System capacity Matrix) or a lesser number at no additional charge for their current features. Specifying the number of agents higher than their system maximum and / or adding features will be charged based on current prices. The ACD Agent capacity can not exceed the system TN capacity.

Please complete one form per Meridian 1 location.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Web Based Services

In keeping with our commitment to “Customer Value” we have aggressively enhanced our list of “Global” web based services for our business partners to include a Keycode Retrieval System (KRS). By working with members of the Distributor Alliance Council (DAC) we have developed the most intuitive and comprehensive web application to date for the retrieval of Customer Keycodes.

We are confident that the use of this tool will better fulfill our commitment to our partners for quality customer service and improved order management. This tool provides our partners the ability to retrieve both current and historical keycodes for their customers with 24 x 7 availability. In addition, we provide a complete set of tools with which to manage keycodes, including the capability to compare keycodes.

To access this application you must first complete the registration process which begins by completing the form found at the following URL http://www.nortelnetworks.com/servsup/krs/ after the registration form is completed we will notify you with your User ID and Password.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Applications - Special Policies

This section contains exceptions to the general policies, process, and procedures described in other sections of this product catalog. These exceptions apply only to the following specific Meridian 1 product applications:

- SYMPOSIUM Agent
- SYMPOSIUM TAPI Server
- SYMPOSIUM WebResponse Server
- Open IVR
- Meridian Mail Reporter (MMR) Service Plan
- SYMPOSIUM Messenger
- Meridian Passport Software Policy

SYMPOSIUM Agent

This section describes the services provided by the Enterprise Solutions Field Service and SYMPOSIUM Professional Services in conjunction with SYMPOSIUM Agent. SYMPOSIUM Agent is software that is installed on customer-provided Windows computers to enables call center agents to provide more intelligent and personalized customer.

SYMPOSIUM Agent Software Support (SV000149)

One year of software support is provided with the SYMPOSIUM Agent. The service is effective 10 business days after the product is shipped by Nortel Networks. To continue receiving this support, SV000149 can be purchased for each installation site on an annual basis. Access to this service is obtained by calling 1-612-932-8343. This software support includes the following services:

- Assisting end users or distributor support personnel with general answers to questions about the installation of SYMPOSIUM Agent.
- Accepting the first call for help from a distributor support technician or end user's lead operator.
- Assisting end users in general use of SYMPOSIUM Agent operation. Assistance with the implementation of SYMPOSIUM Agent integrations with end user's applications and databases is not included.
- Accepting problem reports and design change requires submitting them to the appropriate Nortel Networks design organization.
- Provision of any generally release up-issues or problem fixes.

Telephone assistance is available during normal 8 a.m. to 5 p.m. business hours (Central time).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SYMPOSIUM Agent INSTALL - PREP (SV000147)

This support includes up to 8 hours of remote coordination of the installation of SYMPOSIUM Agent application software on the agent's desktop PCs. This support does not cover TAPI Server installation, client server connectivity, installing TAPI Remote Service Provider software on client PCs, or any integration with third-party applications (such as using DDE, OLE, or Keystroke macros). Included is:

- One conference call to review the completed pre-installation checklist prior to the start of the installation.
- Assistance via phone while the distributor or end user performs the installation of the five (5) initial clients at a new site. General answers to questions about the installation of SYMPOSIUM Agent will be answered however, this does not includes specific questions about implementation with SYMPOSIUM Agent and end user's databases.
- Installation assistance is performed during normal 8 a.m. to 5 p.m. business hours (Central time).

SYMPOSIUM Agent INSTALL - PRO (SV000148)

The INSTALL-PRO provides a Nortel Networks Professional Services Engineer (PSE) on site for one eight hour day to install SYMPOSIUM Agent and/or to provide installation assistance to the end user's/distributor's field technicians. Included are:

- At least one conference call to review the completed pre-installation checklist prior to Nortel Networks performing on-site installation.
- Installation coordination from receipt of order through completion of installation.
- Installation of SYMPOSIUM Agent using Windows 95 Note Pad as the database to provide operational verification. Assistance with the implementation of SYMPOSIUM Agent integrations with end user' applications and databases is not included.
- Normally 5 to 8 seats of SYMPOSIUM Agent can be installed in one day.
- On-site installation is performed during normal business hours.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SYMPOSIUM Professional Services Order Process

If the end user requires integration services (SYMPOSIUM Agent with Customer's application via DDE, OLE or Keystrokes macros) or customization of CallGuides, then the SYMPOSIUM Professional Services group may be contacted.

- Distributor calls 1-800-467-0273 to request SPS support.
- Distributor completes requirements checklist and qualifies the lead information.
- SPS provides a quote and the authorization/contracts documents.
- Distributor accepts the work order and submits a Purchase Order within 5 days.
- SPS performs implementation of authorized work effort.

SYMPOSIUM Professional Services (SPS) can provide customization and integration for SYMPOSIUM Agent.

For more information, call 1-800-467-0273

SYMPOSIUM TAPI Server

This section describes the services provided by the Enterprise Solutions Field Service organization in conjunction with SYMPOSIUM TAPI Server. The SYMPOSIUM TAPI Server is software that is installed on a customer-provided Windows NT server which allows the customer to implement TAPI 2.X compliant application, such as SYMPOSIUM Call Manager or SYMPOSIUM Agent in client-server network environments. Other TAPI-compliant applications developed by Nortel Networks, SYMPOSIUM Partner Program Vendors, or Nortel Networks' Business Affiliates may also be used. The Nortel Networks Business Affiliate Action Line can be contacted at 972 684-1564 for a current list of developers and applications.

TAPI Server Software Support Services (SV000091)

One year of Nortel Networks provided, telephone software support service is provided with the SYMPOSIUM TAPI Server base package. Software support includes the following services:

- Answering general installation questions.
- Accepting the first call for help from a distributor support technician or end user's lead operator.
- Assisting end users in general system operation
- Referring the end user to user manuals when appropriate.
- Accepting problem reports and design change requests submitting them to the appropriate Nortel Networks design organization.
- Provision of any generally release up-issues or problem fixes.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Access to this service is obtained by calling 1-612-932-8303. The service becomes available ten business days after the product is shipped by Nortel Networks. Software Support can be renewed on an annual basis by ordering the Service Package, SV000091.

CTS does not provide technical support services for TAPI Server software but can be called upon to support Meridian Link or other system problems.

> ***Note:*** Nortel Networks' Enterprise Solutions Field Services offer Meridian Link INSTALL ASSIST (SVC1035) which will provide Nortel Networks support via telephone to the Distributor's field technicians as the Distributor's field technicians install Meridian Link.

TAPI Server INSTALL-PREP (SV000088)

Installation requires detailed planning before the first piece of equipment reaches the customer site. If a single item in the installation process is delayed, the entire installation is delayed, diminishing customer satisfaction and reducing profits. Nortel Networks' INSTALL-PREP pre-installation verification service is intended to help ensure a smooth, on-time installation. The INSTALL-PREP service package includes:

- At least one conference call to assist the end user/distributor in understanding the guidelines specified in the Pre-Installation Checklist (i.e.: Meridian 1 PBX minimum release levels, Meridian Link/SCCS Link Upgrades, Windows NT Server/LAN requirements and Client Desktop specifics) prior to the start of the installation
- Installation coordination from receipt of order through scheduling the installation.
- Assistance via phone while the Distributor/End User performs the following:
  - — Installation and configuration of the Meridian Link. This includes the loading and configuring of the Meridian Link software.
  - — Installation and configuration of the Meridian 1 TAPI Server software on the dedicated Windows NT server.
  - — Final system configuration, testing and system operational "fine-tuning" as necessary.
  - — Installation assistance is performed during normal 8 to 5 business hours.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

TAPI Server INSTALL-PRO (SV000089)

The INSTALL-PRO service package consists of everything within the INSTALL-PREP package plus a Nortel Networks Professional Services Engineer (PSE) performing the on-site installation and/or providing on-site installation assistance to the end user's/distributor's field technicians. The INSTALL-PRO service package includes:

- An ENFS Professional Services Engineer will travel to the end user location to provide three eight hour days of the following on-site installation activities:
  - — Assist the Distributor's Technician in the installation and configuration of the Meridian Link. This includes the loading and configuring of the Meridian Link software.
  - — Assist the Distributor/End User's LAN Administrator in the installation and configuration of the Meridian 1 TAPI Server software on the dedicated Windows NT server.
  - — Assist the Distributor/End User personnel in final system configuration, testing and system operational "fine-tuning" as necessary.
  - — Verify Maintenance Modem functionality (call to CSC for remote test).
  - — Installation activities will be considered complete when the Distributor/ End User signs the Nortel Networks "Order Acknowledgment".
- On-site installation is performed during normal business hours.

Installation Support Limitations

Purchase of either SYMPOSIUM TAPI Server INSTALL-PREP or PRO is strongly recommended to ensure smooth installation. If neither INSTALL-PREP or PRO are purchased, Enterprise Field Service will provide fee-based installation support to Distributor personnel who have attended TAPI Server Installation training.

SYMPOSIUM WebResponse Server

Use the following order codes to request the various services offered by Nortel Networks Enterprise Solutions.

Installation and support options

Order code	Description	Option type
SV00018	SYMPOSIUM WebResponse Server Installation Service	Installation
SV000183	SYMPOSIUM WebResponse Server Annual Telephone Support	Post-warranty support
SV000182	SYMPOSIUM WebResponse Server Additional One-day Installation Services	Installation

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000184

Symposium WebResponse Server Installation Services

At least two pre-installation conference calls will be chaired by a Nortel-EN/ Field Services Technical Specialist to assist the end user/Distributor in readying the customer-provided Windows NT Server, the end user's LAN/WAN/Internet environment, and the client PCs for use with Symposium WebResponse Server. Complete Symposium WebResponse Server installation activities will be performed by a fully trained Nortel-EN/Field Services Professional Services Engineer. The on-site installation service includes a maximum of five days of labor on the end user's premises to verify the customer supplied Windows NT Server has a working TCP/IP network connection. A Nortel Professional Services Engineer then loads and configures the Sybase software and the Symposium WebResponse Server software onto customer supplied Windows NT Server. Installation also includes the loading and configuring of approximately five client end users with the Symposium WebResponse Server client software, the Sybase Client Software, and build a basic configuration of one Web form on the Client. The end user/Distributor is responsible for the configuring of additional Symposium WebResponse Server Clients. On the Web site server, the Nortel Professional Services Engineer will assist the customer as they load and configure the CGI software onto the customer's Web site and also assist the customer as they load and configure the Entrust software. The Nortel Professional Service Engineers will verify that a “Web surfer” can complete the generic form/transaction and then verify that this generic form/transaction is received at the Symposium WebResponse Server Client PC and that the Client PC can process the form/transaction to closure.

SV000183

Symposium WebResponse Server Annual Telephone Support

The Nortel-EN/Field Services Customer Support Center (CSC) will accept all requests for assistance from the customer's Symposium WebResponse Server administrator. The CSC can assist the end users in diagnosing Symposium WebResponse Server operational problems and then recommend the appropriate course of action to remedy them. The CSC will also use remote access when appropriate. This cursory level of telephone support will involve general answers to questions about the operation of the Symposium WebResponse Server product and direct the callers to the appropriate documentation when applicable. The telephone support will not provide specific answers about the implementation of Symposium WebResponse Server product in that end user's environment. This service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday. If expert support is required, the caller will be directed to Nortel's Symposium Professional Services organization where a quote for these expert services can be provided.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000182
Symposium WebResponse Server Additional One-Day Installation Services
Includes one eight hour day of on-site software installation activity performed by a fully trained Nortel-EN/Field Services Professional Services Engineer. The installation charges include installation of Symposium WebResponse Server Client Software and the Sybase Client Software onto the end user PCs. The Professional Services Engineer will then perform the appropriate operational verification. Normally 5 to 8 seats can be installed in one day. On-site installation is performed during normal business hours.

Open IVR

This section describes the services provided for Open IVR by the following organizations:

- Enterprise Solutions Field Services (ESFS)
- Enterprise Solutions Customer Support Services (CSS) Applications Development Services (ADS)

See the "Technical Support" section in this catalog for general information about ESFS. Enterprise Solutions/CSS ADS services are described later in this section.

Enterprise Solutions Field Service support

Ordering policy

Open IVR requires the purchase of installation and first-year maintenance. Enterprise Solutions FS provides installation and first-year maintenance. Contact and place orders through Enterprise Solutions FS in Minnetonka, MN, at (612) 932-8110.

Pricing of the ESFS Open IVR services requires custom quoting. Contact ESFS Account Management at (612) 932-8110 to for pricing. Nortel Networks develops the detailed statement of work as a portion of the Open IVR product implementation.

Support services

Available support services for Open IVR are as follows:

- INSTALL-PREP
- INSTALL-PRO
- First-Year Maintenance

  Note: The Open IVR service offerings apply to the Meridian 1 marketplace until Field Introduction, First-Market Applications, or verification-office activities are complete for other Nortel Networks product markets (e.g., SL-100, DMS).

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

INSTALL-PREP

Installation requires detailed planning before any equipment reaches the customer site. If a single item in the installation process is delayed, the entire installation is delayed, diminishing customer satisfaction and reducing profits. Nortel Networks' INSTALL-PREP pre-installation verification service ensures a smooth on-time installation.

The INSTALL-PREP service package includes such things as coordination of pre-installation activities by Nortel Networks technical specialists/field engineers. For a list of pre-installation activities see "Technical Support" section in this catalog.

INSTALL-PRO

The INSTALL-PRO service package consists of everything within the INSTALL-PREP package plus the PSE performing the on-site installation and/or providing on-site installation assistance to the end user's/distributor's field technicians.

For a list of pre-installation and installation activities see "Technical Support" section in this catalog.

Yearly maintenance services

Open IVR requires maintenance support services. Maintenance support services typically includes the following services:

- Accepting the first call for help from the end user's lead administrator
- Assisting end users in general system operation
- Referring the end user to user manuals when appropriate
- Keeping equipment in serviceable condition or restoring it to serviceable condition
- Dispatching Nortel Networks PSEs when on-site assistance is required

Open IVR requires Standard Service Level. The "7x24" Service Level is also available. For more information about support levels, see "Technical Support" section in this catalog.

Post-sales IVR applications development support

Enterprise Solutions/CSS ADS provides the post-sales on-demand IVR applications support. ADS fees are based on the Meridian 1 (Options 11-81) CTS Technical Support fees described in the Meridian 1 Product Catalog, "Technical Support" section. Call 1-800-766-ETAS (1-800-766-3827) to reach ADS.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Support services

Senior Support Engineers, who are experts in the supported product comprise the Enterprise Solutions/CSS ADS organization. These engineers have in-depth experience and qualifications related to C, C++, and UNIX languages, plus relational databases and Novell CNE training. The function is supported by extensive, dedicated, and fully supported lab facilities equipped with various interconnected Meridian 1 Call Center products.

Ordering process

Under the Customer Premises Equipment (CPE) Distributor Agreement, the distributor must initiate requests to the Enterprise Solutions/CSS ADS for end-user IVR application development support. Enterprise Solutions/CSS ADS invoices the distributor for service rendered to end users.

A distributor submit a PO to initiate the IVR post-sale development support services provided by Enterprise Solutions/CSS ADS. Nortel Networks requires a customer (i.e., business affiliate, distributor, VAD/VAR) to submit credit authorization if the customer has not previously conducted business with Nortel Networks and does not have a customer identification (ID) number.

Meridian Mail Reporter (MMR) Service Plan

Meridian Mail Reporter (MMR) includes a 90-Day Service Plan and offers an optional MMR One-Year Extended Service Plan. If the MMR One-Year Extended-Service Plan is purchased with a new system, or during the initial 90-day period, total support services include 90 days plus 12 months for a total of 15 months. If purchased outside of the initial 90-day period, the plan provides support services for 12 months from the purchase date.

MMR service plan provides the following types of services.

- Defect resolution
- Limited installation support
- Navigation support
- Interpretation

Defect resolution

Defect resolution provides analysis and resolution for the following items.

- MMR Data Corruption
- Documentation inconsistencies
- Software design fault
- Software out-of-box failure

Limited installation support

The limited installation support provides remote telephone support for problems relating to software installation ensuring the application loads properly in the PC and presents an application-launch screen.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Navigation support

Navigation support provides assistance with the methodology for effective manipulation/utilization of the application. Navigation supports includes the following items.

- Location
- Report generation
- Configuration

Interpretation

Interpretation provides analysis and derivation of subsequent actions suggested by the results of a particular report. The customer makes the decisions regarding what action to take, but Service Connection provides information so the customer can understand the report output implications.

Support service availability

Nortel Networks provides all MMR support services during normal business hours by the Service Connection Advisory Group located in Richardson, Texas. Normal business hours are Monday through Friday from 8:00 a.m. to 5:00 p.m. CST, excluding Nortel Networks holidays. Part of the Nortel Networks Enterprise Solutions/Customer Support Services organization, Service Connection is dedicated to providing support for desktop applications, network applications, and call-center applications. Contact the Service Connection at 1-800-766-ETAS (1-800-766-3827).

SYMPOSIUM Messenger

Ordering process and procedures

Transaction order types

The following order types and contacts apply to SYMPOSIUM Messenger.

Custom orders	Stock orders	Service orders
SYMPOSIUM Messenger systems System expansions System upgrades Software updates Merchandise components	Sales collateral	Repair orders Training Technical Support

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Order contacts

Product/order type	Norstar Enterprise Solutions sales collateral
Custom & stock orders	Enterprise Solutions Customer Response Center 2305 Mission College Blvd. Santa Clara, CA 95054-1599 1-800-321-2649 FAX (408) 565-2530
Technical support	Enterprise Solutions CTS 9701 Data Park Minnetonka, MN 55843 1-800-527-0797 FAX (612) 932-8325
Training and repair orders	Nortel Networks 9701 Data Park Minnetonka, MN 55343 (612) 932-8000

Warranty-period repair and replacement service

Nortel Networks manages the repair and replacement of defective SYMPOSIUM Messenger system hardware covered by warranty. Nortel Networks performs such repair and replacement at the end user's location.

Software returns contact

Ship all SYMPOSIUM Messenger return software materials to the following address.

Nortel Networks
9701 Data Park
Minnetonka, MN 55343
(612) 932-8000

Installation and service

The SYMPOSIUM Messenger System solution provides a single point of contact for SYMPOSIUM Messenger System hardware, software, installation, and hardware maintenance needs. The price of the SYMPOSIUM Messenger system includes one year of basic maintenance (8:00 a.m. to 5:00 p.m. service coverage).

Nortel Networks provides an option to purchase an installation option that includes the following installation services at a schedule mutually agreed upon. SYMPOSIUM Messenger system installation consists of placing the integrated SYMPOSIUM Messenger system hardware and the SYMPOSIUM Messenger system software at the end user’s installation location ready for in-service usage.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Installation includes the following services.

- Installation of the integrated SYMPOSIUM Messenger system hardware and SYMPOSIUM Messenger system software at the specified location.
- Installation and connection of the short haul modem from the SYMPOSIUM Messenger system to the appropriate Meridian Mail ACCESS port.
- Installation and connection from the SYMPOSIUM Messenger System to the appropriate LAN.
- Installation and connection from the SYMPOSIUM Messenger System to the appropriate FAX lines.
- Testing of components.
- Demonstration of basic SYMPOSIUM Messenger System Software applications functionality.

  Note: Distributor is subject to charges listed in the following Technical Assistance Service Fees section, if delays are encountered beyond Nortel Networks' control.

Meridian Application Server Support and Service Overview

All Distributors of Nortel Networks's Meridian Application Server and its applications (Messenger and Assistant) will now have the option of purchasing the services the Distributor requires.

Nortel Networks's Enterprise Solutions / Field Services (EN/Field Services) organization will offer the following services for the Meridian Application Server:

- On-site installation
- On-site system administrator and end-user training
- Telephone Support
- On-site service

The following order codes can be used to request the various services being offered by Nortel Networks Enterprise Solutions / Field Services.

MAS Application Service order codes

Order code	Description	Option type
SV000019	Messenger: Meridian Application Installation and Setup	Installation
SV000112	Installation Telephone Support while the Distributor performs the on-site installation of the Messenger Meridian Application Server	Installation
SV000115	Installation Telephone Support while the Distributor performs the on-site installation of the Assistant Meridian Application Server	Installation
SV000021	Meridian Application Server Installation, Setup and Messenger Administration & User Training	Installation and Training

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MAS Application Service order codes

Order code	Description	Option type
SV000023	Meridian Application Server Installation, Setup and Assistant Administration & User Training	Installation and Training
SV00069	Meridian Application Server Installation, Setup and SYMPOSIUM Messenger/Assistant Training	Installation and Training
SV000020	Messenger System Administrator and Client End-user Training, Instructor Led	Training
SV000022	Assistant 1.0 System Administrator and Client End-user Training, Instructor Led	Training
SV000024	Upgraded First-Year Extended Phone Support to 7x24	Upgrade
SV000025	8 to 5 Phone Support with 8 to 5 On-site Hardware Repair Service	Upgrade
SV000026	8 to 5 Phone Support with 8 to 5 On-site Hardware Repair Service	Post Warranty Service
SV000027	7x24 Phone Support with 8 to 5 On-site Hardware Repair Service	Post Warranty Service
SV000110	Messenger 8 to 5 Phone Support	Post Warranty Service
SV000111	Messenger 7x24 Phone Support	Post Warranty Service
SV000113	Assistant 8 to 5 Phone Support	Post Warranty Service
SV000114	Assistant 7x24 Phone Support	Post Warranty Service
SV000181	Installation Telephone Support while the Distributor performs additional user client license installation	Installation

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Installation Only Options

The following options exist for installation only options.

SV000019

Meridian Application Server Installation and Setup

Currently, installation service must be ordered with every MAS Server.

A pre-installation checklist to the end user's location is coordinated by Nortel Networks technical specialists and performed by an Nortel Networks-EN/Field Services Field Engineer to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Complete Meridian Application Server installation activities are performed by a fully trained Nortel Networks-EN/ Field Services Professional Services Engineer. Installation includes set up on the end user's premises of the Meridian Application Server and connection of the server to the specified LAN and Meridian Mail System. Installation also includes the loading and configuring of approximately three client end users with the Messenger/ Assistant client software. Nortel Networks also provides “basis” Windows coaching to ensure that the Messenger/ Assistant client software was loaded and configured properly. Nortel Networks also provides “basis” Windows assistance to improve system performance and overall ease of operation. The end user/Distributor is responsible for the addition of subsequent Messenger/ Assistant clients to the Meridian Application Server.

SV000112

Installation Telephone Support while the Distributor performs the on-site installation of the Messenger Meridian Application Server

This is a future offering as the Distributors are trained to install Messenger.

A pre-installation conference call is coordinated by Nortel Networks technical specialists to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Telephone assistance during the installation is provided by a fully trained Nortel Networks-EN/Field Services Professional Services Engineer.

SV000115

Installation Telephone Support while the Distributor performs the on-site installation of the Assistant Meridian Application Server

This is a future offering as the Distributors are trained to install Assistant.

A pre-installation conference call is coordinated by Nortel Networks technical specialists to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Assistant Meridian Application Server. Telephone assistance during the installation is provided by a fully trained Nortel Networks-EN/Field Services Professional Services Engineer.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000181
Installation Telephone Support while the Distributor performs additional user client license installation
This is an offering used when ordering additional user client licenses.

A pre-installation conference call is coordinated by Nortel Networks technical specialists to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client Pcs for Messenger User Client Licenses. Telephone assistance during the installation is provided by a fully trained Nortel Networks-En/Field Services Professional Services Engineer.

Installation and Training Options
The following installation and training options are available.

SV000021
Meridian Application Server Installation, Setup and Messenger Training
A pre-installation checklist to the end user's location is coordinated by Nortel Networks technical specialists and performed by an Nortel Networks-EN/Field Services Field Engineer to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Complete Meridian Application Server installation activities are performed by a fully trained Nortel Networks-EN/Field Services Professional Services Engineer. Installation includes set up on the end user's premises of the Meridian Application Server and connection of the server to the specified LAN and Meridian Mail System. Installation also includes the loading and configuring of approximately three client end users with the Messenger client software. Nortel Networks provides “basic” Windows coaching to ensure that the Messenger client software was loaded and configured properly. Nortel Networks provides “basic” Windows assistance to improve system performance and overall ease of operation. The end user/Distributor is responsible for the addition of subsequent Messenger clients to the Meridian Application Server.

A Nortel Networks-EN/Field Services Professional Services Engineer provides on-site Messenger 3.0 training for the customer's system administrator at each end user's location immediately after installation of the Meridian Application Server. Also included is basic end user training for approximately three client end users. EN/FS uses the Nortel Networks approved System Administrator Training Materials.

> ***Note:*** Limit the class to a maximum of two end-user System Administrators and three client end users.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000023

Meridian Application Server Installation, Setup and Assistant Training

A pre-installation checklist to the end-user's location is coordinated by Nortel Networks technical specialists and performed by an Nortel Networks-EN/Field Services Field Engineer to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Complete Meridian Application Server installation activities are performed by a fully trained Nortel Networks-EN/ Field Services Professional Services Engineer. Installation includes set up on the end user's premises of the Meridian Application Server and connection of the server to the specified LAN and Meridian Mail System. Installation also includes the loading and configuring of approximately three client end users with the Assistant client software. Nortel Networks also provides “basic” Windows coaching to ensure that the Assistant client software was loaded and configured properly. Nortel Networks provides “basic” Windows assistance to improve system performance and overall ease of operation. The end user/ Distributor is responsible for the addition of subsequent Assistant clients to the Meridian Application Server.

A Nortel Networks-EN/Field Services Professional Services Engineer provides on-site Assistant training for the customer's system administrator at each end user's location immediately after installation of the Meridian Application Server. Also included is basic end user training for approximately three client end users. EN/FS uses the Nortel Networks approved System Administrator Training Materials.

> ***Note:*** Limit the class to a maximum of two end-user System Administrators and three client end users.

SV000069

Meridian Application Server Installation, Setup and SYMPOSIUM Messenger/ Assistant Training

A pre-installation checklist to the end user's location is coordinated by Nortel Networks technical specialists and performed by an Nortel Networks-EN/Field Services Field Engineer to assist the end user/Distributor in readying the Meridian 1, the Meridian Mail system, the LAN environment and the client PCs for the Meridian Application Server. Complete Meridian Application Server installation activities are performed by a fully trained Nortel Networks-EN/ Field Services Professional Services Engineer. Installation includes set up on the end user's premises of the Meridian Application Server and connection of the server to the specified LAN and Meridian Mail System. Installation also includes the loading and configuring of approximately three client end users with the Messenger/Assistant client software. Nortel Networks provides “basic” Windows coaching to ensure that the Messenger/Assistant client software was loaded and configured properly. Nortel Networks provides “basis” Windows assistance to improve system performance and overall ease of operation. The end user/Distributor is responsible for the addition of subsequent Messenger/ Assistant clients to the Meridian Application Server.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A Nortel Networks-EN/Field Services Professional Services Engineer provides on-site Messenger/Assistant training for the customer's system administrator at each end user's location immediately after installation of the Meridian Application Server. Also included is basic end-user training for approximately three client end users. EN/FS uses the Nortel Networks approved System Administrator Training Materials.

> ***Note:*** Limit the class to a maximum of two end user System Administrators and three client end users.

Training Only Options

The following options are available for training.

SV000020

Messenger System Administrator and Client End User Training - Instructor Led

A Nortel Networks-EN/Field Services Professional Services Engineer provides on-site Messenger training for the customer's system administrator at each end user's location immediately after installation of the Meridian Application Server. Also included is basic end user training for approximately three client end users. EN/FS uses the Nortel Networks approved System Administrator Training Materials.

> ***Note:*** Limit the class to a maximum of two end-user System Administrators and three client end users.

SV000022

Assistant 1.0 System Administrator and Client End User Training - Instructor Led

A Nortel Networks-EN/Field Services Professional Services Engineer provides on-site Assistant 1.0 training for the customer's system administrator at each end user's location immediately after installation of the Meridian Application Server. Also included is basic end user training for approximately three client end users. EN/FS uses the Nortel Networks approved System Administrator Training Materials.

> ***Note:*** Limit the class to a maximum of two end-user System Administrators and three client end users.

Warranty Service Options

The following warranty service options are available.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000024
Upgraded First Year Extended Phone Support to 7 X 24
The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC assists the System Administrator in determining the failing component and sends a replacement part to the System Administrator for use in the repair. This warranty service is provided on a seven day a week, twenty-four hour a day basis.

SV000025
8 to 5 Phone Support with 8 to 5 On-site Hardware Repair Service
The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC dispatches a Nortel Networks-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel Networks-EN/Field Services Field Engineer replaces the failing component and verifies complete Meridian Application Server operation. This warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

Post Warranty Service Options
The following post warranty service options are available.

SV000026
8 to 5 Phone Support with 8 to 5 On-site Hardware Repair Service
The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC dispatches a Nortel Networks-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel Networks-EN/Field Services Field Engineer replaces the failing component and verifies complete Meridian Application Server operation. This post warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000027

7 X 24 Phone Support with 8 to 5 On-site Hardware Repair Service

The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Meridian Application Server administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC dispatches a Nortel Networks-EN/Field Services Field Engineer to the site for on-site trouble-shooting assistance. If a hardware failure occurs, the Nortel Networks-EN/Field Services Field Engineer replaces the failing component and verifies complete Meridian Application Server operation. This post warranty phone support is provided on a seven day a week, twenty-four hour a day basis and the on-site service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

SV000110

Messenger 8 to 5 Phone Support

The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Messenger system administrator. The CSC can assist the end users in diagnosing Meridian Application Server and Messenger operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC assists the System Administrator in determining the failing component and sends a replacement part to the System Administrator for use in the repair. This post warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

SV000111

Messenger 7 X 24 Phone Support

The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Messenger system administrator. The CSC can assist the end users in diagnosing Meridian Application Server operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC assists the System Administrator in determining the failing component and sends a replacement part to the System Administrator for use in the repair. This post warranty service is provided on a seven day a week, twenty-four hour a day basis.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000113
Assistant 8 to 5 Phone Support
The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Assistant system administrator. The CSC can assist the end users in diagnosing Meridian Application Server and Assistant operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC assists the System Administrator in determining the failing component and sends a replacement part to the System Administrator for use in the repair. This post warranty service is available between the hours of 8:00 a.m. to 5:00 p.m., Monday through Friday.

SV000114
Assistant 7 X 24 Phone Support
The Nortel Networks-EN/Field Services Customer Support Center (CSC) accepts all requests for assistance from the customer's Assistant system administrator. The CSC can assist the end users in diagnosing Meridian Application Server and Assistant operational problems and then recommend the appropriate course of action to remedy them. The CSC uses remote access when appropriate. If a hardware failure is assumed, the CSC assists the System Administrator in determining the failing component and sends a replacement part to the System Administrator for use in the repair. This post warranty service is provided on a seven days a week, twenty-four hour a day basis.

Software support and basic maintenance

Nortel Networks provides the following types of support to assist the distributor in restoring the SYMPOSIUM Messenger system to the pre-incident level of functionality:

- “Software Support” for the SYMPOSIUM Messenger system software
- “Basic Maintenance” Services for SYMPOSIUM Messenger system hardware

Support services

Support consists of the following services:

- Interpretation of documentation that Nortel Networks may initiate related to service problems.
- Assistance in interpreting results of problem diagnostics by telephone.
- Determination of the action required to resolve the incident.
- On-site support as described in the “On-site support,” section.

Nortel Networks attempts to determine the cause of any reported problem using the remote access embedded in the SYMPOSIUM Messenger system software, provided the end user agreed to provide the necessary business-phone access to the SYMPOSIUM Messenger system. Support personnel uses the results of the remote examination to determine the action required to resolve the situation.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Telephone support schedule

Nortel Networks provides software support and basic maintenance for a system during the warranty period during the PPM for problems within the scope of the warranty. The PPM is 8:00 a.m. to 5:00 p.m. local time, Monday through Friday excluding Nortel Networks holidays.

For problems reported during the PPM, Nortel Networks provides technical assistance within two hours from the time Nortel Networks receives the call from the end user.

On-site support

If deemed necessary by Nortel Networks, on-site support for problems within the scope of the warranty is available at no additional charge during the PPM.

If Nortel Networks determines on-site support is required, Nortel Networks contacts the nearest Nortel Networks Service Center. Nortel Networks bases the following on-site estimated response times on the distance from the end-users installation location to the nearest Nortel Networks Service Center

> ***Note:*** Response time represents the average elapsed time starting from the point in time when Nortel Networks and the end user determine on-site support is required and Nortel Networks initiates a call to the closest Nortel Networks Service Center and ending when the Nortel Networks field service engineer arrives on-site. Do not construe response time as the time required to “fix” the problem or as Nortel Networks's guaranteed response time.

Distance	Response Time
0 - 75 miles	4 hours
76 - 125 miles	6 hours
126 miles and over	next day

Technical Assistance Service fees

Nortel Networks provides telephone support and/or on-site support for the SYMPOSIUM Messenger system per the following fees specified. Problems deemed outside the scope of the warranty include, but are not limited to, the following items:

- System incorrectly re-installed by other than Nortel Networks.
- Configuration does not conform to Nortel Networks specifications.
- Warranty period has expired.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Nortel Networks charges the following prices for telephone support and/or work done on-site, when the support required is not included in the scope of work previously described.

Telephone support

Hours	Cost
8 a.m. to 5p.m. Monday thru Friday	$150.00 per hour
5 p.m. to 8 a.m. Monday thru Saturday	$225.00 per hour
Sunday/Holiday	$300.00 per hour
Note 1: Hours are based on the local time. ***Note 2:*** The minimum charge for telephone support is one hour. ***Note 3:*** Telephone/data links incur additional charges.	

The following table provides schedule and fees for on-site support.

On-site support

Hours	Cost
8 a.m. to 5 p.m. Monday thru Friday	$150.00 per hour
5 p.m. to 8 a.m. Monday thru Saturday	$200.00 per hour
Sunday/Holiday	$200.00 per hour
Note 1: Hours are based on the local time. ***Note 2:*** Travel time to and from the installation location are charged at the applicable rate per hour plus reasonable expenses including, but not limited to, travel, meals, and accommodations.	

Hardware and Software Packaging

Messenger is a turnkey solution that fits perfectly with Meridian Mail systems. It is compatible with popular local area network (LAN) operating systems such as Novell NetWare or Microsoft LAN Manager, using networking options such as Ethernet or Token Ring.

Meridian Mail requirements

- Meridian Mail Release 11
- ACCESS Enable Software Option
- RSM Package or Utility Card

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Messenger PC Requirements (Clients)

- IBM PC or compatible with Pentium 75 or greater
- Microsoft DOS 3.3 or greater
- 16 MB RAM
- VGA monitor
- 22 MB disk space for Unified Client
- 4 MB disk space for Inbox Client

Client Operating Systems Supported

- Microsoft Windows 95
- Microsoft Windows 98
- Microsoft Windows NT 4.0

  Note: Windows 3.x is no longer supported.

LAN requirements

Messenger operates in Ethernet or Token Ring LANs that utilize Winsock 1.1 compliant TCP/IP protocol stacks. Since voice messages are recorded and played through the telephone, LAN traffic is held to a minimum.

- LAN architectures
  - — Ethernet or Token Ring
- LAN protocols
  - — TCP/IP (no NetBIOS requirement)

Packaging

Package content

The SYMPOSIUM Messenger package contains the following components:

- SYMPOSIUM Messenger Server (hardware, software, installation, and warranty period maintenance services)
- LAN interface (hardware and software)
- Client software
- Standard set of Nortel Networks documentation

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System configuration

Customers purchase SYMPOSIUM Messenger by making component selections based on answers to a series of questions. The first question determines the service offering desired and, therefore, determines the SYMPOSIUM Messenger Server. Next, the customer defines the LAN Interface and selects the number of client users of the SYMPOSIUM Messenger system. Finally, optional items are selected to complete the system definition.

Based on the customer-provided system definition, Nortel Networks configures the appropriate SYMPOSIUM Messenger Server, adds the appropriate LAN interface package, and documents the Site-License selection. Optional hardware, service application, and documentation selections are also provisioned for shipment. When shipped to the customer, all the system software is pre-configured to the customer requirements and loaded on the server hard disk. A backup of the system software is included on a tape cartridge and/or additional floppies.

Policies

Server hardware is packaged as one of two SYMPOSIUM Messenger Server options based on the service offerings of either of the following options:

- SYMPOSIUM Messenger Visual Voice Messaging
- SYMPOSIUM Messenger Visual Voice and Fax Messaging

The following concerns apply to the SYMPOSIUM Messenger Server options.

- Both SYMPOSIUM Messenger Server options are sold with a standard short-haul modem connection to Meridian Mail.
- SYMPOSIUM Messenger Fax on Demand application can be installed only with the SYMPOSIUM Messenger Visual Voice and Fax Messaging service offering and the optional Large Disk Drive as a prerequisite.
- SYMPOSIUM Messenger Fax on Demand application and user configurations with larger than normal storage requirements necessitate pre-sales engineering to ensure the correct system sizing. This is based on the following items:
  - — service offering selection
  - — number of client users
  - — parameters of application storage and port usage.
- Client software is sold as a site license with specific upper limits for both new system sales and for system expansions.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

New system orders (hardware and software)

New system orders must be accompanied by a completed SYMPOSIUM Messenger Configuration Guide and Pre-Installation checklist. A copy may be obtained from the Nortel Networks Information Center. The order fulfillment does not begin until this form is provided. When placing a new system order, both server hardware and client software components must be specified.

Use the following guidelines for new system orders:

- Meet site environment prerequisites
- Select the appropriate service offering
- Select the appropriate LAN connectivity option
- Order the appropriate site license

Meet site environment prerequisites

Nortel Networks requires the customer to meet the site environment prerequisites as previously cited. All SYMPOSIUM Messenger systems require Meridian Mail. If Meridian Mail is not in place, order a new Meridian Mail EC or Modular GP system using the normal ordering procedures.

Select the appropriate service offering

Select one of the following service offerings:

- Visual Voice Messaging
- Visual Voice and Fax Messaging

Select the appropriate LAN connectivity option

Select one of the following connectivity options:

- Ethernet - TCP/IP protocols
- Token Ring - TCP/IP protocols

Order the appropriate site license

Order one of the following licenses:

- 25 user configuration
- 50 user configuration
- 100 user configuration
- 200 user configuration
- 500 user configuration
- 1,000 user configuration
- 2,000 user configuration

Combinations of the above can be ordered. Configurations greater than or equal to 1,000 users require engineering assistance from Nortel Networks.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

New system software

Client software is sold as a site license with specific upper limits. New systems ship with one copy of the appropriate client software material to be used as a "golden master" for loading onto individual user PCs.

System upgrades, expansions, and merchandise orders

Client expansion

The expansion from one user level to another does not require a dedicated kit with associated part number. Rather, order the appropriate end-user site license; which are the same as for a new installation. Multiple part numbers can be ordered to bring a customer Site License up to the appropriate number of end user client packages.

Charges for system expansion include the current price (RTU Fees) of all applicable client site license packages, plus the software service transaction fee ($650).

> ***Note:*** Orders must clearly identify the current total clients under site license and the desired new total clients under site license.

Combination client expansion and system upgrade

Customers desiring to both increase the number of client users (expansion) and add Fax Messaging functionality to a Voice Messaging only system (upgrade) will be required to effect a two step order.

1. Order upgrade for existing client site license level
2. Order the desired client expansion to go to the new desired client site license level for Voice and Fax Messaging services.

Charges for a combination client expansion and system upgrade include the price of (RTU fees) all applicable client site license packages, plus software transaction fee ($650).

> ***Note:*** Orders must clearly identify the current total clients under site license and the desired new total clients under site license.

Upgrade to Visual Voice and Fax Messaging Service

To upgrade from Visual Voice Messaging to Visual Voice and FAX Messaging Service, the new functionality will be delivered on a new client diskette as with an initial system purchase.

Upgrade software

In addition to the client Site License Agreements, the customer will be required to upgrade the original Visual Voice Messenger server platform. Additional Fax Modem Cards and memory may be required, dependent upon the size of the intended expansion.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Optional software

Once the customer has chosen the Visual Voice and Fax Messaging Service option, they will be able to select the Fax on Demand application. Fax on Demand will require the large disk drive hardware option regardless of the number of client users.

Meridian Passport Software Policy

The Meridian Passport Software Policy differs from Meridian 1 in that the software used with Meridian Passport is very closely tied to the Nortel Networks Magellan Passport Software. Meridian Passport software is delivered on CD-ROM as an individual software product containing a single stream release. Product improvements and new features are made available in subsequent releases. Routine fixes and software maintenance are delivered on a new issue of a release and are scheduled at regular intervals. Subscribers are advised of new software release and subsequent up issues through Product Bulletins issued by Meridian Passport Product Line Management.

Software Upgrades

Meridian Passport requires that software in all operational machines be maintained on an active or sustained release.

Meridian Passport Product Management plans two releases of software along with one up-issue per release per year. There is an annual mandatory charge of $650.00 per system per year for Software upgrades and up-issues after the first year.

Payment of the annual fee entitles the subscriber to the following items.

- Load the new release and activate the currently owned features.
- Further extends the software warranty by 12 months.

Hardware Upgrades

If hardware upgrades are required with a new release of software, then a Product Bulletin is issued to identify the new components.

Software Release Numbering

Meridian Passport

The software numbering for Meridian Passport follows the Magellan Passport format. The format consists of a release number; e.g., Rls 3.5, followed by an issue number; e.g., S5. It is usually written Rls 3.5.S5 or Rls 3.5.5.

Meridian Passport Manager

The software number for Meridian Passport Manager consists of a Release number and a version number; e.g., 2.2 0.82.3 is Release 2.2 and version 0.82.3.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software Ratings

Meridian Passport software has the following ratings.

- Active
- Sustained
- Retired

Active

The Active software rating is the software release that is currently shipped with new Meridian Passport systems. It has full CTS support, “bug-fix” activity, and all documentation is available.

Sustained

The Sustained software rating is a software release that was previously active and is no longer available on new Meridian Passport systems. It has limited CTS support, replacement CDs and documentation are available.

Retired

The Retired software is obsolete software where the customer should upgrade to an Active release, additional features cannot be added, CTS support is limited, no “bug fix” activity, and documentation is no longer available.

CTS Support Pricing

Existing Meridian 1 support pricing applies, regional, for Meridian Passport support.

> ***Note:*** All support activity with other than authorized support personnel will be handled as billable, with applicable CSR fees applied.

Authorized Support Personnel

Nortel Networks Meridian Passport Support works with Authorized Distributor Support Engineers, who have the required skills for installation and support of the Meridian Passport product. A submission form can be obtained by contacting the CTS support group.

For use only by Nortel Networks and Nortel Networks’ authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Hardware/Software Status

Software status

Software support based on status

Nortel Networks has developed a software system to provide quality status support. Refer to the following tables for available software product support:

Software support availability

Status	New Parts Available	System CTS Support	Engineering Changes	Repair Parts Available
Current	Yes	Full	Yes	Yes
Active	Yes	Full	Yes	Yes
Sustained	No	Full	Yes	Yes
Retired	No	Limited	No	Limited

Software support matrix

Product	Current	Active	Sustained	Retired
New Systems	Yes	No	No	No
System Upgrades	Yes	No	No	No
Release Updates	Yes	Yes	Yes	No
Additional Features/ Expanded Capacity (Note 1)	Yes	Yes	Yes	No (Note 2)
Additional Bug Fixes Planned	Yes	Yes	No	No
Replacement Tapes/Disks Available	Yes	Yes	Yes	Yes
CTS Support	Full (Note 3)	Full (Note 3)	Limited (Note 4)	Limited (Note 4)

Note 1: If addition of feature requires you to go to a generic/release which is not supported on your system, you must go to the current software release.

Note 2: If additional features or capacity are required, software must be brought to a sustained, active, or current release status.

Note 3: CTS diagnoses and resolves software problems.

Note 4: CTS support is limited to problem diagnosis.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software status

Options 21 - 81 software release status

System	Status
X03	Retired
X04	Retired
X05	Retired
X07	Retired
X09	Retired
X14	Retired
X37	Retired
X11.1	Retired
X11.2	Retired
X11.3	Retired
X11.4	Retired
X11.5	Retired
X11.7	Retired
X11.8	Retired
X11.9	Retired
X11.10	Retired
X11.11	Retired
X11.12	Retired
X11.13	Retired
X11.14	Retired
X11.15	Retired
X11.16	Retired
X11.17	Sustained
X11.18	Retired
X11.19	Active
X11.20	Retired
X11.21	Active
X11.22	Sustained
X11.23	Sustained
X11.24	Active
X11.25	Current

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option 11 software release status

System	Status
X11.16	Retired
X11.18	Sustained
X11.20	Retired
X11.21	Active
X11.22	Sustained
X11.23	Sustained
X11.24	Active
X11.25	Current

Applications software status

Applications software support matrix

Description	Current	Active	Sustained	Retired
Meridian Mail	R12	R11	R10	R3, R4, R5, R6, R7, R8, R9 (Note)
ACD-MAX				R1, R2, R3, R3.1, R3.2, R4
ACD-D				R4.5, R5, R6, R7, R8, R9.2
Meridian Link	R4B			R2, R3, R4
Meridian MAX (AM)	R 8 (SNN, SNNE)	4.33 (Opt 2,3,4) 6.31 (SEE)	R3.4, R4.21	R3.3, R5
Integrated IVR		R2.2	R1.13, R1.26, R2.08	
IVR Open	R4.0		R2.0, R2.5	
Meridian MAX-IPE/ IPEE	R8		R4.62, 6, 7	R5
Customer Controlled Routing (CCR)	R3			R2.18
Meridian NAC	R2			R1
Note: Release 9.66 is available for up-issue of previous Release 9 software issues. Release 9 is still retired, the up-issue is provided solely to address year 2000 issues as discussed in Sales and Marketing Bulletin 1153-G dated June 1998 and entitled “Meridian Mail Release 9 and 10 Century compliant Up-issues.”				

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Hardware status

System status

Meridian 1/ SL-1 system status

System	Status
L	Retired
VL	Retired
VLE	Retired
A	Retired
LE	Retired
XL	Retired
M	Retired
S	Retired
MS	Retired
N	Retired
XN	Retired
ST	Sustained
STE	Active
RT	Active
NT	Active
XT	Active
Option 11	Sustained
Option 11C	Current
Option 11E	Active
Option 21A	Sustained
Option 21	Sustained
Option 21E	Active
Option 51	Active
Option 51C	Current
Option 61	Active
Option 61C	Current
Option 71	Active
Option 81	Current
Option 81C	Current

Retired systems

System	Status
Pulse 80	Retired
Pulse 120	Retired
OMNIFACTS	Retired

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Retired systems

IMS	Retired

Applications hardware status

Meridian 1 applications hardware status

System	Status
ACD-D (PDP)	Retired
ACD-MAX (HP Vectra)	Retired
MAX Options 1, 2, 3, 4	Retired
MAX-SEE	Retired
MAX-SNN	Retired
MAX-IPE	Retired
MAX-SNNE	Current
MAX-IPEE	Current
NAC 1 (HP Vectra)	Retired
NAC 2	Current
Meridian Mail MP	Retired
Meridian Mail SP	Retired
Meridian Mail Modular Option	Sustained
Meridian Mail ST/RT Option	Retired
Meridian Mail NT/XT Option	Retired
Meridian Mail Option S Cabinet	Retired
Meridian Mail Option X Cabinet	Retired
Meridian Mail GP	Retired
Meridian Mail Modular EC	Active
Meridian Mail Modular GP	Active
Meridian Mail Card Option	Active
Meridian Mail EC11	Active

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 system/software compatibility matrix

The table below lists system software releases, their status, and the software application releases they support. Numbers in parentheses refer to notes found at the end of this table.

System/software compatibility matrix

Base Software (Note 2)	System Supported (Note 3)	Meridian Mail	Meridian MAX (AM)	ACD-MAX	ACD-D	Meridian Link	CCR
X11.24 **Current**	51C, 61C, 81, 81C	R. 8 R. 9 R. 10 R. 11 R. 12	R. 4 R. 6 R. 7 R. 8 R. 9	R. 4		R. 5	R. 3
X11.23 **Active**	51C, 61C, 81, 81C	R. 8 (2) R. 9 R. 10 R. 11 R. 12	R. 4 R. 6 R. 7 R. 8 R. 9	R. 4		R. 5	R. 3
X11.22 **Sustained**	51C, 61C, 81, 81C	R. 8 (2) R. 9 R. 10 R. 11 R. 12	R. 3 R. 4 R. 6 R. 7 R. 8 R. 9	R. 4		R. 4 R. 4B R. 5	R. 3
X11.21 **Active**	STE,RT,NT, XT,21E,51, 51C,61,61C, 71,81, 81C	R. 8 (2) R. 9 R.10 R. 11 R. 12	R. 3 R. 4 R. 6 R. 7 R. 8 R. 9	R. 3 R. 4		R. 2 R. 3 R. 4 R. 4B R. 5	R. 3
X11.20 **Retired**	STE,RT,NT, XT,21E,51, 51C,61,61C, 71,81	R. 7 (2) R. 8 (2) R. 9	R. 3 R. 4 R. 6 R. 7 R. 8 R. 9	R. 3 R. 4		R. 2 R. 3 R. 4 R. 4B R. 5	R. 3
X11.19 **Active**	STE, RT, NT XT, 21E,51 61, 71, 81	R. 6 (2) R. 7 (2) R. 8 (2) R. 9 R. 10 R. 11 R. 12	R. 3 R. 4 R. 6 R. 7 R. 8 R. 9	R. 3.2 R. 4		R. 3 R. 2 R. 4 R. 4B R. 5	R. 3
X11.18 **Retired**	STE, RT, NT, XT, 21E, 51, 61, 71, 81	R. 5 R. 6 (2) R. 7 (2) R. 8 (2) R. 9	R. 3 R. 4 R. 6 R. 7 R. 8 R. 9	R. 3.2 R. 4		R. 2 R. 3 R. 4	R. 3

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System/software compatibility matrix

Base Software (Note 2)	System Supported (Note 3)	Meridian Mail	Meridian MAX (AM)	ACD-MAX	ACD-D	Meridian Link	CCR
X11.17 **Sustained**	ST, RT, NT, XT, 21, 21A, 51, 61,71	R. 5 R. 6 (2) R. 7 (2) R. 8 (2) R. 9 R. 10 R. 11 R. 12	R. 3 R. 4 R. 6 R. 7 R. 8 r. 9	R. 3.2.1A (1) R. 3.25 (1) R. 4 (1)	R. 9.2 (1)	R. 2 R. 3 R. 4	R. 3
X11.16 **Retired**	ST,RT,NT, XT, 21, 21A, 51, 61, 71	R. 4 R. 5 R. 6 (2) R. 7 (2) R. 8 (2)	R. 3.3	R. 3.2.1A (1) R. 3.25 (1)	R. 7 (1) R. 8 (1) R. 9.2 (1)	R. 2	
X11.15 **Retired**	ST, RT, NT, XT, 21,21A, 51, 61, 71	R. 4 R. 5 R. 7 (2) R. 8 (2)	R. 3.3	R. 3	R. 7 (1) R. 8 (1) R. 9.2 (1)		
X11.14 **Retired**	ST,RT,NT, XN,XT	R. 4 R. 5 R. 7 (2) R. 8 (2) R. 9 R.10		R. 2 R. 3 R. 3.25	R. 6 (1) R. 7 (1) R. 8 (1) R. 9.2		
X11.13 **Retired**	MS,N,XN, ST,RT,NT, XT	R. 4 R. 5 R. 7 (2)		R. 2 R. 3	R. 6 (1) R. 7 (1) R. 8 (1) R. 9.0 R. 9.1		
X11.12 **Retired**	MS,N,XN, ST,RT,NT, XT	R. 4 R. 5 R. 7 (2)		R. 2 R. 3	R. 6 (1) R. 7 (1) R. 8 R. 9		
X11.10 **Retired**	S,MS,N, XN,ST, NT,XT	R. 4		R. 2 R. 3	R. 6 (1) R. 7 (1) R. 8 R. 9		
X11.9 **Retired**	LE(23), VLE, XL(24), S,MS,N, XN,ST, NT,XT	R. 4		R. 1 R. 2 R. 3	R. 4 R. 5 R. 6 R. 7 R. 8 R. 9		
X11.8 **Retired**	LE(23), VLE, XL(24),S, MS,N,XN, NT,XT				R. 4.5 R. 5 R. 6 R. 7 R. 8		

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System/software compatibility matrix

Base Software (Note 2)	System Supported (Note 3)	Meridian Mail	Meridian MAX (AM)	ACD-MAX	ACD-D	Meridian Link	CCR
X11.7 Retired	LE(23), VLE, XL(24),M, S,MS,N,XN				R. 4.5 R. 5		
X11.5 Retired	LE(23), VLE, XL(24),M, S,MS,N,XN				R. 4.5 R. 5		
X11.4 Retired	LE(23), VLE, XL(24),M, S,MS,N,XN						
X11.3 Retired	LE(23), VLE, XL(24),M				R. 4.5		
X11.2 Retired	LE(23), VLE, XL(24), M (Note 4)						
X11.1 Retired	LE(23), VLE, XL(24),M						
X37 Retired	LE(23,96), VLE, XL(24,97), M,S, MS (Note 4)						
X14 Retired	VL,LE(23), VLE						
X09 Retired	LE(23), VLE,XL(24)						
X07 Retired	LE(23), VLE,A						
X05 Retired	L,VL, LE(23), VLE,A						
X04 Retired	L,VL, LE(23), VLE,A						
X03 Retired	L,VL						
X02 Retired	L,VL						
X01 Retired	L						

***Note 1**:* This item has limited functionality.

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

System/software compatibility matrix

Base Software (Note 2)	System Supported (Note 3)	Meridian Mail	Meridian MAX (AM)	ACD-MAX	ACD-D	Meridian Link	CCR

Note 2*:* Some features may not be supported by all releases of application software: Check the Software section of the Product Catalog, the Engineering Handbook, the Controlled Release Bulletin and/or the NTPs for specific features supported.

Note 3*:* All other systems require hardware update to “current” release. Hard drive mandatory for XT and Option 71.

Note 4*:* Systems supported depends on specific release.

Note 5: For additional information on all note items, please refer to section 1, “Ordering Procedures.

Meridian 1 Option 11/11E/11C System Compatibility Matrix

Base Software	System Supported	Meridian Mail Option 11	Meridian MAX (IPE/IPEE)	ACD-MAX	ACD-D	Meridian Link	Meridian CCR	IVR
X11.24 **Current**	11C	R.8, R.9, R.10, R.11, R.12	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	5	3	2.0 (Note 2)
X11.23 **Active**	11C	R.8, R.9, R.10, R.11 R.12	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	5	3	2.0 (Note 2)
X11.22 **Sustained**	11C	R.8, R.9, R.10, R.11 R.12	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	5	3	2.0 (Note 2)
X11.21 **Active**	11E	R.8, R.9, R.10, R.11 R.12	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	4B	3	2.0 (Note 2)
X11.20 **Retired**	11E	R.6, R.8, R.9, R.10	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	4B	3	2.0 (Note 2)
X11.18 **Sustained**	11	R.6, R.8, R.9, R.10	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	N/S	N/S	N/S

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Option 11/11E/11C System Compatibility Matrix

Base Software	System Supported	Meridian Mail Option 11	Meridian MAX (IPE/IPEE)	ACD-MAX	ACD-D	Meridian Link	Meridian CCR	IVR
X11.16 **Retired**	11	R.6, R.8, R.9, R.10	R.4.62 R.6 R.7 R.8 R.9	N/S	N/S	N/S	N/S	N/S
Note 1: N/S equals Not Supported. ***Note 2:*** Meridian Mail Option 11 release 9.4 or later.								

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

For use only by Nortel Networks and Nortel Networks' authorized distributors. Not for public disclosure.

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Index

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Symbols

"IVR delivers to FedEx" Article 369, 1490
"The Value to Strategic Alliances" 1649
(UPS) Shared Rack Model - 110V - Up to 4 MRS/Rack or AP/Rack Shelves 280, 958, 1459

Numerics

1 1/3 Amp Fuse 187, 1175, 1500, 1558
1 GB Disk Drive 1628
1 GB Hard Drive 1628
1 GB SCSI SCA Disk Drive 1623
1 Megabyte Buffer 1602
1 Yr. Update Subscription - VINES SFT - V386/TEAM (SUP-120) 1552
1 Yr. Update Subscription - VINES SFT-CNS/V386/ V386D3 MC (SUP-105) 1552
1.0 Administration Guide 26, 1628
1.0GB Hard Disk Drive 1401, 1407, 1588, 1596
1.2 GByte Hard Disk/155 MByte Tape Drive Assembly 326, 595, 1412
1.2 GByte Hard Disk/600 MByte Tape Drive Assembly 326, 595, 1412
1.5 MB DTI/PRI/TMDI Administration and Maintenance Guide 64, 70, 349, 1497, 1498, 1670
1.544 Mbit DTI/PRI Administration & Maintenance Guide 1656, 1658
1.544 MByte Carrier Cable 65, 193, 702, 1430
1.5M Baud Converter (RPE) 1505, 1681
1.5M PRI/DTI To DS1V Cable (10 Ft.) 1619
1.5M PRI/DTI To DS1V Cable (16 Ft.) 1619
1.5M PRI/DTI To DS1V Cable (32 Ft.) 1619
10 Base T Hub 307, 857, 1446
10 Ft. Ethernet Cable, Category 5 38, 223, 306, 409, 1371
10 Ft. M4000 PTR Cable 1570
1000VA UPS Hardware Spare 294, 928, 1455
1001rp Installation and Maintenance Guide - French 1670
1001rp PII SBC BIOS 1001rp AC and DC 221, 1446
1003t SYMPOSIUM Call Center Server Advanced with RAID (DMS) 34, 45, 1065, 1471
100-Agent Increment for Meridian MAX-SNN/SNNE Release 9 Software 317, 1181, 1510
100MB Ethernet Kit 1624
101 Enhanced Keyboard 222, 859, 1447
101 Enhanced Keyboard Spare 281, 295, 965, 1460, 1626
101292an MAX Option 3 to Option 4 Software Expansion 1707
101SL1-1 1525
102SL1-1 1525
103SL1-1 1525
104SL1-1 1525
105MB Disk/150MB Tape Assembly 1412, 1600
105SL1-1 1525
106SL1-1 1525
107SL1-1 1525
108SL1-1 1525
10-Agent Increment for Meridian MAX-IPE/IPEE Release 9 Software 318, 1181, 1510
10BaseT Ethernet Cable, Crossed 335, 1431
10V Converter Pack 1506, 1682
11 x 14.875 Paper 1569
110 VAC Power Supply 1587
110V Power Cord 335, 381, 1364
111SL1-1 1525
112SL1-1 1525
113SL1-1 1525
114SL1-1 1525
115SL1-1 1525
116SL1-1 1525
117SL1-1 1525
118SL1-1 1525
119SL1-1 1525
12 Mbyte Memory Card 1442, 1622
1200 Ft. Tape (8.5 In.) 1569
120MB Disk ST506 (SA211) Expansion Drive 1366, 1549
120MB Server/2MB RAM (SA132) 1549
120MB Server/4MB RAM (SA134) 1550
123SL1-1 1525
124SL1-1 1525
125SL1-1 1525
126SL1-1 1525
128 MB DIMM 221, 430, 1374, 1560
128 MB SDRAM 221, 1377
128K Memory 1504, 1680
128MB DIMM 38, 221, 1374
128MB RAM 1625
128MB SDRAM 29, 306, 1375
128SL1-1 1525
129SL1-1 1525
12-Port Loopstart Voice Port Assembly for MRS/Tower or MRS/Rack 1585
130SL1-1 1525
131SL1-1 1525
132SL1-1 1525
133SL1-1 1525
134SL1-1 1525
13GB Data Cartridge 38, 220, 304, 424, 1373
14 Foot, Shielded Ethernet Cable 39, 223, 1375
14" Monitor Spare 1460, 1626
14" SVGA Color Monitor 41, 222, 307, 856, 1446
14" SVGA Monitor 1556

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

140SL1-1 1525
141SL1-1 1525
142SL1-1 1525
143SL1-1 1525
144SL1-1 1525
146 MB Server w/8 MB Memory and 32KB Cache Memory (CNS44C) 1554
146MB (formatted) SCSI (EXP130) Expansion Disk Drive 1549
146MB Expansion Disk (ESD140) 1551
146MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS44D) 1552
146MB Server/3MB RAM (DTS233) 1549
146MB Server/4MB RAM (CNS42B) 1551
146MB Server/4MB RAM (SAS144) 1551
146MB Server/8MB RAM (CNS44B) 1551
146MB Server/8MB RAM/Cache (CNS44A) 1554
146SL1-1 1526
147SL1-1 1526
148SL1-1 1526
15 Amp Circuit Breaker 1547
15 Ft. Ethernet Cable, Category 5 38, 223, 306, 409, 1371
15" Color X-Terminal Monochrome with DEC Style Keyboard 1566
150 MByte Data Cassette Tape 326, 386, 1366
150MB Tape Backup - VINES 386/486 - MC SVRS (EXT215) 1554
150MB Tape Backup for VINES/286,386 (EXT115) 1551
150MB Tape Drive for CNS/BNS Upgrade (BSU115) 1551
150MB Tape Drive Unit 1557
150SL1-1 1526
150V Power Distribution Box 1499, 1671
151SL1-1 1526
15-30 Minute Battery Back-up Unit 66, 197, 700, 1429, 1614
153SL1-1 1526
154SL1-1 1526
155MB Hard Disk 1481, 1649
155MB Hard Disk Assembly 1400, 1588
155MB Hard Disk Drive 1407, 1596
155SL1-1 1526
156SL1-1 1526
157MB Disk ST506 (SA212) Expansion Drive 1366, 1549
157MB Server/4MB RAM (SA144) 1549
157SL1-1 1526
158SL1-1 1526
16 Bit Adapter 1587
16 MB Memory Upgrade 1628
16 Port Hotel/Motel Message Waiting Line Card 1506, 1683
16 Port Message Waiting Line Card 1506, 1682
16 to 20 Port Expansion Kit 1639
16 to 32 Session Expansion for 3270 and 5250 1560
16/1/3 Passive Backplane Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
160SL1-1 1526
161SL1-1 1526
162SL1-1 1526
163SL1-1 1526
164SL1-1 1526
165SL1-1 1526
166SL1-1 1526
167SL1-1 1526
168SL1-1 1526
169SL1-1 1526
16MB Expansion RAM for OPEN IVR 2.x AP or MRS/AP Spare 282, 969, 1461
16MB RAM Spare 294, 927, 1455
16MB SIMM 67, 197, 713, 1432
17 In. Color X-Terminal with DEC Style Keyboard 272, 498, 1382
17" Monitor Spare 1460, 1626
17" SVGA Color Monitor 307, 856, 1446
17" SVGA Monitor 1559
170 MB Disk Drive Upgrade (10 Hours Storage) 1714
170MB Disk Drive 1556
171SL1-1 1526
172MB Disk/Tape Unit 1412, 1600
172SL1-1 1526
173SL1-1 1526
174SL1-1 1526
175SL1-1 1526
176SL1-1 1526
177SL1-1 1526
178SL1-1 1526
180MB Hard Disk Drive Unit 1557
180SL1-1 1526
181SL1-1 1526
182SL1-1 1526
183SL1-1 1526
185SL1-1 1526
186SL1-1 1527
187 MB Hard Disk Assembly 1399, 1587
187SL1-1 1527
188SL1-1 1527
19" Rackmount Monitor Enclosure Spare 282, 966, 1460
190SL1-1 1527
191SL1-1 1527
192K Memory 1503, 1679
192SL1-1 1527
193SL1-1 1527
194SL1-1 1527
195SL1-1 1527

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

196SL1-1 1527
197SL1-1 1527
198SL1-1 1527
1995 TeleProfessional Reprint
Bringing Technologies Together for Maximum Call Center Performance 360, 1487
1GB Disk Drive 1522, 1718
1-Port DS1V Function Processor 1438, 1618
1-port DS1V Functional Processor 1438, 1618
1-Port DS3 Function Processor 1438, 1619
2 Ft. Ethernet Cable, Category 5 38, 223, 306, 409, 1370
2 Full Service Ports - Ports 3 & 4, 7 & 8 or 11 & 12 230, 237, 1045, 1469
2 Full Services Ports - Ports 5 & 6 or 9 & 10 237, 1044, 1469
2 GB Hard Drive 1628
2 Meg Memory 1399, 1401, 1587, 1588
2 Mile Fiber Daughterboard - Multi-Mode 67, 179, 710, 1431
2 Mile Fiber Daughterboard Single Mode 67, 179, 714, 1432
2 Mile Fiber Receiver Card - Multi-Mode 1432, 1616
2 Mile Fiber Receiver Card - Single Mode 67, 179, 714, 1432, 1617
2 Mile Multi Mode DUAL Port Fiber Daughterboard 68, 179, 715, 1432
2 Port Basic Service Voice Processing Package, Card Option 237, 494, 1381
2 Port Full Service Voice Processing Package, Card Option 237, 493, 1381
2 Port SDI Cable (6 Ft.) 67, 193, 1428, 1612
2 Port SDI I/O to DTE/DCE Cable (16 Ft.) 191, 627, 1418
2 Port SDI I/O to DTE/DCE Cable (48 Ft.) 191, 628, 1418
2.0 GByte Hard Disk/600 MByte Tape Drive Assembly 326, 596, 1412
2.0 MB DTI Card with Clock Controller 65, 178, 1427
2.0 MB DTI/PRI Administration and Maintenance Guide 63, 349, 1498
2.0 MB DTI/PRI Administration/Maintenance Guide 63, 349, 1497, 1665
2.0 MB DTI/PRI Networking 99, 108, 1234, 1515
2.0MB DTI Card with Clock Controller 1427, 1611
2.0MB DTI Package Option 11C 65, 161, 876, 1449
2.0MB DTI/PRI Twisted Pair Cable 65, 193, 1430
2.0MB Dual Port DTI/PRI 177, 555, 1403
2.0MB PRI Package Option 11C 65, 161, 876, 1449
2.0MB Primary Rate Interface Card 65, 178, 703, 1430
2.2GB Cartridge Tape (10/Pkg) (AA210) 1552
2.2GB Cartridge Tape (AA200) 1553
2.2GB Internal Tape Drive for CNS Servers (EXT322) 1553
2.2GB Tape Cleaning Cartridge (AA250) 1552
2.5MB Memory 1401, 1589
200 Series Base System Assembly 41, 221, 1445
200i Installation and Maintenance Guide - French 1671
200SL1-1 1527
201SL1-1 1527
202SL1-1 1527
203SL1-1 1527
204SL1-1 1527
205SL1-1 1527
206SL1-1 1527
207SL1-1 1527
20-Line Serial Communications Option Installation (DA190) 1649
210SL1-1 1527
212 A Modem 1548
212 A/O Modem 1547
212SL1-1 1527
213SL1-1 1527
214SL1-1 1527
215SL1-1 1527
216SL1-1 1527
217SL1-1 1527
218SL1-1 1527
219SL1-1 1527
220V Power Cord 240, 392, 1367
223SL1-1 1527
224SL1-1 1527
225SL1-1 1527
226SL1-1 1527
227SL1-1 1527
228SL1-1 158, 377, 1364
229SL1-1 1528
230SL1-1 1528
231SL1-1 1528
232SL1-1 1528
233MHz MMX SBC Kit for AP (700tp), MRS/AP (700tp), MRS/Tower, MRS/Rack, AP/Rack 1626
234M Disk 1398, 1583
234SL1-1 1528
235SL1-1 1528
238SL1-1 1528
239SL1-1 1528
2-4 Hour Battery Back-Up Unit 66, 197, 700, 1429, 1614
24 Port T1 Board 1371, 1559
24 to 28 Port Expansion Kit 1639
240 MByte Hard Disk/155 MByte Tape Drive Assembly 326, 596, 1412
240MB Hard Disk Drive Unit 326, 402, 1369
241SL1-1 1528
242SL1-1 1528

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

243SL1-1 1528
244SL1-1 1528
245SL1-1 1528
246SL1-1 1528
247SL1-1 1528
248SL1-1 1528
249SL1-1 1528
24MB Call Processor Card (CP) 1408, 1596
24-Port T1 Voice Port Assembly for MRS/Tower or MRS/Rack 1585
25 Ft. Ethernet Cable, Category 5 38, 223, 306, 409, 1371
25 Pair Double Ended Cable 239, 392, 1367
25 Pair Single Ended Cable 239, 392, 1367
250SL1-1 1528
251SL1-1 1528
252SL1-1 1528
255SL1-1 1528
256 MB SDRAM 30, 221, 1377
256K RAM Memory 1505, 1682
256KB L2 Async Cache Spare 294, 928, 1455
256MB RAM 1625
256SL1-1 1528
257SL1-1 1528
258SL1-1 1528
259SL1-1 1528
260SL1-1 1528
278SL1-1 1528
280SL1-1 1528
281SL1-1 1528
282SL1-1 1528
285SL1-1 1528
286SL1-1 1528
287SL1-1 1528
290SL1-1 1528
291SL1-1 1529
293SL1-1 1529
29806 IMS Key Cap Kit 1570
299SL1-1 1529
2-Conductor Line Cord (25 Ft.) Satin, (M2000 Series and M3901) 205, 404, 1369
2GB 16BIT Ultra SCSI Disk Drive Spare 1460, 1626
2GB SCSI SCA Disk Drive 304, 305, 854, 1446
2GB SCSI SCA Disk Drive (Hot Swap) Spare 1626
2GB Ultra SCSI Disk Drive 304, 857, 1446
2M Baud Converter (RPE) 1505, 1681
3 Port CPU Interconnect 1502, 1679
3.5 Inch Digital Cassette Tape Drive 1366, 1553
3.5" EIDE Floppy Drive 41, 307, 854, 1446
3.5" SCSI DAT Tape Drive Spare 1460, 1626
30 Ft. DUAL Port Fiber Daughterboard 68, 179, 715, 1432
30 Ft. Fiber Daughterboard - Multi Mode 67, 179, 710, 1431
30 Ft. Fiber Receiver Card 67, 179, 710, 1431
30/150V PE Power Converter 1505, 1682
300MB Disk Drive 1366, 1369, 1370, 1553, 1558, 1559
300MB Hard Disk Assembly 1482, 1649
300MB Hard Disk Drive 1400, 1407, 1588, 1596
300SL1-1 1529
300W Power Supply 38, 221, 303, 1375
301SL1-1 1529
302SL1-1 1529
303SL1-1 1529
304SL1-1 1529
305SL1-1 1529
306SL1-1 1529
307SL1-1 1529
308SL1-1 1529
309SL1-1 1529
30-Port E1 Voice Port Assembly for MRS/AP 1584
30-Port E1 Voice Port Assembly for MRS/Tower or MRS/Rack 1585
30V Converter Pack 1506, 1683
310SL1-1 1529
311SL1-1 1529
312SL1-1 1529
313SL1-1 1529
314SL1-1 1529
315SL1-1 1529
316SL1-1 1529
317SL1-1 1529
318SL1-1 1529
319SL1-1 1529
32 MB DIMM 305, 1376
32 MB Memory Upgrade 270, 975, 1462
32 Session Expansion for 3270 or 5250 1586
32 to 36 Port Expansion Kit 1639
320 MB Server/8MB RAM (CNS54b) 1553
320MB Expansion Disk (ESD150) 1553
320MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS54D) 1552
320MB Server w/8MB Memory and 32KB Cache Memory (CNS54C) 1554
320MB Server/8MB RAM/Cache (CNS54A) 1554
320SL1-1 1529
321SL1-1 1529
322SL1-1 1529
323SL1-1 1529
324SL1-1 1529
325SL1-1 1529
326SL1-1 1529
3270 BSC Data Communications Software 1704
3270 Communications Controller 1369, 1558
3270 Communications Controller with Transition Card 1366, 1553
3270 Host Communications - SDLC 1585

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

3270 Host Communications - SDLC - 16 Ports 1583
3270 Host Communications - SDLC - 4 Ports 1583
3270 Host Communications - SDLC - 8 Ports 1583
3270 Host Communications - Token Ring - 16 Ports 1583
3270 Host Communications - Token Ring - 4 Ports 1583
3270 Host Communications - Token Ring - 8 Ports 1583
3270 Host Communications - Token Ring (32 Sessions) 1585
3270 SDLC Data Communications Software 1704
3270 SNA SDLC Manuals 1584
3270/BSC Option Guide (DA182-01) 1648
3270/SNA Option Guide (DA181-01) 1553
327SL1-1 1529
328SL1-1 1529
329SL1-1 1529
32K x 17R/W Memory (CDR) 1501, 1677
32MB DRAM SIMM Upgrade Kit 182, 1056, 1470
32MB Expansion RAM for AP or MRS/AP Spare 1626
32MB Expansion RAM for MRS/Tower or MRS/Rack Spare 282, 966, 1460
32MB Flash Memory Upgrade Kit 182, 1057, 1470
32MB RAM Spare 1624
33 Ft. Plastic Fiber Cable (11E/11C) 66, 187, 403, 1369
33.6 KBPS External Data/Fax Modem 272, 423, 1373
330SL1-1 1529
331SL1-1 1530
332SL1-1 1530
333SL1-1 1530
334SL1-1 1530
335SL1-1 1530
336SL1-1 1530
337SL1-1 1530
338SL1-1 1530
339SL1-1 1530
340SL1-1 1530
344SL1-1 1530
345SL1-1 1530
346SL1-1 1530
347SL1-1 1530
350 MB Hard Disk Assembly 1399, 1587
350MB Disk Upgrade 1714
350SL1-1 1530
351SL1-1 1530
352SL1-1 1530
36 to 40 Port Expansion Kit 1639
360SL1-1 1530
361SL1-1 1530
370SL1-1 1530
371SL1-1 1530
372SL1-1 1530
373SL1-1 1530
374SL1-1 1530
375SL1-1 1530
3-Button Mouse Spare 281, 295, 965, 1460
3M Tape Drive Cleaning Kit 1569
3MB PCMCIA Flash Card 1560
3PE to I/O Housing Cable (8 Ft.) 195, 830, 1443
3-Port DS1 ATM Function Processor 1438, 1619
3-Port DS3 ATM Function Processor 1438, 1619
3-Port DS3/E3 Termination Panel 1439, 1619
3-port SDI Cable (1.5m or 5 Ft.) 67, 193, 703, 1430
4 Ft. Ethernet Cable, Category 5 38, 223, 306, 408, 1370
4 GB Hard Drive 1628
4 GB IDE Drive for the 200i System 42, 222, 860, 1447
4 Mbyte Floppy Disk Unit 1442, 1622
4 Mbyte Multi-Disk Unit 1442, 1622
4 Port Basic Service Voice Processing Package, EC/EC11 247, 258, 490, 1381
4 Port Basic Service Voice Processing Package, Modular GP 259, 492, 1381
4 Port Basic Service Voice Processing Package, Options 259, 492, 1381
4 Port Fax Modem Card AudioFax 270, 559, 1405
4 Port Full Service Voice Processing Package, EC/EC11 247, 258, 490, 1381
4 Port Full Service Voice Processing Package, Modular GP 259, 491, 1381
4 Port Full Service Voice Processing Package, Options 259, 492, 1381
4 Port RS232 Cable 249, 268, 578, 1408
4 Port SDI Assembly 159, 446, 1378, 1527
4 Port SDI Assembly - EMI 1527
4 Port SDI Cable 67, 193, 695, 1428, 1612
4 Port SDI Paddle Board Assembly 159, 446, 1378
4 Stack Bus Redundancy Package 1639
4 to 8 Port Basic Service Voice Processing Expansion Package, EC/EC 11 259, 493, 1381
4 to 8 Port Full Service Voice Processing Expansion Package, EC/EC11 258, 493, 1381
4 to 8 Session Expansion for 3270 and 5250 1560
4 Wire E&M Trunk 1502, 1678
4.5GB Modular Hard Disk Drive 258, 267, 574, 1407
4.5GB SCA UltraSCSI Hard Disk Spare 295, 930, 1455
4.5GB SCSI Disk Drive Spare for OIVR 4.0 MRS/Rack or Rack AP 1626
4.5GB SCSI SCA Disk Drive Spare for AP, MRS/AP, R4 MRS/Tower 1626
40 MB Disk Drive 1555
400SL1-1 1530
401SL1-1 1530

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

402SL1-1 1530
403SL1-1 1530
404SL1-1 1530
409SL1-1 1530
40MB PCMCIA Card - Blank 25, 1558
410SL1-1 1530
411SL1-1 1530
412SL1-1 1530
413SL1-1 1531
414SL1-1 1531
415SL1-1 1531
416SL1-1 1531
417SL1-1 1531
418SL1-1 1531
420SL1-1 1531
421SL1-1 1531
422SL1-1 1531
423SL1-1 1531
424SL1-1 1531
425SL1-1 1531
426SL1-1 1531
430SL1-1 1531
431SL1-1 1531
432SL1-1 1531
433SL1-1 1531
434SL1-1 1531
435SL1-1 1531
436SL1-1 1531
437SL1-1 1531
438SL1-1 1531
439SL1-1 1531
43MB 1552
43MB Kit (CS019) 1382, 1568
43MB Server/2MB RAM (SA112) 1549
440SL1-1 1531
441SL1-1 1531
442SL1-1 1531
443SL1-1 1531
444SL1-1 1531
445SL1-1 1531
446SL1-1 1531
447SL1-1 1531
448SL1-1 1531
449SL1-1 1531
450SL1-1 1532
451SL1-1 1532
452SL1-1 1532
460SL1-1 1532
461SL1-1 1532
462SL1-1 1532
463SL1-1 1532
464SL1-1 1532
465SL1-1 1532
466SL1-1 1532
467SL1-1 1532
468SL1-1 1532
469SL1-1 1532
470SL1-1 1532
471SL1-1 1532
472SL1-1 1532
473SL1-1 1532
474SL1-1 1532
475SL1-1 1532
476SL1-1 1532
477SL1-1 1532
478SL1-1 1532
479SL1-1 1532
-48 VDC Power Converter 1587
48 VDC TO 120 VAC Static Inverter Spare 1460, 1626
-48 VDC Wiring Harness 1587
-48 VDC Wiring Harness $725-650 (Replaces NT4G13AK) 1587
480SL1-1 1532
481SL1-1 1532
482SL1-1 1532
484SL1-1 1532
48MB Call Processor Card (CP) 81/81C Systems with 68030/48MB CP Requires X11 Release 21 Software Generic 1611 1408, 1596
48MB Memory Upgrade Kit 1638
48V DC 400W Load Sharing Hot Swap Power Supply 38, 221, 1374
48V DC 400W Load Sharing Hot Swap Power Supply Spare 282, 970, 1461
-48V DC Rectifier Assembly (QRF8) 1638
48V Rectifier 1506, 1683
48V Rectifier Assembly 1507, 1684
48V Regulator 1501, 1677
-48volt Rectifier 185, 501, 1384
495SL1-1 1532
498SL1-1 1532
499SL1-1 1532
4GB 16Bit Ultra SCSI Disk Drive 304, 857, 1446
4GB SCSI Hot Swap Disk Drive 221, 304, 305, 854, 1446
4K x 16 ROM 1502, 1503, 1678, 1679
4K x 17 R/W Memory 1502, 1679
4-Line Serial Communications Adapter (NM100) 1366, 1549
4MB Memory Expansion Board (EMB104) 1551
4-Port DS1 Function Processor 1438, 1618
4-Port DS1C (Channelized) Function Processor 1438, 1618
4-Port DSP Daughter Card 59, 239, 820, 1441
4-Port Loopstart Card 1560
5 Port RS232 Cable 268, 577, 1408
5/12V Converter 1505, 1682

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

5/12V Converter Pack 1502, 1678
5/12V Converter Pack (RPE) 1506, 1683
50 Amp Rectifier 185, 550, 1401, 1589
50 Amp Rectifier Expansion Assembly Installation NTP 353, 1485
50 Amp Rectifier Expansion Package 160, 469, 1379
50 Hours (1 x 540MB disk) 1559
50 Pin Connector Cover Plate 198, 1141, 1481
500 Line Card for Modem Pool Interface 1503, 1679
500/2500 Line Card 1503, 1505, 1680, 1681
500/2500 Line Card (16 Port) 1505, 1681
500SL1-1 1532
501SL1-1 1532
502SL1-1 1532
503SL1-1 1532
504SL1-1 1533
505SL1-1 1533
506SL1-1 1533
507SL1-1 1533
508SL1-1 1533
50M Streaming Tape 1398, 1583
5-1/4 In. Floppy Diskette 1548
510SL1-1 1533
511SL1-1 1533
512K Memory Card 1505, 1682
512KB Video RAM Spare 294, 928, 1455
512SL1-1 1533
513SL1-1 1533
514SL1-1 1533
515SL1-1 1533
520SL1-1 1533
521SL1-1 1533
522SL1-1 1533
52310 1533
52311 1533
52323 1533
52330 1533
52331 1533
52332 1533
52333 1533
523SL1-1 1533
52410 1533
52420 1533
52430 1533
52431 1533
52450 1533
52451 1533
52452 1533
52453 1533
52454 1533
524SL1-1 1533
5250 Host Communication - Token Ring - 16 Ports 1583
5250 Host Communications - SDLC 1585
5250 Host Communications - SDLC - 16 Ports 1583
5250 Host Communications - SDLC - 4 Ports 1583
5250 Host Communications - SDLC - 8 Ports 1583
5250 Host Communications - Token Ring 1585
5250 Host Communications - Token Ring - 4 Ports 1583
5250 Host Communications - Token Ring - 8 Ports 1583
52500 1533
52501 1533
52502 1534
52503 1534
52504 1534
525SL1-1 1534
525W Power Supply Spare 295, 929, 1455
52600 1534
52601 1534
52602 1534
52603 1534
52610 1534
526SL1-1 1534
527SL1-1 1534
528SL1-1 1534
529SL1-1 1534
52MB (formatted) SCSI (EXP110) Expansion Disk Drive 1549
52MB Server/2MB RAM (DTS212) 1549
-52V/30 Amp Rectifier 1407, 1596
-52volt Rectifier 185, 502, 1384
530SL1-1 1534
531SL1-1 1534
532SL1-1 1534
533SL1-1 1534
534SL1-1 1534
535SL1-1 1534
536SL1-1 1534
537SL1-1 1534
538SL1-1 1534
539SL1-1 1534
542SL1-1 1534
543SL1-1 1534
544SL1-1 1534
545SL1-1 1534
546SL1-1 1534
547SL1-1 1534
548SL1-1 1534
549SL1-1 1534
550SL1-1 1534
551SL1-1 1534
552SL1-1 1535
5535 Keyboard w/Keylock 1570
553SL1-1 1535
554SL1-1 1535
555SL1-1 1535

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

556SL1-1 1535
557SL1-1 1535
558SL1-1 1535
559SL1-1 1535
561SL1-1 1535
562SL1-1 1535
563SL1-1 1535
569SL1-1 1535
571SL1-1 1535
573SL1-1 1535
574SL1-1 323, 377, 1364
575SL1-1 1535
57600 1535
57635 1535
577SL1-1 1535
578SL1-1 1535
57935 1535
579SL1-1 1535
580SL1-1 1535
581SL1-1 1535
582SL1-1 1535
583SL1-1 1535
58600 1535
58635 1535
586SL1-1 1535
587SL1-1 1535
588SL1-1 1535
58935 1535
589SL1-1 1535
590SL1-1 1535
591SL1-1 1535
592SL1-1 1536
593SL1-1 1536
594SL1-1 1536
595SL1-1 1536
59600 1536
59635 1536
596SL1-1 1536
597SL1-1 1536
598SL1-1 1536
59935 1536
599SL1-1 156, 377, 1364
-5V ISA Card Spare for Rack AP and MRS/Rack 283, 1462
6 Drive SCSI Rack Assembly Spare OIVR 4 283, 1461
6 Mbyte Memory Card 1442, 1622
60001 1536
60002 1536
60003 1536
60005 1536
60006 1536
60008 1536
60010 1536
60013 1536
60014 1536
60020 1536
600MB Data Cassette Tape 326, 1369
600MB Hard Disk 1383, 1570
600MB Hard Disk Drive 1400, 1407, 1588, 1596
600MB Tape Drive Repair Kit 25, 1561
600MB Tape Drive Unit 25, 1558
600SL1-1 1536
601SL1-1 1536
602SL1-1 1536
603SL1-1 1536
604SL1-1 1536
605SL1-1 1536
606SL1-1 1536
607SL1-1 1536
608SL1-1 1536
609SL1-1 1536
60MB Tape Backup VINES/286,386 (EXT106) 1551
610SL1-1 1536
611SL1-1 1536
612SL1-1 1536
613SL1-1 1536
614SL1-1 1537
615SL1-1 1537
618SL1-1 1537
619SL1-1 1537
620SL1-1 1537
621SL1-1 1537
622SL1-1 1537
623SL1-1 1537
624SL1-1 1537
625SL1-1 1537
626SL1-1 1537
627SL1-1 1537
628SL1-1 1537
629SL1-1 1537
63010 1537
63011 1537
63012 1537
63013 1537
63014 1537
63015 265, 378, 1364
63016 265, 378, 1364
63017 265, 378, 1364
63018 1537
63019 1537
63020 1537
63021 1537
63022 1537
63023 1537
63024 1537
63025 1537
63026 1537, 1538
63027 1538

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

63028 1538
63029 1538
63030 1538
63031 265, 379, 1364
63032 1538
63033 265, 379, 1364
63034 1538
63035 1538
63036 1538
63037 1538
63038 1538
63039 1538
63040 1538
63041 1538
63042 1538
63043 1538
63044 1538
63046 1538
63047 1538
63048 1538
63049 1538
63050 1538
63051 1538
63052 1538
63053 1538
63054 1538
63055 1538
63056 1538
63057 1538
63058 1538
63059 1538
63060 265, 380, 1364
63061 1539
63062 1539
630SL1-1 1539
631SL1-1 1539
632SL1-1 1539
633SL1-1 1539
634SL1-1 1539
635SL1-1 1539
638SL1-1 1539
639SL1-1 1539
64 MB Memory Upgrade Package 270, 976, 1462
64 MB SIMM 304, 1375
640SL1-1 1539
641SL1-1 1539
642SL1-1 1539
643SL1-1 1539
644SL1-1 1539
645SL1-1 1539
646SL1-1 1539
647SL1-1 1539
648SL1-1 1539
649SL1-1 1539
64K Memory Module 1504, 1680
64K Memory Module Assembly 1530
64MB (SIMM) Expansion RAM for AP or MRS/AP 1626
64MB RAM Expansion for AP or MRS/AP 1624
64MB RAM Expansion for OIVR 4.0 AP, MRS/AP and MRS 276, 935, 1455
64MB SDRAM DIMM 304, 1375
650SL1-1 1539
651SL1-1 1539
652SL1-1 1539
653SL1-1 1539
654SL1-1 1539
655SL1-1 1539
656SL1-1 1539
657SL1-1 1539
658SL1-1 1539
659SL1-1 1539
660 MB Server w/8MB Burst Memory and 8KB On-Chip Cache (CNS64D) 1552
660 MB Server w/8MB Memory and 32KB Cache Memory (CNS64C) 1552
660SL1-1 1539
661SL1-1 1539
662SL1-1 1540
663SL1-1 1540
664SL1-1 1540
665SL1-1 1540
666SL1-1 1540
667SL1-1 1540
668SL1-1 1540
669SL1-1 1540
670SL1-1 1540
671SL1-1 1540
672SL1-1 1540
673SL1-1 1540
674SL1-1 1540
675SL1-1 1540
676SL1-1 1540
677SL1-1 1540
678SL1-1 1540
68 pin Wide SCSI Cable 221, 303, 424, 1373
6-8 Port Basic Service Voice Processing Expansion Package, Card Option 237, 494, 1381
6-8 Port Full Service Voice Processing Expansion Package, Card Option 237, 494, 1381
68040/48MB Call Processor 1419, 1606
68040/64MB Call Processor 1419, 1606
68040/96MB Call Processor 1419, 1606
68060 Enhanced 112MB Call Processor 1401, 1589
68060 Enhanced 128MB Call Processor 177, 551, 1401, 1589
68060 Enhanced 160MB Call Processor 177, 551, 1401

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

68060 Enhanced 48MB Call Processor 1401, 1589
68060 Enhanced 64MB Call Processor 1401, 1589
68060 Enhanced 80MB Call Processor 1401, 1589
68060/112MB Call Processor 1401, 1589
68060/48MB Call Processor 1401, 1589
68060/64MB Call Processor 1401, 1589
68060/80MB Call Processor 1401, 1589
680SL1-1 1540
681SL1-1 1540
683SL1-1 1540
684SL1-1 1540
685SL1-1 1540
686SL1-1 1540
687SL1-1 1540
688SL1-1 1540
68K Processor Card 1408, 1597
68K Processor Pack 239, 694, 1427, 1611
690SL1-1 1540
691SL1-1 1540
692SL1-1 1540
693SL1-1 1540
694SL1-1 1540
6-Conductor Line Cord (14 Ft. for M2000 Series requiring external power and M3902, M3903, M3904 and M3905) 205, 385, 1366
6-Conductor Line Cord (25 Ft. M2000 Series requiring external power, and for M3902, M3903, M3904 and M3905) 1552
6-Conductor Line Cord (7 Ft. for M2000 telephones requiring external power, standard for M3902, M3903, M3904, and M3905) 205, 385, 1366
6-Line Serial COM Adapter - MC Servers (ICA210) 1552
6M Processor Assembly 1638
6MS Processor Assembly 1638
6-Serial Line Intelligent Communication Adapter (ICA108) 1551
7 Ft. Ethernet Cable, Category 5 38, 223, 306, 409, 1371
700 Series DC Power Converter 41, 222, 307, 858, 1447
701t 128 MB DIMM 303, 1373
701t 64 MB DIMM 303, 1373
702t Base Documentation Package, English 31, 227, 842, 1444
702t Base System 1375, 1561
702t BIOS 226, 1446
702t CPU 450 MHz Pentium II 38, 306, 1375
702t Installation and Maintenance Guide 228, 307, 1162, 1493
702t Installation and Maintenance Guide - French 1671
702t OEM System With no Processor and no Memory 28, 38, 303, 1375
702t SYMPOSIUM Call Center Server Advanced with RAID (DMS) 34, 1065, 1471
702t System Setup Utility 226, 1446
706SL1-1 1540
707SL1-1 1541
70MB Disk ST506 (SA210) Expansion Drive 1365, 1549
70MB Server/2MB RAM (SA122) 1549
70MB Server/4MB RAM (SA124) 1550
710SL1-1 1541
711SL1-1 1541
718SL1-1 1541
730SL1-1 1541
731SL1-1 1541
732SL1-1 1541
735SL1-1 1541
736SL1-1 1541
737SL1-1 1541
739SL1-1 1541
740SL1-1 1541
745SL1-1 1541
746SL1-1 1541
747SL1-1 1541
748SL1-1 1541
749SL1-1 1541
750SL1-1 1541
753SL1-1 1541
754SL1-1 1541
755SL1-1 1541
756SL1-1 1541
757SL1-1 1541
758SL1-1 1541
759SL1-1 1541
75MHz P5 Processor for Alt/Mag 1559
766SL1-1 1541
767SL1-1 1541
768K Memory 1505, 1681
768K Memory Card 1506, 1683
768K RAM Assembly 1545
768SL1-1 1541
769SL1-1 1542
770SL1-1 1542
771SL1-1 1542
772SL1-1 1542
773SL1-1 1542
774SL1-1 1542
775SL1-1 1542
776SL1-1 1542
777SL1-1 1542
778SL1-1 1542
779SL1-1 1542
780SL1-1 1542
790SL1-1 1542
795SL1-1 1542
796SL1-1 1542

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

8 Port Basic Service Voice Processing Package, EC/EC11 247, 258, 491, 1381
8 port DCE DB25 Octa Cable Spare 295, 930, 1455
8 Port Digiboard with DCE Octa Cable 1560
8 Port Full Service Voice Processing Package, EC/EC11 247, 258, 491, 1381
8 Port Terminal Concentrator (TC) (RJ-11 Connections) 1554
8 Port Terminal Concentrator/FM (TC/FM) (RJ45) 327, 388, 1367
8 Stack Bus Redundancy Package 1639
8 to 16 Session Expansion for 3270 and 5250 1560
8.5 x 11 Paper 1569
80 MB Disk Drive Upgrade (5 Hours Storage) 1714
800SL1-1 1542
801SL1-1 1542
802SL1-1 1542
803SL1-1 1542
80MB (formatted) SCSI (EXP120) Expansion Disk Drive 1549
80MB Disk Drive 1367, 1555
80MB Expansion Disk (ESD120) 1551
80MB Server w/4MB Memory and 32KB Cache Memory (CNS22C) 1553
80MB Server/3MB RAM (DTS223) 1549
80MB Server/4MB RAM (CNS22B) 1551
80MB Server/4MB RAM (SAS124) 1551
810SL1-1 1542
811SL1-1 1542
812SL1-1 1542
813SL1-1 1542
814SL1-1 1542
815SL1-1 1542
816SL1-1 1542
817SL1-1 1542
820SL1-1 1542
821SL1-1 1542
822SL1-1 1542
823SL1-1 1542
826SL1-1 1542
827SL1-1 1542
828SL1-1 1542
829SL1-1 1543
830SL1-1 1543
831SL1-1 1543
832SL1-1 1543
833SL1-1 1543
834SL1-1 1543
835SL1-1 1543
836SL1-1 1543
837SL1-1 1543
838SL1-1 1543
839SL1-1 1543
840SL1-1 1543
850SL1-1 1543
851SL1-1 1543
852SL1-1 1543
853SL1-1 1543
854SL1-1 1543
855SL1-1 1543
856SL1-1 1543
859SL1-1 1543
861SL1-1 1543
862SL1-1 1543
863SL1-1 1543
864SL1-1 1543
865SL1-1 1543
866SL1-1 1543
867SL1-1 1543
868SL1-1 1543
869SL1-1 1543
871SL1-1 1543
872SL1-1 1543
875SL1-1 1543
876SL1-1 1543
882SL1-1 1543
883SL1-1 1544
884SL1-1 1544
885SL1-1 1544
886SL1-1 1544
887SL1-1 1544
888SL1-1 1544
889SL1-1 1544
891SL1-1 1544
892SL1-1 1544
894SL1-1 1544
895SL1-1 1544
896SL1-1 1544
8-Channel Asynchronous I/O Card Kit 316, 327, 577, 1408
8-Channel Asynchronous I/O Software Support for Meridian MAX Releases 6, 7, and 8 (MAX-SNN and MAX-SNNE) 319, 1224, 1514
8-Channel Asynchronous I/O Support for Meridian MAX Release 9 Software 317, 1181, 1510
8K ROM 1502, 1503, 1678, 1679
8K ROM Card 1505, 1681
8K x 17 R/W Memory (CDR-Single Port) 1503, 1679
8MB Memory Expansion Board (EMB108) 1551
8MB PCMCIA Flash Card 176, 343, 1373
8-Port Communications Controller Board 1548
8-Port ISDN/BRI Voice Port Assembly for MRS/AP 1584
8-Port ISDN/BRI Voice Port Assembly for MRS/Tower or MRS/Rack 1585
8-Port V.11 Function Processor 1438, 1618
8-Port V.35 Function Processor 1438, 1619
8-port V.35 Functional Processor 1438, 1618

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

9 Drop SC Bus Cable 39, 223, 1376
9 GB Disk Hot Swap 42, 222, 1447
9 GB Hard Drive 1628
9 GB SCSI Disk 42, 222, 1447
900SL1-1 1544
910SL1-1 1544
920SL1-1 1544
921SL1-1 1544
922SL1-1 1544
923SL1-1 1544
924SL1-1 1544
925SL1-1 1544
926SL1-1 1544
930SL1-1 1544
931SL1-1 1544
932SL1-1 1544
933SL1-1 1544
934SL1-1 1544
935SL1-1 1544
936SL1-1 1544
937SL1-1 1544
938SL1-1 1544
939SL1-1 1544
940SL1-1 1544
941SL1-1 1544
942SL1-1 1544
943SL1-1 1545
944SL1-1 1545
950SL1-1 1545
951SL1-1 1545
952SL1-1 1545
953SL1-1 1545
954SL1-1 1545
955SL1-1 1545
956SL1-1 1545
957SL1-1 1545
958SL1-1 1545
959SL1-1 1545
9600 Baud Modem 1558
960SL1-1 1545
961SL1-1 1545
962SL1-1 1545
963SL1-1 1545
964SL1-1 1545
965SL1-1 1545
966SL1-1 1545
967SL1-1 1545
969SL1-1 1545
970SL1-1 1545
971SL1-1 1545
972SL1-1 1545
974SL1-1 1545
975SL1-1 1545
976SL1-1 1545
977SL1-1 1545
979SL1-1 1545
980SL1-1 1545
981SL1-1 1545
982SL1-1 1545
983SL1-1 1546
984SL1-1 1546
985SL1-1 1546
9GB Hot-Swap Ultra2 SCSI LP Hard Disk Drive 29, 306, 1376

A

A, S, M/ST Cabinet Upgrade Assembly 1714
A/M/MS/L/S/ST Upgrade Assembly 1714
A/MS Shelf Upgrade Assembly 1542
A0100025 187, 1364
A0110539 1546
A0237451 187, 380, 1364
A0239439 1546
A0247602 1546
A0247603 1546
A0247604 1546
A0247605 1546
A0247606 1546
A0247607 1546
A0247632 1546
A0247633 1546
A0247634 1546
A0247635 1546
A0247636 1546
A0247644 1546
A0247645 1546
A0247646 1546
A0253756 1546
A0253757 1546
A0253758 1546
A0253778 1546
A0253779 1546
A0254746 1546
A0254763 1546
A0254951 1546
A0256222 1546
A0263854 187, 380, 1364
A0273211 1546
A0273213 1546
A0274225 205, 380, 1364
A0274243 1546
A0274934 1546
A0275286 187, 381, 1364
A0283471 1546
A0283540 1546
A0283581 1547

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0285536 1547
A0286116 1547
A0287305 1547
A0288529 209, 381, 1364
A0291215 1547
A0291605 1547
A0292116 1547
A0292928 335, 381, 1364
A0293344 1547
A0296006 1547
A0296738 1547
A0297075 1364, 1547
A0297366 1547
A0297963 1547
A0297998 1547
A0298000 1547
A0298626 1364, 1547
A0298627 1364, 1547
A0298628 1364, 1547
A0298629 1364, 1547
A0298634 1364, 1547
A0298635 1364, 1547
A0298636 1364, 1547
A0298637 1364, 1547
A0298638 1364, 1547
A0298639 1364, 1547
A0298640 1364, 1547
A0298641 1365, 1547
A0299899 1547
A0300752 187, 381, 1365
A0300753 187, 381, 1365
A0301005 1547
A0302358 1547
A0310198 1547
A0310532 1547
A0314408 205, 382, 1365
A0314597 326, 382, 1365
A0315068 1547
A0317073 1547
A0318327 205, 382, 1365
A0318330 205, 382, 1365
A0318423 187, 382, 1365
A0319032 1365, 1548
A0319033 1365, 1548
A0320897 1365, 1548
A0321130 1548
A0322433 1365, 1548
A0322434 1365, 1548
A0322435 1365, 1548
A0322436 1365, 1548
A0324084 1548
A0325663 1548
A0325987 1548
A0326595 1365, 1548
A0326596 1365, 1548
A0326597 1365, 1548
A0326598 1365, 1548
A0326745 267, 383, 1365
A0326760 1548
A0326761 187, 383, 1365
A0326762 187, 383, 1365
A0326763 187, 383, 1365
A0326766 1365, 1548
A0326767 1365, 1548
A0326768 1365, 1548
A0326769 1365, 1548
A0326775 1548
A0326800 1548
A0327123 1548
A0327128 205, 384, 1365
A0327130 1548
A0327146 1548
A0327147 1548
A0329160 1548
A0329723 1548
A0329748 1548
A0329944 1548
A0329960 1548
A0334590 205, 384, 1365
A0336406 209, 384, 1365
A0336822 1549
A0336823 209, 384, 1365
A0336834 1549
A0336854 1549
A0336855 1549
A0336856 1549
A0336857 1549
A0336858 1365, 1549
A0336859 1366, 1549
A0336860 1366, 1549
A0336861 1366, 1549
A0336862 1549
A0336863 1549
A0336864 1549
A0336865 1549
A0336866 1549
A0336867 1549
A0336868 1549
A0336869 1549
A0336901 1549
A0336902 1549
A0336903 1549
A0336904 1549
A0336905 1549
A0336906 1549
A0336907 1549
A0336908 1366, 1549
A0336909 1366, 1549

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0336910 1366, 1549
A0336911 1549
A0336912 1549
A0336913 1549
A0336914 1549
A0336915 1549
A0336916 1549
A0336917 1550
A0336918 1550
A0336919 1550
A0336920 1550
A0336922 1550
A0336923 1550
A0336924 1550
A0336925 1550
A0336926 1550
A0336927 1550
A0336928 1550
A0336929 1550
A0336930 1550
A0336931 1550
A0336932 1550
A0336982 1550
A0336993 1550
A0336994 1550
A0336995 1550
A0336996 1550
A0336997 1550
A0336998 1550
A0336999 1550
A0337000 1550
A0339690 1550
A0341310 1550
A0343001 1550
A0343022 1550
A0343023 1550
A0343028 1550
A0343029 1550
A0343030 1550
A0343031 1550
A0344336 185, 384, 1366
A0344337 185, 385, 1366
A0345125 1550
A0345240 1551
A0345290 1366, 1551
A0345291 1366, 1551
A0345292 1366, 1551
A0345357 1551
A0345358 1551
A0345359 1551
A0345360 1551
A0345361 1551
A0345362 1551
A0345363 1551
A0345364 1551
A0345365 1551
A0345367 1551
A0345370 1551
A0345371 1551
A0345373 1551
A0345374 1551
A0345376 1551
A0345377 1551
A0345378 1551
A0345379 1551
A0345381 1551
A0345383 1366, 1551
A0345384 1366, 1551
A0345385 1366, 1551
A0345915 1551
A0345916 1551
A0345917 1551
A0345919 1551
A0345920 1551
A0345921 1551
A0345922 1551
A0345923 1551
A0345924 1552
A0345930 1552
A0345963 1552
A0345985 1552
A0345986 1552
A0346862 205, 385, 1366
A0346863 205, 385, 1366
A0346864 1552
A0348785 209, 385, 1366
A0351166 327, 386, 1366
A0351167 327, 386, 1366
A0351295 1552
A0351296 1552
A0351297 1552
A0351298 1552
A0351299 1552
A0351300 1552
A0351301 1552
A0351302 1552
A0351303 1552
A0351304 1552
A0351305 1552
A0351306 1552
A0351307 1552
A0351308 1552
A0351309 1552
A0351310 1552
A0351311 1552
A0351312 1552
A0351313 1552
A0351315 1552

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0351316 1552
A0351317 1552
A0351318 1552
A0351319 1552
A0351320 1552
A0351321 1552
A0351322 1552
A0351323 1552
A0351324 1553
A0351325 1553
A0351326 1553
A0351356 1366, 1553
A0351371 1366, 1553
A0351484 1553
A0351485 1553
A0351509 239, 249, 267, 327, 386, 1366
A0351919 327, 386, 1366
A0352209 1366, 1553
A0352210 1366, 1553
A0352271 326, 386, 1366
A0352758 317, 387, 1366
A0353378 1553
A0353397 1553
A0353398 1553
A0353670 1553
A0353671 1553
A0353672 1553
A0353673 1553
A0353674 1553
A0353675 1553
A0353676 1553
A0353677 1553
A0353678 1553
A0353679 1553
A0353680 1553
A0353681 1553
A0353682 1553
A0353683 1553
A0353684 1553
A0353685 1553
A0353686 1553
A0353687 1553
A0353688 1553
A0353689 1553
A0354417 1553
A0354454 1553
A0354471 1554
A0354682 1554
A0354683 1554
A0354954 185, 387, 1366
A0355200 196, 387, 1366
A0355244 1554
A0355245 1554
A0360824 1366
A0361284 1554
A0361365 187, 387, 1367
A0361709 196, 388, 1367
A0362142 1554
A0362143 1554
A0362144 1554
A0362175 1554
A0365364 1554
A0365365 1554
A0365366 1554
A0366311 1554
A0367335 209, 388, 1367
A0367601 209, 388, 1367
A0367752 1554
A0367754 1554
A0367916 185, 388, 1367
A0368534 327, 388, 1367
A0368760 239, 249, 267, 326, 389, 1367
A0368901 1554
A0369107 187, 389, 1367
A0369284 1554
A0369437 1554
A0369438 1554
A0369439 1554
A0369440 1554
A0369441 1554
A0369442 1554
A0369443 1554
A0369444 1554
A0369453 1554
A0369454 1554
A0369499 1554
A0369706 1554
A0369707 1554
A0369708 1554
A0369709 1554
A0369710 1554
A0369711 1555
A0369712 1555
A0369779 1555
A0369788 272, 389, 1367
A0370853 1555
A0370854 1555
A0372990 1555
A0374277 1555
A0376171 239, 249, 267, 390, 1367
A0376518 1555
A0376839 1367, 1555
A0376918 327, 390, 1367
A0376960 1555
A0377097 1367, 1555
A0377172 209, 390, 1367
A0377786 1367, 1555
A0377787 1555

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0377957 327, 391, 1367
A0377992 196, 1367
A0378002 1555
A0378003 1555
A0378004 1555
A0378005 1555
A0378006 1555
A0378007 1555
A0378008 1555
A0378009 1555
A0378010 1555
A0378011 1555
A0378012 1555
A0378013 1555
A0378014 1555
A0378015 1555
A0378016 1555
A0378017 1555
A0378018 1555
A0378019 1555
A0378020 1555
A0378021 1555
A0378022 1556
A0378023 1556
A0378025 1556
A0378152 1556
A0378153 1556
A0378154 1556
A0378219 1556
A0378220 267, 391, 1367
A0378251 1556
A0378252 196, 391, 1367
A0378327 1556
A0378652 66, 391, 1367
A0378688 327, 391, 1367
A0378849 1556
A0379350 239, 392, 1367
A0379351 239, 392, 1367
A0379412 240, 392, 1367
A0379431 66, 196, 392, 1367
A0379589 392, 1367
A0379673 240, 250, 392, 1367
A0379976 1556
A0380908 1367, 1556
A0381016 66, 196, 393, 1367
A0381391 1556
A0381458 1367, 1556
A0383333 296, 306, 393, 1367
A0383524 1367, 1556
A0383526 240, 250, 269, 393, 1367
A0383528 1556
A0383534 1367, 1556
A0384883 1556
A0385576 267, 393, 1367
A0386003 1556
A0386014 1556
A0386015 1556
A0386049 327, 394, 1367
A0386050 294, 394, 1367
A0386101 1368, 1556
A0387583 206, 394, 1368
A0387584 1556
A0387585 1556
A0387586 206, 394, 1368
A0387587 1556
A0387588 206, 394, 1368
A0387589 1556
A0387590 206, 395, 1368
A0387591 1556
A0387592 206, 395, 1368
A0387593 1556
A0387594 1556
A0387595 206, 395, 1368
A0387596 206, 395, 1368
A0387597 1556
A0387598 206, 396, 1368
A0387599 206, 396, 1368
A0387600 1556
A0387601 1556
A0387602 1556
A0387603 206, 396, 1368
A0387604 206, 396, 1368
A0387605 1556
A0387606 206, 397, 1368
A0387607 206, 397, 1368
A0387608 206, 397, 1368
A0387609 206, 397, 1368
A0387610 206, 398, 1368
A0387611 207, 398, 1368
A0387612 1557
A0387613 207, 398, 1368
A0387614 207, 398, 1368
A0387615 1557
A0387616 207, 399, 1368
A0387617 1557
A0387618 1557
A0387619 1557
A0387620 1557
A0387621 1557
A0387622 1557
A0387623 1557
A0387624 207, 399, 1368
A0387625 1557
A0387626 1557
A0387627 1557
A0387628 1557
A0387629 207, 399, 1368
A0387630 1557

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0387631 207, 399, 1368
A0387632 1557
A0387633 1557
A0387634 207, 400, 1368
A0387635 207, 400, 1368
A0387636 1557
A0387637 207, 400, 1368
A0387638 207, 400, 1368
A0387639 207, 401, 1368
A0387640 1557
A0387641 1557
A0387642 1557
A0387643 1557
A0388536 1557
A0389770 344, 1368
A0390595 207, 401, 1368
A0394669 1557
A0397391 1557
A0397394 1557
A0397705 207, 401, 1368
A0397852 350, 1368
A0397928 1557
A0399070 1557
A0408927 1557
A0408928 1557
A0409894 1557
A0600040 1557
A0600069 1369, 1557
A0600070 1557
A0600071 1557
A0600074 1558
A0600181 1369, 1558
A0600398 1369, 1558
A0600711 1369, 1558
A0600712 1369, 1558
A0601164 1558
A0601182 327, 1369
A0601396 196, 401, 1369
A0601397 196, 401, 1369
A0601464 223, 273, 306, 402, 1369
A0602257 1369, 1558
A0603704 1369, 1558
A0605411 326, 1369
A0609632 1558
A0609633 1558
A0609639 272, 1369
A0609641 272, 1369
A0614339 1558
A0615902 207, 1369
A0617009 1558
A0617010 1558
A0617011 326, 402, 1369
A0617012 25, 1558
A0618446 362, 1369
A0619621 196, 402, 1369
A0619919 1558
A0620100 66, 185, 402, 1369
A0620530 220, 1369
A0621070 269, 1369
A0622451 1558
A0622715 362, 1369
A0622896 273, 283, 402, 1369
A0623885 1558
A0627746 1558
A0627875 303, 305, 403, 1369
A0630697 239, 249, 267, 272, 283, 403, 1369
A0630704 1369, 1558
A0632449 1558
A0632902 66, 187, 403, 1369
A0633585 239, 249, 272, 283, 404, 1369
A0633651 25, 1558
A0634101 205, 404, 1369
A0634488 1369, 1558
A0634489 1369, 1558
A0634490 1369, 1558
A0634491 1369, 1558
A0634492 176, 404, 1370
A0634493 176, 404, 1370
A0634494 187, 404, 1370
A0634495 187, 405, 1370
A0634496 187, 405, 1370
A0634497 1558
A0634498 1558
A0636813 273, 283, 1370
A0637618 1558
A0637723 1558
A0637730 1558
A0637736 1558
A0637905 1370, 1558
A0638225 1559
A0638430 1559
A0638465 1559
A0638483 273, 283, 1370
A0638486 1559
A0638596 1559
A0638600 1559
A0638602 1559
A0638603 1559
A0638645 196, 273, 405, 1370
A0638930 1559
A0639011 1559
A0639207 1559
A0639209 1559
A0639224 1559
A0639225 272, 405, 1370
A0639226 272, 1370
A0639229 272, 283, 406, 1370
A0639230 1559

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0639231 1559
A0639271 1559
A0639272 1559
A0639335 1559
A0639513 273, 283, 406, 1370
A0639530 273, 283, 406, 1370
A0639546 1559
A0639569 273, 283, 406, 1370
A0639617 273, 283, 305, 406, 1370
A0639811 1559
A0639812 1559
A0640190 273, 283, 342, 407, 1370
A0640192 273, 283, 343, 407, 1370
A0640194 273, 284, 343, 407, 1370
A0640736 1559
A0642533 1559
A0643619 1559
A0644926 1559
A0644928 1559
A0645393 1370, 1559
A0645811 296, 306, 407, 1370
A0646699 273, 284, 305, 408, 1370
A0646715 273, 284, 305, 408, 1370
A0646718 305, 408, 1370
A0646721 305, 408, 1370
A0647283 1370, 1559
A0647317 273, 284, 305, 408, 1370
A0648372 223, 306, 408, 1370
A0648374 223, 306, 409, 1370
A0648375 223, 306, 409, 1371
A0648377 223, 306, 409, 1371
A0648378 223, 306, 409, 1371
A0648379 223, 306, 409, 1371
A0648522 1559
A0648523 1559
A0650990 1371, 1559
A0650996 273, 284, 410, 1371
A0651002 1559
A0651032 273, 284, 410, 1371
A0651035 273, 284, 410, 1371
A0651036 274, 284, 410, 1371
A0651037 274, 284, 410, 1371
A0651038 274, 284, 411, 1371
A0651039 274, 284, 411, 1371
A0651040 274, 284, 411, 1371
A0651041 274, 284, 411, 1371
A0651060 274, 284, 412, 1371
A0651062 274, 284, 412, 1371
A0651064 274, 284, 412, 1371
A0651108 1559
A0651111 1560
A0651112 1560
A0651329 1560
A0651349 1560
A0651350 274, 284, 412, 1371
A0651681 274, 284, 1371
A0652237 305, 412, 1371
A0652239 274, 413, 1371
A0652358 1560
A0652361 1560
A0652365 202, 413, 1371
A0652369 202, 413, 1371
A0652628 1560
A0652633 274, 284, 413, 1371
A0652634 274, 284, 413, 1371
A0652635 274, 284, 414, 1371
A0652638 274, 284, 414, 1371
A0652675 1560
A0652681 274, 284, 414, 1371
A0652687 274, 284, 414, 1371
A0652688 274, 284, 415, 1371
A0654392 1560
A0654393 1560
A0654394 1560
A0654949 274, 284, 1371
A0656847 274, 284, 305, 415, 1371
A0656874 274, 284, 305, 415, 1371
A0657076 1560
A0657566 274, 284, 415, 1371
A0657617 1560
A0657727 1560
A0657728 274, 285, 416, 1371
A0657730 274, 285, 416, 1372
A0657777 274, 285, 416, 1372
A0658110 274, 285, 416, 1372
A0658342 305, 416, 1372
A0658485 274, 285, 417, 1372
A0658488 274, 285, 417, 1372
A0658493 327, 417, 1372
A0658655 274, 285, 417, 1372
A0658690 274, 285, 418, 1372
A0658784 1560
A0658874 305, 418, 1372
A0658957 274, 285, 418, 1372
A0659125 272, 285, 418, 1372
A0659158 275, 285, 419, 1372
A0660140 1560
A0660167 1372, 1560
A0660168 332, 419, 1372
A0660169 332, 419, 1372
A0660170 332, 419, 1372
A0660171 332, 420, 1372
A0660172 332, 1372
A0660173 332, 420, 1372
A0660175 332, 420, 1372
A0660403 1560
A0660524 305, 420, 1372
A0660538 303, 305, 421, 1372

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0665488 332, 421, 1372
A0665642 332, 1372
A0666779 275, 285, 421, 1372
A0667973 1560
A0667975 1560
A0667976 1560
A0668892 1560
A0669467 326, 421, 1372
A0669468 326, 421, 1372
A0670533 303, 422, 1373
A0670630 1560
A0670634 303, 422, 1373
A0670802 303, 422, 1373
A0670854 1560
A0671007 1560
A0671783 303, 422, 1373
A0672418 303, 422, 1373
A0672913 350, 1373
A0672941 303, 423, 1373
A0674453 272, 423, 1373
A0676108 220, 423, 1373
A0677506 220, 304, 423, 1373
A0677508 220, 304, 424, 1373
A0681164 220, 1373
A0681326 220, 424, 1373
A0681873 221, 1373
A0683319 303, 424, 1373
A0683638 176, 343, 1373
A0683743 221, 1373
A0684753 221, 303, 424, 1373
A0684761 223, 1373
A0684822 223, 1373
A0685305 223, 1373
A0687194 1560
A0687196 1560
A0688017 176, 1373
A0688664 209, 424, 1373
A0696007 1560
A0696008 327, 425, 1373
A0720557 205, 425, 1373
A0720558 205, 425, 1373
A0720559 205, 425, 1373
A0720560 205, 425, 1373
A0720561 205, 426, 1373
A0720562 205, 426, 1373
A0720936 303, 1373
A0720937 303, 1373
A0721792 304, 426, 1373
A0721902 239, 249, 426, 1373
A0722048 304, 426, 1373
A0722070 304, 427, 1374
A0722084 304, 427, 1374
A0722476 306, 427, 1374
A0722762 304, 427, 1374
A0722776 1560
A0722777 1560
A0723663 221, 1374
A0723759 304, 428, 1374
A0724209 1560
A0724372 304, 1374
A0724373 304, 1374
A0724374 304, 1374
A0724375 304, 1374
A0725300 304, 428, 1374
A0725342 209, 1374
A0725949 221, 428, 1374
A0726965 304, 428, 1374
A0726966 304, 1374
A0727294 304, 429, 1374
A0727295 304, 429, 1374
A0728440 304, 429, 1374
A0728441 304, 429, 1374
A0728841 196, 1374
A0728871 1560
A0729069 221, 304, 1374
A0729360 1560
A0729362 202, 430, 1374
A0729364 1560
A0730854 326, 430, 1374
A0730856 25, 1561
A0731666 221, 1374
A0732456 1374, 1561
A0732458 1374, 1561
A0732527 1374, 1561
A0732528 1374, 1561
A0734765 430, 1374
A0734767 430, 1374
A0735349 221, 430, 1374
A0738130 221, 1374
A0741558 303, 1375
A0741561 221, 303, 1375
A0741567 221, 1375
A0741570 303, 1375
A0741571 303, 1375
A0741572 223, 1375
A0741573 303, 1375
A0741574 303, 1375
A0741576 221, 303, 1375
A0741577 303, 1375
A0741579 304, 1375
A0741582 1375, 1561
A0741595 304, 1375
A0743996 1561
A0744456 221, 431, 1375
A0744720 304, 1375
A0744727 306, 1375
A0757981 187, 431, 1375
A0757982 188, 431, 1375

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

A0759609 1375, 1561
A0759612 1375, 1561
A0759618 1375, 1561
A0759620 1375, 1561
A0761147 1561
A0761148 306, 1375
A0761993 188, 431, 1375
A0762506 185, 1375
A0766163 221, 1375
A0766182 221, 432, 1375
A0766331 188, 432, 1375
A0766997 221, 432, 1375
A0767002 1561
A0769307 1561
A0769310 223, 1375
A0769312 221, 432, 1375
A0771059 1561
A0772567 223, 1375
A0773054 176, 432, 1375
A0773055 176, 433, 1375
A0773056 176, 433, 1375
A0773059 176, 433, 1375
A0774466 434, 1375
A0774467 434, 1376
A0774468 434, 1376
A0774469 434, 1376
A0774470 435, 1376
A0774471 435, 1376
A0774472 435, 1376
A0774861 305, 1376
A0780247 221, 435, 1376
A0786611 1376, 1561
A0788107 223, 1376
A0788129 223, 436, 1376
A0788131 223, 1376
A0788198 223, 1376
A0797692 305, 1376
A0797705 305, 1376
A0797722 305, 1376
A0797724 305, 1376
A0797727 305, 1376
A0797938 305, 1376
A0797941 221, 1376
A0797948 305, 1376
A0797950 306, 1376
A0797971 306, 1376
A0797984 306, 1376
A0798087 306, 1376
A0798092 306, 1376
A0798117 306, 1376
A0798129 306, 1376
A0798155 306, 1377
A0798177 306, 1377
A0798258 306, 1377
A0798259 306, 1377
A0798260 306, 1377
A0800927 306, 1377
A0801312 306, 1377
A0802022 221, 1377
A0803022 221, 1377
A0805092 221, 1377
A0805434 221, 436, 1377
A0806019 223, 1377
A0810496 176, 436, 1377
A0811762 188, 436, 1377
A0813446 221, 1377
AC Outlet Adapter 1568
AC Power Distribution Box 1499, 1671
AC Rack Cabinet - Expansion 280, 957, 1459
AC Rack Cabinet - Full Assembly 280, 957, 1458
AC to DC Inverter for SYMPOSIUM Call Center, 48 to 240 Volt 1447, 1623
AC/DC Adapter 1568
AC/DC Power Converter 185, 1375, 1558
AC/DC Power Supply 66, 186, 250, 712, 714, 1427, 1432, 1611
Access API Ver. 1 Software License 1536
ACCESS Configuration Guide - MM13 349, 1496
ACCESS Link Kit for Meridian Mail 8, 9, 10, 11 307, 857, 1446
Accessory Package 1553
ACD 35MM Slide Updates 1647
ACD Agent Single Line Telephone Quick Reference Card (25/PK) 347, 1485, 1655
ACD Agent Telephone User Guide (15/PK) 1660
ACD Agents Telephone User Guide (15/PK) 1648
ACD Customer Slide Presentation Revision 2 1648
ACD D Application Software 1704
ACD D/MAX Report Enhancements 154, 1238, 1515
ACD Display Option, Ash 1396, 1581
ACD Display Option, Black 1396, 1581
ACD Display Option, Gray 1396, 1581
ACD Fax Pop 275, 1196, 1511
ACD Feature Document X11/X37 (15/PK) 352, 1481
ACD Link (MAX/ACD-D) 154, 1238, 1515
ACD Load Management (ACD-C2) 154, 1237, 1515
ACD Management Reports 1647
ACD MAX 2.0 Supervisors User Guide 1649
ACD MAX 3.0 Supervisor Guide 1653
ACD MAX Base Software Single to Dual Tower Upgrade 1705
ACD MAX Brochure 1649
ACD MAX Customer Controlled Routing Support and Reporting Option - Single or Dual Tower 1705
ACD MAX Demo Disk and Cassette 1653
ACD MAX Dual Tower Hardware Package 1609
ACD MAX Dual Tower Software 1609
ACD MAX Management Reports 1651

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

ACD MAX Networking Option - Single to Dual Tower Upgrade 1705
ACD MAX Networking Option Dual Tower 1544
ACD MAX Networking Option Single Tower 1544
ACD MAX Product Sales Guide 1651
ACD MAX Release 2.0 35MM Presentation 1652
ACD MAX Release 3.0 NTPs 1654
ACD MAX Release 4 - Dual Tower Hardware Upgrade Package 1714
ACD MAX Release 4 - Network Administration Center Connectivity 1706
ACD MAX Release 4 - Single Tower Hardware Upgrade Package 1714
ACD MAX Release 4 Software Upgrade - Dual Tower (ACD MAX Release 3 or below to Release 4) 1706
ACD MAX Release 4 Software Upgrade - Single Tower (ACD MAX Release 3 or below to Release 4) 1705
ACD MAX Release 4 User Documentation 1656
ACD MAX Sales Flyer 1652
ACD MAX Single to Dual Tower Upgrade Package 1609
ACD MAX Single Tower Hardware Package 1609
ACD MAX Single Tower Software 1609
ACD MAX Single Tower/Dual Upgrade 1609
ACD MAX Slide Presentation 1651
ACD MAX Software New Release Charge 1534
ACD MAX Software Service Transaction Fee 323, 377, 1364
ACD NTPs (Includes all ACD Packages) 1653
ACD Overview Folder 1648
ACD Package A & B 1648
ACD Package C 1648
ACD Package C Supervisor User Guide 352, 1484
ACD Package C Supervisors User Guide 1648
ACD Package D 1648
ACD Package D Management Reports 1654
ACD Portfolio Package 1648
ACD Product Sales Guide 1646
ACD Quick Reference Guide 1647
ACD Reference Guide 1656, 1662, 1663, 1664, 1666
ACD Reference Guide NTP 1658, 1659, 1660
ACD Reference Guide, Release 24 and Earlier 348, 1494
ACD Reference Guides 346, 1438, 1668
ACD Reports (ACD C1) 1697
ACD Reports Feature 154, 1237, 1515
ACD Sales Guide Updates 1652
ACD Supervisor Telephone User Guide 353, 1487
ACD Supervisor Telephone User Guide (15/PK) 1660
ACD Supervisors Telephone User Guide (15/PK) 1648
ACD Timed Overflow 154, 1239, 1515
ACD/Message Processing 101, 112, 124, 132, 140, 147, 1240, 1241, 1515, 1697
ACD-C Supervisor User Guide 1656
ACD-D Auxiliary Processor Software Service Transaction Fee 1693
ACD-D Basic Software Package (for Meridian SL-1 LE/N/NT) 1532
ACD-D Basic Software Package (for Meridian SL-1 MS/ST) 1532
ACD-D Basic Software Package (for Meridian SL-1 XL/XN/NT) 1532
ACD-D Networking User Guide (15/PK) 351, 1481
ACD-D Supervisor User Guide 351, 1481
ACD-D to Meridian MAX-IPE Release 7 Software Upgrade 1697
ACD-D to Meridian MAX-IPEE Release 8 Software Upgrade 1698
ACD-D to Meridian MAX-IPEE Release 9 Software Upgrade 318, 765, 1435
ACD-D to Meridian MAX-SNN Release 7 Software Upgrade 1697
ACD-D to Meridian MAX-SNNE Release 8 Software Upgrade 1697
ACD-D to Meridian MAX-SNNE Release 9 Software Upgrade 317, 759, 1435
ACD-D, ACD-MAX and MAX-IPE to Meridian MAX-SNN Hardware Upgrade Package, AC Power 1711
ACD-D, ACD-MAX and MAX-IPE to Meridian MAX-SNN Hardware Upgrade Package, DC Power 1711
ACD-MAX to Meridian MAX-IPE Release 7 Upgrade 1697
ACD-MAX to Meridian MAX-IPEE Release 8 Software Upgrade 1697
ACD-MAX to Meridian MAX-IPEE Release 9 Software Upgrade 318, 766, 1435
ACD-MAX to Meridian MAX-SNN Release 7 Software Upgrade 1697
ACD-MAX to Meridian MAX-SNNE Release 8 Software Upgrade 1697
ACD-MAX to Meridian MAX-SNNE Release 9 Software Upgrade 317, 760, 1435
ACD-MAX/NAC to Meridian MAX-IPEE/NAC 2 Data Conversion Kit 326, 496, 1382
Adapter 1499, 1671
Adapter Assembly-EMI 1542
Adapter Housing 186, 198, 1147, 1482
Adapter Plate for SDI Filter Connector 198, 1140, 1481
Additional CPU Assembly 1525
Additional One Day On-Site Messenger Training 271, 1511
Additional Shelf (Memory) Assembly 1525

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Additional Shelf (Network) Assembly 1525
Add-On Data Module (ADM) (Asynchronous Only) 1501, 1677
Add-On Data Module (ADM) (Synchronous/ Asynchronous) 1501, 1677
Add-On Module (10 Button) 1500, 1676
Add-On Module (20 Button) 1501, 1677
Address Bus Jumper Cable 268, 577, 1408
Adjustable Stand (M2250/M1250) 209, 534, 1398
ADM 24V Transformer (QMT7/QMT8) 1642
ADM Asynchronous Switch Setting Label 1642
ADM Black Faceplate (Bare) 1642
ADM Instruction Card 1642
ADM Power Cord NE-M2QC (7 Ft.) 1546
ADM Set Interconnect Cord NE-M4QD (21 In.) 187, 381, 1364
ADM Synch Switch Setting Label 1642
ADM Technical Specifications 1645
Administration Guide 353, 1485, 1655, 1656, 1658
Administrative Enhancements 1695
Administrators Guide - BNS/DTS/VINES (DA207-01) 1647
AdminPlus Administration Guide 1651
Adminplus Administration Guide Release 5 (Document Only) 1653
AdminPlus Administration Guide, Release 7 1655
AdminPlus Administration Guide, Release 8 1657
AdminPlus Administration Guide, Release 9 1595
AdminPlus Brochure 1658
AdminPlus Enable Option 257, 1254, 1516
AdminPlus Enable Software 1700
AdminPlus PC Software and NTP (Rel. 4) 1651
AdminPlus PC Software and NTP (Rel. 5/6) 1653
AdminPlus PC Software and NTP (Release 7) 1656
AdminPlus PC Software and NTP (Release 8) 1657
AdminPlus PC Software and NTP, Release 8 1658
AdminPlus PC Software and NTP, Release 9 1595
ADSI License RTU - 1 AP (or MRS/AP) 278, 946, 1457
Advanced ACD Features 154, 1237, 1515
Advanced ACD Features (ACD B) 1697
Advanced Application Software 1429, 1612
Advanced Applications Software 698, 1429, 1612, 1613
Advanced Applications Software (Add. 100 TNs) 1699
Advanced Applications Software Update 1699
Advanced ESN Features 153, 1215, 1513
Advanced Features 1697
Advanced Hospitality Features 153, 1211, 1513, 1695
Advanced Hospitality/PMSI 98, 108, 120, 131, 139, 147, 1222, 1514, 1696
Advanced ISDN Features 153, 1247, 1516, 1697
Advanced NetWare V.2.15 1552
Advanced Voice and Data Capabilities w/ISDN BRI 367, 1486
Agent Key Cap Package (50/PK) 206, 395, 1368
Agent Whisper 275, 1195, 1511
AILC - Asynchronous Interface Line Card 1503, 1679
AIM Installation Card (15/PK) 351, 1481
AIM Technical Specification 1644
AIM User Guide (15/PK) 1643
AIOD C25 Data Trunk 1501, 1677
Air Filter 1644
Air Filter (NT2R02AA) 1644
Air Probe Harness 184, 607, 1415
Alarm Adapter Cable 196, 1173, 1500, 1675
Alarm and Control Circuit Pack for MPP600 and MFA150 185, 569, 1406
Alarm Cable 268, 578, 1408, 1619
Alarm Cable Kit System 600/48 to MPP600 1659
Alarm Cable System 600/48 to QCA13 1659
Alarm Interface Cable (45 Ft.) 189, 608, 1415
Alarm Monitor Cable 1604
Alarm Monitor Cable (1 Ft.) 189, 609, 610, 1415, 1416, 1604
Alarm Monitor Cable (10 Ft.) 189, 609, 1415
Alarm Monitor Cable (12 Ft.) 189, 611, 1416
Alarm Monitor Cable (6 Ft.) 189, 609, 1415
Alarm Monitor Cable Harness 189, 609, 610, 1415
Alarm Status Board Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
Alarm Status Module 38, 220, 1373
Alarm Termination 1683
Alarm Terminator 198, 826, 1442
Alarm/Modem Cable (25 Ft.) 187, 1364
Alarm/Modem Cable Assembly-Initial Caps only 249, 713, 1432
Alignment Bracket (Expansion Cabinet) 198, 1483
Alternate User Interface 1 User Guide (15 per Package) 350, 520, 1389
Alternate User Interface Installation/Administration Guide 355, 1493
AML Link Cable 268, 1144, 1481
Amplified Handset (Spade/Spade) 1547
Amplified Handset Kit for SL-1 Set 1642
Amplified Handset Module (Includes Attendant Handset Assembly) 1501, 1677
Analog Display Service Interface (ADSI) Support 1586
Analog Line Card 1413, 1602
Analog Loop Start Cable 32, 223, 1445
Analog Message Waiting Line Card 65, 178, 600, 1413, 1602, 1603
Analog Terminal Adapter (ATA) (M2000 Series) 203, 531, 1397
Analog Terminal Adapter Quick Reference Card (Package of 15 P0872254) 351, 1403
Anderson Jacobs Acoustic Modem 1568

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Angle (Cable Rack Support) 1640
Answer Agent Key Cap Package (50/PK) 206, 395, 1368
Answer Emergency Key Cap Package (50/PK) 1556
AP Redundancy - 1 Voice Port RTU for 1 AP 43, 276, 936, 1456
AP Token Ring Lan Interface Kit 272, 283, 406, 1370
APM Custom Upgrade 331, 993, 1464
APM Upgrade, 1 Server/100 Seats to 10 Servers/1000 Seats 331, 992, 1464
APM Upgrade, 10 Servers/1000 Seats to 25 Servers/2500 Seats 331, 992, 1464
APM Upgrade, 100 Servers/5000 Seats to 250 Servers/10000 Seats 331, 992, 1464
APM Upgrade, 25 Servers/2500 Seats to 100 Servers/5000 Seats 331, 992, 1464
APM Upgrade, 250 Servers/10000 Seats to 500 Servers/25000 Seats 331, 993, 1464
APM, 1 Server/100 Seat Configuration 330, 988, 1463
APM, 10 Servers/1000 Seat Configuration 330, 988, 1463
APM, 100 Servers/5000 Seat Configuration 330, 988, 1463
APM, 25 Servers/2500 Seat Configuration 330, 988, 1463
APM, 250 Servers/10000 Seat Configuration 330, 989, 1463
APM, 500 Servers/25000 Seat Configuration 330, 989, 1464
APM, Basic Membership Support Package, Renewed Annually 331, 994, 1464
APM, Custom Configurations 330, 989, 1464
APM, Elite Membership Support Package, Renewed Annually 331, 995, 1464
APM, Full Documentation (Hardcopy) 331, 994, 1464
APM, Installation (Mandatory Service, Performed by a Certified APM Installation Engineer) 331, 993, 1464
APM, OEM Configuration 331, 990, 1464
APM, Product Training 331, 994, 1464
APM, Professional Services/System Integration/Consulting 331, 993, 1464
APM, Quick Reference Guides (Hardcopy) 331, 994, 1464
APM, Service Provider Hosted Model 331, 995, 1464
APM, Unlimited Configuration 331, 989, 1464
Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC) 1548
Apple Macintosh Interface Cable DB-9 (Male) to RJ11 (Male) (Macintosh to Digital Set) 187, 383, 1365
Apple Macintosh Interface Cable DIN 8 (Male) to RJ11 (Male) (Macintosh Direct Connect to DAC/AILC) 187, 383, 1365
Apple Macintosh Interface Cable DIN8/DB25 (Macintosh to Digital Set) 187, 383, 1365
Application Equipment Module AC 326, 590, 1411
Application Equipment Module DC 326, 590, 1411
Application License Kit 308, 310, 325, 522, 1390
Application Module Chassis Assembly 326, 596, 1412
Application Module Documentation Package 1576
Application Module NTP 344, 1368
Application Module Power Supply AC 326, 596, 1412
Application Module Power Supply DC 326, 596, 1412
Application Module to SDI Paddle Board Cable (10 Ft.) 328, 591, 1411
Application Module to SDI Paddle Board Cable (2 Ft.) 1600
Application Module to SDI Paddle Board Cable (20 Ft.) 328, 591, 1411
Application Module to SDI Paddle Board Cable (35 Ft.) 328, 591, 1411
Application Module to SDI Paddle Board Cable (45 Ft.) 328, 592, 1411
Application Module to SDI Paddle Board Cable (6 Ft.) 328, 591, 1411
Application Processor - Development 1585
Application Processor - Runtime 1585
Application Processor 3MB 1587
Application Server Master Driver CD Bootable 32, 224, 854, 1446
Arabic Prompt-Bilingual 1702
Arabic Prompt-Unilingual 1702
Architect & Evolution Update Release II 1650
Architecture and Evolution Script/Slide X11 R9 ST 1648
ARCNET LAN Software 1550
Arithmetic Logic Unit (CDR) 1503, 1679
AS0070 1561
AS0071 317, 342, 437, 1377
AS0072 1561
AS0073 321, 327, 437, 1377
AS0074 317, 342, 438, 1377
AS0075 321, 327, 438, 1377
AS1001A 1561
AS1001D 1561
AS1002A 1561
AS1002D 1561
AS1004A 1561
AS1005A 1561
AS1005D 1561

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

AS1006A 158, 439, 1377
AS1006D 158, 439, 1377
AS1007A 158, 440, 1377
AS1007D 158, 440, 1377
AS1008 1561
AS1009 1561
AS1010 1561
AS1011 1561
AS1012 1561
AS1013 158, 440, 1377
AS101403 1561
AS101435 1561
AS101493 1561
AS1015D 1561
AS1016D 1562
AS1017D 158, 441, 1377
AS1018D 1562
AS1019 159, 441, 1377
AS1020 159, 441, 1377
AS1021 159, 441, 1377
AS1022 159, 442, 1377
AS1023 1562
AS1025 1562
AS1027 1562
AS1028 1562
AS1029 1562
AS103003 201, 442, 1377
AS103035 201, 442, 1377
AS103093 201, 443, 1377
AS1031 1562
AS1032 1562
AS1035 1562
AS1036 1562
AS1037 1562
AS1038 1562
AS1039A 159, 443, 1377
AS1039D 159, 444, 1377
AS1040 159, 444, 1377
AS1041 159, 445, 1378
AS1042 159, 445, 1378
AS1043 159, 445, 1378
AS1045 1562
AS1046 1562
AS1047 1562
AS1048 1562
AS1050 327, 446, 1378
AS1051 159, 446, 1378
AS1052 159, 446, 1378
AS1053A 25, 1562
AS1053D 25, 1562
AS1054A 159, 447, 1378
AS1054D 159, 447, 1378
AS1055A 1562
AS1055D 1562
AS1057 1562
AS1058 1562
AS1059 1562
AS1060 1562
AS1061 159, 447, 1378
AS1062 159, 448, 1378
AS1063 159, 448, 1378
AS1064A 1562
AS1064D 1562
AS1066 204, 448, 1378
AS1071 1562
AS1072 1562
AS1073 65, 159, 448, 1378
AS1074 65, 159, 449, 1378
AS1078 159, 449, 1378
AS1079 188, 449, 1378
AS1080 1562
AS1081A 159, 450, 1378
AS1081D 159, 450, 1378
AS1082 350, 450, 1378
AS1083 350, 451, 1378
AS1084 350, 451, 1378
AS1087D 159, 451, 1378
AS1088D 159, 452, 1378
AS1089 159, 452, 1378
AS1090A 159, 453, 1378
AS1090D 159, 453, 1378
AS1091A 159, 454, 1378
AS1091D 159, 454, 1378
AS1092A 159, 455, 1378
AS1092D 159, 456, 1378
AS1093 159, 456, 1378
AS1094A 159, 457, 1378
AS1094D 159, 457, 1378
AS1095A 159, 458, 1379
AS1095D 159, 458, 1379
AS1100D 1562
AS1101D 1563
AS1102D 1563
AS1103D 1563
AS1130 159, 342, 459, 1379
AS1131 1563
AS1132 159, 342, 459, 1379
AS1140 160, 460, 1379
AS1141 160, 460, 1379
AS1142 160, 461, 1379
AS1143 160, 462, 1379
AS1144 160, 462, 1379
AS1145 160, 463, 1379
AS1146 160, 464, 1379
AS1147 160, 464, 1379
AS1171 70, 160, 465, 1379
AS1172 70, 160, 466, 1379
AS1173 70, 160, 466, 1379

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

AS1174 70, 160, 467, 1379
AS1175 70, 188, 468, 1379
AS1180 1563
AS1182 207, 468, 1379
AS1200D 160, 468, 1379
AS1201D 160, 469, 1379
AS1202D 1563
AS1203D 1563
AS1204D 160, 469, 1379
AS1205 1563
AS1206 1563
AS1207 1563
AS1208A 160, 342, 469, 1379
AS1208D 160, 342, 470, 1379
AS1209 1563
AS1209D 160, 470, 1379
AS1210 1563
AS1210D 160, 470, 1379
AS1211 1563
AS1240 160, 471, 1379
AS1241 160, 471, 1379
AS1242 160, 471, 1379
AS1243 160, 472, 1379
AS1250 160, 472, 1379
AS1300 1563
AS1301 1563
AS1302 1563
AS1303 1563
AS1304 1563
AS1305 1563
AS1306 1563
AS1307 1563
AS1308 1563
AS1309 1563
AS1310 1563
AS1311 1563
AS1460 176, 472, 1379
AS1461 176, 473, 1379
AS1500A 332, 473, 1379
AS1501 332, 474, 1380
AS2001A 1563
AS2001D 1563
AS2002A 1563
AS2002D 1563
AS7000A 1563
AS7000D 1564
AS7001A 1564
AS7001D 1564
AS7002A 1564
AS7002D 1564
AS7003A 1564
AS7003D 1564
AS7004A 1564
AS7004D 1564
AS7005A 1564
AS7005D 1564
AS7006A 1564
AS7006D 1564
AS7007 1564
AS7008A 1564
AS7008D 1564
AS7009A 1564
AS7009D 1564
AS7010 248, 266, 474, 1380
AS7011 239, 474, 1380
AS7012 248, 266, 475, 1380
AS7013 1564
AS7015 266, 475, 1380
AS7016 1564
AS7018A 1564
AS7018D 1564
AS7019A 1564
AS7019D 1564
AS7020A 1564
AS7020D 1565
AS7021A 260, 476, 1380
AS7021D 260, 476, 1380
AS7022A 1565
AS7022D 1565
AS7023A 260, 477, 1380
AS7023D 260, 477, 1380
AS7024 1565
AS7025 260, 478, 1380
AS7029 258, 478, 1380
AS7030A 1565
AS7030D 1565
AS7031A 258, 479, 1380
AS7031D 258, 479, 1380
AS7032A 1565
AS7032D 1565
AS7033A 258, 480, 1380
AS7033D 258, 480, 1380
AS7036A 1565
AS7036D 1565
AS7037A 258, 480, 1380
AS7037D 258, 481, 1380
AS7038 1565
AS7039 1565
AS7040 1565
AS7041 1565
AS7042 1565
AS7043A 261, 481, 1380
AS7043D 261, 482, 1380
AS7044A 261, 482, 1380
AS7044D 261, 483, 1380
AS7045A 261, 484, 1380
AS7045D 261, 484, 1380
AS7046A 261, 485, 1381

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

AS7046D 261, 485, 1381
AS7047D 261, 486, 1381
AS7048D 261, 486, 1381
AS7049D 261, 487, 1381
AS7050D 261, 487, 1381
AS7051 1565
AS7052 1565
AS7053 1565
AS7054 1565
AS7055 1565
AS7060D 1565
AS7061D 1565
AS7062D 1565
AS7063D 1565
AS7064D 1565
AS7065D 1565
AS7066D 1565
AS7067D 1565
AS7070D 266, 342, 488, 1381
AS7080 266, 342, 488, 1381
AS7081 266, 342, 488, 1381
AS7082 266, 489, 1381
AS7083 248, 342, 489, 1381
AS7090 1566
AS7091 1566
AS7092 1566
AS7093 1566
AS7100 247, 489, 1381
AS7101 239, 490, 1381
AS7102 1566
AS7103 1566
AS7104 1566
AS7105 1566
AS7106 1566
AS7107 1566
AS7108 247, 258, 490, 1381
AS7109 247, 258, 490, 1381
AS7110 247, 258, 491, 1381
AS7111 247, 258, 491, 1381
AS7112 259, 491, 1381
AS7113 259, 492, 1381
AS7114 259, 492, 1381
AS7115 259, 492, 1381
AS7116 258, 493, 1381
AS7117 259, 493, 1381
AS7120 237, 493, 1381
AS7121 237, 494, 1381
AS7122 237, 494, 1381
AS7123 237, 494, 1381
AS7124 1566
AS7125 1566
AS7190 1566
AS7200 160, 495, 1381
AS7201 160, 495, 1381
AS7202 160, 495, 1381
AS7309 1566
AS7310 1566
AS7311 1566
AS7312 1566
AS7505 317, 342, 496, 1382
AS7506 326, 496, 1382
AS7512 316, 497, 1382
AS7523A 1566
AS7523D 1566
AS7534 316, 497, 1382
AS8600 272, 498, 1382
AS8601 1566
ASCII Pak - Female 1542
ASCII Pak-Male 1542
Ash Sets 1618
Ash Sets for NTKS1030 1618
Assembly 3-Fan 62XX Spare OIVR 4 AP, MRS/AP, MRS Tower 283, 1461
Assembly AC Entry Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
Assembly DC Entry Spare 282, 1461
Assembly, Meridian Mail Alternate User Interface 1 235, 245, 256, 631, 1066, 1419, 1471
Assistant 1.0 Administration and User Training 27, 1694
Assistant 1.0 Computer Based Training 1625
Assistant 1.0 MAS Installation and Administration and User Training 1694
Assistant 100 User License 270, 964, 1459
Assistant 1000 User License 1625
Assistant 200 User License 1625
Assistant 25 User License 1625
Assistant 50 User License 1625
Assistant 500 User License 1625
Assistant Installation Phone Support 1694
Assistant Post Warranty Phone 7x24 27, 1694
Assistant Post Warranty Phone 8-5 27, 1694
Assistant Server Application Software 1625
AST (100 Increment) 63, 74, 890, 1450
Asynchronous Data Option (M2009, M2112, M2018, M2317) 204, 502, 1386, 1573
Asynchronous Data Option Installation Procedure (15/PK) 351, 1481
Asynchronous Interface Line Unit Brochure 1646
Asynchronous Interface Module (AIM) 1501, 1677
Asynchronous Terminal Emulation Guide (DA183-01) 1553
Asynchronous Terminal Emulation with File Transfer (HA101) 1550
Asynchronous/Synchronous Interface Module (ASIM) 1501, 1676
AT to PS/2 Keyboard Cable Adapter Spare 282, 967, 1461

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

AT&T Connections Hardware Package 1367, 1556
ATA/MCA Footstand, Ash (M2006, M2008, M2008HF) 203, 532, 1398
ATA/MCA Footstand, Ash (M2616, M2216ACD) 203, 533, 1398
ATA/MCA Footstand, Black (M2006, M2008, M2008HF) 203, 532, 1397
ATA/MCA Footstand, Black (M2616, M2216ACD) 203, 533, 1398
ATA/MCA Footstand, Gray (M2006, M2008, M2008HF) 203, 532, 1398
ATA/MCA Footstand, Gray (M2616, M2216ACD) 203, 533, 1398
ATA/MCA Jumper Kit 209, 532, 1397
ATA/MCA Transformer 209, 424, 1373
ATM Application Software Package 1621
Attendant Administration Overlay 210, 1153, 1486
Attendant Administration User Guide (15/PK) 351, 1481
Attendant Alternative Answer 152, 1209, 1513
Attendant Console 1500, 1676
Attendant Console M1250 1391, 1577
Attendant Console User Guide (1/PK) 353, 1489, 1663
Attendant Handset 1570
Attendant Overflow Position 97, 107, 119, 130, 138, 146, 152, 1208, 1213, 1513
Attendant Recall Key Cap Package (50/PK) 1556
Audio Cable 193, 692, 1426
Audio Interface Unit 1559
Audio Interface Unit (AIU) 1637
Audio Interface Unit Hardware 1398, 1583
Audiofax Server Software Only (Kit) 271, 978, 1462
Authorization Code 1695
Auto Answer Key Cap Package (50/PK) 1557
Auto Dial Key Cap Package (50/PK) 206, 394, 1368
Automatic Call Distribution (ACD) Package D Software for PDP 11/44 1532
Automatic Call Distribution Reference Guide NTP 1657
Automatic Call Distributor (ACD) Package D Software for PDP 11/23 Plus 1532
Automatic Handsfree Answerback Interface Kit 1500, 1676
Automatic Handsfree Interface Kit 1500, 1676
Automatic Number Identification (ANI) 152, 1206, 1512
Automatic Trunk Maintenance 97, 107, 118, 130, 138, 145, 1205, 1512
Automatic Wake-Up Calls Quick Reference Card (25/PK) 1655
Auxiliary Alarm Cable (48 Ft.) 189, 1413
Auxiliary Cable 188, 510, 1388
Auxiliary Processor Link 154, 1249, 1516

B

B0198494 1566
B0202061 1382, 1566
B0202082 1566
B0206661 1566
B0206675 1566
B0206676 1566
B0206677 1566
B0206678 1566
B0206682 1566
B0210365 1382, 1567
B0210372 1567
B0225152 1567
B0225153 1567
B0225161 1567
Back Cover 1639
Back Panel 1645
Background Terminal User Guide 1648
Background Terminal User Guide (15/PK) 63, 70, 352, 1484
Background Terminal User Guide X37 (15/PK) 1646
Backplane Cable Extraction Tool 199, 1151, 1485
Backplane Stiffener Kit 269, 575, 1407
Backplane to I/O Cable 268, 1408, 1597
Backplane to Network Cable 1591
Backup Tape Drive 41, 305, 858, 1447
Backwards Compatible Daughterboard 67, 179, 710, 1432
Banyan Application Directory (DA150) 1648
Banyan BNS Option Installation Document (DA192) 1553
Banyan EXP-DTS Opt. Installation Document (DA191) 1553
Banyan Field Service Manual for BNS (DA140) 1648
Banyan Mail (PA100) 1550
Banyan Network Card Configuration 1648
BANYAN Option Installation Documentation for NT LANSTAR PC Network 1648
Base (10/20 Button Module, BLF) 1639
Base (SL-1 Set) 1639
Base AP (700tp), 0 Port - Global 276, 935, 1455
Base AP, Runtime Software, 0 Port-Global 1625
Base AP/Rack, AC, Global 276, 936, 1456
Base AP/Rack, DC, Global 276, 936, 1456
Base Chassis for MRS/AP or AP 1460, 1626
Base Chassis for MRS/Rack - AC Power Spare 282, 968, 1461
Base Chassis for MRS/Rack - DC Power Spare 282, 968, 1461
Base Chassis for OIVR 4.0 Tower AP and MRS/Tower Spare 282, 967, 1461
Base Documentation Package, North America 276, 932, 1455

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Base Extension 1647
Base for QCW Console 1640
Base MRS/AP (700tp), 0 Port - Global 277, 939, 1456
Base MRS/AP, Runtime Software, 0 Port - Global 1625
Base MRS/Rack, AC, 0 Port - Global 277, 937, 1456
Base MRS/Rack, DC, 0 Port - Global 277, 938, 1456
Base MRS/Tower, 0 Port - Global 277, 936, 1456
Base Single Board Computer for AP or MRS/AP Spare 1461, 1626
Base Single Board Computer for MRS/Tower or MRS/Rack Spare 282, 967, 1461
Base Software Features Package - Options 153 and 209 297, 1470
Base System (Tower) 1559
Base System Intel 750tMM 1559
Basic ACD Features 154, 1236, 1515
Basic ACD Features (ACD A) 1697
Basic Administration Guide - French 229, 1498
Basic Cabinet 1582
Basic ESN Features 153, 1215, 1513
Basic H/M Program
  Generic 407 (VLE) 1533
Basic H/M Program X07
  Generic 307 (LE) 1533
  Generic 507 (A) 1532
Basic Hospitality 98, 108, 120, 131, 139, 146, 1221, 1222, 1514
Basic Hotel/Motel Program SL-1M (707) (M) 1531
Basic ISDN Features 153, 1246, 1516, 1697
Basic Port License 1704
Basic Program
  404 1539
  Generic 1011 1689
  Generic 104/504 1536
  Generic 105/305 1540
  Generic 204 1536
  Generic 205/405 1540
  Generic 304 1539
  Generic 309 1540
  Generic 311 1535
  Generic 314 (Autovon) 1540
  Generic 337 (LE) 1529
  Generic 409 1540
  Generic 411 1535
  Generic 414 1540
  Generic 437 (VLE) 1529
  Generic 505 1540
  Generic 609 1540
  Generic 611 1535
  Generic 637 (XL) 1529
  Generic 711 1534, 1535
  Generic 737 (M) 1529, 1534
  Generic 811/1111/1311 1541
  Generic 911/1211 1541
Basic Rate Interface 100, 111, 123, 132, 139, 147, 1232, 1233, 1515, 1697
Basic Rate Signaling Concentrator 197, 1408
Basic SL-1MS 1526
Basic Software Package 1527
Basic Telecom Management Guide 349, 1498
Battery 196, 391, 1367
Battery Backup Distribution Box 1499, 1671
Battery Backup Supply Cable 1674
Battery Backup Supply Extension Cable 1674
Battery Distribution Box 187, 1499, 1671
Battery Junction Box 66, 197, 696, 1428, 1612
Battery Monitor 1501, 1502, 1678
Bezel, Collar (Lamp Strip) 1641
Bisynchronous Serial Communications Adapter (NM115) 1366, 1549
Bit Transparent Data 1621
Black Box ABC Switch 250, 269, 535, 1398
Black Box ABCDE Switch 196, 1367
Black Box HP Cable 1554
Black Sets 1618
Black Sets for NTKS1030 1618
Black Sets for Option 11C Compact Hospitality Communications Package - NTKS1010 1618
Blank Brand Line Insert, Ash, (M2000 Series) 208, 1139, 1480
Blank Brand Line Insert, Gray (Package of 250 P0784493) (M2000 Series) 208, 1139, 1480
Blank Brandline Insert, Ash 1661
Blank Brandline Insert, Black 1661
Blank Brandline Insert, Black (Package of 250 P0784403) (M2000 Series) 208, 1139, 1480
Blank Brandline Insert, Gray 1661
Blank DAT Tape - 4/8GB Spare 282, 970, 1461
Blank Diskette Label 1656
Blank Faceplate (.875) (NT2R07AA & NT2R05AA) 1582
Blank Faceplate (0.875 In.) 197, 603, 1414
Blank Faceplate (1 In.) 197, 603, 1414
Blank Faceplate (1.75) (NT2R07AA & NT2R05AA) 1582
Blank Faceplate (2 In.) 197, 604, 1414
Blank Faceplate (2.625) (NT2R07AA & NT2R05AA) 1582
Blank Faceplate (MCCS) 1611
Blank Faceplate (MSU) QMM38 1645
Blank Insert (Light Gray) 199, 1157, 1491
Blank Pack 1619
Blank Packlet for EOI 199, 1148, 1483
Blank Panel 1595
Blank QIC Tape - 2.5GB Spare 282, 970, 1461
Blank Tape (300 Ft.) (Mini-CDR) 1569
Blank Tape (450 Ft.) (Mini-CDR) 1569
BLF Cord Kit 1641

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

BLF Designation Labels 1641
BLF/CGM User Guide (5/PK) 352, 1484
BLF/Console Graphics User Guide 1653
Blower Unit 1398, 1583
Blue Cable Routing Panel Assembly (Cantilever Mount) 1642
Blue Cable Routing Panel Assembly (Center Mount) 1640
Blue Cooling and Cable Routing Panel Assembly 1509, 1686
BNS 20 Line Serial (BNS290) Communications Option (Factory Installed) 1549
BNS 20 Line Serial (BNS291) Communications Option (Field Installed) 1549
BNS 4 Drive Capacity (BNX544) 2 157 MB Disk 1549
BNS 4MB Memory (SA242) Expansion Board 1549
BNS 8 Drive Capacity (BNX548) 4 157 MB Disk 1549
BNS Backplane Kit (16 Lines) (CS001) 1382, 1568
BNS Backplane Kit (20 Lines) 1382, 1568
BNS Battery Pack Kit (CS014) 1568
BNS Card Guide Kit (CS003) 1568
BNS CPU Board Kit (CS015) 1382, 1568
BNS DC Distribution Board (CS080) 1382, 1568
BNS Disk Cable Kit (CS016) 1568
BNS Fan Kit (115 Volt) (CS005) 1568
BNS Fan Kit (220 Volt) (CS006) 1568
BNS Front Console Assembly (CS081) 1382, 1568
BNS Fuse Holder Kit (CS039) 1568
BNS Fuse Kit (CS010) 1568
BNS Keyswitch Kit (CS008) 1568
BNS Latch Release Kit (CS004) 1568
BNS Line Filter Kit (CS007) 1568
BNS Memory Kit (4MB) (CS036) 1382, 1568
BNS Power Distribution Cable Kit (CS011) 1567
BNS Power Supply Kit (CS009) 1382, 1567
BNS SCSI Cable Kit (CS017) 1567
BNS Side and Top Panel Kit (CS038) 1567
BNS Tape Drive Kit (Full Height) (CS012) 1382, 1568
BNS Upgrade to BNS/386-25 CPU/8MB Memory Expansion (BSU24C) 1554
BNS Upper Battery Assembly (CS082) 1568
BNS/CNS Console Cable (SA280) 1550
BNS/CNS PC Console Cable (SA281) 1550
BNS/CNS Server Console (SA260) 1549
BNS/CNS Upgrade 1551
BNS/DTS 2MB Memory (SA241) Expansion Board 1366, 1549
BNS/DTS Disk Controller Kit (CS018) 1382, 1567
BNS/DTS Tape Controller Kit (CS013) 1382, 1567
Bracket 1640
Bracket Assembly (CDR) 1641
Bracket for QPC417 1643
Bracket Support (11 In.) 1641, 1644
Bracket Support (2 In.) 1640
Brandline Insert, Charcoal (Package of 250 P0904455, M3900 Series) 40, 208, 809, 1439
Brandline Insert, Platinum (Package of 250 P0904456, M3900 Series) 40, 208, 809, 1439
Break Interconnect Cable (6 Ft.) 41, 223, 1445
Breakout Panel Assembly 41, 221, 851, 1445
BRI Administration and Maintenance Guide 353, 1485
BRI Guide, Release 25 63, 349, 1498
BRI Module (U Interface) 333, 717, 1433
Bridge 1620
British English Female Prompt - Bilingual 1702
British English Female Prompt - Unilingual 1702
British English Male Prompt - Biligual 1702
British English Male Prompt - Unilingual 1702
Brooktrout 4 Port Fax Card 270, 559, 1405
Buffer Interface Converter (Room Status & Maid Status) 1364, 1547
Built-In BIX MDF Assembly (for 863SL1-1 SL-1ST) 1543
Bulkhead Assembly (EMI) 1643
Bus Cable 1595
Bus Terminating Unit (BTU) 183, 1178, 1504, 1680
Bus Termination Unit (BTU) 1501, 1502, 1677, 1678
Bus Terminator 249, 712, 1432
Business Affiliates Brochure 359, 1485
Busy Lamp Field Console Graphics User Guide 1651
Busy Lamp Field/Console Graphics Module 204, 535, 1398, 1583, 1584
Button 1639
Buzz Key Cap Package (50/PK) 1557

C

C0022571 1567
C0035996 1567
C0040777 1567
C0041748 1567
C0045095 1567
C0045763 1567
C0046926 1567
C0046928 1567
C0046930 1567
C0046977 1382, 1567
C0046980 1382, 1567
C0048650 1567
C0052473 1567
C0056273 1567
C25 Voice Processor Card 237, 695, 1427, 1566, 1612
C2502242 1567
C2502243 1567

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

C2502244 1567
C2502246 1382, 1567
C2502247 1567
C2502248 1382, 1567
C2502249 1382, 1567
C2502250 1567
C2502251 1567
C2502252 1382, 1567
C2502253 1382, 1567
C2502254 1567
C2502255 1382, 1567
C2502256 1567
C2502257 1567
C2502258 1382, 1568
C2502259 1568
C2502260 1568
C2502261 1568
C2502262 1568
C2502263 1382, 1568
C2502264 1568
C2502265 1382, 1568
C2502266 1382, 1568
C2502267 1568
C2502268 1568
C2502269 1568
C2502270 1568
C2502271 1382, 1568
C2502272 1568
C2502273 1382, 1568
C2502274 1382, 1568
C2502490 1568
C2502491 1382, 1568
C2502492 1382, 1568
C2502493 1382, 1568
C2502494 1568
C2502495 1568
C2502496 1568
C2502497 1568
C2502498 1568
C2502499 1382, 1568
C2502500 1382, 1568
C2502501 1382, 1568
C2502503 1382, 1568
C2502504 1568
C2502505 1568
C2502506 1568
C2502507 1568
C2502508 1569
C2502509 1569
Cabinet Assembly (w/o Rectifiers) 1638
Cabinet Door Key 1567
Cabinet Expansion Kit (NT0R02AA) (A0311688) 1582
Cabinet Grounding Package #1 198, 1142, 1481
Cabinet Grounding Package #2 198, 1142, 1481
Cabinet Grounding Package #3 198, 1142, 1481
Cabinet Harness 1582
Cabinet Level Label - 530 1644
Cabinet Panel Upgrade Assembly (CDR Cabinet) 1528
Cabinet Panel Upgrade Assembly (Double Bay Cabinet) 1528
Cabinet Panel Upgrade Assembly (Single Bay Cabinet) 1528
Cabinet Upgrade Kit 70, 178, 709, 1431
Cable 196, 1174, 1500, 1570, 1675
PC serial/modem (DB25/DB25) 1405
Cable - 2.0MB DDP Coax to LTU 50 Ft. 193, 707, 1431
Cable - 2.0MB DDP I/O to MDF 50 Ft. 190, 615, 1417
Cable - 2.0MB DDP to I/O 8 Ft. 193, 706, 1431
Cable - 2.0MB DDP to MDF 50 Ft. 193, 707, 1431
Cable (18 Ft.) 1675
Cable (20-Pin, A-Slot) 1582
Cable (20-Pin, Z-Slot) 1582
Cable (20-Pos, 20-Pin) 1582
Cable (35 Ft.) 1675
Cable (3-Pos, 20-Pin) 1583
Cable (3-Pos, 50-Pin) 1582
Cable (50 Ft.) 1675
Cable (6 Ft.) 1675
Cable 20 Ft. Coax - 2.0MB DTI/PRI to MDF 65, 193, 1430
Cable Adapter 195, 1171, 1499, 1671, 1673
Cable Assembly 1675
Cable Assembly (1 Ft.) 1569
Cable Assembly (2 Ft.) 1569
Cable Assembly (QCA28 Cabinet) 1640
Cable Assembly, Breakout Box InterconnectCable, 15 Ft. 41, 221, 1445
Cable Connector (6 Ft.) 1675
Cable TC to Printer (RJ-11 to DB25) 1650
Cable TC to SDI Link (HSL and Configuration Control Link) (RJ-11 to DB25) 1650
Cable TC to Supervisor PC (Return to Console Link) (RJ-11 to DB9) 1652
Cable TC to Terminal (RJ-11 to DB25) 1651
Cable TC to XSDI (HSL and Configuration Control) (RJ11 to DB9) 1555
Cable TC/FM to Modem (Remote Supervisor) (RJ45 to DB25) 329, 1420, 1555
Cable TC/FM to NAC Network Link and Remote Supervisor Log-In Link (RJ45 to DB25) 329, 633, 1420, 1557
Cable TC/FM to Printer (RJ45 to DB25) 329, 1420, 1554
Cable TC/FM to SDI (HSL and Configuration Control) (RJ45 to DB25) 329, 1420
Cable TC/FM to Supervisor PC (Return to Console

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Link) (RJ45 to DB9) 329, 1420, 1554
Cable TC/FM to Terminal (RJ45 to DB25) 329, 1420, 1554
Cable TC/FM to XSDI (HSL and Configuration Control) (RJ45 to DB9) 1555
Cable, Conn. (1 Ft.) 1546
Cable, Conn. (10 Ft.) M/M 1672
Cable, Conn. (2 Ft.) 1546
Cable, Conn. (4 Ft.) 1546
Cable, Conn. (6 Ft.) (M/M) 1546
Cable, Connector 1673
Cable, Connector (1.5 Ft.) 1546
Cable, Connector (10 Ft.) 1546, 1674
Cable, Connector (10 Ft.) (Female/Female) (Clock to Clock) 195, 1171, 1499, 1673
Cable, Connector (10 Ft.) F/F 1672
Cable, Connector (10 Ft.) M/M 1672
Cable, Connector (15 Ft.) 1546
Cable, Connector (15 Ft.) M/M 1672
Cable, Connector (16 Ft.) (M/F), TTY RS-232 (5.25m) 187, 380, 1364
Cable, Connector (16 Ft.) (M/M), TTY RS-232 (5.25m) 187, 380, 1364
Cable, Connector (16 Ft.) (SDI) 1675
Cable, Connector (2 Ft.) 1546, 1675
Cable, Connector (2 Ft.) M/M 1672
Cable, Connector (20 Ft.) 1546
Cable, Connector (20 Ft.) M/M 1672
Cable, Connector (25 Ft.) 1546
Cable, Connector (25 Ft.) (Female/Female) 1671
Cable, Connector (25 Ft.) M/M 1672
Cable, Connector (27 In.) M/M 1673
Cable, Connector (3 Ft.) 1676
Cable, Connector (3 Ft.) M/M 1672
Cable, Connector (30 Ft.) 1546
Cable, Connector (30 In.) M/M 1673
Cable, Connector (33 In.) (Male/Male) 1673
Cable, Connector (35 Ft.) 1546
Cable, Connector (35 Ft.) M/M 1672
Cable, Connector (4 Ft.) 1546
Cable, Connector (4 Ft.) M/M 1672
Cable, Connector (4.5 Ft.) (M/M) (CE to CE Inter-Connect) 1673
Cable, Connector (40 Ft.) 1546
Cable, Connector (40 In.) M/M 1673
Cable, Connector (43 In.) M/M 1673
Cable, Connector (45 Ft.) 1546
Cable, Connector (45 Ft.) M/M 1672
Cable, Connector (48 In.) (Male/Male) 195, 1172, 1499, 1673
Cable, Connector (5 Ft.) (QCB6A) (Tape Interface) 1546
Cable, Connector (50 Ft.) (SDI) 1675
Cable, Connector (50 Ft.) M/M 1672
Cable, Connector (55 In.) (Male/Male) 1673
Cable, Connector (58 In.) (Male/Male) 1673
Cable, Connector (6 Ft.) 1546
Cable, Connector (6 Ft.) M/M 1672
Cable, Connector (61 In.) (Male/Male) 195, 1172, 1499, 1673
Cable, Connector (68 In.) (Male/Male) 1673
Cable, Connector (7 Ft.) (Male/Female) (DTI to I/O Panel) 195, 1171, 1499, 1673
Cable, Connector (7 Ft.) (Male/Female) (PRI/DTI to Echo Canceler) 195, 1171, 1499, 1673
Cable, Connector (7 Ft.) M/M (DTI to Clock) 1673
Cable, Connector (71 In.) (Male/Male) 1673
Cable, Connector (74 In.) (Male/Male) 195, 1172, 1499, 1673
Cable, Connector (8 Ft.) (QCB6A) (Tape Interface) 1546
Cable, Connector (CDR) 1676
Cable, Connector (Maintenance) 1676
Cable, Connector (QBL21) 1672
Cable, Connector (QSP43) 195, 1499, 1672
Cable, Connector (QSP44) 1673
Cable, CPU Faceplate Ribbon 1674
Cable, Intra-Cabinet (25 Conductor 95 In.) (EMI) 196, 1175, 1500, 1675
Cable, Intra-Cabinet (25 pin 65 In.) (EMI) 1672
Cable, Intra-Cabinet (25 pin 75 In.) (EMI) 1672
Cable, Intra-Cabinet (50 pin 20 In.) 1672
Cable, Intra-Cabinet (50 pin 40 In.) 1672
Cable, Intra-Cabinet (50 pin 60 In.) (EMI) 1672
Cable, Intra-Cabinet (50 pin 80 In.) (EMI) 1672
Cable, Intra-Cabinet (SDI) (30 In.) (25 cond) 1673
Call by Call Service 154, 1248, 1516
Call Center Business Planning Guide and Tools 359, 1483
Call Center Integration Package (CCIP)-M1 Connectivity Option 4 Port Increment 1705
Call Center Integration Package (CCIP)-M1 Connectivity Option-4 Port Base 1704
Call Center Journal
- Air Miles Program Takes Off 361, 1488
- Available in all Sizes 360, 1487
- Better By The Minute 361, 1488
- Beyond Expectation 361, 1488
- Financial Powerhouse 361, 1487
- Healthcare - Just What the Dr. Ordered 361, 1487
- Making the Perfect Match 360, 1487
- MAXcaster Forecasting 361, 1488
- Move Up To MAX 361, 1488
- Priority Special Report 362, 1488
- The CTI Call Center 362, 1488
- Working With a Net 361, 1487

Call Center Networking 101, 112, 124, 132, 140, 147, 1243, 1515

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Call Center Software 100, New System (1 Agent) 297, 634, 1420
Call Center Software 100, New System (10 Agent) 297, 634, 1420
Call Center Software 100, New System (100 Agent) 297, 635, 1420
Call Center Software 100, New System (1000 Agent) 1609
Call Center Software 100, New System (50 Agent) 297, 635, 1420
Call Center Software 100, New System (500 Agent) 297, 636, 1420
Call Center Software 100, Upgrade from CCR only (1 Agent) 301, 662, 1423
Call Center Software 100, Upgrade from CCR only (10 Agent) 301, 663, 1423
Call Center Software 100, Upgrade from CCR only (100 Agent) 301, 664, 1423
Call Center Software 100, Upgrade from CCR only (1000 Agent) 1609
Call Center Software 100, Upgrade from CCR only (50 Agent) 301, 663, 1423
Call Center Software 100, Upgrade from CCR only (500 Agent) 301, 664, 1423
Call Center Software 100, Upgrade From MAX 5 (1 Agent) 299, 659, 1422
Call Center Software 100, Upgrade from MAX 5 (10 Agent) 299, 659, 1422
Call Center Software 100, Upgrade from MAX 5 (100 Agent) 299, 660, 1422
Call Center Software 100, Upgrade from MAX 5 (1000 Agent) 1609
Call Center Software 100, Upgrade from MAX 5 (50 Agent) 299, 660, 1422
Call Center Software 100, Upgrade from MAX 5 (500 Agent) 299, 661, 1422
Call Center Software 100, Upgrade from MAX 6 (1 Agent) 299, 652, 1422
Call Center Software 100, Upgrade from MAX 6 (10 Agent) 299, 653, 1422
Call Center Software 100, Upgrade from MAX 6 (100 Agent) 299, 654, 1422
Call Center Software 100, Upgrade from MAX 6 (1000 Agent) 1609
Call Center Software 100, Upgrade from MAX 6 (50 Agent) 299, 653, 1422
Call Center Software 100, Upgrade from MAX 6 (500 Agent) 299, 654, 1422
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1 Agent) 298, 643, 1421
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (10 Agent) 298, 643, 1421
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (100 Agent) 298, 644, 1421
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (1000 Agent) 1609
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (50 Agent) 298, 644, 1421
Call Center Software 100, Upgrade from MAX 7/8/9 Fundamental or Enhanced (500 Agent) 298, 645, 1421
Call Center Software 100, Upgrade from Max Pre-release 5 or PDP (1 Agent) 299, 669, 1423
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (10 Agent) 299, 669, 1423
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (100 Agent) 299, 670, 1423
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (1000 Agent) 1609
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (50 Agent) 299, 670, 1423
Call Center Software 100, Upgrade from MAX Pre-Release 5 or PDP (500 Agent) 299, 671, 1423
Call Center Software 200, New System (1 Agent) 297, 637, 1420
Call Center Software 200, New System (10 Agent) 297, 637, 1420
Call Center Software 200, New System (100 Agent) 297, 638, 1420
Call Center Software 200, New System (1000 Agent) 1609
Call Center Software 200, New System (50 Agent) 297, 638, 1420
Call Center Software 200, New System (500 Agent) 297, 638, 1420
Call Center Software 200, Upgrade from CCR only (1 Agent) 301, 666, 1423
Call Center Software 200, Upgrade from CCR only (10 Agent) 301, 666, 1423
Call Center Software 200, Upgrade from CCR only (100 Agent) 301, 667, 1423
Call Center Software 200, Upgrade from CCR only (1000 Agent) 1609
Call Center Software 200, Upgrade from CCR only (50 Agent) 301, 667, 1423
Call Center Software 200, Upgrade from CCR only (500 Agent) 301, 668, 1423
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1 Agent) 300, 672, 1423
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (10 Agent) 300, 672, 1423

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (100 Agent) 300, 673, 1424
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (1000 Agent) 1609
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (50 Agent) 300, 673, 1423
Call Center Software 200, Upgrade from MAX 7/8/9 Virtual to CCS 200 (500 Agent) 300, 674, 1424
Call Center Software 200, Upgrade from MAX and CCR (1 Agent) 300, 646, 1421
Call Center Software 200, Upgrade from MAX and CCR (10 Agent) 300, 646, 1421
Call Center Software 200, Upgrade from MAX and CCR (100 Agent) 300, 647, 1421
Call Center Software 200, Upgrade from MAX and CCR (1000 Agent) 1609
Call Center Software 200, Upgrade from MAX and CCR (50 Agent) 300, 647, 1421
Call Center Software 200, Upgrade from MAX and CCR (500 Agent) 300, 648, 1421
Call Center Software 300, New System (1 Agent) 298, 640, 1420
Call Center Software 300, New System (10 Agent) 298, 640, 1420
Call Center Software 300, New System (100 Agent) 298, 641, 1421
Call Center Software 300, New System (1000 Agent) 1609
Call Center Software 300, New System (50 Agent) 298, 641, 1421
Call Center Software 300, New System (500 Agent) 298, 642, 1421
Call Center Software 300, Upgrade From MAX NACD and/or NAC (1 Agent) 301, 649, 1421
Call Center Software 300, Upgrade from MAX NACD and/or NAC (10 Agent) 301, 649, 1421
Call Center Software 300, Upgrade from MAX NACD and/or NAC (100 Agent) 301, 650, 1422
Call Center Software 300, Upgrade from MAX NACD and/or NAC (1000 Agent) 1609
Call Center Software 300, Upgrade from MAX NACD and/or NAC (50 Agent) 301, 650, 1422
Call Center Software 300, Upgrade from MAX NACD and/or NAC (500 Agent) 301, 651, 1422
Call Center Software 300, Upgrade From NACD (1 Agent) 302, 656, 1422
Call Center Software 300, Upgrade from NACD (10 Agent) 302, 656, 1422
Call Center Software 300, Upgrade from NACD (100 Agent) 302, 657, 1422
Call Center Software 300, Upgrade from NACD (1000 Agent) 1609
Call Center Software 300, Upgrade from NACD (50 Agent) 302, 657, 1422
Call Center Software 300, Upgrade from NACD (500 Agent) 302, 658, 1422
Call Center Video "Customer Service Takes Flight" 362, 1488
Call Identification (CALL-ID Package 247) 63, 890, 1450
Call Pickup Key Cap Package (50/PK) 1557
Call Pilot Connectivity 99, 108, 1236, 1515
Call Processor II 93, 864, 1448
Call Waiting Key Cap Package (50/PK) 1557
Calling Number Key Cap Package (50/PK) 1556
CallPilot 1 Speech Activated Messaging Channel 45, 224, 1102, 1473
CallPilot 1.0 Patch Software 226, 914, 1453
CallPilot 1.06 Administration Client CD Assembly 227, 915, 1453
CallPilot 1.06 Desktop Messaging CD (English & French) 227, 1453
CallPilot 1.06 Documentation CD-ROM 227, 849, 1445
CallPilot 1.06 Keycode Package 219, 913, 1453
CallPilot 1.07 1001rp AC Base Package 36, 219, 1121, 1475
CallPilot 1.07 1001rp Base Documentation Package, English 31, 227, 843, 1444
CallPilot 1.07 1001rp DC Base Package 36, 219, 1121, 1475
CallPilot 1.07 1001rp Installation and Configuration Guide 32, 227, 848, 1445
CallPilot 1.07 200i Installation and Configuration Server Hardware Guide 37, 228, 1496
CallPilot 1.07 702t Base Package 36, 219, 1120, 1475
CallPilot 1.07 702t Installation and Configuration Guide Package 31, 227, 847, 1445
CallPilot 1.07 Administration Client CD 33, 226, 914, 1453
CallPilot 1.07 Administrators Guide 37, 229, 1169, 1496
CallPilot 1.07 Applications Builder Guide 37, 229, 1169, 1496
CallPilot 1.07 Base Software Assembly 33, 224, 1453
CallPilot 1.07 Client Software Installation 37, 229, 1169, 1496
CallPilot 1.07 Desktop Messaging CD 33, 226, 914, 1453
CallPilot 1.07 Desktop Messaging Quick Reference Guide, Quantity 10 32, 227, 850, 1445
CallPilot 1.07 Desktop Messaging Software Installation and Maintenance Guide 37, 229, 1497
CallPilot 1.07 Desktop Quick Reference Guide Package,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

French 32, 227, 851, 1445
CallPilot 1.07 Documentation CD-ROM 32, 227, 849, 1445
CallPilot 1.07 Feature Operations Video 37, 223, 1498
CallPilot 1.07 GB, 200i Ethernet LAN Option 33, 220, 919, 1454
CallPilot 1.07 GB, 200i Token Ring LAN Option 33, 220, 919, 1454
CallPilot 1.07 GB, 700/1000 Series Ethernet LAN Option 34, 220, 920, 1454
CallPilot 1.07 GB, 700/1000 Series Token Ring LAN Option 34, 220, 920, 1454
CallPilot 1.07 GB, DSE Connectivity Option - Lucent 2 Wire 36, 223, 1122, 1475
CallPilot 1.07 GB, DSE Connectivity Option - Mitel 36, 223, 1122, 1475
CallPilot 1.07 GB, DSE Connectivity Option - Siemens/ ROLM 36, 223, 1122, 1475
CallPilot 1.07 GB, MPC-8 - Expand Option (No Charge) 34, 224, 920, 1454
CallPilot 1.07 GB, T1 (SL-100) Connectivity Option - SL-100 36, 223, 1123, 1475
CallPilot 1.07 Getting Started Guide 37, 229, 1168, 1496
CallPilot 1.07 Installation and Configuration Guide Package 31, 227, 847, 1445
CallPilot 1.07 Installation and configuration Switch Set Up 36, 228, 1167, 1496
CallPilot 1.07 IPE (200i) Base Documentation Package 31, 227, 842, 1444
CallPilot 1.07 IPE Base Package 36, 219, 1120, 1475
CallPilot 1.07 IPE Base Server Software Assembly 33, 224, 1453
CallPilot 1.07 Language Prompts CD 33, 226, 1453
CallPilot 1.07 Language Prompts CD Sets (3) 33, 224, 915, 1453
CallPilot 1.07 Meridian Mail to CallPilot Migration Guide 37, 229, 1496
CallPilot 1.07 Meridian Mail to CallPilot Migration Tape 226, 1453
CallPilot 1.07 Monitoring and Security for Administrators 37, 229, 1168, 1496
CallPilot 1.07 Networking Package 41, 227, 846, 1445
CallPilot 1.07 New System Ordering Code 36, 226, 1475
CallPilot 1.07 PEP Software CD 33, 226, 914, 1453
CallPilot 1.07 Planning and Engineering Guide 37, 229, 1168, 1496
CallPilot 1.07 Reporter Guide 37, 229, 1496
CallPilot 1.07 Server Software CD 33, 226, 914, 1453
CallPilot 1.07 Telset User Guide Package - Canadian French 31, 227, 800, 1437
CallPilot 1.07 to Lucent (2 Wire) Integration Software 36, 226, 1118, 1475
CallPilot 1.07 to Meridian 1 Integration Software 226, 1118, 1475
CallPilot 1.07 to Mitel Integration Software 36, 226, 1119, 1475
CallPilot 1.07 to Siemens/Rolm Integration Software 36, 226, 1119, 1475
CallPilot 1.07 to SL-100 Integration Software 36, 226, 1119, 1475
CallPilot 1.07 Upgrade Ordering Code 36, 226, 1119, 1475
CallPilot 1.07 Web Messaging CD 33, 226, 915, 1453
CallPilot 100 BaseT Ethernet Adapter PCI - Tower and Rack 42, 220, 858, 1447
CallPilot 1001rp Installation and Configuration Server Hardware 229, 1168, 1496
CallPilot 1001rp Installation and Maintenance Guide - 1.06 229, 1497
CallPilot 1001rp Installation Guide 228, 1164, 1494
CallPilot 128 MB DIMM 38, 221, 431, 1375
CallPilot 14" Monitor Kit 42, 222, 917, 1454
CallPilot 2 FAX Channels 45, 224, 1102, 1473
CallPilot 2 Voice Channels 34, 224, 1103, 1473
CallPilot 200 Series Installation Guide 228, 1162, 1167, 1493, 1495
CallPilot 4 Voice Channels 45, 224, 1102, 1473
CallPilot 5000 Fax Users 34, 225, 1473
CallPilot 700 Series RAID Kit 42, 224, 918, 1454
CallPilot 702t Configuration Assembly 1624
CallPilot 702t Installation and Configuration Server Hardware - Part 2 37, 229, 1496
CallPilot Additional Prompt Language 219, 1111, 1474
CallPilot Advanced Administration Documentation Package - English 227, 845, 1444
CallPilot Advanced Administration Guide - Volume 1 228, 1493
CallPilot Advanced Administration Guide - Volume 2 228, 1493
CallPilot Advanced Administration Guide, Volume 1 - French 229, 1498
CallPilot Advanced Administration Guide, Volume 2 - French 229, 1498
CallPilot AMIS Installation and Administration Guide 46, 228, 1493
CallPilot AMIS Networking Documentation Package - English 227, 846, 1445
CallPilot Applications Builder FAX Option 226, 1111, 1474
CallPilot Applications Builder Guide 228, 229, 1493, 1498

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CallPilot Asia Pacific Desktop Client CD ROM 228, 1459
CallPilot Asia Pacific Language & Desktop Client CD ROM 228, 1459
CallPilot Asia Pacific Language Prompts CD ROM 227, 1459
CallPilot ATA Drive with Programmed Flash 222, 860, 1447
CallPilot Basic Administration Documentation Package - English 218, 219, 844, 1444, 1623
CallPilot Basic Administration Guide 228, 1164, 1493
CallPilot Bulk - System Order Code 36, 219, 1475
CallPilot CD ROM DRIVE 222, 859, 1447
CallPilot CD ROM Drive 42, 222, 918, 1454
CallPilot Conversion 1 Speech Channel to 2 Fax Channels 46, 226, 1115, 1475
CallPilot Conversion 1 Speech Channel to 4 Voice Channels 36, 226, 1475
CallPilot Conversion 2 Fax Channels to 1 Speech Channel 46, 226, 1115, 1475
CallPilot Conversion 2 Fax Channels to 4 Voice Channels 35, 226, 1475
CallPilot Conversion 2 Speech Channels to 4 Voice Channels 219, 1115, 1475
CallPilot Conversion 4 Fax Channels to 4 Voice Channels 219, 1114, 1475
CallPilot Conversion 4 Voice Channels to 1 Speech Channel 35, 226, 1475
CallPilot Conversion 4 Voice Channels to 2 Fax Channels 35, 226, 1475
CallPilot Conversion 4 Voice Channels to 2 Speech Channels 219, 1114, 1474
CallPilot Conversion 4 Voice Channels to 4 Fax Channels 219, 1114, 1474
CallPilot Desktop Messaging - Lotus Notes Guide 228, 1493
CallPilot Desktop Messaging - MS Exchange Guide 228, 1493
CallPilot Desktop Messaging Capability - 100 Users 45, 48, 225, 1106, 1473
CallPilot Desktop Messaging Capability - 1000 Users 225, 1107, 1473
CallPilot Desktop Messaging Capability - 20 Users 35, 45, 48, 219, 225, 1105, 1473
CallPilot Desktop Messaging Capability - 200 Users 35, 46, 48, 225, 1106, 1473
CallPilot Desktop Messaging Capability - 50 Users 45, 48, 219, 1106, 1473
CallPilot Desktop Messaging Capability - 500 Users 225, 1106, 1473
CallPilot Desktop Messaging Capability - 5000 Users 35, 225, 1473
CallPilot Desktop Messaging for Exchange/Outlook 1.06 229, 1497
CallPilot Desktop Messaging for Internet Mail Clients - 1.06 229, 1497
CallPilot Desktop Messaging for Lotus Notes - 1.06 229, 1497
CallPilot Disk and 50 Hour Storage Expansion - Rack 1631
CallPilot Disk and 50 Hour Storage Expansion - Tower 1631
CallPilot Documentation CD ROM 227, 848, 1445, 1623
CallPilot Dongle Serial Adapter - Tower/Rack Systems 38, 221, 1374
CallPilot DSE Extender Cable - 100 Ft. 38, 221, 1375
CallPilot Enterprise Networking Documentation Package - English 227, 846, 1445
CallPilot Enterprise Networking Installation and Administration Guide 46, 228, 1493
CallPilot Ethernet Adaptor PCMCIA (IPE System) 42, 222, 859, 1447
CallPilot Ethernet LAN Connection Kit - IPE Systems 42, 220, 916, 1453
CallPilot European Language & Desktop Client CD ROM Kit 1625
CallPilot External Modem Kit 42, 222, 913, 1453
CallPilot External SCSI Tape Drive, 4GB (IPE System) 42, 222, 1447
CallPilot External Tape Drive - IPE Systems 42, 222, 916, 1453
CallPilot FAX Capability - 100 Users 45, 48, 225, 1104, 1473
CallPilot FAX Capability - 1000 Users 45, 225, 1105, 1473
CallPilot Fax Capability - 20 Users 34, 225, 1473
CallPilot FAX Capability - 200 Users 45, 48, 225, 1104, 1473
CallPilot Fax Capability - 200 Users 35, 225, 1473
CallPilot FAX Capability - 50 Users 45, 48, 219, 1104, 1473
CallPilot FAX Capability - 500 Users 45, 225, 1105, 1473
CallPilot FAX Capability -20 Users 45, 48, 219, 1104, 1473
CallPilot Installation Worksheet Package 227, 849, 1445
CallPilot Integrated AMIS Installation and Administration Guide 46, 228, 1494
CallPilot Integrated AMIS Networking Documentation Package - English 227, 848, 1445
CallPilot Integration Suite 223, 1117, 1475
CallPilot Intermediate SCSI Cable 41, 223, 852, 1445
CallPilot Internal Ethernet Cabling (IPE System) 41, 221, 852, 1445

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CallPilot Internet Messaging Guide 228, 1493
CallPilot IPE Base System - English 219, 1094, 1473, 1631
CallPilot IPE Spares Package 222, 1112, 1474
CallPilot Maintenance and Diagnostic Guide 228, 1167, 1495, 1669
CallPilot MGate Cable - 20 Ft. 221, 853, 1446
CallPilot MGate Cable - 20ft 223, 1446
CallPilot MGate Card 1444
CallPilot MGate Kit 220, 918, 1454, 1624
CallPilot MPB-16 41, 219, 919, 1446, 1454, 1623, 1624
CallPilot MPB-16 Cable 221, 853, 1446
CallPilot MPC-8 41, 220, 851, 1445
CallPilot Multimedia Mailboxes with Voice - 10,000 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 100 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 1000 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 20 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 200 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 50 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 500 Users 35, 224, 1474
CallPilot Multimedia Mailboxes with Voice - 5000 Users 35, 224, 1474
CallPilot Multimedia Users Guide 28
CallPilot Network Planning Guide 46, 228, 1493
CallPilot Networking (EN, AMIS, VPIM) 1 to 96 Channels 35, 225, 1474
CallPilot Networking, 1 to 24 Channels 219, 1109, 1474
CallPilot Networking, 25 to 48 Channels 219, 1109, 1474
CallPilot Networking, 49 to 96 Channels 219, 1109, 1474
CallPilot NMS Installation and Administration Guide 46, 48, 228, 1493
CallPilot NMS Networking Documentation Package - English 227, 848, 1445
CallPilot NMS Networking, 1 to 24 Channels 219, 1110, 1474
CallPilot NMS Networking, 1 to 96 Channels 35, 225, 1111, 1474
CallPilot NMS Networking, 25 to 48 Channels 219, 1110, 1474
CallPilot NMS Networking, 49 to 96 Channels 219, 1110, 1474
CallPilot Planning and Engineering Guide 228, 1164, 1493
CallPilot Platform Migration Order Code 36, 226, 1475
CallPilot Power Supply AC - Rack System 221, 1373
CallPilot Rack Mount AC Spares Package 222, 1113, 1474
CallPilot Rack Mount DC Spares Package 222, 1113, 1474
CallPilot Rack Mount System AC - English 219, 1100, 1473, 1631
CallPilot Rack Mount System DC - English 219, 1098, 1473, 1631
CallPilot Recovery Kit - IPE 42, 222, 916, 1454
CallPilot Reporter Guide 228, 1493
CallPilot Software Installation Guide 228, 1167, 1495, 1669
CallPilot Speech Activated Messaging Capability - 100 Users 46, 48, 225, 1108, 1474
CallPilot Speech Activated Messaging Capability - 1000 Users 46, 225, 1108, 1474
CallPilot Speech Activated Messaging Capability - 20 Users 35, 46, 48, 219, 225, 1107, 1473, 1474
CallPilot Speech Activated Messaging Capability - 200 Users 35, 46, 48, 225, 1108, 1474
CallPilot Speech Activated Messaging Capability - 50 Users 46, 48, 219, 1107, 1474
CallPilot Speech Activated Messaging Capability - 500 Users 46, 225, 1108, 1474
CallPilot Speech Activated Messaging Capability - 5000 Users 35, 225, 1474
CallPilot Speech Activated Messaging Vocabulary 219, 1112, 1474
CallPilot Speech Recognition Users Guide 228, 1493
CallPilot Storage Expansion - 10 hours 219, 1103, 1473
CallPilot Storage Expansion - 50 Hours 219, 1103, 1473
CallPilot Support Tools Guide 1669
CallPilot Telset Guide Package 227, 1444
CallPilot Telset Guide Package (Quantity 10), English 31, 227, 1437
CallPilot Telset Guides, English, Quantity 15 227, 845, 1444
CallPilot Telset Guides, French, Quantity 15 227, 846, 1445
CallPilot Telset Quick Reference Guide 228, 1493
CallPilot to Lucent (2 Wire) Integration 36, 223, 1116, 1475
CallPilot to Meridian 1 Integration 222, 1116, 1475
CallPilot to Mitel Integration 36, 223, 1117, 1475
CallPilot to Nortel SL-100 Integration 36, 223, 1117, 1475
CallPilot to Siemens/Rolm Integration 36, 223, 1116, 1475

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Callpilot Token Ring Adapter PCMCIA (IPE System) 42, 222, 859, 1447
CallPilot Token Ring Cabling (IPE System) 41, 221, 852, 1445
CallPilot Token Ring LAN Kit - IPE Systems 42, 220, 915, 1453
CallPilot Tower Spares Package 222, 1112, 1474
CallPilot Tower System - English 219, 1096, 1473, 1631
CallPilot Tower/Rack Internal Tape Drive Kit 42, 222, 917, 1454
CallPilot VPIM Networking Documentation Package - English 227, 847, 1445
CallPilot VPIM Networking Package 46, 228, 1494
CallPilot What's New for Release 1.06 1497
CallPilot WhatsNewforRelease1.06' 229
Canadian French Prompt - Bilingual 1701
Canadian French Prompt - Unilingual 1701
Canadian Tire Video 362, 1488
Cap Amber 1641
Cap Clear 1641
Cap Package 1641
Cap Package (Basic & Display) 1641
Cap Transparent Red 1641
Carbon Copy Software 1555, 1596
Card Holder Group (Telephone Directory Number) 1639
Card Option 2GB Disk Drive 1617
Card Option 4.5GB Disk Drive 239, 714, 1432
Card Option Expanded Storage Level 1-2 1703
Card Option Expanded Storage Level 2-3 1703
Card, Line Designation 1645
Cardcage Upgrade Parts Kit 183, 1389
Carrier Interface (RPE) 1506, 1683
Carrier Maintenance (RPE) 1505, 1682
Carrier Remote Floor Standing Remote Package AC 159, 458, 1379
Carrier Remote Floor Standing Remote Package DC 159, 458, 1379
Carrier Remote IPE Interface NTP 1664
Carrier Remote Local Package 159, 456, 1378
Carrier Remote Main Wall Mount Remote Package AC 159, 457, 1378
Carrier Remote Main Wall Mount Remote Package DC 159, 457, 1378
Carrier Shelf 0 (RPE) (LH Mount) 1507, 1684
Carrier Shelf 1 (RPE)(RH Mount) 1507, 1683
Carrier Wall Mount Cable Kit 189, 1413
Cartridge Tape - 150MB (AA102) VINES 286/386 1551
Cartridge Tape - 4MB (AA100) 1549
Cartridge Tape - 60MB (AA101) 1549
CAS - Main 153, 1210, 1513
CAS - Main/Remote 97, 107, 119, 130, 138, 146, 1212, 1513
CAS - Remote 153, 1210, 1513
CAS Key Cap Package (50/PK) 1556
Caster (1) 196, 388, 1367
Caster (Basic Cabinet) 1547
CCIP - CompuCALL Agent/Port License 275, 1193, 1511
CCIP M1 Connectivity Software 1668
CCIP Meridian 1 Connectivity Documentation 1667, 1668
CCIP Meridian 1 Connectivity, 12 Port Expansion 1586
CCIP Meridian 1 Connectivity, Initial 12 Ports 1398, 1586
CCIP Screen Pop 275, 1195, 1511
cCNI to 3PE or IGS to IGM Cable (10 Ft.) 190, 617, 1417
cCNI to 3PE or IGS to IGM Cable (12 Ft.) 190, 617, 1417
cCNI to 3PE or IGS to IGM Cable (16 Ft.) 190, 617, 618, 1417
cCNI to 3PE or IGS to IGM Cable (25ft/7.6M) 190, 1417
cCNI to 3PE or IGS to IGM Cable (4 Ft.) 190, 617, 1417
cCNI to 3PE or IGS to IGM Cable (50ft./15.2M) 190, 1417
cCNI to 3PE or IGS to IGM Cable (6 Ft.) 190, 617, 1417
cCNI to 3PE or IGS to IGM Cable (8 Ft.) 190, 617, 1417
cCNI to I/O Panel Cable (2 Ft.) 188, 545, 1400
CCR 3B & Link 5 Documentation Package 1576
CCR 3B and Link 5 Documentation Package 1389
CCR 3B/Link 5 Documentation Package 344, 1389, 1576
CCR-NACD Interworking 101, 113, 124, 133, 1244, 1515
CD ROM Meridian Mail Alternate User Interface 1606
CD ROM with Jewel Case 334, 1433, 1617
CDR - Link 1695
CDR Cabinet Assembly 1526
CDR Cabinet Assembly (Single Port) 1526
CDR Door Panel (EMI) 1646
CDR Door Panel Assembly 1645
CDR ROM (Multi-Port) 1503, 1679
CDR ROM 1 (Single Port) 1501, 1677
CDR ROM 2 (Single Port) 1501, 1677
CDR Tape Control 1501, 1677
CDR Timing 1503, 1679
CDR/SDI Cable (RS232) (25 Ft.) (Connects SL-1 to TDR) 1569
CD-ROM Media Request 350, 1185, 1510
CD-ROM, CD-ROM X11 Release 24, North America 344, 1403

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CD-ROM, X11 Release 25 1438
CE Alarm Adapter Cable 1675
CE Backplane 1505, 1682
CE Backplane Expansion 1504, 1680
CE Bus Extender 1504, 1680
CE Cabinet Assembly 1545
CE CPU Cabinet Assembly 1544
CE Network Cabinet 1671
CE Network Cabinet Assembly 1526
CE Power Adapter Cable 1673
CE Shelf (w/Mounting Bracket) 1508, 1685
CE/CPU Cabinet Assembly for Hotel/Motel-Dual CPU 1545
CE/PE Cabinet 1671
CE/PE Cardcage (AC/DC) 1413, 1603
CE/PE Expansion Tier 1508, 1684
Central Answering Position (Caps) 347, 1489
Central Answering Position Guide 353, 1486, 1670
Central Answering Position Guide (10/PK) 1655
Central Processor Unit (CPU) 1503, 1505, 1679, 1681, 1682
Centralized Answering Position Package (M2216ACD-1), Ash 1561
Centralized Answering Position Package (M2216ACD-1), Black 1561
Centralized Answering Position Package (M2216ACD-1), Gray 1561
Centralized Answering Position Packages (M2616), Ash 201, 442, 1377
Centralized Answering Position Packages (M2616), Black 201, 442, 1377
Centralized Answering Position Packages (M2616), Gray 201, 443, 1377
Centralized Power Cabinet (QCA13) J2412A-1L6/18/24 1567
Centralized Power Unit 1509, 1686
Centrex Switch Hook Flash 1688
CERP Shelf 1507, 1683
Changeover & Memory Arbitrator 1502, 1505, 1678, 1681
Changeover & Memory Arbitrator Card 1442, 1622
Changeover and Memory Arbitrator 1504, 1681
Charge Key Cap Package (50/PK) 206, 397, 1368
Chassis Assembly (CDR) 1641
Chassis Fiber Expansion Package (2mi. Multi-Mode) 64, 161, 874, 1449
Chassis Fiber Expansion Package (2mi. Single-Mode) 64, 161, 875, 1449
Chassis Fiber Expansion Package (30 Ft.) 64, 161, 874, 1449
Chassis Front Panel 303, 1375
Chassis Side Access Cover 304, 1375
Chassis Unit 1641
Circuit Breaker 1567
Circuit Breaker (CB1) 1567
Circuit Breaker (CB2) 1546
Circuit Breaker Kit, 10 AMP - 600/48 186, 1152, 1486
Circuit Breaker Kit, 15 AMP - 600/48 186, 1152, 1486
Circuit Breaker Kit, 20 AMP - 600/48 186, 1152, 1486
Circuit Breaker Kit, 30 AMP - 600/48 186, 1152, 1486
Circuit Breaker Kit, 5 AMP - 600/48 186, 1152, 1486
Circuit Breaker Kit, 50 AMP - 600/48 186, 1152, 1486
Circuit Breaker Panel 1588
Circuit Breaker Panel for J2412A-1 Cabinet 1566
Circuit Breaker, 15 Amp 1655
Citizen Printer 196, 1374
CLASS Modem card 64, 177, 554, 1402
CLASS Software 97, 107, 119, 1214, 1513
Cleaning Cartridge 38, 303, 305, 403, 1369
Clear Feature Key Caps (1 each, standard for all Meridian Digital Telephones and Attendant Consoles) 1643
Clear Feature Key Caps (1 each, standard for M2000 Series and Attendant Consoles) 208, 1148, 1482
Clear Window Menu Cover, M3901, Package of 15 207, 527, 1391
Client Training CBT 1629
Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 100 Users 1628
Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 1000 Users 1629
Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 300 Users 1628
Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 500 Users 1629
Client Upgrade Package from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging, 800 Users 1629
Clock Controller 183, 1178, 1504, 1680
Clock Controller (Stratum 3) 1431, 1616
Clock Controller Card 178, 1428, 1612
Clock Controller to Clock Controller Cable (4 Ft.) 190, 616, 1417, 1604
Clock Controller to Clock Controller Cable (6 Ft.) 190, 616, 1417, 1604
Clock Controller to I/O Panel Cable 188, 514, 1388
Clock Controller to Junctor Cable (10 Ft.) 190, 616, 1417, 1604

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Clock Controller to Junctor Cable (4 Ft.) 190, 616, 1417, 1604
Clock Controller to Junctor Cable (6 Ft.) 190, 616, 1417, 1604
Clock Controller to Junctor Cable (8 Ft.) 190, 616, 1417, 1604
Clock to FIJI Cable, (22 Ft.) 195, 838, 1444
Clock to FIJI Cable, (4 Ft.-4.5 Ft.) 195, 837, 1444
Clock to FIJI Cable, (5.5 Ft.-8 Ft.) 195, 838, 1444
Cloth, Cleaning, Anti-Static 1647
Clothing Clip (10/PK) 1555
Cluster Interface Card (CIC) 1426, 1611
CND Applications Package 1529
CND Applications Software 1548
CND Expansion Kit 1676
CNI to 3PE Cable (10 Ft.) 194, 825, 1442, 1622
CNI to 3PE Cable (12 Ft.) 194, 825, 1442, 1622
CNI to 3PE Cable (16 Ft.) 1622
CNI to 3PE Cable (25 Ft.) 194, 825, 1442, 1622
CNI to 3PE Cable (5 Ft.) 194, 1442
CNI to I/O Panel Ethernet Cable (13 In.) 1623
CNI to I/O Panel Ethernet Cable (17 In.) 1623
CNI to I/O Panel Ethernet Cable (20 In.) 195, 268, 830, 1443
CNI-3 to 3PE (35 Ft.) 194, 825, 1442
CNI-3 to 3PE Cable (50 Ft.) 194, 826, 1442
CNI-3 TO 3PE/EMSI TO MDU Cable (10 Ft.) 192, 632, 1420
CNI-3 TO 3PE/EMSI TO MDU Cable (12 Ft.) 192, 633, 1420
CNI-3 to 3PE/EMSI to MDU Cable (2 Ft.) 1609
CNI-3 TO 3PE/EMSI TO MDU Cable (25 Ft.) 192, 633, 1420
CNI-3 TO 3PE/EMSI TO MDU Cable (50 Ft.) 192, 633, 1420
CNI-3 to 3PE/EMSI to MDU Cable (6 Ft.) 1609
CNI-3 TO 3PE/EMSI TO MDU Cable (8 Ft.) 192, 632, 1420
CNS Disk Expansion 660MB SCSI Disk Drive (ESD160) 1554
CNS Memory Expansion 4MB Burst (CNS 486 CPU Only) (EMB204) 1552
CNS Memory Expansion 8MB Burst (CNS 486 CPU Only) (EMB208) 1552
CNS Upgrade to CNS/486-CPU/8MB Burst Memory Expansion (BSU24D) 1552
CO/FX/Trunk w/Message Registration Detector Circuit 1503, 1680
CO/FX/Trunk with Message Registration Detector Circuit 1502, 1678
CO/FX/WATS Trunk 1502, 1505, 1678, 1682
COAX Balun 1570
COAX Cable w/BNC Connectors (16 Ft.) 1611
COAX Cable w/BNC Connectors (8 Ft.) 1611
COAX Elimination & Switching System Brochure 1644
Coax Interface Module and ASIM Power Supply 1549
Coax Interface Module User Guide (15/PK) 1645
Co-Axial Interface Module (CIM) 1426, 1611
Columbia National Incorporated
  SYMPOSIUM Integrated IVR Success Story 370, 1488
Column Expansion Package AC 160, 498, 1382
Column Expansion Package DC 160, 498, 1382
Column Spacer Kit (2.75 In.) 184, 612, 1416
Column Spacer Kit (5.25 In.) 184, 612, 1416
Combination
  Meridian Mail Overview and Meridian Mail Feature Operations Videos 355, 1522
Common Equipment Module Power Distribution Unit 186, 613, 1416
Common Equipment Power Supply AC 186, 603, 1414, 1603
Common Equipment Power Supply DC 185, 570, 1406, 1596
Common Equipment Shelf 1507, 1508, 1684, 1685
Common Equipment Shelf (CPU) 1507, 1683
Common Equipment Shelf 0 (CDR) 1507, 1683
Common Equipment Shelf 1 1507, 1683
Common Equipment Shelf 2 1508, 1685
Common Equipment/Memory (QCA58) 1508, 1685
Common, Peripheral Equipment Module AC 1603
Common/Peripheral Equipment Module AC 1603
Common/Peripheral Equipment Module DC 1603
Common/Peripheral Equipment Module Power Distribution Unit 1604
Common/Peripheral Equipment Power Supply 1410, 1599
Common/Peripheral Equipment Power Supply AC 1411, 1599
Common/Peripheral Equipment Power Supply DC 1407, 1410, 1596, 1599
Compact Hospitality Guest Administration Console RS232 Cable (40 ft.) 61, 1442
Compact Hospitality Meridian Mail Guest Cards (15) 60, 1163, 1493
Compact Hospitality RS-232 Serial Module 1442
Compact Option Additional Language 61, 804, 1437
Compact Option Dual Language Prompting 61, 804, 1437
Compact Option Mail Documentation Package 1591
Complete H/M Program
  Generic 307 (LE) 1533
  Generic 407 (VLE) 1533
  Generic 507 (A) 1532
Complete Hospitality Package (N) 1688
Complete Hospitality Package (NT) 1691
Complete Hospitality Package (RT) 1693

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Complete Hospitality Package (S, MS) 1688
Complete Hospitality Package (ST) 1690
Complete Hospitality Package (XN) 1689
Complete Hospitality Package (XT) 1692
Complete Hotel/Motel Package (LE) 1529
Complete Hotel/Motel Package (MS, M) 1529
Complete Hotel/Motel Package (S) 1534
Complete Hotel/Motel Package (VLE, XL) 1529
Complete Hotel/Motel Program SL-1M (707) (M) 1531
Complete Shelf Assembly (PERP A & B) 1543
Condensed administration programs and features implementation 1654, 1662
Condensed maintenance programs 1654, 1662
Condensed Switch Settings Card and Product Compatibility 1657
Condensed switch settings, card and product compatibility 1658, 1660, 1661, 1662
Condensed system installation and maintenance 1658, 1660, 1661, 1662
Condensed X11 administration programs and feature implementation 1657
Condensed X11 administration programs and features implementation 1659, 1660
Condensed X11 maintenance programs 1657, 1658, 1659, 1660
Condensed X11 system management overview, applications and security 1660, 1662
Condensed X11 system messages 1657, 1658, 1659, 1660, 1661, 1662
Conduit Kit - MPP600 1660
Conference 1504, 1680
Conference Auto Dial Key Cap Package (50/PK) 1557
Conference Bridge Bundle 1620
Conference Card 183, 1177, 1503, 1680
Conference Hotline Key Cap Package (50/PK) 1557
Conference Key Cap Package (50/PK) 1557
Conference Speed Call Key Cap Package (50/PK) 1557
Conference/Network Card 1503, 1679
Conference/TDS Card 178, 602, 1414, 1603
Configuration Control Option - Single to Dual Tower Upgrade 1705
Configuration Control Option Dual Tower 1544
Configuration Control Option Single Tower 1544
Connectionless Routing Software 1620
Connector Adapter Bracket 198, 1145, 1482
Connector Adapter Panel Housing 186, 198, 1146, 1482
Connector Bail Lock Kit 1547
Connector Cable (34 In.) 1674
Connector Cable for VINES 286,386 UPS (VNS285) 1552
Connector Card RPE 1682
Connector Cover Panel 198, 1145, 1482
Connector Hardware Package (25 Conductor) 196, 499, 1383
Connector Hardware Package (50 Conductor) 196, 499, 1383
Connector Housing (Side Panel) 198, 1144, 1482
Connector Housing (Top Panel) 198, 1146, 1482
Connector Housing Box Assembly 158, 377, 1364
Connector Housing Package 186, 198, 1147, 1482
Connector Housing Package (Part of P0704511) 1651
Connector Housing/SDI Cover Plate Bracket Assembly 1528
Connector Kit 1587
Connector Mounting Kit 165, 1324, 1521
Console 1500, 1676
Console Overlay 1642
Consulting Services (On Site) 1 day 1694
Consulting Services (Telephone Support) 1 hour 1694
Continuous Voice Recognition Expansion (2 ports) 1559
Control and Distribution Panel 1596
Control and Timing 1502, 1503, 1504, 1678, 1680, 1681
Control Cable Kit System 600/48 to MPP600 1659
Control Card for J2412AA-1 Control Panel 1481, 1646
Control Card for J2412AA-1, L1, 2, 3 Control Panel 1480, 1641
Control Card for NT5C03 Rectifier 1401, 1589
Control Interface and Memory 1502, 1678
Control Panel Assembly 1567
Control Processor e/w 256 MB Hard Drive 1438, 1619
Control Processor e/w 810 MB Hard Drive 1438, 1619
Controlled COS Key Cap Package (50/PK) 1556
Controller - Four Card 178, 599, 1413, 1602
Controller - Two Card 1413, 1602
Controller to I/O Cable (20 Inch) 191, 627, 1418
Controller/Monitor PCBA 1406, 1595
Controlling Access Privileges Workbook 346, 368, 1484, 1486
Conversion Plate (50 to 36 Pos) Cantilever 1652
Conversion Plate (50 to 36 Pos) Center 1653
Cooling Unit 1509, 1686
Cooling Unit (CDR) 1509, 1686
Cooling Unit Cover for QUD9 1649
Cooling Unit Filter Assembly 184, 1145, 1482
Coordinated Dialing Plan 153, 1214, 1513
Cord Assembly (CDR) 1567
Cord, Assembly RS232 ADM (6 In.) (Male/Female) 1546
Core Bus Terminator 177, 575, 1407
Core CardCage (AC/DC) 1596
Core Module DC 1596
Core Multi-Drive Unit (CMDU) 1408, 1596
Core/Network Cardcage (AC/DC) 183, 1402, 1590, 1606

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Core/Network Power Supply AC 186, 1414
Core/Network Power Supply DC 185, 1406
Core-Cabinet Upgrade Cable Group 1-2 1622
Core-Cabinet Upgrade Cable Kit, Group 0 1622
Core-Cabinet Upgrade Cable Kit, Groups 1-4 195, 828, 1443
Core-Cabinet Upgrade Cable Kit, Groups 3-4 1622
Core-to-Network Interface Card (CNI) 1408, 1596
Core-to-Network Interface Card (CNI-3) 179, 837, 1444
Corporate Directory, Virtual Office 93, 864, 1448
Cover (Add-On Module) 1639
Cover (Console) (QCW2/QCW3/QCW4) 1640
Cover (SL-1 Set) 1639
Cover AC Panel 1644
Cover Plate 25 Pin Connector (EMI) 1643
Cover Plate 50 Pin Connector (EMI) 1643
CP Card Field Memory Upgrade Procedure 349, 1498, 1666, 1670
CP card field memory upgrade procedure 1667
CP PII Call Processor Card (128MB Memory) 176, 436, 1376, 1377, 1561
CP PII Ethernet to Ethernet Cable (8.5 Ft./3m) 195, 837, 1444
CP PII to I/O Panel DCE Cable (48 In.) 188, 544, 1400
CP PII to I/O Panel DtE Cable (48 In.) 188, 544, 1400
CP PII to I/O Panel Ethernet Cable (48 In.) 188, 544, 1400
CP PII with IGS Reference Library 26, 1618
CP to CP Cable (6 Ft.) 194, 824, 1442, 1622
CP to I/O Panel RS232 Cable 188, 597, 1412, 1600
CPC45 1569
cPCI Card Slot Filler Panel 182, 1169, 1497
cPCI Core Network Interface Card (2 Ports) 25, 30, 40, 177, 543, 1399, 1588
cPCI Core Network Interface Transition Card 25, 30, 40, 177, 543, 1399, 1588
cPCI Core/Network Card Cage AC/DC 183, 542, 1399
cPCI LED/LCD Display Panel 197, 1400
cPCI Multi-Media Disk Unit 185, 542, 1399
cPCI System Utility Card 177, 543, 1399
cPCI System Utility Transition Card 177, 544, 1400
cPCI Upgrade Kit AC 183, 545, 1400
cPCI Upgrade Kit DC 183, 545, 1400
CPLUS 2000 Directory/Message Center PC Software 1606
CPLUS 2000 Installation Guide 352, 1483
CPLUS 2000 User Guide 352, 1483
CPLUS Directory and Messaging PC Software (Release 2) 1554
CPLUS Document Binder 1655
CPLUS Flyer 1657
CPLUS LAN Key Installation Guide 354, 1490, 1655
CPLUS LAN Key Software 1606
CPLUS PC Key Cap Labels (each) (for PC keyboard) 208, 1483
CPLUS Performer Installation Guide 354, 1490, 1655
CPLUS Performer Software 1606
CPLUS Performer User Guide 354, 1490, 1655
CPLUS Release 2 Installation Guide 1654
CPLUS Release 2 to Latest Release 3 Software Upgrade 1606
CPLUS Release 2 User Guide 1654
CPLUS Release 3 Directory/Message Center PC Software 1606
CPLUS Release 3 Installation Guide 354, 1490, 1655
CPLUS Release 3 to Latest Release 3 Software Upgrade 1606
CPLUS Release 3 User Guide 354, 1490, 1655
CPU (350Mhz) 1561
CPU Cable (2 In.) 190, 618, 1417
CPU Cardcage (AC/DC) 1415, 1603
CPU Changeover 1502, 1503, 1678, 1679
CPU Interface Cable (10 Ft.) 190, 620, 1417, 1605
CPU Interface Cable (12 Ft.) 191, 620, 1417, 1605
CPU Interface Cable (16 Ft.) 191, 621, 1417, 1605
CPU Interface Cable (20 Ft.) 191, 621, 1418, 1605
CPU Interface Cable (25 Ft.) 191, 621, 1418, 1605
CPU Interface Cable (5 Ft.) 191, 621, 624, 1418, 1605
CPU Interface Cable (6 Ft.) 195, 827, 1443
CPU Interface Card 1505, 1681
CPU Kit Including Installed Heatsink Adhesive and Clip for Pentium Processor 275, 285, 421, 1372
CPU Miscellaneous Register (CDR) 1503, 1679
CPU Module AC 1603
CPU Module DC 1603
CPU or Network to Network Cable (2 Ft.) 192, 630, 1419
CPU or Network to Network Cable (4 Ft.) 192, 630, 1419
CPU or Network to Network Cable (6 Ft.) 192, 630, 1419
CPU Power Adapter 1642, 1643, 1644, 1673
CPU Power Monitor Adapter 1643
CPU to Network Cable (2 Ft.) 1605
CPU to Network Cable (6 Ft.) 1605
CPU/CONF Card 1427, 1611
CPU/Conference Card 1427, 1611
CPU/MDU Interface Cable (2 Ft.) 1605
CPU/MDU Interface Cable (4 Ft.) 190, 620, 1417, 1605
CPU/MDU Interface Cable (6 Ft.) 190, 620, 1417, 1605
CPU/MDU Interface Cable (8 Ft.) 190, 620, 1417

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

CPU/MDU Interface Cable (8Ft.) 1605
CPU/Memory Shelf 1507, 1683, 1684
CPU/Memory Shelf (Cantilever Mount) 1507, 1684
CPU/Memory Shelf (Center Mount) 1507, 1684
CPU/Network Cardcage (AC/DC) 1406, 1595
CRT Cable 267, 268, 549, 1143, 1401, 1481
CSL Cable 267, 549, 1401, 1649, 1674
CT to CT Bus Cable 32, 223, 1445
CTX Access Key Cap Package (50/PK) 1556
Custom Calculator Option - Single to Dual Tower Upgrade 1705
Custom Calculator Option Dual Tower 1544
Custom Calculator Option Single Tower 1544
Custom Cell Builder RTU - 1 AP (or MRS/AP) 43, 277, 940, 1456
Customer Configuration Backup and Restore (Coil) 63, 70, 347, 349, 1489, 1497, 1670
Customer Configuration Backup and Restore Guide 1657
Customer Controlled Routing Call Scripting Flowcharts Job Aid 350, 1382
Customer Controlled Routing Conversion Software Kit 1696
Customer Controlled Routing Conversion Software Kit with 240 Active Associations 1696
Customer Controlled Routing Hardware Package AC 1710
Customer Controlled Routing Hardware Package DC 1710
Customer Controlled Routing Quick Reference Card 352, 1483
Customer Controlled Routing Release 2 to Release 3 Software Upgrade 1705
Customer Controlled Routing Release 3 Advanced Maintenance Guide 1660
Customer Controlled Routing Release 3 Engineering Guide 1661
Customer Controlled Routing Release 3 High Capacity Hardware Package 1312, 1520
Customer Controlled Routing Release 3 NTPs 1576
Customer Controlled Routing Release 3 Software and Documentation Package 1705
Customer Controlled Routing Release 3 Spares Package 1710
Customer Controlled Routing Release 3 User Guide 350, 1389, 1576
Customer Controlled Routing Release 3B from 20 to 240 Active Scripts Software Upgrade Package 1705
Customer Controlled Routing Release 3B with 240 Active Associations Software and Documentation Package 1705
Customer Controlled Routing Release 3B with 240 Active Associations Software Upgrade Package 1705
Customer Controlled Routing Release 3B with twenty (20) Active Scripts Software Documentation Package 1705
Customer Controlled Routing Release 3B/Link Release 4B Advanced Maintenance Guide 352, 1483
Customer Controlled Routing Release 3B/Link Release 4B Engineering Guide 1655
Customer Controlled Routing Release 3B/Link Release 5B Engineering Guide 354, 1490
Customer Controlled Routing Release 3C from 20 to 240 Active Scripts Software Upgrade Package 325, 1272, 1518
Customer Controlled Routing Release 3C with 240 Active Associations Software and Documentation Package 1518
Customer Controlled Routing Release 3C with 240 Active Associations Software Upgrade Package 325, 1273, 1518
Customer Controlled Routing Release 3C with Twenty (20) Active Scripts Software Documentation Package 1518
Customer Controlled Routing Software and Documentation Package 1705
Customer Controlled Routing Software Service Transaction Fee 325, 1182, 1510
Customer Controlled Routing User Guide 350, 1368
Customer Controlled Routing Users Guide 1655
Customer Controlled Routing Users Guide & A-C2/ NACD Documentation 1556
Customer Profile
The Toronto Star 360, 1486
Customer Provided DC Power Assembly 158, 441, 1377
Customer Satisfaction Guarantee Program Applications Insert 356, 1497
Customer Satisfaction Guarantee Program Meridian 1 Insert 356, 1497
Customer Satisfaction Guarantee Program Norstar Insert 356, 1497
Customer Satisfaction Guarantee Program Presentation Folder 356, 1497
Customer Satisfaction Guarantee Program Registration Card Insert 357, 1497

D

D Channel Interface Card 1506, 1682
Danish Prompt-Bilingual 1703
Danish Prompt-Unilingual 1703
Dark Gray UEM Overlay Kit 199, 1496
Data Access Card 65, 178, 589, 1411, 1599
Data Cartridge 39, 221, 303, 305, 421, 435, 1372,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1376
Data Cartridge (XL) 1569
Data Input Forms (Release 22) 347, 1490
Data Input Forms (Release 23) 354, 1491, 1668
Data Input Forms (Release 24) 1670
Data Input Forms (Release 25) 355, 1497
Data Key Cap Package (50/PK) 1557
Data Modem (GDC103JM) 1383, 1569
Data Modem GDC103A3 1383, 1569
Data Service Slide Presentation 1650
DataBase 2 Modem 1548
Database Connectivity Software - INFORMIX - RTU 278, 293, 945, 1457
Database Connectivity Software - INGRES - RTU 278, 293, 945, 1457
Database Connectivity Software - Microsoft SQL Server - RTU 278, 946, 1457
Database Connectivity Software - ORACLE - RTU 278, 293, 945, 1457
Database Connectivity Software - SYBASE - RTU 278, 293, 945, 1457
Database Upgrade Tool 67, 197, 711, 1432
DB25 Female Pin Connector (AILU) (F232-422A) 185, 385, 1366
DB25 Male Pin Connector (AILU) (M232-422A) 185, 384, 1366
DB25F-DB9F Cable Adapter 267, 393, 1367
DC Ammeter (For QBL6) 1567
DC Power Cable for PS400-48 Power Supply 38, 221, 428, 1374
DC Power Cable for PS400-48 Power Supply Spare 282, 971, 1461
DC Power Converter 1438, 1618
DC Power Panel 1582
DC Power Supply for Rack Cabinet 38, 220, 423, 1373
DC Power Supply for Rack Cabinet Spare 282, 969, 1461
DC Rack Cabinet - Expansion 280, 958, 1459, 1625
DC Rack Cabinet - Expansion - 220V Inverter 1625
DC Rack Cabinet - Full Assembly 280, 958, 1459
DC Rack Cabinet - Full Assembly - 220V Inverter 1625
DC Thermostat Harness 184, 611, 1416
DC UEM Assembly 1618
DC/DC Power Supply 66, 186, 1427, 1432, 1611
DC300 XLP Back-Up Tape 267, 383, 1365
DC600A 60MB Back Up Tape 326, 382, 1365
DC6150 Back-Up Tape 1555
DC6250 250MB Back Up Tape 239, 249, 267, 326, 389, 1367
D-Channel Handler Card 177, 570, 1406, 1595
DCHI Card 65, 178, 701, 1430, 1615
DDP to Clock Controller Cable (14 Ft.) 193, 1430
DDP to Clock Controller Cable (2 Ft. 8 In.) 193, 1430
DDP to Clock Controller Cable (4 Ft.) 193, 1430
DDP to Clock Controller Cable (7 Ft.) 193, 1431
DDP to DCHI Cable (18 Ft.) 193, 1431
DDP to DCHI Cable (35 Ft.) 193, 1431
DDP to DCHI Cable (50 Ft.) 193, 1431
DDP to DCHI Cable (6 Ft.) 193, 1431
DDP to MSDL Cable (18 Ft.) 193, 1431
DDP to MSDL Cable (35 Ft.) 193, 1431
DDP to MSDL Cable (50 Ft.) 193, 1431
DDP to MSDL Cable (6 Ft.) 193, 1431
DEC 320 Terminal 1365, 1548
DEC 420 Terminal 1367, 1555
DEC Printer 1480
DEC Printer Package 1562
DEC Style Keyboard 272, 1369
DEC Terminal Package 239, 474, 1380
DEC/NT Data Connectivity Brochure 1647
Degausser (CDR) 1567
Designation Label, EMSI 199, 1148, 1483
Designation Strip, Option 21E 1654
Designation Tabs 1641
Designation Tabs (1 each, M2250/M1250) 208, 1145, 1482
Designation Tabs (Booklet) 1640
Designation Tabs (Console/Autovon Function) 1642
Designation Tabs (M2000 Series) 1653
Designation Tabs (QSU1/QSU3/QSU60/QSU61) 1640
Designation Tabs (QSU71) 1644
Desktop Messaging for Internet Client Guide - French 1670
Desktop Messaging for Lotus Notes - Latin American Spanish 228, 1496
Desktop Messaging for Microsoft Exchange/Outlook - Latin American Spanish 228, 1496
Desktop Messaging Guide for Lotus Notes - French 229, 1497
Desktop Messaging Guide for MS Exchange - French 229, 1497
Desktop Messaging Quick Reference Guide - French - Package of 100 227, 851, 1445
Desktop Messaging Quick Reference Guide French - Package of 25 227, 850, 1445
Desktop Messaging Quick Reference Guide, Quantity 100 227, 850, 1445
Desktop Messaging Quick Reference Guide, Quantity 25 227, 850, 1445
Development License - 1 User 43, 277, 941, 1456
Development License - 4 Users 277, 940, 1456
Development License Upgrade - 1 to 4 Users 43, 277, 940, 1456
Development System Upgrade Package Release 2.08 to Release 2.2 923, 1454
Dial Mechanism Assembly (QCW1, QCW2, QSU1A-QSU1E) 1639

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Dial Pulse Detection for any 4 Port Loopstart Card 279, 949, 1457
Dialing on the Desktop Video 1655
Dialogic DT1/480SC Dual Span T1 SL-100 Connectivity Card 32, 222, 1447
Dictation Trunk Applique 1506, 1682
Dictation Trunk Applique w/DCK Interface 1502, 1678
Digi PC/Xem Spare 295, 929, 1455
Digit Display Console 1500, 1676
Digital Line Card 1413, 1602
Digital Line Card (DLC) 65, 600, 1413
Digital Power Unit 1384, 1571
Digital Shelf 1398, 1582
Digital Shelf Assembly 1638
Digital Tel 35mm Customer Presentation and Script 1650
Digital Trunk Cable 50 Ft. 1587
Digital Trunk Line Cable 50 Ft. 1587
Digital Trunk Link SRU 1587
Digital Voice Processor Card 239, 694, 1427, 1612
Digitone Receiver 1505, 1506, 1681, 1682
Digitone Receiver Card 178, 602, 1414, 1603
Direct Inward System Access (DISA) 97, 107, 119, 130, 138, 146, 153, 1216, 1513
Directory Faceplate (QSU71) 1643
Directory Insert 1645
Directory Insert, Gray (QSU71) 1646
Directory Services 1533
DISA Option 11C Compact 59, 806, 1438
Discharge Terminal Panel #1 for J2412A-1 Cabinet 1566
Discharge Terminal Panel #2 for J2412A-1 Cabinet 1566
Discharge/Fuse Panel for J2412A-1 Cabinet 1566
Discrete Voice Recognition Expansion (4 ports) 1559
Disk Drive Cable 1674
Disk Drive Controller 1501, 1676
Disk Drive Shelf (Cantilever Mount) 1508, 1684
Disk Drive Shelf/MSU (Center Mount) 1508, 1684
Disk Mirroring Software for MRS/Tower or MRS/Rack 1586
Disk Shelf Power Converter (QMM38) 1505, 1681
Disk/Tape Power Unit 1384, 1571
Disk/Tape Shelf 1398, 1583
Display Agent Key Cap Package (50/PK) 206, 395, 1368
Display Key Cap Package (50/PK) 207, 400, 1368
Display Option Cable 210, 1150, 1484
Display Queue Key Cap Package (50/PK) 206, 394, 1368
Displayphone 3270 Keycap Kit 1547
Displayphone Key Cap Kit 1643
Distributor M1 Common Services and Station Administration Upgrade 1636
DMS SCCS Release 3 CD-ROM Document CD (Merchandise) 34, 921, 1454
DMS SCCS Release 3.0 CD-ROM Client CD (Merchandise) 30, 678, 1424
DMS SCCS Release 3.0 Peripherals Package 34, 1064, 1471
DN Expansion 97, 107, 118, 130, 138, 145, 152, 1204, 1512
DN Pickup Key Cap Package (50/PK) 207, 398, 1368
Dongle 28, 40, 712, 1432
Door Panel (L) (EMI) (Blue) 1646
Door Panel (R) (EMI) (Blue) 1646
Door Panel Lock Latch Kit 197, 632, 1419
Double Key Expansion Module Footstand, Ash (M2000 Series) 203, 1154, 1487
Double Key Expansion Module Footstand, Black (M2000 Series) 203, 1154, 1486
Double Key Expansion Module Footstand, Gray (M2000 Series) 203, 1154, 1487
Downloadable DCHI for DDP 178, 1430
Drill Fixture 1654
Dry Clean Cartridge 38, 220, 304, 423, 1373
DS-1 Assembly 1383, 1571
DS-1 Cable 1582
DS1 Cable (54") 1618
DS-1 Synchronous Interface Assembly 1638
DS-1 Synchronous/Asynchronous Interface Assembly 1638
DS1/E1 Termination Panel 1439, 1619
DS3/E3 ATM Control Cable (54") 1619
DS3/E3 Cable (66") 1618
DS3/E3 Cable with Ferrite 1619
DS3/E3 Control Cable (54") 1618
DS3/E3 Termination Panel 1439, 1619
DSP Application Module 333, 717, 1433
DSP Card Spare for Speech Recognition or Text-to-Speech 281, 964, 1459
DSP Connectivity Option - MSL-100 34, 222, 921, 1454
DSP Connectivity Package - Digitel 34, 222, 920, 1454
DSS-150 Direct Station Select Unit 1419, 1606
DSS-9000 Direct Station Select Unit 204, 631, 1419
DSS-9000 Installation and Maintenance Manual 352, 1483
DSS-9000 Key Cap Remover Tool 209, 1483
DSS-9000 Key Number Labels-Enhanced Mode 208, 1483
DSS-9000 Key Number Labels-Standard Mode 208, 1483
DSS-9000 User Manual 352, 1483
DTI Crosscable 1582
DTI Packaged Assembly 1528

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

DTI Technical Specification 1644
DTI/CPI Network Carrier Interface 1504, 1680
DTI/PRA Adapter Plate Package 186, 198, 1147, 1482
DTI/PRI Card 40, 65, 178, 693, 1427, 1611
DTI/PRI Package 40, 65, 159, 449, 1378
DTS 146MB SCSI Disk (CS042) 1382, 1568
DTS 200 SCSI Cable Kit (CS043) 1568
DTS 200 Tape Cable Kit (CS044) 1568
DTS 3 Drive Capacity (EXP220) 1 80 MB Disk 1549
DTS 3 Drive Capacity (EXP230) 1 146 MB Disk 1549
DTS 52MB SCSI Disk (CS040) 1382, 1568
DTS 80MB SCSI Disk (CS041) 1382, 1568
DTS Card Guide Kit (CS023) 1567
DTS Console Cable (SA282) 1550
DTS Disk Cable Kit (CS028) 1567
DTS Front Panel LED Kit (CS025) 1568
DTS I/O Board Kit (CS024) 1382, 1567
DTS Motherboard (CS022) 1382, 1567
DTS PC Console Cable (SA283) 1550
DTS Power Harness (CS029) 1567
DTS SCSI Cable Kit (CS027) 1567
DTS Server Console (SA261) 1549
DTS Tape Cable Kit (CS033) 1567
DTS Tape Drive Kit (Half Height) (CS030) 1382, 1568
DTS Uninterruptible (UPS120) Power Supply (UPS) (120V) 1549
DTS Uninterruptible (UPS240) Power Supply (UPS) (240V) 1549
DTS UPS Cable Kit (CS026) 1567
DTS/100/200 Hardware Maintenance Manual (DA151) 1649
DTS/EXP Power Supply (CS034) 1382, 1567
DUAL COAX Balun 1570
Dual Compact NTP Storage Sleeve 1650
Dual Digitone Receiver Daughter Board 1506, 1682
Dual DSX30XV Interconnect Cable 224, 1446
Dual Ethernet Adapter RJ45 for I/O Panel 195, 842, 1444
Dual Intergroup Switch 177, 553, 1402
Dual Loop PE Shelf 26, 1507, 1684
Dual Loop Peripheral Buffer 1505, 1681
Dual Module Interface Cable (12 Ft.) 1600
Dual Network 1503, 1679
Dual Network/Intra-Connection Cable (Cantilever) 267, 548, 1400
Dual Network/Intra-Connection Cable (Center) 1588
Dual NTP Rack (Double) (Gray) 1644
Dual Pentium II CPU 221, 432, 1375
Dual Pentium III SBC 42, 222, 860, 1447
Dual Port DTI/PRI (DDP) Card 25, 30, 40, 177, 552, 1402, 1589
Dual Port DTI/PRI Package 160, 495, 1381
Dual Port DTI/PRI Package (Cabinet) 160, 495, 1381
Dual Port DTI/PRI Package (ST, STE, RT) 160, 495, 1381
Dual Port SDI Assembly - EMI 1528
Dual Port SDI Assembly-EMI 1543
Dual Port SDI Paddle Board 1415, 1604
Dual Serial Data Interface (SDI) Cable 1622
Dual Transport Cable 1582
Dual-Port DTI/PRI (DDP) Card 1402, 1589
Dummy Faceplate - Dual 1641
Dummy Faceplate - Single 1641
Dutch Prompt-Bilingual 1702
Dutch Prompt-Unilingual 1702
DVS Bus Cable 268, 572, 1407
DVS Bus Cable (57 Inches) 268, 572, 1407
DVS Bus Cable (6 Ft.) 268, 572, 1407
DVS Bus Cable (Internal) (132 Inches) 268, 572, 1407

E

E&M Trunk Card 40, 65, 178, 602, 1414, 1603
E&M/DX/Page Trunk 1506, 1682
E1201A 160, 498, 1382
E1201D 160, 498, 1382
Earpiece with Foam Cover (10/PK) 1555
Earthquake Bracing Kit (1 Module Column) 184, 1416
Earthquake Bracing Kit (2 Module Column) 184, 614, 1416
Earthquake Bracing Kit (3 Module Column) 184, 614, 1416
Earthquake Bracing Kit (4 Module Column) 184, 614, 1416
Earthquake Bracing Kit (Four Module Column) 1604
Earthquake Bracing Kit (Three Module Column) 1604
Earthquake Bracing Kit (Two Module Column) 1604
Earthquake Bracing Rod (3 Module) 184, 1146, 1482
Earthquake Bracing Rod (4 Module) 184, 1146, 1482
EasyLan with Meridian Extension 1551, 1554
EC11 Backplane and Cabinet Assembly 250, 711, 1432
EC11 Base System Software Initial Caps 1707
Electronic Brandlining - Display Customization 99, 108, 120, 1245, 1516
Electro-Optical Interface Packlet 188, 508, 1388, 1575
Emergency Key Cap Package (50/PK) 206, 396, 1368
Emergency Notification Installation/User Guide 332, 1372
Emergency Response Installation/User Guide 332, 419, 1372
Emergency Services Access (ESA) Enhanced Services 99, 108, 120, 1236, 1515

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

EMI Shield 1647
EMI Shield (Metal Type) 186, 1149, 1483
EMI Shield (Plastic Type) 186, 1149, 1483
Empty Compact NTP Binder 347, 1484
EMSI/SMDU Power Cable (2 Ft.) 1608
EMSI/SMDU Power Cable (6 Ft.) 1608
EMSI/SMDU Signal Cable (2 Ft.) 1607
EMSI/SMDU Signal Cable (6 Ft.) 1607
Enable Package 381, 382 for M3900 Sets Phase II 33, 42, 201, 892, 1450
Engineering Handbook Issue II 1649
Engineering NTP 1644
Enhanced ACD Overflow 101, 112, 124, 132, 140, 147, 154, 1238, 1241, 1515
Enhanced ACD Routing 101, 112, 124, 132, 140, 147, 154, 1240, 1242, 1515
Enhanced Business (no DISA) Software Update 1700
Enhanced Business Software 698, 1428, 1612
Enhanced Business Software (Add. 100 TNs) 92, 1251, 1516, 1699
Enhanced Business Software (no DISA) 699, 1429, 1613
Enhanced Business Software Update 92, 1252, 1516, 1699
Enhanced Call Center Management 101, 112, 124, 132, 140, 147, 1242, 1515
Enhanced Call Center Routing 101, 112, 124, 132, 140, 147, 1243, 1515, 1697
Enhanced Call Treatment 154, 1240, 1515
Enhanced Card Option 2 Basic Service Ports - Ports 5 and 6 or 9 and 10 237, 1044, 1469
Enhanced Card Option 2 Basic Service Ports - Ports 7 and 8 or 11 and 12 237, 1044, 1469
Enhanced IVR Reports 275, 1196, 1511
Enhanced Mass Storage Interface Card 1419, 1607
Enhanced Meridian Mail Card Option 4-12 Ports, 5/10/24/54 Hours Package 235, 1043, 1469
Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/200/400 Hour Package AC 255, 1291, 1519
Enhanced Meridian Mail EC Option 28-48 Port 26/54/84/114/200/400 Hour Package DC 255, 1293, 1519
Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package AC 255, 1294, 1519
Enhanced Meridian Mail EC Option 3 Node Migration, 28-48 Port 30/60/90/120/200/400 Hour Package, DC 255, 1295, 1519
Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/200 Hour Package AC 255, 1289, 1519
Enhanced Meridian Mail EC Option 4-24 Port 11/24/36/54/100/200 Hour Package DC 255, 1290, 1519
Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/300/600 Hour Package AC 255, 1297, 1519
Enhanced Meridian Mail EC Option 52-72 Port 45/90/120/180/300/600 Hour Package DC 255, 1298, 1519
Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/400/800 Hour Package AC 256, 1300, 1519
Enhanced Meridian Mail EC Option 76-96 Port 60/120/180/240/400/800 Hour Package DC 256, 1301, 1519
Enhanced Meridian Mail EC11 1 to 2 Node Expansion Package 247, 1045, 1469
Enhanced Meridian Mail EC11 24-48 port, 26/54/84/114/200/400 Hour Package 245, 1311, 1519
Enhanced Meridian Mail EC11 8-24 Port, 11/24/36/54/100/200 Hour Package 245, 1310, 1519
Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package AC 260, 1046, 1469
Enhanced Meridian Mail Modular EC Node Expansion 1st Position Package DC 260, 1046, 1469
Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package AC 261, 1047, 1469
Enhanced Meridian Mail Modular EC Node Expansion 2nd Position Package DC 261, 1048, 1469
Enhanced Meridian Mail Modular EC Node Expansion 3rd Position Package 261, 1048, 1469
Enhanced Meridian Mail Modular GP 16-24 Port 26/54/84/114/200/400 Hours Package DC 256, 1304, 1519
Enhanced Meridian Mail Modular GP 28-32 Port 30/60/90/120/200/400 Hours Package DC 256, 1305, 1519
Enhanced Meridian Mail Modular GP 36-48 Port 45/90/120/180/300/600 Hours Package DC 256, 1307, 1519
Enhanced Meridian Mail Modular GP 4-12 Port 11/24/36/54/100/200 Hours Package DC 256, 1302, 1519
Enhanced Meridian Mail Modular GP 52-64 Port 60/120/180/240/400/800 Hours Package DC 256, 1308, 1519
Enhanced Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC 261, 1049, 1470
Enhanced Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC 261, 1049, 1470
Enhanced Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC 261, 1050, 1470
Enhanced Meridian Mail Modular GP MMP40 4 to 5

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Node Expansion Package DC 261, 1051, 1470
Enhanced Processor for Card Option Systems 240, 1409
Enhanced Processor for Meridian Mail EC 249, 267, 580, 1409
Enhanced Processor for Modular Option and Modular Option GP 267, 580, 1409
Enhanced Processor Upgrade, EC 263, 1092, 1473
Enhanced Processor Upgrade, Modular Option, Modular Option GP 263, 264, 265, 1093, 1473
Enhanced SDI 1504, 1680
Enterprise Business Software (Add. 100 TNs) 92, 1251, 1516, 1699
Enterprise Business Software Update 92, 1252, 1516, 1700
EOI to Fiber Management Optical Cable (Multi Mode) 188, 509, 1388
EOI to Fiber Management Optical Cable (Single Mode) 188, 509, 1388
EOI to I/O Panel Optical Cable (Multi Mode) 188, 509, 1388
EOI to I/O Panel Optical Cable (Single Mode) 188, 508, 1388
ESBC 1399, 1587
ESBC (Bus) 1400, 1588
ESBC Terminator 266, 547, 1400
ESD/DRAM SIMM Accessory Kit 182, 1057, 1470
ESDI 25 pin Female to 15 pin Male Link Cable (20") 188, 1411
ESDI Cable (10 Ft.) 328, 593, 1411, 1600
ESDI Cable (2 Ft.) 328, 593, 1411, 1600
ESDI Cable (20 Ft.) 328, 593, 1411, 1600
ESDI Cable (35 Ft.) 328, 593, 1411, 1600
ESDI Cable (45 Ft.) 328, 594, 1411, 1600
ESDI Cable (6 Ft.) 328, 593, 1411, 1600
ESN Analysis and Reporting User Guide 1666
Ethernet & DB9 Adapter with 25pr Connector 193, 1427
Ethernet Adapter (Options 21-81C) 1590
Ethernet Adapter Cable 67, 194, 296, 307, 710, 1432
Ethernet Adapter for Option 11C 1590
Ethernet Adapter Kit 276, 294, 932, 1455
Ethernet Cable (100 Ft.) 272, 592, 1411
Ethernet Cable (12 Ft.) 328, 592, 1411
Ethernet Cable (2 Ft.) 328, 1411
Ethernet Cable (Thinnet 50 Ft.) and Terminator 272, 592, 1411
Ethernet Cable 25 Ft. Spare 282, 966, 1460
Ethernet LAN Interface - Netware SPX 1627
Ethernet LAN Interface Board 271, 979, 1463
Ethernet LAN Interface Card with NETBEUI drivers 1627
Ethernet LAN Interface Card with Netware IPX NetBIOS drivers 1627
Ethernet LAN Interface Card with TCP NetBIOS drivers 1627
Ethernet NetBEUI LAN Integration Software 1628
Ethernet Netware SPX LAN Integration Software 1628
Ethernet/3Com Software 1550
Ethernet/InterLan Software 1550
Ethernet/U-B Software 1550
EuroFrench Prompt - Bilingual 1700, 1701
EuroFrench Prompt - Unilingual 1701
EuroSpanish Prompt-Bilingual 1702
EuroSpanish Prompt-Unilingual 1702
EXP Front Panel LED Kit (CS047) 1568
EXP Power Load Board Kit (CS046) 1382, 1568
EXP SCSI Expansion Cable Kit (CS045) 1568
Expansion Cabinet 1671
Expansion Cabinet Cable Kit 67, 194, 712, 1432
Expansion Cable - Copper (7 Ft.) 67, 193, 694, 1427
Expansion Cartridge 67, 197, 696, 1428, 1612
Expansion Daughterboard 67, 178, 702, 1430
Expansion Fiber Interface (EFI) Kit 67, 193, 704, 1430, 1615
Expansion Tier Assembly 1508, 1684
Expansion Wall Mount Remote Package AC 159, 454, 1378
Expansion Wall Mount Remote Package DC 159, 454, 1378
Expedite Fee for Same Day Shipment 1694
Extended System Monitor Serial Link Cable (25 Ft.) 189, 607, 1415
Extension Cable (2 Ft.) 327, 510, 1388
Extension Local Carrier Cable Assembly 161, 599, 1413
Extension Local Maintenance Cable Assembly 161, 599, 1413
External Alerter and Recording Interface User Guide (M3900 Series, Package of 15 P0903793) 350, 524, 1390
External Alerter Interface (M2000 Series) 202, 530, 1397
External Modem (14,400 bps, V.32 bis with V.42 bis) 196, 273, 405, 1370
External Modem 33.6 41, 222, 307, 327, 856, 1446
External Modem Cable 1600
External Modem Spare 281, 295, 965, 1460
External RSM Breakout Assembly (4 RS-232 Ports) 230, 912, 1453
External Tape Drive Carrying Case 1556
External Tape Drive Installation Document (DA219) 1553
External Tape Drive Package 1428, 1612
External Tape Drive Package, Tandberg 239, 249, 696, 1428, 1612

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

External Voice Bus Cable (10Ft.) 268, 1408, 1597
External Voice Bus Cable (2.5 Ft.) 268, 1408, 1597
External Voice Bus Cable (5Ft.) 268, 1408, 1597
External Voice Bus Terminator 269, 1408

F

F/F Wide to Narrow SCSI Cable Adapter 38, 223, 1373
Faceplate - 10 Button Module - Black 1639
Faceplate - 10 Button Module - Brown 1639
Faceplate - 20 Button Module - Black 1639
Faceplate - 20 Button Module - Brown 1639
Faceplate - ADM Hinged Control Cover - Black 198, 1481
Faceplate - Black 1641
Faceplate - Brown 1641
Faceplate - QMT3 - BLF (Brown) 1640
Faceplate - QMT4 - Handset Module (Brown) 1640
Faceplate - Set - Black 1640
Faceplate - Set - Brown 1640
Factory Data Base (CDR) Set-Up (Optional) 1535
Fan Air Filter Spare OIVR 4 AP, MRS/AP, MRS Tower 283, 1461
Fan Assembly 38, 221, 303, 1375
Fan Bracket 303, 1375
Fan Filter Air (2) Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
Fan Filter Air Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
Fan Interconnect Cable (12 In.) 1674
Fan Interconnect Cable (29 In.) 1674
Fan Interconnect Cable (34 In.) 1674
Fan Inverter (QRF8) 1502, 1678
Fan Inverter (QSD4) 1506, 1682
Fan Kit Assembly 1647
Fan Module (each) Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
Fan Module Assembly 221, 1375
Fan Power Cable 1674, 1675
Fan Terminating Plug 1675
Fan Unit - Option 21A 1548, 1554
Fan, 8 VDC (NT2R23AA) 1547
Fast CE Bus Extender 1501, 1677
Fast CPU ALU High 1501, 1677
Fast CPU ALU Low 1501, 1677
Fast CPU Control 1501, 1677
Fast CPU Sequencer 1501, 1677
Fast TDS 97, 107, 119, 130, 138, 145, 153, 1210, 1513
Fast Tone and Digit Switch 1505, 1681
FastView Software and Documentation 1574
FastView Software, MCA and Documentation Marketing Package #2A (1 to 19 Units) 1635
FastView Software, MCA and Documentation Marketing Package #2B (20 to 49 Units) 1635
FastView Software, MCA and Documentation Marketing Package #2C (50+ Units) 1635
FastView Software, MCA, M2216 and Documentation Marketing Package #4A (1 to 19 Units) 1636
FastView Software, MCA, M2216 and Documentation Marketing Package #4B (20 to 49 Units) 1636
FastView Software, MCA, M2216 and Documentation Marketing Package #4C (50+ Units) 1636
FastView User Guide 353, 1489
FastView+ and MCA Software and Documentation 1574
FastView+ Software and Documentation 1574
FastView+ Software Upgrade Package and Documentation 1574
FastView+ Software, MCA and Documentation Marketing Package #3A (1 to 19 Units) 1635
FastView+ Software, MCA and Documentation Marketing Package #3B (20 to 49 Units) 1635
FastView+ Software, MCA and Documentation Marketing Package #3C (50+ Units) 1635
FastView+ Software, MCA, M2216 and Documentation Marketing Package #5A (1 to 19 Units) 1636
FastView+ Software, MCA, M2216 and Documentation Marketing Package #5B (20 to 49 Units) 1636
FastView+ Software, MCA, M2216 and Documentation Marketing Package #5C (50+ Units) 1636
Fault and Clearing Guide 1670
Fault Clearing Guide 349, 353, 1485, 1498, 1655, 1656, 1658
Fault Clearing Guide (Coil) 1665
Fax - Gammalink - 12 Port Card and 12 Port RTU 43, 279, 949, 1457
Fax - Gammalink - 12 Port Card Spare 281, 963, 1459
Fax - Gammalink - 4 Port Card and 4 Port RTU 43, 279, 950, 1457
Fax - Gammalink - 4 Port Card Spare 281, 964, 1459
Fax - Gammalink - 6 Port Card and 6 Port RTU 43, 279, 949, 1457
Fax - Gammalink - 6 Port Card Spare 281, 963, 1459
Feature Card Label Sheet (M3901, Package of 25 P0906396) 40, 207, 524, 1390
Feature Document X11 release 21 1663, 1664
Feature Document X11 release 22 1666
Feature Document X11 Release 23 1667
Feature Group D 97, 107, 119, 130, 138, 146, 153, 1215, 1513
Feature Key Designation Labels with Telephone Number Card (25/PK) 209, 1483
Feature Key Label Sheets (Standard) 1652
Feature Key Label Sheets, ACD 1649
Female Telco Cable (2 Ft.) 190, 618, 1417

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Female Telco Cable (3 Ft.) 190, 618, 1417
Female Telco Cable (4 Ft.) 190, 618, 1417
Female Telco Cable (6 Ft.) 190, 618, 1417
Fiber Cable (33 Ft.) 1615
Fiber Controller to System Monitor & SDI Cable 188, 509, 1388
Fiber Interface Kit 70, 188, 468, 1379
Fiber Junctor Interface Card (FIJI) 179, 837, 1444
Fiber Management Kit 67, 193, 704, 1430
Fiber Multi-IPE Interface Card - Multi Mode (1-4 Superloops) 176, 432, 1369, 1374, 1375, 1558, 1561
Fiber Multi-IPE Interface Card - Single Mode (1-4 Superloops) 176, 433, 1374, 1375, 1561
Fiber Network 93, 864, 1448
Fiber Network Clock-Clock Synch Cable, (20 Ft.) 195, 841, 1444
Fiber Network Clock-Clock Synch Cable, (6 Ft.) 195, 840, 1444
Fiber Network Fabric Adapter Panel 188, 436, 1377
Fiber Network Group Assembly Package AC 161, 753, 1434
Fiber Network Group Assembly Package DC 161, 754, 1435
Fiber Network Group Column Package AC 161, 757, 1435
Fiber Network Group Column Package DC 161, 758, 1435
Fiber Network Reference Guide 25, 1590
Fiber Peripheral Controller Card 1387, 1575
Fiber Receiver Pack - 2 Mile Multi-Mode 67, 179, 1432
Fiber Remote Floor Standing Remote Package AC 159, 455, 1378
Fiber Remote Floor Standing Remote Package DC 159, 456, 1378
Fiber Remote Local Package 159, 452, 1378
Fiber Remote Main Wall Mount Remote Package AC 159, 453, 1378
Fiber Remote Main Wall Mount Remote Package DC 159, 453, 1378
Fiber Remote Multi-IPE Interface - Multi Mode (1-2 Superloops) 176, 433, 1369, 1374, 1375, 1558, 1561
Fiber Remote Multi-IPE Interface - Rack Mount Shelf Option 187, 404, 1370
Fiber Remote Multi-IPE Interface - Redundant Option (Multi Mode) 176, 404, 1370
Fiber Remote Multi-IPE Interface - Redundant Option (Single Mode) 176, 404, 1370
Fiber Remote Multi-IPE Interface - Single Mode (1-2 Superloops) 1369, 1558
Fiber Remote Multi-IPE Interface - Single Mode (1-4 Superloops) 1369, 1558
Fiber Remote Multi-IPE Interface Single Mode (1-2 Superloops) 176, 433, 1374, 1375, 1561
Fiber Remote Multi-IPE NTP 1665
Fiber Remote Peripheral Controller Card 177, 508, 1387
Fiber Routing Guide 69, 199, 1488
Fiber Superloop Network Card 177, 508, 1387, 1575
Fiber Superloop to System Monitor & SDI Cable 188, 509, 1388
Field Failure Report Tag (Circuit Card and Shelf Equipment) 1645
Field Failure Report Tag (Telephone and Console Equipment) 198, 1141, 1481
Field Service Manual for CNS (DA223) 1552
FIJI Fiber Ring Cable, (50 Ft.) 195, 840, 1444
FIJI Group Conversion Kit 161, 756, 1435
FIJI to FIJI Fiber Ring Cable, (10 Ft./3M) 195, 839, 1444
FIJI to FIJI Fiber Ring Cable, (12 Ft./3.6M) 195, 839, 1444
FIJI to FIJI Fiber Ring Cable, (14 Ft./4.2M) 195, 839, 1444
FIJI to FIJI Fiber Ring Cable, (19 Ft./6M) 195, 839, 1444
FIJI to FIJI Fiber Ring Cable, (26 Ft./8M) 195, 840, 1444
FIJI to FIJI Fiber Ring Cable, (32 Ft./10M) 195, 840, 1444
FIJI to FIJI Fiber Ring Cable, (6 Ft./2M) 195, 838, 1444
FIJI to FIJI Synch Cable 195, 838, 1444
Filler Panel 197, 269, 588, 1410
Filler Panel - Ringing Generator 197, 588, 1410
Filler Panel Blower 1644
Filler Panel Shelf 1644
Filler Panel, Application Model 317, 387, 1366
Filler Plate 1639, 1647
Filler Plate For Fiber Controller 199, 1155, 1487
Filler Plate for Fiber Controller 1655
Filter (QUD1) (CDR) 1640
Filter Assembly for P0575526 (QUD5) QUD1, QUD3, QUD9 1644
Filter Assembly for QUD15 1643
Filter Assembly for QUD15, QUD20 1644
Filter Connector 198, 1142, 1481
Filter Connector (25 Conductor) (EMI) 1547
Filter Connector (50 cond) EMI 1570
Filter Connector (50 Conductor) (EMI) 187, 382, 1365
Filter For P0575526, QUD1, QUD3, QUD9 1641
Filter Unit Assembly 1641
Filter, PRI/DTI I/O 198, 1141, 1481
Finnish Prompt-Bilingual 1702
Finnish Prompt-Unilingual 1702

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

First Rectifier O/P Cable 1597
Flash Key Cap Package (50/PK) 1557
Flash Over Key Cap Package (50/PK) 1557
Flexible Tones and Cadences 97, 107, 119, 130, 138, 145, 153, 1211, 1513
Floor Module Anchor Hole Template 30, 197, 614, 1416
Floor Mounting Kit 1600
Floor Mounting Kit (Non-Seismic) 184, 614, 1416
Floppy Cable 38, 223, 1373, 1375
Floppy Disk Assembly - Dual CPU 1562
Floppy Disk Assembly - Single CPU 1562
Floppy Disk Interface Card 1506, 1682
Floppy Disk Interface to Floppy Disk Unit (2 Ft.) 1605
Floppy Disk Interface to Floppy Disk Unit (3 Ft.) 1605
Floppy Disk Interface to Floppy Disk Unit (4 Ft.) 1605
Floppy Disk Interface to Floppy Disk Unit (6 Ft.) 1605
Floppy Disk Module 1500, 1676
Floppy Disk Unit 1416, 1604
Floppy Drive Assembly 1501, 1676
Floppy Drive Spare 295, 929, 1455
Follow Me Service 275, 1197, 1511
Footstand, Charcoal (M3901, M3902) 200, 808, 1439
Footstand, Charcoal (M3903, M3904, M3905) 200, 808, 1439
Footstand, Platinum (M3901, M3902) 200, 808, 1439
Footstand, Platinum (M3903, M3904, M3905) 200, 808, 1439
Forward Key Cap Package (50/PK) 1557
Four Optical Adaptors Kit 197, 508, 1388
Four Port Data Line Card 1503, 1679
Four-Port SDI 183, 1179, 1506, 1683
Fred Hutchinson Application Report 1646
FRMII Alarm Cable (32 Ft.) 188, 431, 1375
FRMII MMI/Modem Isolator 188, 431, 1375
FRMII System Monitor Isolator 187, 431, 1375
Front & Rear Fascia Panel (CDR) 1645
Front and Read Fascia Panel (CDR) (Blue) 1646
Front and Rear Fascia Panel 1645
Front and Rear Fascia Panel (Blue) 1646
Front Chassis Cover 303, 1375
Front Cover Panel 1640
Front Door Assembly (NT2R02AA) 1582
Front or Rear Door Kit for Rack Cabinet Spare 282, 969, 1461
Front Panel Cable 303, 1375
Front/Rear Cover 184, 198, 632, 1419, 1444, 1604
Full Documentation Package (CD) 276, 932, 1455
Full Featured Software Package 1527
Function 1504, 1681
Function Pack 1501, 1677
Fuse Block 1671
Fuse Kit 1583, 1640
Fuse Rating Upgrade Assembly 1676
Fuse, .180 Amp 187, 1176, 1500
Fuse, .25 Amp 187, 1176, 1500
Fuse, .50 Amp 187, 1176, 1500
Fuse, 1.33 Amp 187, 1175, 1500
Fuse, 100 Amp (For QBL6) 1567
Fuse, 2. Amp 187, 1175, 1500
Fuse, 3. Amp 187, 1176, 1500
Fuse, 30 Amp (For QBL6) 1567
Fuse, 5. Amp 187, 1176, 1500

G

Gender Changer (Female/Female) 239, 249, 267, 327, 386, 1366
General Business (no DISA) Software Update 1700
General Business Firmware Cartridge 1366, 1551
General Business Software 698, 1428, 1612
General Business Software (Add. 100 TNs) 92, 1250, 1516, 1699
General Business Software (no DISA) 698, 1429, 1613
General Business Software Update 92, 1252, 1516, 1699
General Information and Planning Handbook (Coil) 1663, 1665
General Purpose Signal Processor 266, 546, 1400, 1588
Generic X11 Input/Output Guide 1656
Generic X11 Software Guide 1656
Generic X11 Special Features Guide 1656
German Prompt - Bilingual 1702
German Prompt - Unilingual 1702
Graphical Services Extension Manuals 1658
Gray Cable Routing Panel Assembly (Cantilever Mount) 1645
Gray Cable Routing Panel Assembly (Center Mount) 1645
Gray Cooling and Cable Routing Panel Assembly 1686
Gray Market Pamphlet for Distributors 363, 1495
Gray Market Pamphlet for End Users 363, 1495
Gray Sets 1618
Grey Sets for NTKS1030 1618
Ground Bar 67, 197, 704, 1430
Ground Bar/LRE - Large 185, 574, 1407
Ground Bar/LRE - Small 185, 575, 1407
Ground Extension Cable 196, 1174, 1500, 1675
Ground Lug 198, 1143, 1481
Ground Start Bundle 1575
Ground Window Assembly 1641
Group Call Key Cap Package (50/PK) 206, 396, 1368
Group Listening Switch 1683
Group Pickup Key Cap Package (50/PK) 206, 397, 1368

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Growth I/O Panel 199, 1151, 1486
GSP Cable 268, 571, 1407
GSP Card, Flexible Assignment 1566
GSP Tier 1 Cable Router 1588
GSP Tier 2 Cable Router 1588
GSP Tier 3 Cable Router 1588
Guide to Banyan Publications (DA220-02) 1554

H

H/M PE Shelf System 1508, 1685
H/M ST Shelf System 1508, 1685
H008 350, 1382
H009 1569
H013 350, 1383
H014 350, 1383
H015 350, 1383
H017 1569
H018 1569
H019 1569
H020 1569
H021 350, 1383
H022 350, 1383
HABC (High Availability Bus Controller) 266, 546, 1400
HABC Terminator 266, 546, 1400
Handset Cord (5 Ft. 6 In.) Spade/Spade 1548
Handset Cord (6 Ft.) - Black, (M2000 Series) 205, 384, 1365
Handset Cord (6 Ft.) - Gray, (M2000 Series) 205, 382, 1365
Handset Cord (9 Ft.) (Standard) - Ash, (M2000 Series) 205, 382, 1365
Handset Cord (9 Ft.) (Standard) - Black, (M2000 Series) 205, 384, 1365
Handset Cord (9 Ft.) (Standard) - Gray, (M2000 Series) 205, 382, 1365
Handset Cord (Ash) (5.6 Ft.) Spade/Spade (4 Conductor) 1547
Handset Cord with PJ Type Plug (M2250/M1250) 209, 385, 1366
Handset Cord, 12 Ft. Ash (M2000 Series) 1546
Handset Cord, 6 Ft. Ash (M2000 Series) 205, 380, 1364
Handset Cord, Charcoal, 12 Ft. (M3900 Series) 205, 425, 1373
Handset Cord, Charcoal, 6 Ft. (M3900 Series) 205, 426, 1373
Handset Cord, Charcoal, 9 Ft. (Standard, M3900 Series) 205, 425, 1373
Handset Cord, Platinum, 12 Ft. (M3900 Series) 205, 425, 1373
Handset Cord, Platinum, 6 Ft. (M3900 Series) 205, 426, 1373
Handset Cord, Platinum, 9 Ft. (Standard, M3900 Series) 205, 425, 1373
Handset Cord/12 Ft./Black, (M2000 Series) 1548
Handset Cord/12 Ft./Gray, (M2000 Series) 1548
Handset Kit, Charcoal (M3905) 41, 206, 810, 1439
Handset Kit, Platinum (M3905) 41, 206, 810, 1439
Handset Module 1501, 1677
Handset, Charcoal (M3900 Series) 41, 206, 809, 1439
Handset, Modular 1548
Handset, Platinum (M3900 Series) 40, 206, 809, 1439
Handsets, BTS Style, Mercury Switch, Gray 1571
Handsets, BTS Style, Push-To-Mute, Ash 1571
Handsets, BTS Style, Push-To-Mute, Black 1571
Handsets, BTS Style, Push-To-Mute, Gray 1571
Handsets, BTS Style, Push-To-Talk, Ash 1571
Handsets, BTS Style, Push-To-Talk, Gray 1571
Handsets/BTS Style/Push-To-Talk/Black 1550
Handsfree Interface Kit 1500, 1676
Handsfree/Mute Key Caps 1652
Handsfree/Mute Key Caps Package (50/PK) 1557
Hard Drive Data Cable 41, 221, 853, 1445
Hard Drive for High Performance MRS/AP, Tower AP, and MRS/Tower 1624
Hard Drive for High Performance Rack AP and MRS/Rack 1624
Hard Drive Mounting Screw for Hot Swappable Drive (1000rp) Spare MRS/Rack or Rack AP 282, 1461
Hard Drive Power Cable 46, 223, 1143, 1481
HDLC Transparent Data 1621
Head Cleaner DAT Tape Spare 282, 970, 1461
Headset Interface Kit 1500, 1676
Headstart - Switch Configuration Package 435, 1376
Headstart - Verification Package 430, 1374
Headstart Pre-Installation Package 435, 1376
High Density PE Shelf 1508, 1684, 1685
High Performance MRS/AP (700TP), 0 Port, Global 1625
High Performance MRS/Rack, AC, 0 Port, Global 1625
High Performance MRS/Rack, DC, 0 Port, Global 1625
High Performance MRS/Tower, 0 Port - Global 1625
High Performance Rack AP, AC, Global 1625
High Performance Rack AP, DC, Global 1625
High Performance Tower AP (700TP), 0 Port - Global 1625
High Reliability Package (Generic 309/311) 1525
High Speed Data Card (2 Port) 1506, 1683
High Speed Data Module (HSDM) 110V Power Supply 1501, 1677
High Speed Data Module User Guide (15/PK) 352, 1482

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Hinged Door Kit 1642
Hold Down Device 1547
Hold in Queue for IVR 101, 112, 124, 133, 140, 147, 1244, 1515
Hold Key Cap Package (15/PK) 207, 401, 1368
Hold Key Caps 1652
Hook Switch Assembly (SL-1 Set) 1640
Horizontal Jumper 1587
Hospitality Screen Enhancements 97, 107, 119, 130, 138, 146, 153, 1212, 1513
Hospitality Voice Services 98, 108, 120, 131, 139, 147, 1222, 1514
Hospitality Voice Services Documentation 1607
Hospitality Voice Services Software 256, 1253, 1516, 1700
Hospitality Voice Services Software, Release 11 1700
Hospitality/Healthcare Features 152, 1208, 1513
Host Connectivity Hardware - Ethernet Adapter Kit (For TN3270 or TN5250 Option) 277, 941, 1456
Host Connectivity Hardware - SDLC Adapter Kit (For SNA3270 or SNA5250 Option) 277, 292, 295, 941, 1456
Host Connectivity Hardware - Serial Adapter Base Kit (For VT100 Option) 277, 292, 942, 1456
Host Connectivity Hardware - Serial Adapter Expansion Kit (For VT100 Option) 277, 292, 942, 1456
Host Connectivity Hardware - Token Ring Adapter Kit (For SNA3270 or SNA5250 Option) 277, 292, 941, 1456
Host Connectivity Software - SNA3270 - 16 Session RTU Expansion 277, 292, 943, 1456
Host Connectivity Software - SNA3270 - Base and 16 Session RTU 277, 292, 942, 1456
Host Connectivity Software - SNA5250 - 16 Session RTU Expansion 278, 292, 944, 1457
Host Connectivity Software - SNA5250 - Base and 16 Session RTU 278, 292, 944, 1457
Host Connectivity Software - TN3270 - 16 Session RTU Expansion 278, 943, 1456
Host Connectivity Software - TN3270 - Base and 16 Session RTU 277, 942, 1456
Host Connectivity Software - TN5250 - 16 Session RTU Expansion 278, 944, 1457
Host Connectivity Software - TN5250 - Base and 16 Session RTU 278, 944, 1457
Host Connectivity Software - VT100 - 16 Session Base RTU 43, 278, 292, 943, 1457
Host Connectivity Software - VT100 - 16 Session RTU Expansion 43, 278, 943, 1457
Host Enhanced Voice Processing Cable Kit 327, 446, 1378
Hot Line Key Cap Package (50/PK) 206, 394, 1368
Hotel/Motel Package (Basic) (LE) 1529
Hotel/Motel Package (Basic) (MS, M) 1529
Hotel/Motel Package (Basic) (S) 1534
Hotel/Motel Package (Basic) (VLE, XL) 1529
Hot-Swap Fan Assembly 38, 220, 424, 1373
HP 700/22 Terminal - Amber 1553
HP DeskJet (Lower Cost Alternative to LaserJet II for Text and Graphics 1554
HP DeskJet 500 Printer 1556
HP LaserJet 4M Series IV Printer 1556
HP LaserJet IV Series IV Printer 1556
HP LaserJet Series II Printer (High Resolution, Publication Quality Text 1554
HP LaserJet Series III Printer (High Resolution, Publication Quality, 1555
HP PaintJet 1554
HP RuggedWriter Printer 1553
HP Terminal 1584
HP ThinkJet Printer 1550, 1557, 1584, 1638
HP Vectra Basic System 1609
HP Vectra-Single Tower 1609
HP700/32 Terminal - Amber 1555
HP7970 CDR Tape Unit 1382, 1567
HVS Hardware Package 239, 490, 1381
Hybrids Kit 183, 553, 1402

I

I/O Cable 1582, 1600
I/O Cable (31 In.) 1592
I/O Cable (33 In.) 1591
I/O Cable (40 In.) 1592
I/O Cable (42 In.) 1592
I/O Cable (9 In.) 1595
IBM 3270/BSC Emulation-32 (BSC100) 1550
IBM 3270/BSC Emulation-64 (BSC101) 1550
IBM 3270/SNA Emulation-16 (SNA103) 1550
IBM 3270/SNA Emulation-32 (SNA100) 1550
IBM 3270/SNA Emulation-64 (SNA101) 1550
IBM 3270/SNA Emulation-96 (SNA102) 1550
IBM 3270/SNA File Transfer Upgrade (SNA105) 1551
IBM PC Network Software 1550
IBM Token Ring Software 1550
IDE Cable to CD ROM 40, 223, 1377
IDE Cable to CD ROM 702t/1001rp 223, 1373
IDE CD-ROM Drive 42, 222, 304, 858, 1447
Ide@Room 100 User IDs Upgrade 1610
Ide@Room 500 User ID Upgrade 1610
Ide@Room INSTALL PREP (Hardware and Software) 1694
Ide@Room INSTALL PRO (Hardware and Software) 1694
Ide@Room On-Site Service (Hardware and Software) 1694

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Ide@Room Software and Hardware Bundle including 100 User IDs, a Windows NT Server and 12 Port MICB Card 1610
Ide@Room Software and Hardware Bundle including 300 User IDs, a Windows NT Server and 24 Port MICB Card 1610
Ide@Room Software and Hardware Bundle including 500 User IDs, a Windows NT Server and 32 Port MICB Card 1610
Ide@Room Software Only INSTALL PREP 1695
Ide@Room Software Only INSTALL PRO 1695
Ide@Room Software Only Telephone Support 1695
Ide@Room Software with 100 User IDs 1610
Ide@Room Software with 50 User IDs 1610
Ide@Room Telephone Support (Hardware and Software) 1695
IIVR 2.2 Fax Card Spare 295, 929, 1455
IIVR 2.2 Fax Response Hardware - 4 ports 293, 925, 1454
IIVR 2.2 Fax Response Software Base Package - 2 ports 293, 925, 1454
IIVR 2.2 Fax Response Software Expansion - 1 port 293, 926, 1454
IIVR 2.2 Memory Package - 64MB 1624
IIVR 2.2 Runtime to Development Upgrade Base Package - 4 ports 291, 924, 1454
IIVR 2.2 Runtime to Development Upgrade Expansion - 4 ports 291, 924, 1454
IIVR 2.2 Software Media 295, 927, 1454
IIVR 2.2 Supplementary Patch CD 294, 927, 1454
IIVR 2.2 Update Documentation Package 295, 930, 1455
IIVR 2.2 UPS Package 293, 926, 1454
IIVR 2.2 Voice Port Expansion - 4 ports - Development System 291, 923, 1454
IIVR 2.2 Voice Port Expansion - 4 ports - Runtime System 291, 924, 1454
Immediate Key Cap Package (50/PK) 1557
IMS Multi-Attendant (Omninote software) 1530
IMS Single Attendant (Omninote software) 1530
IMS/Omnifacts Standard Configuration 1527
In-Bound Call Management Service 97 1705
In-Calls Key Cap Package (50/PK) 207, 398, 1368
Increment the Option 11C RAN Connections ISM parameter by 1 63, 74, 891, 1450
Infolink Cable 1582
InfoLink Interface 1384, 1571
Information Card Gray/M2009 1645
Information Card/Ash/M2009 1645
Information Window 1645
In-House Software Conversion Fee 156, 1184, 1510
Inmac 328 Adapter 1570
INMAC Null Modem 1548
Input Bus Bar Assembly for J2412A-1 Cabinet 1566
Input Jumper 1587
Input/Output Drive Unit with CD-ROM 1402, 1590
Input/Output Guide X11 Release 1-16 NTP 1653
Input/Output Processor Card (IOP) 1407, 1596
Insert 1640
Installation and Maintenance Guide 1655
Installation and Maintenance NTP 1653
Installation Diskette 308, 1465
Installation Flowchart and Worksheets - Part 1 (English) 37, 229, 1498
Installation Guide 353, 1485, 1649, 1655, 1656, 1658
Installation Guide (Coil) 1665
Installation NTP 1643, 1644, 1646, 1647, 1649
Installation Reference Guide 1655
Installation Upgrade for Meridian MAX 3, 4, 4.6 & 5 Systems (to Release 6) 321, 353, 1487
Installation Upgrade for Visit Messenger 1.0 /1.1 to Visit Messenger 2.0 1694
INSTFAST 1569
Insulating Washer Kit 197, 613, 1416
Integrated CPU/12MB Memory Card 1442, 1622
Integrated CPU/6 Mbyte Memory Card 1442, 1622
Integrated IVR 2.2 Memory Package 32 MB 294, 926, 1454
Integrated Service Digital Line Card (ISDLC) 26, 1505, 1681
Integrated Services Access 1690, 1691, 1692
Integration Package for Meridian Link - 4 Port Expansion RTU 281, 961, 1459
Integration Package for Meridian Link - Media (CD) and 4 Port Base RTU 281, 961, 1459
Integration Package for Meridian Link (SCCS Version) - 4 Port Expansion RTU 278, 962, 1459
Integration Package for Meridian Link (SCCS Version) - Base and 4 Port RTU 278, 962, 1459
Integration Package for Meridian Link (SCCS Version) User Guide 286, 1460
Integration Package for Nortel TAPI Server - 4 Port Expansion RTU 1625
Integration Package for Nortel TAPI Server - Media (CD) and 4 Port Base RTU 1625
Intelligent OPS Line Card 64, 177, 515, 1389, 1575
Intelligent Peripheral Equipment Cardcage (AC/DC) 184, 605, 1415
Intelligent Peripheral Equipment Module AC 184, 605, 1415, 1604
Intelligent Peripheral Equipment Module DC 184, 605, 1415, 1604
Intelligent Peripheral Equipment Module Package AC 159, 447, 1378
Intelligent Peripheral Equipment Module Package DC 159, 447, 1378
Inter Group Module 184, 604, 1415

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Inter-Cabinet Cable (13 Ft.) 1622
Inter-Cabinet Cable (16 Ft.) 1622
Inter-Cabinet Clock Cable (16 Ft.) 194, 827, 1443
Inter-Cabinet Clock Reference Cable 188, 515, 1388
Inter-Cabinet Network Cable (12 Ft.) 190, 192, 615, 630, 1417, 1419
Inter-Cabinet Network Cable (20 Ft.) 190, 192, 615, 630, 1417, 1419
Inter-Cabinet Network Cable (22 Ft.) 194, 827, 1443
Inter-Cabinet Network Cable (30 Ft.) 190, 192, 615, 630, 1417, 1419
Inter-Cabinet Network Cable (38 Ft.) 192, 1419
Inter-Cabinet Network Cable (6 Ft.) 190, 192, 615, 629, 1417, 1419
Intercom Key Cap Package (50/PK) 1557
Interconnect Cable 268, 578, 1408
Inter-Exchange Carrier 1697
Inter-Exchange Carrier/In-Band ANI 153, 1247, 1516
Interface 1504, 1681
Interface Connector Bracket 1647
Interface Pack 1501, 1677
Interflow Key Cap Package (50/PK) 1556
Intergroup Switch 1503, 1679
Intergroup Switch to Intergroup Module Cable (10 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (12 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (16 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (20 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (25 Ft.) 1605
Intergroup Switch to Intergroup Module Cable (4 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (6 Ft.) 1604
Intergroup Switch to Intergroup Module Cable (8 Ft.) 1604
Internet Registration Kit 198, 883, 1449
Internet Software Download Guide 1667
Internet Telephone Software Parameter (Large System) 34, 58, 62, 157, 1058, 1470
Internet Telephone Software Parameter (Small System) 34, 58, 62, 157, 1058, 1470
Intra-Cabinet Network Cable (12 Ft.) 192, 681, 682, 1425
Intra-Cabinet Network Cable (14 Ft.) 192, 681, 682, 1425
Intra-Cabinet Network Cable (16 Ft.) 192, 681, 682, 1425
Intra-Cabinet Network Cable (40 In.) 192, 193, 680, 681, 682, 683, 1425
Intra-Cabinet Network Cable (70 In.) 192, 193, 681, 682, 683, 1425
Intra-Cabinet Network Cable (85 In.) 192, 193, 681, 682, 683, 1425
Introduction to Meridian Mail Presentation 350, 1383
IODU/C Pack 185, 554, 1402
IODU/C Reference Guide 1668, 1669
IOP to I/O Panel Ethernet Cable 1600
IOP to I/O Panel Ethernet Cable (42 in./1m) 189, 597, 1412
IOP to IOP SCSI Cable (6 Ft.) 194, 825, 1442, 1622
IOP/CMDU Card 1402, 1590
IP Line Card, Spare 178, 1419
IP Line Card-Base Card 1606
IP Line Card-Spare 1419, 1606
IP Telecommuter System Package 182, 1056, 1470
IPE CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit 36, 226, 1118, 1475
IPE Cardcage Expansion Kit 1576
IPE Cardcage Expansion Kit (AC) 183, 518, 1389
IPE Cardcage Expansion Kit (DC) 183, 518, 1389
IPE/IPEE Option 11 to Option 21-81C Conversion Kit 316, 796, 1436
IPE/IPEE Option 21-81C to Option 11 Conversion Kit 316, 796, 1437
IPEE 1GB Hard Drive Repair Kit 326, 430, 1374
ISA Token Ring Network Card 1623
ISA Token Ring Network Card Spare 1626
ISDN AP Brochure 1650
ISDN Basic Rate Interface 1662, 1663, 1664, 1665
ISDN basic rate interface 1667
ISDN Basic Rate Interface Guide NTP 1657, 1658
ISDN Basic Rate Interface NTP 1659, 1660
ISDN Basic Rate Interface, Release 24 and Earlier 348, 1494
ISDN Cable 335, 1431
ISDN Networking 98, 107, 119, 131, 139, 146, 1217, 1218, 1513
ISDN Networking Solutions Brochure 367, 1486
ISDN Primary Rate Access Brochure 1648
ISDN Q.Sig Supplementary Services 99, 108, 120, 131, 1234, 1515
ISDN Signaling Link 153, 1247, 1516
ISDN Signaling Link Brochure 367, 1486
ISDN Signaling Link Sales Feature Sheet 1650
ISDN, Ethernet & Admin Cables 334, 1443
ISDN/AP Pass Through Service 95 1705
Italian Prompt - Bilingual 1701
Italian Prompt - Unilingual 1701
ITG 2.0 Pre-programmed Q.SIG D-Channel Interface PCMCIA Card 180, 983, 1463
IVMS Link 154, 1249, 1516
IVR 2.0 Application Development Software 1704
IVR Development Documentation Package 295, 537,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1398
IVR Generator Digital Prompt Tool Guide 1668
IVR Operational Documentation Package 295, 536, 1398

J

J0000110 1569
J0000240 1569
J0000241 1569
J0000242 1569
J0000243 1569
J2412AA-1 Control Panel for J2412A-1 Cabinet 1382, 1567
Japanese Prompt - Bilingual 1701
Japanese Prompt - Unilingual 1701
Journal Administration and User Guide 61, 1493
Journal Call Accounting Software with Billing 61, 63, 802, 1437
Journal Rate Table (Update) 61, 1163, 1493
Journal User Guide 1667
Journal/Registrar Software CDROM Up-Issue 61, 802, 1437
Jumper Pins 1546
Jumpers (8/PK) (M2000 Series) 209, 381, 1364
Junction Assembly 1640, 1641
Junction Box 1596
Junction Box QBL15 187, 1174, 1500, 1675
Junction End 1640
Junction Side 1640
Junctor Board 183, 1503, 1679
Junctor to I/O Housing Cable (6 Ft.) 195, 828, 1443

K

Kermit File Transfer (HA102) 1550
Key and Lock Master 273, 284, 305, 408, 1370
Key Cap Package 1645
Key Cap Package (M3905) 208, 808, 1439
Key Cap Tool (M3905) 209, 810, 1439
Key Cap, Green with Clear Window (1 each, Standard for all Meridian) 1645
Key Cap, Orange with Clear Window (1 each, Standard for all Meridian) 208, 1143, 1481
Key Cap, Red with Clear Window (1 each, Standard for all Meridian) 208, 1146, 1482
Key Caps, Green 208, 1482
Key Expansion Module Cable, (M2000 Series) 209, 527, 1391, 1560
Key-based Expansion Module Kit 1, Charcoal 200, 815, 1440
Key-based Expansion Module Kit 1, Platinum 200, 815, 1440
Key-based Expansion Module Kit 2, Charcoal 201, 816, 1440
Key-based Expansion Module Kit 2, Platinum 200, 816, 1440
Key-based Expansion Module Without Footstand, Charcoal 200, 815, 1440
Key-based Expansion Module Without Footstand, Platinum 200, 1440
Keyboard 273, 283, 1370
Keyboard (QCW3) 1502, 1678
Keyboard (QCW3/QCW4) 1502, 1678
Keyboard and Mouse for Base MRS/Tower 277, 937, 1456
Keyboard Pack 1503, 1679
Keyboard with Dial Pad, (QCW3/QCW4) 182, 1502, 1678
Keyboard/Monitor/Mouse Cable, Switch Box-to-Peripherals 283, 1462
Keycode 1665
Keylock 276, 931, 1455
Keylock Software Security Device 294, 394, 1367
Kit Extension (Back to Back) 1640
Kit Extension (Basic) 1640
Kit Extension (Front, Rear & Junction) 1640
Kit Extension (Junction Corner) 1640
Kit, Wall Mount 1574
Kit, Wall Mount (Single Basic or Display Set) 1639
Korean Prompt - Bilingual 1701
Korean Prompt - Unilingual 1701

L

L or LE/N CE Cabinet Expansion Assembly 1528
L or LE/N CE Shelf Expansion Assembly 1528
L(Dual CPU)/LE(Dual CPU) Upgrade Assembly 1527
L(Single CPU)/LE(Dual CPU) Upgrade Assembly 1527
L/LE Upgrade Assembly (Single CPU/Half Network Group) 1527
L/N Cabinet Upgrade Assembly (Dual CPU) 1542
L/N Cabinet Upgrade Assembly (Single CPU) 1542
Label Kit 1558
Label Kit for Inter-Cabinet Cables 199, 1151, 1484
Lamp Field Array (BLF) 1501, 1677
LAN 100 4 Stack Cabinet Package 1639
LAN 100 8 Stack Cabinet Package 1639
LAN 100 Base Hub Package 1639
LAN 100 Hub Expansion Package 1639
LAN Driver Documentation Set (DA256-00) 1552
LAN Interface Unit 1587
LAN MSNET 1648
Lan NDP and Installation Guide 1648

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Lan Reference Manual - Small Cabinet 1648
LAN Transceiver 327, 391, 1367
LANLink Assembly 1638
LANLink Assembly (NT0R23AB, NT0R25AB) 1383, 1571
LanLink Assembly (NT0R23AB, NT0R25AB) 1383, 1571
LANLink I/o Cable 1582
LANlink Interface Card 1383, 1571
LAN-Pak 1542
LANSTAR 1000 Sales Flyer 1653
LANSTAR 16 Kit 1406, 1595
Lanstar 3270 Protocol Converter Technical Specifications 1644
LANSTAR 8 Kit 1398, 1582
LANSTAR Appletalk Bridge (User Guide Included) 1649
Lanstar Appletalk User Guide 2.0 1648
LANSTAR Application Brief 1654
LANSTAR ASIM Technical Specification 1644
LANSTAR Blower 1405, 1591
Lanstar Cabinet Package (Full Shelf) 1638
Lanstar Cabinet Package (Half Shelf) 1638
Lanstar Compat. Guidelines User Guide 1646
Lanstar Data Ser. Reference Guide/Directory 1647
Lanstar Data Service Reference Guide/Directions 1647
LANSTAR Interface Card Flyer 1653
LANSTAR MAC SCSI Flyer 1653
LANSTAR MSNET 1533
LANSTAR NetWare Driver 1650
LANSTAR PC - Adapter/BANYAN Interface Software (Version 2.11) 1551
LANSTAR PC - Adapter/BANYAN Interface Software (Version 3.01) 1553
Lanstar PC Product Sales Guide 1647
Lanstar PC Terminal Emulator Guide 1646
LANSTAR Presentation Folder 1654
LANSTAR PS/2 MC Adapter Card 1398, 1399, 1584, 1587
LANSTAR Slide Presentation 1654
Lanstar Slide Presentation 1651
LANSTAR/4 Stack Assembly 1595
LANSTAR/8 Stack Assembly 1595
LANSTAR/LAN 100 (60 In.) Cabinet 1595
Large Keypad Template 229, 1497
Last Number Redial Key Cap Package (50/PK) 207, 400, 1368
Latin American Spanish Prompt - Bilingual 1701
Latin American Spanish Prompt - Unilingual 1701, 1702
LE/N Cabinet Upgrade Assembly (Dual CPU) 1528
LE/N Cabinet Upgrade Assembly (Single CPU) 1528
LE/N Shelf Upgrade Assembly (Dual CPU) 1528
LE/N Shelf Upgrade Assembly (Single CPU) 1528
LE/NT Full Network Group Cabinet Upgrade 1714
LE/NT Half Network Group Cabinet Upgrade 1714
LED Assembly (Console) Single Strip (Row A, B, C & G) 1640
LED Assembly (Console) Single Strip (Row D & E) 1640
LED Assembly (Console) Single Strip (Row F) 1640
Left Door Panel Assembly 1645
Left Front Panel Assembly 1639
Left Mounting Bracket 1643
Left Side Panel 1645
Legacy Handset, Ash (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S) 206, 500, 1383
Legacy Handset, Ash (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1) 206, 501, 1383
Legacy Handset, Ash (NT2K models M2006, M2008, M2616, M2216ACD-1) 1570
Legacy Handset, Black (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S) 206, 500, 1383
Legacy Handset, Black (NT2K & NT9K Models M2006, M2008, M2616, M2216ACD-1) 206, 501, 1383
Legacy Handset, Black (NT2K models M2006, M2008, M2616, M2216ACD-1 1570
Legacy Handset, Gray (M2250 and NTZK Models M2006, M2008, M2616, M2216ACD-1, M2016S) 206, 500, 1383
Legacy Handset, Gray (NT2K & NT9K Models M2006, M2008, M2616, M2216 ACD-1) 206, 501, 1383
Legacy Handset, Gray (NT2K models M2006, M2008, M2616, M2216 ACD-1 1570
Legacy Module for APM, 1 Server/100 Seats 331, 990, 1464
Legacy Module for APM, 10 Servers/1000 Seats 331, 990, 1464
Legacy Module for APM, 100 Servers/5000 Seats 331, 990, 1464
Legacy Module for APM, 25 Servers/2500 Seats 331, 990, 1464
Legacy Module for APM, 250 Servers/10000 Seats 331, 991, 1464
Legacy Module for APM, 500 Servers/25000 Seats 331, 991, 1464
Legacy Module for APM, Custom Configuration 331, 991, 1464
Legacy Module for APM, Unlimited Configuration 331, 991, 1464
Lens, Line Designation 1645
Liberation 3-in-1 Direct Connect Headset (Unamplified) 1611

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Liberation AC Adapter for MPA 1555
Liberation CLASSIC, Binaural UNC, Headband (All Amplifier Models) 1556
Liberation CLASSIC, Monaural, Earhook (All Amplifier Models) 1555
Liberation CLASSIC, Monaural, Earloop (All Amplifier Models) 1555
Liberation CLASSIC, Monaural, Headband (All Amplifier Models) 1555
Liberation CTI Headset 1611
Liberation DIRECT for Norstar, Binaural UNC 1556
Liberation DURA PLUS, Binaural NC, Headband (All Amplifier Models) 1559
Liberation DURA PLUS, Monaural NC, Headband (All Amplifier Models) 1559
Liberation Earhook Conversion Kit 1555
Liberation Earloop Conversion Kit 1555
Liberation Earpiece Foam Cushion (Pack of 10) 1555
Liberation FLEX, Binaural NC, Headband (All Amplifier Models) 1560
Liberation FLEX, Monaural NC, 3 in 1 (All Amplifier Models) 1560
Liberation Flexible Earhook Conversion Kit 1561
Liberation Headband Conversion Kit 1555
Liberation Headset Conversion Kit 1555
Liberation Headset Cord Clothing Clip 1556
Liberation Headset Extension Cord, 10 Ft. (QD to QD) 1555
Liberation Headset Flyer 1657
Liberation Headset Modular Electret-Earloop, Monaural 1555
Liberation Headset Modular Electret-Headband, Monaural 1555
Liberation Headset PJ327 Carbon-Earhook, Monaural 1555
Liberation Headset PJ327 Carbon-Earloop, Monaural 1555
Liberation Headset PJ327 Carbon-Headband, Binaural 1556
Liberation Headset PJ327 Carbon-Headband, Monaural 1555
Liberation Headset, Modular Electret-Earhook, Monaural 1555
Liberation In-Line Amplifier with Mute (M2250, M1250, M2216ACD-2) 1655
Liberation Multi-Purpose Amplifier (MPA) 1555
Liberation Multi-Purpose Amplifier II (MPAII) 1611
Liberation On-Line Indicator for MPAII 1558
Liberation PERFORMA, Binaural NC, Headband (All Amplifier Models) 1560
Liberation PERFORMA, Monaural NC, Headband (All Amplifier Models) 1560
Liberation Replacement Bottom Cord for MPA/MPAII 1718
Liberation Sales Flyer 1556
Liberation Training Video 1556
Liberation Unamplified Bottom Cord 1669
Liberation Voyager 3-in-1 Headset (M2616CT) 1611
Liberation Wireless Amplifier (with Base Station) 1559
Liberation Wireless Amplifier Replacement Battery Pack 1611
Library Navigator 349, 1498, 1661, 1663, 1664, 1665, 1667
Library Navigator NTP 1661
Library Navigator, Release 24 and Earlier 348, 1494
License File 276, 931, 1455
Light Gray UEM Overlay Kit 199, 1496
Light Probe Kit 1676
Line Card Configuration Guide 1617
Line Cord (7 Ft.) 1547
Line Cord (Silver) (13 Ft.) Spade/Spade (6 Conductor) 1546
Line Cord/2-Conductor /7 Ft./Satin/Standard (M2000 Series and M3901) 1547
Line Cord/2-Conductor/14 Ft./Satin, (M2000 Series and M3901) 1547
Line Load Control 97, 107, 119, 130, 138, 146, 153, 1209, 1213, 1513
Line Side T1 Support - RTU For 24 Port T1 - Spanish 278, 948, 1457
Line-side T1 Interface Assembly (11) 176, 473, 1379
Line-side T1 Interface Assembly (21-81) 176, 472, 1379
Line-Side T1 Interface Cable 177, 552, 1402
Line-Side T1 Interface Card 177, 551, 1401, 1402, 1589
Line-side T1 Interface Card (Option 11) 1402, 1589
Line-Side T1 Interface Card (Option 11/11E/11C) 66, 177, 552, 1402, 1589
Line-Side T1 Interface Card Description, Installation and Maintenance 66, 182, 1488, 1670
Line-Side T1 Interface NTP (Standalone) 1663
Link O, A&M Service 1 1705
Literature Pack 1651, 1652
Literature Pack (M2006, M2008) 207, 1369, 1582
Literature Pack (M2018) 1647
Literature Pack (M2112) 1647
Literature Pack (M2216-ACD 1/2) 207, 1397, 1557
Literature Pack (M2317) 208, 1481
Literature Pack (M2616, M2016S) 207, 1397, 1582
Literature Pack SL-1 Basic 1553
Literature Pack/M2000 1647
Local Carrier Buffer (RPE) 1505, 1681
Local Carrier Interface Card 178, 598, 1412, 1601, 1602
Local Carrier Shelf Assembly 1541
Local Carrier/Monitor Cable Assembly 160, 598, 1413

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Local External Maintenance Cable Assembly 160, 598, 1413
Local Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops) 160, 461, 1379
Local Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops) 160, 464, 1379
Local fiber Multi-IPE Assembly - Single Mode (1-2 Superloops) 160, 460, 1379
Local Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops) 160, 462, 1379
Local Fiber Multi-IPE Interface Cable (30 Ft.) 187, 405, 1370
Local Maintenance/Clock Cable Assembly 160, 598, 1413
Local Mini Carrier Extender Cable 66, 183, 555, 1403
Local Mini Carrier Extender Card (Option 11) 66, 177, 555, 1403, 1590
Local Mini Carrier Extender Card (Options 21-81) 177, 554, 1403, 1590
Local Mini Carrier Interface Cable 66, 183, 1403
Local Mini Carrier Interface Card (Option 11) 66, 177, 1403, 1590
Local Mini Carrier Interface Card (Options 21-81) 177, 1403, 1590
Local Network Interface Assembly 1540
Local RPE/PE Expansion Assembly (with MDF Assembly) 1544
Lock Washer 1639
Lodging Firmware Cartridge 1366, 1551
Loop Conversion Fee 1185, 1510
Loop Signaling Trunk 1503, 1506, 1680, 1682
Loops Requiring Conversion/Balancing 1184, 1510
LSPC Cabinet Package 1638
LSPC Hardware Package 1638
LSPC Terminal Emulator 1533
Lug Kit, Crimp-Type #8 1655
Lug Kit, Screw-Type #8 186, 1150, 1483
LVD Kit 1664

M

M/M Wide-Nar SCSI Adapter 38, 221, 304, 1374
M/MS CE Upgrade Assembly 1544
M/MS/L/LE/NT Cabinet Upgrade Assembly 1714
M1109 Compact Telephone, Ash 1508, 1685
M1109 Compact Telephone, Gray 1508, 1686
M1250 Meridian SL-1 Attendant Console 1541
M1250/M2250 Attendant Administration User Guide (5/PK) 352, 1482
M1250/M2250 Attendant Console Guide 1655
M1250/M2250 Attendant Console Quick Reference Card 1655
M1250/M2250 Attendant Console Quick Reference Card (25/PK) 352, 1484
M1250/M2250 Attendant Console User Guide 1654
M1250/M2250 Attendant Console User Guide (1/PK) 1662
M1250/M2250 Attendant Console User Guide (5/PK) 1656
M1250/M2250 Attendant Line Cord 209, 1419, 1550, 1558
M2000 Mac Pak 1542
M2000 Series Telephones User Guide (15/PK) 1646
M2000/3000 Telephone Data Option User Guide (15/PK) 1646
M2006/M2008/M2008HF & M2616 Digital Telephone Product Brief 365, 1484
M2216 ACD Telephone Quick Reference Card (100/PK) 1652
M2216 ACD Telephone User Guide (15/PK) 1652
M2216 ACD Telephone User Guide (Package of 15 P0902629) 350, 451, 1378
M2216 Quick Reference Card (100/PK) 1660
M2216 User Guide (15/PK) 1660, 1667
M2216 User Guide (Package of 15 P0859507) 1590
M2216 User Guide (Pk of 15 P0831877) 1590
M2216ACD Telephone Product Brief 366, 1484
M2216ACD Telephone User Guide (English) (Package of 15 P0902629) 351, 1403
M2250 Attendant Console 204, 577, 1408, 1597
M2250 Attendant Supervisory Module 209, 597, 1412
M2317 Telephone Quick Reference Card (100/PK) 352, 1481
M2317 Telephone User Guide (15/PK) 350, 353, 451, 1378, 1487, 1647, 1660
M3000 Directory Archiver 1367, 1555
M3000 Mac Pak 1542
M3000 Touchphone User Guide 1646, 1656, 1662
M3000 Touchphone User Guide (15/PK) 1658, 1660
M3900 Series Accessories Product Brief 366, 1497
M3900 Series Meridian Digital Telephones Brochure 366, 1497
M3901, M3902, M3903 Meridian Digital Telephones Product Brief 366, 1497
M3904 Professional Meridian Digital Telephone Product Brief 366, 1497
M3905 Call Center Meridian Digital Telephone Product Brief 366, 1497
M4020 1569
M4020 Terminal 1569
M5000TD-1 Release 2 User Guide 1658
M5000TD-1 Terminal Adapter Release 2 1569
M5000TD-1 V.35 Connector 1556
M5317TDX TSDN BRI Telephone Flyer 1658
M5317TDX, Ash, Release 2 1569

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

M5317TDX, Black, Release 2 1569
M5317TX, Ash, Release 2 1569
M5317TX, Black, Release 2 1569
M7000 Memory Expansion Module 1366, 1551
Mac Direct-Connect Pak 1542
Mac SCSI Kit 1406, 1595
MacIntosh II Interface Card and Cable 1384, 1571
MacVINES Mail Gateway (MAC100) 1554
MacVines Mail Gateway Administrators Guide (10/PK) (DA232) 1554
MacVines Mail Gateway Users Guide (DA233) 1554
Magnetic Tape (CDR) 1567
Magnus 2.5GB Data Cartridge 239, 249, 267, 272, 283, 403, 1369
Main Cabinet Cable Kit 67, 179, 712, 1432
Main Fiber Interface (MFI) Kit 67, 193, 703, 1430, 1615
Main Power Bay Assembly 1562
Main/Expansion Cabinet 67, 197, 694, 1427, 1432, 1616
Maintenance and Diagnostic Guide - French 1670
Maintenance Extender Cable 193, 692, 1426
Maintenance Interface Cable 188, 432, 1375, 1558
Maintenance Messages (SEERs) - MM13 349, 1496
Maintenance NTP 1644, 1646, 1647, 1649
Make Set Busy Key Cap Package (50/PK) 207, 400, 1368
Making the Most of Voice Mail Brochure 372, 1486
Mandarin Prompt - Bilingual 1701
Mandarin Prompt - Unilingual 1701
Marketing Package DMS SYMPOSIUM Call Center Server, New System 34, 303, 1060, 1471
Marketing Package DMS SYMPOSIUM Call Center Server, Spare System 34, 1060, 1471
Marketing Package DMS SYMPOSIUM Call Center Server, Upgrade System 34, 1060, 1471
Marketing Package Symposium Call Center Server, NCC 302, 1059, 1471
Marketing Package Symposium Call Center Server, New System 302, 1059, 1470
Marketing Package Symposium Call Center Server, Spare System 302, 1471
Marketing Package Symposium Call Center Server, Upgrade System 302, 1059, 1471
Marketing Package, SCCS NCC (Network Control Center) Release 3.0 Software 298, 1064, 1471
MAS - Model 500 Serial Card Kit 25, 1591
MAS 486/33 Access port upgrade for Visit Messenger 1.1 and Visit Assistant 1.0 1628
MAS Installation and Maintenance Guide 271, 1491
MAS Model 500 2GB Hard Drive Option 270, 976, 1462
MAS Model 501 2GB Hard Drive Option 270, 976, 1462
MAS Model 501 Server 26, 1628
MAS Model 501 Spares Kit 271, 979, 1462
MAS Post Warranty Premium Service 271, 1187, 1510
MAS Post Warranty Service 271, 1186, 1510
MAS Premium Warranty Upgrade 271, 1186, 1510
Extended Telephone Support 271, 1186, 1510
MAS Server Installation and Setup 26, 1694
MASI Assembly 1383, 1571
MAS-Model 100 Spares Kit 271, 343, 978, 1462
MAS-Model 500 Spares Package 271, 343, 979, 1462
Mass Storage 234 Assembly 1638
Mass Storage Assembly 1500, 1676
Mass Storage Interface Card 183, 1178, 1505, 1681
Mass Storage Unit 1673, 1674
Mass Storage Unit Assembly 1500, 1676
MAT 4 End User Single Site Package 1126, 1479
Mat 4 Multi Location Distribution Station Administration 1126, 1479
MAT 4 Single Location Distributor Station Administration 1125, 1479
MAT 4.x Buffer Box Reference Guide 353, 1489
MAT 4.x Call Accounting Base Upgrade 1635
MAT 4.x Call Accounting Expansion Cap 1635
MAT 4.x Call Accounting Large Expansion 1635
MAT 4.x Call Accounting Medium Expansion 1635
MAT 4.x Call Accounting Mini Expansion 1635
MAT 4.x Call Accounting Module Base 1635
MAT 4.x Call Accounting Small Expansion 1635
MAT 4.x Call Accounting User Guide 353, 1488
MAT 4.x Call Tracking Module 1635
MAT 4.x Call Tracking Upgrade 1635
MAT 4.x Call Tracking User Guide 353, 1488
MAT 4.x Common Services User Guide 351, 1419
MAT 4.x Distributor Multi Location Station Administration Upgrade 1635
MAT 4.x Distributor Single Location Station Administration Upgrade 1635
MAT 4.x End User Multi Site Package 1635
MAT 4.x End User Single Site Package 1635
MAT 4.x Multi Location Distribution Station Administration 1635
MAT 4.x Multi Site Common Services Upgrade 1635
MAT 4.x Multi Site Expansion 1635
MAT 4.x Multi Site Expansion Cap 1635
MAT 4.x North American Rate Table 1635
MAT 4.x Single Location Distributor Station Administration 1635
MAT 4.x Single Site Common Services Upgrade 1635
MAT 4.x Single to Multi Site Expansion 1635
MAT 4.x Station Administration Module 1635
MAT 4.x Station Administration Upgrade 1635

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MAT 4.x Station Administration User Guide 353, 1488
MAT 4.x Traffic Analysis Module 1635
MAT 4.x Traffic Analysis Upgrade 1635
MAT 4.x Traffic Analysis User Guide 353, 1488
MAT 5 Administration Marketing Bundle 1637
MAT 5 Alarm Management Module 1636
MAT 5 Alarm Management Upgrade 1637
MAT 5 Call Accounting Base Upgrade 1637
MAT 5 Call Accounting Expansion Cap License 1666, 1668
MAT 5 Call Accounting Expansion Cap License Upgrade 1666, 1668
MAT 5 Call Accounting Large Expansion License 1666, 1668
MAT 5 Call Accounting Large Expansion License Upgrade 1666, 1668
MAT 5 Call Accounting Medium Expansion License 1666, 1668
MAT 5 Call Accounting Medium Expansion License Upgrade 1666, 1668
MAT 5 Call Accounting Mini Expansion License 1666, 1668
MAT 5 Call Accounting Mini Expansion License Upgrade 1666, 1668
MAT 5 Call Accounting Module 1636
MAT 5 Call Accounting Small Expansion License 1666, 1668
MAT 5 Call Accounting Small Expansion License Upgrade 1666, 1668
MAT 5 Call Tracking Module 1636
MAT 5 Call Tracking Upgrade 1637
MAT 5 Diskettes 1637
MAT 5 Distributor Common Services 1636
MAT 5 Distributor Single Location Common Services and Station Upgrade 1637
MAT 5 End User Common Services 1636
MAT 5 End User Common Services Upgrade 1636
MAT 5 End User Five (5) Additional M1 System License 1666, 1668
MAT 5 End User Site Expansion Upgrade 1667, 1668
MAT 5 ESN Analysis and Reporting Tool Module 1636
MAT 5 ESN Analysis and Reporting Upgrade 1637
MAT 5 Maintenance Marketing Bundle 1637
MAT 5 Maintenance Windows Module 1636
MAT 5 Maintenance Windows Upgrade 1637
MAT 5 Station Administration Module 1636
MAT 5 Station Administration Upgrade 1636
MAT 5 System Management Marketing Bundle 1637
MAT 5 to 5.x Flat-fee Upgrade 1636, 1637
MAT 5 Traffic Analysis Module 1636
MAT 5 Traffic Analysis Upgrade 1636, 1637
MAT 5 User Guides Binder 350, 1373
MAT 5.7 Option 11C Compact - Update Disk Package 1622
MAT 5.x Alarm Management User Guide 354, 1490
MAT 5.x Call Accounting User Guide 354, 1491, 1666, 1667
MAT 5.x Call Tracking User Guide 354, 1490
MAT 5.x Common Services User Guide 354, 1491
MAT 5.x Common Services User Guide and Binder 1606
MAT 5.x ESN Analysis and Reporting Tool User Guide 354, 1490, 1667
MAT 5.x Maintenance Windows User Guide 354, 1491, 1666
MAT 5.x Station Administration User Guide 354, 1490
MAT 5.x to 6 Flat-fee Upgrade 1630
MAT 5.x Traffic Analysis User Guide 354, 1490, 1666
MAT 5/6 to MAT 6.X, Flat Fee Upgrade 339, 1034, 1468, 1630
MAT 6 Administration Marketing Bundle 339, 1032, 1468
MAT 6 Alarm Management Module 339, 1031, 1468
MAT 6 Call Accounting Base Upgrade 340, 1033, 1468
MAT 6 Call Accounting Expansion Cap License 339, 1160, 1492
MAT 6 Call Accounting Expansion Cap License Upgrade 340, 1162, 1492
MAT 6 Call Accounting Large Expansion License 339, 1160, 1492
MAT 6 Call Accounting Large Expansion License Upgrade 340, 1161, 1492
MAT 6 Call Accounting Medium Expansion License 339, 1160, 1492
MAT 6 Call Accounting Medium Expansion License Upgrade 340, 1161, 1492
MAT 6 Call Accounting Mini Expansion License 339, 1159, 1492
MAT 6 Call Accounting Mini Expansion License Upgrade 340, 1161, 1492
MAT 6 Call Accounting Module 339, 1030, 1467
MAT 6 Call Accounting Small Expansion License 339, 1159, 1492
MAT 6 Call Accounting Small Expansion License Upgrade 340, 1161, 1492
MAT 6 Call Tracking Module 339, 1029, 1467
MAT 6 Call Tracking Upgrade 340, 1033, 1468
MAT 6 Distributor Common Services 1629
MAT 6 Distributor Single Location Common Services and Station Upgrade 1629
MAT 6 End User Common Services 1629
MAT 6 End User Common Services Upgrade 1630
MAT 6 End User Five (5) Additional Meridian 1 System Licenses 339, 1159, 1492

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MAT 6 End User Site Expansion Upgrade 340, 1160, 1492
MAT 6 ESN Analysis and Reporting Tool Module 339, 1030, 1468
MAT 6 Maintenance Marketing Bundle 339, 1031, 1468
MAT 6 Maintenance Windows Module 339, 1030, 1468
MAT 6 Option 11C Compact Introduction Guide 60, 1495
MAT 6 Station Administration Module 339, 1028, 1467
MAT 6 Station Administration Upgrade 340, 1032, 1468
MAT 6 System Management Marketing Bundle 339, 1032, 1468
MAT 6 Traffic Analysis Module 339, 1029, 1467
MAT 6 Traffic Analysis Upgrade 340, 1033, 1468
MAT 6 User Guide Package 1669
MAT 6, Distributor Common Services 338, 1028, 1467, 1629
MAT 6, Distributor Single Location Common Services and Station Upgrade 340, 1033, 1468, 1629, 1630
MAT 6, End User Common Services 338, 1027, 1467, 1629
MAT 6, End User Common Services Upgrade 340, 1034, 1468, 1630
MAT 6, User Guide and CD Package 339, 1031, 1468, 1629
MAT 6.1 Compact Introduction Guide 1669
MAT Call Accounting Base Upgrade 341, 1137, 1480
MAT Call Accounting Expansion Cap 1133, 1480
MAT Call Accounting Large Expansion 1132, 1480
MAT Call Accounting Medium Expansion 341, 1132, 1480
MAT Call Accounting Mini Expansion 1133, 1480
MAT Call Accounting Module Base 1130, 1480
MAT Call Accounting Small Expansion 341, 1131, 1480
MAT Call Tracking Module 1130, 1480
MAT Call Tracking Upgrade 341, 1137, 1480
MAT Data Buffering and Access 97, 107, 1207, 1512
MAT Distributor Multi-Location Station Administration Upgrade 341, 1134, 1480
MAT Distributor Single Location Station Administration Upgrade 341, 1134, 1480
MAT End User Multi Site Package 1127, 1479
MAT Multi Site Common Services Upgrade 341, 1135, 1480
MAT Multi Site Expansion 1128, 1479
MAT Multi Site Expansion Cap 1128, 1479
MAT North American Sample Rate Table 1131, 1480
MAT PC Dongle to OTM Client Upgrade 338, 1453
MAT Single Site Common Services Upgrade 341, 1135, 1480
MAT Single to Multi Site Expansion 1127, 1479
MAT Station Administration Module 1129, 1480
MAT Station Administration Upgrade 341, 1136, 1480
MAT Traffic Analysis Module 1129, 1480
MAT Traffic Analysis Upgrade 341, 1136, 1480
MAX Release 5 Supervisor Reference Guide 1576
MAX Release 5 Supervisor User Guide 1659
MAXcaster Quick Reference Guide English 323, 354, 1489
MAXcaster Quick Reference Guide French 323, 354, 1490
MAXcaster Software and Documentation Package English 323, 534, 1398
MAXcaster Software and Documentation Package French 323, 534, 1398
MAXcaster User Guide English 323, 353, 1488, 1664
MAXcaster User Guide French 323, 353, 1488, 1664
MAX-IPE to IPEE Upgrade Kit #1 26, 1617
MAX-IPE to IPEE Upgrade Kit #2 316, 797, 1437
MCCS Power Supply (2nd power supply) 1611
MCDS - Asynchronous Card 1503, 1679
MDF 50 Pin Cable with Ethernet (25 Ft.) 328, 513, 1388
MDF 50 Pin Cable with Ethernet (45 Ft.) 328, 514, 1388
MDF 50 Pin Cable without Ethernet (10 Ft.) 328, 514, 1388
MDF 50 Pin Cable without Ethernet (25 Ft.) 328, 514, 1388
MDF Locking Bar Restraint Bracket 69, 198, 1483
MDR 2000 Buffer Box 128Kb (117vac/60Hz) 337, 340, 341, 1137, 1480
MDR 2000 Buffer Box 2 Mb (117vac/60Hz) 337, 340, 341, 1138, 1480
MDR 2000 Buffer Box 512Kb (117vac/60Hz) 337, 340, 341, 1138, 1480
Memory 2M 1383, 1570
Memory 6M 1571
Memory Controller 1502, 1678
Memory Shelf 1507, 1683
Memory Shelf (Center Mount) 1507, 1684
Memory Shelf (QCA55) 1508, 1685
Memory/Peripheral Signaling Card 1414, 1603
Meridian 1 ACD Feature Document - Release 21 360, 1488
Meridian 1 Attendant Hospitality Services 1 Console Bundle 45, 204, 1037, 1468

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Attendant Hospitality Services 1 Console Software Bundle 45, 204, 1039, 1469
Meridian 1 Attendant Hospitality Services 2 Console Bundle 204, 1037, 1468
Meridian 1 Attendant Hospitality Services 2 Console Software Bundle 204, 1039, 1469
Meridian 1 Attendant Hospitality Services 3 Console Bundle 45, 204, 1038, 1468
Meridian 1 Attendant Hospitality Services 3 Console Software Bundle 45, 204, 1039, 1469
Meridian 1 Attendant Hospitality Services Large (4) Console Bundle 45, 204, 1038, 1468
Meridian 1 Attendant Hospitality Services Large (4) Console Software Bundle 45, 204, 1039, 1469
Meridian 1 Attendant Hospitality Services Large Expansion Bundle 45, 204, 1038, 1468
Meridian 1 Attendant Hospitality Services Large Software Expansion Bundle 204, 1040, 1469
Meridian 1 Attendant Hospitality Services Software for Expansion from 1 to 2 Console Bundle 204, 1040, 1469
Meridian 1 Attendant Hospitality Services Software for Expansion from 2 to 3 Console Bundle 45, 204, 1040, 1469
Meridian 1 Attendant Hospitality Services Software for Expansion from 3 to 4 Console Bundle 45, 204, 1040, 1469
Meridian 1 Attendant PC 205, 1138, 1480
Meridian 1 Attendant PC Blank Brandline Insert (Package of 1) 210, 1488
Meridian 1 Attendant PC Brochure 364, 1492
Meridian 1 Attendant PC CD-ROM Sales Demo 1669
Meridian 1 Attendant PC Handset Cord with PJ-Type Plug 205, 1427, 1560
Meridian 1 Attendant PC LAN Interface Installation Guide 347, 1491
Meridian 1 Attendant PC LAN Interface Module 184, 205, 1139, 1480
Meridian 1 Attendant PC S/W Installation Guide 1668
Meridian 1 Attendant PC S/W Quick Start Guide 1668
Meridian 1 Attendant PC Software Installation Guide 348, 1495
Meridian 1 Attendant PC Software Quick Start Guide 348, 1495
Meridian 1 Attendant PC Software Tutorial 209, 1374
Meridian 1 Attendant PC Software User Guide 348, 1495, 1668
Meridian 1 Attendant PC Unit Installation Guide 347, 1490
Meridian 1 Attendant PC Unit Quick Reference Guide 347, 1491
Meridian 1 Attendant PC/Hospitality Installation Quick Start Guide 205, 1495
Meridian 1 Attendant PC/Hospitality Software Quick Start Guide 205, 348, 1494
Meridian 1 Attendant PC/Hospitality User Guide 205, 1494
Meridian 1 Base System Software
Release 23 116, 1202, 1512
Release 24 104, 1202, 1512
Release 25 94, 1203, 1512
Meridian 1 Building Communications Solutions Brochure 1667
Meridian 1 Call Center Testimonial 352, 1484
Meridian 1 Digital Telephone Video "Larry Ring Live" 367, 1485
Meridian 1 Distributor Small System Documentation Subscription 1617
Meridian 1 Evergreen By Design Brochure 364, 1490
Meridian 1 Evergreen by Design Video 1665
Meridian 1 Evolution at Yale and SITA Video 1669
Meridian 1 Feature Glossary (Price is Per Set) 1687
Meridian 1 Future Direction CD-ROM 1669
Meridian 1 Lanstar Brochure 1653
Meridian 1 Logo Insert (Aqua Blue) 199, 1150, 1483
Meridian 1 New Core Product Introductions - Sales & Marketing Readiness Package 1666
Meridian 1 New Core Products
Racing to Win Video 368, 1492
Meridian 1 New Core Products Video 367, 1490
Meridian 1 NT System Package 1708
Meridian 1 NTS Driver 1591
Meridian 1 NTS Network Managers Guide 1664
Meridian 1 NTS Release 2.0 Driver Package 1591
Meridian 1 NTS Release 2.0 IVR Integration Option 1591
Meridian 1 NTS Release 2.0 Meridian Mail Tool Option 1591
Meridian 1 Option 11C
Building a High-Performance Network Brochure 363, 1490
Meridian 1 Option 11C "High Performance in a Small Package" Brochure 363, 1490
Meridian 1 Option 11C Compact Brochure 364, 1496, 1669
Meridian 1 Option 11C Compact Business Case 363, 1492
Meridian 1 Option 11C Compact CD-ROM Demo 365, 1493
Meridian 1 Option 11C Compact Hospitality Package Brochure 363, 1494
Meridian 1 Option 11C Compact Video 356, 1493
Meridian 1 Option 21E System Package AC 1708
Meridian 1 Option 21E System Package DC 1708
Meridian 1 Option 51 System Package AC 1708
Meridian 1 Option 51 System Package DC 1708

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian 1 Option 51C System Package AC 158, 1278, 1518
Meridian 1 Option 51C System Package DC 158, 1280, 1519
Meridian 1 Option 61 System Package AC 1708
Meridian 1 Option 61 System Package DC 1708
Meridian 1 Option 71 Package AC 1708
Meridian 1 Option 71 Package DC 1708
Meridian 1 Option 81 System Package AC 1708
Meridian 1 Option 81 System Package DC 1708
Meridian 1 Option 81C System Package AC 158, 1284, 1519
Meridian 1 Option 81C System Package DC 158, 1286, 1519
Meridian 1 Packet Handler 100, 111, 123, 132, 139, 147, 1233, 1515
Meridian 1 Quick Reference Guide Updates 1653
Meridian 1 Quick Tips Guide 353, 1487
Meridian 1 Reference Library (Release 20) 1558
Meridian 1 Reference Library (Release 21) 1558, 1559
Meridian 1 Reference Library (Release 22) 1560
Meridian 1 Reference Library (Release 23) 1598
Meridian 1 Reference Library, Release 24 and Earlier 344, 556, 1403
Meridian 1 Reference Library, Release 25 345, 807, 1438
Meridian 1 Release 17 Base Software 151, 1200, 1512
Meridian 1 Release 18 Base Software 1695
Meridian 1 Release 19 Base Software 144, 1200, 1512
Meridian 1 Release 20 Base Software 1695
Meridian 1 Release 21 & New Products Video 367, 1487
Meridian 1 Release 21 Base Software 136, 1201, 1512
Meridian 1 Release 22 Base Software 128, 1201, 1512
Meridian 1 Remote Services Brochure 1664
Meridian 1 Remote Services Portfolio Brochure 364, 1495
Meridian 1 RT System Package 1708
Meridian 1 Security Audit 1201 to 2500 lines 1695
Meridian 1 Security Audit 2501 + lines 1695
Meridian 1 Security Audit 401 to 800 lines 1695
Meridian 1 Security Audit 801 to 1200 lines 1695
Meridian 1 Security Audit Additional charge for database downloading (per hour) 1695
Meridian 1 Security Audit Per Hour 46, 1199, 1512
Meridian 1 Security Audit-Meridian Mail Option Additional charges for individual mailbox review (per mailbox) 1695
Meridian 1 Security Consulting per day plus travel and expense 46, 1199, 1512
Meridian 1 Security Seminar (per day) Plus Travel and Expense for One Consultant 46, 1200, 1512
Meridian 1 ST System Package 1708
Meridian 1 System Option 21 + IPE Module AC 1707
Meridian 1 System Option 21 + IPE Module DC 1707
Meridian 1 System Option 21 + IPE Module DC with Rectifiers 1707
Meridian 1 System Option 21 AC 1707
Meridian 1 System Option 21 DC 1707
Meridian 1 System Option 21 DC with Rectifiers 1707
Meridian 1 System Option 21A AC 1707
Meridian 1 System Option 51 AC 1707
Meridian 1 System Option 51 DC 1707
Meridian 1 System Option 51 DC with Rectifiers 1707
Meridian 1 System Option 61 AC 1707
Meridian 1 System Option 61 DC 1707
Meridian 1 System Option 61 DC with Rectifiers 1707
Meridian 1 System Option 71 AC 1707
Meridian 1 System Option 71 DC 1707
Meridian 1 System Option 71 DC with Rectifiers 1707
Meridian 1 System Specifications Brochure 363, 1495, 1667
Meridian 1 TAPI Server Documentation 1599
Meridian 1 TAPI Server License Agreement 1665
Meridian 1 TAPI Server Release 1 (Includes One-Year Software Support) 1599
Meridian 1 TAPI Server Release 1 Software Service Transaction Fee 1694
Meridian 1 TAPI Server Release 1 with IVR/Networking Option (Includes One-Year Software Support) 1599
Meridian 1 TAPI Server Release 1 with IVR/Networking Option Software Service Transaction Fee 1694
Meridian 1 Toll Fraud Brochure 368, 1485
Meridian 1 Trunk Tip/Ring Cable (50 Ft.) 188, 1402
Meridian 1 Trunk Tip/Ring Cable (8 Ft) 1589
Meridian 1 Trunk Tip/Ring Cable (8 Ft) NT, XT 1590
Meridian 1 Trunk Tip/Ring Cable (8 Ft.) 188, 1402
Meridian 1 Trunk Tip/Ring Cable (8 Ft.) NT, XT 188, 552, 1402
Meridian 1 Trunk Tip/Ring Cable (8 Ft.) ST, STE, RT 188, 1402
Meridian 1 XT System Package 1708
Meridian 2000 Series Digital Telephones Brochure 1657
Meridian 2616CT Wall Transformer (Standard) 1561
Meridian 911 46, 55, 101, 113, 124, 133, 140, 148, 1244, 1245, 1515, 1697
Meridian ACCESS Configuration Guide (NTP 555-7001-3150) 347, 1485
Meridian ACCESS Developers Reference Manual 347, 1485
Meridian ACCESS Enable Option Reference Manual

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

347, 1485
Meridian Access RSM Assembly - Modular 1588
Meridian Access RSM Assembly - Non-Modular 1589
Meridian Accessory Connection Module (ACM), Charcoal (M3900 Series) 41, 201, 818, 1440
Meridian Accessory Connection Module (ACM), Platinum (M3900 Series) 41, 201, 818, 1440
Meridian ACD at Mary Kay Cosmetics Video 1652
Meridian ACD Display Option, Ash 1396, 1581
Meridian ACD Display Option, Black 1396, 1581
Meridian ACD Display Option, Gray 1397, 1581
Meridian ACD Package A-C2 and Network ACD 352, 1484
Meridian Administration Tools (MAT 6) Demo CD 365, 1495
Meridian Administration Tools (MAT) Brochure 365, 1490
Meridian Administration Tools (MAT) Demo Disk 1666
Meridian Administration Tools (MAT) Sales Guide 1666
Meridian Administration Tools Common Services User Guide 1601
Meridian Administration Tools Distributor Common Services 1601
Meridian Administration Tools Multi Site Station Administration and Traffic Analysis Upgrade 1563
Meridian Administration Tools Multi Site Traffic Analysis Upgrade 1563
Meridian Administration Tools Multi-Site Common Services 1601
Meridian Administration Tools Multi-Site Expansion 1601
Meridian Administration Tools Multi-Site Station Administration Upgrade 1563
Meridian Administration Tools Single Site Station Administration and Traffic Analysis Upgrade 1563
Meridian Administration Tools Single Site Station Administration Upgrade 1563
Meridian Administration Tools Single Site Traffic Analysis Upgrade 1563
Meridian Administration Tools Single-Site Common Services 1601
Meridian Administration Tools Single-Site to Multi-Site Upgrade 1601
Meridian Administration Tools Software Service Transaction Fee 1694
Meridian Administration Tools Station Administration and Traffic Analysis Incentive Price Cap 1563
Meridian Administration Tools Station Administration Incentive Price Cap 1563
Meridian Administration Tools Station Administration Module 1601
Meridian Administration Tools Station Administration Module Upgrade 1601
Meridian Administration Tools Station Administration Module User Guide 1601
Meridian Administration Tools Traffic Analysis Incentive Price Cap 1563
Meridian Administration Tools Traffic Analysis Module 1601
Meridian Administration Tools Traffic Analysis Module Upgrade 1601
Meridian Administration Tools Traffic Analysis Module User Guide 1601
Meridian Analog Terminal Adapter (ATA), Charcoal (M3900 Series) 201, 818, 1440
Meridian Analog Terminal Adapter (ATA), Platinum (M3900 Series) 201, 817, 1440
Meridian Analog Terminal Adapter User Guide (M3900 Series, Package of 15 P0903785) 1577
Meridian Applications Server Model 100 1628
Meridian Applications Server Model 500 1628
Meridian Attendant Console Sales Feature Sheet 1649
Meridian Attendant Message Center Demo Disk 1654
Meridian Attendant Message Center Slide Presentation 352, 1483
Meridian Bandwidth Controller Brochure 1650
Meridian Base Software 1695
Meridian Call Center Capabilities Guide 360, 1487
Meridian Call Center Executive Overhead Presentation 360, 1487
Meridian Call Center Networking Brochure (NAC/NACD) 359, 1484
Meridian Communications Adapter 1397, 1582
Meridian Communications Adapter (M2000 Series) 202, 531, 1397
Meridian Communications Adapter (MCA) (M2000 Series) 203, 531, 1397
Meridian Communications Adapter (MCA), Charcoal (M3900 Series) 26, 1440, 1620
Meridian Communications Adapter (MCA), Platinum (M3900 Series) 26, 1440, 1620
Meridian Communications Adapter Product Brief 365, 1484
Meridian Communications adapter quick reference card (25/PK) 1657, 1660
Meridian Communications adapter user guide (15/PK) 1657, 1660
Meridian Communications Adapter User Guide (M3900 Series, Package of 15 P0903781) 25, 1576
Meridian Communications Adapter User Guide (Package of 15 P0859508) 351, 1403
Meridian Communications Adapter User Guide (Pk of

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

15 P0744323) 1559
Meridian Communications Unit 185, 828, 1443
Meridian Communications Unit User Guide and Meridian Communication Adapter Reference Guide 353, 1485
Meridian COMPANION CLID/CPND/Privacy 97, 107, 119, 130, 138, 1216, 1513
Meridian COMPANION NTP Documentation 353, 1487
Meridian connection 1533
Meridian Customer Defined NET 1648
Meridian Customer Presentation Kit 1667
Meridian Display Module Quick Reference Card (100/PK) 1652
Meridian Display Option, Ash 1396, 1397, 1581
Meridian Display Option, Ash (10 Language) 202, 528, 1397
Meridian Display Option, Ash (3 Language) 202, 529, 1397, 1581
Meridian Display Option, Black 1396, 1397, 1581
Meridian Display Option, Black (10 Language) 202, 528, 1397
Meridian Display Option, Black (3 Language) 202, 529, 1397, 1581
Meridian Display Option, Gray 1396, 1397, 1581
Meridian Display Option, Gray (10 Language) 202, 529, 1397
Meridian Display Option, Gray (3 Language) 202, 530, 1397, 1581
Meridian Display-Based Expansion Module, Charcoal (M3900 Series) 201, 817, 1440
Meridian Display-Based Expansion Module, Platinum (M3900 Series) 201, 817, 1440
Meridian Electronic Voice Mail Brochure 1648
Meridian External Alerter and Recording Interface, Charcoal (M3900 Series) 201, 816, 1440
Meridian External Alerter and Recording Interface, Platinum (M3900 Series) 201, 816, 1440
Meridian HomeOffice II Line Card C/W Management/Interconnect Cable and Installer Notes 334, 831, 1443
Meridian HomeOffice II Line Card Configuration Guide 334, 1433
Meridian HomeOffice II Network Administration Guide 334, 1433
Meridian HomeOffice II Planning Guide 334, 1433
Meridian HomeOffice II Router 1433, 1617
Meridian HomeOffice II Router (NTQR03AA) with M2616 334, 830, 1443
Meridian HomeOffice II Router ACD with M2216 Digital Set 334, 831, 1443
Meridian HomeOffice II Router C/W CD-ROM, User Guide 334, 1443
Meridian HomeOffice II User Guide 334, 1433, 1617
Meridian Hospitality Voice Services Features 154, 1250, 1516
Meridian HVS Administration Reference Manual 347, 1485
Meridian HVS GAC Reference Manual 347, 1485
Meridian I Option 11C Technical Overview Brochure 1667
Meridian Integrated Conference Bridge (Ide@Room Version) 12 Port Card 1425, 1610
Meridian Integrated Conference Bridge (Ide@Room Version) 12 to 24 Port Upgrade 1629
Meridian Integrated Conference Bridge (Ide@Room Version) 12 to 32 Port Upgrade 1629
Meridian Integrated Conference Bridge (Ide@Room version) 16 to 32 port upgrade 1629
Meridian Integrated Conference Bridge (Ide@Room Version) 24 Port Card 1465, 1629
Meridian Integrated Conference Bridge (Ide@Room version) 24 to 32 Port Upgrade 1629
Meridian Integrated Conference Bridge (Ide@Room Version) 32 Port Card 1466, 1629
Meridian Integrated Conference Bridge (MICB) Brochure 364, 1491
Meridian Integrated Conference Bridge (Release 2) 12 Port Card 180, 996, 1464
Meridian Integrated Conference Bridge (Release 2) 12 to 16 Port Upgrade 180, 998, 1465
Meridian Integrated Conference Bridge (Release 2) 12 to 24 Port Upgrade 180, 998, 1465
Meridian Integrated Conference Bridge (Release 2) 12 to 32 Port Upgrade 180, 998, 1465
Meridian Integrated Conference Bridge (Release 2) 12 to 42 Port Upgrade 181, 1019, 1467
Meridian Integrated Conference Bridge (Release 2) 12 to 50 Port Upgrade 181, 1020, 1467
Meridian Integrated Conference Bridge (Release 2) 12 to 62 Port Upgrade 181, 1020, 1467
Meridian Integrated Conference Bridge (Release 2) 16 Port Card 180, 996, 1464
Meridian Integrated Conference Bridge (Release 2) 16 to 24 Port Upgrade 180, 999, 1465
Meridian Integrated Conference Bridge (Release 2) 16 to 32 Port Upgrade 180, 999, 1465
Meridian Integrated Conference Bridge (Release 2) 16 to 42 Port Upgrade 181, 1021, 1467
Meridian Integrated Conference Bridge (Release 2) 16 to 50 Port Upgrade 181, 1021, 1467
Meridian Integrated Conference Bridge (Release 2) 16 to 62 Port Upgrade 181, 1022, 1467
Meridian Integrated Conference Bridge (Release 2) 24 Port Card 180, 997, 1464
Meridian Integrated Conference Bridge (Release 2) 24 to 32 Port Upgrade 180, 999, 1465
Meridian Integrated Conference Bridge (Release 2) 24 to

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

42 Port Upgrade 181, 1022, 1467
Meridian Integrated Conference Bridge (Release 2) 24 to 50 Port Upgrade 181, 1023, 1467
Meridian Integrated Conference Bridge (Release 2) 24 to 62 Port Upgrade 181, 1023, 1467
Meridian Integrated Conference Bridge (Release 2) 32 Port Card 180, 997, 1464
Meridian Integrated Conference Bridge (Release 2) 32 to 42 Port Upgrade 181, 1024, 1467
Meridian Integrated Conference Bridge (Release 2) 32 to 50 Port Upgrade 181, 1024, 1467
Meridian Integrated Conference Bridge (Release 2) 32 to 62 Port Upgrade 181, 1025, 1467
Meridian Integrated Conference Bridge (Release 2) 42 Port Card 181, 1018, 1466
Meridian Integrated Conference Bridge (Release 2) 42 to 50 Port Upgrade 181, 1025, 1467
Meridian Integrated Conference Bridge (Release 2) 42 to 62 Port Upgrade 181, 1026, 1467
Meridian Integrated Conference Bridge (Release 2) 50 Port Card 181, 1018, 1467
Meridian Integrated Conference Bridge (Release 2) 50 to 62 Port Upgrade 181, 1026, 1467
Meridian Integrated Conference Bridge (Release 2) 62 Port Card 181, 1019, 1467
Meridian Integrated Conference Bridge (Release 2) Base Card 177, 343, 553, 1402, 1590
Meridian Integrated Conference Bridge (Release 2) NTP Guide 348, 1495
Meridian Integrated Conference Bridge (Release 2) PCMCIA Drive 177, 343, 554, 1403
Meridian Integrated Conference Bridge (Release 2) Quick Reference Pack 351, 556, 1403
Meridian Integrated Conference Bridge (Release 2) User Guide 355, 1495
Meridian Integrated Conference Bridge Base Card 1402, 1590
Meridian Integrated Conference Bridge NTP Guide 1667
Meridian Integrated Conference Bridge PCMCIA Drive 1590
Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) Card Upgrade Kit 181, 1027, 1467
Meridian Integrated Conference Bridge to Meridian Integrated Conference Bridge (Release 2) PCMCIA Upgrade Kit 181, 1026, 1467
Meridian Integrated Conference Bridge User Guide 1667
Meridian Integrated IP Telephony Gateway (ITG) Base Card 1431, 1616
Meridian Integrated IP Telephony Gateway (ITG) Card 1468, 1631
Meridian Integrated IP Telephony Gateway (ITG) Card (Hardware) 1629
Meridian Integrated IP Telephony Gateway (ITG) NTPs 1669
Meridian Integrated IP Telephony Gateway (ITG) PCMCIA Card 65, 182, 1036, 1468
Meridian Integrated IP Telephony Gateway Flyer 363, 1495
Meridian Integrated IP Telephony Gateway Large System Voice Port Ethernet Cable 1616
Meridian Integrated IP Telephony Gateway Large Systems Package 1631
Meridian Integrated IP Telephony Gateway Option 11C/ 11E Package 1631
Meridian Integrated IP Telephony Gateway Option 11C/ 11E Voice Port Ethernet Cable 1616
Meridian Integrated ITG I/O Panel Ethernet and Serial Port Adapter Cable 1620
Meridian Integrated Personal Call Director, 16 ports 100 users 176, 1007, 1466
Meridian Integrated Personal Call Director, 24 ports 150 users 176, 1008, 1466
Meridian Integrated Personal Call Director, 32 ports 200 users 176, 1008, 1466
Meridian Integrated Personal Call Director, 8 ports 50 users 176, 1007, 1466
Meridian Integrated RAN (Release 2) Base Card 1426, 1611
Meridian Integrated RAN (Release 2) Base Spare Card 178, 343, 692, 1426
Meridian Integrated RAN (Release 2) Large (10 Channels) 180, 981, 1463
Meridian Integrated RAN (Release 2) Medium (6 Channels) 179, 981, 1463
Meridian Integrated RAN (Release 2) Medium to Large Upgrade 180, 982, 1463
Meridian Integrated RAN (Release 2) NTP Guide 343, 348, 1493
Meridian Integrated RAN (Release 2) Small (5 Channels) 179, 980, 1463
Meridian Integrated RAN (Release 2) Small to Large Upgrade 180, 982, 1463
Meridian Integrated RAN (Release 2) Small to Medium Upgrade 180, 982, 1463
Meridian Integrated RAN Base Card 1426, 1611
Meridian Integrated RAN NTP Guide 1666
Meridian Integrated Recorded Announcer (MIRAN) Brochure 364, 1491
Meridian Integrated Voice Services (MIVS) NTP 349, 1498
Meridian Integrated Voice Services (MIVS) PCMCIA 197, 1404
Meridian Integrated Voice Services (MIVS) SPARE 197, 1404
Meridian Integrated Voice Services, 2 Port 182, 1053,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1470
Meridian Integrated Voice Services, 2 to 4 Port Upgrade 182, 1054, 1470
Meridian Integrated Voice Services, 2 to 8 Port Upgrade 182, 1055, 1470
Meridian Integrated Voice Services, 4 Port 182, 1054, 1470
Meridian Integrated Voice Services, 4 to 8 Port Upgrade 182, 1055, 1470
Meridian Integrated Voice Services, 8 Port 182, 1054, 1470
Meridian IP Telecommuter Client Application CD 179, 830, 1443
Meridian IP Telecommuter Large Systems Package 1631
Meridian IP Telecommuter NTP 26, 37, 46, 349, 1498, 1670
Meridian IP Telecommuter NTP CD ROM 25, 31, 40, 346, 1438, 1606
Meridian IP Telecommuter Option 11C Package 1631
Meridian IP Telecommuter PCMCIA Card 182, 1037, 1468
Meridian IP Telephony Gateway (ITG) Base Card 65, 178, 707, 1431
Meridian IP Telephony Gateway (ITG) Card 65, 182, 1036, 1468
Meridian IP Telephony Gateway (ITG) Line 2.0 Line Card 34, 58, 62, 158, 1057, 1470
Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (CD-ROM) 31, 345, 720, 1433
Meridian IP Telephony Gateway (ITG) Line 2.0 NTP (Paper) 37, 349, 1170, 1498
Meridian IP Telephony Gateway (ITG) Line 2.0 Software CD-ROM 31, 58, 62, 157, 720, 1433
Meridian IP Telephony Gateway (ITG) NTPs 65, 349, 1496
Meridian IP Telephony Gateway (ITG) Small and Large Systems Package 65, 182, 1036, 1468
Meridian IP Telephony Gateway Line 2.0 Systems Package 34, 58, 62, 158, 1058, 1470
Meridian IPE Application Module Conversion from Option 11 Chassis to Option 21-81 Chassis 1714
Meridian IPE Application Module for Option 11 1558
Meridian IPE Application Module for Options 21-81 1558
Meridian IPE Application Module without Tape/Disk for Option 11 1558
Meridian IPE Application Module without Tape/Disk for Option 21-81 1369, 1557
Meridian IPEE Application Module for Option 11 326, 421, 1372
Meridian IPEE Application Module for Options 21-81C 326, 421, 1372
Meridian ITG 2.0 486 Software Upgrade PCMCIA Card 196, 499, 1383
Meridian ITG 2.0 D-Channel PCMCIA Pigtail Cable 194, 707, 1431
Meridian ITG 2.0 ELAN, TLAN, RS232 and D-CHIP Port Cable with MSDL Filter 194, 708, 1431
Meridian ITG 2.0 ELAN, TLAN, RS232 Port Cable 194, 807, 1439
Meridian ITG 2.0 I/O Panel Mounting Connector 197, 708, 1431
Meridian ITG 2.0 Inter-Cabinet Cable 10 Ft. (Optional) 195, 983, 1463
Meridian ITG 2.0 Intra-Cabinet Cable 1 Ft. 195, 983, 1463
Meridian ITG 2.0 ISDN Large Systems Package 182, 1041, 1469
Meridian ITG 2.0 ISDN Small Systems Package 182, 1041, 1469
Meridian ITG 2.0 Large Systems Upgrade Kit from ITG 1.0 to ITG 2.0 182, 1042, 1469
Meridian ITG 2.0 NTP 349, 1170, 1497
Meridian ITG 2.0 Pentium 24 Port Card 177, 499, 1383
Meridian ITG 2.0 Pentium Software Upgrade PCMCIA Card 197, 500, 1383
Meridian ITG 2.0 Small and Large Systems 24-Port Package 182, 1042, 1469
Meridian ITG 2.0 Small Systems Upgrade Kit from ITG 1.0 to ITG 2.0 182, 1043, 1469
Meridian ITG 2.0 Upgrade Kit D-CHIP Port Cable for NTCW80AA Pack 194, 708, 1431
Meridian ITG 2.0 Upgrade Kit ELAN, TLAN, RS232 and D-CHIP Port Cable (NTCW80CA) 194, 708, 1431
Meridian ITG Backplane and D-Sub Com Port Cable 194, 1439
Meridian IVR 3270 Over Token Ring Host Communications 1586
Meridian IVR 3270 SNA/SDLC Host Communications 1586
Meridian IVR 5250 over SNA/SDLC Host Communications 1586
Meridian IVR 5250 over Token Ring Host Communication 1586
Meridian IVR ACCESS Link Cable Kit 294, 295, 631, 1419
Meridian IVR Applications Module 272, 590, 1411, 1600
Meridian IVR Audio Line Interface Kit 294, 515, 1389
Meridian IVR Development 2 port Expansion Software Option 11 1585
Meridian IVR Development 4 Port Expansion Software

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

(12 Ports) 1704
Meridian IVR Development 4 Port Expansion Software Option 21-81 1585
Meridian IVR Development Base Software (12 Ports) 1704
Meridian IVR Development Hardware Package AC 1710
Meridian IVR Development Hardware Package DC 1710
Meridian IVR Development Module 344, 1398
Meridian IVR Development System - Upgrade from Release 1 (75MHz, 32 MB RAM) 1585
Meridian IVR Development System, 2 port, Option 11 1585
Meridian IVR Development System, 2 port, Option 11 (75 MHz, 32 MB RAM) 1585
Meridian IVR Development System, 4 port, Option 11-81 1585
Meridian IVR Development System, 4 port, Option 21-81 (75MHz, 32MB RAM) 1585
Meridian IVR Development System-Upgrade from Release 1 1585
Meridian IVR FAX Response Expansion Software, 1 Port 1586
Meridian IVR FAX Response Hardware, 4 Port 1586
Meridian IVR FAX Response Software Initial 2 Ports 1586
Meridian IVR Operational NTPs 344, 1398
Meridian IVR Pentium CPU Upgrade, 100MHz 1559
Meridian IVR Run-time 2 Port Expansion Software Option 11 1585
Meridian IVR Run-Time 4 Port Expansion Software 1704
Meridian IVR Run-Time 4 Port Expansion Software Option 21-81 1585
Meridian IVR Run-Time Base Software (12 Ports) 1704
Meridian IVR Run-Time Hardware Package AC 1710
Meridian IVR Run-Time Hardware Package DC 1710
Meridian IVR Run-Time System, 2 port, Option 11 1585
Meridian IVR Run-time System, 2 port, Option 11 (75MHz, 32 MB RAM) 1585
Meridian IVR Run-Time System, 4 port, Option 11-81 1585
Meridian IVR Run-time System, 4 port, Option 21-81 (75MHz, 32 MB RAM) 1585
Meridian IVR Run-time to Development System upgrade, 2 port Expansion Software, Option 11 1585
Meridian IVR Run-Time to Development System Upgrade, 4 Port Expansion Software, Options 21-81 1585
Meridian IVR Run-time to Development System upgrade, Initial 2 ports Option 11 1586
Meridian IVR Run-Time to Development System Upgrade, Initial 4 Ports Option 21-81 1586
Meridian IVR Run-Time to Development Upgrade Software (12 Ports) 1704
Meridian IVR Run-Time to Development Upgrade Software (4 Ports) 1704
Meridian IVR Serial Board 8 ports with Octa cable 1559
Meridian IVR Software Service Transaction Fee 1694
Meridian IVR SQL Informix Database Access 1586
Meridian IVR SQL Ingres Database Access 1586
Meridian IVR SQL Oracle Database Access 1586
Meridian IVR SQL Sybase Database Access 1586
Meridian IVR Uninterruptible Power Supply (UPS) for Application Processor 1586
Meridian IVR VT100 Host Communication 1586
Meridian Japanese Display Option, Ash 202, 530, 1397, 1581
Meridian Japanese Display Option, Black 202, 530, 1397, 1581
Meridian Japanese Display Option, Gray 202, 530, 1397, 1581
Meridian Key Expansion Module, Ash 1396, 1480, 1580, 1581, 1639
Meridian Key Expansion Module, Ash, (M2000 Series) 202, 1396
Meridian Key Expansion Module, Black 1396, 1580, 1581, 1639
Meridian Key Expansion Module, Black, (M2000 Series) 202, 1396
Meridian Key Expansion Module, Gray 1396, 1480, 1581, 1639
Meridian Key Expansion Module, Gray (M2000 Series) 202, 1396
Meridian Key-Based Expansion Module, Charcoal (M3900 Series) 26, 1440, 1620
Meridian Key-Based Expansion Module, Platinum (M3900 Series) 26, 1440, 1620
Meridian Lanstar ASCII Terminal Package 1638
Meridian LANSTAR NetWare Installation Supplement 1650
Meridian Liberation Headsets Product Brief 367, 1498
Meridian Link 1698
Meridian Link - ISDN/AP 1698
Meridian Link - Server 1698
Meridian Link & CCR Co-Resident AST/Agent Software Level 148, 1275, 1518
Meridian Link & CCR Co-Resident NTPs 1576
Meridian Link & CCR Co-Resident Service Transaction Fee 325, 1184, 1510
Meridian Link & CCR Co-Resident Software 1706
Meridian Link & CCR-AM Module AC 1710
Meridian Link & CCR-AM Module DC 1710

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Link & CCR-IPE Module (Option 11) 1708
Meridian Link & CCR-IPE Module (Option 21-81) 1708
Meridian Link & CCR-IPEE Module (Option 11) 1288, 1519
Meridian Link & CCR-IPEE Module (Option 21-81C) 1288, 1519
Meridian Link 5C & CCR 3C Co-Resident Software (20 scripts) 1518
Meridian Link 5C & CCR 3C Co-Resident Software (240 scripts) 1518
Meridian Link Brochure 359, 1484
Meridian Link Documentation 1600
Meridian Link General Guide 1653
Meridian Link INSTALL-ASSIST 325, 1512
Meridian Link ISDN/AP 1698
Meridian Link ISDN/AP Conversion Software Kit 1696
Meridian Link ISDN/AP Pass Through (For DEC) 1705
Meridian Link Module Package AC 1708
Meridian Link Module Package DC 1708
Meridian Link Module Software 101, 113, 125, 133, 141, 148, 154, 1246, 1250, 1516, 1698
Meridian Link Module Software/Documentation Package 1600
Meridian Link Release 3 ISDN/AP Pass Through Software 1705
Meridian Link Release 3 ISDN/AP Pass Through Software Upgrade 1714
Meridian Link Release 3 X.25 Software 1705
Meridian Link Release 3 X.25 Software Upgrade 1714
Meridian Link Release 4 Documentation Package 1576
Meridian Link Release 4 ISDN/AP Pass Through Software 1705
Meridian Link Release 4 ISDN/AP Pass Through Software Upgrade 1714
Meridian Link Release 4 X.25 Software 1705
Meridian Link Release 4 X.25 Software Upgrade 1714
Meridian Link Release 4B X.25 Software 1705
Meridian Link Release 4B X.25 Software Upgrade 1714
Meridian Link Release 5C Software 1518
Meridian Link Release 5C Software Upgrade 325, 1274, 1518
Meridian Link Release X.25 Conversion Software Kit 1696
Meridian Link Software 1600
Meridian Link Software Service Transaction Fee 1694
Meridian Link TCP/IP Software Upgrade 1591
Meridian Link X.25 (For IBM, HP, and Tandem) 1705
Meridian Link X.25 Conversion Software Kit 1696
Meridian Link/CCR Co-Resident Application Tape Assembly 1583
Meridian M1006, M2008 and M2616 User Card (Quick Reference Card, Pk of 100 Ea. P0722007) 1590
Meridian M1109 Compact Telephone, Ash 1508, 1686
Meridian M1109 Compact Telephone, Gray 1509, 1686
Meridian M2006 Single Line Digital Telephone with Data, Ash 1476, 1631
Meridian M2006 Single Line Digital Telephone with Data, Black 1475, 1631
Meridian M2006 Single Line Digital Telephone with Data, Dolphin Gray 1476, 1631
Meridian M2006 Single Line Digital Telephone with MCA Data, Ash 1391, 1476, 1577, 1631
Meridian M2006 Single Line Digital Telephone with MCA Data, Black 1391, 1476, 1577, 1631
Meridian M2006 Single Line Digital Telephone with MCA Data, Gray 1391, 1476, 1577, 1631
Meridian M2006 Single Line Digital Telephone, Basic, Ash 201, 684, 1391, 1425, 1475, 1577, 1631
Meridian M2006 Single Line Digital Telephone, Basic, Black 201, 684, 1391, 1425, 1475, 1577, 1631
Meridian M2006 Single Line Digital Telephone, Basic, Gray 201, 684, 1391, 1425, 1475, 1577, 1631
Meridian M2006, M2008, M2008HF & M2616 User Guide (Package of 15 P0820918) 1590
Meridian M2006, M2008, M2008HF & M2616 User Guide (pk of 15 P0834425) 1590
Meridian M2006, M2008, M2008HF & M2616, M2016S User Guide (English) (Package of 15 P0902627) 351, 1403
Meridian M2008 Standard Business Telephone w/ Display & MCA Data, Ash 1476, 1632
Meridian M2008 Standard Business Telephone w/ Display & MCA Data, Black 1476, 1632
Meridian M2008 Standard Business Telephone w/ Display & MCA Data, Gray 1476, 1632
Meridian M2008 Standard Business Telephone with Data, Ash 1476, 1632
Meridian M2008 Standard Business Telephone with Data, Black 1476, 1632
Meridian M2008 Standard Business Telephone with Data, Gray 1476, 1632
Meridian M2008 Standard Business Telephone with Display & Data, Ash 1476, 1632
Meridian M2008 Standard Business Telephone with Display & Data, Black 1476, 1632
Meridian M2008 Standard Business Telephone with Display & Data, Gray 1476, 1632
Meridian M2008 Standard Business Telephone with Display & MCA Data, Ash 1477, 1632

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian M2008 Standard Business Telephone with Display & MCA Data, Black 1477, 1632
Meridian M2008 Standard Business Telephone with Display & MCA Data, Gray 1477, 1632
Meridian M2008 Standard Business Telephone with Display and MCA Data, Ash 1392, 1393, 1577, 1578
Meridian M2008 Standard Business Telephone with Display and MCA Data, Black 1392, 1393, 1577, 1578
Meridian M2008 Standard Business Telephone with Display and MCA Data, Gray 1392, 1393, 1577, 1578
Meridian M2008 Standard Business Telephone with Display, Ash 201, 687, 1392, 1394, 1426, 1476, 1477, 1577, 1578, 1579, 1632
Meridian M2008 Standard Business Telephone with Display, Black 201, 686, 1392, 1393, 1394, 1426, 1476, 1477, 1577, 1578, 1579, 1632
Meridian M2008 Standard Business Telephone with Display, Gray 201, 687, 1392, 1394, 1426, 1476, 1477, 1577, 1579, 1632
Meridian M2008 Standard Business Telephone with MCA Data, Ash 1393, 1476, 1578, 1632
Meridian M2008 Standard Business Telephone with MCA Data, Black 1393, 1476, 1578, 1632
Meridian M2008 Standard Business Telephone with MCA Data, Gray 1393, 1476, 1578, 1632
Meridian M2008 Standard Business Telephone, Basic, Ash 201, 685, 1391, 1392, 1425, 1476, 1577, 1631
Meridian M2008 Standard Business Telephone, Basic, Black 201, 684, 1391, 1392, 1425, 1476, 1577, 1631
Meridian M2008 Standard Business Telephone, Basic, Gray 201, 685, 1391, 1392, 1425, 1476, 1577, 1632
Meridian M2008HF Standard Business Telephone with Display and MCA Data, Ash 1393, 1394, 1578, 1579
Meridian M2008HF Standard Business Telephone with Display and MCA Data, Black 1393, 1394, 1578, 1579
Meridian M2008HF Standard Business Telephone with Display and MCA Data, Gray 1393, 1394, 1578, 1579
Meridian M2008HF Standard Business Telephone with Display, Ash 202, 688, 1392, 1394, 1426, 1578, 1579
Meridian M2008HF Standard Business Telephone with Display, Black 201, 687, 1392, 1394, 1426, 1577, 1578, 1579
Meridian M2008HF Standard Business Telephone with Display, Gray 202, 688, 1392, 1394, 1426, 1578, 1579
Meridian M2008HF Standard Business Telephone with MCA Data, Ash 1393, 1578
Meridian M2008HF Standard Business Telephone with MCA Data, Black 1393, 1578
Meridian M2008HF Standard Business Telephone with MCA Data, Gray 1393, 1578
Meridian M2008HF Standard Business Telephone, Basic, Ash 201, 686, 1392, 1394, 1425, 1577, 1579
Meridian M2008HF Standard Business Telephone, Basic, Black 201, 685, 1391, 1392, 1394, 1425, 1577, 1579
Meridian M2008HF Standard Business Telephone, Basic, Gray 201, 686, 1392, 1394, 1425, 1577, 1579
Meridian M2009 Digital Telephone with Data, Ash 1384, 1385, 1572
Meridian M2009 Digital Telephone with Data, Black 1384, 1385, 1572
Meridian M2009 Digital Telephone with Data, Gray 1384, 1385, 1572
Meridian M2009 Digital Telephone with Date, Gray 1384, 1572
Meridian M2009 Digital Telephone, Ash 1384, 1571
Meridian M2009 Digital Telephone, Black 1384, 1571
Meridian M2009 Digital Telephone, Gray 1384, 1571, 1572
Meridian M2016S Secure Telephone with Data, Ash 1478, 1633
Meridian M2016S Secure Telephone with Data, Black 1478, 1633
Meridian M2016S Secure Telephone with Data, Gray 1478, 1633
Meridian M2016S Secure Telephone with Display & Data, Ash 1478, 1633
Meridian M2016S Secure Telephone with Display & Data, Black 1478, 1633
Meridian M2016S Secure Telephone with Display & Data, Gray 1478, 1633
Meridian M2016S Secure Telephone with Display & MCA Data, Ash 1478, 1633
Meridian M2016S Secure Telephone with Display & MCA Data, Black 1478, 1633
Meridian M2016S Secure Telephone with Display & MCA Data, Gray 1478, 1633
Meridian M2016S Secure Telephone with Display, Ash 1478, 1633
Meridian M2016S Secure Telephone with Display, Black 1478, 1633
Meridian M2016S Secure Telephone with Display, Gray 1478, 1633
Meridian M2016S Secure Telephone with MCA Data,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Ash 1478, 1633
Meridian M2016S Secure Telephone with MCA Data, Black 1478, 1633
Meridian M2016S Secure Telephone with MCA Data, Gray 1478, 1633
Meridian M2016S Secure Telephone, Basic, Ash 202, 1124, 1478
Meridian M2016S Secure Telephone, Basic, Black 1478, 1633
Meridian M2016S Secure Telephone, Basic, Gray 1478, 1633
Meridian M2018 Digital Telephone with Data, Ash 1385, 1386, 1573
Meridian M2018 Digital Telephone with Data, Black 1385, 1386, 1573
Meridian M2018 Digital Telephone with Data, Gray 1386, 1573
Meridian M2018 Digital Telephone, Ash 1385, 1573
Meridian M2018 Digital Telephone, Black 1385, 1573
Meridian M2018 Digital Telephone, Gray 1385, 1573
Meridian M2018S Secure Telephone 1385, 1573
Meridian M2018S Secure Telephone with Data, Ash 1386, 1419, 1573, 1574, 1605
Meridian M2018S Secure Telephone, Ash 1574
Meridian M2112 Digital Telephone with Data, Ash 1385, 1572, 1573
Meridian M2112 Digital Telephone with Data, Black 1385, 1572, 1573
Meridian M2112 Digital Telephone with Data, Gray 1385, 1572, 1573
Meridian M2112 Digital Telephone, Ash 1385, 1572
Meridian M2112 Digital Telephone, Black 1385, 1572
Meridian M2112 Digital Telephone, Gray 1385, 1572
Meridian M2216 ACD-1 Basic Telephone, Ash 1396, 1478, 1479, 1580, 1634
Meridian M2216 ACD-1 Basic Telephone, Black 1396, 1478, 1479, 1580, 1634
Meridian M2216 ACD-1 Basic Telephone, Gray 1396, 1478, 1479, 1580, 1634
Meridian M2216 ACD-1 Telephone with Data, Ash 1479, 1634
Meridian M2216 ACD-1 Telephone with Data, Black 1478, 1634
Meridian M2216 ACD-1 Telephone with Data, Gray 1479, 1634
Meridian M2216 ACD-1 Telephone with MCA Data, Ash 1395, 1396, 1479, 1580, 1634
Meridian M2216 ACD-1 Telephone with MCA Data, Black 1395, 1396, 1479, 1580, 1634
Meridian M2216 ACD-1 Telephone with MCA Data, Gray 1396, 1479, 1580, 1634
Meridian M2216 ACD-2 Telephone with Data, Ash 1479, 1634
Meridian M2216 ACD-2 Telephone with Data, Black 1479, 1634
Meridian M2216 ACD-2 Telephone with Data, Gray 1479, 1634
Meridian M2216 ACD-2 Telephone with MCA Data, Ash 1479, 1634
Meridian M2216 ACD-2 Telephone with MCA Data, Black 1479, 1634
Meridian M2216 ACD-2 Telephone with MCA Data, Gray 1479, 1634
Meridian M2216 ACD-2 Telephone, Basic, Ash 1479, 1634
Meridian M2216 ACD-2 Telephone, Basic, Black 1479, 1634
Meridian M2216 ACD-2 Telephone, Basic, Gray 1479, 1634
Meridian M2216ACD Telephone, Ash 202, 691, 1426
Meridian M2216ACD Telephone, Black 202, 690, 1426
Meridian M2216ACD Telephone, Grey 202, 691, 1426
Meridian M2250 Attendant Console Product Brief 365, 1484
Meridian M2250 Attendant Console User Guide 1651
Meridian M2317 Digital Display Telephone with Data, Ash 1386, 1387, 1574
Meridian M2317 Digital Display Telephone with Data, Black 1386, 1387, 1574
Meridian M2317 Digital Display Telephone with Data, Gray 1386, 1387, 1574
Meridian M2317 Digital Display Telephone, Ash 1386, 1574
Meridian M2317 Digital Display Telephone, Black 1386, 1574
Meridian M2317 Digital Display Telephone, Gray 1386, 1574
Meridian M2317 Digital Telephone Brochure 1648
Meridian M2317 Intelligent Telephone Flyer 1657
Meridian M2317 Intelligent Telephone with Data, Ash 203, 504, 1387
Meridian M2317 Intelligent Telephone with Data, Black 203, 503, 1387
Meridian M2317 Intelligent Telephone with Data, Gray 203, 504, 1387
Meridian M2317 Intelligent Telephone, Ash 203, 503, 1386
Meridian M2317 Intelligent Telephone, Black 203, 502, 1386
Meridian M2317 Intelligent Telephone, Gray 203, 503, 1386
Meridian M2616 Performance-Plus Telephone with Data, Ash 1477, 1632
Meridian M2616 Performance-Plus Telephone with Data, Black 1477, 1632

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian M2616 Performance-Plus Telephone with Data, Gray 1477, 1632
Meridian M2616 Performance-Plus Telephone with Display & Data, Ash 1477, 1633
Meridian M2616 Performance-Plus Telephone with Display & Data, Black 1477, 1633
Meridian M2616 Performance-Plus Telephone with Display & Data, Gray 1477, 1633
Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Ash 1477, 1478, 1633
Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Black 1477, 1478, 1633
Meridian M2616 Performance-Plus Telephone with Display & MCA Data, Gray 1477, 1478, 1633
Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Ash 1394, 1395, 1579, 1580
Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Black 1394, 1395, 1579
Meridian M2616 Performance-Plus Telephone with Display and MCA Data, Gray 1395, 1579, 1580
Meridian M2616 Performance-Plus Telephone with Display, Ash 202, 690, 1395, 1426, 1477, 1478, 1579, 1580, 1633
Meridian M2616 Performance-Plus Telephone with Display, Black 202, 689, 1395, 1426, 1477, 1478, 1579, 1580, 1633
Meridian M2616 Performance-Plus Telephone with Display, Gray 202, 690, 1395, 1426, 1477, 1478, 1579, 1580, 1633
Meridian M2616 Performance-Plus Telephone with MCA Data, Ash 1395, 1477, 1580, 1633
Meridian M2616 Performance-Plus Telephone with MCA Data, Black 1395, 1477, 1580, 1632
Meridian M2616 Performance-Plus Telephone with MCA Data, Gray 1395, 1477, 1580, 1633
Meridian M2616 Performance-Plus Telephone, Basic, Ash 202, 689, 1394, 1426, 1477, 1579, 1632
Meridian M2616 Performance-Plus Telephone, Basic, Black 202, 688, 1394, 1426, 1477, 1579, 1632
Meridian M2616 Performance-Plus Telephone, Basic, Gray 202, 689, 1394, 1426, 1477, 1579, 1632
Meridian M2616CT (Cordless Telephone), Ash 1397, 1581
Meridian M2616CT (Cordless Telephone), Black 1397, 1581
Meridian M2616CT (Cordless Telephone), Gray 1397, 1581
Meridian M2616CT 1000 mAh Battery Pack with Vibrate Alerter, Black 1560
Meridian M2616CT 1000 mAh Battery with Vibrate Alerter, Ash 1560
Meridian M2616CT 1000 mAh Battery with Vibrate Alerter, Gray 1560
Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Ash 1560
Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Black 1560
Meridian M2616CT 700 mAh Battery with Vibrate Alerter, Gray 1560
Meridian M2616CT 700 mAh Battery, Ash (Standard) 202, 430, 1374
Meridian M2616CT 700 mAh Battery, Black (Standard) 202, 413, 1371
Meridian M2616CT 700 mAh Battery, Gray (Standard) 202, 413, 1371
Meridian M2616CT Belt Clip, Ash 1665
Meridian M2616CT Belt Clip, Black 1665
Meridian M2616CT Belt Clip, Gray 1665
Meridian M2616CT Cordless Telephone Flyer 1670
Meridian M2616CT Handset Accessory Package (Standard) 1582
Meridian M2616CT Handset Leather Pouch 1668
Meridian M2616CT User Guide (Package of 15 of P0838286) 1590
Meridian M2616CT Wall Transformer (Standard) 1560
Meridian M3000 Asynchronous Data Option 1386, 1573
Meridian M3000 Set Sales Flyers 1649
Meridian M3000 Touchphone with Data, Black 1386, 1573
Meridian M3000 Touchphone, Black 1386, 1573
Meridian M3900 Series Quick Reference Guide, Release 1 (Package of 15 P0903628) 351, 526, 1391
Meridian M3901 Entry, Charcoal 200, 810, 1439
Meridian M3901 Entry, Platinum 200, 810, 1439
Meridian M3901, 2,3,4 User Guide Release 2, (Package of 5 P0987180) No Charge 210, 524, 1390
Meridian M3901, 2,3,4 User Guide, Release 2 (Package of 5 P0987180) 210, 525, 1390
Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627) 40, 350, 525, 1390
Meridian M3901, M3902, M3903, M3904 User Guide Release 1 (Package of 15 P0903627) N/C 350, 524, 1390
Meridian M3902 Basic, Charcoal 200, 811, 1439
Meridian M3902 Basic, Platinum 200, 811, 1439
Meridian M3903 Enhanced, Release 1, Charcoal 200, 812, 1439

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian M3903 Enhanced, Release 1, Platinum 200, 811, 1439
Meridian M3903 Enhanced, Release 2, Charcoal 200, 812, 1439
Meridian M3903 Enhanced, Release 2, Platinum 200, 812, 1439
Meridian M3904 Professional, Release 1, Charcoal 200, 813, 1439
Meridian M3904 Professional, Release 1, Platinum 200, 812, 1439
Meridian M3904 Professional, Release 2, Charcoal 200, 813, 1439
Meridian M3904 Professional, Release 2, Platinum 200, 813, 1439
Meridian M3905 Call Center, Release 1, Charcoal 200, 814, 1439
Meridian M3905 Call Center, Release 1, Platinum 200, 814, 1439
Meridian M3905 Call Center, Release 2, Charcoal 31, 200, 815, 1440
Meridian M3905 Call Center, Release 2, Platinum 31, 200, 814, 1440
Meridian M3905 Quick Reference Guide (Package of 15 P0907179) 30, 210, 527, 1391
Meridian M3905 Quick Reference Guide, Release 1 (Package of 15 P0903630) 351, 526, 1391
Meridian M3905 Series Quick Reference Guide, Release 2 (Package of 15 P0907178) 210, 526, 1391
Meridian M3905 User Guide (Package of 5 P0907181) 210, 526, 1391
Meridian M3905 User Guide (Package of 5 P0907181) No Charge 210, 525, 1391
Meridian M3905 User Guide Release 1 (Package of 15 P0903629) N/C 350, 525, 1390
Meridian M3905 User Guide, Release 1 (Package of 15 P0903629) 40, 350, 526, 1391
Meridian Mail
The Electronic Front Door for Business Video 374, 1486
Meridian Mail "GP" Reference Manual 1653
Meridian Mail "GP" Reference Manual Release 7 1654
Meridian Mail 1.0GB Disk Drive Upgrade 1712
Meridian Mail 11 "Updating Voice Menu Prompts" Cards (15/PK) 354, 1489
Meridian Mail 11 Administration Manual 351, 1404
Meridian Mail 11 Administration Manual for Multi-Customer Systems 351, 1404
Meridian Mail 11 AMIS Networking Installation and Administration Guide 354, 1489
Meridian Mail 11 Call Answering Package (50/PK) (DMS) 351, 558, 1404
Meridian Mail 11 Card Option Manual 351, 1404
Meridian Mail 11 CD ROM Package (NTPs) 345, 1404
Meridian Mail 11 Enterprise Networking, Installation and Administration Guide 354, 1489
Meridian Mail 11 Fax on Demand Application Guide 354, 1489
Meridian Mail 11 Feature Operations Video 1718
Meridian Mail 11 HVS GAC Guide / Guest Voice Messaging Reference Guide 353, 1489
Meridian Mail 11 HVS Implementation Guide 353, 1489
Meridian Mail 11 Maintenance Messages (SEERS) 60, 354, 1156, 1489
Meridian Mail 11 Modular Option EC Manual (Release 1) 1591
Meridian Mail 11 Modular Option GP Administration Manual 351, 1404
Meridian Mail 11 Modular Option GP Administration Manual for Multi-Customer Systems 351, 1404
Meridian Mail 11 Modular Option GP Manual 351, 1404
Meridian Mail 11 Modular Option Manual 351, 1404
Meridian Mail 11 Network Message Services Installation and Administration Guide 354, 1489
Meridian Mail 11 Network Planning Guide 354, 1489
Meridian Mail 11 Networking, Installation and Administration Guide 354, 1489
Meridian Mail 11 Option 11 EC (EC11) Manual 351, 1404
Meridian Mail 11 Overview (Release 11) (All) 1591
Meridian Mail 11 System Installation and Modification Guide 353, 1489
Meridian Mail 11 Virtual Node AMIS Networking Installation and Administration Guide 354, 1489
Meridian Mail 11 Voice Messaging (VMUIF) Package (15/PK) 351, 557, 1404
Meridian Mail 11 Voice Messaging Package (15/PK) 351, 557, 1404
Meridian Mail 11 Voice Messaging Quick Reference Card 30/Pkg 354, 1489
Meridian Mail 11 Voice Services Application Guide 354, 1489
Meridian Mail 2-24 Upgrade Service Charge 1188, 1511
Meridian Mail 25-48 Upgrade Service Charge 1188, 1511
Meridian Mail 2GB Disk Shadowing Prime Node Package 258, 478, 1380
Meridian Mail 2GB Disk Shadowing Voice Node Package AC 258, 480, 1380
Meridian Mail 2GB Disk Shadowing Voice Node Package DC 258, 481, 1380
Meridian Mail 300MB Disk Drive Upgrade 1712

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail 300MB Disk Shadowing Voice Node Package AC 1565
Meridian Mail 300MB Disk Shadowing Voice Node Package DC 1565
Meridian Mail 300MB Disk Upgrade 1714
Meridian Mail 49-64 Upgrade Service Charge 1188, 1511
Meridian Mail 5 Hour Base Software 1700
Meridian Mail 5 to 11 Hours Software 1700
Meridian Mail 600MB Disk Upgrade 1714
Meridian Mail 65-96 Upgrade Service Charge 1188, 1511
Meridian Mail ACCESS Developers Reference Manual, Release 10 345, 586, 1410
Meridian Mail ACCESS Enable Option 257, 1256, 1517
Meridian Mail Access Enable Option 1702
Meridian Mail ACCESS Enable Option Reference Manual, Release 10 345, 586, 1410
Meridian Mail ACCESS Enable Option, Release 10 & 11 1702
Meridian Mail ACCESS Enable Option, Release 7 1702
Meridian Mail ACCESS Enable Option, Release 8 1702
Meridian Mail ACCESS Enable Option, Release 9 1702
Meridian Mail Additional Language 256, 1255, 1516
Meridian Mail AdminPlus Enable Option 236, 246, 1269, 1517
Meridian Mail AdminPlus Enable Software, Release 7 1700
Meridian Mail AdminPlus Enable Software, Release 8 1700
Meridian Mail AdminPlus Enable Software, Release 9 1700
Meridian Mail Alternative Remote Access Package 266, 489, 1381
Meridian Mail AMIS Networking (Virtual Node) 257, 1257, 1517, 1702
Meridian Mail AMIS Networking (Virtual Node), Release 11 1703
Meridian Mail AMIS Open Networking 257, 1258, 1517, 1703
Meridian Mail AMIS Open Networking, Release 11 1703
Meridian Mail AMIS Virtual Node Networking Installation and Administration Guide 355, 1492
Meridian Mail AutoAdmin Link Software 257, 1264, 1517
Meridian Mail AutoAdmin Software Package 1566
Meridian Mail AutoAdmin Software Package EC, Modular Option, GP 256, 866, 1448
Meridian Mail Base Software 1613, 1700
Meridian Mail Base Software (Rel. 5) 1700
Meridian Mail Base Software (Rel. 6) 1700
Meridian Mail Base Software (Rel. 7) 1700
Meridian Mail Basic to Full Service per Port Software Upgrade 247, 259, 1263, 1517
Meridian Mail Bus Cable 1588
Meridian Mail Bus Cable - Five Nodes 267, 548, 1401
Meridian Mail Bus Cable - Two Nodes 267, 548, 1401
Meridian Mail Call Answering User Guide Package (VMUIF), English, (50/Pkg) 1595
Meridian Mail Card Option 1GB Disk Drive Upgrade 1712
Meridian Mail Card Option 2 Ports 5 Hours Package 1710
Meridian Mail Card Option 2-6 Ports, 5/10/24 Hours Package, Release 8 1710
Meridian Mail Card Option 2-6 Ports, 5/10/24 Hours Package, Release 9 1710
Meridian Mail Card Option 2-6 Ports, 5/10/24/54 Hours Package 1710
Meridian Mail Card Option 4 Ports 10 Hours Package 1710
Meridian Mail Card Option 4 Ports 5 Hours Package 1710
Meridian Mail Card Option 4-6 Ports, 5/10/24/54 Hours Package 1710
Meridian Mail Card Option 6 Ports 10 Hours Package 1710
Meridian Mail Card Option 6 Ports 5 Hours Package 1710
Meridian Mail Card Option 6 to 8 Port Expansion 1566
Meridian Mail Card Option 6 to 8 Port Expansion Package, Release 8 1566
Meridian Mail Card Option 8-12 Ports, 5/10/24 Hours Package, Release 8 1710
Meridian Mail Card Option 8-12 Ports, 5/10/24 Hours Package, Release 9 1710
Meridian Mail Card Option 8-12 Ports, 5/10/24/54 Hours Package 1710
Meridian Mail Card Option ACCESS Enable Option, Release 9 1704
Meridian Mail Card Option Base Pack, 2-6 Ports 240, 695, 1427, 1612
Meridian Mail Card Option Base Package, 8-12 Ports 240, 695, 1428, 1612
Meridian Mail Card Option Basic to Full Service License Fee Upgrade 237, 1271, 1518
Meridian Mail Card Option Documentation Package 1612
Meridian Mail Card Option Expanded Storage Software Level 1-2 238, 1265, 1517
Meridian Mail Card Option Expanded Storage Software Level 2-3 238, 1265, 1517
Meridian Mail Card Option Expanded Storage Software

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Level 3-4 238, 1271, 1518
Meridian Mail Card Option Master Tape - Asia/Pacific 1614
Meridian Mail Card Option Master Tape - Asia/Pacific, Release 9 1614
Meridian Mail Card Option Master Tape - European 1 1613
Meridian Mail Card Option Master Tape - European 1, Release 9 1613
Meridian Mail Card Option Master Tape - European 2 1613
Meridian Mail Card Option Master Tape - European 2, Release 9 1613
Meridian Mail Card Option Master Tape - European 3 1614
Meridian Mail Card Option Master Tape - European 3, Release 9 1614
Meridian Mail Card Option Master Tape - European 4, Release 9 1614
Meridian Mail Card Option Master Tape - North American, Release 8 1613
Meridian Mail Card Option Master Tape - North American, Release 9 1613
Meridian Mail Card Option Multi-Customer 1704
Meridian Mail Card Option Multi-Customer, Release 8 1704
Meridian Mail Card Option Multi-Customer, Release 9 1704
Meridian Mail Card Option Network Message Service Software, Release 8 1704
Meridian Mail Card Option Reference Manual 1595
Meridian Mail Card Option Reference Manual, Release 10 345, 587, 1410
Meridian Mail Card Option Release 10 Base Software 1703
Meridian Mail Card Option Release 11 Base Software 1703
Meridian Mail Card Option Release 12 Base Software 1704
Meridian Mail Card Option Release 6 to Release 11 Upgrade 1713
Meridian Mail Card Option Release 6 to Release 12 Upgrade 1713
Meridian Mail Card Option Release 6 to Release 13 Upgrade 238, 1067, 1471
Meridian Mail Card Option Release 6 to Release 8 Software Update Fee 1537
Meridian Mail Card Option Release 6 to Release 9 Software Update Fee 1537, 1538
Meridian Mail Card Option Release 8 Base Software 1703
Meridian Mail Card Option Release 8 to Release 10 Software Update Fee 1538
Meridian Mail Card Option Release 8 to Release 9 Software Update Fee 1537
Meridian Mail Card Option Release 8/9/10/11/12 to Release 13 Upgrade 238, 1068, 1471
Meridian Mail Card Option Release 9 Base Software 1703
Meridian Mail Card Option Release 9 to Release 10 Software Update Fee 1538
Meridian Mail Card Option Releases 8, 9, 10 to Release 11 Upgrade 1713
Meridian Mail Card Option Releases 8/9/10/11 to Release 12 Upgrade 1714
Meridian Mail Card Option Voice Forms 1704
Meridian Mail Card Option Voice Forms Software, Release 8 1704
Meridian Mail Common Software Networking Software 1536
Meridian Mail Common Software Secured Messaging Software 1536
Meridian Mail Common Software Voice Menus Software 1536
Meridian Mail Compact Option 68K Memory Card 59, 819, 1440, 1441, 1621
Meridian Mail Compact Option Base Hardware Package 1621
Meridian Mail Compact Option Enhanced 68K Memory and 4-Port DSP Unit 1409, 1598
Meridian Mail Compact Option Enterprise Networking Installation and Administration Guide Release 11 60, 1158, 1491
Meridian Mail Compact Option S/W Package 1621
Meridian Mail Compact Option S/W Package. 1621
Meridian Mail Compact Option System Administration Guide 60, 1158, 1491
Meridian Mail Compact Option User Guide Package 1591
Meridian Mail Connections Reference Manual (AT&T), Release 9 347, 1485
Meridian Mail Connections Reference Manual (NEC), Release 9 347, 1485
Meridian Mail Connections Reference Manual (Rolm), Release 9 347, 1485
Meridian Mail Connections Reference Manual AT&T, Release 9 347, 1486
Meridian Mail Connections Reference Manual NEC, Release 9 347, 1486
Meridian Mail Connections Reference Manual ROLM, Release 9 347, 1486
Meridian Mail Dual Language Prompt 257, 1256, 1516
Meridian Mail EC 9.19 to 9.66 Upgrade Keycode 263, 562, 1405
Meridian Mail EC Module AC 269, 1408
Meridian Mail EC Module DC 269, 1408
Meridian Mail EC Release 8, 9.19 to Release 11 Upgrade

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1713
Meridian Mail EC Release 8, 9.19 to Release 12 Upgrade 1713
Meridian Mail EC Release 8, 9.19 to Release 13 Upgrade 263, 1071, 1472
Meridian Mail EC Release 9.58 and later/Release 10 to Release 11 Upgrade 1713
Meridian Mail EC Release 9.58 and Later/Release 10/11 to Release 12 Upgrade 1713
Meridian Mail EC Release 9.58 and Later/Release 10/11/12 to Release 13 Upgrade 263, 1072, 1472
Meridian Mail EC11 1 to 2 Node Expansion Package 247, 489, 1381
Meridian Mail EC11 Base Software, Release 11 1707
Meridian Mail EC11 Base Software, Release 12 1707
Meridian Mail EC11 Base Software, Release 13 245, 1052, 1470
Meridian Mail EC11 Installation and Modification Guide, MM10 351, 581, 1409, 1599
Meridian Mail EC11 Release 10 to Release 11 Upgrade 1714
Meridian Mail EC11 Release 10 to Release 12 Upgrade 1714
Meridian Mail EC11 Release 10, 11, or 12 to Release 13 Upgrade 248, 1068, 1471
Meridian Mail EC11 Spares Package 248, 342, 489, 1381
Meridian Mail EC11 to EC Migration 28-48 Port AC Package 248, 1319, 1520
Meridian Mail EC11 to EC Migration 28-48 Port DC Package 248, 1319, 1520
Meridian Mail EC11 to EC Migration 4-24 Port AC Package 248, 1318, 1520
Meridian Mail EC11 to EC Migration 4-24 Port DC Package 248, 1318, 1520
Meridian Mail Enterprise Networking Installation and Administration Guide Release 12 60, 1492
Meridian Mail Expanded Storage Software 1700
Meridian Mail Expanded Storage Software Level 0-1 230, 1053, 1470
Meridian Mail Expanded Storage Software Level 1-2 248, 262, 1259, 1517, 1703
Meridian Mail Expanded Storage Software Level 2-3 248, 262, 1260, 1517, 1703
Meridian Mail Expanded Storage Software Level 3-4 248, 262, 1260, 1517
Meridian Mail Expanded Storage Software Level 4-5 248, 262, 1261, 1517
Meridian Mail Expanded Storage Software Level 5-6 248, 262, 1262, 1517
Meridian Mail Fax on Demand Software 257, 1261, 1517, 1703
Meridian Mail Fax on Demand, Release 11 1703
Meridian Mail Feature Operations Video 1718
Meridian Mail Features 1698
Meridian Mail Features and Functionality Brochure 372, 1485
Meridian Mail Functionality Service Fee 1188, 1511
Meridian Mail GP 20 Ports 26/54 Hours Base Package 1608
Meridian Mail GP 20 Ports 84/114 Hours Base Package 1608
Meridian Mail GP 36 Ports 45/90 Hours Base Package 1608
Meridian Mail GP 4 Ports 11/24 Hours Base Package 1607
Meridian Mail GP 4 Ports 36/54 Hours Base Package 1607
Meridian Mail GP 48 Ports 180/240 Hours Base Package 1608
Meridian Mail GP 48 Ports 60/120 Hours Base Package 1608
Meridian Mail GP Brochure 372, 1485
Meridian Mail GP from 1 to 2 Node Expansion Package 1608
Meridian Mail GP from 12 to 16 Ports, 300MB Disk, Expansion Package 1608
Meridian Mail GP from 2 to 3 Node Expansion Package 1565
Meridian Mail GP from 24 to 28 Ports, 1.0GB Disk, Expansion Package 1608
Meridian Mail GP from 24 to 28 Ports, 300MB Disk, Expansion Package 1608
Meridian Mail GP from 3 to 4 Node Expansion Package 1565
Meridian Mail GP from 4 to 5 Node Expansion Package 1608
Meridian Mail GP from 48 to 52 Ports, 300MB Disk, Expansion Package 1608
Meridian Mail GP Multi-SMDI Software 257, 1263, 1517
Meridian Mail GP Reference Manual 346, 1484
Meridian Mail GP Spares Kit I 1608
Meridian Mail GP Spares Kit II 1608
Meridian Mail GP/X Cabinet Release 8 Tape Drive Upgrade Package 1711
Meridian Mail Guest Voice Messaging Software 1536
Meridian Mail Hardware Key Code Service 237, 247, 259, 260, 1184, 1510
Meridian Mail Hospitality Voice Services (HVS) Hardware Kit 1607
Meridian Mail Hospitality Voice Services Installation and Administration Study Guide 1569
Meridian Mail HVS Collateral, American Spanish 1658
Meridian Mail HVS Collateral, Brazilian Portuguese 1659
Meridian Mail HVS Collateral, European French 1658

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail HVS GAC/Guest Voice Messaging Reference Guide - MM13 349, 1496
Meridian Mail HVS User Guide, American, Spanish 352, 1484
Meridian Mail HVS User Guide, Brazilian, Portuguese 353, 1485
Meridian Mail HVS User Guide, European, French 352, 1484
Meridian Mail Link 154, 1249, 1516
Meridian Mail Master Tape - Asia/Pacific 1592
Meridian Mail Master Tape - Asia/Pacific, Release 10 1593, 1614
Meridian Mail Master Tape - Asia/Pacific, Release 8 1592
Meridian Mail Master Tape - Asia/Pacific, Release 9 1592, 1593
Meridian Mail Master Tape - Europe 1, Release 10 1592, 1613
Meridian Mail Master Tape - Europe 1, Release 9 1592, 1593
Meridian Mail Master Tape - Europe 2, Release 10 1592, 1613, 1614
Meridian Mail Master Tape - Europe 2, Release 9 1592, 1593
Meridian Mail Master Tape - Europe 3, Release 10 1592, 1593, 1614
Meridian Mail Master Tape - Europe 3, Release 9 1592, 1593
Meridian Mail Master Tape - Europe 4, Release 10 1593, 1614
Meridian Mail Master Tape - Europe 4, Release 9 1592, 1593
Meridian Mail Master Tape - European 1, Release 8 1592
Meridian Mail Master Tape - European 2, Release 8 1592
Meridian Mail Master Tape - European 3, Release 8 1592
Meridian Mail Master Tape - North America, Release 10 1592
Meridian Mail Master Tape - North American (Standalone), Release 10 1593
Meridian Mail Master Tape - North American, Release 10 1613
Meridian Mail Master Tape - North American, Release 8 1592
Meridian Mail Master Tape - North American, Release 9 1592, 1593
Meridian Mail Master Tape, Asia/Pacific 1 - Release 11 1594
Meridian Mail Master Tape, Asia/Pacific 1 - Release 11.19 231, 242, 253, 565, 1405
Meridian Mail Master Tape, Asia/Pacific 1 - Release 12 1594
Meridian Mail Master Tape, Asia/Pacific 1 - Release 12.13 232, 243, 254, 567, 1405
Meridian Mail Master Tape, Asia/Pacific 1 - Release 13 25, 1599
Meridian Mail Master Tape, Asia/Pacific 2 - Release 11 1594
Meridian Mail Master Tape, Asia/Pacific 2 - Release 11.19 231, 242, 253, 565, 1405
Meridian Mail Master Tape, Asia/Pacific 2 - Release 12 1594
Meridian Mail Master Tape, Asia/Pacific 2 - Release 12.13 233, 243, 255, 568, 1405
Meridian Mail Master Tape, Asia/Pacific 2 - Release 13 25, 1599
Meridian Mail Master Tape, European 1 - Release 11 1594
Meridian Mail Master Tape, European 1 - Release 11.19 230, 241, 252, 563, 1405
Meridian Mail Master Tape, European 1 - Release 12 1594
Meridian Mail Master Tape, European 1 - Release 12.13 232, 242, 254, 566, 1405
Meridian Mail Master Tape, European 1 - Release 13 25, 1598
Meridian Mail Master Tape, European 2 - Release 11 1594
Meridian Mail Master Tape, European 2 - Release 11.19 230, 241, 252, 563, 1405
Meridian Mail Master Tape, European 2 - Release 12 1594
Meridian Mail Master Tape, European 2 - Release 12.13 232, 242, 254, 566, 1405
Meridian Mail Master Tape, European 2 - Release 13 25, 1599
Meridian Mail Master Tape, European 3 - Release 11 1594
Meridian Mail Master Tape, European 3 - Release 11.19 231, 241, 253, 564, 1405
Meridian Mail Master Tape, European 3 - Release 12 1594
Meridian Mail Master Tape, European 3 - Release 12.13 232, 243, 254, 566, 1405
Meridian Mail Master Tape, European 3 - Release 13 25, 1599
Meridian Mail Master Tape, European 4 - Release 11 1594
Meridian Mail Master Tape, European 4 - Release 11.19 231, 241, 253, 564, 1405
Meridian Mail Master Tape, European 4 - Release 12 1594
Meridian Mail Master Tape, European 4 - Release 12.13 232, 243, 254, 567, 1405
Meridian Mail Master Tape, European 4 - Release 13 25, 1599

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Master Tape, European 5 - Release 11 1594
Meridian Mail Master Tape, European 5 - Release 11.19 231, 241, 253, 564, 1405
Meridian Mail Master Tape, European 5 - Release 12 1594
Meridian Mail Master Tape, European 5 - Release 12.13 232, 243, 254, 567, 1405
Meridian Mail Master Tape, European 5 - Release 13 25, 1599
Meridian Mail Master Tape, North American - Release 11 1593
Meridian Mail Master Tape, North American - Release 12 1594
Meridian Mail Master Tape, North American 1 - Release 12.13 231, 242, 253, 565, 1405
Meridian Mail Master Tape, North American 1 - Release 13 25, 1598
Meridian Mail Master Tape, North American 2 - Release 11 1594
Meridian Mail Master Tape, North American 2 - Release 11.19 230, 241, 252, 563, 1405
Meridian Mail Master Tape, North American 2 - Release 12 1594
Meridian Mail Master Tape, North American 2 - Release 12.13 231, 242, 253, 566, 1405
Meridian Mail Master Tape, North American 2 - Release 13 25, 1598
Meridian Mail Messaging User Guide Package (DMS) (English) (50/Pkg) 1595
Meridian Mail Migration 265, 1259, 1517
Meridian Mail Migration to Modular GP Prime Node, 1.0GB Package DC 1711
Meridian Mail Migration to Modular GP Prime Node, 300MB Package DC 1711
Meridian Mail Migration to Modular GP Voice Node, 300MB Package DC 1711
Meridian Mail Migration to Modular GP Voice Node, 600MB/1.0GB Package DC 1711
Meridian Mail Migration to Modular Option GP Prime Node, 300MB Package DC 265, 1320, 1520
Meridian Mail Migration to Modular Option GP Prime Node, 600MB/1GB Package DC 265, 1321, 1520
Meridian Mail Migration to Modular Option GP Voice Node, 300MB Package DC 265, 1320, 1520
Meridian Mail Migration to Modular Option GP Voice Node, 600MB/1GB Package DC 265, 1321, 1520
Meridian Mail Migration to Modular Option Prime Node, 1.0GB Package AC 1711
Meridian Mail Migration to Modular Option Prime Node, 1.0GB Package DC 1711
Meridian Mail Migration to Modular Option Prime Node, 300MB Package AC 264, 1314, 1520, 1711
Meridian Mail Migration to Modular Option Prime Node, 300MB Package DC 264, 1314, 1520, 1711
Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package AC 264, 1316, 1520
Meridian Mail Migration to Modular Option Prime Node, 600MB/1GB Package DC 264, 1316, 1520
Meridian Mail Migration to Modular Option Voice Node, 1.0GB Package AC 1711
Meridian Mail Migration to Modular Option Voice Node, 1.0GB Package DC 1711
Meridian Mail Migration to Modular Option Voice Node, 300MB Package AC 264, 1315, 1520, 1711
Meridian Mail Migration to Modular Option Voice Node, 300MB Package DC 264, 1315, 1520, 1711
Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package AC 264, 1317, 1520
Meridian Mail Migration to Modular Option Voice Node, 600MB/1GB Package DC 264, 1317, 1520
Meridian Mail Mini Networking Package 33, 230, 912, 1453
Meridian Mail Mini Option, 2 Ports, 2 Hours Package 230, 1052, 1470
Meridian Mail Mini Option, 4 Ports, 5 Hours Package 230, 1052, 1470
Meridian Mail Mini Option, 8 Ports, 5 Hours Package 230, 1053, 1470
Meridian Mail Modem Kit 1608
Meridian Mail Modem Package 240, 250, 269, 713, 1432, 1616
Meridian Mail Modem Setup Document 1666
Meridian Mail Modular 1.0GB Disk/Tape Drive Upgrade 1712
Meridian Mail Modular 1.0GB Hard Disk/Tape Drive Unit 1407, 1596
Meridian Mail Modular 300MB Hard Disk/Tape Drive Unit 1407, 1596
Meridian Mail Modular EC 16-24 Port 26/54 Hours Package AC 1709
Meridian Mail Modular EC 16-24 Port 26/54 Hours Package DC 1709
Meridian Mail Modular EC 16-24 Port 54/114/200 Hours Package AC 1709
Meridian Mail Modular EC 16-24 Port 54/114/200 Hours Package DC 1709
Meridian Mail Modular EC 28-32 Port 30/60 Hours

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Package AC 1709
Meridian Mail Modular EC 28-32 Port 30/60 Hours Package DC 1709
Meridian Mail Modular EC 28-32 Port 60/120/200 Hours Package AC 1709
Meridian Mail Modular EC 28-32 Port 60/120/200 Hours Package DC 1709
Meridian Mail Modular EC 2GB Disk Drive Upgrade 263, 1322, 1520
Meridian Mail Modular EC 2GB Disk Drive with Power Upgrade 263, 1322, 1520
Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package AC 258, 479, 1380
Meridian Mail Modular EC 2GB Disk Shadowing 3/5 Node Package DC 258, 479, 1380
Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package AC 258, 480, 1380
Meridian Mail Modular EC 2GB Disk Shadowing 4 Node Package DC 258, 480, 1380
Meridian Mail Modular EC 300MB Disk Shadowing 3/5 Node Package AC 1565
Meridian Mail Modular EC 300MB Disk Shadowing 3/5 Node Package DC 1565
Meridian Mail Modular EC 300MB Disk Shadowing 4 Node Package AC 1565
Meridian Mail Modular EC 300MB Disk Shadowing 4 Node Package DC 1565
Meridian Mail Modular EC 300MB Hard Disk Drive 1409, 1597
Meridian Mail Modular EC 300MB Hard Disk Drive with Power 1409, 1597
Meridian Mail Modular EC 36-48 Port 45/90 Hours Package AC 1709
Meridian Mail Modular EC 36-48 Port 45/90 Hours Package DC 1709
Meridian Mail Modular EC 36-48 Port 90/180/300 Hours Package AC 1709
Meridian Mail Modular EC 36-48 Port 90/180/300 Hours Package DC 1709
Meridian Mail Modular EC 4-12 Port 11/24 Hours Package AC 1709
Meridian Mail Modular EC 4-12 Port 11/24 Hours Package DC 1709
Meridian Mail Modular EC 4-12 Port 24/54/100 Hours Package AC 1709
Meridian Mail Modular EC 4-12 Port 24/54/100 Hours Package DC 1709
Meridian Mail Modular EC 52-64 Port 120/240/400 Hours Package AC 1709
Meridian Mail Modular EC 52-64 Port 120/240/400 Hours Package DC 1709
Meridian Mail Modular EC 52-64 Port 60/120 Hours Package AC 1709
Meridian Mail Modular EC 52-64 Port 60/120 Hours Package DC 1709
Meridian Mail Modular EC Alternative Remote Access Package 1565
Meridian Mail Modular EC Installation & Maintenance Quick Reference Manual, Release 10 345, 587, 1410
Meridian Mail Modular EC Node Expansion 1st Position Package AC 260, 476, 1380
Meridian Mail Modular EC Node Expansion 1st Position Package DC 260, 476, 1380
Meridian Mail Modular EC Node Expansion 1st Position, 300MB Disk, Package AC 1564
Meridian Mail Modular EC Node Expansion 1st Position, 300MB Disk, Package DC 1565
Meridian Mail Modular EC Node Expansion 2nd Position Package AC 260, 477, 1380
Meridian Mail Modular EC Node Expansion 2nd Position Package DC 260, 477, 1380
Meridian Mail Modular EC Node Expansion 2nd Position, 300MB Disk, Package AC 1565
Meridian Mail Modular EC Node Expansion 2nd Position, 300MB Disk, Package DC 1565
Meridian Mail Modular EC Node Expansion 3rd Position Package 260, 478, 1380
Meridian Mail Modular EC Node Expansion 3rd Position, 300MB Disk, Package 1565
Meridian Mail Modular EC Spares Package 1 1565
Meridian Mail Modular EC Spares Package 2 1565
Meridian Mail Modular EC Tape Drive Unit 1409, 1597
Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive 1409, 1597
Meridian Mail Modular EC/EC11 1.0GB Hard Disk Drive with Power 1409, 1597
Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive 249, 267, 579, 1409
Meridian Mail Modular EC/EC11 4.5GB Hard Disk Drive with Power 246, 249, 258, 267, 579, 1409
Meridian Mail Modular GP 16-24 Port 26/54 Hour Package DC 1709
Meridian Mail Modular GP 16-24 Port 54/114 Hour Package DC 1709
Meridian Mail Modular GP 28-32 Port 30/60 Hour Package DC 1709
Meridian Mail Modular GP 28-32 Port 60/120 Hour Package DC 1709
Meridian Mail Modular GP 36-48 Port 45/90 Hour Package DC 1709
Meridian Mail Modular GP 36-48 Port 90/180 Hour Package DC 1709
Meridian Mail Modular GP 4-12 Port 11/24 Hour Package DC 1709
Meridian Mail Modular GP 4-12 Port 24/54 Hour

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Package DC 1709
Meridian Mail Modular GP 52-64 Port 120/240 Hour Package DC 1710
Meridian Mail Modular GP 52-64 Port 60/120 Hour Package DC 1709
Meridian Mail Modular GP from 12 to 16 Ports, 1.0GB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 12 to 16 Ports, 300MB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 24 to 28 Ports, 1.0GB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 24 to 28 Ports, 300MB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 32 to 36 Ports, 1.0GB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 32 to 36 Ports, 300MB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 48 to 52 Ports, 1.0GB Disk, Expansion Package DC 1565
Meridian Mail Modular GP from 48 to 52 Ports, 300MB Disk, Expansion Package DC 1565
Meridian Mail Modular GP MMP40 1 to 2 Node Expansion Package DC 261, 486, 1381
Meridian Mail Modular GP MMP40 2 to 3 Node Expansion Package DC 261, 486, 1381
Meridian Mail Modular GP MMP40 3 to 4 Node Expansion Package DC 261, 487, 1381
Meridian Mail Modular GP MMP40 4 to 5 Node Expansion Package DC 261, 487, 1381
Meridian Mail Modular GP Power Supply DC 266, 570, 1406, 1442, 1622
Meridian Mail Modular GP Reference Manual, Release 8 347, 1485
Meridian Mail Modular GP Release 5 to Release 11 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 5 to Release 12 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 5 to Release 13 Upgrade or Migration from GP to Modular GP 263, 1074, 1472
Meridian Mail Modular GP Release 7 to Release 11 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 7 to Release 12 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 7 to Release 13 Upgrade or Migration from GP to Modular GP 263, 265, 1075, 1472
Meridian Mail Modular GP Release 8 to Release 11 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 8 to Release 12 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 8 to Release 13 Upgrade or Migration from GP to Modular GP 263, 265, 1076, 1472
Meridian Mail Modular GP Release 9/10 to Release 11 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 9/10/11 to Release 12 Upgrade or Migration from GP to Modular GP 1713
Meridian Mail Modular GP Release 9/10/11/12 to Release 13 Upgrade or Migration from GP to Modular GP 263, 1077, 1472
Meridian Mail Modular GP Spares Package 266, 342, 488, 1381
Meridian Mail Modular HVS Package 248, 266, 474, 1380
Meridian Mail Modular Option 2GB Disk Drive Upgrade 263, 264, 265, 1322, 1520
Meridian Mail Modular Option 300MB Disk Drive Upgrade 1712
Meridian Mail Modular Option EC Installation & Maintenance Quick Reference Guide, Release 9 353, 1487
Meridian Mail Modular Option EC Reference Manual 347, 1484
Meridian Mail Modular Option EC Reference Manual, Release 10 345, 585, 1410
Meridian Mail Modular Option EC Release 9 Reference Manual 1595
Meridian Mail Modular Option EC/EC11 Spares Package 1 266, 342, 488, 1381
Meridian Mail Modular Option EC/EC11 Spares Package 2 266, 342, 488, 1381
Meridian Mail Modular Option Enhanced Capacity (EC) Installation Photo Guide 350, 1383
Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package AC 261, 1085, 1472
Meridian Mail Modular Option Enhanced Processor 1 to 2 Node Expansion Package DC 262, 1086, 1472
Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package AC 262, 1087, 1472
Meridian Mail Modular Option Enhanced Processor 2 to 3 Node, Expansion Package DC 262, 1088, 1472
Meridian Mail Modular Option Enhanced Processor 3 to 4 Node Expansion Package AC 262, 1089, 1472
Meridian Mail Modular Option Enhanced Processor 3 to

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

4 Node Expansion Package DC 262, 1090, 1472
Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package AC 262, 1091, 1473
Meridian Mail Modular Option Enhanced Processor 4 to 5 Node Expansion Package DC 262, 1092, 1473
Meridian Mail Modular Option Expansion Package Networking Kit 1564
Meridian Mail Modular Option Expansion Package Spares Kit AC 1564
Meridian Mail Modular Option Expansion Package Spares Kit DC 1564
Meridian Mail Modular Option from 1 to 2 Node, Expansion Package AC 1564
Meridian Mail Modular Option from 1 to 2 Node, Expansion Package DC 1564
Meridian Mail Modular Option from 12 to 16 Ports, 300MB Disk, Expansion Package AC 1563
Meridian Mail Modular Option from 12 to 16 Ports, 300MB Disk, Expansion Package DC 1564
Meridian Mail Modular Option from 2 to 3 Node, Expansion Package AC 1564
Meridian Mail Modular Option from 2 to 3 Node, Expansion Package DC 1564
Meridian Mail Modular Option from 24 to 28 Ports, 1.0GB Disk, Expansion Package AC 1564
Meridian Mail Modular Option from 24 to 28 Ports, 1.0GB Disk, Expansion Package DC 1564
Meridian Mail Modular Option from 24 to 28 Ports, 300MB Disk, Expansion Package AC 1564
Meridian Mail Modular Option from 24 to 28 Ports, 300MB Disk, Expansion Package DC 1564
Meridian Mail Modular Option from 28 to 32 Ports, 300MB Disk, Expansion Package AC 1564
Meridian Mail Modular Option from 28 to 32 Ports, 300MB Disk, Expansion Package DC 1564
Meridian Mail Modular Option from 3 to 4 Node, Expansion Package AC 1564
Meridian Mail Modular Option from 3 to 4 Node, Expansion Package DC 1564
Meridian Mail Modular Option from 32 to 36 Ports, 300MB Disk, Expansion Package AC 1564
Meridian Mail Modular Option from 32 to 36 Ports, 300MB Disk, Expansion Package DC 1564
Meridian Mail Modular Option from 4 to 5 Node, Expansion Package AC 1564
Meridian Mail Modular Option from 4 to 5 Node, Expansion Package DC 1564
Meridian Mail Modular Option from 48 to 52 Ports, 300MB Disk, Expansion Package AC 1564
Meridian Mail Modular Option from 48 to 52 Ports, 300MB Disk, Expansion Package DC 1564
Meridian Mail Modular Option GP Installation Photo Guide 350, 1383
Meridian Mail Modular Option GP Reference Manual, Release 10 345, 585, 1410
Meridian Mail Modular Option GP Reference Manual, Release 9 1595
Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package AC 261, 481, 1380
Meridian Mail Modular Option MMP40 1 to 2 Node Expansion Package DC 261, 482, 1380
Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package AC 261, 482, 1380
Meridian Mail Modular Option MMP40 2 to 3 Node, Expansion Package DC 261, 483, 1380
Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package AC 261, 484, 1380
Meridian Mail Modular Option MMP40 3 to 4 Node Expansion Package DC 261, 484, 1380
Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package AC 261, 485, 1381
Meridian Mail Modular Option MMP40 4 to 5 Node Expansion Package DC 261, 485, 1381
Meridian Mail Modular Option Package 16 Ports 26/54 Hours AC 1708
Meridian Mail Modular Option Package 16 Ports 26/54 Hours DC 1708
Meridian Mail Modular Option Package 16 Ports 84/114 Hours AC 1708
Meridian Mail Modular Option Package 16 Ports 84/114 Hours DC 1709
Meridian Mail Modular Option Package 24 Ports 120/180 Hours AC 1708
Meridian Mail Modular Option Package 24 Ports 120/180 Hours DC 1708
Meridian Mail Modular Option Package 24 Ports 45/90 Hours AC 1708
Meridian Mail Modular Option Package 24 Ports 45/90 Hours DC 1708
Meridian Mail Modular Option Package 4 Ports 11/24 Hours DC 1708
Meridian Mail Modular Option Package 4 Ports 36/54 Hours AC 1708
Meridian Mail Modular Option Package 4 Ports 36/54 Hours DC 1708
Meridian Mail Modular Option Package 4 Ports 5/11 Hours AC 1708
Meridian Mail Modular Option Package 4 Ports 5/11 Hours DC 1708
Meridian Mail Modular Option Package 4 Ports, 11/24 Hours AC 1708
Meridian Mail Modular Option Package 40 Ports 180/240 Hours AC 1709
Meridian Mail Modular Option Package 40 Ports 180/240 Hours DC 1709

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Modular Option Package 40 Ports 60/120 Hours AC 1709
Meridian Mail Modular Option Package 40 Ports 60/120 Hours DC 1709
Meridian Mail Modular Option Reference Manual Release 7 1654
Meridian Mail Modular Option Reference Manual, Release 10 345, 585, 1410
Meridian Mail Modular Option Reference Manual, Release 8 352, 1484
Meridian Mail Modular Option Release 5 to Release 11 Upgrade or Migration from Options to Modular Option 1712
Meridian Mail Modular Option Release 5 to Release 12 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 5 to Release 13 Upgrade or Migration from Options to Modular Option 264, 266, 1078, 1472
Meridian Mail Modular Option Release 6/7 to Release 11 Upgrade or Migration from Options to Modular Option 1712
Meridian Mail Modular Option Release 6/7 to Release 12 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 6/7 to Release 13 Upgrade or Migration from Options to Modular Option 264, 266, 1080, 1472
Meridian Mail Modular Option Release 8 to Release 11 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 8 to Release 12 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 8 to Release 13 Upgrade or Migration from Options to Modular Option 264, 266, 1081, 1472
Meridian Mail Modular Option Release 9/10 to Release 11 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 9/10/11 to Release 12 Upgrade or Migration from Options to Modular Option 1713
Meridian Mail Modular Option Release 9/10/11/12 to Release 13 Upgrade or Migration from Options to Modular Option 264, 266, 1082, 1472
Meridian Mail Modular Option with Guest Voice Messaging Reference Manual 1654
Meridian Mail Modular Options Manual 344, 1387
Meridian Mail Modular Options Reference Manual Release 5 1653
Meridian Mail Modular Options Reference Manual Release 6 1654
Meridian Mail Modular RSM Package 266, 475, 1380
Meridian Mail Module AC 269, 573, 1407
Meridian Mail Module DC 269, 573, 1407
Meridian Mail MP ACCESS Software 1651
Meridian Mail MP Option 16 1533
Meridian Mail MP Option 36 1533
Meridian Mail MP Option 48 1533
Meridian Mail MP Package (12) 1637
Meridian Mail MP Package (16) 1637
Meridian Mail MP Package (4) 1637, 1638
Meridian Mail MP Package (8) 1637
Meridian Mail MP SFS 1650
Meridian Mail MP Voice Menus Option 1536
Meridian Mail MP.4 Hardware Configuration 1651
Meridian Mail MP.4 Install/Software Configuration 1651
Meridian Mail MP.4 Seer Manual 1651
Meridian Mail MP.4 Voice Messaging Pocket Guide (100/PK) 1651
Meridian Mail MP.4 Voice Messaging User Guide 1651
Meridian Mail MP.4 Voice Messaging User Guide (15/PK) 1651
Meridian Mail MSM Brochure 372, 1485
Meridian Mail Multi-Customer 257, 1258, 1517, 1703
Meridian Mail Multi-Customer (GP), Release 11 1703
Meridian Mail Multi-Customer Administration 1569
Meridian Mail Multi-Customer System Administration Reference Manual 347, 1485
Meridian Mail Multi-Customer System Reference Manual (DMS), Release 10 345, 586, 1410
Meridian Mail Multi-Customer System Reference Manual, Release 10 345, 585, 1410
Meridian Mail Multi-Customer Systems Reference Manual (DMS), Release 9 345, 1406
Meridian Mail Multi-Customer, Release 10 1703
Meridian Mail Multi-Customer, Release 11 1703
Meridian Mail Multi-Customer, Release 8 1703
Meridian Mail Multi-Customer, Release 9 1703
Meridian Mail Multi-Media Services Reference Manual 351, 568, 1406
Meridian Mail Multiple Administration 257, 1259, 1517
Meridian Mail Net Gateway 236, 246, 257, 538, 1399
Meridian Mail Networking 1700
Meridian Mail Networking / Enterprise Networking, Release 11 1700
Meridian Mail Networking Hardware Package 1639
Meridian Mail Networking Kit 1608
Meridian Mail Networking Modem Package 248, 266, 475, 1380
Meridian Mail Networking Option 1536
Meridian Mail Networking Services Administration

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Guide 351, 568, 1406
Meridian Mail Networking/Enterprise Networking 257, 1255, 1516
Meridian Mail NTP Card Option 346, 1484
Meridian Mail Option 1533, 1534
Meridian Mail Option - S Cabinet 12 Port 24 Hours Package 1607
Meridian Mail Option - S Cabinet 16 Port 26 Hours Package 1607
Meridian Mail Option - S Cabinet 16 Port 84 Hours 1607
Meridian Mail Option - S Cabinet 4 Port 11 Hours Package 1607
Meridian Mail Option - S Cabinet 4 Port 24 Hours Package 1607
Meridian Mail Option - S Cabinet 4 Port 36 Hours Package 1607
Meridian Mail Option - S Cabinet 4 Port 5 Hours Package 1607
Meridian Mail Option - S Cabinet 8 Port 11 Hours Package 1607
Meridian Mail Option - S Cabinet 8 Port 24 Hours Package 1607
Meridian Mail Option - X Cabinet 20 Ports 26/54 Hours Package 1608
Meridian Mail Option - X Cabinet 20 Ports 84/114 Hours Package 1608
Meridian Mail Option - X Cabinet 36 Ports 120/180 Hours Package 1608
Meridian Mail Option - X Cabinet 36 Ports 45/90 Hours Package 1608
Meridian Mail Option - X Cabinet 4 Ports 11/24 Hours Package 1608
Meridian Mail Option - X Cabinet 4 Ports 36/54 Hours Package 1608
Meridian Mail Option - X Cabinet 48 Ports 180/240 Hours Package 1608
Meridian Mail Option - X Cabinet 48 Ports 60/120 Hours Package 1608
Meridian Mail Option - X Cabinet Spares Kit I 1608
Meridian Mail Option - X Cabinet Spares Kit II 1608
Meridian Mail Option - X Cabinet Upgrade Package 1609
Meridian Mail Option (Option and ST/RT Option) 5 Hour Software 1534
Meridian Mail Option (Option and ST/RT Option) 5 to 11 Hours Software 1534
Meridian Mail Option (Option and ST/RT Option) Base Software 1534
Meridian Mail Option (Option and ST/RT Option) Expanded Storage Software 1534
Meridian Mail Option 11 ACCESS Enable Option 236, 245, 1268, 1517
Meridian Mail Option 11 ACCESS Enable Option, Release 10 & 11 1704
Meridian Mail Option 11 Additional Language 235, 245, 1266, 1517
Meridian Mail Option 11 AMIS Networking 236, 246, 1268, 1517, 1704
Meridian Mail Option 11 AMIS Networking, Release 11 1704
Meridian Mail Option 11 AutoAdmin Link Software 236, 245, 1269, 1517
Meridian Mail Option 11 AutoAdmin Software Package 1566
Meridian Mail Option 11 AutoAdmin Software Package - MM13 235, 245, 865, 1448
Meridian Mail Option 11 Dual Language Prompt 235, 245, 1266, 1517
Meridian Mail Option 11 Fax on Demand Software 235, 245, 1265, 1517
Meridian Mail Option 11 Fax on Demand Software, Release 11 1704
Meridian Mail Option 11 Fax on Demand Software, Release 9, 10 1704
Meridian Mail Option 11 HVS Software 235, 245, 1266, 1517, 1704
Meridian Mail Option 11 HVS Software, Release 11 1704
Meridian Mail Option 11 Multi-Customer 236, 245, 1267, 1517
Meridian Mail Option 11 Multi-Customer, Release 10 1704
Meridian Mail Option 11 Multi-Customer, Release 11 1704
Meridian Mail Option 11 Network Message Service Software 236, 246, 1268, 1517
Meridian Mail Option 11 Network Message Services, Prime Site, Release 11 and Later 236, 246, 1270, 1518
Meridian Mail Option 11 Network Message Services, Remote Site, Release 11 and Later 236, 246, 1270, 1518
Meridian Mail Option 11 Networking Software 1704
Meridian Mail Option 11 Networking Software, Release 11 or Later 236, 246, 1267, 1517
Meridian Mail Option 11 Networking/Enterprise Networking Software, Release 11 1704
Meridian Mail Option 11 Outcalling 236, 245, 1269, 1518
Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12, 13) 236, 246, 865, 1448
Meridian Mail Option 11 Reporter Single-Site to Multi-Site Upgrade Package (Releases 10, 11, 12) 1711
Meridian Mail Option 11 VMUIF 236, 245, 1270, 1518

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Option 11 Voice Forms 235, 245, 1267, 1517
Meridian Mail Option 11 Voice Forms Software, Release 9-11 1704
Meridian Mail Option 12 Port 24 Hours Cantilever Mount 1597
Meridian Mail Option 12 Port 24 Hours Center Mount 1598
Meridian Mail Option 16 Ports 26/54 Hours Package (Cantilever Mount) 1597
Meridian Mail Option 16 Ports 26/54 Hours Package (Center Mount) 1598
Meridian Mail Option 16 Ports 84/114 Hours Package (Cantilever Mount) 1597
Meridian Mail Option 16 Ports 84/114 Hours Package (Center Mount) 1598
Meridian Mail Option 4 Port 24 Hours Cantilever Mount 1597
Meridian Mail Option 4 Port 24 Hours Center Mount 1598
Meridian Mail Option 4 Port 5 Hours Cantilever Mount 1597
Meridian Mail Option 4 Port 5 Hours Center Mount 1598
Meridian Mail Option 4 Ports 11/24 Hours Package (Cantilever Mount) 1597
Meridian Mail Option 4 Ports 11/24 Hours Package (Center Mount) 1598
Meridian Mail Option 4 Ports 36/54 Hours Package (Cantilever Mount) 1597
Meridian Mail Option 4 Ports 36/54 Hours Package (Center Mount) 1598
Meridian Mail Option 4 Ports 5/11 Hours Package (Cantilever Mount) 1597
Meridian Mail Option 4 Ports 5/11 Hours Package (Center Mount) 1598
Meridian Mail Option 8 1533
Meridian Mail Option 8 Port 11 Hours Cantilever Mount 1597
Meridian Mail Option 8 Port 11 Hours Center Mount 1598
Meridian Mail Option 8 Port 24 Hours Cantilever Mount 1597
Meridian Mail Option 8 Port 24 Hours Center Mount 1598
Meridian Mail Option from 12 to 16 Port Expansion Package (Cantilever Mount) 1598
Meridian Mail Option from 12 to 16 Port Expansion Package (Center Mount) 1598
Meridian Mail Option from 12 to 16 Ports, 300MB Disk, Expansion Package (Cantilever Mount) 1598
Meridian Mail Option from 12 to 16 Ports, 300MB Disk, Expansion Package (Center Mount) 1598
Meridian Mail Option MMP40 1 to 2 Node Expansion Package (Cantilever Mount) 1565
Meridian Mail Option MMP40 1 to 2 Node Expansion Package (Center Mount) 1565
Meridian Mail Option NT/XT SFS 1650
Meridian Mail Option SFS 1649
Meridian Mail Option Software ACCESS Development Software 1651
Meridian Mail Option Spares Kit I 1607
Meridian Mail Option Spares Kit II 1607
Meridian Mail Option X Cabinet Base Software 1538
Meridian Mail Option X Cabinet Expanded Storage Software 1538
Meridian Mail Options (Networking) Reference Manual Release 6 1654
Meridian Mail Options (NT/XT) Release 10 Upgrade Package 1711
Meridian Mail Options (ST/RT) Release 10 Upgrade Package 1711
Meridian Mail Options NTP Release 5 1653
Meridian Mail Options Reference Manual 346, 1484, 1649, 1654
Meridian Mail Options Reference Manual, Release 10 345, 584, 1410
Meridian Mail Outcalling 257, 1262, 1517
Meridian Mail Package (12) 1638
Meridian Mail Package (20) 1638
Meridian Mail Package (24) 1638
Meridian Mail Package (28) 1639
Meridian Mail Package (40) 1639
Meridian Mail PC Software 1651
Meridian Mail PE Shelf (Cantilever) 1400, 1588
Meridian Mail PE Shelf (Center) 1400, 1588
Meridian Mail Product Sales Guide Revision 1 1649
Meridian Mail Product Sales Guide Update 1649
Meridian Mail Quick Reference Cards (Package of 30) 352, 1485
Meridian Mail Quick Reference Cards (PKG of 30) 1563
Meridian Mail Release 10 Base Software 1700
Meridian Mail Release 10 to Release 11 Software Update Fee, EC11 1539
Meridian Mail Release 10.11 Master Tape - North American 2 250, 560, 1405
Meridian Mail Release 10.11 Master Tape Asia/Pacific 241, 251, 562, 1405
Meridian Mail Release 10.11 Master Tape Asia/Pacific Card Option 234, 699, 1429
Meridian Mail Release 10.11 Master Tape European 1 240, 250, 561, 1405
Meridian Mail Release 10.11 Master Tape European 2 240, 251, 561, 1405
Meridian Mail Release 10.11 Master Tape European 2 Card Option 234, 699, 1429
Meridian Mail Release 10.11 Master Tape European 3

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

251, 561, 1405
Meridian Mail Release 10.11 Master Tape European 3 Card Option 235, 700, 1429
Meridian Mail Release 10.11 Master Tape European 4 240, 251, 562, 1405
Meridian Mail Release 10.11 Master Tape European 4 Card Option 245, 255, 700, 1429
Meridian Mail Release 10.11 Master Tape European Card Option 234, 699, 1429
Meridian Mail Release 10.11 Master Tape North American 240, 250, 560, 1405
Meridian Mail Release 10.11 Master Tape North American Card Option 235, 700, 1429
Meridian Mail Release 11 Base Software 1700
Meridian Mail Release 11 Compact Option Port Expansion (Ports 5 & 6) 59, 822, 1441
Meridian Mail Release 11 Compact Option Port Expansion (Ports 7&8) 59, 822, 1441
Meridian Mail Release 11 or Release 12 to Release 13 Compact Option Software Upgrade Package 59, 805, 1437
Meridian Mail Release 11.19 Software Tape 59, 562, 1405
Meridian Mail Release 12 AMIS Networking Installation and Administration Guide 355, 1491
Meridian Mail Release 12 Base Software 1700
Meridian Mail Release 12 Card Option Installation and Maintenance Guide 347, 1491
Meridian Mail Release 12 CD ROM Package (NTPs) 345, 1404
Meridian Mail Release 12 Compact Option 4 Ports 24 Hours Package 58, 806, 1438
Meridian Mail Release 12 Compact Option Port Expansion (Ports 5 & 6) 59, 822, 1441
Meridian Mail Release 12 Compact Option Port Expansion (Ports 7 & 8) 59, 823, 1441
Meridian Mail Release 12 Difference Guide 350, 1383
Meridian Mail Release 12 Fax On Demand Application Guide 355, 1491
Meridian Mail Release 12 Feature Operations Video 355, 1521
Meridian Mail Release 12 HVS Implementation Guide 355, 1491
Meridian Mail Release 12 HVS/Guest Voice Messaging Reference Guide 355, 1491
Meridian Mail Release 12 Maintenance Messages (SEERs) 60, 1491
Meridian Mail Release 12 Modular Option EC Manual 344, 1387
Meridian Mail Release 12 Modular Option GP Manual 344, 1387
Meridian Mail Release 12 Network Message Services Installation and Administration Guide 355, 1491
Meridian Mail Release 12 Networking Installation and Administration Guide 355, 1491
Meridian Mail Release 12 Networking Planning Guide 355, 1491
Meridian Mail Release 12 Option 11 EC/EC11 Manual 344, 1387
Meridian Mail Release 12 Outcalling Application Guide 355, 1491
Meridian Mail Release 12 Overview 344, 1387
Meridian Mail Release 12 System Administration Manual EC, Modular Option, EC11, Card Option 344, 1404
Meridian Mail Release 12 System Administration Manual Multi-Customer EC, Modular Option, EC11, Card Option 344, 1404
Meridian Mail Release 12 System Administration Manual Multi-Customer, Modular Option GP/ MSM 345, 1404
Meridian Mail Release 12 System Administration Manual, Modular Option GP/MSM 345, 1404
Meridian Mail Release 12 System Administration Tools Guide 275, 1492
Meridian Mail Release 12 System Installation and Modification Guide 355, 1491
Meridian Mail Release 12 Voice Messaging "Updating Voice Menu Prompts" Card 355, 1492
Meridian Mail Release 12 Voice Messaging Package 60, 1387
Meridian Mail Release 12 Voice Messaging Package (VMUIF) 344, 507, 1387
Meridian Mail Release 12 Voice Messaging Quick Reference Card 355, 1492
Meridian Mail Release 12 Voice Services Application Guide 355, 1491
Meridian Mail Release 12.12 Master Tape Asia/Pacific 1 1594
Meridian Mail Release 12.12 Master Tape Asia/Pacific 2 1594
Meridian Mail Release 12.12 Master Tape European 2 1594
Meridian Mail Release 12.12 Master Tape European 5 1594
Meridian Mail Release 12.12 Master Tape European1 1594
Meridian Mail Release 12.12 Master Tape european3 1594
Meridian Mail Release 12.12 Master Tape European4 1594
Meridian Mail Release 12.12 Master Tape North American 1594
Meridian Mail Release 13 Base Software 230, 235, 256, 1051, 1140, 1470, 1480

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail Release 13 Call Answering (VMUIF) Package 344, 521, 1390
Meridian Mail Release 13 Card Option Installation and Maintenance Guide 349, 1496
Meridian Mail Release 13 CD ROM Package (NTP) 344, 521, 1389
Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 5 & 6) 59, 822, 1441
Meridian Mail Release 13 Compact Option Port Expansion Package (Ports 7 & 8) 59, 823, 1441
Meridian Mail Release 13 Feature Operations Video 355, 1497
Meridian Mail Release 13 Keycode 230, 1497
Meridian Mail Release 13 Modular Option EC Manuals 344, 520, 1389
Meridian Mail Release 13 Modular Option GP Manual 344, 520, 1389
Meridian Mail Release 13 Modular Option Manual 344, 520, 1389
Meridian Mail Release 13 Option 11 EC (EC11) Manual 344, 521, 1389
Meridian Mail Release 13 PC CD-ROM 345, 1433
Meridian Mail Release 13 Voice Messaging (VMUIF) Package 344, 522, 1390
Meridian Mail Release 13 Voice Messaging Package (15 Per Package) 344, 521, 1389
Meridian Mail Release 3 to 4 Software service transaction fee 1534
Meridian Mail Release 3 to 5 Software Service Fee 1537
Meridian Mail Release 3 to 6 Software Service Fee 1537
Meridian Mail Release 3 to Release 11 Software Migration, from Options to Modular Option 1712
Meridian Mail Release 3 to Release 12 Software Migration, from Options to Modular Option 1713
Meridian Mail Release 3 to Release 13 Software Migration, from Options to Modular Option 266, 1083, 1472
Meridian Mail Release 3 to Release 7 Software Migration, from Options to Modular EC 265, 378, 1364
Meridian Mail Release 3 to Release 8 Software Update Fee 1537
Meridian Mail Release 4 to 5 Software Service Fee 1537
Meridian Mail Release 4 to 6 Software Service Fee 1537
Meridian Mail Release 4 to Release 11 Software Migration, from Options to a Modular Option 1712
Meridian Mail Release 4 to Release 11 Software Migration, GP to Modular GP 1713
Meridian Mail Release 4 to Release 12 Software Migration, from Options to Modular Option 1713
Meridian Mail Release 4 to Release 12 Software Migration, GP to Modular GP 1713
Meridian Mail Release 4 to Release 13 Software Migration, from Options to Modular Option 266, 1084, 1472
Meridian Mail Release 4 to Release 13 Software Migration, GP to Modular GP 263, 1073, 1472
Meridian Mail Release 4 to Release 5 Hardware Package 1607
Meridian Mail Release 4 to Release 7 Software Migration, from Options to Modular EC 265, 378, 1364
Meridian Mail Release 4 to Release 8 Software Update Fee 1537
Meridian Mail Release 5 to 6 Software Service Fee 1537
Meridian Mail Release 5 to Release 7 Software Migration, from Options, Modular Option to Modular EC 265, 378, 1364
Meridian Mail Release 5 to Release 8 Software Update Fee 1537
Meridian Mail Release 5 to Release 8 Software Update Fee, GP 1538
Meridian Mail Release 5 to Release 8 Software Update Fee, Modular Option 1538
Meridian Mail Release 5 to Release 8 Software Update Fee, Options 1538
Meridian Mail Release 6 to Release 8 Software Migration, from Options to Modular EC 265, 379, 1364
Meridian Mail Release 6 to Release 8 Software Update Fee 1537
Meridian Mail Release 6 to Release 8 Software Update Fee, Modular Option 1538
Meridian Mail Release 6/7 to 9 Software Update, Modular Option 1538
Meridian Mail Release 6/7 to 9 Software Update, Options 1538
Meridian Mail Release 6/7 to Release 10 Software Update Fee, Modular Option 1538
Meridian Mail Release 6/7 to Release 10 Software Update Fee, Options 1538
Meridian Mail Release 6/7 to Release 8 Software Migration, from Modular Option to Modular EC 265, 380, 1364
Meridian Mail Release 7 to Release 8 Software Migration, from Options to Modular EC 265,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

379, 1364
Meridian Mail Release 7 to Release 8 Software Update Fee 1537
Meridian Mail Release 7 to Release 8 Software Update Fee, GP 1538
Meridian Mail Release 7 to Release 8 Software Update Fee, Modular Option 1538
Meridian Mail Release 8 Base Software 1700
Meridian Mail Release 8 Engineering Handbook 1659
Meridian Mail Release 8 Hardware Upgrade Package 1711
Meridian Mail Release 8 to 9 Software Update, Modular Option 1538
Meridian Mail Release 8 to 9 Software Update, Modular Option GP 1538
Meridian Mail Release 8 to 9 Software Update, Options 1538
Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option 1538
Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option EC 1538
Meridian Mail Release 8 to Release 10 Software Update Fee, Modular Option GP 1538
Meridian Mail Release 8 to Release 10 Software Update Fee, Options (ST/RT, NT/XT) 1538
Meridian Mail Release 8 to Release 9 Software Update Fee, EC 1538
Meridian Mail Release 8, 9 or 10 to Release 11 Migration, Options, Modular Option to Modular EC 1538
Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Card Option 1538
Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Modular Option 1538
Meridian Mail Release 8, 9 or 10 to Release 11 Software Update Fee, Modular Option GP 1538
Meridian Mail Release 8, 9, 10, 11, or 12 to Release 13 Migration, Options, Modular Option to Modular EC 256, 1070, 1472
Meridian Mail Release 8, 9, 10, or 11 to Release 12 Migration, Options, Modular Option to Modular EC 1539
Meridian Mail Release 9 ACCESS Developers Reference Manual 1595
Meridian Mail Release 9 ACCESS Enable Option Reference Manual 1595
Meridian Mail Release 9 Base Software 1700
Meridian Mail Release 9 Card Option Reference Manual 1595
Meridian Mail Release 9 HVS Administrative Reference Manual 1595
Meridian Mail Release 9 HVS GAC User Guide 353, 1486
Meridian Mail Release 9 Multi-customer System Reference Manual 1595
Meridian Mail Release 9 System Administration Reference Manual 1595
Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option 1538
Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option EC 1538
Meridian Mail Release 9 to Release 10 Software Update Fee, Modular Option GP 1538
Meridian Mail Release 9 to Release 10 Software Update Fee, Options (ST/RT, NT/XT) 1538
Meridian Mail Release 9 Voice Forms Transcriber User Guide 353, 1486
Meridian Mail Reporter 2.0 Multiple Site PC Software Package 1703
Meridian Mail Reporter 2.0 Single Site PC Software Package 1703
Meridian Mail Reporter 2.0 User Guide 354, 1156, 1490
Meridian Mail Reporter Multi Site Software 1566
Meridian Mail Reporter Multi Site Software Release 13 257, 1070, 1471
Meridian Mail Reporter Multi Site Software, Option 11 1566
Meridian Mail Reporter Multi Site Software, Option 11 - MM13 236, 246, 1066, 1471
Meridian Mail Reporter Multiple Site PC Software Package 1703
Meridian Mail Reporter One Year Extended Service Plan 236, 246, 257, 1200, 1512
Meridian Mail Reporter Product Sheet 372, 1481
Meridian Mail Reporter Release 1, Software Multi-Site North America Package 1606
Meridian Mail Reporter Release 2.0, Software Multi-Site North America Package 1606
Meridian Mail Reporter Release 2.0, Software Single Site North America Package 1606
Meridian Mail Reporter Single Site PC Software Package 1703
Meridian Mail Reporter Single Site Software 1566
Meridian Mail Reporter Single Site Software MM13 257, 1069, 1471
Meridian Mail Reporter Single Site Software, Option 11 1566
Meridian Mail Reporter Single Site Software, Option 11 MM13 236, 246, 1065, 1471
Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package 257, 866, 1448
Meridian Mail Reporter Single-Site to Multi-Site Upgrade Package (Release 10, 11, 12) 1711
Meridian Mail Reporter User Guide 1664
Meridian Mail Reports 1569
Meridian Mail RSM Package 1564
Meridian Mail Security 1569

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Mail SEERS Reference Manual, Release 10 345, 587, 1410
Meridian Mail Shelf (NT/XT) Option Release 8 Tape Drive Upgrade Package 1711
Meridian Mail Single Terminal Access Package 1564
Meridian Mail SL-1 300MB Disk Upgrade 1714
Meridian Mail SL-1 Option 1533
Meridian Mail SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 75, 77, 85) 1535, 1536
Meridian Mail Slide Updates to Revision 1, Release 4 1650
Meridian Mail SMDI Connections Software 256, 1263, 1517
Meridian Mail SMDI Software 257, 1262, 1517
Meridian Mail Software Service Transaction Fee 236, 246, 257, 1183, 1510
Meridian Mail SP 11 Software 1533
Meridian Mail SP 24 Software 1533
Meridian Mail SP 5 Software 1533
Meridian Mail SP and SL-1 Option Reference Manual 1651
Meridian Mail SP Reference Manual 1648
Meridian Mail SP SFS 1650
Meridian Mail SP Special Software Pkg (7, 17, 35, 109, 40, 45, 46, 77, 85) 1535, 1536
Meridian Mail Spares Kit (2 Meg) 1638
Meridian Mail Spares Kit (6 Meg) 1639
Meridian Mail ST/RT and Option 4 Ports 5/11 Hours Package 1606
Meridian Mail ST/RT and S Option 16 Port 84/114 Hours Package 1607
Meridian Mail ST/RT and S Option 16 Ports 26/54 Hours Package 1607
Meridian Mail ST/RT and S Option 4 Port 36/54 Hours Package 1607
Meridian Mail ST/RT and S Option 4 Ports 11/24 Hours Package 1607
Meridian Mail ST/RT Option 12 Port 24 Hours Package 1607
Meridian Mail ST/RT Option 4 Port 24 Hours Package 1607
Meridian Mail ST/RT Option 4 Port 5 Hours Package 1606
Meridian Mail ST/RT Option 8 Port 11 Hours Package 1607
Meridian Mail ST/RT Option 8 Port 24 Hours Package 1607
Meridian Mail ST/RT Option from 12 to 16 Port Expansion Package 1607
Meridian Mail ST/RT Option from 12 to 16 Ports, 300MB Disk, Expansion Package 1607
Meridian Mail ST/RT Option MMP40 1 to 2 Node Expansion Package 1565
Meridian Mail ST/RT Option Release 8 Tape Drive Upgrade Package 1711
Meridian Mail ST/RT Option Spares Kit Cantilever/ Center Mounts 1607
Meridian Mail System Administration Reference Manual 352, 1485
Meridian Mail System Administration Reference Manual (DMS), Release 10 345, 587, 1410
Meridian Mail System Administration Reference Manual (DMS), Release 9 345, 1406
Meridian Mail System Administration Reference Manual, Release 10 345, 586, 1410
Meridian Mail Tape Prep Fee 1536
Meridian Mail to CallPilot Migration Utility Tape and Documentation 250, 269, 913, 1453
Meridian Mail to Nortel CallPilot Migration Guide 228, 1493
Meridian Mail Train the Trainer 350, 1383
Meridian Mail Training Video 1718
Meridian Mail Upgrade/Expansion to Modular Option Package 1 to 2 Node 1712
Meridian Mail Upgrade/Expansion to Modular Option Package 2 to 4 Node 1712
Meridian Mail Upgrades Brochure 373, 1491
Meridian Mail VMUIF 257, 1264, 1517, 1703
Meridian Mail VMUIF, Option 11 1704
Meridian Mail Voice Forms 257, 1257, 1517, 1569, 1703
Meridian Mail Voice Forms, Release 8 1703
Meridian Mail Voice Menus Applications Guide 374, 1482
Meridian Mail Voice Messaging Pocket Guide Release 4 1651
Meridian Mail Voice Messaging User Guide (15/PK) 352, 1485
Meridian Mail Voice Messaging User Guide (can be used with Release 4,5 1653
Meridian Mail Voice Messaging User Guide Release 7 1654
Meridian Mail Voice Processing Solutions 1652
Meridian Mail X Cabinet from 1 to 2 Node Expansion Package 1608
Meridian Mail X Cabinet from 12 to 16 Ports, 300MB Disk, Expansion Package 1608
Meridian Mail X Cabinet from 2 to 3 Node Expansion Package 1565
Meridian Mail X Cabinet from 24 to 28 Ports, 1.0GB Disk, Expansion Package 1609
Meridian Mail X Cabinet from 24 to 28 Ports, 300MB Disk, Expansion Package 1608
Meridian Mail X Cabinet from 3 to 4 Node Expansion Package 1565
Meridian Mail X Cabinet from 4 to 5 Node Expansion Package 1609
Meridian Mail X Cabinet from 48 to 52 Ports, 300MB

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Disk, Expansion Package 1609
Meridian Mail, Release 9.66 Master Tape, Asia/Pacific 1 252, 1405
Meridian Mail, Release 9.66 Master Tape, Asia/Pacific Card Option 233, 244, 1429
Meridian Mail, Release 9.66 Master Tape, European 1 251, 1405
Meridian Mail, Release 9.66 Master Tape, European 1 Card Option 233, 244, 1429
Meridian Mail, Release 9.66 Master Tape, European 2 252, 1405
Meridian Mail, Release 9.66 Master Tape, European 2 Card Option 233, 244, 1429
Meridian Mail, Release 9.66 Master Tape, European 3 252, 1405
Meridian Mail, Release 9.66 Master Tape, European 3 Card Option 234, 244, 1429
Meridian Mail, Release 9.66 Master Tape, European 4 Card Option 235, 245, 1429
Meridian Mail, Release 9.66 Master Tape, North American 251, 1405
Meridian Mail, Release 9.66 Master Tape, North American Card Option 234, 244, 1429
Meridian Manager 1652, 1653
Meridian Manager Brochure 1652
Meridian Manager CPU Upgrade 1698
Meridian Manager Demo Disk 1652
Meridian Manager Documentation Package (Version 2) 1622
Meridian Manager Replacement Package 1250, 1516
Meridian Manager Slide Presentation 1652
Meridian Manager Version 2.4 1698, 1699
Meridian MAX 1000 Agent Software for Release 4 1707
Meridian MAX 6 NTPs 321, 344, 1389
Meridian MAX 8 Installation Upgrade Guide (English) 321, 1157, 1490
Meridian MAX Demo Disk 1662
Meridian MAX Installation and Maintenance Student Guide (for Single (SEE) and Dual (DEE) Module Systems Only) 1656
Meridian MAX Installation Upgrade Guide for Meridian MAX 3.4 and 4.6 systems (to Release 5) 1659
Meridian MAX LAN Connectivity Software for Release 6 (Available in Increments of 1-59) 319, 1224, 1514
Meridian MAX MQA Option for Enhanced and Virtual Software (Release 8) 319, 1223, 1514
Meridian MAX MQA Option for Virtual Software (Release 7) 319, 1248, 1516
Meridian MAX MSI Option for Virtual Software (Release 7) 319, 1232, 1515
Meridian MAX MTE One-Time Enable Fee for Release 6 319, 1224, 1514
Meridian MAX Networking Expansion 1706
Meridian MAX Networking for Option 1 & 2 1706
Meridian MAX Networking for Option 3 & 4 1706
Meridian MAX Networking for Release 4, Option 1 & 2 1706
Meridian MAX Networking for Release 4, Option 3 & 4 1706
Meridian MAX Networking for Release 6 319, 1276, 1518
Meridian MAX Networking Option 1/2 to Option 3/4 Software Expansion 1706
Meridian MAX One-Time LAN Connectivity Fee for Release 6 319, 1223, 1514
Meridian MAX Option 1 Hardware Package AC 1710
Meridian MAX Option 1 Hardware Package DC 1710
Meridian MAX Option 1 Software 1706
Meridian MAX Option 1 to Option 2 Expansion Package 316, 497, 1382
Meridian MAX Option 1 to Option 2 Software Expansion 1706
Meridian MAX Option 2 Hardware Package AC 1710
Meridian MAX Option 2 Hardware Package DC 1710
Meridian MAX Option 2 Migration Package AC 1714
Meridian MAX Option 2 Migration Package DC 1714
Meridian MAX Option 2 Software 1706
Meridian MAX Option 2 to Option 3 Expansion Package AC 1566
Meridian MAX Option 2 to Option 3 Expansion Package DC 1566
Meridian MAX Option 2 to Option 3 Software Expansion 1706
Meridian MAX Option 3 Hardware Package AC 1710
Meridian MAX Option 3 Hardware Package DC 1710
Meridian MAX Option 3 Migration Package AC 1714
Meridian MAX Option 3 Migration Package DC 1714
Meridian MAX Option 3 Software 1706
Meridian MAX Option 3 to Option 4 Expansion Package 316, 497, 1382
Meridian MAX Option 4 Hardware Package AC 1710
Meridian MAX Option 4 Hardware Package DC 1710
Meridian MAX Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 5) 1659
Meridian MAX R8 System Software Migration from Meridian MAX-IPE or IPEE (Fundamental) to Meridian MAX-SNNE (Fundamental) 1696
Meridian MAX Release 3 NTPs 1655
Meridian MAX Release 3 or 4 on Option 1 or 2 to MAX-SEE 6 Upgrade (160 Agents) 320, 1226, 1514
Meridian MAX Release 3 or 4 to Meridian MAX-IPE Release 7 Software Upgrade 1697
Meridian MAX Release 3 or 4 to Meridian MAX-IPEE Release 8 Software Upgrade 1697
Meridian MAX Release 3 or 4 to Meridian MAX-SNNE

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Release 8 Software Upgrade 1697
Meridian MAX Release 3 to 4 Software Upgrade - Option 1 1707
Meridian MAX Release 3 to 4 Software Upgrade - Option 2 1707
Meridian MAX Release 3 to 4 Software Upgrade - Option 3 1707
Meridian MAX Release 3 to 4 Software Upgrade - Option 4 1707
Meridian MAX Release 3,4 to MAX-SNN Release 7 Software Upgrade 1696
Meridian MAX Release 4 NTPs 1557, 1623
Meridian MAX Release 4 Option 1 Software 1706
Meridian MAX Release 4 Option 1 to Option 2 Software Expansion 1706
Meridian MAX Release 4 Option 2 Software 1706
Meridian MAX Release 4 Option 2 to Option 3 Software Expansion 1707
Meridian MAX Release 4 Option 3 Software 1706
Meridian MAX Release 4 Option 3 to Option 4 Software Expansion 1707
Meridian MAX Release 4 Option 4 Software 1706
Meridian MAX Release 4 Supervisors User Guide 1557
Meridian MAX Release 4 to 6 Base Software Upgrade (200 Agents) 1696
Meridian MAX Release 4 Users Guide Package 1623
Meridian MAX Release 4.62 or 5 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade 1697
Meridian MAX Release 5 Base Software (200 Agents) 1696
Meridian MAX Release 5 Base Software Upgrade (200 Agents) 1696
Meridian MAX Release 5 Capacity Configurator Tool 1561
Meridian MAX Release 5 NTP Package 1576
Meridian MAX Release 5 Single Module Software Upgrade (160 Agents) 1696
Meridian MAX Release 5 Software Upgrade, PDP 1696
Meridian MAX Release 5 to MAX-IPE Release 6 Base Software Upgrade 320, 1228, 1514
Meridian MAX Release 5 to MAX-IPE Release 7 Software Upgrade 1697
Meridian MAX Release 5 to MAX-SNN Release 7 Software Upgrade 1696
Meridian MAX Release 5 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade 1696
Meridian MAX Release 6 Application Tape 1576
Meridian MAX Release 6 Base Software for new Systems (includes 200 Agents) 1696
Meridian MAX Release 6 Capacity Configurator Tool 321, 327, 518, 1389, 1561
Meridian MAX Release 6 NTP Package 321, 344, 1389
Meridian MAX Release 6 Software Upgrade from a PDP System 1696
Meridian MAX Release 6 Supervisor Reference Guide 321, 350, 1389
Meridian MAX Release 6 Supervisors User Guide 322, 353, 1487
Meridian MAX Release 6 to MAX-IPE Release 7 Software Upgrade 1697
Meridian MAX Release 6 to MAX-SNN Release 7 Software Upgrade 1696
Meridian MAX Release 6 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade 1697
Meridian MAX Release 6 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade 1696
Meridian MAX Release 6 UNIX O/S Tape 1576
Meridian MAX Release 7 Capacity Configurator Tool 321, 327, 437, 1377
Meridian MAX Release 7 Complete Documentation Package 321, 350, 519, 1389
Meridian MAX Release 7 Installation Upgrade Guide for Meridian MAX Releases 3 through 6 Systems 321, 1156, 1488
Meridian MAX Release 7 Supervisors User Guide 321, 350, 519, 1389
Meridian MAX Release 7 Technical Documentation Package 321, 350, 519, 1389
Meridian MAX Release 7 to Meridian MAX-IPE or MAX-IPEE Release 8 Software Upgrade 1696
Meridian MAX Release 7 to Meridian MAX-SNN or MAX-SNNE Release 8 Software Upgrade 1696
Meridian MAX Release 8 Application Tape 1575
Meridian MAX Release 8 Capacity Configuration Tool 1576
Meridian MAX Release 8 Capacity Configurator Tool 321, 327, 438, 1377
Meridian MAX Release 8 Complete Documentation Package 321, 516, 1389
Meridian MAX Release 8 NTPs (English) 321, 516, 1389
Meridian MAX Release 8 Supervisors User Guide 321, 516, 1389
Meridian MAX Release 8 Sys. Software Migration from Meridian MAX-IPE or IPEE (Enhanced) to Meridian MAX-SNNE (Enhanced) 1696
Meridian MAX Release 8 System Software Migration from Meridian MAX-IPE or IPEE (Virtual) to Meridian MAX-SNNE (Virtual) 1696
Meridian MAX Release 8 System Software Migration from Meridian MAX-SNN to Meridian MAX-SNNE 1695
Meridian MAX Release 8 UNIX O/S Tape 1576

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian MAX Release 9 Capacity Configuration Tool 1576
Meridian MAX Release 9 Documentation Package (English) 321, 581, 1409
Meridian MAX Release 9 Reproduction/Keycode 320, 1163, 1493
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Enhanced to MAX-SNNE Enhanced 318, 788, 1436
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Fundamental to MAX-SNNE Fundamental 318, 787, 1436
Meridian MAX Release 9 Software Migration from MAX-IPE/IPEE Virtual to MAX-SNNE Virtual 318, 789, 1436
Meridian MAX Release 9 Software Migration from MAX-SNN to MAX-SNNE 318, 786, 1436
Meridian MAX Release 9 Supervisor's User Guide (English) 581, 797, 1409, 1437
Meridian MAX Release 9 SupervisorsUserGuide(English) 321
Meridian MAX Release 9 SupervisorsUserGuide(English)' 321
Meridian MAX Release 9 Upgrade Guide (to Release 9) 321, 1162, 1493
Meridian MAX Release 9.3 Capacity Configuration Tool 321, 327, 518, 1389
Meridian MAX Releases 6, 7 and 8 Software Service Transaction Fee (AM) 320, 1182, 1510
Meridian MAX SEE Release 5 to 6 Software Upgrade (160 Agents) 320, 1227, 1514
Meridian MAX-AM Release 3 or 4 to Meridian MAX-IPEE Release 9 Software Upgrade 318, 767, 1435
Meridian MAX-AM Release 3 or 4 to Meridian MAX-SNNE Release 9 Software Upgrade 317, 761, 1435
Meridian MAX-AM Release 6 Software Media Replacement/Upissue 319, 794, 1436
Meridian MAX-AM Release 7.5 Software Media Replacement/Upissue 319, 798, 1437
Meridian MAX-AM Release 8 Software Media Replacement/Upissue 319, 799, 1437
Meridian MAXcaster Flyer 362, 1489
Meridian MAX-IPE 20 Agent Software Increment for Release 4 1706
Meridian MAX-IPE Base Software 1706
Meridian MAX-IPE Module (Option 11) 1710
Meridian MAX-IPE Module (Option 21-81) 1710
Meridian MAX-IPE NTPs Release 4.6 1575
Meridian MAX-IPE or MAX-IPEE 20-Agent Software Increment for Releases 6, 7 and 8 319, 1276, 1518
Meridian MAX-IPE or MAX-IPEE Release 8 Enhanced to Virtual Software Option Upgrade 320, 1232, 1515
Meridian MAX-IPE or MAX-IPEE Release 8 Fundamental to Enhanced Software Option Upgrade 320, 1231, 1514
Meridian MAX-IPE Premium Features for Release 6 319, 1276, 1518
Meridian MAX-IPE Release 4 to MAX-IPE Release 6 Base Software Upgrade 320, 1277, 1518
Meridian MAX-IPE Release 4.62, 5 or 6 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade 318, 768, 1435
Meridian MAX-IPE Release 5 Base Software 1706
Meridian MAX-IPE Release 5 Base Software Upgrade 1706
Meridian MAX-IPE Release 6 Base Software for new systems 1706
Meridian MAX-IPE Release 6 Software Media Replacement/Upissue 319, 795, 1436
Meridian MAX-IPE Release 7 Enhanced Software 1706
Meridian MAX-IPE Release 7 Enhanced to Virtual Option Upgrade 320, 1231, 1514
Meridian MAX-IPE Release 7 Fundamental Software 1706
Meridian MAX-IPE Release 7 Fundamental to Enhanced Option Upgrade 320, 1230, 1514
Meridian MAX-IPE Release 7 Virtual Software with FastView+ 1706
Meridian MAX-IPE Supervisors User Guide Release 4.6 1575
Meridian MAX-IPE/IPEE Release 7 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade 318, 769, 1435
Meridian MAX-IPE/IPEE Release 7.5 Software Media Replacement/Upissue 319, 798, 1437
Meridian MAX-IPE/IPEE Release 8 Software Media Replacement/Upissue 319, 799, 1437
Meridian MAX-IPE/IPEE Release 8 to Meridian MAX-IPE/IPEE Release 9 Software Upgrade 318, 770, 1435
Meridian MAX-IPE/IPEE Release 9 Enhanced to Virtual Feature Level Promotion 318, 785, 1436
Meridian MAX-IPE/IPEE Release 9 Fundamental to Enhanced Feature Level Promotion 318, 784, 1436
Meridian MAX-IPE/IPEE Release 9 Software Replacement/Upissue 319, 771, 1435
Meridian MAX-IPE/MAX-IPEE Releases 6, 7 and 8 Software Service Transaction Fee 321, 1183, 1510
Meridian MAX-IPEE Module (Option 11) 316, 793, 1436, 1710

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian MAX-IPEE Module (Option 21-81C) 316, 794, 1436, 1710
Meridian MAX-IPEE Release 8 Enhanced Software 1706
Meridian MAX-IPEE Release 8 Fundamental Software 1706
Meridian MAX-IPEE Release 8 Virtual Software 1706
Meridian MAX-IPEE Release 9 Enhanced Software 318, 782, 1436
Meridian MAX-IPEE Release 9 Fundamental Software 318, 781, 1436
Meridian MAX-IPEE Release 9 Virtual Software 318, 783, 1436
Meridian MAX-SEE (Option 1,2) and MAX-DEE (Option 3,4) to Meridian MAX-SNN Hardware Upgrade Package 1711
Meridian MAX-SEE (Option 1,2) and MAX-DEE (Option 3,4) to Meridian MAX-SNNE Hardware Upgrade Package 1711
Meridian MAX-SEE Spares Kit 317, 342, 496, 1382
Meridian MAX-SEE/SNN Release 5 or 6 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade 317, 762, 1435
Meridian MAX-SNN and MAX-SNNE Release 8 Enhanced to Virtual Software Option Upgrade 320, 1230, 1514
Meridian MAX-SNN and MAX-SNNE Release 8 Fundamental to Enhanced Software Option Upgrade 320, 1229, 1514
Meridian MAX-SNN or MAX-SNNE 100-Agent Increment for Meridian MAX Releases 6, 7, and 8 319, 1223, 1514
Meridian MAX-SNN Release 5 to 6 Base Software Upgrade (200 Agents) 320, 1225, 1514
Meridian MAX-SNN Release 7 Enhanced 1697
Meridian MAX-SNN Release 7 Enhanced to Virtual Software Option Upgrade 320, 1229, 1514
Meridian MAX-SNN Release 7 Fundamental Software 1697
Meridian MAX-SNN Release 7 Fundamental to Enhanced Software Option Upgrade 320, 1228, 1514
Meridian MAX-SNN Release 7 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade 317, 763, 1435
Meridian MAX-SNN Release 7 Virtual Software with FastView+ 1697
Meridian MAX-SNN Spares Kit 317, 342, 437, 1377
Meridian MAX-SNN System Hardware, AC Power 1707
Meridian MAX-SNN System Hardware, DC Power 1707
Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade 316, 791, 1436
Meridian MAX-SNN to Meridian MAX-SNNE Hardware Upgrade Package 1711
Meridian MAX-SNN/SNNE Release 8 to Meridian MAX-SNN/SNNE Release 9 Software Upgrade 317, 764, 1435
Meridian MAX-SNN/SNNE Release 9 Enhanced to Virtual Feature Level Promotion 317, 780, 1436
Meridian MAX-SNN/SNNE Release 9 Fundamental to Enhanced Feature Level Promotion 317, 779, 1436
Meridian MAX-SNN/SNNE Release 9 Software Replacement/Upissue 319, 771, 1435
Meridian MAX-SNNE Release 8 Enhanced Software 1697
Meridian MAX-SNNE Release 8 Fundamental Software 1697
Meridian MAX-SNNE Release 8 Virtual Software 1697
Meridian MAX-SNNE Release 9 Enhanced Software 317, 777, 1435
Meridian MAX-SNNE Release 9 Fundamental Software 317, 776, 1435
Meridian MAX-SNNE Release 9 Virtual Software 317, 778, 1436
Meridian MAX-SNNE Spares Kit 317, 342, 438, 1377
Meridian MAX-SNNE System Hardware, AC Power 316, 792, 1436, 1707
Meridian MAX-SNNE System Hardware, DC Power 316, 792, 1436, 1707
Meridian Message Center SL-1 Special Software Pkg (7, 17, 35, 109, 40, 45, 46) 1535, 1536
Meridian Message Center SL-1 Special Software Pkg (7,17,35,109,40,45,46) 1535
Meridian Message Processing Feature Guide 374, 1486
Meridian Messaging Banking Solutions Brief 373, 1486
Meridian Messaging Education Solutions Brief 373, 1486
Meridian Messaging General Business Solutions Brief 372, 1486
Meridian Messaging Healthcare Solutions Brief 372, 1486
Meridian Modular Telephone Quick Reference Card (100/PK) 1652, 1654
Meridian Modular Telephone Template (100/PK) 352, 1482
Meridian Modular Telephone User Guide 1652, 1662, 1664
Meridian Modular telephone user guide 1654, 1657
Meridian Modular Telephone User Guide (Package of 15 P0902627) 350, 450, 1378

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian Modular Telephones & Options Quick Reference Guide (Package of 15 ea. P0815252) 1590
Meridian Modular Telephones Quick Reference Guide (English) (Package of 15 P0902628) 351, 1403
Meridian MultiMedia Messaging Overview Video 374, 1488
Meridian MultiMedia Messaging Sales Guide (Shrinkwrapped) 374, 1490
Meridian NAC Release 2 Supervisor's User Guide (English) 1575
Meridian NAC Release 2.5 Base Hardware Upgrade Package, AC 324, 1323, 1520
Meridian NAC Release 2.5 Base Hardware Upgrade Package, DC 324, 1324, 1520
Meridian NAC Release 2.5 Base System Hardware Platform, DC 324, 1313, 1520
Meridian NAC Software Service Transaction Fee (AM) 324, 1164, 1494
Meridian NAC, Release 2.5 Base System Hardware Platform, AC 324, 1312, 1520
Meridian NAC-AM Release 2.5 Upissue/Software Replacement 323, 795, 1436
Meridian Networking Feature Document 347, 1488, 1653, 1659, 1662
Meridian Option MAX/MAX-SEE to Meridian MAX-SNNE Hardware Upgrade 316, 791, 1436
Meridian Passport and NMS Documentation (CD-ROM) 1620
Meridian Passport ATM Binder 1620
Meridian Passport Base Information Binder 1619
Meridian Passport Base Software 1620
Meridian Passport Components Binder 1620
Meridian Passport Description and Installation Binder 1619
Meridian Passport Documentation (CD-ROM) 1620
Meridian Passport Frame Relay and HDLC Binder 1620
Meridian Passport Frame Relay Software Package 1620
Meridian Passport Manager for MAT 1621
Meridian Passport Manager Package 1621
Meridian Passport Module DC Power Harness 1619
Meridian Passport Module Package (-48V DC Power) 1619
Meridian Passport Module Software Package 1620
Meridian Passport Operations Binder 1619, 1620
Meridian Passport System Management Binder 1620
Meridian Passport System Package (-48V DC Power) (Free Standing Module) 1619
Meridian Passport Voice Services Binder 1620
Meridian Personal Directory PC Utility, Charcoal (M3900 Series) 201, 819, 1440
Meridian Personal Directory PC Utility, Platinum (M3900 Series) 201, 819, 1440
Meridian Private-Switch Emergency Notification Event Monitor Software 332, 1372
Meridian Private-Switch Emergency Notification Installation Kit 332, 420, 1372
Meridian Private-Switch Emergency Notification PC Software 332, 420, 474, 1372, 1380
Meridian Private-Switch Emergency Response AC Power Supply 332, 420, 1372
Meridian Private-Switch Emergency Response Configuration Software 332, 419, 1372
Meridian Private-Switch Emergency Response Installation Kit 332, 419, 1372
Meridian Private-Switch Emergency Response Unit 332, 421, 1372, 1560
Meridian Private-Switch Emergency Response Unit-AC Version 332, 473, 1379
Meridian Programmable Data Adapter 1397, 1581
Meridian S-1 Evergreen 35MM Presentation/Script 1651
Meridian Safe 32-400 Lines 1566
Meridian Safe 401-800 Lines 1566
Meridian Safe 801+ Lines 1566
Meridian Safe Additional Sites 1201+ Lines 1602
Meridian Safe Additional Sites 32-400 Lines 1602
Meridian Safe Additional Sites 401-800 Lines 1602
Meridian Safe Additional Sites 801-1200 Lines 1602
Meridian Safe Advanced Sites 1201+ Lines 1566
Meridian Safe Central Site 1201+ Lines 1602
Meridian Safe Central Site 32-400 Lines 1602
Meridian Safe Central Site 401-800 Lines 1602
Meridian Safe Central Site 801-1200 Lines 1602
Meridian Set Overview Brochure 1649
Meridian SL-1 & Hewlett Packard 1647
Meridian SL-1 Data Services Application-Conn Guide 1652
Meridian SL-1 General Information and Engineering 346, 1482
Meridian SL-1 Information Sales Handbook 1645
Meridian SL-1 Laser Printer Installation Package 1549
Meridian SL-1 MS Installation and Acceptance 1651
Meridian SL-1 MS Maintenance 1651
Meridian SL-1 N Installation and Acceptance 1651
Meridian SL-1 N Maintenance 1651
Meridian SL-1 NT Installation and Acceptance 346, 1482
Meridian SL-1 NT Maintenance 346, 1482
Meridian SL-1 Overview Brochure 1649
Meridian SL-1 RT Brochure 1649
Meridian SL-1 RT Installation and Acceptance 1650
Meridian SL-1 RT Maintenance 1650
Meridian SL-1 ST Installation and Acceptance 346, 1482
Meridian SL-1 ST Maintenance 346, 1482

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Meridian SL-1 System 35MM Upgrade Presentation 1650
Meridian SL-1 System Upgrade 35MM Presentation 1652
Meridian SL-1 XN Installation and Acceptance 1651
Meridian SL-1 XN Maintenance 1651
Meridian SL-1 XT Installation and Acceptance 346, 1482
Meridian SL-1 XT Maintenance 346, 1482
Meridian SL-1/500 Telephone Extension Designation Cards (1 Box of 1,000 Cards for use with SL-1 QSU Style & Std Analog) 352, 1484
Meridian SL1-NT Sales Feature Sheet 1649
Meridian SL1-RT Sales Feature Sheet 1649
Meridian SL-1S Retrofit Package 1646
Meridian SL1-ST Sales Feature Sheet 1649
Meridian SL1-XT Sales Feature Sheet 1649
Meridian SL-RT 35MM Update to ST Customer Presentation 1649
Meridian Telecenter 1.0 1595
Meridian Telecenter 1.1 1595
Meridian Terminal Emulator (MTE) Release 6 for Windows Software Package 1576
Meridian Terminal Emulator (MTE) Release 9 Assembly (Single User) 1617
Meridian Terminal Emulator (MTE) Release 9 Assembly (System License) 1617
Meridian Terminal Emulator (MTE) Release 9 Software (Single User) 1617
Meridian Terminal Emulator (MTE) Release 9 Software (System License) 1617
Meridian Terminal Emulator (MTE) Release 9 Software Upgrade (Single User) 1617
Meridian Terminal Emulator (MTE) Release 9 Software Upgrade (System License) 1617
Meridian Terminal Emulator (MTE) Release 9 Upgrade Assembly (Single User) 1617
Meridian Terminal Emulator (MTE) Release 9 Upgrade Assembly (System License) 1617
Meridian Terminal Emulator (MTE) Release 9 User Guide 322, 1162, 1493
Meridian Terminal Emulator (MTE) Release 9 User Guide (Multilingual English, French, Spanish) 322, 797, 1437
Meridian Terminal Emulator (MTE) Release 9.3 Software (Single User) 322, 772, 1435
Meridian Terminal Emulator (MTE) Release 9.3 Software (System License) 322, 773, 1435
Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (Single User) 322, 774, 1435
Meridian Terminal Emulator (MTE) Release 9.3 Software Upgrade (System License) 322, 775, 1435
Meridian Text Telephony System - 100 User System Package 1583
Meridian Text Telephony System - 25 User System Package 1583
Meridian Text Telephony System - 250 User System Package 1583
Meridian Text Telephony System - 50 User System Package 1583
Meridian Text Telephony System PC Client Package - 100 Users 269, 1000, 1465
Meridian Text Telephony System PC Client Package - 25 Users 269, 1000, 1465
Meridian Text Telephony System PC Client Package - 250 Users 269, 1001, 1465
Meridian Text Telephony System PC Client Package - 50 Users 269, 1000, 1465
Meridian Text Telephony System Quick Start Guide 1669
Meridian Text Telephony System TDD/TTY Modem 269, 1001, 1465
Meridian Voice Forms 1703
Meridian Voice Forms Implementation User Guide 352, 1485
Meridian Voice Forms Reference Manual 347, 1485
Meridian Voice Forms Transcriber User Guide 352, 1485
Meridian Voice Messaging User Guide - Release 3 1649
Meridian Wall Mount Kit, Charcoal (M3903, M3904, M3905) 200, 809, 1439
Meridian Wall Mount Kit, Platinum (M3903, M3904, M3905) 200, 808, 1439
Meridian/Unity III Designation Cards (1 Box of 1,000 Card for use w/ M2000 Digital Tel. & Unity III) 352, 1484
Message Cancel Key Cap Package (50/PK) 1556
Message Center Key Cap Package (50/PK) 1556
Message Indicator Key Cap Package (50/PK) 206, 396, 1368
Message Key Cap Package (50/PK) 1557
Message Registration Key Cap Package (50/PK) 1556
Message Taker 275, 1195, 1511
Message Waiting 150V Power Supply 1509, 1686
Message Waiting Power Supply 1504, 1680
Messenger 1.1 Fax on Demand 26, 1627
Messenger 1.1 Fax on Demand Upgrade 1627
Messenger 1.1 Server Software Kit 26, 1628
Messenger 1.1 to 2.0 Software Upgrade 1628
Messenger 1.1 Windows Client Package, 100 Users 26, 1626
Messenger 2.0 Interactive CD-ROM 375, 1488
Messenger 2.0 Interactive Demo Disks (Macintosh) 374, 1488
Messenger 2.0 Mac Client Package - 100 Users 270,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

971, 1462
Messenger 2.0 Mac Client Package - 1000 Users 1627
Messenger 2.0 Mac Client Package - 200 Users 1627
Messenger 2.0 Mac Client Package - 2000 Users 1627
Messenger 2.0 Mac Client Package - 25 Users 1627
Messenger 2.0 Mac Client Package - 50 Users 1627
Messenger 2.0 Mac Client Package - 500 Users 1627
Messenger 2.0 Product Sheet 373, 1489
Messenger 2.0 Server Software Meridian Mail, Fax, and E-Mail 1628
Messenger 2.0 to 3.0 Software Upgrade 1628
Messenger 2.0 Windows Client Package - 100 Users 1626
Messenger 2.0 Windows Client Package - 1000 Users 1627
Messenger 2.0 Windows Client Package - 200 Users 1627
Messenger 2.0 Windows Client Package - 2000 Users 1627
Messenger 2.0 Windows Client Package - 25 Users 1626
Messenger 2.0 Windows Client Package - 50 Users 1627
Messenger 2.0 Windows Client Package - 500 Users 1627
Messenger 2.0/3.0 Maintenance Release--Installation Phone Support for Customers NOT under Warranty or Maintenance 271, 1198, 1512
Messenger 2.0/3.0 Maintenance Release--On-Site Installation Support for Customers NOT under Warranty or Maintenance 271, 1198, 1512
Messenger 2.0/3.0 Maintenance Release--Phone Installation Support for Customers Under Warranty or Maintenance 271, 1198, 1512
Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (Customer Not Under Maintenance or Warranty) 270, 974, 1462
Messenger 2.0/3.0 Maintenance Software Kit-Audiofax (For Customers Under Maintenance or Warranty) 270, 974, 1462
Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Not Under Maintenance or Warranty) 270, 975, 1462
Messenger 2.0/3.0 Maintenance Software Kit-BrookTrout (Customer Under Maintenance or Warranty) 270, 975, 1462
Messenger 2.0/3.0 System Administration Guide 1628
Messenger 2.0/3.0 to 4.0 Migration Phone Support 1197, 1512
Messenger 2.0/3.0 to 4.0 On-Site Migration Support 271, 1197, 1511
Messenger 3.0 Windows Client Package - 100 Users 1627
Messenger 3.0 Windows Client Package - 1000 Users 1627
Messenger 3.0 Windows Client Package - 200 Users 26, 1627
Messenger 3.0 Windows Client Package - 2000 Users 1627
Messenger 3.0 Windows Client Package - 25 Users 1627
Messenger 3.0 Windows Client Package - 50 Users 1627
Messenger 3.0 Windows Client Package - 500 Users 1627
Messenger 3.0/2.0 Server Software (Brooktrout) 1628
Messenger 4.0
  Installation and Administration and User Training, On-site 27, 1694
  On-site Administration and User Training 271, 1185, 1510
Messenger 4.0 Administration Guide 271, 1493
Messenger 4.0 Server Software and 4 Port Card - Brooktrout 270, 977, 1462
Messenger 4.0 Server Software Only Kit - Brooktrout 270, 978, 1462
Messenger 4.0 Windows Client Package - 100 26, 1627
Messenger 4.0 Windows Client Package - 1000 26, 1627
Messenger 4.0 Windows Client Package - 200 26, 1627
Messenger 4.0 Windows Client Package - 2000 26, 1627
Messenger 4.0 Windows Client Package - 25 270, 972, 1462
Messenger 4.0 Windows Client Package - 50 26, 1627
Messenger 4.0 Windows Client Package - 500 26, 1627
Messenger and Assistant Install 1694
Messenger Computer Based Training 271, 980, 1463
Messenger Fax on Demand Software 270, 972, 1462
Messenger Installation Phone Support 271, 1189, 1511
Messenger Post Warranty Phone 7x24 271, 1189, 1511
Messenger Post Warranty Phone 8-5 271, 1189, 1511
Messenger Quick Reference Card - 100 Pack 271, 977, 1462
Messenger Quick Reference Card - 25 Pack 271, 976, 1462
Messenger Software Audiofax Upgrade Kit 2.0/3.0 to 4.0 270, 973, 1462
Messenger Software Brooktrout Upgrade Kit 2.0/3.0 to 4.0 270, 973, 1462
Messenger Software Upgrade Kit Only 1.1 to 3.0 1628
Messenger Windows User Interface 1628
Meter Circuit Pack for MPP600 and MFA150 185, 569, 1406
Meter Control Panel 1597
MF Receiver Card - IPE 25, 1426, 1611

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MF Sender 1502, 1678
MFA Spare Fuse Kit 186, 342, 1150, 1483
MFA150 Battery Tray 185, 550, 1401
MFA150 Modular Power Assembly - Dual Shelf 160, 469, 1379
MFA150 Modular Power Assembly - Single Shelf 160, 468, 1379
MFA150 User Guide/NTP 346, 1483
MFI/EFI Power Cable 193, 704, 1430, 1615
MGate Card 220, 247, 249, 836, 1443, 1444
MICA NTP 348, 1493
MICA Pack 1404
MICA Pack without Security Device 177, 558, 1404
MICA PCMCIA Flash Card (with MICA software included) 177, 558, 1404
MICA PCMCIA Flash with 12 Ports 180, 1014, 1466
MICA PCMCIA Flash with 16 Ports 180, 1014, 1466
MICA PCMCIA Flash with 20 Ports 180, 1014, 1466
MICA PCMCIA Flash with 24 Ports 180, 1015, 1466
MICA PCMCIA Flash with 28 Ports 180, 1015, 1466
MICA PCMCIA Flash with 32 Ports 181, 1016, 1466
MICA PCMCIA Flash with 5 Ports 180, 1013, 1466
MICA PCMCIA Flash with 8 Ports 180, 1013, 1466
MICA PCMCIA Hard Drive Replacement (includes MICA software) 177, 558, 1404
MICA PCMCIA Hard Drive with 12 Ports 180, 1010, 1466
MICA PCMCIA Hard Drive with 16 Ports 180, 1011, 1466
MICA PCMCIA Hard Drive with 20 Ports 180, 1011, 1466
MICA PCMCIA Hard Drive with 24 Ports 180, 1012, 1466
MICA PCMCIA Hard Drive with 28 Ports 180, 1012, 1466
MICA PCMCIA Hard Drive with 32 Ports 180, 1012, 1466
MICA PCMCIA Hard Drive with 5 Ports 180, 1010, 1466
MICA PCMCIA Hard Drive with 8 Ports 180, 1010, 1466
MICA Upgrade Add 12 Ports 164, 1017, 1466
MICA Upgrade add 16 ports 181, 1017, 1466
MICA Upgrade add 24 ports 181, 1017, 1466
MICA Upgrade Add 27 Ports 164, 1017, 1466
MICA Upgrade add 3 ports 181, 1016, 1466
MICA Upgrade add 4 ports 181, 1016, 1466
MICA Upgrade add 8 ports 181, 1016, 1466
MICB Software Upgrade Kit 177, 343, 1404
MIG Reach Line Card Installation and Administration Guide 334, 718, 1433
Mini Carrier Remote NTP 66, 347, 1492
Mini Chassis Expander 40, 68, 1432
Mini Cooling Unit 1509, 1686
Mini IPE 1.5 MB DTI/PRI Guide 60, 1158, 1491
Mini IPE 1.5MB DTI/PRI Cable 61, 824, 1441
Mini IPE 1.5MB DTI/PRI Card 59, 820, 1441
Mini IPE 1.5MB DTI/PRI Package 58, 824, 1441
Mini IPE 16 Port Analog Line Card 59, 820, 1441
Mini IPE 24 Port Digital Line Card 59, 820, 1441
Mini IPE 4 Port Trunk Card 61, 824, 1442
Mini IPE 4 Port Trunk/4 Port Line Card 59, 820, 1441
Mini Local Package (Option 11) 66, 161, 1002, 1465, 1629
Mini Local Package (Options 21-81) 161, 1002, 1465, 1629
Mini Remote Package AC 66, 161, 1003, 1465
Mini Remote Package DC 66, 161, 1003, 1465
Mini Tape Unit & Shelf (QCA28) 1509, 1686
Mini-CDR Package 1543
Mini-Terminal Bus Assembly 1647
MIPCD 16 Port Upgrade 176, 1009, 1466
MIPCD 24 port Upgrade 176, 1009, 1466
MIPCD 50 Users Expansion 176, 1008, 1466
MIPCD 8 Port Upgrade 176, 1009, 1466
MIPCD Kit 25, 1591
MIPCD NTP Guide (English) 26, 349, 1498, 1669
MIPCD NTP Guide (French) 26, 349, 1498, 1669
MIPCD PCMCIA Drive 176, 559, 1404, 1591
MIPCD Spare Base Card 176, 559, 1404
MIPCD User Guide (English) 26, 349, 1498, 1669, 1670
MIPCD User Guide (French) 26, 350, 1499, 1669
MIRAN (Release 2) Ethernet & DB9 Adapter 1620
MIRAN (Release 2) Pack 1611
MIRAN 1.53 (Upissue) 8MB PCMCIA Card 1617
MIRAN 1.56 (Upissue) 8MB PCMCIA Card 179, 1435
MIRAN Pack 1427, 1611
MIRAN to MIRAN Release 2 Card Upgrade Kit 179, 807, 1438
MIRAN to MIRAN Release 2 PCMCIA Upgrade Kit 26, 1618
Miscellaneous 1501, 1504, 1677, 1681
Miscellaneous/Peripheral Signaling 1506, 1682
MIVR Development NTPs 1559
MIVR Operational NTPs 1559
MIVR Software Reproduction 295, 1156, 1489
MM Release 13.13 Master Tape Asia/Pacific 1 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape Asia/Pacific 2 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape Europe 1 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape Europe 2 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape Europe 3 30, 233, 243, 255, 1409

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

MM Release 13.13 Master Tape Europe 4 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape Europe 5 30, 233, 243, 255, 1409
MM Release 13.13 Master Tape NA 2 30, 233, 243, 255, 1409
MM13.13 Master Tape NA 1 30, 233, 243, 255, 1409
MMDU Data Cable for CD and Hard Drive 188, 1400
MMDU Data Cable for Floppy Drive 188, 544, 1400
MMDU Power Cable 188, 544, 1400
MMI Cable Kit (32 Ft.) 189, 335, 1412, 1433
MMI Cable Kit (32 ft.) 189, 1412
MMP40 Processor, Classic 266, 549, 1401
MMP40 Processor, Modular EC/EC11 249, 267, 579, 1409
MMP40 Upgrade, EC 1711
MMP40 Upgrade, Modular Option, Modular Option GP 1712
MMP40 Upgrade, Option (NT/XT) 1712
MMP40 Upgrade, Option (ST/RT) 1712
MMR CD ROM 350, 1387
Modem Cable 188, 514, 1388
Modem Cable (DB9 to DB25) 329, 693, 1427, 1554
Modem Cable (DB9F to DB25M) 1560
Modem Cable (RS232) - 18 In. (Connects TDR to modem) 1569
Modem Cable Spare (DB9F to DB25M) 275, 971, 1461
Modem Cable, 10 Ft. DB9 Female to DB25 Male 38, 223, 273, 306, 402, 1369
Modem Cable, 10 ft., DB9 Female to DB25 Male 295, 930, 1455
Modem Eliminator Female to Female 196, 401, 1369
Modem Eliminator Male to Female 196, 401, 1369
Modem for SMDI Link in T1 Application 29, 220, 1369
Modem I/O Cable 1600
Modem Kit 197, 1389
Modular Macpack 1562
Modular Meridian Terminals 1688
Modular Option GP Installation and Maintenance Guide - MM13 348, 1496
Modular Option GP Site and Installation and Planning Guide - MM13 348, 1496
Modular Option Installation and Maintenance Guide - MM13 348, 1496
Module Expansion Rods 184, 614, 1416
Module Side Cover 184, 632, 1419, 1606, 1622, 1650
Monitor - 14" 276, 281, 933, 1455
Monitor - 17" 276, 281, 933, 1455
Monitor - 21" 276, 281, 933, 1455
Monitor - 21" Spare 1626
Montana State University
SYMPOSIUM Integrated IVR Success Story 370, 1487
Motorola 28.8 Fax/Data Modem 1559
Motorola UNIX R3V7 Manuals 1658
Mounting Bracket 69, 198, 1145, 1482, 1483
Mounting Bracket Assembly for QMM45 1646
Mounting Bracket Lower SDI Connector 198, 1140, 1481
Mounting Bracket Upper SDI Connector 1644
Mounting Kit Assembly for QSD81 1574
Mouse 272, 1369
Mouse - 3-Button PS/2-Type 1560
Mouse - 3-button PS/2-type 1559
MP Upgrade to Option Cantilever 4 Port/11 Hours 1715
MP Upgrade to Option Cantilever 8 Port/24 Hours 1715
MP Upgrade to Option Center 4 Port/11 Hours 1715
MP Upgrade to Option Center 8 Port/24 Hours 1715
MP Upgrade to Option X Cabinet 12 Port/11 Hours 1715
MP Upgrade to Option X Cabinet 16 Port/26 Hours 1715
MP Upgrade to Option X Cabinet 20 Port/26 Hours 1715
MP Upgrade to Option X Cabinet 24 Port/45 Hours 1715
MP Upgrade to Option X Cabinet 32 Port/45 Hours 1715
MP Upgrade to Option X Cabinet 4 Port/11 Hours 1715
MP Upgrade to Option X Cabinet 48 Port/45 Hours 1715
MP Upgrade to Option X Cabinet 8 Port/11 Hours 1715
MP Upgrade to ST/RT Option 4 Port/11 Hours 1715
MP Upgrade to ST/RT Option 8 Port/24 Hours 1715
MPB 16-2T Carrier Card 32, 221, 1446
MPB 16-4 41, 220, 1446
MPP600 Modular Power Package-Main Cabinet 1563
MPP600 Modular Power Package-Supplemental Cabinet 1563
MPP600 Power System NTP 1658
MPR25E Modular Power Rectifier, 25 Amps 185, 550, 1401, 1589
MPS150 Modular Power Shelf 23" Rackmount 185, 550, 1401
MPS75 Modular Power Shelf, 75 Amps 185, 550, 1401, 1589
MRS North American ISDN PRI Option Package 1632
MRS to UPS Communications Cable 274, 284, 1371
MRS Tower/Rack Disk Drive (1.05GB) 272, 405, 1370
MRS Tower/Rack Ethernet Controller 1559
MRS/AP Base Development System (12 Ports Loopstart) 1584
MRS/AP Base Development System (24 Ports T1)

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1584
MRS/AP Base Development System (30 ports E1) 1584
MRS/AP Base Development System (4 Ports Loopstart) 1584
MRS/AP Base Development System (8 ports ISDN/BRI, 5 hours) 1584
MRS/AP Base Runtime System (12 Ports Loopstart) 1584
MRS/AP Base Runtime System (24 Ports T1) 1584
MRS/AP Base Runtime System (30 ports E1) 1584
MRS/AP Base Runtime System (4 Port Loopstart) 1584
MRS/AP Base Runtime System (8 ports ISDN/BRI, 5 hours) 1584
MRS/AP or AP 17 Inch SVGA Monitor 1586
MRS/Rack AC Base System (12 port LS) Assembly 1587
MRS/Rack AC Base System (24 port T1) Assembly 1587
MRS/Rack Base System with AC Power (12 Port Loopstart) 1584
MRS/Rack Base System with AC Power (24 Port T1) 1584
MRS/Rack Base System with AC Power (30 port E1) 1584
MRS/Rack Base System with AC Power (8 port ISDN/BRI, 40 hours) 1584
MRS/Rack Base System with DC Power (12 Port Loopstart) 1584
MRS/Rack Base System with DC Power (24 Port T1) 1585
MRS/Rack Base System with DC Power (30 port E1) 1585
MRS/Rack Base System with DC Power (8 port ISDN/BRI, 40 hours) 1584
MRS/Rack Cabinet 1559
MRS/Rack DC Base System (12 port LS) Assembly 1586
MRS/Rack DC Base System (24 port T1) Assembly 1586
MRS/Tower Base System (12 Port Loopstart) 1584
MRS/Tower Base System (12 port LS) Assembly 1586
MRS/Tower Base System (24 Port T1) Assembly 1584
MRS/Tower Base System (24 port T1) Assembly 1586
MRS/Tower Base System (30 port E1) 1584
MRS/tower Base System (8 port ISDN/BRI, 40 hours) 1584
MRS/Tower or MRS/Rack (AC) Uninterruptible Power Supply 1586
MRS/Tower or MRS/Rack Token Ring Controller 272, 1370
MS/NT Shelf Upgrade Assembly 1714
MS/ST Shelf Upgrade Assembly 1715
MS-1 Cabinet 1587
MS-1 Cabinet Door Latch 1587
MSDL DCHI Interface Cable (18 Ft.) 194, 826, 1442
MSDL DCHI Interface Cable (35 Ft.) 194, 826, 1442
MSDL DCHI Interface Cable (50 Ft.) 194, 827, 1442
MSDL DCHI Interface Cable (6 Ft.) 194, 826, 1442
MSDL Intercabinet Cable Kit 188, 449, 1378
MSDL to I/O Panel Cable (6 Ft.) 194, 827, 1442
MTE Release 5 Software (Single User) for DOS 322, 517, 1389
MTE Release 6 User Guide 323, 1488
MTE Release 7 Software (Single User) for Windows (English) 1576
MTE Release 7 Software (Single User) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 7 Software (System Package) for Windows (English) 1576
MTE Release 7 Software (System Package) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 7 Transaction Upgrade Fee 1694
MTE Release 7 User Guide (English) 1576, 1665
MTE Release 7 User Guide (Multilingual English, French, Spanish, German) 322, 1389
MTE Release 7 User Guide (multilingual English, French, Spanish, German) 323, 1488
MTE Release 8 Software (Single User) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 8 Software (System Package) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 8 Software Upgrade (Single User) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 8 Software Upgrade (System Package) for Windows (Multilingual English, French, Spanish, German) 1576
MTE Release 8 User Guide (English) 1668
MTE Release 8 User Guide (Multilingual English, French, Spanish, German) 322, 519, 1389
MTE Release 8 User Guide (multilingual English, French, Spanish, German) 322, 1157, 1491
MTTS 1.0 Administration Guide 269, 1493
MTTS 1.0 Installation Guide 269, 1493
MTTS 1.0 User Guide 269, 1493
Multi Disk Assembly - Dual CPU 1562
Multi Disk Assembly - Single CPU 1562
Multi Disk Unit 1417, 1604
Multi I/O Cable 335, 1433, 1617
Multi Line Telephone User Guide (Trifold) (100/PK) 1646
Multi Protocol Communications Controller (MPCC)

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1528
Multi Purpose Amplifier (MPA) Sales Flyer 1556
Multi-Attendant SL-1LE/N Total Software Package 1530
Multi-Attendant SL-1M/MS Total Software Package 1530
Multi-Attendant SL-1VLE/XL/XN Total Software Package 1530
Multichannel Coax System (MCCS) with One Power Supply 1426, 1610
Multichannel Coax System (MCCS) with two power supplies 1426, 1611
Multi-Channel Data System (MCDS) Desk Cabinet 1671
Multi-Channel Data System (MCDS) Power 1509, 1686
Multi-Channel Data System (MCDS) Rack Cabinet 1671
Multi-Channel Data System (MCDS) Shelf 1507, 1683, 1684
Multi-Customer 152, 1205, 1512
Multi-Frequency IPE Receiver Card (4 Channel) 178, 691, 1426
Multi-Frequency Receiver Card 1683
Multigroup Control 1501, 1677
Multigroup Extender 1501, 1677
Multigroup Switch 1501, 1677
Multi-Line CAP User Guide 60, 1495, 1669
Multimedia Messaging Quick Reference Card - Latin American Spanish 228, 1496
Multimedia Messaging User Guide - Latin American Spanish 228, 1496
Multi-Output Power Supply (MOPS) 209, 384, 1365
Multiple Queue Assignment 101, 113, 124, 133, 140, 1245, 1516
Multiple Queue Assignment (MQA) Reporting for Meridian MAX Release 9 Software 317, 318, 1180, 1510
Multi-Purpose ISDN Signaling Processor (MISP) 177, 576, 1408
Multi-Purpose Serial Data Link (MSDL) 178, 576, 1408, 1596
Multi-Signal Processor (MSP) 1587
Multi-Site Reconfiguration 1699
Multi-SMDI Software 1703
Multi-Tenant 97, 107, 118, 130, 138, 145, 152, 1206, 1512
Music Broadcast 99, 109, 121, 1235, 1515
MVC00165 1569
MVC00166 1569
MVC00410 1383, 1569
MVC00947 1569
MVC01113 1569
MVC01114 1569
MVC01119 1569
MVC01121 1569
MVC01243 1383, 1569
MVC01250 1569
MVC01305 1569
MVC01306 1569
MVC01309 1569
MVC01310 1569
MVC01312 1569
MVC01313 1569
MVC01314 1569
MVC01315 1569
MVC01316 1569
MVC01335 1570
MVC01347 1570
MVC01421 1570
MVC01498 1570
MVC01557 1570
MVC01561 196, 499, 1383
MVC01562 196, 499, 1383
MVC01906 1570
MVC02031 1570
MVC02032 1570
MVC02033 1570
MVC02121 1570
MVC02259 1570
MVC02400 1383, 1570
MVC02403 1570
MVC03067 1570
MVME X.25 Communications Card Kit (MVME333, MVME705, Cable) 1366, 1553
MVME147SA-1 Processor Card (M68030, 25Mhz, 8MB) 327, 386, 1366
MVME147SB-1 Processor Card (M68030, 25Mhz, 16MB) 327, 391, 1367
MVME167-03 Processor Card (M68040, 25 Mhz, 16MByte) 1369, 1558
MVME167-33 Processor Card (M68040, 33Mhz, 16MB) 176, 1373
MVME167-34 Processor Card (M68040, 33Mhz, 32MB) 327, 394, 1367
MVME167A or 02 Processor Card (M68040, 25Mhz, 8MB) 1558
MVME177-004 Processor Card (M68060, 50 Mhz, 32 MByte) 1560
MVME177-005 Processor Card (M68060, 50 Mhz, 64MB) 327, 425, 1373
MVME332XTS 8-Channel Asynchronous I/O Card 327, 390, 1367
MVME705B Transition Card (for MVME333) 327, 386, 1366
MVME712AM Transition Card with Built-in Modem (for MVME147) 327, 386, 1366
MVME712M Transition Card without built-in modem

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

(for MVME167 and MVME177) 327, 1369
MW Power Supply P14 Extension Kit Assembly 1569
MW/DND 150V Power Supply 1509, 1686
MW/DND Line Card 1502, 1504, 1678, 1680

N

NA Enhanced Business Feature Set 1624
NA Enterprise Business Feature Set 1624
NA Feature Set #1 1623, 1624
NA Feature Set #2 1624
NA Feature Set #3 1624
NA Feature Set #4 1624
NA General Business Feature Set 1624
NA NAS/VNS Feature Set 1624
NAC (Release 1) Connectivity Enabler for Meridian MAX 1707
NAC (Release 2) Connectivity Enabler for Meridian MAX Releases 6 and 7 319, 1278, 1518
NAC 2.5 User Guide Supplement 324, 1164, 1494
NAC Connectivity for Meridian MAX Release 8 319, 1278, 1518
NAC Connectivity for Meridian MAX Release 9 Software 317, 318, 1180, 1510
NAC Release 2 Documentation Package (English) 324, 516, 1389
NARS 153, 1214, 1513
NARS/CDR Format 97, 107, 118, 130, 138, 145, 1204, 1512
NAS Software (Add. 100 TNs) 92, 1251, 1516, 1699
NAS Software Update 92, 1253, 1516, 1700
NCD X-Terminal (15 In. Mono/8MB) 1369, 1558
NCD X-Terminal (17 In. Color/8MB) 1368, 1556
NCD15R 15" Monochrome Monitor (8MB) 1558
NCD15R X-Terminal Base 1558
NEC Connections Hardware Kit 1367, 1556
Network 1504, 1680
Network ACD 154, 1239, 1515
Network Administration Center Connectivity NTP 346, 1483
Network Administration Center Hardware Package 1623
Network Administration Center NTP 346, 1483
Network Administration Center Release 2 Application Tape 1575
Network Administration Center Release 2 Installation NTP + System Administration and Maintenance Guide 1575
Network Administration Center Release 2 Supervisors User Guide 1655
Network Administration Center Release 2.5 Base Software Package 323, 1274, 1518
Network Administration Center Release 2.5 Base Software Upgrade 323, 1275, 1518
Network Administration Center Software and Documentation Package 1623
Network Administration Center Supervisors User Guide 1656
Network Administration Guide 1617
Network Assembly 1530, 1543
Network Attendant Services 98, 108, 119, 131, 139, 1220, 1513
Network Authorization Code 153, 1214, 1513
Network Cable Inter-Cabinet (12 Ft.) 1675
Network Cable Intra-Cabinet (40 In.) 1675
Network Cable Intra-Cabinet (70 In.) 1675
Network Cable Intra-Cabinet (85 In.) 1675
Network Cable NT/XT 1570
Network Cable Package - 2nd Group 159, 441, 1377
Network Cable Package - 3rd Group 159, 441, 1377
Network Cable Package - 4th Group 159, 441, 1377
Network Cable Package - 5th Group 159, 442, 1377
Network Cable, Intra-Cabinet (6 Ft.) 1675
Network Card 183, 1177, 1503, 1679
Network Cardcage (AC/DC) 183, 604, 1415, 1603
Network Extender 1504, 1680
Network Group 1 or 2 Shelf Assembly 1562
Network Group 3 Shelf Assembly 1562
Network Group 4 Shelf Assembly 1562
Network Group Assembly 1525, 1526, 1545
Network Group Assembly for Hotel/Motel 1546
Network Group Expansion Interface Kit 1622
Network Group Expansion Interface Package 159, 449, 1378
Network Group Package AC 158, 439, 1377
Network Group Package DC 158, 439, 1377
Network Hybrid Installation Procedure 347, 1488
Network Installation Guide - Banyan/BNS (DA120) 1647
Network Installation Guide - Banyan/DTS (DA121) 1647
Network Installation Guide - CNS (DA213-02) 1553
Network Installation Guide - VINES/286 (DA203) 1647
Network Installation Guide VINES 386 (DA203-04) 1553
Network Mail (DA208-01) 1553
Network Management (NM130) 1550
Network Management Guide (DA202-01) 1553
Network Management System (NMS) Accounting Management 1621
Network Management System (NMS) Advisor 1 1621
Network Management System (NMS) Advisor 2 1621
Network Management System (NMS) Architect 1 1621
Network Management System (NMS) Architect 2 1621
Network Management System (NMS) Architect 3 1621
Network Management System (NMS) Expert Advisor

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1621
Network Management System (NMS) LAN Services 1621
Network Management System (NMS) Meridian View (per workstation) 1621
Network Management System (NMS) Performance Management 1621
Network Management System (NMS) SNMP Integrator 1621
Network Management System (NMS) Utilities 1621
Network Message Service Software 257, 1254, 1516
Network Message Services 98, 108, 119, 131, 139, 154, 1221, 1248, 1514, 1516, 1696
Network Message Services Prime Site Software, Release 11 1700
Network Message Services Prime Site Software, Release 11 and Later 257, 1254, 1516
Network Message Services Remote Site Software, Release 11 257, 1264, 1517
Network Module AC 183, 604, 1415, 1603
Network Module DC 183, 604, 1415, 1603
Network Module Package AC 158, 440, 1377
Network Module Package DC 158, 440, 1377
Network PC Printing (PCP100) 1551
Network Planning Guide 349, 1498
Network Services Extension Manuals 1658
Network Shelf (LH Mount) 1507, 1508, 1684, 1685
Network Shelf (RH Mount) 1507, 1508, 1684, 1685
Network to Controller Cable (10 Ft.) 191, 626, 1418
Network to Controller Cable (12 Ft.) 191, 626, 1418
Network to Controller Cable (16 Ft.) 191, 627, 1418
Network to Controller Cable (25 Ft.) 191, 627, 1418
Network to Controller Cable (4 Ft.) 191, 626, 1418
Network to Controller Cable (45 Ft.) 191, 627, 1418
Network to Controller Cable (6 Ft.) 191, 626, 1418
Network to Controller Cable (8 Ft.) 191, 626, 1418
Network to I/O Cable (5 Ft.) 191, 625, 1418, 1605
Network to I/O Cable (6 Ft.) 191, 625, 1418, 1605
Network to I/O Cable Assembly 239, 268, 1408
Network to PE Cable (10 Ft.) 191, 623, 1418, 1605
Network to PE Cable (16 Ft.) 191, 624, 1418, 1605
Network to PE Cable (2 Ft.) 191, 622, 1418, 1605
Network to PE Cable (20 Ft.) 191, 624, 1418, 1605
Network to PE Cable (25 Ft.) 191, 624, 1418, 1605
Network to PE Cable (4 Ft.) 191, 623, 1418, 1605
Network to PE Cable (45 Ft.) 191, 624, 1418, 1605
Network to PE Cable (6 Ft.) 191, 623, 1418, 1605
Network to PE Cable (8 Ft.) 191, 623, 1418, 1605
Network Voice Processor 266, 545, 1400, 1588
Network/DTR Card 1414, 1603
Network/MSU Shelf 1508, 1684
Network/PE Cabinet Assembly 1545
Network/PE Cabinet Assembly for Hotel/Motel 1546
Networking 97, 107, 119, 131, 138, 146, 1217, 1513
Networking Hardware Kit 272, 697, 1428
Next Generation Connectivity 100, 112, 515, 1389
Night Key Cap Package (50/PK) 207, 399, 1368
NLI Cable 10 Ft. 249, 711, 1432
NLI Cable 20 Ft. 249, 711, 1432
NLI Cable 30 Ft. 249, 711, 1432
Noisy Location, Handset, Ash 1570
Noisy Location, Handset, Black 1570
Noisy Location, Handset, Gray 1570
Non-Hot-Swap Tray 29, 306, 1376
Nortel IVR CompuCALL Integration Package 275, 1192, 1511
Nortel Meridian
Transition to the Year 2000 Video 364, 1494
Nortel Networks SYMPOSIUM IVR Brochure 368, 1489
Nortel Promotional Funds Handbook 375, 1485
Nortel SYMPOSIUM Messenger Demo CD-ROM 25, 1590
Nortel's 1-Meg Modem 1433
Nortel's SYMPOSIUM IVR Customer Testimonial Video 1490
NortelsSYMPOSIUMIVRCustomerTestimonialVideo' 371
North American ISDN PRI Option for 24 Port T1 Card 278, 948, 1457
Norwegian Prompt 1701
Norwegian Prompt - Bilingual 1701
Not Ready Key Cap Package (50/PK) 206, 398, 1368
NT "Lines of Power" V.H.S. Tape 1651
NT/HP Alliance Brochure 359, 1484
NT/IBM Alliance Brochure 359, 1484
NT/Tandem Alliance Brochure 359, 1484
NT/XT Cabinet Upgrade Assembly 1718
NT0961AA 177, 499, 1383
NT0962AA 196, 499, 1383
NT0963AA 197, 500, 1383
NT0C09BC03 1570
NT0C09BC35 1570
NT0C09BC93 1570
NT0C09EA03 206, 500, 1383
NT0C09EA35 206, 500, 1383
NT0C09EA93 206, 500, 1383
NT0C09EK03 1570
NT0C09EK35 1570
NT0C09EK93 1570
NT0C09EL03 206, 501, 1383
NT0C09EL35 206, 501, 1383
NT0C09EL-93 206, 501, 1383
NT0M96DC 1570
NT0M96DG 1570
NT0M96DQ 1570
NT0M96DT 1570

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT0M96DU 1570
NT0M96QC 1570
NT0M96QG 1570
NT0R03AA 1383, 1570
NT0R04AA 1383, 1570
NT0R08AA 1383, 1570
NT0R09AA 1383, 1570
NT0R12AA 1383, 1570
NT0R20AA 1383, 1570
NT0R24AA 1383, 1570
NT0R26AA 1383, 1571
NT0R27AA 1383, 1571
NT0R28AA 1383, 1571
NT0R28AB 1383, 1571
NT0R28AC 1383, 1571
NT0R30AA 1383, 1571
NT0R50AA 1384, 1571
NT0R52AA 1384, 1571
NT0R53AA 1384, 1571
NT0R60AA 1384, 1571
NT0R66AA 1571
NT0R67AA 1384, 1571
NT0R71AA 185, 501, 1384
NT0R72AA 185, 502, 1384
NT0R82AA 1571
NT0R82AB 1571
NT0R82AC 1571
NT0R82AD 1571
NT0R82AE 1571
NT0R82AF 1571
NT0X21AV 183, 502, 1384
NT-1 Basic Unit RM 1616
NT-1 Network Terminal Adapter Product Brief 365, 1484
NT-1 Stand Alone Unit 1616
NT1344AA 227, 1384
NT1F04GA66 200, 1384
NT1F04GA70 200, 1384
NT1F04HA35 1571
NT1F04HA93 1571
NT1F04JA03 1571
NT1F04JA35 1571
NT1F04JA93 1571
NT1F04KA35 1571
NT1F05AA35 1384, 1571
NT1F05AA93 1384, 1571
NT1F05AB03 1384, 1571
NT1F05AB35 1384, 1571
NT1F05AB93 1384, 1571
NT1F05AD03 1384, 1571
NT1F05AD35 1384, 1571
NT1F05AD93 1384, 1571
NT1F05AE03 1384, 1571
NT1F05AE35 1384, 1571
NT1F05AE93 1384, 1572
NT1F05BA35 1384, 1572
NT1F05BA93 1384, 1572
NT1F05BB03 1384, 1572
NT1F05BB35 1384, 1572
NT1F05BB93 1384, 1572
NT1F05MB03 1384, 1572
NT1F05MB35 1384, 1572
NT1F05MB93 1384, 1572
NT1F05MD03 1384, 1572
NT1F05MD35 1384, 1572
NT1F05MD93 1384, 1572
NT1F05ME03 1385, 1572
NT1F05ME35 1385, 1572
NT1F05ME93 1385, 1572
NT1F06AA35 1385, 1572
NT1F06AA93 1385, 1572
NT1F06AB03 1385, 1572
NT1F06AB35 1385, 1572
NT1F06AB93 1385, 1572
NT1F06AE03 1385, 1572
NT1F06AE35 1385, 1572
NT1F06AE93 1385, 1572
NT1F06AF03 1385, 1572
NT1F06AF35 1385, 1572
NT1F06AF93 1385, 1572
NT1F06BA35 1385, 1572
NT1F06BA93 1385, 1572
NT1F06BB03 1385, 1572
NT1F06BB35 1385, 1572
NT1F06BB93 1385, 1572
NT1F06MB03 1385, 1572
NT1F06MB35 1385, 1572
NT1F06MB93 1385, 1572
NT1F06ME03 1385, 1573
NT1F06ME35 1385, 1573
NT1F06ME93 1385, 1573
NT1F06MF03 1385, 1573
NT1F06MF35 1385, 1573
NT1F06MF93 1385, 1573
NT1F07AA03 1385, 1573
NT1F07AA35 1385, 1573
NT1F07AA93 1385, 1573
NT1F07AB35 1385, 1573
NT1F07AC03 1385, 1573
NT1F07AC35 1385, 1573
NT1F07AC93 1385, 1573
NT1F07BA03 1385, 1573
NT1F07BA35 1385, 1573
NT1F07BA93 1386, 1573
NT1F07BB35 1386, 1573
NT1F07MA03 1386, 1573
NT1F07MA35 1386, 1573
NT1F07MA93 1386, 1573

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT1F07MC03 1386, 1573
NT1F07MC35 1386, 1573
NT1F07MC93 1386, 1573
NT1F09AA 1386, 1573
NT1F09AC 204, 502, 1386
NT1F10AA 1386, 1573
NT1F10AB 1386, 1573
NT1F11AA03 1386, 1573
NT1F11AB03 1386, 1573
NT1F11AD03 1386, 1573
NT1F11AK03 1386, 1573
NT1F11BA03 1386, 1573
NT1F11BB03 1386, 1573
NT1F11MD03 1386, 1573
NT1F11MK03 1386, 1573
NT1F14AA 1574
NT1F21AA03 1386, 1574
NT1F21AA35 1386, 1574
NT1F21AA93 1386, 1574
NT1F21AB03 1386, 1574
NT1F21AB35 1386, 1574
NT1F21AB93 1386, 1574
NT1F21AE03 203, 502, 1386
NT1F21AE35 203, 503, 1386
NT1F21AE93 203, 503, 1386
NT1F21BA03 1386, 1574
NT1F21BA35 1386, 1574
NT1F21BA93 1386, 1574
NT1F21MA03 1386, 1574
NT1F21MA35 1387, 1574
NT1F21MA93 1387, 1574
NT1F21MB03 1387, 1574
NT1F21MB35 1387, 1574
NT1F21MB93 1387, 1574
NT1F21ME03 203, 503, 1387
NT1F21ME35 203, 504, 1387
NT1F21ME93 203, 504, 1387
NT1F27AA 1574
NT1F27BA 1574
NT1F27BB 310, 1387
NT1F27EA 1574
NT1F27EB 310, 504, 1387
NT1F28BA 1574
NT1F32AA 1574
NT1F32BA 1574
NT1F33AA 1574
NT1F33BA 1574
NT1F34AA 1574
NT1F34BA 1574
NT1F35AA 1574
NT1F35BA 1574
NT1F4030 1574
NT1F50AA35 1574
NT1F50AB35 1574
NT1F57AA 308, 504, 1387
NT1F57BA 308, 505, 1387
NT1F57CA 309, 505, 1387
NT1F57DA 309, 505, 1387
NT1F58AA 309, 506, 1387
NT1F58BA 309, 506, 1387
NT1F58CA 309, 506, 1387
NT1F58DA 309, 507, 1387
NT1F59AA 1575
NT1F59BA 1575
NT1F59CA 1575
NT1F59DA 1575
NT1F67AA 1575
NT1F68AA 309, 1387
NT1F69AA 1575
NT1F73AA 350, 1387
NT1F80AA 309, 507, 1387
NT1F80BA 1575
NT1F80CA 1575
NT1F86AA 309, 1387
NT1F87AA 1575
NT1F89AA 344, 1387
NT1F90AA 344, 1387
NT1F91AA 344, 1387
NT1F92AA 344, 1387
NT1F93AA 344, 1387
NT1F94AA 60, 1387
NT1F97AA 344, 507, 1387
NT1GS24 1575
NT1GS48 1575
NT1P61AA 1387, 1575
NT1P61BA 1387, 1575
NT1P61CA 177, 508, 1387
NT1P62AA 1387, 1575
NT1P62BA 1387, 1575
NT1P62CA 1387, 1575
NT1P62EA 177, 508, 1387
NT1P63AA 1388, 1575
NT1P63CA 188, 508, 1388
NT1P6501 197, 508, 1388
NT1P6601 197, 508, 1388
NT1P75AA 188, 508, 1388
NT1P75BA 188, 509, 1388
NT1P76AA 188, 509, 1388
NT1P78AA 188, 509, 1388
NT1P79AA 188, 509, 1388
NT1P79BA 188, 509, 1388
NT1P84AA 188, 510, 1388
NT1P85AA 188, 510, 1388
NT1P87AA 188, 510, 1388
NT1P93AA 1575
NT1P93BA 1575
NT1P93CA 1575
NT1P94BA 1575

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT1P94CA 1575
NT1P95AA 1575
NT1P98AA 1575
NT1P98BA 1575
NT1P98CA 1575
NT1R03AA 327, 510, 1388
NT1R03BA 327, 510, 1388
NT1R03CA 327, 510, 1388
NT1R03DB 267, 327, 511, 1388
NT1R03DC 327, 511, 1388
NT1R03DF 327, 511, 1388
NT1R03DP 327, 512, 1388
NT1R03DV 327, 512, 1388
NT1R03EB 327, 512, 1388
NT1R03EC 328, 512, 1388
NT1R03EF 328, 513, 1388
NT1R03EP 267, 328, 513, 1388
NT1R03EV 328, 513, 1388
NT1R03FP 328, 513, 1388
NT1R03FV 328, 514, 1388
NT1R03GP 328, 514, 1388
NT1R03GV 328, 514, 1388
NT1R03HF 188, 514, 1388
NT1R04AA 188, 514, 1388
NT1R05AA 188, 515, 1388
NT1R11AA 1575
NT1R11CC 1575
NT1R16BB 294, 515, 1389
NT1R20AA 1389, 1575
NT1R20AB 64, 177, 515, 1389
NT1R27AA 1575
NT1R28AA 1575
NT1R29AA 100, 112, 515, 1389
NT1R31AA 324, 516, 1389
NT1R32AA 1575
NT1R33AA 1575
NT1R34AA 1575
NT1R36AA 1576
NT1R37AA 321, 516, 1389
NT1R39AA 321, 516, 1389
NT1R42AA 1576
NT1R43AA 1576
NT1R49AA 321, 516, 1389
NT1R54AA 1576
NT1R55AA 1576
NT1R55AB 350, 1389
NT1R56AB 1576
NT1R56AD 1576
NT1R56AE 1389
NT1R57AA 1576
NT1R57AB 1576
NT1R57AD 1576
NT1R57AE 344, 1389
NT1R59AA 100, 112, 517, 1389
NT1R60AA 1576
NT1R61AA 344, 1389
NT1R62AA 1576
NT1R64AA 321, 344, 1389
NT1R65AA 321, 344, 1389
NT1R66AA 321, 350, 1389
NT1R67EA 1576
NT1R75AA 322, 517, 1389
NT1R75BA 1576
NT1R75CA 1576
NT1R75DA 1576
NT1R75EA 1576
NT1R76BA 321, 327, 518, 1389
NT1R76DA 1576
NT1R76EA 1576
NT1R76EB 321, 327, 518, 1389
NT1R79AA 1576
NT1R81AA 1576
NT1R89AA 183, 518, 1389
NT1R89BA 183, 518, 1389
NT1R90AA 1576
NT1R90BA 183, 1389
NT1R90CA 1576
NT1R91AA 197, 1389
NT1R93AA 321, 350, 519, 1389
NT1R94AA 321, 350, 519, 1389
NT1R95AA 321, 350, 519, 1389
NT1R96CA 1576
NT1R96DA 1576
NT1R96EA 1576
NT1R97EA 1576
NT1R98AA 322, 1389
NT1R98BA 1576
NT1R98EA 322, 519, 1389
NT2F09AA 350, 520, 1389
NT2F20AA 344, 520, 1389
NT2F21AA 344, 520, 1389
NT2F22AA 344, 520, 1389
NT2F23AA 344, 521, 1389
NT2F24AA 344, 521, 1389
NT2F25AA 344, 521, 1389
NT2F26AA 344, 521, 1390
NT2F27AA 344, 522, 1390
NT2F59AA 308, 310, 325, 522, 1390
NT2F60AA 310, 522, 1390
NT2F61AA 310, 1390
NT2F61BA 310, 1390
NT2F61CA 310, 1390
NT2F61DA 310, 1390
NT2F61EA 310, 1390
NT2F62AA 308, 523, 1390
NT2F63AA 308, 1390
NT2F63BA 308, 1390
NT2F63CA 308, 1390

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT2F64AA 310, 1390
NT2F64BA 310, 1390
NT2F64CA 308, 523, 1390
NT2F65AA 310, 523, 1390
NT2F65BA 310, 524, 1390
NT2F73AA 1390
NT2F75AA 25, 1576
NT2F76AA 1577
NT2F77AA 350, 524, 1390
NT2F78AA 207, 524, 1390
NT2F7901 350, 524, 1390
NT2F7903 210, 524, 1390
NT2F79AA 350, 525, 1390
NT2F79AB 210, 525, 1390
NT2F8001 350, 525, 1390
NT2F8003 210, 525, 1391
NT2F80AA 350, 526, 1391
NT2F80AB 210, 526, 1391
NT2F81AA 351, 526, 1391
NT2F81AB 210, 526, 1391
NT2F82AA 351, 526, 1391
NT2F82AB 210, 527, 1391
NT2F83AA 207, 527, 1391
NT2F84AA 207, 527, 1391
NT2G00AA35 1391, 1577
NT2G00AC35 1391, 1577
NT2K03BA 209, 527, 1391
NT2K05GA03 1391, 1577
NT2K05GA35 1391, 1577
NT2K05GA93 1391, 1577
NT2K05GD03 1391, 1577
NT2K05GD35 1391, 1577
NT2K05GD93 1391, 1577
NT2K05GT03 1391, 1577
NT2K05GT35 1391, 1577
NT2K05GT93 1391, 1577
NT2K05GV03 1391, 1577
NT2K05GV35 1391, 1577
NT2K05GV93 1391, 1577
NT2K08GA03 1391, 1577
NT2K08GA35 1391, 1577
NT2K08GA93 1391, 1577
NT2K08GB03 1391, 1577
NT2K08GB35 1392, 1577
NT2K08GB93 1392, 1577
NT2K08GC03 1392, 1577
NT2K08GC35 1392, 1577
NT2K08GC93 1392, 1577
NT2K08GD03 1392, 1577
NT2K08GD35 1392, 1577
NT2K08GD93 1392, 1577
NT2K08GG03 1392, 1577
NT2K08GG35 1392, 1577
NT2K08GG93 1392, 1577
NT2K08GH03 1392, 1577
NT2K08GH35 1392, 1577
NT2K08GH93 1392, 1577
NT2K08GK03 1392, 1577
NT2K08GK35 1392, 1578
NT2K08GK93 1392, 1578
NT2K08GL03 1392, 1578
NT2K08GL35 1392, 1578
NT2K08GL93 1392, 1578
NT2K08GN03 1392, 1578
NT2K08GN35 1392, 1578
NT2K08GN93 1392, 1578
NT2K08GP03 1393, 1578
NT2K08GP35 1393, 1578
NT2K08GP93 1393, 1578
NT2K08GR03 1393, 1578
NT2K08GR35 1393, 1578
NT2K08GR93 1393, 1578
NT2K08GS03 1393, 1578
NT2K08GS35 1393, 1578
NT2K08GS93 1393, 1578
NT2K08GT03 1393, 1578
NT2K08GT35 1393, 1578
NT2K08GT93 1393, 1578
NT2K08GU03 1393, 1578
NT2K08GU35 1393, 1578
NT2K08GU93 1393, 1578
NT2K08GV03 1393, 1578
NT2K08GV35 1393, 1578
NT2K08GV93 1393, 1578
NT2K08GX03 1393, 1578
NT2K08GX35 1393, 1578
NT2K08GX93 1393, 1578
NT2K08XE03 1393, 1578
NT2K08XE35 1394, 1578
NT2K08XE93 1394, 1579
NT2K08XF03 1394, 1579
NT2K08XF35 1394, 1579
NT2K08XF93 1394, 1579
NT2K08ZC03 1394, 1579
NT2K08ZC35 1394, 1579
NT2K08ZC93 1394, 1579
NT2K08ZL03 1394, 1579
NT2K08ZL35 1394, 1579
NT2K08ZL93 1394, 1579
NT2K08ZS03 1394, 1579
NT2K08ZS35 1394, 1579
NT2K08ZS93 1394, 1579
NT2K10WA 1394, 1579
NT2K10WB 1394, 1579
NT2K10WC 1394, 1579
NT2K10WD 209, 528, 1394
NT2K16GA03 1394, 1579
NT2K16GA35 1394, 1579

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT2K16GA93 1394, 1579
NT2K16GD03 1394, 1579
NT2K16GD35 1394, 1579
NT2K16GD93 1394, 1579
NT2K16GG03 1394, 1579
NT2K16GG35 1394, 1579
NT2K16GG93 1395, 1579
NT2K16GH03 1395, 1579
NT2K16GH35 1395, 1579
NT2K16GH93 1395, 1579
NT2K16GN03 1395, 1579
NT2K16GN35 1395, 1579
NT2K16GN93 1395, 1579
NT2K16GR03 1395, 1579
NT2K16GR35 1395, 1580
NT2K16GR93 1395, 1580
NT2K16GT03 1395, 1580
NT2K16GT35 1395, 1580
NT2K16GT93 1395, 1580
NT2K16GV03 1395, 1580
NT2K16GV35 1395, 1580
NT2K16GV93 1395, 1580
NT2K16XE03 1395, 1580
NT2K16XE35 1395, 1580
NT2K16XE93 1395, 1580
NT2K16XF03 1395, 1580
NT2K16XF35 1395, 1580
NT2K16XF93 1395, 1580
NT2K18GG03 1395, 1580
NT2K18GG35 1395, 1580
NT2K18GG93 1396, 1580
NT2K18GH03 1396, 1580
NT2K18GH35 1396, 1580
NT2K18GH93 1396, 1580
NT2K18GN03 1396, 1580
NT2K18GN35 1396, 1580
NT2K18GN93 1396, 1580
NT2K18GR03 1396, 1580
NT2K18GR35 1396, 1580
NT2K18GR93 1396, 1580
NT2K18XE03 1396, 1580
NT2K18XE35 1396, 1580
NT2K18XE93 1396, 1580
NT2K18XF03 1396, 1580
NT2K18XF35 1396, 1580
NT2K18XF93 1396, 1580
NT2K22VH03 202, 1396
NT2K22VH35 202, 1396
NT2K22VH93 202, 1396
NT2K22WA03 1396, 1580
NT2K22WA35 1396, 1580
NT2K22WA93 1396, 1581
NT2K22XH03 1396, 1581
NT2K22XH35 1396, 1581
NT2K22XH93 1396, 1581
NT2K24KA03 1581
NT2K24KA35 1581
NT2K24KA93 1581
NT2K24WA03 1396, 1581
NT2K24WA35 1396, 1581
NT2K24WA93 1396, 1581
NT2K25YH03 1396, 1581
NT2K25YH35 1396, 1581
NT2K25YH93 1396, 1581
NT2K25YJ03 1396, 1581
NT2K25YJ35 1396, 1581
NT2K25YJ93 1397, 1581
NT2K25YL03 1397, 1581
NT2K25YL35 1397, 1581
NT2K25YL93 1397, 1581
NT2K28AA03 1397, 1581
NT2K28AA35 1397, 1581
NT2K28AA93 1397, 1581
NT2K28AB03 202, 528, 1397
NT2K28AB35 202, 528, 1397
NT2K28AB93 202, 529, 1397
NT2K28AC03 1397, 1581
NT2K28AC35 1397, 1581
NT2K28AC93 1397, 1581
NT2K28AD03 202, 529, 1397
NT2K28AD35 202, 529, 1397
NT2K28AD93 202, 530, 1397
NT2K28KA03 1581
NT2K28KA35 1581
NT2K28KA93 1581
NT2K28KB-03 202, 530, 1397
NT2K28KB-35 202, 530, 1397
NT2K28KB-93 202, 530, 1397
NT2K33AA 1397
NT2K34AA 1397
NT2K36AA03 1397, 1581
NT2K36AA35 1397, 1581
NT2K36AA93 1397, 1581
NT2K40WA 202, 530, 1397
NT2K64WA 1397, 1581
NT2K64WB 1397, 1581
NT2K64WC 1397, 1581
NT2K65XH 1397, 1582
NT2K65XJ 1397, 1582
NT2K65XR 202, 531, 1397
NT2K68AA 203, 531, 1397
NT2K69AA 203, 531, 1397
NT2K71AA 209, 532, 1397
NT2K80AA 1582
NT2K80AB 1582
NT2K80AD 207, 1397
NT2K80GB 207, 1397
NT2K83AA03 203, 532, 1397

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT2K83AA35 203, 532, 1398
NT2K83AA93 203, 532, 1398
NT2K83BA03 203, 533, 1398
NT2K83BA35 203, 533, 1398
NT2K83BA93 203, 533, 1398
NT2K84AA 1582
NT2R02AA 1582
NT2R03AA 1398, 1582
NT2R05AA 1582
NT2R07AA 1398, 1582
NT2R08AA 1582
NT2R08AC 1582
NT2R08AD 1582
NT2R08AE 1582
NT2R08AG 1582
NT2R08AH 1582
NT2R08AJ 1582
NT2R08AK 1582
NT2R08AN 1582
NT2R08AR 1582
NT2R08AS 1582
NT2R08AT 1582
NT2R08AU 1582
NT2R08AV 1582
NT2R08AW 1582
NT2R08AX 1582
NT2R0901 1582
NT2R12AA 1582
NT2R15AA 1398, 1582
NT2R16AA 1582
NT2R17AA 1582
NT2R18AA 1582
NT2R19AA 1582
NT2R21AA 1582
NT2R22AA 1582
NT2R23AA 1398, 1583
NT2R24AA 1398, 1583
NT2R25AA 1583
NT2R26AA 1583
NT2R2703 1583
NT2R27AA 1583
NT2R28AA 1583
NT2R29AA 1583
NT2R31AA 1583
NT2R50AA 1398, 1583
NT2R51AC 1583
NT2R51AD 1583
NT2R54AA 1583
NT2R54BA 1583
NT2R54CA 1583
NT2R55AA 1583
NT2R55BA 1583
NT2R55CA 1583
NT2R56AA 1583
NT2R56BA 1583
NT2R56CA 1583
NT2R57AA 1583
NT2R57BA 1583
NT2R57CA 1583
NT2R59AA 1583
NT2R70AA 1398, 1583
NT2R81AA 323, 534, 1398
NT2R81BA 323, 534, 1398
NT2R8601 1398, 1583
NT2R96AA 1583
NT2R96BA 1583
NT2R96CA 1583
NT2R96DA 1583
NT2R99AA 1398
NT2R99BA 1583
NT3G30AA35 209, 534, 1398
NT3G40AA35 1583
NT3G40AB35 1398, 1584
NT3G40BB35 204, 535, 1398
NT3M20AA 1584
NT3M36AE 1398, 1584
NT3M50AC 1398, 1584
NT3M50AD 250, 269, 535, 1398
NT3M56AC 1584
NT3R01CA 344, 1398
NT3R01DA 344, 1398
NT3R01EA 1584
NT3R04AA 1584
NT3R05AA 1584
NT3R06AA 1584
NT3R07AA 1584
NT3R10AA 1584
NT3R10BA 1584
NT3R10CA 1584
NT3R10DA 1584
NT3R10EA 1584
NT3R11AA 1584
NT3R11BA 1584
NT3R11CA 1584
NT3R11DA 1584
NT3R11EA 1584
NT3R12AA 280, 535, 1398
NT3R12BA 1584
NT3R12CA 1584
NT3R12DA 1584
NT3R12EA 1584
NT3R13AA 1584
NT3R13BA 1584
NT3R13CA 1584
NT3R13EA 1584
NT3R14AA 1584
NT3R14BA 1584
NT3R14CA 1584

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT3R14EA 1584
NT3R15AA 1584
NT3R15BA 1584
NT3R15CA 1585
NT3R15EA 1585
NT3R16AA 1585
NT3R16BA 1585
NT3R17AA 1585
NT3R17BA 1585
NT3R17CA 1585
NT3R17EA 1585
NT3R18AA 1585
NT3R18BA 1585
NT3R18CA 1585
NT3R19AA 1585
NT3R19BA 1585
NT3R20AA 1585
NT3R20BA 1585
NT3R23AA 275, 536, 1398
NT3R23BA 275, 285, 536, 1398
NT3R24AA 1585
NT3R25AA 1585
NT3R25BA 1585
NT3R25CA 1585
NT3R25DA 1585
NT3R26AA 1585
NT3R26BA 1585
NT3R26CA 1585
NT3R26DA 1585
NT3R27AA 1585
NT3R27BA 1585
NT3R28AA 290, 536, 1398
NT3R29AA 1585
NT3R29CA 1585
NT3R30AA 1585
NT3R30CA 1585
NT3R31AA 1585
NT3R31CA 1585
NT3R32CA 1586
NT3R33AA 1586
NT3R33BA 1586
NT3R34AA 1586
NT3R35AA 1586
NT3R35BA 1586
NT3R35CA 1586
NT3R35DA 1586
NT3R39AA 1586
NT3R43AA 1586
NT3R43BA 1586
NT3R45AA 1586
NT3R45BA 1586
NT3R45CA 1586
NT3R45DA 1586
NT3R46AA 1586
NT3R51AA 295, 536, 1398
NT3R52AA 295, 537, 1398
NT3R53CA 1398, 1586
NT3R53DA 1586
NT3R67AA 272, 285, 537, 1398
NT3R67BA 272, 285, 537, 1399
NT3R71AA 236, 246, 257, 538, 1399
NT3R7201 1586
NT3R7204 1586
NT3R7209 1586
NT3R7212 1586
NT3R74AA 1586
NT3R74CA 1586
NT3R75AA 272, 285, 538, 1399
NT3R75BA 272, 285, 538, 1399
NT3R76AA 280, 539, 1399
NT3R76BA 280, 539, 1399
NT3R76CA 280, 540, 1399
NT3R77AA 280, 540, 1399
NT3R77BA 280, 540, 1399
NT3R78AA 280, 541, 1399
NT3R78BA 280, 541, 1399
NT3R79AA 1586
NT3R79BA 280, 541, 1399
NT3R80AA 1586
NT3R81AA 1586
NT3R81AB 1586
NT3R82BA 1586
NT3R83AA 275, 542, 1399
NT3R87AA 1586
NT3R92AA 1586
NT3R92CA 1586
NT3R93AA 1586
NT3R93CA 1586
NT3R94AA 1587
NT3R94CA 1587
NT3R9501 226, 1399
NT4G08BA 1399, 1587
NT4G08BB 1399, 1587
NT4G08CA 1399, 1587
NT4G09BC 1587
NT4G09CC 1587
NT4G09DC 1587
NT4G09EC 1587
NT4G13AJ 1587
NT4G13AK 1587
NT4G13AL 1587
NT4G13BA 1587
NT4G13EB 1399, 1587
NT4G13FA 1587
NT4G23AD 1587
NT4G23AE 1587
NT4G23BA 1587
NT4G25CA 1587

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT4G25CB 1399, 1587
NT4G26AC 1399, 1587
NT4G32BA 1587
NT4G40CA 1587
NT4G41BA 1587
NT4G42CA 1587
NT4G46CA 1587
NT4G46JD 1399, 1587
NT4G46KD 1399, 1587
NT4G46LD 1587
NT4G50DA 1587
NT4G59AB 1587
NT4G59AC 1399, 1587
NT4G59AF 1399, 1587
NT4G59AG 1399, 1587
NT4G81YE 1588
NT4N43AA 185, 542, 1399
NT4N46AA 183, 542, 1399
NT4N50AA 185, 542, 1399
NT4N65AA 25, 1399, 1588
NT4N65AB 177, 543, 1399
NT4N66AA 25, 1399, 1588
NT4N66AB 177, 543, 1399
NT4N67AA 177, 543, 1399
NT4N6809 197, 543, 1400
NT4N68AA 177, 544, 1400
NT4N71BA 197, 1400
NT4N88AA 188, 544, 1400
NT4N88BA 188, 544, 1400
NT4N89AA 188, 1400
NT4N90AA 188, 544, 1400
NT4N92AA 188, 1400
NT4N93AA 188, 544, 1400
NT4N95AA 188, 544, 1400
NT4N96AA 188, 545, 1400
NT4N97AA 183, 545, 1400
NT4N97BA 183, 545, 1400
NT4R01AA 1400, 1588
NT4R01AC 266, 545, 1400
NT4R03AA 1400, 1588
NT4R03AB 266, 546, 1400
NT4R04AA 1588
NT4R04AB 266, 546, 1400
NT4R05AA 1400, 1588
NT4R05AB 1400, 1588
NT4R06AA 1400, 1588
NT4R06AB 1400, 1588
NT4R08AA 266, 546, 1400
NT4R09AA 1400, 1588
NT4R09BA 1400, 1588
NT4R10AA 266, 546, 1400
NT4R11AA 266, 547, 1400
NT4R20AA 267, 547, 1400
NT4R20AB 267, 547, 1400
NT4R2102 267, 548, 1400
NT4R2104 1588
NT4R2106 1400, 1588
NT4R2107 1400, 1588
NT4R2108 1400, 1588
NT4R2109 1401, 1588
NT4R28AA 1401, 1588
NT4R28AB 1401, 1588
NT4R28AC 1401, 1588
NT4R28BA 267, 548, 1401
NT4R30AA 1588
NT4R30AB 1588
NT4R30AC 1588
NT4R30AD 1588
NT4R30AE 1588
NT4R30AF 1588
NT4R32AA 1401, 1588
NT4R33AA 1588
NT4R35AA 267, 548, 1401
NT4R36AA 267, 548, 1401
NT4R37AA 267, 548, 1401
NT4R44AA 1401, 1588
NT4R45AA 266, 549, 1401
NT4R57AA 1588
NT4R58AA 1588
NT4R58AB 267, 549, 1401
NT4R59AA 267, 549, 1401
NT4R60AA 267, 549, 1401
NT4R61AA 268, 550, 1401
NT4R61BA 1588
NT4R68AA 1588
NT4R69AA 1589
NT4R71AA 1401, 1589
NT5C03 1589
NT5C03BJ 1401, 1589
NT5C03CH 1401, 1589
NT5C04 1589
NT5C04CA 1401, 1589
NT5C06CA 1401, 1589
NT5C06CC 185, 550, 1401
NT5C07AB 1589
NT5C07AC 185, 550, 1401
NT5C10CC 1589
NT5C10CC1 185, 550, 1401
NT5C11BC 185, 550, 1401
NT5C12AC 185, 550, 1401
NT5D03AA 1401, 1589
NT5D03BA 1401, 1589
NT5D03CA 1401, 1589
NT5D03EA 1401, 1589
NT5D03FA 1401, 1589
NT5D03FB 177, 551, 1401
NT5D03PB 177, 551, 1401
NT5D10AA 1401, 1589

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT5D10CA 1401, 1589
NT5D10EA 1401, 1589
NT5D10JA 1401, 1589
NT5D11AA 1401, 1589
NT5D11AB 1402, 1589
NT5D11AC 1402, 1589
NT5D11AD 1402, 1589
NT5D11AE 177, 551, 1402
NT5D12 Dual-port DTI/PRI Card Product Description and Installation 353, 1488
NT5D12AA 1402, 1589
NT5D12AB 1402, 1589
NT5D12AC 1402, 1589
NT5D12AD 1402, 1589
NT5D12AF 25, 1402, 1589
NT5D12AG 177, 552, 1402
NT5D13AA 177, 552, 1402
NT5D14AA 1402, 1589
NT5D14AB 1402, 1589
NT5D14AC 1402, 1589
NT5D14AD 66, 177, 552, 1402
NT5D16AA 1589
NT5D16BA 188, 1402
NT5D16CA 1590
NT5D16DA 188, 1402
NT5D16EA 188, 552, 1402
NT5D17AA 188, 1402
NT5D19AA 188, 553, 1402
NT5D20AA 1402, 1590
NT5D20BA 1402, 1590
NT5D2103 1590
NT5D2104 183, 1402
NT5D30AA 177, 553, 1402
NT5D40AA 183, 553, 1402
NT5D51AA 1402, 1590
NT5D51AB 1402, 1590
NT5D51AC 177, 343, 553, 1402
NT5D52AA 1590
NT5D52AB 1590
NT5D52AC 176, 1402
NT5D52BA 1590
NT5D52BB 1590
NT5D52BC 176, 1402
NT5D60AA 64, 177, 554, 1402
NT5D61 IODU/C Reference Guide 349, 1498, 1670
NT5D61AA 1402, 1590
NT5D61AB 185, 554, 1402
NT5D62AA 1590
NT5D62BA 1590
NT5D62BB 177, 343, 554, 1403
NT5D64AA 1403, 1590
NT5D64BA 1403, 1590
NT5D64CA 177, 1403
NT5D65AA 1403, 1590
NT5D65BA 1403, 1590
NT5D65CA 177, 554, 1403
NT5D67AA 1403, 1590
NT5D67BA 1403, 1590
NT5D67CA 66, 177, 1403
NT5D68AA 1403, 1590
NT5D68BA 1403, 1590
NT5D68CA 66, 177, 1403
NT5D69AA 1403, 1590
NT5D69BA 1403, 1590
NT5D69CA 66, 177, 555, 1403
NT5D83AA 25, 1590
NT5D85AA 66, 183, 1403
NT5D86AA 66, 183, 555, 1403
NT5D87AA 66, 183, 1403
NT5D90BA 197, 555, 1403
NT5D97AA 177, 555, 1403
NT5F33BA 351, 556, 1403
NT5F3401 344, 1403
NT5F34AA 344, 556, 1403
NT5F36AA 344, 556, 1403
NT5F37AA 25, 1590
NT5F49AA 351, 1403
NT5F50AA 1590
NT5F50AB 1590
NT5F50AC 351, 1403
NT5F51AA 1590
NT5F52AA 208, 557, 1403
NT5F53AA 1590
NT5F53AC 351, 1403
NT5F54AB 351, 1403
NT5F55AA 1590
NT5F55AB 1590
NT5F55AC 351, 1403
NT5F56AA 344, 1404
NT5F57AA 344, 1404
NT5F58AA 345, 1404
NT5F59AA 345, 1404
NT5F69AA 1590
NT5F81AA 345, 1404
NT5F82AA 351, 1404
NT5F83AA 1591
NT5F84AA 351, 1404
NT5F85AA 351, 1404
NT5F86AA 351, 1404
NT5F87AA 351, 1404
NT5F88AA 351, 557, 1404
NT5F89AA 351, 557, 1404
NT5F90AA 1591
NT5F91AA 351, 558, 1404
NT5F93AA 351, 1404
NT5F94AA 351, 1404
NT5F96AA 1591
NT5F97AA 1591

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT5F98AA 345, 1404
NT5F99AA 351, 1404
NT5G01AA 1404
NT5G03AA 1404
NT5G11AA 177, 558, 1404
NT5G15AA 197, 1404
NT5G31AA 177, 558, 1404
NT5G32AA 177, 558, 1404
NT5G33AA 197, 1404
NT5G53AA 25, 1591
NT5G71AA 176, 559, 1404
NT5G91AA 1591
NT5G91AB 176, 559, 1404
NT5G92AA 177, 343, 1404
NT5G95AA 177, 1404
NT5K1110 1591
NT5P41AQ 1405
NT5P41AZ 270, 559, 1405
NT5P41TC 25, 1591
NT5P41ZR 270, 559, 1405
NT5P43DF 1591
NT5P44FA 1591
NT5P44FB 1591
NT5P46FA 1591
NT5P46GA 1591
NT5P46HA 1591
NT5P46JA 1591
NT5P46LA 1591
NT5P46MA 1591
NT5P46NA 1591
NT5P46PA 1591
NT5P60AA 1591
NT5P60AB 1591
NT5P60AC 1591
NT5P60AD 1591
NT5P61AA 1591
NT5P70DA 560, 1405
NT5P70EA 560, 1405
NT5P9201 1591
NT5P9203 1591
NT5P92AA 1591
NT5P92AB 1591
NT5P92BA 1591
NT5P92BB 1591
NT5R05AA 1405, 1591
NT5R07AA 1591
NT5R08AA 1591
NT5R09AA 1591
NT5R09AB 1592
NT5R09AE 1592
NT5R09AF 1592
NT5R11AA 1592
NT5R11BA 1592
NT5R11BB 1592
NT5R12AA 1592
NT5R12AB 1592
NT5R13AA 1592
NT5R13AB 1592
NT5R13AC 1592
NT5R13BB 1592
NT5R13BC 1592
NT5R13CC 1592
NT5R13CD 1592
NT5R16CA 1592
NT5R17CA 1592
NT5R18HA 1592
NT5R18JA 1592
NT5R18KA 1592
NT5R18LA 1592
NT5R33AA 1592
NT5R33AB 1592
NT5R33AD 1592
NT5R33AS 1592
NT5R33AU 240, 250, 560, 1405
NT5R33BA 1592
NT5R33BB 1592
NT5R33BD 1592
NT5R33BS 1592
NT5R33BU 250, 560, 1405
NT5R33CA 1592
NT5R33CB 1592
NT5R33CD 1592
NT5R33CS 1592
NT5R33CU 240, 250, 561, 1405
NT5R33DA 1592
NT5R33DB 1593
NT5R33DD 1593
NT5R33DS 1593
NT5R33DU 240, 251, 561, 1405
NT5R33EA 1593
NT5R33EB 1593
NT5R33ED 1593
NT5R33ES 1593
NT5R33EU 251, 561, 1405
NT5R33FA 1593
NT5R33FB 1593
NT5R33FD 1593
NT5R33FS 1593
NT5R33FU 240, 251, 562, 1405
NT5R33GA 1593
NT5R33GB 1593
NT5R33GD 1593
NT5R33GS 1593
NT5R33GU 241, 251, 562, 1405
NT5R33JS 1593
NT5R33LS 1593
NT5R3501 263, 562, 1405
NT5R35AA 1593

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT5R35AB 1593
NT5R35AD 251, 1405
NT5R35BA 1593
NT5R35BB 1593
NT5R35CA 1593
NT5R35CB 1593
NT5R35CD 251, 1405
NT5R35DA 1593
NT5R35DB 1593
NT5R35DD 252, 1405
NT5R35EA 1593
NT5R35EB 1593
NT5R35ED 252, 1405
NT5R35FA 1593
NT5R35FB 1593
NT5R35LD 252, 1405
NT5R35NA 1593
NT5R35PA 1593
NT5R36AA 1593
NT5R36AB 1593
NT5R36AC 59, 562, 1405
NT5R36BA 1594
NT5R36BB 1594
NT5R36BC 230, 241, 252, 563, 1405
NT5R36CA 1594
NT5R36CB 1594
NT5R36CC 230, 241, 252, 563, 1405
NT5R36DA 1594
NT5R36DB 1594
NT5R36DC 230, 241, 252, 563, 1405
NT5R36EA 1594
NT5R36EB 1594
NT5R36EC 231, 241, 253, 564, 1405
NT5R36FA 1594
NT5R36FB 1594
NT5R36FC 231, 241, 253, 564, 1405
NT5R36GA 1594
NT5R36GB 1594
NT5R36GC 231, 241, 253, 564, 1405
NT5R36HA 1594
NT5R36HB 1594
NT5R36HC 231, 242, 253, 565, 1405
NT5R36JA 1594
NT5R36JB 1594
NT5R36JC 231, 242, 253, 565, 1405
NT5R45AA 1594
NT5R45AB 1594
NT5R45AC 231, 242, 253, 565, 1405
NT5R45BA 1594
NT5R45BB 1594
NT5R45BC 231, 242, 253, 566, 1405
NT5R45CA 1594
NT5R45CB 1594
NT5R45CC 232, 242, 254, 566, 1405
NT5R45DA 1594
NT5R45DB 1594
NT5R45DC 232, 242, 254, 566, 1405
NT5R45EA 1594
NT5R45EB 1594
NT5R45EC 232, 243, 254, 566, 1405
NT5R45FA 1594
NT5R45FB 1594
NT5R45FC 232, 243, 254, 567, 1405
NT5R45GA 1594
NT5R45GB 1594
NT5R45GC 232, 243, 254, 567, 1405
NT5R45HA 1594
NT5R45HB 1594
NT5R45HC 232, 243, 254, 567, 1405
NT5R45JA 1594
NT5R45JB 1594
NT5R45JC 233, 243, 255, 568, 1405
NT5R46AA 351, 568, 1406
NT5R52AC 1595
NT5R53AB 1595
NT5R53AC 1595
NT5R55AB 1406, 1595
NT5R56AA 1595
NT5R56AB 1595
NT5R56AC 1595
NT5R63AA 1406, 1595
NT5R64AA 1406, 1595
NT5R70AA 1595
NT5R70AB 1595
NT5R70AC 1595
NT5R82AB 1595
NT5R83AA 1595
NT5R85AA 1595
NT5R86AA 1595
NT5R87AA 345, 1406
NT5R88AA 1595
NT5R89AA 1595
NT5R90AA 1595
NT5R91AA 1595
NT5R92AA 1595
NT5R93AA 1595
NT5R93CA 1595
NT5R95AA 1595
NT5R96AA 1595
NT5R98AA 351, 568, 1406
NT5R99AA 345, 1406
NT6C14PA 185, 568, 1406
NT6C14PE 185, 568, 1406
NT6C14PF 185, 569, 1406
NT6C14PG 185, 569, 1406
NT6C25FF 185, 569, 1406
NT6C25PC 185, 569, 1406
NT6C25PD 185, 569, 1406

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT6C40CF 185, 570, 1406
NT6D00AB 1406, 1595
NT6D00AC 1595
NT6D00BC 1595
NT6D11AB 1406, 1595
NT6D11AC 1406, 1595
NT6D11AF 177, 570, 1406
NT6D3903 1406, 1595
NT6D3906 1406, 1595
NT6D40AA 1406, 1596
NT6D40AB 1406, 1596
NT6D40AD 1406, 1596
NT6D40BA 185, 570, 1406
NT6D41AA 1406, 1596
NT6D41AB 1406, 1596
NT6D41AD 185, 570, 1406
NT6D41BA 266, 570, 1406
NT6D41CA 185, 1406
NT6D42CB 1406, 1596
NT6D42CC 1406, 1596
NT6D42CD 185, 571, 1407
NT6D43AA 1407, 1596
NT6D4406 268, 571, 1407
NT6D4407 268, 571, 1407
NT6D4408 268, 571, 1407
NT6D4409 268, 571, 1407
NT6D4410 268, 572, 1407
NT6D4411 268, 572, 1407
NT6D4412 268, 572, 1407
NT6D4415 268, 572, 1407
NT6D4417 268, 572, 1407
NT6D4418 268, 573, 1407
NT6D4419 268, 573, 1407
NT6D44AA 269, 573, 1407
NT6D44DC 269, 573, 1407
NT6D45AA 1407, 1596
NT6D45CA 263, 267, 574, 1407
NT6D46AA 1407, 1596
NT6D47AA 1407, 1596
NT6D47BA 1407, 1596
NT6D47DA 1407, 1596
NT6D48AA 1407, 1596
NT6D48BA 1407, 1596
NT6D48DA 1407, 1596
NT6D48EA 1407, 1596
NT6D48FA 258, 267, 574, 1407
NT6D48GA 263, 267, 574, 1407
NT6D51AA 327, 574, 1407
NT6D52AA 1407, 1596
NT6D52BA 1407, 1596
NT6D5303 185, 574, 1407
NT6D5304 185, 575, 1407
NT6D53AA 1596
NT6D54AA 186, 575, 1407
NT6D54CA 269, 575, 1407
NT6D6003 177, 575, 1407
NT6D6008 1596
NT6D60DA 1596
NT6D63AA 1407, 1596
NT6D63BA 1407, 1596
NT6D64AA 1408, 1596
NT6D65AA 1408, 1596
NT6D65AB 1408, 1596
NT6D66 CP Card Field Memory Upgrade 1663
NT6D66AA 1408, 1596
NT6D66DA 1408, 1596
NT6D70AA 64, 177, 575, 1408
NT6D71AA 65, 177, 576, 1408
NT6D72AA 197, 1408
NT6D73AA 177, 576, 1408
NT6D78AA 1596
NT6D80AA 1408, 1596
NT6D80AB 178, 576, 1408
NT6D81AA 178, 576, 1408
NT6D82 Power System 349, 1498, 1662
NT6D82 Power System NTP 1655
NT6D8201 1596
NT6D8202 1596
NT6D8203 1596
NT6D8204 1597
NT6D8207 1597
NT6D8208 1597
NT6D8209 1597
NT6D8211 1597
NT6D8212 1597
NT6D8213 1597
NT6D8215 1597
NT6D98AA 316, 327, 577, 1408
NT6G00AA35 1408, 1597
NT6G00AC35 1408, 1597
NT6G00AD35 1408, 1597
NT6G00AE35 1408, 1597
NT6G00AF 1597
NT6G00AF35 204, 577, 1408
NT6P0104 268, 577, 1408
NT6P0106 269, 1408
NT6P0109 268, 577, 1408
NT6P0110 249, 268, 578, 1408
NT6P0111 1597
NT6P0112 268, 578, 1408
NT6P0113 268, 578, 1408
NT6P0114 1597
NT6P0118 1597
NT6P0119 1597
NT6P0122 239, 268, 1408
NT6P0123 268, 1408
NT6P0124 268, 1408
NT6P0125 268, 1408

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT6P0126 268, 1408
NT6P01AA 269, 1408
NT6P01BA 269, 1408
NT6P02AA 1408, 1597
NT6P03AA 1408, 1597
NT6P04AA 258, 266, 578, 1409
NT6P05AA 1409, 1597
NT6P05BA 263, 267, 578, 1409
NT6P06AA 1409, 1597
NT6P07AA 1409, 1597
NT6P07BA 249, 267, 579, 1409
NT6P08AA 258, 266, 579, 1409
NT6P42AA 249, 267, 579, 1409
NT6P43AA 1409, 1597
NT6P44AA 1409, 1597
NT6P44BA 246, 249, 258, 267, 579, 1409
NT6P97AA 249, 267, 579, 1409
NT6R00AA 1597
NT6R00AB 1597
NT6R01AA 1597
NT6R01AB 1597
NT6R02AA 1597
NT6R02AB 1597
NT6R03AA 1597
NT6R03AB 1597
NT6R04AA 1597
NT6R04AB 1597
NT6R06AA 1598
NT6R06AB 1598
NT6R06AC 1598
NT6R06AD 1598
NT6R07AA 1598
NT6R0801 1598
NT6R08AA 1598
NT6R08AB 1598
NT6R08AD 1598
NT6R0901 1598
NT6R09AA 1598
NT6R10AA 1598
NT6R10AD 307, 580, 1409
NT6R10BA 1598
NT6R14AA 267, 580, 1409
NT6R15AA 249, 267, 580, 1409
NT6R16AA 240, 1409
NT6R16AB 239, 1409
NT6R17AA 1409, 1598
NT6R20AA 1598
NT6R20AB 1598
NT6R21AA 1598
NT6R21AB 1598
NT6R22AA 1598
NT6R22AB 1598
NT6R23AA 1598
NT6R23AB 1598
NT6R24AA 1598
NT6R24AB 1598
NT6R30AB 1598
NT6R31AB 1598
NT6R32AB 1598
NT6R33AB 1598
NT6R40AA 1598
NT6R41AA 321, 581, 1409
NT6R43AA 321, 581, 1409
NT6R47AA 25, 1598
NT6R47AD 233, 243, 255, 1409
NT6R47BA 25, 1598
NT6R47BD 233, 243, 255, 1409
NT6R47CA 25, 1598
NT6R47CD 233, 243, 255, 1409
NT6R47DA 25, 1599
NT6R47DD 233, 243, 255, 1409
NT6R47EA 25, 1599
NT6R47ED 233, 243, 255, 1409
NT6R47FA 25, 1599
NT6R47FD 233, 243, 255, 1409
NT6R47GA 25, 1599
NT6R47GD 233, 243, 255, 1409
NT6R47HA 25, 1599
NT6R47HD 233, 243, 255, 1409
NT6R47JA 25, 1599
NT6R47JD 233, 243, 255, 1409
NT6R49AA 351, 581, 1409
NT6R50AA 1599
NT6R50AB 325, 582, 1409
NT6R55AA 1599
NT6R56AA 1599
NT6R60AA 1599
NT6R6602 1599
NT6R66AA 1599
NT6R67AA 325, 582, 1409
NT6R68AA 325, 583, 1409
NT6R69AA 1599
NT6R69AB 325, 583, 1410
NT6R77AA 1599
NT6R77AB 1599
NT6R77AD 345, 584, 1410
NT6R78AA 1599
NT6R78AB 1599
NT6R78AD 63, 584, 1410
NT6R79AA 1599
NT6R79AB 325, 584, 1410
NT6R81AA 345, 584, 1410
NT6R82AA 345, 585, 1410
NT6R83AA 345, 585, 1410
NT6R84AA 345, 585, 1410
NT6R85AA 345, 585, 1410
NT6R86AA 345, 586, 1410
NT6R87AA 345, 586, 1410

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT6R88AA 345, 586, 1410
NT6R89AA 345, 586, 1410
NT6R90AA 345, 587, 1410
NT6R91AA 345, 587, 1410
NT6R92AA 1599
NT6R93AA 345, 587, 1410
NT6R94AA 1599
NT6R99AA 345, 587, 1410
NT7D00AA 183, 588, 1410
NT7D00AC 1599
NT7D00BA 183, 588, 1410
NT7D03AA 1410, 1599
NT7D04AA 1410, 1599
NT7D04AB 1410, 1599
NT7D05AA 197, 588, 1410
NT7D06AA 197, 269, 588, 1410
NT7D0902 183, 197, 588, 1410
NT7D09AA 1599
NT7D09CA 183, 589, 1410
NT7D10AA 1410, 1599
NT7D10CA 1411, 1599
NT7D1201 186, 589, 1411
NT7D12AA 186, 589, 1411
NT7D14AA 1411, 1599
NT7D15AA 1411, 1599
NT7D15AB 1411, 1599
NT7D16 Data Access Card NTP 346, 1484
NT7D16AA 1411, 1599
NT7D16AB 1411, 1599
NT7D16BA 65, 178, 589, 1411
NT7D17AC 1599
NT7D17DC 1600
NT7D18AA 326, 590, 1411
NT7D18AB 326, 590, 1411
NT7D18KA 327, 590, 1411
NT7D19PA 1411, 1600
NT7D19RA 272, 590, 1411
NT7D44AA 1411, 1600
NT7D44BA 1411, 1600
NT7D45AA 1411, 1600
NT7D46AA 328, 591, 1411
NT7D46AB 1600
NT7D46AD 328, 591, 1411
NT7D46AF 328, 591, 1411
NT7D46AL 328, 591, 1411
NT7D46AT 328, 591, 1411
NT7D46AV 328, 592, 1411
NT7D47AG 328, 592, 1411
NT7D47BA 272, 592, 1411
NT7D47BB 272, 592, 1411
NT7D47DA 328, 1411
NT7D47EA 272, 296, 306, 328, 1411
NT7D48AA 328, 592, 1411
NT7D58AB 1600
NT7D58AD 1600
NT7D58AF 1600
NT7D58AL 1600
NT7D58AT 1600
NT7D58AV 1600
NT7D58BB 188, 1411
NT7D58EB 328, 593, 1411
NT7D58ED 328, 593, 1411
NT7D58EF 328, 593, 1411
NT7D58EL 328, 593, 1411
NT7D58ET 328, 593, 1411
NT7D58EV 328, 594, 1411
NT7D60AA 1600
NT7D61AB 1600
NT7D61AD 1600
NT7D61AF 1600
NT7D61AL 1600
NT7D61AT 1600
NT7D61AV 1600
NT7D61EB 328, 594, 1411
NT7D61ED 328, 594, 1412
NT7D61EF 328, 594, 1412
NT7D61EL 328, 594, 1412
NT7D61ET 328, 595, 1412
NT7D61EV 328, 595, 1412
NT7D62AA 1412, 1600
NT7D62AB 1412, 1600
NT7D62AC 326, 595, 1412
NT7D62CA 326, 595, 1412
NT7D62DA 326, 596, 1412
NT7D62EA 326, 596, 1412
NT7D63AA 326, 596, 1412
NT7D64AA 326, 596, 1412
NT7D64DC 326, 596, 1412
NT7D67CA 1412, 1600
NT7D67CB 1412, 1600
NT7D71AA 1600
NT7D71BA 328, 597, 1412
NT7D72AA 1600
NT7D73AA 1600
NT7D74AA 1600
NT7D75AA 1600
NT7D79AA 1600
NT7D89BA 1600
NT7D89CA 188, 597, 1412
NT7D90BA 1600
NT7D90CA 1600
NT7D90DA 189, 597, 1412
NT7D95AA 272, 1412
NT7D97AG 1600
NT7D99AA 268, 328, 597, 1412
NT7E74AA 1600
NT7G10AA 209, 597, 1412
NT7R27AA 1601

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT7R27BA 1601
NT7R27CA 1601
NT7R28AA 1601
NT7R28BA 1601
NT7R28CA 1601
NT7R29AA 1601
NT7R30AA 1601
NT7R30BA 1601
NT7R30CA 1601
NT7R31AA 1601
NT7R31BA 1601
NT7R31CA 1601
NT7R32AA 1601
NT7R33AA 1601
NT7R35AA 1601
NT7R35BA 1601
NT7R35CA 1601
NT7R36AA 1601
NT7R36BA 1601
NT7R36CA 1601
NT7R37AA 1601
NT7R37BA 1601
NT7R37CA 1601
NT7R38AA 1601
NT7R38BA 1601
NT7R38CA 1601
NT7R39AA 1601
NT7R39BA 1601
NT7R39CA 1601
NT7R51AA 1412, 1601
NT7R51AB 1412, 1601
NT7R51AC 1412, 1602
NT7R51AD 178, 598, 1412
NT7R52AA 1412, 1602
NT7R52AB 1412, 1602
NT7R52AC 1412, 1602
NT7R52AD 178, 598, 1412
NT7R62AA 1602
NT7R66AA 189, 1412
NT7R66BA 189, 1412
NT7R66BB 189, 1412
NT7R67BA 160, 598, 1413
NT7R67CA 160, 598, 1413
NT7R67DA 160, 598, 1413
NT7R68AA 161, 599, 1413
NT7R68BA 161, 599, 1413
NT7R68CA 1602
NT7R68DA 1602
NT7R69AA 161, 599, 1413
NT7R69BA 161, 599, 1413
NT7R70AA 1602
NT7R70BA 1602
NT7R70CA 1602
NT7R70DA 1602
NT7R70JA 1602
NT7R70KA 1602
NT7R70LA 1602
NT7R70MA 1602
NT7R7101 1602
NT7R71AA 1602
NT7R72CA 1602
NT7R74AA 1602
NT7R86AA 189, 1413
NT7R87AA 189, 1413
NT7R87BA 66, 189, 1413
NT7R94AA 189, 1413
NT8D01AC 1413, 1602
NT8D01AD 1413, 1602
NT8D01BC 178, 599, 1413
NT8D02AA 1413, 1602
NT8D02AB 1413, 1602
NT8D02EA 1413, 1602
NT8D02EB 1413, 1602
NT8D02GA 65, 600, 1413
NT8D03AA 1413, 1602
NT8D03AB 1413, 1602
NT8D03AE 1413, 1602
NT8D03AJ 1413, 1602
NT8D04AA 1413, 1602
NT8D04BA 178, 600, 1413
NT8D06AA 1413, 1602
NT8D06AB 186, 600, 1413
NT8D09AA 1602
NT8D09AB 1413, 1602
NT8D09AD 1413, 1602
NT8D09AG 1413, 1603
NT8D09AJ 1413, 1603
NT8D09AK 1413, 1603
NT8D09AL 1413, 1603
NT8D09BA 65, 178, 600, 1413
NT8D1103 1413, 1603
NT8D1107 197, 600, 1413
NT8D11AC 1603
NT8D11BC 1603
NT8D11DC 1603
NT8D1303 183, 601, 1413
NT8D13AA 183, 601, 1414
NT8D13DC 183, 601, 1414
NT8D14AA 1414, 1603
NT8D14AE 1414, 1603
NT8D14AH 1414, 1603
NT8D14AJ 1414, 1603
NT8D14AK 1414, 1603
NT8D14BA 1414, 1603
NT8D14BB 65, 178, 601, 1414
NT8D15AA 1414, 1603
NT8D15AH 1414, 1603
NT8D15AJ 1414, 1603

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT8D15AK 65, 178, 602, 1414
NT8D16AA 1414, 1603
NT8D16AB 178, 602, 1414
NT8D17AA 1414, 1603
NT8D17CA 1414, 1603
NT8D17EA 1414, 1603
NT8D17FA 178, 602, 1414
NT8D18AA 1414, 1603
NT8D18AB 1414, 1603
NT8D19AA 1414, 1603
NT8D21AA 1414, 1603
NT8D21AB 186, 602, 1414
NT8D22AB 1414, 1603
NT8D22AC 197, 602, 1414
NT8D27AB 1603
NT8D27BB 183, 197, 603, 1414
NT8D29AA 1414, 1603
NT8D29AB 186, 603, 1414
NT8D29BA 186, 1414
NT8D31AA 197, 603, 1414
NT8D31AB 197, 603, 1414
NT8D31AD 197, 604, 1414
NT8D31AE 269, 604, 1415
NT8D3403 1415, 1603
NT8D34AA 1603
NT8D34DC 1603
NT8D3503 1415, 1603
NT8D3507 183, 604, 1415
NT8D35AA 1603
NT8D35BA 183, 604, 1415
NT8D35DC 1603
NT8D35EA 183, 604, 1415
NT8D36AA 184, 604, 1415
NT8D3703 184, 605, 1415
NT8D37AA 1604
NT8D37BA 184, 605, 1415
NT8D37DC 1604
NT8D37EC 184, 605, 1415
NT8D39AA 1604
NT8D40AA 186, 605, 1415
NT8D41AA 1415, 1604
NT8D41BA 178, 1415
NT8D46AA 189, 605, 1415
NT8D46AB 189, 606, 1415
NT8D46AC 184, 606, 1415
NT8D46AD 189, 606, 1415
NT8D46AG 189, 606, 1415
NT8D46AH 1604
NT8D46AJ 189, 606, 1415
NT8D46AL 189, 606, 1415
NT8D46AM 184, 607, 1415
NT8D46AP 189, 607, 1415
NT8D46AQ 189, 607, 1415
NT8D46AS 189, 607, 1415
NT8D46AT 189, 607, 1415
NT8D46AU 189, 608, 1415
NT8D46AV 189, 608, 1415
NT8D46AW 189, 608, 1415
NT8D46AX 189, 608, 1415
NT8D46AY 189, 608, 1415
NT8D46BA 189, 609, 1415
NT8D46BB 189, 609, 1415
NT8D46BC 189, 609, 1415
NT8D46BD 189, 609, 1415
NT8D46BE 189, 609, 1415
NT8D46BF 189, 610, 1415
NT8D46BG 189, 610, 1415
NT8D46BH 189, 610, 1416
NT8D46BJ 189, 610, 1416
NT8D46BK 1604
NT8D46BL 1604
NT8D46BM 189, 610, 1416
NT8D46BV 189, 611, 1416
NT8D46CD 328, 611, 1416
NT8D46CH 189, 611, 1416
NT8D46CV 189, 611, 1416
NT8D46DC 184, 611, 1416
NT8D46DH 189, 612, 1416
NT8D46EH 189, 612, 1416
NT8D47DC 1604
NT8D49AA 184, 612, 1416
NT8D49BA 184, 612, 1416
NT8D52AA 1416, 1604
NT8D52AB 184, 612, 1416
NT8D52DC 1416, 1604
NT8D52DD 184, 612, 1416
NT8D53AB 1416, 1604
NT8D53AD 1604
NT8D53BB 1416, 1604
NT8D53CA 186, 613, 1416
NT8D55AA 1604
NT8D55BA 1604
NT8D56AA 186, 613, 1416
NT8D56AC 1604
NT8D57AA 186, 613, 1416
NT8D63AA 184, 613, 1416
NT8D6401 197, 613, 1416
NT8D64AA 1604
NT8D64AB 1604
NT8D64AC 1604
NT8D64BD 184, 614, 1416
NT8D64BE 184, 1416
NT8D64BF 184, 614, 1416
NT8D64BH 197, 614, 1416
NT8D64CA 184, 614, 1416
NT8D64CB 184, 614, 1416
NT8D64CC 184, 614, 1416
NT8D64CD 184, 1416

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT8D64CE 184, 1416
NT8D68AA 1416, 1604
NT8D69AA 1417, 1604
NT8D7217 190, 615, 1417
NT8D73AD 190, 615, 1417
NT8D73AF 190, 615, 1417
NT8D73AL 190, 615, 1417
NT8D73AS 190, 615, 1417
NT8D74AC 1604
NT8D74AD 1604
NT8D74AE 1604
NT8D74AF 1604
NT8D74BC 190, 616, 1417
NT8D74BD 190, 616, 1417
NT8D74BE 190, 616, 1417
NT8D74BF 190, 616, 1417
NT8D75AC 1604
NT8D75AD 1604
NT8D75BC 190, 616, 1417
NT8D75BD 190, 616, 1417
NT8D76AC 1604
NT8D76AD 1604
NT8D76AE 1604
NT8D76AF 1604
NT8D76AG 1604
NT8D76AJ 1604
NT8D76AL 1604
NT8D76AP 1605
NT8D76BC 190, 617, 1417
NT8D76BD 190, 617, 1417
NT8D76BE 190, 617, 1417
NT8D76BF 190, 617, 1417
NT8D76BG 190, 617, 1417
NT8D76BJ 190, 617, 1417
NT8D76BP 190, 618, 1417
NT8D76BR 190, 1417
NT8D76BS 190, 1417
NT8D77AA 1605
NT8D77AB 1605
NT8D77AC 1605
NT8D77AD 1605
NT8D77BA 190, 618, 1417
NT8D77BB 190, 618, 1417
NT8D77BC 190, 618, 1417
NT8D77BD 190, 618, 1417
NT8D78AA 190, 618, 1417
NT8D79AB 190, 619, 1417
NT8D79AC 190, 619, 1417
NT8D79AD 190, 619, 1417
NT8D79AE 190, 619, 1417
NT8D79AF 190, 619, 1417
NT8D80AB 1605
NT8D80AC 1605
NT8D80AD 1605
NT8D80AE 1605
NT8D80AF 1605
NT8D80AG 1605
NT8D80AJ 1605
NT8D80AL 1605
NT8D80AP 1605
NT8D80AZ 1605
NT8D80BC 190, 620, 1417
NT8D80BD 190, 620, 1417
NT8D80BE 190, 620, 1417
NT8D80BF 190, 620, 1417
NT8D80BG 191, 620, 1417
NT8D80BJ 191, 621, 1417
NT8D80BL 191, 621, 1418
NT8D80BP 191, 621, 1418
NT8D80BZ 191, 621, 1418
NT8D81AA 191, 622, 1418
NT8D82AC 1605
NT8D82AD 191, 622, 1418
NT8D83AC 1605
NT8D83AD 191, 622, 1418
NT8D84AA 191, 622, 1418
NT8D85AB 1605
NT8D85AC 1605
NT8D85AD 1605
NT8D85AE 1605
NT8D85AF 1605
NT8D85AJ 1605
NT8D85AL 1605
NT8D85AP 1605
NT8D85AV 1605
NT8D85AZ 1605
NT8D85BB 191, 622, 1418
NT8D85BC 191, 623, 1418
NT8D85BD 191, 623, 1418
NT8D85BE 191, 623, 1418
NT8D85BF 191, 623, 1418
NT8D85BJ 191, 624, 1418
NT8D85BL 191, 624, 1418
NT8D85BP 191, 624, 1418
NT8D85BV 191, 624, 1418
NT8D85BZ 191, 624, 1418
NT8D86AC 1605
NT8D86AD 1605
NT8D86BD 191, 625, 1418
NT8D88AC 191, 625, 1418
NT8D88AD 191, 625, 1418
NT8D90AF 191, 625, 1418
NT8D91AC 191, 626, 1418
NT8D91AD 191, 626, 1418
NT8D91AE 191, 626, 1418
NT8D91AF 191, 626, 1418
NT8D91AG 191, 626, 1418
NT8D91AJ 191, 627, 1418

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT8D91AP 191, 627, 1418
NT8D91AV 191, 627, 1418
NT8D92AB 191, 627, 1418
NT8D93AJ 191, 627, 1418
NT8D93AW 191, 628, 1418
NT8D95AJ 191, 628, 1418
NT8D95AT 191, 628, 1419
NT8D95AW 191, 628, 1419
NT8D95BJ 191, 628, 1419
NT8D95BT 192, 629, 1419
NT8D95BW 192, 629, 1419
NT8D96AB 192, 629, 1419
NT8D96AE 1605
NT8D96AE VME Multiport Cable 1557, 1605
NT8D96BE 328, 629, 1419
NT8D97AX 1605
NT8D98AD 192, 629, 1419
NT8D98AF 192, 630, 1419
NT8D98AL 192, 630, 1419
NT8D98AS 192, 630, 1419
NT8D98AT 192, 1419
NT8D99AB 192, 630, 1419
NT8D99AC 192, 630, 1419
NT8D99AD 192, 630, 1419
NT8D99BB 1605
NT8D99BD 1605
NT8K90AA35 1419, 1605
NT8R01AA 294, 295, 631, 1419
NT8R03AA 351, 1419
NT8R04AA 1606
NT8R11AA 1606
NT8R14AA 1606
NT8R15AA 1606
NT8R16AA 1606
NT8R17AA 1419, 1606
NT8R17AB 178, 1419
NT8R2001 1606
NT8R20AA 235, 245, 256, 631, 1419
NT8R70AA 25, 1606
NT8UX0603 1606
NT9D00AA 1606
NT9D01AA 1606
NT9D02AA 1606
NT9D03AA 1606
NT9D04AA 1606
NT9D05AA 1606
NT9D06AA 1419, 1606
NT9D07AB 1606
NT9D07AC 1606
NT9D07AD 1606
NT9D07CA 1606
NT9D07DA 1606
NT9D08AA 204, 631, 1419
NT9D09AA 1606
NT9D1103 1606
NT9D13AA 209, 1419
NT9D1501 197, 632, 1419
NT9D15AA 184, 632, 1419
NT9D17AA 1606
NT9D18AA 184, 632, 1419
NT9D19AA 1419, 1606
NT9D19AB 1419, 1606
NT9D19CA 1419, 1606
NT9D19CB 1419, 1606
NT9D19HA 1419, 1606
NT9D19HB 1419, 1606
NT9D20AA 1606
NT9D20AB 1606
NT9D21AA 1607
NT9D21AB 1607
NT9D22AA 1607
NT9D22AB 1607
NT9D23AA 1607
NT9D23AB 1607
NT9D24AA 1607
NT9D24AB 1607
NT9D25AA 1607
NT9D25AB 1607
NT9D26AB 1607
NT9D27AB 1607
NT9D28AB 1607
NT9D33AA 1419, 1607
NT9D34AA 1419, 1607
NT9D35AB 1607
NT9D36AB 1607
NT9D38AA 192, 1419
NT9D39AA 192, 1419
NT9D40AA 1607
NT9D40AB 1607
NT9D41AA 1607
NT9D41AB 1607
NT9D42AA 1607
NT9D42AB 1607
NT9D43AA 1607
NT9D43AB 1607
NT9D44AA 1607
NT9D44AB 1607
NT9D47AB 1607
NT9D47AD 1607
NT9D48AA 1607
NT9D49AA 1607
NT9D50AA 1607
NT9D51AA 1607
NT9D52AA 1608
NT9D53AA 1608
NT9D54AA 1608
NT9D55AA 1608
NT9D56AA 1608

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT9D57AA 1608
NT9D58AA 1608
NT9D59AA 1608
NT9D60AA 1608
NT9D61AA 1608
NT9D62AA 1608
NT9D63AA 1608
NT9D64AA 1608
NT9D65AA 1608
NT9D66AA 1608
NT9D66AB 1608
NT9D66AD 1608
NT9D67AA 1608
NT9D69AA 1608
NT9D70AA 1608
NT9D71AA 1608
NT9D72AA 1608
NT9D73AA 1608
NT9D74AA 1608
NT9D75AA 1608
NT9D76AA 1608
NT9D77AA 1608
NT9D78AA 1608
NT9D79AA 1608
NT9D8001 329, 1420
NT9D8002 329, 1420
NT9D8003 329, 1420
NT9D8004 329, 1420
NT9D80AA 1608
NT9D81AA 1608
NT9D82AA 1608
NT9D83AA 1609
NT9D84AA 1609
NT9D85AA 1609
NT9D86AA 1609
NT9D89AB 1609
NT9D89AD 1609
NT9D89CA 192, 632, 1420
NT9D89DA 192, 632, 1420
NT9D89EA 192, 633, 1420
NT9D89FA 192, 633, 1420
NT9D89GA 192, 633, 1420
NT9D90 1609
NT9D9007 329, 1420
NT9D9008 329, 633, 1420
NT9D90AB 1609
NT9D90AD 1609
NT9D90AE 1609
NT9D90BA 1609
NT9D91AE 1609
NT9D92AA 1609
NT9D92AB 1609
NT9D99AA 269, 634, 1420
NT9F01AA 1609
NT9F01AB 1609
NT9F02AA 297, 634, 1420
NT9F02BA 297, 634, 1420
NT9F02CA 297, 635, 1420
NT9F02DA 297, 635, 1420
NT9F02EA 297, 636, 1420
NT9F02FA 1609
NT9F02GA 297, 636, 1420
NT9F02HA 297, 636, 1420
NT9F02JA 297, 636, 1420
NT9F03AA 297, 637, 1420
NT9F03BA 297, 637, 1420
NT9F03CA 297, 638, 1420
NT9F03DA 297, 638, 1420
NT9F03EA 297, 638, 1420
NT9F03FA 1609
NT9F03GA 297, 639, 1420
NT9F03HA 297, 639, 1420
NT9F03JA 297, 639, 1420
NT9F04AA 298, 640, 1420
NT9F04BA 298, 640, 1420
NT9F04CA 298, 641, 1421
NT9F04DA 298, 641, 1421
NT9F04EA 298, 642, 1421
NT9F04FA 1609
NT9F04GA 298, 642, 1421
NT9F04HA 298, 642, 1421
NT9F04JA 298, 642, 1421
NT9F06AA 298, 643, 1421
NT9F06BA 298, 643, 1421
NT9F06CA 298, 644, 1421
NT9F06DA 298, 644, 1421
NT9F06EA 298, 645, 1421
NT9F06FA 1609
NT9F06GA 299, 645, 1421
NT9F06HA 299, 645, 1421
NT9F06JA 299, 646, 1421
NT9F07AA 300, 646, 1421
NT9F07BA 300, 646, 1421
NT9F07CA 300, 647, 1421
NT9F07DA 300, 647, 1421
NT9F07EA 300, 648, 1421
NT9F07FA 1609
NT9F07GA 300, 648, 1421
NT9F07HA 300, 648, 1421
NT9F07JA 300, 648, 1421
NT9F08AA 301, 649, 1421
NT9F08BA 301, 649, 1421
NT9F08CA 301, 650, 1422
NT9F08DA 301, 650, 1422
NT9F08EA 301, 651, 1422
NT9F08FA 1609
NT9F08GA 301, 302, 651, 1422
NT9F08HA 301, 302, 651, 1422

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT9F08JA 301, 302, 652, 1422
NT9F09AA 299, 652, 1422
NT9F09BA 299, 653, 1422
NT9F09CA 299, 653, 1422
NT9F09DA 299, 654, 1422
NT9F09EA 299, 654, 1422
NT9F09FA 1609
NT9F09GA 299, 655, 1422
NT9F09HA 299, 655, 1422
NT9F09JA 299, 655, 1422
NT9F10AA 302, 656, 1422
NT9F10BA 302, 656, 1422
NT9F10CA 302, 657, 1422
NT9F10DA 302, 657, 1422
NT9F10EA 302, 658, 1422
NT9F10FA 1609
NT9F10GA 302, 658, 1422
NT9F10HA 302, 658, 1422
NT9F10JA 302, 658, 1422
NT9F11AA 299, 659, 1422
NT9F11BA 299, 659, 1422
NT9F11CA 299, 660, 1422
NT9F11DA 299, 660, 1422
NT9F11EA 299, 661, 1422
NT9F11FA 1609
NT9F11GA 299, 661, 1422
NT9F11HA 299, 661, 1423
NT9F11JA 299, 662, 1423
NT9F12AA 301, 662, 1423
NT9F12BA 301, 663, 1423
NT9F12CA 301, 663, 1423
NT9F12DA 301, 664, 1423
NT9F12EA 301, 664, 1423
NT9F12FA 1609
NT9F12GA 301, 665, 1423
NT9F12HA 301, 665, 1423
NT9F12JA 301, 665, 1423
NT9F13AA 301, 666, 1423
NT9F13BA 301, 666, 1423
NT9F13CA 301, 667, 1423
NT9F13DA 301, 667, 1423
NT9F13EA 301, 668, 1423
NT9F13FA 1609
NT9F13GA 301, 668, 1423
NT9F13HA 301, 668, 1423
NT9F13JA 301, 668, 1423
NT9F14AA 299, 669, 1423
NT9F14BA 299, 669, 1423
NT9F14CA 299, 670, 1423
NT9F14DA 299, 670, 1423
NT9F14EA 299, 671, 1423
NT9F14FA 1609
NT9F14GA 299, 671, 1423
NT9F14HA 300, 671, 1423
NT9F14JA 300, 672, 1423
NT9F15AA 300, 672, 1423
NT9F15BA 300, 672, 1423
NT9F15CA 300, 673, 1423
NT9F15DA 300, 673, 1424
NT9F15EA 300, 674, 1424
NT9F15FA 1609
NT9F15GA 300, 674, 1424
NT9F15HA 300, 674, 1424
NT9F15JA 301, 674, 1424
NT9F17AA 295, 675, 1424
NT9F17BA 295, 675, 1424
NT9F17CA 295, 675, 1424
NT9F19AA 295, 676, 1424
NT9F19AB 295, 676, 1424
NT9F23AA 1424, 1609
NT9F23CA 1424, 1609
NT9F24AA 1424, 1609
NT9F24CA 1424, 1610
NT9F25AA 1424, 1610
NT9F26BA 1424, 1610
NT9F26CA 1424, 1610
NT9F26EA 1424, 1610
NT9F26FA 1424, 1610
NT9F26GA 1424, 1610
NT9F26HA 1424, 1610
NT9F27AA 303, 677, 1424
NT9F27AC 303, 677, 1424
NT9F28AA 1424, 1610
NT9F28BA 1424, 1610
NT9F28CA 1610
NT9F30AA 25, 1610
NT9F30AD 25, 1610
NT9F31AA 25, 1610
NT9F31AD 25, 1610
NT9F41AD 297, 677, 1424
NT9F43AA 1610
NT9F43AC 306, 678, 1424
NT9F43AD 678, 1424
NT9F45AB 1610
NT9F45AE 1610
NT9F45DA 1610
NT9F46AA 25, 1610
NT9F46AC 307, 678, 1425
NT9F51AA 1610
NT9F51AB 25, 1610
NT9F51AC 297, 678, 1425
NT9F53AA 307, 1425
NT9F81AA 1610
NT9F81BA 1610
NT9F81CA 1610
NT9F81EA 1610
NT9F81FA 1610
NT9F83AA 1425, 1610

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NT9F84AA 297, 1425
NT9F88AA 1610
NT9F88BA 1610
NT9F90AA 302, 679, 1425
NT9F90BA 302, 680, 1425
NT9J93AD 192, 680, 1425
NT9J94AB 1610
NT9J96AC 192, 680, 1425
NT9J96AD 192, 681, 1425
NT9J96AE 192, 681, 1425
NT9J96AG 192, 681, 1425
NT9J96AH 192, 681, 1425
NT9J96AJ 192, 681, 1425
NT9J97AC 192, 681, 1425
NT9J97AD 192, 682, 1425
NT9J97AE 192, 682, 1425
NT9J97AG 192, 682, 1425
NT9J97AH 192, 682, 1425
NT9J97AJ 192, 682, 1425
NT9J98AC 192, 682, 1425
NT9J98AD 192, 683, 1425
NT9J98AE 192, 683, 1425
NT9J99AC 193, 683, 1425
NT9J99AD 193, 683, 1425
NT9J99AE 193, 683, 1425
NT9K05AA03 201, 684, 1425
NT9K05AA35 201, 684, 1425
NT9K05AA93 201, 684, 1425
NT9K08AA03 201, 684, 1425
NT9K08AA35 201, 685, 1425
NT9K08AA93 201, 685, 1425
NT9K08AB03 201, 685, 1425
NT9K08AB35 201, 686, 1425
NT9K08AB93 201, 686, 1425
NT9K08AC03 201, 686, 1426
NT9K08AC35 201, 687, 1426
NT9K08AC93 201, 687, 1426
NT9K08AD03 201, 687, 1426
NT9K08AD35 202, 688, 1426
NT9K08AD93 202, 688, 1426
NT9K16AA03 202, 688, 1426
NT9K16AA35 202, 689, 1426
NT9K16AA93 202, 689, 1426
NT9K16AC03 202, 689, 1426
NT9K16AC35 202, 690, 1426
NT9K16AC93 202, 690, 1426
NT9K18AC03 202, 690, 1426
NT9K18AC35 202, 691, 1426
NT9K18AC93 202, 691, 1426
NT9N01AA 1426, 1610
NT9N01BA 1426, 1611
NT9N02 1426, 1611
NT9N03 1611
NT9N07 1611
NT9N20 1426, 1611
NT9N30AA 1611
NT9N30AB 1611
NTA149AA 1611
NTA149AQ 1611
NTA149BI 1611
NTA149BM 1611
NTA149BP 1611
NTAG26AA 25, 1426, 1611
NTAG26AB 178, 691, 1426
NTAG36AA 1426, 1611
NTAG36AB 1426, 1611
NTAG36AC 178, 343, 692, 1426
NTAG81AA 193, 692, 1426
NTAG81BA 193, 692, 1426
NTAG81CA 193, 692, 1426
NTAG81DA 193, 692, 1426
NTAG81GA 193, 1427
NTAG88AA 1427, 1611
NTAG88AB 1611
NTAG95AA 205, 1427
NTAK01AA 1427, 1611
NTAK01CA 1427, 1611
NTAK02AA 1427, 1611
NTAK02AB 1427, 1611
NTAK02BB 1427, 1611
NTAK02BC 67, 178, 693, 1427
NTAK03AA 1427, 1611
NTAK03BA 1427, 1611
NTAK03DA 67, 178, 693, 1427
NTAK0420 66, 193, 1427
NTAK04AA 1427, 1611
NTAK04AB 1611
NTAK05AA 1427, 1611
NTAK09AA 1427, 1611
NTAK09BA 1427, 1611
NTAK09DA 65, 178, 693, 1427
NTAK10DB 1427, 1611
NTAK10DC 65, 178, 1427
NTAK1104 67, 193, 693, 1427
NTAK1108 67, 193, 693, 1427
NTAK1118 329, 693, 1427
NTAK11BA 1611
NTAK11BB 1427
NTAK11BD 67, 197, 694, 1427
NTAK1204 67, 193, 694, 1427
NTAK12AA 1611
NTAK12BA 1611
NTAK12BB 1427
NTAK1305 239, 694, 1427
NTAK13AA 239, 694, 1427
NTAK14AA 1427, 1611
NTAK14BA 239, 694, 1427
NTAK15AA 1427, 1612

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTAK15AB 239, 694, 1427
NTAK16AA 1427, 1612
NTAK16AB 237, 695, 1427
NTAK17AA 1427, 1612
NTAK17AB 240, 695, 1427
NTAK17BA 1428, 1612
NTAK17BB 240, 695, 1428
NTAK18AA 1428, 1612
NTAK18BA 240, 695, 1428
NTAK19AA 1612
NTAK19BA 1612
NTAK19EC 67, 193, 1428
NTAK19FB 67, 193, 695, 1428
NTAK20AA 1428, 1612
NTAK20AB 1428, 1612
NTAK20AC 1428, 1612
NTAK20AD 178, 1428
NTAK21AA 1428, 1612
NTAK21BA 67, 197, 696, 1428
NTAK27AA 67, 197, 696, 1428
NTAK28AA 1612
NTAK28AB 66, 197, 696, 1428
NTAK30CA 1428, 1612
NTAK30DA 1612
NTAK30DB 239, 249, 696, 1428
NTAK36AA 239, 696, 1428
NTAK37AA 239, 697, 1428
NTAK38AA 1612
NTAK38AC 1612
NTAK39AA 1612
NTAK39AB 239, 249, 697, 1428
NTAK40AA 272, 697, 1428
NTAK57AA 1428, 1612
NTAK57AB 1428, 1612
NTAK57AC 1428, 1612
NTAK57AD 1428, 1612
NTAK57AE 1612
NTAK57AG 698, 1428
NTAK57BA 1428, 1612
NTAK57BB 1428, 1612
NTAK57BC 1428, 1612
NTAK57BD 1428, 1612
NTAK57BE 1612
NTAK57BG 698, 1428
NTAK57CA 1428, 1612
NTAK57CB 1428, 1612
NTAK57CC 1428, 1612
NTAK57CD 1612
NTAK57CE 1612
NTAK57CG 698, 1429
NTAK57DA 1429, 1612
NTAK57DB 1429, 1612
NTAK57DC 1429, 1613
NTAK57DD 1429, 1613
NTAK57DE 1613
NTAK57DG 698, 1429
NTAK57GE 1613
NTAK57GG 698, 1429
NTAK57HE 1613
NTAK57HG 699, 1429
NTAK57IE 1613
NTAK57IG 699, 1429
NTAK72AA 1613
NTAK72AC 1613
NTAK72AE 1613
NTAK72AG 1613
NTAK72AJ 1613
NTAK72AK 1613
NTAK72AL 1613
NTAK72AM 1613
NTAK72AN 1613
NTAK72AP 1613
NTAK72AS 1613
NTAK72BC 1613
NTAK72BG 1613
NTAK72BJ 1613
NTAK72BK 1613
NTAK72BM 1613
NTAK72BN 1613
NTAK72BP 1613
NTAK72BS 1613
NTAK72BT 233, 244, 1429
NTAK72CC 1613
NTAK72CG 1613
NTAK72CJ 1613
NTAK72CK 1613
NTAK72CM 1613
NTAK72CN 1613
NTAK72CP 1613
NTAK72CS 1614
NTAK72CT 233, 244, 1429
NTAK72DC 1614
NTAK72DD 1614
NTAK72DG 1614
NTAK72DJ 1614
NTAK72DK 1614
NTAK72DM 1614
NTAK72DN 1614
NTAK72DP 1614
NTAK72DS 1614
NTAK72DT 233, 244, 1429
NTAK72EC 1614
NTAK72EG 1614
NTAK72EJ 1614
NTAK72EK 1614
NTAK72EM 1614
NTAK72EN 1614
NTAK72EP 1614

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTAK72ES 1614
NTAK72FG 1614
NTAK72FJ 1614
NTAK72FK 1614
NTAK72FM 1614
NTAK72FN 1614
NTAK72FP 1614
NTAK72FS 1614
NTAK72GN 234, 699, 1429
NTAK72GT 234, 244, 1429
NTAK72HN 234, 699, 1429
NTAK72HS 1614
NTAK72JS 1614
NTAK72KN 234, 699, 1429
NTAK72KT 234, 244, 1429
NTAK72LN 235, 700, 1429
NTAK72LT 235, 245, 1429
NTAK72MM 1614
NTAK72NM 1614
NTAK72PN 235, 700, 1429
NTAK72QN 245, 255, 700, 1429
NTAK75AA 1614
NTAK75AB 66, 197, 700, 1429
NTAK76AA 1614
NTAK76AB 66, 197, 700, 1429
NTAK80AA 67, 197, 701, 1429
NTAK82AA 1614
NTAK82AB 1615
NTAK82AD 1615
NTAK82AE 1615
NTAK82AF 345, 1429
NTAK9204 67, 197, 701, 1429
NTAK92AA 1429, 1615
NTAK92AB 1429, 1615
NTAK92BA 67, 197, 701, 1429
NTAK93AA 1430, 1615
NTAK93AB 65, 178, 701, 1430
NTAK98AA 67, 193, 249, 702, 1430
NTBK04AA 65, 193, 702, 1430
NTBK05CA 65, 193, 1430
NTBK05DA 65, 193, 1430
NTBK22AA 65, 178, 702, 1430
NTBK45AB 1430, 1615
NTBK45AC 67, 178, 702, 1430
NTBK47AB 67, 178, 702, 1430
NTBK48AA 67, 193, 703, 1430
NTBK50AA 65, 178, 703, 1430
NTBK51AA 178, 1430
NTBK51BA 65, 67, 178, 1430
NTBK54AB 67, 193, 703, 1430
NTBK54AC 1430, 1615
NTBK55AB 67, 193, 704, 1430
NTBK55AC 1430, 1615
NTBK62AA 1615
NTBK62AB 193, 704, 1430
NTBK78AA 1615
NTBK80AA 67, 197, 704, 1430
NTBK81AA 67, 193, 704, 1430
NTBK83AA 1615
NTBK83AB 1615
NTBK83AD 1615
NTBK83AE 1615
NTBK83AG 84, 705, 1430
NTBK83BA 1615
NTBK83BB 1615
NTBK83BD 1615
NTBK83BE 1615
NTBK83BG 90, 705, 1430
NTBK83CA 1615
NTBK83CB 1615
NTBK83CD 1615
NTBK83CE 1615
NTBK83CG 91, 705, 1430
NTBK83DA 1615
NTBK83DB 1615
NTBK83DD 1615
NTBK83DE 1615
NTBK83DG 91, 705, 1430
NTBK83EA 1615
NTBK83EB 1615
NTBK83ED 1615
NTBK83EE 1615
NTBK83EG 91, 706, 1430
NTBK83FA 1615
NTBK83FB 1615
NTBK83FD 1615
NTBK83FE 1616
NTBK83FG 91, 706, 1430
NTBK83GA 1616
NTBK83GB 1616
NTBK83GD 1616
NTBK83GE 1616
NTBK83GG 91, 706, 1430
NTBK83HA 1616
NTBK83HB 1616
NTBK83HD 1616
NTBK83HE 1616
NTBK83HG 92, 706, 1430
NTBX80AA 1616
NTBX84AA 1616
NTBX84BA 1616
NTCG03AA 193, 1430
NTCG03AB 193, 1430
NTCG03AC 193, 1430
NTCG03AD 193, 1431
NTCK45AA 193, 706, 1431
NTCK46AA 193, 1431
NTCK46AB 193, 1431

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTCK46AC 193, 1431
NTCK46AD 193, 1431
NTCK78AA 193, 707, 1431
NTCK79AA 193, 707, 1431
NTCK80AA 193, 1431
NTCK80AB 193, 1431
NTCK80AC 193, 1431
NTCK80AD 193, 1431
NTCW80AA 1431, 1616
NTCW80CA 65, 178, 707, 1431
NTCW84BA 1616
NTCW84CA 1616
NTCW84EA 194, 707, 1431
NTCW84FA 1616
NTCW84GA 1616
NTCW84JA 197, 708, 1431
NTCW84KA 194, 708, 1431
NTCW84LA 194, 708, 1431
NTCW84MA 194, 708, 1431
NTDF29AB 1431, 1616
NTDJ65AA 335, 1431
NTDJ66AA 335, 1431
NTDJ67AA 335, 1431
NTDK01AA 1616
NTDK01AB 1616
NTDK01AC 1616
NTDK01BA 1616
NTDK01BB 1616
NTDK01BC 1616
NTDK16BA 67, 178, 709, 1431
NTDK18AA 70, 178, 709, 1431
NTDK19AA 70, 178, 709, 1431
NTDK20AB 1431, 1616
NTDK20AD 1431, 1616
NTDK20DA 1431, 1616
NTDK20EA 67, 178, 709, 1431
NTDK21AA 67, 178, 709, 1431
NTDK22AA 67, 179, 710, 1431
NTDK23AA 67, 179, 710, 1431
NTDK23BA 67, 179, 710, 1431
NTDK24AB 67, 179, 710, 1431
NTDK25AB 1432, 1616
NTDK25BB 67, 179, 1432
NTDK26AA 67, 179, 710, 1432
NTDK27AA 67, 194, 296, 307, 710, 1432
NTDK30AA 67, 197, 711, 1432
NTDK32AA 250, 711, 1432
NTDK3302 249, 711, 1432
NTDK3303 249, 711, 1432
NTDK3304 249, 711, 1432
NTDK35AA 250, 712, 1432
NTDK36AA 249, 712, 1432
NTDK48AA 67, 179, 712, 1432
NTDK49AA 67, 194, 712, 1432
NTDK50BA 1432, 1616
NTDK57AA 712, 1432
NTDK58AA 249, 268, 713, 1432
NTDK59AA 249, 713, 1432
NTDK63BA 1616
NTDK63BB 1616
NTDK66AA 1616
NTDK66AB 240, 250, 269, 713, 1432
NTDK68AA 67, 197, 713, 1432
NTDK72AA 66, 186, 1432
NTDK74AA 1617
NTDK74AB 239, 714, 1432
NTDK76AA 1617
NTDK76AB 1617
NTDK76AD 1617
NTDK78AA 66, 186, 714, 1432
NTDK79AA 67, 179, 714, 1432
NTDK80AA 1432, 1617
NTDK80BA 67, 179, 714, 1432
NTDK81AA 68, 179, 714, 1432
NTDK84AA 68, 179, 715, 1432
NTDK85AA 68, 179, 715, 1432
NTDK88AA 68, 194, 1432
NTDK89AA 68, 194, 1432
NTDK90AA 1617
NTDK91BA 68, 1432
NTDK92BA 68, 1432
NTDK97AB 68, 179, 715, 1432
NTDR02AA 1433, 1617
NTDR05AA 1617
NTDR05AB 1617
NTDR05AC 334, 1433
NTDR06AA 1617
NTDR06AB 1617
NTDR06AC 334, 1433
NTDR07AA 1617
NTDR07AB 1617
NTDR07AC 334, 1433
NTDR15AA 1617
NTDR15AB 1617
NTDR15AC 334, 1433
NTDR16AA 1617
NTDR16AB 334, 1433
NTDR50AA 1617
NTDR50AB 335, 1433
NTDR52AA 335, 1433
NTDR58AA 335, 1433
NTDR59AA 335, 1433
NTDR60AA 334, 1433
NTDR68AA 333, 716, 1433
NTDR69AA 333, 716, 1433
NTDR70AA 333, 716, 1433
NTDR71AA 333, 717, 1433
NTDR73AA 333, 717, 1433

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTDR74AA 333, 717, 1433
NTDR79AA 333, 717, 1433
NTDR80AA 333, 718, 1433
NTDR81AA 334, 718, 1433
NTDR82AA 334, 718, 1433
NTDR83AA 334, 718, 1433
NTDR84AA 334, 719, 1433
NTDR85AA 334, 719, 1433
NTDR87AA 333, 719, 1433
NTDR88AA 333, 719, 1433
NTDW01AA 345, 1433
NTDW80AA 58, 62, 157, 720, 1433
NTDW81AA 345, 720, 1433
NTEX35AA 1433
NTHF01AA 295, 1433
NTHF02AA 296, 720, 1433
NTHF02AB 296, 720, 1433
NTHF03AA 296, 721, 1433
NTHF03AB 296, 721, 1434
NTHF06AA 296, 721, 1434
NTHF06AB 296, 721, 1434
NTHF07AA 1617
NTHF07AC 296, 722, 1434
NTHF23AB 1617
NTHF24AB 296, 723, 1434
NTHF28AB 296, 724, 1434
NTHF29AB 296, 724, 1434
NTHF30AB 296, 724, 1434
NTHF35AA 296, 725, 1434
NTHF36AA 296, 725, 1434
NTHF62AA 1617
NTHF63AA 296, 726, 1434
NTHF69AA 296, 726, 1434
NTHU21AC 727, 1434, 1617
NTHU21DC 164, 730, 1434, 1617
NTHU22AC 164, 733, 1434
NTHU22DC 164, 735, 1434
NTHU24AC 164, 737, 1434
NTHU24DC 164, 739, 1434
NTHU28AC 164, 741, 1434
NTHU28DC 164, 744, 1434
NTHU29AC 164, 747, 1434
NTHU29DC 164, 750, 1434
NTHY01AA 161, 752, 1434
NTHY01AC 161, 752, 1434
NTHY01DC 161, 753, 1434
NTHY20AC 161, 753, 1434
NTHY20DC 161, 754, 1435
NTHY21AA 161, 755, 1435
NTHY23AA 161, 756, 1435
NTHY24AC 161, 757, 1435
NTHY24DC 161, 758, 1435
NTJG06AA 1617
NTJG06AC 179, 1435
NTJH01AA 317, 759, 1435
NTJH01BA 317, 760, 1435
NTJH01CA 317, 761, 1435
NTJH01DA 317, 762, 1435
NTJH01EA 317, 763, 1435
NTJH01FA 317, 764, 1435
NTJH02AA 318, 765, 1435
NTJH02BA 318, 766, 1435
NTJH02CA 318, 767, 1435
NTJH02DA 318, 768, 1435
NTJH02EA 318, 769, 1435
NTJH02FA 318, 770, 1435
NTJH03AA 1617
NTJH03BA 1617
NTJH03CA 1617
NTJH03DA 1617
NTJH05AA 319, 771, 1435
NTJH05BA 319, 771, 1435
NTJH09AA 1617
NTJH09AB 322, 772, 1435
NTJH09BA 1617
NTJH09BB 322, 773, 1435
NTJH09CA 1617
NTJH09CB 322, 774, 1435
NTJH09DA 1617
NTJH09DB 322, 775, 1435
NTJH10AA 317, 776, 1435
NTJH10BA 317, 777, 1435
NTJH10CA 317, 778, 1436
NTJH10DA 317, 779, 1436
NTJH10EA 317, 780, 1436
NTJH11AA 318, 781, 1436
NTJH11BA 318, 782, 1436
NTJH11CA 318, 783, 1436
NTJH11DA 318, 784, 1436
NTJH11EA 318, 785, 1436
NTJH12AA 318, 786, 1436
NTJH12BA 318, 787, 1436
NTJH12CA 318, 788, 1436
NTJH12DA 318, 789, 1436
NTJH15AA 316, 790, 1436
NTJH15BA 316, 790, 1436
NTJH15CA 316, 791, 1436
NTJH15DA 316, 791, 1436
NTJH15EA 316, 792, 1436
NTJH15FA 316, 792, 1436
NTJH17AA 316, 793, 1436
NTJH17BA 316, 794, 1436
NTJH90AA 319, 794, 1436
NTJH91AA 319, 795, 1436
NTJH92AA 323, 795, 1436
NTJH93AA 316, 796, 1436
NTJH93BA 316, 796, 1437
NTJH93EA 26, 1617

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTJH93FA 316, 797, 1437
NTJH94AA 321, 797, 1437
NTJH95AA 322, 797, 1437
NTJH97AA 319, 798, 1437
NTJH97BA 319, 798, 1437
NTJH98AA 319, 799, 1437
NTJH98BA 319, 799, 1437
NTJR27AA 227, 800, 1437
NTJR48AA 227, 1437
NTKG80CD 1617
NTKG80CE 26, 1618
NTKG80CF 345, 800, 1437
NTKS0003 1618
NTKS0035 1618
NTKS0093 1618
NTKS0103 1618
NTKS0135 1618
NTKS0193 1618
NTKS0303 1618
NTKS0335 1618
NTKS0393 1618
NTKS1001 1618
NTKS1002 58, 800, 1437
NTKS1003 1618
NTKS1005 61, 801, 1437
NTKS1010 1618
NTKS1011 58, 801, 1437
NTKS1012 61, 63, 802, 1437
NTKS1013 61, 63, 75, 802, 1437
NTKS1015 61, 802, 1437
NTKS1020 1618
NTKS1030 1618
NTKS2001 58, 803, 1437
NTKS2002 58, 803, 1437
NTKS2010 58, 803, 1437
NTKS2011 58, 804, 1437
NTKS2020 58, 804, 1437
NTKS2030 1618
NTKS2050 61, 804, 1437
NTKS2051 61, 804, 1437
NTKS2052 59, 805, 1437
NTKS2500 59, 805, 1437
NTKS2501 59, 805, 1437
NTKS3001 58, 806, 1438
NTKS9050 59, 806, 1438
NTKS9051 59, 806, 1438
NTLH01AA 1438
NTLH02AA 345, 807, 1438
NTLH03AA 345, 1438
NTLH04AA 345, 1438
NTLH05AA 345, 1438
NTLH06AA 346, 1438
NTLH08AA 63, 346, 1438
NTLH09AA 346, 1438
NTLH10AA 346, 1438
NTLH11AA 346, 1438
NTLH12AA 346, 1438
NTLH13AA 346, 1438
NTLH14AA 346, 1438
NTLH15AA 26, 1618
NTLH16AA 346, 1438
NTLT82AA 26, 1618
NTLT83AA 179, 807, 1438
NTMA01AA 1618
NTMA01BA 1618
NTMA02AA 1618
NTMA03AA 1618
NTMA05AA 1618
NTMA06AA 1618
NTMA07AA 1618
NTMA08AA 1618
NTMA08BA 1618
NTMA09AA 1438, 1618
NTMA11AA 1438, 1618
NTMA12AA 1438, 1618
NTMA12AC 1438, 1618
NTMA13AA 1438, 1618
NTMA17AA 1438, 1618
NTMA18AA 1438, 1618
NTMA18AB 1438, 1619
NTMA20AA 1438, 1619
NTMA21AA 1438, 1619
NTMA21AB 1438, 1619
NTMA22AA 1438, 1619
NTMA24AA 1438, 1619
NTMA27AA 1619
NTMA29AA 1619
NTMA31AA 1619
NTMA32AA 1619
NTMA34AA 1619
NTMA36AA 1619
NTMA36BA 1619
NTMA36CA 1619
NTMA49AA 1439, 1619
NTMA50AA 1619
NTMA62AA 1619
NTMA67AA 1619
NTMA7001 1619
NTMA75AA 1619
NTMA75AB 1439, 1619
NTMA76AA 1439, 1619
NTMA78AA 1619
NTMA78AB 1439, 1619
NTMA79AA 1439, 1619
NTMA9011 1619
NTMA9013 1619
NTMA9111 1619
NTMA9113 1619

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTMA9901 1619
NTMA9902 1619
NTMA9903 1619
NTMA9911 1619
NTMA9912 1619
NTMA9913 1620
NTMA9921 1620
NTMA9922 1620
NTMA9923 1620
NTMA9931 1620
NTMA9932 1620
NTMA9933 1620
NTMA9941 1620
NTMA9942 1620
NTMA9943 1620
NTMA9952 1620
NTMA9953 1620
NTMA9991 1620
NTMA9992 1620
NTMA99AA 1620
NTMA99BA 1620
NTMA99CA 1620
NTMF94AA 1620
NTMF94BA 1620
NTMF94DA 194, 1439
NTMF94EA 194, 807, 1439
NTMN0006 208, 808, 1439
NTMN13AA66 200, 808, 1439
NTMN13AA70 200, 808, 1439
NTMN14AA66 200, 808, 1439
NTMN14AA70 200, 808, 1439
NTMN15AA66 200, 808, 1439
NTMN15AA70 200, 809, 1439
NTMN16AA66 208, 809, 1439
NTMN16AA70 208, 809, 1439
NTMN17AA66 206, 809, 1439
NTMN17AA70 206, 809, 1439
NTMN18AA66 206, 810, 1439
NTMN18AA70 206, 810, 1439
NTMN19AA 209, 810, 1439
NTMN31BA66 200, 810, 1439
NTMN31BA70 200, 810, 1439
NTMN32BA66 200, 811, 1439
NTMN32BA70 200, 811, 1439
NTMN33BA66 200, 811, 1439
NTMN33BA70 200, 812, 1439
NTMN33FA66 200, 812, 1439
NTMN33FA70 200, 812, 1439
NTMN34BA66 200, 812, 1439
NTMN34BA70 200, 813, 1439
NTMN34FA66 200, 813, 1439
NTMN34FA70 200, 813, 1439
NTMN35BA66 200, 814, 1439
NTMN35BA70 200, 814, 1439
NTMN35FA-66 200, 814, 1440
NTMN35FA-70 200, 815, 1440
NTMN37AA66 200, 1440
NTMN37AA70 200, 815, 1440
NTMN38AA66 200, 815, 1440
NTMN38AA70 200, 815, 1440
NTMN38BA66 200, 816, 1440
NTMN38BA70 201, 816, 1440
NTMN59AA66 201, 816, 1440
NTMN59AA70 201, 816, 1440
NTMN66AA66 26, 1440, 1620
NTMN66AA70 26, 1440, 1620
NTMN67AA66 201, 817, 1440
NTMN67AA70 201, 817, 1440
NTMN68AA66 201, 817, 1440
NTMN68AA70 201, 818, 1440
NTMN69AA66 26, 1440, 1620
NTMN69AA70 26, 1440, 1620
NTMN71AA66 201, 818, 1440
NTMN71AA70 201, 818, 1440
NTMN80AA 209, 818, 1440
NTMN82AA66 201, 819, 1440
NTMN82AA70 201, 819, 1440
NTMS01AA 1620
NTMS01CA 1620
NTMS1001 1620
NTMS1101 1620
NTMS21AA 1620
NTMS22AA 1620
NTMS2425 1620
NTMS31AA 1620
NTMS4001 1620
NTMS4825 1620
NTMS5001 1620
NTMS54AA 1621
NTMS61AA 1621
NTMS62AA 1621
NTMS71AA 1621
NTMS91AA 1621
NTMS91BA 1621
NTMS91DA 1621
NTMS91EA 1621
NTMS92AA 1621
NTMS93AA 1621
NTMS93BA 1621
NTMS93CA 1621
NTMS94AA 1621
NTMS94BA 1621
NTMS95AA 1621
NTMS96AA 1621
NTMS97AA 1621
NTMS9801 1621
NTMS98AA 1621
NTMS9901 1621

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTMW01AA 59, 819, 1440
NTMW02AA 1440, 1621
NTMW02AB 59, 819, 1441
NTMW03AA 59, 239, 820, 1441
NTMW04AA 59, 820, 1441
NTMW05AA 59, 820, 1441
NTMW06AA 59, 820, 1441
NTMW07AA 59, 820, 1441
NTMW0802 61, 820, 1441
NTMW08AA 1441
NTMW10AA 1441
NTMW11AA 1441, 1621
NTMW11AB 59, 821, 1441
NTMW14AA 58, 821, 1441
NTMW14BA 58, 821, 1441
NTMW15AA 1621
NTMW16AA 59, 822, 1441
NTMW16AB 59, 822, 1441
NTMW16BA 59, 822, 1441
NTMW17AA 59, 822, 1441
NTMW17AB 59, 823, 1441
NTMW17BA 59, 823, 1441
NTMW18AB 1621
NTMW18AC 1621
NTMW30AC 1441, 1621
NTMW30AD 59, 823, 1441
NTMW30BA 59, 823, 1441
NTMW30BB 59, 1441
NTMW30BC 60, 1441
NTMW30BD 60, 1441
NTMW30CC 1621
NTMW30DC 1621
NTMW30EC 1621
NTMW30FC 1621
NTMW35AA 61, 1441
NTMW37AA 61, 824, 1441
NTMW38AA 58, 824, 1441
NTMW42AA 1621
NTMW42BA 1621
NTMW42CA 60, 1442
NTMW43AA 1621
NTMW43AB 1621
NTMW43BA 60, 824, 1442
NTMW44AA 61, 824, 1442
NTMW45AA 1622
NTMW50AA 1442
NTMW55AA 61, 1442
NTND01BA 1442, 1622
NTND01CA 1442, 1622
NTND02BA 1442, 1622
NTND05AA 1442, 1622
NTND08AA 1442, 1622
NTND08AB 1442, 1622
NTND08AC 1442, 1622
NTND08AE 1442, 1622
NTND09BA 1442, 1622
NTND09CA 1442, 1622
NTND10AA 1442, 1622
NTND11AA 1622
NTND11BA 194, 824, 1442
NTND13AC 1622
NTND13BC 194, 825, 1442
NTND14AB 1622
NTND14AC 1622
NTND14AD 1622
NTND14AE 1622
NTND14BA 194, 1442
NTND14BB 194, 825, 1442
NTND14BC 194, 825, 1442
NTND14BD 194, 825, 1442
NTND14BE 194, 825, 1442
NTND14BG 194, 825, 1442
NTND14BX 194, 826, 1442
NTND15AA 1442, 1622
NTND16AA 1442, 1622
NTND20AA 198, 826, 1442
NTND21AA 1622
NTND22AB 1622
NTND26AA 194, 826, 1442
NTND26AB 194, 826, 1442
NTND26AC 194, 826, 1442
NTND26AD 194, 827, 1442
NTND27AB 194, 827, 1442
NTND28AA 1622
NTND28BA 1622
NTND28BB 194, 827, 1443
NTND28BC 194, 827, 1443
NTND29AA 195, 827, 1443
NTND30AA 195, 828, 1443
NTND31AA 1443, 1622
NTND31AB 1443, 1622
NTND33AA 1622
NTND33BB 1622
NTND33BC 1622
NTND33BD 1622
NTND33CB 1622
NTND33CC 195, 828, 1443
NTND33CD 1622
NTND33DA 195, 828, 1443
NTND36AA 185, 828, 1443
NTND37AA 1622
NTND46AE 1622
NTND63AA 1623
NTND64AA 1623
NTND80AA 1623
NTND82AA 268, 829, 1443
NTND82AB 268, 272, 1443
NTND91AA 249, 268, 829, 1443

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTND91AB 249, 268, 829, 1443
NTND93AA 250, 269, 829, 1443
NTND94BA 1623
NTND94CA 1623
NTND94DA 195, 268, 830, 1443
NTND95AA 195, 830, 1443
NTNH13AA 179, 830, 1443
NTP 553-2001-320 Software conversion 1657, 1659, 1660, 1661, 1662
NTP 553-2201-156 XN/XT Network Module Expansion 1654, 1657, 1659, 1662
NTP 553-2901-110 ISDN/AP 1657
NTP 553-2901-110 Meridian Link ISDN/AP 1659
NTP 553-3001-110 NT6D82 Power System 1657, 1659
NTP 553-3001-570 Power Monitor/CE Auxiliary Shelves 1656, 1659
NTP Assembly 344, 1389
NTP Binder (Compact) 1654
NTP PTE LANSTAR Reference Manual 1648
NTP Rack 1640
NTP Rack (Double Bay) (White) 1644
NTP Rack (Single Bay) (White) 1644
NTPD00AA 1623
NTPD01AA 1623
NTQR01AA 334, 830, 1443
NTQR01BA 334, 831, 1443
NTQR02AA 334, 831, 1443
NTQR03AA 334, 1443
NTQR05AA 333, 831, 1443
NTQR06AA 333, 832, 1443
NTQR07AA 333, 832, 1443
NTQR08AA 333, 832, 1443
NTQR09AA 333, 833, 1443
NTQR10AA 333, 833, 1443
NTQR11AA 333, 834, 1443
NTQR12AA 333, 834, 1443
NTQR14AA 333, 835, 1443
NTQR15AA 333, 835, 1443
NTQR16AA 333, 835, 1443
NTQR17AA 333, 836, 1443
NTRB18AA 247, 249, 836, 1443
NTRB18BA 1444
NTRB18CA 220, 836, 1444
NTRB21AA 65, 179, 836, 1444
NTRB33AA 179, 837, 1444
NTRB34AA 179, 837, 1444
NTRC17AA 195, 837, 1444
NTRC46AA 195, 837, 1444
NTRC46BA 195, 838, 1444
NTRC46CA 195, 838, 1444
NTRC47AA 195, 838, 1444
NTRC48AA 195, 838, 1444
NTRC48BA 195, 839, 1444
NTRC48CA 195, 839, 1444
NTRC48DA 195, 839, 1444
NTRC48EA 195, 839, 1444
NTRC48FA 195, 840, 1444
NTRC48GA 195, 840, 1444
NTRC48HA 195, 840, 1444
NTRC49AA 195, 840, 1444
NTRC49BA 195, 841, 1444
NTRD25AA 184, 841, 1444
NTRD25BA 184, 841, 1444
NTRE18AA 198, 1444
NTRE39AA 179, 841, 1444
NTRE40AA 195, 842, 1444
NTRG08AD 227, 842, 1444
NTRG09AD 227, 842, 1444
NTRG10AD 227, 843, 1444
NTRG11AA 1623
NTRG11AB 218, 844, 1444
NTRG11AC 219, 844, 1444
NTRG12AA 227, 845, 1444
NTRG13AA 227, 1444
NTRG13AB 227, 845, 1444
NTRG13BB 227, 846, 1445
NTRG14AA 227, 846, 1445
NTRG14AC 227, 846, 1445
NTRG15AA 227, 846, 1445
NTRG15AC 227, 847, 1445
NTRG16AA 227, 847, 1445
NTRG16AC 227, 847, 1445
NTRG17AA 227, 848, 1445
NTRG17AC 227, 848, 1445
NTRG18AA 227, 848, 1445
NTRG19AA 1623
NTRG19AB 227, 848, 1445
NTRG19AC 227, 849, 1445
NTRG19AD 227, 849, 1445
NTRG20AA 227, 849, 1445
NTRG22AA 227, 850, 1445
NTRG22AC 227, 850, 1445
NTRG22BA 227, 850, 1445
NTRG22CB 227, 850, 1445
NTRG22DB 227, 851, 1445
NTRG22EC 227, 851, 1445
NTRH01AA 220, 851, 1445
NTRH08AA 1623
NTRH0910 223, 1445
NTRH0911 221, 1445
NTRH0914 223, 1445
NTRH0915 223, 1445
NTRH09AA 221, 851, 1445
NTRH1405 221, 852, 1445
NTRH1406 221, 852, 1445
NTRH1407 223, 852, 1445
NTRH1408 223, 852, 1445

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTRH1409 223, 852, 1445
NTRH14AA 221, 1445
NTRH16BA 221, 853, 1445
NTRH2010 221, 853, 1446
NTRH2011 221, 853, 1446
NTRH2012 223, 1446
NTRH2013 224, 1446
NTRH20AA 1446, 1623
NTRH20BA 220, 1446
NTRH21CA 221, 1446
NTRH8003 221, 1446
NTRH8025 226, 1446
NTRH8026 226, 1446
NTRH8027 226, 853, 1446
NTRH8032 221, 1446
NTRH8033 226, 1446
NTRH8042 221, 1446
NTRH8101 224, 854, 1446
NTRH9001 1623
NTRH9002 304, 305, 854, 1446
NTRH9003 221, 304, 305, 854, 1446
NTRH9004 307, 854, 1446
NTRH9005 305, 854, 1446
NTRH9006 304, 305, 855, 1446
NTRH9007 224, 307, 855, 1446
NTRH9009 303, 307, 855, 1446
NTRH9010 220, 303, 307, 855, 1446
NTRH9011 222, 307, 856, 1446
NTRH9012 307, 856, 1446
NTRH9013 222, 285, 307, 856, 1446
NTRH9014 222, 307, 856, 1446
NTRH9016 222, 307, 327, 856, 1446
NTRH9017 307, 857, 1446
NTRH9026 1623
NTRH9027 307, 857, 1446
NTRH9029 304, 857, 1446
NTRH9030 304, 857, 1446
NTRH9031 304, 858, 1446
NTRH9032 222, 307, 858, 1447
NTRH9033 1447, 1623
NTRH9034 305, 858, 1447
NTRH9035 222, 304, 858, 1447
NTRH9036 220, 858, 1447
NTRH9037 222, 859, 1447
NTRH9038 222, 1447
NTRH9039 222, 859, 1447
NTRH9040 222, 859, 1447
NTRH9048 222, 859, 1447
NTRH9049 222, 860, 1447
NTRH9053 222, 1447
NTRH9054 222, 1447
NTRH9055 222, 860, 1447
NTRH9056 26, 1623
NTRH9057 222, 1447
NTRH9059 222, 1447
NTRH9060 222, 1447
NTRH9065 222, 1447
NTRH9068 222, 860, 1447
NTRH9069 220, 222, 860, 1447
NTRH9100 306, 1447
NTRK26AA 860, 1447
NTRK26BA 861, 1447
NTRK26CA 861, 1447
NTRK26DA 861, 1447
NTRK26EA 861, 1447
NTRK26GA 861, 1447
NTRK26HA 862, 1447
NTRK26JA 862, 1447
NTRK27AA 862, 1447
NTRK27BA 862, 1447
NTRK27CA 862, 1448
NTRK27DA 863, 1448
NTRK27EA 863, 1448
NTRK27GA 863, 1448
NTRK27HA 863, 1448
NTRK27JA 863, 1448
NTS 1st Year Software Support 1694
NTS Additional One Year for Telephone Software Support 1694
NTS101AA 93, 864, 1448
NTS102AA 93, 864, 1448
NTS103AA 93, 864, 1448
NTS130AA 235, 245, 864, 1448
NTS132AA 235, 245, 865, 1448
NTS133AA 236, 246, 865, 1448
NTS134AA 256, 865, 1448
NTS136AA 256, 866, 1448
NTS137AA 257, 866, 1448
NTSF1001 1623
NTSF1002 1623
NTSF1030 62, 866, 1448
NTSF1031 62, 867, 1448
NTSF1032 64, 158, 867, 1448
NTSF1033 64, 158, 868, 1448
NTSF1101 62, 868, 1448
NTSF1102 62, 869, 1448
NTSF2001 1623
NTSF2002 1623
NTSF2003 1623
NTSF2004 1623
NTSF2005 1623
NTSF2006 1623
NTSF2101 64, 161, 869, 1448
NTSF2102 64, 161, 870, 1448
NTSF2103 64, 161, 871, 1448
NTSF2104 64, 161, 871, 1448
NTSF2105 64, 161, 872, 1448
NTSF2106 64, 161, 873, 1448

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTSF2200 64, 161, 874, 1449
NTSF2201 64, 161, 874, 1449
NTSF2202 64, 161, 875, 1449
NTSF3001 346, 876, 1449
NTSF3100 65, 161, 876, 1449
NTSF3101 65, 161, 876, 1449
NTSF6001 70, 164, 876, 1449
NTSF6002 70, 164, 877, 1449
NTSF6003 70, 164, 877, 1449
NTSF6004 70, 164, 878, 1449
NTSF6005 70, 164, 879, 1449
NTSF6006 71, 164, 880, 1449
NTSF6007 71, 164, 880, 1449
NTSF6008 71, 164, 881, 1449
NTSF6101 1623
NTSF6102 1623
NTSF6103 1623
NTSF6104 1623
NTSF6105 1623
NTSF6106 1623
NTSF6107 1623
NTSF6108 1623
NTSF6501 59, 882, 1449
NTSF6800 65, 161, 883, 1449
NTSF6851 198, 883, 1449
NTSF8011 62, 883, 1449
NTSF8012 62, 884, 1449
NTSF8013 62, 884, 1449
NTSF8014 62, 884, 1449
NTSF8020 62, 74, 885, 1449
NTSF8021 62, 74, 885, 1449
NTSF8022 62, 71, 74, 885, 1449
NTSF8023 62, 71, 74, 886, 1449
NTSF8028 71, 74, 886, 1449
NTSF8029 71, 74, 886, 1449
NTSF8030 74, 887, 1449
NTSF8031 74, 887, 1449
NTSF8048 69, 74, 888, 1449
NTSF8049 69, 74, 888, 1449
NTSF8050 69, 74, 888, 1449
NTSF8051 69, 74, 889, 1449
NTSF8101 63, 74, 889, 1449
NTSF8102 63, 74, 889, 1450
NTSF8103 63, 74, 889, 1450
NTSF8104 63, 74, 890, 1450
NTSF8501 63, 74, 890, 1450
NTSF8508 63, 74, 890, 1450
NTSF8509 63, 890, 1450
NTSF8512 63, 75, 891, 1450
NTSF8513 63, 75, 891, 1450
NTSF8514 63, 74, 891, 1450
NTSF8516 63, 891, 1450
NTSF8519 201, 892, 1450
NTSF8702 69, 92, 892, 1450
NTSF8712 69, 74, 892, 1450
NTSF8722 69, 92, 893, 1450
NTSF8730 63, 74, 893, 1450
NTSK11AA 68, 75, 893, 1450
NTSK11AB 68, 75, 894, 1450
NTSK11AC 68, 75, 894, 1450
NTSK11AF 68, 75, 894, 1450
NTSK11AG 68, 75, 894, 1450
NTSK11AH 68, 75, 895, 1450
NTSK11AK 68, 75, 179, 895, 1450
NTSK11AL 179, 895, 1450
NTSK11AN 68, 75, 179, 895, 1450
NTSK11AP 68, 75, 179, 896, 1450
NTSK11BA 68, 179, 1450
NTSK11BB 68, 179, 1450
NTSK11BC 68, 179, 1450
NTSK11BF 68, 179, 1450
NTSK11BG 68, 179, 1450
NTSK11BH 68, 179, 896, 1450
NTSK11BK 68, 75, 179, 896, 1450
NTSK11BL 179, 896, 1450
NTSK11BN 68, 75, 179, 896, 1451
NTSK11CA 1623
NTSK11CF 1624
NTSK11CG 1624
NTSK11CH 1624
NTSK11CK 1624
NTSK11CL 1451
NTSK11CN 1451
NTSK11DA 1624
NTSK11DF 1624
NTSK11DG 1624
NTSK11DH 1624
NTSK11DK 1624
NTSK11DL 1451
NTSK11DN 1451
NTSK11EA 1624
NTSK11EF 1624
NTSK11EG 1624
NTSK11EH 1624
NTSK11EK 1624
NTSK11EL 1451
NTSK11EN 1451
NTSK11FA 1624
NTSK11FF 1624
NTSK11FG 1624
NTSK11FH 1624
NTSK11FK 1624
NTSK11FL 1451
NTSK11FN 1451
NTSK11ZK 1451, 1624
NTSK11ZN 68, 1451
NTSW31AA 156, 897, 1451
NTSZ00AC 158, 897, 1451

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTSZ00DC 158, 899, 1451
NTSZ25AC 158, 901, 1451
NTSZ25DC 158, 904, 1451
NTSZ26AC 158, 906, 1451
NTSZ26DC 158, 909, 1451
NTTK08AA 68, 198, 1451
NTTK09AA 68, 198, 1451
NTTK10AA 68, 198, 1451
NTTK11AA 68, 198, 1451
NTTK13AA 68, 179, 1451
NTTK14AA 66, 195, 1451
NTTK24AA 68, 198, 1451
NTTK30AA 26, 1624
NTTK30AB 64, 346, 911, 1451
NTTK31AA 26, 1624
NTTK31AB 63, 346, 911, 1451
NTTK32AB 1624
NTTK32CB 64, 346, 911, 1451
NTTK33AB 63, 70, 346, 912, 1451
NTTK38AB 63, 198, 1451
NTTK44AA 239, 1451
NTTK45AA 68, 912, 1451
NTTL01AA 336, 1452
NTTL01BA 336, 1452
NTTL01CA 336, 1452
NTTL02AA 336, 1452
NTTL02BA 336, 1452
NTTL02CA 336, 1452
NTTL02DA 336, 1452
NTTL03AA 336, 1452
NTTL03BA 336, 1452
NTTL03CA 336, 1452
NTTL03DA 336, 1452
NTTL04AA 336, 1452
NTTL04BA 336, 1452
NTTL04CA 336, 1452
NTTL04DA 336, 1452
NTTL05AA 337, 1452
NTTL06AA 337, 1452
NTTL06BA 337, 1452
NTTL06CA 337, 1452
NTTL06DA 337, 1452
NTTL06EA 337, 1452
NTTL08AA 336, 1452
NTTL08BA 336, 1452
NTTL08CA 336, 1452
NTTL09AA 336, 1452
NTTL09BA 336, 1452
NTTL09CA 336, 1452
NTTL10AA 338, 1452
NTTL11AA 337, 1452
NTTL11BA 337, 1452
NTTL11CA 337, 1452
NTTL12AA 337, 1452
NTTL12BA 337, 1452
NTTL12CA 337, 1453
NTTL12DA 337, 1453
NTTL13AA 337, 1453
NTTL13BA 337, 1453
NTTL13CA 337, 1453
NTTL13DA 337, 1453
NTTL14AA 337, 1453
NTTL14BA 337, 1453
NTTL14CA 337, 1453
NTTL14DA 337, 1453
NTTL17AA 337, 1453
NTTL18AA 338, 1453
NTTL19AA 338, 1453
NTTL19BA 338, 1453
NTTL19CA 338, 1453
NT-Tone Amplified Receiver Module - Black 1606
NTTS36AA 230, 912, 1453
NTTS50AA 230, 912, 1453
NTUB06AA 1624
NTUB14AB 219, 913, 1453
NTUB16AA 222, 913, 1453
NTUB20AD 224, 1453
NTUB22AD 224, 1453
NTUB24AA 250, 269, 913, 1453
NTUB24AB 226, 1453
NTUB40AC 226, 914, 1453
NTUB41AC 226, 914, 1453
NTUB42AB 227, 1453
NTUB42AC 226, 914, 1453
NTUB43AA 226, 914, 1453
NTUB43AC 226, 914, 1453
NTUB44AC 226, 1453
NTUB44BC 224, 915, 1453
NTUB45AC 226, 915, 1453
NTUB46AB 227, 915, 1453
NTUB51AA 220, 915, 1453
NTUB52AA 220, 916, 1453
NTUB53AA 222, 916, 1453
NTUB54AA 222, 916, 1454
NTUB55AA 222, 917, 1454
NTUB56AA 222, 917, 1454
NTUB57AA 1624
NTUB57AB 220, 918, 1454
NTUB58AA 224, 918, 1454
NTUB59AA 222, 918, 1454
NTUB60AA 1624
NTUB60AB 219, 919, 1454
NTUB71AA 220, 919, 1454
NTUB72AA 220, 919, 1454
NTUB73AA 220, 920, 1454
NTUB74AA 220, 920, 1454
NTUB80AA 224, 920, 1454
NTUB81AA 222, 920, 1454

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTUB83AA 222, 921, 1454
NTUF24AA 921, 1454
NTV200AA 921, 1454
NTV200BA 922, 1454
NTV200CA 923, 1454
NTV201AA 291, 923, 1454
NTV201AB 291, 924, 1454
NTV201AC 291, 924, 1454
NTV201AD 291, 924, 1454
NTV201AE 925, 1454
NTV201AQ 293, 925, 1454
NTV201AR 293, 925, 1454
NTV201AS 293, 926, 1454
NTV201AT 926, 1454
NTV201AU 293, 926, 1454
NTV201AV 294, 926, 1454
NTV201AX 1624
NTV201BA 294, 927, 1454
NTV202AA 295, 927, 1454
NTV202AB 294, 927, 1455
NTV202AC 294, 928, 1455
NTV202AD 294, 928, 1455
NTV202AE 294, 928, 1455
NTV202AF 294, 928, 1455
NTV202AH 295, 929, 1455
NTV202AJ 295, 929, 1455
NTV202AK 295, 929, 1455
NTV202AL 295, 929, 1455
NTV202AM 295, 930, 1455
NTV202AP 295, 930, 1455
NTV202AR 1624
NTV202AW 295, 930, 1455
NTV202AY 295, 930, 1455
NTV400KA 276, 931, 1455
NTV400LA 276, 931, 1455
NTV401PA 276, 931, 1455
NTV401SA 276, 932, 1455
NTV402AA 276, 932, 1455
NTV402CA 276, 932, 1455
NTV403EA 276, 294, 932, 1455
NTV403EB 1624
NTV403TA 275, 276, 294, 1455
NTV404LA 276, 281, 933, 1455
NTV404MA 276, 281, 933, 1455
NTV404SA 276, 281, 933, 1455
NTV405UA 276, 933, 1455
NTV405VA 1455, 1624
NTV406CA 276, 281, 934, 1455
NTV406DA 276, 281, 934, 1455
NTV406PP 1624
NTV406RA 276, 281, 934, 1455
NTV406RH 1624
NTV406TA 276, 281, 934, 1455
NTV406TH 1624
NTV407AA 1624
NTV407LA 1625
NTV407LL 1625
NTV407MA 276, 935, 1455
NTV410AA 1625
NTV410BA 276, 935, 1455
NTV410HP 1625
NTV411NA 276, 935, 1455
NTV412RA 276, 936, 1456
NTV413AA 276, 936, 1456
NTV413DA 276, 936, 1456
NTV413PA 1625
NTV413PD 1625
NTV420AA 277, 936, 1456
NTV420HP 1625
NTV420KA 277, 937, 1456
NTV421NA 277, 937, 1456
NTV430AA 277, 937, 1456
NTV430DA 277, 938, 1456
NTV430PA 1625
NTV430PD 1625
NTV430RA 277, 938, 1456
NTV430RR 1625
NTV430SA 277, 938, 1456
NTV431NA 277, 939, 1456
NTV440AA 1625
NTV440BA 277, 939, 1456
NTV440HP 1625
NTV441NA 277, 939, 1456
NTV450CA 277, 940, 1456
NTV450LA 277, 940, 1456
NTV450MA 277, 940, 1456
NTV450PA 277, 940, 1456
NTV450SA 277, 941, 1456
NTV452EA 277, 941, 1456
NTV452SA 277, 292, 295, 941, 1456
NTV452TA 277, 292, 941, 1456
NTV452VA 277, 292, 942, 1456
NTV452WA 277, 292, 942, 1456
NTV453AA 277, 292, 942, 1456
NTV453BA 277, 942, 1456
NTV453SA 277, 292, 943, 1456
NTV453TA 278, 943, 1456
NTV454VA 278, 292, 943, 1457
NTV454WA 278, 943, 1457
NTV454YA 1625
NTV454ZA 1625
NTV455AA 278, 292, 944, 1457
NTV455BA 278, 944, 1457
NTV455SA 278, 292, 944, 1457
NTV455TA 278, 944, 1457
NTV456AA 278, 293, 945, 1457
NTV456BA 278, 293, 945, 1457
NTV456CA 278, 293, 945, 1457

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTV456DA 278, 293, 945, 1457
NTV456EA 1625
NTV456MA 278, 946, 1457
NTV457PA 278, 946, 1457
NTV457WA 278, 946, 1457
NTV460AA 278, 946, 1457
NTV460SA 276, 947, 1457
NTV461NA 278, 947, 1457
NTV461PA 278, 947, 1457
NTV462NA 278, 280, 948, 1457
NTV462PA 278, 948, 1457
NTV462TA 278, 948, 1457
NTV464NA 279, 280, 948, 1457
NTV464ZA 279, 949, 1457
NTV467LA 279, 949, 1457
NTV467MA 279, 949, 1457
NTV467SA 279, 950, 1457
NTV468CA 279, 950, 1457
NTV468LA 279, 950, 1457
NTV468PA 279, 951, 1457
NTV468QA 279, 951, 1457
NTV468RA 279, 951, 1458
NTV468SA 279, 952, 1458
NTV468TA 279, 952, 1458
NTV468UA 279, 952, 1458
NTV468VA 279, 953, 1458
NTV468WA 279, 953, 1458
NTV468YA 279, 953, 1458
NTV468ZA 279, 954, 1458
NTV469CA 279, 954, 1458
NTV469LA 279, 954, 1458
NTV469PA 279, 954, 1458
NTV469QA 279, 955, 1458
NTV469RA 279, 955, 1458
NTV469SA 279, 955, 1458
NTV469TA 279, 955, 1458
NTV469UA 279, 956, 1458
NTV469VA 280, 956, 1458
NTV469WA 280, 956, 1458
NTV469YA 280, 956, 1458
NTV469ZA 280, 957, 1458
NTV472AA 280, 957, 1458
NTV472BA 280, 957, 1459
NTV472DA 280, 958, 1459
NTV472EA 1625
NTV472FA 1625
NTV472NA 1625
NTV472XA 1625
NTV472YA 280, 958, 1459
NTV472ZA 1625
NTV474NA 280, 958, 1459
NTV481CA 281, 959, 1459
NTV481DA 281, 959, 1459
NTV481HA 281, 960, 1459
NTV481LA 281, 960, 1459
NTV481PA 280, 960, 1459
NTV481SA 281, 961, 1459
NTV481UA 281, 961, 1459
NTV482MA 281, 961, 1459
NTV482NA 281, 961, 1459
NTV482SA 278, 962, 1459
NTV482TA 278, 962, 1459
NTV483TA 1625
NTV483UA 1625
NTV491NA 281, 962, 1459
NTV491PA 281, 962, 1459
NTV492NA 281, 963, 1459
NTV494NA 281, 963, 1459
NTV497LA 281, 963, 1459
NTV497MA 281, 963, 1459
NTV497SA 281, 964, 1459
NTV498PA 281, 964, 1459
NTVA0001 1625
NTVA0002 270, 964, 1459
NTVA0004 1625
NTVA0006 1625
NTVA0008 1625
NTVA0009 1625
NTVA01AA 1625
NTVA11AA 1625
NTVB00AA 1625
NTVB01AA 227, 1459
NTVB02AA 228, 1459
NTVB03AA 228, 1459
NTVE8202 285, 1459
NTVE8203 285, 1459
NTVE8204 285, 1459
NTVE8205 285, 1460
NTVE8206 285, 1460
NTVE8207 285, 1460
NTVE8208 285, 1460
NTVE8209 285, 1460
NTVE8210 285, 1460
NTVE8211 285, 1460
NTVE8212 285, 1460
NTVE8213 285, 1460
NTVE8214 286, 1460
NTVE8215 286, 1460
NTVE8217 1625
NTVE8218 286, 1460
NTVE8219 1625
NTVE8220 1625
NTVE8221 286, 1460
NTVE8224 286, 1460
NTVE8225 1626
NTVE8227 286, 1460
NTVE9002 1626
NTVE9003 1626

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTVE9005 1460, 1626
NTVE9006 1460, 1626
NTVE9009 281, 295, 964, 1460
NTVE9011 1460, 1626
NTVE9012 1460, 1626
NTVE9013 281, 295, 965, 1460
NTVE9014 281, 295, 965, 1460
NTVE9016 281, 295, 965, 1460
NTVE9026 1626
NTVE9029 1460, 1626
NTVE9030 1626
NTVE9032 1460, 1626
NTVE9041 282, 965, 1460
NTVE9042 1626
NTVE9044 282, 966, 1460
NTVE9045 282, 966, 1460
NTVE9901 282, 966, 1460
NTVE9902 1626
NTVE9903 282, 966, 1460
NTVE9904 1460, 1626
NTVE9905 1461, 1626
NTVE9906 282, 967, 1461
NTVE9907 282, 967, 1461
NTVE9908 282, 1461
NTVE9909 282, 967, 1461
NTVE9910 282, 967, 1461
NTVE9911 282, 968, 1461
NTVE9912 282, 968, 1461
NTVE9913 282, 968, 1461
NTVE9915 282, 968, 1461
NTVE9917 282, 969, 1461
NTVE9918 1626
NTVE9919 282, 969, 1461
NTVE9920 1626
NTVE9921 282, 969, 1461
NTVE9922 1626
NTVE9923 282, 969, 1461
NTVE9924 282, 970, 1461
NTVE9925 282, 970, 1461
NTVE9926 282, 970, 1461
NTVE9927 282, 970, 1461
NTVE9928 282, 971, 1461
NTVE9930 1626
NTVE9931 1626
NTVE9932 275, 971, 1461
NTVE9933 282, 1461
NTVE9934 282, 1461
NTVE9935 282, 1461
NTVE9936 282, 1461
NTVE9937 282, 1461
NTVE9938 282, 1461
NTVE9939 282, 1461
NTVE9940 282, 1461
NTVE9941 282, 1461
NTVE9942 282, 1461
NTVE9943 283, 1461
NTVE9944 283, 1461
NTVE9945 283, 1461
NTVE9946 283, 1461
NTVE9947 283, 1461
NTVE9951 283, 1462
NTVE9952 283, 1462
NTVE9953 283, 1462
NTVE9954 283, 1462
NTVE9955 283, 1462
NTVE9956 1626
NTVE9957 283, 1462
NTVE9958 283, 1462
NTVF44AA 307, 971, 1462
NTVM0001 1626
NTVM0002 26, 1626
NTVM0003 1626
NTVM0004 1626
NTVM0005 1626
NTVM0006 1626
NTVM0007 1626
NTVM0008 1626
NTVM0009 1626
NTVM0010 1626
NTVM0012 1626
NTVM0013 1626
NTVM0014 1626
NTVM0016 1627
NTVM0027 1627
NTVM0028 1627
NTVM0029 1627
NTVM0030 1627
NTVM0034 1627
NTVM0035 1627
NTVM0036 270, 971, 1462
NTVM0037 1627
NTVM0038 1627
NTVM0039 1627
NTVM0040 1627
NTVM0051 1627
NTVM0052 1627
NTVM0053 1627
NTVM0054 26, 1627
NTVM0055 1627
NTVM0056 1627
NTVM0057 1627
NTVM0061 270, 972, 1462
NTVM0062 26, 1627
NTVM0063 26, 1627
NTVM0064 26, 1627
NTVM0065 26, 1627
NTVM0066 26, 1627
NTVM0067 26, 1627

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTVM00AA 1627
NTVM00BA 1627
NTVM00CA 1627
NTVM00DA 1627
NTVM00EA 1627
NTVM00FA 1627
NTVM00GA 1627
NTVM00HA 1627
NTVM00JA 26, 1627
NTVM00JB 270, 972, 1462
NTVM00JC 1627
NTVM00KA 270, 972, 1462
NTVM00LA 1628
NTVM00MA 1628
NTVM00NA 1628
NTVM00PA 1628
NTVM00RA 1628
NTVM00SA 1628
NTVM00SB 1628
NTVM00SC 1628
NTVM00SD 270, 973, 1462
NTVM00SE 270, 973, 1462
NTVM00SF 26, 1628
NTVM00SG 270, 974, 1462
NTVM00SH 270, 974, 1462
NTVM00SJ 270, 975, 1462
NTVM00SK 270, 975, 1462
NTVM00WA 1628
NTVM00XA 1628
NTVM00YA 270, 975, 1462
NTVM00YB 270, 976, 1462
NTVM00ZA 1628
NTVM00ZB 1628
NTVM00ZC 1628
NTVM00ZD 1628
NTVM00ZE 1628
NTVM00ZF 270, 976, 1462
NTVM00ZG 270, 976, 1462
NTVM0100 1628
NTVM0101 271, 976, 1462
NTVM0103 271, 977, 1462
NTVM0200 26, 1628
NTVM0300 1628
NTVM0301 1628
NTVM12AA 1628
NTVM12BA 1628
NTVM12BB 1628
NTVM12CA 1628
NTVM12DA 26, 1628
NTVM13AA 1628
NTVM15AA 1628
NTVM15BA 270, 977, 1462
NTVM15CA 270, 978, 1462
NTVM16AA 26, 1628
NTVM17AA 271, 978, 1462
NTVM18AA 271, 343, 978, 1462
NTVM19AA 271, 343, 979, 1462
NTVM19AB 271, 979, 1462
NTVM3301 1628
NTVM4019 271, 979, 1463
NTVM4022 1628
NTVM4024 271, 980, 1463
NTVM50UG 1628
NTVM52UG 1628
NTVM54UG 1629
NTVM56UG 1629
NTVM58UG 1629
NTVM6002 1629
NTVM60AA 271, 980, 1463
NTVP1000 179, 980, 1463
NTVP1001 179, 981, 1463
NTVP1002 180, 981, 1463
NTVP1010 180, 982, 1463
NTVP1011 180, 982, 1463
NTVP1012 180, 982, 1463
NTWE04AC 195, 983, 1463
NTWE04AD 195, 983, 1463
NTWE07AA 180, 983, 1463
NTWH90AA 1629
NTY210AA 330, 983, 1463
NTY211AA 330, 984, 1463
NTY212AA 330, 984, 1463
NTY213AA 330, 984, 1463
NTY214AA 330, 984, 1463
NTY215AA 330, 984, 1463
NTY216AA 330, 985, 1463
NTY217AA 330, 985, 1463
NTY218AA 330, 985, 1463
NTY219AA 330, 985, 1463
NTY220AA 330, 986, 1463
NTY221AA 330, 986, 1463
NTY222AA 330, 986, 1463
NTY223AA 330, 986, 1463
NTY224AA 330, 986, 1463
NTY230AA 330, 987, 1463
NTY231AA 330, 987, 1463
NTY232AA 330, 987, 1463
NTY233AA 330, 987, 1463
NTY240AA 330, 988, 1463
NTY241AA 330, 988, 1463
NTY242AA 330, 988, 1463
NTY243AA 330, 988, 1463
NTY244AA 330, 989, 1463
NTY245AA 330, 989, 1464
NTY246AA 330, 989, 1464
NTY247AA 331, 989, 1464
NTY248AA 331, 990, 1464
NTY250AA 331, 990, 1464

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTY251AA 331, 990, 1464
NTY252AA 331, 990, 1464
NTY253AA 331, 990, 1464
NTY254AA 331, 991, 1464
NTY255AA 331, 991, 1464
NTY256AA 331, 991, 1464
NTY257AA 331, 991, 1464
NTY260AA 331, 992, 1464
NTY261AA 331, 992, 1464
NTY262AA 331, 992, 1464
NTY263AA 331, 992, 1464
NTY264AA 331, 993, 1464
NTY265AA 331, 993, 1464
NTY270AA 331, 993, 1464
NTY271AA 331, 993, 1464
NTY272AA 331, 994, 1464
NTY273AA 331, 994, 1464
NTY274AA 331, 994, 1464
NTY275AA 331, 994, 1464
NTY276AA 331, 995, 1464
NTY277AA 331, 995, 1464
NTY278AA 330, 995, 1464
NTZB01AA 180, 996, 1464
NTZB01BA 180, 996, 1464
NTZB01CA 180, 997, 1464
NTZB01DA 180, 997, 1464
NTZB02AA 180, 998, 1465
NTZB02BA 180, 998, 1465
NTZB02CA 180, 998, 1465
NTZB02DA 180, 999, 1465
NTZB02EA 180, 999, 1465
NTZB02FA 180, 999, 1465
NTZB05AA 269, 1000, 1465
NTZB05BA 269, 1000, 1465
NTZB05CA 269, 1000, 1465
NTZB05DA 269, 1001, 1465
NTZB05MA 269, 1001, 1465
NTZB06AA 1629
NTZB06AB 161, 1002, 1465
NTZB07AA 1629
NTZB07AB 66, 161, 1002, 1465
NTZB08AA 66, 161, 1003, 1465
NTZB09AA 66, 161, 1003, 1465
NTZB11AB 310, 1004, 1465
NTZB11BB 310, 1004, 1465
NTZB11CB 310, 1004, 1465
NTZB13AB 310, 1005, 1465
NTZB13BB 310, 1005, 1465
NTZB13CB 310, 1005, 1465
NTZB15AB 310, 1006, 1465
NTZB15BB 311, 1006, 1465
NTZB15CB 311, 1006, 1465
NTZB20BA 1629
NTZB2101 308, 1465
NTZB21AA 1629
NTZB21BA 1629
NTZB21CA 1629
NTZB22AA 1465, 1629
NTZB22BA 1629
NTZB22CA 1629
NTZB22DA 1466, 1629
NTZB22EA 1629
NTZB22FA 1629
NTZB77AA 176, 1007, 1466
NTZB78AA 176, 1007, 1466
NTZB79AA 176, 1008, 1466
NTZB80AA 176, 1008, 1466
NTZB87AA 176, 1008, 1466
NTZB88AA 176, 1009, 1466
NTZB88BA 176, 1009, 1466
NTZB88CA 176, 1009, 1466
NTZB91AA 180, 1010, 1466
NTZB91BA 180, 1010, 1466
NTZB91CA 180, 1010, 1466
NTZB91DA 180, 1011, 1466
NTZB91EA 180, 1011, 1466
NTZB91FA 180, 1012, 1466
NTZB91GA 180, 1012, 1466
NTZB91HA 180, 1012, 1466
NTZB92AA 180, 1013, 1466
NTZB92BA 180, 1013, 1466
NTZB92CA 180, 1014, 1466
NTZB92DA 180, 1014, 1466
NTZB92EA 180, 1014, 1466
NTZB92FA 180, 1015, 1466
NTZB92GA 180, 1015, 1466
NTZB92HA 181, 1016, 1466
NTZB93AA 181, 1016, 1466
NTZB93BA 181, 1016, 1466
NTZB93CA 181, 1016, 1466
NTZB93DA 181, 1017, 1466
NTZB93EA 181, 1017, 1466
NTZB93FA 164, 1017, 1466
NTZB93GA 164, 1017, 1466
NTZB94AA 181, 1018, 1466
NTZB94BA 181, 1018, 1467
NTZB94CA 181, 1019, 1467
NTZB95AA 181, 1019, 1467
NTZB95BA 181, 1020, 1467
NTZB95CA 181, 1020, 1467
NTZB95DA 181, 1021, 1467
NTZB95EA 181, 1021, 1467
NTZB95FA 181, 1022, 1467
NTZB95GA 181, 1022, 1467
NTZB95HA 181, 1023, 1467
NTZB95JA 181, 1023, 1467
NTZB95KA 181, 1024, 1467
NTZB95LA 181, 1024, 1467

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZB95MA 181, 1025, 1467
NTZB95NA 181, 1025, 1467
NTZB95PA 181, 1026, 1467
NTZB95QA 181, 1026, 1467
NTZB96AA 181, 1026, 1467
NTZB96BA 181, 1027, 1467
NTZC01AA 1629
NTZC01AB 1629
NTZC01AC 1629
NTZC01AD 1629
NTZC01AF 338, 1027, 1467
NTZC01BA 1629
NTZC01BB 1629
NTZC01BC 1629
NTZC01BD 1629
NTZC01BF 338, 1028, 1467
NTZC02AA 339, 1028, 1467
NTZC02BA 339, 1029, 1467
NTZC02CA 339, 1029, 1467
NTZC02DA 339, 1030, 1467
NTZC02EA 339, 1030, 1468
NTZC02FA 339, 1030, 1468
NTZC02GA 339, 1031, 1468
NTZC03AA 1629
NTZC03AC 1629
NTZC03AD 1629
NTZC03AF 339, 1031, 1468
NTZC04AA 339, 1031, 1468
NTZC04BA 339, 1032, 1468
NTZC04CA 339, 1032, 1468
NTZC06AA 340, 1032, 1468
NTZC06BA 340, 1033, 1468
NTZC06CA 340, 1033, 1468
NTZC06DA 340, 1033, 1468
NTZC07AA 1629
NTZC07AB 1629
NTZC07AC 1630
NTZC07AD 1630
NTZC07AF 340, 1033, 1468
NTZC08AA 1630
NTZC08AB 1630
NTZC08AC 1630
NTZC08AD 1630
NTZC08AF 339, 1034, 1468
NTZC09AA 1630
NTZC09AB 1630
NTZC09AC 1630
NTZC09AD 1630
NTZC09AF 340, 1034, 1468
NTZC10AA 1630
NTZC10AB 1630
NTZC10AC 1630
NTZC10AD 1630
NTZC10AF 339, 1034, 1468
NTZC10BA 1630
NTZC10BB 1630
NTZC10BC 1630
NTZC10BD 1630
NTZC10BF 339, 1034, 1468
NTZC10CA 1630
NTZC10CB 1630
NTZC10CC 1630
NTZC10CD 1630
NTZC10CF 339, 1035, 1468
NTZC10DA 1630
NTZC10DB 1630
NTZC10DC 1630
NTZC10DD 1630
NTZC10DF 339, 1035, 1468
NTZC10EA 1630
NTZC10EB 1630
NTZC10EC 1631
NTZC10ED 1631
NTZC10EF 339, 1035, 1468
NTZC12AA 1631
NTZC12BA 1631
NTZC12CA 65, 182, 1036, 1468
NTZC13AA 1468, 1631
NTZC13BA 65, 182, 1036, 1468
NTZC14AA 65, 182, 1036, 1468
NTZC17AA 1631
NTZC18AA 1631
NTZC19AA 182, 1037, 1468
NTZC35AA 204, 1037, 1468
NTZC35BA 204, 1037, 1468
NTZC35CA 204, 1038, 1468
NTZC35DA 204, 1038, 1468
NTZC35EA 204, 1038, 1468
NTZC36AA 204, 1039, 1469
NTZC36BA 204, 1039, 1469
NTZC36CA 204, 1039, 1469
NTZC36DA 204, 1039, 1469
NTZC36EA 204, 1040, 1469
NTZC37AA 204, 1040, 1469
NTZC37BA 204, 1040, 1469
NTZC37CA 204, 1040, 1469
NTZC44AA 182, 1041, 1469
NTZC44BA 182, 1041, 1469
NTZC45AA 182, 1042, 1469
NTZC47AA 182, 1042, 1469
NTZC47BA 182, 1043, 1469
NTZC49AA 235, 1043, 1469
NTZC50AA 237, 1044, 1469
NTZC50BA 237, 1044, 1469
NTZC51AA 237, 1044, 1469
NTZC51BA 230, 237, 1045, 1469
NTZC52AA 247, 1045, 1469
NTZC53AA 260, 1046, 1469

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZC53BA 260, 1046, 1469
NTZC54AA 261, 1047, 1469
NTZC54BA 261, 1048, 1469
NTZC55AA 261, 1048, 1469
NTZC56AA 261, 1049, 1470
NTZC56BA 261, 1049, 1470
NTZC56CA 261, 1050, 1470
NTZC56DA 261, 1051, 1470
NTZC57AA 230, 235, 1051, 1470
NTZC57BA 245, 1052, 1470
NTZC58AA 230, 1052, 1470
NTZC58BA 230, 1052, 1470
NTZC58CA 230, 1053, 1470
NTZC59AA 230, 1053, 1470
NTZC62AA 182, 1053, 1470
NTZC62BA 182, 1054, 1470
NTZC62CA 182, 1054, 1470
NTZC63AA 182, 1054, 1470
NTZC63BA 182, 1055, 1470
NTZC63CA 182, 1055, 1470
NTZC65AA 182, 1056, 1470
NTZC70AA 297, 1470
NTZC70BA 297, 1470
NTZC70CA 297, 1470
NTZC70DA 297, 1470
NTZC75AA 182, 1056, 1470
NTZC76AA 182, 1057, 1470
NTZC77AA 182, 1057, 1470
NTZC80AA 58, 62, 158, 1057, 1470
NTZC81AA 58, 62, 158, 1058, 1470
NTZC82AA 58, 62, 157, 1058, 1470
NTZC84AA 58, 62, 157, 1058, 1470
NTZC90BB 1631
NTZC91BA 198, 1059, 1470
NTZD0001 302, 1059, 1470
NTZD0002 302, 1059, 1471
NTZD0003 302, 1471
NTZD0004 302, 1059, 1471
NTZD0005 303, 1060, 1471
NTZD0006 1060, 1471
NTZD0007 1060, 1471
NTZD02AA 303, 1061, 1471
NTZD02AD 303, 1062, 1471
NTZD02BA 303, 1062, 1471
NTZD02BD 303, 1063, 1471
NTZD06AA 1631
NTZD06AD 1631
NTZD06AE 1631
NTZD06AF 298, 1063, 1471
NTZD07AA 307, 1063, 1471
NTZD08AA 307, 1064, 1471
NTZD10AA 307, 1064, 1471
NTZD10AF 298, 1064, 1471
NTZD11AA 26, 1631
NTZD11AD 1631
NTZD13AF 298, 1064, 1471
NTZD21AA 1064, 1471
NTZD24AA 1065, 1471
NTZD26AA 1065, 1471
NTZD27AA 1065, 1471
NTZD52AA 1631
NTZD53AA 1631
NTZD61AA 236, 246, 1065, 1471
NTZD61BA 236, 246, 1066, 1471
NTZD62AA 235, 245, 256, 1066, 1471
NTZD63AA 238, 1067, 1471
NTZD63BA 238, 1068, 1471
NTZD65AA 248, 1068, 1471
NTZD66AA 257, 1069, 1471
NTZD66BA 257, 1070, 1471
NTZD67AA 256, 1070, 1472
NTZD68AA 263, 1071, 1472
NTZD68BA 263, 1072, 1472
NTZD69AA 263, 1073, 1472
NTZD69BA 263, 1074, 1472
NTZD69CA 263, 265, 1075, 1472
NTZD69DA 263, 265, 1076, 1472
NTZD69EA 263, 1077, 1472
NTZD70AA 264, 266, 1078, 1472
NTZD70BA 264, 266, 1080, 1472
NTZD70CA 264, 266, 1081, 1472
NTZD70DA 264, 266, 1082, 1472
NTZD70EA 266, 1083, 1472
NTZD70FA 266, 1084, 1472
NTZD71AA 261, 1085, 1472
NTZD71BA 262, 1086, 1472
NTZD72AA 262, 1087, 1472
NTZD72BA 262, 1088, 1472
NTZD73AA 262, 1089, 1472
NTZD73BA 262, 1090, 1472
NTZD74AA 262, 1091, 1473
NTZD74BA 262, 1092, 1473
NTZD75AA 263, 1092, 1473
NTZD75BA 263, 264, 265, 1093, 1473
NTZD80AA 1631
NTZD81AA 298, 1093, 1473
NTZE01AA 219, 1094, 1473
NTZE01AB 1631
NTZE02AA 219, 1096, 1473
NTZE02AB 1631
NTZE03AA 219, 1098, 1473
NTZE03AB 1631
NTZE04AA 219, 1100, 1473
NTZE04AB 1631
NTZE07AA 224, 1102, 1473
NTZE07BA 224, 1102, 1473
NTZE07CA 224, 1102, 1473
NTZE07EA 224, 1103, 1473

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZE08AA 219, 1103, 1473
NTZE08BA 219, 1103, 1473
NTZE09AA 1631
NTZE09BA 1631
NTZE10AA 219, 1104, 1473
NTZE10BA 219, 1104, 1473
NTZE10CA 225, 1104, 1473
NTZE10DA 225, 1104, 1473
NTZE10EA 225, 1105, 1473
NTZE10FA 225, 1105, 1473
NTZE10HA 225, 1473
NTZE10JA 225, 1473
NTZE10KA 225, 1473
NTZE11AA 219, 1105, 1473
NTZE11BA 219, 1106, 1473
NTZE11CA 225, 1106, 1473
NTZE11DA 225, 1106, 1473
NTZE11EA 225, 1106, 1473
NTZE11FA 225, 1107, 1473
NTZE11HA 225, 1473
NTZE11JA 225, 1473
NTZE11KA 225, 1473
NTZE12AA 219, 1107, 1473
NTZE12BA 219, 1107, 1474
NTZE12CA 225, 1108, 1474
NTZE12DA 225, 1108, 1474
NTZE12EA 225, 1108, 1474
NTZE12FA 225, 1108, 1474
NTZE12HA 225, 1474
NTZE12JA 225, 1474
NTZE12KA 225, 1474
NTZE13AA 219, 1109, 1474
NTZE13BA 219, 1109, 1474
NTZE13CA 219, 1109, 1474
NTZE13DA 225, 1474
NTZE14AA 219, 1110, 1474
NTZE14BA 219, 1110, 1474
NTZE14CA 219, 1110, 1474
NTZE14DA 225, 1111, 1474
NTZE15AA 226, 1111, 1474
NTZE16AA 219, 1111, 1474
NTZE16BA 219, 1112, 1474
NTZE19AA 224, 1474
NTZE19BA 224, 1474
NTZE19CA 224, 1474
NTZE19DA 224, 1474
NTZE19EA 224, 1474
NTZE19FA 224, 1474
NTZE19GA 224, 1474
NTZE19HA 224, 1474
NTZE24AA 222, 1112, 1474
NTZE24BA 222, 1112, 1474
NTZE24CA 222, 1113, 1474
NTZE24DA 222, 1113, 1474
NTZE25AA 219, 1114, 1474
NTZE25BA 219, 1114, 1474
NTZE25CA 226, 1475
NTZE25DA 226, 1475
NTZE26AA 219, 1114, 1475
NTZE26BA 226, 1115, 1475
NTZE26CA 226, 1475
NTZE27AA 226, 1115, 1475
NTZE27BA 219, 1115, 1475
NTZE27CA 226, 1475
NTZE29AA 222, 1116, 1475
NTZE29BA 223, 1116, 1475
NTZE29CA 223, 1116, 1475
NTZE29DA 223, 1117, 1475
NTZE29EA 223, 1117, 1475
NTZE30AA 223, 1117, 1475
NTZE31AA 226, 1118, 1475
NTZE31BA 226, 1118, 1475
NTZE39AA 226, 1118, 1475
NTZE39BA 226, 1118, 1475
NTZE39CA 226, 1119, 1475
NTZE39DA 226, 1119, 1475
NTZE39EA 226, 1119, 1475
NTZE4001 226, 1475
NTZE4002 226, 1119, 1475
NTZE4003 226, 1475
NTZE4004 219, 1475
NTZE80AA 219, 1120, 1475
NTZE81AA 219, 1120, 1475
NTZE82AA 219, 1121, 1475
NTZE83AA 219, 1121, 1475
NTZE99BA 223, 1122, 1475
NTZE99CA 223, 1122, 1475
NTZE99DA 223, 1122, 1475
NTZE99EA 223, 1123, 1475
NTZK06AA03 1475, 1631
NTZK06AA35 1475, 1631
NTZK06AA93 1475, 1631
NTZK06AB03 1475, 1631
NTZK06AB35 1476, 1631
NTZK06AB93 1476, 1631
NTZK06AC03 1476, 1631
NTZK06AC35 1476, 1631
NTZK06AC93 1476, 1631
NTZK0700 1631
NTZK08AA03 1476, 1631
NTZK08AA35 1476, 1631
NTZK08AA93 1476, 1632
NTZK08AB03 1476, 1632
NTZK08AB35 1476, 1632
NTZK08AB93 1476, 1632
NTZK08AC03 1476, 1632
NTZK08AC35 1476, 1632
NTZK08AC93 1476, 1632

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZK08BA03 1476, 1632
NTZK08BA35 1476, 1632
NTZK08BA93 1476, 1632
NTZK08BB03 1476, 1632
NTZK08BB35 1476, 1632
NTZK08BB93 1476, 1632
NTZK08BC03 1476, 1632
NTZK08BC35 1476, 1632
NTZK08BC93 1476, 1632
NTZK08CA03 1477, 1632
NTZK08CA35 1477, 1632
NTZK08CA93 1477, 1632
NTZK08CC03 1477, 1632
NTZK08CC35 1477, 1632
NTZK08CC93 1477, 1632
NTZK0900 1632
NTZK1000 1632
NTZK13AA 1632
NTZK13BA 1632
NTZK14AA 273, 285, 1123, 1477
NTZK16AA03 1477, 1632
NTZK16AA35 1477, 1632
NTZK16AA93 1477, 1632
NTZK16AB03 1477, 1632
NTZK16AB35 1477, 1632
NTZK16AB93 1477, 1632
NTZK16AC03 1477, 1632
NTZK16AC35 1477, 1633
NTZK16AC93 1477, 1633
NTZK16BA03 1477, 1633
NTZK16BA35 1477, 1633
NTZK16BA93 1477, 1633
NTZK16BB03 1477, 1633
NTZK16BB35 1477, 1633
NTZK16BB93 1477, 1633
NTZK16BC03 1477, 1633
NTZK16BC35 1477, 1633
NTZK16BC93 1477, 1633
NTZK16CA03 1478, 1633
NTZK16CA35 1478, 1633
NTZK16CA93 1478, 1633
NTZK16CC03 1478, 1633
NTZK16CC35 1478, 1633
NTZK16CC93 1478, 1633
NTZK20AA03 1478, 1633
NTZK20AA35 202, 1124, 1478
NTZK20AA93 1478, 1633
NTZK20AB03 1478, 1633
NTZK20AB35 1478, 1633
NTZK20AB93 1478, 1633
NTZK20AC03 1478, 1633
NTZK20AC35 1478, 1633
NTZK20AC93 1478, 1633
NTZK20BA03 1478, 1633
NTZK20BA35 1478, 1633
NTZK20BA93 1478, 1633
NTZK20BB03 1478, 1633
NTZK20BB35 1478, 1633
NTZK20BB93 1478, 1633
NTZK20BC03 1478, 1633
NTZK20BC35 1478, 1633
NTZK20BC93 1478, 1633
NTZK22AA03 1478, 1634
NTZK22AA35 1478, 1634
NTZK22AA93 1478, 1634
NTZK22AB03 1478, 1634
NTZK22AB35 1479, 1634
NTZK22AB93 1479, 1634
NTZK22AC03 1479, 1634
NTZK22AC35 1479, 1634
NTZK22AC93 1479, 1634
NTZK22CA03 1479, 1634
NTZK22CA35 1479, 1634
NTZK22CA93 1479, 1634
NTZK22CC03 1479, 1634
NTZK22CC93 1479, 1634
NTZK23AA03 1479, 1634
NTZK23AA35 1479, 1634
NTZK23AA93 1479, 1634
NTZK23AB03 1479, 1634
NTZK23AB35 1479, 1634
NTZK23AB93 1479, 1634
NTZK23AC03 1479, 1634
NTZK23AC35 1479, 1634
NTZK23AC93 1479, 1634
NTZK23CA03 1479, 1634
NTZK23CA35 1479, 1634
NTZK23CA93 1479, 1634
NTZK23CC03 1479, 1634
NTZK23CC35 1479, 1634
NTZK23CC93 1479, 1634
NTZK27AA 1634
NTZK27BA 1634
NTZK27CA 1634
NTZK29AA 311, 1124, 1479
NTZK29BA 311, 1124, 1479
NTZK29CA 311, 1125, 1479
NTZK37AA 1635
NTZK37AD 1125, 1479
NTZK37BA 1635
NTZK37BD 1126, 1479
NTZK38AA 1635
NTZK38AD 1126, 1479
NTZK38BA 1635
NTZK38BD 1127, 1479
NTZK39AA 1635
NTZK39AD 1127, 1479
NTZK39BA 1635

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZK39BD 1128, 1479
NTZK39CA 1635
NTZK39CD 1128, 1479
NTZK40AA 1635
NTZK40AD 1129, 1480
NTZK41AA 1635
NTZK41AD 1129, 1480
NTZK42AA 1635
NTZK42AD 1130, 1480
NTZK43AA 1635
NTZK43AD 1130, 1480
NTZK44AA 1635
NTZK44AD 1131, 1480
NTZK45BA 1635
NTZK45BD 341, 1131, 1480
NTZK45CA 1635
NTZK45CD 341, 1132, 1480
NTZK45DA 1635
NTZK45DD 1132, 1480
NTZK45EA 1635
NTZK45ED 1133, 1480
NTZK45FB 1635
NTZK45FD 1133, 1480
NTZK46AA 1635
NTZK46AD 341, 1134, 1480
NTZK46BA 1635
NTZK46BD 341, 1134, 1480
NTZK47AA 1635
NTZK47AD 341, 1135, 1480
NTZK47BA 1635
NTZK47BD 341, 1135, 1480
NTZK48AA 1635
NTZK48AD 341, 1136, 1480
NTZK49AA 1635
NTZK49AD 341, 1136, 1480
NTZK50AA 1635
NTZK50AD 341, 1137, 1480
NTZK51AA 1635
NTZK51AD 341, 1137, 1480
NTZK52BA 337, 340, 341, 1137, 1480
NTZK52CA 337, 340, 341, 1138, 1480
NTZK52DA 337, 340, 341, 1138, 1480
NTZK53AA 1635
NTZK53BA 1635
NTZK53CA 1635
NTZK55AA 1635
NTZK55BA 1635
NTZK55CA 1635
NTZK57AA 1636
NTZK57BA 1636
NTZK57CA 1636
NTZK59AA 1636
NTZK59BA 1636
NTZK59CA 1636
NTZK63AA 1636
NTZK63AD 1636
NTZK63CA 1636
NTZK63CD 1636
NTZK64AA 1636
NTZK64AD 1636
NTZK64BA 1636
NTZK64BD 1636
NTZK64CA 1636
NTZK64CD 1636
NTZK64DA 1636
NTZK64DD 1636
NTZK64EA 1636
NTZK64ED 1636
NTZK64FA 1636
NTZK64FD 1636
NTZK64GA 1636
NTZK64GD 1636
NTZK65AA 1636
NTZK65AB 1636
NTZK65AD 1636
NTZK65BA 1636
NTZK66AA 1636
NTZK66AD 1636
NTZK66BA 1636
NTZK66BD 1637
NTZK66CA 1637
NTZK66CD 1637
NTZK66DA 1637
NTZK66DD 1637
NTZK67AA 1637
NTZK67AD 1637
NTZK67CA 1637
NTZK67CD 1637
NTZK67FA 1637
NTZK67FD 1637
NTZK72AA 1637
NTZK72BA 1637
NTZK72DA 1637
NTZK72FA 1637
NTZK73BA 1637
NTZK80AA 1637
NTZK81AA 1637
NTZK86AA 1637
NTZK8900 1637
NTZK89BB 1637
NTZK91EB 1637
NTZK91FB 1637
NTZK91GB 1637
NTZK93AB 1637
NTZK95AD 1637
NTZK96AD 1637
NTZK98AA 1637
NTZK99AD 1637

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

NTZR07BA 205, 1138, 1480
NTZR09BA 184, 205, 1139, 1480
NTZR10AA 1637
NTZR11AA 1637
NTZR12AA 1637
NTZR13AA 1637
NTZR15AA 1638
NTZR16AA 1638
NTZR17AA 1638
NTZR18AA 1638
NTZR19AA 1638
NTZR20AA 1638
NTZR21AA 1638
NTZR21AB 1638
NTZR21AC 1638
NTZR21AD 1638
NTZR22AA 1638
NTZR23AA 1638
NTZR24AA 1638
NTZR25AA 1638
NTZR26AA 1638
NTZR27AA 1638
NTZR28AA 1638
NTZR29AA 1638
NTZR30AA 1638
NTZR31AA 1638
NTZR32AA 1638
NTZR33AA 1638
NTZR34AA 1638
NTZR35AA 1638
NTZR36AA 1638
NTZR37AA 1638
NTZR37AB 1638
NTZR38AA 1638
NTZR39AA 1638
NTZR40AA 1638
NTZR40BA 1480
NTZR41AA 1638
NTZR42AA 1638
NTZR43AA 1638
NTZR44AA 1638
NTZR50AA 1639
NTZR50AA03 208, 1139, 1480
NTZR50AA35 208, 1139, 1480
NTZR50AA93 208, 1139, 1480
NTZR51AA 1639
NTZR52AA 1639
NTZR53AA 1639
NTZR54AA 1639
NTZR55AA 1639
NTZR56AA 1639
NTZR57AA 1639
NTZR57CA 256, 1140, 1480
NTZR60BA 1639
NTZR61BA 1639
NTZR62AA 1639
NTZR62BA 1639
NTZR63AA 1639
NTZR63BA 1639
Null Modem Adapter 250, 269, 829, 1443
Null Modem Adapter (Male/Female) 1570
Null Modem Cable (10 Ft.) 268, 328, 597, 1412
Null Modem Cable (25 Ft.) 1570
Null Modem Connector, (Female/Female) 66, 196, 393, 1367
Null Modem Connector, Female/Male 66, 391, 1367
Numeric Display Replacement Kit (QCW2) 1641
NVP Cable 268, 571, 1407
NVP Card, Flexible Assignment 1566
NVP Daisychain Cable 268, 550, 1144, 1401, 1481
NVP Extension Cable 1588
NVP Tier 1 Cable Router 1588
NVP Tier 2 Cable Router 1588
NVP Tier 3 Cable Router 1588
NY2K22VH03 1639
NY2K22VH35 1480, 1639
NY2K22VH93 1480, 1639

O

Observe Key Cap Package (50/PK) 207, 398, 1368
OC-3 ATM Mixed Mode Function Processor 1619
OC-3 ATM MX Fiber Cable Assembly 1619
OC-3 Fiber Interface Package 1619
OIVR 2.x Hardware - 1.05GB Disk Drive (Rack) 274, 284, 411, 1371
OIVR 2.x Hardware - 1.05GB Disk Drive (Tower) 274, 284, 411, 1371
OIVR 2.x Hardware - 10 position Connector PEB Cable 274, 284, 415, 1371
OIVR 2.x Hardware - 12-port Loopstart Network Interface Module 273, 284, 410, 1371
OIVR 2.x Hardware - 12-Port Loopstart Voice Port Assembly 280, 535, 1398
OIVR 2.x Hardware - 12-port Voice Processing Card 273, 284, 410, 1371
OIVR 2.x Hardware - 2 Port Brooktrout Fax Card 274, 284, 413, 1371
OIVR 2.X Hardware - 24-Port T1 Voice Port Assembly for MRS/AP 1584
OIVR 2.x Hardware - 256KB L2 Async Cache for AP or MRS/AP 273, 283, 406, 1370
OIVR 2.x Hardware - 350W AC Power Supply (Rack) 274, 284, 415, 1371
OIVR 2.x Hardware - 350W DC Power Supply (Rack) 274, 284, 414, 1371
OIVR 2.x Hardware - 4 Port Brooktrout Fax Card 274,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

284, 413, 1371
OIVR 2.x Hardware - 450W Power Supply (Tower) 274, 284, 412, 1371
OIVR 2.X Hardware - 4-Port Loopstart Voice Assembly for MRS/AP 1584
OIVR 2.x Hardware - 6 Ft. SCSI Cable for MRS 274, 285, 417, 1372
OIVR 2.x Hardware - 8 Port Brooktrout Fax Card 274, 284, 414, 1371
OIVR 2.x Hardware - Apertus Communications Board (SDLC) 274, 284, 414, 1371
OIVR 2.x Hardware - Cabinet Rail Assembly 272, 285, 418, 1372
OIVR 2.x Hardware - Cable, LCD for AP or MRS/AP 274, 284, 305, 415, 1371
OIVR 2.x Hardware - Continuous Speech Recognition - 2 Ports 280, 541, 1399
OIVR 2.x Hardware - Continuous Speech Recognition - North American Vocabularies Package 1637
OIVR 2.x Hardware - Continuous Speech Recognition 2 Port Expansion 280, 541, 1399
OIVR 2.x Hardware - CPU Module Battery for MRS 274, 285, 416, 1372
OIVR 2.x Hardware - CPU Module with 32MB Memory 274, 284, 412, 1371
OIVR 2.x Hardware - CPU Module with no Memory 274, 284, 412, 1371
OIVR 2.x Hardware - Digiboard DTE 8 Port DB25 Male Cable 274, 284, 412, 1371
OIVR 2.x Hardware - Digital Prompt Tool Package 1632
OIVR 2.x Hardware - Discrete Speech Recognition - 4 Port Expansion 280, 540, 1399
OIVR 2.x Hardware - Discrete Speech Recognition - 4 Ports 280, 540, 1399
OIVR 2.x Hardware - Discrete Speech Recognition - North American Vocabularies Package 1637
OIVR 2.x Hardware - Drive LED Panel for AP or MRS/AP 273, 284, 305, 408, 1370
OIVR 2.x Hardware - Ethernet Controller for MRS 274, 284, 411, 1371
OIVR 2.x Hardware - Expansion RAM - 16MB SIMM with Parity 273, 283, 305, 406, 1370
OIVR 2.x Hardware - Expansion RAM - 8MB SIMM with Parity 273, 283, 406, 1370
OIVR 2.x Hardware - Fan (100cfm) 273, 284, 305, 408, 1370
OIVR 2.x Hardware - Floppy Cable for MRS 274, 285, 417, 1372
OIVR 2.x Hardware - Floppy Disk Drive for MRS 274, 285, 418, 1372
OIVR 2.x Hardware - Floppy Drive, 3.5 In. 274, 413, 1371
OIVR 2.x Hardware - Installation and Maintenance Guide 1599
OIVR 2.x Hardware - International System Prompts 1637
OIVR 2.x Hardware - IVR Development Documentation Package 1584
OIVR 2.x Hardware - IVR Documentation Package 1584
OIVR 2.x Hardware - IVR Operational Documentation Package 1584
OIVR 2.x Hardware - IVR Options Documentation Package 1584
OIVR 2.x Hardware - Keyboard 41, 222, 285, 307, 856, 1446
OIVR 2.x Hardware - Keylock Adapter 274, 285, 417, 1372
OIVR 2.x Hardware - Loopstart Interface Cable (DB25F to RJ23X) 274, 285, 416, 1372
OIVR 2.x Hardware - MRS System Recovery Software Ethernet 272, 285, 537, 1398
OIVR 2.x Hardware - MRS System Recovery Software Token Ring 272, 285, 537, 1399
OIVR 2.x Hardware - MRS to Terminal Cable (DB25F to DB25M) 274, 285, 416, 1371
OIVR 2.x Hardware - MRS/AP or AP 32MB Memory Upgrade 1585
OIVR 2.x Hardware - MRS/AP or AP Ethernet LAN Interface 275, 536, 1398
OIVR 2.x Hardware - MRS/AP or AP Token Ring LAN Interface 275, 285, 536, 1398
OIVR 2.x Hardware - MRS/AP or AP Uninterruptible Power Supply 1586
OIVR 2.x Hardware - MRS/Rack AC Spares Kit 273, 284, 343, 407, 1370
OIVR 2.x Hardware - MRS/Rack DC Spares Kit 273, 283, 343, 407, 1370
OIVR 2.x Hardware - MRS/Rack Fan Assembly 274, 285, 418, 1372
OIVR 2.x Hardware - MRS/Tower Air Filter 274, 285, 416, 1372
OIVR 2.x Hardware - MRS/Tower or MRS/Rack Disk Drive (1.05GB) 273, 285, 1123, 1477
OIVR 2.X Hardware - MRS/Tower or MRS/Rack Ethernet Lan Interface 272, 285, 538, 1399
OIVR 2.x Hardware - MRS/Tower or MRS/Rack Token Ring LAN Interface 272, 285, 538, 1399
OIVR 2.x Hardware - MRS/Tower Spares Kit 273, 283, 342, 407, 1370
OIVR 2.x Hardware - Open IVR System Prompts - North America 1637
OIVR 2.x Hardware - Operational NTP Assembly 1586
OIVR 2.x Hardware - Power Supply, 525W for AP or MRS/AP 274, 284, 305, 415, 1371
OIVR 2.x Hardware - Prompt Management Software 1559

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

OIVR 2.x Hardware - Redundant DC Power Supply for MRS/Rack 274, 284, 414, 1371
OIVR 2.x Hardware - Riser Board for AP or MRS/AP 275, 285, 419, 1372
OIVR 2.x Hardware - Runtime to Development Upgrade AP or MRS/AP (excludes Prompt Manager) 1632
OIVR 2.x Hardware - Runtime to Development Upgrade AP or MRS/AP (includes Prompt Manager) 1632
OIVR 2.x Hardware - SCSI Disk Controller for MRS 274, 284, 410, 1371
OIVR 2.x Hardware - Serial I/O Controller for MRS 274, 284, 410, 1371
OIVR 2.x Hardware - Tape Drive (2.5GB) 273, 283, 402, 1369
OIVR 2.x Hardware - Text-to-Speech 4 Port Expansion 280, 541, 1399
OIVR 2.x Hardware - Text-To-Text Speech - North American Vocabularies Package 1637
OIVR 2.x Hardware - Token Ring Controller for MRS 274, 284, 411, 1371
OIVR 2.X Hardware - Video DRAM Expansion (512KB to 1MB Expansion) 273, 283, 406, 1370
OIVR 2.x Hardware - Voice and Data Storage (1GB) for MRS/AP or AP 275, 542, 1399
OIVR 2.x Hardware - VRP Voice Recognition Card 273, 284, 410, 1371
OIVR 2.x Hardware - VT100 Communications Board (16 ports) & Cable 1559
OIVR 2.x Hardware Fax Support - 2 Ports 280, 539, 1399
OIVR 2.x Hardware Fax Support - 4 Ports 280, 539, 1399
OIVR 2.x Hardware Fax Support - 8 Ports 280, 540, 1399
OIVR 2.x Hardware UPS for AP and MRS/AP 28
OMNIFACTS Application Software Maintenance (Multi) 1535
OMNIFACTS Application Software Maintenance (Single) 1535
OMNIFACTS Basic Capability (Generic 4002) 1535
OMNIFACTS Full Featured (Generic 4004) 1535
OMNIFACTS Option 1 Enhanced Reports 1535
OMNIFACTS Option 2 Automated Directory Look-Up (ADLU) 1535
OMNIFACTS Resale of Services (Hobic) (Generic 4005) 1535
OMNIFACTS Stand-Alone Automated Directory Look-up (ADLU) (Generic 4008) 1535
OMNIFACTS V&H Coordinate/Costing Module Updates (CDR) 1535
Omninet/Corvus Software 1550
One Year On-Site Maintenance - Dual Tower 1693
One Year On-Site Maintenance - Single Tower 1693
One-Year On-Site Maintenance - Network Administration Center 1693
Online Call Keycap & Power Supply 334, 1443
Onsite Removal/Replacement 271, 1186, 1510
Open IVR 2.5 Audio Interface Unit Guide 1663
Open IVR 2.5 North American PRI Guide 1668
Open IVR 2.5 Upgrade Package 1631
OPEN IVR Release 4 - Application Development Guide 285, 1460
OPEN IVR Release 4 - Audio Interface Guide 1625
OPEN IVR Release 4 - Cell Catalog Guide 285, 1460
OPEN IVR Release 4 - Error Messages Guide 285, 1460
OPEN IVR Release 4 - Fax Option Guide 285, 1460
OPEN IVR Release 4 - Installation, Upgrade and Maintenance 285, 1459
OPEN IVR Release 4 - Integration Package for Meridian Link Guide 286, 1460
OPEN IVR Release 4 - Integration Package for Nortel TAPI Server Guide 1626
OPEN IVR Release 4 - Planning and Engineering Guide 285, 1460
OPEN IVR Release 4 - Product Guide 285, 1459
OPEN IVR Release 4 - Prompt Conversion Guide 1625
OPEN IVR Release 4 - Prompt Import Utility Guide 286, 1460
OPEN IVR Release 4 - Prompt Management Overview Guide 1625
OPEN IVR Release 4 - Service Console Interface Guide 285, 1460
OPEN IVR Release 4 - SNA Host Communications Guide 286, 1460
OPEN IVR Release 4 - Speech Recognition Guide 285, 1460
OPEN IVR Release 4 - System Administration Guide 285, 1459
OPEN IVR Release 4 - Text-To-Speech Guide 285, 1460
OPEN IVR Release 4 - VT100 Configuration and Development Guide 286, 1460
OPEN IVR Release 4 - Web Option Guide 285, 1460
Open Management System - Passport 1621
OpenLink Database Support 1625
OPS Cable 67, 197, 701, 1429
OPS Protection Module 67, 197, 701, 1429, 1615
OPS Protector Device 66, 196, 392, 1367
Optical Cable Management Card (OCMC) 179, 841, 1444
Option 1 1528
Option 1 - Reporting Package 1541
Option 10 - Multi Printers 1541
Option 11 - Additional VDT (17-32) 1541
Option 11 0531 22 Mbyte Add-On Disk Drive

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

(MVC01477) 1528
Option 11 Cabinet Pedestal 67, 197, 696, 1428
Option 11 CE Spares Package 1562
Option 11 Documentation Package 1614, 1615
Option 11 Downloadable DCHI 65, 67, 178, 1430
Option 11 Expansion Cabinet 1427, 1611
Option 11 Expansion Package AC/DC 1562
Option 11 Expansion Package DC/DC 1562
Option 11 Main Cabinet 1611
Option 11 NTP Package 1615
Option 11 NTP Package Release 18 345, 1429, 1615
Option 11 Sales Call Sheet (50/PK) 1656
Option 11 Sales Call Sheet Fax Form (50/PK) 1656
Option 11 System Back-Up Cartridge 67, 197, 701, 1429
Option 11 System Package AC/DC 1707
Option 11 System Package DC/DC 1708
Option 11 Technical Reference Guide 1655, 1656, 1658
Option 11/11E 2 Cabinet to Option 11C 2 Cabinet Ethernet (2 Mile Single Mode Fiber) 1623
Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Ethernet (2 Mile Single Mode Fiber) 1623
Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Fiber (2 Mile) 1623
Option 11/11E 3 Cabinet to Option 11C 3 Cabinet Fiber (30 Ft.) 1623
Option 11/11E to 11C - Two Cabinet Ethernet Upgrade (2 Mile - Single Mode Fiber) 71, 164, 880, 1449
Option 11/11E to 11C Single Cabinet Upgrade 70, 164, 876, 1449, 1623
Option 11/11E to 11C Three Cabinet Fiber Upgrade (2 mile) 71, 164, 880, 1449
Option 11/11E to 11C Three Cabinet Fiber Upgrade (30 Ft.) 70, 164, 879, 1449
Option 11/11E to 11C Three Cabinet Single Mode Fiber Upgrade (2 Mile) 71, 164, 881, 1449
Option 11/11E to 11C Two Cabinet Copper 1623
Option 11/11E to 11C Two Cabinet Copper Upgrade 70, 164, 877, 1449
Option 11/11E to 11C Two Cabinet Fiber (2 Mile) 1623
Option 11/11E to 11C Two Cabinet Fiber (30 Ft.) 1623
Option 11/11E to 11C Two Cabinet Fiber Upgrade (2 mile) 70, 164, 878, 1449
Option 11/11E to 11C Two Cabinet Fiber Upgrade (30 Ft.) 70, 164, 877, 1449
Option 11/11E to Option 11C Enhanced Business Software Upgrade 71, 74, 886, 1449
Option 11/11E to Option 11C Enterprise Software Upgrade 74, 887, 1449
Option 11/11E to Option 11C General Business Software Upgrade 71, 74, 886, 1449
Option 11/11E to Option 11C NAS/VNS Software Upgrade 74, 887, 1449
Option 11C - 2 Mile Expansion Cabinet AC 64, 161, 871, 1448, 1623
Option 11C - 2 Mile Expansion Cabinet DC 64, 161, 871, 1448, 1623
Option 11C - 2 Mile Expansion Cabinet Package AC (Single Mode Fiber) 64, 161, 872, 1448, 1623
Option 11C - 2 Mile Expansion Cabinet Package DC (Single Mode Fiber) 1623
Option 11C - 2 Mile Expansion Cabinet Single Mode DC 64, 161, 873, 1448
Option 11C - 30 Ft. Expansion Cabinet AC 64, 161, 869, 1448, 1623
Option 11C - 30 Ft. Expansion Cabinet DC 64, 161, 870, 1448, 1623
Option 11C 100 Additional TNs - Enhanced Business 63, 74, 889, 1450
Option 11C 100 Additional TNs - Enterprise 63, 74, 889, 1450
Option 11C 100 Additional TNs - General Business 63, 74, 889, 1449
Option 11C 100 Additional TNs - NAS/VNS 63, 74, 890, 1450
Option 11C 48MB Blank PCMCIA Memory Card Assembly 33, 68, 912, 1451
Option 11C 48MB Software Daughterboard (Blank) 68, 179, 1451
Option 11C Administration & Maintenance I/O Guides 1670
Option 11C Blank Software Daughterboard 68, 179, 714, 1432
Option 11C- Blank Software Daughterboard 67, 178, 709, 1431
Option 11C BRI Guide (Release 18 to 24) - English 63, 349, 1497, 1670
Option 11C Compact - 10m Fiber Receiver Card 1441
Option 11C Compact 1.5MB DTI/PRI Guide 1669
Option 11C Compact AC Power Supply 59, 821, 1441, 1621
Option 11C Compact Advanced Hospitality Communications Feature Set (S/W) 1621
Option 11C Compact Advanced Hospitality Communications Package 58, 801, 1437
Option 11C Compact Advanced Hospitality Package - Additional 8 TN's 804, 1437
Option 11C Compact Advanced Hospitality Package - Additional 8 TNs' 58
Option 11C Compact Cabinet Assembly 1441
Option 11C Compact Cabinet Fan Assembly 61, 820, 1441
Option 11C Compact Call Center Communications Expansion TN's 1618
Option 11C Compact CCBR Guide 1668

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option 11C Compact Central Answering Position Guide 1668
Option 11C Compact Customer Documentation Package 60, 824, 1442, 1621
Option 11C Compact Demo Package 1618
Option 11C Compact Documentation - CD ROM 1621
Option 11C Compact Documentation Library (CDROM) 60, 1442, 1621
Option 11C Compact Expansion Cabinet Package 58, 821, 1441
Option 11C Compact Features and Services Guide 60, 1495, 1668
Option 11C Compact Hospitality 10-slot cabinet 61, 1441
Option 11C Compact Hospitality 10-slot Expansion Cabinet Package 58, 821, 1441
Option 11C Compact Hospitality Communications Expansion TN's 803, 1437
Option 11C Compact Hospitality Communications Expansion TNs' 58
Option 11C Compact Hospitality Communications Feature Set (S/W) 1621
Option 11C Compact Hospitality Communications Package 1618
Option 11C Compact Hospitality Digital Sets - Ash 1618
Option 11C Compact Hospitality Digital Sets - Grey 1618
Option 11C Compact Hospitality Guest Administration Console 1556
Option 11C Compact Inter-Office Communications Feature Set (S/W) 1621
Option 11C Compact InterOffice Communications Package 58, 800, 1437
Option 11C Compact InterOffice Communications Package - Additional 8 TN's 803, 1437
Option 11C Compact InterOffice Communications Package - Additional 8 TNs' 58
Option 11C Compact Network Message Communications Expansion TN's (8) 804, 1437
Option 11C Compact Network Message Communications Expansion TNs(8)' 58
Option 11C Compact Network Message Communications Package 1618
Option 11C Compact NMS Mail Reference Guide 60, 1493
Option 11C Compact Office Communications Feature Set (S/W) 1621
Option 11C Compact Office Communications Package 1618
Option 11C Compact Office Communications Package - Additional 8 TN's 803, 1437
Option 11C Compact Office Communications Package - Additional 8 TNs' 58
Option 11C Compact Planning and Installation Guide 60, 1495, 1668, 1669
Option 11C Compact Release 1.10 Programmed Software Daughterboard 1441, 1621
Option 11C Compact Release 2.0 Programmed Software Daughterboard 59, 823, 1441
Option 11C Compact Set Based Administration 60, 1157, 1491
Option 11C Compact Small Call Center Communications Package 1618
Option 11C Compact Software Delivery Card (PCMCIA) Release 1.00 59, 823, 1441
Option 11C Compact Software I/O Guides 1668
Option 11C Compact Software Input-Output Guide 60, 1495, 1669
Option 11C Compact Spares Package 61, 801, 1437
Option 11C Compact System Core Card 59, 819, 1440
Option 11C Compact Technical Reference Guide 60, 1493, 1668
Option 11C Compact to Option 11C Migration Package 59, 882, 1449
Option 11C Customer Documentation Library on CD-ROM 1617
Option 11C Customer Documentation Library on CD-ROM (Release 24) 1617
Option 11C Customer Documentation Library on CD-ROM, Release 25 64, 346, 911, 1451
Option 11C Distributor Technical Library Package 1616
Option 11C Distributor Technical Library Package, Release 25 63, 70, 346, 912, 1451
Option 11C Electronic Brandlining - Display Customization 63, 75, 891, 1450
Option 11C Enhanced Business Feature Set - Release 24B 1624
Option 11C Enhanced Business Feature Set - Release 25 28, 1451
Option 11C Enhanced Business Software Feature Upgrade 69, 74, 888, 1449
Option 11C Enhanced Business Software Package 62, 74, 885, 1449
Option 11C Enterprise Business Feature Set - Release 24B 1624
Option 11C Enterprise Business Feature Set - Release 25 28, 1451
Option 11C Enterprise Software Feature Upgrade 69, 74, 888, 1449
Option 11C Enterprise Software Package 62, 71, 74, 885, 1449
Option 11C General Business Feature Set - Release 24B 1624
Option 11C General Business Feature Set - Release 25

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

28, 1451
Option 11C General Business Software Feature Upgrade 69, 74, 888, 1449
Option 11C General Business Software Package 62, 74, 885, 1449
Option 11C Mini 19 Inch Rack Mount Kit 68, 198, 1451
Option 11C Mini 48 Port Digital Line Card 67, 178, 709, 1431
Option 11C Mini Chassis CPU Upgrade Package 64, 158, 868, 1448
Option 11C Mini Chassis Expander Cable Kit 68, 194, 1432
Option 11C Mini Chassis Expander Package 64, 158, 867, 1448
Option 11C Mini Chassis Package 62, 866, 1448
Option 11C Mini Chassis Package with SSC 62, 867, 1448
Option 11C Mini Customer Documentation Library on CD-ROM (Release 24) 1624
Option 11C Mini English Documentation Suite - Release 24 - Coil 1617
Option 11C Mini English Documentation Suite - Release 25 - Coil 26, 1618
Option 11C Mini Enhanced Business Software Package 62, 884, 1449
Option 11C Mini Enterprise Business Software Package 62, 884, 1449
Option 11C Mini Fiber Cable Management Kit 68, 198, 1451
Option 11C Mini Fiber Expansion Documentation Package 63, 198, 1451
Option 11C Mini General Business Software Package 62, 883, 1449
Option 11C Mini Horizontal Wall Mount Kit 68, 198, 1451
Option 11C Mini Main Chassis 68, 1432
Option 11C Mini Main Chassis Cable Kit 68, 194, 1432
Option 11C Mini NAS/VNS Software Package 62, 884, 1449
Option 11C Mini Power Cord Kit 66, 195, 1451
Option 11C Mini Release 24B Technical Reference Guide - English 1670
Option 11C Mini Release 25 English Documentation Package, Coil 345, 800, 1437
Option 11C Mini Shelf Table Mount Kit 68, 198, 1451
Option 11C Mini System Controller Card (Blank) 68, 179, 715, 1432
Option 11C Mini Vertical Wall Mount Kit 68, 198, 1451
Option 11C NAS/VNS Feature Set - Release 24B 1624
Option 11C NAS/VNS Feature Set - Release 25 28, 1451
Option 11C NAS/VNS Software Feature Upgrade 69, 74, 889, 1449
Option 11C NAS/VNS Software Package 62, 71, 74, 886, 1449
Option 11C Package #22 - DISA 63, 74, 890, 1450
Option 11C Programming Fee for PCMCIA Card 69, 182, 1157, 1490
Option 11C R24 English Documentation Package - Coil 63, 584, 1410
Option 11C RAN Connections for Release 23.18 63, 75, 891, 1450
Option 11C Release 22 1.5MB DTI/PRI Guide - English 1665
Option 11C Release 22 BRI Guide - English 1665
Option 11C Release 22 English Documentation Package - Binder 1599
Option 11C Release 22 English Documentation Package - Coil 1599
Option 11C Release 22 Technical Reference Guide - English 1665
Option 11C Release 22.08 Programmed PCMCIA Card 47, 68, 179, 1450
Option 11C Release 22.16 Programmed PCMCIA Card 47, 68, 179, 1450
Option 11C Release 22.46 Programmed PCMCIA Card 42, 47, 68, 179, 1450
Option 11C Release 23 1.5MB DTI/PRI Guide - English 1668
Option 11C Release 23 BRI Guide - English 1668
Option 11C Release 23 English Documentation Package - Binder 1599
Option 11C Release 23 English Documentation Package - Coil 1599
Option 11C Release 23 for CallPilot (Keycode only) 63, 891, 1450
Option 11C Release 23.18 Programmed PCMCIA Card 47, 68, 179, 1450
Option 11C Release 23.35 Programmed PCMCIA Card 47, 68, 179, 1450
Option 11C Release 23.55 Programmed PCMCIA Card 47, 68, 179, 896, 1450
Option 11C Release 24 English Documentation Package - Binder 345, 584, 1410
Option 11C Release 24 Technical Reference Guide - English 1670
Option 11C Release 24.24 Programmed PCMCIA Card 47, 68, 75, 179, 896, 1450
Option 11C Release 25 English Documentation Package, Binder 26, 64, 346, 911, 1451, 1624
Option 11C Release 25 English Documentation Package, Coil 26, 63, 346, 911, 1451, 1624
Option 11C Release 25 Programmed 40MB PCMCIA Card 179, 896, 1450

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option 11C Release 25 Programmed PCMCIA Card 47, 68, 75, 179, 896, 1451
Option 11C Release 25 Technical Reference Guide - English 63, 70, 349, 1497
Option 11C Single Cabinet AC 62, 868, 1448
Option 11C Single Cabinet DC 62, 869, 1448
Option 11C Single Cabinet Hardware Package AC 1623
Option 11C Single Cabinet Hardware Package DC 1623
Option 11C Software Daughterboard - Release 22.08D 68, 75, 893, 1450
Option 11C Software Daughterboard - Release 22.16 68, 75, 894, 1450
Option 11C Software Daughterboard - Release 22.46 68, 75, 894, 1450
Option 11C Software Daughterboard - Release 23.18 68, 75, 894, 1450
Option 11C Software Daughterboard - Release 23.35 68, 75, 894, 1450
Option 11C Software Daughterboard - Release 23.55 68, 75, 895, 1450
Option 11C Software Daughterboard - Release 24.24 68, 75, 179, 895, 1450
Option 11C Software Daughterboard - Release 25 68, 75, 179, 895, 1450
Option 11C Software Daughterboard - Release 25 Combo 33, 68, 75, 179, 896, 1450
Option 11C Software Rls 24C Upissue Keycode 33, 42, 69, 92, 893, 1450
Option 11C Software Upgrade Fee to Current 69, 74, 892, 1450
Option 11C Software Upissue Keycode 69, 92, 892, 1450
Option 11C System Core Card 67, 178, 709, 1431
Option 11C TMDI D-Channels Keycode 63, 74, 893, 1450
Option 11C TMDI Package (1.5MB DTI/PRI) 65, 161, 883, 1449
Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Binder) 1662, 1663, 1664
Option 11E - 1.5MB DTI/PRI Administration & Maintenance (Coil) 1661, 1663, 1664
Option 11E - 1.5MB DTI/PRI Administration and Maintenance (Binder) 64, 70, 347, 1489
Option 11E - Base Documentation Package (Binders) 1616
Option 11E - Base Documentation Package (Coil) 1616
Option 11E - BRI Administration & Maintenance (Binder) 1665
Option 11E - BRI Administration & Maintenance (Coil) 1663, 1665
Option 11E - BRI Administration and Maintenance (Binder) 64, 70, 347, 1489
Option 11E - CAP/Central Answering Position (Coil) 1661, 1662
Option 11E - Customer Reconfiguration Backup & Restore (Coil) 1661, 1662, 1665
Option 11E - Fault Clearing Guide (Coil) 1661, 1662
Option 11E - Installation Guide (Coil) 1661, 1663, 1664
Option 11E - ISDN BRI Administration & Maintenance (Binder) 1662, 1663
Option 11E - ISDN BRI Administration & Maintenance (Coil) 1661
Option 11E - Read Me First Handbook (Coil) 1661
Option 11E - Technical Reference Guide (Binder) 64, 70, 347, 1489, 1662, 1663
Option 11E - Technical Reference Guide (Coil) 1661, 1663
Option 11E - Upgrade Procedures (Coil) 1661, 1663, 1665
Option 11E - X11 Software Guide (Coil) 1662, 1663, 1665
Option 11E 1st Expansion Cabinet Package AC 70, 160, 465, 1379
Option 11E 1st Expansion Cabinet Package DC 70, 160, 466, 1379
Option 11E 2nd Expansion Cabinet Package AC 70, 160, 466, 1379
Option 11E 2nd Expansion Cabinet Package DC 70, 160, 467, 1379
Option 11E Dual Cabinet Core Upgrade Package 1711
Option 11E Main Cabinet 1427
Option 11E MISP Circuit Card 65, 178, 702, 1430
Option 11E Single Cabinet Core Upgrade Package 1711
Option 11E System Package AC/DC 1708
Option 11E System Package DC/DC 1708
Option 12 - Additional Agents 1541
Option 13 - DNIS Reporting 1541
Option 14 - Custom Format Selection 1541
Option 14 80 column 120 CPS Model 6182 (MVC01480) Desktop Printer 1528
Option 15 - Agent Activity Code Report 1541
Option 2 1529
Option 21 + IPE Module CE Spares Package 1561
Option 21 CE Spares Package 1561
Option 21 Module Upgrade Package AC 1715
Option 21 Module Upgrade Package DC 1715
Option 21 Module Upgrade/Expansion Package AC 1715
Option 21 Module Upgrade/Expansion Package DC 1715
Option 21A Module Upgrade Package AC 1716
Option 21A Pedestal/Top Cap Conversion Package 1561
Option 21E CE Spares Package 1562

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option 21E System Spares Package 1562
Option 3 1528
Option 4 1529
Option 4 - Staff Management Aid 1541
Option 4 & 6 1536
Option 4,5,30 & 31 1545
Option 5 - Enhanced Status Display 1541
Option 51 CE Spares Package 1561
Option 51 CPU Redundancy Assembly AC 1561
Option 51 CPU Redundancy Assembly DC 1561
Option 51 from A/M/S/MS/ST/21A/21/21E Upgrade Package AC 1716
Option 51 from A/M/S/MS/ST/21A/21/21E Upgrade Package DC 1716
Option 51 from Option 21/21E CardCage Upgrade Package AC 1716
Option 51 from Option 21/21E CardCage Upgrade Package DC 1716
Option 51 Module Upgrade Package AC 1715
Option 51 Module Upgrade Package DC 1715
Option 51 Module Upgrade/Expansion Package AC 1715
Option 51 Module Upgrade/Expansion Package DC 1715
Option 51 Multi-Disk Unit, Memory and ROM Upgrade Package 1717
Option 51/61 CE Spares Package 1561, 1562
Option 51/61 System Spares Package 1562
Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package AC 165, 1333, 1521
Option 51C from A/M/S/MS/ST/STE/21A/21/21E Upgrade Package DC 165, 1334, 1521
Option 51C from Option 21/21E Cardcage Upgrade Package AC 165, 1336, 1521
Option 51C from Option 21/21E Cardcage Upgrade Package DC 165, 1337, 1521
Option 51C from Option 51 Cardcage Upgrade Package AC/DC 165, 1338, 1521
Option 51C/61C/81 CE Spares Package 159, 342, 459, 1379
Option 51C/61C/81 CE Spares Package (24 MB CP) 1562
Option 51C/61C/81 System Spares Package 1563
Option 51C/61C/81 System Spares Package (24 MB CP) 1562
Option 51C/61C/81C System Spares Package 159, 342, 459, 1379
Option 6 - Expanded Trunk Routes 1541
Option 61 from A/M/S/MS/L/LE(23,96)/N/ST/STE/21A/21/21E Upgrade Package AC 1717
Option 61 from A/M/S/MS/L/LE(23,96)/N/ST/STE/21A/21/21E Upgrade Package DC 1717
Option 61 from Option 51 Upgrade Package AC 1717
Option 61 from Option 51 Upgrade Package DC 1717
Option 61 from RT Upgrade Package AC 1717
Option 61 from RT Upgrade Package DC 1717
Option 61 Module Upgrade Package AC 1715
Option 61 Module Upgrade Package DC 1715
Option 61 Module Upgrade/Expansion Package AC 1715
Option 61 Module Upgrade/Expansion Package DC 1715
Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/21A/21/21E Upgrade Package AC 165, 1325, 1521
Option 61C from A/M/S/MS/L/LE(23,96)/N/NT/ST/STE/RT/21A/21/21E Upgrade Package DC 165, 1327, 1521
Option 61C from Option 51 Upgrade Package AC 165, 1330, 1521
Option 61C from Option 51 Upgrade Package DC 165, 1331, 1521
Option 61C from Option 51C Upgrade Package AC 165, 1340, 1521
Option 61C from Option 51C Upgrade Package DC 165, 1341, 1521
Option 61C from Option 61 Cardcage Upgrade Package AC/DC 165, 1328, 1521
Option 61C System Package AC 158, 1281, 1519
Option 61C System Package DC 158, 1283, 1519
Option 7 1529
Option 7 - Additional VDT (8-16) 1541
Option 71 CE Spares Package 1561, 1562
Option 71 from L/LE(23,96)/N/VL/VLE/XL(24,97)/XN Upgrade Package AC 1717
Option 71 from L/LE(23,96)/N/VL/VLE/XL(24,97)/XN Upgrade Package DC 1717
Option 71 from NT/61 Upgrade Package AC 1717
Option 71 from NT/61 Upgrade Package DC 1717
Option 71 Module Upgrade Package AC 1715
Option 71 Module Upgrade Package DC 1715
Option 71 Module Upgrade/Expansion Package AC 1715
Option 71 Module Upgrade/Expansion Package DC 1716
Option 71 System Spares Package 1562
Option 8 - Multi-Customer 1541
Option 81 - Required for Option 81 97, 107, 118, 130, 138, 1206, 1512
Option 81 Cardcage Upgrade Parts Kit 1576
Option 81 Database Transfer Cable 1623
Option 81 from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/61/71 Core and Network Upgrade Package AC 1717
Option 81 from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/61/71 Core and Network Upgrade Package DC 1717
Option 81 from Option 61C Upgrade Package AC

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1717, 1718
Option 81 from Option 61C Upgrade Package DC 1718
Option 81 from Option 71 Card Cage Upgrade Package AC/DC 1717
Option 81 from XN/XT/71 Core Upgrade Package AC (Dual Column) 1717
Option 81 from XN/XT/71 Core Upgrade Package AC (Single Column) 1717
Option 81 from XN/XT/71 Core Upgrade Package DC (Dual Column) 1717
Option 81 from XN/XT/71 Core Upgrade Package DC (Single Column) 1717
Option 81 Network Cable Package, 2nd Group 159, 444, 1377
Option 81 Network Cable Package, 3rd Group 159, 445, 1378
Option 81 Network Cable Package, 4th Group 159, 445, 1378
Option 81 Network Cable Package, 5th Group 159, 445, 1378
Option 81/81C Network Group Assembly AC 159, 443, 1377
Option 81/81C Network Group Assembly DC 159, 444, 1377
Option 81C - Required for Option 81C 97, 107, 118, 130, 138, 1207, 1512
Option 81C (CP PII) Power Supply Spares Package AC 161, 752, 1434
Option 81C (CP PII) Power Supply Spares Package DC 161, 753, 1434
Option 81C (CP PII) Reference Library, Release 25 344, 556, 1403
Option 81C (CP PII) Systems Spares Package 161, 752, 1434
Option 81C 68060 Enhanced Call Process New System Pkg AC (IGS Network Included) 158, 897, 1451
Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Cage Upgrade Package AC 164, 733, 1434
Option 81C Call Processor PII from 71/81/81C (NT8D34, NT6D60, NT5D21) Card Upgrade Package DC 164, 735, 1434
Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package AC 164, 747, 1434
Option 81C Call Processor PII from L/LE/N/VL/VLE/XL/NT Module Upgrade Package DC 164, 750, 1434
Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/51C or 61C (NT9D11, NT5D21) Upgrade Package AC 164, 741, 1434
Option 81C Call Processor PII from Option 51 or 61 (NT6D39)/51C or 61C (NT9D11, NT5D21) Upgrade Package DC 164, 744, 1434
Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package AC 727, 1434, 1617
Option 81C Call Processor PII from XN/XT/71 (QCA55/108 Cabinets) Module Upgrade Package DC 164, 730, 1434, 1617
Option 81C Call Processor PII New System DC (IGS Network Included) 158, 909, 1451
Option 81C Call Processor PII New System Package AC (Fiber Network Fabric Included) 158, 901, 1451
Option 81C Call Processor PII New System Package AC (IGS Network Included) 158, 906, 1451
Option 81C Call Processor PII New System Package DC (Fiber Network Fabric Included) 158, 904, 1451
Option 81C Core Cabinet Cable Kit, Group 0 195, 828, 1443
Option 81C Core/Network Group Kit 160, 472, 1379
Option 81C Fiber Core Network Group 0 Kit 161, 755, 1435
Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/71 Core and Network Upgrade Package AC 165, 1343, 1521
Option 81C from L/LE(23,96)/N/VL/VLE/XL(24,97)/NT/XN/XT/71 Core and Network Upgrade Package DC 165, 1346, 1521
Option 81C from Option 61 (Modular) Upgrade Package AC 165, 1521
Option 81C from Option 61 (modular) Upgrade Package DC 165, 1521
Option 81C from Option 61C (NT5D21) Upgrade AC 164, 737, 1434
Option 81C from Option 61C (NT5D21) Upgrade DC 164, 739, 1434
Option 81C from Option 61C Upgrade (Package #1) AC 165, 1361, 1521
Option 81C from Option 61C Upgrade (Package #1) DC 165, 1521
Option 81C from Option 61C Upgrade (Package #2) AC 165, 1521
Option 81C from Option 61C Upgrade (Package #2) DC 165, 1521
Option 81C from Option 61C Upgrade (Package #3) AC 165, 1521
Option 81C from Option 61C Upgrade (Package #3) DC 165, 1521
Option 81C from Option 71 Card Cage Upgrade Package AC/DC 165, 1354, 1521
Option 81C from Option 81 Card Cage Upgrade Package AC/DC 165, 1521
Option 81C from XN/XT/71 Core Upgrade Package AC (Dual Column) 165, 1349, 1521

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option 81C from XN/XT/71 Core Upgrade Package AC (Single Column) 165, 1356, 1521
Option 81C from XN/XT/71 Core Upgrade Package DC (Dual Column) 165, 1352, 1521
Option 81C from XN/XT/71 Core Upgrade Package DC (Single Column) 165, 1359, 1521
Option 81C Network Cable Package, 2nd Group 160, 471, 1379
Option 81C Network Cable Package, 3rd Group 160, 471, 1379
Option 81C Network Cable Package, 4th Group 160, 471, 1379
Option 81C Network Cable Package, 5th Group 160, 472, 1379
Option 81C New System Package DC 158, 899, 1451
Option 9 - Enhanced Load Management 1541
Option Group 1, Advanced Station Features (A, M, MS) 1534
Option Group 1, Advanced Station Features (L, LE, N, NT, RT) 1536
Option Group 1, Advanced Station Features (S) 1534
Option Group 1, Advanced Station Features (ST) 1689
Option Group 1, Advanced Station Features (VL, VLE, XL, XN, XT) 1536
Option Group 10 1537, 1542
Option Group 100, 81 and 99, Room Status (RT) 1692
Option Group 100, 81 and 99, Room Status (ST) 1690
Option Group 100, 81 and 99, Room Status (XT) 1692
Option Group 100, 81, 99, Room Status (N) 1688
Option Group 100, 81, 99, Room Status (NT) 1691
Option Group 100, 81, 99, Room Status (S, MS) 1687
Option Group 100, 81, 99, Room Status (XN) 1689
Option Group 101, 81 and 99, Message Registration (RT) 1693
Option Group 101, 81 and 99, Message Registration (ST) 1690
Option Group 101, 81 and 99, Message Registration (XT) 1692
Option Group 101, 81, 99, Message Registration (N) 1688
Option Group 101, 81, 99, Message Registration (NT) 1691
Option Group 101, 81, 99, Message Registration (S, MS) 1687
Option Group 101, 81, 99, Message Registration (XN) 1689
Option Group 102, 81 and 99, Automatic Wakeup (RT) 1693
Option Group 102, 81 and 99, Automatic Wakeup (XT) 1692
Option Group 102, 81, 99, Automatic Wakeup (N) 1688
Option Group 102, 81, 99, Automatic Wakeup (NT) 1691
Option Group 102, 81, 99, Automatic Wakeup (S, MS) 1687
Option Group 102, 81, 99, Automatic Wakeup (XN) 1689
Option Group 103, 81, 99, Property Management System Interface (N) 1688
Option Group 103, 81, 99, Property Management System Interface (NT) 1691
Option Group 103, 81, 99, Property Management System Interface (RT) 1693
Option Group 103, 81, 99, Property Management System Interface (S, MS) 1687
Option Group 103, 81, 99, Property Management System Interface (ST) 1690
Option Group 103, 81, 99, Property Management System Interface (XN) 1689
Option Group 103, 81, 99, Property Management System Interface (XT) 1692
Option Group 105, Line Load Control (N) 1688
Option Group 105, Line Load Control (RT) 1693
Option Group 105, Line Load Control (S, MS) 1687
Option Group 105, Line Load Control (ST) 1690
Option Group 105, Line Load Control (XN) 1689
Option Group 105, Line Load Control (XT) 1692
Option Group 107, Malicious Call Trace (N) 1688
Option Group 107, Malicious Call Trace (NT) 1691
Option Group 107, Malicious Call Trace (RT) 1693
Option Group 107, Malicious Call Trace (S, MS) 1687
Option Group 107, Malicious Call Trace (ST) 1690
Option Group 107, Malicious Call Trace (XN) 1689
Option Group 107, Malicious Call Trace (XT) 1692
Option Group 108, Internal CDR (N) 1688
Option Group 108, Internal CDR (NT) 1691
Option Group 108, Internal CDR (RT) 1693
Option Group 108, Internal CDR (S, MS) 1687
Option Group 108, Internal CDR (ST) 1690
Option Group 108, Internal CDR (XN) 1689
Option Group 108, Internal CDR (XT) 1692
Option Group 109, Auxiliary Processor Link (N) 1688
Option Group 109, Auxiliary Processor Link (NT) 1691
Option Group 109, Auxiliary Processor Link (RT) 1693
Option Group 109, Auxiliary Processor Link (S, MS) 1687
Option Group 109, Auxiliary Processor Link (ST) 1690
Option Group 109, Auxiliary Processor Link (XN) 1689
Option Group 109, Auxiliary Processor Link (XT) 1692
Option Group 110, Trunk Verification from a Station (LE) 1687
Option Group 110, Trunk Verification From a Station (N) 1688
Option Group 110, Trunk Verification From a Station (NT) 1691
Option Group 110, Trunk Verification From a Station (RT) 1693

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option Group 110, Trunk Verification from a Station (S, MS) 1687
Option Group 110, Trunk Verification From a Station (ST) 1690
Option Group 110, Trunk Verification from a Station (VLE) 1687
Option Group 110, Trunk Verification from a Station (XL) 1687
Option Group 110, Trunk Verification From a Station (XN) 1689
Option Group 110, Trunk Verification From a Station (XT) 1692
Option Group 111, ACD Timed Overflow (N) 1688
Option Group 111, ACD Timed Overflow (NT) 1691
Option Group 111, ACD Timed Overflow (RT) 1693
Option Group 111, ACD Timed Overflow (S, MS) 1687
Option Group 111, ACD Timed Overflow (ST) 1690
Option Group 111, ACD Timed Overflow (XN) 1689
Option Group 111, ACD Timed Overflow (XT) 1692
Option Group 113, Incoming DID Digit Conversion (N) 1688
Option Group 113, Incoming DID Digit Conversion (NT) 1691
Option Group 113, Incoming DID Digit Conversion (RT) 1693
Option Group 113, Incoming DID Digit Conversion (S, MS) 1687
Option Group 113, Incoming DID Digit Conversion (ST) 1690
Option Group 113, Incoming DID Digit Conversion (XN) 1689
Option Group 113, Incoming DID Digit Conversion (XT) 1692
Option Group 114 and 155, ACD-D/MAX Report Enhancements (NT) 1691
Option Group 114 and 155, ACD-D/MAX Report Enhancements (RT) 1693
Option Group 114 and 155, ACD-D/MAX Report Enhancements (ST) 1690
Option Group 114 and 155, ACD-D/MAX Report Enhancements (XN) 1689
Option Group 114 and 155, ACD-D/MAX Report Enhancements (XT) 1692
Option Group 114, 155, ACD-D/MAX Report Enhancements (N) 1688
Option Group 115, Directed Call Pickup (N) 1688
Option Group 115, Directed Call Pickup (NT) 1691
Option Group 115, Directed Call Pickup (RT) 1693
Option Group 115, Directed Call Pickup (S, MS) 1688
Option Group 115, Directed Call Pickup (ST) 1690
Option Group 115, Directed Call Pickup (XN) 1689
Option Group 115, Directed Call Pickup (XT) 1692
Option Group 116, ACD Priority Agents (N) 1688
Option Group 116, ACD Priority Agents (NT) 1691
Option Group 116, ACD Priority Agents (RT) 1693
Option Group 116, ACD Priority Agents (S, MS) 1688
Option Group 116, ACD Priority Agents (ST) 1690
Option Group 116, ACD Priority Agents (XN) 1689
Option Group 116, ACD Priority Agents (XT) 1692
Option Group 117, Call By Call Service (N) 1689
Option Group 117, Call By Call Service (NT) 1691
Option Group 117, Call By Call Service (RT) 1693
Option Group 117, Call By Call Service (ST) 1690
Option Group 117, Call By Call Service (XN) 1689
Option Group 117, Call By Call Service (XT) 1692
Option Group 118, Calling Line ID in CDR (N) 1689
Option Group 118, Calling Line ID in CDR (NT) 1691
Option Group 118, Calling Line ID in CDR (RT) 1693
Option Group 118, Calling Line ID in CDR (XN) 1689
Option Group 118, Calling Line ID in CDR (XT) 1692
Option Group 118. Calling Line ID in CDR (ST) 1690
Option Group 119, Enhanced Music (N) 1688
Option Group 119, Enhanced Music (NT) 1691
Option Group 119, Enhanced Music (RT) 1693
Option Group 119, Enhanced Music (S, MS) 1688
Option Group 119, Enhanced Music (ST) 1690
Option Group 119, Enhanced Music (XN) 1689
Option Group 119, Enhanced Music (XT) 1692
Option Group 12, Automatic Number Identification (ANI) (A, M, S, MS, ST) 1543
Option Group 12, Automatic Number Identification (ANI) (L, LE, N, NT, RT) 1536
Option Group 12, Automatic Number Identification (ANI) (VL, VLE, XL, XN, XT) 1537
Option Group 13, Route Selection for ANI (A, M, S, MS, ST) 1543
Option Group 13, Route Selection for ANI (L, LE, N, NT, RT) 1539
Option Group 13, Route Selection for ANI (VL, VLE, XL, XN, XT) 1539
Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (LE, N, NT, RT) 1534
Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (M, MS) 1536
Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (S, ST) 1531
Option Group 14, 28, 32, 57 & 61, Basic Automatic Route Selection (BARS) (VLE, XL, XN, XT) 1534
Option Group 14, 28, 32, 58 & 61, NARS (LE, N, NT, RT) 1544
Option Group 14, 28, 32, 58 & 61, NARS (MS, M) 1544
Option Group 14, 28, 32, 58 & 61, NARS (S, ST) 1532
Option Group 14, 28, 32, 58 & 61, NARS (VLE, XL, XN, XT) 1544
Option Group 14, 28, 32, 59 & 61, Coordinated Dialing

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Plan (LE, N, NT, RT) 1544
Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (MS, M) 1544
Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (S, ST) 1532
Option Group 14, 28, 32, 59 & 61, Coordinated Dialing Plan (VLE, XL, XN, XT) 1544
Option Group 14, Automatic Route Selection (ARS) (A, M, S, MS) 1535
Option Group 14, Automatic Route Selection (ARS) (L, LE) 1536
Option Group 14, Automatic Route Selection (ARS) (VL, VLE, XL) 1536
Option Group 145 and 146, Primary Rate Access (NT) 1691
Option Group 145 and 146, Primary Rate Access (RT) 1693
Option Group 145 and 146, Primary Rate Access (ST) 1690
Option Group 145 and 146, Primary Rate Access (XN) 1689
Option Group 145 and 146, Primary Rate Access (XT) 1692
Option Group 145 and 147, ISDN Signaling Link (NT) 1691
Option Group 145 and 147, ISDN Signaling Link (RT) 1693
Option Group 145 and 147, ISDN Signaling Link (ST) 1690
Option Group 145 and 147, ISDN Signaling Link (XN) 1689
Option Group 145 and 147, ISDN Signaling Link (XT) 1692
Option Group 145, 146, Primary Rate Access (N) 1688
Option Group 147, 145, ISDN Signaling Link (N) 1688
Option Group 148, Advance ISDN Features (N) 1688
Option Group 148, Advance ISDN Features (NT) 1691
Option Group 148, Advance ISDN Features (RT) 1693
Option Group 148, Advance ISDN Features (ST) 1690
Option Group 148, Advance ISDN Features (XT) 1692
Option Group 148, Advanced ISDN Features (XN) 1689
Option Group 149, Inter-Exchange Carrier (N) 1688
Option Group 149, Inter-exchange Carrier (NT) 1691
Option Group 149, Inter-exchange Carrier (RT) 1693
Option Group 149, Inter-exchange carrier (ST) 1690
Option Group 149, Inter-exchange Carrier (XN) 1689
Option Group 149, Inter-exchange Carrier (XT) 1692
Option Group 15, Remote Peripheral Equipment (RPE) (A, M, MS, ST) 1543
Option Group 15, Remote Peripheral Equipment (RPE) (L, LE, N, NT, RT) 1536
Option Group 15, Remote Peripheral Equipment (RPE) (VL, VLE, XL, XN, XT) 1537
Option Group 150, Directory Number Expansion (MS) 1688
Option Group 150, Directory Number Expansion (N) 1688
Option Group 150, Directory Number Expansion (NT) 1691
Option Group 150, Directory Number Expansion (RT) 1693
Option Group 150, Directory Number Expansion (ST) 1690
Option Group 150, Directory Number Expansion (XN) 1689
Option Group 150, Directory Number Expansion (XT) 1692
Option Group 151, Expanded Call Detail Recording (MS) 1688
Option Group 151, Expanded Call Detail Recording (N) 1688
Option Group 151, Expanded Call Detail Recording (NT) 1691
Option Group 151, Expanded Call Detail Recording (RT) 1693
Option Group 151, Expanded Call Detail Recording (ST) 1690
Option Group 151, Expanded Call Detail Recording (XN) 1689
Option Group 151, Expanded Call Detail Recording (XT) 1692
Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85 and 109, Meridian Link ISDN A/P (NT) 1691
Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (RT) 1693
Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (XN) 1689
Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, 109, Meridian Link ISDN A/P (XT) 1692
Option Group 153, 19, 35, 40, 41, 45, 75, 77, 85, and 109, Meridian Link ISDN A/P (ST) 1690
Option Group 157, Centrex Switch Hook flash (NT) 1691
Option Group 157, Centrex Switch Hook Flash (RT) 1693
Option Group 157, Centrex Switch Hook Flash (ST) 1690
Option Group 157, Centrex Switch Hook Flash (XN) 1689
Option Group 157, Centrex Switch Hook Flash (XT) 1692
Option Group 17 1539, 1543
Option Group 170, Modular Meridian Terminals (NT) 1691
Option Group 170, Modular Meridian Terminals (RT) 1693
Option Group 170, Modular Meridian Terminals (ST)

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1690
Option Group 170, Modular Meridian Terminals (XN) 1689
Option Group 170, Modular Meridian Terminals (XT) 1692
Option Group 18, 2500 Set Features (A, MS, M) 1539
Option Group 18, 2500 Set Features (Call Forward, Hold, Speed Call) (LE) 1534
Option Group 18, 2500 Set Features (Call Forward, Hold, Speed Call) (VLE) 1534
Option Group 18, 2500 Set Features (L, LE, N, NT, RT) 1540
Option Group 18, 2500 Set Features (S, ST) 1534
Option Group 18, 2500 Set Features (VL, VLE, XL, XN, XT) 1539
Option Group 19 1539
Option Group 19, 50 & 51, ACD Link Software (LE) 1687
Option Group 19, 50 & 51, ACD Link Software (N) 1688
Option Group 19, 50 & 51, ACD Link Software (NT) 1691
Option Group 19, 50 & 51, ACD Link Software (RT) 1693
Option Group 19, 50 & 51, ACD Link Software (S, M, MS) 1688
Option Group 19, 50 & 51, ACD Link Software (ST) 1690
Option Group 19, 50 & 51, ACD Link Software (XL) 1687
Option Group 19, 50 & 51, ACD Link Software (XN) 1689
Option Group 19, 50 & 51, ACD Link Software (XT) 1692
Option Group 19, 50, 51, ACD Link Software (VLE) 1687
Option Group 2, Multi-Customer (A, M, S, MS, ST) 1534
Option Group 2, Multi-Customer (L, LE, N, NT, RT) 1536
Option Group 2, Multi-Customer (VLE, VL, XL, XN, XT) 1536
Option Group 20, Office Data Administration System (ODAS) (A, M, S, MS, ST) 1540
Option Group 20, Office Data Administration System (ODAS) (L, LE, N, NT, RT) 1540
Option Group 20, Office Data Administration System (ODAS) (VL, VLE, XL, XN, XT) 1540
Option Group 21, Dial Intercom (A, S, MS, M, ST) 1543
Option Group 21, Dial Intercom (L, LE, N, NT, RT) 1539
Option Group 21, Dial Intercom (VL, VLE, XN, XT, XL) 1539
Option Group 22, Direct Inward System Access (DISA) (A, MS, M) 1535
Option Group 22, Direct Inward System Access (DISA) (L, LE, N, NT, RT) 1539
Option Group 22, Direct Inward System Access (DISA) (S, ST) 1531
Option Group 22, Direct Inward System Access (DISA) (VL, XN, XT, VLE, XL) 1539
Option Group 23 & 24, CDR Charge Account Code (A, S, MS, M, ST) 1543
Option Group 23 & 24, CDR Charge Account Code (L, LE, N, NT, RT) 1540
Option Group 23 & 24, CDR Charge Account Code (VL, VLE, XN, XT, XL) 1540
Option Group 24 & 25, Authorization Code (A, S, MS, M, ST) 1535
Option Group 24 & 25, Authorization Code (L, LE, N, NT, RT) 1539
Option Group 24 & 25, Authorization Code (VL, VLE, XN, XT, XL) 1539
Option Group 24, 25 & 63, Network Authorization Code (LE, N, NT, RT) 1544
Option Group 24, 25 & 63, Network Authorization Code (MS, M) 1544
Option Group 24, 25 & 63, Network Authorization Code (S, ST) 1532
Option Group 24, 25 & 63, Network Authorization Code (VLE, XL, XN, XT) 1544
Option Group 26, Centralized Attendant Service (CAS Main) (A, S, MS, M, ST) 1543
Option Group 26, Centralized Attendant Service (CAS Main) (L, LE, N, NT, RT) 1539
Option Group 26, Centralized Attendant Service (CAS Main) (VL, VLE, XN, XT, XL) 1539
Option Group 27, Centralized Attendant Service (CAS Remote) (A, S, MS, M, ST) 1543
Option Group 27, Centralized Attendant Service (CAS Remote) (L, LE, N, NT, RT) 1540
Option Group 27, Centralized Attendant Service (CAS Remote) (VL, VLE, XN, XT, XL) 1540
Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (A, S, MS, M) 1535
Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (L, LE) 1539
Option Group 28 & 29, ARS Priority Queuing/ARS Traffic (VL, VLE, XL) 1539
Option Group 28 & 62, Off-Hook Queuing (LE, N, NT, RT) 1544
Option Group 28 & 62, Off-Hook Queuing (MS, M) 1544
Option Group 28 & 62, Off-Hook Queuing (S, ST) 1532
Option Group 28 & 62, Off-Hook Queuing (VLE, XL, XN, XT) 1544

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (LE, N, NT, RT) 1534
Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (S, ST, MS, M) 1536
Option Group 29, 32 & 60, ARS Traffic/ARS Priority Queuing (VLE, XL, XN, XT) 1534
Option Group 3 Automatic Identification of Outward Dial (AIOD) 1536
Option Group 30, PMS Interface (HIS) (LE) 1528
Option Group 30, PMS Interface (HIS) (S, MS) 1528
Option Group 30, PMS Interface (HIS) (VLE, XL) 1528
Option Group 31, Message Registration (A) 1532
Option Group 31, Message Registration (LE) 1529, 1533
Option Group 31, Message Registration (M) 1531
Option Group 31, Message Registration (S, MS, M) 1529
Option Group 31, Message Registration (VLE) 1533
Option Group 31, Message Registration (VLE, XL) 1529
Option Group 32, 5-Digit Dialing (LE) 1529
Option Group 32, 5-Digit Dialing (S, MS, M) 1529
Option Group 32, 5-Digit Dialing (VLE, XL) 1529
Option Group 32, Message Waiting (A) 1543
Option Group 32, Message Waiting (LE) 1539
Option Group 32, Message Waiting (VLE) 1539
Option Group 33, Call Park (LE) 1529
Option Group 33, Call Park (LE, N, NT, RT) 1531
Option Group 33, Call Park (MS, M) 1531
Option Group 33, Call Park (S, MS, M) 1529
Option Group 33, Call Park (S, ST) 1531
Option Group 33, Call Park (VLE, XL) 1529
Option Group 33, Call Park (VLE, XL, XN, XT) 1531
Option Group 33, System Park (A) 1532
Option Group 33, System Park (LE) 1533
Option Group 33, System Park (M) 1531
Option Group 33, System Park (VLE) 1533
Option Group 34, Supervisory Console (LE) 1529
Option Group 34, Supervisory Console (S, MS, M) 1529
Option Group 34, Supervisory Console (VLE, XL) 1530
Option Group 34, System Speed Call (LE, N, NT, RT) 1531
Option Group 34, System Speed Call (MS. M) 1531
Option Group 34, System Speed Call (S, ST) 1531
Option Group 34, System Speed Call (VLE, XL, XN, XT) 1531
Option Group 35 & 109, IMS Software (LE, N, NT, RT) 1530
Option Group 35 & 109, IMS Software (S, ST, MS, M) 1530
Option Group 35 & 109, IMS Software (VLE, XL, XN, XT) 1530
Option Group 35, Callers Name Display (LE) 1529
Option Group 35, Callers Name Display (S, MS) 1529
Option Group 35, Callers Name Display (VLE, XL) 1529
Option Group 36, Recorded Overflow Announcement (LE) 1530
Option Group 36, Recorded Overflow Announcement (LE, N, NT, RT) 1531
Option Group 36, Recorded Overflow Announcement (S, MS, M) 1530
Option Group 36, Recorded Overflow Announcement (S, ST, MS, M) 1531
Option Group 36, Recorded Overflow Announcement (VLE, XL) 1530
Option Group 36, Recorded Overflow Announcement (VLE, XL, XN, XT) 1531
Option Group 37 & 32, ESN Signaling (LE, N, NT, RT) 1545
Option Group 37 & 32, ESN Signaling (MS, M) 1545
Option Group 37 & 32, ESN Signaling (S, ST) 1532
Option Group 37 & 32, ESN Signaling (VLE, XL, XN, XT) 1545
Option Group 37, Automatic Wake-Up (A) 1533
Option Group 37, Automatic Wake-Up (LE) 1533
Option Group 37, Automatic Wake-Up (M, S, MS) 1531
Option Group 37, Automatic Wake-Up (VLE, XL) 1533
Option Group 38, ESN Queuing (CBQCM, CCBQ) (LE, N, NT, RT) 1545
Option Group 38, ESN Queuing (CBQCM, CCBQ) (MS, M) 1545
Option Group 38, ESN Queuing (CBQCM, CCBQ) (S, ST) 1532
Option Group 38, ESN Queuing (CBQCM, CCBQ) (VLE, XL, XN, XT) 1545
Option Group 38, Room Status (A) 1533
Option Group 38, Room Status (LE) 1533
Option Group 38, Room Status (M, S, MS) 1531
Option Group 38, Room Status (VLE, XL) 1534
Option Group 39, History File (M) 1531
Option Group 39, Network Speed Call (LE, N, NT, RT) 1545
Option Group 39, Network Speed Call (MS, M) 1545
Option Group 39, Network Speed Call (S, ST) 1532
Option Group 39, Network Speed Call (VLE, XL, XN, XT) 1545
Option Group 4 & 30 1544, 1545
Option Group 4 & 31 1535
Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (A, M, MS) 1535
Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (L, LE, N, NT, RT) 1537

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (S, ST) 1531
Option Group 4 & 5, Call Detail Recording (CDR) - List (TTY) (VLE, VL, XL, XN, XT) 1537
Option Group 4 & 6 1535, 1536
Option Group 4, 5 & 30 1532
Option Group 4, 5 & 31 1532
Option Group 4, 5 & 6 1535, 1537
Option Group 4, 5, 6 & 30 1532
Option Group 4, 6 & 30 1532
Option Group 4,5 & 30 1545
Option Group 4,5,6 & 30 1545
Option Group 4,6 & 30 1545
Option Group 40 & 46, Message Center (A, S, MS, M, ST) 1543
Option Group 40 & 46, Message Center (L, LE, N, NT, RT) 1540
Option Group 40 & 46, Message Center (VL, VLE, XN, XT, XL) 1540
Option Group 41 and 42, Automatic Call Distribution (ACD) Package C1 (M,MS) 1534
Option Group 41 and 44, Automatic Call Distribution (ACD) Package B (M, MS) 1534
Option Group 41, 44, Automatic Call Distribution (ACD) Package B (S,ST) 1531
Option Group 42, Automatic Call Distribution (ACD) Package C1 (LE, N, RT, NT) 1540
Option Group 42, Automatic Call Distribution (ACD) Package C1 (S,ST) 1531
Option Group 42, Automatic Call Distribution (ACD) Package C1 (VLE, XL, XN, XT) 1540
Option Group 43, Automatic Call Distribution (ACD) Package C2 (LE, N, RT, NT) 1540
Option Group 43, Automatic Call Distribution (ACD) Package C2 (M,MS) 1534
Option Group 43, Automatic Call Distribution (ACD) Package C2 (S,ST) 1531
Option Group 43, Automatic Call Distribution (ACD) Package C2 (VLE, XL, XN, XT) 1540
Option Group 44, Music Package (LE, N, NT, RT) 1540
Option Group 44, Music Package (S, MS, M, ST) 1534
Option Group 44, Music Package (VLE, XL, XN, XT) 1540
Option Group 46, Basic Message Center (LE, N, NT, RT) 1534
Option Group 46, Basic Message Center (S, MS, M, ST) 1534
Option Group 46, Basic Message Center (VLE, XL, XN, XT) 1534
Option Group 47, Automatic Handsfree Answerback (A, S, MS, M, ST) 1539
Option Group 47, Automatic Handsfree Answerback (L, LE, N, NT, RT) 1539
Option Group 47, Automatic Handsfree Answerback (VL, VLE, XN, XT, XL) 1540
Option Group 48, Group Call (A, S, MS, M, ST) 1539
Option Group 48, Group Call (L, LE, N, NT, RT) 1539
Option Group 48, Group Call (VL, VLE, XN, XT, XL) 1540
Option Group 49 & 32, New Flexible Code Restriction Package (LE, N, NT, RT) 1532
Option Group 49 & 32, New Flexible Code Restriction Package (S, ST, MS, M) 1531
Option Group 49 & 32, New Flexible Code Restriction Package (VLE, XL, XN, XT) 1532
Option Group 49, New Flexible Code Restriction (LE) 1530
Option Group 49, New Flexible Code Restriction (S, MS, N) 1530
Option Group 49, New Flexible Code Restriction (VLE, XL) 1530
Option Group 52, CDR Forced Charge Account (LE, N, NT, RT) 1540
Option Group 52, CDR Forced Charge Account (S, MS, M, ST) 1534
Option Group 52, CDR Forced Charge Account (VLE, XL, XN, XT) 1540
Option Group 53, Automatic Set Relocation (LE, N, NT, RT) 1535
Option Group 53, Automatic Set Relocation (S, ST, M, MS) 1535
Option Group 53, Automatic Set Relocation (VLE, XL, XN, XT) 1535
Option Group 53, Controlled Class of Service (LE) 1530
Option Group 53, Controlled Class of Service (S, MS, M) 1530
Option Group 53, Controlled Class of Service (VLE, XL) 1530
Option Group 54, Attendant Administration (LE, N, NT, RT) 1535
Option Group 54, Attendant Administration (S, ST, MS, M) 1535
Option Group 54, Attendant Administration (VLE, XL, XN, XT) 1536
Option Group 55, History File (N, NT, RT, XN, XT, LE, VLE, XL) 1536
Option Group 55, History File (S, MS, M, ST) 1543
Option Group 56, Attendant Overflow Position (LE, N, NT, RT) 1536
Option Group 56, Attendant Overflow Position (S, ST, MS, M) 1536
Option Group 56, Attendant Overflow Position (VLE, XL, XN, XT) 1536
Option Group 56, Flexible Hotline (LE) 1530
Option Group 56, Flexible Hotline (S, MS, M) 1530
Option Group 56, Flexible Hotline (VLE, XL) 1530

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option Group 64, Stored Number Redial (LE, N, NT, RT) 1533
Option Group 64, Stored Number Redial (S, ST, MS, M) 1533
Option Group 64, Stored Number Redial (VLE, XL, XN, XT) 1533
Option Group 65 & 84, Automatic Trunk Maintenance (LE, N, NT, RT) 1530
Option Group 65 & 84, Automatic Trunk Maintenance (S, ST, MS, M) 1530
Option Group 65 & 84, Automatic Trunk Maintenance (VLE, XL, XN, XT) 1530
Option Group 67, Network Transfer (LE, N, NT, RT) 1545
Option Group 67, Network Transfer (MS, M) 1545
Option Group 67, Network Transfer (S, ST) 1532
Option Group 67, Network Transfer (VLE, XL, XN, XT) 1545
Option Group 7, 17, 19, 40, 41, 42, 43, 44, 45, 50 & 51 1532
Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (L, LE, N, NT, RT) 1539
Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (S, ST) 1531
Option Group 7, 17, 40 & 45, Automatic Call Distribution (ACD) Package A (VL, VLE, XN, XT, XL) 1539
Option Group 7, 17, 40, & 45, Automatic Call Distribution (ACD) Package A (A, MS, M) 1535
Option Group 7, 17, 40, 41, 44 and 45, Automatic Call Distribution Package B (LE, N, RT, NT) 1540
Option Group 7, 17, 40, 41, 44 and 45, Automatic Call Distribution Package B (VLE, XL, XN, XT) 1540
Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (A, M, MS) 1541
Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (L, LE, N, NT, RT) 1541
Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (S, ST) 1534
Option Group 7, 8, 10, 17 & 19, Feature Package I (one) (VL, VLE, XL, XN, XT) 1541
Option Group 7, Recorded Announcement (A, M) 1542
Option Group 7, Recorded Announcement (L, LE) 1537
Option Group 7, Recorded Announcement (VL, VLE, XL) 1537
Option Group 7,17,19,40,41,42,43,44,45,50 & 51 1532
Option Group 70, Flexible Hotline (LE, N, NT, RT) 1541
Option Group 70, Flexible Hotline (S, ST, MS, M) 1541
Option Group 70, Flexible Hotline (VLE, XL, XN, XT) 1541
Option Group 71, Deluxe Hold (LE, N, NT, RT) 1542
Option Group 71, Deluxe Hold (S, ST, MS, M) 1542
Option Group 71, Deluxe Hold (VLE, XL, XN, XT) 1542
Option Group 72, Automatic Line Selection (LE, N, NT, RT) 1542
Option Group 72, Automatic Line Selection (S, ST, MS, M) 1542
Option Group 72, Automatic Line Selection (VLE, XL, XN, XT) 1542
Option Group 73, 500 Set Features (LE, N, NT, RT) 1542
Option Group 73, 500 Set Features (S, ST, MS, M) 1542
Option Group 73, 500 Set Features (VLE, XL, XN, XT) 1542
Option Group 74, Distinctive Ringing (LE, N, NT, RT) 1542
Option Group 74, Distinctive Ringing (MS, M) 1542
Option Group 74, Distinctive Ringing (S, ST) 1531
Option Group 74, Distinctive Ringing (VLE, XL, XN, XT) 1542
Option Group 75, PBX Interface (LE, N, NT, RT) 1529
Option Group 75, PBX Interface (MS, ST) 1529
Option Group 75, PBX Interface (VLE, XL, XN, XT) 1529
Option Group 76, Departmental LDN (LE, N, NT, RT) 1526
Option Group 76, Departmental LDN (S, ST, MS, M) 1526
Option Group 76, Departmental LDN (VLE, XL, XN, XT) 1526
Option Group 77 & 85, Command and Status Link (CSL) (LE, N, NT, RT) 1691
Option Group 77 & 85, Command and Status Link (CSL) (ST, MS) 1690
Option Group 77 & 85, Command and Status Link (CSL) (XL, XN, XT) 1692
Option Group 8 1537, 1543
Option Group 80, Station Category Indication (LE, N, NT, RT) 1531
Option Group 80, Station Category Indication (S, ST, MS, M) 1531
Option Group 80, Station Category Indication (VLE, XL, XN, XT) 1531
Option Group 81, Controlled Class of Service (LE, N, NT, RT) 1531
Option Group 81, Controlled Class of Service (S, ST, MS, M) 1531
Option Group 81, Controlled Class of Service (VLE, XL, XN, XT) 1531
Option Group 83, ACD/CDR Q Record (LE, N, NT, RT) 1527

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Option Group 83, ACD/CDR Q Record (S, ST, MS, M) 1527
Option Group 83, ACD/CDR Q Record (VLE, XL, XN, XT) 1527
Option Group 86, Multi-Tenant Service (LE, N, NT, RT) 1525
Option Group 86, Multi-Tenant Service (S, ST, MS, M) 1525
Option Group 86, Multi-Tenant Service (VLE, XL, XN, XT) 1525
Option Group 87, Fast TDS (LE, N, NT, RT) 1693
Option Group 87, Fast TDS (S, ST, MS, M) 1693
Option Group 87, Fast TDS (VLE, XL, XN, XT) 1693
Option Group 88, Meridian Digital Telephones (LE, N, NT, RT) 1525
Option Group 88, Meridian Digital Telephones (S, ST, MS, M) 1525
Option Group 88, Meridian Digital Telephones (VLE, XL, XN, XT) 1525
Option Group 89, M3000 Touchphone (LE, N, NT, RT) 1525
Option Group 89, Meridian M3000 Touchphone (S, ST, MS, M) 1525
Option Group 89, Meridian M3000 Touchphone (VLE, XL, XN, XT) 1525
Option Group 9 & 16, Do-Not-Disturb (DND) Group (A, M, S, MS, ST) 1542
Option Group 9 & 16, Do-Not-Disturb (DND) Group (L, LE, N, NT, RT) 1537
Option Group 9 & 16, Do-Not-Disturb (DND) Group (VL, VLE, XL, XN, XT) 1537
Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (A, S, MS, M, ST) 1541
Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (L, LE, N, NT, RT) 1541
Option Group 9, 16, 18, 21, 40, 46, 47 & 48, Feature Package II (two) (VL, VLE, XN, XT, XL) 1541
Option Group 90, Last Number Redial (LE, N, NT, RT) 1532
Option Group 90, Last Number Redial (S, ST, MS, M) 1532
Option Group 90, Last Number Redial (VLE, XL, XN, XT) 1532
Option Group 91, Meridian M2317 Digital Display Telephone (LE, N, NT, RT) 1690
Option Group 91, Meridian M2317 Digital Display Telephone (S, ST, MS, M) 1690
Option Group 91, Meridian M2317 Digital Display Telephone (VLE, XL, XN, XT) 1691
Option Group 92, Pretranslation (LE, N, NT, RT) 1532
Option Group 92, Pretranslation (S, ST, MS, M) 1532
Option Group 92, Pretranslation (VLE, XL, XN, XT) 1532
Option Group 93, Supervisory Console (LE, N, NT, RT) 1532
Option Group 93, Supervisory Console (S, ST, MS, M) 1532
Option Group 93, Supervisory Console (VLE, XL, XN, XT) 1532
Option Group 95, 19, 88, 89 and 91, Call Party Name Display (NT) 1691
Option Group 95, 19, 88, 89 and 91, Call Party Name Display (RT) 1692
Option Group 95, 19, 88, 89 and 91, Call Party Name Display (ST) 1690
Option Group 95, 19, 88, 89 and 91, Call Party Name Display (XT) 1691
Option Group 95, 19, 88, 89, 91, Call Party Name Display (N) 1688
Option Group 95, 19, 88, 89, 91, Call Party Name Display (S, MS) 1687
Option Group 95, 19, 88, 89, 91, Call Party Name Display (XN) 1689
Option Group 98, Dialed Number Identification Service (N) 1688
Option Group 98, Dialed Number Identification Service (NT) 1691
Option Group 98, Dialed Number Identification Service (RT) 1692
Option Group 98, Dialed Number Identification Service (S, MS) 1687
Option Group 98, Dialed Number Identification Service (ST) 1690
Option Group 98, Dialed Number Identification Service (XN) 1689
Option Group 98, Dialed Number Identification Service (XT) 1692
Option Shelf Full Wired/Enhanced 1508, 1685
OPX Line 1502, 1678
OTM 1.0 Enhanced to Premium Server, 50 Sets 337, 1452
OTM 1.0 Enhanced, MAT Upgrade, 50 Sets Expansion 336, 1452
OTM 1.0 Enhanced, MAT Upgrade, Server, 50 Sets 336, 1452
OTM 1.0 Enhanced, Server, 50 Sets 336, 1452
OTM 1.0 General to Enhanced Server, 50 Sets 337, 1452
OTM 1.0 General to Premium Server, 50 Sets 337, 1452
OTM 1.0 General, MAT Upgrade, 50 Sets Expansion 336, 1452
OTM 1.0 General, MAT Upgrade, Server, 50 Sets 336, 1452
OTM 1.0 General, Server, 50 Sets 336, 1452
OTM 1.0 Installation and Engineering User Guide 338, 1498

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

OTM 1.0 Premium, MAT Upgrade, 50 Sets Expansion 336, 1452
OTM 1.0 Premium, MAT Upgrade, Server, 50 Sets 336, 1452
OTM 1.0 Premium, Server, 50 Sets 336, 1452
OTM 1.0 User Guide 338, 1498
OTM 1.x Enhanced to Premium, 1000 Sets Expansion 337, 1453
OTM 1.x Enhanced to Premium, 250 Sets Expansion 337, 1453
OTM 1.x Enhanced to Premium, 50 Sets Expansion 337, 1453
OTM 1.x Enhanced to Premium, 5000 Sets Expansion 337, 1453
OTM 1.x Enhanced, 1000 Sets Expansion 336, 1452
OTM 1.x Enhanced, 250 Sets Expansion 336, 1452
OTM 1.x Enhanced, 50 Sets Expansion 336, 1452
OTM 1.x Enhanced, 5000 Sets Expansion 336, 1452
OTM 1.x General to Enhanced, 1000 Sets Expansion 337, 1453
OTM 1.x General to Enhanced, 250 Sets Expansion 337, 1452
OTM 1.x General to Enhanced, 50 Sets Expansion 337, 1452
OTM 1.x General to Enhanced, 5000 Sets Expansion 337, 1453
OTM 1.x General to Premium, 1000 Sets Expansion 337, 1453
OTM 1.x General to Premium, 250 Sets Expansion 337, 1453
OTM 1.x General to Premium, 50 Sets Expansion 337, 1453
OTM 1.x General to Premium, 5000 Sets Expansion 337, 1453
OTM 1.x General, 1000 Sets Expansion 336, 1452
OTM 1.x General, 250 Sets Expansion 336, 1452
OTM 1.x General, 50 Sets Expansion 336, 1452
OTM 1.x General, 5000 Sets Expansion 336, 1452
OTM 1.x Premium, 1000 Sets Expansion 336, 1452
OTM 1.x Premium, 250 Sets Expansion 336, 1452
OTM 1.x Premium, 50 Sets Expansion 336, 1452
OTM 1.x Premium, 5000 Sets Expansion 336, 1452
OTM Access Server 337, 1453
OTM Billing 1.x General, 100 RU 337, 1452
OTM Billing 1.x General, 1000 RU Expansion 337, 1452
OTM Billing 1.x General, 10000 RU Expansion 337, 1452
OTM Billing 1.x General, 250 RU Expansion 337, 1452
OTM Billing 1.x General, 5000 RU Expansion 337, 1452
OTM Billing 1.x General, 50000 RU Expansion 337, 1452
OTM Billing 1.x General, MAT Upgrade, 100 RUs 338, 1452
OTM Service, Rate Tables - MDR 338, 1512
OTM, Additional Client for Five (5) PCs 338, 1453
OTM, Additional Client for One (1) PC 338, 1453
OTM, Additional Client for Ten (10) PCs 338, 1453
Out-Bound Call Management Service 98 1705
Output Bus Bar Assembly for J2412A-1 Cabinet 1642
Overhead Cable Tray Kit 184, 613, 1416
Overhead Wireway Flange Fitting 1644
Override Key Cap Package (50/PK) 1557
Overview, Installation and Programming 1670

P

P0286117 1639
P0515934 1639
P0523535 1639
P0533539 1639
P0535603 1639
P0535652 1639
P0536035 1639
P0536494 1639
P0536495 1639
P0537535 1639
P0537735 1639
P0537835 1639
P0537903 1639
P0537926 1639
P0538003 1639
P0538026 1639
P0538869 1639
P0544026 1640
P0544126 1640
P0544435 1640
P0544535 1640
P0546135 1640
P0547127 1640
P0547128 1640
P0548753 1640
P0548754 1640
P0548798 1640
P0548815 1640
P0548834 1640
P0549791 1640
P0549799 1640
P0552003 1640
P0552026 1640
P0552414 1640
P0552519 1640
P0552525 1640
P0552526 1640
P0552532 1640

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0552536 1640
P0552944 1640
P0552945 1640
P0552946 1640
P0552947 1640
P0552948 1640
P0552949 1640
P0552950 1640
P0552951 1640
P0552952 1640
P0552953 1640
P0559427 1640
P0559498 1640
P0559499 1641
P0560497 1641
P0560527 1641
P0560624 1641
P0560630 1641
P0562926 1480, 1641
P0565036 1641
P0565037 1641
P0566916 1641
P0567037 1641
P0567062 1641
P0568118 1641
P0569864 1641
P0572335 1641
P0572336 1641
P0572395 1641
P0572472 1641
P0575526 1641
P0575529 1641
P0575531 1641
P0575570 1641
P0582251 1641
P0582279 1641
P0584534 1641
P0584535 1641
P0584536 1641
P0584537 1641
P0584538 1641
P0586306 1641
P0586308 1641
P0586309 1641
P0586312 1641
P0586340 1641
P0586395 1641
P0587440 1642
P0593922 1642
P0593940 1642
P0593964 1642
P0593965 1642
P0593966 1642
P0593967 1642
P0593968 1642
P0593969 1642
P0593970 1642
P0593971 1642
P0593972 1642
P0593977 198, 1481
P0594493 1642
P0594497 1642
P0594498 1642
P0594499 1642
P0595358 1642
P0595359 1642
P0596156 1642
P0613887 1642
P0614658 1642
P0618693 1642
P0622357 1642
P0627392 1642
P0627404 1642
P0629649 1642
P0630408 1642
P0630513 1642
P0630519 1642
P0631118 1642
P0631119 1643
P0631120 1643
P0631121 1643
P0632657 1643
P0632685 1643
P0632699 1643
P0632974 1643
P0632975 1643
P0632976 1643
P0632977 1643
P0633389 1643
P0634868 1643
P0634869 1643
P0634871 1643
P0634911 1643
P0635020 351, 1481
P0635684 1643
P0635898 1643
P0637212 1643
P0637213 1643
P0637214 1643
P0637245 1643
P0637674 1643
P0637697 1643
P0637959 1643
P0639984 198, 1140, 1481
P0639986 1643
P0641250 1643
P0641251 1643
P0641253 1643

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0641254 1643
P0641255 1643
P0641460 1644
P0641463 1644
P0641464 1644
P0641465 1644
P0641466 1644
P0641477 198, 1140, 1481
P0641615 1644
P0641638 1644
P0641826 1644
P0641829 1644
P0641838 1644
P0642526 1644
P0642917 198, 1141, 1481
P0642924 1644
P0643174 1644
P0643763 198, 1141, 1481
P0643862 1644
P0645025 1644
P0645026 1644
P0645043 1644
P0645044 1644
P0645045 1644
P0645717 1644
P0645723 1644
P0645909 1644
P0646995 1644
P0647281 1644
P0649527 1644
P0649968 195, 1141, 1481
P0649998 1644
P0650296 1644
P0650855 1644
P0650859 1644
P0650860 1644
P0650866 1644
P0650867 1644
P0650879 1644
P0650893 1644
P0652720 208, 1141, 1481
P0652721 1645
P0652740 1645
P0652741 1645
P0652765 1645
P0652766 1645
P0652971 1645
P0653302 1645
P0656064 1645
P0656080 1645
P0657569 372, 1481
P0657710 1645
P0657840 1645
P0657842 1645
P0657886 1645
P0658999 1645
P0660405 198, 1141, 1481
P0660406 1645
P0660427 1645
P0660429 1645
P0660431 1645
P0660432 1645
P0660433 1645
P0660464 1645
P0660478 1645
P0661194 1645
P0661883 351, 1481
P0663365 1645
P0663367 1645
P0663392 1645
P0663399 1645
P0663400 1645
P0663401 1645
P0663402 1645
P0663404 1645
P0663435 1645
P0665351 1645
P0665588 1645
P0665594 1646
P0667282 1646
P0667297 1646
P0667321 1646
P0667323 1646
P0667325 1646
P0667329 351, 1481
P0667334 1646
P0669418 1646
P0669419 1646
P0669420 1646
P0671604 1646
P0671605 1646
P0671606 1646
P0671607 1646
P0673102 1646
P0673966 1646
P0673998 1646
P0673999 351, 1481
P0674953 1646
P0674954 1646
P0674955 1646
P0674956 1646
P0676050 1646
P0676069 1646
P0676070 1646
P0676071 1646
P0676095 1646
P0676096 1646
P0676097 1646

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0677283 1481, 1646
P0677315 1646
P0677580 198, 1142, 1481
P0677581 1646
P0677585 1646
P0677587 198, 1142, 1481
P0677588 198, 1142, 1481
P0677591 351, 1481
P0677592 1646
P0677593 1646
P0677799 1647
P0678258 198, 1142, 1481
P0680121 1647
P0680793 209, 1142, 1481
P0682732 1647
P0682859 1647
P0682860 1647
P0684414 223, 1143, 1481
P0685498 1647
P0685499 1647
P0686288 1647
P0686289 1647
P0686290 1647
P0686478 1647
P0686669 1647
P0686745 1647
P0686747 1647
P0686986 1647
P0686988 1647
P0687153 351, 1481
P0687154 1647
P0687341 1647
P0687431 1647
P0687491 1647
P0687641 1647
P0687643 1647
P0687644 1647
P0688051 1647
P0688053 1647
P0688122 1647
P0688445 1647
P0688542 1647
P0688544 1647
P0688545 1647
P0688546 1647
P0688547 1647
P0688548 1647
P0688549 1647
P0688550 1648
P0688551 1648
P0688552 1648
P0688553 1648
P0688554 1648
P0688555 1648
P0688556 1648
P0688557 1648
P0688558 1648
P0688559 1648
P0688609 208, 1481
P0689117 1648
P0689118 1648
P0689184 1648
P0689435 1648
P0689682 1648
P0689706 1648
P0689707 1648
P0689753 1648
P0689755 351, 1481
P0689757 351, 1481
P0689837 1648
P0689838 1648
P0689839 1648
P0689840 1648
P0689841 1648
P0689842 1648
P0690094 1648
P0690095 1648
P0690152 352, 1481
P0690763 352, 1481
P0691037 198, 1143, 1481
P0693020 1648
P0693364 1648
P0693365 1648
P0693926 1648
P0693951 1648
P0694319 1648
P0694608 1648
P0694609 1648
P0694611 1649
P0694612 1649
P0694621 1649
P0694682 1649
P0694698 208, 1143, 1481
P0694714 1649
P0694715 1649
P0694841 1649
P0694842 1649
P0695120 1649
P0695166 1649
P0695167 268, 1143, 1481
P0695169 268, 1144, 1481
P0695170 1649
P0695624 1649
P0695822 268, 1144, 1481
P0695823 268, 1144, 1481
P0695826 1481, 1649
P0695827 1482, 1649
P0696010 1649

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0696493 1649
P0696494 1649
P0696547 198, 1144, 1482
P0696591 1649
P0696592 1649
P0696749 352, 1482
P0696752 1649
P0697180 1649
P0697181 1649
P0697182 1649
P0697183 1649
P0697194 1649
P0697195 1649
P0697290 1649
P0697291 1649
P0697292 1649
P0697487 1649
P0697511 1649
P0697550 198, 1145, 1482
P0697559 198, 1145, 1482
P0697664 1649
P0697707 198, 1145, 1482
P0697880 1649
P0698119 1649
P0698280 1650
P0698887 1650
P0698888 1650
P0698958 1650
P0698959 1650
P0698960 1650
P0699029 1650
P0699120 1650
P0699121 1650
P0699122 1650
P0699124 208, 1145, 1482
P0699345 1650
P0699378 346, 1482
P0699379 346, 1482
P0699380 346, 1482
P0699381 346, 1482
P0699382 346, 1482
P0699383 346, 1482
P0699384 1650
P0699385 1650
P0699386 1650
P0699387 346, 1482
P0699388 1650
P0699724 1650
P0699766 1650
P0699798 184, 1145, 1482
P0699851 184, 1146, 1482
P0699884 1650
P0700257 1650
P0700258 1650
P0700340 1650
P0700341 1650
P0700342 1650
P0700563 208, 1146, 1482
P0700724 1650
P0700725 1650
P0700726 1650
P0700727 1650
P0700728 1650
P0700816 1650
P0700817 1650
P0700818 1651
P0701306 1651
P0701307 1651
P0701308 1651
P0701309 1651
P0701310 1651
P0701311 1651
P0701352 184, 1146, 1482
P0701353 184, 1146, 1482
P0701381 1651
P0701382 1651
P0701383 1651
P0701446 1651
P0701633 1651
P0701634 1651
P0701681 1651
P0701874 352, 1482
P0701875 1651
P0702043 1651
P0702044 1651
P0702280 1651
P0702281 1651
P0702282 1651
P0702321 1651
P0702380 198, 1146, 1482
P0702574 1651
P0702575 1651
P0702577 1651
P0702688 1651
P0702689 1651
P0702779 374, 1482
P0702800 352, 1482
P0702942 1651
P0703066 1651
P0703300 1651
P0703612 1651
P0703633 1651
P0703678 1651
P0703680 1651
P0703846 1651
P0703905 186, 198, 1146, 1482
P0703906 186, 198, 1147, 1482
P0703960 186, 198, 1147, 1482

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0703961 186, 1147, 1482
P0703991 1652
P0704071 1652
P0704094 1652
P0704096 1652
P0704282 1652
P0704283 1652
P0704284 1652
P0704285 1652
P0704407 1652
P0704511 186, 198, 1147, 1482
P0704514 1652
P0704654 1652
P0704746 1652
P0704747 1652
P0704832 1652
P0705038 1652
P0705039 1652
P0705046 1652
P0705052 1652
P0705081 1652
P0705510 1652
P0705511 1652
P0705512 1652
P0705513 1652
P0705622 1652
P0705623 1652
P0705679 1652
P0705800 208, 1482
P0705801 208, 1148, 1482
P0705952 1652
P0705986 1652
P0705987 1652
P0705992 1652
P0705993 1652
P0705994 1652
P0705995 1652
P0705996 1652
P0705997 1653
P0705998 1653
P0705999 1653
P0706000 1653
P0706431 1653
P0706646 1653
P0706875 1653
P0706926 1653
P0707305 1653
P0707306 1653
P0707593 352, 1482
P0707698 1653
P0707699 1653
P0707700 352, 1482
P0708732 1653
P0709566 1653
P0710203 1653
P0710364 1653
P0710422 1653
P0710530 1653
P0710531 1653
P0710532 1653
P0710533 1653
P0710534 1653
P0710535 1653
P0710536 1653
P0710927 1653
P0710928 1653
P0712139 1653
P0712140 1653
P0712141 1653
P0712142 1653
P0712143 1654
P0712203 1654
P0712690 1654
P0712942 1654
P0713311 1654
P0713319 1654
P0713323 1654
P0713674 352, 1483
P0713826 1654
P0714208 1654
P0714224 69, 198, 1483
P0714236 69, 198, 1483
P0714359 1654
P0714360 1654
P0714686 1654
P0714687 1654
P0714688 208, 1483
P0714692 352, 1483
P0714693 352, 1483
P0714694 208, 1483
P0714695 208, 1483
P0714791 1654
P0714793 1654
P0714848 1654
P0714849 1654
P0714863 1654
P0714864 1654
P0715045 1654
P0715046 1654
P0715058 1654
P0715802 198, 1483
P0715980 1654
P0715981 1654
P0715982 1654
P0715983 1654
P0722007 1654
P0722008 1654
P0722420 1654

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0722421 1654
P0722422 1654
P0722423 1654
P0722848 1654
P0722849 199, 1148, 1483
P0722850 199, 1148, 1483
P0723443 209, 1148, 1483
P0723459 199, 1148, 1483
P0723522 352, 1483
P0724136 359, 1483
P0724138 1654
P0724352 1655
P0724945 352, 1483
P0724947 1655
P0725913 1655
P0725917 1655
P0726365 1655
P0726664 346, 1483
P0727748 1655
P0727750 1655
P0727752 1655
P0727753 1655
P0727766 1655
P0727842 186, 1149, 1483
P0727843 186, 1149, 1483
P0727984 1655
P0728236 1655
P0728237 1655
P0728239 352, 1483
P0728240 352, 1483
P0728241 1655
P0728242 1655
P0728489 1655
P0728490 1655
P0729330 1655
P0729332 1655
P0729334 1655
P0729336 1655
P0729338 1655
P0729362 1655
P0729367 1655
P0729469 209, 1483
P0729617 1655
P0729840 1655
P0729843 186, 342, 1149, 1483
P0729844 1655
P0729845 1655
P0729846 186, 342, 1149, 1483
P0729847 186, 342, 1149, 1483
P0730064 186, 1150, 1483
P0730065 1655
P0730076 1655
P0730121 346, 1483
P0730128 1655
P0730129 352, 1483
P0730252 186, 342, 1150, 1483
P0730351 1655
P0730610 1655
P0731580 1655
P0731602 352, 1483
P0731603 1656
P0731760 1656
P0731761 1656
P0731813 209, 1150, 1483
P0732148 1656
P0732177 1656
P0732496 209, 1483
P0733203 199, 1150, 1483
P0734019 346, 1483
P0734021 346, 1483
P0734022 1656
P0734380 352, 1484
P0734851 1656
P0734852 1656
P0734853 1656
P0734854 1656
P0734855 1656
P0734856 1656
P0734857 1656
P0735064 346, 1484
P0735209 1656
P0735210 1656
P0735211 63, 70, 352, 1484
P0735252 346, 1484
P0735300 1656
P0735303 1656
P0735304 1656
P0735305 1656
P0735306 1656
P0735307 1656
P0735309 1656
P0735394 1656
P0735539 352, 1484
P0735904 1656
P0735905 1656
P0735906 1656
P0736062 352, 1484
P0736063 1656
P0736064 1656
P0736220 1656
P0737036 1656
P0738399 1657
P0738400 1657
P0738401 1657
P0738402 1657
P0738403 1657
P0738404 1657
P0738405 1657

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0738406 1657
P0738407 1657
P0738409 1657
P0738410 1657
P0738411 1657
P0738412 1657
P0738413 1657
P0738414 1657
P0738417 352, 1484
P0738418 1657
P0738420 1657
P0738421 1657
P0738422 1657
P0738423 1657
P0738424 1657
P0738425 1657
P0738426 1657
P0738599 1657
P0738600 210, 1150, 1484
P0738616 352, 1484
P0738690 1657
P0738832 1657
P0738866 199, 1151, 1484
P0739518 346, 1484
P0739519 352, 1484
P0739520 346, 1484
P0739521 346, 1484
P0739522 1657
P0739523 1657
P0739575 347, 1484
P0739690 1657
P0739719 1657
P0739720 365, 1484
P0739721 365, 1484
P0739722 1657
P0739723 1657
P0739726 365, 1484
P0739727 365, 1484
P0739730 1657
P0739833 359, 1484
P0739834 359, 1484
P0739835 366, 1484
P0739836 359, 1484
P0739838 359, 1484
P0739839 359, 1484
P0739849 1658
P0739850 372, 1484
P0740245 1658
P0740384 352, 1484
P0740385 1658
P0740400 352, 1484
P0740401 1658
P0740420 352, 1484
P0740421 352, 1484
P0740423 347, 1484
P0740426 1658
P0740751 1658
P0740839 1658
P0740884 1658
P0741126 1658
P0741127 1658
P0741128 1658
P0741129 1658
P0741130 1658
P0741131 1658
P0741295 347, 1485
P0741297 352, 1485
P0741298 347, 1485
P0741301 347, 1485
P0741302 347, 1485
P0741303 347, 1485
P0741304 347, 1485
P0741305 347, 1485
P0741306 347, 1485
P0741307 347, 1485
P0741308 347, 1485
P0741309 352, 1485
P0741310 352, 1485
P0741311 352, 1485
P0741489 199, 1151, 1485
P0741522 1658
P0741565 352, 1485
P0741670 1658
P0741768 1658
P0741769 1658
P0741770 1658
P0741771 1658
P0741982 372, 1485
P0741983 372, 1485
P0742037 1658
P0742038 1658
P0742039 1658
P0742040 1658
P0742041 1658
P0742042 1658
P0742043 1658
P0742044 1658
P0742045 1658
P0742046 1658
P0742047 1658
P0742048 1658
P0742049 1658
P0742050 1658
P0742051 1659
P0742128 1659
P0742129 1659
P0742471 1659
P0742473 1659

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0742631 1659
P0742737 1659
P0742833 347, 1485
P0742870 1659
P0743363 353, 1485
P0743364 353, 1485
P0743367 353, 1485
P0743368 353, 1485
P0743369 353, 1485
P0743482 186, 342, 1485
P0743512 353, 1485
P0743618 353, 1485
P0743619 1659
P0743664 1659
P0743683 1659
P0743687 1659
P0743724 353, 1485
P0743899 1659
P0743975 372, 1485
P0744195 1659
P0744196 1659
P0744197 1659
P0744198 1659
P0744199 1659
P0744200 1659
P0744201 1659
P0744202 1659
P0744203 1659
P0744204 1659
P0744205 1659
P0744206 1659
P0744208 1659
P0744209 1659
P0744210 1659
P0744211 1659
P0744212 1659
P0744213 1659
P0744214 1659
P0744215 1659
P0744216 1660
P0744217 1660
P0744218 1660
P0744219 1660
P0744255 347, 1485
P0744256 1660
P0744257 1660
P0744258 1660
P0744259 1660
P0744260 1660
P0744261 1660
P0744262 1660
P0744265 368, 1485
P0744266 367, 1485
P0744268 1660
P0744323 1660
P0744329 1660
P0744752 375, 1485
P0744808 1660
P0744840 359, 1485
P0744873 186, 1151, 1486
P0745631 367, 1486
P0745632 367, 1486
P0745633 367, 1486
P0745635 367, 1486
P0745713 199, 1151, 1486
P0745716 186, 1151, 1486
P0745758 353, 1486
P0745957 374, 1486
P0746049 372, 1486
P0746275 372, 1486
P0746276 372, 1486
P0746277 373, 1486
P0746278 373, 1486
P0746456 1660
P0746457 1660
P0746458 1660
P0746459 1660
P0746460 1660
P0746461 1660
P0746462 1660
P0746463 1660
P0746464 1660
P0746465 1660
P0746466 1660
P0746467 1660
P0746468 1660
P0746469 1660
P0746470 1660
P0746471 1660
P0746472 1660
P0746475 1660
P0746527 347, 1486
P0746528 347, 1486
P0746529 347, 1486
P0746530 353, 1486
P0746564 353, 1486
P0746602 186, 1152, 1486
P0746603 186, 1152, 1486
P0746604 186, 1152, 1486
P0746605 186, 1152, 1486
P0746607 186, 1152, 1486
P0746608 186, 1152, 1486
P0746653 368, 1486
P0747013 1660
P0747014 1661
P0747107 1661
P0748232 374, 1486
P0748297 1661

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0748298 1661
P0748299 1661
P0748300 1661
P0748301 1661
P0748302 1661
P0748303 1661
P0748304 1661
P0748305 1661
P0748306 1661
P0748307 1661
P0749025 360, 1486
P0751003 1661
P0768143 210, 1153, 1486
P0778303 1661
P0778335 1661
P0778393 1661
P0780103 203, 1153, 1486
P0780135 203, 1153, 1486
P0780193 203, 1153, 1486
P0780203 203, 1154, 1486
P0780235 203, 1154, 1487
P0780293 203, 1154, 1487
P0784403 1661
P0784435 1661
P0784493 1661
P0784503 210, 1154, 1487
P0784535 210, 1155, 1487
P0784593 210, 1155, 1487
P0800399 1661
P0800406 1661
P0800410 1661
P0800412 1661
P0800413 1661
P0800416 1661
P0800441 1661
P0800442 1661
P0800444 1661
P0800513 1661
P0800514 1661
P0800515 1661
P0800516 1661
P0800517 1661
P0800518 1662
P0800519 1662
P0800520 1662
P0800521 1662
P0800522 1662
P0800523 1662
P0800524 1662
P0800525 1662
P0800553 347, 1487
P0800554 1662
P0800555 1662
P0800556 1662
P0800557 1662
P0800558 1662
P0800559 1662
P0800560 1662
P0800561 1662
P0800562 1662
P0800563 1662
P0800565 1662
P0800567 353, 1487
P0800569 1662
P0800571 1662
P0800600 1662
P0800601 1662
P0802085 321, 353, 1487
P0802087 322, 353, 1487
P0802089 322, 353, 1487
P0802279 1662
P0802282 1662
P0802290 1662
P0802672 1662
P0803126 353, 1487
P0803182 353, 1487
P0803269 360, 1487
P0803833 1662
P0803870 199, 1155, 1487
P0805675 1662
P0805676 1662
P0805693 1662
P0806071 371, 1487
P0807243 370, 1487
P0807245 360, 1487
P0808873 360, 1487
P0808874 360, 1487
P0808875 361, 1487
P0808876 361, 1487
P0808877 361, 1487
P0809259 1662
P0809260 1662
P0809261 1662
P0809263 1663
P0809264 1663
P0809265 1663
P0809274 1663
P0809276 1663
P0809279 1663
P0809280 1663
P0809282 1663
P0809285 1663
P0809287 1663
P0809479 1663
P0809892 353, 1487
P0811110 1663
P0813732 1663
P0813821 1663

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0813947 1663
P0813948 353, 1487
P0813950 353, 1487
P0813951 1663
P0813952 1663
P0813953 1663
P0813954 1663
P0813955 1663
P0813956 1663
P0813957 1663
P0813958 1663
P0813959 1663
P0813960 1663
P0813961 1663
P0813962 1663
P0813963 1663
P0813964 1663
P0813966 1663
P0813967 1663
P0813968 1663
P0813969 1663
P0813970 347, 1487
P0813971 1664
P0813972 1664
P0814186 1664
P0814188 373, 1487
P0814833 353, 1487
P0815188 347, 1155, 1487
P0815254 367, 1487
P0815255 360, 1487
P0815258 361, 1488
P0815259 361, 1488
P0815260 361, 1488
P0815261 361, 1488
P0815275 1664
P0815276 1664
P0815375 323, 353, 1488
P0815376 323, 353, 1488
P0815404 66, 182, 1488
P0815593 321, 1156, 1488
P0815602 323, 1488
P0816320 1664
P0816367 187, 1156, 1488
P0816832 69, 199, 1488
P0817917 360, 1488
P0817918 362, 1488
P0817919 362, 1488
P0817920 361, 1488
P0818829 1664
P0819082 1664
P0819089 370, 1488
P0819090 1664
P0819765 347, 1488
P0819906 362, 1488
P0819975 374, 1488
P0820897 1664
P0820898 1664
P0820899 1664
P0820900 1664
P0820901 1664
P0820902 1664
P0820903 1664
P0820904 1664
P0820905 1664
P0820906 1664
P0820907 1664
P0820908 1664
P0820909 1664
P0820910 1664
P0820911 1664
P0820912 1664
P0820913 1664
P0820914 1664
P0820915 1664
P0820916 1664
P0820917 1664
P0820918 1664
P0820954 362, 1488
P0821268 1664
P0821273 1664
P0821274 1664
P0821277 1665
P0821279 1665
P0821280 1665
P0821281 1665
P0821303 323, 1488
P0821361 375, 1488
P0821363 374, 1488
P0821458 1665
P0821459 1665
P0828635 210, 1488
P0832159 347, 1488
P0832908 1665
P0832912 1665
P0833297 1665
P0833301 1665
P0833302 1665
P0833303 1665
P0833305 1665
P0833777 353, 1488
P0833798 353, 1488
P0833799 353, 1488
P0833800 353, 1488
P0833801 353, 1488
P0833802 353, 1489
P0834426 353, 1489
P0834606 1665
P0834786 1665

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0835201 353, 1489
P0835240 347, 1489
P0835273 63, 70, 347, 1489
P0835516 347, 1489
P0837440 1665
P0837621 64, 70, 347, 1489
P0837630 1665
P0837637 1665
P0837640 64, 70, 347, 1489
P0837643 1665
P0837647 64, 70, 347, 1489
P0837650 1665
P0838403 1665
P0838435 1665
P0838493 1665
P0839909 353, 1489
P0839910 353, 1489
P0839915 353, 1489
P0839920 354, 1489
P0839921 354, 1489
P0839922 354, 1489
P0839923 354, 1489
P0839924 354, 1489
P0839925 354, 1489
P0839926 354, 1489
P0839934 354, 1489
P0839941 60, 354, 1156, 1489
P0839943 354, 1489
P0839945 354, 1489
P0839989 368, 1489
P0839990 368, 1489
P0839991 368, 1489
P0839993 323, 354, 1489
P0840491 1665
P0842656 1665
P0842657 1665
P0842658 1665
P0842659 1665
P0842660 1665
P0842661 1665
P0842662 1665
P0842663 1665
P0842664 1665
P0842665 1665
P0842666 1666
P0842837 1666
P0842838 1666
P0842839 1666
P0842840 1666
P0842841 1666
P0842842 1666
P0842843 1666
P0842844 1666
P0842845 1666
P0842849 1666
P0843029 362, 1489
P0843060 373, 1489
P0843070 295, 1156, 1489
P0843834 354, 1490
P0843835 1666
P0843836 1666
P0843837 354, 1490
P0843838 1666
P0843839 1666
P0843840 354, 1490
P0843875 1666
P0843877 1666
P0843878 1666
P0843879 1666
P0843880 1666
P0843987 374, 1490
P0844036 371, 1490
P0844341 323, 354, 1490
P0844587 375, 1490
P0844588 375, 1490
P0844589 375, 1490
P0845109 371, 1490
P0845932 1666
P0845933 1666
P0845934 1666
P0845935 1666
P0847112 1666
P0847123 1666
P0847870 354, 1156, 1490
P0849011 1666
P0849012 1666
P0849802 347, 1490
P0850378 1666
P0850509 1666
P0850716 69, 182, 1157, 1490
P0853412 321, 1157, 1490
P0853935 1666
P0853936 367, 1490
P0853937 371, 1490
P0853938 365, 1490
P0853939 1666
P0854530 1666
P0854560 354, 1490
P0855219 1667
P0857603 1667
P0857663 1667
P0857665 363, 1490
P0857666 363, 1490
P0857667 364, 1490
P0857668 1667
P0857669 1667
P0857833 1667
P0858339 1667

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0858340 1667
P0859507 1667
P0859735 1667
P0859913 369, 1490
P0865353 369, 1490
P0865356 354, 1490
P0865358 354, 1490
P0865359 354, 1490
P0865360 354, 1490
P0865361 354, 1490
P0865362 347, 1490
P0866762 1667
P0866881 1667
P0867594 354, 1490
P0867595 1667
P0867596 354, 1490
P0868044 1667
P0868045 1667
P0868046 1667
P0868047 1667
P0868048 1667
P0868049 1667
P0868050 1667
P0868051 1667
P0868052 1667
P0868056 347, 1491
P0868057 1667
P0868058 1667
P0868059 1667
P0868060 1667
P0868061 1667
P0868062 1667
P0868064 1667
P0868065 1667
P0868066 1667
P0868067 1667
P0868068 1667
P0868069 1667
P0868071 1668
P0868347 1668
P0868348 1668
P0868349 1668
P0868350 1668
P0868351 1668
P0868352 1668
P0868353 1668
P0868354 1668
P0868355 1668
P0868356 1668
P0868357 1668
P0868358 1668
P0868359 354, 1491
P0868440 354, 1491
P0869327 1668
P0869771 364, 1491
P0869772 364, 1491
P0870332 1668
P0870432 1668
P0870433 322, 1157, 1491
P0870633 1668
P0870639 1668
P0870718 199, 1157, 1491
P0871231 271, 1491
P0871232 1668
P0871739 354, 1491
P0871843 369, 1491
P0871844 369, 1491
P0872703 1668
P0872784 1668
P0872785 60, 1157, 1491
P0872786 1668
P0872787 1668
P0872788 60, 1158, 1491
P0872789 1668
P0872790 1668
P0872791 1668
P0873149 373, 1491
P0873435 1668
P0873717 60, 1158, 1491
P0873719 60, 1158, 1491
P0873891 1668
P0873892 1668
P0873893 1668
P0874391 347, 1491
P0874537 1668
P0875061 1668
P0875063 1668
P0875113 354, 1491
P0875712 369, 1491
P0875813 1668
P0875888 355, 1491
P0875895 347, 1491
P0875898 355, 1491
P0875899 355, 1491
P0875900 355, 1491
P0875903 355, 1491
P0875904 355, 1491
P0875905 60, 1491
P0875906 355, 1491
P0875908 355, 1491
P0875910 355, 1491
P0875911 355, 1491
P0875912 355, 1492
P0875913 60, 1492
P0875922 275, 1492
P0875936 355, 1492
P0875941 355, 1492
P0876242 1158, 1492

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0876243 1669
P0876250 1669
P0876251 1669
P0876252 1669
P0876257 1669
P0876258 1669
P0876261 307, 1158, 1492
P0876262 307, 1159, 1492
P0876389 339, 1159, 1492
P0876390 339, 1159, 1492
P0876391 339, 1159, 1492
P0876392 339, 1160, 1492
P0876393 339, 1160, 1492
P0876394 339, 1160, 1492
P0876395 340, 1160, 1492
P0876396 340, 1161, 1492
P0876397 340, 1161, 1492
P0876398 340, 1161, 1492
P0876399 340, 1161, 1492
P0876400 340, 1162, 1492
P0876404 1669
P0877708 371, 1492
P0877889 1669
P0878305 1669
P0878306 368, 1492
P0878308 1669
P0878469 66, 347, 1492
P0878476 363, 1492
P0878478 364, 1492
P0878479 1669
P0879421 1669
P0879480 307, 1492
P0879481 308, 1492
P0879709 1669
P0879824 356, 1493
P0879825 365, 1493
P0881354 271, 1493
P0881397 321, 1162, 1493
P0881398 322, 1162, 1493
P0882201 1669
P0884266 1669
P0884613 355, 1493
P0884766 60, 1493
P0884828 1669
P0884895 228, 1162, 1493
P0884909 228, 307, 1162, 1493
P0885042 1669
P0885044 61, 1163, 1493
P0885111 320, 1163, 1493
P0885159 269, 1493
P0885160 269, 1493
P0885161 269, 1493
P0885212 1669
P0885213 1669
P0885214 1669
P0885215 1669
P0885216 60, 1493
P0885218 1669
P0885219 61, 1493
P0885220 60, 1493
P0885221 60, 1163, 1493
P0885695 348, 1493
P0885697 26, 1669
P0885698 1669
P0885702 343, 348, 1493
P0886005 26, 1669
P0886006 26, 1669
P0886124 228, 1164, 1493
P0886125 1669
P0886126 228, 1164, 1493
P0886127 228, 1493
P0886128 228, 1493
P0886130 228, 1493
P0886132 228, 1493
P0886133 228, 1493
P0886135 228, 1493
P0886136 1669
P0886137 1669
P0886138 228, 1493
P0886141 228, 1493
P0886142 228, 1493
P0886143 228, 1493
P0886144 228, 1493
P0886145 228, 1493
P0886146 228, 1493
P0886147 228, 1493
P0886148 228, 1494
P0886149 228, 1494
P0886590 1669
P0886656 324, 1164, 1494
P0886776 228, 1164, 1494
P0887067 1669
P0887069 1669
P0887333 1669
P0887334 1670
P0887335 296, 1494
P0887541 364, 1494
P0888010 1670
P0888012 1670
P0888021 1670
P0888025 1670
P0888788 1670
P0889187 348, 1494
P0889188 348, 1494
P0889189 348, 1494
P0889190 348, 1494
P0889191 63, 348, 1494
P0889192 348, 1494

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0889193 348, 1494
P0889194 348, 1494
P0889195 348, 1494
P0889196 348, 1494
P0889197 348, 1494
P0889198 348, 1494
P0889199 1670
P0889200 348, 1494
P0889201 348, 1494
P0889202 348, 1494
P0889203 348, 1494
P0889204 348, 1494
P0889235 348, 1494
P0889236 348, 1494
P0889248 1670
P0889249 363, 1494
P0889406 324, 1164, 1494
P0889431 348, 1494
P0889883 205, 348, 1494
P0889884 205, 1494
P0889885 205, 1495
P0889981 369, 1495
P0889982 369, 1495
P0889983 369, 1495
P0889984 369, 1495
P0889985 369, 1495
P0889986 373, 1165, 1495
P0889987 370, 1165, 1495
P0889988 373, 1165, 1495
P0889989 370, 1165, 1495
P0889990 370, 1166, 1495
P0889991 370, 1166, 1495
P0889992 370, 1166, 1495
P0889993 370, 1166, 1495
P0889994 370, 1166, 1495
P0889995 348, 1495
P0889996 355, 1495
P0890034 1670
P0890035 1670
P0890121 60, 1495
P0890122 60, 1495
P0890123 60, 1495
P0890124 60, 1495
P0890125 60, 1495
P0890732 348, 1495
P0891204 363, 1495
P0891205 365, 1495
P0891206 364, 1495
P0891207 363, 1495
P0891208 363, 1495
P0891209 363, 1495
P0891256 348, 1495
P0891257 348, 1495
P0891258 348, 1495
P0891259 26, 1670
P0891452 1670
P0891453 1670
P0891454 1670
P0891456 1670
P0891458 1670
P0891460 1670
P0891463 1670
P0891465 1670
P0891467 1670
P0891468 1670
P0891469 1670
P0891472 1670
P0902865 26, 1670
P0903073 228, 1167, 1495
P0903074 228, 1167, 1495
P0903075 228, 1167, 1495
P0903507 1670
P0903934 364, 1496
P0904477 199, 1496
P0904478 199, 1496
P0904485 348, 1496
P0904486 348, 1496
P0904487 348, 1496
P0904492 349, 1496
P0904493 349, 1496
P0904494 349, 1496
P0904567 349, 1496
P0904927 349, 1496
P0905051 65, 349, 1496
P0905519 228, 1496
P0905560 228, 1496
P0905610 228, 1496
P0905622 228, 1496
P0905783 228, 1167, 1496
P0905786 228, 1496
P0905787 229, 1496
P0905788 229, 1168, 1496
P0905789 229, 1168, 1496
P0905790 229, 1168, 1496
P0905791 229, 1168, 1496
P0905796 229, 1169, 1496
P0905797 229, 1169, 1496
P0905798 229, 1496
P0905799 229, 1169, 1496
P0905800 229, 1496
P0905810 229, 1497
P0905816 229, 1497
P0905817 229, 1497
P0905818 1670
P0906299 356, 1497
P0906300 356, 1497
P0906301 356, 1497
P0906303 356, 1497

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

P0906304 357, 1497
P0906308 182, 1169, 1497
P0906569 349, 1170, 1497
P0906932 230, 1497
P0907026 1670
P0907072 349, 1497
P0907146 355, 1497
P0907149 355, 1497
P0907386 1670
P0907437 1670
P0907449 63, 349, 1497
P0907452 63, 70, 349, 1497
P0907453 64, 70, 349, 1497
P0907454 63, 349, 1497
P0907455 63, 349, 1497
P0907622 296, 1497
P0907624 296, 1497
P0907827 229, 1497
P0907828 229, 1497
P0907829 229, 1497
P0907831 229, 1497
P0907840 229, 1497
P0908782 296, 1497
P0909234 229, 1497
P0909235 229, 1497
P0909314 366, 1497
P0909315 366, 1497
P0909316 366, 1497
P0909317 366, 1497
P0909318 366, 1497
P0909319 367, 1498
P0909573 349, 1498
P0909663 297, 1170, 1498
P0909937 1670
P0909939 229, 1498
P0909940 229, 1498
P0909941 229, 1498
P0909942 1670
P0909943 1670
P0909944 1670
P0909945 1670
P0909946 1671
P0909947 229, 1498
P0910102 338, 1498
P0910103 338, 1498
P0910151 1671
P0910775 349, 1498
P0910776 349, 1498
P0910777 349, 1498
P0910790 63, 70, 349, 1498
P0910791 64, 70, 349, 1498
P0910793 63, 349, 1498
P0910795 63, 349, 1498
P0910806 349, 1170, 1498
P0911675 307, 1498
P0912432 349, 1498
P0912433 349, 1498
P0912434 349, 1498
P0912435 349, 1498
P0912436 349, 1498
P0912857 349, 1498
P0912861 349, 1498
P0912862 349, 1498
P0912864 349, 1498
P0913184 223, 1498
P0914163 349, 1498
P0914300 229, 1498
P0914505 349, 1498
P0914553 349, 1498
P0914554 350, 1499
P0960326 210, 1170, 1499
P096D326 1671
Pack, CPU Bus Extender, N 1504, 1680
Package of 10 322, 519, 797, 1389, 1437, 1576
Package of 10 Option 11C Documentation CD-ROMs 346, 876, 1449
Packageof10' 321
Panasonic KX-P1180 Printer 1382, 1568
Panel, Hinged Door 1641
Parallel Diode Kit 1597
Park Key Cap Package (50/PK) 207, 399, 1368
Passport (Frame/Cell) Network Trunk Software 1620
Path Oriented Routing Software 1620
P-Bus 2 Segment 1583
P-Bus 3 Segment 1583
P-Bus 4 Segment 1583
P-Bus 5 Segment 1583
P-Bus Kit Assembly, 2-Pos 1638
P-Bus Kit Assembly, 3-Pos 1638
PC Application Guide - MM13 349, 1497
PC Dial-In Guide (DA209-01) 1553
PC Dongle for One (1) PC 1630, 1637
PC Dongle for One (1) PC and User Guide 339, 1034, 1468, 1630
PC Dongle for Two Hundred Fifty (250) PCs 1630, 1637
PC Dongles for Fifty (50) PC and 30 User Guides 339, 1035, 1468, 1630
PC Dongles for Fifty (50) PCs 1630, 1637
PC Dongles for Five (5) PC and User Guides 339, 1034, 1468, 1630
PC Dongles for Five (5) PCs 1630, 1637
PC Dongles for Ten (10) PC and User Guides 339, 1035, 1468, 1630
PC Dongles for Ten (10) PCs 1630, 1637
PC Dongles for Two Hundred Fifty (250) PC and 100 User Guides 339, 1035, 1468, 1630, 1631
PC Interface Card User Guide (15/PK) 1644

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

PC Maintenance Cable 188, 193, 553, 692, 1402, 1426
PC Pack, Entopia MMP40, Card Option (Any Slot) 30, 239, 1409
PC Pak 1542
PC/TCP Server Based License Software (TCP120) 1551
PC/TCP Server Based Licensed Software with Routing (TCP100) 1553
PCI 10MB Ethernet Adapter Spare 281, 295, 964, 1460
PCI Ethernet Adapter 303, 307, 855, 1446
PCI SCSI Adapter Spare 1626
PCI Token Ring Network Card 41, 220, 303, 307, 855, 1446
PCI Video Adapter Spare for OIVR 4.0 AP, MRS/AP, or MRS 282, 965, 1460
PCMCIA Flash Card Upgrade, MIPCD 30, 40, 177, 1404
PDP-11, HP Vectra, MAX-IPE, and MAX-IPEE to Meridian MAX-SNNE Hardware Upgrade Package, AC Power 1711
PDP-11, HP Vectra, MAX-IPE, and MAX-IPEE to Meridian MAX-SNNE Hardware Upgrade Package, DC Power 1711
PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, AC Power 316, 790, 1436
PDP-11, HP Vectra, MAX-IPE/IPEE to Meridian MAX-SNNE Hardware Upgrade, DC Power 316, 790, 1436
PE and Power Cabinet 1671
PE Backplane 183, 1504, 1505, 1680, 1682
PE Backplane/Expansion 1504, 1680
PE Cabinet 1671
PE Cabinet #1 Assembly 1527
PE Cabinet #2 Assembly 1527
PE Cabinet Assembly 1527, 1543
PE Expansion Tier 1507, 1684
PE Shelf (Cantilever) 1400, 1588
PE Shelf (Center Mount) 1400, 1588
PE Shelf Assembly-EMI "A & B" 1542
PE Shelf Assembly-EMI "A" 1542
PE/PRI Cabinet Assembly 1546
Pedestal - AC 1603
Pedestal - DC 1599
Pedestal AC 183, 197, 603, 1414
Pedestal Assembly AC 184, 841, 1444, 1561
Pedestal Assembly DC 184, 841, 1444, 1561
Pedestal Blower Unit AC 184, 612, 1416, 1604
Pedestal Blower Unit DC 184, 612, 1416, 1604
Pedestal DC 183, 589, 1410
Pedestal Fan Unit AC 1599
Pedestal Fan Unit DC 1600
Pedestal/Top Cap Package AC 159, 450, 1378
Pedestal/Top Cap Package DC 159, 450, 1378
Pentium CPU Upgrade 1628
Pentium III BIOS 221, 1446
Pentium III SBC 500MHz CPU 40, 221, 1377
Pentium III Xeon 500 MHz, 512KB ECC L2 Cache 29, 306, 1376
Pentium Platform Based Messenger 1.1 to 4.0 Upgrade 26, 1628
Pentium SBC Upgrade for PEB-based MRS 280, 960, 1459
Peripheral Buffer 1503, 1504, 1505, 1679, 1680, 1681
Peripheral Cable Female 239, 696, 1428
Peripheral Cable Male 239, 697, 1428
Peripheral Drive Rail 303, 1375
Peripheral Equipment Cardcage (AC/DC) 183, 601, 1413
Peripheral Equipment Module AC 183, 601, 1414
Peripheral Equipment Module DC 183, 601, 1414
Peripheral Equipment Module Package AC 25, 1562
Peripheral Equipment Module Package DC 25, 1562
Peripheral Equipment Module Power Distribution Unit 186, 613, 1416
Peripheral Equipment Power Supply AC 186, 600, 1413, 1602
Peripheral Equipment Power Supply DC 185, 570, 1406, 1596
Peripheral Equipment Shelf 1507, 1684
Peripheral Equipment Shelf (LH Mount) 1507, 1508, 1684, 1685
Peripheral Equipment Shelf (RH Mount) 1507, 1508, 1684, 1685
Peripheral Equipment Shelf 0 (LH Mount) 1507, 1684
Peripheral Equipment Shelf 1 (RH Mount) 1508, 1684
Peripheral Shelf Adapter 1676
Peripheral Shelf Assembly 1529, 1530
Peripheral Shelf Assembly-EMI 1529
Peripheral Signaling 183, 1177, 1503, 1679
PERP "A" Shelf Assembly 1543
Personal Computer (PC) Interface Card 1504, 1680
Personal Mailbox Administration 235, 245, 864, 1448
PFTU/Console Power Cable 67, 193, 693, 1427
Pigtail Jumper Block 1623
Planning and Engineering Guide - French 1670
Planning and Engineering NTP 1653
Planning and Installation Guide 1670
Planning Guide 1617
Plastic Guard - Cabinet Input (QBL10, QBL11, QBL13) 1642
Plastic Guard - Cabinet Input (QBL3, QBL5, QBL7, QBL8, QBL14) 1642
Plastic Guard - Converter Input (QBL10, QBL11) 1641

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Plastic Guard - Converter Input (QBL13) 1641
Plastic Guard - Converter Input (QBL14) (RPE) 1641
Plastic Guard - Converter Input (QBL3) 1642
Plastic Guard - Converter Input (QBL5) 1641
Plastic Guard - Converter Input (QBL7) 1641
Plastic Screws 1641
Platform Upgrade Guide for ACD-MAX 3, 4 and ACD-D Systems (to Release 6) 322, 353, 1487
Plug Adapter (QUW9) 1646
pnridian MAX Option 4 Software 1706
Portuguese Prompt-Bilingual 1702
Portuguese Prompt-Unilingual 1702
Position Busy Key Cap Package (50/PK) 206, 396, 1368
Post Installation Activities 1670
Powell DEC Cable 239, 249, 267, 390, 1367
Power & Signaling Cable (Tier 1 & 2) 1675
Power & Signaling Cable (Tier 3) 196, 1174, 1500, 1675
Power Adapter Cable 195, 196, 1172, 1173, 1499, 1673, 1674
Power Adapter Cable (RPE)/QBL14 1641
Power Backplane 1504, 1680
Power Bar - 6 Outlets - 2 Meters Cable Spare 282, 969, 1461
Power Board 239, 694, 1427
Power Cable 66, 188, 193, 510, 1388, 1427
Power Connector Cable (1st Module) 1674
Power Connector Cable (2nd Module) 196, 1173, 1499, 1674
Power Connector Cable (Basic) 196, 1173, 1499, 1674
Power Connector Cable (QRF12) 1674
Power Connector Cable (QSD73) 196, 1173, 1500, 1675
Power Connector Cable (QUAA3) 1674
Power Control (QCA55, QCA58, QCA108, QCA109, QCA96, QCA97) 1508, 1685
Power Control (QCA74) 1508, 1685
Power Control Shelf 1507, 1683
Power Converter (All Voltages) 1505, 1682
Power Converter Blank 1618
Power Converter Shelf (RH Mount) 1507, 1683
Power Cord - NEMA 5-15P to IEC 320, 6 Ft., 125V, 10A 296, 306, 392, 407, 1367, 1370
Power Cord AC (230V) 186, 605, 1415
Power Distribution Box 1499, 1671
Power Distribution Box (QCA10) 1499, 1671
Power Distribution Box (QCA14) 1499, 1671
Power Distribution Box (QCA23, QCA28) 1499, 1671
Power Distribution Box (QCA24) 1499, 1671
Power Distribution Box (QCA25) 1499, 1671
Power Distribution Box (QCA6, QCA28) 1499, 1671
Power Distribution Box (QCA8) 1499, 1671
Power Distribution Box (RPE) 1499, 1671
Power Distribution Panel - 4 1595
Power Distribution Panel - 8 1595
Power Distribution Unit 1398, 1499, 1582, 1671
Power Distribution Unit - Option 21A 1604
Power Distribution Unit (CDR) 1510, 1687
Power Distribution Unit (QCA10) 1509, 1687
Power Distribution Unit (QCA136) 1509, 1687
Power Distribution Unit (QCA137) 1509, 1687
Power Distribution Unit (QCA14) 1509, 1687
Power Distribution Unit (QCA147) 1509, 1687
Power Distribution Unit (QCA23) 1510, 1687
Power Distribution Unit (QCA24) 1509, 1687
Power Distribution Unit (QCA25) 1509, 1687
Power Distribution Unit (QCA6, QCA28) 1509, 1686
Power Distribution Unit (QCA60) 1509, 1687
Power Distribution Unit (QCA7) 1509, 1687
Power Distribution Unit (QCA8) 1509, 1687
Power Distribution Unit AC 186, 613, 1416, 1604
Power Distribution Unit DC 185, 542, 1399, 1410, 1412, 1599, 1600
Power Extension Cable 1643
Power Fail Transfer Cable (100 Ft.) 1674
Power Fail Transfer Cable (25 Ft.) 1674
Power Fail Transfer Cable (50 Ft.) 196, 1173, 1500
Power Fail Transfer Unit 196, 387, 1366, 1509, 1604, 1686
Power Harness 1591
Power Harness (NT2R24AA) 1582
Power Harness, Fan 1650
Power Harness, Fan (Short) 1650
Power Harness, Main 1650
Power Harness, Shelf 1650
Power Harness, Shelf (Short) 1650
Power Monitor Adapter 1499, 1671
Power Monitor Backplane 1582
Power Monitor Comm Cable 1582
Power Monitor Pack 183, 1179, 1506, 1683
Power Monitor PCBA 1384, 1571
Power Monitor Shelf 1582
Power Monitor/CE Auxiliary Shelf Assembly (Cantilever Mount) 1562
Power Monitor/CE Auxiliary Shelf Assembly (Center Mount) 1562
Power Monitor/CE Auxiliary Shelves 347, 1487
Power Monitor/Common Equipment Auxiliary Shelf (Cantilever) 1411, 1600
Power Monitor/Common Equipment Auxiliary Shelf (Center) 1411, 1600
Power Regulator Card 178, 576, 1408
Power Sense Monitor Kit 327, 590, 1411
Power Shelf Assembly-EMI (QSD10) 1542
Power Shunt Assembly for J2412A-1 Cabinet 1642
Power Supply 209, 384, 1365, 1399, 1401, 1548,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1587, 1588
Power Supply - 48V DC 185, 388, 1367
Power Supply (LANSTAR Cabinet) 1591
Power Supply 16V (BLF/CGM) 209, 388, 1367
Power Supply 350W Spare OIVR 4 AP, MRS/AP 283, 1461
Power Supply AC - 500 Watts 40, 221, 436, 1377
Power Supply Assembly 1406, 1595
Power Supply Board 1394, 1579
Power Supply Board Cable 1657
Power Supply Board Cable (M2000 Series) 209, 1148, 1483
Power Supply Board, (M2000 Series NT2K65 and NT2K40) 209, 528, 1394
Power Supply Cable 67, 193, 249, 702, 1430
Power Supply Package (LANSTAR Cabinet) 1638
Power Supply Spares Package AC 160, 342, 469, 1379
Power Supply Spares Package DC 160, 342, 470, 1379
Power Supply without 3.3V Output (3 Rail) Spare 282, 1461
Power Transformer, 15 Volt 1640
Power Unit 1509, 1686
Power Unit (Fan & Inverter) 1509, 1686
Power Unit (Fan) 1509, 1686
PowerView Banking ADSI Bill Payment - ADMS 1705
PowerView Banking ADSI Remote Banking - ADMS 1705
PowerView Banking DTMF Bill Payment - ADMS 1705
PowerView Banking DTMF Remote Banking - ADMS 1705
PowerView Banking Full Package - ADMS 1705
PRA Packaged Assembly 1525
Pre-Packaged Basic SL-1M System (No Lines, Trunks, Digitone or 1543
Pre-Packaged Executive SL-1S {40 (SL-1) Lines, 8 Trunks, 1 Console, 36 1526
Pre-Packaged Flexible 8x32 SL-1ST 1543
Pre-Packaged SL-1LE ACD System (32 Agent Lines, 40 ACD Trunks, Dual CPU) 1525
Pre-Packaged SL-1LE ACD System (32 Agents, 40 Trunks, and Single CPU) 1525
Pre-packaged SL-1LE Hotel/Motel System 1525
Pre-Packaged SL-1LE Hotel/Motel System (96 Lines, 12 Trunks, Digitone, 1525
Pre-Packaged SL-1LE System (100 Lines, 10 CO Trunks, 1 Digit Display 1525
Pre-Packaged SL-1LE Tandem System (8 Lines, 30 Trunks, Single CPU) 1525
Pre-Packaged SL-1M System (60 Lines, 10 Trunks, 1 Console/Digitone, 1543
Pre-Packaged SL-1MS (120 Lines, 20 Trunks, Digitone, 1 Console) 1526
Pre-Packaged SL-1MS (180 Lines, 28 Trunks, Digitone, 1 Console) 1526
Pre-Packaged SL-1MS (80 Lines, 16 Trunks, Digitone, 1 Console) 1526
Pre-Packaged SL-1MS ACD System (16 Terminal Lines, 20 ACD Trunks, 16 1526
Pre-Packaged SL-1MS Hotel/Motel System (180 Lines, 28 Trunks, Digitone, 1527
Pre-Packaged SL-1MS Hotel/Motel System (56 Lines, 12 Trunks, Digitone, 1526
Pre-Packaged Sl-1MS Hotel/Motel System(120 Lines, 20 Trunks, Digitone, 1527
Pre-Packaged SL-1N ACD System (32 Agent Lines, 40 ACD Trunks, Single 1525
Pre-Packaged SL-1N System (104 Lines, 10 CO Trunks, 1 Digit Display 1525
Pre-packaged SL-1N Tandem System (8 Lines, 30 Trunks, Single CPU, Half 1525
Pre-Packaged SL-1NT ACD System 1526
Pre-Packaged SL-1NT Hotel/Motel System (500 Lines) 1530
Pre-Packaged SL-1NT System 1526
Pre-packaged SL-1RT System 1544
Pre-Packaged SL-1S (56 Lines, 12 Trunks, Digitone, 1 Console) 1526
Pre-Packaged SL-1S 8x32 Digital System {8 CO Trunks, 24 Digital Lines 1527
Pre-Packaged SL-1S 8x32 SL-1 System {8 CO Trunks, 24 SL-1 Lines (23 SL-1 1527
Pre-Packaged SL-1S Hotel/Motel System {32 (500/2500) Message Waiting 1526
Pre-Packaged SL-1S Hotel/Motel System {48 (500/2500) Message Waiting 1527
Pre-Packaged SL-1S System {16 (500/2500) Lines, 16 (SL-1) Lines, 8 1526
Pre-Packaged SL-1S System {32 (500/2500) Lines, 24 (SL-1) Lines, 12 1526
Pre-Packaged SL-1S System {32 (500/2500) Lines, 8 Trunks, Digitone, 1526
Pre-Packaged SL-1S System {56 (500/2500) Lines, 12 Trunks, Digitone, 1 Console 1526
Pre-Packaged SL-1ST (52 Lines, 12 Trunks, Digitone, 1 Console) 1543
Pre-Packaged SL-1ST 8x32 System with Digital Sets {8 CO Trunks, 24 SL-1 1543
Pre-Packaged SL-1ST 8x32 System with SL-1 Sets {8 CO Trunks, 24 SL-1 1543
Pre-Packaged SL-1ST ACD System (16 Terminal Lines, 20 ACD Trunks, 16 1543
Pre-Packaged SL-1ST Hotel/Motel System (200 Lines) 1530
Pre-Printed Feature Key Cap Package (1 PK of 11 Key Caps, A0637619) 207, 468, 1379

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Pre-Printed Feature Key Cap Package (15 Packages of 11 Key Caps Each) 208, 557, 1403
PRI Package 159, 447, 1378
PRI Package (2nd Tier) 159, 448, 1378
PRI Package (Cabinet) 159, 448, 1378
PRI/DTI Echo Canceler to I/O Cable (6 Ft.) 192, 680, 1425
PRI/DTI I/O Cable (50 Ft.) 195, 1171, 1499, 1673
PRI/DTI I/O to MDF Cable (50 Ft.) 1605
PRI/DTI To Clock Controller Cable (10 Ft.) 190, 619, 1417
PRI/DTI To Clock Controller Cable (2 Ft.) 190, 619, 1417
PRI/DTI To Clock Controller Cable (4 Ft.) 190, 619, 1417
PRI/DTI To Clock Controller Cable (6 Ft.) 190, 619, 1417
PRI/DTI To Clock Controller Cable (8 Ft.) 190, 619, 1417
PRI/DTI to I/O Cable (4 Ft.) 1605
PRI/DTI to I/O Cable (6 Ft.) 191, 622, 1418
Primary Rate Access 153, 1246, 1516
Primary Rate Interface Card 183, 1179, 1506, 1682
Prime Power Cabinet (QCA13) J2412A-1 L6/18/27/28/29 1567
Prime Rectifier Cabinet Assembly 1562
Printer Cable (RS232) (18 In.) (Connects TDR to Printer) 1568
Priority Key Cap Package (50/PK) 1557
Privacy Release Key Cap Package (50/PK) 207, 399, 1368
Private ISDN Networking 98, 108, 119, 131, 139, 146, 1218, 1513, 1695
Private Networking (no DISA) Software Update 1700
Private Networking Software 698, 1428, 1429, 1612
Private Networking Software (Add. 100 TNs) 1699
Private Networking Software (no DISA) 699, 1429, 1613
Private Networking Software Update 1699
Processor 2M Assembly 1638
Processor 2MS Assembly 1638
Processor 4M Assembly 1638
Processor 4MS Assembly 1638
Processor 68000 1383, 1570
Processor 6M Assembly 1638
Processor 6MS Assembly 1638
Processor Cable 1582
Professional Billing Firmware Cartridge 1366, 1551
Program Key Cap Package (50/PK) 206, 397, 1368
Program Key Caps 1652
Programmable Data Adapter User Guide 1652
Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.01 59, 1441
Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 1.10 60, 1441
Programmed 40MB PCMCIA Flash Memory Card - Option 11C Compact Release 2.0 60, 1441
Prompt Manager and Loading Tool - 1 AP (or MRS/AP) 43, 277, 940, 1456
Prompt Transfer Tools Guide for AIU 1668
ProNET/Proteon Software 1550
Property Management Systems Interface 152, 1208, 1513
Protecting Your Voice Mail System Brochure 373, 1487
Protective Grommet (12-3/4 In. strip lengths) 1687
Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 110V Desk Mount 1365, 1548
Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 110V Rack Mount 1365, 1548
Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 220V Desk Mount 1365, 1548
Protocol Converter - (SL-1 System 36 Gateway) ASCII to SNA/SDLC 220V Rack Mount 1365, 1548
Protocol Converter - ASCII SNA/SDLC 220V Desk Mount 1365, 1548
Protocol Converter - ASCII SNA/SDLC 220V Rack Mount 1365, 1548
Protocol Converter - ASCII to Bisynchronous 110V Desk Mount 1365, 1548
Protocol Converter - ASCII to Bisynchronous 110V Rack Mount 1365, 1548
Protocol Converter - ASCII to Bisynchronous 220V Desk Mount 1365, 1548
Protocol Converter - ASCII to Bisynchronous 220V Rack Mount 1365, 1548
Protocol Converter - ASCII to SNA/SDLC 110V Desk Mount 1365, 1548
Protocol Converter - ASCII to SNA/SDLC 110V Rack Mount 1365, 1548
Protocol Converter SNA/SDLC SL-174 1365, 1547
Protocol Converter-ASCII SNA/SDLC 1364, 1547
Protocol Convertor SNA/SDLC SL-174 1364, 1547
Protocol Convertor-ASCII BISC 110V 1364, 1547
Protocol Convertor-ASCII BISC 220V 1364, 1547
Protocol Convertor-ASCII SNA/SDLC 1364, 1547
PS/2 MC Adapter Card 1399, 1587
Public ISDN Access 98, 108, 119, 131, 139, 146, 1219, 1513
PureSpeech Recite Development Kit - 1 AP RTU 43, 278, 946, 1457
Push Fastener for 50 Pin Connector Cover Plates 1645

Q

Q.Sig ISDN Networking Software 98, 108, 120, 131, 1233, 1234, 1515

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QAA29 1499, 1671
QAA33 1499, 1671
QAA47A 1499, 1671
QBK2 1671
QBL10 1671
QBL10B 1499, 1671
QBL11 1499, 1671
QBL12 1671
QBL12F 187, 1499
QBL13 1499, 1671
QBL14 1499, 1671
QBL15 1671
QBL15H 187, 1499
QBL16 1499, 1671
QBL21 1499, 1671
QBL24 1499, 1671
QBL26 1499, 1671
QBL3 1499, 1671
QBL5 1499, 1671
QBL6 1499, 1671
QBL7 1499, 1671
QBL8 1499, 1671
QBL9 1499, 1671
QCA13 Power System NTP (Set of 2) 346, 1483
QCA137 1671
QCA14 1671
QCA25 1671
QCA37 1671
QCA7 1671
QCA76 1671
QCA77 1671
QCA8 1671
QCAD109 1671
QCAD109A 195, 1171, 1499
QCAD110A 1671
QCAD110B 1672
QCAD111 1672
QCAD111A 195, 1499
QCAD112 1672
QCAD112B 1672
QCAD115 1672
QCAD116 1672
QCAD117 1672
QCAD118 1672
QCAD119 1672
QCAD120 1672
QCAD122A 1672
QCAD122B 1672
QCAD122C 1672
QCAD122D 1672
QCAD122E 1672
QCAD122F 1672
QCAD123A 1672
QCAD123B 1672
QCAD123C 1672
QCAD123D 1672
QCAD123E 1672
QCAD123F 1672
QCAD123G 1672
QCAD123H 1672
QCAD124A 1672
QCAD124B 1672
QCAD124C 1672
QCAD124D 1672
QCAD124E 1672
QCAD124F 1672
QCAD124G 1672
QCAD124H 1672
QCAD124J 1672
QCAD124K 1672
QCAD125 1673
QCAD125A 195, 1171, 1499
QCAD126 1673
QCAD128 1673
QCAD128A 195, 1171, 1499
QCAD129 1673
QCAD129A 195, 1171, 1499
QCAD130 1673
QCAD133 1673
QCAD133A 195, 1171, 1499
QCAD136 1673
QCAD137 1673
QCAD138 1673
QCAD138A 1673
QCAD139 1673
QCAD139A 195, 1172, 1499
QCAD141 1673
QCAD141A 1673
QCAD172 1673
QCAD172B 1673
QCAD176 1673
QCAD176A 1673
QCAD18 1673
QCAD18A 1673
QCAD190 1673
QCAD190A 195, 1172, 1499
QCAD191 1673
QCAD192 1673
QCAD193 1673
QCAD193A 195, 1172, 1499
QCAD194 1673
QCAD195 1673
QCAD196 1673
QCAD196A 195, 1172, 1499
QCAD197 1673
QCAD198 1673
QCAD199 1673
QCAD199A 1673

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QCAD200 1673
QCAD201 1673
QCAD206 1673
QCAD209 1673
QCAD209B 1674
QCAD240 1674
QCAD254 1674
QCAD25AA 196, 1172, 1499
QCAD273 1674
QCAD273A 1674
QCAD274 1674
QCAD274A 196, 1172, 1499
QCAD275 1674
QCAD275A 1674
QCAD276 1674
QCAD276A 1674
QCAD277 1674
QCAD277A 196, 1173, 1499
QCAD278 1674
QCAD278A 196, 1173, 1499
QCAD279 1674
QCAD279B 1674
QCAD283 1674
QCAD283A 1674
QCAD284 1674
QCAD284A 196, 1173, 1499
QCAD287 1674
QCAD287B 1674
QCAD290 1674
QCAD293A1 1674
QCAD294B1 1674
QCAD294B2 196, 1173, 1500
QCAD294B3 1674
QCAD295 1674
QCAD295A 1674
QCAD299A 1674
QCAD2A 1674
QCAD300A 1674
QCAD301 1674
QCAD301A 1674
QCAD302A1 1674
QCAD302A2 1674
QCAD302A3 1674
QCAD303 1674
QCAD303A 1675
QCAD304 1675
QCAD304A 1675
QCAD306 1675
QCAD306B 196, 1173, 1500
QCAD308 1675
QCAD308A 1675
QCAD309 1675
QCAD309A 196, 1173, 1500
QCAD310 1675
QCAD310A 196, 1174, 1500
QCAD311A1 1675
QCAD311A2 1675
QCAD311A3 1675
QCAD312A 1675
QCAD312B 1675
QCAD313 1675
QCAD313A 196, 1174, 1500
QCAD317 1675
QCAD318 1675
QCAD318A 196, 1174, 1500
QCAD319 1675
QCAD319A 196, 1174, 1500
QCAD320A 1675
QCAD320B 1675
QCAD321 1675
QCAD321A 187, 1174, 1500
QCAD325 1675
QCAD325A 196, 1174, 1500
QCAD328A 1675
QCAD328B 1675
QCAD328C 1675
QCAD328D 1675
QCAD332 1675
QCAD332A 196, 1175, 1500
QCAD333 1675
QCAD339 1675
QCAD349 1675
QCAD349A 1675
QCAD36 1675
QCAD37 1675
QCAD42 1675
QCAD42A 196, 1175, 1500
QCAD5A 1675
QCAD5B 1676
QCB12A 1676
QCB13A 1676
QCB7C 1676
QCB9A 1676
QCN100 1500, 1676
QCN101 1500, 1676
QCN102 1500, 1676
QCW2 1500, 1676
QCW3 1500, 1676
QCW4 1500, 1676
QFF1A 187, 1175, 1500
QFF1AB 187, 1175, 1500
QFF1B 187, 1175, 1500
QFF1C 187, 1176, 1500
QFF1D 187, 1176, 1500
QFF1E 187, 1176, 1500
QFF1F 187, 1176, 1500
QFF1G 187, 1176, 1500
QKK1 1500, 1676

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QKK3 1500, 1676
QKK8 1500, 1676
QKM12A 1676
QKM13A 1676
QKM176A 1676
QKM262A 1676
QKM289 1676
QKN1 1500, 1676
QMM38 1500, 1676
QMM42 1676
QMM43 1500, 1676
QMM45 1676
QMM45A 1500, 1676
QMT1 1500, 1676
QMT102 1501, 1676
QMT103 1501, 1676
QMT104 1501, 1676
QMT11 1676
QMT11 User Guide (15/PK) 1644
QMT11D 1501, 1676
QMT12 1676
QMT12E 1501, 1677
QMT15 1501, 1677
QMT2 1501, 1677
QMT21 1501, 1677
QMT21C1 1501, 1677
QMT3 1501, 1677
QMT4 1501, 1677
QMT7 1501, 1677
QMT8 1501, 1677
QMT8 Installation Card (15/PK) 1642
QMT9 1501, 1677
QPA57 1501, 1677
QPA58 1501, 1677
QPA59 1501, 1677
QPA62 1501, 1677
QPC130 1501, 1677
QPC131 1501, 1677
QPC132 1501, 1677
QPC135 1501, 1677
QPC136 1501, 1677
QPC137 1501, 1677
QPC138 1501, 1677
QPC139B 1501, 1677
QPC155 1501, 1677
QPC156 1501, 1677
QPC157 1501, 1677
QPC158 1501, 1677
QPC162 1501, 1677
QPC163 1501, 1677
QPC164 1501, 1677
QPC167 1501, 1678
QPC171 1501, 1678
QPC187 1501, 1678
QPC188D 1502, 1678
QPC189 1502, 1678
QPC190 1502, 1678
QPC192 1502, 1678
QPC197D 1502, 1678
QPC199 1502, 1678
QPC212 1502, 1678
QPC213 1502, 1678
QPC214 1502, 1678
QPC215 1678
QPC215D 1502, 1678
QPC216 1502, 1678
QPC218 1502, 1678
QPC219 1502, 1678
QPC220 1502, 1678
QPC228 1502, 1678
QPC237E 1502, 1678
QPC239 1502, 1678
QPC240 1502, 1678
QPC241 1502, 1678
QPC246 1502, 1678
QPC247 1678
QPC247A 182, 1502
QPC248 1502, 1678
QPC250 1502, 1678
QPC251 1502, 1678
QPC264 1502, 1678
QPC267 1502, 1678
QPC268 1502, 1678
QPC271 1502, 1678
QPC274 1502, 1678
QPC297 1502, 1678
QPC298 1502, 1679
QPC30 1502, 1679
QPC300 1502, 1679
QPC301 1503, 1679
QPC31 1503, 1679
QPC311 1503, 1679
QPC32 1503, 1679
QPC33 1503, 1679
QPC353 1503, 1679
QPC362 1503, 1679
QPC374 1503, 1679
QPC376 1503, 1679
QPC387 1503, 1679
QPC39 1503, 1679
QPC397 1503, 1679
QPC40 1503, 1679
QPC41 1503, 1679
QPC411 1503, 1679
QPC412C 1503, 1679
QPC414 1679
QPC414C 183, 1177, 1503
QPC417 1679

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QPC417A 183, 1503
QPC42 1503, 1679
QPC420 1503, 1679
QPC422 1503, 1679
QPC423 1503, 1679
QPC424 1503, 1679
QPC425 1503, 1679
QPC426 1503, 1679
QPC43 1679
QPC430 1503, 1679
QPC432 1503, 1679
QPC43R 183, 1177, 1503
QPC44 1503, 1679
QPC441 1679
QPC441F 183, 1177, 1503
QPC443 1503, 1680
QPC444 1680
QPC444A 183, 1177, 1503
QPC449C 1503, 1680
QPC45 1503, 1680
QPC450G 1503, 1680
QPC451 1503, 1680
QPC452 1503, 1680
QPC46 1504, 1680
QPC464 1504, 1680
QPC471 1680
QPC471H 183, 1178, 1504
QPC472 1504, 1680
QPC477 1680
QPC477A10 1504, 1680
QPC477A9 183, 1178, 1504
QPC477B10 183, 1178, 1504
QPC478 1504, 1680
QPC479 1504, 1680
QPC486 1504, 1680
QPC487 1504, 1680
QPC494A 1504, 1680
QPC496 1680
QPC496A 1504, 1680
QPC50 1504, 1680
QPC500 1504, 1680
QPC501 1504, 1680
QPC502 1504, 1680
QPC503 1504, 1680
QPC509 1504, 1680
QPC51 1504, 1680
QPC512 1504, 1680
QPC513 1680
QPC513H 1504, 1680
QPC52 1504, 1680
QPC53 1504, 1680
QPC54 1504, 1680
QPC55 1504, 1680
QPC552 1504, 1681
QPC553 1504, 1681
QPC554 1504, 1681
QPC555 1504, 1681
QPC556 1504, 1681
QPC557 1504, 1681
QPC571 1504, 1681
QPC573 1505, 1681
QPC574B 1505, 1681
QPC578 1681
QPC578D 26, 1505, 1681
QPC579 1505, 1681
QPC580 1505, 1681
QPC581 1505, 1681
QPC583 1505, 1681
QPC584 1681
QPC584M 183, 1178, 1505
QPC585A 1505, 1681
QPC594 1505, 1681
QPC599 1505, 1681
QPC60 1505, 1681
QPC600 1505, 1681
QPC601 1505, 1681
QPC602 1505, 1681
QPC609 1681
QPC609D 1505, 1681
QPC61 1505, 1681
QPC62 1505, 1681
QPC63 1505, 1681
QPC64 1505, 1681
QPC65 1505, 1681
QPC659 1681
QPC659E 1505, 1681
QPC66 1505, 1681
QPC662 1505, 1681
QPC67 1505, 1682
QPC672 1505, 1682
QPC673 1505, 1682
QPC674 1505, 1682
QPC687 1505, 1682
QPC691 1505, 1682
QPC699 1505, 1682
QPC70 1505, 1682
QPC700 1505, 1682
QPC701 1682
QPC701A1 1505, 1682
QPC702 1682
QPC702A1 183, 1505
QPC705 1505, 1682
QPC706 1505, 1682
QPC709 1506, 1682
QPC710 1682
QPC710A 1506, 1682
QPC717 1506, 1682
QPC71H 1506, 1682

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QPC72 1506, 1682
QPC720 1682
QPC720F 183, 1179, 1506
QPC723A 1506, 1682
QPC73 1506, 1682
QPC742F 1506, 1682
QPC74C 1506, 1682
QPC75 1506, 1682
QPC755 1682
QPC757 1506, 1682
QPC78 1506, 1682
QPC782 1506, 1682
QPC789 1682
QPC789A 1506, 1682
QPC79 1506, 1682
QPC80H 1506, 1682
QPC814 1506, 1683
QPC82E 1506, 1683
QPC84 1683
QPC841 1683
QPC841C 183, 1179, 1506
QPC84S 183, 1179, 1506
QPC85 1506, 1683
QPC916 1683
QPC918 1506, 1683
QPC930 1506, 1683
QPC937 1506, 1683
QPC939 1506, 1683
QPC940 1506, 1683
QPC99 1506, 1683
QPF23 1683
QPF23A 187, 1179, 1506
QPF36 1683
QPF36B 187, 1180, 1506
QPF37 1683
QRF12 1506, 1683
QRF8 1506, 1683
QRF9 1506, 1683
QSAM3 1683
QSD1 1507, 1683
QSD10 1507, 1683
QSD11 1507, 1683
QSD12 1507, 1683
QSD13 1507, 1683
QSD14 1507, 1683
QSD15 1507, 1683
QSD16 1507, 1683
QSD17 1507, 1683
QSD18 1507, 1683
QSD19 1507, 1683
QSD2 1507, 1683
QSD23 1507, 1683
QSD26 1507, 1683
QSD27 1683
QSD27A 1507, 1684
QSD3 1507, 1684
QSD31 1507, 1684
QSD32 1507, 1684
QSD33 1507, 1684
QSD34 1507, 1684
QSD35 1507, 1684
QSD36 1507, 1684
QSD37 1507, 1684
QSD39 1507, 1684
QSD4 1507, 1684
QSD40 1507, 1684
QSD54 1507, 1684
QSD55 1507, 1684
QSD58 1507, 1684
QSD59 1507, 1684
QSD6 1507, 1684
QSD60 1507, 1684
QSD61 1507, 1684
QSD62 1507, 1684
QSD64 1507, 1684
QSD65 1684
QSD65A 26, 1507, 1684
QSD66 1507, 1684
QSD67 1508, 1684
QSD68 1508, 1684
QSD69 1684
QSD7 1508, 1684
QSD73 1508, 1684
QSD76 1508, 1684
QSD79B 1508, 1684
QSD80 1508, 1684, 1685
QSD81A 1508, 1685
QSD82 1508, 1685
QSD83 1508, 1685
QSD9 1508, 1685
QSP31 1508, 1685
QSP32 1508, 1685
QSP35 1508, 1685
QSP36 1508, 1685
QSP39 1508, 1685
QSP40 1508, 1685
QSP41 1508, 1685
QSP43 1508, 1685
QSP44 1508, 1685
QSP45 1508, 1685
QSP6 1508, 1685
QSP7 1508, 1685
QSR2F1 1508, 1685
QSR2G1 1508, 1685
QSU1 1508, 1685
QSU3 1508, 1685
QSU60 1508, 1685
QSU61 1508, 1685

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

QSU7 1508, 1685
QSU71B35 1508, 1685
QSU71B93 1508, 1686
QSU71C35 1508, 1686
QSU71C93 1509, 1686
QSY19 1509, 1686
QSY22 1509, 1686
QSY22 Mounting Bracket 1643
QSY22 Mounting Bracket (LH) 1643
QSY22 Mounting Bracket (RH) 1643
QSY27 1686
QSY27A 1509, 1686
QUA1 1509, 1686
QUA4A1 1686
QUA5A 1509, 1686
QUA6 1686
QUA6A 1509, 1686
QUAA3 1686
QUAA3C 1509, 1686
QUAA5 1686
QUAA5A 1509, 1686
Quad SDI Paddle Board 178, 1415
Quality Assurance Overview 1650
Quality Audio-Visual 1570
QUD1 1509, 1686
QUD15 1509, 1686
QUD20B 1686
QUD24 1509, 1686
QUD25 1509, 1686
QUD3 1509, 1686
QUD4 1509, 1686
QUD5 1509, 1686
QUD6 1509, 1686
QUD8 1509, 1686
QUD9 1509, 1686
Quick Installation Pre-Printed Keycaps (10 Cards of 10 Pre-Printed Keycaps) 209, 1150, 1483
Quick Reference Guide - Black Binder 375, 1490
Quiet Print 1569
QUT1 1509, 1686
QUT2 1509, 1686
QUT3 1509, 1686
QUW1 1509, 1686
QUW3 1509, 1686
QUW9 1509, 1686
QUX1 1509, 1686
QUX10 1509, 1687
QUX11 1509, 1687
QUX16 1509, 1687
QUX19 1509, 1687
QUX2 1509, 1687
QUX20 1509, 1687
QUX21 1509, 1687
QUX22 1509, 1687
QUX3 1509, 1687
QUX4 1509, 1687
QUX5 1509, 1687
QUX6 1510, 1687
QUX9 1510, 1687

R

R001 1687
R0059715 1687
Rack 24 Balun 1548
Rack AP or MRS/Rack Server-to-Switch Box Cable Spare 283, 1462
Rack Rails 39, 221, 1376
Rackmount Cabinet for MRS/Rack - 21" Spare 282, 968, 1461
Rackmount Keyboard Drawer Spare 282, 966, 1460
Rackmount NT1 Star Card 1616
Reach Line Card - 16 Port 333, 716, 1433
Reach Line Card - 32 Port - Option 11 333, 717, 1433
Reach Line Card - 32 Port - Option 51-81 333, 716, 1433
Reach Line Card Cable - Basic Version 333, 717, 1433
Reach Line Card Cable - Enhanced Version 333, 718, 1433
Read Me First Card 1655
Read Me First Card (10/PK) 1656, 1658
Read Me First Handbook 1665
Ready to Use Fee/Meridian Mail PC Software 1536
Real Time Clock & ROM 1501, 1502, 1678
Rear Door Assembly (NT2R02AA) 1583
Rear Mount Conduit/Wiring Kit 183, 197, 588, 1410
Receiver Unit (SL-1 Handset) 1547
Recorded Announcement Broadcast 99, 109, 121, 1235, 1515
Recorder Announcement Trunk 1506, 1682
Rectifier Assembly 1562
Rectifier Card for J-2357D-1, List 1 Rectifier 1566
Rectifier Card for the J-2357D-1, list 3 Rectifier 1566
Rectifier Control (QSD4) 1506, 1682
Rectifier Cords, 15 Amp, 125V 1674
Rectifier Cords, 20 Amp, 225V 196, 1172, 1499, 1674
Rectifier Cords, 30 Amp, 125V 1674
Rectifier Input Cable 1582
Rectifier J-2357D-1, List 3 for the J-2412A Cabinet (B0210372-B0205582) 1382, 1566
Rectifier Rack 186, 589, 1411
Rectifier Rack Assembly 159, 451, 452, 1378, 1561
Rectifier Support/Air Baffle 186, 589, 1411
Rectifier Wiring Kit 186, 575, 1407
Rectifier, 100 Amp 185, 387, 1366

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Rectifier, 50 Amp 1401, 1589
Rectifier, -52V/30 Amp 1407, 1596
Redundant 500W DC Power for MRS/RACK or Rack AP 1625
Redundant AC Power for Base MRS/Rack or Rack AP 277, 938, 1456
Redundant DC Power for Base MRS/Rack or Rack AP 277, 938, 1456
Redundant Power Supply for DC-powered MRS/Rack 1558
Reference Manual for 100A Rectifier (A0354954) 1654
Reference Manual for NT6D82 Power System 1654
Regional Supplement to Base AP - North America 276, 935, 1455
Regional Supplement to Base MRS/AP - North America 277, 939, 1456
Regional Supplement to Base MRS/Rack (AC or DC) - North America 277, 939, 1456
Regional Supplement to Base MRS/Tower - North America 277, 937, 1456
Registrar Front Desk Software with Billing 61, 63, 75, 802, 1437
Registrar User Guide 60, 1493
Regular Telephone User Guide 1662
Regular Telephone User Guide (15/PK) 1646, 1660
Relay Rack 1596
Relay Rack (23 In. x 7 Ft.) 1547
Release 17 to Release 18 (with Option 18) NTP Update Package 1659
Release 18 (non-Option 81) to Release 18 (with Option 81) NTP Upgrade Package 1659
Release 2.X Development to Release 4.0 Development Upgrade 281, 959, 1459
Release 20 Data Input Forms 353, 1487
Release 20 Software Cartridge - Enhanced 1615
Release 20 Software Cartridge - Enhanced (No DISA) 1615
Release 20 Software Cartridge - Enterprise 1615
Release 20 Software Cartridge - Enterprise (No DISA) 1615
Release 20 Software Cartridge - General 1615
Release 20 Software Cartridge - General (No DISA) 1615
Release 20 Software Cartridge - Network Attendant Service 1616
Release 20 Software Cartridge - Network Attendant Service (No DISA) 1616
Release 21 Data Input Forms 1663
Release 21 Software Cartridge - Enhanced (No DISA) 91, 706, 1430, 1615
Release 21 Software Cartridge - Enhanced Business Package 90, 705, 1430, 1615
Release 21 Software Cartridge - Enterprise (No DISA) 1615
Release 21 Software Cartridge - Enterprise Business (No DISA) 91, 706, 1430, 1616
Release 21 Software Cartridge - Enterprise Business Package 91, 705, 1430, 1615
Release 21 Software Cartridge - General (No DISA) 91, 705, 1430, 1615
Release 21 Software Cartridge - General Business Package 84, 705, 1430, 1615
Release 21 Software Cartridge - Network Attendant Service (NAS) 1616
Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package 91, 706, 1430, 1616
Release 21 Software Cartridge - Network Attendant Service (NAS)/Virtual Network Services (VNS) Package (No DISA) 92, 706, 1430, 1616
Release 21 Software Cartridge - Network Attendant Service (No DISA) 1616
Release 21 Update package 1663
Release 24.24 Programmed Mini System Controller Pack 1451, 1624
Release 25 Programmed Mini System Controller Pack 68, 1451
Release 25A US Enhanced Business Feature Set 1451
Release 25A US Enterprise Business Feature Set 1451
Release 25A US General Business Feature Set 28, 1451
Release 25A US NAS/VNS Feature Set 28, 1451
Release 3.0 Base Software and Documentation 297, 677, 1424
Release Key Cap Package (50/PK) 207, 401, 1368
Release Key Caps 1652
Release Line Trunk 1502, 1678
Remote Agent 1 Year Support 1695
Remote Agent Hardware and Documentation 1574
Remote Agent Hardware, FastView Software and Documentation Marketing Package #2 1574
Remote Agent Hardware, FastView Software and Documentation Marketing Package #6 1574
Remote Agent Hardware, FastView Software and Documentation Marketing Package #7 1574
Remote Agent Hardware, FastView Software, MCA, M2216 and Documentation (Marketing Package #4) 1574
Remote Agent Hardware, FastView+ Software and Documentation Marketing Package #3 1574
Remote Agent Hardware, FastView+ Software, MCA, M2216 and Documentation (Marketing Package #5) 1574
Remote Agent Hardware, M2216 and Documentation Marketing Package #1 1574
Remote Agent Install PREP 1694
Remote Agent Install Prep 1695

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Remote Agent Installation PRO 1694, 1695
Remote Agent One Year Support 1694
Remote Asynchronous Dial-In (NA100) 1550
Remote Cable Kit 188, 510, 1388
Remote Carrier Cabinet Panel Assembly 1602
Remote Carrier Interface Card 178, 598, 1412, 1602
Remote Carrier Shelf Assembly 1541
Remote Carrier/Alarm Cabinet Cable Assembly 1602
Remote Carrier/Alarm Cable Assembly 161, 599, 1413
Remote Digital Extender Card 1431, 1616
Remote Fiber Multi-IPE Assembly - Multi Mode (1-2 Superloops) 160, 462, 1379
Remote Fiber Multi-IPE Assembly - Multi Mode (1-4 Superloops) 160, 464, 1379
Remote Fiber Multi-IPE Assembly - Single Mode (1-2 Superloops) 160, 460, 1379
Remote Fiber Multi-IPE Assembly - Single Mode (1-4 Superloops) 160, 463, 1379
Remote FRMII Cable (30 ft.) 187, 405, 1370
Remote Maintenance Cabinet Cable Assembly 1602
Remote Maintenance Cable Assembly 161, 599, 1413
Remote Mini Carrier Interface Cable 66, 183, 1403
Remote Mini Carrier Interface Card 66, 177, 1403, 1590
Remote Network Interface Assembly 1541
Remote Office 9110 4-User Expansion Package - 16 RLC 31, 333, 835, 1443
Remote Office 9110 4-User Starter Package - 16 RLC 31, 333, 835, 1443
Remote Office 9110 Unit with North American Power Supply 31, 333, 835, 1443
Remote Office 9115 4-User Expansion Package - 16 RLC 31, 333, 834, 1443
Remote Office 9115 4-User Starter Package - 16 RLC 31, 333, 834, 1443
Remote Office 9115 Unit with North American Power Supply 31, 333, 836, 1443
Remote Office 911x North American Power Supply 31, 333, 719, 1433
Remote Office 911x User Guide 31, 334, 719, 1433
Remote Office 9150 8-User Expansion Package 47, 333, 833, 1443
Remote Office 9150 8-User Starter Package - 16 RLC 47, 333, 832, 1443
Remote Office 9150 8-User Starter Package - 32 RLC Option 11 47, 333, 832, 1443
Remote Office 9150 8-User Starter Package - 32 RLC Option 51-81 47, 333, 832, 1443
Remote Office 9150 8-User VoIP Package - 16 RLC 47, 333, 831, 1443
Remote Office 9150 Branch Expansion Package 47, 333, 833, 1443
Remote Office 9150 Installation and Administration Guide 47, 334, 719, 1433
Remote Office 9150 Unit 47, 333, 716, 1433
Remote Office 9150 Universal Power Supply 47, 333, 719, 1433
Remote Office Product CD-ROM Package 47, 334, 718, 1433
Remote Office Technical Training CD-ROM Package 47, 334, 718, 1433
Remote Peripheral Equipment Guide 346, 1438, 1661, 1663, 1664, 1665, 1667
Remote Peripheral Equipment Guide, Release 24 and Earlier 348, 1495
Remote Peripheral Switch (RPE) 1505, 1681
Remote RPE Expansion Shelf Power Cable 1674
Remote RPE Expansion Tier (with MDF Assembly) 1544
Remote RPE/PE Expansion Tier Package 1544
Remote Software Option 97, 107, 119, 131, 138, 1216, 1513
Replacement Battery (For NTAK75AA/AB) 66, 185, 402, 1369
Replacement Processor Installation Kit 1560
Resale-of-Services Software Package 1527
Reservations Software 1588
Ribbon Cable (0.5 Ft.) 1642
Ribbon Cable (QSD31) 1547
Ribbon Cable, RS232, (Male/Male) 25 Pin, Straight-Through (6 Ft.) 195, 1141, 1481
Right Door Panel Assembly 1645
Right Front Panel Assembly 1639
Right Mounting Bracket 1643
Right Side Panel 1645
Right to Use Fee/Meridian Mail MP Access Software 1536
RILC - RS232C Interface Line Card 1506, 1682
RILC Patch Panel 1550
Ring Again Key Cap Package (50/PK) 207, 401, 1368
Ringing Generator 1501, 1678
Ringing Generator AC 186, 602, 1414, 1603
Ringing Generator DC 185, 571, 1406, 1407, 1410, 1596, 1599
RJ11 Adapter for PJ327 Phone 1555
RJ45 Cable 187, 387, 1367
RJ45/RS232 Connector 196, 402, 1369
Rls 24C Software Service Transaction Fee for upgrades from Rls 24 to 24C (25.08) 33, 42, 156, 897, 1451
Rolm Connections Hardware Kit 1367, 1556
ROM 2 Module 1502, 1678
ROM 3 Module 1502, 1678
ROM Card 1442, 1443, 1504, 1505, 1506, 1622, 1680, 1681, 1682, 1683
ROM Card (Memory Enhancement) 1505, 1681
RPE 153, 1209, 1513

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

RPE - Remote Package AC 1562
RPE - Remote Package DC 1562
RPE Cabinet Assembly - Remote (Network Carrier Shelf, 10 PE Card Slots, 1544
RPE Cabinet Assembly - Remote (with MDF Assembly) 1544
RPE Carrier Module Assembly AC 1562
RPE Carrier Module Assembly DC 1562
RPE Carrier Module DC 1604
RPE Expansion Tier 1684
RPE to I/O Cable (2 Ft.) 1610
RS232 - V.35 Adapter Cable for HSDM (Female) 187, 381, 1365
RS232 - V.35 Adapter Cable for HSDM (Male) 187, 381, 1365
RS232 - V.35 Adapter Cable for MCA/MCU (Female) 192, 1419, 1557
RS232 - V.35 Adapter Cable for MCA/MCU (Male) 192, 1419, 1557
RS232 Cable 1570
RS232 Interface Guide (15/PK) 351, 1481
RS232 Modem Cable 1570
RS232 Modem Cable (NM120) 1549
RS232 Modem Pool Cable 1675, 1676
RS232 Null Modem Cable (10 Ft.) 268, 829, 1443
RS232 Null Modem Cable (25 Ft.) 268, 272, 1443
RS232 Null Modem Cable (50 Ft.) 1570
RS232 Straight Cable (10 Ft.) 249, 268, 829, 1443, 1554
RS232 Straight Cable (25 Ft.) 249, 268, 829, 1443, 1554
RS232C Service Module 240, 266, 546, 695, 1400, 1428, 1588, 1612
RS232-Y Cable 268, 573, 1407
RSM 4 Port Breakout Cable 249, 268, 713, 1432
RSM Alarm Adapter Cable 267, 548, 1401
RSM Cable 33, 239, 267, 268, 549, 571, 1401, 1407, 1451, 1588
RSM Cable (50 Ft.) 267, 547, 1400
RSM Fanout Cable (25 Ft.) 267, 547, 1400
RSM Installation Kit - Modular 269, 634, 1420
RT Clock Chip 274, 284, 1371
RT Floppy Disk Unit, Memory and ROM Upgrade Package 1717
RT/NT/XT/61/71 Multi-Disk Unit, Memory and ROM Upgrade Package 1717
Rubber Feet (100 each, for all Meridian Digital Telephones) 210, 1170, 1499, 1671
Runtime System Upgrade Package Release 2.08 to Release 2.2 922, 1454

S

S/T Interface Line Card (SILC) 64, 177, 575, 1408
S0005899 317, 318, 1180, 1510
S0005901 317, 318, 1180, 1510
S0005906 317, 1181, 1510
S0005907 318, 1181, 1510
S0005908 317, 1181, 1510
S0311110 1687
S0311850 1687
S0411110 1687
S0411850 1687
S0611110 1687
S0611850 1687
S0711095 1687
S0711098 1687
S0711100 1687
S0711101 1687
S0711102 1687
S0711103 1687
S0711105 1687
S0711107 1687
S0711108 1687
S0711109 1687
S0711110 1687
S0711111 1687
S0711113 1687
S0711115 1688
S0711116 1688
S0711119 1688
S0711150 1688
S0711151 1688
S0711837 1688
S0711850 1688
S0811095 1688
S0811098 1688
S0811100 1688
S0811101 1688
S0811102 1688
S0811103 1688
S0811105 1688
S0811107 1688
S0811108 1688
S0811109 1688
S0811110 1688
S0811111 1688
S0811113 1688
S0811115 1688
S0811116 1688
S0811119 1688
S0811150 1688
S0811151 1688
S0811157 1688
S0811170 1688

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

S0811837 1688
S0811850 1688
S0811851 1688
S0890001 1688
S0890002 1688
S0890003 1688
S0890004 1688
S0890005 1689
S0890006 1689
S0911095 1689
S0911098 1689
S0911100 1689
S0911101 1689
S0911102 1689
S0911103 1689
S0911105 1689
S0911107 1689
S0911108 1689
S0911109 1689
S0911110 1689
S0911111 1689
S0911113 1689
S0911115 1689
S0911116 1689
S0911119 1689
S0911150 1689
S0911151 1689
S0911153 1689
S0911157 1689
S0911170 1689
S0911837 1689
S0911850 1689
S0911851 1689
S0990001 1689
S0990002 1689
S0990003 1689
S0990004 1689
S0990005 1689
S0990006 1689
S1011000 1689
S1011001 1689
S1011091 1690
S1011095 1690
S1011098 1690
S1011100 1690
S1011101 1690
S1011102 1690
S1011103 1690
S1011105 1690
S1011107 1690
S1011108 1690
S1011109 1690
S1011110 1690
S1011111 1690
S1011112 1690
S1011113 1690
S1011115 1690
S1011116 1690
S1011119 1690
S1011150 1690
S1011151 1690
S1011153 1690
S1011157 1690
S1011170 1690
S1011785 1690
S1011837 1690
S1011850 1690
S1011851 1690
S1090001 1690
S1090002 1690
S1090003 1690
S1090004 1690
S1090005 1690
S1090006 1690
S1111091 1690
S1111095 1691
S1111098 1691
S1111100 1691
S1111101 1691
S1111102 1691
S1111103 1691
S1111105 1691
S1111107 1691
S1111108 1691
S1111109 1691
S1111110 1691
S1111111 1691
S1111112 1691
S1111113 1691
S1111115 1691
S1111116 1691
S1111119 1691
S1111150 1691
S1111151 1691
S1111153 1691
S1111157 1691
S1111170 1691
S1111785 1691
S1111837 1691
S1111850 1691
S1111851 1691
S1190001 1691
S1190002 1691
S1190003 1691
S1190004 1691
S1190005 1691
S1190006 1691
S1211091 1691

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

S1211095 1691
S1211098 1692
S1211100 1692
S1211101 1692
S1211102 1692
S1211103 1692
S1211105 1692
S1211107 1692
S1211108 1692
S1211109 1692
S1211110 1692
S1211111 1692
S1211112 1692
S1211113 1692
S1211115 1692
S1211116 1692
S1211119 1692
S1211150 1692
S1211151 1692
S1211153 1692
S1211157 1692
S1211170 1692
S1211785 1692
S1211837 1692
S1211850 1692
S1211851 1692
S1290001 1692
S1290002 1692
S1290003 1692
S1290004 1692
S1290005 1692
S1290006 1692
S1311095 1692
S1311098 1692
S1311100 1692
S1311101 1693
S1311102 1693
S1311103 1693
S1311105 1693
S1311107 1693
S1311108 1693
S1311109 1693
S1311110 1693
S1311111 1693
S1311113 1693
S1311115 1693
S1311116 1693
S1311119 1693
S1311150 1693
S1311151 1693
S1311153 1693
S1311157 1693
S1311170 1693
S1311837 1693
S1311850 1693
S1311851 1693
S1390001 1693
S1390002 1693
S1390003 1693
S1390004 1693
S1390005 1693
S1390006 1693
S7S11087 1693
S8311087 1693
S9611087 1693
Sales Trifold-ENFS SCCS Server Hardware & Software Installation 369, 1495
Sales Trifold-ENFS SCCS Server Maintenance 369, 1495
Sales Trifold-ENFS SCCS Service Overview 369, 1495
Sales Trifold-ENFS SCCS Site Readiness Evaluation 369, 1495
Sales Trifold-SPS CTI Assessment and Design 370, 1165, 1495
Sales Trifold-SPS SCCS Call Center Business Assessment 373, 1165, 1495
Sales Trifold-SPS SCCS Callflow Design/Database Preparation 369, 1495
Sales Trifold-SPS SCCS HDX Design & Implementation 373, 1165, 1495
Sales Trifold-SPS SCCS Migration Analysis 370, 1165, 1495
Sales Trifold-SPS SCCS Post Production Review 370, 1166, 1495
Sales Trifold-SPS SCCS Project Management 370, 1166, 1495
Sales Trifold-SPS SCCS Remote Database Entry 370, 1166, 1495
Sales Trifold-SPS SCCS Script Design & Implementation 370, 1166, 1495
Sales Trifold-SPS SCCS Supervisor Workshop 370, 1166, 1495
Same Day Shipment per Order Expedite Fee 325, 1510
SBC for High Performance MRS/AP, AP, and MRS 1624
SCCS Marketing Package, Windows NT 4.0 Client 307, 1064, 1471
SCCS Software Assembly, Release 24 X11 PEP CD-ROM 307, 1425
SCCS Software Upgrade Package for Individual Agents, R1.0/R1.1/R1.5 to R3.0 298, 1093, 1473
SCCS Software Upgrade Package, R1.0 to R3.0 298, 1064, 1471
SCCS Software Upgrade Package, R1.1/1.5 to R3.0 298, 1063, 1471
SCO IPX/SPX LAN Integration Software 1628
Screw 1647

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Screw Package 1570
SCSI 3.5 DAT Tape Drive 304, 305, 855, 1446
SCSI 4.5GB Hard Drive for OIVR 4.0 MRS/Rack and Rack AP 276, 281, 934, 1455
SCSI 4.5GB Hard Drive for OIVR 4.0 Tower AP, MRS/AP, MRS/Tower 276, 281, 934, 1455
SCSI Adapter 39, 221, 432, 1375, 1561
SCSI Backplane Spare OIVR 4 MRS/Rack or Rack AP 282, 1461
SCSI Cable 268, 571, 1407
SCSI Cable (6 Ft.) 40, 239, 694, 1427
SCSI CD ROM Drive Spare 1460, 1626
SCSI CD-ROM Drive 305, 854, 1446
SCSI CD-ROM Drive for AP, MRS/AP, MRS/Tower, MRS/Rack 276, 281, 934, 1455
SCSI Connector 1561
SCSI Daisychain Cable 268, 1144, 1481
SCSI DAT Tape Drive for AP, MRS/AP, MRS/Tower, MRS/Rack 276, 281, 934, 1455
SCSI Rack Drive Carrier (each) Spare OIVR 4 283, 1461
SCSI RAID Controller 41, 224, 307, 855, 1446
SCSI RAID Drivers 221, 1446
SCSI RAM 1399, 1587
SCSI Tape Cable 1649
SCSI Termination, Active 327, 417, 1372
SCSI Terminator 240, 250, 392, 1367
SCSI/Backplane Cable 268, 572, 1407
SCSI/Daisy Chain Cable 268, 573, 1407
SDI Adapter Plate Package 186, 1147, 1482
SDI Cable 67, 193, 693, 1427
SDI Cable (10 Ft.) 328, 594, 1412, 1600
SDI Cable (2 Ft.) 328, 594, 1411, 1600
SDI Cable (20 Ft.) 328, 594, 1412, 1600
SDI Cable (35 Ft.) 328, 595, 1412, 1600
SDI Cable (45 Ft.) 328, 595, 1412, 1600
SDI Cable (6 Ft.) 328, 594, 1412
SDI Cable (6 ft.) 1600
SDI Cable Kit (10 Ft.) 189, 335, 1412, 1433
SDI I/O Cable 328, 591, 1411
SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Female) 191, 628, 1419
SDI I/O to DTE/DCE Cable (16 Ft.) (Male/Male) 191, 628, 1418
SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Female) 192, 629, 1419
SDI I/O to DTE/DCE Cable (34 Ft.) (Male/Male) 191, 628, 1419
SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Female) 192, 629, 1419
SDI I/O to DTE/DCE Cable (48 Ft.) (Male/Male) 191, 628, 1419
SDI Multi-Port Cable (2 Ft.) 192, 629, 1419
SDI Multi-Port Extension Cable (10 Ft.) 191, 625, 1418
SDI Paddleboard to I/O Cable (18 In.) 191, 622, 1418
SDI to I/O Cable (4 Ft.) 1605
SDI to I/O Cable (6 Ft.) 191, 622, 1418
SDI/DCH Card 67, 178, 693, 1427, 1611
SDI/DCH Package 65, 159, 448, 1378
SDI/Peripheral Signaling Card with Battery 1442, 1622
Seamless Transition to ISDN BRI Brochure 367, 1486
Second Rectifier O/P Cable 1597
Secured Messaging Software 245, 256, 1253, 1516
Security Data Cartridge 1676
Security Device Holder 197, 543, 1400
SEER Cable 1582
Segmented Bus Extender 1502, 1678
Segmented Network Shelf 0 1507, 1683
Segmented Network Shelf 1 1507, 1683
Seismic Anchor Kit 1597
Seismic Bracing Anchor Kit (Bellcore) 184, 1416
Seismic Bracing Anchor Kit (OSHPD) 184, 1416
Seismic Main Power Bay Assembly 1563
Seismic Rack (23 In. x 4 Ft.) 185, 570, 1406
Seismic Relay Rack 1597
Seismic Relay Rack (23 In. x 7 Ft.) 1554
Seismic Supplemental Power Bay Assembly 1563
Self-paced Technical Training CD 334, 1433
Sequencer (CDR) 1503, 1679
Serial 9 Pin Cable 335, 1431
Serial Communication Installation Guide (DA201-04) 1553
Serial Communications Option Installation (DA180) 1648
Serial Data Interface (Dual) 1501, 1677
Serial Data Interface (Single) (CDR) 1503, 1569, 1680
Serial I/O Cable 328, 592, 1411
Serial-Parallel Converter for Printers 269, 1369
SERP1001 1693
SERP1002 1693
SERP1003 1693
SERV0001 1693
SERV0002 156, 1182, 1510
SERV0003 156, 1182, 1510
SERV0004 325, 1510
SERV0005 320, 1182, 1510
SERV0006 325, 1182, 1510
SERV0007 1694
SERV0017 321, 1183, 1510
SERV0018 1694
SERV0019 236, 246, 257, 1183, 1510
SERV0020 237, 247, 259, 260, 1184, 1510
SERV0025 1694
SERV0030 1694
SERV0031 156, 1184, 1510

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SERV0033 325, 1184, 1510
SERV0041 1694
SERV0042 1694
SERV0055 1184, 1510
SERV0056 1184, 1510
SERV0058 1185, 1510
SERV0064 1694
SERV0065 1694
SERV0080 350, 1185, 1510
SERV3001 1694
SERV3002 1694
Server Operations Guide (DA205-03) 1647
Server Upgrade Kit from VISIT Messenger Visual Voice Messaging to Visual Voice and Fax Messaging 1627
Server-to-Server/LAN Software (IM100) 1550
Server-to-Server/WAN Software (IM101) 1550
Server-to-Server/X.25 (PDN100) 1550
Service Code for Telephone Support to Add Additional User Client License(s) Req. if adding clients to existing systems 271, 1193, 1511
Service Printer Package 1638
Set Based Administration Guide 1669
SFT NetWare V.2.15 1552
Share UPS Spare for OIVR 4.0 MRS/Rack or Rack AP 283, 1462
Shelf Cable 1675
Shielded 4-Port Octopus Cable with Ethernet 327, 510, 1388
Shielded 4-Port Octopus Cable without Ethernet 327, 510, 1388
Shielded 9-Drop Wide SCSI Cable 39, 223, 436, 1376
Shoulder Rest, Charcoal (M3900 Series) 200, 1384
Shoulder Rest, Platinum (M3900 Series) 200, 1384
Shroud B, Big 1644
Shroud B, Small 1645
Side Cover Panel 1640
Side Fascia Panel 1645
Side Fascia Panel (Blue) 1646
Side Panel (Double Bay)-EMI 1643
Side Panel (Left & Right) 1645
Side Panel (Single Bay)-EMI 1643
Side Panel Assembly 1640
Silent Print 1569
SIMMS Memory Upgrade Kit 1638
Simple Signaling Cable for OIVR 4.0 Rack UPS 283, 1462
Single Key Expansion Module Footstand, Ash, (M2000 Series) 203, 1153, 1486
Single Key Expansion Module Footstand, Black (M2000 Series) 203, 1153, 1486
Single Key Expansion Module Footstand, Gray, (M2000 Series) 203, 1153, 1486
Single Line Telephone User Guide (Trifold) (100/PK) 351, 1481
Single Port SDI Assembly-EMI (CDR) 1528
Single Transport Cable 1582
Single-Attendant SL-1LE/N Total Software Package 1530
Single-Attendant SL-1M/MS Total Software Package 1530
Single-Attendant SL-1VLE/XL/XN Total Software Package 1530
SL-1 A/M/MS/L/LE to ST Shelf Upgrade Package 1714
SL-1 A/M/MS/L/LE/S to ST Upgrade Package 1716
SL-1 A/M/MS/L/S to ST Additional Network Assembly (QCA36, QCA148 1714
SL-1 ACD Telephone (Dual Headset Jack) 1508, 1685
SL-1 Attendant Console User Guide (15/PK) 1646
SL-1 Autovon Feature Document 1569
SL-1 CDR Product Sales Guide 1646
SL-1 Console Line Cord 1546
SL-1 Data Line Card 1503, 1679
SL-1 Data Product Usage and Connectivity 1645
SL-1 Data User Guide (15/PK) 1642
SL-1 Digit Display Phone 1508, 1685
SL-1 Digit Display Telephone 1508, 1685
SL-1 Digital Display Telephone User Guide (15/PK) 1646
SL-1 Digital Set w/Data Option Tech 1646
SL-1 Displayphone - AB07 User Guide Supplement 1645
SL-1 Displayphone (NT6K10AB) 1547
SL-1 Displayphone (NT6K10AC) 1547
SL-1 Displayphone (NT6K10AD) 1547
SL-1 Displayphone (NT6K10AE) 1548
SL-1 Integrated Voice & Data Station Demonstrator Package 1528
SL-1 Integrated Voice & Data Station Demonstrator Retrofit Package 1528
SL-1 LE/N/VLE/XL/XN Floppy Disk Drive (5.25 In.) Upgrade Package (QCA23, QCA24 Cabinet) 1715
SL-1 Line Card 1503, 1505, 1680, 1681
SL-1 M/MS/L/LE to NT Upgrade Package 1716
SL-1 MS CE Shelf Expansion Assembly 1544
SL-1 MS Floppy Disk Drive (5.25 In.) Upgrade Package 1715
SL-1 MS to NT Shelf Upgrade Package 1715
SL-1 N to NT Shelf Upgrade Package (QCA23 Cabinet) 1714
SL-1 N/XN Floppy Disk Drive (5.25 In.) Upgrade Package 1715
SL-1 NT to XT Cabinet Upgrade Package 1716
SL-1 Quick Reference Guide 2 1650
SL-1 Quick Reference Guides 1 1651

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SL-1 ST/RT Expansion Cabinet Assembly - One Shelf 1543
SL-1 ST/RT Expansion Cabinet Assembly - Two Shelf 1544
SL-1 Station Demonstrator Manual 1643
SL-1 Telephone (Fully Modular) 1508, 1685
SL-1 Telephone Handset 1546
SL-1 Telephone Handset w/QUU1C Fluxcoil (QSU3) 1546
SL-1 Telephone Set 1508, 1685
SL-1 VL/VLE/XL/XN to XT Upgrade Package 1716
SL-1 X11 Feature Document 1646
SL-1A to SL-1M Hardware Conversion Kit 1542
SL-1A/LE Upgrade Assembly (Single CPU/Half Network) 1527
SL-1LE High Reliability Package (Generic 305) 1525
SL-1LE High Traffic Package 1525
SL-1LE Hotel/Motel CE Expansion Package 1525
SL-1LE to NT Shelf Upgrade Package (QCA23 Cabinet) 1718
SL-1M High Density PE Shelf Assembly (QCA37 Cabinet) 1543
SL-1MS Hotel/Motel Software Package 1526
SL-1MS Special Software Feature Package II 1526
SL-1MS Special Software Feature Package III 1526
SL-1N CE Expansion Package (Single CPU/Half Network Group to Dual 1526
SL-1N to NT Shelf Upgrade Package (QCA58 Cabinet) 1718
SL-1NT Hotel/Motel Software Package 1530
SL-1NT to Option 71 Module Upgrade Package AC 1716
SL-1NT to Option 71 Module Upgrade Package DC 1716
SL-1RT Business Software Feature Prepackage 1544
SL-1RT Health Care Software Feature Prepackage 1544
SL-1RT to Option 61 Module Upgrade Package AC 1716
SL-1RT to Option 61 Module Upgrade Package DC 1716
SL-1RT/NT/XT Floppy Disk Drive (3.5 In.)/ROM Upgrade Package 1716
SL-1RT/NT/XT Multi Disk Drive (3.5 In.) w/Hard Disk Drive/ROM Upgrade 1716
SL-1S Battery Backup Assembly 1526
SL-1S Console Assembly 1528
SL-1S Floppy Disk Drive (5.25 In.) Upgrade Package 1718
SL-1S Hotel/Motel Software Package 1526
SL-1S PE Shelf Assembly 1528
SL-1S Power Fail Transfer Assembly 1528
SL-1S Prepackage Software 1528
SL-1S Special Software Feature Package I 1526
SL-1S Special Software Feature Package II 1526
SL-1S Special Software Feature Package III 1526
SL-1ST CE/PE Expansion Assembly (with MDF Assembly) 1543
SL-1ST Console Assembly 1528
SL-1ST Environmental Improvement Assembly (For One and Two Tier SL-1ST) 1543
SL-1ST Floppy Disk Drive (3.5 In.)/ROM Upgrade Package 1716
SL-1ST Hotel/Motel Software Package 1530
SL-1ST Memory Expansion Assembly 1528
SL-1ST PE Expansion Assembly - One Shelf (with MDF Assembly) 1527
SL-1ST PE Expansion Assembly - Two Shelf (with MDF Assembly) 1543
SL-1ST PE Expansion Assembly-First Shelf 1528
SL-1ST Prepackage Software 1542
SL-1ST Product Sales Guide 1647
SL-1ST Setting a New Standard 1647
SL-1ST Slide Presentation 1647
SL-1ST Special Software Feature Package I 1542
SL-1ST Special Software Feature Package II 1542
SL-1ST Special Software Feature Package III 1542
SL-1ST/RT CE/PE Expansion Tier Package 1543
SL-1ST/RT Cooling Unit Assembly 1543
SL-1ST/RT Expansion Tier Package- 2 Shelves 1543
SL-1ST/RT Expansion Tier Package-1 Shelf 1527
SL-1ST/RT Local RPE/PE Expansion Tier Package 1544
SL-1XN to XT Shelf Upgrade Package (QCA24 Cabinet) 1718
SL-1XN to XT Shelf Upgrade Package (QCA55 Cabinet) 1718
Slide Ramp Set 1654
SL-ST Article Reprints 1648
SLX25-108A X.25 Gateway (PAD) 8 Ports 110V 1365, 1548
SLX25-116A X.25 Gateway (PAD) 16 Ports 110V 1365, 1548
Small Keypad Template 229, 1497
Small System Multi Disk Unit 1419, 1607
Smart Splitter 1560
SMDI Software 1537
SMTP Gateway Option Guide (DA241) 1552
SMTP Mail Gateway (MGW110) 1554
SNA (3270/5250) Host Connectivity Upgrade from Release 2.08 to Release 2.2 925, 1454
SNMP Open Alarms 97, 107, 118, 130, 1207, 1512
Software Assembly, CCS 100 - New System Software (1 Agent) 32, 860, 1447
Software Assembly, CCS 100 - New System Software (10 Agents) 32, 861, 1447
Software Assembly, CCS 100 - New System Software (100 Agents) 32, 861, 1447

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Software Assembly, CCS 100 - New System Software (20 Agents) 32, 862, 1447
Software Assembly, CCS 100 - New System Software (200 Agents) 32, 862, 1447
Software Assembly, CCS 100 - New System Software (5 Agents) 32, 861, 1447
Software Assembly, CCS 100 - New System Software (50 Agents) 32, 861, 1447
Software Assembly, CCS 100 - New System Software (500 Agents) 32, 861, 1447
Software Assembly, CCS 100 - New System Software, 20 Agents 297, 636, 1420
Software Assembly, CCS 100 - New System Software, 200 Agents 297, 636, 1420
Software Assembly, CCS 100 - New System Software, 5 Agents 297, 636, 1420
Software Assembly, CCS 100 Upgrade, CCR, 20 Agents 301, 665, 1423
Software Assembly, CCS 100 Upgrade, CCR, 200 Agents 301, 665, 1423
Software Assembly, CCS 100 Upgrade, CCR, 5 Agents 301, 665, 1423
Software Assembly, CCS 100 Upgrade, MAX 5, 20 Agents 299, 661, 1423
Software Assembly, CCS 100 Upgrade, MAX 5, 200 Agents 299, 662, 1423
Software Assembly, CCS 100 Upgrade, MAX 5, 5 Agents 299, 661, 1422
Software Assembly, CCS 100 Upgrade, MAX 6, 20 Agents 299, 655, 1422
Software Assembly, CCS 100 Upgrade, MAX 6, 200 Agents 299, 655, 1422
Software Assembly, CCS 100 Upgrade, MAX 6, 5 Agents 299, 655, 1422
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 20 Agents 299, 645, 1421
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 200 Agents 299, 646, 1421
Software Assembly, CCS 100 Upgrade, MAX 7-9 Fundamental or Enhanced, 5 Agents 299, 645, 1421
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 20 Agents 300, 671, 1423
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 200 Agents 300, 672, 1423
Software Assembly, CCS 100 Upgrade, Pre MAX 5 or PDP, 5 Agents 299, 671, 1423
Software Assembly, CCS 200 - New System Software (1 Agent) 32, 862, 1447
Software Assembly, CCS 200 - New System Software (10 Agents) 32, 862, 1447
Software Assembly, CCS 200 - New System Software (100 Agents) 33, 863, 1448
Software Assembly, CCS 200 - New System Software (20 Agents) 33, 863, 1448
Software Assembly, CCS 200 - New System Software (200 Agents) 33, 863, 1448
Software Assembly, CCS 200 - New System Software (5 Agents) 33, 863, 1448
Software Assembly, CCS 200 - New System Software (50 Agents) 32, 862, 1448
Software Assembly, CCS 200 - New System Software (500 Agents) 33, 863, 1448
Software Assembly, CCS 200 - New System Software, 20 Agents 297, 639, 1420
Software Assembly, CCS 200 - New System Software, 200 Agents 297, 639, 1420
Software Assembly, CCS 200 - New System Software, 5 Agents 297, 639, 1420
Software Assembly, CCS 200 Upgrade, CCR, 20 Agents 301, 668, 1423
Software Assembly, CCS 200 Upgrade, CCR, 200 Agents 301, 668, 1423
Software Assembly, CCS 200 Upgrade, CCR, 5 Agents 301, 668, 1423
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 20 Agents 300, 674, 1424
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 200 Agents 301, 674, 1424
Software Assembly, CCS 200 Upgrade, MAX 7/8/9 Virtual, 5 Agents 300, 674, 1424
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (20 Agents) 300, 648, 1421
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (200 Agents) 300, 648, 1421
Software Assembly, CCS 200 Upgrade, MAX Virtual with CCR (5 Agents) 300, 648, 1421
Software Assembly, CCS 300 - New System Software, 20 Agents 298, 642, 1421
Software Assembly, CCS 300 - New System Software, 200 Agents 298, 642, 1421
Software Assembly, CCS 300 - New System Software, 5 Agents 298, 642, 1421
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (20 Agents) 301, 302, 651, 1422
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (200 Agents) 301, 302, 652, 1422
Software Assembly, CCS 300 Upgrade, From NAC and/or NACD (5 Agents) 301, 302, 651, 1422
Software Assembly, CCS 300 Upgrade, From NACD, 20 Agents 302, 658, 1422
Software Assembly, CCS 300 Upgrade, From NACD, 200 Agents 302, 658, 1422
Software Assembly, CCS 300 Upgrade, From NACD, 5 Agents 302, 658, 1422
Software Assembly, Emergency Repair Disks 226,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

1399
Software Assembly, SCCS Release 3 Base Software (DMS/MSL) 34, 1065, 1471
Software conversion procedures 1663, 1664, 1666, 1667
Software Conversion Procedures, Release 24 and Earlier 348, 1494
Software Feature, Personal Mailbox Administration (PMA) 256, 865, 1448
Software Features Package (Base) - Options 42, 43, 50, 114, and 155 297, 1470
Software Features Package (CCS100) - Options 214, 215, 218 297, 1470
Software Features Package (CCS300) - Option 207 297, 1470
Software Installation Guide - French 1670
Software Installation Kit (Non-Autovon) 197, 198, 555, 1059, 1403, 1470, 1631
Software Installation Menu 1665
Software Service Transaction Fee 156, 377, 1364
Software Upgrade - Host Connectivity Software Upgrade - R2 AP or MRS/AP 281, 960, 1459
Software Upgrade - OPEN IVR 2.0/2.5 to 4.0 (PEB) - Serial Board Upgrade for R2 MRS with Speech Recognition Option 281, 961, 1459
Software Upgrade - OPEN IVR 2.01/2.5 to 4.0 (PEB) - L and H TTS Dongle Replacement 281, 960, 1459
Software Upgrade - Open IVR 2.01/2.5 to 4.0 (PEB) - Media (CD) and 1 AP or MRS/AP RTU 281, 959, 1459
Software Upgrade - UPS Software Upgrade - R2 AP, MRS/AP 281, 961, 1459
Software X11 Release 1-16 NTP 1653
Software X11 Release 4 to 14 - Compact Size 1650
Software X11 Rls 4 to 14 NTP 1644
Software X37 Release 4+ NTP 1651
Software X37 Rls 4 + NTP 1644
Software-Based Disk Mirroring License RTU - OIVR 4.0 AP, MRS, or MRS/AP 43, 276, 947, 1457
SOIVR 4.0 - CAS & ISDN Signaling Option Guide 286, 1460
SP 11 to 24 Storage Expansion Software (Order with U9100 Upgrade) 1533
SP 12 Port/24 Hour Package 1606
SP 4 Port/24 Hour Package 1606
SP 4 Port/5 Hour Package 1606
SP 5 to 11 Storage Expansion Software (Expands 5 to 11 Hours) 1533
SP 8 Port/11 Hour Package 1606
SP 8 Port/24 Hour Package 1606
SP Networking Package 1608
SP Spares Kit 1606
Spacer, Extension (Left) 1647
Spacer, Extension (Right) 1647
Spare Circuit Breaker Kit, 1 Amp 1655
Spare Circuit Breaker Kit, 10 Amp 1655
Spare Circuit Breaker Kit, 20 Amp 186, 342, 1149, 1483
Spare Circuit Breaker Kit, 30 Amp 186, 342, 1149, 1483
Spare Circuit Breaker Kit, 5 Amp 186, 342, 1149, 1483
Spare Circuit Breaker Kit, 50 Amp - MPP600/MFA150 186, 342, 1485
Spare Fuse & Breaker Kit 1597
Spare set of blank 3.5 inch 4MB floppy diskettes 156, 1182, 1510
Spare set of blank 5.25 in diskettes 156, 1182, 1510
Special Application Features 152, 1203, 1512
Special Applications Display, Ash 1397, 1581
Special Applications Display, Black 1397, 1581
Special Applications Display, Gray 1397, 1581
Special Console/Line Card Package 158, 440, 1377
Special Features - Compact Size 1650
Special Features NTP 1642, 1643, 1653
Special Meridian 1 Attendant PC with Digital Line Card 204, 448, 1378
Special Pedestal Assembly AC 1563
Special Pedestal Assembly DC 1563
Special Peripheral Equipment Module Package AC 1563
Special Peripheral Equipment Module Package DC 1563
Speech Activity Detection Software 1621
Speech Recognition - PureSpeech - Continuous Digits - 2 Port RTU Expansion 44, 279, 954, 1458
Speech Recognition - PureSpeech Recite - Continuous Digits - Base Card and 2 Port RTU 43, 279, 951, 1457
Speech Recognition - PureSpeech Recite - IQ - 2 Port RTU Expansion 44, 279, 955, 1458
Speech Recognition - PureSpeech Recite - IQ - Base Card and 2 Port RTU 44, 279, 952, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - 2 Port RTU Expansion 44, 279, 280, 955, 956, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - Continuous Digits - Base Card and 2 Port RTU 44, 279, 952, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - IQ - 2 Port RTU Expansion 44, 280, 957, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - IQ - Base Card and 2 Port RTU 44, 279, 954, 1458

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Speech Recognition - PureSpeech Recite - LA Spanish - Lite - 2 Port RTU Expansion 44, 279, 956, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - Lite - Base Card and 2 Port RTU 44, 279, 952, 1458
Speech Recognition - PureSpeech Recite - LA Spanish - Pro - Base Card and 2 Port RTU 44, 279, 953, 1458
Speech Recognition - PureSpeech Recite - Lite - 2 Port RTU Expansion 44, 279, 955, 1458
Speech Recognition - PureSpeech Recite - Lite - Base Card and 2 Port RTU 43, 279, 951, 1457
Speech Recognition - PureSpeech Recite - Pro - 2 Port RTU Expansion 44, 279, 955, 1458
Speech Recognition - PureSpeech Recite - Pro - Base Card and 2 Port RTU 43, 279, 951, 1458
Speech Recognition - VCS for Antares - Continuous - 2 Port RTU Expansion 44, 280, 956, 1458
Speech Recognition - VCS for Antares - Continuous - Base Card and 2 Port RTU 44, 279, 953, 1458
Speech Recognition - VCS for Antares - Discrete - 4 Port RTU Expansion 44, 280, 956, 1458
Speech Recognition - VCS for Antares - Discrete - Base Card and 4 Port RTU 44, 279, 953, 1458
Speed Call Key Cap Package (50/PK) 1557
Sprinter Ribbon 1569
SQL Informix Database Access 1559
SQL Ingres Database Access 1559
SQL Oracle Database Access 1559
SQL Sybase Database Access 1559
SSC Upgrade Kit 70, 178, 709, 1431
ST/RT Upgrade Assembly 1714
STADATA Station Automation System User Guide 1658
Standard Telephone User Guide 353, 1487
Standard Telephony Services Software Support 1695
Standoff 1570
Static Inverter (CDR) 1382, 1567
Station Administration 1698
Station Administration 1.2 to 1.3 Upgrade for Enhancements 1698
Station Administration 1.3 Demonstrator 1654
Station Administration Documentation (Version 1) 1653
Station Administration Version 2.4 1699
Station Administration Version Update 1698
Station Camp-On 1695
Station Data (STADATA) Base Automatic System 1652
Status Key Cap Package (50/PK) 1556
STE from ST or 21E from 21A/21 Upgrade Package 1716
STE from ST or Option 21E from Option 21A/21 Upgrade Package 1717
STE/21E Multi Disk Unit and Memory Upgrade Package 1716
Stored Number Redial Key Cap Package (50/PK) 207, 400, 1368
Straight Through RS232 Cable Male/Female (10 Ft.) 328, 513, 1388
Straight Through RS232 Cable Male/Female (2 Ft.) 327, 512, 1388
Straight Through RS232 Cable Male/Female (25 Ft.) 267, 328, 513, 1388
Straight Through RS232 Cable Male/Female (4 Ft.) 328, 512, 1388
Straight Through RS232 Cable Male/Female (45 Ft.) 328, 513, 1388
Straight Through RS232 Cable Male/Male (10 Ft.) 327, 511, 1388
Straight Through RS232 Cable Male/Male (2 Ft.) 267, 327, 511, 1388
Straight Through RS232 Cable Male/Male (25 Ft.) 327, 512, 1388
Straight Through RS232 Cable Male/Male (4 Ft.) 327, 511, 1388
Straight Through RS232 Cable Male/Male (45 Ft.) 327, 512, 1388
Strider Ribbon 1569
Strider Vertical Format Tape 1569
Sub-D Filter Connector (25 Conductor) 187, 389, 1367
SuperLoop Adapter Plate 197, 600, 1413
SuperLoop Network Card 178, 600, 1413, 1602
Supervisor Key Cap Package (50/PK) 206, 397, 1368
Supervisor Users Guide 352, 1483
Supervisory Console 152, 1208, 1502, 1513, 1678
Supplement to Administrators Guide (DA206-01) 1647
Supplemental Distribution Panel 1596
Supplemental Power Bay Assembly 1563
Supplementary Cabinet 1567
Supplementary Patch CD 276, 931, 1455
Supplementary Power Cabinet (QCA13) J2412A-1L17/19 1566
Support Bracket (11 In. Gray) 1645
SV000019 26, 1694
SV000020 271, 1185, 1510
SV000021 27, 1694
SV000022 27, 1694
SV000023 1694
SV000024 271, 1186, 1510
SV000025 271, 1186, 1510
SV000026 271, 1186, 1510
SV000027 271, 1187, 1510
SV000069 1694
SV000072 1694

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SV000073 1694
SV000074 1694
SV000088 326, 1187, 1510
SV000089 326, 1187, 1510
SV000091 302, 1187, 1511
SV000098 1188, 1511
SV000099 1188, 1511
SV000100 1188, 1511
SV000101 1188, 1511
SV000102 1188, 1511
SV000110 271, 1189, 1511
SV000111 271, 1189, 1511
SV000112 271, 1189, 1511
SV000113 27, 1694
SV000114 27, 1694
SV000115 1694
SV000117 302, 1190, 1511
SV000118 1694
SV000119 1694
SV000120 1694
SV000121 1694
SV000122 1694
SV000123 1694
SV000124 1694
SV000125 302, 1190, 1511
SV000126 311, 1190, 1511
SV000127 311, 1191, 1511
SV000128 311, 1191, 1511
SV000143 1694
SV000144 1694
SV000145 1694
SV000147 310, 1191, 1511
SV000148 310, 1192, 1511
SV000149 310, 1192, 1511
SV000175 275, 1192, 1511
SV000176 275, 1193, 1511
SV000177 275, 1193, 1511
SV000181 271, 1193, 1511
SV000182 308, 1194, 1511
SV000183 308, 1194, 1511
SV000184 308, 1194, 1511
SV000251 271, 1511
SV000252 275, 1195, 1511
SV000253 275, 1195, 1511
SV000254 275, 1195, 1511
SV000255 275, 1195, 1511
SV000257 275, 1196, 1511
SV000259 275, 1196, 1511
SV000260 275, 1196, 1511
SV000261 275, 1196, 1511
SV000262 275, 1197, 1511
SV000276 271, 1197, 1511
SV000277 1197, 1512
SV000278 271, 1198, 1512
SV000279 271, 1198, 1512
SV000280 271, 1198, 1512
SV000281 1694
SV000282 1694
SV000283 1694
SV000284 1695
SV000285 1695
SV000286 1695
SV000287 1695
SV000288 302, 1512
SV000384 1695
SV000397 338, 1512
SV000399 296, 1199, 1512
SVC0001 1199, 1512
SVC0002 1695
SVC0003 1695
SVC0004 1695
SVC0005 1695
SVC0006 1695
SVC0007 1199, 1512
SVC0009 1695
SVC0010 1200, 1512
SVC1001 1695
SVC1003 1695
SVC1004 1695
SVC1006 236, 246, 257, 1200, 1512
SVC1007 1695
SVC1008 1695
SVC1009 1695
SVC1017 1695
SVC1018 1695
SVC1019 1695
SVC1035 325, 1512
SVC1101 1695
SW0000A 1695
SW0000B 1695
SW0000C 151, 1200, 1512
SW0000D 1695
SW0000E 144, 1200, 1512
SW0000F 1695
SW0000G 136, 1201, 1512
SW0000H 128, 1201, 1512
SW0000J 116, 1202, 1512
SW0000K 104, 1202, 1512
SW0000L 94, 1203, 1512
SW0001A 152, 1203, 1512
SW0002A 1695
SW0003A 97, 107, 118, 130, 138, 145, 1204, 1512
SW0005A 97, 107, 118, 130, 138, 145, 152, 1204, 1512
SW0006A 97, 107, 118, 130, 138, 145, 1205, 1512
SW0008A 152, 1205, 1512

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW0009A 97, 107, 118, 130, 138, 145, 152, 1206, 1512
SW0010A 152, 1206, 1512
SW0011A 97, 107, 118, 130, 138, 1206, 1512
SW0013A 97, 107, 118, 130, 138, 1207, 1512
SW0015A 97, 107, 118, 130, 1207, 1512
SW0016A 97, 107, 1207, 1512
SW0017A 152, 1208, 1513
SW0018A 152, 1208, 1513
SW0019A 152, 1208, 1513
SW0020A 152, 1208, 1513
SW0021A 152, 1209, 1513
SW0022A 153, 1209, 1513
SW0023A 1695
SW0024A 153, 1209, 1513
SW0025A 153, 1210, 1513
SW0026A 153, 1210, 1513
SW0027A 1695
SW0028A 97, 107, 119, 130, 138, 145, 153, 1210, 1513
SW0029A 1695
SW0029B 153, 1211, 1513
SW0030A 119, 130, 138, 145, 153, 1211, 1513
SW0030B 97, 107, 1211, 1513
SW0031A 97, 107, 119, 130, 138, 146, 153, 1212, 1513
SW0032A 97, 107, 119, 130, 138, 146, 1212, 1513
SW0033A 97, 107, 119, 130, 138, 146, 1213, 1513
SW0034A 97, 107, 119, 130, 138, 146, 1213, 1513
SW0035A 1695
SW0040A 97, 107, 119, 1214, 1513
SW0041A 153, 1214, 1513
SW0042A 153, 1214, 1513
SW0043A 153, 1214, 1513
SW0044A 153, 1215, 1513
SW0045A 153, 1215, 1513
SW0046A 97, 107, 119, 130, 138, 146, 153, 1215, 1513
SW0047A 97, 107, 119, 130, 138, 146, 153, 1216, 1513
SW0048A 97, 107, 119, 130, 138, 1216, 1513
SW0049A 97, 107, 119, 131, 138, 1216, 1513
SW0050A 146, 1217, 1513
SW0050B 97, 107, 119, 131, 138, 1217, 1513
SW0051A 146, 1217, 1513
SW0051B 98, 107, 119, 131, 139, 1218, 1513
SW0052A 146, 1218, 1513
SW0052B 1695
SW0052C 1695
SW0052D 98, 108, 119, 131, 139, 1218, 1513
SW0053A 131, 139, 146, 1219, 1513
SW0053B 98, 108, 119, 1219, 1513
SW0055A 98, 108, 119, 131, 139, 1220, 1513
SW0057A 98, 108, 119, 131, 139, 1220, 1513
SW0058A 1695
SW0059A 1696
SW0059B 98, 108, 119, 131, 139, 1221, 1514
SW0060A 98, 120, 131, 139, 146, 1221, 1514
SW0060B 108, 120, 1222, 1514
SW0061A 1696
SW0061B 98, 108, 120, 131, 139, 147, 1222, 1514
SW0062A 98, 108, 120, 131, 139, 147, 1222, 1514
SW0064A 319, 1223, 1514
SW0065A 1696
SW0066A 1696
SW0067A 1696
SW0068A 1696
SW0069A 1696
SW0070A 1696
SW0070B 1696
SW0071A 319, 1223, 1514
SW0072A 319, 1223, 1514
SW0073A 319, 1224, 1514
SW0074A 319, 1224, 1514
SW0075A 1696
SW0076A 1696
SW0076B 1696
SW0077A 1696
SW0078A 1696
SW0078B 1696
SW0079A 1696
SW0080A 1696
SW0081A 319, 1224, 1514
SW0082A 1696
SW0082B 1696
SW0082C 1696
SW0083A 320, 1225, 1514
SW0083B 1696
SW0083C 1696
SW0084A 1696
SW0084B 1696
SW0084C 1697
SW0085A 320, 1226, 1514
SW0085B 1697
SW0085C 1697
SW0086A 320, 1227, 1514
SW0087A 320, 1228, 1514
SW0088A 1697
SW0088B 1697
SW0089A 1697
SW0089B 1697
SW0090A 1697
SW0090B 1697

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW0091A 1697
SW0091B 1697
SW0092A 1697
SW0092B 1697
SW0093A 320, 1228, 1514
SW0093B 320, 1229, 1514
SW0094A 320, 1229, 1514
SW0094B 320, 1230, 1514
SW0095A 1697
SW0095B 1697
SW0096A 320, 1230, 1514
SW0096B 320, 1231, 1514
SW0097A 320, 1231, 1514
SW0097B 320, 1232, 1515
SW0098A 319, 1232, 1515
SW0099A 1697
SW0099B 1697
SW0101A 1697
SW0101B 147, 1232, 1515
SW0101C 100, 111, 123, 132, 139, 1233, 1515
SW0102A 100, 111, 123, 132, 139, 147, 1233, 1515
SW0104A 120, 131, 1233, 1515
SW0104B 98, 108, 1234, 1515
SW0105A 99, 108, 120, 131, 1234, 1515
SW0110A 99, 108, 1234, 1515
SW0150A 99, 109, 121, 1235, 1515
SW0155A 99, 109, 121, 1235, 1515
SW0165A 99, 108, 120, 1236, 1515
SW0170A 99, 108, 1236, 1515
SW0201A 1697
SW0201B 154, 1236, 1515
SW0202A 1697
SW0202B 1697
SW0202C 154, 1237, 1515
SW0203A 1697
SW0203B 154, 1237, 1515
SW0204A 154, 1237, 1515
SW0205A 154, 1238, 1515
SW0206A 154, 1238, 1515
SW0207A 154, 1238, 1515
SW0208A 154, 1239, 1515
SW0209A 154, 1239, 1515
SW0210A 154, 1240, 1515
SW0211A 154, 1240, 1515
SW0221A 1697
SW0221B 147, 1240, 1515
SW0221C 101, 112, 124, 132, 140, 1241, 1515
SW0222A 101, 112, 124, 132, 140, 147, 1241, 1515
SW0223A 101, 112, 124, 132, 140, 147, 1242, 1515
SW0224A 101, 112, 124, 132, 140, 147, 1242, 1515
SW0225A 1697
SW0225B 101, 112, 124, 132, 140, 147, 1243, 1515
SW0226A 101, 112, 124, 132, 140, 147, 1243, 1515
SW0227A 101, 112, 124, 133, 140, 147, 1244, 1515
SW0228A 101, 113, 124, 133, 1244, 1515
SW0229A 148, 1244, 1515
SW0229B 1697
SW0229C 113, 124, 133, 140, 1245, 1515
SW0229D 101, 1245, 1515
SW0230A 101, 113, 124, 133, 140, 1245, 1516
SW0234A 99, 108, 120, 1245, 1516
SW0251A 101, 113, 125, 133, 141, 148, 1246, 1516
SW0300A 1697
SW0300B 1697
SW0300C 153, 1246, 1516
SW0301A 153, 1246, 1516
SW0302A 153, 1247, 1516
SW0303A 1697
SW0303B 153, 1247, 1516
SW0304A 1697
SW0304B 153, 1247, 1516
SW0305A 154, 1248, 1516
SW0306A 154, 1248, 1516
SW0350A 1697
SW0350B 1697
SW0351A 1697
SW0351B 1698
SW0352A 319, 1248, 1516
SW0401A 154, 1249, 1516
SW0402A 154, 1249, 1516
SW0403A 154, 1249, 1516
SW0403B 1698
SW0404A 1698
SW0405A 1698
SW0405B 1698
SW0406A 1698
SW0406B 1698
SW0406C 154, 1250, 1516
SW0407A 154, 1250, 1516
SW1001A 1698
SW1003A 1698
SW1004A 1698
SW1005A 1698
SW1006A 1698
SW1007A 1698
SW1008A 1698
SW1009A 1698
SW1010A 1698
SW1011A 1698
SW1012A 1698

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW1013A 1698
SW1014A 1698
SW1015A 1698
SW1016A 1698
SW1020A 1698
SW1021A 1698
SW1022A 1698
SW1023A 1698
SW1024A 1698
SW1025A 1698
SW1026A 1698
SW1027A 1698
SW1028A 1698
SW1029A 1698
SW1030A 1698
SW1031A 1698
SW1032A 1699
SW1033A 1699
SW1034A 1699
SW1035A 1699
SW1036A 1699
SW1037A 1250, 1516
SW1038 1699
SW1101A 1699
SW1102A 1699
SW1103A 1699
SW1104A 1699
SW1111A 1699
SW1112A 1699
SW1113A 1699
SW1114A 1699
SW1121A 1699
SW1121B 1699
SW1121C 1699
SW1121E 92, 1250, 1516
SW1122A 1699
SW1122B 1699
SW1122C 1699
SW1122E 92, 1251, 1516
SW1123A 1699
SW1124A 1699
SW1126A 1699
SW1126B 1699
SW1126D 92, 1251, 1516
SW1127A 1699
SW1127B 1699
SW1127D 92, 1251, 1516
SW1131A 1699
SW1131B 1699
SW1131C 1699
SW1131E 92, 1252, 1516
SW1132A 1699
SW1132B 1699
SW1132C 1699
SW1132E 92, 1252, 1516
SW1133A 1699
SW1134A 1699
SW1136A 1700
SW1137A 1700
SW1138A 1700
SW1141A 1700
SW1141B 1700
SW1141D 92, 1252, 1516
SW1142A 1700
SW1142B 1700
SW1142D 92, 1253, 1516
SW7000 1700
SW7000A 1700
SW7000B 1700
SW7000C 1700
SW7000D 1700
SW7000E 1700
SW7000F 1700
SW7000G 1700
SW7000H 1700
SW7001 1700
SW7002 1700
SW7003 1700
SW7004 1700
SW7004A 1700
SW7004B 256, 1253, 1516
SW7005 1700
SW7007 245, 256, 1253, 1516
SW7008 257, 1254, 1516
SW7008A 1700
SW7008B 257, 1254, 1516
SW7009 1700
SW7009A 1700
SW7009B 1700
SW7009C 1700
SW7009D 257, 1254, 1516
SW7010 1700
SW7010A 1700
SW7010B 257, 1255, 1516
SW7011B 1700, 1701
SW7011U 1701
SW7012B 1701
SW7012U 1701
SW7013B 1701
SW7013U 1701
SW7014B 1701
SW7014U 1701
SW7015B 1701
SW7015U 1701
SW7016B 1701
SW7016U 1701
SW7017B 1701
SW7017U 1701

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW7018B 1701
SW7018U 1701
SW7019B 1701
SW7019U 1701, 1702
SW7020B 1702
SW7020U 1702
SW7021B 1702
SW7021U 1702
SW7022B 1702
SW7022U 1702
SW7023 256, 1255, 1516
SW7023B 1702
SW7023U 1702
SW7024 257, 1256, 1516
SW7024B 1702
SW7024U 1702
SW7025B 1702
SW7025U 1702
SW7026B 1702
SW7026U 1702
SW7028B 1702
SW7028U 1702
SW7029B 1702
SW7029U 1702
SW7030 1702
SW7030A 1702
SW7030B 1702
SW7030C 1702
SW7030D 1702
SW7030E 257, 1256, 1517
SW7035 1702
SW7035A 1703
SW7035B 1703
SW7035C 257, 1257, 1517
SW7035U 1703
SW7040 1703
SW7040B 1703
SW7040C 1703
SW7040D 257, 1257, 1517
SW7041 1703
SW7041B 1703
SW7041C 1703
SW7041D 1703
SW7041E 1703
SW7041F 1703
SW7041G 257, 1258, 1517
SW7042 1703
SW7042A 1703
SW7042B 257, 1258, 1517
SW7043 257, 1259, 1517
SW7044 1703
SW7045 1703
SW7046 1703
SW7047 1703
SW7049 248, 262, 1259, 1517
SW7050 265, 1259, 1517
SW7051 1703
SW7052 1703
SW7053 1703
SW7054 248, 262, 1260, 1517
SW7055 248, 262, 1260, 1517
SW7056 248, 262, 1261, 1517
SW7057 1703
SW7057A 1703
SW7057B 257, 1261, 1517
SW7058 257, 1262, 1517
SW7059 248, 262, 1262, 1517
SW7060 257, 1262, 1517
SW7061 256, 1263, 1517
SW7062 257, 1263, 1517
SW7065 247, 259, 1263, 1517
SW7066 1703
SW7067 1703
SW7068 257, 1264, 1517
SW7070 1703
SW7072 257, 1264, 1517
SW7074 257, 1264, 1517
SW7100D 1703
SW7100E 1703
SW7100F 1703
SW7100G 1703
SW7100H 1704
SW7101A 1704
SW7102 238, 1265, 1517
SW7103 238, 1265, 1517
SW7104 1704
SW7104A 1704
SW7104B 235, 245, 1265, 1517
SW7109 235, 245, 1266, 1517
SW7110 235, 245, 1266, 1517
SW7111 1704
SW7111A 1704
SW7111B 235, 245, 1266, 1517
SW7112 1704
SW7112A 1704
SW7112B 236, 246, 1267, 1517
SW7113 1704
SW7113B 1704
SW7113C 1704
SW7113D 235, 245, 1267, 1517
SW7114 1704
SW7114B 1704
SW7114C 1704
SW7114D 1704
SW7114E 1704
SW7114F 236, 245, 1267, 1517
SW7115 1704
SW7115A 1704

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW7115B 236, 246, 1268, 1517
SW7116 236, 246, 1268, 1517
SW7116B 1704
SW7117 1704
SW7117B 1704
SW7117C 236, 245, 1268, 1517
SW7118 236, 246, 1269, 1517
SW7119 236, 245, 1269, 1517
SW7120 1704
SW7121 236, 245, 1269, 1518
SW7122 236, 245, 1270, 1518
SW7123 236, 246, 1270, 1518
SW7124 236, 246, 1270, 1518
SW7140 238, 1271, 1518
SW7151 237, 1271, 1518
SW7200 1704
SW7201 1704
SW7202 1704
SW7203 1704
SW7204 1704
SW7205 1704
SW7206 1704
SW7207 1704
SW7208 1704
SW7209 1704
SW7211 1704
SW7212 1704
SW7213 1705
SW7220 1705
SW7221 1705
SW7222 1705
SW7223 1705
SW7224 1705
SW7301A 1705
SW7301B 1705
SW7301C 1705
SW7301D 1705
SW7302A 1705
SW7303A 1705
SW7304A 1705
SW7305B 1705
SW7305C 1705
SW7305D 1705
SW7307 1705
SW7307A 1518
SW7401 1705
SW7402 1705
SW7403 1705
SW7404 1705
SW7410 1705
SW7411 1705
SW7412 1705
SW7413 1705
SW7413A 1518
SW7414 1705
SW7414A 1518
SW7415 1705
SW7415A 325, 1272, 1518
SW7416 1705
SW7416A 325, 1273, 1518
SW7417A 325, 1274, 1518
SW7421 1705
SW7422 1705
SW7423 1706
SW7424 1706
SW7426 323, 1274, 1518
SW7427 323, 1275, 1518
SW7460 1706
SW7460A 1518
SW7461 1706
SW7461A 1518
SW7464 148, 1275, 1518
SW7501 1706
SW7501A 1706
SW7502 1706
SW7502A 1706
SW7503 1706
SW7503A 1706
SW7504 1706
SW7504A 1706
SW7505 1706
SW7505A 1706
SW7505B 319, 1276, 1518
SW7506 1706
SW7506A 1706
SW7507 1706
SW7507A 1706
SW7510A 1706
SW7510B 1706
SW7510C 1706
SW7511A 1706
SW7511B 319, 1276, 1518
SW7512 1706
SW7512A 1706
SW7513A 319, 1276, 1518
SW7514A 1706
SW7514B 320, 1277, 1518
SW7520A 1706
SW7520B 1706
SW7521A 1706
SW7521B 1706
SW7522A 1706
SW7522B 1706
SW7523 1706
SW7523A 1707
SW7524A 1707
SW7525A 1707
SW7525B 319, 1278, 1518

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SW7525C 319, 1278, 1518
SW7534 1707
SW7534A 1707
SW7551A 1707
SW7552A 1707
SW7553A 1707
SW7554A 1707
SW7700F 1707
SW7700G 1707
SW7700H 1707
Swedish Prompt - Bilingual 1701
Swedish Prompt - Unilingual 1701
Switch Air Flow Assembly (NT2R02AA) 1641
Switch and Connector Assembly 1641
Switch Settings, Card and Product Compatibility 1666
Switch settings, card and product compatibility 1664, 1667
Switch Settings, Card and Product Compatibility, Release 24 and Earlier 348, 1494
Switch to Switch Conversion Fee 1184, 1510
SY0070A 1707
SY0070D 1707
SY0073A 1707
SY0073D 1707
SY1001A 1707
SY1001D 1707
SY1001R 1707
SY1002A 1707
SY1002D 1707
SY1002R 1707
SY1003A 1707
SY1003D 1707
SY1003R 1707
SY1004A 1707
SY1004D 1707
SY1004R 1707
SY1005A 1707
SY1005D 1707
SY1005R 1707
SY1006A 1707
SY1007 1707
SY1008 1708
SY1009A 158, 1278, 1518
SY1009D 158, 1280, 1519
SY1011A 1708
SY1011D 1708
SY1012A 1708
SY1012D 1708
SY1013A 1708
SY1013D 1708
SY1014A 1708
SY1014D 1708
SY1015A 1708
SY1015D 1708
SY1016A 158, 1281, 1519
SY1016D 158, 1283, 1519
SY1025A 158, 1284, 1519
SY1025D 158, 1286, 1519
SY1107 1708
SY1108 1708
SY1151 1708
SY1152 1708
SY1153 1708
SY1154 1708
SY1200A 1708
SY1200D 1708
SY1220 1708
SY1221 1708
SY1222 1288, 1519
SY1223 1288, 1519
SY7000A 1708
SY7000D 1708
SY7001A 1708
SY7001D 1708
SY7002A 1708
SY7002D 1708
SY7003A 1708
SY7003D 1708
SY7004A 1708
SY7004D 1708
SY7005A 1708
SY7005D 1708
SY7006A 1708
SY7006D 1709
SY7007A 1709
SY7007D 1709
SY7008A 1709
SY7008D 1709
SY7010A 1709
SY7010D 1709
SY7011A 1709
SY7011D 1709
SY7012A 1709
SY7012D 1709
SY7013A 1709
SY7013D 1709
SY7014A 1709
SY7014D 1709
SY7015A 1709
SY7015D 1709
SY7016A 1709
SY7016D 1709
SY7017A 1709
SY7017D 1709
SY7018A 1709
SY7018D 1709
SY7019A 1709
SY7019D 1709

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SY7020A 255, 1289, 1519
SY7020D 255, 1290, 1519
SY7021A 255, 1291, 1519
SY7021D 255, 1293, 1519
SY7022A 255, 1294, 1519
SY7022D 255, 1295, 1519
SY7023A 255, 1297, 1519
SY7023D 255, 1298, 1519
SY7024A 256, 1300, 1519
SY7024D 256, 1301, 1519
SY7060D 1709
SY7061D 1709
SY7062D 1709
SY7063D 1709
SY7064D 1709
SY7065D 1709
SY7066D 1709
SY7067D 1709
SY7068D 1709
SY7069D 1710
SY7075D 256, 1302, 1519
SY7076D 256, 1304, 1519
SY7077D 256, 1305, 1519
SY7078D 256, 1307, 1519
SY7079D 256, 1308, 1519
SY7101 1710
SY7102 1710
SY7103 1710
SY7104 1710
SY7105 1710
SY7106 1710
SY7107 1710
SY7108 1710
SY7109 1710
SY7110 1710
SY7111 1710
SY7112 1710
SY7201A 1710
SY7201D 1710
SY7202A 1710
SY7202D 1710
SY7210 245, 1310, 1519
SY7211 245, 1311, 1519
SY7410A 1710
SY7410D 1710
SY7411A 1710
SY7411D 1710
SY7412 1312, 1520
SY7413 1710
SY7421A 324, 1312, 1520
SY7421D 324, 1313, 1520
SY7501A 1710
SY7501D 1710
SY7502A 1710
SY7502D 1710
SY7503A 1710
SY7503D 1710
SY7504A 1710
SY7504D 1710
SY7505 1710
SY7506 1710
SY7507 1710
SY7508 1710
Symon View 297, 1425
SYMPOSIUM Agent 1.1 Base Software 309, 1387
SYMPOSIUM Agent 1.1 Replacement/Up-issue Package 310, 1390
SYMPOSIUM Agent 2 (1 User) 310, 1390
SYMPOSIUM Agent 2 (10 Users) 310, 1390
SYMPOSIUM Agent 2 (100 Users) 310, 1390
SYMPOSIUM Agent 2 (50 Users) 310, 1390
SYMPOSIUM Agent 2 (500 Users) 310, 1390
SYMPOSIUM Agent 2 Base Software 310, 522, 1390
SYMPOSIUM Agent 2 Replacement/Up-issue Package 310, 1390
SYMPOSIUM Agent Install-Prep 310, 1191, 1511
SYMPOSIUM Agent Install-Pro 310, 1192, 1511
SYMPOSIUM Agent Package 1 (101-200 Agents) 309, 505, 1387
SYMPOSIUM Agent Package 1 (1-50 Agents) 308, 504, 1387
SYMPOSIUM Agent Package 1 (201 + Agents) 309, 505, 1387
SYMPOSIUM Agent Package 1 (51-100 Agents) 308, 505, 1387
SYMPOSIUM Agent Package 1 Base Software 1575
SYMPOSIUM Agent Package 2 (101-200 Agents) 309, 506, 1387
SYMPOSIUM Agent Package 2 (1-50 Agents) 309, 506, 1387
SYMPOSIUM Agent Package 2 (201 + Agents) 309, 507, 1387
SYMPOSIUM Agent Package 2 (51-100 Agents) 309, 506, 1387
SYMPOSIUM Agent Package 3 (101-200 Agents) 1575
SYMPOSIUM Agent Package 3 (1-50 Agents) 1575
SYMPOSIUM Agent Package 3 (201 + Agents) 1575
SYMPOSIUM Agent Package 3 (51-100 Agents) 1575
SYMPOSIUM Agent Package 3 Base Software 1575
SYMPOSIUM Agent Software Support 310, 1192, 1511
SYMPOSIUM Agent Upgrade - Package 1 to 2 309, 507, 1387
SYMPOSIUM Agent Upgrade - Package 1 to 3 1575
SYMPOSIUM Agent Upgrade - Package 2 to 3 1575
Symposium Agent Upgrade Package 1 or Package 2 to Package 3 - Base Software 1575

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Symposium Agent Upgrade Package 1 to Package 2 - Base Software 309, 1387
SYMPOSIUM Agent Upgrade Package 1 to Symposium Agent 2 310, 523, 1390
SYMPOSIUM Agent Upgrade Package 2 to SYMPOSIUM Agent 2 310, 524, 1390
SYMPOSIUM Call Center 701t CPU Upgrade Kit without CPU 1560
SYMPOSIUM Call Center Advanced Maintenance and Diagnostics Guide (English) 1666
SYMPOSIUM Call Center Assessment (Full) 1694
SYMPOSIUM Call Center Assessment (Mini) 1694
SYMPOSIUM Call Center Base Software 1609
SYMPOSIUM Call Center Capacity Assessment Tool 1586, 1610
SYMPOSIUM Call Center Documentation CD-ROM 1598
SYMPOSIUM Call Center Documentation CD-ROM (Multilingual) 307, 971, 1462
SYMPOSIUM Call Center Documentation Package (English) 1598
SYMPOSIUM Call Center Installation 302, 1190, 1511
SYMPOSIUM Call Center Migration Plan 1694
SYMPOSIUM Call Center Release 1 Capacity Assessment Tool 1586
SYMPOSIUM Call Center Release 1 Capacity Complete Documentation Package (English) 1598
SYMPOSIUM Call Center Release 1 Client Software 1586
SYMPOSIUM Call Center Release 1, Database Access & Report Management Guide 1669
SYMPOSIUM Call Center Release 1.0 French Client CD-ROM 1586
SYMPOSIUM Call Center Release 1.1 Base Software 1609
SYMPOSIUM Call Center Release 1.1 Client CD-ROM 1610
SYMPOSIUM Call Center Release 1.1 Documentation CD-ROM 1598
SYMPOSIUM Call Center Release 1.5 Base Software 1631
SYMPOSIUM Call Center Release 1.5 Client CD-ROM 306, 678, 1424
SYMPOSIUM Call Center Resource Management Guide (English) 1598
Symposium Call Center Server - Next Generation 100, 112, 517, 1389
SYMPOSIUM Call Center Server 1001t 25, 1610
SYMPOSIUM Call Center Server 1001t 300Mhz Processor 304, 427, 1374
SYMPOSIUM Call Center Server 1001t 32MB SCRAM 304, 428, 1374
SYMPOSIUM Call Center Server 1001t Base System 304, 426, 1373
SYMPOSIUM Call Center Server 1001t Blower 304, 429, 1374
SYMPOSIUM Call Center Server 1001t Cable Narrow, SCSI 304, 1374
SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Bottom 304, 1374
SYMPOSIUM Call Center Server 1001t Cable Wide, SCSI Top 304, 1374
SYMPOSIUM Call Center Server 1001t Cable, IDE CD-ROM 304, 1374
SYMPOSIUM Call Center Server 1001t CPU Retention Mechanism 304, 428, 1374
SYMPOSIUM Call Center Server 1001t EPAC Blower Duct 304, 1374
SYMPOSIUM Call Center Server 1001t Hardware Installation Guide 307, 1492
SYMPOSIUM Call Center Server 1001t Maintenance and Diagnostics Guide 308, 1492
SYMPOSIUM Call Center Server 1001t Power Supply 360W 304, 428, 1374
SYMPOSIUM Call Center Server 1001t Redundant Fan Kit 304, 429, 1374
SYMPOSIUM Call Center Server 1001t SCRAM Memory Board 304, 427, 1374
SYMPOSIUM Call Center Server 1001t SCSI Backplane Kit 304, 427, 1374
SYMPOSIUM Call Center Server 1001t Side Cover 304, 429, 1374
SYMPOSIUM Call Center Server 1001t System Board 304, 426, 1373
SYMPOSIUM Call Center Server 1001t Top Cover 304, 429, 1374
SYMPOSIUM Call Center Server 1001t with RAID 25, 1610
SYMPOSIUM Call Center Server 1003t 1.44MB Floppy Disk Drive 30, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t 256MB 50ns EDO DIMM Kit (4x64MB) 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t 32x MAX EIDE CD-ROM Drive 30, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t Base System 32, 42, 306, 1447
SYMPOSIUM Call Center Server 1003t Fan Assembly for CPU 29, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t Fan Assembly for Input/Output, Retainer 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t Fan Assembly for System Board 29, 39, 306, 1376
SYMPOSIUM Call Center Server 1003t Hardware Installation and Diagnostics Guide 37, 46, 307, 1498
SYMPOSIUM Call Center Server 1003t Input/Output

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

PCA 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t Internal SCSI Input/Output Cable 29, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t Memory PCA 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t Mini-DIN Mouse 30, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t NetServer Hot-Swap Ultra2 Internal Storage Cage 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t NetServer Keyboard 29, 39, 306, 1377
SYMPOSIUM Call Center Server 1003t PCI Ethernet Adapter 29, 39, 306, 1376
SYMPOSIUM Call Center Server 1003t Peripherals Package 30, 40, 303, 677, 1424
SYMPOSIUM Call Center Server 1003t Processor Terminator 30, 40, 306, 1377
SYMPOSIUM Call Center Server 1003t System Board PCA 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t Voltage Regulator Module 29, 39, 305, 1376
SYMPOSIUM Call Center Server 1003t Wide SCSI Host Adapter Board 29, 39, 306, 1376
SYMPOSIUM Call Center Server 701t 275W Power Supply 303, 422, 1373
SYMPOSIUM Call Center Server 701t 3.5" Floppy Drive Bracket 1560
SYMPOSIUM Call Center Server 701t 32MB DIMM 303, 422, 1373
SYMPOSIUM Call Center Server 701t Advanced 1424, 1610
SYMPOSIUM Call Center Server 701t Advanced with RAID 1424, 1610
SYMPOSIUM Call Center Server 701t Assembly Peripheral Bay 303, 422, 1373
SYMPOSIUM Call Center Server 701t CPU 200Mz PPRO 256K L2 Cache 303, 422, 1373
SYMPOSIUM Call Center Server 701t Front Panel and Cable (Power/Reset Switches + LED) 303, 423, 1373
SYMPOSIUM Call Center Server 701t Platform Server System (32Mb) 304, 858, 1446
SYMPOSIUM Call Center Server 701t SCSI Cable Kit 303, 424, 1373
SYMPOSIUM Call Center Server 701t, RAID Kit A 1610
SYMPOSIUM Call Center Server Administration Assembly 1598
SYMPOSIUM Call Center Server Back-up and Restore Instructions 1670
SYMPOSIUM Call Center Server Capacity Assessment Guide 1668, 1670
SYMPOSIUM Call Center Server Capacity Assessment Tool 1610
SYMPOSIUM Call Center Server Client Installation 302, 1512
Symposium Call Center Server Feature Document 369, 1491
SYMPOSIUM Call Center Server French Release 1.0 Base Software 26, 1631
SYMPOSIUM Call Center Server Graphical Real Time Display CD-ROM 307, 1063, 1471
SYMPOSIUM Call Center Server Installation Assembly 1598
SYMPOSIUM Call Center Server Peripherals Package 303, 677, 1424
SYMPOSIUM Call Center Server Planning and Engineering Guide 1669, 1670
SYMPOSIUM Call Center Server Power Supply Module, 300W 29, 306, 1376
SYMPOSIUM Call Center Server Release 1 and the Meridian 1 1669, 1670
SYMPOSIUM Call Center Server Release 1, 701t Hardware Installation Guide 307, 1159, 1492
SYMPOSIUM Call Center Server Release 1, 701t Maintenance and Diagnostics Guide 307, 1158, 1492
SYMPOSIUM Call Center Server Release 1, Administration Assembly 1598
SYMPOSIUM Call Center Server Release 1, Call Center Management Guide 1669
SYMPOSIUM Call Center Server Release 1, Database Access and Report Management Guide 1670
SYMPOSIUM Call Center Server Release 1, End to End Task Flow 1158, 1492
SYMPOSIUM Call Center Server Release 1, Historical Statistics Guide 1669
SYMPOSIUM Call Center Server Release 1, Installation Assembly 1598
SYMPOSIUM Call Center Server Release 1, Planning & Engineering Guide 1666
SYMPOSIUM Call Center Server Release 1, Real-Time Display and Statistics Guide 1669
SYMPOSIUM Call Center Server Release 1, Scripting Guide 1669, 1670
SYMPOSIUM Call Center Server Release 1.0 Replacement Software 1610
SYMPOSIUM Call Center Server Release 1.1 Replacement Software 25, 1610
SYMPOSIUM Call Center Server Release 1.5 Documentation CD-ROM 307, 580, 1409
SYMPOSIUM Call Center Server Release 1.5 Replacement Software 297, 678, 1425
SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly 25, 307, 678, 1398, 1425, 1610

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SYMPOSIUM Call Center Server Supplementary CD-ROM Assembly (French) 1583
SYMPOSIUM Call Center Server Terminator Board 306, 427, 1374
SYMPOSIUM Call Center Server Upgrade from Release 1.0 to Release 1.5 1631
SYMPOSIUM Call Center Server Upgrade from Release 1.1 to Release 1.5 1631
SYMPOSIUM Call Center Server Upgrade to Release 1.1 1631
SYMPOSIUM Call Center Server Windows NT 4.0 Client CD-ROM 307, 1064, 1471
SYMPOSIUM Call Center Server, 1003t with Windows NT 3.51 30, 40, 302, 679, 1425
SYMPOSIUM Call Center Server, 1003t with Windows NT 4.0 31, 40, 302, 680, 1425
SYMPOSIUM Call Center Server, 701t Fan, 120mm plus Cardguide 303, 422, 1373
SYMPOSIUM Call Center Server, 702t Advanced 34, 303, 1062, 1471
SYMPOSIUM Call Center Server, 702t Advanced with RAID 34, 303, 1063, 1471
SYMPOSIUM Call Center Server, 702t Advanced with RAID with Windows NT 3.51 48, 303, 1062, 1471
SYMPOSIUM Call Center Server, 702t Advanced with Windows NT 3.51 47, 303, 1061, 1471
SYMPOSIUM Call Center System Administration Documentation Package (English -10) 1598
SYMPOSIUM Call Center System Resource Management Guide (English - 10) 1598
SYMPOSIUM Express Call Center - 1 Agent Increment 295, 675, 1424
SYMPOSIUM Express Call Center - 10 Agent Increment 295, 675, 1424
SYMPOSIUM Express Call Center - 5 Agent Increment 295, 675, 1424
Symposium Express Call Center 1 Agent Increment 296, 724, 1434
Symposium Express Call Center 10 Agent Increment 296, 724, 1434
Symposium Express Call Center 2.0 Replacement/Up-Issue Software Package 295, 676, 1424
Symposium Express Call Center 5 Agent Increment 296, 724, 1434
Symposium Express Call Center Addendum to Planning, Installation, and Administration Guide 297, 1170, 1498
SYMPOSIUM Express Call Center Base System 1617, 1631
SYMPOSIUM Express Call Center Documentation CD 296, 721, 1434
SYMPOSIUM Express Call Center Documentation Suite 296, 722, 1434, 1617
SYMPOSIUM Express Call Center Installation and Configuration Service 296, 1199, 1512
SYMPOSIUM Express Call Center LAN Package Option 11C 296, 725, 1434
Symposium Express Call Center LAN Package, 51C 296, 726, 1434
SYMPOSIUM Express Call Center LAN Package, Options 61C-81C 296, 725, 1434
SYMPOSIUM Express Call Center Management Guide 296, 1497, 1670
SYMPOSIUM Express Call Center Planning, Installation and Administration Guide, English 296, 1494
SYMPOSIUM Express Call Center Quick Reference Card 1669
SYMPOSIUM Express Call Center Release 1.0 Client Application CD, English 296, 720, 1433
Symposium Express Call Center Release 1.0 Server Application CD 295, 1433
SYMPOSIUM Express Call Center Release 2.0 Base System 296, 723, 1434
SYMPOSIUM Express Call Center Release 2.0 Base System Upgrade from Release 1.0 296, 726, 1434
SYMPOSIUM Express Call Center Release 2.0 Client Application CD, English 296, 720, 1433
SYMPOSIUM Express Call Center Replacement/Up-Issue Software Package 295, 676, 1424
SYMPOSIUM Express Call Center Server Reports and Displays Guide 296, 1497, 1669
SYMPOSIUM Express Call Center Supplementary CD 296, 721, 1433
Symposium Express Call Center Supplementary CD 296, 721, 1434
SYMPOSIUM Express Call Center Task Flow Guide 296, 1497, 1669
SYMPOSIUM Express Call Center Upgrade to Release 2.0 1617
SYMPOSIUM Express Call Center, Option 11C Compact System 1631
SYMPOSIUM FastView INSTALL-PREP Remote Installation 311, 1191, 1511
SYMPOSIUM FastView INSTALL-PRO Installation 5 to 8 Seats 311, 1190, 1511
SYMPOSIUM FastView New Software Package 1C 310, 504, 1387
Symposium FastView New Software with MCA and Documentation Package 3A (1-19 Units) 1634
SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7A (1-19 Units) 310, 1005, 1465
SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7B (20-49 units) 310, 1005, 1465

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SYMPOSIUM FastView New Software, Communicator Card and Documentation Package 7C (50+ Units) 310, 1005, 1465
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8A (1-19 Units) 310, 1006, 1465
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8B (20-49 Units) 311, 1006, 1465
SYMPOSIUM FastView New Software, Communicator Card, M2216 and Documentation Package 8C (50+ Units) 311, 1006, 1465
Symposium FastView New Software, MCA and Documentation Package 3B (20-49 Units) 1634
Symposium FastView New Software, MCA and Documentation Package 3C (50+ units) 1634
SYMPOSIUM FastView New Software, MCA M2216 and Documentation Package 5A (1-19 Units) 311, 1124, 1479
SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5B (20-49 Units) 311, 1124, 1479
SYMPOSIUM FastView New Software, MCA, M2216 and Documentation Package 5C (50+ Units) 311, 1125, 1479
SYMPOSIUM FastView Software Support 311, 1191, 1511
SYMPOSIUM FastView Upgrade Software Package 1A 310, 1387
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6A (1-19 Units) 310, 1004, 1465
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6B (20-49 units) 310, 1004, 1465
SYMPOSIUM FastView Upgrade Software, Communicator Card and Documentation Package 6C (50+ Units) 310, 1004, 1465
SYMPOSIUM FastView/FastView+ Information Sheet 369, 1490
SYMPOSIUM Integrated IVR Data 368, 1489
SYMPOSIUM Integrated IVR Tactical Audio Sales Training 371, 1487
SYMPOSIUM IVR CD-ROM Interactive Product Demo 371, 1492
SYMPOSIUM Open IVR Data Sheet 368, 1489
SYMPOSIUM OPEN IVR Demo Disk and Audio Course 371, 1490
SYMPOSIUM Open IVR Demonstration Disks 371, 1490
SYMPOSIUM Portfolio Package 369, 1491
SYMPOSIUM Remote Agent Sheet 369, 1491
SYMPOSIUM Script Implementation, Validation and Testing 1694
SYMPOSIUM Semi-Annual Re-Evaluation 1694
SYMPOSIUM Server 1000t, RAID Kit A 1424, 1610
SYMPOSIUM Server 1000t, RAID Kit B 1424, 1610
SYMPOSIUM Server, 1000t - with Chassis, Motherboard, and Floppy Drive Assembly 305, 418, 1372
SYMPOSIUM Server, 1000t 26 Gb Tape Upgrade 1424, 1610
SYMPOSIUM Server, 1000t 32 Mb RAM Upgrade 1424, 1610
SYMPOSIUM Server, 1000t 4 Gb HD Upgrade 1424, 1610
SYMPOSIUM Server, 1000t Advanced 1424, 1610
SYMPOSIUM Server, 1000t Base 1424, 1609
SYMPOSIUM Server, 1000t Base with RAID 1424, 1609
SYMPOSIUM Server, 1000t Chassis Assembly, No Power Supply 1370, 1559
SYMPOSIUM Server, 1000t Drive Tray 305, 412, 1371
SYMPOSIUM Server, 1000t Dual Processor Upgrade 1424, 1610
SYMPOSIUM Server, 1000t Foot 305, 408, 1370
SYMPOSIUM Server, 1000t Mid 1424, 1609
SYMPOSIUM Server, 1000t Mid with RAID 1424, 1610
SYMPOSIUM Server, 1000t Peripheral Mounting Rail 305, 408, 1370
SYMPOSIUM Server, 1000t XXPress 166 MHz P5 CPU with 512KB Sync Cache 305, 420, 1372
SYMPOSIUM Server, 1000t XXPress Memory Board with NO DRAM Included 305, 416, 1372
SYMPOSIUM Solution Orientation and Script Design 1694
SYMPOSIUM System Administration Training 1694
SYMPOSIUM TAPI Driver for ICM - TCP/IP 560, 1405
SYMPOSIUM TAPI Driver for ICM with Bay ARN Router 560, 1405
SYMPOSIUM TAPI Server, One Additional Year of Software Support 302, 1187, 1511
SYMPOSIUM TAPI Service Provider for Meridian 1 Release 2 325, 582, 1409, 1599
SYMPOSIUM TAPI Service Provider for Meridian 1, Release 2 Direct Connect Option 325, 583, 1409
SYMPOSIUM TAPI Service Provider INSTALL-PREP 326, 1187, 1510
SYMPOSIUM TAPI Service Provider INSTALL-PRO 326, 1187, 1510
SYMPOSIUM TAPI Service Provider Release 2 CD ROM 1599

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

SYMPOSIUM TAPI Service Provider Release 2 Customer Information Label 1669
SYMPOSIUM TAPI Service Provider Release 2, IVR and Networking Option 325, 582, 1409
SYMPOSIUM TAPI Service Provider Release 2, Software and Documentation 1599
SYMPOSIUM TAPI Service Provider Replacement CD-ROM 325, 584, 1410, 1599
SYMPOSIUM TAPI Service Provider Security Device 1583
SYMPOSIUM TAPI Service Provider Upgrade Software 325, 583, 1410, 1599
SYMPOSIUM Transaction Fee 302, 1190, 1511
SYMPOSIUM WebResponse Server 1 Client Expansion Package 1629
SYMPOSIUM WebResponse Server 10 Client Expansion Package 1629
SYMPOSIUM WebResponse Server 2 - One Client Expansion Package 308, 1390
SYMPOSIUM WebResponse Server 2 - Ten Client Expansion Package 308, 1390
SYMPOSIUM WebResponse Server 2 - Twenty Five Client Expansion Package 308, 1390
SYMPOSIUM WebResponse Server 2 Basic Package 308, 523, 1390
Symposium WebResponse Server 2 PEP 1390
SYMPOSIUM WebResponse Server 2 Replacement Package 308, 523, 1390
SYMPOSIUM WebResponse Server 25 Client Expansion Package 1629
SYMPOSIUM WebResponse Server Additional 1 Day Installation Services 308, 1194, 1511
SYMPOSIUM WebResponse Server Annual Telephone Support 308, 1194, 1511
SYMPOSIUM WebResponse Server Basic Package 1629
SYMPOSIUM WebResponse Server Installation Service 308, 1194, 1511
Synchronous Data Formatter 1383, 1570
System 600/48 & MPP 600 Seismic Anchor 183, 502, 1384
System 600/48 Control Circuit Pack 185, 569, 1406
System 600/48 DC Duct 187, 1156, 1488, 1642
System 600/48 Front Access Controller 185, 569, 1406
System 600/48 Fuse Circuit Pack 185, 569, 1406
System 600/48 Isolation Kit 186, 1151, 1486
System 600/48 LVD Interface Circuit Pack 185, 568, 1406
System 600/48 Modular Power Package - Main Cabinet 160, 470, 1379
System 600/48 Modular Power Package - Supplemental Cabinet 160, 470, 1379
System 600/48 NTP 347, 1155, 1487
System 600/48 Seismic Anchor 1676
System 600/48 Supplemental Cabinet Adaptor 185, 568, 1406
System Administration Guide 1655
System and software update guide NTP 1659, 1660
System and Software Upgrade Guide 345, 1438, 1667
System and software upgrade guide 1661, 1663, 1664, 1665
System and software upgrade guide NTP 1661
System and Software Upgrade Guide, Release 24 and Earlier 348, 1494
System Clock Generator 1503, 1679
System Core Card 1431, 1616
System Core Pack 67, 178, 702, 1430, 1615
System installation and maintenance 1664, 1666, 1667
System Installation and Maintenance Guide 345, 1438
System installation and maintenance guide 1661, 1663, 1664, 1665, 1667
System Installation and Maintenance Guide NTP 1657
System installation and maintenance guide NTP 1658, 1659, 1660, 1661
System Installation and Maintenance Guide, Release 24 and Earlier 348, 1494
System Installation and Maintenance, Release 24 and Earlier 348, 1494
System management overview, applications & security spirals 1667
System Management Overview, Applications and Security Spirals, Release 24 and Earlier 348, 1494
System Matrix Printer 1547
System Monitor 197, 602, 1414, 1603
System Monitor - Option 21A 1411, 1599
System Monitor Column Cable (30 In.) 189, 605, 1415
System Monitor Column Cable (AEM) 328, 611, 1416
System Monitor Inter-CPU Cable (30 In.) 189, 607, 1415
System Monitor Jumper Cable (11 In.) 189, 606, 1415
System Monitor Panel 1411, 1599
System Monitor Serial Link Cable (7 Ft.) 189, 606, 1415
System Monitor to MDF Cable (100 Ft.) 189, 612, 1416
System Monitor to MDF Cable (150 Ft.) 189, 612, 1416
System Monitor to MDF Cable (32 Ft.) 189, 610, 1416
System Monitor to Power Cabinet Cable (100 Ft.) 189, 611, 1416
System Monitor to Power Cabinet Cable (32 Ft.) 189,

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

608, 1415
System Monitor to Power Cabinet Cable (64 Ft.) 189, 611, 1416
System Monitor to QBL12 Cable (32 Ft.) 189, 608, 1415
System Monitor to QBL15 Cable (32 Ft.) 189, 607, 1415
System Monitor to SDI Cable (60 In.) 189, 606, 1415
System Monitor to SDI Paddleboard Cable (34 In.) 189, 606, 1415
System Monitor to UPS (Alpha) Cable (45 Ft.) 189, 608, 1415
System Monitor to UPS (Best) Cable (45 Ft.) 189, 606, 1415
System Monitor to UPS (Exide) Cable (45 Ft.) 189, 607, 1415
System Option 21, 51, 61, 71 Installation & Maintenance Guide 1656
System Option 21, 51, 61, 71 Installation and Maintenance Guide 1656, 1657
System Option 21, 51, 61, 71 Planning and Engineering Guide 1656
System Overview 35mm Presentation 1652
System Peripheral Switch - 8 Way Spare 282, 968, 1461
System Planning and Engineering Guide 345, 1438
System planning and engineering guide 1661, 1663, 1664, 1665, 1667
System Planning and Engineering Guide NTP 1657
System planning and engineering guide NTP 1658, 1659, 1660, 1661
System Planning and Engineering Guide, Release 24 and Earlier 348, 1494
System Recovery Boot Package 276, 932, 1455
System Speed Call Key Cap Package (50/PK) 1557
System Tape (450 Ft.) 1567
System Tape 450 Ft. 1567
System Utility to XSM Cable 188, 1400
Systems in Action Upgrade Flyers 1651
Systems Programming Guide 349, 1498

T

T1 2 Pair Cable with RJ48 Connector 29, 223, 1376
T1 Carrier Link Cable Kit (32 Ft.) 189, 1413
T1 Link Cable Kit (32 Ft.) 66, 189, 1413
T1 Multipurpose Digital Interface (TMDI) 65, 179, 836, 1444
T1 Port Assembly (24 ports) 273, 283, 1370
Taiwan-Mandarin Prompt-Bilingual 1702
Taiwan-Mandarin Prompt-Unilingual 1702
Tandberg EC Tape Drive Unit, EC 263, 267, 578, 1409
Tandberg Tape & Disk Drive Unit, Modular Option 1407, 1596
Tandberg Tape and 4.5GB Disk Drive Unit, Modular Option 263, 267, 574, 1407
Tandberg Tape Drive Cleaning Kit 239, 249, 272, 283, 404, 1369
Tandberg Tape Drive Unit - External 239, 249, 426, 1370, 1373, 1558
Tandberg Tape Drive Unit Options (ST/RT, NT/XT) 267, 548, 1401
Tandberg Tape Drive Unit, Modular Option 263, 267, 574, 1407
Tape Assembly 1399, 1587, 1649
Tape Backup Unit Spare 294, 928, 1455
Tape Drive 1401, 1588
Tape Drive Blank Faceplate 269, 604, 1415
Tape Drive Cleaning Kit 267, 391, 1367
Tape Drive Unit 1401, 1407, 1588, 1596
Tape Drive Wall Mounting Kit 239, 249, 697, 1428, 1612
Tape Shelf 1507, 1684
Tape Unit 1509, 1686
Tape Unit & Shelf 1509, 1686
Tape Unit and Shelf 1508, 1685
Tape Unit Interface 1503, 1679
TAPI Integration - Remote Installation 275, 1196, 1511
TAPI Integration - Solution Pro 275, 1196, 1511
TAPI Server INSTALL-PREP 1695
TAPI Server INSTALL-PRO 1695
TAPI Server Software Support 1695
TCP/IP Option Guide (DA212) 1553
TCP/IP Routing (TCP100) 1551
TCP/IP Server-to-Server (TCP200) 1551
TDR 1000 Assembly 1553
TDR 1000 Basic Unit 1366, 1551
TDR 600 Assembly 1553
TDR 600 Basic Unit 1366, 1551
TDS/DTR Card 67, 178, 693, 1427, 1611
Technical Reference Guide 353, 1485
Technical Reference Guide, Release 25 63, 70, 349, 1498
Telecom 25 Pair (50-Pin) to 6DB-25 Female Connector 196, 1174, 1500, 1675
Telecom 25 Pair (50-Pin) to 6DB-25 Male Connector 196, 1174, 1500, 1675
Telephone Number Card - Gray 1645
Telephone Number Card White 1641
Telephone Number Lens (1 each, Standard for all Meridian Digital Telephones and Attendant Consoles) (M2000 Series) 208, 1141, 1481
Telephone Number Sheet (M3900 Series, Package of 15 P0888695) 40, 207, 527, 1391
Telephony Services INSTALL-PREP 1695

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Telephony Services INSTALL-PRO 1695
Teleset Guide Package - Latin American Spanish 227, 1384
Terminal Bracket Assembly 1645
Terminating Plug 187, 1179, 1180, 1506, 1683
Text to Speech - L and H - 6 Port RTU Expansion 44, 279, 954, 1458
Text to Speech - L and H - Base Card and 6 Port RTU 43, 279, 950, 1457
Text to Speech - TrueVoice - Base Card and 2 Port RTU 43, 279, 950, 1457
Text to Speech - TruVoice - 2 Port RTU Expansion 44, 279, 954, 1458
Text-To-Speech (4 ports) 1586
Text-to-Speech Card 1559
Text-To-Speech Expansion (4 ports) 1559
Thermostat 1567
Thermostat Harness 184, 606, 1415
Third Rectifier O/P Cable 1597
This code allows the addition software packages to be enabled for Inter-Office Feature Set. 59, 806, 1438
Three Button Mouse 41, 222, 307, 856, 1446
Three Port Segmented Extender 1502, 1678
Three-Port Extender 183, 1177, 1503, 1679
Tilt Base 1661
Tip and Ring Cable (20 In.) 191, 622, 1418
Token Ring Adapter Kit 275, 276, 294, 1455
Token Ring Bridging (TRB100) 1552
Token Ring LAN Interface - Netware SPX 1628
Token Ring LAN Interface Board 271, 980, 1463
Token Ring LAN Interface Card with NETBEUI drivers 1627
Token Ring LAN Interface Card with Netware IPX NetBIOS drivers 1627
Token Ring LAN Interface Card with TCP NetBIOS drivers 1627
Token Ring, NetBEUI LAN Integration Software 1628
Tone & Digit Switch 1502, 1678
Tone and Digit Switch 1 1504, 1680
Tone and Digit Switch 2 1504, 1680
Tone and Digit Switch for CAS 1502, 1678
Tone Detector 1383, 1503, 1570, 1679
Top Cap - Option 21A 1599
Top Cap AC 183, 588, 1410
Top Cap Cable Egress Panel 184, 1146, 1482
Top Cap DC 183, 588, 1410
Top Cover 1640
Top Cover Filler Plate - Ash 1661
Top Cover Filler Plate - Black 1661
Top Cover Filler Plate - Gray 1661
Top Cover Filler Plate, Ash (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S) 210, 1155, 1487
Top Cover Filler Plate, Black (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S) 210, 1154, 1487
Top Cover Filler Plate, Gray (1 each for M2006, M2008/M2008HF, M2216, M2216 ACD and M2016S) 210, 1155, 1487
Top Cover Louver 1646
Tower AP or Tower MRS/AP Wide SCSI Terminator Spare 283, 1462
Tower/Rack CallPilot 1.05/1.06 to CallPilot 1.07 Upgrade Kit 36, 226, 1118, 1475
Trace Key Cap Package (50/PK) 207, 399, 1368
Traffic Reporting 1698
Traffic Reporting 1.5 Demonstrator 1654
Traffic Reporting Documentation (Version 1) 352, 1482
Traffic Reporting Version 1.4 to 1.5 Upgrade 1698
Traffic Reporting Version 2.4 1699
Traffic Reporting Version Update 1698
Transceiver 296, 306, 393, 1367
Transceiver (MAU to 10 Base T) 42, 220, 222, 860, 1447
Transfer Key Cap Package (50/PK) 1557
Transfer Unit 1509, 1686
Transfer Unit Assembly - EMI 1527
Transfer Unit Assembly-EMI 1528
Transformer Power 5/12V QMT11 1547
Transformer, 24V AC (M1250/DSS-9000) 209, 390, 1367
Transition Cable 272, 1412
Transition Card (for MVME332) 327, 574, 1407
Transmitter Unit (SL-1 Handset) 1548
Transport Controller 1383, 1570
Transport Repeater 1383, 1570
Transport Terminator 1383, 1570
Triple SDI Cable (External) 1675
Triple SDI Cable (Internal) 196, 1175, 1500, 1675
Triple SDI Cable Assembly - EMI 1527
Trunk Cable (15 Ft.) 1587
Trunk Cable (30 Ft.) 1587
Trunk Cable (60 Ft.) 1587
Trunk Cable (90 Ft.) 1587
TWINAX Balun 1570
Twisted Pair Cable 14 Ft 1571
Twisted Pair Cable 25 Ft 1571
Twisted Pair Cable 3 Ft 1571
Twisted Pair Cable 37 Ft 1571
Twisted Pair Cable 50 Ft 1571
Twisted Pair Cable 7 Ft 1571
Two Optical Adaptors Kit 197, 508, 1388
Two-Module Pedestal Assembly AC 1561
Two-Module Pedestal Assembly DC 1561

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

U

U0070A 1711
U0070D 1711
U0071 1711
U0073A 1711
U0073D 1711
U0074 1711
U0075 1711
U1107 1711
U1108 1711
U7000 1711
U7001 1711
U7002 1711
U7003 1711
U7004 1711
U7005 1711
U7006 1711
U7007 1711
U7010A 1711
U7010D 1711
U7011A 1711
U7011D 1711
U7012A 1711
U7012D 1711
U7013A 1711
U7013D 1711
U7014A 264, 1314, 1520
U7014D 264, 1314, 1520
U7015A 264, 1315, 1520
U7015D 264, 1315, 1520
U7016A 264, 1316, 1520
U7016D 264, 1316, 1520
U7017A 264, 1317, 1520
U7017D 264, 1317, 1520
U7018001 248, 1318, 1520
U7018002 248, 1318, 1520
U7018003 248, 1319, 1520
U7018004 248, 1319, 1520
U7060D 1711
U7061D 1711
U7062D 1711
U7063D 1711
U7064 1711
U7065 1712
U7066 1712
U7067 1712
U7068D 265, 1320, 1520
U7069D 265, 1320, 1520
U7070 265, 1321, 1520
U7071D 265, 1321, 1520
U7100A 1712
U7100D 1712
U7101A 1712
U7101D 1712
U7200A 1712
U7200D 1712
U7201A 1712
U7201D 1712
U7202 263, 1322, 1520
U7203 263, 1322, 1520
U7205 1712
U7206 1712
U7207 263, 264, 265, 1322, 1520
U7208 1712
U7209 1712
U7210 1712
U7211 1712
U7212 1712
U7213 1712
U7214 1712
U7215 1713
U7216 1713
U7217 1713
U7218 1713
U7219 1713
U7220 1713
U7221 1713
U7222 1713
U7230 1713
U7231 1713
U7232 1713
U7233 1713
U7234 1713
U7235 1713
U7236 1713
U7237 1713
U7238 1713
U7239 1713
U7240 1713
U7241 1713
U7242 1713
U7243 1713
U7250 1713
U7251 1713
U7252 1713
U7253 1714
U7260 1714
U7261 1714
U7301C 1714
U7301D 1714
U7305C 1714
U7305D 1714
U7306 1714
U7405 1714
U7406 1714
U7502A 1714
U7502D 1714

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

U7503A 1714
U7503D 1714
U7504 1714
U7600A 324, 1323, 1520
U7600D 324, 1324, 1520
U9100 1714
U9101 1714
U9105 1714
U9110 1714
U9200 1714
U9201 1714
U9202 1714
U9246 1714
U9250 1714
U9251 1714
U9252 1714
U9300 1714
U9301 1714
U9310 1714
U9370 1714
U9371 1714
U9372 1714
U9373 1714
U9374 1714
U9375 1715
U9400 1715
U9401 1715
U9402 1715
U9403 1715
U9404 1715
U9405 1715
U9406 1715
U9407 1715
U9410 1715
U9411 1715
U9412 1715
U9413 1715
U9414 1715
U9415 1715
U9500 1715
U9501 1715
U9502 1715
U9503 1715
U9600A 1715
U9600D 1715
U9601A 1715
U9601D 1715
U9602A 1715
U9602D 1715
U9603A 1715
U9603D 1715
U9604A 1715
U9604D 1715
U9605A 1715
U9605D 1715
U9606A 1715
U9606D 1715
U9607A 1715
U9607D 1716
U9608A 1716
U9608D 1716
U9609A 1716
U9609D 1716
U9610 1716
U9611 1716
U9612 1716
U9613 1716
U9614 1716
U9615A 1716
U9616 1716
U9617 1716
U9618 1716
U9619 1716
U9620 165, 1324, 1521
U9624A 1716
U9624D 1716
U9625A 1716
U9625D 1716
U9626A 1717
U9626D 1717
U9627A 1717
U9627D 1717
U9628A 1717
U9628D 1717
U9629A 1717
U9629D 1717
U9630A 1717
U9630D 1717
U9631 1717
U9632 1717
U9633 1717
U9634 1717
U9635 1717
U9636A 1717
U9636D 1717
U9637A 1717
U9637D 1717
U9638A 1717
U9638D 1717
U9639A 165, 1325, 1521
U9639D 165, 1327, 1521
U9640 165, 1328, 1521
U9641A 165, 1330, 1521
U9641D 165, 1331, 1521
U9642A 1717, 1718
U9642D 1718
U9643A 165, 1333, 1521
U9643D 165, 1334, 1521

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

U9644A 165, 1336, 1521
U9644D 165, 1337, 1521
U9645 165, 1338, 1521
U9646A 165, 1340, 1521
U9646D 165, 1341, 1521
U9650A 165, 1343, 1521
U9650D 165, 1346, 1521
U9651A 165, 1349, 1521
U9651D 165, 1352, 1521
U9652 165, 1354, 1521
U9653A 165, 1356, 1521
U9653D 165, 1359, 1521
U9654A 165, 1361, 1521
U9654D 165, 1521
U9655A 165, 1521
U9655D 165, 1521
U9656A 165, 1521
U9656D 165, 1521
U9657 165, 1521
U9658A 165, 1521
U9658D 165, 1521
U9700 1718
U9800 1718
U9801 1718
U9850 1718
U9851 1718
U9900 1718
U9901 1718
U9902 1718
U9903 1718
U9924 1718
U9980 1718
UDS 2440 Modem 1366
UDS FastTalk Modem, 9600 Baud 1556
UDS Modem 1398, 1584
UDS V.3225 Synchronous Modem 272, 389, 1367
U-Interface Line Card (UILC) 65, 177, 576, 1408
Uninterruptable Power Supply Unit 1570
Uninterruptible Power Supply (UPS) 110V - OIVR 4.0 Tower AP, MRS/AP, or MRS/Tower 276, 933, 1455
Uninterruptible Power Supply (UPS) Kit for Messenger Server 270, 972, 1462
Uninterruptible Power Supply (UPS) Shared Rack Model - 110 V - Up to 3 MRS/Rack or AP/Rack Shelves 1625
Uninterruptible Power Supply (UPS) Shared Rack Model - 220 V - Up to 3 MRS/Rack or AP/Rack Shelves 1625
Uninterruptible Power Supply (UPS) Tower Model - 220V - 1 AP, MRS/AP, or MRS/Tower 1455, 1624
Uninterruptible Power Supply Option Installation Documentation (DA185) 1648
Universal I/O Panel 186, 1151, 1486, 1654
Universal MIxx Ethernet Adapter (for IPE Modules) 176, 1402
Universal MIxx Ethernet Adapter (Option 11) 176, 1402
Universal Peripheral Equipment Shelf 1507, 1684
Universal Power Supply 335, 1433
Universal Trunk Card 40, 65, 178, 601, 1414, 1603
UNIX O/S Tape 1575
UNIX OS Software 1600
UNIX R3V7.1 1622
Update to Black Quick Reference Guide Binder 375, 1490
Updates to Engineering Handbook Issue 2 1650
Upgrade Engineering & Installation Guide NTP 1657
Upgrade Engineering and Installation Guide NTP 1658
Upgrade Guide 1670
Upgrade Package from 32-800 Lines to 801-1200 Lines 1718
Upgrade Package from 801-1200 Lines to 1201+ Lines 1718
Upgrade Package IIVR Release 1 to Release 2.2 921, 1454
Upgrade Procedures (Coil) 1665
Upgrade to P0705039 1652
UPS Control Cable (DTS285) 1549
UPS for AC-powered MRS/Tower and MRS/Rack 1558
UPS for AP or MRS/AP 1558
UPS Smart Signalling Cable Spare 283, 1462
UPS Software Upgrade from Release 2.08 to Release 2.2 926, 1454
US Meridian 1 Product Catalog Binder Set 1397
US Meridian 1 Product Catalog Contents 1397
User Guide 1617, 1649
User Reference Card 1655
Users Guide - BNS/DTS/VINES (DA204-01) 1647
Utility Card with Modem 1408, 1597
Utility Card without Modem 249, 267, 579, 1409

V

V.11 Termination Panel 1439, 1619
V.24 Cable (360") 1618
V.35 Add-On Data Module 1501, 1676, 1677
V.35 Fanout Panel 1619
V.35 Termination Panel 1439, 1619
V.35/V.11 Cable (54") 1618
V005 1718
V006 1718
V006-11 1718
V006-12 355, 1521
V008 355, 1522

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Value Added Services & Feature Sales Feature Sheet 1650
Ventel 9600 Plus Modem 1367, 1556
Ventel Modem (EC2400) (Release 6.0) 1552
Venture 1 Headset w/15 Ft. Coiled Cord 1508, 1685
Venture 1 Headset w/5 Ft. Straight Cord 1508, 1685
Vertical Jumper 1587
VGA Monitor Cable - 2 Meters Spare 1626
VGA Monitor Cable - 4 Meters Spare 1626
Video Card Adapter 38, 221, 1373, 1560
View Manager Basic Technical Support 330, 985, 1463
View Manager Consulting and Professional Services 330, 986, 1463
View Manager Custom Configuration 330, 985, 1463
View Manager Documentation Set 330, 986, 1463
View Manager Elite Technical Support 330, 985, 1463
View Manager for Hosted Service Provider 330, 995, 1464
View Manager Installation Services 330, 986, 1463
View Manager License Upgrade to 100 Users 330, 987, 1463
View Manager License Upgrade to 200 Users 330, 987, 1463
View Manager License Upgrade to 25 Users 330, 987, 1463
View Manager License Upgrade to 50 Users 330, 987, 1463
View Manager OEM Configuration 330, 985, 1463
View Manager Product Training 330, 986, 1463
View Manager Quick Reference Guides 330, 986, 1463
View Manager with 100 User License 330, 984, 1463
View Manager with 200 User License 330, 984, 1463
View Manager with 25 User License 330, 984, 1463
View Manager with 5 User License 330, 983, 1463
View Manager with 50 User License 330, 984, 1463
View Manager with Greater than 200 User License 330, 984, 1463
VINES 3.0 Administration Planning Guide (DA207) 1553
VINES 3.0 Administration Reference (DA206) 1553
VINES 3.0 Server Options Guide (DA205) 1553
VINES 3.0 Users Guide (DA204) 1553
VINES 4.0 Software Upgrade - RTS - BNS/DTS (SSU-400RTS) 1554
VINES 4.0 Software Upgrade - RTS - CNS (SSU-404RTS) 1555
VINES 4.0 Software Upgrade - RTS - VINES/286 (SSU-402RTS) 1554
VINES 4.0 Software Upgrade - RTS - VINES/386 (SSU-403RTS) 1555
VINES 4.0 Software Upgrade - RTS - VINES/386 TEAM (SSU-403TRTS) 1554
VINES 4.0 Software Upgrade - RTS - VINES/386D3 MC (SSU-405RTS) 1552
VINES 4.0 Software Upgrade - VINES/286 (SSU-402) 1552
VINES 4.0 Software Upgrade - VINES/386 (SSU-403) 1552
VINES 4.0 Software Upgrade - VINES/386 TEAM (SSU-403T) 1552
VINES 4.0 Software Upgrade - VINES/386D3 MC (SSU-405) 1552
VINES 4.0 Software Upgrade-BNS/DTS (SSU-400) 1552
Vines 4.0 Software Upgrade-CNS (SSU-404) 1552
VINES Application Developers Guide & Reference (DA224) 1552
VINES Application Developers Programming Interfaces (DA225) 1552
VINES Applications Toolkit (VDT100) (CNS/386) 1554
VINES Architecture Definition (DA142) 1648
VINES Programmers Interface (DOS) (DA141) 1648
VINES Token Ring Bridging Option Guide (DA251-00) 1552
VINES Users Guide and Command Ref-Diskette (DA222) 1552
VINES/286 Software (VNS286R4) 1550
VINES/286 to 386 Upgrade 1553
VINES/286,386 UPS (120VAC) (UPS121) 1551
VINES/286,386 UPS (240VAC) (UPS241) 1551
VINES/386 Microchan Software Package (VNS386D3) 1554
VINES/386 Software (VNS386R4) 1551
VINES/386 Team Software Package (VTM386) 1554
VINES/386 TEAM to VINES/386 Upgrade (UTM386) 1554
VINES/BNS Software (VNS680) 1551
VINES/CNS Software (VNS682) 1551
VINES/DTS Software (VNS681) 1551
Virtual Network Service 98, 108, 119, 131, 139, 1220, 1513
VISIT FastCall 1.1 with MCA Connectivity/cables 1591
VISIT FastCall 1.1 with TelAdaptor Connectivity 1591
VISIT FastCall 1.1 without Connectivity 1591
VISIT FastCall Installation - (Per Scheduled 8 Hour Day On-Site, 5 to 8 Seats) 1569
VISIT FastCall Remote Installation Support 1695
VISIT FastCall/NTS Right To Use 1591
VISIT FastCall/NTS Right to Use for Option 11 1591
VISIT FastCall/NTS Upgrade Right to Use 1591
VISIT FastCall/NTS Upgrade Right To Use for Option 11 1591
VISIT FastCall/NTS Version 1.1 1591

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

VISIT FastCall/NTS Version 1.1 for Option 11 1591
VISIT FastCall/NTS Version 1.1 Upgrade 1591
VISIT FastCall/NTS Version 1.1 Upgrade for Option 11 1591
VISIT Messenger Demo Disk-MAC 1662
VISIT Messenger Demo Disk-PC 1662
VISIT Messenger Server Administration Guide 1628
VISIT Messenger User Guide 1628
VISIT Messenger Visual Voice and FAX Messaging Client Package, 1000 Users 1626
VISIT Messenger Visual Voice and FAX Messaging Client Package, 300 Users 1626
VISIT Messenger Visual Voice and FAX Messaging Client Package, 500 Users 1626
VISIT Messenger Visual Voice and FAX Messaging Client Package, 800 Users 1626
VISIT Messenger Visual Voice and Fax Messaging Server Package, 4 Port 1628
VISIT Messenger Visual Voice Messaging Client Package, 100 Users 1626
VISIT Messenger Visual Voice Messaging Client Package, 1000 Users 1626
VISIT Messenger Visual Voice Messaging Client Package, 300 Users 1626
VISIT Messenger Visual Voice Messaging Client Package, 500 Users 1626
VISIT Messenger Visual Voice Messaging Client Package, 800 Users 1626
VISIT Messenger Visual Voice Messaging Server Package 1628
VistaLAN/Allen Bradley Software 1550
VL to VLE/XL Network Group Upgrade Assembly 1526
VL, VLE or XL/XN Memory Expansion Upgrade Assembly 1714
VL, VLE or XL/XN Network Group Upgrade Assembly (Cabinet Basis) 1528
VL, VLE, XL, XN/XT Cabinet Upgrade Package 1718
VL/VLE CE CPU Cabinet Upgrade Assembly 1526
VL/XL CE Upgrade Assembly 1544
VLAN Maintenance Cable 193, 692, 1426
VLE or XL/XN Network Group Upgrade Assembly (Shelf Basis) 1528
VLE/XL CPU Upgrade Assembly 1544
VLE/XL/XT Two Network Group Cabinet Upgrade 1714
VLE/XN Cabinet Upgrade Assembly 1545
VLE/XN Shelf Upgrade Assembly 1545
VM 1.1 25 Clients Fax and Voice 1626
VME - Ethernet Cable, I/O to Transceiver 272, 296, 306, 328, 1411
VME Built-In Modem External Cable 328, 597, 1412
VME Multi-Port Cable 328, 629, 1419
VME Slot Bypass Card 1557
Voice Activated Business Directory 1000 Name Expansion Kit 1575
Voice Activated Business Directory 1500 Name Expansion Kit 1575
Voice Activated Business Directory 4 ports, 1000 names 1575
Voice Activated Business Directory 4 Ports, 1500 Names 1575
Voice Activated Business Directory 4 ports, 1500 names 1591
Voice Activated Business Directory 4 ports, 4000 names 1591
Voice Activated Business Directory 4 ports, 500 names 1575
Voice Activated Business Directory 4 to 8 Port Expansion Kit 1575
Voice Activated Business Directory 500 Name Expansion Kit 1575
Voice Activated Business Directory 8 Ports, 1000 Names 1575
Voice Activated Business Directory 8 Ports, 1500 Names 1575
Voice Activated Business Directory 8 ports, 1500 names 1591
Voice Activated Business Directory 8 ports, 4000 names 1591
Voice Activated Business Directory Back-up Drive 1591
Voice Activated Business Directory Color Monitor 1591
Voice Activated Business Directory Professional Services 1695
Voice Activated Business Directory Release 1 to Release 2 Upgrade 1631
Voice Call Key Cap Package (50/PK) 1556
Voice Compressor 1383, 1571
Voice Form 275, 1195, 1511
Voice Menus and Voice Forms Brochure 372, 1484
Voice Menus Software 1700
Voice Messaging 16 1533
Voice Messaging 8 1533
Voice Messaging Pocket Guide 1649
Voice Messaging Template 1646
Voice Messaging Template (Digital Sets) (100/PK) 351, 1481
Voice Package 1620
Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America 43, 278, 947, 1457
Voice Port Assembly - 16 Port Loopstart and 16 Port RTU - North America - Pulse Detection 43, 278, 947, 1457
Voice Port Assembly - 16 Port Loopstart Spare - North America 281, 962, 1459
Voice Port Assembly - 16 Port Loopstart Spare - North

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

America - PULSE DETECTION 281, 962, 1459
Voice Port Assembly - 24 Port T1 and 24 Port RTU - North America 43, 278, 280, 948, 1457
Voice Port Assembly - 24 Port T1 Spare - North America 281, 963, 1459
Voice Port Assembly - 4 Port Loopstart and 4 Port RTU - North America and CALA 43, 279, 280, 948, 1457
Voice Port Assembly - 4 Port Loopstart Spare - North America and CALA 281, 963, 1459
Voice Prompt/Database Editor for Run-Time Systems Only 290, 536, 1398
Voice Service Slide Presen Rev 1 1648
Voice Service Slide Updates 1648
Vol. #1 Engineering 1642, 1643
Vol. #2 PE Installation/Maintenance 1642, 1643
Vol. #3 Software X11 Rls. 1-3 1642
Vol. #3 Software X37 Rls. 1-3 1643
Vol. #4 System Installation/Maintenance 1642
VP4 Card 258, 266, 578, 1409
VP4 Card - Flexible Assignment 1566
VP8 Card 258, 266, 579, 1409
VP8 Card - Flexible Assignment 1566
VT100 Communications Board (32 Ports) 1559
VT100 Host Communications - 16 Ports 1585
VT100 Host Communications - 32 Ports 1585
VT100 Host Communications - 8 Ports 1585
VT100 over TN - Base and 16 Sessions 1625
VT100 over TN - Expansion 16 Sessions 1625
VT520 Video Terminal 240, 250, 269, 393, 1367
VTG Adapter Cable 29, 223, 1376
VTG VB2001 26, 1623
VTG VB2002 42, 47, 222, 1447
VTG VB2007 42, 47, 222, 1447
VTG VB2009 32, 222, 1447

W

Waiting Key Cap Package (50/PK) 206, 395, 1368
Wake Up Key Cap Package (50/PK) 1557
Wall Mount Handset Clip (1 each, for all Meridian Digital Telephones) 209, 1142, 1481
Wall Transformer 1640
Wall Transformer (M3900 Series) 209, 818, 1440
Wall Transformer, 110VAC-26.7VAC, (used with NT2K10xx) 209, 388, 1367
Web Call Back 275, 1193, 1511
Web Integration Software - 1 AP RTU 278, 946, 1457
What's New For Release 1.06 - French 1670
What's New In Meridian Mail Release 13 1496
WhatsNewInMeridianMailRelease13' 349
White Telecom Professional QRG Binder 375, 1490
Wide SCSI Cable 223, 1375
Wide SCSI Cable - 68 Pin Spare 282, 967, 1461
Wide SCSI Terminator 39, 221, 432, 1375
Wide to Narrow SCSI Cable Adapter Spare 282, 1461
Winchester Hard Disk Assembly 1501, 1676
Windows NT 4.0 Install Diskette 41, 226, 1446
Windows NT 4.0 OS Recovery CD 41, 226, 853, 1446
Winning With Application Sales
Meridian Call Center Sales Training Kit (with video) 362, 1369
Meridian Call Center Sales Training Kit (without video) 362, 1369
Work Order System 2.3 Demonstrator 1654
Work Order System Version 2.4 1699
Work Order System Version Update 1698
Work Order Systems 1698
Work Order Systems Documentation (Version 1) 1653

X

X Windows/Motif Manuals 1658
X.25 Communications Adapter (NM127) 1366, 1549
X.25 Communications Controller 1369, 1558
X.25 Data Communications Software 1704
X.25 Gateway 1533
X.25 Option Guide (DA184-03) 1648
X.29 Option-Asynchronous Term Emulation over X.25 (HA201) 1552
X0645393 1522, 1718
X11 Administration Programs 349, 1498, 1667
X11 administration programs 1663, 1664, 1666
X11 Administration Programs, Release 24 and Earlier 348, 1494
X11 Data Features 346, 1438
X11 data features 1662, 1664, 1667
X11 Data Features Guide NTP 1657
X11 data features guide NTP 1658
X11 data features NTP 1659, 1660
X11 Data Features, Release 24 and Earlier 348, 1494
X11 Data Input Forms (Release 17) 1656
X11 Data Input Forms (Release 19) 1660
X11 Data input forms (Release 19) 1657
X11 Data Input Forms Release 15 1569
X11 feature document 1657, 1659, 1660, 1662
X11 Feature Document (Release 12 Supplement) (5/PK) 352, 1482
X11 Feature Document (Release 17) 1656
X11 Feature Document, Release 24 and Earlier 348, 1494
X11 Hospitality Features 346, 1438
X11 hospitality features 1662, 1664, 1666, 1667
X11 Hospitality Features Guide NTP 1657

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

X11 hospitality features guide NTP 1658
X11 hospitality features NTP 1659, 1660
X11 Hospitality Features, Release 24 and Earlier 348, 1494
X11 Input/Output Guide 346, 1438
X11 input/output guide 1662, 1663, 1664, 1665, 1667
X11 input/output guide NTP 1659, 1660, 1661
X11 Input/Output Guide NTP (Release 1-18) 1657
X11 input/output guide NTP (Release 1-18) 1658
X11 Input/Output Guide, Release 24 and Earlier 348, 1494
X11 Input/Output Reference Guide 1654, 1656
X11 Maintenance Programs 349, 1498, 1667
X11 maintenance programs 1663, 1664, 1666
X11 Maintenance Programs, Release 24 and Earlier 348, 1494
X11 Networking Features 346, 1438
X11 Networking features 1662, 1663, 1664, 1665
X11 networking features 1667
X11 Networking Features Guide NTP 1657
X11 networking features guide NTP 1658
X11 networking features NTP 1659, 1660
X11 Networking Features, Release 24 and Earlier 348, 1494
X11 Release 16 to Release 17 NTP Update Package 1656
X11 Release 17 to Release 18 NTP Update Package 1657
X11 Release 18 Non-Option 81 to Release 19 Option 61C Update Package 1654
X11 Release 18 Option 81 to Release 19 Upgrade Package 1660
X11 Release 19 NANP to Release 19 Option 61C Update Package 1661
X11 Release 19 to Release 19 NANP Update Package 1660
X11 Release 19 with Option 61C to Release 20 Update Package 1662
X11 Software Features Guide 63, 346, 1438, 1667
X11 software features guide 1662, 1663, 1664, 1665
X11 software features guide NTP 1658, 1659, 1660, 1661
X11 Software Features Guide, Release 24 and Earlier 63, 348, 1494
X11 Software Guide 352, 1483, 1655, 1656, 1658
X11 Software Guide NTP (Release 1-18) 1657
X11 Software Input/Output Guide (Coil) 347, 1489
X11 system management guide NTP 1659
X11 system management overview, applications and security 1663, 1664, 1666
X11 System Management, Overview, Applications and Security Guide 346, 1438
X11 system management, overview, applications and security guide 1662, 1663, 1664, 1665, 1667
X11 system management, overview, applications and security guide NTP 1660
X11 System Management, Overview, Applications and Security Guide, Release 24 and Earlier 348, 1494
X11 System Message & Option Settings (Release 16) 1652
X11 System Messages 349, 1498
X11 system messages 1663, 1664, 1666, 1667
X11 System Messages & Option Settings 1654, 1656
X11 System Messages, Release 24 and Earlier 348, 1494
X27 Software Release Upgrade 59, 805, 1437
X27 Software Up-issue (within the same Release) 59, 805, 1437
X37 Data Input Forms Release 6 1645
X9950745 1718
XIOX $100000 Remote Access Warranty 1694
XIOX External Hacker Deadbolt 1560
XIOX Hacker Preventer 1200+ Lines 1602
XIOX Hacker Preventer 32-400 Lines 1560
XIOX Hacker Preventer 401-800 Lines 1560
XIOX Hacker Preventer 801+ Lines 1560
XIOX Hacker Tracker 1602, 1699
XIOX Internal Hacker Deadbolt 1602
XN Memory Expansion Upgrade Assembly 1718
XN Memory Shelf Upgrade Assembly 1718
XN/XT Network Module Expansion 347, 1487
XSM Cable with Ferrite 1619
XT CE Cabinet Assembly 1545

Y

Yearly Support for SYMPOSIUM TAPI Driver up to 100 Hours 434, 1376
Yearly Support for SYMPOSIUM TAPI Driver up to 200 Hours 435, 1376
Yearly Support for SYMPOSIUM TAPI Driver up to 32 Hours 430, 1374
Yearly Support for SYMPOSIUM TAPI Driver up to 40 Hours 434, 1375
Yearly Support for SYMPOSIUM TAPI Driver up to 45 Hours 434, 1376
Yearly Support for SYMPOSIUM TAPI Driver up to 50 Hours 434, 1376

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Copyright 1998 Nortel Networks

This pricing aid is provided “as is” with no warranties of any nature, written or oral, statutory, expressed, or implied, including, without limitation, the warranty of merchantability and the warranty of fitness for a particular purpose. Nortel Networks shall not be liable to or through distributor for any special incidential, or consequential damages, of any nature or for any reason, arising out of distributor’s use of this pricing aid, even if Nortel Networks has been advised of the possibility of surch damages.

FOR USE BY NORTEL NETWORKS AND NORTEL NETWORKS’ AUTHORIZED DISTRIBUTORS. NOT FOR PUBLIC DISCLOSURE: The information contained in this document is the property of Nortel Networks. Except as specifically authorized in writing by Nortel Networks, the holder of this document shall keep the information contained herein confidential and shall protect same in whole or in part from disclosure an dissemination to third parties and use same for evaluation purposes only.

TRADEMARKS: ACCESS, CENTURION, COMPANION, CPLUS, DIGITONE, DMS, DMS-100, DMS-250, GALILEO, INTERLUDE, IVR, JAZZ, LIBERATION, LINK, MAESTRO, MAGELLAN, MERIDIAN, MERIDIAN 1, MERIDIAN DIGITAL CENTREX, MERIDIAN HOMELINK, MERIDIAN LINK, MERIDIAN MAIL, MERIDIAN SAFE, MILLENNIUM, NORSTAR, NORTEL, NORTEL NETWORKS, NORTHERN TELECOM, NT, PASSPORT, POWERTOUCH, PREVUE, QUICK TOUCH, SILHOUETTE, SL, SL-100, STARTALK, SUPERNODE, SYMPHONY, TELADAPT, VISIT, VISIT ASSISTANT, VISIT ENR, VISIT FastCall, VISIT MESSENGER, VISIT VIDEO, VISIT VOICE, and VISTA are trademarks of Nortel Networks.

Apple, AT&T, BANYAN, C, C+, Centrex, DEC, Fort Knox, HP, IBM, InfoLink, Informix, Ingres, Inmac, LANLink, LANSTAR, Mac, MacVINES, Microsoft DOS, Microsoft LAN Manager, Microsoft Windows, Microsoft, Motorola, NEC, NetBEUI, NetBIOS, Novell, Novell Netware, Oracle, Powell, Rolm, Sybase, Tandberg, UDS, UNIX, UNIX O, Vectra, Ventel, and VINES are used for identification purposes only and are owned by companies or individuals not affiliated with Nortel Networks.

Nortel Networks
Commercial Offer Management
2375A N. Glenville Dr.
Richardson, Texas 75082-4399
800 321-2649, select 6 then 5

Artisan Technology Group - Quality Instrumentation ... Guaranteed | (888) 88-SOURCE | www.artisantg.com

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP