ARTISAN®
TECHNOLOGY GROUP

Your **definitive** source for quality pre-owned equipment.

Artisan Technology Group
(217) 352-9330 | sales@artisantg.com | artisantg.com

Full-service, independent repair center
with experienced engineers and technicians on staff.

We buy your excess, underutilized, and idle equipment
along with credit for buybacks and trade-ins.

Custom engineering
so your equipment works exactly as you specify.

- Critical and expedited services
- In stock / Ready-to-ship
- Leasing / Rentals / Demos
- ITAR-certified secure asset solutions

Expert team | Trust guarantee | 100% satisfaction

All trademarks, brand names, and brands appearing herein are the property of their respective owners.

Find the *Physik Instrumente E-503.00* at our website: *Click HERE*

PZT Actuators
PZT Flexure NanoPositioners
PZT Active Optics / Steering Mirrors
Tutorial: Piezoelectrics...
Capacitive Position Sensors
PZT Control Electronics
MicroPositioners / Hexapod Systems
Photonics Alignment & Packaging Systems
Motor Controllers
Index

http://www.pi.ws
info@pi.ws

E-530 Power Supply for E-500 Systems

Ordering Information

E-530.00
Multi-Function Power Supply Module for E-500

Custom Designs for Volume Buyers



E-530.00

- **Included in E-500 Chassis**
- **Provides Power for all E-500-Installable Modules**
- **90-264 VAC Operating Range**

The E-530.00 multi-function power supply module is part of the E-500 chassis (for PZT amplifier & position-servo-controller systems for high- and low-voltage PZTs). It delivers the required operating voltages for all available plug-in modules.

Technical Data

Models	E-530.00
Function:	Primary switching power supply
Output voltages:	+127 V, 0.6 A -33 V, 0.6 A +27 V, 4 A +/- 15 V, 1 A +5 V, 3 A
Dimensions:	205 x 105 x 75 mm
Weight:	1.1 kg
Operating voltage:	90-264 VAC, 50-60 Hz (primary switching wide-range P/S)
Max. power consumption:	150 W
Primary fuse:	1.6 A, slow

E-531.00 Power Supply for E-501 Systems

Ordering Information

E-531.00
Multi-Function Power Supply Module for E-501

Custom Designs for Volume Buyers



E-531.00

- **Included in E-501 Chassis**
- **Provides Power for all E-501-Installable Modules**
- **90-120 / 220-264 VAC Operating Range**

The E-531.00 multi-function power supply module is part of the E-501 chassis (for PZT amplifier & position-servo-controller systems for high- and low-voltage PZTs). It delivers the required operating voltages for all available plug-in modules.

Technical Data

Models	E-531.00
Function:	Linear regulated power supply
Output voltages:	+130 V, 0.2 A, -27 V, 0.2 A +24 V, 1 A, +/- 15 V, 0.5 A +5 V, 1 A
Dimensions:	205 x 105 x 75 mm
Weight:	1 kg
Operating voltage:	90-120 VAC, 50-60 Hz 220-264 VAC, 50-60 Hz
Max. power consumption:	150 W
Primary fuse:	0.63 A, slow

Artisan Technology Group is an independent supplier of quality pre-owned equipment

Gold-standard solutions

Extend the life of your critical industrial, commercial, and military systems with our superior service and support.

We buy equipment

Planning to upgrade your current equipment? Have surplus equipment taking up shelf space? We'll give it a new home.

Learn more!

Visit us at **artisantg.com** for more info on price quotes, drivers, technical specifications, manuals, and documentation.

Artisan Scientific Corporation dba Artisan Technology Group is not an affiliate, representative, or authorized distributor for any manufacturer listed herein.

We're here to make your life easier. How can we help you today?

(217) 352-9330 | sales@artisantg.com | artisantg.com

ARTISAN® TECHNOLOGY GROUP