



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com

PZT Actuators
PZT Flexure NanoPositioners
PZT Active Optics / Steering Mirrors
Tutorial: Piezoelectrics...
Capacitive Position Sensors
PZT Control Electronics
MicroPositioners / Hexapod Systems
Photonics Alignment & Packaging Systems
Motor Controllers
Index

<http://www.pi.ws>
info@pi.ws

E-530

Power Supply for E-500 Systems

Ordering Information

E-530.00
 Multi-Function Power Supply Module
 for E-500

Custom Designs
 for Volume Buyers



- Included in E-500 Chassis
- Provides Power for all E-500-Installable Modules
- 90-264 VAC Operating Range

The E-530.00 multi-function power supply module is part of the E-500 chassis (for PZT amplifier & position-servo-controller systems for high- and low-voltage PZTs). It delivers the required operating voltages for all available plug-in modules.

Technical Data

Models	E-530.00
Function:	Primary switching power supply
Output voltages:	+127 V, 0.6 A -33 V, 0.6 A +27 V, 4 A +/- 15 V, 1 A +5 V, 3 A
Dimensions:	205 x 105 x 75 mm
Weight:	1.1 kg
Operating voltage:	90-264 VAC, 50-60 Hz (primary switching wide-range P/S)
Max. power consumption:	150 W
Primary fuse:	1.6 A, slow

E-530.00

E-531.00

Power Supply for E-501 Systems

Ordering Information

E-531.00
 Multi-Function Power Supply Module
 for E-501

Custom Designs
 for Volume Buyers



- Included in E-501 Chassis
- Provides Power for all E-501-Installable Modules
- 90-120 / 220-264 VAC Operating Range

The E-531.00 multi-function power supply module is part of the E-501 chassis (for PZT amplifier & position-servo-controller systems for high- and low-voltage PZTs). It delivers the required operating voltages for all available plug-in modules.

Technical Data

Models	E-531.00
Function:	Linear regulated power supply
Output voltages:	+130 V, 0.2 A, -27 V, 0.2 A +24 V, 1 A, +/- 15 V, 0.5 A +5 V, 1 A
Dimensions:	205 x 105 x 75 mm
Weight:	1 kg
Operating voltage:	90-120 VAC, 50-60 Hz 220-264 VAC, 50-60 Hz
Max. power consumption:	150 W
Primary fuse:	0.63 A, slow

E-531.00



Artisan Technology Group is your source for quality new and certified-used/pre-owned equipment

- FAST SHIPPING AND DELIVERY
- TENS OF THOUSANDS OF IN-STOCK ITEMS
- EQUIPMENT DEMOS
- HUNDREDS OF MANUFACTURERS SUPPORTED
- LEASING/MONTHLY RENTALS
- ITAR CERTIFIED SECURE ASSET SOLUTIONS

SERVICE CENTER REPAIRS

Experienced engineers and technicians on staff at our full-service, in-house repair center

*InstraView*SM REMOTE INSPECTION

Remotely inspect equipment before purchasing with our interactive website at www.instraview.com ↗

WE BUY USED EQUIPMENT

Sell your excess, underutilized, and idle used equipment. We also offer credit for buy-backs and trade-ins. www.artisanng.com/WeBuyEquipment ↗

LOOKING FOR MORE INFORMATION?

Visit us on the web at www.artisanng.com ↗ for more information on price quotations, drivers, technical specifications, manuals, and documentation

Contact us: (888) 88-SOURCE | sales@artisanng.com | www.artisanng.com